Title page

Title. Behavioural analysis of swarming mosquitoes reveals higher hearing sensitivity

than previously measured with electrophysiology methods

Running title. Hearing sensitivity in swarming mosquitoes

Names and affiliations. Lionel Feugère,[1, 2] Olivier Roux,[1, 3] Gabriella Gibson[2]

[1] MIVEGEC, Univ. Montpellier, IRD, CNRS, Montpellier, France,

[2] Natural Resources Institute, University of Greenwich, Chatham, Kent ME4 4TB, UK.

[3] Institut de Recherche en Sciences de la Santé (IRSS), 01 BP 545 Bobo-Dioulasso 01,

Burkina Faso.

Corresponding author's email. lionel.feugere@riseup.net.

Keywords. Auditory processing, bioacoustics, free-flying, Johnston's organ, insect

sensory system, sound sensitivity.

Summary statement

We measured hearing sensitivity to sound playback recordings in free-flying male

mosquitoes using a behavioural method for tracking flight dynamics and wingbeat

frequency.

Abstract

Mosquitoes of many species mate in station-keeping swarms. Mating chases ensue as soon as a male detects the flight tones of a female with his auditory organs. Previous studies of hearing thresholds have mainly used electrophysiological methods that prevent the mosquito from flying naturally. The main aim of this study was to quantify behaviourally the sound-level threshold at which males can hear females. Free-flying male *Anopheles coluzzii* were released in a large arena (~2 m high x 2 m x 1 m) with a conspicuous object on the ground that stimulates swarming behaviour. Males were exposed to a range of natural and synthetic played-back sounds of female flight. We monitored the responses of males and their distance to the speaker by recording changes in their wingbeat frequency and angular speed. We show that the mean male behavioural threshold of particle-velocity hearing lies between 13-20 dB SVL (95%-CI). A conservative estimate of 20 dB SVL (i.e., < 0.5 µm/s particle velocity) is already 12 to 26 dB lower than most of the published electrophysiological measurements from the Johnston's organ. In addition, we suggest that 1) the first harmonic of female flight-sound is sufficient for males to detect her presence, 2) males respond with a greater amplitude to single-female sounds than to the sound of a group of females and 3) the response of males to the playback of the flight sound of a live female is the same as that of a recorded sound of constant frequency and amplitude.

 MAIN TEXT

Introduction

Hearing is a key sensory modality for mosquito mating; it enables males to detect females

at a distance through the combined sounds of their respective flapping wings (Warren et

al., 2009; Simões et al., 2018; Feugère et al., 2021b). The more sensitive males are to

flight sounds, the further away they can hear a female and the sooner they detect and close

in on a nearby female in the context of highly competitive mating-swarms. The male

antennal organs of mosquitoes are the most sensitive to sound described so far among

arthropods (Göpfert and Robert, 2000), however, the measurement of hearing sensitivity is

usually performed on tethered males, which prevents natural body movement such as

antennal orientation and wing flapping behaviour in response to female sound. Only a few

studies have measured hearing thresholds behaviourally (Menda et al., 2019; Lapshin and

Vorontsov, 2021; Feugère et al., 2021b). The measurement of behavioural sound-

sensitivity in flying male mosquitoes faces the difficulty of monitoring how much sound

energy actually reaches their antennae because the sound level meter is at a fixed-position,

whereas the position of the male mosquito is continuously changing during his flight. The

aim of this study was to quantify behaviourally the overall sound-level threshold at which

males can hear females, i.e. the limit of sensitivity of a male to locate a female in flight.

Accordingly, we had to determine the components of female-wingbeat sound that male

mosquitoes are most responsive to, so that our definition of the sound level includes only

the frequency bands audible to males.

Mosquitoes hear airborne sound by detecting air-particle velocity through friction between air particles and the mosquito's fibrillae located on the flagellum of their antennae. Unfortunately, there are no instruments that can truly measure particle-velocity on the market as yet (Zhou and Miles, 2017), however, it can be estimated by using pressure-gradient microphones (commonly called 'particle-velocity microphones'). Another strategy to estimate particle-velocity is to use pressure microphones located in the far-field of the sound source, i.e., where the sound pressure level (SPL) can be approximated to that of sound particle velocity level (SVL). However, SPL hearing thresholds have sometimes been measured under the near-field condition instead of far-field (Tischner, 1953; Belton, 1961; Dou et al., 2021), which means there is a risk that some reported hearing thresholds may have been under-estimated, as elaborated in the Discussion section.

Hearing thresholds can be assessed by measuring a physiological or behavioural response to a given stimulus sound level and sound frequency. Among the physiological methods, laser vibrometry records the vibration of the flagellum (Göpfert et al., 1999; Pennetier et al., 2010), however, it is limited when assessing hearing threshold because the recorded vibration only refers to the input to the hearing chain (i.e., flagella movement) and does not provide any indication as to whether or not the neurons of the mosquito have been neuro-electrically activated following the sound-induced vibration of the flagella. Unlike laser vibrometry, electrical responses of the JOs to airborne sound stimuli result from the complete sensory chain of the auditory system (i.e., from the mechanical vibration of the flagella to the electrical response of the JOs). With this method, the electrical response-threshold in male *Culex pipiens pipiens* JOs showed a mean sensitivity of 32 dB SVL per JO scolopidia (range of 22-44 dB SVL; n=74 JO scolopidia; criterion = 2 dB above noise floor; 18-21°C) (Lapshin and Vorontsov, 2019) and a mean of 44 dB SVL per mosquito in

three male *Culex quinquefasciatus* JOs (range of 36-52 dB SVL; n=3 males; criterion = 10

dB above noise floor) (Warren et al., 2009). In *Aedes aegypti,* the male JO nerve was

shown to respond to a mean of 40 dB SVL (range of 31-50 dB SVL; n=11 males) (Menda

et al., 2019). In some species, such as *Anopheles coluzzii*, the antennal fibrillae are

extended only during their active phase, which improves their JO hearing sensitivity by 17

dB in terms of SVL (Pennetier et al., 2010). Under this antennal physiological state,

Pennetier *et al.* (2010) measured a JO response-threshold in two male *An. coluzzii* of only

10 dB SVL (range of 5-12 dB SVL, i.e., particle velocity of $1.5\pm0.6\ 10^{-7}$ m/s; n=4

measurements on 2 males; criterion = 1.4 recording noise floor).

In a distortion-product based hearing system, as proposed for mosquitoes, hearing

sensitivity can be further enhanced (or even produced) by the mosquito beating its wings

(Lapshin, 2012). However, electrophysiological and laser vibrometry methods prevent

mosquitoes from beating their wings, so in order to simulate the effect of male flight on

the male auditory organ, it is possible to combine the male's flight sound-frequency with

the female stimulus sound. For example, male *Cx. pipiens pipiens* JO sensitivity was

improved by 7 dB with the addition of simulated flight sound at the main frequency

optimum (18-22 °C) (Lapshin, 2012).

The results of electrophysiological and laser vibrometry studies can be difficult to

compare against each other due to differences in methodologies used to assess threshold

responses (e.g. determination of statistical definitions of neural thresholds and variations

in the locations of electrodes). In addition, the main goal of these studies is not always

about measuring absolute hearing thresholds, and as a consequence the number of

replicates can be too few to analyse statistically.

Behavioural methods also face similar constraints, however, the assessment of physiological responses to sound stimuli offer a more natural context that enables more natural responses to sound. Behavioural responses provide more robust evidence of auditory outcomes because the whole auditory chain plus the motor responses are included. To our knowledge, there are only three published behavioural studies of mosquito sensitivity to sound intensity. First, Menda *et al.* (2019) measured the behavioural response of *Ae. aegypti* to 40 and 65 dB SVL by monitoring the take-off of resting mosquitoes in a cage located in the far-field of the sound-source. However, the behavioural methodology was not appropriate for the natural physiological context of swarming behaviour in this species; in the field both male and female *Ae. aegypti* fly continuously once the males detect the female's flight tones (i.e., they rarely rest and take-off again). Indeed, male responsiveness to sound was found to be reduced when not flying (Lapshin, 2012).

Second, Feugère *et al.* (2021b) measured the flight and wingbeat frequency response of free-flying, swarming male *An. coluzzii* to a range of sound levels of a played-back group of females and found a response at 33±3 dB SPL. However, males may respond better to the sound of individual females rather than a group of females that would occupy a relatively wide range of wingbeat frequencies, as described for *Ae. aegypti* (Wishart and Riordan, 1959).

Third, Lapshin and Vorontsov (Lapshin and Vorontsov, 2021) showed an increase in flight speed in swarming male *Aedes communis* in response to the sound frequency of females in the field, with a hearing sound-level threshold of 26 dB SVL on average (26 dB SPL under far-field conditions; 12°C).

The aim of our study was to investigate the behavioural hearing threshold of *An. coluzzii* males; Pennetier et al. (2010) measurements suggest that their JO may be as sensitive as 10 dB SVL (range of 5-12 dB SVL, n=4 measurements on 2 males, criterion = 1.4 recording noise floor). As suggested 70 years ago by Roth (1948), male hearing may be enhanced during swarming behaviour (i.e., flying in loops over a floor marker, station-keeping while they wait for females to join the swarm) when male sensitivity to the sound of flying females is expected to be maximised. Therefore, we used a modified approach of Lapshin *et al.* who worked in the field with *Ae. communis* (Lapshin and Vorontsov, 2021). Our study was performed under the following conditions: 1) in a laboratory sound-proof chamber, with controlled measurement of sound levels; 2) with a range of type of sounds to be exposed to males; 3) by monitoring both the male flight-tone and the flight-dynamic quantitatively; and 4) with *An. coluzzii*, a swarming species belonging to the *Anopheles gambiae* complex. 'Sound-level values' depend on how sound level is defined and on the type of sound stimuli, therefore, a meaningful sound-level definition should be related to the sound-frequency band and temporal patterns which mosquitoes are sensitive to. For this reason, our main aim of quantifying hearing threshold was inter-connected with the following questions:

- o Is the second harmonic of female flight tones necessary to stimulate a response in males? We need this information to establish the frequency band(s) for which the sound level is defined to be appropriate to mosquito hearing.
- o Is temporal variation in natural female sound required for males to detect females or is a single-frequency at a constant amplitude sufficient?
- o Do the flight tones of a group of females have the same effect on male hearing as those of a single female, over a range of sound levels? The main interest in the last two questions is to investigate whether we can use single-frequency sounds to

161   mimic female sound, which will make the hearing threshold easier to estimate in

162   future studies.

164 **Materials and Methods**

166   **Mosquitoes**

All experiments were performed with virgin *An. coluzzii* Coetzee & Wilkerson. The

colony was established at the Natural Resources Institute (NRI), University of Greenwich

(UK) from eggs provided by the Institut de Recherche en Sciences de la Santé (IRSS),

Burkina Faso. Eggs were obtained from a colony established in 2017 from wild gravid

females collected from inhabited human dwellings in Bama, Burkina Faso (11°23'14"N,

4°24'42"W). Females were identified to species level by PCR (Fanello et al., 2002). The

NRI colonies were kept in environmentally controlled laboratory rooms with a 12h:12h

light:dark cycle (lights went off at 15h00), >60% relative humidity and ~24-26°C. Larvae

were fed Tetramin® fish-flakes and rice powder. Adult males and females were separated

< 12h post-emergence to ensure all females were virgin and fed a solution of 10% sucrose

and 1%-saline *ad libitum*. Adult mosquitoes were kept in cube cages of ~30 cm sides,

populated with a) ~300 virgin females and b) ~20 males.

181   **Experimental setup**

183   The basic experimental setup (Fig. 1) is the same as for a previous study with *An. coluzzii*

184   (Feugère et al., 2021b) as described below.

Sound-proof chamber. All experiments were conducted in a sound-proof chamber to limit

interference from external sounds. The chamber consisted of double-skin sound-proof

walls, ceiling and floor (*L* x *W* x *H* = 2.7 m x 1.9 m x 2.3 m), producing a reverberation

time ≤ 0.07 s for frequencies above 200 Hz (IAC Acoustics, manufacturers). The SPL in

the sound-proof room without any playback was always quieter than that with playback of

the sound stimuli in the third-octave frequency band of the sound stimulus (Fig. S1 A).

Below 176 Hz (upper limit of the 125 Hz octave band), the ambient noise level rase (Fig.

S1 B; 25 dB at 125 Hz), due to low-frequency vibration of the building's aeration system,

which may have been detected by the *An. coluzzii* auditory system (Pennetier et al., 2010)

as a low-frequency background noise to the sound stimulus.

Swarming arena. The swarming arena in the sound-proof chamber was designed to

include the key environmental conditions and sensory cues known to control mating and

swarming flight in the field. A large mosquito bed-net enclosure (NATURO, *L* x *W* x *H* =

1.8 m x 1.7 m x 2 m) filling most of a sound-proof chamber (Fig. 1) enabled mosquitoes to

fly freely in a volume 100 times greater than that covered by the typical swarming space.

Lighting was provided by an artificial-sunlight system to imitate natural daylight, sunrise

and sunset (LEDs 5630, HMCO FLEXIBLE dimmer, and PLeD software, custom-built).

Dimming the ambient light level at the appropriate circadian time elicits mosquitoes to

take-off, followed by swarming behaviour in response to the presence of a visually

conspicuous matt-black marker on the floor; both males and virgin females fly in loops

above the marker, but this is rarely observed if males are present because males mate with

females quickly and mated females cease swarming behaviour (Poda et al., 2019; Gibson,

1985). We used virgin female swarming behaviour to record their flight sound within a

relatively limited distance from the marker.

Sound recording and monitoring. The wingbeats (aka, 'flight tones') of mosquitoes in the

laboratory were recorded with a weatherproof microphone (Sennheiser MKH60; RF-

condenser; super-cardioid polar pattern at 0.5-1 kHz, with amplitude decrease of > 15 dB

beyond 90° from the microphone head; sensitivity at 1 kHz: 40 mV/Pa; A-weighting

equivalent noise level: 8 dB) directed toward the swarm location. The microphone was

located at a distance of 0.89 m from the centre of the swarm area for the experimental

male mosquitoes and the sound recording of the 30-female swarm stimulus (Fig. 1),

except for the recording of the 1-female sound-stimulus for which the microphone was

located at 0.75 m from the centre of the swarm area. The microphone was plugged into a

Scarlett 18i8 audio interface on a Windows7 computer running Pro Tools First 12.8 (Avid

Technology, Inc).

Flight track recording. The 3D flight trajectories of male mosquitoes were recorded at a

sampling rate of 50 Hz with Trackit software (SciTrackS GmbH, Switzerland (Fry et al.,

2004)). Two video cameras (Basler, ace A640-120gm) were fitted with wide-angle lenses

(Computar, T3Z3510CS, 1/3" 3.5-10.5mm f1.0 Varifocal, Manual Iris) to maximize 3D

volume of video-tracking. IR lights (Raytec RM25-F-120 RAYMAX 25 FUSION)

enabled the tracking system to detect flying mosquitoes as silhouettes against an IR-

illuminated white back-wall made of thin cotton cloth (Fig. 1). The 3D-flight trajectories

were smoothed using a cubic spline interpolation at a sampling frequency of 200 Hz on

Matlab (version R2017a)

Temperature monitoring. Temperature was monitored by type-T thermocouples (IEC 584

Class 1, Omega) associated with a temperature logger (HH506RA, Omega) totalling a

measurement accuracy error of ±0.9°C. The chosen thermocouple was located on a room

wall at a height of 85 cm from the floor. The four recordings of the reference sound

stimuli (two species, two sexes) were recorded at 28.0°C. The mean temperature and

standard deviation of the behavioural assays were 28.0±0.3°C.

Sound stimuli

Recording context. Two recordings of the natural flight-sounds of 3-6 days-old swarming

females were recorded and used to produce the played-back stimuli for the behavioural

assays. These sound recordings consisted of 1) a single swarming female or 2) a group of

30 swarming females; in both cases mosquitoes were released into the swarming arena 2

days before the experiment to acclimatize. The standard environmental conditions in the

room were: 12h:12h light:dark cycle with a 1h artificial dawn/dusk transition in light

intensity and ~60-75% RH.

Signal generation. We generated 4 types of stimulation signals ('2-harmonic 1-female',

'2-harmonic 30-female', '1-harmonic 1-female' and '1-harmonic constant') (Audio S1 to

S4; signal spectrum in Fig. 2) over a range of sound levels, producing 10 stimuli in total.

First, we selected the first 7s section of the sound of a single female swarming over the

marker (Audio S5). Second, a 7s section of the sound of 30 swarming females was

selected (Audio S6), ~10 min after the first female started to swarm. Four sound levels for

each of the 1- and 30-female sounds were selected (10-45 dB SPL, Table 1)**,** based on

results of preliminary experiments. These 8 stimuli contained the two first harmonics. A

high-pass filter was added to all the stimuli to remove the electrical noise below the first

harmonic (at the noise level, see Fig. 2 and Table S1). In addition, we generated a 33 dB

SPL stimulus, which has been shown in preliminary experiments to be the lowest level sound stimulus that females detect in the sound-proof chamber (but see Method section 'Corrected SPLs for estimating the hearing threshold' below). This sound stimulus included only the first harmonic because it has been shown electrophysiologically that the male auditory organ is more sensitive to the first harmonic than higher harmonics (Pennetier et al., 2010; Warren et al., 2009). Finally, we generated a synthetic 1-harmonic sound, called '1-harmonic constant stimulus', with constant frequency and amplitude over time (set at the same mean peak-amplitude and mean frequency as the '1-harmonic 1-female' sound). A gradual increase/decrease over 1 s in the level of the start and end sounds were added to avoid creating sound artefacts due to the signal truncation, and to make the stimulus more natural (possibly important for active antennal amplification (Jackson and Robert, 2006)). The 10 stimuli were played sequentially, with a 10 s interval of silence to be played-back during the behavioural assays. To avoid an effect of the order in which stimuli were played, 10 different sequences were generated, each containing the 10 sounds in random order. All stimuli were sampled at 8 kHz / 24 bits and designed in Matlab (R2017a, The Mathworks Inc, Natick, USA). Fig. 2 gives the sound spectrum and amplitude along time of each type of stimulus. Table S1 gives the filter/frequency parameters used to generate the stimuli. Table 1 gives the sound levels for each of them. Audio S5 and Audio S6 are the original 1-female and 30-female sound recordings, respectively. Audio S1 to S4 are the 4 types of stimuli; 2-harmonic 1-female, 2-harmonic 30-female, 1-harmonic 1-female, 1-harmonic constant, respectively.

Sound diffusion. Sequences of sound stimuli were played-back from a speaker (Genelec 8010A) plugged into a Scarlett 18i8 sound card running pro-Tools First and Audacity on Windows 7. The speaker is composed of two membranes (ø 76 mm and 19 mm). The centre of the larger speaker's membrane was located 57 cm above the floor, 15 cm from

the back wall and 0.9 m from the swarming centre (Fig. 1). The speaker's self-generated

noise was less than 5 dB SPL (A-weighted) and the sound card's Equivalent Input Noise

was -127 dBu.

Data Subsets. While stimuli were played-back in random order during a single

experiment, they can be grouped into three overlapping subsets (Fig. 3), each of which

corresponds to one of the questions presented at the end of the Introduction;

Subset A: study of the effect of the second harmonic on male hearing (1-harmonic *vs* 2-

harmonic stimuli), Subset B: investigation of the effect of 'types of sound stimulus'

(single-frequency *vs* pre-recorded played-back stimuli) and Subset C: effect of the number

of females (1 *vs* 30) in the recorded-sound stimuli and of the sound levels of the sound

stimuli on male hearing to estimate the hearing threshold.

Behavioural assays

To investigate the sensitivity of swarming males to female sounds, we played-back the

female sound stimuli to swarming males in the sound-proof chamber. About twenty 3-4

days-old males were released the day prior to experiments at ~ 18h00 in the sound

recording flight arena. At 15h00, after the ceiling lights had dimmed to the lowest

intensity, the horizon light completed a 10 min dimming period and then kept at a constant

dim light intensity until the experiment was finished. When at least one male started to

swarm robustly over the marker, the first sequence of all 10 sound stimuli (i.e. the 4 types

of stimuli, with 4 sound levels for 2 of them, see Method section 'Signal generation') was

played-back from the speaker (see Movie S1 with a male exposed to one sound stimulus;

see Fig. S2 for examples of responses for each type of stimulus). After 10 stimuli were

played and if the male(s) was still swarming, or as soon as at least one male started

swarming, a new sequence of 10 stimuli was immediately played and so on, until up to 10

sequences were played or after 50 min of constant horizon light, either of which marking

the end of the experiment for the day (= 1 replicate). Males were then collected and

removed from the flight arena. A new group of ~20 male mosquitoes were released in the

sound-proof chamber, to be used for a new replicate the next day (one replicate per day,

for 10 days in August-September 2018).

Sound pressure level (SPL)

Measurement. Stimulus SPLs were measured at the mean male swarming position with a

sound meter (Casella, CEL633C1, Class 1) set as follows: reference pressure of 20 µPa;

no octave weighting (i.e., dB Z); slow octave time-constant (IEC 61672-1: 2002); octave

and third-octave bands; calibrated twice a day (CEL-120/1, Class 1, at 94 dB / 1 kHz)

before and after each measurement. The speaker and the software/soundcard gains were

set to be the same as during the behavioural experiment.

Third-octave bands. All SPLs reported in this study included only the frequency bands

that are audible to male mosquitoes, i.e., mostly the first harmonic of the female (Warren

et al., 2009; Pennetier et al., 2010). They were calculated as follows: $10 log_{10}(10^{0.1L_{B1}} +$

$10^{0.1L_{B2}})$ where L_{B1} and L_{B2} are SPL measurements in frequency bands *B1* and *B2*;

B1=500 Hz and *B2*=630 Hz are the third-octave bands nearest the female's wingbeat

frequency of the first harmonic (Table 1; and Fig. S1 for all third-octave values).

Corrected SPLs for estimating the hearing threshold. The sound of 1-female was

recorded at a distance of 0.7±0.2 m, which gave a relatively low signal-to-noise ratio

compared to the high signal-to-noise ratio of the sound of 30-females recorded at 0.9±0.2

m. As explained in the Method section 'Sound stimuli', noise was removed below the first

harmonic and above the second harmonic but not in-between to limit artefacts in the sound

stimulus. SPL was computed over the frequency-band of the first harmonics, which, for

the 2-harmonic 1-female sound, included a part of the noise between the first and second

harmonics. Results from Subset A indicated that males did not need this noise to respond

to sound because they reacted to the 2-harmonic 1-female sound as much as to the 1-

harmonic 1-female sound. Since these two stimuli had the same first-harmonic amplitude

but a SPL difference of 8 dB (Table 1), and because SPL was defined over a frequency

band below the second harmonic, we established that the noise between the first and

second harmonics is responsible for 8 dB in our SPL measurements. In order to estimate

an accurate hearing threshold, we applied a correction of 8 dB to the sound level of the 2-

harmonic 1-female stimuli (Subset C). All sound levels, with correction or not, are

summarized in Table 1.

Control of distance between live mosquito and playback speaker. Swarming mosquitoes

confine themselves to a limited area of the flight arena naturally, which enables us to

estimate the incident SPL at the mosquito's location, because the distance between

swarming mosquitoes and the sound stimulus source was limited to a known range. The

speaker (Genelec 8010A) that reproduced the females' flight tones was placed 0.9 m from

the centre of the swarm marker. Their flight positions were recorded by 3D-tracking

Trackit Software (Fry et al., 2004) (Figs 4 A, 4 B) which enabled us to determine the

distance between a mosquito and the speaker emitting mosquito sound to be 0.9±0.2 m,

95%-CI (Fig. 4 C).

Estimate of SPL errors at mosquito's location. Two types of SPL errors were taken into

account. The first is related to the time variation of the sound stimulus levels which were

between ±0.3 dB and ±0.9 dB (maximum error), depending on the stimulus (see Fig. 2 for

an example of stimulus sound-level over time). The second type of measurement

uncertainty arises when the sound level should be estimated from the mosquito's position,

and not from the fixed microphone position. Indeed, SPLs were measured at the expected

centre of the station-keeping swarm-flight of the test male mosquitoes. However, the

distance between the male and the speaker varied as 0.9±0.2 m (95%-CI, Fig. 4 C), due to

the males' swarming-flight pattern, which changed the sound level they were exposed to,

accordingly. We evaluated this error by playing-back the *An. coluzzii* female sound

stimulus and measured the sound level in a sphere around the expected swarming area

centre: the maximum error was ±2 dB. This error is considered to be conservative (at least

95%-CI) and was used to interpret the results of the experiments (see Table 1).

Physical sound quantities produced by a speaker and sensed by mosquitoes. We

monitored the sound level of the played-back stimuli by recording the sound pressure level

(SPL), however, mosquito hearing organs are sensitive to particle velocity level (SVL)

(Fletcher, 1978). The root-mean square value (RMS) particle velocity v_{RMS} and the RMS

sound pressure p_{RMS} can be related as follows, assuming the speaker to be a point source

radiating spherically a sound frequency f at a distance r from the source (air impedance

$Z_{air}(28°C) = 408$ N.s.m^{-3}; sound speed $c(28°C)=348$ m/s) (Beranek and Mellow, 2012):

384
$$v_{RMS}(r) = \frac{p_{RMS}(r)}{Z_{air}} \sqrt{1 + \left(\frac{c}{2\pi f r}\right)^2}, \quad (1).$$

385   The SPL $L_p \overset{\text{def}}{=} 20log_{10}(p_{RMS}/p_0)$ and the associated particle-velocity level

386    $L_v = 20log_{10}(v_{RMS} Z_{air} /p_0)$ (reference $p_0 = 2.0 \; 10^{-5}$ Pa) can be calculated as follows:

387
$$L_v(r) = L_p(r) + 10log_{10}\left(1 + \left(\frac{c}{2\pi fr}\right)^2\right), \quad (2).$$

Considering that the female sound stimulus does not have any frequency components

below $f = 440$ Hz (the smallest frequency value of the group of first harmonics of the

swarming females at -12 dB below the peak at 536 Hz, Fig. 2), the SVL is equal to the

SPL at 0.9 m away from a monopole sound source of these frequencies, under a negligible

error of less than 0.1 dB (due to the mosquito oscillating distance of ±0.2 m to the speaker,

calculated from equation (2)). As a consequence, and since mosquitoes are sensitive to

SVL and for easier comparison with other studies, we report the SPL as SVL. Arthur et al.

(2014) measured the particle-velocity attenuation rate in front or behind *Ae. aegypti* to be

between a monopole and a dipole. Note that our monopole assumption for mosquito wing-

flapping is conservative since higher orders (dipole, quadripole) produce sound levels that

decrease more rapidly with distance (Bennet-Clark, 1998).

Extraction of traits used to quantify male responses

Following the results of preliminary experiments, we used two components of male flight:

1) **angular-speed**, calculated from their 3D trajectories and 2) **wingbeat frequency**,

extracted from sound recordings (see Fig. 4 B for example and statistics of wingbeat and

flight dynamic characteristics before, during and after exposure to the loudest 1-female

sound-stimuli (44±2 dB SVL)). The two components were synchronized using the same

techniques as in a previously published study (Feugère et al., 2021c).

Angular-speed refers to how much the mosquito flight direction changes per unit time. It

was calculated from the linear-velocity components provided by the Trackit software as

follows: $avel = \Delta\theta / \Delta t$, where $\Delta t = t_n - t_{n+1}$ is the duration between two consecutive time

indexes n and $n+1$, and $\Delta\theta$ is the turn angle defined as:

$$\Delta\theta = acos \frac{v_n . v_{n+1}}{|v_n| . |v_{n+1}|}, \qquad (3)$$

where v_n is the three-dimensional linear velocity vector of the mosquito at time index n

and $|v_n|$ is its magnitude. The criteria used to include a tracked flight in the data analysis

were that the mosquito was swarming over the marker for at least 1 s before and after the

sound stimulus onset.

Wingbeat frequency. Only the first and/or the second harmonic of female sound stimuli

were played-back (~400-1200 Hz) in order to free the frequency domain of the male's

third harmonic from the female's sound. This allowed us to capture the male's third

harmonic without overlapping with the sound stimulus (example of spectrogram in Fig. 4

A). The peak of the third harmonic was detected every 40 ms between 2190 and 2920 Hz

using the Fast Fourier Transform algorithm (256-ms FFT-window, Hanning-windowed).

When several mosquitoes (from 1 to 6) were present over the swarming marker, the

detected value was the peak of the energy in the frequency band 2190-2920 Hz and not the

mean of the peak from individual mosquitoes (because it was not possible to track the

wingbeat frequencies of individual mosquitoes). Then, the male's third-harmonics (i.e., 3

x wingbeat frequency) were divided by 3 to get the wingbeat frequency (i.e., the first-

harmonic frequency). Finally, a 3-point median filter was applied over time to reduce

wingbeat tracking error. Fig. 4 A gives an example of detected wingbeat frequencies of

males while Fig. 4 B shows the distribution of the detected wingbeat frequency over time for all recordings.

Upper-quartile difference. Since preliminary experiments suggested that mosquitoes responded to sound by increasing their wingbeat frequency and their angular speed somewhere during the first second of the sound stimuli, the upper-quartile angular-speeds and the upper-quartile wingbeat frequencies were automatically detected during the first 1s stimulus time interval. Indeed, 'upper-quartile' is 1) a more robust metric than median or mean to measure the amplitude of a short peak, which the onset time cannot be predictable precisely and 2) a more reliable metric than 'maximum' to avoid false detection. Then, this value was subtracted from the upper-quartile value computed during the 1s segment just before the stimulus onset, for each individual recording to reduce noise related to individual mosquito variability (Fig. 4 A shows graphically how the parameters were computed).

Statistics

Wingbeat-frequency and angular-speed values for a given stimulus were averaged over the different responses of the same day to form a replicate. The wingbeat and angular-speed response-parameters were analysed using a Bayesian Linear Mixed-Effects Model (*blmer* function, *lme4* package, R). Stimulus sound levels (continuous), number of females in the recording (1 or 30), number of harmonics (1 or 2) and sound type (recording or synthesis) and their interaction were considered as fixed effects. Days, for which replicates were performed, were considered random effects. The dataset was split into the 3 subsets A, B, C, as shown in Fig. 3. A total of 6 models were built (2 parameters x 3 subsets). Stepwise

removal of terms was used for model selection, followed by likelihood ratio tests. Term

removals that significantly reduced explanatory power ($p<0.05$) were retained in the

minimal adequate model (Crawley, 2007). No data transformation was needed to ensure

variance homogeneity of variables (Fligner-Killeen test, *Fligner.test* function, R) and

normality of model residuals (Shapiro-Wilk test, *shapiro.test* function, R), except for

Subset C wingbeat-frequency which was transformed via optimality (*MLE_LambertW*

function, *LambertW* package, R (Goerg, 2016)); see Fig. S3 for normality *qqplots* and

Table S2 for normality and variance homogeneity test results.

For subsets A and B, an additional one-sample t-test (with BF-correction for multiple

comparisons) was performed independently for each distribution to measure the

significance of the mean to 0, which is the "no response" reference. For subset C, the

quietest 2-harmonic 30-female sound-stimulus was not included in the model because its

sound level was too close to the background noise level to be corrected as the three other

2-harmonic 30-female sound-stimuli. The hearing threshold was estimated by the crossing

of the $y=0$ axis (i.e., no response, including with the LambertW transformation) with the

prediction of the fixed-effect components of the mean and associated 95%-CI (*bootMer*

function with *nsim=500, lme4* package, R). The Lambert transformation does not change

the 0 value of the distribution. All analyses were performed using R (version 3.5.3).

Model Subsets resulted in a sampling size of $n=10$ for Subset A and B and $n=9$ or $n=10$

for Subset C (see legend of Fig. 5 for details; see Method Section 'Behavioural assays' for

how a replicate was defined).

Results

Males mostly use the female's first harmonic to hear her flight tone (Subset A)

Subset-A sound-stimuli with one or two harmonics were heard by males as the response distributions are different from the null distribution (Fig. 5 A), for both angular-speed (upper-quartile angular-speed difference: one-sample t=5.7, df=9, BH-corrected p<0.001, mean=1.5 rad/s; one-sample t=5.0, df=9, BH-corrected p<0.001, mean=1.0 rad/s, respectively) and wingbeat frequency (upper-quartile wingbeat-frequency difference: one-sample t=5.2, df=9, BH-corrected p<0.001, mean=16 Hz; one-sample t=4.6, df=9, BH-corrected p=0.0013, mean=13 Hz, respectively).

Our results show no differences in response of males exposed to the first-harmonic's sound of a female flight tone or the combination of the first and second harmonic sounds with noise in-between of the same female flight tone (upper-quartile angular-speed difference: LRT, χ^2=2.6, df=1, p=0.11; upper-quartile wingbeat-frequency difference: LRT, χ^2=1.1, df=1, p=0.29).

Males react to a 'pure-sound' (1-harmonic constant sound) at least as much as to a 'natural sound' (1-harmonic 1-female sound) (Subset B)

Subset-B stimuli, i.e. 1-harmonic 1-female sound and 1-harmonic constant sound, were both heard by the males because the response distributions were different from the null distribution (Fig. 5 B), for both the angular-speed (upper-quartile angular-speed difference: one-sample t=5.7, df=9, BH-corrected p<0.001, mean=1.5 rad/s; one-sample

$t=5.4$, $df=38$, BH-corrected $p<0.001$, mean=1.6 rad/s, respectively) and the wingbeat

frequency (upper-quartile wingbeat-frequency difference: one-sample $t=5.2$, $df=9$, BH-

corrected $p<0.001$, mean=16 Hz; one-sample $t=5.1$, $df=38$, BH-corrected $p<0.001$,

mean=30 Hz, respectively).

Our results show there is little difference in the male response between the 1-harmonic 1-

female sound-stimulus and the 1-harmonic constant sound of the same mean

frequency/SVL. While males change their angular-speed with the same amplitude in

response to these two stimuli, they change their wingbeat frequency two times more with

the 1-harmonic constant sound (upper-quartile angular-speed difference: LRT $\chi^2=0.052$,

$df=1$, $p=0.82$; upper-quartile wingbeat-frequency difference: LRT $\chi^2=4.5$, $df=1$, $p=0.033$,

respectively).

Males react to the 1-female sound more than to the 30-female sound, with a hearing

threshold less than 20 dB SVL (Subset C)

Using data subset C (see Table 1 for sound levels), our results (Fig. 5 C) show that free-

flying males respond to the sound stimuli, providing the sound level was high enough, by

increasing both their angular-speed and their wingbeat frequency as the tested sound

levels increased (upper-quartile angular-speed difference: LRT $\chi^2=36.8$, $df=1$, $p<0.001$,

effect size=0.12 rad/s per dB SVL; and LambertW-transformed upper-quartile wingbeat-

frequency difference: LRT $\chi^2=23.8$, $df=1$, $p<0.001$, respectively). The number of females

had small effect, but this was not interpretable, because of distinct values of sound levels

for each number of females (upper-quartile angular-speed difference: LRT $\chi^2=3.3$, $df=1$,

$p<0.001$, 1.2 rad/s for 1-female vs 0.6 rad/s for 30-female stimuli; and LambertW-

transformed upper-quartile wingbeat-frequency difference: LRT χ^2=3.2, df=1, p=0.073, 20

Hz for 1-female *vs* 10 Hz for 30-female stimuli, respectively). However, globally, the

males responded more to the 1-female sound than to the 30-female sound as the sound

level increased (i.e. interaction between the sound level and the number of female; upper-

quartile angular-speed difference: LRT χ^2=3.3, df=1, p=0.070, effect size = additional 0.05

rad/s per dB SVL for 1-female sound-stimulus; and LambertW-transformed upper-quartile

wingbeat-frequency difference: LRT χ^2=10.3, df=1, p=0.0013, respectively).

For 2-harmonic 30-female sound-stimuli (Fig. 5 C, red colour), the mean sound-level

threshold was 21 dB SVL with a 13-27 dB SVL 95%-CI, if considering the angular-speed

as response parameter. Using the wingbeat frequency parameter, the mean sound-level

threshold was 19 dB SVL with a 9-23 dB SVL 95%-CI. For 2-harmonic 1-female sound-

stimuli (Fig. 5 C, green colour), the mean sound-level threshold was 15 dB SVL with an

9-19 dB SVL 95%-CI, if considering the angular-speed to be a response parameter. Using

the wingbeat frequency parameter, the mean sound-level threshold was 17 dB SVL with a

13-20 dB SVL 95%-CI. Considering these latter stimuli, which are the most ecological

ones, a conservative estimate of the hearing threshold is then 20 dB SVL.

Discussion

Behavioural assessment of hearing threshold in swarming mosquitoes

Inter-mosquito acoustic communication is believed to occur at short range only (Feugère

et al., 2021b), during mating behaviour when mosquitoes are flying in loops near a visual

marker. *Anopheles coluzzii* males gather in tens to thousands over station-keeping swarm

sites, while virgin females join the swarm in much fewer numbers as they mate only once

in a life-time. Once a male detects a female's presence from her wing-flapping sound, the

male starts to chase the female (Pantoja-Sanchez *et al.*, 2019). Thus, there is strong

competition between males to detect relatively rare females (~1% male:female ratio

(Kaindoa et al., 2017; Charlwood and Jones, 1980). Accordingly, acute hearing sensitivity

is highly advantageous to males, along with other factors such as their own wingbeat

acoustic power (Lapshin, 2012) and frequency (Somers et al., 2021) in the context of

distortion-product hearing.

Under laboratory conditions (27-29°C), we show that male *An. coluzzii* respond strongly

to 1-harmonic constant sound of 26±2 dB SVL at the female's mean wingbeat frequency

(Fig. 5 B and Table 1) and we estimate the hearing threshold to be 20 dB SVL or less with

a 95%-CI using 2-harmonic 1-female sounds (13-20 dB SVL). Researchers have used

electrophysiological mosquito preparations to measure hearing thresholds in the

Johnston's organ, which does not involve free-flying, pre-mating behaviour, such as

swarming (but see Feugère et al. (2021) and Lapshin and Vorontsov (2021)). This may

explain why these electrophysiological studies usually found far higher sound thresholds

than in our study (see Introduction section). Lower hearing thresholds measured by

electrophysiological methods can partly be explained by the absence of flight tones in

males, which is known to be important to enhance the sensitivity in males to female

sound. This creates mixed-harmonics for which the JO is tuned to, as shown by

electrophysiology mosquito preparations exposed to flight sound simulation, which lowers

the hearing threshold by 7 dB in *Cx. pipiens pipiens* (Lapshin, 2012). However, this may

not be the only explanation. Mosquitoes exhibit 'active hearing', which can be triggered

only during specific physiological states (Göpfert and Robert, 2001; Su et al., 2018), one of which may be swarming. It may be that males can enhance hearing to detect a female that is approaching a male swarm before she is chased by a competitor.

The only other species to have been explored in relation to these aspects of swarming flight is *Ae. communis* (Lapshin and Vorontsov, 2021); in the field, the mean hearing-threshold of males at the female's wingbeat frequency was shown to be particularly low, 26 dB SVL. However, their method consisted in monitoring flight-speed changes in natural swarms by eye, which may not have enabled them to measure the smallest response amplitudes, thereby over-estimating the threshold (Lapshin and Vorontsov, 2021). On the contrary, we measured both flight dynamics and wingbeat frequency from quantitative measurements. Also, ambient temperatures were very different (~12°C for Lapshin and Vorontsov (2021) *vs* 27-29°C for our recording), which can change hearing sensitivities.

Finally, electrophysiological measurements in the JO are usually averaged over JO scolopidia, however, this could misrepresent the effective signal that triggers a behavioural response. Indeed, in addition to individual sensitivity in frequency and threshold, JO scolopidia are sensitive to the direction of the sound wave, and then only the JO scolopidia which are aligned with the sound wave-front display a low response-threshold. As a consequence, averaging all JO-scolopidium thresholds may over-estimate hearing thresholds (Lapshin and Vorontsov, 2019).

Male response to sound and the effect of number of females

Males change their wingbeat frequency with a greater amplitude when exposed to 1-

female sound than to 30-female sound, however, the change in angular-speed was small

and its statistical significance was marginal (Subset C). This occurs despite the relatively

greater amount of noise in-between the 1^{st} and 2^{nd} harmonic in the sound stimulus of the

1-female; the difference may have been stronger if the prominence of the harmonics had

similar values in the tested stimuli. Two comments merit emphasis; the first is that a group

of frequencies that are attractive alone (e.g., grouped-female sounds) have a masking

effect on mosquito auditory perception. These results support reports published 80 years

ago with *Ae. aegypti* males; it was observed that these mosquitoes were not attracted to

two or more sounds at a time, even though each of these sounds were attractive on their

own (Wishart and Riordan, 1959).

Second, it is interesting that males respond more with their wingbeat frequency than with

their flight trajectory or dynamics. The change in wingbeat-frequency is consistent with a

current theory that during a chase between a male and a female, the male moves to the

sound source by tracking the female's wingbeat sound and adjusts his own wingbeat

frequency to hear her better, through an auditory mechanism based on antennal distortion

products (Warren et al., 2009, Simões et al., 2019). In our case, the sound wave-front is

almost planar at the male's position, due to the distance and membrane dimension of the

speaker, contrary to the sound wave of a female of the same sound level which would be

far more spherical. This may create contradictory signals in the mosquito auditory system,

i.e., the sound level suggests that the female is very close, but the sound wave-shape gives

poor information about her actual location.

The question of hearing higher harmonics and the significance of background noise

Males are known to detect mainly the female's first harmonic to hear her flight tone.

Indeed, *Ae. aegypti* respond (with clasping and seizing movements in flight) to low

frequencies under 500 Hz (i.e., 1-harmonic sounds) using tuning forks (Roth, 1948), while

other species, such as *Cx. pipiens pipiens*, have a narrower frequency range of response

(500-600 Hz) when swarming (Gibson, 1985). In *Toxorhynchites brevipalpis, Cx. pipiens*

pipiens, and *An. gambiae s.l.*, electrophysiology revealed that male antennae are sensitive

to a large frequency-band up to 2 kHz that encompasses the two first harmonics, however,

the electrical tuning of their JO is very narrow and centred on the difference wingbeat

frequency of the two sexes which is close to the female's first harmonic (Gibson et al.,

2010). With respect to behaviour, Wishart and Riordan (1959) trapped as many *Ae.*

aegypti males with the sound of 1-harmonic tones as with the complete flight sound.

Moreover, when removing the first harmonic from female flight tone recordings, *Ae.*

aegypti males did not respond anymore, but the authors reported their results without any

further information. This absence of a male's response if the female's first-harmonic is

removed from the stimulus is similar to our results with *An. gambiae*, which shows a

similar male response if the second harmonic of the female flight-tone is removed. On the

contrary, it has been reported that male *Ae. aegypti* can hear the female second-harmonic,

but without inferential statistics (Cator et al., 2009), and their results were also contested

with arguments based on auditory processing of phasic information in the JO nerves of *Cx.*

quinquefasciatus (Warren et al., 2009). However, the image channel resulting from the

non-linear vibration of the antennae from the sound of the two sexes was shown to

reinforce the hearing sensitivity of males close to/slightly above the frequency of the

female's second harmonic in electrophysiological measurements in *Cx. pipiens pipiens*

(Lapshin, 2012) and *Ae. communis* (Lapshin and Vorontsov, 2021). The results of our

behavioural assay suggest that this reinforcement is negligible in practice, at least in *An.*

coluzzii.

The limitation of our stimulus recording approach is to be found in the long distances

between the microphone and the single female (0.7±0.2 m), which induced a low signal-

to-noise ratio of 1.7, despite noise filtering below the first harmonic and above the second

harmonic (against a ratio of ~48 for the 2-harmonic 1-female stimulus; if considering the

noise level as the noise floor between the 2 harmonics, using the Matlab function *snr*).

Indeed, because of these different signal-to-noise ratios, the 2-harmonic 1-female stimulus

can be seen as a frequency band of noise (ranging from the first to the second harmonic

frequencies) instead of a true 2-harmonic sound.

However, this noise asymmetry between the two stimuli also shows that males are not

fundamentally disturbed by noise; the noisiest stimulus (2-harmonic 1-female) induced as

much response as the least noisy stimulus (2-harmonic 30-female). Wishart and Riordan

(1959) found that female sound (500 Hz) is still an attractant to males, with at least up to

10 dB of noise above the signal sound level for *Ae. aegypti* males, but was not an

attractant on the next tested step of 20 dB of noise above the signal level. The noise was

composed of the superposition of sine waves of 100, 156, and 282 Hz plus square waves

of 933, 1840, and 4130 Hz, which probably did not create as much noise around the

female sound frequency as in our case. The hearing mechanism based on antennal

distortion products uses the loud wingbeat frequency of the listener to amplify the nearby,

but possibly quiet, wingbeat frequency of a potential mate (Lapshin 2012). By changing

its own wingbeat-frequency, it is possible to change the distortion product frequency

elicited by the nearby flying mate, which, theoretically, may help detect very faint

harmonics against a relatively high level of background noise, especially when this noise

is limited to the frequency band between the two harmonics.

Constant sound *vs* 'natural' sound

Constant sound and female pre-recorded flight-tones have been known to trigger a

response in mosquitoes for a long time (Roth, 1948; Kahn and Offenhauser, 1949).

However, to our knowledge, no comparisons has been formally analysed between pre-

recorded sounds and constant sound of the same frequency. Our results in Subset B show

that the 1-harmonic constant sound behaves somewhat like a supernormal stimulus (for

the wing-beat frequency response-parameter) compared to a 1-harmonic natural sound, at

least at 26 dB SVL. Furthermore, Subset A allows us to conclude that males respond as

much to 1-harmonic 'natural' sound as to 2-harmonic 'natural' sound. By combining

results from Subset A and B, we deduce that mosquitoes hear natural sound as well as

pure sound. This means that the information carried in the sound that elicits a male

response is mostly the mean wingbeat frequency. A proper study could be carried out 1)

with 1-harmonic constant sounds to control the sound level better than with pre-recorded

sounds, and 2) by using larger ranges of frequencies and sound levels than in the present

study, i.e., we would need to conduct a 'behavioural audiogram'.

Monitoring SVL from SPL measurements

Many studies report hearing thresholds based on SPL, which is a physical quantity that

mosquitoes do not detect. We also monitored sound level with SPL, but we fulfilled the

experimental conditions to provide equivalence between SPL and SVL, which mosquitoes

do detect (see Methods section). Some studies have referred to SPL values as hearing

thresholds, even though the equivalence conditions were not fulfilled or were unknown.

Wishart and Riordan (1959) estimated that *Ae. aegypti* responds to a sound of

approximately 20 dB SPL from experiments involving 30cm-side netting cages and sound

stimuli presented through a diffuse speaker held against the cage netting. However,

mosquitoes could be located a few centimetres from the loudspeaker, where SPL and SVL

are not equivalent at this distance, i.e., when SPL would not be a good physical quantity to

describe what the mosquito auditory organs are exposed to. Another example is Belton *et*

al. (1961); a response threshold in the Johnston's organs of male *Ae. aegypti* was

measured to be between 0 and 10 dB SPL; SPL to SVL using a formulae that assumed far-

field condition (without stating so, though). Unfortunately, the study did not provide

enough details of the experimental setup to know the distance between the pressure

microphone and the loudspeaker; thus, the thresholds were probably inaccurate. More

recently, Dou *et al.* (2021) put their loudspeaker at 2.5 cm against their 30cm-side cage to

measure the response of mosquitoes and monitored the sound level with an SPL meter in

the middle of the cage. They measured flight response to sound in *Ae. aegypti* females for

the first time, from a threshold of 79 dB SPL, which could be far more in terms of SPL

since it was measured in the middle of the cage and mosquitoes were free to move along

the cage's sides, near the loudspeaker. In addition, SVL may have been far greater than

SPL at this distance from the speaker. Taken together, SVLs probably do not occur with

ecologically-relevant sounds, however, this could be used to inform the design of sound

traps or reveal unknown auditory mechanisms.

Acknowledgments

Natalie Morley (insect rearing), Stephen Young (discussion about statistics; design of the

synchronization electronic tool; design of high-pass frequency electronics to adjust the

dimming LED system).

Competing interests

The authors declare no conflict of interest.

Funding Statement

This work is supported by a Research Grant from Agence Nationale de la Recherche

[JCJC-15-CE35-0001-01 to O.R.] and Human Frontier Science Program [RGP0038/2019

to G.G].

Data Availability

Raw response files (sound and tracked flight trajectories) are available at:

https://doi.org/10.5061/dryad.9cnp5hqhj (Feugère et al., 2021a). Sound stimuli (Audio S1

to S4), as well as the original sound recordings (Audio S5, Audio S6) are available as

supplementary material. Custom audio–video code for parameter-extraction and audio–

video synchronization (modified Matlab files from

https://doi.org/10.17632/hn3nv7wxpk.3 (Feugère, 2020)), custom statistics code for data

analysis and figure plot (R files) and dataset (Text files) are available at

https://doi.org/10.17632/6w5jttwkj8.2 (Feugère, 2021).

Author contributions

Conceptualization LF, GG; Methodology LF, GG; Software LF; Formal Analysis LF;

Investigation LF; Data Curation LF; Writing – Original Draft LF; Writing – Review &

Editing OR, GG; Visualization LF; Supervision GG, OR; Funding Acquisition OR, GG,

LF.

References

Arthur, B. J., Emr, K. S., Wyttenbach, R. A. and Hoy, R. R. (2014). Mosquito (*Aedes aegypti*) flight tones: Frequency, harmonicity, spherical spreading, and phase relationships. *J. Acoust. Soc. Am.* **135**(2), 933-941.

Bennet-Clark, H. C. (1998). Size and scale effects as constraints in insect sound communication. *Philos. Trans. R. Soc., B.* **353**, 407-429.

Beranek, L. L. and Mellow, T. J. (2012). Chapter 5 – Microphones. In *Acoustics: sound fields and transducer* (ed. L. L. Beranek and T. J. Mellow), pp. 199-240, Oxford:Academic Press.

Belton, P. (1961). The physiology of sound reception in insects. *Proc. Ent. Soc. Ont.* **92**, Entomological Society of Ontario, 20-26.

Cator, L. J., Arthur, B. J., Harrington, L. C. and Hoy, R. R. (2009). Harmonic convergence in the love songs of the dengue vector mosquito. *Science* **323**, 1077-1079.

Charlwood, J. D. and Jones, M. D. R. (1980). Mating in the mosquito, *Anopheles gambiae s.l.. Physiol. Entomol.* **5**, 315-320.

Crawley, M. J. (2007). Mixed-Effects Models. In *The R book*, pp. 627-660. New York: John Wiley & Sons.

Dou, Z., Madan, A., Carlson, J. S., Chung, J., Spoleti, T., Dimopoulos, G., Cammarato, A. and Mittal, R. (2021). Acoustotactic response of mosquitoes in untethered flight to incidental sound. *Sci. Rep.* **11,** 1884.

Fanello, C., Santolamazza, F. and Della Torre, A. (2002). Simultaneous identification of species and molecular forms of the *Anopheles gambiae* complex by PCR-RFLP. *Med. Vet. Entomol.* **16**, 461-464.

Feugère, L. (2020). Code for audio-video parameter extraction and statistical tests related to mosquito response to opposite-sex sound-stimuli. *Mendeley Data*, V3, https://doi.org/10.17632/hn3nv7wxpk.3

Feugère, L. (2021). Code for audio-video parameter extraction, statistical tests and figure design related to characterization of male-mosquito hearing. *Mendeley Data*, V2, https://doi.org/10.17632/6w5jttwkj8.2

Feugère, L., Gibson, G. and Roux, O. (2021a), Audio and 3D flight-track recordings of mosquito responses to opposite-sex sound-stimuli, *Dryad*, *Dataset*, https://doi.org/10.5061/dryad.9cnp5hqhj

Feugère, L., Gibson, G., Manoukis, N. C. and Roux, O. (2021b). Mosquito sound communication: are male swarms loud enough to attract females? *J. R. Soc. Interface* **18**(177), 20210121.

Feugère, L., Gibson, G., Manoukis, N. C., Roux, O. (2021c). Supplementary material from "Mosquito sound communication: are male swarms loud enough to attract females?". *The Royal Society. Collection*. https://doi.org/10.6084/m9.figshare.c.5361985.v1

Fletcher, N. H. (1978). Acoustical response of hair receptors in insects. *J. Comp. Physiol.* **127**, 185-189.

Fry, S., Muller, P., Baumann, H.-J., Straw, A., Bichsel, M. and Robert, D. (2004). Context-dependent stimulus presentation to freely moving animals in 3D. *J. Neurosci. Methods* **135**, 149-157.

Gibson, G. (1985). Swarming behavior of the mosquito *Culex pipiens quinquefasciatus*: a quantitative analysis. *Physiol. Entomol.* **10**, 283-296.

Gibson, G., Warren, B. and Russel, J. I. (2010). Humming in tune: sex and species recognition by mosquitoes on the wing. *JARO* **11**, 527-540.

Goerg, G. M. (2016). Lambert W random variables—a new family of generalized skewed distributions with applications to risk estimation. *Ann. Appl. Stat.* **5**(3), 2197-2230.

Göpfert, M., Briegel, H. and Robert, D. (1999). Mosquito hearing: sound-induced

antennal vibrations in male and female *Aedes aegypti*. *J. Exp. Biol.* **202**(20), 2727-2738.

Göpfert, M. C. and Robert, D. (2000). Nanometre-range acoustic sensitivity in male and

female mosquitoes. *Proc. R. Soc. B* **267**, 453-457.

Göpfert, M. C. and Robert, D. (2001). Active auditory mechanics in mosquitoes. *Proc.*

R. Soc. B **268**(1465), 333-339.

Jackson, J. C. and Robert, D. (2006). Nonlinear auditory mechanism enhances female

sounds for male mosquitoes. *Proc. Natl. Acad. Sci. U. S. A.* **103**(45), 16734-16739.

Kahn, M. C. and Offenhauser, W. (1949). The first field tests of recorded mosquito

sounds used for mosquito destruction. *Am. J. Trop. Med.* **s1-29**(5), 811-825.

Kaindoa E. W, Ngowo H. S, Limwagu A., Mkandawile G., Kihonda J., Masalu J. P.,

Bwanary H., Diabate A. and Okumu F. O. (2017). New evidence of mating swarms of

the malaria vector, *Anopheles arabiensis* in Tanzania. *Wellcome Open Res.* **2**, 88.

Lapshin, D. N. (2012). Mosquito bioacoustics: Auditory processing in *Culex pipiens*

pipiens l. males (Diptera, Culicidae) during flight simulation. *Entomol. Rev.* **92**(6), 605–

621.

Lapshin, D. N. and Vorontsov, D. D. (2019). Directional and frequency characteristics of

auditory neurons in *Culex* male mosquitoes. *J. Exp. Biol.* **222**(21), jeb208785

Lapshin, D. N. and Vorontsov, D. D. (2021). Frequency tuning of swarming male

mosquitoes (*Aedes communis*, Culicidae) and its neural mechanisms. *J. Insect Physiol.* **0**,

104233.

Menda, G., Nitzany, E. I., Shamble, P. S., Wells, A., Harrington, L. C., Miles, R. N.

and Hoy, R. R. (2019). The long and short of hearing in the mosquito *Aedes aegypti*.

Curr. Biol. **29**, 709-714.

Pantoja-Sanchez, H., Gomez, S., Velez, V., Avila, F.W., and Alfonso-Parra, C. (2019).

Precopulatory acoustic interactions of the new world malaria vector *Anopheles albimanus*

(Diptera: Culicidae). *Parasites Vectors* **12**(1), 386.

Pennetier, C., Warren, B., Dabiré, K. R., Russel, J. I. and Gibson, G. (2010). "Singing

on the wing" as a mechanism for species recognition in the malarial mosquito *Anopheles*

gambiae. *Curr. Biol.* **20**, 131-136.

Poda, S. B., Nignan, C., Gnankiné, O., Dabiré, R. K., Diabaté, A. and Roux, O.

(2019). Sex aggregation and species segregation cues in swarming mosquitoes: role of

ground visual markers. *Parasites Vectors* **12**(1), 589.

Roth, L. M. (1948). A study of mosquito behavior. An experimental laboratory study of

the sexual behavior of *Aedes aegypti* (Linnaeus). *Am. Midl. Nat.* **40**(028), 265-352.

Simões, P. M. V., Ingham, R. A., Gibson, G. and Russell, I. J. (2018). Masking of an

auditory behaviour reveals how male mosquitoes use distortion to detect females. *Proc. R.*

Soc. B **285**(1871).

Somers, J., Georgiades, M., Su, M. P., Bagi, J., Andrés, M., Mills, G., Ntabaliba, W.,

Moore, S. J., Spaccapelo, R. and Albert, J. T. (2021). Flight-tone mediated circadian

control of audibility in mating swarms of *Anopheles* mosquitoes. *bioRxiv*

doi:2021.07.12.452033.

Su, M. P., Andrés, M., Boyd-Gibbins, N., Somers, J. and Albert, J. T. (2018). Sex and

species specific hearing mechanisms in mosquito flagellar ears. *Nat. Commun.* **9**, 3911.

Tischner, H. (1953). Über den gehörsinn von stechmücken. *Acustica* **3**, 335-343.

Warren, B., Gibson, G. and Russel, J. I. (2009). Sex recognition through midflight

mating duets in *Culex* Mosquitoes is mediated by acoustic distortion. *Curr. Biol.* **19**, 485-

491.

Wishart, G. and Riordan, D. F. (1959). Flight responses to various sounds by adult

males of *Aedes aegypti* (L.) (Diptera: Culicidae). *Can. Entomol.* **91**, 181-191.

Zhou, J. and Miles, R. N. (2017). Sensing fluctuating airflow with spider silk, *Proc. Natl.*

Acad. Sci. U. S. A. **114**(46), 12120-12125.

Figure legends

Fig. 1. Sound-proof chamber setup for recording sound and video of *An. coluzzii* behaviour (modified version from (Feugère et al., 2021b)). (A) Bird's-eye and (B) side views of sound-proof chamber. Blue shaded areas indicate the 3D fields-of-view of cameras recording mosquito flight paths. Two IR-sensitive cameras fitted with IR pass filters recorded flying mosquitoes as black silhouettes against evenly lit IR- background. A separate lighting system provided gradual semi-natural dusk visible to mosquitoes, consisting of dispersed dim white lights on ceiling and 'sunset' lighting below horizon (opaque wall ~40 cm tall). A microphone recorded flight sounds of mosquitoes swarming directly above black swarm marker. A thermocouple (85 cm above ground level) recorded temperature at ~ mean swarm height. A speaker located behind IR-illuminated thin-cotton sheet, outside net enclosure played back sound stimuli.

(C) Bird's-eye and (D) side views of the superimposed flight tracks of the entire dataset.

Fig. 2. Spectral and temporal properties of sound stimuli. Spectral (first column) and temporal (second column) properties of sound stimuli of one single swarming *An. coluzzii* female (top row) compared to that of 30 females (bottom row). The originally recorded sounds are represented with a dotted line (Audio S1 and Audio S2 for a unfiltered 1-female and 30-female, respectively; not used directly as sound stimuli). The 1-harmonic 1-female sound is shown as a semi-dotted-dashed red line, while the 2-harmonic sounds are represented by a solid pink line. Magnitude spectra were calculated over 7 s and averaged over 50-Hz windows. The root-mean-square pressure levels were computed over a 0.1 s time window with 0.05 s overlap, along the 7 s duration of the stimuli. See Table S1 for characteristics of filters applied to Audio S1 and Audio S2 to generate the 1-harmonic and 2-harmonic stimuli.

Fig. 3. Data subsets for our analysis (A, B, C). Subset A was used to study the effect of the number of harmonics in the sound stimuli. Subset B was used to compare the sound type (playback of female sound or constant sound of the same wingbeat frequency). Subset C was used to study the effect of number of mosquito(es) (1 female or 30 females).

Fig. 4. Flight and sound responses of *An. coluzzii* males to sound-stimuli. Male flight-characteristics and wingbeat-frequencies (blue) before, during and after playback of female (red rectangle) sound stimuli.

(A) Example of male response to the loudest 2-harmonic 1-female sound-stimulus over 27 s of recording. Stimulus was played-back 10 s from beginning of flight recording and lasted 7 s (red rectangular shading). First five rows show flight parameters (relative X,Y and Z positions, plus linear and angular flight speeds). 'Z' dimension represents relative distance to the speaker (located 0.9 m from $Z=0$). Before-last row shows mean wingbeat frequency (WBF). Periodic flight pattern, typical of swarming behaviour, is evident in X, Y and Z plots. In the angular-speed and wingbeat frequency plots, the two red lines correspond to the upper-quartile over 1s and the arrows represent the differences between the two red lines, which are the parameters computed for monitoring the male response (see Methods section 'Extraction of traits used to quantify male responses'). Last row shows the spectrogram of sound recordings before, during and after the sound stimulus; the colour gradient represents the sound level given a frequency and a time (the darker the colour, the louder the frequency). Movie S1 gives the associated raw image and sound recording. See Fig. S2 for examples of responses to the 4 types of sound stimulus.

(B) Same as (A) but without spectrogram and for all-male responses to the loudest 2-harmonic 1-female sound-stimulus. Darkest coloured lines represent running median, darkest areas represent second and third quartiles and light areas represent the 90^{th}

percentile of data. The sample size of the distribution of flight coordinates and velocities corresponds to the number of male flight tracks (n=104), and that of the WBF distribution corresponds to the number of swarms (n=61) where mean WBFs over the number of mosquitoes per swarm were calculated (1 to 6 males per swarm). Linear and angular speed, and wingbeat frequency clearly increased in response to the onset of this sound stimulus, plus there was a slight tendency to increase in flight height (Y (m)).

(C) Probability distribution of distance between a male and the speaker during sound stimulus playback for all stimuli; distances ranged between 0.9±0.2 m. This distance interval was used to estimate the uncertainties of the acoustic prediction in Table 1. The sample size of the distribution of distances corresponds to the number of male flight tracks (n=104).

Fig. 5. Results of behavioural experiment. Top and bottom rows show the increase in upper-quartile angular-speed and wingbeat frequency, respectively, when playing-back a given sound stimulus. Black dotted lines represent the absence of change in parameters before and during the stimuli. Each sample is the average of several measurements on the same day. Each sample corresponds to a different group of mosquitoes (consisting of 1 to 6 in each sample). See Method Section 'Statistics' and Results Sections for statistical tests. **(A)** Male *An. coluzzii* responses to 1- or 2-harmonic sounds of a single female (data subset A, n=10 in each boxplot). Boxplots of the parameters show the median, 2^{nd} and 3^{rd} quartiles. Outliers shown as diamond shapes are outside the interval [Q1 – 1.5 * IQD, Q3 +1.5 * IQD] which is represented by whiskers (Q1 = first quartile; Q3 = third quartile and IQD = interquartile distance). Disk and error bars in each distribution show mean and standard error.

(B) Male *An. coluzzii* responses to 1-harmonic 1-female sound or to single-frequency

sound (data subset B, n=10 in each boxplot). Boxplots, disk and error bars have the same

meaning as in (A).

(C) Male *An. coluzzii* responses to 2-harmonic sounds of single or 30 females along SVLs

(data subset C, n=9 for the quietest 1-female stimulus and the two loudest 30-female

stimuli, n=10 for other stimuli). Continuous lines and associated coloured areas represent

the mean and 95%-CI. SVL were corrected as explained in Method section 'Corrected

SPLs for estimating the hearing threshold'. The green dotted lines represent the lowest

estimate of the hearing threshold from the response to 1-female 2-harmonic sound-stimuli.

Table

Subset	Single/ Group	Number of harmonics	Recording/ Synthetic	Sound level (dB SPL)			
				SPL measurement of the two 1/3-octave bands closest to the first-harmonic at fixed distances from the speaker (0.9 m)			Error due to ±0.2 m oscillation (and total error)
				Mean value	Corrected mean value	Error over the 7 s	
NA	Silence playback	NA		6.9		±0.3	±0.3
A	Single	1	Recording	25.0		±0.9	±2
		2		32.6		±0.3	±2
B	Single	1	Recording	25.0		±0.9	±2
			Synthetic	26.0		±0.2	±2
C	Single	2	Recording	10.6	NA	±0.5	±2
				22.4	14.4	±0.4	±2
				32.6	24.6	±0.3	±2
				44.2	36.2	±0.6	±2
	Group (~30)			17.1		±0.5	±2
				23.1		±0.4	±2
				32.9		±0.5	±2
				44.9		±0.5	±2

994   **Table 1. Description of stimulus sound-levels**. This table gives the sound pressure levels

995   (SPL ref 20 µPa) and associated errors of all played-back sound stimuli at the male's mean

996   location in the frequency range of the female's first harmonic. See Methods 'Corrected

997   SPLs for estimating the hearing threshold' for the corrected SPL mean value and Methods

998   section 'Estimate of SPL errors at mosquito's location' for last two columns. SPLs are

999   equal to SVLs in our setup (see Method section 'Monitoring SVL from SPL

1000   measurements). For frequency characteristics, see Fig. 2 and Table S1.