The MAPK/ERK channel capacity exceeds 6 bit/hour

Paweł Nałęcz-Jawecki[1], Paolo Armando Gagliardi[2], Marek Kochańczyk[1],

Coralie Dessauges[2,#], Olivier Pertz[2*], Tomasz Lipniacki[1*]

[1] Institute of Fundamental Technological Research, Polish Academy of Sciences, Warsaw, Poland

[2] Institute of Cell Biology, University of Bern, Bern, Switzerland

[#] Current address: Laboratory of Systems Pharmacology, Harvard Medical School, Boston, Massachusetts, United
   States of America

[*] Corresponding authors: E-mails: olivier.pertz@izb.unibe.ch (OP), tlipnia@ippt.pan.pl (TL)

ABSTRACT

Living cells utilize signaling pathways to sense, transduce, and process information. As the extracellular

stimulation often has rich temporal characteristics which may govern dynamic cellular responses, it is

important to quantify the rate of information flow through the signaling pathways. In this study, we used

an epithelial cell line expressing a light-activatable FGF receptor and an ERK activity reporter to assess

the ability of the MAPK/ERK pathway to transduce signal encoded in a sequence of pulses. By

stimulating the cells with random light pulse trains, we demonstrated that the MAPK/ERK channel

capacity is at least 6 bits per hour. The input reconstruction algorithm detects the light pulses with 1-min

accuracy 5 min after their occurrence. The high information transmission rate may enable the pathway to

coordinate multiple processes including cell movement and respond to rapidly varying stimuli such as

chemoattracting gradients created by other cells.

Author summary

To respond to external stimulation, living cells need to transfer information from membrane receptors to downstream proteins that regulate physiological outcomes. In this study we used cells expressing a light-activatable receptor that transmits signals to MAPK/ERK transduction pathway, which regulates numerous physiological processes including proliferation, differentiation and cell motility. By stimulating these cells with various sequences of short light pulses we found that ERK, the last component of the considered signal transduction pathway, may receive at least 6 bits per hour. This bitrate allows 6 binary decisions per hour, enabling rapid responses to varied extracellular stimuli.

Introduction

Living cells communicate with each other and constantly monitor their extracellular milieu. Upon receiving a stimulus, they have to recognize its identity and act accordingly to operate in a coordinated manner and properly adapt to the changing environment. At the molecular level, recognition of a specific signal as well as its reliable transmission and appropriate interpretation involve diverse intracellular processes that are notoriously stochastic [1]. At the single-cell level, major intracellular signaling pathways respond to an external stimulus in a crude all-or-nothing manner [2–5]. The inability of individual cells to resolve the level of stimulation is reflected in the amount of information about the ligand concentration the signaling pathways can transmit, which has been estimated to only slightly exceed 1 bit [6–9].

However, when cells are subjected to temporally varying stimulation by morphogens, hormones, or cytokines, it is of interest to quantify the maximum rate at which information can be transferred through a biochemical signaling pathway. A similar question has been asked before in the fields of neuroscience and bacteria or amoebae chemotaxis. Neurons utilize precise timing of spikes to evoke proper response [10–12]. The information transmission rate (or simply bitrate) through a single neuron may reach tens of

bits per second [13,14]. For bacteria navigating in a chemical gradient, the drift velocity scales linearly

with the gradient, while the bitrate was found to be proportional to the square of the gradient [15]. When

concentration varies on the length scales of millimeters to centimeters, the chemotactic system of *E. coli*

transfers about 0.01 bit per second, which allows bacteria to climb up the gradient with a few percent of its

swimming speed. This suggests that at low gradients, drift velocity is information limited [15]. Without

explicitly quantifying the information flow, Meier *et al*. [16] showed that *Dictyostelium discoideum*

amoebae may synchronously readapt their migration direction to switching chemotactic gradient

oscillating at rates up to 0.02 Hz. This suggests that the rate of information transmission to the navigation

system is up to 1 bit per minute, and the limit is achieved if all cell decisions are correct. The maximum

bitrate depends on biophysics of a specific information channel. In the case of neurons, where the bitrates

are highest, information is transmitted with the help of fast electro-chemical signals; in the case of *E. coli*

and MAPK, information is transmitted by means of posttranslational proteins modifications, thus expected

bitrates are lower. The bitrate observed in the *E. coli* chemotactic system can be higher than that expected

for the MAPK channel, because bacteria are much smaller than a eukaryotic cell. Some other signaling

pathways such, as that of NF-κB or p53, require protein synthesis and degradation, which are slower than

post-translational modifications, and so for these pathways even lower bitrates are expected.

Gagliardi *et al*. [17] demonstrated that the ERK pulses triggered locally by growth factors shed by

apoptotic cells coordinate the maintenance of epithelial integrity. *In vivo* studies showed pulsatile ERK

dynamics during wound healing in mice, wherein the wound edge initiates recurrent, quasiperiodic

mechanochemical traveling fronts of ERK activity [18]. Such waves were also observed during

mammalian epidermis development [19] and during scale regeneration in zebrafish [20]. Pulsatile ERK

dynamics has been observed also for tonic EGF stimulation, for example Albeck *et al*. [21] and Aoki *et al*.

[22] have shown that the MAPK pathway converts various types of stimulation into ERK pulses,

suggesting their role in generating physiological outcomes.

In this study, we assessed the capability of the MAPK/ERK pathway to transduce information

encoded in a sequence of stimulatory pulses, and estimated the lower bound for the rate of information

transmission through this pathway. In light of the mentioned findings, we focused solely on pulsatile

stimulation protocols. As we conjecture that protocols ensuring highest information transfer are used for

cell signaling, we searched for a protocol that would maximize the information transmission rate, and thus

estimated the MAPK/ERK channel capacity. We considered three different families of pulsatile input

protocols: (i) *binary encoding*, resembling digital communication with zeros and ones occurring in well-

defined, temporally equidistant time slots, is plausibly the simplest pulsatile stimulation protocol; (ii)

interval encoding, with exponentially-distributed waiting times in discrete time domain (so, effectively,

geometrically-distributed waiting times), is statistically maximally random (entropic); this protocol is also

natural form the biological perspective as it implies constant propensity of receiving stimulation pulses in

time; (iii) *interval encoding with an additional gap* after each pulse is an attempt to tailor a maximally

entropic stimulation to cells characterized by an inextricable refractory (resting) period. We used an

epithelial cell line with an optogenetically modified fibroblast growth factor receptor (optoFGFR) [23,24]

which allowed us to stimulate the pathway with short light pulses activating ERK with the similar kinetics

as EGF or FGF [25]. The cell line is stably transfected with a reporter, enabling fine temporal monitoring

of ERK activity. By stimulating cells with random pulse trains, generated with probabilistic algorithms

according to protocols from the three families, and applying classifier-based algorithm to reconstruct the

stimulatory sequence, we demonstrated that the maximum information transmission rate through the

pathway exceeds 6 bits per hour. A classifier-free approach gives an even higher estimate of about 8.5

bits per hour.

Results

Information encoding and information transmission rate

The maximum amount of information that can be transmitted through a communication channel per unit time using the best possible input protocol is called the channel capacity C:

$$C = \max_{\text{protocols}} \lim_{\Delta t \to \infty} \frac{I(S,R)}{\Delta t} \tag{1}$$

where $I(S, R)$ is the mutual information between the input (signal) S and the output (response) R in an experiment of duration Δt [26]. In this work, we computed $I(S, R)$ as the difference:

$$I(S,R) = H(S) - H(S|R) \tag{2}$$

where $H(S)$ is the input entropy (the amount of information sent), which in our experimental design can be computed directly from the assumed probabilistic distribution of the pathway-stimulating input sequence; and $H(S|R)$ is the conditional entropy (the amount of information lost), which captures the uncertainty introduced by the channel (here: the signaling pathway). The value $H(S|R)$ depends both on the channel and the signal and as such is estimated based on experimental data.

There are multiple ways to encode information in a train of pulses. When the magnitudes of all stimulation pulses are equal, the input can be perceived as a sequence of 0s (no pulse) and 1s (pulse). The input information (or entropy) rate increases with the frequency of pulses, reaching the maximum for binary sequences that have equal probabilities of 0 and 1. However, shorter intervals between pulses imply higher information loss due to imperfect transmission. One should thus expect that there exists an optimum, for which the bitrate is maximal.

We applied three types of pulsatile stimulation protocols to estimate the lower bound for the channel capacity of the MAPK/ERK pathway (see Fig. 1A and Materials and methods for details). In what we call the *binary encoding protocol*, information is encoded in a sequence of 0s and 1s sent at regular time intervals τ_{clock} with equal probabilities. In our experiments, we stimulated cells with light pulses according

to a 0/1 sequence of length 19: `1011010011110000101` and its logic negation (both of them

containing each of the 16 possible subsequences of length 4 exactly once, which allowed us to collect

good statistics in a single, relatively short experiment). In the *interval encoding protocol*, information is

encoded in the lengths of intervals between subsequent input light pulses. To maximize the input entropy

(which, in light of Eq. (2), bounds the transmitted information from above), the intervals were drawn from

geometric distribution. In the *interval encoding protocol with a minimal gap*, the time intervals were also

drawn from geometric distribution (with the average inter-pulse interval τ_{geom}), and then τ_{gap} was added to

the drawn value, thus the expected value of the inter-pulse interval was $\tau_{geom} + \tau_{gap}$. For each τ_{gap}, we

chose τ_{geom} that maximizes the input entropy (see Materials and methods for details). Introduction of τ_{gap}

reduces the input entropy rate compared to the interval encoding protocols, but increases the percentage of

cells evoking a timely response to a light pulse, which facilitates accurate information transmission.

Detection of pulses

To quantify the bitrate through the MAPK/ERK pathway, we used the human mammary epithelial cell

line MCF-10A with both an optogenetically modified fibroblast growth factor receptor (optoFGFR)

[17,25], which can be activated with blue light (470 nm), and a fluorescent ERK kinase translocation

reporter (ERK KTR), which translocates from the nucleus to the cytoplasm when phosphorylated by ERK

(Fig. 1B). The cells were stimulated with short (100 ms, see Materials and methods) blue light pulses

according to the three types of encoding protocols (Fig. 1A). ERK KTR translocation was measured at

one-minute resolution (Fig. 1C–D; see Materials and methods and S1 Fig for details of the workflow).

We observed that the signal was transduced from optoFGFR to ERK KTR within single minutes,

consistently with Ref. [25], with the steepest translocation increment (drop of the nuclear ERK KTR

fluorescence) observed between 2 and 3 min, maximum translocation at 6 min, and steepest translocation

decrement around 11 min after the light pulse (Fig. 1E).

We then employed a classifier based on the *k*-nearest neighbors (*k*NN) algorithm (see Materials and

methods for details) to reconstruct the sequence of stimulatory light pulses using the quantified single-cell

trajectories of nuclear ERK KTR (Fig. 1D). The algorithm was designed to predict the timing of light

pulses using a short (overall, 8 minute-long) window sliding over the ERK KTR translocation trajectory.

The method was typically able to predict the pulse timing with one-minute resolution (Fig. 1F), markedly

better than any individual pulse feature (*cf*. Fig. 1E–F). The percentage of detected pulses increases

sharply with the time interval between the pulse to be detected and the previous pulse, reaching about 70%

for the interval of 10 min and nearly 90% for the interval of 15 min (Fig. 1G). Missed pulses, pulses

detected as occurring earlier or later (proportion of which is shown in Fig. 1G), and false detections are

responsible for the information loss.

Fig 1. Decoding pulsatile signals relayed through the MAPK/ERK pathway.

(A)   Input: three considered protocols of encoding information in a pulse train. In binary encoding, a pulse is

152   either present or not in each of the temporally equidistant slots. In interval encoding, information is carried by

153   the lengths of time intervals between subsequent pulses. The intervals are drawn from a geometric

154   distribution (with one-minute resolution). In interval encoding with a minimal gap, the intervals are drawn

155   from a geometric distribution and a fixed "gap" is added. Small numbers in bold typeface denote intervals

156   between pulse slots (in binary encoding) and inter-pulse intervals (in both interval encodings).

157   **(B)**   Diagram of the MAPK/ERK pathway within the engineered MCF-10A cells. Blue light activates optoFGFR,

158   triggering a kinase cascade, which culminates in ERK activation. The fluorescent (mRuby2) ERK KTR,

159   which in non-stimulated cells is mostly localized to the nucleus, upon phosphorylation by active nuclear ERK

160   (ppERK) is exported to the cytoplasm. (A drop of) the mean nuclear fluorescence of ERK KTR is used as a

161   proxy of its translocation and ERK activity.

162   **(C)**   Output: ERK KTR translocation in response to activation of optoFGFR by a light pulse at t_0. Nuclear

163   contours of 13 cells are marked with different colors. For the sake of presentation, microscopic images are

164   normalized such that the original 10%–90% quantiles of pixel intensity span over the whole grayscale range,

165   black to white.

166   **(D)**   Input reconstruction: time track of ERK KTR translocation in response to a sequence of 4 light pulses in the

167   13 cells marked in panel C. The shaded interval is the interval in which the snapshots shown in panel C were

168   acquired; the trajectories correspond to respective color-coded nuclear outlines shown in panel C. Green bars

169   show the proportion of cells (estimated based on 400 single cell trajectories) in which a pulse was detected by

170   the trained classifier.

171   **(E)**   Histograms of three basic temporal features characterizing the ERK KTR translocation profile: time to the

172   largest translocation increment, the peak of translocation, and the largest translocation decrement (all with

173   respect to the time of a light pulse that elicited the characterized response). In a typical cell, the translocation

174   has the steepest slope between 2 and 3 min after the light pulse, reaches the maximum at 6 min, and rebounds

175   at the highest rate between 10 and 11 min after the light pulse. Data from all 6 experiments with the interval

176   encoding protocol.

177   **(F)**   Accuracy of the light pulse detection. Most of the pulses are detected exactly with one-minute

178   resolution. Data as in panel E, classifier trained on other cells from the same experiment.

179 **(G)** Proportion of cells in which a pulse was detected as a function of the interval after the previous pulse. Data as

180 in panel F.

Bitrate estimation

We computed the information loss along the pathway as the entropy of the input conditioned on its

(classifier-based) reconstruction from single-cell ERK KTR trajectories, $H(S/R)$. Next, by subtracting the

information loss from the input entropy $H(S)$, we quantified the transmitted information $I(S/R)$, and

eventually, by dividing the result by experiment duration, we estimated the bitrate. It is important to stress

that our method of pulse detection is based only on an 8-min rolling window, hence we do not use prior

knowledge about the minimal gap between pulses.

In Fig. 2A we show 10 example single-cell ERK KTR translocation trajectories of cells responding to

the first sequence used in the binary encoding protocol with the time span between subsequent digits

(clock period) $\tau_{clock} = 10$ min. The percentage of cells identified as responding to light pulses varied from

around 80% to nearly 100%. As expected, the detectability is higher when the time span from the

preceding pulse is 20 min or more (more than 95% pulses are detected). A tiny percentage of cells, $\leq 1\%$,

was incorrectly identified as responding at time points without a light pulse.

For the binary protocol we performed experiments for 7 different clock periods ranging from 3 to 30

min (Fig. 2B). The input information rate, 1 bit/τ_{clock}, decreases with increasing τ_{clock} but, as expected, for

longer τ_{clock} the fraction of information lost due to missed pulses or false detections is lower. For the

shortest τ_{clock} of 3 min, the input information rate reached 20 bit/h, but due to severe information loss the

transmitted information rate was lower than for $\tau_{clock} = 5$ min (Fig. 2B). It should be noted that in the case

of the binary encoding protocol during input reconstruction we utilize the *a priori* knowledge of the time

points in which the light pulses could have occurred ("pulse slots"). Thus, based on the ERK KTR

translocation trajectory we have to decide only whether the light pulses occurred in these time points or

not. This makes the reconstruction easier than in the interval encoding protocols, however binary

encoding appears rather artificial in the biological context.

In Fig. 2C we show a representative part of ERK KTR translocation trajectories in 10 cells responding

to stimulation with light according to the interval encoding protocol with $\tau_{geom} = 32$ min. For all but one

input pulse the percentage of cells identified as responding timely exceeds 75% and is generally higher for

pulses occurring after a longer time span from the previous pulse. For inter-pulse intervals below 10 min,

the detectability decreases rapidly (for example, the pulse at minute 744 that occurred 8 min after its

predecessor was detected timely by only 25% of cells). For each pulse there is also a fraction of

detections that indicate an input pulse 1 min before or after the true pulse.

We performed 6 experiments according to the interval encoding protocol with τ_{geom} ranging from 22 to

55 min (Fig. 2D). The highest bitrate of 6.3 bit/h was found for τ_{geom} 36 min, while for $\tau_{geom} = 32$ and 42

min the bitrate was found equal 5.3 and 5.0 bit/h, respectively. The shortest (22 min) and longest (55 min)

average intervals resulted in, respectively, the highest and the lowest information loss. This causes that

for these two suboptimal protocols, having respectively high (15 bit/h) and low (7.7 bit/h) input

information rate, the bitrate is similar, between 4 and 5 bit/h. The information is lost due to the imprecise

detections (that carry incomplete information about the timing of pulses), missed pulses and false

detections (Fig. 2D). The estimation of the information loss due to these three types of signal

reconstruction errors is outlined in S2 Fig, panels C–E, and described in Materials and methods.

In Fig. 2E, we show 10 example trajectories for the interval encoding protocol with $\tau_{geom} = 10$ min and

a gap of $\tau_{gap} = 20$ min (giving together the mean inter-pulse interval equal 30 min). The ERK KTR

translocation pulses are well distinguishable and thus in around 90% of single-cell trajectories the

stimulation pulses were reconstructed with one-minute resolution. For this protocol the bitrate was found

to be the highest, equal 7.0 bit/h based on two experimental replicates (Fig. 2F). The somewhat lower

bitrate of 6.2 bit/h was found for the protocol with $\tau_{geom} = 8$ min and $\tau_{gap} = 15$ min (average of two

replicates). As for the previous protocol, information is lost due to the three types of errors.

Fig. 2. Pulse detection and bitrate estimation in three protocols.

(A) Binary encoding: 10 representative trajectories from an experiment with slots every $\tau_{clock} = 10$ min. Stimulation pulses are marked with blue down-pointing triangles. Small filled circles indicate light pulses detected based on the corresponding trajectories. Percentage-labeled green bars in each pulse slot show the fraction of cells in which a pulse was correctly detected. Fractions of false positive detections are shown as percentage-labeled gray bars.

(B) Binary encoding: bitrate and sources of bitrate loss in experiments with various clock periods. In each column, total height of the stacked bars is equal to the input entropy rate. The number of analyzed cell trajectories was 3200 for clock periods τ_{clock} ranging from 3 to 15 min and 1200 for $\tau_{clock} = 20$ and 30 min. Each analyzed cell trajectory contained 19 pulse slots.

(C) Interval encoding: 10 representative trajectories from the experiment with the mean interval $\tau_{geom} = 36$ min. Stimulation pulses are marked with blue down-pointing triangles. Colored dots indicate light pulses

detected based on the corresponding trajectories. Green bars show the fraction of cells in which a pulse was

detected in a particular minute.

(D) Interval encoding: bitrate and sources of bitrate loss in experiments with various mean intervals. In each

column, total height of the stacked bars is equal to the input entropy rate. The number of analyzed cell

trajectories was 400 in each of 6 experiments. The mean number of light pulses in analyzed trajectories was

in the range 24–60 depending on the mean interval (all experiments lasted 27–33 h).

(E) Interval encoding with a minimal gap: 10 representative trajectories from the experiment with a minimal gap

of $\tau_{gap} = 20$ min and the inverse of the optimized geometric distribution parameter $\tau_{geom} = 10$ min. Graphical

convention as in panel C.

(F) Interval encoding with a minimal gap: bitrate and loss sources in experiments with various minimal gaps and

mean intervals. In each column, total height of the stacked bars is equal to the input entropy rate. The number

of analyzed cell trajectories was 400 in each of 9 experiments. The mean number of light pulses in analyzed

trajectories was in the range 19–96 depending on the mean interval (all experiments last 27–33 h).

Latency and accuracy of signal detection

In Fig. 3A–C we gathered all the experiments to estimate the maximum bitrate that can be achieved across

all 3 protocols. From 6 to 9 experiments performed for each protocol we selected 2–4 experiments for

which we obtained the highest bitrate, and estimated the lower bound of the maximum bitrate as the

average over these selected experiments. As a result, we obtained the following bounds (mean ± standard

error of the mean):

• 4.1 ± 0.1 bit/h for the binary encoding protocol with the optimal clock period (τ_{clock}) in the range of

5–7 min,

• 5.6 ± 0.4 bit/h for the interval encoding protocol with the optimal average interval (τ_{geom}) in the

range of 32–42 min, and

• 6.6 ± 0.3 bit/h for the interval encoding protocol with a minimal gap, with the optimal gap interval

(τ_{gap}) in the range of 15–20 min and the (inverse of the) corresponding geometric distribution

parameter (τ_{geom}) in the range of 8–10 min.

Altogether, the above results show that the channel capacity of the MAPK/ERK pathway exceeds 6 bit/h

and suggest that the highest bitrate can be achieved for the interval encoding protocol with a gap.

We should mention that the bitrate estimations were obtained after rejecting the fraction $f = 20\%$ of

ERK KTR trajectories that exhibit the lowest variability, that is, those with the smallest average square

change of the nuclear intensity between subsequent snapshots. As we can see in S3 Fig, panel A, the

maximum bitrate estimated for each of three protocols is an increasing function of f for f in the range from

0 to 50%. In the case of the binary encoding, the maximum bitrate increases nearly linearly with f, which

results from the fact that for short clock periods lower variability directly corresponds to lower chance of

responding to a light pulse. However, for the interval encoding protocol the most significant increase is

observed in the range 0–20%, which motivated us to remove 20% trajectories. At least some of these

trajectories come from cells with optoFGFR or ERK KTR not functioning properly.

In S3 Fig, panels B–D, we show the histograms of bitrate measured for single cells in all experiments

for the three encoding protocols. The orange area in the histograms corresponds to the removed 20%

fraction of cells. We can notice that the histograms for the interval encoding protocol with a minimal gap

are bimodal, but by removing the 20% of cells we may eradicate the lower mode, which additionally

justifies the choice of the particular value of f (for consistency we removed the same fraction of

trajectories from experiments for the other two protocols).

All bitrate estimations are based on the ERK KTR translocation trajectory analyzed in an 8 min-wide

rolling window that ends $t_D = 5$ min after the hypothetical pulse to be detected (t_D stands for 'time to

decision'). This means that we account for information that is available for each cell 5 min after the pulse

that the cell is expected to recognize. In Fig. 3D we give the maximal bitrate estimates (for the interval

encoding protocol with a minimal gap jointly for the experiments with the highest bitrate, encircled in

Fig. 3A–C) as a function of t_D. We found that increasing t_D beyond 5 min only marginally increases the

bitrate, while decreasing it below 3 min dramatically decreases the bitrate (which possibly reflects the fact

that the maximum increment is usually observed between 2 and 3 min after the pulse).

Fig 3. Channel capacity estimation – reconstruction-based approach.

(A)–(C) Information transmission rate for the three protocol families. In A, each data point is a mean of 8–10

experiments, and standard deviation of these replicates is shown. In B and C, where each point corresponds to

a single replicate, the standard deviation of the estimates obtained after 10 random train–test splits of the 400

cell trajectories is shown. The maximum bitrate for a given protocol is estimated (from below) as the mean ±

standard error of the mean of 2–4 encircled points and marked with a dashed line.

(D)–(E) Lower bound of maximum bitrate as a function of time from pulse to its detection for two interval encoding

protocols. Points correspond to experiments encircled in panels B and C; line shows the average over these

experiments. Pulse detection is based on the ERK KTR trajectory window that begins 2 min before a pulse

slot and ends at the time after the pulse slot indicated on the horizontal axis (classification is always based on

three overlapping slices of their length adjusted to the length of the window). The 8 min-long window (red

circle) was used for pulse detection throughout the paper.

Reconstruction-free bitrate estimation

An advantage of the reconstruction-based approach is that it enables discerning particular sources of classification errors (as shown in Fig. 2B, 2D, and 2F) and provides insight into information available to a responding cell. On the other hand, any classifier loses some information about the responding cell and thus provides a lower bound on the estimate of the cell capability of transmitting information. Therefore (prompted by an anonymous Reviewer), we performed a direct (reconstruction-free) estimation of the information transmission rate for both families of interval encoding protocols. We used the kNN ($k = 20$) algorithm to estimate the conditional entropy $H(S/R)$, where R is the quantified response, and obtain $I(S,R)$ = $H(S) - H(S/R)$. Then, by dividing the result by experiment duration, we estimated the bitrate, see Materials and methods. As in the reconstruction-based approach, we used an 8-min rolling window. As shown in Fig. 4A and 4B, the reconstruction-free estimates are about 2 bit/h higher than those obtained in the reconstruction-based approach, and equal (mean ± standard error of the mean):

- 8.2 ± 0.1 bit/h for the interval encoding protocol (based on four data points encircled in Fig. 4A) and

- 8.5 ± 0.2 bit/h for the interval encoding protocol with a minimal gap (based on six data points encircled in Fig. 4B).

Fig 4. Channel capacity estimation – reconstruction-free approach.

(A)–**(B)** Information transmission rate for two families of interval encoding protocols. Error bars indicate the

standard deviation of the estimates obtained after 10 random resamplings of 50% (200 out of 400) cell

trajectories. The maximum bitrate for a given protocol is estimated as the mean ± standard error of the

mean of 4 or 6 encircled points and marked with a dashed line.

The largest difference between the reconstruction-based and the reconstruction-free approach can be

observed for data points corresponding to the shortest mean intervals (*cf*. Fig. 3B and Fig. 4A).

Heuristically, it can be explained as follows: In the reconstruction-based approach, the small missed pulse

errors (occurring for pulses preceded by long intervals) are averaged with large missed pulse errors

(occurring for pulses preceded by short intervals). Thus, for short mean intervals, the average fidelity of

the pulse reconstruction is relatively low which implies high $H(S/R)$ calculated from the confusion matrix.

To illustrate this with a simple example: when one sends 20 zero-one digits, and the first 10 of them are

received with $p = 1$ confidence, while remaining with $p = \frac{1}{2}$ confidence, then the transmitted information

is 10 bits (provided that the receiver knows which bits should be trusted). However, when the receiver

does not know which bits should be trusted, the averaged confidence is $p_a = \frac{3}{4}$, which implies that the

transmitted information is $20\,(1 - H(S/R)) = 20\,(1 + p_a \log_2(p_a) + (1 - p_a) \log_2(1 - p_a)) \approx 3.8$ bit. In the

reconstruction-free approach the uncertainty about pulses is not averaged.

Discussion

Toettcher *et al*. [27] showed that the RAS–ERK module of the MAPK pathway may transmit input signals

across a broad range of timescales, from 4 min to multiple hours. Here, by applying signal reconstruction-

based approach we estimated the information transmission rate from FGFR to an ERK activity reporter to

find that the MAPK/ERK channel capacity exceeds 6 bit/h. In a direct, reconstruction-free approach, we

obtained a higher estimate of 8.5 bit/h, which shows that at the signal reconstruction step a substantial

portion of information is lost. It is debatable, however, whether cells can utilize the input information

without "reconstructing the signal".

We analyzed three protocols to encode information: binary encoding, interval encoding, and interval

encoding with a minimal gap, to find that interval-encoded information can be transmitted at a

significantly higher bitrate than binary-encoded information. The presence of a minimal gap between

pulses of length comparable to the refractory time (*i.e.*, time in which the cell may not unambiguously

respond to a subsequent pulse) further increases the bitrate (although this increase is small for the

reconstruction-free approach). The lower bound of the MAPK/ERK channel capacity found in this study

is well above our earlier purely theoretical estimates [28], which suggested a bitrate between 1.4 and 1.9

bit/h. Those MAPK-model estimates were obtained for the binary protocol, but the main source of

discrepancy is the longer refractory time of ~50 min, arising in the computational model [29]. Interval

encoding appears the most natural from the biological perspective as it assumes that pulses occur

independently with some constant intensity (the mean interval is the inverse of the intensity). These

random pulses can be associated with single-cell apoptosis, which recently has been found to trigger

synchronous ERK activation [30] that propagates radially for about three cell "layers" [17].

Using the reconstruction-based approach we found that for the interval encoding with a minimal gap

the bitrate may exceed 6 bit/h, which can be considered as a "safe" lower bound on the MAPK/ERK

channel capacity. The fact that interval encoding is associated with the highest bitrate follows from the

cells' ability to respond to light pulses in a very synchronous manner. The light pulses can be detected

nearly perfectly with one-minute resolution (provided that the time from the preceding pulse is longer than

the refractory time), based on the ERK activity in an 8-min interval ending 5 min after the light pulse.

Synchronous responses to the stimuli may enable long-distance waves of ERK activity that assist wound

healing, inducing collective cell migration [18,31]. In our experiments we do not observe communication

between cells, because all cells are illuminated equally and simultaneously. However, when cells are

stimulated in a single spot only, for example due to an apoptotic event, one may observe propagation of an

ERK activity wave outside of this spot [17,32]. This clearly indicates for cell-to-cell communication and

propagation of information. One could expect that even if such wounding- or apoptosis-generated waves

are initiated at small time intervals, the first "layer" of cells filters out the pulses that occur within the

refractory time, and thus the farther "layers" of cells will be subjected to stimulation that resembles the

interval encoding with a minimal gap.

Since we have not investigated signaling with resolution finer than 1 min we may not rule out that the

MAPK/ERK channel capacity exceeds the determined lower bound of 6 bit/h. Using finer temporal

discretization would increase the entropy of the input, but in the reconstruction-based approach it would

also result in more classification errors, therefore both $H(S)$ and $H(S|R)$ would be increased. Even for one-

minute resolution, a substantial part of information loss is due to inaccurate detections (see Fig. 2D and

2F).

In our analysis we lumped together responses of different cells. This is known to reduce the measured

information transfer because cell-to-cell differences in responses are treated as noise. As observed earlier

by Toettcher *et al*. [27], individual cells exhibit precise and reversible Ras/ERK dose-response behavior;

in our case we observe that there are faster and slower cells, and this causes that we occasionally

reconstruct pulses with 1 minute delay or 1 minute in advance. By learning about each individual cell

from its response to first light pulses, one could use its response to reconstruct subsequent pulses with

higher accuracy; such type of analysis was performed by Selimkhanov *et al.* [7]. However, when one

aims at interpreting transmitted information as the ability of cells to exhibit synchronous responses to

stimuli (required for ERK activity wave propagation), cell-to-cell differences can be interpreted as an

(extrinsic) noise.

Cells send, receive, and process information, however a natural question is how the information

transmitted at the rate exceeding 6 bit/h can be utilized. Intuitively, high information rate is critical when

a cell has to respond to constantly changing stimuli. Neurons were shown to transmit information at rates

of tens of bits per second [13,14]. *E. coli* chemotactic system transfers about 0.01 bit per second, and this

information rate limits its drift velocity in shallow chemical gradients [15]. Meier *et al*. [16] showed that

D. discoideum (chemotaxis of which is known to be regulated by an atypical MAP kinase, ERKB [33,34])

may navigate in a switching chemotactic gradient, changing its direction within a minute. This suggests

the information processing rate of about 1 bit per minute, or less if some cell switch-or-not decisions are

incorrect.

In higher organisms, the MAPK/ERK pathway is known to coordinate diverse complex behaviors and

cell fate decisions, such as cell proliferation, differentiation, migration, senescence and apoptosis [35].

The distinction between particular cell fates depends on ERK pulsatile activity integrated over timescales

of multiple hours [36]. RAS-to-ERK cascade transmits signals (and information) from numerous inputs to

numerous outputs regulated by ERK and its upstream components, MEK, RAF, and RAS. During

collective cell migration, ERK controls myosin contractile pulses [37]. Spatially localized RAS activation

is responsible for formation of actin-based cell protrusions [38], which arise and contract at the timescale

of single minutes [39], directing cell motion. Since ERK works as a RAS-activated (via RAF and MEK)

RAS inhibitor [40], the ERK activity profile influences cell protrusion and retraction, and thus cell motion

[41]. The high information capacity of the MAPK/ERK channel demonstrated in this study enables

coordination of the versatile functions associated with ERK and its upstream kinases, with cell motion in

response to rapidly changing stimuli likely being the process the most information is fed into.

Materials and methods

Cell lines

417   The MCF-10A human mammary epithelial cells (derived from an adult female) were a gift of J.S. Brugge.

418   The cells were modified to stably express the nuclear marker H2B-miRFP703, the ERK biosensor ERK-

419   KTR-mRuby2 [42] and the optogenetic actuator optoFGFR [23] and used before in Refs. [17,25].

Cell culture

The modified MCF-10A cells were cultured in tissue-culture treated plastic flasks and fed with a growth medium composed of DMEM:F12 (1:1) supplemented with horse serum 5%, recombinant human EGF (20 ng/ml, Peprotech), L-glutamine, hydrocortisone (0.5 μg/ml, Sigma-Aldrich/Merck), insulin (10 μg/ml, Sigma-Aldrich/Merck), penicillin (200 U/ml) and streptomycin (200 μg/ml). The cells were routinely split upon reaching ~90% confluency. For time-lapse optogenetic experiments, cells were seeded on 24-well 1.5 glass bottom plates (Cellvis) coated with 5 μg/ml fibronectin (PanReac AppliChem) at 1×10^5 cells/well density in growth medium two days before the experiment. Four hours before the optogenetic stimulation (2.5 h before imaging), cells were washed twice with PBS and then cultured in a starvation medium composed of DMEM:F12 (1:1) supplemented with BSA (0.3% Sigma-Aldrich/Merck), L-glutamine, hydrocortisone (0.5 μg/ml, Sigma-Aldrich/Merck).

Optogenetic stimulation

OptoFGFR was stimulated with pulses of blue LED light (100 ms, 470 nm, 3 W/cm^2) applied according to specific stimulation protocols (see a further subsection on stimulation protocols). It should be noticed that for short pulses the response depends on the total pulse energy per unit surface, and that 0.3 J/cm^2 is above the saturation dose [25].

Imaging

Imaging experiments were performed on an epifluorescence Eclipse Ti inverted fluorescence microscope (Nikon) controlled by NIS-Elements (Nikon) with a Plan Apo air 20× (NA 0.8) objective. Laser-based autofocus was used throughout the experiments. Image acquisition was performed with an Andor Zyla 4.2 plus camera at the 16-bit depth every 1 min. The following excitation and emission filters were used: far red: 640 nm, ET705/72m; red: 555 nm, ET652/60m; green: 470 nm, ET525/36m. Imaging started 1.5 h before the onset of optogenetic stimulation (to provide proper history for ERK KTR track normalization, see a further subsection on signal processing).

Stimulation protocols

In the case of binary encoding, all stimulation protocols have 19 temporally equidistant pulse "slots". We applied the following fixed pattern of pulses: 1011010011110000101 (1=pulse, 0=no pulse), which is the shortest sequence containing uniquely every possible subsequence of four binary digits. For each "clock period" (i.e., time between pulse slots) this sequence (in one field of view) and its logic negation (in another field of view) were used. Since the clock periods ranged from 3 min to 30 min, overall protocol durations ranged from 19×3=57 to 19×30=570 min. The estimated values of the information transmission rate are means computed for tracks obtained from 2 fields of view and 4–5 biological replicates for each clock period, except for the clock periods of 20 min and 30 min, for which 10 fields of view from a single biological replicate were used.

In the case of interval encoding, the inter-pulse intervals were chosen in a randomized manner: the interval lengths were first selected to best reflect the underlying distribution, either geometric or geometric with a minimal gap, given the time budget of a single experiment (~26 h), and then randomly shuffled. A four hour-long resting period was added in the middle of the experiment to allow the cells to regenerate in 3 of 6 experiments with stimulation according to the protocol without a gap and 5 of 9 experiments with stimulation according to the protocol with a minimal gap; however, no significant difference was observed between results of the experiments with and without the resting period. The resting period and the initial 90-min starvation period were excluded from the analysis. The first pulse of the sequence and the first pulse after the resting period were also discarded as non-representative. Overall, in each protocol there were 24–131 analyzed pulses (during 25–31 h) depending on the assumed average interval between pulses.

Nuclei detection and cell tracking

The nuclei were detected in the channel of fluorescently tagged histone 2B (H2B)-miRFP703 using local thresholding. Outlines of overlapping nuclei were split based on geometric convexity defects when

possible. Outlines of nuclei that were partially out of frame were excluded from analysis. The nuclei

were tracked automatically using a greedy algorithm based on parameters such as proximity of outlines in

subsequent time points, their surface area, eccentricity, orientation, total fluorescence intensity and

intensity distribution. ERK KTR trajectories were obtained by calculating within each tracked nuclear

outline the mean intensity in the ERK KTR channel. All image processing was performed within our

custom software, SHUTTLETRACKER.

Signal processing

For each tracked nucleus, the mean ERK KTR intensity in its contour was quantified and normalized, first

with the whole-image mean intensity in the ERK KTR channel (to compensate for possible global changes

in fluorescence), and then with the average over the cell 120-min history (to account for variation in ERK

KTR expression or its uneven visibility in individual cells). Such normalized values were subtracted from

1 and then referred to simply as 'ERK KTR translocation' and denoted x_t, where t indicates a time point

and directly corresponds to the minute of the imaged part of the experiment. Of note, for nuclear ERK

KTR signal constant in time, such normalization and linear transformation would imply $x_t = 0$.

Selection of tracks

483   In each field of view, we ranked tracks by their length and then by their quality, defined as low variation

484   of the nuclear area within the track, and preselected 500 top scoring tracks. To eliminate cells that

485   responded weakly to stimulation, for example due to low reporter expression, we further rejected 100

486   tracks (20%) with the lowest sum-of-squares of the discrete derivative of the ERK KTR translocation

487   trajectory (computed after only the first step of normalization).

Input reconstruction

Binary encoding. For each experiment, 200 out of the 400 ERK KTR translocation trajectories were

randomly selected as a train set, and 200 trajectories from cells stimulated with the negated sequence as

the test set. For each potential light pulse time point t_0, referred to as "slot", we extracted slices of $\ell = 6$

subsequent time points beginning at three different shifts with respect to t_0: 2 min before the slot (that is,

from $t_0 - 2$ to $t_0 + 3$), 1 min before the slot (from $t_0 - 1$ to $t_0 + 4$), and exactly on the time point of the slot

(from t_0 to $t_0 + 5$). For each slice we computed $\ell - 1$ discrete backward derivatives, $\Delta x_t = x_t - x_{t-1}$.

Separately for each of the three sets of slices (corresponding to a specific shift with respect to t_0), a kNN

($k = 20$) classifier [43] with ($\ell - 1$)-dimensional Euclidean distance was trained and evaluated so that each

slice in the test set was labeled with 0/1 depending on the predicted occurrence of a light pulse in its slot.

In this way, three 0/1 labels were assigned to a single slot. To obtain input signal reconstruction in each

slot of x_t, an ensemble classifier combined three binary predictions through hard voting, $i.e.$, pulse is

confirmed if two or three predictions are 'yes'. In the estimation of the confusion matrix (described

further), the whole procedure was repeated for 10 random resamplings of the training set and the test set.

We checked that the reconstruction is not improved for higher k.

Interval encoding. The ERK KTR translocation trajectories from each experiment were split into the

training set (200 randomly selected trajectories) and the test set (200 remaining trajectories). Each

trajectory was represented as a set of overlapping slices of $\ell = 6$ subsequent time points. The slices

constitute a perfect 6-fold coverage meaning that each (non-terminal) time point belongs to 6 (partially

overlapping) slices. Each slice was labeled with the "time after pulse" (TAP) being the time from the last

light pulse to the last time point of the slice (or from the previous pulse if this time is shorter than 3 min);

this adjustment is important in the case of very short, 3–4 min, inter-pulse intervals). For each slice we

computed $\ell - 1$ discrete backward derivatives, $\Delta x_t = x_t - x_{t-1}$. A kNN ($k = 20$) classifier [43] with ($\ell - 1$)-

dimensional Euclidean distance was trained to predict a TAP associated with each slice. Slices with TAP

values of 3, 4, or 5 min were used to predict pulses through hard voting: time points indicated by at least

two of three slices were considered as time points having a light pulse in the final reconstruction (see S2

Fig, panels A–B). To additionally prevent a single pulse from being predicted multiple times, if more than

one prediction was indicated within any three subsequent time points, all predictions except the first one

were discarded. In the estimation of the contingency table (described further), the whole procedure was

repeated for 10 different random partitionings of trajectories into the test set and the train set.

Let us notice that in both the binary and the interval encoding protocols, the decision whether to

classify a given time point t_0 as a point containing a light pulse was made based on 3 subsequent, partially

overlapping slices of length 6, which cover 8 subsequent values of x_t (for t ranging from $t_0 - 2$ to $t_0 + 5$).

Thus, only information available to a cell 5 min after the pulse was used by the trained ensemble classifier

to make a prediction. In Fig. 3D–E, the length of this window is varied to check how fast information is

accumulated.

Bitrate computation

525   We estimated the bitrate as the amount of information $I(S, R)$ between the input signal S and the elicited

526   response R sent within an interval corresponding to the total input duration Δt according to the formula:

$$i(S, R) = \frac{I(S,R)}{\Delta t} = \frac{H(S) - H(S|R)}{\Delta t} = \frac{H(S)}{\Delta t} - \frac{H(S|R)}{\Delta t} \tag{3}$$

528   where $H(S)$ is the entropy of an input signal and $H(S/R)$ is the entropy of the input conditioned on the

529   response in the case of reconstruction-free approach or on the output-based reconstruction of the input in

530   the case of reconstruction-based approach. As described below, the input entropy rate, $h(S) := H(S)/\Delta t$,

531   may be determined theoretically, whereas the conditional entropy $H(S/R)$ is calculated based on ERK KTR

532   translocation trajectories.

Input entropy rate

534   In the case of the binary encoding protocol, input sequences contain 0/1 digits occurring independently

535   with identical probabilities of ½ in temporally equidistant pulse slots. The entropy of such 19-digit input

536   sequences is $H_{\text{binary}}(S) = 19$ bits. When digits occur in pulse slots τ_{clock} apart, then the input entropy rate

537   per digit is

$$h_{\text{binary}}(S; \tau_{\text{clock}}) = \frac{19 \text{ bits}}{19\,\tau_{\text{clock}}} = 1 \text{ bit}/\tau_{\text{clock}} \tag{4}$$

Since τ_{clock} is the clock period of the binary encoding protocol, equation (4) expresses the input entropy

rate per clock period.

In the case of the interval encoding protocols, intervals between pulses are drawn at random from the

geometric distribution with the rate parameter $p = 1/\tau_{\text{geom}}$ and are optionally lengthened by adding τ_{gap}.

The entropy of the geometric distribution is

$$-\frac{p \log_2 p + (1-p) \log_2 (1-p)}{p} = \tau_{\text{geom}} \log_2 \tau_{\text{geom}} - \left(\tau_{\text{geom}} - 1\right) \log_2 \left(\tau_{\text{geom}} - 1\right) \tag{5}$$

so the input entropy rate $h_{\text{interval}}(S; \tau_{\text{geom}}, \tau_{\text{gap}})$ is

$$h_{\text{interval}}(S, \tau_{\text{geom}}, \tau_{\text{gap}}) = \frac{\tau_{\text{geom}} \log_2 \tau_{\text{geom}} - (\tau_{\text{geom}} - 1) \log_2 (\tau_{\text{geom}} - 1)}{\tau_{\text{geom}} + \tau_{\text{gap}}} \tag{6}$$

where $\tau_{\text{geom}} + \tau_{\text{gap}}$ is the mean inter-pulse interval. Since in the interval encoding protocols, digits 0/1

occur at the one-minute resolution, h_{interval} computed in Eq. (6) is also the entropy per digit. For the

interval encoding protocol (nominally without a minimal gap), τ_{geom} was varied and a technical τ_{gap} of 2

min was introduced in experiments to avoid ambiguities in signal reconstruction. For the protocol with a

minimal gap, τ_{gap} was varied and τ_{geom} was adjusted through numerical optimization to maximize

$h_{\text{interval}}(S; \tau_{\text{geom}}, \tau_{\text{gap}})$.

Conditional entropy – reconstruction-based approach

For the binary and the interval encoding protocols, we estimate from above the conditional entropy $H(S|R)$

per digit of the input given its reconstruction (throughout this section, R denotes input reconstruction). In

light of equation (3) this will provide us with a lower bound on the bitrate $i(S, R)$. Entropy of a joint

distribution is lower than the sum of individual entropies [44], thus

$$H(S|R) \leq \sum_d H(S_d|R) \tag{7}$$

where S_d is a single input digit and $H(S_d|R)$ is the entropy of that input digit conditioned on the whole-

sequence reconstruction R. The equality holds only when R and S jointly are a Markov process, this is,

when digits occur independently and the reconstruction of a given digit does not depend on other digits.

Of note, in our experiments the input digits are independent for the binary encoding protocol, but

dependent for the interval encoding protocol with a (minimal) gap. However, even for the binary

encoding protocol, the probability of detecting a pulse (digit '1') depends on the time interval from the

previous '1'.

Further, from the data processing inequality [44], for the binary encoding protocol, we have

$$H(S_d|R) \leq H(S_d|R_d) \tag{8}$$

568   where $H(S_d|R_d)$ is the entropy of an input digit S_d conditioned on its reconstruction R_d, and for the interval

569   encoding protocols we have

$$H(S_d|R) \leq H(S_d|(R_{d-1}, R_d, R_{d+1})) \tag{9}$$

571   where $H(S_d|(R_{d-1}, R_d, R_{d+1}))$ is the entropy of S_d conditioned on three subsequent digits of the

572   reconstruction.

573   Taken together, from inequalities (7)–(9) we have

$$H(S|R) \leq \sum_d H(S_d|R_d) \quad \text{and} \quad H(S|R) \leq \sum_d H(S_d|(R_{d-1}, R_d, R_{d+1})) \tag{10}$$

575   which means that to obtain upper bounds on conditional entropies for the binary encoding and the interval

576   encoding protocols we have to calculate $H(S_d|R_d)$ and $H(S_d|(R_{d-1}, R_d, R_{d+1}))$, respectively.

577   **Calculation of $H(S_d|R_d)$ for binary encoding.** To obtain $H(S_d|R_d)$, we calculated the confusion matrix

578   between S_d and R_d:

$$
\begin{array}{c c}
 & R_d \\
 & \begin{array}{c c} 1 & 0 \end{array} \\
S_d \begin{array}{c} 1 \\ 0 \end{array} & \begin{array}{c c} TP & FN \\ FP & TN \end{array}
\end{array} \tag{11}
$$

580   where TP, FP, FN, TN are, respectively, the probabilities of true positive detections, false positive

581   detections ("false detections"), false negative detections ("missed pulses"), and true negative detections

582 averaged over all time points, all selected tracks, and all partitions of data into the train set and the test set.

583 Based on this confusion matrix we calculated $H(S_d|R_d)$ according to the definition as:

584
$$H(S_d|R_d) = -E(\log_2 p(S_d|R_d)) = -\sum_{s,r\in\{0,1\}} p(S_d = s, R_d = r) \log_2 \frac{p(S_d=s,R_d=r)}{p(R_d=r)} \qquad (12)$$

585 **Calculation of $H(S_d|(R_{d-1}, R_d, R_{d+1}))$ for interval encoding.** For this encoding, we computed the

586 contingency table showing the relation between S_d and the reconstruction of the three subsequent digits

587 (R_{d-1}, R_d, R_{d+1}), which also accounts for information carried by inaccurate detections:

588
$$
\begin{array}{c}
(R_{d-1}, R_d, R_{d+1}) \\
\begin{array}{c|cccc}
 & (0,0,0) & (1,0,0) & (0,1,0) & (0,0,1) \\
\hline
S_d \quad 1 & p_{(0,0,0);1} & p_{(1,0,0);1} & p_{(0,1,0);1} & p_{(0,0,1);1} \\
\quad\;\; 0 & p_{(0,0,0);0} & p_{(1,0,0);0} & p_{(0,1,0);0} & p_{(0,0,1);0}
\end{array}
\end{array}
\qquad (13)
$$

The entries of the contingency table are joint probabilities $p_{(r-,\,r0,\,r+);s} = p(S_d = s, (R_{d-1}, R_d, R_{d+1}) =$

$(r_-, r_0, r_+))$ of input signal $s \in \{0, 1\}$ and reconstructed input $(r_-, r_0, r_+) \in \{(0,0,0), (1,0,0), (0,1,0), (0,0,1)\}$.

In contrast to the confusion matrix for the binary encoding, these joint probabilities have no

straightforward interpretation in terms of TP, FP, FN, TN or inaccurate detection probabilities. The

combinations of (R_{d-1}, R_d, R_{d+1}) containing two or three 1s do not occur due to the prior elimination of

detections that are closer than 3 min apart. The conditional entropy was calculated according to the

definition as:

596
$$H(S_d|(R_{d-1}, R_d, R_{d+1})) = -\sum_{s,r_-,r_0,r_+\in\{0,1\}} p_{(r_-,r_0,r_+);s} \log_2 \frac{p_{(r_-,r_0,r_+);s}}{p(R_d=r)} \qquad (14)$$

597 To summarize, bitrate may be computed based on equation (3) with input entropy rates given by equations

598 (4) and (5) and conditional entropies given by equations (12) and (14) in the case of the binary encoding

599 protocols and in the case of interval encoding protocols, respectively.

Reconstruction-based approach – sources of information loss

To determine the sources of the information loss (Fig. 2BDF), we sequentially corrected all types of errors

in the reconstruction: false detections (false positives), missed pulses (false negatives), and for the interval

encoding protocols also inaccurate (deferred or advanced) detections. After each correction step, we

recomputed the confusion matrix/contingency table and attributed the decrease of conditional entropy and

the resulting increases of bitrate to the particular type of error. Since the obtained results depend on a

particular order of correction steps, to compare individual contributions from the three corresponding

types of reconstruction errors, we calculated each of these contributions by averaging over all possible

orders of the correction steps (2 permutations for the binary encoding protocol; 6 permutations for the

interval encoding protocols; see S2 Fig, panels C–E). Of note, each sequence of correction steps restores

exactly the input signal and the estimated bitrate losses associated with considered error types sum up to

the total bitrate loss. Since the procedure is symmetric with respect to each type of error, these

contributions may be compared.

Conditional entropy – reconstruction-free approach

To estimate the information transmission rate directly, *i.e.*, without the reconstruction step (Fig. 4), we

split the trajectories into slices of length $\ell = 8$ as described above and labeled them with 0/1 depending on

whether an input pulse occurred at the time point 5 min before the last time point in the slice. The slice

length $\ell = 8$ was chosen to comply with the reconstruction-based approach, where we used three

consecutive slices of length 6 that jointly span over an interval of 8 time points. Seven $(= \ell - 1)$ finite

differences were computed for each slice, r, embedding all slices in the 7-dimensional Euclidian space.

For each r, $k = 20$ nearest neighbors were found (including the slice itself) and the numbers n_0 and n_1 of

neighbors marked with 0 and 1, respectively, were counted $(n_0 + n_1 = k)$. For each slice, the conditional

entropy was estimated according to the formula:

623
$$H(S|r) = -\left(\frac{n_0}{k}\log_2\frac{n_0}{k} + \frac{n_1}{k}\log_2\frac{n_1}{k}\right) + \text{bias correction} \tag{15}$$

624   where (Miller–Madow) bias correction is $1/(2k \ln 2)$ if both n_0 and n_1 are non-zero, and 0 otherwise

625   [45,46]. The overall conditional entropy $H(S|R)$ was estimated by averaging $H(S|r)$ over all slices r. The

626   procedure was performed on 200 trajectories randomly chosen out of 400 cell trajectories in each

627   experiment, and repeated 10 times for different choices to evaluate the robustness of the estimate.

Acknowledgments

We thank Prof. Joan S. Brugge from Harvard Medical School, Boston, MA for providing the MCF-10A

human mammary epithelial cells line. We acknowledge support of the Microscopy Imaging Center of the

University of Bern (https://www.mic.unibe.ch).

References

1. Bowsher CG, Swain PS. Identifying sources of variation and the flow of information in biochemical networks. Proc Natl Acad Sci USA. 2012;109: E1320-1328. doi:10.1073/pnas.1119407109

2. Das J, Ho M, Zikherman J, Govern C, Yang M, Weiss A, et al. Digital signaling and hysteresis characterize Ras activation in lymphoid cells. Cell. 2009;136: 337–351. doi:10.1016/j.cell.2008.11.051

3. Markevich NI, Hoek JB, Kholodenko BN. Signaling switches and bistability arising from multisite phosphorylation in protein kinase cascades. J Cell Biol. 2004;164: 353–359. doi:10.1083/jcb.200308060

4. Tay S, Hughey JJ, Lee TK, Lipniacki T, Quake SR, Covert MW. Single-cell NF-κB dynamics reveal digital activation and analogue information processing. Nature. 2010;466: 267–271. doi:10.1038/nature09145

5. Turner DA, Paszek P, Woodcock DJ, Nelson DE, Horton CA, Wang Y, et al. Physiological levels of TNFalpha stimulation induce stochastic dynamics of NF-kappaB responses in single living cells. J Cell Sci. 2010;123: 2834–2843. doi:10.1242/jcs.069641

6. Cheong R, Rhee A, Wang CJ, Nemenman I, Levchenko A. Information transduction capacity of noisy biochemical signaling networks. Science. 2011;334: 354–358. doi:10.1126/science.1204553

7. Selimkhanov J, Taylor B, Yao J, Pilko A, Albeck J, Hoffmann A, et al. Accurate information transmission through dynamic biochemical signaling networks. Science. 2014;346: 1370–1373. doi:10.1126/science.1254933

8. Tang Y, Adelaja A, Ye FX-F, Deeds E, Wollman R, Hoffmann A. Quantifying information accumulation encoded in the dynamics of biochemical signaling. Nat Commun. 2021;12: 1272. doi:10.1038/s41467-021-21562-0

9. Tudelska K, Markiewicz J, Kochańczyk M, Czerkies M, Prus W, Korwek Z, et al. Information processing in the NF-κB pathway. Sci Rep. 2017;7: 15926. doi:10.1038/s41598-017-16166-y

10. Butts DA, Weng C, Jin J, Yeh C-I, Lesica NA, Alonso J-M, et al. Temporal precision in the neural code and the timescales of natural vision. Nature. 2007;449: 92–95. doi:10.1038/nature06105

11. Gollisch T, Meister M. Rapid neural coding in the retina with relative spike latencies. Science. 2008;319: 1108–1111. doi:10.1126/science.1149639

12. MacKay DM, McCulloch WS. The limiting information capacity of a neuronal link. Bull Math
Biophys. 1952;14: 127–135. doi:10.1007/BF02477711

13. Arnold MM, Szczepanski J, Montejo N, Amigó JM, Wajnryb E, Sanchez-Vives MV. Information
content in cortical spike trains during brain state transitions. J Sleep Res. 2013;22: 13–21.
doi:10.1111/j.1365-2869.2012.01031.x

14. Strong SP, Koberle R, de Ruyter van Steveninck RR, Bialek W. Entropy and information in neural
spike trains. Phys Rev Lett. 1998;80: 197–200. doi:10.1103/PhysRevLett.80.197

15. Mattingly HH, Kamino K, Machta BB, Emonet T. Escherichia coli chemotaxis is information limited.
Nat Phys. 2021;17: 1426–1431. doi:10.1038/s41567-021-01380-3

16. Meier B, Zielinski A, Weber C, Arcizet D, Youssef S, Franosch T, et al. Chemotactic cell trapping in
controlled alternating gradient fields. Proc Natl Acad Sci USA. 2011;108: 11417–11422.
doi:10.1073/pnas.1014853108

17. Gagliardi PA, Dobrzyński M, Jacques M-A, Dessauges C, Ender P, Blum Y, et al. Collective
ERK/Akt activity waves orchestrate epithelial homeostasis by driving apoptosis-induced survival. Dev
Cell. 2021;56: 1712-1726.e6. doi:10.1016/j.devcel.2021.05.007

18. Hiratsuka T, Fujita Y, Naoki H, Aoki K, Kamioka Y, Matsuda M. Intercellular propagation of
extracellular signal-regulated kinase activation revealed by in vivo imaging of mouse skin. Davis R,
editor. eLife Sciences. 2015;4: e05178. doi:10.7554/eLife.05178

19. Hiratsuka T, Bordeu I, Pruessner G, Watt FM. Regulation of ERK basal and pulsatile activity control
proliferation and exit from the stem cell compartment in mammalian epidermis. Proc Natl Acad Sci
USA. 2020;117: 17796–17807. doi:10.1073/pnas.2006965117

20. De Simone A, Evanitsky MN, Hayden L, Cox BD, Wang J, Tornini VA, et al. Control of osteoblast
regeneration by a train of Erk activity waves. Nature. 2021;590: 129–133. doi:10.1038/s41586-020-
03085-8

21. Albeck JG, Mills GB, Brugge JS. Frequency-modulated pulses of ERK activity transmit quantitative
proliferation signals. Mol Cell. 2013;49: 249–261. doi:10.1016/j.molcel.2012.11.002

22. Aoki K, Kumagai Y, Sakurai A, Komatsu N, Fujita Y, Shionyu C, et al. Stochastic ERK activation
induced by noise and cell-to-cell propagation regulates cell density-dependent proliferation. Molecular
Cell. 2013;52: 529–540. doi:10.1016/j.molcel.2013.09.015

23. Kim N, Kim JM, Lee M, Kim CY, Chang K-Y, Heo WD. Spatiotemporal control of fibroblast growth
factor receptor signals by blue light. Chem Biol. 2014;21: 903–912.
doi:10.1016/j.chembiol.2014.05.013

24. Bugaj LJ, Choksi AT, Mesuda CK, Kane RS, Schaffer DV. Optogenetic protein clustering and
signaling activation in mammalian cells. Nat Methods. 2013;10: 249–252. doi:10.1038/nmeth.2360

25. Dessauges C, Mikelson J, Dobrzyński M, Jacques M, Frismantiene A, Gagliardi PA, et al.
Optogenetic actuator – ERK biosensor circuits identify MAPK network nodes that shape ERK
dynamics. Mol Syst Biol. 2022;18: e10670. doi:10.15252/msb.202110670

26. Shannon CE. A Mathematical Theory of Communication. Bell Syst Tech J. 1948;27: 379–423.
doi:10.1002/j.1538-7305.1948.tb01338.x

27. Toettcher JE, Weiner OD, Lim WA. Using optogenetics to interrogate the dynamic control of signal
transmission by the Ras/Erk module. Cell. 2013;155: 1422–1434. doi:10.1016/j.cell.2013.11.004

28. Grabowski F, Czyż P, Kochańczyk M, Lipniacki T. Limits to the rate of information transmission
through the MAPK pathway. J R Soc Interface. 2019;16: 20180792. doi:10.1098/rsif.2018.0792

29. Kochańczyk M, Kocieniewski P, Kozłowska E, Jaruszewicz-Błońska J, Sparta B, Pargett M, et al.
Relaxation oscillations and hierarchy of feedbacks in MAPK signaling. Sci Rep. 2017;7: 38244.
doi:10.1038/srep38244

30. Valon L, Davidović A, Levillayer F, Villars A, Chouly M, Cerqueira-Campos F, et al. Robustness of
epithelial sealing is an emerging property of local ERK feedback driven by cell elimination. Dev Cell.
2021;56: 1700-1711.e8. doi:10.1016/j.devcel.2021.05.006

31. Aoki K, Kondo Y, Naoki H, Hiratsuka T, Itoh RE, Matsuda M. Propagating wave of ERK activation
orients collective cell migration. Dev Cell. 2017;43: 305-317.e5. doi:10.1016/j.devcel.2017.10.016

32. Gagliardi PA, Grädel B, Jacques M-A, Hinderling L, Ender P, Cohen AR, et al. Automatic detection
of spatio-temporal signalling patterns in cell collectives. bioRxiv; 2022. p. 2022.07.12.499734.
doi:10.1101/2022.07.12.499734

33. Schwebs DJ, Pan M, Adhikari N, Kuburich NA, Jin T, Hadwiger JA. Dictyostelium Erk2 is an
atypical MAPK required for chemotaxis. Cellular Signal. 2018;46: 154–165.
doi:10.1016/j.cellsig.2018.03.006

34. Nichols JME, Paschke P, Peak-Chew S, Williams TD, Tweedy L, Skehel M, et al. The Atypical MAP
Kinase ErkB Transmits Distinct Chemotactic Signals through a Core Signaling Module. Dev Cell.
2019;48: 491-505.e9. doi:10.1016/j.devcel.2018.12.001

35. Sun Y, Liu W-Z, Liu T, Feng X, Yang N, Zhou H-F. Signaling pathway of MAPK/ERK in cell
proliferation, differentiation, migration, senescence and apoptosis. J Recept Signal Transduct Res.
2015;35: 600–604. doi:10.3109/10799893.2015.1030412

36. Ender P, Gagliardi PA, Dobrzyński M, Frismantiene A, Dessauges C, Höhener T, et al.
Spatiotemporal control of ERK pulse frequency coordinates fate decisions during mammary acinar
morphogenesis. Dev Cell. 2022;57: 2153-2167.e6. doi:10.1016/j.devcel.2022.08.008

37. Hino N, Rossetti L, Marín-Llauradó A, Aoki K, Trepat X, Matsuda M, et al. ERK-Mediated
Mechanochemical Waves Direct Collective Cell Polarization. Dev Cell. 2020;53: 646-660.e8.
doi:10.1016/j.devcel.2020.05.011

38. Sasaki AT, Chun C, Takeda K, Firtel RA. Localized Ras signaling at the leading edge regulates PI3K,
cell polarity, and directional cell movement. J Cell Biol. 2004;167: 505–518.
doi:10.1083/jcb.200406177

39. Yang J-M, Bhattacharya S, West-Foyle H, Hung C-F, Wu T-C, Iglesias PA, et al. Integrating chemical
and mechanical signals through dynamic coupling between cellular protrusions and pulsed ERK
activation. Nat Commun. 2018;9: 4673. doi:10.1038/s41467-018-07150-9

40. Zhan H, Bhattacharya S, Cai H, Iglesias PA, Huang C-H, Devreotes PN. An excitable Ras/PI3K/ERK
signaling network controls migration and oncogenic transformation in epithelial cells. Dev Cell.
2020;54: 608-623.e5. doi:10.1016/j.devcel.2020.08.001

41. Tanimura S, Takeda K. ERK signalling as a regulator of cell motility. J Biochem. 2017;162: 145–154.
doi:10.1093/jb/mvx048

42. Regot S, Hughey JJ, Bajar BT, Carrasco S, Covert MW. High-sensitivity measurements of multiple
kinase activities in live single cells. Cell. 2014;157: 1724–1734. doi:10.1016/j.cell.2014.04.039

43. Pedregosa F, Varoquaux G, Gramfort A, Michel V, Thirion B, Grisel O, et al. Scikit-learn: Machine
learning in Python. J Mach Learn Res. 2011;12: 2825–2830.

44. Cover TM, Thomas JA. Elements of information theory. 2nd ed. Hoboken, N.J: Wiley-Interscience;
2006.

45. Miller G. Note on the bias of information estimates. Information Theory in Psychology: Problems and
Methods. Glencoe, IL: Free Press; 1955. pp. 95–100.

46. Paninski L. Estimation of entropy and mutual information. Neural Comput. 2003;15: 1191–1253.
doi:10.1162/089976603321780272

Supporting Information

A separate Supporting Information PFD file contains:

- **S1 Fig.** Experimental and data analysis workflow (reconstruction-based approach).

- **S2 Fig.** Interval encoding: input sequence reconstruction algorithm and determination of the sources of information loss (reconstruction-based approach).

- **S3 Fig.** Cell-to-cell bitrate variability and exclusion of non-responding cells (reconstruction-based approach).

Other supporting materials for this article include:

Source data at DOI: 10.5281/zenodo.7808385
Source code at URL: https://github.com/pawelnalecz/pulsatile-information