# Active Anemosensing Hypothesis: How Flying Insects Could Estimate Ambient Wind Direction Through Sensory Integration & Active Movement

Floris van Breugel          Renan Jewell          Jaleesa Houle

*Abstract*— **Estimating the direction of ambient fluid flow is a crucial step during chemical plume tracking for flying and swimming animals. How animals accomplish this remains an open area of investigation. Recent calcium imaging with tethered flying *Drosophila* has shown that flies encode the angular direction of multiple sensory modalities in their central complex: orientation, apparent wind (or airspeed) direction, and direction of motion. Here we describe a general framework for how these three sensory modalities can be integrated over time to provide a continuous estimate of ambient wind direction. After validating our framework using a flying drone, we use simulations to show that ambient wind direction can be most accurately estimated with trajectories characterized by frequent, large magnitude turns. Furthermore, sensory measurements and estimates of their derivatives must be integrated over a period of time that incorporates at least one of these turns. Finally, we discuss approaches that insects might use to simplify the required computations, and present a list of testable predictions. Together, our results suggest that ambient flow estimation may be an important driver underlying the zigzagging maneuvers characteristic of plume tracking animals' trajectories.**

*Keywords:* anemotaxis, anemosensing, active sensing, insect flight, plume tracking

## I. Introduction

Estimating the direction of ambient flow is a critical step for both swimming and flying animals during chemical plume tracking behaviors [1]. Without access to stationary flow sensors, however, the ambient direction of fluid flow cannot be directly measured [2]. How animals resolve this challenge remains an open area of investigation. Recent experimental work with fish has shown that they use temporal changes of flow from mechanosensory measurements to deduce flow direction during rheotaxis [3]. Comparatively less is known about how insects resolve this challenge while flying in windy environments.

Flying insects can measure *apparent wind*, corresponding to the vector sum of the ambient wind and motion induced wind. Decoupling apparent wind into its component parts is a straightforward vector subtraction if given absolute trajectory information in the same units as apparent wind. Insects, however, do not have direct access to such information, as would be available to engineered systems with access to GPS measurements. It is conceivable for an insect to estimate absolute ground speed using optic flow and inertial measurements (e.g. [4]), or to estimate ambient wind direction using a combination of optic flow and apparent wind [5]. However, both such approaches rely on calibrated measurements of the magnitude of optic flow and other modalities. Optic flow responses of insects, however, have depth- [6], texture- [7], temperature- [8], and state- [9] dependent response properties, resulting in constantly varying and unknown sensor gains. The magnitude of other sensor modalities will have similar time-dependent properties. How insects overcome these challenges to estimate ambient wind direction during flight remains an open question.

Recent advances in our understanding of insect sensory processing offer new insight. Through calcium imaging experiments, it has been found that a central part of their brain, the fan-shaped body and doughnut-shaped ellipsoid body, encodes 2-dimensional angular compass information such as head orientation from visual landmarks [10] or polarization [11], apparent wind angle from their antennae [12], [13], and angular direction of motion from vision [14]–[16]. Neuroanatomical studies suggest that similar sensory encodings exist in many invertebrates [17]. These angular encodings do not suffer from the same calibration challenges as magnitude measurements, since angular directions are equivalent to calculating the ratio of two perpendicular magnitude measurements, eliminating the unknown sensor gain. This feature and the physical overlap in the brain of the aforementioned sensory modalities presents an attractive hypothesis that perhaps they play a central role in insects' ability to estimate ambient wind direction.

One strategy that relies solely on such angular measurements, and partially explains insects' ability to orient with respect to ambient wind, is called visual anemotaxis [18]. This algorithm would allow insects to orient upwind by turning until the angle of perceived apparent wind is aligned with the angle of motion. Behavioral experiments with free and tethered flies, however, suggest that their turns are often open-loop and ballistic in nature, and not actively controlled throughout the turn itself [19]–[21]. Furthermore, their free

Dept. of Mechanical Engineering, University of Nevada, Reno, NV
Dept. of Intelligent Systems Engineering, University of Indiana, Bloomington, IN
Dept. of Mechanical Engineering, University of Nevada, Reno, NV

flight plume tracking behavior indicates that they are capable of moving crosswind at arbitrary body orientations with respect to the wind direction [22]. Together, these behavioral experiments suggest that insects may be capable of estimating the direction of ambient wind throughout their flight trajectories.

A recent nonlinear observability analysis of the three key sensor modalities encoded in the central brain of flies–orientation, apparent wind angle, and direction of motion–found that this sensor suite is mathematically sufficient for estimating the direction of ambient wind without explicitly requiring upwind orientation. Furthermore, even if both the sensors and actuators are subject to unknown additive and multiplicative calibration constants, the parameters for the angular sensors can be self-calibrated. Estimating ambient wind direction in this manner, however, is only feasible for certain trajectories, such as those where the insect changes course direction. Precisely what trajectories offer the potential for the most accurate estimates, as well as which computations are actually required to estimate the ambient wind direction, remains an open area of investigation.

This manuscript addresses the aforementioned knowledge gap through a detailed mathematical analysis and subsequent simulations. First we establish the mathematical relationships required to estimate ambient wind direction that are applicable to any estimator using the three measurements we consider. Second, we describe an optimal framework for estimating the ambient wind direction and validate the robustness of our approach using data from a flying drone. Third, we use our optimal framework to determine which types of trajectories are capable of providing the most accurate estimates under a variety of conditions. By using an optimal framework to answer this question we ensure that our results are equally applicable to other computationally simpler estimation algorithms designed for the same task. Finally, we discuss how insects might simplify the computations required to estimate ambient wind direction and discuss testable hypotheses that can be used to determine whether insects use an active anemosensing approach to maintain an internal model of ambient wind direction, or rely on visual anemotaxis to infer upwind using closed-loop feedback control.

## II. Mathematics of Estimating Ambient Wind Direction

In this section we first review visual anemotaxis, and then develop a general framework for understanding how ambient wind direction $\zeta(t)$ could be estimated. In both cases we restrict our analysis to only consider the kinematic relationships and time history of three angular measurements (Fig. 1),

$$\boldsymbol{h}(t) = [\phi(t), \gamma(t), \psi(t)]^T, \tag{1}$$

where $\phi(t)$ is the head orientation with respect to a global coordinate frame, $\gamma(t)$ is the angular direction of airspeed

relative to the head coordinate frame (which is equivalent to the direction of apparent wind $+180°$), and $\psi(t)$ is the angular direction of motion relative to the head coordinate frame. For notational simplicity we drop the $(t)$ going forward.

Fig. 1: Trigonometric relationships of the angular sensory measurements.

We begin by defining the relationship between the angular measurements $\boldsymbol{h}$, the groundspeed ($g$), and wind speed ($w$) provided by the Law of sines (see Fig. 1):

$$\frac{g}{w} = \frac{\sin(\beta)}{\sin(\delta)} = \frac{\sin(\gamma + \phi - \zeta)}{\sin(\gamma - \psi)}. \tag{2}$$

This relationship highlights the challenge of using the airspeed direction $\gamma$ to estimate the wind direction, as any changes in the value of $\gamma$ could be the result of changes in $\zeta, g,$ or $w$, none of which are available measurements for the insect.

Since we are only concerned with estimating $\zeta$, we can simplify the relationship by defining a new variable $v = g/w$ to describe a non-dimensional velocity as the ratio of ground speed and wind speed, yielding:

$$v \sin(\gamma - \psi) = \sin(\gamma + \phi - \zeta). \tag{3}$$

### A. Visual Anemotaxis (a review)

Before defining our framework for active anemosensing, we briefly review the mathematics of the visual anemotaxis hypothesis using Eqn. 3. Consider what would happen if a fly were to actively control its orientation ($\phi$) and direction of motion ($\psi$) based on sensory feedback such that changes in these states are described by the following differential equations:

$$\frac{\partial}{\partial t}\phi = \dot{\phi} = \gamma, \tag{4a}$$

$$\frac{\partial}{\partial t}\psi = \dot{\psi} = -\psi. \tag{4b}$$

Together, these control laws will ensure that the fly is oriented in the direction of its airspeed ($\gamma = 0$) and moving in the direction that it is oriented ($\psi = 0$). To understand how this effects the fly's movement relative to the ambient

wind direction we introduce a new variable for the course direction relative to the ambient wind direction,

$$\psi_\zeta = \phi + \psi - \zeta. \tag{5}$$

Next we calculate the derivative of $\psi_\zeta$, under the assumption that the fly changes its course direction much faster than any changes in the ambient wind direction (i.e. $\dot{\zeta} \approx 0$),

$$\dot{\psi}_\zeta = \dot{\phi} + \dot{\psi} - \dot{\zeta} \approx \gamma - \psi. \tag{6}$$

We now rearrange Eqn. 5 as $\phi - \zeta = \psi_\zeta - \psi$ and substitute it into Eqn. 3, followed by a substitution of $\dot{\psi}_\zeta$ for the two instances of $\gamma - \psi$ yielding the following,

$$v \sin(\dot{\psi}_\zeta) = \sin(\dot{\psi}_\zeta + \psi_\zeta). \tag{7}$$

We now solve Eqn. 7 for $\dot{\psi}_\zeta$ as follows,

$$\dot{\psi}_\zeta = \tan^{-1}\left(\frac{\sin \psi_\zeta}{v - \cos \psi_\zeta}\right). \tag{8}$$

This expression allows us to analyze the stable and unstable equilibria for global course direction in relation to the ambient wind direction for different values of $v$ using a 1-dimensional phase portrait (Fig. 2). This analysis shows that although moving downwind and upwind are both equilibria, upwind movement ($\psi_\zeta = \pm\pi$) is the only stable outcome.

Fig. 2: Visual anemotaxis guarantees stable upwind movement regardless of $v$. Each trace shows the phase portrait for different values of $v$ given Eqn. 8. The arrows provide a visual aid that shows the flow along the phase space; their direction is determined by the sign of $\dot{\psi}_\zeta$.

### B. Active Anemosensing

In contrast to visual anemotaxis, which would allow an insect to determine upwind, we now develop a framework for estimating the ambient wind direction that does not first require finding upwind. To begin, we simplify the measurement space by introducing two new variables, and rewrite Eqn. 3 as follows,

$$\alpha = \gamma + \phi, \tag{9a}$$
$$\delta = \gamma - \psi, \tag{9b}$$
$$v \sin \delta = \sin \alpha \cos \zeta - \cos \alpha \sin \zeta. \tag{9c}$$

Eqn. 9 has two unknowns $v$ and $\zeta$, resulting in an underdetermined system given the measurements $\alpha$ and $\delta$. To uniquely determine $\zeta$, we add the following constraint from the time-derivative of Eqn. 9,

$$\begin{aligned}\dot{v}\sin\delta + v\dot{\delta}\cos\delta = \dot{\alpha}\cos\alpha\cos\zeta - \dot{\zeta}\sin\alpha\sin\zeta \\ + \dot{\alpha}\sin\alpha\sin\zeta - \dot{\zeta}\cos\alpha\cos\zeta,\end{aligned} \tag{10}$$

$$\dot{v} = \frac{d}{dt}v, \tag{11a}$$
$$\dot{\zeta} = \frac{d}{dt}\zeta. \tag{11b}$$

Together, equations 9c-11 represent four equations and four unknowns, and therefore fully constrain $\zeta$ provided that derivatives of the measurements can be calculated or measured. Thus, in principle any number of methods could be used to estimate $\zeta$ using these relationships as constraints. However, solving for $\zeta$ is not a well-posed problem for all trajectories. To better understand which trajectories lead to accurate estimates under varying levels of sensory noise and for different natural wind dynamics we develop an optimal framework for estimating $\zeta$ using convex methods in the following section.

### C. Active Anemosensing using Convex Optimization

In this section we construct an objective function of the form $\ell = \|L\| + \|dL\|$ that is linear with respect to the unknowns such that it can be efficiently solved using traditional convex optimization tools.

The terms in Eqn. 10 containing $\dot{\zeta}$ include the product of two unknowns, resulting in a non-convex formulation. Thus, we introduce the assumption that the wind direction changes relatively slowly in time compared to the other dynamics. That is, for any given time window of length $\tau$ we assume that $\dot{\zeta} = 0$, but the other derivative terms may all be non-zero and time-varying.

We can now build a convex estimator that incorporates measurements from a given window of time $[k - \tau, k]$ to estimate the average wind direction for that window ($\overline{\zeta}_k$). To build our estimator we define the following two loss functions derived from Eqns. 3,10:

$$L = v \sin \delta - \sin \alpha \cos \overline{\zeta} + \cos \alpha \sin \overline{\zeta}, \tag{12a}$$
$$dL = v\dot{\delta}\cos\delta + \dot{v}\sin\delta - \dot{\alpha}\cos\alpha\cos\overline{\zeta} - \dot{\alpha}\sin\alpha\sin\overline{\zeta}, \tag{12b}$$

which define a fully constrained convex optimization problem over the time window $[k - \tau, k]$ to estimate the average ambient wind direction $\overline{\zeta}$:

$$\min_{\overline{\zeta}_k, v_{k-\tau:k}} \quad \ell_k = \|L\|_1 + \|dL\|_2 \tag{13}$$
$$\text{Given} \quad \{\alpha, \dot{\alpha}, \delta, \dot{\delta}\}_{k-\tau:k}.$$

This optimization problem will find the best estimate for
a single value of $\hat{\overline{\zeta}}_k$, and a timeseries for $\hat{v}$, given sensory
measurements from a window in time from $k-\tau$ to $k$. Because
the errors in the derivative estimates will almost always
be larger than the errors in the undifferentiated values, we
apply a $2-norm$ to $dL$ and a $1-norm$ to $L$. Although the
optimization problem given in Eqn. 13 is convex, it does
not follow Disciplined Convex Programming (DCP) rules
because of the trigonometric functions. To efficiently solve
the problem we can recast it as two DCP problems. For the
first, we divide $L, dL$ by $\cos\overline{\zeta}$, absorbing this constant term
into $v$, denoted as $v^c$, and then optimizing to find $\tan\overline{\zeta}$ using
the following expressions:

$$L^c = (\sin\delta)\, v^c + (\cos\alpha)\, \tan\overline{\zeta^c} - (\sin\alpha), \tag{14a}$$
$$dL^c = (\dot{\delta}\cos\delta)\, v^c + (\sin\delta)\, \dot{v}^c - (\dot{\alpha}\sin\alpha)\, \tan\overline{\zeta^c} - (\dot{\alpha}\cos\alpha). \tag{14b}$$

14 Extracting $\hat{\overline{\zeta^c}}$ from $\tan\hat{\overline{\zeta^c}}$ results in an ambiguity of
15 $\pm n\pi, \quad n \in \mathbb{Z}$, which we resolve using the following constraint
16 derived from Eqn. 9:

$$\text{sign}(\ \sin\delta\ ) == \text{sign}(\ \sin(\alpha - \overline{\zeta})\ ). \tag{15}$$

If $\overline{\zeta}$ happens to be close to $\pi/2 \pm n\pi, \quad n \in \mathbb{Z}$, then
dividing by $\cos(\overline{\zeta})$ can result in large errors because of the
division-by-zero that arises. Thus, to improve accuracy we
solve a second optimization problem where we divide by
$\sin(\overline{\zeta})$ instead of $\cos(\overline{\zeta})$ and optimize to find $\cot(\hat{\overline{\zeta}})$ using the
following modified expressions:

$$L^s = (\sin\delta)\, v^s - (\sin\alpha)\, \cot\overline{\zeta^s} + (\cos\alpha),$$
$$dL^s = (\dot{\delta}\cos\delta)\, v^s + (\sin\delta)\, \dot{v}^s - (\dot{\alpha}\cos\alpha)\, \cot\overline{\zeta^s} - (\dot{\alpha}\sin\alpha), \tag{16}$$

and choose the value of $\hat{\overline{\zeta}}$ from the choices $\{\hat{\overline{\zeta^c}}, \hat{\overline{\zeta^s}}\}$ that cor-
responds to the smaller of the two values for $\ell^c_{min}, \ell^s_{min}$. Note
that because we estimate an average wind direction given
measurements from a segment of time $\tau$-long, the estimate
$\hat{\overline{\zeta}}_k$ is delayed by $\tau/2$. In our analysis we automatically adjust
for this delay in order to compare the estimate to the true
values, however, in a real-time application it is important to
note the potential impact of this delay, and therefore smaller
values of $\tau$ should be preferred.

### D. Practical Considerations and Time Constants

To mitigate the effects of noise we assimilate measurement
data across time using three different time constants (Fig.
3A). Note that these time constants are fundamental to our
overall active anemosensing hypothesis, and not a specific
feature of the convex solver we implement. With respect
to our convex solver, the time constants define the window

Fig. 3: (A) Visual representation of the three time constants $(\omega, \tau, T)$ fundamental to our active anemosensing hypothesis. (B) Outline of our convex ambient wind direction estimation algorithm. Note that the convex optimization steps in the orange box could be replaced with other workflows that are less optimal but more computationally efficient by using simplifications and heuristics, as we discuss in the Discussion.

Fig. 4: Natural wind exhibits periods of both dynamic or consistent wind directions. (A) Landscape where wind measurements were collected in northern Nevada. (B) Time series of wind direction and speed. Shaded regions indicate segments used throughout our analysis. (C-D) Probability density of changes in wind direction as a function of elapsed time for the two shaded regions shown in B (see text for detail).

over which the solver is defined to operate. Therefore, the impact of these time constants on the resulting wind direction estimates should generalize beyond our particular convex solver, and we explore the impact of each of these time constants in the Results.

(1: $\omega$) Rather than use the true measurements and a naive finite difference derivative, we estimate smoothed values for the measurements ($\hat{\bullet}$), and their derivatives ($\hat{\dot{\bullet}}$), using a butterworth filter with a specified cutoff frequency, $\omega$ [23]. The cutoff frequency effectively describes the maximum frequency of expected changes in the measurement.

(2: $\tau$) To estimate the ambient wind direction, we assimilate sensory measurements over a window in time of size $\tau$.

(3: $T$) We find that resolving the $n\pi$ ambiguity (Eqn. 15) sometimes benefits from incorporating measurements across a longer time span, $T$, compared to the time span $\tau$ used for estimating $\zeta \pm n\pi$.

Figure 3B provides a visual summary of our entire convex estimation framework, taking these three practical considerations and time constants into account.

### III. Methods

This section provides an overview of our implementation of the convex estimation framework described in the prior section, real world wind measurements, candidate trajectory selections, simulations, and our drone platform for validating the robustness of our estimator framework.

#### A. Implementation of Estimation Framework

To solve the convex optimization problems outlined in Fig. 3 we used the open source python package pynumdiff to estimate butterworth smoothed derivatives [ [24], and cvxpy [25] with the proprietary MOSEK solver [26]. For computational efficiency we estimated wind directions for every $10^{th}$ time step (6 Hz for our validation experiment and 1 Hz for our simulation experiments).

#### B. Real world wind measurements

We collected wind direction and speed data using two 3-D ultrasonic anemometers (Trisonica mini, Anemoment, Longmont CO) operating at 10 Hz positioned orthogonal to one another to ensure accurate readings of both horizontal and vertical wind components. We collected data in an open desert environment (Fig. 4A) roughly similar that used in recent large scale plume tracking experiments [27]. As is common in such environments, the vertical wind component was minimal, whereas the horizontal wind varied over the course of the day, with periods characterized by low speeds and frequent changes in direction, as well as sequences with higher wind speeds and more consistent direction (Fig. 4B). We ran our simulations on two segments of this data to compare performance in dynamic and consistent wind.

To visualize the likelihood of a shift in wind direction over time, we took the difference between a point in the recorded time-series and a point at various time lags between 0.1 and 1000 seconds. The differences in wind direction at each lag were computed by moving both forward and backward in time, and those values were subsequently averaged. By repeating this analysis throughout the time-series, we were able to create a frequency distribution that encompasses every point in the series for all computed time lags. We then used this distribution to generate a heat map, which demonstrates the approximate probability and magnitude that wind direction will change at any given time over a period of 1000 seconds. In our dynamic wind segment, changes in wind direction became increasingly likely after 10-50

Fig. 5: Plume tracking flies initiate turns at 0.5 Hz and decelerate as they enter the turn. (A) Stereotypical flight trajectory of a plume tracking insect from [22]. (B) Power spectra of of the cross-wind velocity for trajectories during which flies experienced an attractive odor, are moving on average upwind, and are at least 1 second long (N=700 trajectories). (C) Angular velocity during isolated turns from the trajectories in B (n=4006 turns). Color encodes peak angular velocity. Thick lines show the average for three groups corresponding to peak angular velocity ranges of [230° − 570°], [570° − 917°] and [> 917°]. (D) Change in course angle relative to the point in time indicated by the dashed line. (E) Change in ground speed relative to the point in time indicated by the dashed line.

seconds (Fig. 4C), whereas for the consistent wind segment large changes in wind direction were rare for the entire time series (Fig. 4D).

### C. Candidate trajectories

To design our candidate trajectories, we took inspiration from previously published data on plume tracking fruit flies flying in a laminar flow wind tunnel [22]. In the presence of attractive odors, fruit flies perform upwind and crosswind flight maneuvers referred to as surges and casts (Fig. 5A). Although this behavior has received substantial attention, aspects of their flight dynamics have escaped scrutiny, which we briefly address here by reanalyzing these previously published data. To focus our analysis on plume tracking individuals, we selected trajectories with durations greater than 1 second during which an odor (ethanol) was encountered at least once while moving (on average) upwind in 0.4 m/s wind, resulting in 700 trajectories. These flies exhibited regular changes in course direction at a rate of approximately 0.5 Hz (Fig. 5B), corresponding to ∼ 1 left and ∼ 1 right turn every two seconds.

Flies generally accomplish changes in course direction using rapid turns called saccades [19]–[21], [28]. To understand the dynamics of the saccades during plume tracking specifically, we isolated individual turns from the 700 trajectories by selecting 1-second long snippets during which the flies exhibited a minimum angular velocity of 230°/sec, and no greater than 460°/sec prior or after the turn (Fig. 5C). This threshold choice is consistent with prior saccade analyses of freely flying flies which used a threshold of 300°/sec [19]. The amplitude of their turns range from small adjustments to 180° changes (Fig. 5D), with an overall average of 110°. As with flies flying in the absence of odor or wind [19], the saccade magnitude is strongly correlated with the peak angular velocity during the turn, suggesting they have an internal model of their new desired heading prior to initiating the turn, an observation that goes against the prediction of the

visual anemotaxis hypothesis. In order to make these rapid changes in direction flies first decelerate, and then accelerate as they exit the turn (Fig. 5E), though there is substantial additional variability in velocity throughout their trajectories.

Based on the behavior of plume tracking flies, we primarily consider trajectories stereotyped by regular changes in direction accompanied by synchronized changes in ground speed. We consider three categories of trajectories with small (∼20°), medium (∼90°), and large (∼160°) turn angles. For the small turn trajectories, the magnitude of each turn is selected randomly from a uniform distribution of 16-24°. For medium and large turn trajectories these uniform distributions were 72-108° and 144-171°, respectively. We applied a Gaussian smoothing kernel to these piecewise constant course directions, resulting in smooth yet still concentrated turns. Although plume tracking insects do exhibit vertical movements, we restricted our candidate trajectories to movements parallel to the ground plane for simplicity. Since natural wind typically exhibits little velocity in the vertical component, it need not be estimated. For the orientation of our simulated flies, we consider two cases inspired by the active control required by visual anemotaxis: either constant $\psi = 0$ or constant $\gamma = 0$. Finally, we also consider constant ground speed trajectories.

### D. Simulations

To determine the accuracy of ambient wind estimates for different trajectories in natural wind conditions, we simulated the trajectories described in the previous section in both the 25 minute long dynamic- and 12 minute long consistent-wind scenarios at a temporal resolution of 0.1 seconds (the time resolution of our wind data). To focus our analysis on the impact of the trajectory shape, rather than the feedback control necessary to achieve that trajectory, we programmed the trajectories kinematically, thus changes in wind speed and direction did not have any effect on the shape of the trajectories in our simulations. We justify this decision by noting

Fig. 6: Ambient wind direction estimation using the framework outlined in Fig. 3 is robust to real world sensor data. (A) Drone used for data collection. (B) Ambient wind direction and speed during piloted flight. (C) Trajectory kinematics of piloted flight provided by GPS measurements. (D) Sensor measurements (light green points) and smoothed sensor estimates (dark green lines). (E) Comparison of true wind direction (black), estimated wind direction using GPS derived ground speed measurements (blue), and estimated wind direction using the sensor data from D and the framework outlined in Fig. 3 for two different values of $T$ (red). Convex estimates are aligned based on the median time stamp in a given window for $\tau$.

that flies exhibit exceptional visual and mechanosensory feedback mechanisms for gust rejection [29]. We extracted the three sensory modalities under consideration, and applied zero-mean Gaussian noise with standard deviations ranging between $17° - 67°$. All simulations were performed with the same initial random seed to ensure a fair comparison across different conditions.

Next we smoothed the sensor measurements and estimated their derivatives using a butterworth filter and ran the estimates through our optimal estimation framework for different values of $\tau$ and $T$. For each individual wind direction estimate, we calculate the absolute value of the error between the estimate and the true wind direction.

### E. Drone hardware for validation experiments

*Platform*. To validate our estimation approach we built a quadrotor drone using a Holybro X500 frame (Fig. 6A). The drone was controlled by a PixHawk flight controller, which provides a hardware interface for certain sensors and control loops required for basic drone operations. The PixHawk was flashed with PX4 software and configured using the QGroundControl software. The drone was powered by a 14.8 V 5200 mAh 60C 4S LiPo battery (Zeee Power), which provided approximately 5-10 minutes of flight time with our full payload in 2 m/s wind. The drone was piloted manually, using a 2.4GHz controller (FrSky Taranis Q X7) that communicated flight commands to a compatible receiver (FrSky Taranis Receiver X8R) connected to the PixHawk.

*Sensors*. The PixHawk board has a built in IMU, which provides heading, attitude, angular velocities, and linear acceleration measurements at 60 Hz. To provide ground truth data for our experiment we mounted a GPS (Holybro M8N GPS) to the top of the drone which provided latitude/longitude/altitude measurements at 60 Hz. Validating our estimation protocol required two additional sensors for optic flow (which provides a measure of $\psi$) and air speed (which provides a measure of $\gamma$). For optic flow we mounted a USB camera (ELP 1080p camera with a 2.9mm wide angle lens) underneath the drone operating at 30 Hz. Image data was used to calculate 2D optic flow in real time using the Lucas Kanade algorithm [30], [31] with OpenCV [32]. For air speed measurements we mounted a 3D ultrasonic anemometer (Trisonica mini from Anemoment) to the top of the drone operating at 40 Hz.

*Data collection*. To collect sensor data, we installed an NVIDIA Jetson TX2 as a companion computer below the drone, mounted using a custom 3D printed mount. The TX2 was equipped with a 1 TB NVMe M.2 SSD for quickly recording flight data, and a PCI-e USB hub to provide sufficient inputs for our USB camera and anemometer. Above the TX2 board, we mounted a mobile wifi hotspot to provide a wireless interface to the TX2. We flashed the TX2 with Linux4Tegra and installed ROS (Robot Operating System) to provide a centralized interface to all of our sensors. We used the MavROS package to interface with the PixHawk, which provides access to the IMU measurements and RC controller inputs. Two other custom ROS packages were used to calculate optic flow and interface with the anemometer. All flight data was recorded into a single ROS bag file for offline analysis. All sensor data was linearly interpolated to the highest sensor frequency of 60 Hz prior to analysis, along

with corrections for declination and sensor orientations.

## IV. Validation

Before using our optimal estimation framework and simulation approach to understand which trajectories are best suited for estimating the ambient wind direction, we wanted to verify the algorithm's robustness to real world data. To collect validation data, we manually piloted a sensor-equipped drone in a designated radio controlled flight space (Reno Radio Control Club Field) in the northern Nevada desert (Fig. 4A). We recorded the ambient wind direction and speed with a pair of orthogonal ultrasonic anemometers (Trisonica Mini, Anemoment, Longmont CO) positioned approximately 2 m off the ground. We manually piloted the drone back and forth at 1-3 m/s (Fig. 6C) at an altitude of $\sim$ 4 m, and recorded the three sensor modalities of interest (Fig. 6D). For our butterworth smoothing filter we chose a cutoff frequency of $\omega = 0.1$ Hz, the approximate turning frequency of the drone's trajectory), which helped to reduce the inherent sensor noise.

To provide a ground truth for the ambient wind direction estimates, we vector-subtracted the absolute ground velocity from the GPS and the two horizontal components of the apparent airspeed measurements (Fig. 6E, blue). Some of the errors in this ground truth estimate are explained by vertical wind measured by the drone-mounted anemometer (linear regression $R^2 = 0.1$, $pval < 10^{-3}$). Since the ambient wind exhibited very little movement in the vertical dimension, and the drone exhibited very little pitch and yaw during its trajectory, the changes in vertical wind measured on the drone were likely due to changes in downdraft from the rotors required for stabilizing the altitude of the drone.

Finally, we applied our optimal estimation algorithm to the sensor data to estimate the ambient wind direction with $\tau = 10$ sec (the approximate turning frequency of the drone), and two values of $T$ (Fig. 6E, red). The larger value of $T = 50$ provided better discrimination between the up- and downwind options. The similarity between the ground truth estimate using GPS, and our optimal estimation approach using only angular sensor measurements, indicates that the algorithm outlined in Sec. II is sufficiently robust to handle real-world data.

## V. Results

Using a series of simulations we set out to determine which types of trajectories can provide the most accurate ambient wind direction estimates. For each candidate trajectory we consider (e.g. Fig. 7A-B), and for a variety of sensor noise magnitudes, we calculated the corresponding sensor measurements for either the dynamic or consistent wind scenario, and estimated the smoothed sensor estimates and their derivatives for a given choice of $\omega$ (e.g. using a cutoff frequency $\omega$=turning frequency: Fig. 7C). Then, for a given choice of $\tau$ and $T$ we estimated ambient wind direction values using our convex optimization framework (e.g. Fig. 7D) and calculated the associated errors (e.g. Fig. 7E). Repeating this analysis for a variety turning frequencies and values of $\tau$ and $T$ revealed that there is an optimal choice of $\tau$ for any given turning frequency (Fig. 7F). In some

Fig. 7: (A) Example simulated trajectory and (B) ground speed for a turning frequency of 0.1 Hz. (C) Sensor measurements for the trajectory shown in A-B simulated in our dynamic wind scenario (Fig. 4B, red shading) with $\mathcal{N} = (0°, 17°)$ Gaussian noise applied (light green dots), along with subsequently smoothed estimates (dark green lines). (D) Comparison of the true wind direction and estimate for $\tau = T = 10$. (E) Error in wind direction estimate for each estimate shown in D, along with the median and 95% confidence interval. Star: median error for $T = 50$. (F) Simulation results for different combinations of turning frequency, $\tau$ and $T$, plotted as in E. (G) Median error values from F plotted as a heatmap with respect to turning frequency and $\tau$. Red dashed lined: contour indicating the best performance ±5°. Ellipse: best fit ellipse representing the red dashed contour. Star: center of ellipse.

cases, particularly for small values of $\tau$, choosing $T > \tau$ provided a modest reduction in the error compared to $T = \tau$, suggesting that distinguishing between up- and down-wind is a particular challenge. This is also apparent in the bimodal distribution of errors seen in some scenarios (e.g. turning frequency=0.02 Hz, $\tau = 10, 50$ sec).

To better visualize the optimal choice of both $\tau$ and the turning frequency, we plot the median errors for each case as a heatmap (e.g. Fig. 7G). In many of the cases we consider, several combinations of $\tau$ and the turning frequency offer similar performance. To capture this range of optima, we determined which combinations result in a median error that is within $\pm 5°$ of the optimum (Fig. 7G red contour), and approximate this contour with an ellipse for visual simplicity. From this analysis we can conclude that for trajectories with $90°$ turns, variable velocity, and constant $\psi = 0$, in our dynamic wind scenario with sensors subject to modest noise, the optimal turning frequency ranges from 0.1-1 Hz, with values of $\tau$ ranging from 2-50 seconds.

*A. Analysis of time constants*

The optimal combinations of turning frequency and $\tau$ all occur where there is at least 1 turn per time $\tau$ (Fig. 8A). At sufficiently long values of $\tau$, however, there is a high likelihood of the wind having changed direction in our dynamic wind scenario, which increases the median error. As a result, the optimal choice of $\tau$ is constrained to be large enough to capture a change in flight direction, but short enough to avoid likely changes in ambient wind direction.

To better understand the sensitivity of our results to choices of the cutoff frequency $\omega$ in our smoothing filter, we performed a parameter sweep of $\omega$ (Fig. 8B). We considered values of $\omega$ equal to the product of the turning frequency and five constants: $[0.1, 0.5, 1, 2, 10]$. For combinations of fast turning frequencies and short $\tau$ (upper left corner of the heatmap), choosing a smaller cutoff frequency ($0.1*$turning frequency) provided a modest reduction in median error of the wind direction estimates. Overall, however, a choice of $\omega =$ turning frequency generally performs well.

To understand how different values of $T$ might change the estimation accuracy we performed a parameter sweep of $T$. We considered values of $T$ equal to the product of $\tau$ and four constants: $[1, 5, 25, 125]$. For combinations of fast turning frequencies and short $\tau$ choosing $T = \tau$ performs poorly (Fig. 8A). However, choosing a much larger value of $T$, e.g. $T = 125\tau$, substantially improves the accuracy of ambient wind direction estimates for these scenarios (Fig. 8C). For a turning frequency of 0.5 Hz and $\tau = 0.4$ sec the optimal choice of $T = 125\tau = 50$ sec, which incorporates information across 50 individual turns. Overall, we conclude that assimilating sensory measurements across at least one turn is required, but is most important for distinguishing between up and downwind.

Fig. 8: Turning frequency dictates optimal choices of $\omega$, $\tau$, and $T$. (A) Heatmap duplicated from Fig. 7G, i.e. dynamic wind, $90°$ turns, and Gaussian sensor noise $\mathcal{N} = (0°, 17°)$. Combinations of turning frequency and $\tau$ above the white-black line correspond to cases where there is at least on full left or right turn per unit $\tau$. The blue dashed line shows the median probability of a change in wind direction for our dynamic wind scenario, copied from Fig. 4C. (B) Heatmap plotted as in A, but showing the lowest median error across five choices of $\omega$; numbers indicate the optimal choice of $\omega_{opt}$ relative to a nominal choice of $\omega =$turning frequency. (C) Heatmap plotted as in A, but showing the lowest median error across four choices of $T$; numbers indicate the optimal choice of $T_{opt}$ relative to $\tau$. For good performance, $T$ is always sufficiently large to encompass at least one left or right turn.

*B. Analysis of turn angle & sensor noise*

Next we set out to answer the question: are small or large turns more effective for estimating the ambient wind direction under dynamic wind conditions? We repeated the analysis summarized in Fig. 8A for trajectories consisting of small, medium, and large turns (Fig. 9A). Across a wide range of sensor noise, larger turns consistently provide more accurate ambient wind direction estimates. As with the first example provided, across all cases the lowest errors are achieved when there is at least one turn per unit $\tau$. Choosing $\omega =$turning frequency again works well across this entire range of turn angles and sensor noise levels (Supp. Fig. S1). For short $\tau$, estimation errors can again be reduced by choosing large enough values of $T$ to incorporate measurements across at least one turn (Supp. Fig. S2).

To provide some intuition about how accurate or poor the estimates of ambient wind direction estimates can be, and the characteristics the errors, we show four representative examples in Fig. 9B-E. For fast turns and short $\tau$, the estimates are noisy, but the largest errors are characterized by errors in distinguishing between up- and down-wind, i.e.

Fig. 9: Larger turn angles result in better performance and smaller optimal values for $\tau$. (A) Simulation results for the dynamic wind segment plotted as in Fig. 7G. (B-E) Representative examples comparing true and estimated wind directions for combinations of turn angle, noise, turning frequency, and $\tau$ as indicated by the letter placements in A.

errors of $\pm\pi$ (Fig. 9B). Small turn angles result in poor estimates even when information is assimilated across at least one turn (Fig. 9C). For large turns, assimilating measurement information across a larger value of $\tau$ results in smoother (less responsive) estimates (compare Fig. 9D-E).

For larger values of sensor noise, regardless of the turn angle magnitude, the optimal range of turning frequency decreases slightly. One likely explanation for this is that as the sensor noise increases it becomes increasingly difficult to filter out noise without sacrificing the signal. Slower turning frequencies help to alleviate this by allowing the use of a more aggressive cutoff frequency that can smooth the noise more effectively. In order to maintain at least one turn per unit $\tau$ for these slower turning frequencies, however, means that the optimal value for $\tau$ must increase. This makes the estimator less able to respond to rapid fluctuations in wind direction (e.g. Fig. 9E).

There are essentially three categories of errors lumped together under our single error metric: (1) poor estimates of $min(|\hat{\zeta} - \zeta| \pm \pi)$ (i.e. the errors that are (much) less than $\pi$), which typically result from either too small a choice of $\tau$ or too small a turn angle (e.g. Fig. 9B-C);(2) poor estimates

of the $\pm n\pi$ ambiguity, typically resulting from too small a choice of $T$ (compare Fig. 8A,C); and (3) overly smooth estimates of $\hat{\zeta}$ as a result of integrating sensory information over too large of a time window $\tau$ (e.g. Fig. 9E). To mitigate all three error categories requires an intermediate value of $\tau$, medium to large turn angles, and a sufficiently large value of $T$.

### C. Dynamic vs. consistent wind

Next we turn our attention to how the optimal values of $\tau$, turning frequency, and turn angle change if the wind has a more consistent direction over time (Supp. Fig. S3). For consistent wind, the overall error achieved by trajectories with small, medium, and large turns is quite similar, suggesting that large turns are a particularly important trajectory feature when the wind direction is dynamic. Meanwhile, consistent wind is less sensitive to the specific choice of turning frequency or $\tau$. That is, larger values of $\tau$ as well as slower turning frequencies are both effective, whereas these choices led to increased errors in the dynamic wind scenario. In summary (Fig. 10), we find that when the wind direction is dynamic a higher turning frequency, shorter $\tau$, and larger

Fig. 10: Summary of simulation results for dynamic and consistent wind and different trajectory candidates. (A) Sample trajectories. (B) Example error heatmaps for large turn angles and Gaussian noise $\mathcal{N} = (0°, 34°)$ plotted as in Fig. 9. (C) Median optimal error, i.e. the error value at the location of the star from the heatmap plots, for different turn angles and noise levels. Vertical bars indicate the $\pm5°$ range used to define the ellipses. (D) Optimal values of $\tau$, i.e. the abscissa location of the star from the heatmap plots. Vertical bars indicate the maximum width of the ellipse. (E) Optimal values of turning frequency, i.e. the ordinate location of the star from the heatmap plots. Vertical bars indicate the maximum height of the ellipse. Colored and numbered arrows highlight the key results summarized in the discussion.

turn angles all become more important to accurately estimate the ambient wind direction.

### D. Constant ground speed & constant γ trajectories

Finally, we turn our attention to two variations of the trajectory candidates to answer two questions: would trajectories with constant ground speed ($\dot{g} = 0$) or constant $\gamma = 0$ provide any improvements in the estimates over trajectories with variable ground speed and constant $\psi = -0$? These choices are motivated by the observation that many insects use visual information to maintain a constant ground speed [33], and typically orient their bodies in the direction of their airspeed [22]. The results for these trajectories are summarized in Fig. 10, see also Supp. Figs. S4-5.

Constant ground speed trajectories show almost no change in optimal median error, $\tau$, and turning frequency compared to the variable ground speed trajectories. Constant $\gamma = 0$ trajectories, however, do show some subtle but important improvements: reduced errors for shorter values of $\tau$ under high levels of sensor noise. Why might this be the case?

In our simulations the wind speed was typically higher than the ground speed (mean wind speed was 2.3 m/s for the dynamic wind scenario; mean ground speed was 0.84 m/s for a turning frequency of 0.1 Hz). Thus, by adopting a constant $\gamma = 0$ trajectory the agents are generally oriented in a similar direction despite changing their direction of travel (compare the trajectory plots from Fig. 10). As a result, $\dot{\phi}$ remains quite small for the constant $\gamma$ trajectories, making it easier to accurately estimate $\phi$ with large levels of sensor noise. To analyze this effect quantitatively we simulated constant $\psi$ and constant $\gamma$ trajectories in the dynamic wind scenario and find that the absolute errors of the smoothed estimates ($\omega = 0.1$ Hz) for $\delta$ are similar for the two cases, but the smoothed estimates for $\phi$ have half the error for the constant $\gamma$ trajectories (Fig. 11). With better estimates of the true sensor values, it is no surprise that the resulting ambient wind direction estimates are also more accurate.

Fig. 11: Mean absolute error in estimates of $\delta = \gamma - \psi$ and $\phi$ for constant-$\psi$ and constant-$\gamma$ trajectories with large turn angles ($\sim 160°$), a turning frequency of 0.1 Hz, and Gaussian noise with a standard deviation of 67°, for the dynamic wind scenario, for 10 different random seeds. Lines and shading show the median and 95% confidence interval.

## VI. Discussion

Recent release-and-recapture experiments with fruit flies in a feature-sparse desert showed that these tiny insects are able to locate the source of odor plumes from substantial distances over the course of $\sim 10$ minutes under a variety of wind conditions. In those experiments, flies were most successful at lower wind speeds [27]. Although this result is intuitive from a biomechanics perspective, these low wind speeds are typically associated with more variable wind directions [34], making the plume tracking task more challenging. Flies' plume tracking success under such conditions suggests that they are adept at following odor plumes in variable direction wind conditions. Our active anemosensing hypothesis provides a potential explanation for how they might accomplish this by integrating three angular sensor measurements known to be encoded in their central complex: orientation, airspeed direction, and direction of movement.

### A. Summary of key results

We begin our discussion with a summary of our key results (see numbered arrows in Fig. 10). (1) Large changes in course direction are most effective for accurately estimating the ambient wind direction. This is especially true when the wind direction changes frequently. (2) For both dynamic and consistent wind cases, it is important that sensory information be integrated across at least 1 turn. (3a) In dynamic wind, long integration times ($\tau$) lead to larger errors, and (3b) faster turning frequencies are also necessary. (4a) When subject to large amounts of sensor noise, slower turning frequencies offer better estimates by allowing the use of more aggressive smoothing filters to reject noise. (4b) Constant-$\gamma = 0$ trajectories, however, are better able to withstand high levels of sensor noise with high frequency turns. (5) In terms of estimation accuracy, constant-ground-speed and constant-$\gamma$ trajectories offer no substantial advantage over variable-ground-speed and constant-$\psi$ trajectories. (6) For

large amounts of sensor noise applied to trajectories with large turn angles, however, constant-$\gamma$ trajectories allow for shorter integration times (smaller $\tau$) compared to constant-$\psi$ trajectories. (7) A key challenge is distinguishing between up- and downwind. In other words, it is challenging for an insect to determine if they are flying faster than the wind speed but headed downwind, versus flying slowly upwind. This challenge can be more reliably overcome by integrating information across a longer period of time ($T > \tau$) (see Fig. 8).

### B. Zig-zag maneuvers optimize wind direction estimation

The trajectories exhibited by flying and swimming animals during plume tracking across a wide range of taxa are nearly all characterized by some form of zigzagging, or casting [1]. Zigzagging, however, is not explicitly required for plume tracking if ambient wind direction information is directly accessible. For example, walking cockroaches are adept at following plumes but do not exhibit the classic zigzagging behavior [35]. Walking *Drosophila* also do not need to perform zigzagging trajectories when presented with a homogeneous and consistent odor plume, instead they will continue straight upwind [36]. For a walking animal, estimating the ambient wind direction from apparent wind estimates is trivial: they can either hold still for a brief moment, or rely on proprioceptive cues to accurately estimate their ground speed or distance travelled given their stepping speed and leg length [37], [38]. Indeed, visually blind flies have no trouble in finding the direction of ambient wind [36]. Of course, some changes in direction are required in order to stay centered on the plume, especially for turbulent plumes [39], but these changes in direction need not be rhythmic, frequent, nor large.

Furthermore, in some efforts to reverse engineer plume tracking strategies using an "optimal" reinforcement learning framework for agents that are provided with ambient wind direction information, the distinctive casting exhibited by animals appears to be largely absent [40], or diminished when the agent is inside the plume [41]. These findings together with our results presented here suggest that the zigzagging exhibited by flying insects, and likely other flying and swimming animals too, is crucial for them to estimate the ambient wind direction in order to guide plume tracking decisions.

### C. Advantage of constant $\gamma$ trajectories

In cases where sensor noise is high and turn angles are large, constant $\gamma$ trajectories offer an advantage by making it easier to estimate the true sensor values from noisy measurements, and their corresponding derivatives. We would expect this advantage to disappear when the ground speed is much greater than the wind speed, at which point constant $\gamma = 0$ trajectories will be more similar to constant $\psi = 0$ trajectories. Flies do generally orient their bodies

so as to maintain an approximately constant $\gamma$ [22], though future work will be required to determine if they also orient their heads to maintain constant $\gamma$ during free flight plume tracking behaviors. If they do, it would add new support to a previously proposed hypothesis that insects control their movement so as to simplify estimating sensor measurements and their derivatives [6].

### D. Optimal choice of time constants

Our active anemosensing hypothesis involves the assimilation of sensory measurements across three different time constants: $\omega$, $\tau$, and $T$. Our results suggest that a good rule of thumb for accurate ambient wind direction estimates is to choose $\omega =$ turning frequency, and $\tau = T \geq 2/\omega$. This ensures that wind direction estimates are always based on information that spans at least one left or right turn. With noisier sensor measurements, slower turning frequencies and longer values of $\tau$ are helpful. The increased errors associated with shorter values of $\tau$ can be partially mitigated by using a much larger value for $T$.

### E. Simplified mathematics with constant velocity control

It is unlikely that insects use the approach we outline in Fig. 3 due to the computational expense (for example, solving the estimation for $\tau = T = 10$ & $dt = 0.1$ takes $\approx 160 \pm 20$ milliseconds on a powerful desktop computer). There are, however, simplifications that would allow insects to solve a much simpler problem. Although plume tracking insects do exhibit variability in their ground speed (e.g. Fig. 5E), it is also well established that insects use visual feedback in order to maintain approximately constant ground speeds [27], [33], [42]. Furthermore, some studies have found that insects will fly faster (prior to landing) in the presence of higher wind speeds [43], which would help maintain $v = g/w$ at roughly a constant value. Although the constant ground speed trajectories we considered offered little help in estimation accuracy, assuming a constant *ratio* of ground speed to wind speed (i.e. $\dot{v} = 0$) over the period $\tau$ allows for a diversity of simplified algorithms that we describe below. For (most of) these methods, future work will be required to determine how sensitive they are to breaking their assumption of $\dot{v} = \dot{g}/w - \dot{w}g/w^2 = 0$.

*1) Quadrant sensing:* The first simplification we consider does not aim to precisely determine the ambient wind direction, instead it only identifies which 90° quadrant the wind direction lies inside. This requires two comparisons of signs. First, recall the following equation (derived from Eqn. 3 with $\delta = \gamma - \psi$ and $\alpha = \gamma + \phi$):

$$v \sin(\delta) = \sin(\alpha - \zeta). \tag{17}$$

Although $v$ is unknown, it is defined as a magnitude and must be $> 0$, so we can write:

$$\text{sign}(\delta) = \text{sign}(\alpha - \zeta). \tag{18}$$

This relationship can be used to determine which hemisphere the ambient wind is coming from, and is the same constraint we use in our convex optimization formulation to disambiguate between up- and downwind. To further constrain the wind direction to one of four quadrants, we can place a similar constraint on the derivative of Eqn. 17 (assuming $\dot{\zeta} = 0$ over the period of time over which the derivative is calculated):

$$\dot{v} \sin(\delta) + v\dot{\delta} \cos \delta = \dot{\alpha} \cdot \cos(\alpha - \zeta). \tag{19}$$

We can now place the same type of sign constraint on this equation:

$$\text{sign}\big(\dot{v} \sin(\delta) + v\dot{\delta} \cos \delta\big) = \text{sign}\big(\dot{\alpha} \cdot \cos(\alpha - \zeta)\big). \tag{20}$$

As long as $|\dot{v}| < |v\dot{\delta} \cot \delta|$, we can ignore the $\dot{v}$ term such that we have the following constraint (which eliminates the unknown $v$ from the equation):

$$\text{sign}\left(\frac{\dot{\delta} \cos \delta}{\dot{\alpha}}\right) = \text{sign}\big(\cos(\alpha - \zeta)\big). \tag{21}$$

Together, Eqns. 18 and 21 can be used to determine which of four quadrants the ambient wind direction is coming from. Note that although this approach does not provide a precise estimate of wind direction, it may be sufficient for some behaviors, and sequential quadrant estimates could be combined (e.g. through a Bayesian framework) to build a more precise wind direction estimate over time (i.e. over the course of several turns).

*2) Discrete least squares solution:* Under the assumption of constant $v = g/w$, our convex optimization approach (solid orange box, Fig. 3B) reduces to a simple matrix inversion based on Eqn. 14:

$$\begin{bmatrix} \hat{v}_k^c \\ \tan \hat{\zeta}_k^c \end{bmatrix} = \begin{bmatrix} \sin \delta_k & \cos \alpha_k \\ \sin \delta_{k-1} & \cos \alpha_{k-1} \\ \vdots & \vdots \\ \sin \delta_{k-\tau} & \cos \alpha_{k-\tau} \end{bmatrix}^+ \begin{bmatrix} \sin \alpha_k \\ \sin \alpha_{k-1} \\ \vdots \\ \sin \alpha_{k-\tau} \end{bmatrix}, \tag{22}$$

where the $^+$ is the Moore-Penrose pseudoinverse. As with our convex approach (which allows $\dot{v} \neq 0$), this matrix inversion must be solved for the two cases ($\tan \hat{\zeta}_k^c$ and $\cot \hat{\zeta}_k^s$), and up- and downwind options must be disambiguated. The quadrant sensing approach could be used in conjunction with least squares estimates of $\hat{\zeta}_k^c$ and $\hat{\zeta}_k^s$ to accurately estimate the wind direction.

Of course, it is unlikely that insects have the neural capacity to invert arbitrary matrices. If we only consider two

discrete measurements separated by time $\tau$ we can write a closed form solution for the 2x2 matrix inversion problem:

$$\hat{\bar{\zeta}}_k^c + n_k\pi = \tan^{-1}\frac{\sin\alpha_{k-\tau}\sin\delta_k - \sin\alpha_k\sin\delta_{k-\tau}}{\sin\delta_k\cos\alpha_{k-\tau} - \cos\alpha_k\sin\delta_{k-\tau}}, \quad (23)$$

which can be rearranged into the following form to highlight the implicit finite difference calculations that are required,

$$\hat{\bar{\zeta}}_k^c + n_k\pi = \tan^{-1}\frac{\sin(0.5(d\alpha - d\delta))\sin(\overline{\alpha}+\overline{\delta}) - \sin(0.5(d\alpha+d\delta))\sin(\overline{\alpha}-\overline{\delta})}{\sin(0.5(d\alpha-d\delta))\cos(\overline{\alpha}+\overline{\delta}) - \sin(0.5(d\alpha+d\delta))\cos(\overline{\alpha}-\overline{\delta})}, \quad (24)$$

where $d\delta$ represents a finite difference, $d\delta = \delta_k - \delta_{k-\tau}$ and $\overline{\delta}$ represents a mean calculation, $\overline{\delta} = 0.5(\delta_k + \delta_{k-\tau})$, and similarly for $d\alpha, \overline{\alpha}$.

Because this solution only incorporates measurements from two discrete moments in time, it would likely work best either with filtered measurements to reduce noise, and/or with a filter applied to the resulting $\hat{\zeta}$ estimates. Furthermore, the best choice of $\tau$ would likely be one that maximizes the difference between the two measurements as a result of a controlled turn, i.e. $\tau$ should be some multiple of half the turning period.

*3) Continuous direct estimate:* A different option (again assuming $\dot{v} = 0$) is to recombine Eqn. 9c and Eqn. 10 to define a closed form solution for $\zeta$ as follows,

$$\zeta \pm n\pi = 2\tan^{-1}\frac{\dot{\delta} - \sqrt{\dot{\delta}^2 + (\tan^2\delta)(\dot{\gamma}^2 + 2\dot{\gamma}\dot{\phi} + \dot{\phi}^2)}}{\dot{\gamma} + \dot{\phi}\tan\delta} + \phi + \gamma. \quad (25)$$

Again, up- and downwind must be disambiguated. This formulation requires sufficiently accurate derivatives of the sensor measurements. As with the quadrant sensing approach, the derivatives could be calculated as a discrete finite difference for measurements taken time $\tau$ apart, where $\tau$ is some multiple of half of the turning period.

*F. Considerations for neural implementation*

A common theme across each of the simplified estimation approaches outlined above is the presence of a derivative (or finite difference) of sensory measurements, as predicted by a prior nonlinear observability analysis [44]. One plausible neural implementation for performing this calculation would be through a mechanism similar to the delay-and-correlate circuit employed for optic flow calculations [45], [46]. Our analysis of different trajectories found that it is important for sensory information to be incorporated over a sufficiently large time constant, $\tau$, such that information in assimilated from both sides of at least one turn. Thus, if insects do employ a delay-and-correlate mechanism to estimate the derivative of sensory measurements such as $\delta$, we would expect the delay to be either synchronized with voluntary turns, or to be hard-coded as one or multiple values with a time constant equal to half of the typical turning period (i.e. 1 Hz based on Fig. 5).

Each of the three simplified approaches require evaluating complex mathematical expressions containing trigonometric functions as well as multiplication and division. How might the brain perform these computations? In principle, a feed-forward neural network can be used to approximate any of these mathematical expressions [47], however, accurate approximations may require too many elements to be practical. Instead, some simplifications or alternative reference frames may be used. The tangent function, for example, could be evaluated as a ratio of two orthogonal vectors, and recent work has revealed how flies can perform certain vector calculations related to navigation [16], [48]. Multiplication and division in general can be converted to addition and subtraction if the calculations are performed in a log-space. Finally, it is quite possible that for the limited range of likely inputs an insect might actually experience due to environmental, biomechanical, or behavioral constraints, the true mathematical expressions could potentially be simplified without introducing excessive errors. For example, if angles are typically small due to behavioral control of $\psi$ or $\gamma$, small angle approximations could be employed (i.e. $\sin(\gamma) \approx \gamma$).

*G. Limitations*

In our analysis we only considered kinematically prescribed trajectories. In other words, we assumed that the agents were able to perfectly counteract the effects of any changes in wind direction or speed on their behavior. In practice, although flying insects do have exceptional gust rejection abilities [29], they will be thrown off course when subject to strong enough gusts. In such cases, it could be that estimation accuracy of wind direction actually improves due to the change in course direction, though only if the wind is not so overpowering that the insects end up drifting with the wind [44].

We focused our active anemosensing estimation framework on the principle of exclusively relying on angular sensory measurements known to be encoded in the central part of the insects brain. A more traditional estimation approach from engineering would combine control inputs with these available measurements and a detailed dynamics model of the relevant physics to provide more accurate estimates, for example using a nonlinear Kalman filter [49]. It is conceivable that insects could incorporate copies of their motor control commands with a model of the muscle output and aerodynamic forces to more accurately estimate the wind direction, however, this would require detailed calibrations of all of the model parameters. As with the sensory system, these parameters will vary in time due to damage [50], temperature fluctuations [51], or other circumstances, making it challenging to rely on a model-based approach. A significant advantage of relying exclusively on angular measurements is that the entire angular sensorimotor pathway relevant to ambient wind estimation can in principle be self-calibrated without external help [44].

## H. Hypotheses and predictions

If flies exclusively rely on visual anemotaxis, they would not be able to make arbitrary changes in course with respect to the ambient wind direction. Instead, they would need to determine upwind, or perform rhythmic maneuvers centered around the upwind direction. Under our active anemosensing hypothesis, however, flies could continuously adjust their course angle without first orienting upwind. Future experiments with flying insects that are motivated to move upwind and subject to rapidly changing wind directions or artificial visual cues could help to distinguish between these cases.

With respect to computational complexity, the three estimation approaches that assume constant $v = g/w$ provide the most biologically plausible implementations of our active anemosensing hypothesis. Future work will be necessary to determine how sensitive these implementations are to violations of the constant $v$. In each of these cases we would expect to find a clear encoding of $\delta = \gamma - \psi$ in the flies' brain. Furthermore, we would expect to find neural pathways capable of differentiating this signal with a time constant roughly equal to half their stereotypical turning period of $\sim 2$ sec. We might also expect to find the angular velocity (of the head) to enter the equation.

In our new analysis of previously published plume tracking fly trajectories, we found that flies typically cast at approximately 0.5 Hz, i.e. $\sim 1$ left and $\sim 1$ right turn every two seconds. Our active anemosensing hypothesis suggests that for this turning frequency, flies would have most accurate wind direction estimates for a $\tau \geq 1$ sec. This would allow flies to be effective at tracking plumes in highly dynamic wind that changes direction on the scale of 1 second, possibly explaining the release and recapture successes at low wind speeds described previously. For insects with noisier sensory measurements, either due to fundamental sensor limits or environmental constraints such as low light levels, we predict that the turning frequency should decrease. Larger plume tracking animals such as albatross [52] could also conceivably employ active anemosensing to estimate ambient wind direction. With slower dynamics due to their more massive bodies we would also expect to see slower turning frequencies. For both cases, we predict that slower turning frequencies should lead to larger required values of $\tau$ and thus slower responses to rapid changes in wind direction, though this could be partially mitigated by employing constant $\gamma = 0$ trajectories and using larger values for $T$.

One particular challenge our analysis highlights is that of distinguishing up- vs. downwind. To resolve this challenge, insects could use a similar approach to our solution (Eqn. 15), or perhaps they employ a combination of active anemosensing and visual anemotaxis to guarantee that during plume tracking behaviors they are always generally headed upwind, this would be equivalent to using a very large value of $T$.

## Acknowledgements

We thank Ethan Swierski for help with developing and testing the drone, and Katherine Nagel for helpful discussions and feedback on the manuscript.

## Funding Statement

This work was partially supported by grants from the Air Force Research Lab to FvB (FA8651-20-1-0002), Air Force Office of Scientific Research to FvB (FA9550-21-0122), the Sloan Foundation to FvB (FG-2020-13422), the National Science Foundation (NSF) BioSoRo REU site with Award Number EEC 1852578 to support RJ, and an NSF EPSCOR UROP Scholarship to JH.

## VII. Data accessibility statement

All of the code associated with this paper is provided in an open source repository here: `https://github.com/florisvb/active_anemosensing` [53]. Data is available as a Data Dryad repository here: `https://doi.org/10.5061/dryad.gb5mkkwrv`, and will be available upon publication.

## References

[1] K. L. Baker, M. Dickinson, T. M. Findley, D. H. Gire, M. Louis, M. P. Suver, J. V. Verhagen, K. I. Nagel, and M. C. Smear, "Algorithms for olfactory search across species," *The Journal of Neuroscience*, vol. 38, pp. 9383–9389, Oct. 2018.

[2] H. Schöne, *Spatial Orientation: The Spatial Control of Behavior in Animals and Man*. Princeton University Press, 2014.

[3] P. Oteiza, I. Odstrcil, G. Lauder, R. Portugues, and F. Engert, "A novel mechanism for mechanosensory-based rheotaxis in larval zebrafish," *Nature*, vol. 547, pp. 445–448, July 2017.

[4] B. Lingenfelter, A. Nag, and F. van Breugel, "Insect inspired vision-based velocity estimation through spatial pooling of optic flow during linear motion," *Bioinspiration & Biomimetics*, vol. 16, no. 6, p. 066004, 2021.

[5] A. J. Rutkowski, M. M. Miller, R. D. Quinn, and M. A. Willis, "Egomotion estimation with optic flow and air velocity sensors," *Biological Cybernetics*, vol. 104, pp. 351–367, June 2011.

[6] F. van Breugel, K. Morgansen, and M. H. Dickinson, "Monocular distance estimation from optic flow during active landing maneuvers," *Bioinspiration & Biomimetics*, vol. 9, p. 025002, May 2014.

[7] D. C. O'Carroll, N. J. Bidweii, S. B. Laughlin, and E. J. Warrant, "Insect motion detectors matched to visual ecology," *Nature*, vol. 382, pp. 63–66, July 1996.

[8] B. Tatler, D. C. O'Carroll, and S. B. Laughlin, "Temperature and the temporal resolving power of fly photoreceptors," *Journal of Comparative Physiology A: Sensory, Neural, and Behavioral Physiology*, vol. 186, pp. 399–407, Apr. 2000.

[9] G. Maimon, A. D. Straw, and M. H. Dickinson, "Active flight increases the gain of visual motion processing in drosophila," *Nature Neuroscience*, vol. 13, pp. 393–399, Feb. 2010.

[10] J. D. Seelig and V. Jayaraman, "Neural dynamics for landmark orientation and angular path integration," *Nature*, vol. 521, pp. 186–191, May 2015.

[11] Y. M. Giraldo *et al.*, "Sun navigation requires compass neurons in drosophila," *Current Biology*, vol. 28, pp. 2845–2852.e4, Sept. 2018.

[12] T. S. Okubo, P. Patella, I. D'Alessandro, and R. I. Wilson, "A neural network for wind-guided compass navigation," *Neuron*, vol. 107, pp. 924–940.e18, Sept. 2020.

[13] T. A. Currier, A. M. Matheson, and K. I. Nagel, "Encoding and control of orientation to airflow by a set of drosophila fan-shaped body neurons," *eLife*, vol. 9, Dec. 2020.

[14] P. T. Weir, B. Schnell, and M. H. Dickinson, "Central complex neurons exhibit behaviorally gated responses to visual motion in drosophila," *Journal of Neurophysiology*, vol. 111, pp. 62–71, Jan. 2014.

[15] J. Green, A. Adachi, K. K. Shah, J. D. Hirokawa, P. S. Magani, and G. Maimon, "A neural circuit architecture for angular integration in drosophila," *Nature*, vol. 546, pp. 101–106, May 2017.

[16] C. Lyu, L. Abbott, and G. Maimon, "A neuronal circuit for vector computation builds an allocentric traveling-direction signal in the drosophila fan-shaped body," *bioRxiv*, 2020.

[17] H. H. Thoen, J. Marshall, G. H. Wolff, and N. J. Strausfeld, "Insect-like organization of the stomatopod central complex: Functional and phylogenetic implications," *Frontiers in Behavioral Neuroscience*, vol. 11, Feb. 2017.

[18] J. S. Kennedy, "The visual responses of flying mosquitoes.," *Proceedings of the Zoological Society of London*, vol. A109, no. 4, pp. 221–242, 1940.

[19] F. van Breugel and M. H. Dickinson, "The visual control of landing and obstacle avoidance in the fruit fly drosophila melanogaster," *Journal of Experimental Biology*, vol. 215, pp. 1783–1798, May 2012.

[20] J. A. Bender, "Visual stimulation of saccades in magnetically tethered drosophila," *Journal of Experimental Biology*, vol. 209, pp. 3170–3182, Aug. 2006.

[21] J.-M. Mongeau and M. A. Frye, "Drosophila spatiotemporally integrates visual signals to control saccades," *Current Biology*, vol. 27, pp. 2901–2914.e2, Oct. 2017.

[22] F. van Breugel and M. H. Dickinson, "Plume-tracking behavior of flying drosophila emerges from a set of distinct sensory-motor reflexes," *Current Biology*, vol. 24, pp. 274–286, Feb. 2014.

[23] S. Butterworth, "On the theory of filter amplifiers," *Experimental Wireless and the Wireless Engineer*, vol. 7, pp. 536–541, 1930.

[24] F. V. Breugel, Y. Liu, B. W. Brunton, and J. N. Kutz, "Pynumdiff: A python package for numerical differentiation of noisy time-series data," *Journal of Open Source Software*, vol. 7, no. 71, p. 4078, 2022.

[25] S. Diamond and S. Boyd, "CVXPY: A Python-embedded modeling language for convex optimization," *Journal of Machine Learning Research*, vol. 17, no. 83, pp. 1–5, 2016.

[26] M. ApS, *The MOSEK optimization API for Python. Version 8.1.*, 2018.

[27] K. J. Leitch, F. V. Ponce, W. B. Dickson, F. van Breugel, and M. H. Dickinson, "The long-distance flight behavior of drosophila supports an agent-based model for wind-assisted dispersal in insects," *Proceedings of the National Academy of Sciences*, vol. 118, no. 17, 2021.

[28] F. T. Muijres, M. J. Elzinga, N. A. Iwasaki, and M. H. Dickinson, "Body saccades of drosophila consist of stereotyped banked turns," *The Journal of experimental biology*, vol. 218, no. 6, pp. 864–875, 2015.

[29] S. B. Fuller, A. D. Straw, M. Y. Peek, R. M. Murray, and M. H. Dickinson, "Flying drosophila stabilize their vision-based velocity controller by sensing wind with their antennae," *Proceedings of the National Academy of Sciences*, vol. 111, no. 13, pp. E1182–E1191, 2014.

[30] B. D. Lucas and T. Kanade, "An iterative image registration technique with an application to stereo vision (ijcai)," in *Proceedings of the 7th International Joint Conference on Artificial Intelligence (IJCAI '81)*, pp. 674–679, April 1981.

[31] S. Baker and I. Matthews, "Lucas-kanade 20 years on: A unifying framework," *International Journal of Computer Vision*, vol. 56, pp. 221–255, Feb. 2004.

[32] G. Bradski, "The OpenCV Library," *Dr. Dobb's Journal of Software Tools*, 2000.

[33] C. T. David, "Compensation for height in the control of ground speed by drosophila in a new, ' barber's pole' wind tunnel," *Journal of comparative physiology*, vol. 147, pp. 485–493, 1982.

[34] D. Anfossi, D. Öttl, G. Degrazia, and l. Goulart, "An analysis of sonic anemometer observations in low wind speed conditions," *Boundary-Layer Meteorology*, vol. 114, no. 1, pp. 179–203, 2005.

[35] M. Willis and J. Avondet, "Odor-modulated orientation in walking male cockroaches periplaneta americana, and the effects of odor plumes of different structure," *Journal of Experimental Biology*, vol. 208, no. 4, pp. 721–735, 2005.

[36] E. Álvarez-Salvado, A. M. Licata, E. G. Connor, M. K. McHugh, B. M. King, N. Stavropoulos, J. D. Victor, J. P. Crimaldi, and K. I. Nagel, "Elementary sensory-motor transformations underlying olfactory navigation in walking fruit-flies," *eLife*, vol. 7, Aug. 2018.

[37] M. Wittlinger, R. Wehner, and H. Wolf, "The ant odometer: stepping on stilts and stumps," *science*, vol. 312, no. 5782, pp. 1965–1967, 2006.

[38] I. S. Kim and M. H. Dickinson, "Idiothetic path integration in the fruit fly drosophila melanogaster," *Current Biology*, vol. 27, no. 15, pp. 2227–2238, 2017.

[39] M. Demir, N. Kadakia, H. D. Anderson, D. A. Clark, and T. Emonet, "Walking drosophila navigate complex plumes using stochastic decisions biased by the timing of odor encounters," *Elife*, vol. 9, p. e57524, 2020.

[40] M. Vergassola, E. Villermaux, and B. I. Shraiman, "'infotaxis' as a strategy for searching without gradients," *Nature*, vol. 445, no. 7126, pp. 406–409, 2007.

[41] S. H. Singh, F. van Breugel, R. P. Rao, and B. W. Brunton, "Emergent behavior and neural dynamics in artificial agents tracking turbulent plumes," *arXiv preprint arXiv:2109.12434*, 2021.

[42] A. Barron, "Visual regulation of ground speed and headwind compensation in freely flying honey bees (apis mellifera l.)," *Journal of Experimental Biology*, vol. 209, pp. 978–984, Mar. 2006.

[43] J. J. Chang, J. D. Crall, and S. A. Combes, "Wind alters landing dynamics in bumblebees," *Journal of Experimental Biology*, Jan. 2016.

[44] F. van Breugel, "A nonlinear observability analysis of ambient wind estimation with uncalibrated sensors, inspired by insect neural encoding," 2021.

[45] B. Hassenstein and W. Reichardt, "Systemtheoretische analyse der zeit-, reihenfolgen-und vorzeichenauswertung bei der bewegungsperzeption des rüsselkäfers chlorophanus," *Zeitschrift für Naturforschung B*, vol. 11, no. 9-10, pp. 513–524, 1956.

[46] A. Borst, "Models of motion detection," *Nature neuroscience*, vol. 3, no. 11, pp. 1168–1168, 2000.

[47] K. Hornik, M. Stinchcombe, and H. White, "Multilayer feedforward networks are universal approximators," *Neural Networks*, vol. 2, pp. 359–366, Jan. 1989.

[48] Y. E. Fisher, "Flexible navigational computations in the drosophila central complex," *Current Opinion in Neurobiology*, vol. 73, p. 102514, Apr. 2022.

[49] S. J. Julier and J. K. Uhlmann, "New extension of the kalman filter to nonlinear systems," in *Signal processing, sensor fusion, and target recognition VI*, vol. 3068, pp. 182–193, International Society for Optics and Photonics, 1997.

[50] D. J. Foster and R. V. Cartar, "What causes wing wear in foraging bumble bees?," *Journal of Experimental Biology*, vol. 214, pp. 1896–1901, May 2011.

[51] N. George, S. Sponberg, and T. Daniel, "Temperature gradients drive mechanical energy gradients in the flight muscle of manduca sexta," *Journal of Experimental Biology*, vol. 215, no. 3, pp. 471–479, 2012.

[52] G. A. Nevitt, M. Losekoot, and H. Weimerskirch, "Evidence for olfactory search in wandering albatross, diomedea exulans," *Proceedings of the National Academy of Sciences*, vol. 105, no. 12, pp. 4576–4581, 2008.

[53] F. van Breugel, "florisvb/active_anemosensing: v0.0.1," Mar. 2022.

# VIII. Supplemental figures

Fig. S1: Optimal choice of turning frequency and $\tau$ are minimally effected by the precise choice of $\omega$. Heatmaps are plotted as in Fig. 8B for three types of trajectories and noise levels. Comparing this figure with Fig. 9 shows that the precise choice of $\omega$ has little effect on the median error.

Fig. S2: For trajectories with medium and large turn angles, ambient wind direction estimates can be improved for small $\tau$ scenarios by using a much larger value of $T$ to disambiguate between up- and down-wind. Heatmaps are plotted as in Fig. 8C for three types of trajectories and noise levels.

Fig. S3: In consistent wind scenarios, errors in ambient wind direction estimates are lower, larger values of $\tau$ are permissable, as are slower turning frequencies. Data plotted as in Fig. 9

Fig. S4: Constant velocity trajectories do not offer any advantage in estimation accuracy compared to variable velocity trajectories. Data plotted as in Fig. 9

Fig. S5: Constant $\gamma$ trajectories offer a subtle improvement in estimation accuracy for scenarios with large turns and high noise. Specifically, lower estimation errors can be achieved for smaller values of $\tau$. See text for detailed discussion. Data plotted as in Fig. 9