Phase-Restoring Subpixel Image Registration: Enhancing Motion Detection Performance in Fourier-domain Optical Coherence Tomography

Huakun Li[1], Bingyao Tan[2,3], Vimal Prabhu Pandiyan[4], Veluchamy Amutha Barathi[2,5,6], Ramkumar Sabesan[4], Leopold Schmetterer[1-3,6-10], Tong Ling[1-3,11,*]

[1] *School of Chemistry, Chemical Engineering and Biotechnology, Nanyang Technological University, Singapore.*

[2] *Singapore Eye Research Institute, Singapore National Eye Centre, Singapore.*

[3] *SERI-NTU Advanced Ocular Engineering (STANCE) Program, Singapore.*

[4] *Department of Ophthalmology, University of Washington, Seattle, WA 98109, USA.*

[5] *Department of Ophthalmology, Yong Loo Lin School of Medicine, National University of Singapore and National University Health System, Singapore.*

[6] *Ophthalmology & Visual Sciences Academic Clinical Program (Eye ACP), Duke-NUS Medical School, Singapore.*

[7] *Institute of Molecular and Clinical Ophthalmology, Basel, Switzerland.*

[8] *Center for Medical Physics and Biomedical Engineering, Medical University of Vienna, Austria.*

[9] *Department of Clinical Pharmacology, Medical University of Vienna, Austria.*

[10] *Rothschild Foundation Hospital, Paris, France.*

[11] *School of Electrical and Electronic Engineering, Nanyang Technological University, Singapore.*

* To whom correspondence may be addressed.

E-mail: tong.ling@ntu.edu.sg

Abstract

Phase-sensitive Fourier-domain optical coherence tomography (FD-OCT) enables in-vivo, label-free imaging of cellular movements with detection sensitivity down to the nanometer scale, and it is widely employed in emerging functional imaging modalities, such as optoretinography (ORG), Doppler OCT, and optical coherence elastography. However, when imaging tissue dynamics in vivo, tissue movement or bulk motion introduces decorrelation noise that compromises motion detection performance, particularly in terms of sensitivity and accuracy. Here, we demonstrate that the motion-related decorrelation noise in FD-OCT can be accurately corrected by restoring the initial sampling points using our proposed Phase-Restoring Subpixel Image Registration (PRESIR) method. Derived from a general FD-OCT model, the PRESIR method enables translational shifting of complex-valued OCT images over arbitrary displacements with subpixel precision, while accurately restoring phase components. Unlike conventional approaches that shift OCT images either in the spatial domain at the pixel level or in the spatial frequency domain for subpixel correction, our method reconstructs OCT images by correcting axial displacement in the spectral domain (k domain) and lateral displacement in the spatial frequency domain. We validated the PRESIR method through simulations, phantom experiments, and in-vivo optoretinography in both rodents and human subjects. Our approach significantly reduced decorrelation noise during the imaging of moving samples, achieving phase sensitivity close to the fundamental limit determined by the signal-to-noise ratio (SNR).

Keywords: Decorrelation noise, image registration, optical coherence tomography, retina, optoretinography, phase-sensitive imaging.

1. Introduction

Fourier-domain optical coherence tomography (FD-OCT) enables depth-resolved imaging via the Fourier transform of the spectral interferogram between the back-scattered light from the sample and the reference beam [1]. While conventional OCTs utilize the amplitude component of OCT signals, which represents the light intensity scattered from anatomical microstructures, phase-sensitive OCT exploits the phase difference between repeated A-scans [2], B-scans [3, 4], or volumetric scans [5] to achieve imaging of structural dynamics with sensitivity down to the

nanometer scale [2]. Owing to its high motion sensitivity, phase-sensitive OCT has led to the

development of several label-free functional imaging modalities. For instance, Doppler OCT has

been widely used in velocimetry to quantify blood flow velocity [6], while optical coherence

elastography was developed to evaluate tissue biomechanical properties [4, 7]. Recently, the

application of phase-sensitive OCT for imaging the functional activity of photoreceptors in

response to light stimuli, generally termed optoretinography (ORG), has sparked significant

interest in both scientific research and clinical diagnosis [8, 9, 10, 11]. Furthermore, phase-

sensitive OCT may pave the way for all-optical interferometric thermometry in non-damaging

photothermal therapies [12, 13].

Despite the ever-growing impact of phase-sensitive OCT, it is well known that the measured phase

change possesses a decorrelation noise besides the desired optical path difference (OPD) and the

signal-to-noise ratio (SNR) dependent phase noise. Even without any change in the tissue structure

that causes the speckle pattern to decorrelate, the decorrelation noise still occurs when the sample

undergoes bulk movements. Such motion-related decorrelation noise is introduced by the

mismatch between the sampling points in consecutive OCT images [14, 15], which can be

problematic for in-vivo measurements where the sample is constantly affected by vascular

pulsation, breathing, and other involuntary movements. When the bulk movement of the sample

is of interest, the decorrelation noise can severely degrade the fidelity of the measured axial

movement, especially if the magnitude of the movement goes near or above the OCT system's

axial resolution (on the order of a few microns) [16]. Alternatively, when examining local tissue

deformation (e.g. for in-vivo optoretinography), it is common practice to use the self-referenced

method to cancel out unwanted phase drifts caused by the bulk tissue movement and the inevitable

fluctuations in the OPD between the sample arm and the reference arm [17]. However, the

detrimental effect of decorrelation noise in this scenario has long been overlooked, as the phase

uncertainty due to the sampling point mismatch can still vary from one pixel to another along the

same A-line [6].

In fact, the complex-valued OCT signal at each pixel can be modeled as a coherent superposition

of scattered light from adjacent scatterers, weighted by the point spread function (PSF) centered

at that pixel [18, 19]. As illustrated by the numerical simulations in a recent report by Hepburn et

al. [20], the phase inaccuracy in speckles with respect to the actual motion was seen to result from
the change in the weights of scatterers in the aforementioned superposition. A corollary of this
finding is that any tissue movement will change the positions of individual scatterers relative to
the pixel of interest in the OCT image, inevitably altering their scattered light's contribution to the
coherent superposition and leading to an unwanted phase variation. From this perspective, the
extra phase variation due to the sampling point mismatch can be regarded as a deterministic error
(termed "motion-induced phase error" in this article) instead of stochastic noise, if the scatterers'
relative locations remain fixed in the sample [21]. In other words, maintaining identical sampling
points during the sample movement, which can be achieved by post-hoc image registration, may
allow mitigating or even eliminating the motion-related decorrelation noise entirely. Moreover,
the effectiveness of such an approach depends on the accuracy with which we can restore the
original sampling points, preferably down to the subpixel level.

Typically, image registration in OCT involves two steps: motion estimation and image correction.
Although normalized cross-correlation (NCC)-based [22, 23] and phase-only correlation-based
methods [24] enable subpixel level motion estimation in both axial and lateral directions,
conventional image correction approaches, which shift the original complex-valued OCT image
[25, 26] or the 2-4 fold upsampled OCT image [27] in pixels, are limited by the discrete interval
determined by the upsampling rate. To facilitate image shifting over arbitrary distances, an
intuitive thought (referred to as the FT-based method in this article) is to treat complex-valued
OCT images as digital images and directly multiply the Fourier transform (FT) of the image by an
exponential term [28]. However, Lee et al. reported that the FT-based method's performance,
evaluated by the magnitude of cross-correlation between registered images, was significantly
inferior to that of upsampling methods [28], likely due to the omission of the unique physics
underlying the axial formation of the FD-OCT signal.

In this article, we propose a Phase-Restoring Subpixel Image Registration (PRESIR) method that
takes into account the nuances between the FD-OCT signals in the axial and lateral directions. Our
proposed method is capable of accurately restoring phase components when shifting images in
FD-OCT. In addition, we identified the root cause of the motion-induced phase error using analytic
formulas and analyzed its influence on motion detection accuracy through numerical simulations.

Notably, we found that the PRESIR method eliminated the motion-induced phase error and

achieved motion detection sensitivity approaching the theoretical limit in simulations and synthetic

phantom experiments. Moreover, we compared the motion detection sensitivity of the pixel-level

image registration method, the FT-based method, and the proposed PRESIR method when

detecting nanoscopic tissue deformations within moving samples. We found that the PRESIR

method significantly improved detection performance in in-vivo ORG for rodents and human

subjects.

This work significantly expands upon our preliminary findings presented at the SPIE Photonics

West 2023 [29, 30] by incorporating more rigorous analyses of the proposed methodology and

thorough experimental validations. Besides, no conference paper was published alongside those

previous oral presentations.

2. Methods

2.1 Analytic explanation of the motion-induced phase error in FD-OCT

OCT signals originate from the light scattered from individual scatterers within a sample [18]. If

the sample is physically displaced by Δx and Δz in the lateral and axial directions, respectively,

the reflectivity distributions $\eta_R(x,z)$ and $\eta_T(x,z)$ of the reference frame and target frame can be

written as,

136
$$\eta_R(x,z) = \sum_j r_j \delta(x - x_j, z - z_j), \tag{1}$$

137
$$\eta_T(x,z) = \sum_j r_j \delta(x - x_j - \Delta x, z - z_j - \Delta z), \tag{2}$$

138 where $\delta(\ )$ is the Dirac delta function, j is the index of scatterers, r_j and (x_j, z_j) denote the electric

139 field reflectivity and the coordinate of the j^{th} scatterer in the reference frame.

141 Taking into account Eqs. (1-2) and the general FD-OCT model (see Appendix A), we can derive

142 the complex-valued OCT images $\widetilde{A_R}(x,z)$ and $\widetilde{A_T}(x,z)$ measured from the reference and target

143 positions as follows:

144
$$\widetilde{A_R}(x,z) = \sum_j r_{Rj}(x,z)\exp[-i2k_0(z - z_j)], \tag{3}$$

145
$$\widetilde{A_T}(x,z) = \exp(i2k_0\Delta z) \sum_j r_{Tj}(x,z)\exp[-i2k_0(z - z_j)], \tag{4}$$

where $r_{Rj}(x,z)$ and $r_{Tj}(x,z)$ represent the PSF-weighted reflectivities of the j^{th} scatterer in the reference and target frames, respectively, as defined in Appendix B.

Consequently, we can express the phase difference $\Delta\varphi$ between the complex-valued OCT image $\widetilde{A_R}(x,z)$ and $\widetilde{A_T}(x,z)$ as follows:

$$\Delta\varphi(x,z) = \arg\left(\widetilde{A_T}\widetilde{A_R}^*\right) = 2k_0\Delta z$$

$$+\arg\left(\sum_j r_{Tj}(x,z)\exp(i2k_0z_j) \cdot \sum_j r_{Rj}(x,z)\exp(-i2k_0z_j)\right), \tag{5}$$

where $\arg(\ )$ denotes the calculation of argument, and $*$ is the complex conjugate operation.

Equation (5) demonstrates that the phase difference $\Delta\varphi(x,z)$ is affected not only by a phase change of $2k_0\Delta z$, which directly corresponds to the desired OPL change, but also by an additional error term arising from the variation in the PSF-weighted reflectivity that occurs with sample movement. Throughout this article, we denote this error as the motion-induced phase error. While our derivation is limited to motion within the (x,z) plane, it is important to note that the motion-induced phase error is also applicable to out-of-plane movement along the y-axis. Intriguingly, the above derivation reveals that the motion-induced phase error is pixel-specific and varies from pixel to pixel. Hence, self-referenced measurements that determine the phase difference between two pixels at different depths are ineffective in eliminating the motion-induced phase error.

2.2 Phase-restoring subpixel image shifting for accurate motion correction in FD-OCT

We conceived our phase-restoring subpixel image shifting approach from the general FD-OCT model (see Appendix A), where the way FD-OCT signals are formed in the axial direction departs fundamentally from how digital images are captured by standard cameras. As translational motion between cross-sectional frames is the dominant source of motion artifacts in high-speed OCT imaging, compared with rotational movement or image distortion within individual cross-sections [26], this study mainly concerns and corrects the translational shifts between the reference and target images.

We assume that the measured sample undergoes a translational shift of Δx in the lateral (x) direction and Δz in the axial (z) direction from the reference frame to the target frame. According

176 to the general FD-OCT model (see Eq. (A4) in Appendix A), the complex-valued spectral

177 interferograms of the reference frame $\tilde{I}_R$ and the target frame $\tilde{I}_T$ can be modeled as,

178
$$\tilde{I}_R(x,k) = S(k)\sum_j r_j \exp\left[-2\frac{(x-x_j)^2}{w_l^2}\right]\exp(i2kz_j), \tag{6}$$

179
$$\tilde{I}_T(x,k) = S(k)\sum_j r_j \exp\left[-2\frac{(x-x_j-\Delta x)^2}{w_l^2}\right]\exp\left[i2k(z_j+\Delta z)\right], \tag{7}$$

where k is the wavenumber, $S(k)$ is the power spectrum of the light source, r_j and (x_j, z_j) denote

the electric field reflectivity and the coordinate of the j^{th} scatterer in the reference frame, w_l is the

$1/e^2$ spot radius of the OCT beam focused on the sample. Note that the axial coordinate (z) in this

study, as well as z_j and Δz mentioned earlier, represents the optical path length (OPL) resulting

from both refractive index and axial location of the sample.

From Eqs. (6) and (7), it is evident that the axial location of an individual scatterer results in an

exponential term $\exp(i2kz_j)$ in the detected OCT signal, where $2kz_j$ is the OPD between the

beam scattered from the sample and the reference beam. In contrast, the OCT signal in the lateral

direction is determined by the scatterer's lateral location convolved with a PSF, similar to

capturing digital images using standard cameras. Considering the difference in the imaging

principle in the axial direction, if we manually multiply the spectral interferogram in FD-OCT with

a numerical term $\exp(i2k\Delta z')$, we can arbitrarily shift the image axially by any displacement with

an OPL of $\Delta z'$ as if the sample were displaced by the exact same distance in the real world. Unlike

conventional subpixel image shifting approaches, the above process does not require interpolation

or a sampling frequency that is sufficiently high to avoid aliasing.

More specifically, comparing Eqs. (6) and (7), the spectral interferograms before and after the

displacement satisfy the following relation [31, 32],

199
$$\tilde{I}_R(x,k) = \tilde{I}_T(x+\Delta x,k)\cdot\exp(-i2k\Delta z), \tag{8}$$

200 and it can be further written as,

201
$$\tilde{I}_R(x,k) = \tilde{I}_T(x+\Delta x,k)\cdot\exp(-i2k_0\Delta z)\cdot\exp\left[-i2(k-k_0)\Delta z\right], \tag{9}$$

where k_0 is the center wavenumber of the light source spectrum. The first exponential term

$\exp(-i2k_0\Delta z)$ accounts for the change of OPL, and the second wavenumber-dependent term

$\exp[-i2(k - k_0)\Delta z]$, in fact, corresponds to the sampling point mismatch induced by the axial

motion.

When applying the above findings to image registration in FD-OCT, we found that multiplying

both aforementioned exponential terms enables accurate reconstruction of complex-valued OCT

images as if the sample were physically shifted back, as written in Eq. (10),

210
$$\widetilde{I_c}(x, k) = \widetilde{I_T}(x, k) \cdot \exp(-i2k_0\Delta z) \cdot \exp[-i2(k - k_0)\Delta z], \qquad (10)$$

211 where $\widetilde{I_c}$ is the accurately reconstructed spectral interferogram after the axial correction. Equation

212 (10) is useful for eliminating the negative influence of bulk motion in self-referenced

213 measurements, such as when imaging local tissue deformations in vivo.

215 Notably, we can also correct the OCT image by multiplying only the second term, which eliminates

216 the extra motion-induced phase error while retaining the OPL change, as shown in Eq. (11),

217
$$\widetilde{I_c}'^{(x,k)} = \widetilde{I_T}(x, k) \cdot \exp[-i2(k - k_0)\Delta z], \qquad (11)$$

where $\widetilde{I_c}'$ is the corrected spectral interferogram that retains the OPL change. When using phase

signals to detect the sample's bulk movement, Eq. (11) can help isolate and eliminate the motion-

induced phase error that is coupled in the phase signal, allowing us to obtain the desired OPL

change.

To effectively correct for lateral motion, the sample must be sufficiently oversampled in the lateral

direction. Besides, the extra phase noise between adjacent A-scans, caused by bulk sample motion

and system instabilities (e.g., galvanometer jitter and reference arm fluctuations) [33], must be

significantly below π to maintain a stable phase relationship. Under these prerequisites, our lateral

bulk motion correction strategy is similar to the FT-based method, where we conduct the image

shift by multiplying an exponential term in the spatial frequency domain [28, 34]:

229
$$\mathcal{F}_x\{\widetilde{A_C}(x, z)\} = \mathcal{F}_x\{\widetilde{A_T}(x, z)\} \cdot \exp(iu\Delta x), \qquad (12)$$

where $\widetilde{A_C}$ is the reconstructed complex-valued OCT image after lateral correction, and u

represents the lateral spatial frequency. Note that $(\Delta x, \Delta z)$ refers to the displacement from the

reference frame to the target frame. When performing motion correction using Eqs. (10)-(12), the

target frame should be translated back by $(-\Delta x, -\Delta z)$ to its original position.

When benchmarking our proposed method, we compared its performance with the pixel-level

correction and FT-based subpixel motion correction techniques. We also turned off the piezo

actuator in phantom experiments to provide references for imaging static samples. In the FT-based

method, complex-valued OCT images were treated as digital images, and axial and lateral

displacements were corrected by multiplying the spatial frequency domain with $\exp(iu\Delta x) \cdot$

$\exp(iv\Delta z)$, where u and v denote the lateral and axial spatial frequencies, respectively [28]. For

pixel-level correction, we rounded the subpixel bulk movement, estimated using the methods in

the next section, to the nearest integer. Motion correction was then performed by directly shifting

the image by the negative value of the rounded integer.

2.3 Subpixel motion estimation from repeated cross-sectional scans and repeated volumetric

scans

We used various existing methods to achieve motion estimation down to the subpixel level. In

phantom experiments involving only axial motion, we estimated the subpixel-level axial bulk

motion using the phase change extracted from the phantom surface.

For rodent retinal imaging and phantom experiments with two-dimensional movements in the axial

and lateral directions, we adopted the single-step DFT approach [22, 23] to estimate subpixel-level

displacements between the first and subsequent cross-sectional B-scans. Specifically, a 2-fold

upsampled NCC function was first obtained by zero-padding the Fourier spectrum. The location

of its peak was found as the initial estimation. Since only a small neighborhood around the NCC

peak is of interest, the matrix-multiply DFT method was used to compute the κ-fold upsampled

NCC map in a 1.5 x 1.5 pixel neighborhood centered on the initial estimation [23]. In this study,

κ was set to 1000 to allow motion estimation with sufficiently small intervals. Compared with

conventional upsampling strategy using fast Fourier transform (FFT), the matrix multiplication

approach can greatly reduce the computational load.

In repeated volumetric scans for human retinal imaging experiments, we estimated the translational motion of individual B-scans with respect to the B-scans in a pre-selected reference volume. We followed the coarse-to-fine strategy proposed by Do et al. [25, 26], except for that in the fine estimation step, we adopted the single-step DFT approach to extend the previous pixel-level estimation to subpixel-level in the depth (z) and the line (x) dimensions. Briefly, during the coarse estimation step, we first selected a set of sub-volumes containing consecutive B-scans from the target volume. We then estimated the positions of these sub-volumes in the reference volume using the three-dimensional NCC method. Subsequently, for each B-scan in the target volume (referred to as the target B-scan), we determined its coarse shift in the scan (y) direction by linearly interpolating the sparse shifts of the sub-volumes. In the fine estimation step, for each target B-scan, we selected a sub-volume from the reference volume based on the interpolated coarse shift in the scan (y) direction. We then applied the single-step DFT approach to calculate the correlation value and the associated subpixel-level translational motion between the target B-scan and each B-scan in the selected reference sub-volume. Lastly, for each target B-scan, we obtained the estimated shifts ($\Delta x, \Delta y, \Delta z$) in the line, scan, and depth directions that produced the highest correlation value.

2.4 Evaluation metrics for quantitative assessment of motion correction performance

We validated the motion-induced phase error and assessed the performance of motion correction techniques on moving phantom samples and in-vivo retinas. Samples without local deformation allow us to quantitatively characterize the accuracy and sensitivity of phase signals in OCT images: Accuracy, which is defined as the deviation of phase signals from the ground truth movement, was estimated by calculating the spatial standard deviation (σ_s) of the phase signals across all pixels at a single time point; Sensitivity, on the other hand, corresponds to the phase fluctuation over time and was evaluated by computing the temporal standard deviation (σ_t) of phase variation across all time points. To provide a more intuitive understanding of how these metrics affect motion detection accuracy and sensitivity, we converted the phase units (radians) to their corresponding OPL using the equation $OPL = \varphi/2k_0$, where φ is the phase and k_0 is the center wavenumber of the light source spectrum.

3. Experiments

3.1 Point-scan OCT system

A custom-built spectral-domain point-scan OCT system was employed for both phantom and rodent ORG experiments, as previously reported [35]. The sample arm was modified according to specific imaging requirements: For phantom experiments, a scan lens (LSM04-BB, Thorlabs, USA) was placed after the galvo scanner to focus the beam on the sample, resulting in a spot size (full-width at half-maximum, FWHM) of 19.5 μm in air. For rodent ORG experiments, a scan lens (80 mm doublet) and an ocular lens (30 mm and 25 mm doublet) were used to conjugate the galvo scanner to the pupil plane. Their focal lengths were chosen to achieve smaller beam size and enlarged field of view. The theoretical lateral resolution was estimated to be 7.2 μm (FWHM) based on a standard rat eye model [36].

3.2 Phantom fabrication and imaging protocol

Two synthetic phantoms were fabricated by mixing titanium dioxide (TiO2) powder and polydimethylsiloxane (PDMS). Sample #1 had a TiO2-to-PDMS weight ratio of 5% and exhibited fully developed speckles, while a weight ratio of 0.45% was used for Sample #2 to obtain sparsely distributed scatterers. The mixtures were then vacuumed for 20 minutes and cured in an oven (90 °C) for 30 minutes. The phantom patch ($2 \times 2 \times 1$ mm) was cut off and attached to the surface of a high-precision piezo actuator (P-888.91, Physik Instrumente, Germany). A cover glass, as a static reference, was glued to a lens mount and placed over the phantom without contact. The base of the piezo actuator and the cover glass were connected to the last lens of the OCT sample arm using mechanical frames to reduce the disturbance from environmental vibrations.

To evaluate the performance of subpixel motion correction techniques as introduced in Section 2.4, we designed and implemented the following experiment protocols:

Protocol 1. The piezo actuator was driven by a sinusoidal voltage with a frequency of 1 Hz, resulting in a controlled axial vibration of Sample #1 with a peak-to-peak amplitude of ~2.7 μm. We selected a 1 Hz vibration frequency to minimize distortion within each B-scan. The recording consisted of 600 repeated B-scans, each with 1000 A-lines, acquired at 200 Hz.

Protocol 2. The piezo actuator was turned off so that Sample #1 was static, while all other settings

were the same as those in Protocol 1.

Protocol 3. The same voltage input as in Protocol 1 was used to drive the piezo actuator, resulting

in a controlled vibration of Sample #1 in the axial direction with the same frequency. The galvo

scanner was turned off. In the recording, a total of 400 repeated A-lines were acquired with a time

interval of 5 ms.

Protocol 4. To assess motion correction in both axial and lateral directions, we tilted the piezo

actuator to create a vibration direction of approximately 70° relative to the OCT beam. Three

representative samples were included: two phantoms (Sample #1 and #2), and a cover glass

(Sample #3). The piezo actuator was driven by a sinusoidal voltage with a frequency of 1 Hz,

resulting in a controlled vibration of ~8.5 μm in combined directions. The recording consisted of

600 repeated B-scans, each with 1000 A-lines, acquired at 200 Hz.

Protocol 5. The piezo actuator was turned off so that the sample remained static. All other settings

were identical to those in Protocol 4.

3.3 Animal preparation and optoretinogram imaging

The experiments were conducted in compliance with the guidelines and approval from Institutional

Animal Care and Use Committee (IACUC), SingHealth (2020/SHS/1574). Eight Brown Norway

rats were included in the imaging experiments. The animals were anesthetized with ketamine and

xylazine cocktail and fixed in a custom-built stereotaxic holder with integrated bite bar and ear bar

to mitigate the eye movements induced by breathing and heartbeat. Before the OCT imaging, the

pupil of the animal was dilated with a drop of 1% Tropicamide (Alcon, Geneva, Switzerland) and

2.5% Phenylephrine (Alcon, Geneva, Switzerland). During the imaging, the cornea was kept moist

with a balanced salt solution.

In each recording, 800 repeated B-scans were acquired at the same position with each B-scan

consisting of 1000 A-lines. Each dataset took a total acquisition time of 4 seconds. To measure the

rodent ORG in vivo, visual stimulation was generated by a white light LED (MCWHLP1,

Thorlabs, USA). The beam was collimated by an aspheric condenser lens. Then, the stimulation

light was converged by the ocular lens (30 mm and 25 mm doublet), resulting in a 43.4°

Maxwellian illumination on the posterior eye. A short flash with a duration of 2 milliseconds was
delivered to the eye 1 second after the recording started.
354
The phase difference between the inner segment/outer segment junction (IS/OS) and the rod outer
segment (ROS) was extracted to evaluate the functional response of photoreceptors to light stimuli.
This self-referencing step eliminates undesired phase drift across B-scans. The IS/OS and ROS
were segmented using an automatic segmentation algorithm based on graph theory and dynamic
programming [37]. In addition, multiply scattered light from superficial large vessels can cause
tail artifacts that disturb phase stabilities beneath these vessels [38]. Consequently, the regions
below the superficial large vessels were excluded from subsequent phase analysis. To delineate
large vessels, a binary OCT angiogram was generated by setting an adaptive threshold on the
inverse SNR and complex-valued decorrelation space [39].
364
3.4 Adaptive optics line-scan OCT system for human optoretinogram imaging
A custom-built adaptive optics (AO) line-scan OCT system was constructed for human ORG
imaging [11, 40], and the layout can be found in previous report [41]. For human optoretinogram
imaging, the experiment was approved by the University of Washington Institutional Review
Board and was conducted in compliance with the tenets of the Declaration of Helsinki. Three
emmetropic subjects with no known retinal pathologies were enrolled in the study. All subjects
signed an informed consent before their participation. Cycloplegia was introduced with
Tropicamide 1% ophthalmic solution (Akorn Inc.) before the OCT imaging to dilate the pupil and
increase numerical aperture. Prior to recording the human ORG signal, each subject underwent a
dark adaption period of 3 to 4 minutes. Three experiment protocols were employed:
375
Protocol 1. 50 volumes (400 B-scans each) were acquired without visual stimulus at a B-scan rate
of 6 kHz and a volumetric rate of 12.8 Hz.
Protocol 2. A 20-ms visual stimulus (660 ± 10 nm LED in Maxwellian view) was delivered after
10 volumetric scans. 40 volumes were recorded using the same parameters as Protocol 1.
Protocol 3. 50 volumes (600 B-scans each) were acquired without visual stimulus at a B-scan rate
of 12 kHz and a volumetric rate of 17.0 Hz.
382

4. Results

4.1 The numerical validation of motion-induced phase error in FD-OCT, and its accurate correction by PRESIR

Fig. 1. Simulation analysis showing the motion-induced phase error and its accurate correction by PRESIR. (a) Top: The raw phase differences with respect to that at the initial position when moving the simulated sample along the axial direction. Bottom: The distribution of the displacements measured from the above raw phase signals. (b) The distribution of displacements when the sample underwent lateral movement. (c) The motion detection accuracy, calculated from the standard deviation of the phase changes across pixels (σ_s), when the sample was translated along the axial or the lateral direction. (d) The motion detection accuracy (left) before and (right) after motion correction using PRESIR when the sample was moved in both axial and lateral directions.

To examine the proposed motion-induced phase error, we conducted numerical simulations using a close-to-reality model capable of simulating speckle patterns in FD-OCT [42]. The simulation

parameters, including the power spectrum of the light source, lateral resolution, and lateral

sampling rate, were set to be consistent with the phantom experiment. As shown in Fig. 1a, we

gradually translated the simulated sample in the axial direction by 3 μm with a step size of 0.01

μm. We calculated and unwrapped the phase differences between the subsequent positions and the

initial position to obtain the phase change of each pixel. Instead of observing the phase changes in

all pixels being consistent with the global translational shifts, we noticed a clear error band that

fits the prediction of our theoretical analysis (Fig. 1a). Moreover, as the OCT image gradually

decorrelated when we increased the displacement to 3 μm, the phase error band also broadened

dramatically. Figure 1b illustrates the distribution of displacements measured from the sample that

underwent lateral movement. As expected, the center of the distribution remained at 0, while the

increase of lateral shift gradually broadened the distribution.

To quantify the motion detection accuracy, we calculated the standard deviation of measured phase

changes across pixels for each translation position. Figure 1c shows that the spatial standard

deviation of the detected motion (σ_s) across all the pixels gradually increased to ~150 nm and ~30

nm when the sample was translated by 3 μm along the axial and lateral directions, respectively.

This disparity between axial and lateral movements stemmed from the axially compressed OCT

PSF. In our simulation and phantom experiments, the lateral resolution (19.5 μm, FWHM) was

much lower than the axial resolution (1.9 μm, FWHM), resulting in less significant changes in the

PSF-weighted reflectivity (Eq. 5) for lateral motion. Figure 1d also demonstrates that the motion-

induced phase error was dominated by axial motion.

Our PRESIR method can restore the original sampling pixels for translationally shifted OCT

images, thus restoring the original PSF-weighted reflectivity. As shown in Fig. 1d, σ_s measured

from the phase signals corrected by the PRESIR method remained near zero.

4.2 Error-free motion detection and SNR-limited phase sensitivity validated by moving

phantom imaging

To further validate the effectiveness of our PRESIR method in correcting the motion-induced

phase error, we conducted phantom imaging experiments. In the first set of experiments (see

Section 3.2, Protocols 1-3), we vibrated the sample along the axial direction (Fig. 2), as the

simulation analysis indicated that axial movement was the primary contributor to motion-induced

phase error considering an axially compressed OCT PSF. In addition, to demonstrate the PRESIR

method's performance in the presence of both axial and lateral motion and its applicability to

various samples/scenarios, we conducted a second set of experiments (see Section 3.2, Protocols

4 and 5), where we introduced two-dimensional vibrations on three representative samples (Fig.

3).

As depicted in Fig. 2a, a synthetic phantom (refer to Section 3.2) was attached to a piezo actuator

driven by a sinusoidal voltage input to mimic a moving biological tissue; a cover glass served as

a static reference to eliminate undesired phase drift. Temporal phase changes of individual pixels,

measured from the phantom surface (blue curves in Fig. 2b) and the internal speckles (cyan curves

in Fig. 2b, with the outliers removed as per the criterion in Appendix C) exhibited similar

sinusoidal patterns due to axial motion. Meanwhile, noticeable motion-dependent deviations were

observed from the phase changes of individual pixels (blue and cyan curves in Fig. 2b), likely due

to the motion-induced phase error discussed in the preceding theoretical analysis. Supplementary

Video 1 reveals the spatiotemporal evolution of phase errors measured from internal speckle

patterns (an area around the cyan region in Fig. 2a). The phase errors in individual pixels were

repetitive over periodic sinusoidal bulk tissue motion, which corroborated our theoretical analysis

of motion-induced phase errors as deterministic errors instead of stochastic noise.

To correct the motion-induced phase error, we estimated the sample displacement by calculating

the average phase change from the phantom surface. After applying the PRESIR method for

motion correction and removing the outliers (refer to Appendix C for the criterion), we observed

a significant reduction in motion-dependent errors, resulting in consistent OPL changes across all

surface pixels (red curves in Fig. 2b) and internal speckle patterns (pink curves in Fig. 2b). Fig. 2d

shows the distribution of the motion measured from the speckles at five time points (as shown by

the colored dots in Fig. 2b). Compared with the raw phase results (the bottom gray areas in Fig.

2d), the PRESIR method achieved much sharper measurement distributions (the colored peaks in

Fig. 2d). After motion correction using PRESIR, the standard deviation of the detected OPL

change across individual pixels (σ_s) was reduced to a level no longer dependent on motion (red

and pink curves in Fig. 2e).

Fig. 2. Phantom experiments were conducted to validate the motion-induced phase error and our proposed PRESIR method in the presence of axial bulk motion. (a) The structural OCT image of the phantom's cross-section. Scale bar: 300 μm. (b) The OPL change measured from the temporal phase change on the phantom surface across 20 adjacent A-lines (blue region in Fig. 2a) and from the internal speckles (cyan region in Fig. 2a). The blue and cyan curves indicate the results without correction, while the red and pink curves denote the results after PRESIR. (c) Schematic of the sample undergoing axial vibration. We extracted the sample's axial movement by calculating the phase difference between the sample and the cover glass to simulate application scenarios in which the sample's axial bulk motion is of interest. (d) The distribution of the bulk motion measured from the speckles at 5 time points (as labeled by the colored dots in Fig. 2b). (e) At each time point, the standard deviation of the OPL change across space (σ_s) in four configurations (on the surface or from the speckles, with or without PRESIR) is represented by a curve corresponding to the same legend in Fig. 2b. (f) To assess the sensitivity of detecting local deformation during the sample's axial movement, we calculated the phase differences between the internal speckle patterns and the phantom surface when the sample is under controlled axial vibration. (g) Phase variation at individual pixels in the speckle patterns (the cyan region in Fig. 2a) with respect to the phantom surface after corrected by the pixel-level correction (cyan curves), the FT-based correction (green curves), and the PRESIR (pink curves). The dashed gray line indicates the sample bulk motion. (h) The standard deviation of OPL change over time (σ_t) under different conditions (colored halves of the violin plots) and the corresponding theoretical estimated phase sensitivities limited by the SNR (gray halves of the violin plots).

An important application of the proposed PRESIR method is for improving the phase sensitivity during the measurement of the nanoscopic local deformations in moving biological tissues. To evaluate phase sensitivity/stability, we measured the phase differences of individual pixels in the speckle patterns with respect to the phantom surface (Fig. 2f). Figure 2g illustrates phase variations over time in the cyan regions of Fig. 2a, with outliers removed according to the criterion in Appendix C. When using conventional pixel-level correction, the phase error (cyan curves in Fig. 2g) increased gradually as the residual bulk motion, defined as the deviation of the bulk motion (dashed gray curve in Fig. 2g) from the nearest integer, approached half a pixel. Meanwhile, the FT-based method led to even larger phase error (green curves in Fig. 2g). In contrast, after applying the PRESIR method for motion correction, phase variation across all pixels was significantly reduced (pink curves in Fig. 2g), with the remaining phase variation becoming independent of the sample's bulk motion.

In order to quantify the phase sensitivities at individual pixels, we analyzed the temporal standard deviation (σ_t) of the OPL variation over 3-second recordings. Additionally, we calculated the theoretical SNR-limited phase sensitivity for each pixel [2]. As shown in Fig. 2h, due to the sample movement, the phase variations after pixel-level correction (16.4 ± 8.9 nm, mean $\pm$ standard deviation) were significantly higher than the theoretical SNR-limited phase sensitivities (6.2 ± 3.8 nm). Motion correction using the PRESIR method improved the phase stabilities of individual pixels across repeated B-scans to 6.7 ± 2.2 nm. Meanwhile, the SNR-limited phase sensitivities were adjusted to 5.5 ± 2.2 nm owing to the stabilized SNRs. Such performance closely resembled results measured from a static sample across repeated B-scans (6.7 ± 2.3 nm, with SNR-limited phase sensitivities at 5.6 ± 2.4 nm). We determined that the remaining deviation from the SNR-limited phase sensitivity was caused by the instability of the galvo scanner during the scanning [3]. Once we turned off the galvo scanner for repeated A-scans, the phase stabilities measured after motion correction by PRESIR from eight independent trials (5.7 ± 2.2 nm) were considerably close to the SNR-limited phase stability (5.6 ± 2.1 nm). These results demonstrate that the PRESIR method effectively eliminates motion-induced phase errors in phase-sensitive OCT, achieving the fundamental phase sensitivity limit determined by the SNR.

Fig. 3. Phantom experiments demonstrating the effectiveness of the proposed PRESIR method in correcting combined

axial and lateral bulk motion. (a) Schematic of a sample undergoing two-dimensional vibration. Phase stability was

evaluated by calculating the phase difference between speckle patterns (regions enclosed by magenta outlines in Figs.

3c and 3d) and the phantom surface, or between the two surfaces of the cover glass (magenta lines in Fig. 3e). (b) A

representative bulk motion measured from Sample #1 in (c). (c)-(e) Left: Structural images of three representative

samples (Samples #1, #2, and #3) described in Section 3.2. Scale bar: 300 μm. Right: Phase variations measured at

individual pixels after applying pixel-level correction (cyan curves), FT-based correction (green curves), and PRESIR

(pink curves).

In the presence of combined axial and lateral bulk motion (Fig. 3a), we adopted the single-step

DFT approach (see Methods) to estimate the bulk tissue motion (Fig. 3b). To evaluate the phase

stability in Samples #1 and #2 (PDMS samples as described in Section 3.2), we calculated the

phase difference between the internal speckle patterns (regions enclosed by magenta outlines in

Figs. 3c and 3d) and the phantom surface. Outliers were removed according to the criterion

described in Appendix C. For Sample #3 (cover glass), we calculated the phase difference between

two surfaces to assess the phase stability (magenta lines in Fig. 3e). The pixel-level and FT-based

methods resulted in phase variations dependent on the bulk motion. In comparison, our proposed

PRESIR method eliminated the motion-dependent phase variations. A quantitative comparison
using the temporal standard deviation (σ_t) of the OPL variations (Table 1) demonstrated that the
phase stability achieved with PRESIR surpassed that of the benchmark pixel-level correction and
was comparable to a static sample.

Table 1: Measured phase stabilities (σ_t) and estimated SNR-dependent phase stabilities (in brackets) from three
representative samples using different configurations. All values are expressed in nm as mean±standard deviation.

Configuration		Sample #1	Sample #2	Sample #3
Moving sample	Pixel-level	18.0±9.2 (5.6±2.4)	20.7±9.9 (10.1±3.4)	14.7±8.4 (6.8±4.9)
	PRESIR	6.1±2.2 (5.0±1.8)	9.9±2.9 (8.9±2.6)	6.6±2.7 (5.7±2.8)
Static sample		6.0±2.3 (5.1±1.9)	9.8±2.8 (9.0±2.9)	6.5±2.9 (5.6±3.0)

4.3 Improved motion detection sensitivity for in-vivo label-free tissue dynamics imaging at the nanoscopic scale

The phantom imaging experiment demonstrated the PRESIR's ability to eliminate the motion-
induced phase error when measuring the sample's bulk motion (Figs. 2c-e). The experiment also
revealed the significantly improved phase sensitivity/stability when the sample's local deformation
is of interest (Figs. 2f-h and Fig. 3). To further investigate motion detection performance during
label-free imaging of nanoscopic tissue dynamics in vivo, we conducted ORG imaging
experiments in both rodents and humans.

For rodent ORG imaging, we performed repeated B-scans in a wild-type rat's retina using a point-
scan OCT system. Fig. 4a shows a structural image and a time-elapsed M-scan at one A-line. As
shown in Fig. 4b, we estimated the bulk motion of the retina using the efficient single-step DFT
approach (see Methods). The PRESIR method corrected the apparent bulk motion in the raw M-
scan (Fig. 4c, 1st column), resulting in nearly static retinal layers (Fig. 4c, 4th column). In contrast,
pixel-level correction left serrated residual motion (Fig. 4c, 2nd column), while the FT-based
correction method introduced severe side lobes unexpectedly (Fig. 4c, 3rd column).

Fig. 4. In-vivo rodent retinal imaging using a non-AO point-scan OCT. (a) Top: Structural image of a Brown Norway rat's retina. The pink, cyan, and red areas represent the inner segment/outer segment junction (IS/OS), the rod outer segment (ROS) and blood vessels, respectively (refer to Section 3.3). Bottom: a representative time-elapsed M-scan at one A-line. Scale bar in spatial dimension: 100 μm. Scale bar in temporal dimension: 0.5 s. (b) Bulk motion of the retinal tissue estimated by the efficient single-step DFT approach. (c) Enlarged M-scans (enclosed red window in Fig. 3a) without correction (1st column), after pixel-level correction (2nd column), FT-based method correction (3rd column), and PRESIR method correction (4th column). Scale bar in spatial dimension: 20 μm. Scale bar in temporal dimension: 0.2 s. (d) The phase differences between the brightest pixel in IS/OS and ROS on one representative A-line after the pixel-level correction (blue line), the FT-based correction (green line), and the PRESIR (red line), when no light stimulus was delivered to the retina. (e) Standard deviation distribution of phase fluctuation between IS/OS and ROS over time (σ_t) across A-lines, comparing pixel-level correction to PRESIR. The dashed black line represents the barrier where the two methods yield the same performance.

Using the IS/OS layer as a reference to cancel out phase drifts between B-scans, Supplementary Videos 2 and 3 demonstrate the pulsatile deformation before and after applying the PRESIR method. Compared to raw phase signals, the PRESIR method effectively eliminated motion-induced phase errors and enabled reliable visualization of pulsatile deformation, highlighting the importance of optimal bulk tissue correction in detecting local tissue deformation. To quantitatively compare the phase stability enabled by different motion correction methods, the phase difference between the brightest pixels in the IS/OS (the pink area in Fig. 4a) and the ROS (the cyan area in Fig. 4a) was extracted from individual A-lines (Fig. 4d). Across the entire field

of view, except for the region below large superficial vessels, the standard deviation of such phase

differences over time (σ_t) was reduced to 21.1±7.1 nm (mean±standard deviation) by PRESIR,

compared with 23.8±7.4 nm after pixel-level correction and 23.2±8.0 nm after FT-based

correction. Fig. 4e demonstrates that the PRESIR method significantly improved the phase

stability compared with pixel-level correction.

Figure 5a, in its first column, presents a violin plot comparing the phase stabilities previously

shown in Fig. 4e. To assess the robustness of our proposed method, we extended the validation to

an additional seven rats. Across all eight animals (Fig. 5a), our proposed method achieved a phase

stability of 21.3±8.0 nm, outperforming both the pixel-level correction (24.3±8.5 nm) and the FT-

based correction (23.5±8.8 nm). In ORG measurements with a 2-ms light stimulus delivered at

the time $t = 0$, the PRESIR method produced more stable and less noisy ORG signals than pixel-

level correction (Fig. 5b), in which case a clean ORG signal after averaging across 6 pixels is

shown in Fig. 5c.

Fig. 5. Phase stabilities measured from eight rodents and representative ORG signals in response to visual stimuli. (a)

Temporal phase stabilities measured from eight rodents after the pixel-level correction and PRESIR method. (b)

Representative ORG signals after the pixel-level correction (blue line) and the PRESIR (red line) obtained from one

A-line without averaging. (c) ORG signal of a wild-type rat after the PRESIR. The red line represents the average of

6 phase signals with high phase stability during the pre-stimulus period (pre-stimulus $\sigma_t < 10$ nm), and the color band

denotes the range of their standard deviation.

Fig. 6. In-vivo human optoretinography using an AO line-scan OCT. (a) En-face image of the cone outer segment

tips (COST) layer in a human retina. (b) Cross-sectional structural image of the same retina. Scale bar: 100 µm. (c)

Representative time-elapsed M-scans corrected by the pixel-level method (left), the FT-based method (middle) and

the PRESIR method (right). Scale bar in spatial dimension: 20 µm. Scale bar in temporal dimension: 1 s. (d)

Representative phase differences between the IS/OS and COST at individual A-lines after the pixel-level correction

(dashed lines), and the PRESIR (solid lines), when no light stimulus was delivered to the retina. (e) The standard

deviation distribution illustrates phase fluctuations between the IS/OS and COST over time (σ_t) across A-lines,

comparing pixel-level correction with PRESIR. The dashed black line indicates the point at which the two methods

exhibit equivalent performance. (f) Representative human ORG signals measured from individual A-lines (labeled by

the dots in Fig. 6a) showing higher phase stability after the PRESIR (solid lines) than those corrected by the pixel-

level correction (dash lines).

We further tested the proposed method for enhancing motion detection performance in human

ORG imaging using a high-speed adaptive-optics line-scan OCT system. Figs. 6a and 6b show the

en-face image at the cone outer segment tips (COST) and a structural image at one cross-section

of the retina. The translational bulk motion of each volume was estimated using a modified coarse-

to-fine approach (refer to Methods). Regarding motion correction performance, the PRESIR

method achieved more stable retinal layers (Fig. 6c, right) compared with pixel-level correction

(Fig. 6c, left) and the FT-based method (Fig. 6c, middle). Fig. 6d shows the representative phase

differences between the IS/OS and the COST at two individual A-lines without light stimulus

following Section 3.4, Protocol 1. The phase stability was evaluated by calculating the standard

deviation of the phase difference over time (σ_t). As shown in Fig. 6e, across the entire field of

view while excluding gaps between cones based on averaged intensity from IS/OS and COST

layers, the PRESIR method achieved higher phase stability with smaller phase fluctuation standard

deviations (15.3 $\pm$ 9.0 nm, mean $\pm$ standard deviation) compared with pixel-level correction

(19.7$\pm$10.0 nm). In contrast, the FT-based correction significantly degraded the phase stability

(46.4$\pm$17.3 nm). Interestingly, our PRESIR approach not only suppressed unwanted fluctuations

(Fig. 6f, location 2) but also recovered ORG signals (obtained via Section 3.4, Protocol 2) that

would otherwise suffer from phase unwrapping errors when using the pixel-level correction

method (Fig. 6f, location 1).

Fig. 7. In-vivo human retinal imaging in two additional human subjects. (a) and (c) En-face images of the cone outer

segment tips (COST) layer. (b) and (d) Corresponding phase stabilities obtained after the pixel-level correction and

PRESIR.

To assess the generalizability of our findings, we compared the performance of PRESIR with

conventional approaches in two additional human subjects using a faster imaging protocol (Section

3.4, Protocol 3). PRESIR consistently demonstrated superior phase stability across both subjects.

In Subject #2, PRESIR achieved a phase stability of 12.4$\pm$4.3 nm, compared to 18.3$\pm$7.2 nm for

the pixel-level correction and 50.6$\pm$22.2 nm for the FT-based correction (Figs. 7a and 7b).

Similarly, in Subject #3, the phase stability after PRESIR was 14.1$\pm$5.8 nm, compared to 20.2$\pm$8.7

nm after the pixel-level correction and 46.8±18.8 nm after the FT-based correction (Figs. 7c and
7d).

5. Discussion

In this article, we present a phase-restoring subpixel image registration (PRESIR) approach for
post-hoc image registration in FD-OCT, which allows for translational shifting of OCT images by
arbitrary displacements while accurately restoring physically meaningful phase components. We
discovered that in moving samples, the phase difference measured by FD-OCT includes both the
anticipated OPL change corresponding to the sample movement and a motion-induced phase error
arising from alterations in PSF-weighted reflectivity of scatterers. Correcting such phase error
requires reproducing the same sampling points at each frame in the time-elapsed recording. By
employing the PRESIR method, we achieved phase-sensitive imaging of a moving phantom with
a sensitivity close to the fundamental limit set by the SNR. Moreover, we showed that the PRESIR
method substantially improved motion detection performance in label-free imaging of nanoscopic
tissue dynamics in vivo, particularly in the context of emerging functional assessments using
optoretinography.

The residual motion-induced phase error after PRESIR primarily depends on the accuracy of
translational motion estimation, which could be further improved by adopting more sophisticated
subpixel-level motion estimation methods based on model fitting or optimization strategies [24].
Recently, convolutional neural networks (CNNs) have been used to estimate 3D translational
motion between repeated volumetric scans, enabling improved accuracy and reduced
computational time [43, 44].

The present study has several limitations, particularly concerning repeated B-scans in rodent ORG
experiments, where the out-of-plane motion remained uncorrected. Depending on its magnitude,
the out-of-plane motion may decorrelate the speckle patterns and degrade the phase sensitivity.
While translational displacements are the primary source of motion artifacts in high-speed OCT
imaging [26], motion artifacts due to other types of movements may also exist. Recent studies have
employed affine transformation to rectify translation, rotation, and scaling errors [45, 46], while
non-rigid B-spline transformation has been used to assess local deformation between repeated

volumetric scans [47]. Our proposed method may inspire new subpixel-level phase-restoring motion correction approaches for these scenarios. Meanwhile, our current model assumes a collimated OCT beam, justified by the low numerical aperture typically used in ocular imaging OCT systems to maintain a relatively consistent transverse resolution throughout the entire axial (depth) scan [48]. Additional impacts caused by defocus can be found in Appendix D.

Our proposed PRESIR approach has many potential applications in various OCT imaging modalities. In Doppler OCT, the phase difference between repeated or adjacent densely sampled A-scans is calculated to quantify flow velocity [6]. However, as shown in this study, uncorrected motion-induced phase errors can compromise measurement accuracy even when the tissue movement is as small as 10 nm in the axial direction. In optical coherence elastography, both the speckle-tracking and phase-sensitive detection methods were used to estimate sample displacements [7]. The PRESIR method's ability to manipulate OCT images as if the sample were physically shifted might enable new motion estimation methods through optimization. In OCT angiography, complex-value-based algorithms offer higher motion contrast, but their performance is susceptible to phase error due to bulk motion [49], which could be effectively suppressed by the PRESIR method. Furthermore, our proposed approach may also benefit computational imaging technologies [50], where phase stability is critical to their in-vivo implementations.

Acknowledgments

We thank Dr. G. Barbastathis at MIT, Dr. D. Palanker at Stanford University, Drs. A. Roorda and F. Feroldi at the University of California, Berkeley, and Dr. E. Pugh at the University of California, Davis, for fruitful discussions.

Author contributions

H.L. and T.L. conceived and designed the study. B.T. and L.S. built the ultrahigh-resolution point-scan OCT setup. V.P.P. and R.S. built the adaptive optics line-scan OCT setup. H.L., B.T., and V.P.P. conducted the experiments. V.A.B. supported the animal preparation. H.L. and T.L. analyzed the data and wrote the article. All authors reviewed and edited the article. T.L. supervised the study.

Funding sources

Tong Ling acknowledges the support of the National Research Foundation, Singapore for the NRF Fellowship Award (NRF-NRFF14-2022-0005), the Startup Grant (SUG) from Nanyang Technological University, the seed funding programme under NMRC Centre Grant – Singapore Imaging Eye Network (SIENA) (NMRC/CG/C010A/2017), and the Ministry of Education, Singapore under its AcRF Tier 1 Grant (RS19/20; RG28/21). Leopold Schmetterer acknowledges the funding support for the National Medical Research Council (CG/C010A/2017_SERI; OFLCG/004c/2018-00; MOH-000249-00; MOH-000647-00; MOH-001001-00; MOH-001015-00; MOH-000500-00; MOH-000707-00), National Research Foundation Singapore (NRF2019-THE002-0006 and NRF-CRP24-2020-0001), A*STAR (A20H4b0141), the Singapore Eye Research Institute & Nanyang Technological University (SERI-NTU Advanced Ocular Engineering (STANCE) Program), and the SERI-Lee Foundation (LF1019-1) Singapore. Veluchamy A. Barathi acknowledges the support for Singapore NMRC Centre Grant (NMRC/CG/M010/2017/Pre-Clinical). Ramkumar Sabesan and Vimal P. Pandiyan acknowledge the funding support for NIH/NEI grants U01EY032055, R01EY029710; unrestricted grant from Research to Prevent Blindness to UW Ophthalmology, Burroughs Wellcome Fund Careers at the Scientific Interfaces Award.

Data availability

All data needed to evaluate the conclusions in the paper are present in the paper. Additional data related to this paper may be requested from the authors.

Competing interests

H.L. and T.L. are inventors on a PCT patent application (PCT/SG2023/050286) related to this work. V.P.P. and R.S. have a commercial interest in a US patent (PCT/US2020/029984) describing the technology for the line-scan OCT for optoretinography. The authors declare that they have no other competing interests.

Appendix

A. FD-OCT signal manifestations in the k-domain, spatial domain, and spatial frequency domain

We assume that individual scatterers along an A-line in the sample follow a reflectivity distribution $\eta(z)$, which can be written as,

$$\eta(z) = \sum_j r_j \delta(z - z_j), \tag{A1}$$

where z represents the optical path length (OPL) - defined as the integral of refractive index along the physical depth, r_j stands for the electric field reflectivity of the j^{th} scatterer, z_j indicates the axial location of the j^{th} scatterer in OPL, and $\delta(\ )$ denotes the Dirac delta function.

1) Spectral interferogram formed on the detector (k domain)

Under the FD-OCT framework, the corresponding spectral interferogram $\tilde{I}(k)$ can be modeled as the linear superposition of scattered signals from each scatterer [18, 42],

$$\tilde{I}(k) = S(k) \cdot \sum_j r_j \exp(i2kz_j), \tag{A2}$$

where k is the wavenumber and $S(k)$ is the power spectrum of the light source. For simplicity, we have neglected DC terms, auto-correlation terms, complex conjugate artifacts, and constants like the responsivity of the detector.

If we further take the lateral direction (x) into consideration and assume an illumination beam with a Gaussian profile, the field reflectivity map $\eta(x, z)$ and its corresponding two-dimensional (2D) spectral interferogram $\tilde{I}(x, k)$ can be modeled as [19],

$$\eta(x, z) = \sum_j r_j \delta(x - x_j, z - z_j), \tag{A3}$$

$$\tilde{I}(x, k) = S(k) \cdot \sum_j r_j \exp\left[-2\frac{(x-x_j)^2}{w_l^2}\right] \exp(i2kz_j), \tag{A4}$$

where x_j is the lateral position of the j^{th} scatterer, w_l is the $1/e^2$ spot radius of the OCT beam focused on the sample.

2) Complex-valued OCT image obtained from a Gaussian-shaped illumination spectrum (spatial domain)

753 The depth-resolved OCT signal can be reconstructed by performing a Fourier transform along the
754 spectrum (k) direction [18],

$$\tilde{A}(x, \hat{z}) = \mathcal{F}_k\{\tilde{I}(x, k)\}$$

756
$$= \gamma(\hat{z}) \otimes \sum_j r_j \exp\left[-2\frac{(x-x_j)^2}{w_l^2}\right] \delta(\hat{z} - 2z_j) = \sum_j r_j \exp\left[-2\frac{(x-x_j)^2}{w_l^2}\right] \gamma(\hat{z} - 2z_j), \quad \text{(A5)}$$

757 where $\tilde{A}$ is the complex-valued OCT image, and $\hat{z} = 2z$ denotes the round-trip OPL variable. $\gamma(\hat{z})$
758 is the coherence function of the OCT system, defined as the Fourier transform of the power
759 spectrum, while $\otimes$ denotes the convolution operation.
760
761 Given a normalized Gaussian-shaped spectrum $S(k)$, the coherence function can be obtained by,

$$S(k) = \frac{1}{\Delta k \sqrt{\pi}} \exp\left[-\left(\frac{k-k_0}{\Delta k}\right)^2\right], \quad \text{(A6)}$$

763
$$\gamma(\hat{z}) = \mathcal{F}_k\{S(k)\} = \exp\left(-\frac{\Delta k^2 \hat{z}^2}{4}\right) \exp(-ik_0\hat{z}), \quad \text{(A7)}$$

764 where k_0 is the center wavenumber of the light source spectrum and Δk is the half-width of the
765 spectrum at $1/e$ of its maximum.
766
767 Combining Eqs. (A5) and (A7), and substituting $\hat{z}$ by $2z$, the OCT image can be written as,

768
$$\tilde{A}(x, z) = \sum_j r_j \exp\left[-2\frac{(x-x_j)^2}{w_l^2}\right] \cdot \exp\left[-\Delta k^2(z - z_j)^2\right] \exp[-i2k_0(z - z_j)] \quad \text{(A8)}$$

769 and it can be further simplified as,

770
$$\tilde{A}(x, z) = h(x, z) \otimes \eta(x, z), \quad \text{(A9)}$$

771 where $h(x, z) = \exp\left(-2\frac{x^2}{w_l^2}\right) \exp(-\Delta k^2 z^2) \exp(-i2k_0 z)$ is the point spread function (PSF) of the
772 OCT system.
773
774 **3) Fourier transform of the complex-valued OCT image (spatial frequency domain)**
775 The Fourier transform of the complex-valued OCT image is,

776
$$\mathcal{F}_{xz}\{\tilde{A}(x, z)\}(u, v) = \mathcal{F}_{xz}\{h(x, z)\} \cdot \mathcal{F}_{xz}\{\eta(x, z)\} = H(u, v) \cdot \mathcal{F}_{xz}\{\eta(x, z)\}, \quad \text{(A10)}$$

777   where u and v represent the lateral and axial spatial frequency. Equation (A10) indicates that the
778   profile of the spatial frequency signal of a complex-valued OCT image depends on the system's
779   optical transfer function $H(u, v)$, as shown in Eq. (A11),

780
$$H(u, v) = \frac{\pi w_l}{\sqrt{2}\Delta k} \exp\left(-\frac{w_l^2 u^2}{8}\right) \exp\left[-\frac{(v + 2k_0)^2}{4\Delta k^2}\right].$$
(A11)

782   **B. Change in PSF-weighted reflectivity during sample movement**
783   Following Eqs. (1) and (2) in the main text and Eq. (A8) in Appendix A, the complex-valued OCT
784   images $\widetilde{A_R}(x, z)$ and $\widetilde{A_T}(x, z)$ measured from the reference frame and the target frame can be
785   modeled as

786
$$\widetilde{A_R}(x, z) = \sum_j r_{Rj}(x, z)\exp\left[-i2k_0(z - z_j)\right],$$
(A12)

787
$$\widetilde{A_T}(x, z) = \sum_j r_j \exp\left[-2\frac{(x - x_j - \Delta x)^2}{w_l^2}\right] \cdot \exp\left[-\Delta k^2(z - z_j - \Delta z)^2\right] \exp\left[-i2k_0(z - z_j - \Delta z)\right]$$

788
$$= \exp(i2k_0\Delta z) \cdot \sum_j r_{Tj}(x, z)\exp\left[-i2k_0(z - z_j)\right],$$
(A13)

789   where $r_{Rj}(x, z)$ and $r_{Tj}(x, z)$ are defined as the PSF-weighted reflectivities of scatterers in the
790   reference and target frames:

791
$$r_{Rj}(x, z) = r_j \exp\left[-2\frac{(x - x_j)^2}{w_l^2}\right] \exp\left[-\Delta k^2(z - z_j)^2\right],$$
(A14)

792
$$r_{Tj}(x, z) = r_j \exp\left[-2\frac{(x - x_j - \Delta x)^2}{w_l^2}\right] \exp\left[-\Delta k^2(z - z_j - \Delta z)^2\right].$$
(A15)

C. Criterion to remove outliers in phantom experiment
Phase unwrapping errors occurring at a few pixels can distort statistical estimations, causing them
to deviate from the actual distributions of the measured phase signals. For example, when
calculating the standard deviation of the measured phase signals across a series of pixels, these
outliers can result in a substantially overestimated standard deviation, which hinders a reliable
estimation of the measurement accuracy. To exclude the outliers, we adopted the criterion
introduced in previous studies, which sets the upper and lower thresholds as $q_3 + w(q_3 - q_1)$ and
$q_1 - w(q_3 - q_1)$, where w was set to 2 in this study, q_1 and q_3 represent the 25th and 75th
percentiles of the sample data, respectively [51]. Assuming a Gaussian distribution of motion-

induced phase errors across speckle patterns, we expect this threshold to exclude only 0.2% of the

signals. Consequently, the chosen threshold should have a minor impact on the overall signal

distribution while effectively suppressing outliers that deviate significantly from the distribution

profile.

D. Impact of defocus on motion correction

Considering a focused Gaussian beam, the spectral interferogram of the reference frame $\widetilde{I}_R$ can be

written as [48, 52],

811
$$\widetilde{I}_R(x, k; z_0) = S(k) \cdot \sum_j \frac{w_0^2}{w^2(z_j; z_0)} r_j \exp\left[-2\frac{(x-x_j)^2}{w^2(z_j; z_0)}\right]$$

812
$$\cdot \exp\left[i2kz_j + i\frac{kx_j^2}{R(z_j; z_0)} - i2\psi(z_j; z_0)\right], \tag{A16}$$

813 where z_0 is the depth position of the focus and w_0 is the beam radius at the focal plane. $w(z; z_0)$

814 and $R(z; z_0)$ account for the depth-dependent beam waist size and the phase curvature of the

815 wavefront, respectively. $\psi(z_j; z_0)$ is the Guoy phase shift. These parameters are given by,

816
$$w(z_j; z_0) = w_0\sqrt{1 + \left(\frac{z_j - z_0}{z_R}\right)^2}, \tag{A17}$$

817
$$R(z_j; z_0) = (z_j - z_0)\left[1 + \left(\frac{z_R}{z_j - z_0}\right)^2\right], \tag{A18}$$

818
$$\psi(z_j; z_0) = \tan^{-1}\left(\frac{z_j - z_0}{z_R}\right), \tag{A19}$$

where z_R is the Rayleigh range.

The consistency of the PSF across the lateral direction at a given depth suggests that it should not

impact the effectiveness of our lateral motion correction. For simplicity, we will focus on axial

displacement in the following derivation to examine the influence of depth-dependent PSF on the

performance of axial motion correction. When the sample undergoes a bulk motion of Δz along

the axial direction, the corresponding interferogram of the target frame $\widetilde{I}_T$ can be written as,

826
$$\widetilde{I}_T(x, k; z_0) = S(k) \cdot \sum_j \frac{w_0^2}{w^2(z_j + \Delta z; z_0)} r_j \exp\left[-2\frac{(x-x_j)^2}{w^2(z_j + \Delta z; z_0)}\right]$$

827
$$\cdot \exp\left[i2k(z_j + \Delta z) + i\frac{kx_j^2}{R(z_j + \Delta z; z_0)} - i2\psi(z_j + \Delta z; z_0)\right],$$ (A20)

829 If we conduct the same axial motion correction by multiplying an exponential term $\exp(-i2k\Delta z)$

830 as in Eq. (10), the corrected spectral interferogram $\widetilde{I_C}$ is given by,

831
$$\widetilde{I_C}(x, k; z_0) = S(k) \cdot \sum_j \frac{w_0^2}{w^2(z_j + \Delta z; z_0)} r_j \exp\left[-2\frac{(x - x_j)^2}{w^2(z_j + \Delta z; z_0)}\right]$$

832
$$\cdot \exp\left[i2kz_j + i\frac{kx_j^2}{R(z_j + \Delta z; z_0)} - i2\psi(z_j + \Delta z; z_0)\right],$$ (A21)

834 According to Eqs. (A17)-(A19), we have $w(z_j + \Delta z; z_0) = w(z_j; z_0 - \Delta z)$, $R(z_j + \Delta z; z_0) =$

835 $R(z_j; z_0 - \Delta z)$ and $\psi(z_j + \Delta z; z_0) = \psi(z_j; z_0 - \Delta z)$. By substituting these equations into Eq.

836 (A21), it can be rewritten as,

837
$$\widetilde{I_C}(x, k; z_0) = S(k) \cdot \sum_j \frac{w_0^2}{w^2(z_j; z_0 - \Delta z)} r_j \exp\left[-2\frac{(x - x_j)^2}{w^2(z_j; z_0 - \Delta z)}\right]$$

838
$$\cdot \exp\left[i2kz_j + i\frac{kx_j^2}{R(z_j; z_0 - \Delta z)} - i2\psi(z_j; z_0 - \Delta z)\right],$$ (A22)

840 Comparing Eq. (A16) and Eq. (A22), we can conclude that,

841
$$\widetilde{I_C}(x, k; z_0) = \widetilde{I_R}(x, k; z_0 - \Delta z),$$ (A23)

This equation suggests that the corrected frame is equivalent to fixing the sample and shifting the

focal plane by $-\Delta z$. Given that OCT systems typically employ lenses with a low numerical

aperture [48], the impact of focal plane shifts should be minimal, provided that the sample's bulk

movement Δz is significantly smaller than the Rayleigh range (~200 μm for our rodent retinal

imaging). Nevertheless, when the magnitude of bulk tissue motion approaches the Rayleigh range,

the accuracy of the motion correction can be adversely affected. In such cases, numerical focusing

methods could be implemented to mitigate additional impacts caused by the depth-dependent PSF

[53]. Future studies may explore experimental validation of this theoretical analysis.

References

[1] R. Leitgeb, C. Hitzenberger, and A. Fercher. (2003, Apr.). Performance of fourier domain vs.
time domain optical coherence tomography. *Opt. Express.* 11(8), pp. 889-894.

[2] M. A. Choma, A. K. Ellerbee, C. Yang, T. L. Creazzo, and J. A. Izatt. (2005, May). Spectral-
domain phase microscopy. *Optics Letters.* 30(10), pp. 1162-1164.

[3] B. Braaf, K. A. Vermeer, K. V. Vienola, and J. F. de Boer. (2012, Aug.). Angiography of the
retina and the choroid with phase-resolved OCT using interval-optimized backstitched B-
scans. *Opt. Express.* 20(18), pp. 20516-20534.

[4] B. F. Kennedy, S. H. Koh, R. A. McLaughlin, K. M. Kennedy, P. R. T. Munro, and D. D.
Sampson. (2012, Aug.). Strain estimation in phase-sensitive optical coherence
elastography. *Biomedical Optics Express.* 3(8), pp. 1865-1879.

[5] B. F. Kennedy, F. G. Malheiro, L. Chin, and D. Sampson. (2014). Three-dimensional optical
coherence elastography by phase-sensitive comparison of C-scans. *J. Biomed. Opt.* 19(7),
p. 076006.

[6] V. J. Srinivasan *et al.* (2010, Feb.). Quantitative cerebral blood flow with Optical Coherence
Tomography. *Opt. Express.* 18(3), pp. 2477-2494.

[7] K. V. Larin and D. D. Sampson. (2017, Feb.). Optical coherence elastography - OCT at work
in tissue biomechanics [Invited]. *Biomedical Optics Express.* 8(2), pp. 1172-1202.

[8] D. Hillmann, H. Spahr, C. Pfaffle, H. Sudkamp, G. Franke, and G. Huttmann. (2016, Nov.). In
vivo optical imaging of physiological responses to photostimulation in human
photoreceptors. *Proc. Natl. Acad. Sci. U. S. A.* 113(46), pp. 13138-13143.

[9] F. Zhang, K. Kurokawa, A. Lassoued, J. A. Crowell, and D. T. Miller. (2019, Apr.). Cone
photoreceptor classification in the living human eye from photostimulation-induced phase
dynamics. *Proc. Natl. Acad. Sci. U. S. A.* 116(16), pp. 7951-7956.

[10] M. Azimipour, J. V. Migacz, R. J. Zawadzki, J. S. Werner, and R. S. Jonnal. (2019, Mar.).
Functional retinal imaging using adaptive optics swept-source OCT at 1.6 MHz. *Optica.*
6(3), pp. 300-303.

[11] V. P. Pandiyan *et al.* (2020). The optoretinogram reveals the primary steps of
phototransduction in the living human eye. *Science Advances.* 6(37), p. eabc1124.

[12] H. H. Müller *et al.* (2012, May). Imaging thermal expansion and retinal tissue changes during photocoagulation by high speed OCT. *Biomedical Optics Express.* 3(5), pp. 1025-1046.

[13] G. Goetz *et al.* (2018). Interferometric mapping of material properties using thermal perturbation. *Proceedings of the National Academy of Sciences.* 115(11), pp. E2499-E2508.

[14] B. Hyle Park *et al.* (2005, May). Real-time fiber-based multi-functional spectral-domain optical coherence tomography at 1.3 μm. *Opt. Express.* 13(11), pp. 3931-3944.

[15] B. J. Vakoc, G. J. Tearney, and B. E. Bouma. (2009, Jun.). Statistical properties of phase-decorrelation in phase-resolved Doppler optical coherence tomography. *IEEE Trans. Med. Imaging.* 28(6), pp. 814-21.

[16] V. Y. Zaitsev *et al.* (2016). Hybrid method of strain estimation in optical coherence elastography using combined sub-wavelength phase measurements and supra-pixel displacement tracking. *Journal of Biophotonics.* 9(5), pp. 499-509.

[17] R. S. Jonnal, O. P. Kocaoglu, Q. Wang, S. Lee, and D. T. Miller. (2012, Jan.). Phase-sensitive imaging of the outer retina using optical coherence tomography and adaptive optics. *Biomedical Optics Express.* 3(1), pp. 104-124.

[18] J. A. Izatt, M. A. Choma, and A.-H. Dhalla, "Theory of Optical Coherence Tomography," in *Optical Coherence Tomography: Technology and Applications*, W. Drexler and J. G. Fujimoto Eds. Cham: Springer International Publishing, 2015, pp. 65-94.

[19] K. Kurokawa, S. Makita, Y.-J. Hong, and Y. Yasuno. (2015, Jan.). Two-dimensional micro-displacement measurement for laser coagulation using optical coherence tomography. *Biomedical Optics Express.* 6(1), pp. 170-190.

[20] M. S. Hepburn, K. Y. Foo, P. Wijesinghe, P. R. T. Munro, L. Chin, and B. F. Kennedy. (2021, May). Speckle-dependent accuracy in phase-sensitive optical coherence tomography. *Opt. Express.* 29(11), pp. 16950-16968.

[21] R. K. Wang and Z. Ma. (2006, Oct.). Real-time flow imaging by removing texture pattern artifacts in spectral-domain optical Doppler tomography. *Optics Letters.* 31(20), pp. 3001-3003.

[22] J. Y. Fan, Y. He, P. H. Wang, G. X. Liu, and G. H. Shi. (2020, Jul.). Interplane bulk motion analysis and removal based on normalized cross-correlation in optical coherence tomography angiography. *Journal of Biophotonics.* 13(7),

[23] M. Guizar-Sicairos, S. T. Thurman, and J. R. Fienup. (2008). Efficient subpixel image registration algorithms. *Optics letters.* 33(2), pp. 156-158.

[24] X. Tong *et al.* (2019). Image Registration With Fourier-Based Image Correlation: A Comprehensive Review of Developments and Applications. *IEEE Journal of Selected Topics in Applied Earth Observations and Remote Sensing.* 12(10), pp. 4062-4081.

[25] N. H. Do, "Parallel processing for adaptive optics optical coherence tomography (AO-OCT) image registration using GPU," 2016.

[26] Z. Li, V. P. Pandiyan, A. Maloney-Bertelli, X. Jiang, X. Li, and R. Sabesan. (2020, Dec.). Correcting intra-volume distortion for AO-OCT using 3D correlation based registration. *Opt. Express.* 28(25), pp. 38390-38409.

[27] L. Guo *et al.* (2016). Improved motion contrast and processing efficiency in OCT angiography using complex-correlation algorithm. *Journal of Optics.* 18(2), p. 025301.

[28] J. Lee, V. Srinivasan, H. Radhakrishnan, and D. A. Boas. (2011). Motion correction for phase-resolved dynamic optical coherence tomography imaging of rodent cerebral cortex. *Opt. Express.* 19(22), pp. 21258-21270.

[29] H. Li *et al.*, *Subpixel motion correction for phase-sensitive optical coherence tomography* (SPIE BiOS). SPIE, 2023.

[30] T. Ling *et al.*, *Phase-restoring subpixel image registration and automated signal extraction for optoretinography using phase-sensitive OCTs* (SPIE BiOS). SPIE, 2023.

[31] S. Y. Ksenofontov, P. A. Shilyagin, D. A. Terpelov, V. M. Gelikonov, and G. V. Gelikonov. (2020). Numerical method for axial motion artifact correction in retinal spectral-domain optical coherence tomography. *Frontiers of Optoelectronics.* 13(4), pp. 393-401.

[32] D. Hillmann *et al.* (2012). Common approach for compensation of axial motion artifacts in swept-source OCT and dispersion in Fourier-domain OCT. *Opt. Express.* 20(6), pp. 6761-6776.

[33] N. D. Shemonski, S. G. Adie, Y.-Z. Liu, F. A. South, P. S. Carney, and S. A. Boppart. (2014). Stability in computed optical interferometric tomography (Part I): Stability requirements. *Opt. Express.* 22(16), pp. 19183-19197.

[34] P. L. Reu. (2011). Experimental and numerical methods for exact subpixel shifting. *Experimental mechanics.* 51(4), pp. 443-452.

[35] B. Tan, Z. Hosseinaee, L. Han, O. Kralj, L. Sorbara, and K. Bizheva. (2018, Dec.). 250 kHz,
1.5 μm resolution SD-OCT for in-vivo cellular imaging of the human cornea. *Biomedical*
Optics Express. 9(12), pp. 6569-6583.

[36] A. Hughes. (1979). A schematic eye for the rat. *Vision Res.* 19(5), pp. 569-588.

[37] S. J. Chiu, X. T. Li, P. Nicholas, C. A. Toth, J. A. Izatt, and S. Farsiu. (2010, Aug.). Automatic
segmentation of seven retinal layers in SDOCT images congruent with expert manual
segmentation. *Opt. Express.* 18(18), pp. 19413-19428.

[38] M. Zhang *et al.* (2016, Mar 1). Projection-resolved optical coherence tomographic
angiography. *Biomed Opt Express.* 7(3), pp. 816-28.

[39] Y. Zhang *et al.* (2021, Mar.). Automatic 3D adaptive vessel segmentation based on linear
relationship between intensity and complex-decorrelation in optical coherence tomography
angiography. *Quantitative Imaging in Medicine and Surgery.* 11(3), pp. 895-906.

[40] V. P. Pandiyan, X. Jiang, A. Maloney-Bertelli, J. A. Kuchenbecker, U. Sharma, and R.
Sabesan. (2020). High-speed adaptive optics line-scan OCT for cellular-resolution
optoretinography. *Biomedical Optics Express.* 11(9), pp. 5274-5296.

[41] V. P. Pandiyan, X. Jiang, J. A. Kuchenbecker, and R. Sabesan. (2021, Sep.). Reflective mirror-
based line-scan adaptive optics OCT for imaging retinal structure and function. *Biomedical*
Optics Express. 12(9), pp. 5865-5880.

[42] V. Y. Zaitsev, L. Matveev, A. Matveyev, G. Gelikonov, and V. Gelikonov. (2014). A model
for simulating speckle-pattern evolution based on close to reality procedures used in
spectral-domain OCT. *Laser Physics Letters.* 11(10), p. 105601.

[43] J. Sprenger *et al.*, *In-vivo markerless motion detection from volumetric optical coherence*
tomography data using CNNs (SPIE Medical Imaging). SPIE, 2021.

[44] K. Ntatsis *et al.*, *Motion correction in retinal optical coherence tomography imaging using*
deep learning registration (SPIE Medical Imaging). SPIE, 2022.

[45] K. Kurokawa, J. A. Crowell, N. Do, J. J. Lee, and D. T. Miller. (2021, Jan). Multi-reference
global registration of individual A-lines in adaptive optics optical coherence tomography
retinal images (vol 26, 016001, 2021). *J. Biomed. Opt.* 26(1),

[46] T. Tse *et al.* (2024). Generalized 3D registration algorithm for enhancing retinal optical
coherence tomography images. *J. Biomed. Opt.* 29(6), p. 066002.

[47] Y. Cheng, Z. Chu, and R. K. Wang. (2021, Mar). Robust three-dimensional registration on
973    optical coherence tomography angiography for speckle reduction and visualization.
974    *Quantitative Imaging in Medicine and Surgery.* 11(3), pp. 879-894.

975 [48] T. S. Ralston, D. L. Marks, F. Kamalabadi, and S. A. Boppart. (2005). Deconvolution methods
976    for mitigation of transverse blurring in optical coherence tomography. *IEEE Transactions*
977    *on Image Processing.* 14(9), pp. 1254-1264.

978 [49] J. Xu, S. Song, Y. Li, and R. K. Wang. (2017, Dec.). Complex-based OCT angiography
979    algorithm recovers microvascular information better than amplitude- or phase-based
980    algorithms in phase-stable systems. *Phys. Med. Biol.* 63(1), p. 015023.

981 [50] Y.-Z. Liu, F. A. South, Y. Xu, P. S. Carney, and S. A. Boppart. (2017, Mar.). Computational
982    optical coherence tomography [Invited]. *Biomedical Optics Express.* 8(3), pp. 1549-1574.

983 [51] J. Laurikkala, M. Juhola, E. Kentala, N. Lavrac, S. Miksch, and B. Kavsek, "Informal
984    identification of outliers in medical data," in *Fifth international workshop on intelligent*
985    *data analysis in medicine and pharmacology*, 2000, vol. 1, pp. 20-24.

986 [52] K. Tomita *et al.* (2023). Theoretical model for en face optical coherence tomography imaging
987    and its application to volumetric differential contrast imaging. *Biomedical Optics Express.*
988    14(7), pp. 3100-3124.

989 [53] A. Kumar, W. Drexler, and R. A. Leitgeb. (2014). Numerical focusing methods for full field
990    OCT: a comparison based on a common signal model. *Opt. Express.* 22(13), pp. 16061-
991    16078.

992