Microchip-based electrokinetic biosensor: microfabrication and application in membrane protein profiling of extracellular vesicles

Moein Talebian Gevari [1, *], Siddharth Sourabh Sahu [2], Dhrubaditya Mitra [3], Petra Hååg [4], Kristina Viktorsson [4], Shili Zhang [1], Jan Linnros [2], and Apurba Dev [1, 2, *]

[1] Department of Electrical Engineering, The Ångström Laboratory, Uppsala University, 75121 Uppsala, Sweden.

[2] Department of Applied Physics, School of Engineering Sciences, KTH Royal Institute of Technology, 10691 Stockholm, Sweden.

[3] NORDITA, KTH Royal Institute of Technology and Stockholm University, 10691 Stockholm, Sweden.

[4] Department of Oncology-Pathology, Karolinska Institutet, S-171 64, Solna, Sweden.

[*] Corresponding author

E-mail address: apurba.dev@angstrom.uu.se (A. Dev), moein.talebian@angstrom.uu.se (M.T. Gevari).

Abstract

In this study, we demonstrate the fabrication, characterization, and application of a microchip-based electrokinetic biosensor which exploits streaming current for signal transduction. The sensor chips, fabricated using standard silicon fabrication techniques, are based on Si-glass microfluidics offering precision, robustness, and transparency. A custom-built chip-manifold allowing easy interfacing with standard microfluidic connections is also developed which shows leak-free integration of the microchips up to 6 bar of applied pressure. Within this range of pressure, the devices show linear and highly reproducible values for flow rates and streaming current with RMS noise below 20 pA. The microchips designed for multiplexed measurements were tested with the detection of free proteins (streptavidin) and also transmembrane proteins of small extracellular vesicles (sEVs) to demonstrate the capacity of the microchips to detect various types of bio-analytes. The limit of detection (LOD) for streptavidin was estimated to be 0.5 nM while for the transmembrane protein (CD9), the LOD was found to be 1.2×10^6 sEVs/mL. The sensitivity (LOD) of the devices was found to be about 4 times better in targeting CD9 transmembrane protein of H1975 extracellular vesicles when compared to commercial silica capillary which was used previously. The improvement in LOD is attributed to the

higher surface quality of the sensor in terms of the density of surface charges which may be further

exploited for even lower LOD. In addition, optical detection of fluorophore-tagged standard proteins

was done through the optical window of the chip manifold and the transparent glass cap of the

microchip.

Keywords: *Streaming current, microchip biosensor, Extracellular Vesicles, Microfluidics,*

Electrokinetics

1. Introduction

During the past years, the principle of electrokinetic-biosensor exploiting streaming current/potential

method has been applied in the detection of a wide variety of bio-analytes including proteins [1, 2],

ligands [3], DNA [4] and extracellular vesicles [5], thereby demonstrating the excellent potential of the

method as a generic biosensor. The method relies on the electrostatic and hydrodynamic interaction at

the solid-liquid interface inside a microfluidic channel and allows for label-free detection of bio-

analytes. A major benefit of the method stems from its high sensitivity to the surface coverage of an

analyte, which has been previously studied with respect to its influence on the streaming current [6] and

lately, for the determination of concentration of bio-analytes [7]. Besides, the method offers several

practical benefits, such as low sample consumption, simple and inexpensive device architecture, and

possibility to integrate with standard microfluidic technologies for sample sorting, enrichment, and

deliveries. These advantages have obviously attracted further interest in the method aiming for both

improved understanding and exploitation of the governing principles. In particular, we have recently

demonstrated that the surface charge density and the charge contrast between the sensor surface and

analyte play a major role which can be exploited to achieve a far better sensitivity [8, 9]. Further, by

designing appropriate charge-labelled detection probe, we demonstrated the possibility to develop an

immunosandwich assay in electrokinetic sensing, thereby, extending the application of the method in

complex biofluid [8]. A multiplexed detection setup for simultaneous measurement of several bio-

analytes has also been reported [10].

Clearly, the detection principle has matured in its ability to analyze bio-analytes, significantly

improving in both sensitivity and specificity. An improved understanding of how the physical

parameters of an analyte, such as its size and charge, influence the sensor response [11] now provides

us new opportunities to design a more sensitive detector. However, the developments so far have mainly

been shown using commercial silica capillary, which has limited scope to exploit many of the benefits

in practical settings. Instead, an implementation of the detection principle on a microfabricated channels

can help to further leverage some of the key advantages of the method. This includes the design of

shorter and narrower channels to further reduce sample consumption, improving the quality of surface

oxides for better sensitivity and integration of large number of channels for improving the throughput

of multiplexing. In addition, such a microfabricated sensor can open new avenues for research, e.g.,

new material for sensing surface, integration of fluidic actuation, exploring the benefit of nano-

engineered surface and etc.

In this study we, for the first time, report on the fabrication and characterization of a microfabricated

electrokinetic biosensor and a chip manifold for easy integration of the microchips with standard fluidic

connections. The microchannels were fabricated on Si substrate followed by anodic bonding with glass

to achieve high surface quality as well as robust and transparent fluidic channels. The channels were

characterized to have low surface roughness and uniform cross section along the length. The devices

show linear and highly reproducible values for flowrate and streaming current with a standard deviation

below 5 pA, as a function of applied pressure. The microchips designed for multiplexed measurements

were tested with the detection of free proteins (streptavidin) and also transmembrane proteins of small

extracellular vesicles (sEVs) to demonstrate the capacity to detect various types of bio-analytes. The

limit of detection (LOD) for streptavidin was estimated to be 0.5 nM while for the transmembrane

protein (CD9), the LOD was found to be 1.2×10^6 sEVs/mL. The sensitivity (LOD) of the devices were

improved by about 60% in case of streptavidin and 4-fold for CD9 targeted sEVs, when compared to

commercial silica capillary [9]. The improvement in LOD is attributed to a higher density of surface

charges which may be further exploited for even lower LOD. In addition, the chip manifold and the

microchip are equipped with optical window and a transparent glass to utilize optical detection of the

captured targets. The development of highly sensitive and reusable electrokinetic microchip-biosensor

is expected to take the sensing principle one step closer to clinical applications in the near future.

2.   Materials and Methods

2.1. Reagents

For the study we used ultra-pure deionized water (resistivity: 18 MΩ. cm) locally produced. Phosphate

buffered-saline tablets, avidin from egg-white, streptavidin from *Streptomyces avidinii* were purchased

from Sigma Aldrich Sweden AB. For cleaning of the chips, hydrogen peroxide and ammonium

hydroxide were used which were also procured from Sigma Aldrich Sweden AB. The capturing probes

consist of Poly(L-lysine)-graft-biotinylated PEG (PLL-g-PEG-biotin) were purchased from Nanosoft

Polymers. Biotinylated human Anti-CD9 (MEM-61) (catalog no. MA1-19485) antibody and mouse

IgG1 isotype control (catalog no. IC002B) antibodies were purchased from Thermofisher Scientific and

Bio-Techne, UK, respectively.

2.2. sEVs isolation, collection, and characterization

In this study sEVs were isolated from cell culture media of the non small-cell lung cancer (NSCLC)

cell line H1975 (ATCC® CRL-5908™, LGC Standards, Wesel, Germany). The cells were cultured in

RPMI-1640 medium with addition of fetal bovine serum (FBS, 10%) and 2 mM L-glutamine (Gibco,

Life Technologies, Stockholm, Sweden). sEVs were isolated from 50 mL of cell culture media with

two steps of centrifugation to clear out cell debris (200 RCF for 5 min followed by centrifugation of

supernatant at 720 RCF for 10 min, Rotina R38 centrifuge, Hettich). Media was concentrated to about

500 µL using Amicon Ultra-15 Centrifugal Filter Unit with a MWCO of 3 kDa (#UFC900324, Merck

Chemicals and Life Science AB, Solna, Sweden). sEVs were isolated by size-exclusion

chromatography (SEC) on qEVoriginal columns (Izon Science, Oxford, UK) as previously described

[12]. Briefly, the samples were added to the column and were eluted in 500 µL fractions by 0.22 µm

filtered PBS. Fractions 6-10 were pooled and concentrated to about 500 µL using an Amicon® Ultra-4

Centrifugal Filter Unit (#UFC800324, Merck Chemicals and Life Science AB). The particle size and

zeta potential were characterized by nanoparticle tracking analysis (NTA, Zetaview from particle

Metrix). For these analyses the sEVs samples were diluted 1:1000 in filtered PBS. The sample was

injected in 100 μL portions for three times and the cell temperature was maintained at 24°C. The size

analysis was done on eleven positions in the sample cell while for the zeta potential a two-position

measurement was performed.

2.3. Surface functionalization

The exposure of the active surface of the sensor to the air as well as the chemical processes during the

fabrication decrease the quality of the surface oxide. Hence, prior to the antibody/receptor

immobilization, the surface of the microchannels were cleaned using RCA1 (5:1:1 DI-Water:

H_2O_2:NH_4OH) cleaning solution at 88°C for 30 minutes. In this process, atomic layers of silicon dioxide

on top are etched away by the diluted ammonium hydroxide and a fresh layer of silicon dioxide is

created by the hydrogen peroxide solution. Supplementary Information S1 demonstrates the effect of

the cleaning process on the recorded streaming current.

After the RCA1 cleaning process, the surface hydroxyl groups on the microchannel are activated

leading to a larger negative surface charge density. For the antibody/receptor immobilization, we

followed an optimized strategy as reported in our earlier work [8]. In brief, the surface of the

microchannels were first coated with a thin layer of PLL-g-PEG-biotin (PPB) by flowing an aqueous

solution (0.1 mg/mL) of PPB through the microchannels for 30 minutes. For the detection of

streptavidin, PPB layer was directly used where biotin of PPB layer acts as the receptor (Figure 1a).

For the control measurements, the surface of the sensor was covered by high concentration of

streptavidin (500 nM) using PPB. Then different concentrations of streptavidin were injected into the

devices to measure the background signal as the control.

In the case of membrane protein profiling of sEVs, CD9 tetraspanin was targeted. In that case,

biotinylated antibodies for CD9 were conjugated to the PPB coated surface using avidin as a linker

molecule. For the control measurements, mouse IgG1 isotype control antibody was used instead of the

specific capture antibody, i.e. anti-CD9. The concentration of the capture/control antibody was 50

μg/mL in 1xPBS and was immobilized for 1 hour. Prior to the sensing measurements, the microchannels

were treated with pluronic (synperonic) F108 solution for 20 minutes in order to suppress non-specific

binding.

2.4. The measurement setup and the microchip

The experimental setup, shown in Figure 1b, consists of a high-pressure pure nitrogen gas capsule

regulated by an Elveflow OB1 flow controller coupled with a thermal time of flight (TOF) flow sensor

(Elveflow, MSF3) to measure the flowrate during the experiments. The working fluids (either the bio-

sample or the analyte) are hydraulically pushed by the nitrogen gas into the system through PEEK

tubing and microfluidic connections procured from Darwin Microfluidics, France. A continuous train

of trapezoidal pressure pulses between 1.5 and 3 bar, having a pulse duration of 30 s was used in the

method in order to perform a two-points streaming current measurement. The currents were measured

using hollow Platinum tube electrodes placed at the inlet and outlet ports. The resulting streaming

current pulses (ΔI_s) were measured by a Keithley picoammeter (model no. 2636A) while the pressure

pulses (ΔP) were recorded directly by the pressure regulator.

The measured streaming current (I_s) by the electrodes was used to calculate the apparent zeta potential

(ζ^*) of the microchannel surface using Eq. 1 [13].

$$\zeta^* = \frac{\eta}{\varepsilon \varepsilon_0} \frac{\Delta I_s}{\Delta P} \frac{L}{A} \tag{1}$$

where η and $\epsilon \epsilon_0$ refer to the dynamic viscosity and permittivity of the measurement buffer, respectively,

and L and A refer to the length and cross-sectional area of the microchannels, respectively. More details

on the working principle could be found in our previous report [11].

In this study, we performed both real-time and endpoint measurements. The end-point measurements

involved recording the initial baseline (ζ_i^*) and the final baseline after the injection of the sEVs ($\zeta_i^* +$

$\Delta \zeta^*$). The injection of sEVs was done in 1x PBS to maintain the physiological conditions for the sEVs,

whereas both the baselines were measured in 0.1x PBS to reduce the electrostatic screening. A Labview

program recorded the data, and a custom Python script was used to analyze them afterwards. The noise-sensitive components of the experimental setup were placed in a Faraday cage to minimize the exterior perturbation on the measurements. The heart of the assembled system is a custom-built manifold platform to mount the biosensor chip and to ensure a leak-proof interfacing with standard fluidic connectors even at high pressure (up to 6 bar). For this purpose, an octagonal-shaped PEEK block was machined, on the center of which the microchip was placed. Suitable holes are drilled in the block with the same diameter as the inlet/outlet ports on the biosensor. In order to eliminate the leakage from the system, silicone rubber o-rings, purchased from Apple Rubber Inc., the USA, with 1 mm inner diameter were placed between the biosensor and the platform, and finally two plastic plates were used to sandwich the microchip on the platform. An optical window was designed on the plastic holders in order to perform fluorescence microscopy. Figure 1c shows the cross-sectional view of the chip platform along with the microchip. The silicon and glass substrates were purchased from MicroChemicals Company, Germany. Other required material and devices for the microfabrication were provided by Myfab, the Swedish research infrastructure for microtechnology, nanoscience and materials research.

Figure 1 – a) Functionalization technique of the capture probes and the target, b) The schematic of the
experimental setup consisting of the chip holder platform, platinum electrodes, digital ammeter, pressure
regulator, flow sensor, analyte reservoir, and data acquisition system, c) The cross sectional view of the chip
manifold and the microchip

3. Results

The devices are based on silicon-glass microfluidics where the microchannels of rectangular cross
section were etched on Si substrate using reactive ion etching followed by an anodic bonding with thin
quartz glass for sealing the channels. Typical dimensions of the fabricated channels are 10 μm × 25 μm
in cross section and 3 mm in length. A schematic step by step procedures for the microchip processing
and the final product are shown in Figure 2a and b, respectively. For the fabrication, a 100 nm thick
layer of aluminum was sputtered on a 4 inch <100> single-side polished silicon wafer. This was
followed by a coating of 500 nm thick layer of S1813 photoresist by spin coating and a soft baking at

110°C for 2 minutes. The sensor patterns were generated on the surface through the first lithography.

After the development and hard baking of the resist at 120 °C for 10 minutes, the thin aluminum mask

was dry etched so that the sensor pattern appears on the substrate. Thereafter, a 10 μm deep reactive

ion etching of the silicon wafer was performed that forms the general geometry of the sensor (Figure

2a-1). After washing the aluminum mask off the substrate by wet chemistry, a new 300 nm thick

protective aluminum layer was deposited on both sides of the silicon wafer. To create the inlet and

outlet ports, the silicon wafer must be etched through. The bottom aluminum protective layer prevents

helium leakage during the dry etching in the DRIE machine. A second photomask was used to pattern

the inlet and outlet ports on the wafer. Thereafter, a dry etching of the aluminum protective layer (Figure

2a-2) followed by a deep dry etching of the silicon wafer was done (Figure 2a-3). After washing off the

protective layers on the silicon wafer using wet chemistry, the substrate underwent a standard RCA

surface preparation. Finally, a 300 nm thick layer of dry silicon dioxide was thermally grown on the

substrate acting as the active sensing surface.

As the last step of the microfabrication, the substrate underwent a piranha cleaning process prior to the

anodic bonding with a borofloat glass wafer (Figure 2a-4). The final product was diced using a high-

speed rotary saw into 12 mm × 12 mm devices for the experiments. More details of the fabrication

process flow could be found in the supplementary information S2.

Figure 2b shows a fully processed wafer containing 34 chips (left) and also finger-tip size single

microchip (12x12 mm) containing four identical channels with a common inlet (at the center) and

separate outlets. The geometry of the microchip and surface roughness of the fabricated devices were

characterized using white light interferometry (WLI) method. For this purpose, an unbonded device

was cleaned using RCA 1 cleaning solution and the structure was characterized by ZYGO optical

profiler (Nexview NX2). Furthermore, the roughness elements were analyzed individually at different

locations. Figure 2c shows the roughness of the surface. A total number of about 340K data points

were analyzed and the centerline average was 9 nm.

Figure 2 – a) the schematic of the device microfabrication process flow, b) a full wafer prior to bonding and dicing as well as the size scale of the final product, c) Roughness elemental analysis to calculate the mean of the roughness elements

3.1. Electrical and fluidic characterization

To shed light on the noise characteristics of the fabricated biosensor, streaming current was measured by flowing 0.1xPBS through a set of cleaned microchannels at different upstream pressures ranging between 1 and 6 bar. The RMS noise was calculated and is presented in Figure 3a as bar plots for different upstream pressures. Clearly, the RMS noise increases with increasing applied pressure and streaming current. The distribution of noise is shown in the inset of Figure 3a. As seen, the RMS noise remains similar (7 pA with standard deviation below 2 pA, n=3) up to 3 bars of applied pressure but then sharply increases, reaching 21 pA at 6 bars. The noise RMS at 3 bar corresponds to 0.42 mV of zeta potential which we defined as the minimum detectable signal (MDS) for the microchip sensor. Figure 3b shows the volumetric flowrate and streaming current measured in a cleaned microchannel as a function of the applied pressure. As expected, both the current and the flow rate show a linear and highly reproducible dependence on the applied pressure. The linear relation between upstream pressure and the measured flowrate with negligible deviation clearly indicates that both the microchip and the chip manifold are leak-proof within the measured pressure range. A simple Poiseuille estimation of the flowrate is also shown in Figure 3b which demonstrates a negligible deviation of the experimental

flowrate from the theoretical predictions. The error bars correspond to 3 measurements on different

microchips with the same production method.

In order to characterize the flow regime in the microchannel, the Reynolds number was calculated for

different applied upstream pressures ranging from 1 to 6 bar (see section S3). Decreasing the size of the

microchannels and consequently increasing the surface to volume ratio projects the wall effect on the

flow characteristics [14]. A proper model for friction factor calculation could help compare the

experimental data and the theoretical predictions to estimate the wall effects. The pressure drop

estimation is also an important parameter in fluidic characterization of the system. Therefore, different

fluidic components were analyzed, and the estimated pressure drops were calculated (see section S4).

Eventually, a stable and identical flow rate through all the microchannels need to be established as the

devices are design for multiplex sensing. For the purpose of this study, a flow sensor was placed at the

common inlet and the flowrate was measured at 3 bars. Then, channel 1 (C1) was blocked using

microfluidic blockers at the outlet of the chip manifold and the flowrate was measured. The same

process was repeated by blocking other two channels consecutively. Since the channels are expected to

operate in an identical way, a negligible difference in flowrate is required when the sample is injected

through a common inlet. The flowrate measurement data at each microchannel is shown in the section

S5. The standard deviation of the flowrates at different microchannels is 96 nL/min while the average

flowrate is 13 μL/min at 3 bar of upstream pressure. Blocking microchannels and measuring the

flowrate at the others would show a clear picture of the fluidic crosstalk valuable for future multiplex

biosensing. In addition, it is vital to know that a possible blockage in one channel during the experiments

would not lead to the failure and/or deviation of the sensing results in the other microchannels. The

standard deviation of the flowrate at different microchannels demonstrate a negligible fluidic crosstalk

and effect of the blockage in other channels.

Figure 3 – a) Root mean square of the noise at different upstream pressures along with the noise distribution, b)

linear relation between the flowrate and streaming current versus the upstream pressure

3.2. Sensing performance

The sensing performances of the devices were first investigated using a well-studied protein-ligand pair,

i.e. biotin-streptavidin. Figure 4a shows a set of real-time measurements for two concentrations of

streptavidin injected to PPB coated microchannels. For the detection measurement, the zeta potential

of the PPB coated surface was first measured (baseline) by injecting 0.1x PBS, until a stable baseline

was obtained. Thereafter, streptavidin dissolved in 0.1x PBS was injected and the real-time data was

recorded for 1 hour of injection. The results are shown in Figure 4a. As can be seen, the microchip

surface reaches an equilibrium in less than 20 minutes for higher concentrations while it takes over 40

minutes at a lower concentration. In order to compare the results with previously used commercial

microcapillary-based sensor, a set of end-point streptavidin measurements under identical conditions

were performed for both microchip and capillary. For this purpose, a 4 cm long capillary tube with an

inner diameter of 25 μm was used. The microcapillaries were cleaned and functionalized using an

identical procedure as described earlier. Figure 4b shows a comparison between the signals obtained

with a microchip and a microcapillary based system. The measurements were performed for different

concentrations of streptavidin ranging from 10 pM to 100 nM in order to evaluate the limit of detection

in the two cases. As seen, the signal, measured in terms of apparent zeta potential, proportionally

increases from 1.72 mV to 10.25 mV for the microchip. At all of the concentrations, the microchip-

based sensor demonstrated higher sensitivity with an enhanced signal over the capillary-based sensor.

In addition, comparing the error bars of two systems, microchip-based sensing seems more reproducible

in comparison to capillary-based sensing. To further analyze the data and to demonstrate another

potential advantage of having a transparent window in the channel design, the fluorescence signal

arising from the Atto 565 conjugated streptavidin binding to the channels were also recorded. The

images are shown in Figure 4c. As can be seen, the fluorescence intensity scales with the concentrations

as expected. In addition, the control channel shows no/negligible fluorescence signal indicating a good

specificity of the detection. For comparison of the detection sensitivity between the microchip and

capillary-based sensing, we estimated the limit of detection (LOD) by a linear fit of the concentration

vs signal (calibration) curve thus obtained (Figure 4b and supplementary information S6). The LOD

was determined as the concentration of the target corresponding to the MDS of the sensor. The MDS

of the microcapillary and microchips are 0.2 mV and 0.4 mV, respectively. The MDS of the microchip

is slightly higher as compared to microcapillary. This observation is because of having four

interconnected microchannels in microchips while for the microcapillary, a two-microchannel

configuration was used. This observation is inline with the previous work of our group [10]. The LOD

estimated for the microchip and microcapillary based systems was 0.5 nM and 0.8 nM, respectively.

The indicated data points at the lowest concentration were out of the dynamic range of the sensor that

are not considered for LOD calculation.

Beyond protein detection, streaming current-based sensor has also been investigated for the detection

and surface protein profiling of sEVs [5, 10], an emerging bio-analyte which is attracting a significantly

growing interest both for diagnostics and therapeutics [15]. A major advantage of streaming-current

based sensor for sEVs detection arises from its size-dependent sensitivity, as demonstrated in our

previous reports [11]. sEVs (diameter: 50-150 nm) being much larger than proteins can be detected

with a fM range detection sensitivity using the streaming current-based technique [9]. In order to

investigate the performance of the current microchip-based platform, we analyzed the detection

sensitivity of sEVs derived from H1975 lung cancer cell line. The sEVs were first characterized using

a nanoparticle tracking analyzer (NTA, Zetaview from particle Matrix) for their size and zeta potential measurement as presented in Figure 4d, e. The mean diameter of the sEVs as well as their zeta potential were measured to be 132 nm and -25.83 mV, respectively. The narrow distribution of the sEVs zeta potential demonstrates the consistent signal after the detection of the sEVs across the experiments. The sEVs were then detected by targeting their CD9 transmembrane protein using the microchip. Figure 4f shows the barplots representing the signal as a function of different concentration of sEVs. A calibration plot along with the MDS is shown in the supplementary information (S7). The LOD obtained in this case was 1.2×10^6 particles/mL, which is about 4 times lower than the results previously obtained with the capillary based system [9]. Clearly, both for streptavidin and sEVs detection, the microchip-based platform significantly outperforms the previously reported capillary-based system.

Figure 4 – a) Real time sensing of streptavidin using PPB as the capture probe in microchip with respect to time, b) Limit of detection comparison between microcapillary and microchip devices for end point streptavidin detection at different concentrations (controls were subtracted), c) Optical detection of fluorophore-tagged streptavidin captured by PPB in the microchip through the optical window, d) size distribution of the sEVs, e)

zeta potential distribution of sEVs, f) Limit of detection for CD9 biomarker of H1975 derived sEVs at different

concentrations

4. Discussion

The main contribution of the present study is the development of a microchip technology for the streaming current-based detection of biological analytes. While the detection method has been widely studied [2, 5, 9] and innovated during the past years, most of the research has been focused on the fundamental principle and exploitation/optimization of the method aiming to achieve a better sensitivity and specificity [9]. These studies have been done mainly using PDMS microchannel and/or commercial silica microcapillaries. Nevertheless, these research efforts have considerably contributed in the improvement of the method, thereby, extending the applicability of the method for the analysis of various biological targets, e.g., proteins [2], DNA [16] and sEVs [5], as well as exploring different diagnostic opportunities, e.g., the monitoring the efficacy of precision cancer medicine [10], albeit in a laboratory setting. Translation of these technical developments for potential use in clinical setting is an obvious next step which is the primary objective of the research presented here. In this context, the development of a robust and easy-to-use setup is a key requirement along with the development of a microchip that can be mass fabricated. Going further, the entire platform has been characterized for electrical noise, fluidic and electrokinetic characteristics as well as sensitivity towards some common biological targets. In addition, by comparing with a previously used commercial silica capillary, a clear improvement in detection sensitivity has been demonstrated. Some of these aspects are further discussed in the following section. To the best of our knowledge, such a platform has not been reported until now and thereby constitutes the main novelty of the current work.

The microchip and the detection platform: The fabricated microchips clearly show high reliability in the entire pressure range. This is evident from both the flow rate analysis of different chips and micro-channels (Fig 3b and S6) and the streaming current measurement as a function of the applied pressure (Fig 3b). The measurement of streaming current as a function of pressure shows a highly linear behavior with a standard deviation $\sim \pm 90$ pA in the entire pressure range. Fig. 3b also indicates leak-free integration of the chip with the manifold allowing easy interfacing with the commercial microfluidic

connectors. The choice of Si-glass microfluidics offers several other benefits, particularly in the context

of streaming current based bio-detection. As reported earlier [9, 17], surface roughness can negatively

impact the sensitivity of detection. With the optimization of the Si fabrication process, the roughness

can be easily controlled. As shown, in Fig. 2c, the roughness of the fabricated channels stands at a mean

value of 9 nm which is comparable to many antibodies. Secondly, the geometry can be precisely

controlled with nanoscale precision and the anodically-bonded devices offers unparallel chemical

compatibility and bonding strength [18]. Finally, SiO_2 surface has been widely studied for the

immobilization of biological recognition molecules [19, 20] and there are well established protocols

which allows highly reproducible surface functionalization.

Electrical and fluidic characteristics: There is a variety of sources introducing noise in the recorded

data such as flow disturbance, electrical measurement system, ambient noise, microscopic fluctuations

and impurities, and intrinsic sources. The conductive components of the experimental setup are

accommodated inside a Faraday cage and the interior walls of the cage are covered by insulating tapes

to avoid short circuit and electromagnetic noise. The RMS of the noise at different upstream pressures

recommends low applied pressure for the measurements (between 1 and 3 bar). On the other hand, the

two-point streaming current measurement requires two upstream pressures to form the desired

waveform. For the upper value of the pressure 3 bar was nominated. However, for the lower value, 1.5

bar was chosen instead of 1 bar to ensure higher data sampling rate. Therefore, the RMS noise stays

roughly the same for the range of the experiments. In addition, the low absolute value of streaming

current leads to a negligible polarization of the electrodes as demonstrated above by the linear relation

between the upstream pressure and the streaming current in the working range of the device.

The fluidic analysis on the other hand shows that the friction factor inside the microchip agrees with

the analytical predictions. The pressure drop in the fluidic path due to multiple bends in the microchip

manifold, different microfluidic connectors, inlet effects, and the electrovisous effect are studied for the

current system (supplementary information S4) [11, 12].

Sensing performance: The sensitivity of the fabricated devices has been evaluated by detecting

streptavidin at two and five concentrations for real-time and endpoint measurements, respectively. The

results presented in Figure 4a and b, show that the microchip biosensor is suitable for both real-time

and endpoint measurements in a broad range (10 pM to 100 nM). The LOD of the developed technique

in this study was compared with the commercial silica microcapillaries to show the improvement over

our previous data [9]. The calibration curves for both systems show 60% improvement in the limit of

detection for the microchip biosensor. In addition, the measurement uncertainty (standard deviation,

n=3) for the microchip biosensors are significantly lower as compared to that of the capillary biosensors.

On the other hand, the transparent microchips along with the chip manifold facilitates the optical

analysis of the target. The optical window on the chip manifold and its appropriate design for the optical

microscope sample holder makes it possible to optically analyze the targets in the microchannel. The

sensing performance of the platform was also evaluated with the profiling of sEV membrane proteins.

As mentioned earlier, an improvement in the detection sensitivity by a factor of 4 was also observed,

when compared to commercial microcapillary. The improvement can be attributed to a better surface

quality of the thermally grown SiO_2 surface. As demonstrated in our previous report, surface charge

density and electrostatic charge contrast play a critical role in determining the detection sensitivity. In

order to compare the surface charge densities, we cleaned a microchip and a capillary sensor using the

protocol explained earlier. Then measured the baseline. Thereafter, the same process was repeated after

PPB and CD9 antibody functionalization.

Better surface coverage by the PPB layer would make a more positive surface that can attract more

negatively charged targets (streptavidin or sEVs). Therefore, on one hand having a negatively charged

surface at the pH of the buffer used for the experiments could enhance the surface coverage by the PPB

layer and on the other hand, a too negative surface could repel the negatively charged biomolecules

such as the sEVs. To demonstrate the mentioned tradeoff, the surface charge density of the microchip

is calculated and compared with the microcapillaries here.

The 1-dimentional solution of the Poisson-Boltzmann equation that governs the length of the EDL on

a charged surface, shows the relation between surface electrostatic potential and the surface charge

density. The effective surface charge density, on the other hand, could be calculated from the zeta

potential of the surface (Eq. (2)) [23].

$$\sigma_{eff} = \sqrt{8cN\varepsilon_r\varepsilon_0 k_B T}\sinh\left(\frac{e\zeta}{2k_B T}\right) \tag{2}$$

A better surface quality attracts more capture probes on the surface and makes a more positively charged

surface that can act in favor of attracting more negatively charged targets i.e., streptavidin and sEVs.

The effective surface charge density of the bare capillary and the microchip are -5.3×10^{-3} and -5.6×10^{-3}

e/nm^2, respectively, showing higher density of the charges on the bare surface of the microchip as

compared to the capillary. After PPB functionalization, the effective charge density is -0.08×10^{-3} e/nm^2

for the microchip while it is -0.35×10^{-3} e/nm^2 for the capillary sensors. for the capillary sensors. These

numbers after the immobilization of CD9 antibody are -0.45×10^{-3} e/nm^2 and -0.9×10^{-3} e/nm^2 [9] for

microchip and capillary, respectively. This indicates a higher surface adsorption of the positively

charged PPB in case of the microchip, making the overall surface charge density less negative. This

better facilitates the sensing of the negatively charged sEVs and could explain the lower limit of

detection discussed before. The limit of detection for streptavidin and sEVs by CD9 surface protein

were 60% and 4 time better than that of the microcapillaries when compared under identical conditions,

respectively. Finally, the devices were cleaned using the RCA1 cleaning protocol. The results

(supporting information S8) show that the baseline could be recovered up to five times after the

experiments promising a sustainable detection platform.

5. Conclusion

In this study, a microfluidic device was fabricated out of silicon and was covered by a thin layer of

silicon dioxide as the active surface of the biosensor. The hydroxyl groups on the surface carrying

negative charge were activated by wet chemistry to attract Ploy-L-Lysine molecules conjugated with

PEG and biotin on the surface acting as the capture probes for the biosensing. A robust experimental

setup was designed and assembled to facilitate electrical measurements as well as a leak-proof fluidic

path for the experiments. The zeta potential of the microchannel inner surface was calculated using

streaming current measurements during the experiments. The zeta potential of the surface before and

after capturing a specific target is the sensing signal in this study. The measured noise of the fabricated

biosensor was characterized by calculating root mean square at different upstream pressures from 1 to

6 bar. Upstream pressures of 1.5 and 3 bar were chosen as the working condition for the experiments.

The linear relation between the upstream pressure and the measured streaming current/flowrate was

controlled as well as the fluidic crosstalk between the microchannels. Thereafter, the performance of

the microchip-based biosensor was compared with commercial microcapillary tubes. The sensitivity of

the microchip device was one order of magnitude higher, and they showed reusability after the

experiments. Finally, CD9 surface biomarker of the extracellular vesicles from H1975 cell line were

captured specifically by the capture probes immobilized on the surface. The calibration curves show a

1.2×10^6 particle/mL detection limit for the microchip biosensor.

In conclusion, we could demonstrate the successful replacement of microcapillary tubes with

microchip-based biosensors working with streaming current measurement. The results showed a faster,

more sensitive, more robust, and reusable substitution to the commercial microcapillary tubes for

biosensing applications.

Conflict of interest

The authors declare no conflict of interest.

Acknowledgement

This study was supported by grants from the Swedish Research Council (grant no. 2016-05051), the

Erling Persson Family Foundation, Stockholm Cancer Society (#171123, #191293, and #201202), the

Swedish Cancer Society (CAN 2015/401; CAN 2018/597), Stockholm County Council (#20160287

and #20180404), and funds of Karolinska University Hospital FOUU (#75032). Dr. Örjan Vallin and

Dr. Milena De Albuquerque Moreira are acknowledged for their input in the microfabrication steps.

References

[1]   C. Glad, K. Sjödin, and B. Mattiasson, "Streaming potential—a general affinity sensor," *Biosensors*,

vol. 2, no. 2, pp. 89–100, 1986.

[2]   A. Dev *et al.*, "Electrokinetic effect for molecular recognition: A label-free approach for real-time

biosensing," *Biosens. Bioelectron.*, vol. 82, pp. 55–63, 2016.

[3]   J. O. Lee, N. Choi, J.-W. Lee, S. Song, and Y.-P. Kim, "Rapid electrokinetic detection of low-

molecular-weight thiols by redox regulatory protein-DNA interaction in microfluidics," *Sensors Actuators B Chem.*, vol. 336, p. 129735, 2021.

[4] Y. Li, S. N. Lai, and B. Zheng, "A microfluidic streaming potential analyzer for label-free DNA detection," *Sensors Actuators B Chem.*, vol. 259, pp. 871–877, 2018.

[5] S. Cavallaro *et al.*, "Label-free surface protein profiling of extracellular vesicles by an electrokinetic sensor," *ACS sensors*, vol. 4, no. 5, pp. 1399–1408, 2019.

[6] D. Lupa, M. Oćwieja, N. Piergies, A. Baliś, C. Paluszkiewicz, and Z. Adamczyk, "Gold nanoparticles deposited on silica microparticles-Electrokinetic characteristics and application in SERS," *Colloid Interface Sci. Commun.*, vol. 33, p. 100219, 2019.

[7] H. Qi *et al.*, "Rapid detection of trace Cu2+ using an l-cysteine based interdigitated electrode sensor integrated with AC electrokinetic enrichment," *Electrophoresis*, vol. 40, no. 20, pp. 2699–2705, 2019.

[8] S. S. Sahu *et al.*, "Electrokinetic sandwich assay and DNA mediated charge amplification for enhanced sensitivity and specificity," *Biosens. Bioelectron.*, vol. 176, p. 112917, 2021.

[9] S. S. Sahu *et al.*, "Exploiting Electrostatic Interaction for Highly Sensitive Detection of Tumor-Derived Extracellular Vesicles by an Electrokinetic Sensor," *ACS Appl. Mater. Interfaces*, 2021.

[10] S. Cavallaro *et al.*, "Multiplexed electrokinetic sensor for detection and therapy monitoring of extracellular vesicles from liquid biopsies of non-small-cell lung cancer patients," *Biosens. Bioelectron.*, vol. 193, 2021, doi: 10.1016/j.bios.2021.113568.

[11] S. S. Sahu, C. Stiller, S. Cavallaro, A. E. Karlström, J. Linnros, and A. Dev, "Influence of molecular size and zeta potential in electrokinetic biosensing," *Biosens. Bioelectron.*, vol. 152, p. 112005, 2020.

[12] C. Stiller *et al.*, "Detection of tumor-associated membrane receptors on extracellular vesicles from non-small cell lung cancer patients via immuno-PCR," *Cancers (Basel).*, vol. 13, no. 4, p. 922, 2021.

[13] R. J. Hunter, *Zeta potential in colloid science: principles and applications*, vol. 2. Academic press, 2013.

[14] M. Bahrami, M. M. Yovanovich, and J. R. Culham, "Pressure drop of fully developed, laminar flow in rough microtubes," 2006.

[15] N. A. Hanjani *et al.*, "Emerging role of exosomes as biomarkers in cancer treatment and diagnosis," *Crit. Rev. Oncol. Hematol.*, vol. 169, p. 103565, 2022.

[16] D. C. Martins, V. Chu, D. M. F. Prazeres, and J. P. Conde, "Electrical detection of DNA immobilization and hybridization by streaming current measurements in microchannels," *Appl. Phys. Lett.*, vol. 99, no.

18, p. 183702, 2011.

[17]   Z. Adamczyk, K. Sadlej, E. Wajnryb, M. Nattich, M. L. Ekiel-Jeżewska, and J. Bławzdziewicz,

"Streaming potential studies of colloid, polyelectrolyte and protein deposition," *Adv. Colloid Interface*

Sci., vol. 153, no. 1–2, pp. 1–29, 2010.

[18]   Z. Qi *et al.*, "Disposable silicon-glass microfluidic devices: precise, robust and cheap," *Lab Chip*, vol.

18, no. 24, pp. 3872–3880, 2018.

[19]   F. Nessark *et al.*, "Capacitance Polypyrrole-based Impedimetric Immunosensor for Interleukin-10

Cytokine Detection," *Electroanalysis*, vol. 32, no. 8, pp. 1795–1806, 2020.

[20]   L. Jorde, Z. Li, A. Pöppelwerth, J. Piehler, C. You, and C. Meyer, "Biofunctionalization of carbon

nanotubes for reversible site-specific protein immobilization," *J. Appl. Phys.*, vol. 129, no. 9, p. 94302,

2021.

[21]   M. Akbari, D. Sinton, and M. Bahrami, "Pressure drop in rectangular microchannels as compared with

theory based on arbitrary cross section," *J. Fluids Eng.*, vol. 131, no. 4, 2009.

[22]   M. Bahrami, M. M. Yovanovich, and J. R. Culham, "Pressure drop of fully-developed, laminar flow in

microchannels of arbitrary cross-section," in *International Conference on Nanochannels,*

Microchannels, and Minichannels, 2005, vol. 41855, pp. 269–280.

[23]   Z. Ge and Y. Wang, "Estimation of nanodiamond surface charge density from zeta potential and

molecular dynamics simulations," *J. Phys. Chem. B*, vol. 121, no. 15, pp. 3394–3402, 2017.