Large-scale electrophysiology and deep learning reveal distorted neural signal dynamics after hearing loss

Shievanie Sabesan[1], Andreas Fragner[2], Nicholas A. Lesica[1,*]

[1] Ear Institute, University College London, UK

[2] Perceptual Technologies, London, UK

[*] Corresponding author: n.lesica@ucl.ac.uk

Listeners with hearing loss often struggle to understand speech in noise, even with a hearing aid. To better understand the auditory processing deficits that underlie this problem, we made large-scale brain recordings from gerbils, a common animal model for human hearing, while presenting a large database of speech and noise sounds. We first used manifold learning to identify the neural subspace in which speech is encoded and found that it is low-dimensional and that the dynamics within it are profoundly distorted by hearing loss. We then trained a deep neural network (DNN) to replicate the neural coding of speech with and without hearing loss and analyzed the underlying network dynamics. We found that hearing loss primarily impacts spectral processing, creating nonlinear distortions in cross-frequency interactions that result in a hypersensitivity to background noise that persists even after amplification with a hearing aid. Our results identify a new focus for efforts to design improved hearing aids and establish a new standard for the modeling of central brain structures using DNNs.

Introduction

Hearing loss is a widespread problem with far-reaching consequences ranging from lost productivity and social isolation to decreases in quality of life and mental health[1]. It also imposes a growing societal burden with associated costs approaching $1 trillion annually[2]. Hearing aids are the only widely available treatment for hearing loss but, unfortunately, current devices provide limited benefit in many workplace and social settings[3].

The term "hearing loss" does not capture the full spectrum of the effects of cochlear damage on auditory processing. One common consequence of cochlear damage is a loss of sensitivity that renders low-intensity sounds inaudible. This is the "hearing loss" that is assessed in standard clinical tests and is addressed through amplification with hearing aids. But cochlear damage has other consequences beyond lost sensitivity that cause many people to struggle with high-intensity sounds that are well above their audibility threshold[4]. For example, people with hearing loss often have difficulties understanding speech in noisy settings, even with a hearing aid[5]. The pathophysiology underlying these high-intensity deficits remains poorly understood and, as a result, they are largely ignored by clinicians and hearing aid designers.

The consequences of cochlear damage for the processing of both low- and high-intensity sounds have been well described at the level of the auditory nerve[6]. In addition to the general decrease in neural activity resulting from lost sensitivity, there are also complex changes in the spatiotemporal structure of the neural activity patterns that encode acoustic information, such as lost synchrony capture[7] and distorted tonotopy[8]. Many theories have attempted to explain how the peripheral changes associated with hearing loss might lead to perceptual deficits[9,10]. But, with few explicit studies comparing neural coding in central auditory areas before and after hearing loss, it has been difficult to differentiate between competing theories or to identify which peripheral changes are most important to address.

One recent study of individual neurons in the inferior colliculus (IC) with and without hearing loss and hearing aids found that some properties, such as phoneme selectivity, were impacted while others, such as frequency selectivity and trial-to-trial variability, were not[11]. But, while characterizing the impact of hearing loss on neural coding in individual neurons may be sufficient at the level of the auditory nerve (a set of largely homogeneous fibers driven by a few thousand inner hair cells), neural coding in downstream areas such as the IC, which are much larger and more complex, likely involves emergent network-level properties that are not readily apparent in the activity of individual neurons.

One of the challenges in characterizing neural coding at the network level is the high dimensionality of the activity patterns. If the goal is to gain insight into the underlying computations that the activity reflects, it can be useful to find more compact representations of the full activity that retain its important features. This process, often termed "manifold learning"[12,13], typically utilizes techniques such as principal component analysis (PCA) that identify a projection of the full activity into a lower dimensional space that retains as much of its variance as possible. In this study, we use manifold learning to investigate the impact of hearing loss on the neural coding of speech in gerbils, a common animal model for the study of human hearing. We employ large-scale intracranial recordings that allow us to achieve comprehensive sampling of activity from individual animals at the fine spatial and temporal scales that are critical for encoding speech[14].

We begin with the traditional approach to manifold learning, using PCA to identify and analyze the low-dimensional subspace in which most of the variance in the full network activity patterns resides. We focus on the signal manifold, which captures the features of neural activity that are sound-evoked, first establishing that our recordings are sufficient to identify the signal manifold in individual animals and then that the changes in signal dynamics with hearing loss are fundamental, i.e., that the dynamics within the signal manifold are not simply attenuated by hearing loss, but instead are truly distorted. We then continue our analysis using deep neural networks (DNNs) to perform manifold learning within the framework of a stimulus encoding model, which allows us to investigate the impact of hearing loss on the coding of novel sounds.

We demonstrate that training DNNs on our recordings allows for accurate prediction of neural activity in conjunction with identification of the signal manifold. We use the trained DNNs to probe the processing of basic acoustic features and show that hearing loss predominantly affects spectral, rather than temporal, processing. We then probe the processing of speech and find that this impaired spectral processing creates a hypersensitivity to background noise that persists even with a hearing aid and appears to arise from aberrant cross-frequency interactions. Our results demonstrate the power of DNNs to provide new insights into neural coding at the network level and suggest that new approaches to hearing aid design are required to address the highly nonlinear nature of the effects of hearing loss on spectral processing.

Results

We recorded neural activity from the IC of gerbils using electrode arrays with a total of 512 channels, allowing us to sample widely from neurons that were sensitive to the full range of speech frequencies (Fig. 1a). We recorded activity in response to more than 10 hours of speech in each animal,

Large-scale neural recordings

Signal and noise in neural activity

Figure 1: Neural signal and noise in the gerbil inferior colliculus

(**a**) Schematic diagram showing the geometry of custom-designed electrode arrays for large-scale recordings in relation to the gerbil IC (center), along with the speech syllable 'sa' (left) and the neural activity that it elicited during an example recording (right). Each row in the images of the neural activity shows the average multi-unit activity recorded on one electrode over repeated presentations of the syllable, with the units arranged according to their location within the IC. The activity for three units with different center frequencies (CF; frequency for which sensitivity to pure tones is maximal) are shown in detail. (**b**) Schematic diagram showing the method for separating signal and noise in neural activity. The signal is obtained by averaging responses across repeated presentations of identical sounds. The noise is the residual activity that remains after subtracting the signal from the response to each individual presentation. (**c**) Signal and noise in neural activity. Left: Total, signal, and noise variance in neural activity for units recorded from normal hearing animals (horizontal line indicates median, thick vertical line indicates 25th through 75th percentile, thin vertical line indicates 5th through 95th percentile; n = 2,556). Right: Total, signal, and noise correlation in neural activity for pairs of units recorded from normal hearing animals (n = 544,362).

presenting the entire TIMIT speech database[15] twice – once in quiet and once in background noise,
with the overall intensity, speech-to-noise ratio, and noise type varied from sentence to sentence
(with a small number of sentences repeated multiple times under identical conditions to assess trial-
to-trial variability). We processed the recordings to extract multi-unit activity (MUA) spike counts for
each recording channel, using 1.3 ms time bins to account for the fact that neurons in the IC can
encode information about speech with millisecond temporal precision[14].

The neural signal manifold is low dimensional

We began by analyzing activity from animals with normal hearing. As a first step toward
characterizing the neural code for speech at the network level, we determined whether there was

shared variance across units that would allow us to reduce the dimensionality of the activity patterns.
Previous work has shown that the correlations in IC activity are dominated by "signal" (features of
activity that are reproducible across repeated trials and, thus, convey acoustic information) rather
than "noise" (features of activity that vary from trial-to-trial and reflect intrinsic noise or fluctuations in
brain state) (Fig. 1b)[14].

Signal correlations were also dominant in our recordings: although signal variance (the covariance
in activity across repeated trials) accounted for only 40% of the overall variance in activity, signal
correlations accounted for 95% of the total correlation between units (Fig. 1c). For a network
operating in such a regime, with each neuron having more than half of its variance uncorrelated with
that of its neighbors, there is limited scope for reducing the dimensionality of the full activity patterns.
However, given the large signal correlations, it may be possible to identify a low-dimensional
subspace in which the acoustic information represented by the signal is embedded.

We partitioned the recordings from each animal into two sets: a training set that was used to identify
the principal components (PCs) of the activity (Fig. 2a, step 1) and a test set with two repeated trials
that was used to measure the variance that could be explained by each PC. To measure the total
variance explained (Fig. 2a, steps 2a-c), we projected the activity from test trial 1 onto the PCs, then
reconstructed the original activity from the same trial using the PC projection and compared the
reconstruction to the original activity. The overall dimensionality of the neural activity was high, as
expected, with a large number of PCs required for the reconstruction to explain 95% of the total
variance in the original activity (Fig. 2b).

To measure the signal variance explained (Fig. 2a, step 3), we compared the same reconstructed
activity to the original activity from test trial 2 (when using activity from one trial to reconstruct activity
on another, only those features that reliably encode acoustic information across trials can be
successfully reconstructed and, thus, only signal variance can be explained). The signal variance
explained saturated quickly, indicating that the signal dimensionality was much lower than the overall
dimensionality, with only a small number of PCs required to explain 95% of the signal variance in the
original activity (Fig. 2c).

These results suggest that the acoustic information in IC activity is restricted to a low-dimensional
subspace, which we term the neural *signal manifold*, and that PCA is able to identify the dimensions
that define this manifold. To confirm that PCA preferentially identified the signal manifold, we
computed the fraction of the variance explained by each PC that was signal rather than noise
(measured as the covariance between the activity on the two test trials when projected onto each
PC relative to the overall variance after the same projection) and verified that it decreased with each
successive PC (Fig. 2d).

If the signal manifold reflects something fundamental about auditory processing, then we should
expect the activity within it, which we term the *signal dynamics*, to be similar across animals with
the same hearing status. To measure the similarity of the signal dynamics across animals (Fig. 2a,
step 4), we projected the original activity for each animal onto its respective signal manifold and then
determined how much of the variance in the activity from one animal could be explained by the
activity from the another (allowing for additional linear transformation). We found that the signal
dynamics for different animals were remarkably similar, with the signal dynamics from one animal
accounting for, on average, 96% of the variance in the signal dynamics from other animals (Fig. 2e).
This result gives us confidence that the signal manifold is indeed fundamental, and that our methods
are sufficient to identify it robustly in individual animals.

Identifying the neural signal manifold

Figure 2: Neural signal dynamics identified via classical methods

Figure 2: Neural signal dynamics identified via classical methods

(**a**) Schematic diagram showing the method for identifying the neural signal manifold from recordings of neural activity. Step 1: PCA is performed on a subset of the recordings allocated for training. Step 2a: A subset of recordings allocated for testing are projected onto the PCs from step 1. Step 2b: The projections from step 2a are used to reconstruct the test recordings. Step 2c: the reconstructions from step 2b are compared to the test recordings from step 2a to determine the total variance explained. Step 3: the reconstructions from step 2b are compared to another set of test recordings (made during a second presentation of the same sounds) to determine the signal variance explained. Step 4: the projections from step 2a for one animal are compared to the projections for another animal to determine the similarity of the signal dynamics between animals. (**b**) Total variance explained in step 2c as a function of the number of PCs used for the reconstruction. Each thick line shows the results for one normal hearing animal (n = 6). The thin line denotes 95% variance explained. (**c**) Signal variance explained in step 3 as a function of the number of PCs used for the reconstruction. (**d**) Percent of variance explained by each PC that corresponds to neural signal (rather than neural noise) for an example animal. (**e**) Variance explained in step 4 for each pair of normal hearing animals. (**f,g**) Total variance explained in step 2c and signal variance explained in step 3 for animals with hearing loss (n = 6). (**h,i**) Variance explained in step 4 for each pair of animals with hearing loss, and each pair of animals with different hearing status.

Hearing loss distorts neural signal dynamics

We next sought to use analysis of the signal manifold to better understand the impact of hearing loss on the neural code for speech at the network level. We induced sloping mild-to-moderate sensorineural hearing loss (Supp Fig. 1) by exposing gerbils (n = 6) to broadband noise using established protocols[16,17]. After waiting at least one month for the effects of the hearing loss to stabilize, we made neural recordings while presenting the same speech and noise sounds and then performed the same manifold learning.

The results for animals with hearing loss were similar to those for animals with normal hearing: the overall dimensionality of the neural activity was high (Fig. 2f); the dimensionality of the signal manifold was low (Fig. 2g); and the signal dynamics were similar across animals (Fig. 2h; 95% average variance explained), demonstrating again that the signal manifold is fundamental and robust. But the similarity between the signal dynamics of normal hearing animals and animals with hearing loss was much lower than that between animals with the same hearing status (Fig. 2i; 78% average variance explained). This result indicates that the activity within the signal manifold of an animal with hearing loss is not linearly predictable from the activity within the signal manifold of a normal hearing animal and, thus, that the impact of hearing loss at the network level is a true nonlinear distortion that reshapes the neural code in a complex way.

DNNs enable accurate simulation of neural signal dynamics

To develop an understanding of exactly how hearing loss impacts signal dynamics, further investigation is required. However, traditional approaches to manifold learning such as PCA are limited by the fact that they can only be applied to existing recordings. To overcome this limitation, we designed a DNN that allowed us to identify the signal manifold within the framework of an encoding model that maps sound to neural activity (Fig. 3a). If the DNN can be trained to replicate neural activity with high accuracy for a wide range of sounds, it can then be used to probe the effects of hearing loss on signal dynamics using new sounds as needed.

A deep neural network model of the inferior colliculus

Figure 3: Neural signal dynamics identified via deep learning

(**a**) Schematic diagram of the DNN used to predict IC activity. (**b**) Example images of neural activity elicited by a speech syllable from an example recording (left), reconstructed as in step 2b of Fig. 2 (center), and predicted by the DNN (right). (**c**) Left: Predictive power of the DNN for each unit from one animal. The value on the horizontal axis is the fraction of the variance in the neural activity that is explainable (i.e. that is consistent across trials of identical speech). The value on the vertical axis is the percent of this explainable variance that was captured by the DNN. Analogous values for linear-nonlinear (LN) models trained and tested on the same activity are shown for comparison. Right: Average predictive power for all units as a function of the number of channels in the bottleneck layer. Each line shows the results for one animal. (**d**) Fraction of the variance in one set of bottleneck activations explained by another set for each pair of normal hearing animals (left), each pair of animals with hearing loss (center), and each pair of animals with different hearing status (right).

The DNN first projects sound into a high-dimensional feature space using a cascade of convolutional
layers. It then reduces the dimensionality of its feature space through a bottleneck layer and uses a
linear readout to transform the activations in the bottleneck into the neural activity for each recorded
unit. During training, the DNN learns to use the bottleneck to identify the low-dimensional feature
space that captures as much of the explainable variance in the recorded neural activity as possible,
i.e. the signal manifold. (Note that the structure of the DNN is not meant to reflect the anatomy of the
auditory system; it is simply a tool for identifying latent dynamics and predicting neural activity.)

Once the DNN is trained, it can be used to simulate neural activity for any sound, whether it was
presented during neural recordings or not, with the activations in the bottleneck layer reflecting the
underlying signal dynamics. This model-based approach to identifying the signal manifold also has
the added advantage that it eliminates the residual noise that is inevitable with methods such as PCA
(Fig. 3b). (Because the dynamics of the DNN depend only on its sound inputs, they contain only
signal, while methods that operate directly on neural recordings that contain both signal and noise
have a limited ability to separate the two; see decreasing SNR with successive PCs in Fig. 2d).

The utility of the DNN rests on its ability to faithfully reproduce the recorded neural activity. We trained
and tested a separate DNN for each animal (after partitioning the recordings into training and test
sets as described above) and found that they performed with remarkable accuracy. The explainable

variance explained for activity in the test set approached 100% for the units with highest explainable
variance, and was far beyond that achieved by a standard single-layer linear-nonlinear model (Fig.
3c). We varied the size of the bottleneck layer and found that performance plateaued with more than
8 channels for both normal hearing animals and those with hearing loss, consistent with the
dimensionality of the signal manifold identified through PCA (Fig. 3c).

We also assessed the similarity of the DNN-derived signal dynamics across animals by measuring
how much of the variance in the bottleneck activations from one animal could be explained by the
bottleneck activations from another (allowing for additional linear transformation). We found that the
signal dynamics for animals with the same hearing status were nearly identical, while the similarity
between the signal dynamics for animals with normal hearing and those with hearing loss was much
lower (Fig. 3d). Thus, the signal manifold as identified by the DNN appears to have similar properties
to that identified through PCA, with the added advantages of reduced residual noise and the ability
to probe the signal dynamics using novel sounds.

Hearing loss distorts spectral processing

Before continuing our investigation of the neural coding of speech, we first used the DNN to examine
the impact of hearing loss on the processing of basic acoustic features. To assess spectral
processing, we presented the DNN for each animal with a stream of pure tones with different
frequencies and intensities and extracted the activations from the bottleneck layer (Fig. 4a; we set
the dimensionality of the bottleneck layer to 8 for this and all subsequent analyses). The frequency
response areas (FRAs) for individual bottleneck channels resembled those that are typically
observed for individual neurons in the IC: some exhibited a clear preferred frequency at low
intensities and broader tuning at high intensities, while others had more complex shapes (Fig. 4b).
For animals with hearing loss, elevated intensity thresholds were also evident.

To visualize the signal dynamics, we applied PCA to the bottleneck activations (for each intensity
separately) and projected the full dynamics onto the top two PCs, which explained more than 90%
of the variance for these simple sounds (Fig. 4c). For normal hearing animals, the paths traced by
the dynamics within the signal manifold for different sounds, which we term **trajectories**, were
distinct and formed an orderly arrangement, but with a clear change in geometry across intensities
(Fig. 4d). At low intensities, the trajectories for different frequencies were distinct across both PCs,
each of which accounted for substantial variance (the percent of the variance in the signal dynamics
explained by each PC at each intensity is indicated on each panel). But at high intensities, the
trajectories for all frequencies were similar along the first PC, which accounted for the vast majority
of the variance, and varied only along the second PC. These intensity-dependent changes in the
geometry of the signal dynamics are consistent with the known effects of intensity on spectral tuning
in IC neurons. At low intensities, tuning is narrow and, thus, different tone frequencies elicit distinct
population activity patterns. But at high intensities, because tuning is broader, the population activity
patterns elicited by different frequencies are less distinct.

For animals with hearing loss, the signal dynamics were dramatically different. At moderate intensity,
only the lowest frequencies elicited any activation (as expected, given the larger elevation in intensity
thresholds at high frequencies (Supp Fig. 1)). At higher intensity, all tones elicited activation, but
rather than forming an orderly arrangement within the manifold, the trajectories for different
frequencies clustered into two groups. At the highest intensity, the trajectories for different

Figure 4: Neural signal dynamics for pure tones

Figure 4: Neural signal dynamics for pure tones

(**a**) Schematic diagram showing pure tone sounds with different frequencies and intensities and corresponding bottleneck activations. (**b**) FRAs for the 8 bottleneck channels from a normal hearing animal (top) and an animal with hearing loss (bottom). Each subplot shows the average activity for one channel in response to tones with different frequencies and intensities. The colormap for each plot is normalized to the minimum and maximum activity level across all frequencies and intensities. (**c**) Dimensionality reduction of bottleneck activations via PCA. Each line shows the variance explained by the top two PCs for one animal as a function of the intensity of the tones. (**d**) Signal dynamics for pure tones for a normal hearing animal (left) and an animal with hearing loss (right). The top two rows show the projection of the bottleneck activations onto each of the top two PCs as a function of time. The inset value indicates the percent of the variance in the bottleneck activations explained by each PC. The bottom row shows the projections from the top two rows plotted against one another. Each line shows the dynamics for a different tone frequency. Each column shows the dynamics for a different tone intensity. (**e**) RDMs computed from bottleneck activations. The left image shows the average RDM for normal hearing animals for tones at 55 dB SPL. The value of each pixel is proportional to the point-by-point correlation between the activations for a pair of tones with different frequencies. The center image shows the same lower half of the RDM for normal hearing animals along with the upper half of the RDM for animals with hearing loss at the same intensity. The right image shows the same lower half of the RDM for normal hearing animals along with the upper half of the RDM for animals with hearing loss at the best intensity (that which produced the highest point-by-point correlation between the normal hearing and hearing loss RDMs). (**f**) The point-by-point correlation between RDMs for each pair of normal hearing animals (n = 15), and each pair of animals with different hearing status compared at either the same intensity or the best intensity (n = 36). Median values were compared via Kruskal-Wallis one-way ANOVA and Tukey-Kramer post-hoc tests, *** indicates $p < 0.001$, ** indicates $p < 0.01$, * indicates $p < 0.05$, ns indicates not significant. (**g**) Average signal dynamics for pure tones for normal hearing animals (left) and animals with hearing loss (right) after alignment via MCCA. (**h**) The similarity between dynamics after alignment via pairwise CCA (see Methods) for each pair of normal hearing animals, and each pair of animals with different hearing status compared at either the same intensity or the best intensity (that which produced the highest similarity between the dynamics) .

frequencies became more distinct, but clear clustering remained. The increased similarity in the
signal trajectories for different frequencies is consistent with the increased similarity of spectral tuning
between individual IC neurons in animals with hearing loss[18,19], but the clustering of dynamics within
the signal manifold is an emergent network-level phenomenon that has not previously been
observed.

To further analyze the dynamics and allow for direct comparisons across animals, we first turned to
representational similarity analysis (RSA)[20]. RSA uses only the relative distances between
trajectories within a manifold and, thus, does not require the dynamics for different animals to be
aligned. The first step in RSA is to form a representational dissimilarity matrix (RDM) for each set of
trajectories, with each entry in the RDM equal to one minus the point-by-point correlation between a
pair of trajectories for two different sounds (Fig. 4e, left).

The structure of the RDMs were consistent with the observations about the dynamics made above.
For normal hearing animals, the RDMs had a diagonal symmetry with a smooth gradient, indicating
that the similarity of the trajectories for two frequencies decreased gradually as the difference
between the frequencies increased. For animals with hearing loss, the RDMs had a block structure,
indicating that the trajectories formed two clusters (Fig. 4e, center; note that RDMs are symmetric,
so the lower half of the normal hearing RDM is shown with the upper half of the hearing loss RDM
for comparison).

Because we were interested in identifying effects of hearing loss beyond those related to audibility,
we also compared the normal hearing RDMs at a given intensity to the hearing loss RDMs at the
best intensity, i.e., at whatever intensity resulted in the highest similarity to the normal hearing RDM
for each pair of animals (measured as the point-by-point correlation between the RDMs).
Amplification to the best intensity softened the block structure and shifted the transition between

clusters to a lower frequency, but did not fully restore the diagonal structure present in the normal
hearing RDMs (Fig. 4e, right). Overall, the similarity between the RDMs for different normal hearing
animals at moderate intensity (55 dB SPL) was high (0.91 ± 0.01; n = 15 pairwise comparisons; Fig.
4f). The similarity between the normal hearing and hearing loss RDMs at the same moderate intensity
was much lower (0.59 ± 0.02; n = 36) and remained relatively low even at the best intensity (0.78 ±
0.02; n = 36).

The results of RSA are easy to interpret but, because it uses only the relative distances between
trajectories, it can be insensitive to distortions that impact the overall structure of the dynamics. To
allow for direct comparisons of overall structure, we used canonical correlation analysis (CCA)[21].
CCA identifies a series of linear projections, known as canonical components (CCs), that attempt to
align two sets of dynamics such that the point-by-point correlation between trajectories after
projection onto their respective CCs is maximized. The set of CCs for a given set of dynamics are
required to be orthogonal to each other and to explain all of the variance in the original trajectories.
CCA can also be extended to simultaneously align dynamics for an entire group of animals through
multiway canonical correlation analysis (MCCA)[22].

The average dynamics after alignment via CCA exhibited phenomena that were similar to those that
were evident for individual animals (Fig. 4g). For normal hearing animals, the trajectories for different
tone frequencies were distinct and formed an orderly arrangement, with frequency-dependent
variation across two dimensions at low intensities but only one dimension at high intensities. For
animals with hearing loss, the trajectories for different frequencies clustered into two groups at
moderate intensities and remained clustered, albeit more weakly, at high intensities.

To measure the similarity between the dynamics for different animals after alignment via CCA, we
used a weighted sum of the point-by-point correlations between the two sets of dynamics after
projection onto each pair of CCs, with the weight for the correlation associated with each pair of CCs
given by the average variance in the original dynamics that those CCs explained (see Methods for
equation). Overall, the similarity between the dynamics for different normal hearing animals at
moderate intensity after alignment via CCA was extremely high (0.98 ± 0.01; n = 15; Fig. 4h). The
similarity between the aligned dynamics for normal hearing and hearing loss animals at the same
moderate intensity was much lower (0.37 ± 0.02; n = 36) and remained below normal even when
compared at the best intensity (0.88 ± 0.01; n = 36). Taken together, the RSA and CCA results
suggest that the effects of hearing loss result in a fundamental disruption of spectral processing at
the network level, well beyond that which would be expected from the known effects of hearing loss
on the response properties of single neurons.

Hearing loss does not distort temporal processing

We next assessed temporal processing by performing a similar analysis on the bottleneck activations
elicited by a stream of sinusoidally amplitude modulated (SAM) broadband noise sounds with
different modulation frequencies and intensities (Fig. 5a). For these sounds, two dimensions were
again enough to capture almost all of the variance in the full signal dynamics across all intensities
(Fig. 5b). For both normal hearing animals and those with hearing loss, the explicit tracking of
envelope modulations in the signal dynamics decreased with increasing modulation frequency and
increasing intensity (Fig. 5c). But when compared at the same intensity, the dynamics for animals
with hearing loss clearly differed from those for animals with normal hearing (Fig. 5d,e).

Signal dynamics for SAM noise

Figure 5: Neural signal dynamics for amplitude modulated noise

Figure 5: Neural signal dynamics for amplitude modulated noise
(**a**) Schematic diagram showing amplitude modulated noise sounds with different intensities and modulation frequencies. (**b**) Variance in bottleneck activations explained by top two PCs for each animal as function of sound intensity. (**c**) Envelope tracking in signal dynamics measured as the coefficient of variation of the bottleneck activations for sounds with different modulation frequencies at an intensity of 55 dB SPL (left) and sounds at different intensities with a modulation frequency of 100 Hz (right). Values shown are the average across animals. (**d**) Signal dynamics for a normal hearing animal (left) and an animal with hearing loss (right). Each line shows the dynamics for a different modulation frequency. (**e**) Signal dynamics for a modulation frequency of 100 Hz after projection onto the top PC. The top panel shows the dynamics for a normal hearing animal and an animal with hearing loss at 55 dB SPL. The bottom panel shows the same dynamics for the normal hearing animal along with the dynamics for the animal with hearing loss at the best intensity. (**f**) RDMs computed from bottleneck activations and the point-by-point correlation between RDMs for different pairs of animals at 55 dB SPL or best intensity. (**g**) The similarity between dynamics after alignment via pairwise CCA for different pairs of animals at 55 dB SPL or best intensity. (**h**) Schematic diagram showing amplitude modulated noise sounds with different intensities and modulation depths. (**i**) Signal dynamics for a normal hearing animal at 55 dB SPL (left) and an animal with hearing loss at the best intensity (right). Each line shows the dynamics for a different modulation depth. (**j**) The point-by-point correlation between RDMs for different pairs of animals at 55 dB SPL or best intensity. (**k**) The similarity between dynamics after alignment via pairwise CCA for different pairs of animals at 55 dB SPL or best intensity.

This was confirmed by RSA (Fig. 5f), which indicated that while the similarity between normal hearing
RDMs at moderate intensity (55 dB SPL) was extremely high (0.99 ± 0.01; n = 15), the similarity
between normal hearing and hearing loss RDMs was lower (0.76 ± 0.01; n = 36). But when compared
at the best intensity to eliminate differences related to audibility, the dynamics for animals with
hearing loss became nearly identical to those for animals with normal hearing (Fig. 5e), and this was
reflected in the similarity between RDMs (0.99 ± 0.01; n = 36).

Comparing the similarity of the dynamics after alignment via CCA yielded similar results (Fig. 5g).
The similarity between the dynamics for different normal hearing animals at moderate intensity after
alignment via CCA was high (0.97 ± 0.01; n = 15). The similarity between the aligned dynamics for
normal hearing and hearing loss animals was much lower when compared at the same moderate
intensity (0.44 ± 0.02; n = 36) but increased to normal levels when the comparison was made at the
best intensity (0.95 ± 0.01; n = 36). Thus, it appears that hearing loss has little impact on temporal
processing beyond that which results from decreased audibility.

We verified that this was also true for the processing of sounds with different modulation depths. We
performed the same analysis on the bottleneck activations elicited by a stream of SAM noise sounds
with different modulation depths and intensities (and a fixed modulation frequency of 30 Hz; Fig. 5h).
When compared at the best intensity, the signal dynamics for normal hearing animals and animals
with hearing loss were nearly identical (Fig. 5i), with the explicit tracking of envelope modulations
decreasing with decreasing modulation depth. The overall similarity measured at the best intensity
both by RSA (0.99 ± 0.01; n = 36; Fig. 5j) and after alignment via CCA (0.96 ± 0.01; n = 36; Fig. 5k)
confirmed that the impact of hearing loss on temporal processing beyond that which results from
decreased audibility was negligible.

Distortions in the neural code for speech in quiet are largely corrected by amplification

Having established that the distortions in neural signal dynamics caused by hearing loss affect
primarily spectral, rather than temporal, processing for simple sounds, we next returned to speech.
We focused on consonants, which vary widely in their spectral properties and are the primary
contributor to the perceptual deficits exhibited by people with hearing loss when listening to ongoing
speech[23]. We presented the DNN with a stream of isolated consonants (diphone syllables with the

Figure 6: Neural signal dynamics for speech in quiet

(**a**) Schematic diagram showing different consonants. (**b**) Average power spectra for three classes of consonants. The individual consonants are shown in the inset in panel d. (**c**) Variance in bottleneck activations explained by top two PCs for each animal as a function of sound intensity. (**d**) Signal dynamics for a normal hearing animal (left) and an animal with hearing loss (right). Each line shows the dynamics for a different consonant, averaged over all instances. (**e**) RDMs computed from bottleneck activations and the point-by-point correlation between RDMs for different pairs of animals at 60 dB SPL, best intensity, or with a hearing aid. (**f**) The similarity between dynamics after alignment via pairwise CCA for different pairs of animals at 60 dB SPL, best intensity, or with a hearing aid. (**g**) Performance of a support vector machine classifier trained to identify consonants based on bottleneck activations for each normal hearing animal (n = 6) at 60 dB SPL and each animal with hearing loss (n = 6) at either 60 dB SPL, best intensity, or with a hearing aid.

vowel removed), each uttered multiple times by multiple talkers (Fig. 6a). The consonants can be
divided into three broad groups: the vowel-like consonants (nasals and approximants), which are
dominated by low frequencies; the plosives, which are broadband; and the fricatives, which are
dominated by high frequencies (Fig. 6b).

For both normal hearing animals and animals with hearing loss, two dimensions were again sufficient
to explain nearly all of the variance in the bottleneck activations (Fig. 6c). For normal hearing animals,
the dynamics elicited by different consonants followed distinct trajectories that were organized within
the signal manifold according to consonant type (Fig. 6d; the dynamics shown are the average across
all instances of each consonant). For animals with hearing loss, only the vowel-like consonants
elicited responses at moderate intensity (as expected, given the larger elevation in intensity
thresholds at high frequencies (Supp Fig. 1)). At higher intensities, all consonants elicited responses
but the trajectories were not as distinct as with normal hearing and exhibited a clustering similar to
that observed for pure tones (Fig. 4d), which softened at the highest intensity.

The differences in the dynamics for normal hearing animals and those with hearing loss were evident
in the RDMs (Fig. 6e). When compared at a typical conversational intensity (60 dB SPL), the similarity
between normal hearing RDMs was high (0.94 ± 0.01; n = 15), but the similarity between normal
hearing and hearing loss RDMs was low (0.23 ± 0.02; n = 36). The normal hearing and hearing loss
RDMs were much more similar when compared at the best intensity, though some differences
remained (0.87 ± 0.01; n = 36).

Comparing the similarity of the dynamics after alignment via CCA yielded similar results (Fig. 6f).
The similarity between the dynamics for different normal hearing animals after alignment via CCA
was high (0.96 ± 0.01; n = 15). The similarity between normal hearing and hearing loss animals when
compared at the same conversational intensity was much lower (0.31 ± 0.02; n = 36) and increased
when the comparison was made at the best intensity, but not to normal levels (0.77 ± 0.01; n = 36).

Given that hearing loss seems to impact primarily spectral processing, we investigated whether the
distortions in the neural code for speech could be corrected by providing frequency-dependent
amplification using a simulated hearing aid[16,24]. We used the measured ABR threshold shifts for each
animal to set the parameters for the amplification, which resulted in a gain of approximately 10 dB at
low frequencies and 30 dB at high frequencies for speech at conversational intensity (Supp Fig. 1),
and presented the same stream of consonants again after processing with the hearing aid. The
frequency-dependent amplification was effective in reducing the distortion in the dynamics for
animals with hearing loss. The overall similarity between normal hearing and hearing loss animals
as measured by RSA was restored to normal levels (0.91 ± 0.01; n = 36; Fig. 6e), and the similarity
measured after alignment via CCA was also increased, though some residual distortion remained
(0.86 ± 0.01; n = 36; Fig. 6f).

To evaluate the functional significance of the remaining distortion, we turned to decoding. We trained
a support vector machine to classify consonants based on the signal dynamics for each animal. For
normal hearing animals, the decoder identified 55% of consonants correctly (± 1%; n = 6) when the
consonants were presented at conversational intensity (Fig. 6g). For animals with hearing loss,
performance at the same intensity was lower (41 ± 1%; n = 6) but increased substantially at best
intensity (47 ± 1%; n = 6), and increased further still with frequency-dependent amplification by the
hearing aid (49 ± 1%; n = 6). Taken together, these results suggest that the distortions in the neural
code for speech in quiet can be largely corrected with suitable amplification.

Distortions in the neural code for speech in noise persist even after frequency-weighted
amplification

Given that the perceptual difficulties experienced by listeners with hearing loss are most pronounced
in noisy environments, we expected that the addition of background noise to the speech would create
larger distortions in the neural code. We presented the same consonant stream with added speech

babble (background noise formed by adding together the voices of many different talkers; Fig. 7a,b)
at a speech-to-noise ratio of 3 dB, which is typical of real-world settings experienced by hearing aid
users[25]. The addition of background noise increased the dimensionality of the signal dynamics
relative to simple sounds or speech in quiet, especially at high overall intensities; three PCs were
often required to capture more than 90% of the variance (Fig. 7c). (Note that both the speech and
the background noise contribute to the signal dynamics, which encode all incoming sounds without
distinction).

For normal hearing animals, the signal dynamics for speech-in-noise and speech-in-quiet were
nearly identical at the lowest intensities, but differed strongly at higher intensities (Fig. 7d; the
dynamics shown are the average across all instances of each consonant). For speech-in-noise at
the highest intensity, there was a clear distinction between the first PC, which provided a clean
reflection of each consonant (though not the same as for speech in quiet), and the other PCs, which
were dominated by the background noise (despite averaging across all instances of each consonant
with independent noise). The trends were similar for animals with hearing loss, though the
background noise was reflected in the signal dynamics even more strongly.

When compared at the same high intensity (70 dB SPL), typical of a social setting, both RSA and
CCA indicated strong effects of hearing loss on the signal dynamics for speech in noise (Fig. 7e,f).
The similarity between normal hearing RDMs was high (0.89 ± 0.02; n = 15), but the similarity
between normal hearing and hearing loss RDMs was much lower (0.15 ± 0.03; n = 36). Amplification
to best intensity increased the similarity between normal hearing and hearing loss RDMs (0.62 ±
0.02; n = 36), as did the frequency-weighted amplification provided by the hearing aid (0.56 ± 0.03;
n = 36), but neither was sufficient to bring the similarity close to normal levels.

Comparing the similarity of the dynamics after alignment via CCA yielded similar results. The
similarity between the dynamics for different normal hearing animals after alignment via CCA was
high (0.92 ± 0.01; n = 15). The similarity between normal hearing and hearing loss animals when
compared at the same intensity was much lower (0.49 ± 0.02; n = 36) and increased when the
comparison was made at the best intensity (0.68 ± 0.01; n = 36) or after processing with the hearing
aid (0.70 ± 0.02; n = 36), but remained well below normal levels.

Decoding the signal dynamics for each animal suggested that the distortions in the signal dynamics
for speech in noise were functionally significant (Fig. 7g). For normal hearing animals, the decoder
identified 32% of consonants correctly (± 1%; n = 6). For animals with hearing loss, performance at
the same intensity was lower (15 ± 1%; n = 6) and remained well below normal levels both at the
best intensity (23 ± 1%; n = 6) or after processing with the hearing aid (22 ± 1%; n = 6).

Hearing loss causes hypersensitivity to background noise

To gain a better understanding of the differential impact of the background noise with and without
hearing loss, we used MCCA to jointly align the signal dynamics for all animals with normal hearing
and hearing loss so that we could make direct comparisons. We first analyzed the results for speech
in quiet. When compared at best intensity (Fig. 8a), there was good alignment between the dynamics

Signal dynamics for speech in noise

Figure 7: Neural signal dynamics for speech in noise

Figure 7: Neural signal dynamics for speech in noise
(**a**) Schematic diagram showing different consonants in speech babble. (**b**) Average power spectra for three classes of consonants and speech babble. (**c**) Variance in bottleneck activations explained by top two (left) or three (right) PCs for each animal as a function of sound intensity. (**d**) Signal dynamics for a normal hearing animal (top) and an animal with hearing loss (bottom). Each line shows the dynamics for a different consonant, averaged over all instances. Dynamics for speech in quiet are shown alongside those for speech in noise for comparison. (**e**) Point-by-point correlation between RDMs for different pairs of animals at 70 dB SPL, best intensity, or with a hearing aid. (**f**) The similarity between dynamics after alignment via pairwise CCA for different pairs of animals at 70 dB SPL, best intensity, or with a hearing aid. (**g**) Performance of a support vector machine classifier trained to identify consonants based on bottleneck activations for each normal hearing animal at 70 dB SPL, and each animal with hearing loss at 70 dB SPL, best intensity, or with a hearing aid.

for animals with normal hearing and hearing loss. The correlation for pairs of animals after projection
onto the first CC, which accounted for 88 ± 2% and 71 ± 7% of the variance in animals with normal
hearing (n = 6) and hearing loss (n = 6), respectively, was 0.94 ± 0.01 (n = 36). The correlation after
projection onto the second CC, which accounted for the remaining variance, was lower (0.44 ± 0.03;
n = 36).

With the hearing aid (Fig. 8b), the alignment between the dynamics for animals with normal hearing
and hearing loss was even better. The correlation after projection onto the first CC remained high
0.94 ± 0.01 (n = 36) and the correlation after projection onto the second CC rose substantially (0.73
± 0.01; n = 36). These results are consistent with the analysis for speech in quiet above that
suggested that only minimal distortions in the signal dynamics for animals with hearing loss remain
after frequency-weighted amplification is provided (Fig. 6).

For speech in noise, the alignment was generally worse overall. When compared at best intensity
(Fig. 8c), the correlations after projection onto the CCs were 79 ± 1%, 74 ± 3%, and 18 ± 3%,
respectively (n = 36). But even for the first two CCs for which the alignment was relatively good, the
percent of the variance accounted for by each was substantially different for normal hearing animals
and those with hearing loss. The first CC, which provided a clean reflection of each consonant,
accounted for 56 ± 1% of the variance for normal hearing animals (n = 6), but only 38 ± 7% of the
variance for animals with hearing loss (n = 6). Conversely, the second CC, which was dominated by
the background noise, accounted for 41 ± 6% of the variance for animals with hearing loss (n = 6),
but only 28 ± 1% of the variance for animals with normal hearing.

Given the nature of the hearing loss (larger elevation in intensity thresholds at high frequencies; Supp
Fig. 1) and the spectral properties of speech babble (higher power at low frequencies; Fig. 7b), the
hypersensitivity of animals with hearing loss to the background noise is somewhat expected.
However, the problem was, if anything, exacerbated by the selective amplification of high frequencies
provided by the hearing aid (Fig. 8d). The CC that was dominated by the background noise (now the
first CC, since it produced the highest correlation) accounted for 46 ± 6% of the variance for animals
with hearing loss (n = 6), but only 31 ± 1% of the variance for animals with normal hearing, while the
CC that provided a clean reflection of each consonant (now the second CC) accounted for 56 ± 1%
of the variance for normal hearing animals (n = 6), but only 33 ± 6% of the variance for animals with
hearing loss (n = 6). Thus, it appears that hearing loss allows the signal dynamics to be captured by
background noise at the expense of foreground speech in a way that cannot be corrected by simple
frequency-dependent amplification.

To characterize the distortions in spectral processing that underlie this effect, we examined how the
processing of one narrowband sound is impacted by the presence of another. We used narrowband
noise modulated by a 20 Hz sinusoidal envelope as the target sound and narrowband noise

Signal dynamics for speech in quiet

Signal dynamics for speech in noise

Impact of narrowband masker on signal dynamics for narrowband target

Figure 8: Hypersensitivity to background noise after hearing loss

Figure 8: Hypersensitivity to background noise after hearing loss

(**a**) Average signal dynamics for speech in quiet at 60 dB SPL for normal hearing animals (left) and at best intensity for animals with hearing loss (right) after joint alignment via MCCA. The inset value within each panel indicates the average percent of the variance in the bottleneck activations explained by each CC. The inset value between columns indicates the average correlation between the dynamics after projection onto each pair of CCs. (**b**) Average signal dynamics for speech in quiet at 60 dB SPL for normal hearing animals (left) and with a hearing aid for animals with hearing loss (right) after joint alignment via MCCA. (**c**) Average signal dynamics for speech in noise at 70 dB SPL for normal hearing animals (left) and at best intensity for animals with hearing loss (right) after joint alignment via MCCA. (**d**) Average signal dynamics for speech in noise at 70 dB SPL for normal hearing animals (left) and with a hearing aid for animals with hearing loss (right) after joint alignment via MCCA. (**e**) Schematic diagram showing amplitude modulated narrowband noise target and masker sounds. (**f**) Coherence between bottleneck activations for target noise with and without masker noise at 70 dB SPL. Each line shows the coherence for a different target center frequency as a function of the masker center frequency, averaged across individual animals. (**g**) Change in coherence between bottleneck activations for target noise with and without masker noise at 70 dB SPL for animals with hearing loss relative to animals with normal hearing. (**h**) Change in coherence for animals with hearing loss at best intensity relative to animals with normal hearing at 70 dB SPL. (**i**) Change in coherence for animals with hearing loss with a hearing aid relative to animals with normal hearing at 70 dB SPL.

modulated by a pink noise envelope as the masker (Fig. 8e). We varied the center frequency of the
target and masker separately and the intensity of the target and masker together (to maintain a
constant target-to-masker ratio). We presented the target sounds to the DNN for each animal with
and without the masker sounds and measured the differences between the signal dynamics across
the two conditions by computing their coherence (the covariance between the dynamics for each
condition divided by the mean of their variances).

For animals with normal hearing, the coherence between the target only and target plus masker
dynamics ranged from 0.25 to 0.75, with the masker having the largest impact when its center
frequency was similar to that of the target (Fig. 8f). When compared at the same high intensity (70
dB SPL), the coherence for animals with hearing loss was typically lower than normal when the
masker center frequency was low, especially when the target center frequency was high (Fig. 8g).
This regime (high-frequency target, low-frequency masker) is comparable to the speech-in-noise
scenario analyzed above (many consonants contain substantial high frequency content, while
speech babble is dominated by low frequencies, see Fig. 7b), and the increased impact of the masker
with hearing loss is consistent with observed hypersensitivity to background noise at the expense of
foreground speech. For high frequency maskers, the coherence for animals with hearing loss was
often higher than normal, especially for low-frequency targets. This is unsurprising given the sloping
nature of the hearing loss, but this regime (low-frequency target, high-frequency masker) is
uncommon in real-world speech.

When the coherence for animals with normal hearing and hearing loss were compared either at the
best intensity (Fig. 8h) or after frequency-weighted amplification with the hearing aid (Fig. 8i), the
pattern of results was similar. In the regime that is most comparable to consonants in speech babble
(low-frequency masker, high-frequency target), the coherence for animals with hearing loss was
lower than normal. Thus, hearing loss appears to create deficits in spectral processing that manifest
as highly nonlinear distortions in cross-frequency interactions that are particularly problematic for
real-world speech in noise and cannot be corrected by simply compensating for lost sensitivity.

Discussion

460 In this study, we took advantage of recently-developed tools for large-scale neural recordings and
461 nonlinear modeling that allowed us to gain new insights into the impact of hearing loss on auditory
462 processing at the network level. We first used a traditional approach to manifold learning to establish

that the neural code for speech in the IC can be well described by low-dimensional latent signal dynamics that are common across animals with similar hearing status but fundamentally altered by hearing loss. We then trained a DNN to replicate neural coding in the IC with high accuracy using a framework that also facilitated manifold learning. The DNN exhibited dynamics in response to speech that were similar to those identified directly from IC recordings, and further probing of the DNN dynamics with novel sounds allowed us to identify changes in cross-frequency interactions as a key contributor to the distorted neural coding of speech-in-noise with hearing loss.

Suprathreshold effects of hearing loss

The effects of hearing loss beyond increased detection thresholds are typically ignored in clinical assessment and treatment. But these suprathreshold effects are, in fact, the main problem for many people in real-world settings, such as busy workplaces or social gatherings, where sound intensities are high and amplification via a hearing aid provides little benefit. The clinical neglect of suprathreshold effects is not due to a lack of awareness, but rather to a lack of effective treatments. And the lack of effective treatments stems from a lack of understanding of how the many physiological changes that accompany hearing loss contribute to complex perceptual deficits.

Many specific suprathreshold impairments with plausible links to speech-in-noise perception have been identified, such as decreased frequency selectivity, dynamic range, or temporal resolution[4]. But the extent to which each of these specific impairments contributes to real-world hearing problems has been difficult to determine. Our results suggest that changes in spectral processing, particularly in the interactions between different frequencies, are the primary problem. While impaired spectral processing was evident for simple tones as a clustering of dynamical trajectories within the signal manifold, this impairment does not appear to be a major problem for the neural coding of speech per se, as suitable amplification corrected many of the distortions caused by hearing loss for speech in quiet. For speech in noise, however, there was a hypersensitivity to background noise with hearing loss that amplification (simple or frequency-weighted) did little to alleviate, and this was consistent with observed interactions between narrowband sounds, which revealed an increased disruption of high frequency targets by low frequency maskers both with and without amplification. These results are consistent with a recent study that found that hearing loss caused the IC activity patterns elicited by different phonemes to become less distinct, and that a hearing aid failed to correct this problem for speech in noise[16].

Another recent study has provided insight into how the complex spectral distortions that appear to be the root of the problem might arise at the earliest stages of auditory processing[26]. The authors reported that animals with mild-to-moderate sensorineural hearing loss exhibited "distorted tonotopy" in the auditory nerve, with high-frequency fibers responding excessively to low-frequency sounds. They also found that it was this distorted tonotopy (rather than changes in frequency selectivity or temporal processing) that were most responsible for the disrupted neural coding of speech in noise. In the auditory nerve, however, there did not appear to be any analog of the clustering of network dynamics for simple tones that we observed in the IC. Such clustering could arise from normal central processing of distorted peripheral inputs, but it is also possible that plastic changes in central processing that follow hearing loss exacerbate the peripheral distortions. In the latter case, it may be possible to reverse some of these effects and improve speech in noise perception through targeted rehabilitory training.

 A new focus for hearing aid design

The complex suprathreshold effects of hearing loss that are evident in the distorted neural signal
dynamics observed in this study present a difficult challenge for hearing aid designers. Current
hearing aids compensate for changes in the threshold and dynamic range of auditory processing
using a framework built around a bank of bandpass filters with automatic gain control. The signal
processing that can be performed by such a framework is highly constrained and it is difficult to
imagine how it could be used to compensate for problems such as hypersensitivity to background
noise that involve highly nonlinear interactions across frequency bands. It is possible that with a
better understanding of exactly how different frequencies are interacting, new signal processing
frameworks can be designed to offset the more complex effects of hearing loss. But engineering
such a framework that is flexible enough to provide benefit in a wide range of real-world settings will
require conceptual advances that may not be forthcoming in the near term.

One alternative approach to improving the perception of speech in noise that is already showing
promise is speech enhancement, i.e., the suppression of background noise. Hearing aids have
offered noise suppression for many years, but the simple filters based on low-order statistics that are
used by current devices often provide little real-world benefit[27,28]. Recent research on speech
enhancement via DNNs has demonstrated the potential to yield dramatic improvements in
performance[29]. This "deep denoising" may prove effective in situations with a single talker where it
is obvious which sound is of interest. But in others, e.g., with multiple talkers, a sound that is of
primary interest one minute may become a distraction the next. It may be possible to implement
cognitive control to direct enhancement toward the sound of interest but there are many significant
technical challenges that must be overcome before this approach can be widely applied[30].

A more flexible alternative is to identify optimal processing algorithms for hearing aids empirically by
providing DNNs with the data they need to learn how best to transform sounds in order to elicit normal
neural activity from an impaired auditory system[3,31]. By taking advantage of the nonlinear capacity of
DNNs with minimal assumptions, it should be possible to identify novel general-purpose algorithms
that go well beyond the hand-designed processing in current devices. Such algorithms would be
especially valuable in important contexts such as listening to music – a major problem for hearing
aid users[32] – in which denoising cannot help. There are, of course, limits to the degree of hearing
restoration that any hearing aid can provide in cases of severe hearing loss. But the vast majority of
people with hearing loss have only mild-to-moderate cochlear damage[1] and there should be sufficient
functionality remaining within the auditory system for a hearing aid to leverage when attempting elicit
the necessary patterns of neural activity.

Modeling biological neural networks with DNNs

Building computational models of sensory processing has been a long-standing goal in systems
neuroscience. Current models of the sensory periphery can be highly accurate. For example, there
are numerous models of the cochlea that faithfully capture the transformation of incoming sound into
basilar membrane motion and auditory nerve activity[33,34]. Models of sensory processing in the brain,
however, have generally been much less accurate, with even the best models missing out on a
significant fraction of the explainable variance in sub-cortical and cortical neural activity[35–38].

Until recently, efforts to model central sensory processing were constrained by the difficulties of fitting
high-capacity models with limited experimental data. But deep learning has provided a new approach
to fitting models that are well matched to sensory processing and new methods for large-scale
electrophysiology can provide the required big data. Initial efforts to use DNNs to model the sensory

periphery has shown that they can be as accurate as hand-designed biophysical models. In one
recent study, a DNN trained to replicate an established model of the cochlea provided near-perfect
predictions of the model's response to speech and tones[39]. In another study, a DNN trained on retinal
ganglion cell activity predicted nearly all of the explainable variance in responses to natural images[40].

DNN models of sensory processing in the brain have also been shown to outperform traditional
models. DNN models of V1 responses to natural images explained 50% and 80% of the explainable
variance in single-unit spike counts and calcium activity, respectively[41,42], while DNN models of V4
explained 90% of the explainable variance in multi-unit spike counts[43]. DNN models of A1 responses
to speech and other natural sounds perform similarly well, explaining 60% and 70% of the
explainable variance in high-gamma activity and fMRI voxel responses, respectively[44,45].

Our results improve on these initial successes in several important ways. Firstly, our models simulate
neural activity with full temporal resolution, i.e., spike times with millisecond precision. While lower
temporal resolution may be sufficient to describe sensory processing in some contexts, precise spike
timing carries critical information about speech[14]. Secondly, the activity produced by our models is
nearly indistinguishable from that recorded experimentally, capturing more than 95% of the
explainable variance in many cases. This is especially remarkable considering the full temporal
resolution (with lower resolution, variance at fine time scales, which is typically the most difficult to
capture, is simply ignored). Finally, our use of a low-dimensional bottleneck allows us to achieve this
performance within a framework that also provides a compact and interpretable description of the
latent dynamics that underlie the full network activity patterns.

With these advances, it should now be possible to use computational models of the brain for
exploratory basic research, with benefits that are both scientific (studies are no longer data limited)
and ethical (animal experiments can be limited to confirmatory studies), and for technology
development (such as improved hearing aids, as described above). With further effort, it may be
possible to build models that are not only black-box simulators but also mirror the underlying structure
of biological systems[46,47]. Such models would provide powerful platforms for testing mechanistic
hypotheses and developing new ways to address complex network-level dysfunctions that remain
difficult to treat (such as tinnitus).

Methods

Experimental protocol

579   Experiments were performed on 12 young-adult gerbils of both sexes that were born and raised in
580   standard laboratory conditions. Six of the animals were exposed to noise when they were 16-18
581   weeks old. ABR recordings and large-scale IC recordings were made from all animals when they
582   were 20-24 weeks old. All experimental protocols were approved by the UK Home Office (PPL
583   P56840C21).

Noise exposure

Mild-to-moderate sensorineural hearing loss was induced by exposing anesthetized gerbils to high-
pass filtered noise with a 3 dB/octave roll-off below 2 kHz at 118 dB SPL for 3 hours[16,17]. For
anesthesia, an initial injection of 0.2 ml per 100 g body weight was given with fentanyl (0.05 mg per
ml), medetomidine (1 mg per ml), and midazolam (5 mg per ml) in a ratio of 4:1:10. A supplemental
injection of approximately 1/3 of the initial dose was given after 90 minutes. Internal temperature was
monitored and maintained at 38.7° C.

 Preparation for large-scale IC recordings

Animals were placed in a sound-attenuated chamber and anesthetized for surgery with an initial injection of 1 ml per 100 g body weight of ketamine (100 mg per ml), xylazine (20 mg per ml), and saline in a ratio of 5:1:19. The same solution was infused continuously during recording at a rate of approximately 2.2 µl per min. Internal temperature was monitored and maintained at 38.7° C. A small metal rod was mounted on the skull and used to secure the head of the animal in a stereotaxic device. The pinnae were removed and speakers (Etymotic ER-2) coupled to tubes were inserted into both ear canals along with microphones (Etymotic ER-10B+) for calibration. The frequency response of these speakers measured at the entrance of the ear canal was flat (± 5 dB) between 0.2 and 8 kHz. Two craniotomies were made along with incisions in the dura mater, and a 256-channel multi-electrode array was inserted into the central nucleus of the IC in each hemisphere[16]. The arrays were custom-designed to maximize coverage of the portion of the gerbil IC that is sensitive to the frequencies that are present in speech.

Auditory brainstem responses

Before beginning the IC recordings, ABRs were measured. Subdermal needles were used as electrodes with the active electrodes placed behind the ear over the bulla (one on each side), the reference placed over the nose, and the ground placed in a rear leg. Recordings were bandpass filtered between 300 and 3000 Hz. The parallel ABR method[48] was used, with randomly timed tones at multiple frequencies presented simultaneously and independently to each ear. The tone frequencies were 500, 1000, 2000, 4000, and 8000 Hz. Each tone was 5 cycles long and multiplied by a Blackman window of the same duration. Tones were presented at a rate of 40 per s per frequency with alternating polarity for 100 s at each intensity. The activity recorded in the 30 ms following each tone was extracted and thresholds for each frequency were defined as the lowest intensity at which the root mean square (RMS) of the median response across presentations was more than twice the RMS of the median activity recorded in the absence of sound.

Sounds presented during IC recordings

(1) Speech: Sentences were taken from the TIMIT corpus[15] which contains speech read by a wide range of American English speakers. The entire corpus excluding "SA" sentences was used (approximately 4.5 h) and split into training and test sets (4.25 h and 0.25 h, respectively). The training set was presented twice, once on its own and once with background noise. The test set was presented four times, twice in quiet and twice with the same background noise. The intensity for each sentence was chosen at random from 55, 65, 75, or 85 dB SPL. The speech-to-noise ratio (SNR) was chosen at random from either 0 or 10 when the speech intensity was 55 or 65 dB SPL (as is typical of a quiet setting such as a home or an office) or -10 or 0 when the speech intensity was 75 or 85 dB SPL (as is typical of a noisy setting such as a pub). The intensity of the sentences for the two presentations of the test set in quiet were identical, as were the intensity, SNR, and specific noise used for the two presentations of the test set with background noise.

(2) Noise: Background noise sounds were taken from the Microsoft Scalable Noisy Speech Dataset[49], which includes recordings of environmental sounds from a large number of different settings (e.g., café, office, roadside) and specific noises (e.g., washer-dryer, copy machine, public address announcements). A total of 4.5 h of unique noises were used to match the duration of the presented speech. The intensity of the noise presented with each sentence was determined by the intensity of the speech and the SNR as described above.

Multi-unit activity

MUA was measured from recordings on each channel of the electrode array as follows: (1) a
bandpass filter was applied with cutoff frequencies of 700 and 5000 Hz; (2) the standard deviation
of the background noise in the bandpass-filtered signal was estimated as the median absolute
deviation / 0.6745 (this estimate is more robust to outlier values, e.g., neural spikes, than direct
calculation); (3) times at which the bandpass filtered signal made a positive crossing of a threshold
of 3.5 standard deviations were identified and grouped into bins with a width of 1.3 ms. Only units
with a signal correlation (across repeated trials of the speech in the test set) of 0.2 or higher were
used for manifold learning and DNN training (420 ± 24 (mean ± std) units from each animal).

Analysis of recorded neural activity

For each animal, the activity of the recorded units was represented as an $M \times T$ matrix, where M is
the number of units and T is the number of time bins. Separate matrices R_{train}, R_{test1}, and
R_{test2} were formed for the training set and each repetition of the test set (see *Speech* above).

Dimensionality of signal manifold

We applied PCA to R_{train} (after subtracting the mean from each row) to obtain the PCs, ranked in
order of the amount of neural variance they explain. We projected the activity in R_{test1} onto a chosen
number of PCs to obtain the latent dynamics within the manifold spanned by those PCs, yielding a
new $D \times T$ matrix $X_{test1} = ZR_{test1}$, where Z is the $D \times M$ matrix containing the first D PCs. We
reconstructed the activity in R_{test1} from the latent dynamics as $\hat{R}_{test1} = Z^T X_{test1}$ (plus the originally
subtracted means) and measured the total variance explained as the ratio of the covariance between
R_{test1} and $\hat{R}_{test1}$ and the square root of the product of their variances. We reconstructed the activity
in R_{test2} from the same latent dynamics as $\hat{R}_{test2} = Z^T X_{test1}$ (plus the means of the rows of R_{test2})
and measured the signal variance explained as the ratio of the covariance between R_{test2} and $\hat{R}_{test2}$
and the square root of the product of their variances. We defined the dimensionality of the signal
manifold for each animal based on the number PCs required to explain 95% of the signal variance.

Similarity of signal dynamics

We measured the similarity between the signal dynamics for different animals as the variance
explained after linear regression of one set of dynamics X_{test1} onto another $Y_{test1} = X_{test1}\beta + \varepsilon$,
where β is a matrix of regression coefficients and ε is a vector of error terms.

Deep neural network models

DNNs were used to transform sound input into neural activity across four stages: (1) a SincNet layer[50]
with 48 bandpass filters of length 32 samples, each with two learnable parameters (center frequency,
bandwidth), followed by symmetric log activations $Y = \text{sgn}(x)\log(|x| + 1)$; (2) a stack of 5
convolutional layers, each with 128 filters of length 32 samples and stride 2, followed by PReLU
activations; (3) a bottleneck convolutional layer with a specified number of filters of length 32 and
stride 1, followed by PReLU activations; (4) a linear readout layer followed by exponential activations.
The only hyperparameter that was varied was the number of filters in the bottleneck layer. For
comparison with a linear-nonlinear (LN) model, we used a network with the same stages 1 and 4 and
a single convolutional layer between them with 128 filters of length 256 samples and stride 1,
followed by PReLU activations.

Training

Models were trained to transform 24,414.0625 kHz sound input frames of length 8,192 samples into
762.9395 Hz neural activity frames of length 192 samples (corresponding to temporal decimation by
a factor of 5 via the strided convolutions in the encoder block plus a final cropping layer that removed
32 samples at the start and end of each frame to eliminate convolutional edge effects). Sound inputs
were scaled such that an RMS of 0.01 corresponded to a level of 85 dB SPL. Training was performed
in Matlab on a local PC with GPUs (2x NVIDIA RTX 3080) with a batch size of 64 for 10 epochs and
took about 8 h for a typical model. The Adam optimizer was used with a learning rate of 0.0001. The
optimization was framed as Poisson regression with loss function $\sum_{M,T}(\widehat{R} - R \log(\widehat{R}))$, where R is
the recorded neural activity, $\widehat{R}$ is the network output, M is the number of units, and T is the number
of time bins.

Validation

For each animal, data were split into training and test sets (see *Speech* above). The training set was
used to learn the optimal values of the DNN parameters. The final performance of the optimized
network was measured on the test set by calculating the percent of the explainable variance in the
recorded responses that was explained by the network outputs as the ratio of the covariance between
R_{test1} and $\widehat{R}$ and the covariance between R_{test1} and R_{test2}, where $\widehat{R}$ is the network output and R_{test1}
and R_{test2} are the recorded responses to the two presentations of the test speech.

Analysis of bottleneck activations

For each animal, the activations in the bottleneck layer for all sounds from a given class (e.g., all
pure tones or all consonants in noise) were extracted to form the $D_b \ x \ T$ signal dynamics matrix X,
where D_b is the number of bottleneck channels and T is the number of time bins. For visualization,
we applied PCA to the dynamics in X and projected them onto a chosen number of PCs.

Sounds presented to trained DNNs

(1) Pure tones: 100 ms tones with frequencies ranging from 500 Hz to 8000 Hz in 0.2 octave steps;
intensities ranging from 25 dB SPL to 100 dB SPL in 5 dB steps; 10 ms cosine on and off ramps;
and a 100 ms pause between tones.

(2a) SAM noise, fixed modulation depth: 100 ms bursts of bandpass noise with cutoff frequencies of
500 and 8000 Hz; a sinusoidal envelope with frequencies ranging from 10 Hz to 240 Hz in 10 Hz
steps and a modulation depth of 1; intensities ranging from 25 dB SPL to 100 dB SPL in 5 dB steps;
10 ms cosine on and off ramps; and a 100 ms pause between tones.

(2b) SAM noise, fixed modulation frequency: 100 ms bursts of bandpass noise with cutoff frequencies
of 500 and 8000 Hz; a sinusoidal envelope with a modulation depth ranging from 0.1 to 1 in 20
logarithmic steps and a frequency of 30 Hz; intensities ranging from 25 dB SPL to 100 dB SPL in 5
dB steps; 10 ms cosine on and off ramps; and a 100 ms pause between tones.

(3) Isolated consonants: Speech utterances were taken from the Articulation Index LSCP (LDC
Catalog No.: LDC2015S12). Utterances were from 10 American English speakers (5 male, 5 female).
Each speaker pronounced consonant-vowel syllables made from all possible combinations of 22
consonants and 13 vowels. For each utterance, the border between the consonant and vowel was
identified in a semi-automated manner (a clustering algorithm (Matlab *linkage*) was applied to the
spectrogram time bins to identify two clusters based on a correlation metric and the border between

them was inspected and corrected if needed), values after the end of the consonant were set to zero, and the utterance was truncated to 200 ms. Utterances were presented in random order with a 175 ms pause between sounds at intensities ranging from 25 dB SPL to 100 dB SPL in 5 dB steps.

(4) Multi-talker speech babble noise: Continuous speech from 16 different British English speakers from the UCL Scribe database (https://www.phon.ucl.ac.uk/resource/scribe) was summed to create speech babble. The intensity of the babble was set based on the intensity of the isolated consonants to achieve a speech-to-noise ratio of 3 dB.

(5a) Narrowband target: 100 ms bursts of bandpass noise with center frequencies ranging from 500 Hz to 8000 Hz in 0.5 octave steps and a bandwidth of 0.5 octaves; a sinusoidal envelope with a modulation depth of 1 and a frequency of 20 Hz; intensities ranging from 25 dB SPL to 100 dB SPL in 5 dB steps; 10 ms cosine on and off ramps; and a 100 ms pause between tones.

(5b) Narrowband noise: 100 ms bursts of bandpass noise with center frequencies ranging from 500 Hz to 8000 Hz in 0.5 octave steps and a bandwidth of 0.5 octaves; a pink noise envelope (power scaled as inverse of frequency) with a modulation depth ((peak – trough) / peak) of 1; an intensity matched to that of the narrowband target; 10 ms cosine on and off ramps; and a 100 ms pause between tones.

Hearing aid simulation

A 10-channel wide-dynamic range compression hearing aid was simulated using a program provided by Prof. Johsua Alexander (Purdue University)[24]. The crossover frequencies between channels were 200, 500, 1000, 1750, 2750, 4000, 5500, 7000, and 8500 Hz. The intensity thresholds below which amplification was linear for each channel were 45, 43, 40, 38, 35, 33, 28, 30, 36, and 44 dB SPL. The attack and release times (the time constants of the changes in gain following an increase or decrease in the intensity of the incoming sound, respectively) for all channels were 5 and 40 ms, respectively. The gain and compression ratio for each channel were fit individually for each ear of each gerbil using the Cam2B.v2 software provided by Prof. Brian Moore (Cambridge University)[51]. The gain before compression typically ranged from 10 dB at low frequencies to 30 dB at high frequencies. The compression ratios typically ranged from 1 to 2.5, i.e. the increase in sound intensity required to elicit a 1 dB increase in the hearing output ranged from 1 dB to 2.5 dB when compression was engaged.

Representational similarity analysis

For each animal, the signal dynamics matrix X was reshaped to yield $\widetilde{X}$, an $S \; x \; (D_b \; x \; T_S)$ matrix, where S is the number of sounds from a given class and T_S is the number of times bins associated with an individual sound. An $S \; x \; S$ representational dissimilarity matrix (RDM) was formed, with each entry equal to one minus the correlation between a pair of rows in $\widetilde{X}$. To compute overall representational similarity, the upper triangular values (excluding the diagonal) from two $\widetilde{X}$ matrices were reshaped into vectors and the correlation between them was computed. For speech, dynamics were averaged across all instances of each consonant before RDMs were computed.

Canonical correlation analysis

To align two sets of signal dynamics, $U = XA$ and $V = YB$ were computed using QR factorization and singular value decomposition (Matlab *cannoncorr*), where X and Y are the matrices containing the original dynamics, A and B are the matrices containing the canonical components, and U and V

are the aligned dynamics. Overall similarity after alignment was computed as $\sum_{d=1}^{D_b} \rho(U_d, V_d) *$
$(\rho(\hat{X}_d, X)^2 + \rho(\hat{Y}_d, Y)^2)/2$ where U_d and V_d are the projections of X and Y onto the d^{th} pair of
canonical components, $\hat{X}_d = X * (a_d * (a_d^T a_d)^{-1} * a_d)$ and $\hat{Y}_d = Y * (b_d * (b_d^T b_d)^{-1} * b_d)$ are the
reconstructions of X and Y from the d^{th} pair of canonical components and ρ denotes point-by-point
correlation. To jointly align more than two sets of dynamics, multiway CCA was used[22] (Matlab
NoiseTools *nt_mcca*).

Decoding signal dynamics

For each animal, the signal dynamics matrix X was reshaped such that each row contained the
dynamics for one consonant instance. A support vector machine was trained (Matlab *fitcecoc*) to
identify consonants from signal dynamics with a max-wins voting strategy based on all possible
combinations of binary classifiers and 10-fold cross validation.

767 Acknowledgements

768 This work was supported by a Wellcome Trust Senior Research Fellowship [200942/Z/16/Z]. The
769 authors thank A. de Cheveigné, S. Ostojic, J. Á. Gallego, and F. Bruford for their advice.

770 Competing interests

771 N. A. L. is a co-founder of Perceptual Technologies.

772 References

1. Wilson, B. S., Tucci, D. L., Merson, M. H. & O'Donoghue, G. M. Global hearing health care:
new findings and perspectives. *The Lancet* **390**, 2503–2515 (2017).

2. World Health Organization. *World report on hearing*. (2021).

3. Lesica, N. A. Why Do Hearing Aids Fail to Restore Normal Auditory Perception? *Trends*
Neurosci. **41**, 174–185 (2018).

4. Moore, B. C. J. *Cochlear Hearing Loss: Physiological, Psychological and Technical Issues.*
(John Wiley & Sons, 2007).

5. Larson, V. D. *et al.* Efficacy of 3 commonly used hearing aid circuits: A crossover trial.
NIDCD/VA Hearing Aid Clinical Trial Group. *JAMA* **284**, 1806–1813 (2000).

6. Young, E. D. Neural representation of spectral and temporal information in speech. *Philos.*
Trans. R. Soc. B Biol. Sci. **363**, 923–945 (2008).

7. Miller, R. L., Schilling, J. R., Franck, K. R. & Young, E. D. Effects of acoustic trauma on the
representation of the vowel /ɛ/ in cat auditory nerve fibers. *J. Acoust. Soc. Am.* **101**, 3602–3616
(1997).

8. Henry, K. S., Kale, S. & Heinz, M. G. Distorted Tonotopic Coding of Temporal Envelope and
Fine Structure with Noise-Induced Hearing Loss. *J. Neurosci.* **36**, 2227–2237 (2016).

9. Humes, L. E. & Dubno, J. R. Factors Affecting Speech Understanding in Older Adults. in *The*
Aging Auditory System (eds. Gordon-Salant, S., Frisina, R. D., Popper, A. N. & Fay, R. R.)
211–257 (Springer New York, 2010). doi:10.1007/978-1-4419-0993-0_8.

10. Plomp Reinier. A Signal-to-Noise Ratio Model for the Speech-Reception Threshold of the
Hearing Impaired. *J. Speech Lang. Hear. Res.* **29**, 146–154 (1986).

11. Armstrong, A. G., Lam, C. C., Sabesan, S. & Lesica, N. A. Compression and amplification
algorithms in hearing aids impair the selectivity of neural responses to speech. *Nat. Biomed.*
Eng. **6**, 717–730 (2022).

12. Mitchell-Heggs, R., Prado, S., Gava, G. P., Go, M. A. & Schultz, S. R. Neural manifold analysis
of brain circuit dynamics in health and disease. Preprint at
https://doi.org/10.48550/arXiv.2203.11874 (2022).

13. Williamson, R. C., Doiron, B., Smith, M. A. & Yu, B. M. Bridging large-scale neuronal
recordings and large-scale network models using dimensionality reduction. *Curr. Opin.*
Neurobiol. **55**, 40–47 (2019).

14. Garcia-Lazaro, J. A., Belliveau, L. A. C. & Lesica, N. A. Independent population coding of
speech with sub-millisecond precision. *J. Neurosci.* **33**, 19362–19372 (2013).

15. Garofolo, John S. *et al.* TIMIT Acoustic-Phonetic Continuous Speech Corpus. 715776 KB
(1993) doi:10.35111/17GK-BN40.

16. Armstrong, A. G., Lam, C. C., Sabesan, S. & Lesica, N. A. Compression and amplification
algorithms in hearing aids impair the selectivity of neural responses to speech. *Nat. Biomed.*
Eng. 1–14 (2021) doi:10.1038/s41551-021-00707-y.

17. Suberman, T. A. *et al.* A Gerbil Model of Sloping Sensorineural Hearing Loss. *Otol. Neurotol.*
32, 544–552 (2011).

18. Barsz, K., Wilson, W. W. & Walton, J. P. Reorganization of receptive fields following hearing
loss in inferior colliculus neurons. *Neuroscience* **147**, 532–545 (2007).

19. Willott, J. F. Effects of aging, hearing loss, and anatomical location on thresholds of inferior
colliculus neurons in C57BL/6 and CBA mice. *J. Neurophysiol.* **56**, 391–408 (1986).

20. Kriegeskorte, N., Mur, M. & Bandettini, P. A. Representational similarity analysis - connecting
the branches of systems neuroscience. *Front. Syst. Neurosci.* **2**, (2008).

21. Dabagia, M., Kording, K. P. & Dyer, E. L. Comparing high-dimensional neural recordings by
aligning their low-dimensional latent representations. Preprint at
https://doi.org/10.48550/arXiv.2205.08413 (2022).

22. de Cheveigné, A. *et al.* Multiway canonical correlation analysis of brain data. *NeuroImage* **186**,
728–740 (2019).

23. Fogerty, D., Kewley-Port, D. & Humes, L. E. The relative importance of consonant and vowel
segments to the recognition of words and sentences: Effects of age and hearing loss. *J.*
Acoust. Soc. Am. **132**, 1667–1678 (2012).

24. Alexander, J. M. & Masterson, K. Effects of WDRC release time and number of channels on
output SNR and speech recognition. *Ear Hear.* **36**, e35-49 (2015).

25. Christensen, J. H., Saunders, G. H., Porsbo, M. & Pontoppidan, N. H. The everyday acoustic
environment and its association with human heart rate: evidence from real-world data logging
with hearing aids and wearables. *R. Soc. Open Sci.* **8**, 201345.

26. Parida, S. & Heinz, M. G. Distorted Tonotopy Severely Degrades Neural Representations of
Connected Speech in Noise following Acoustic Trauma. *J. Neurosci.* **42**, 1477–1490 (2022).

27. Brons, I., Houben, R. & Dreschler, W. A. Effects of noise reduction on speech intelligibility,
perceived listening effort, and personal preference in hearing-impaired listeners. *Trends Hear.*
18, (2014).

28. Cox, R. M., Johnson, J. A. & Xu, J. Impact of advanced hearing aid technology on speech
understanding for older listeners with mild to moderate, adult-onset, sensorineural hearing loss.
Gerontology **60**, 557–568 (2014).

29. Wang, D. Deep learning reinvents the hearing aid. *IEEE Spectr.* **54**, 32–37 (2017).

30. Geirnaert, S. *et al.* Electroencephalography-Based Auditory Attention Decoding: Toward
Neurosteered Hearing Devices. *IEEE Signal Process. Mag.* **38**, 89–102 (2021).

31. Drakopoulos, F. & Verhulst, S. A Differentiable Optimisation Framework for The Design of
Individualised DNN-based Hearing-Aid Strategies. in *ICASSP 2022-2022 IEEE International
Conference on Acoustics, Speech and Signal Processing (ICASSP)* 351–355 (IEEE, 2022).

32. Madsen, S. M. K. & Moore, B. C. J. Music and hearing aids. *Trends Hear.* **18**, (2014).

33. Saremi, A. *et al.* A comparative study of seven human cochlear filter models. *J. Acoust. Soc.
Am.* **140**, 1618–1634 (2016).

34. Verhulst, S., Altoè, A. & Vasilkov, V. Computational modeling of the human auditory periphery:
Auditory-nerve responses, evoked potentials and hearing loss. *Hear. Res.* **360**, 55–75 (2018).

35. Williamson, R. S., Ahrens, M. B., Linden, J. F. & Sahani, M. Input-Specific Gain Modulation by
Local Sensory Context Shapes Cortical and Thalamic Responses to Complex Sounds. *Neuron*
91, 467–481 (2016).

36. Rahman, M., Willmore, B. D. B., King, A. J. & Harper, N. S. Simple transformations capture
auditory input to cortex. *Proc. Natl. Acad. Sci.* **117**, 28442–28451 (2020).

37. McFarland, J. M., Cui, Y. & Butts, D. A. Inferring Nonlinear Neuronal Computation Based on
Physiologically Plausible Inputs. *PLOS Comput. Biol.* **9**, e1003143 (2013).

38. Vintch, B., Movshon, J. A. & Simoncelli, E. P. A Convolutional Subunit Model for Neuronal
Responses in Macaque V1. *J. Neurosci.* **35**, 14829–14841 (2015).

39. Baby, D., Van Den Broucke, A. & Verhulst, S. A convolutional neural-network model of human
cochlear mechanics and filter tuning for real-time applications. *Nat. Mach. Intell.* 1–10 (2021)
doi:10.1038/s42256-020-00286-8.

40. Maheswaranathan, N. *et al.* The dynamic neural code of the retina for natural scenes. *bioRxiv*
340943 (2019) doi:10.1101/340943.

41. Cadena, S. A. *et al.* Deep convolutional models improve predictions of macaque V1 responses
to natural images. *PLOS Comput. Biol.* **15**, e1006897 (2019).

42. Walker, E. Y. *et al.* Inception loops discover what excites neurons most using deep predictive
models. *Nat. Neurosci.* **22**, 2060–2065 (2019).

43. Bashivan, P., Kar, K. & DiCarlo, J. J. Neural population control via deep image synthesis.
Science **364**, (2019).

44. Keshishian, M. *et al.* Estimating and interpreting nonlinear receptive field of sensory neural
responses with deep neural network models. *eLife* **9**, e53445 (2020).

45. Kell, A. J. E., Yamins, D. L. K., Shook, E. N., Norman-Haignere, S. V. & McDermott, J. H. A
Task-Optimized Neural Network Replicates Human Auditory Behavior, Predicts Brain
Responses, and Reveals a Cortical Processing Hierarchy. *Neuron* **98**, 630-644.e16 (2018).

46. Jazayeri, M. & Ostojic, S. Interpreting neural computations by examining intrinsic and
embedding dimensionality of neural activity. *Curr. Opin. Neurobiol.* **70**, 113–120 (2021).

47. Chung, S. & Abbott, L. F. Neural population geometry: An approach for understanding
biological and artificial neural networks. *Curr. Opin. Neurobiol.* **70**, 137–144 (2021).

48. Polonenko, M. J. & Maddox, R. K. The Parallel Auditory Brainstem Response. *Trends Hear.*
23, 2331216519871395 (2019).

49. Reddy, C. K. A. *et al.* A scalable noisy speech dataset and online subjective test framework.
arXiv:1909.08050 (2019).

50. Ravanelli, M. & Bengio, Y. Speaker Recognition from Raw Waveform with SincNet.
arXiv:1808.00158 (2019).

51. Moore, B. C. J., Glasberg, B. R. & Stone, M. A. Development of a new method for deriving
initial fittings for hearing aids with multi-channel compression: CAMEQ2-HF. *Int. J. Audiol.* **49**,
216–227 (2010).

Auditory brainstem responses

a Normal hearing example   Hearing loss example

b ABR thresholds

c Hearing aid gain

Figure S1: Sloping mild-to-moderate sensorineural hearing loss