A simple approach for image-based modelling of the heart that enables robust simulation of highly heterogeneous electrical excitation.

Michael A Colman & Alan P Benson

School of Biomedical Sciences, Faculty of Biological Sciences, University of Leeds, UK

Abstract

Remodelling of cardiac tissue structure, including intercellular electrical coupling, is a major determinant of the complex and heterogeneous excitation patterns associated with cardiac arrhythmias. Evaluation of the precise mechanisms by which local tissue structure determines global arrhythmic excitation patterns is a major challenge that may be critically important for the development of effective treatment strategies. Computational modelling is a key tool in the study of cardiac arrhythmias, yet the established approaches for organ-scale modelling are unsuitable to capture the impact of local conduction heterogeneities; a novel approach is required to provide this multi-scale mechanistic insight.

We present a fundamentally simple yet powerful approach to simulate electrical excitation in highly heterogeneous whole-heart models that exploits the underlying discreteness of the myocardium. Preliminary simulations demonstrate that this approach can capture lower conduction velocities and reproduce wave breakdown and the development of re-entry in conditions where the established approaches cannot.

1   Introduction

Cardiac arrhythmias are a major cause of morbidity and mortality associated with cardiovascular disease (CVD). Loss of the regular rhythm of the heart can substantially reduce cardiac output, detrimentally affecting the delivery of oxygen and nutrients to the vital organs of the body. Acute arrhythmia events can be fatal and, indeed, sudden cardiac death accounts for a substantial proportion of mortalities associated with CVD[1].

Electrical and structural remodelling occur over the progression of multiple CVDs and it is well established that this generally promotes both the initiation and sustenance of arrhythmia[2,3]. Recent studies have highlighted the mechanistic role by which structural remodelling promotes arrhythmia: conduction heterogeneity contributes to unidirectional conduction block and enables the development of sustained re-entrant circuits[4,5]. However, due to the conflict in spatial scales required to simultaneously resolve local conduction while maintaining the global picture of whole-heart activation, it is a major challenge to fully dissect and elucidate the precise mechanisms by which intercellular coupling and microstructure determine arrhythmia dynamics.

Multi-scale computational modelling has proved an invaluable tool for elucidation of the complex mechanisms underlying arrhythmia; such insight can help to drive novel pharmacological and surgical interventions to prevent, manage, or treat CVD in a diverse population[6–8]. The two most commonly used numerical methods for simulation of organ-scale cardiac electrophysiology are the finite difference method (FDM) and the finite element method (FEM), referring to different mathematical approaches to discretise the mono- or bi-domain reaction-diffusion equations which describe spatial diffusion of electrical or chemical activity[9]. Both of these approaches, however, are limited in their ability to capture the discrete underlying details of electrical coupling between myocytes, and are furthermore not well-suited to modelling the impact of locally heterogeneous conduction associated with structural remodelling, including the proliferation of fibrosis.

Recently, cellular-scale tissue models have been developed which describe intercellular coupling to a much greater level of sophistication[10–13], accounting for the influence of intra- and extracellular spaces, dynamic gap-junction conductance, and the potential role of ephaptic coupling. However, large-scale, whole-chamber image-based models of the heart are computationally intractable to perform at cellular-scale resolutions, and it is not trivial to extend these approaches to the whole-heart scale. There is therefore a strong motivation to develop an approach to discretise image-based tissue models that readily facilitates highly heterogeneous conduction properties and is compatible with these more sophisticated models of electrical coupling. Such a model would offer the possibility to reveal new insight into the mechanisms of cardiac (dys)function and develop ever more accurate models of the heart, including for genuine subject specificity (for example, in patient specific clinical models). Here, we present a fundamentally simple yet powerful network model to achieve this goal. This manuscript will discuss the derivation of the approach and perform demonstration simulations that illustrate how it may be used to model heterogeneous conduction conditions.

2   Results

2.1   Connection maps in 2D and 3D

The presented approach creates a network of axial and transverse inter-nodal connections which
are weighted based on local myocyte orientation on a 2D or 3D structured grid tissue geometry (**Fig.**
1a,c). These weightings determine the magnitude of the nodal conductance values that contribute
to the junctional conductance value at each network connection (**Fig. 1b**). Weighted network
connections are illustrated for three idealised cases (with different, global orientation directions) in
a 2D sheet (**Fig. 2a - left**). It is worth noting that when the orientation points either exactly along the
axis or diagonal, the junctional conductance in that direction is exactly equal to the axial
conductance (g_a) and the transverse coupling is applied also only in one direction (perpendicular);
in these special cases, only two directions have a non-zero weighting (one axial and one transverse;
Fig 2a).

Inter-nodal connections are further illustrated in 2D for the more complex condition with a spatially
varying myocyte orientation vector field (**Fig. 2a - right**) in both control (all connections preserved)
and remodelling (a set proportion of axial and transverse cellular connections have been removed.)
It is worth explaining the patterns that are observed in the cellular connections, for clarity of
interpretation of how the model works. If the orientation points exactly in x, the x-component of the
nodal conductance, g_{xx}^{node}, will be exactly equal to g_a (the axial weight, $W_{xx} = 1$, and transverse
weight, $W_{xx}^{t} = 0$), g_{yy}^{node} will be exactly equal to g_t ($W_{yy} = 0$; $W_{yy}^{t} = 1$) and there will be no diagonal
connections ($W_{xy++} = W_{xy+-} = 0$). As the orientation is rotated towards the diagonal, the axial weight
for the x direction will linearly reduce from 1 to 0 (while the weight for the diagonal linearly increases
from 0 to 1) and the transverse weight for the y direction also linearly reduces from 1 to 0. Thus,
exactly at the diagonal, g_{xx}^{node} and g_{yy}^{node} are 0 for both axial and transverse. As the orientation is
rotated further towards y, the transverse weight for x increases from 0 to 1 along with the axial
weight for y. Thus, g_{xx}^{node} is smallest when the orientation points towards the diagonal, increases to
g_t as the orientation rotates towards y, and increases to g_a as the orientation rotates towards x.

Connection maps are shown for two 3D geometrical models: a human ventricular wedge[14] where
only the myocyte orientation was given (and so the two transverse directions were calculated within
the model; **Fig. 2b**), and a full reconstruction of rat bi-ventricular geometry[8] wherein all three
orientations describing cardiac tissue structure (myocyte, sheet, and sheet normal, corresponding
to the three DT-MRI eigenvectors) were given (Online Supplement **Fig. S5**).

2.2   Verification of conduction patterns and comparison to FDM

The network model was parameterised to match FDM implementations regarding axial and
transverse conduction velocity (see "Methods: Cellular dynamics and model parameters"). There
were some notable differences in the conduction patterns in 2D and 3D between the two
implementations (**Fig. 3**), but the overall patterns and activation time match well, and it is not
necessarily the case that FDM represents a "ground truth". Note that the spatial pattern in both
methods when the orientation is diagonal is not an identical symmetrically rotated version of the
pattern when the orientation is in-axis. This is discussed further in the **Online Supplement**.

2.3   Conduction patterns in heterogeneous media

The impact of removing cellular connections at defined probability thresholds was demonstrated
using a 2D model, implementing the heterogeneous vector field illustrated in **Fig. 2a**, across total
spatial extents of 50×50 nodes and 200×200 nodes, enabling direct relation to visualised
connection maps (**Fig. 4** and **Supplementary Videos 1 and 2**). Removing axial and transverse
connections caused different spatial patterns of activation to emerge which clearly corresponded
to the differential loss of connections in these directions. Non-uniformity in the propagating
wavefront was observed in all conditions where cellular connections were removed. Patterns in
media with sampled distributions of scale factors (rather than the binary choice of
preserved/removed) are shown in the **Online Supplement Fig. S6**.

Preliminary simulations implementing heterogeneously removed cellular connections revealed that
these conditions were sufficient to promote wavefront breakup (**Fig. 5a**), which, in combination with
rapid pacing, could lead to the development of re-entry (not observed with a parameter-matched
global reduction to intercellular coupling in FDM; **Fig. 5b** and **Supplementary Videos 3 and 4**). It
should be clarified that the regimes shown in these cases correspond to a substantial loss of
connections and thus slow global conduction velocities and activation times, and this is reflected in
square-like waves in the FDM implementation.

3   Discussion

3.1   Summary

We have presented a novel approach to construct a network model to describe cardiac intercellular
electrical coupling on structured-grid geometries. The approach calculates coupling weights
between adjacent nodes based on the local myocyte orientation (**Figs. 1-2**). We have demonstrated
that this approach leads to expected conduction patterns in idealised and non-idealised tissue (**Figs.**
3-5). We have further demonstrated that this approach readily facilitates the direct manipulation of
intercellular connections (**Fig. 2**), enabling complex conduction patterns to be simulated, such as
observed with high levels of fibrosis. The model conserves current, is highly stable to complex
media, and naturally accounts for boundary conditions.

3.2   Value of the model

Of the established approaches, FDM is the simplest but has limits regarding numerical stability in
highly heterogeneous or anisotropic conditions; FEM is more complex and robust but is similarly
not well-suited to modelling interrupted cellular connections. Neither model satisfactorily
reproduces very slow conducting re-entrant circuits[15]. One possible explanation for why these
established methods are unsuitable for simulation of these features is that they are derived from a
mathematical discretisation of a spatially continuous system of equations, yet cardiac tissue is
inherently discrete at a sufficiently large spatial scale (that of the myocyte: 10-100 μm) that this
discreteness may be important for dynamics. Our new approach exploits this underlying
discreteness in its fundamental philosophy, presenting advantages over these previous methods in
computational efficiency, simplicity, numerical stability (and consequent ability to solve with simple
numerical methods), and mass conservation. However, the main advantages, and primary
motivation for the development of the model, are as follows:

(i) the ability to directly modify or remove cellular connections, resulting in representation of barriers
to conduction between excitable regions.

(ii) compatibility with the more sophisticated models of intercellular electrical coupling[10,12,13,16],
including models of dynamic, voltage-gated gap-junction conductance.

Implementation of the model readily enables direct replacement of previous implementations using
FDM (the same geometrical and myocyte orientation reconstructions can be used, and conduction
parameters easily matched). For this purpose, the model is made available open-source in two
different packages: i) packaged with the Multi-scale cardiac simulation framework[17] and ii) in a
simplified, single-file implementation in C++ to be extracted and used in any context. Tools to
generate heterogeneous connection maps are also provided with the code, all available at
http://physicsoftheheart.com/downloads.html and https://github.com/michaelcolman/.

3.3   Comparison to previous models of fibrosis

Previous tissue simulations have typically represented fibrosis through a reduction of the diffusion
coefficient and increase in the anisotropy ratio[18,19], reflecting the slower overall conduction velocities
and longer activation times associated with fibrosis and structural remodelling. This is generally
applied homogeneously (i.e., the diffusion coefficient is reduced globally in all fibrosis regions) but
may be applied according to spatial gradient maps[19]. Our approach does not rely on changes to the
coupling strength, but instead reproduces reduced coupling by removing individual intercellular
connections. A change in the anisotropy ratio consequentially arises if axial and transverse
connections were differentially removed (**Fig. 4**).

Example simulations demonstrated that removing cellular connections can produce complex,
heterogeneous, and highly anisotropic conduction patterns which may degenerate into arrhythmic
dynamics; longer activation times and slower average conduction velocities were reproduced but
with a distinct underlying pattern to a simple global reduction in intercellular coupling (**Fig. 5**). The
importance of this feature is highlighted by considering conduction patterns in low coupling
regimes: the FDM method produces unphysiological square-like waves, whereas the new approach
captures the same overall reduction in activation time but with highly heterogeneous underlying
wavefronts. Importantly, re-entry could emerge from regular rapid pacing, rather than requiring a
well-timed S1-S2 stimulus or other complex protocol, more closely reproducing ex vivo and in vivo
experiments[20,21]. Due to the importance of electrotonic interactions on the generation of
phenomena such as alternans[22,23] and afterdepolarisations[17,24], it may be critically important in
disease models to accurately capture the underlying coupling substrate, rather than implement a
simple global reduction to cellular coupling.

Alternatively, other studies have modelled fibrosis by setting selected nodes to be unexcitable[25],
which introduces conduction heterogeneity more comparable to that presented in this study. Our
approach enables conduction barriers to be captured without the need to remove nodes of tissue
from being excitable. This, importantly, can promote temporary unidirectional conduction block
which is a key mechanistic pathway for the generation of re-entrant circuits[26,27]. It is worth noting
that many studies have further included electrotonic coupling between fibroblasts and myocytes in
their descriptions of fibrosis[18,28,29]. This was not considered in the present study but is independent
from the discretisation method and thus trivial to include, if desired, in future studies.

3.4   Comparison to other non-FDM or FEM approaches

Recent studies have presented alternatives to the established approaches for discretising cardiac tissue and solving the propagation of electrical excitation, many focusing on small tissue strands/slices at cellular-scale resolutions. Most directly comparable to our approach, network models of electrical coupling have been previously presented[25,30,31]. However, these models were not designed to implement complex anisotropy and are not directly set up for the modification of individual cellular (or nodal) connections, as in our approach.

At the cellular-scale, multiple recent studies have developed sophisticated models that describe intercellular electrical coupling to varying levels of detail. Some have explicitly described the time- and voltage-dependence of the gap junctional conductance, demonstrating these dynamic properties to be an important regulator of electrical conduction and repolarisation[13,16]. Jæger et al.[10] presented a sophisticated model of intercellular coupling at the individual myocyte scale that accounts for the three domains of the extra-cellular, intra-cellular and membrane spaces. Such an approach enabled simulation of "micro-re-entry", which cannot be reproduced using larger scale discretisations. Other studies have developed approaches that account for ephaptic coupling, in which ion channels localised to the intercalated discs play an important mechanistic role in electrical coupling[11,12]. These studies have demonstrated important dynamical implications for the features that were included, highlighting the disparity between cellular-scale and larger-scale tissue simulations. Translation of these models to the whole-heart scale is non-trivial, and there are many features that would need to be carefully considered (e.g., the relationship between coupling strength and discretisation spatial step; see "Limitations and further work" below). Nevertheless, compared to FDM and FEM, our new approach presents much greater compatibility with these more complex, dynamically regulated models: coupling is solved on the connection, not the node, and the gap-junction conductance of each connection is an explicit parameter which can be easily modified through the inclusion of gating variables, and extended to account for the conductivities in the different cellular/extracellular domains.

Very few studies have attempted to include these finer details of electrical coupling at the whole-heart scale. In Hurtado et al., (2020)[32], non-linear homogenization theory was used to develop an up-scalable approximation of gap junctions that does not require explicit description of the underlying dynamics; in Saliani et al., (2022)[33], a non-ohmic model of intercellular coupling was developed that was applied to a cable-based geometrical model, and included interruptions to intercellular coupling similar to our study. Both approaches offer powerful and complex alternatives to the established models of cardiac intercellular coupling. Our model represents a different philosophy based on simplicity and broad applicability; the ability to easily implement the model on structured grid geometries was a major motivation. It would be valuable in future studies to compare these different models and their resulting dynamics across a range of physiological and pathophysiological conditions.

3.5   Limitations and further work

Whereas this method is based on "intercellular connections", the connection between nodes in a discretised geometry does not directly correspond to individual myocyte connections, as each node/voxel occupies a volume that contains multiple myocytes. This limitation is not unique to our new approach and applies to any tissue implementation that is not at the direct cellular scale. However, this does imply that modifying "intercellular connections" at this scale is not directly

translatable to heterogeneous connections at the individual myocyte level. Nevertheless, it still
enables implementation of functional barriers to conduction without requiring excitable nodes to be
removed, which we argue is a more accurate representation of the underlying substrate. To further
bridge this gap, future studies could develop high-throughput image analysis approaches to derive
this model from local, high-resolution histological data (e.g., describing connexin expression and
fibrosis) further to the whole-heart data for which it has been designed, and appropriate
approximations could be developed in simulations to match models at different scales.

A further limitation, albeit another not specific to this model but rather of most approaches to
modelling spatial coupling, is that the absolute coupling strength between two nodes is dependent
on the spatial resolution such that a set conduction velocity can be matched. However, electrotonic
coupling between myocytes in *reality* is clearly not dependent on the spatial resolution of a
geometrical model, and this may have important implications on dynamics: electrotonic coupling
affects cellular action potential morphology, including the rapid upstroke and the potential
emergence of after depolarisations. Potential solutions to this limitation will be considered in future
works.

Finally, there is a choice of how to treat mixed connections in the model (where one node
contributes an axial but the other a transverse connection), and it is not clear which approach would
be the most accurate. For example, a mixed connection would be observed at an abrupt change in
fibre orientation, where the axial conductance of one node is coupled to the transverse of its
neighbour. As presented in this study, the junctional conductance was simply an average of the two
contributing conductances, independent of which type of connection they were. One could just as
easily make a choice to model such junctions as either fully axial (axial connection only contributes
to the junctional conductance) or fully transverse. This is a choice which could be carefully explored
in future studies.

3.6 Conclusion

We have presented a simple alternative formulation to the reaction-diffusion equation which sums
over gap junctional currents rather than discretising the continuous gradients. Whereas the model
shares superficial similarities with FDM implementations, it also contains a fundamentally different
underlying approach which presents advantages. Most notable is the ability to directly control
intercellular connections, and suitability for integration with more sophisticated models of
intercellular coupling mechanisms. These features enable more accurate and robust simulations of
cardiac tissue to be performed, opening new avenues for the elucidation of underlying arrhythmia
mechanisms.

4 Acknowledgements

257 The authors would like to thank Dr. Dominic Whittaker for helpful conversations during the early
258 development of the approach, and Dr. Enric Alvarez Lacalle and Prof. Arun Holden for providing
259 useful feedback on early versions of the manuscript.

5　Funding

This work was supported by a Medical Research Council, UK, Strategic Skills Fellowship (grant no. MR/M014967/1) and Career Development Award (grant no. MR/V010050/1) awarded to MC, and a British Heart Foundation Project Grant (grant no. PG/16/74/32374) awarded to APB.

6　References

1.　Virani, S. S. *et al.* Heart Disease and Stroke Statistics—2021 Update. *Circulation* **143**, e254–e743 (2021).

2.　Dhein, S. *et al.* Remodeling of cardiac passive electrical properties and susceptibility to ventricular and atrial arrhythmias. *Front. Physiol.* **5**, (2014).

3.　Han, B., Trew, M. L. & Zgierski-Johnston, C. M. Cardiac Conduction Velocity, Remodeling and Arrhythmogenesis. *Cells* **10**, 2923 (2021).

4.　Benoist, D. *et al.* Systems approach to the study of stretch and arrhythmias in right ventricular failure induced in rats by monocrotaline. *Prog. Biophys. Mol. Biol.* **115**, 162–172 (2014).

5.　Prabhu, S. *et al.* Biatrial Electrical and Structural Atrial Changes in Heart Failure. *JACC Clin. Electrophysiol.* **4**, 87–96 (2018).

6.　Lamata, P. *et al.* Images as drivers of progress in cardiac computational modelling. *Prog. Biophys. Mol. Biol.* **115**, 198–212 (2014).

7.　Vadakkumpadan, F. *et al.* Image-based models of cardiac structure with applications in arrhythmia and defibrillation studies. *J. Electrocardiol.* **42**, 157.e1-157.e10 (2009).

8.   Whittaker, D. G., Benson, A. P., Teh, I., Schneider, J. E. & Colman, M. A. Investigation of the Role

of Myocyte Orientations in Cardiac Arrhythmia Using Image-Based Models. *Biophys. J.* **117**,

2396–2408 (2019).

9.   Benson, A. P., Stevenson-Cocks, H. J., Whittaker, D. G., White, E. & Colman, M. A. Multi-scale

approaches for the simulation of cardiac electrophysiology: II − Tissue-level structure and

function. *Methods* **185**, 60–81 (2021).

10. Jæger, K. H., Edwards, A. G., Giles, W. R. & Tveito, A. From Millimeters to Micrometers; Re-

introducing Myocytes in Models of Cardiac Electrophysiology. *Front. Physiol.* **12**, 763584

(2021).

11. Ly, C. & Weinberg, S. H. Automaticity in ventricular myocyte cell pairs with ephaptic and gap

junction coupling. *Chaos Interdiscip. J. Nonlinear Sci.* **32**, 033123 (2022).

12. Weinberg, S. H. Ephaptic coupling rescues conduction failure in weakly coupled cardiac tissue

with voltage-gated gap junctions. *Chaos Interdiscip. J. Nonlinear Sci.* **27**, 093908 (2017).

13. Bragard, J. *et al.* Conductance heterogeneities induced by multistability in the dynamics of

coupled cardiac gap junctions. *Chaos Interdiscip. J. Nonlinear Sci.* **31**, 073144 (2021).

14. Benson, A. P., Halley, G., Li, P., Tong, W. C. & Holden, A. V. Virtual cell and tissue dynamics of

ectopic activation of the ventricles. *Chaos Woodbury N* **17**, 015105 (2007).

15. Campos, F. O. *et al.* Factors Promoting Conduction Slowing as Substrates for Block and

Reentry in Infarcted Hearts. *Biophys. J.* **117**, 2361–2374 (2019).

16. Hawks, C. *et al.* Gap Junction Dynamics Induces Localized Conductance Bistability in Cardiac

Tissue. *Int. J. Bifurc. Chaos* **29**, 1930021 (2019).

17. Colman, M. A. Arrhythmia mechanisms and spontaneous calcium release: Bi-directional

coupling between re-entrant and focal excitation. *PLOS Comput. Biol.* **15**, e1007260 (2019).

18. Morgan, R., Colman, M. A., Chubb, H., Seemann, G. & Aslanidi, O. V. Slow Conduction in the

Border Zones of Patchy Fibrosis Stabilizes the Drivers for Atrial Fibrillation: Insights from Multi-

Scale Human Atrial Modeling. *Front. Physiol.* **7**, (2016).

19. Clayton, R. H. Dispersion of Recovery and Vulnerability to Re-entry in a Model of Human Atrial

Tissue With Simulated Diffuse and Focal Patterns of Fibrosis. *Front. Physiol.* **9**, (2018).

20. Asano, Y., Davidenko, J. M., Baxter, W. T., Gray, R. A. & Jalife, J. Optical Mapping of Drug-

Induced Polymorphic Arrhythmias and Torsade de Pointes in the Isolated Rabbit Heart. *J. Am.*

Coll. Cardiol. **29**, 831–842 (1997).

21. O'Shea, C. *et al.* High resolution optical mapping of cardiac electrophysiology in pre-clinical

models. *Sci. Data* **9**, 135 (2022).

22. Colman, M. A. The Multiple Mechanisms of Spatially Discordant Alternans in the Heart.

Biophys. J. **118**, 2336–2338 (2020).

23. Huang, C., Song, Z., Landaw, J. & Qu, Z. Spatially Discordant Repolarization Alternans in the

Absence of Conduction Velocity Restitution. *Biophys. J.* **118**, 2574–2587 (2020).

24. Alexander, C. *et al.* Initiation of ventricular arrhythmia in the acquired long QT syndrome.

Cardiovasc. Res. cvac103 (2022) doi:10.1093/cvr/cvac103.

25. Vandersickel, N. *et al.* Dynamical anchoring of distant arrhythmia sources by fibrotic regions via

restructuring of the activation pattern. *PLOS Comput. Biol.* **14**, e1006637 (2018).

26. Quan, W. & Rudy, Y. Unidirectional block and reentry of cardiac excitation: a model study. *Circ.*

Res. **66**, 367–382 (1990).

27. Colman, M. A. *et al.* Pro-arrhythmogenic effects of atrial fibrillation-induced electrical

remodelling: insights from the three-dimensional virtual human atria. *J. Physiol.* **591**, 4249–

4272 (2013).

28. MacCannell, K. A. *et al.* A mathematical model of electrotonic interactions between ventricular

myocytes and fibroblasts. *Biophys. J.* **92**, 4121–4132 (2007).

29. Bazhutina, A. *et al.* Mathematical modelling of the mechano-electric coupling in the human

cardiomyocyte electrically connected with fibroblasts. *Prog. Biophys. Mol. Biol.* **159**, 46–57

(2021).

30. Kazbanov, I. V., ten Tusscher, K. H. W. J. & Panfilov, A. V. Effects of Heterogeneous Diffuse

Fibrosis on Arrhythmia Dynamics and Mechanism. *Sci. Rep.* **6**, 20835 (2016).

31. Ten Tusscher, K. H. W. J. & Panfilov, A. V. Influence of diffuse fibrosis on wave propagation in

human ventricular tissue. *EP Eur.* **9**, vi38–vi45 (2007).

32. Hurtado, D. E., Jilberto, J. & Panasenko, G. Non-ohmic tissue conduction in cardiac

electrophysiology: Upscaling the non-linear voltage-dependent conductance of gap junctions.

PLOS Comput. Biol. **16**, e1007232 (2020).

33. Saliani, A., Biswas, S. & Jacquemet, V. Simulation of atrial fibrillation in a non-ohmic propagation

model with dynamic gap junctions. *Chaos Interdiscip. J. Nonlinear Sci.* **32**, 043113 (2022).

34. Kléber, A. G. & Jin, Q. Coupling between cardiac cells—An important determinant of electrical

impulse propagation and arrhythmogenesis. *Biophys. Rev.* **2**, 031301 (2021).

35. LeGrice, I. J. *et al.* Laminar structure of the heart: ventricular myocyte arrangement and

connective tissue architecture in the dog. *Am. J. Physiol.* **269**, H571-582 (1995).

36. Helm, P. A., Tseng, H.-J., Younes, L., McVeigh, E. R. & Winslow, R. L. Ex vivo 3D diffusion tensor

imaging and quantification of cardiac laminar structure. *Magn. Reson. Med.* **54**, 850−859

(2005).

37. Holmes, A. A., Scollan, D. F. & Winslow, R. L. Direct histological validation of diffusion tensor

MRI in formaldehyde-fixed myocardium. *Magn. Reson. Med.* **44**, 157−161 (2000).

38. Hsu, E. W., Muzikant, A. L., Matulevicius, S. A., Penland, R. C. & Henriquez, C. S. Magnetic

resonance myocardial fiber-orientation mapping with direct histological correlation. *Am. J.*

Physiol. **274**, H1627-1634 (1998).

39. Scollan, D. F., Holmes, A., Winslow, R. & Forder, J. Histological validation of myocardial

microstructure obtained from diffusion tensor magnetic resonance imaging. *Am. J. Physiol.*

275, H2308-2318 (1998).

40. Tseng, W.-Y. I., Wedeen, V. J., Reese, T. G., Smith, R. N. & Halpern, E. F. Diffusion tensor MRI

of myocardial fibers and sheets: correspondence with visible cut-face texture. *J. Magn. Reson.*

Imaging JMRI **17**, 31−42 (2003).

Figures

358
359

360
361   ***Figure 1. Summary of model approach.*** ***a*** *– illustration of the different coupling directions and terminology referring to*
362   *these directions, in 2D (left) and 3D (right).* ***b*** *- illustration of how the nodal and junctional conductance parameters are*
363   *related and contribute to the total gap junctional conductance, for three nodes i, j, and k and two junctions n and m.* ***c*** *-*
364   *illustration of the relationship between myocyte orientation angle and the weighting terms towards the axis and diagonal*
365   *within a segment (2D) and towards the axis, in-plane diagonal, elevation diagonal, and corner in a quadrant (3D).*

366
Figure 2. Illustration of weighted network connection maps. a - *illustration of the connection maps in 2D for idealised*
cases with a global myocyte orientation in three different directions (left) and in the case of a spatially varying orientation
field (right) for both control (g_a and g_t are spatially homogeneous; upper) and in a case where 20% of axial and 80% of
transverse connections have been randomly removed (lower). Global orientation maps are illustrated on a 10x10 grid for
clarity in visualisation. **b** - *Illustration of directional condutances in a 3D human ventricular wedge model. Myocyte*
orientation streamlines are shown to provide context, with colour corresponding to either the z- or x-component
(dependent on the view), along with the magnitude of the connection for each direction. The anisotropy ratio is 4:1 (i.e., g_a
= $4g_t$). Note that, for clarity of visualisation, the junctional conductances defined in equations (37-39) have not been scaled
by the 1/Δx etc factors, in order to normalise between axis and diagonal conductances.

376
377

Figure 3. Comparison between activation patterns in parameter matched FDM and network model simulations in 2D with different global orientations (fully in x, exactly in xy^{++}), and in the heterogeneous vector field shown in Fig 2, as well as in the 3D ventricular wedge model. Simulations with global orientation direction were performed on a 300×300 grid at a spatial resolution of $\Delta x = 0.25$ mm with coupling parameters of D1 = 0.4 mm/ms and D2 = 0.1 mm/ms (FDM method) and $g_a = 1.6$ nS/pF and $g_t = 0.4$ nS/pF (network model). Simulations using the vector field for myocyte orientation were performed on a 200×200 grid at a spatial resolution of $\Delta x = 0.2$ mm with coupling parameters of D1 = 0.2 mm/ms and D2 = 0.05 mm/ms (FDM method) and $g_a = 0.8$ nS/pF and $g_t = 0.2$ nS/pF (network model). Simulations on the 3D human ventricular wedge were performed at a spatial resolution of $\Delta x = \Delta y = 0.2125$ mm and $\Delta z = 0.25$ mm with coupling parameters of D1 = 0.1171 mm/ms and D2 = 0.0130 mm/ms (FDM method) and $g_a = 0.55$ nS/pF and $g_t = 0.061$ nS/pF (network model).

Figure 4. Conduction patterns in different connection-removal conditions. a – *Connection maps and activation patterns in a 50×50 grid, where the pattern can be somewhat directly visually related to the connection maps. Control refers to the condition where all connections are present, and the bottom row is the condition where 20% of the axial and 80% of the transverse connections are randomly removed. **b** – connection maps and conduction patterns in four different conditions (control and cases where 50%-50%, 20%-80% and 80%-20% axial-transverse connections have been removed) in a 200×200 grid, where direct visual relation to the connection map is more difficult, but the tissue has sufficient area to permit a reasonable activation time.*

Figure 5. Illustration of wave-break and re-entry occurring in the network model with reduced connections. a – *Voltage snapshots and activation pattern in the 2D model with the same vector orientation field as previous figures, paced from one edge of the tissue.* **b** – *Voltage snapshots in two different pacing scenarios (edge pacing for 5 stimuli, upper, and centre focal pacing for 2 stimuli, lower) on the same model as* **a**. *Sites of conduction block and wave propagation direction are labelled for clarity.*

7 Methods

7.1 Overall approach

Cardiac myocytes are electrically coupled through intercalated discs which are connections between cells that contain gap junctions enabling intercellular flow of ionic currents[34]. Myocytes are elongated in structure (with a length approximately five-to-ten times their diameter) and gap junctions are preferentially located at the longitudinal (or axial) connections, forming fibre-like strands of coupled myocytes. Coupling is also observed in the direction perpendicular to myocyte orientation but is less than in the axial direction, and the conduction velocity in the axial direction is typically at least twice that in the transverse direction[2]. This feature of differentiated axial and transverse intercellular coupling − and the ability to interrupt them individually - underlies the philosophy our proposed novel approach.

The approach operates on a structured gird of nodes i.e., a square (2D) or cuboid (3D) lattice. This represents the simplest discrete reconstruction of cardiac images, as opposed to an unstructured gird comprised of polygonal elements and vertices, and corresponds to the same system on which the FDM approach is applied. In this system, we present the inherently discrete equation governing the voltage differential for some node, i

$$\frac{dV^i}{dt} = \frac{1}{C_m}\left(\sum_n I_{gap}^{(i,n)} - I_{ion}^i\right) \tag{1}$$

Where $I_{gap}^{(i,n)}$ is the current associated with gap junction n that is connected to node i, and the sum over n corresponds to all junctions associated with node i (in 2D this is a sum of up to eight junctions; in 3D it is a sum of up to 26 junctions). It is common to absorb the membrane capacitance, C_m, into the formulation of the ionic currents, through the definition of the maximal conductances in units of nS/pF. The same will be applied here for the conductance of the gap junctions, and so equation (1) simplifies to:

$$\frac{dV^i}{dt} = \sum_n I_{gap}^{(i,n)} - I_{ion}^i \tag{2}$$

The junctional current for some junction, n, between two adjacent nodes, i and j, is defined by:

$$I_{gap}^n = g_{gap}^n\left(V_m^i - V_m^j\right) \tag{3}$$

Where g_{gap}^n is the conductance of gap junction n. The gap junctional current for the nodes i and j, the term that contributes to the sum in equations (1) and (2), is therefore given by:

$$I_{gap}^{(i,n)} = -I_{gap}^n \tag{4}$$

$$I_{gap}^{(j,n)} = I_{gap}^n \tag{5}$$

Note that we use the terms "gap junction", "junctional current" and "junctional conductance"
broadly here, as they may not correspond to individual gap junctions between individual *myocytes,*
but rather the connections between *nodes*. Moreover, this approach is not a formulation of gap
junctional dynamics itself, and the conductance of the junction will be assumed to be constant (i.e.,
not voltage- or time-dependent). Rather, we present a method to discretise the tissue model in order
to determine the magnitude of this gap junctional conductance between neighbouring nodes based
on local myocyte orientation.

We must now determine how nodes are connected to form junctions, and how to derive the gap
junctional conductance, g_{gap}^n based on local myocyte orientation. Throughout the remainder of the
methods section for brevity, only the minimum number of equations necessary to understand the
construction of the model will be shown, exploiting symmetries (e.g., x-directions will be shown but
not the symmetric y and z equivalents); full equations are provided in the Online Supplement.

7.2   Derivation of the approach in 2D

7.2.1   Axial and transverse connections

In a 2D structured grid, each node can be connected to eight other nodes, corresponding to four
along the axes ($\pm x$, $\pm y$) and four along the diagonals ($\pm xy^{++}$, $\pm xy^{+-}$) (**Fig. 1a**). Due to the different
directions along each of these lines being indifferent (+x is the same as -x), this reduces to four
independent connection directions: x, y, xy^{++} and xy^{+-}. Note that xy^{++} refers to the diagonal where the
sign on x and y is identical (+x and +y, or -x and -y) and xy^{+-} to the diagonal where the signs are
different.

The main concept of this approach is that, for each node, the contribution to the connection to its
neighbours in each of these directions will be determined from weighting terms defined by the local
myocyte orientation. Defining g_a as the conductance of a gap junction in the axial direction (along
the primary myocyte orientation) and g_t as the conductance of a gap junction in the transverse
direction (i.e., orthogonal to the primary myocyte orientation), the nodal junctional conductance in
each direction (g_{ei}^{node}) can be described as:

$$g_{xx}^{node} = \frac{1}{\Delta x}\left(g_a.W_{xx} + g_t.W_{xx}^t\right) \tag{6}$$

$$g_{xy^{++}}^{node} = \frac{1}{\sqrt{\Delta x^2 + \Delta y^2}}\left(g_a.W_{xy^{++}} + g_t.W_{xy^{++}}^t\right) \tag{7}$$

And similarly for the y and xy^{+-} directions (Online Supplement), where g_{xx}^{node} is the contribution of
the node to the gap junctional conductances in the x-direction, and equivalently for all other
directions, W_{xx} is the weight towards the x-axis for the axial component, W_{xx}^t is the weight towards
the x-axis for the transverse component (and equivalent for all other directions), and Δx and Δy refer
to the discretisation space step in each dimension and are included from geometrical arguments.
Due to considerations regarding the relationship between coupling strength and the spatial step
(see Discussion), it may also be desirable to define these conductances independent of the spatial
steps. In this case, it is important to retain the factor of $1/\sqrt{2}$ in the diagonal terms, or otherwise
account for the increased distance in the diagonal directions, for geometrical consistency.

7.2.2   Defining the junction conductance and currents

Before describing how the weighting terms are derived, it is important to relate the nodal
conductances (equations 6-7) to the junctional conductance in equation (3). A junction is formed
between all pairs of nodes which correspond to tissue, adjacent to each-other in any of the coupling
directions. For some junction, n, the conductance, g_{gap}^n in equation (3), is given by the mean of the
nodal conductances in the direction in which they are coupled (**Fig. 1b**). For example, for two nodes,
i and j, adjacent to each-other in the x-direction, forming a junction n

478
$$g_{gap}^n = \frac{g_{xx}^i + g_{xx}^j}{2}$$
(8)

479   And equivalently for all other directions in which nodes may be coupled. There is no distinction here
480   whether the connection is axial or transverse, so mixed connections (e.g., at an abrupt change in
481   fibre) are possible. Every time a junction is created, maps must be created (for implementation
482   purposes) defining which node is the positive and which is the negative contributor to this junction

483
$$jn\_map^+(n) = i$$
(9)

484
$$jn\_map^-(n) = j$$
(10)

485   The gap junctional current for junction n, equation (3), is therefore:

486
$$I_{gap}^n = g_{gap}^n \left(V_m^i - V_m^j\right) = g_{gap}^n \left(V_m^{Jn\_map^+(n)} - V_m^{Jn\_map^-(n)}\right)$$
(11)

And these junctional currents are summed for each node as described in equations (2, 4 and 5).

7.2.3   Deriving the weights based on myocyte orientation

The weights that scale the contribution of the axial and transverse gap junctional conductances to
each nodal directional conductance term (equations 6-7) must be defined. The myocyte orientation
in 2D will always point in a segment between one axis and one diagonal direction (**Extended Data**
Fig. 1). Due to periodicities and symmetries in the trigonometric functions, we can consider and
calculate the weight towards the axis and diagonal independent of in which segment the orientation
is pointing. We can first calculate the angle from the x-axis, θ:

495
$$\theta = \sin^{-1}\left(\left\|Oy\right\| \middle/ \sqrt{Ox^2 + Oy^2}\right)$$
(12)

496   where Ox is the x-component of the normalised orientation vector, and Oy is the y-component. This
497   will always return an angle between 0 rad (when the orientation is along the x axis) and π/2 rad
498   (when the orientation is along the y axis). We can then define a weight which linearly depends on
499   this angle as a measure of where the orientation lies between the x or y axis (θ = 0 or π/2 rad,
500   respectively) and the diagonal (θ = π/4 rad):

501
$$W_{axis} = \left\| \left(\theta - \frac{\pi}{4} \right) \middle/ \frac{\pi}{4} \right\|$$
(13)

502   i.e., W_{axis} is equal to 1 if the orientation points exactly along either the x or y axis ($\theta = 0$ or $\pi/2$ rad,
503   respectively), equal to 0 if it points exactly along the diagonal ($\theta = \pi/4$ rad), and linearly varies
504   between 0 and 1 based on the angle in-between (**Extended Data Fig. 1**). The weight towards the
505   diagonal is then simply:

506
$$W_{diagonal} = 1 - W_{axis}$$
(14)

507   A conditional algorithm could then be applied to determine to which axis and diagonal the weighting
508   terms should be applied. Alternatively, and perhaps more concisely, these choices can be absorbed
509   into a single general equation through the introduction of binary pointing parameters. Thus, we may
510   define:

511
$$P_x = \left. \begin{array}{c} 1 \\ 0 \end{array} \right\} \begin{array}{c} x^2 \geq y^2 \\ y^2 > x^2 \end{array}$$
(15)

512
$$P_{xy^+} = \left. \begin{array}{c} 1 \\ 0 \end{array} \right\} \begin{array}{c} xy \geq 0 \\ xy < 0 \end{array}$$
(16)

513   where P_x is a binary parameter which is equal to 1 if the orientation vector points between the x-axis
514   and either diagonal and equals zero otherwise; P_{xy+} is equal to 1 if the orientation points between
515   the diagonal xy^{++} and either axis. Note that P_y and P_{xy-} could also be introduced, defined as 1-P_x and
516   1-P_{xy+}, respectively. From this, the weighting towards the four directions is then given by:

517
$$W_{xx} = P_x W_{axis}$$
(17)

518
$$W_{xy^{++}} = P_{xy^+} W_{diagonal}$$
(18)

This approach can be illustrated by considering some simple example cases (Fig 1D).

7.2.4   Transverse direction

A major feature of this approach is to apply the transverse coupling always at an orthogonal
direction to the myocyte orientation (**Extended Data Fig. 1**), as opposed to FDM, for example, where
the basic isotropic coupling is always applied along the axes, independent of the myocyte
orientation. In 2D the transverse weights are trivial to calculate:

525
$$W_{xx}^t = (1 - P_x) W_{axis} = P_y W_{axis}$$
(19)

526
$$W_{xy^{++}} = \left(1 - P_{xy^+} \right) W_{diagonal} = P_{xy^-} W_{diagonal}$$
(20)

527   Which are the same as equations (17-19) with the pointing parameters swapped.

7.3   Derivation of the approach in 3D

7.3.1   Primary myocyte orientation weights in 3D

In 3D each node can be connected to 26 neighbours (i.e., 13 independent directions given the +/-
directional indifference), corresponding to the axes and diagonals in each plane and the four corners
(**Fig. 1a**). The primary myocyte orientation vector therefore points in a segment which corresponds
to a quadrant on the surface of a cube, i.e., contributing towards the weight of up to four directions
at once (**Fig. 1c**). Similar to the approach in 2D, we can consider how the weights towards these four
directions depend on the angle(s), independent of which axes and diagonals define the quadrant.
The four directions (**Fig. 1c**) correspond to the axis, the in-plane diagonal (dependent on θ_1), the
elevation diagonal (dependent on θ_2) and the corner (dependent on both θ_1 and θ_2). Note that both
θ_1 and θ_2 are defined as the projection in the axis planes i.e., θ_2 does not correspond to the spherical
polar coordinate's elevation angle. We can then define the weight towards each of these directions
as (**Fig. 1c**):

$$W_{axis} = W_{axis}^{plane}.W_{axis}^{elevation} \tag{21}$$

$$W_{diag\_plane} = \left(1 - W_{axis}^{plane}\right).W_{axis}^{elevation} \tag{22}$$

$$W_{diag\_elevation} = W_{axis}^{plane}.\left(1 - W_{axis}^{elevation}\right) \tag{23}$$

$$W_{corner} = \left(1 - W_{axis}^{plane}\right).\left(1 - W_{axis}^{elevation}\right) \tag{24}$$

545   where W_{axis}^{plane} and $W_{axis}^{elevation}$ are defined from the two angles, θ_1 and θ_2, in the same way as the 2D
546   model (dependent on which axes contribute to these calculations). The three angles (θ_{xy}, θ_{xz}, θ_{yz})
547   and corresponding weights (W_{axis}^{xy}, W_{axis}^{xz}, W_{axis}^{yz}) in each plane are defined by:

$$\theta_{xy} = \sin^{-1}\left(\left.\left|Oy\right|\middle/\sqrt{Ox^2 + Oy^2}\right.\right) \tag{25}$$

$$W_{axis}^{xy} = \left.\left|\left(\theta_{xy} - \frac{\pi}{4}\right)\middle/\frac{\pi}{4}\right.\right| \tag{26}$$

550   and the pointing parameters in 3D become:

$$P_x = \left.\begin{cases} 1 \\ 0 \end{cases}\right\} \begin{array}{l} x^2 \geq y^2 \,\&\, x^2 \geq z^2 \\ \quad otherwise \end{array} \tag{27}$$

552
$$P_{xy^+} = \left. \begin{array}{c} 1 \\ 0 \end{array} \right\} \begin{array}{c} xy \geq 0 \\ xy < 0 \end{array} \tag{28}$$

553 And similarly for the y- and z-directions (**Online Supplement**). Note that only one of P_x, P_y and P_z can
554 be non-zero at any time (the orientation can only be pointing primarily towards one of these axes).
555 P_{xy+}, P_{xz+} and P_{yz+} can all be non-zero. In full, therefore, the weights towards the four quadrant
556 directions are given by:

557
$$W_{axis} = P_x.W_{axis}^{xy}.W_{axis}^{xz} + P_y.W_{axis}^{xy}.W_{axis}^{yz} + P_z.W_{axis}^{xz}.W_{axis}^{yz} \tag{29}$$

558
$$W_{diag\_plane} = P_x.\left(1-W_{axis}^{xy}\right).W_{axis}^{xz} + P_y.\left(1-W_{axis}^{xy}\right).W_{axis}^{yz} + P_z.\left(1-W_{axis}^{xz}\right).W_{axis}^{yz} \tag{30}$$

559
$$W_{diag\_elevation} = P_x.W_{axis}^{xy}.\left(1-W_{axis}^{xz}\right) + P_y.W_{axis}^{xy}.\left(1-W_{axis}^{yz}\right) + P_z.W_{axis}^{xz}.\left(1-W_{axis}^{yz}\right) \tag{31}$$

560
$$W_{corner} = P_x.\left(1-W_{axis}^{xy}\right).\left(1-W_{axis}^{xz}\right) + P_y.\left(1-W_{axis}^{xy}\right).\left(1-W_{axis}^{yz}\right) + P_z.\left(1-W_{axis}^{xz}\right).\left(1-W_{axis}^{yz}\right) \tag{32}$$

561 Note that because only one of Px, Py and Pz can be non-zero at a time, these equations reduce
562 immediately to the equivalent of equations (23-26).

563 The weighting towards each direction is defined by:

564
$$W_{xx} = P_x.W_{axis} \tag{33}$$

565
$$W_{xy^{++}} = \left(P_x + P_y\right).P_{xy^+}.W_{diag\_plane} \tag{34}$$

566
$$W_{xz^{++}} = P_x.P_{xz^+}.W_{diag\_elevation} + P_z.P_{xz^+}.W_{diag\_plane} \tag{35}$$

567
$$W_{xyz^{+++}} = P_{xz^+}.P_{yz^+}.W_{corner} \tag{36}$$

And similarly for all other directions (**Online Supplement**). Note that the form of equation (36) results
from the convention that when pointing primarily towards z (P_z =1), the xz diagonal is considered "in
plane" and the yz diagonal considered the "elevation" direction, whereas when pointing towards x
or y, the xz and yz are both considered the elevation direction. This is an arbitrary choice, and the
results would be the same whichever choice is made. As with the 2D case, when the pointing
parameters are factored into these equations, only a maximum of four terms will result in being non-
zero: one axis, two diagonals, and one corner.

7.3.2 Transverse connections in 3D

In 3D, two transverse directions are necessary. These may correspond to the distinguishable "sheet"
and "sheet normal" directions[35] if these data describing the laminar/sheet structure of cardiac tissue
are available [e.g. from diffusion tensor MRI[36–40]] or to two indistinguishable (equal magnitude)
transverse directions if only myocyte orientation data are available (i.e. in the absence of data

describing the laminar/sheet architecture of cardiac tissue). The junctional conductance is therefore
given by:

$$g_{xx}^{node} = \frac{1}{\Delta x}\left(g_a.W_{xx} + g_{t1}.W_{xx}^{t1} + g_{t2}.W_{xx}^{t2}\right) \tag{37}$$

$$g_{xy^{++}}^{node} = \frac{1}{\sqrt{\Delta x^2 + \Delta y^2}}\left(g_a.W_{xy^{++}} + g_{t1}.W_{xy^{++}}^{t1} + g_{t2}.W_{xy^{++}}^{t2}\right) \tag{38}$$

$$g_{xyz^{+++}}^{node} = \frac{1}{\sqrt{\Delta x^2 + \Delta y^2 + \Delta z^2}}\left(g_a.W_{xyz^{+++}} + g_{t1}.W_{xyz^{+++}}^{t1} + g_{t2}.W_{xyz^{+++}}^{t2}\right) \tag{39}$$

585   And similarly for all other directions (**Online Supplement**). Similarly to the 2D case, if these are
586   defined independent of the spatial step, the factors of $1/\sqrt{2}$ and $1/\sqrt{3}$ must be retained for the
587   diagonal and corner directions, respectively. If differentiating between in-sheet and transverse to
588   sheet, then $g_{t1} > g_{t2}$, whereas if not imposing this distinction, $g_{t1} = g_{t2} = g_t$ and the equation(s) reduce
589   to:

$$g_{xx}^{node} = \frac{1}{\Delta x}\left(g_a.W_{xx} + g_t.\left(W_{xx}^{t1} + W_{xx}^{t2}\right)\right) \tag{40}$$

591   If implementation is based on three eigenvectors (e.g, from DTI), then the orientation components
592   of the two transverse vectors directly determine W_{ei}^{t1} and W_{ei}^{t2} for each direction through the same
593   equations (34-37) as the primary orientation vector (**Extended Data Fig. 1**). However, if only
594   information on the primary eigenvector is defined, then we must define the transverse vectors from
595   this (**Online Supplement**).

7.4   Implementing heterogeneous media

One main advantage, and indeed motivation for the development, of the above approach is to be
able to modify cellular connections directly. For example, connexins (gap junctions) are
heterogeneously expressed in tissue and may not exist between every adjacent myocyte. In disease
in particular, highly heterogeneous media may be observed, corresponding to heterogeneity in
connexin expression, or increased fibrosis. The latter may be associated with a loss of cellular
connectivity and changes to the anisotropy ratio of conduction velocity, implying differential loss of
transverse and axial connections.

Implementing these heterogeneities in this network model may be approached in different ways,
depending on the application. For example, a map can be passed in that simply scales local (nodal)
g_a and g_t, in the same way as one might do when using FDM. However, we can also scale the
junctions directly, or even remove them. In this study we demonstrate these different approaches
and their potential impact on function, although it should be clarified that we are not constructing
physiologically validated parameter combinations for different health and disease states but, rather,
demonstrating how this model may be applied in these contexts.

This approach readily facilitates differential removal of axial and transverse cellular connections.
One can define a threshold for each type of connection that determines the probability of a
connection being removed. It is important to identify if a connection is axial (the contribution from
both nodes is from the primary orientation vector), transverse (the contribution from both nodes is
from a transverse vector) or mixed (one node contributes an axial component and the other a
transverse). Once complete, random numbers can be generated and combined with the threshold
to determine which connections are removed. Alternatively, as a more sophisticated approach,
junctional conductance could be scaled by continuous factors, for example, randomly sampled from
various user-defined distributions or based on analysis of variability in experiment.

7.5 Cellular dynamics and model parameters

Example simulations presented in this study were performed using cellular electrophysiology
described by the hybrid minimal model presented in Colman (2019). This is a simple model
parameterised for the magnitudes of ionic currents and voltage range observed in cardiac electrical
excitation. It is useful and desirable to be able to define the connection parameter conductances (g_a
and g_t) from the diffusion coefficient, D, to enable easy implementation to replace FDM, or similar,
where D has been defined to match conduction velocity. A conversion factor can be obtained
through analysis of a simple case (**Online Supplement**), yielding:

628
$$g_a = \frac{D1}{\Delta x} \tag{41}$$

629
$$g_t = \frac{D2}{\Delta x} \tag{42}$$

630 As will be shown in results, this conversion gives the same conduction velocities as the FDM method
631 in these simple conditions. Note that this linear relationship means g_t can be defined from the
632 anisotropy ratio (AR) and g_a, in the same way as often for D1 and D2:

633
$$g_t = g_a / AR \tag{43}$$

In this setup, the units of g_a and g_t are the same as those for the maximal conductances of the ion
currents (nS/pF), as the membrane capacitance (C_m) in equation (1) has been absorbed into these
maximal conductance terms (equation 2). However, this model does not require this to be the case
and enables coupling between cells of different C_m while still conserving current; one could define
g_a as an absolute conductance (nS) and maintain inclusion of the factor C_m^{-1} when implementing
equation (1).

***Extended Data Fig 1. Illustration of pointing parameters and transverse connections. a** – illustration of the different values*
*the binary pointing parameters take dependent on in which segment the myocyte orientation points. **b** - Illustration of the*
*transverse orientation vectors and the directions to which they contribute in 3D. **Left** - illustration of the three orientation*
*vectors as given by imaging data; each vector points in a quadrant, contributing to up to four directions. **Right** – illustration*
of the definition of the two transverse vectors if only the primary eigenvector is given. From the axial orientation, a π/2
rotation is applied towards the z-axis to define transverse vector 1. The cross-product of these two vectors then defines
transverse vector 2, which will always point in the x-y plane.