Revealing unexpected complex encoding but simple decoding mechanisms in motor cortex via separating behaviorally relevant neural signals

Yangang Li[1,2,4], **Xinyun Zhu**[1,2,4], **Yu Qi**[3,4*], **Yueming Wang**[1,5*]

*For correspondence:
qiyu@zju.edu.cn (YQ);
ymingwang@zju.edu.cn (YW)

[1]Qiushi Academy for Advanced Studies, Zhejiang University, Hangzhou, China; [2]College of Computer Science and Technology, Zhejiang University, Hangzhou, China; [3]Affiliated Mental Health Center & Hangzhou Seventh People's Hospital and the MOE Frontier Science Center for Brain Science and Brain-machine Integration, Zhejiang University School of Medicine, Hangzhou, China; [4]The State Key Lab of Brain-Machine Intelligence, Zhejiang University, Hangzhou, China; [5]Zhejiang Brain-Computer Interface Institute, Hangzhou, China

Abstract   In motor cortex, behaviorally-relevant neural responses are entangled with irrelevant signals, which complicates the study of encoding and decoding mechanisms. It remains unclear whether behaviorally-irrelevant signals could conceal some critical truth. One solution is to accurately separate behaviorally-relevant and irrelevant signals, but this approach remains elusive due to the unknown ground truth of behaviorally-relevant signals. Therefore, we propose a framework to define, extract, and validate behaviorally-relevant signals. Analyzing separated signals in three monkeys performing different reaching tasks, we found neural responses previously considered useless encode rich behavioral information in complex nonlinear ways. These responses are critical for neuronal redundancy and reveal movement behaviors occupy a higher-dimensional neural space than previously expected. Surprisingly, when incorporating often-ignored neural dimensions, behavioral information can be decoded linearly as accurately as nonlinear decoding, suggesting linear readout is performed in motor cortex. Our findings prompt that separating behaviorally-relevant signals may help uncover more hidden cortical mechanisms.

Introduction

Understanding how motor cortex encodes and decodes movement behaviors is a fundamental goal of neuroscience (*Kriegeskorte and Douglas, 2019*; *Saxena and Cunningham, 2019*). Here, we define behaviors as behavioral variables of interest measured within a given task, such as arm kine-matics during a motor control task; we employ terms like 'behaviorally-relevant' and 'behaviorally-irrelevant' only regarding such measured behavioral variables. However, achieving this goal faces significant challenges because behaviorally-relevant neural responses are entangled with behaviorally-irrelevant factors such as responses for other variables of no interest (*Fusi et al., 2016*; *Rigotti et al.,*

2013) and ongoing noise (*Azouz and Gray, 1999*; *Faisal et al., 2008*). Generally, irrelevant signals would hinder the accurate investigation of the relationship between neural activity and movement behaviors. This raises concerns about whether irrelevant signals could conceal some critical facts about neural encoding and decoding mechanisms.

If the answer is yes, a natural question arises: what critical facts about neural encoding and decoding would irrelevant signals conceal? In terms of neural encoding, irrelevant signals may mask some small neural components, making their encoded information difficult to detect (*Moreno-Bote et al., 2014*), thereby misleading us to neglect the role of these signals, leading to a partial understanding of neural mechanisms. For example, at the single-neuron level, weakly-tuned neurons are often assumed useless and not analyzed (*Georgopoulos et al., 1986*; *Hochberg et al., 2012*; *Wodlinger et al., 2014*; *Inoue et al., 2018*); at the population level, neural signals composed of lower variance principal components (PCs) are typically treated as noise and discarded (*Churchland et al., 2012*; *Gallego et al., 2018*, *2020*; *Cunningham and Yu, 2014*). So are these ignored signals truly useless or appear that way only due to being covered by irrelevant signals? And what's the role of these ignored signals? In terms of neural decoding, irrelevant signals would significantly complicate the information readout (*Pitkow et al., 2015*; *Yang et al., 2021*), potentially hindering the discovery of the true readout mechanism of behaviorally-relevant responses. Specifically, in motor cortex, in what form (linear or nonlinear) downstream neurons read out behavioral information from neural responses is an open question. The linear readout is biologically plausible and widely used (*Georgopoulos et al., 1986*; *Hochberg et al., 2012*; *Wodlinger et al., 2014*), but recent studies (*Glaser et al., 2020*; *Willsey et al., 2022*) demonstrate nonlinear readout outperforms linear readout. So which readout scheme is more likely to be used by the motor cortex? Whether irrelevant signals are the culprits for the performance gap? Unfortunately, all the above issues remain unclear.

One approach to address the above issues is to accurately separate behaviorally-relevant and irrelevant signals at the single-neuron level and then analyze noise-free behaviorally-relevant signals, which enables us to gain a more accurate and comprehensive understanding of the underlying neural mechanisms. However, this approach is hampered by the fact that the ground truth of behaviorally-relevant signals is unknown, which makes the definition, extraction, and validation of behaviorally-relevant signals a challenging task. As a result, methods of accurate separation remain elusive to date. Existing methods for extracting behaviorally-relevant patterns mainly focus on the latent population level (*Churchland et al., 2012*; *Sani et al., 2021*; *Pandarinath et al., 2018*; *Hurwitz et al., 2021*; *Yu et al., 2008*; *Zhou and Wei, 2020*; *Keshtkaran et al., 2022*) rather than the single-neuron level, and they extract neural activities based on assumptions about specific neural properties, such as linear or nonlinear dynamics (*Sani et al., 2021*; *Pandarinath et al., 2018*). Although these methods have shown promising results, they fail to capture other parts of behaviorally-relevant neural activity that do not meet their assumptions, thereby providing an incomplete picture of behaviorally-relevant neural activity. To overcome these limitations and obtain accurate behaviorally-relevant signals at the single-neuron level, we propose a novel framework that defines, extracts, and validates behaviorally-relevant signals by simultaneously considering such signals' encoding (behaviorally-relevant signals should be similar to raw signals to preserve the underlying neuronal properties) and decoding (behaviorally-relevant signals should contain behavioral information as much as possible) properties (see Methods and Fig. 1). This framework establishes a prerequisite foundation for the subsequent detailed analysis of neural mechanisms.

Here, we conducted experiments using datasets recorded from the motor cortex of three monkeys performing different reaching tasks, where the behavioral variable is movement kinematics. After signal separation by our approach, we first explored how the presence of behaviorally-irrelevant signals affect the analysis of neural activity. We found that behaviorally-irrelevant signals account for a large amount of trial-to-trial neuronal variability, and are evenly distributed across the neural dimensions of behaviorally-relevant signals. Then we explored whether irrelevant signals conceal some facts of neural encoding and decoding. For neural encoding, irrelevant signals obscure the behavioral information encoded by neural responses, especially for neural responses

with a large degree of nonlinearity. Surprisingly, neural responses that are usually ignored (weakly-tuned neurons and neural signals composed of small variance PCs) actually encode rich behavioral information in complex nonlinear ways. These responses underpin an unprecedented neuronal redundancy and reveal that movement behaviors are distributed in a higher-dimensional neural space than previously thought. In addition, we found that the integration of smaller and larger variance PCs results in a synergistic effect, allowing the smaller variance PC signals that cannot be linearly decoded to significantly enhance the linear decoding performance, particularly for finer speed control. This finding suggests that lower variance PC signals are involved in regulating precise motor control. For neural decoding, irrelevant signals complicate information readout. Strikingly, when uncovering small neural components obscured by irrelevant signals, linear decoders can achieve comparable decoding performance with nonlinear decoders, providing strong evidence for the presence of linear readout in motor cortex. Together, our findings reveal unexpected complex encoding but simple decoding mechanisms in the motor cortex. Finally, our study also has implications for developing accurate and robust brain-machine interfaces (BMIs) and, more generally, provides a powerful framework for separating behaviorally-relevant and irrelevant signals, which can be applied to other cortical data to uncover more neural mechanisms masked by behaviorally-irrelevant signals.

Results

Framework for defining, extracting, and validating behaviorally-relevant neural signals

What are behaviorally-relevant neural signals?

Since the ground truth of behaviorally-relevant signals is unknown, the definition of behaviorally-relevant signals is not well established yet. In this study, we propose that behaviorally-relevant signals should meet two requirements: (1) they should be similar to raw signals in order to preserve the underlying neuronal properties (encoding requirement), and (2) they should contain behavioral information as much as possible (decoding requirement). If the signals meet both of these requirements, we consider them to be effective behaviorally-relevant signals.

How to extract behaviorally-relevant signals?

One way to extract behaviorally-relevant signals is to use a distillation model to generate them from raw signals while considering the remaining signals as behaviorally-irrelevant. That is, we assume raw signals (Fig. 1a) are additively composed of behaviorally-relevant (Fig. 1b) and irrelevant (Fig. 1d) signals. However, due to the unknown ground truth of behaviorally-relevant signals, a key challenge for the model is to determine the optimal degree of similarity between the generated signals and raw signals. If the generated signals are too similar to raw signals, they may contain a large amount of irrelevant information, which would hinder the exploration of neural mechanisms. Conversely, if the generated signals are too dissimilar to raw signals, they may lose behaviorally-relevant information, also hindering the exploration of neural mechanisms. To overcome this challenge, we exploited the trade-off between the similarity of generated signals to raw signals (encoding requirement) and their decoding performance of behaviors (decoding requirement) to extract effective behaviorally-relevant signals (for details, see Methods and Fig. S1). The core assumption of our model is that behaviorally-irrelevant signals are noise relative to behaviorally-relevant signals, and thereby irrelevant signals would degrade the decoding generalization of generated behaviorally-relevant signals. Generally, the distillation model is faced with three cases: a bias toward reconstructing raw signals (Fig. 1f), a bias toward decoding behaviors (Fig. 1g), and a proper trade-off between reconstruction and decoding (Fig. 1h). If the distillation model is biased toward extracting signals similar to raw signals, the distilled behaviorally-relevant signals will contain an excessive amount of behaviorally-irrelevant information, affecting the decoding generalization of these signals (Fig. 1f). If the model is biased toward extracting parsimonious signals that are dis-

Figure 1. Semantic illustration of extracting and validating behaviorally-relevant signals. a-e The ideal decomposition of raw signals. **a**, The temporal neuronal activity of raw signals, where x-axis denotes time, and y-axis represents firing rate. Raw signals are decomposed to relevant (**b**) and irrelevant (**d**) signals. The red dotted line indicates the decoding performance of raw signals. The red and blue bars represent the decoding performance of relevant and irrelevant signals. The purple bar represents the reconstruction performance of relevant signals, which measures the neural similarity between generated signals and raw signals. The longer the bar, the larger the performance. The ground truth of relevant signals decode information perfectly (**c**, red bar) and is similar to raw signals to some extent (**c**, purple bar), and the ground truth of irrelevant signals contain little behavioral information (**e**, blue bar). **f-h**, Three different cases of behaviorally-relevant signals distillation. **f**, When the model is biased toward generating relevant signals that are similar to raw signals, it will achieve high reconstruction performance, but the decoding performance will suffer due to the inclusion of too many irrelevant signals. As it is difficult for models to extract complete relevant signals, the residuals will also contain some behavioral information. **g**, When the model is biased toward generating signals that prioritize decoding over similarity to raw signals, it will achieve high decoding performance, but the reconstruction performance will be low. Meanwhile, the residuals will contain a significant amount of behavioral information. **h**, When the model balances the trade-off of decoding and reconstruction capabilities of relevant signals, both decoding and reconstruction performance will be good, and the residuals will only contain a little behavioral information.

Figure 2. Evaluation of separated signals. a, The obstacle avoidance paradigm **b**, The decoding R^2 between true velocity and predicted velocity of raw signals (purple bars with slash lines) and behaviorally-relevant signals obtained by d-VAE (red), PSID (pink), pi-VAE (green), TNDM (blue), and LFADS (light green) on dataset A. Error bars denote mean $\pm$ standard deviation (s.d.) across five cross-validation folds. Asterisks represent significance of Wilcoxon rank-sum test with $^*P < 0.05$, $^{**}P < 0.01$. **c**, Same as **b**, but for behaviorally-irrelevant signals obtained by five different methods. **d**, The neural similarity (R^2) between raw signals and behaviorally-relevant signals extracted by d-VAE, PSID, pi-VAE, TNDM, and LFADS. Error bars represent mean $\pm$ s.d. across five cross-validation folds. Asterisks indicate significance of Wilcoxon rank-sum test with $^{**}P < 0.01$. **e-h** and **i-l**, Same as **a-d**, but for dataset B with the center-out paradigm (**e**) and dataset C with the self-paced reaching paradigm (**i**). **m**, The firing rates of raw signals and distilled signals obtained by d-VAE in five held-out trials under the same condition of dataset B.

₁₃₇ criminative for decoding, the distilled signals will not be similar enough to raw signals, and some
₁₃₈ redundant but useful signals will be left in the residuals (Fig. 1g), making irrelevant signals con-
₁₃₉ tain much behavioral information. Using face recognition as an example, if a model can accurately
₁₄₀ identify an individual using only the person's eyes (assuming these are the most useful features),
₁₄₁ other useful information such as the nose or mouth will be left in the residuals, which could also
₁₄₂ be used to identify the individual. Neither of these two cases is desirable because the former loses
₁₄₃ decoding performance, while the latter loses some useful neural signals, which are not conducive
₁₄₄ to our subsequent analysis of the relationship between behaviorally-relevant signals and behav-
₁₄₅ iors. The behaviorally-relevant signals we want should be similar to raw signals and preserve the
₁₄₆ behavioral information maximally, which can be obtained by balancing the encoding and decoding
₁₄₇ properties of generated behaviorally-relevant signals (Fig. 1h).

How to validate behaviorally-relevant signals?

To validate the effectiveness of the distilled signals, we proposed three criteria. The first criterion
is that the decoding performance of the behaviorally-relevant signals (red bar, Fig.1) should sur-
pass that of raw signals (the red dotted line, Fig.1). Since decoding models, such as deep neural
networks, are more prone to overfit noisy raw signals than behaviorally-relevant signals, the dis-
tilled signals should demonstrate better decoding generalization than the raw signals. The second
criterion is that the behaviorally-irrelevant signals should contain minimal behavioral information
(blue bar, Fig.1). This criterion can assess whether the distilled signals maximally preserve behav-
ioral information from the opposite perspective and effectively exclude undesirable cases, such as
over-generated and under-generated signals. Specifically, in the case of over-generation, suppose
$z = x + y$, where z, x, and y represent raw, relevant, and irrelevant signals, respectively. If the dis-
tilled relevant signals $\hat{x}$ are added extra signals m which do not exist in the real behaviorally-relevant
signals, that is, $\hat{x} = x + m$, then the corresponding residuals $\hat{y}$ will be equal to the ideal irrelevant sig-
nals y plus the negative extra signals $-m$, namely, $\hat{y} = y - m$, thus the residuals $\hat{y}$ contain the amount
of information preserved by negative extra signals $-m$. Similarly, in the case of under-generation,
if the distilled behaviorally-relevant signals are incomplete and lose some useful information, this
lost information will also be reflected in the residuals. In these cases, the distilled signals are not
suitable for analysis. The third criterion is that the distilled behaviorally-relevant signals should
be similar to raw signals to maintain essential neuronal properties (purple bar, Fig.1). If the dis-
tilled signals do not resemble raw signals, they fail to retain the fundamental characteristics of raw
signals, which are not qualified for subsequent analysis. Overall, if the distilled signals satisfy the
above three criteria, we consider the distilled signals to be effective.

d-VAE extracts effective behaviorally-relevant signals

To demonstrate the effectiveness of our model (d-VAE) in extracting behaviorally-relevant signals,
we conducted experiments on the synthetic dataset where the ground truth of relevant and ir-
relevant signals are already known (see Methods) and three benchmark datasets with different
paradigms (Fig. 2a,e,i; see Methods for details), and compared d-VAE with four other distillation
models, including pi-VAE (*Zhou and Wei, 2020*), PSID (*Sani et al., 2021*), TNDM (*Hurwitz et al.,*
2021) and LFADS (*Pandarinath et al., 2018*). Specifically, we first applied these distillation mod-
els to raw signals to obtain the distilled behaviorally-relevant signals, considering the residuals as
behaviorally-irrelevant signals. We then evaluated the decoding R^2 between the predicted veloc-
ity and actual velocity of the two partition signals using a linear Kalman filter (KF) and a nonlinear
artificial neural network (ANN) and measured the neural similarity between behaviorally-relevant
and raw signals. Besides, we compared the decoding performance of behaviorally-relevant signals
extracted by d-VAE and behaviorally-relevant embeddings extracted by CEBRA (a non-generative
method which outperforms pi-VAE) (*Schneider et al., 2023*).

Overall, d-VAE successfully extracts effective behaviorally-relevant signals that meet the three
criteria outlined above on both synthetic (Supplementary Fig. S2) and real data (Fig. 2). On the
synthetic data (Supplementary Fig. S2), results show that d-VAE can strike an effective balance
between the reconstruction and decoding performance of generated signals to extract effective
relevant signals that are similar to the ground truth relevant signals, meanwhile removing effec-
tive irrelevant signals that resemble the ground truth irrelevant signals (Supplementary Fig. S2 a-g),
and outperforms other distillation models (Supplementary Fig. S2 h-k). On the real data, specifi-
cally in the obstacle avoidance task (Fig. 2a), the monkey is required to move the ball from the start
point (yellow) to the target point (blue) without hitting the obstacle. For the decoding performance
of behaviorally-relevant signals (Fig. 2b), the signals distilled by d-VAE outperform the raw signals
(purple bars with slash lines) and the signals distilled by all other distillation models (PSID, pink; pi-
VAE, green; TNDM, blue; and LFADS, light green) with the KF as well as the ANN. For the decoding
performance of behaviorally-irrelevant signals (Fig. 2c), behaviorally-irrelevant signals obtained by
d-VAE achieves the lowest decoding performance compared with behaviorally-irrelevant signals ob-

Figure 3. The effect of irrelevant signals on analyzing neural activity at the single-neuron level. a, The angle difference (AD) of preferred direction (PD) between raw and distilled signals as a function of the R^2 of raw signals on datasets A. When employing R^2 to characterize neurons, it indicates the extent to which neuronal activity is explained by the linear encoding model. Smaller R^2 neurons have a lower capacity for linearly tuning (encoding) behaviors, while larger R^2 neurons have a higher capacity for linearly tuning (encoding) behaviors. Each black point represents a neuron (n = 90). The red curve is the fitting curve between R^2 and AD. Five example larger R^2 neurons' PDs are shown in the inset plot, where the solid and dotted line arrows represent the PDs of relevant and raw signals, respectively. **b**, Comparison of the cosine tuning fit (R^2) before and after distillation of single neurons (black points), where the x-axis and y-axis represent neurons' R^2 of raw and distilled signals, respectively. **c**, Comparison of neurons' Fano factor (FF) averaged across conditions of raw (x-axis) and distilled (y-axis) signals, where FF is used to measure the neuronal variability of different trials in the same condition. **d**, Boxplots of raw (purple) and distilled (red) signals under different conditions for all neurons (12 conditions). Boxplots represent medians (lines), quartiles (boxes), and whiskers extending to ± 1.5 times the interquartile range. The broken lines represent the mean FF across all neurons. **e-h**, Same as **a-d**, but for dataset B (n=159, 8 conditions). **i**, Example of three neurons' raw firing activity decomposed into behaviorally-relevant and irrelevant parts using all trials under two conditions (2 of 8 directions) in held-out test sets of dataset B.

tained by other approaches. Therefore, the combination of dVAE's highest decoding performance
for behaviorally-relevant signals and lowest decoding performance for behaviorally-irrelevant sig-
nals demonstrate its superior ability to extract behaviorally-relevant signals from noisy signals.
For the neural similarity between behaviorally-relevant and raw signals (Fig. 2d), the distilled sig-
nals obtained by d-VAE achieve the highest performance among competitors ($P < 0.01$, Wilcoxon
rank-sum test). Similar results were obtained for the center-out task (Fig. 2e-h) and the self-paced
reaching task (Fig. 2i-l), indicating the consistency of d-VAE's distillation ability across a range of
motor tasks. To provide a more intuitive illustration of the similarity between raw and distilled
signals, we displayed the firing rate of neuronal activity in five trials under the same condition (Fig.
2m), and results clearly show that the firing pattern of distilled signals is similar to the correspond-
ing raw signals. Finally, we compared d-VAE with CEBRA on the four datasets; results show that
d-VAE achieves comparable performance with CEBRA using the ANN decoder but outperforms CE-
BRA with the KF decoder (Supplementary Fig. S3), demonstrating that d-VAE can effectively extract
behavioral information.

In summary, d-VAE distills effective behaviorally-relevant signals that preserve behavioral infor-
mation maximally and are similar to raw signals. Meanwhile, the behaviorally-irrelevant signals
discarded by d-VAE contain a little behavioral information. Therefore, these signals are reliable for
exploring the encoding and decoding mechanisms of relevant signals.

How do behaviorally-irrelevant signals affect the analysis of neural activity at the
single-neuron level?

Following signal separation, we first explored how behaviorally-irrelevant signals affect the analysis
of neural activity at the single-neuron level. Specifically, we examined the effect of irrelevant signals
on two critical properties of neuronal activity: the preferred direction (PD) (*Georgopoulos et al.,*
1986) and trial-to-trial variability. Our objective was to know how irrelevant signals affect the PD of
neurons and whether irrelevant signals contribute significantly to neuronal variability.

To explore how irrelevant signals affect the PD of neurons, we first calculated the PD of both
raw and distilled signals separately and then quantified the PD deviation by the angle difference be-
tween these two signals. Results show that the PD deviation increases as the neuronal R^2 (*Collinger*
et al., 2013; *Wodlinger et al., 2014*) decreases (red curve, Fig. 3a,e and Supplementary Fig. S4a);
neurons with larger R^2 (strongly linear-tuned neurons) exhibit stable PDs with signal distillation
(see example PDs in the inset), while neurons with smaller R^2s (weakly linear-tuned neurons) show
a larger PD deviation. These results indicate that irrelevant signals have a small effect on strongly-
tuned neurons but a large effect on weakly-tuned neurons. One possible reason for the larger PD
deviation in weakly-tuned neurons is that they have a lower degree of linear encoding but a higher
degree of nonlinear encoding, and highly nonlinear structures are more susceptible to interfer-
ence from irrelevant signals (*Nogueira et al., 2023*). Moreover, after filtering out the behaviorally-
irrelevant signals, the cosine tuning fit (R^2) of neurons increases ($P < 10^{-20}$, Wilcoxon signed-rank
test; Fig. 3b,f and Supplementary Fig. S4b), indicating that irrelevant signals reduce the neurons'
tuning expression. Notably, even after removing the interference of irrelevant signals, the R^2 of
neurons remains relatively low. These results demonstrate that the linear encoding model only ex-
plains a small fraction of neural responses, and neuronal activity encodes behavioral information
in complex nonlinear ways.

To investigate whether irrelevant signals significantly contribute to neuronal variability, we com-
pared the neuronal variability (measured with the Fano factor (*Churchland et al., 2010*), FF) of rel-
evant and raw signals. Results show that the condition-averaged FF of each neuron of distilled
signals is lower than that of raw signals ($P < 10^{-20}$, Wilcoxon signed-rank test; Fig. 3c,g), and the
mean (broken line) and median FFs of all neurons under different conditions are also significantly
lower than those of raw signals ($P < 0.01$, Wilcoxon signed-rank test; Fig. 3d,h), indicating that
irrelevant signals significantly contribute to neuronal variability. We then visualized the single-trial
neuronal activity of example neurons under different conditions (Fig. 3i and Supplementary Fig. S5).

Figure 4. The effect of irrelevant signals on analyzing neural activity at the population level. a,b, PCA is separately applied on relevant and irrelevant signals to get relevant PCs and irrelevant PCs. The thick lines represent the cumulative variance explained for the signals on which PCA has been performed, while the thin lines represent the variance explained by those PCs for other signals. Red, blue, and gray colors indicate relevant signals, irrelevant signals, and random Gaussian noise $\mathcal{N}(\mathbf{0}, \mathbf{I})$ (for chance level) where the mean vector is zero and the covariance matrix is the identity matrix. The horizontal lines represent the percentage of variance explained. The vertical lines indicate the number of dimensions accounted for 90% of the variance in behaviorally-relevant (left) and irrelevant (right) signals. For convenience, we defined the principal component subspace describing the top 90% variance as the primary subspace and the subspace capturing the last 10% variance as the secondary subspace. The cumulative variance explained for behaviorally-relevant (**a**) and irrelevant (**b**) signals got by d-VAE on dataset A. **c,d**, PCA is applied on raw signals to get raw PCs. **c**, The bar plot shows the composition of each raw PC. The inset pie plot shows the overall proportion of raw signals, where red, blue, and purple colors indicate relevant signals, irrelevant signals, and the correlation between relevant and relevant signals. The PC marked with a red triangle indicates the last PC where the variance of relevant signals is greater than or equal to that of irrelevant signals. **d**, The cumulative variance explained by raw PCs for different signals, where the thick line represents the cumulative variance explained for raw signals (purple), while the thin line represents the variance explained for relevant (red) and irrelevant (blue) signals. **e-h**, Same as **a-d**, but for dataset B.

Results demonstrate that the patterns of relevant signals are more consistent and stable across different trials than raw signals, and the firing activity of irrelevant signals varies randomly. These results indicate that irrelevant signals significantly contribute to neuronal variability, and eliminating the interference of irrelevant signals enables us observe the changes in neural pattern more accurately.

How do behaviorally-irrelevant signals affect the analysis of neural activity at the population level?

The neural population structure is an essential characteristic of neural activity. Here, we examined how behaviorally-irrelevant signals affect the analysis of neural activity at the population level, including four aspects: (1) the population properties of relevant and irrelevant signals, (2) the subspace overlap relationship between the two signal components, (3) how the two partitions contribute to raw signals, and (4) the difference in population properties between raw and distilled signals.

To explore the population properties of relevant and irrelevant signals, we separately applied

principal component analysis (PCA) on each partition to obtain the corresponding cumulative vari-
ance curve in a descending variance order. Our results show that the primary subspace (capturing
the top 90% variance) of relevant signals (thick red line, Fig.4a,e and Supplementary Fig. S6a) is
only explained by a few dimensions (7, 13, and 9 for each dataset), indicating that the primary part
of behaviorally-relevant signals exists in a low-dimensional subspace. In contrast, the primary sub-
space of irrelevant signals (thick blue line, Fig. 4b,f and Supplementary Fig. S6b) requires more
dimensions (46, 81, and 59). The variance distribution of behaviorally-irrelevant signals across
dimensions (thick blue line, Fig. 4b,f and Supplementary Fig. S6b) is more even than behaviorally-
relevant signals (thick red line, Fig. 4a,e and Supplementary Fig. S6a) but not as uniform as Gaus-
sian noise $\mathcal{N}(\mathbf{0}, \mathbf{I})$ (thin gray line, Fig.4b,f and Supplementary Fig. S6b), indicating that irrelevant
signals are not pure noise but rather bear some significant structure, which may represent infor-
mation from other irrelevant tasks.

To investigate the subspace overlap between relevant and irrelevant signals, we calculated how
many variances of irrelevant signals can be captured by relevant PCs by projecting irrelevant sig-
nals onto relevant PCs and vice versa (*Elsayed et al., 2016*; *Rouse and Schieber, 2018*; *Jiang et al.,*
2020)(see Methods). We found that the variance of irrelevant signals increases relatively uniformly
over relevant PCs (blue thin line, Fig. 4a,e and Supplementary Fig. S6a), like random noise's variance
accumulation explained by relevant PCs (gray thin line, Fig. 4a,e and Supplementary Fig. S6a); sim-
ilar results are observed for relevant signals explained by irrelevant PCs (red thin line, Fig. 4b,f and
Supplementary Fig. S6b). These results indicate that relevant PCs can not match the informative
dimensions of irrelevant signals and vice versa, suggesting the dimensions of behaviorally-relevant
and irrelevant signals are unrelated. It is worth mentioning that the signals obtained by pi-VAE are
in contrast to our findings. Its results show that a few relevant PCs can explain a considerable
variance of irrelevant signals (thin red line, Supplementary Fig. S7b,f,j), which indicates that the
relevant and irrelevant PCs are closely related. The possible reason is that the pi-VAE leaks a lot of
information into the irrelevant signals. Notably, Fig. 4a,e and Supplementary Fig. S6a show that ir-
relevant signals got by d-VAE projecting on behaviorally-relevant primary subspace only capture a
little variance information (9%, 12%, and 9%), indicating that the primary subspace of behaviorally-
relevant signals is nearly orthogonal to irrelevant space.

To investigate the composition of raw signals by the two partitions, we performed PCA on raw
neural signals to obtain raw PCs, and then projected the relevant and irrelevant signals onto these
PCs to assess the proportion of variance of raw signals explained by each partition. First, we ana-
lyzed the overall proportion of relevant and irrelevant signals that constitute the raw signals (the
inset pie plot, Fig. 4c,g and Supplementary Fig. S6c). The variance of the raw signals is composed of
three parts: the variance of relevant signals, the variance of irrelevant signals, and the correlation
between relevant and irrelevant signals (see Methods). The results demonstrate that the irrele-
vant signals account for a large proportion of raw signals, suggesting the motor cortex encodes
considerable information that is not related to the measured behaviors. In addition, there is only a
weak correlation between relevant and irrelevant signals, implying that behaviorally-relevant and
irrelevant signals are nearly uncorrelated.

We then examined the proportions of relevant and irrelevant signals in each PC of raw signals.
We found that relevant signals (red) occupy the dominant proportions in the larger variance raw
PCs (before the PC marked with a red triangle), while irrelevant signals (blue) occupy the dominant
proportions in the smaller variance raw PCs (after the PC marked with a red triangle) (Fig. 4c,g
and Supplementary Fig. S6c). Similar results are observed in the accumulation of each raw PC (Fig.
4d,h and Supplementary Fig. S6d). Specifically, the results show that the variance accumulation of
raw signals (purple line) in larger variance PCs is mainly contributed by relevant signals (red line),
while irrelevant signals (blue line) primarily contribute to the lower variance PCs. These results
demonstrate that irrelevant signals have a small effect on larger variance raw PCs but a large effect
on smaller variance raw PCs. This finding eliminates the concern that irrelevant signals would
significantly affect the top few PCs of raw signals and thus produce inaccurate conclusions. To

Figure 5. Smaller R^2 **neurons encode rich behavioral information in complex nonlinear ways. a**, The comparison of decoding performance between raw (purple) and distilled signals (red) on dataset A with different neuron groups, including smaller R^2 neuron ($R^2 <= 0.03$), larger R^2 neuron ($R^2 > 0.03$), and all neurons. Error bars indicate mean $\pm$ s.d. across five cross-validation folds. Asterisks denote significance of Wilcoxon rank-sum test with $\star P < 0.05$, $\star\star P < 0.01$. **b**, The correlation matrix of all neurons of raw (left) and behaviorally-relevant (right) signals on dataset A. Neurons are ordered to highlight correlation structure (details in Methods). **c**, The decoding performance of KF (left) and ANN (right) with neurons dropped out from larger to smaller R^2 on dataset A. The vertical gray line indicates the number of dropped neurons at which raw and behaviorally-relevant signals have the greatest performance difference. **d-f**, Same as **a-c**, for dataset B.

₃₁₃ further validate this finding, we used the top six PCs as jPCA (*Churchland et al., 2012*) did to examine
₃₁₄ the rotational dynamics of distilled and raw signals (Fig. S8). Results show that the rotational
₃₁₅ dynamics of distilled signals are similar to those of raw signals.

₃₁₆ Finally, to directly compare the population properties of raw and relevant signals, we plotted
₃₁₇ the cumulative variance curves of raw and relevant signals (Supplementary Fig. S9). Results (upper
₃₁₈ left corner curves, Supplementary Fig. S9) show that the cumulative variance curve of relevant
₃₁₉ signals (red line) accumulates faster than that of raw signals (purple line) in the preceding larger
₃₂₀ variance PCs, indicating that the variance of the relevant signal is more concentrated in the larger
₃₂₁ variance PCs than that of raw signals. Furthermore, we found that the dimensionality of primary
₃₂₂ subspace of raw signals (26, 64, and 45 for datasets A, B, and C) is significantly higher than that of
₃₂₃ behaviorally-relevant signals (7, 13, and 9), indicating that using raw signals to estimate the neural
₃₂₄ dimensionality of behaviors leads to an overestimation.

Distilled behaviorally-relevant signals uncover that smaller R^2 neurons encode rich behavioral information in complex nonlinear ways

₃₂₇ The results presented above regarding PDs (Fig. 3 and Fig. S4) demonstrate that irrelevant signals
₃₂₈ significantly impact smaller R^2 neurons and weakly impact larger R^2 neurons. Under the interfer-
₃₂₉ ence of irrelevant signals, it is difficult to explore the amount of behavioral information in neuronal
₃₃₀ activity. Given that we have accurately separated the behaviorally-relevant and irrelevant signals,
₃₃₁ we explored whether irrelevant signals would mask some encoded information of neuronal activity,
₃₃₂ especially for smaller R^2 neurons.

₃₃₃ To answer the question, we divided the neurons into two groups of smaller R^2 ($R^2 <= 0.03$)
₃₃₄ and larger R^2 ($R^2 > 0.03$), and then used decoding models to assess how much information is en-

coded in raw and distilled signals. As shown in Fig. 5a, for the smaller R^2 neuron group, both KF and ANN decode behavioral information poorly on raw signals, but achieve high decoding performance using relevant signals. Specifically, the KF decoder (left plot, Fig. 5a) improves the decoding R^2 significantly from 0.044 to 0.616 (improves by about 1300%; $P < 0.01$, Wilcoxon rank-sum test) after signal distillation; the ANN decoder (right plot, Fig. 5a) improves from 0.374 to 0.753 (improves by about 100%; $P < 0.01$, Wilcoxon rank-sum test). For the larger R^2 neuron group, the decoding performance of relevant signals with ANN does not improve much compared with the decoding performance of raw signals, but the decoding performance of relevant signals with KF is significantly better than that of raw signals ($P < 0.01$, Wilcoxon rank-sum test). Similar results are obtained with datasets B (Fig. 5d) and C (Supplementary Fig. S10d). These results indicate that irrelevant signals mask behavioral information encoded by neuronal populations, especially for smaller R^2 neurons with a higher degree of nonlinearity, and that smaller R^2 neurons actually encode rich behavioral information.

The fact that the smaller R^2 neurons encode rich information seems unexpected, and interestingly, we cannot obtain this rich information solely by distilling smaller R^2 neurons. This observation gives rise to two alternative scenarios. The first is that larger R^2 neurons introduce additional signals to smaller R^2 neurons, which they do not inherently possess, resulting in an excessive amount of behavioral information within the smaller R^2 neurons. The second is that the smaller R^2 neurons inherently possess a substantial amount of information, and larger R^2 neurons utilize their neural activity, which is correlated with that of small R^2 neurons, to aid in restoring the small R^2 neurons' original appearance; this process is analogous to image denoising, where damaged noisy pixels necessitate the assistance of their correlated, clean neighboring pixels to recover their original appearance. We initially tested the first scenario and found it to be unsupported for two key reasons. Firstly, our model enforces that distilled neuronal activity closely resembles the corresponding original neuronal activity, effectively preventing the generation of arbitrarily shaped neuronal activity, such as that of other neurons. As shown in Fig. 3i and Supplementary Fig. S5, our distilled relevant neuronal activity exhibits a high degree of similarity to the corresponding raw neuronal activity. To assess whether the distilled neurons exhibit the highest similarity to the corresponding raw neurons, we compared the neural similarity (R^2) of each distilled neuron to all raw neurons. The results indicate that 78/90 (87%, dataset A), 153/159 (96%, dataset B), and 91/91 (100%, dataset C) distilled neurons are most similar to the corresponding neurons. The remaining distilled neurons rank among the top four in similarity to the corresponding neurons, further confirming the close resemblance of distilled neuronal activity to the corresponding raw neuronal activity. Secondly, as we emphasized in the section on validating behaviorally-relevant signals with the second criterion, if this large amount of information is compensated by other neurons, the residuals should also contain a large amount of information. However, as illustrated in Fig. 2c, g, and k, the residuals contain only a little information. Therefore, based on these two reasons, the first scenario is rejected. Then we tested the second scenario. To verify this scenario, we conducted experiments using synthetic data with known ground truth (see Methods). In this dataset, small R^2 neurons inherently contained a substantial amount of information but were obscured by noise, making them undecodable. We aimed to assess whether d-VAE could recover the lost information and restore the damaged neuronal activity. The results demonstrate that, with the assistance of large R^2 neurons, d-VAE effectively recovers a significant amount of information that are obscured by noise (Fig. S11a). Additionally, the distilled signals exhibit a remarkable improvement in neural similarity to the ground truth compared to the raw signals ($P < 0.01$, Wilcoxon rank-sum test; Fig. S11b). Therefore, these results support the second scenario and collectively confirm that smaller R^2 neurons indeed contain rich behavioral information, and this finding is not a by-product of d-VAE.

Given that both smaller and larger R^2 neurons encode rich behavioral information, it is worth noting that the sum of the decoding performance of smaller R^2 neurons and larger R^2 neurons is significantly greater than that of all neurons for relevant signals (red bar, Fig. 5a,d and Supple-

mentary Fig. S10a), demonstrating that movement parameters are encoded very redundantly in neuronal population. In contrast, we can not find this degree of neural redundancy in raw signals (purple bar, Fig. 5a,d and Supplementary Fig. S10a) because the encoded information of smaller R^2 neurons are masked by irrelevant signals. Therefore, these smaller R^2 neurons, which are usually ignored, are actually useful and play a critical role in supporting neural redundancy. Generally, cortical redundancy can arise from neuronal correlations, which are critical for revealing certain aspects of neural circuit organization (*Yatsenko et al., 2015*). Accordingly, we visualized the ordered correlation matrix of neurons (see Methods) for both raw and relevant signals (Fig. 5b,e and Supplementary Fig. S10b) and found that the neuronal correlation of relevant signals is stronger than that of raw signals. These results demonstrate that irrelevant signals weaken the neuronal correlation, which may hinder the accurate investigation of neural circuit organization.

Considering the rich redundancy and strong correlation of neuronal activity, we wondered whether the neuronal population could utilize redundant information from other neurons to exhibit robustness under the perturbation of neuronal destruction. To investigate this question, we evaluated the decoding performance of dropping out neurons from larger R^2 to smaller R^2 on raw and relevant signals. The results (Fig. 5c,f and Supplementary Fig. S10c) show that the decoding performance of the KF and ANN on raw signals (purple line) decreases steadily before the number of neurons marked (vertical gray line), and the remaining smaller R^2 neurons decode behavioral information poorly. In contrast, even if many neurons are lost, the decoding performance of KF and ANN on relevant signals (red line) maintains high accuracy. This finding indicates that behaviorally-relevant signals are robust to the disturbance of neuron drop-out, and smaller R^2 neurons play a critical role in compensating for the failure of larger R^2 neurons. In contrast, this robustness can not be observed in raw signals because irrelevant signals mask neurons' information and weaken their correlation. Notably, the ANN outperforms the KF when only smaller R^2 neurons are left (Fig. 5c,f and Supplementary Fig. S10c), suggesting that smaller R^2 neurons can fully exploit their nonlinear ability to cope with large-scale neuronal destruction.

Distilled behaviorally-relevant signals uncover that signals composed of smaller variance PCs encode rich behavioral information in complex nonlinear ways

The results presented above regarding subspace overlap (Fig. 4 and Fig. S6) show that irrelevant signals have a small impact on larger variance PCs but dominate smaller variance PCs. Therefore, we aimed to investigate whether irrelevant signals would mask some encoded information of neural population, especially signals composed of smaller variance PCs.

To answer the question, we compared the decoding performance of raw and distilled signals with different raw PC groups. Specifically, we firstly divided the raw PCs into two groups, that is, smaller variance PCs and larger variance PCs, defined by ratio of relevant to irrelevant signals in the raw PCs (the red triangle, see Fig. 4c,g and Supplementary Fig. S6c). Then we projected raw and distilled signals onto these two PC groups and got the corresponding signals. Results show that, for the smaller variance PC group, both KF and ANN achieve much better performance on distilled signals than raw signals ($P < 0.01$, Wilcoxon rank-sum test, for ANN), whereas for the larger variance PC group, the decoding performance of relevant signals does not improve a lot compared with the decoding performance of raw signals (see Fig. 6a,d and Supplementary Fig. S10a). These results demonstrate that irrelevant signals mask the behavioral information encoded by different PC groups, especially for signals composed of smaller variance PCs (smaller variance PC signals), and smaller variance PC signals actually encode rich behavioral information.

The above results are based on raw PCs. However, raw PCs are biased by irrelevant signals and thus cannot faithfully reflect the characteristics of relevant signals. As we have successfully separated the behaviorally-relevant signals, we aimed to explore how behavioral information of distilled signals is distributed across relevant PCs. To do so, we used decoding models to evaluated the amount of behavioral information contained in cumulative PCs of relevant signals (using raw signals as a comparison). The cumulative variance explained by PCs in descending and as-

Figure 6. Signals composed of smaller variance PCs encode rich behavioral information in complex nonlinear ways. a, The comparison of decoding performance between raw (purple) and distilled signals (red) composed of different raw PC groups, including smaller variance PCs (the proportion of irrelevant signals that make up raw PCs is higher than that of relevant signals), larger variance PCs (the proportion of irrelevant signals is lower than that of relevant ones) on dataset A. Error bars indicate mean $\pm$ s.d. across five cross-validation folds. Asterisks denote significance of Wilcoxon rank-sum test with $^\star P < 0.05$, $^{\star\star} P < 0.01$. **b**, The cumulative decoding performance of signals composed of cumulative PCs that are ordered from smaller to larger variance using KF (left) and ANN (right) on dataset A. The red patches indicate the decoding ability of the last 10% variance of relevant signals. **c**, The cumulative decoding performance of signals composed of cumulative PCs that are ordered from larger to smaller variance using KF (left) and ANN (right) on dataset A. The red patches indicate the decoding gain of the last 10% variance signals of relevant signals superimposing on their top 90% variance signals. The inset shows the partially enlarged plot for view clearly. **d-f**, Same as **a-c**, but for dataset B.

cending order of variance and the dimensionality corresponding to the top 90% variance signals (called primary signals) and the last 10% variance signals (called secondary signals) are shown in Supplementary Fig. S9.

Here we first investigated secondary signals' decoding ability solely by accumulating PCs from smaller to larger variance. The results show that, for relevant signals, KF can hardly decode behavioral information solely using secondary signals (red line; left plot, Fig. 6b,e and Supplementary Fig. S10e), but ANN can decode rich information (red line; right plot, Fig. 6b,e and Supplementary Fig. S10e). These results indicate that smaller variance PC signals encode rich information in complex nonlinear ways. In contrast, when using raw signals composed of the same number of dimensions as the secondary signals (purple line, Fig. 6b,e and Supplementary Fig. S10e), the amount of information identified by ANN is significantly smaller than that of relevant secondary signals ($P < 0.01$, Wilcoxon rank-sum test). These results demonstrate that signals composed of these neural dimensions actually encode rich behavioral information, and irrelevant signals make them seem insignificant, indicating that behavioral information is distributed in a higher-dimensional subspace than expected from raw signals.

We then investigated the effect of superimposing secondary signals on primary signals by accumulating PCs from larger to lower variance. The results (Fig. 6c,f and Supplementary Fig. S10f) show that secondary signals improve the decoding performance of ANN a little but improve the decoding performance of KF a lot. The discrepancy between the two decoders reflects their differ-

ent abilities to utilize the information within the signal. KF cannot use the nonlinear information in primary signals as effectively as ANN can and thus requires secondary signals to improve decoding performance. Notably, the improvement of KF using secondary signals is significantly higher than using raw signals composed of the same number of dimensions as the secondary signals ($P < 0.01$, Wilcoxon rank-sum test). These results demonstrate that these smaller variance PC signals actually encode behavioral information, and irrelevant signals make their encoded information difficult to be linearly decoded, suggesting that behavioral information exists in a higher-dimensional subspace than anticipated from raw signals. Interestingly, we can find that although secondary signals nonlinearly encode behavioral information and are decoded poorly by linear decoders, they considerably improve KF performance by superimposing on primary signals (Fig. 6c,f and Supplementary Fig. S10f left); and the sum of the sole decoding performance of primary and secondary signals is lower than the decoding performance of full signals. These results indicate that the combination of smaller and larger variance PCs produces a synergy effect (*Narayanan et al., 2005*) enabling secondary signals that cannot be linearly decoded to improve the linear decoding performance.

Finally, considering the substantial enhancement in KF decoding performance when superimposing the secondary signals on the primary ones, we explored which aspect of movement parameters was improved. In BMIs, directional control has achieved great success (*Georgopoulos et al., 1986*; *Hochberg et al., 2012*), but precise speed control, especially at lower speeds such as hold or stop, has always been challenging (*Wodlinger et al., 2014*; *Inoue et al., 2018*). Thus we hypothesized that these signals might improve the lower-speed velocity. To test this, we divided samples into lower-speed and higher-speed regions and assessed which region improved the most by superimposing the secondary signals (see details in Methods). After superimposing the secondary signals, the absolute improvement ratio of the lower-speed region is significantly higher than that of the higher-speed region ($P < 0.05$, Wilcoxon rank-sum test; Supplementary Fig.S12a,b,c). Furthermore, we visualized the relative improvement ratio of five example trials for the two regions, and the results (Supplementary Fig. S12d) demonstrate that secondary signals significantly improve the estimation of lower speed. These results demonstrate that the secondary signals enhance the lower-speed control, suggesting that smaller variance PC signals are involved in regulating precise motor control.

Distilled behaviorally-relevant signals suggest that motor cortex may use a linear readout mechanism to generate movement behaviors

Understanding the readout mechanism of the motor cortex is crucial for both neuroscience and neural engineering, which remains unclear. By filtering out the interference of behaviorally-irrelevant signals, we found a stunning result: the linear decoder KF achieves comparable performance to that of the nonlinear decoder ANN ($P = 0.10, 0.15$, and 0.55 for datasets A, B, and C, Wilcoxon rank-sum test; Fig. 2b,f,g). Considering the decoding performance and model complexity (the simplicity principle, also called Occam's razor), movement behaviors are more likely to be generated by the linear readout, suggesting linear readout is performed in the motor cortex.

Given the significant improvement in linear decoding performance, one might doubt that it is our distillation model that makes signals that are inherently nonlinearly decodable become linearly decodable. In practice, this situation does not hold for two reasons. Firstly, if such a scenario were to occur, given that the signals extracted by d-VAE exhibit significantly different linear decoding performance compared to the ground truth, this difference would be reflected at the signal level, and theoretically, this difference should be substantial enough to be recognizable, rather than so minor as to be imperceptible. Consequently, this would result in lower neural similarity between these signals and the ground truth, as well as raw signals, and a substantial amount of uncharacterized signals of the ground truth signals would be left within the residuals, leading to the residuals containing a considerable amount of information. In this scenario, these signals would be effectively excluded by our criteria. To clarify it, let's consider an example. Suppose $z = x + y = n^2 + y$, where z, x, y, and n represent raw signals, relevant signals, irrelevant signals, and latent variables,

respectively. If the distilled relevant signals are $\hat{x} = n$, then these signals can be linear decoded accurately. However, the corresponding irrelevant signals are $n^2 - n + z$; thus, irrelevant signals will have much information, and these extracted relevant signals will not be selected. Secondly, our synthetic experiments offer additional evidence supporting the conclusion that d-VAE does not make inherently nonlinearly decodable signals become linearly decodable ones. As depicted in Fig. S11c, there exists a significant performance gap between KF and ANN when decoding the ground truth signals of smaller R^2 neurons ($P < 0.01$, Wilcoxon rank-sum test). KF exhibits notably low performance, leaving substantial room for compensation by d-VAE. However, following processing by d-VAE, KF's performance of distilled signals fails to surpass its already low ground truth performance and remains significantly inferior to ANN's performance ($P < 0.01$, Wilcoxon rank-sum test). These results collectively confirm that our approach does not convert signals that are inherently nonlinearly decodable into linearly decodable ones.

In summary, these findings demonstrate that behaviorally-irrelevant signals significantly complicate the readout of behavioral information and provide compelling evidence supporting the notion that the motor cortex uses a linear readout mechanism to generate movement behaviors.

Discussion

In this study, we proposed a new perspective for studying neural mechanisms, namely, using separated accurate behaviorally-relevant signals instead of raw signals; and we provided a novel distillation framework to define, extract, and validate behaviorally-relevant signals. By separating behaviorally-relevant and irrelevant signals, we found that neural responses previously considered useless encode rich behavioral information in complex nonlinear ways, and they play an important role in neural encoding and decoding. Furthermore, we found that linear decoders can achieve comparable performance to that of nonlinear decoders, providing compelling evidence for the presence of linear readout in the motor cortex. Overall, our results reveal unexpected complex encoding but simple decoding mechanisms in the motor cortex.

Signal separation by d-VAE

Behaviorally-relevant patterns can be extracted either at single-neuron or latent neural population levels. In our study, we focused on the single-neuron level, aiming to preserve the underlying properties of individual neurons. By maintaining the properties of each neuron, researchers can investigate how the neuronal population performs when one of the neurons is destroyed. This kind of analysis is particularly useful in closed-loop stimulation experiments that use electrophysiological (*Sun et al., 2022*) or optogenetic (*Zhang et al., 2022*) interventions. Furthermore, behaviorally-relevant signals also allow for population-level analysis and provide clean benchmark signals to test and compare the variance capture ability of different hypothesis-driven models.

At the single-neuron level, it is common practice to use trial-averaged neuronal responses of the same task parameters to analyze neural mechanisms (*Kobak et al., 2016*; *Rouse and Schieber, 2018*). However, trial averaging sacrifices single-trial information, thereby providing an incomplete characterization of neural activity. Furthermore, trial-averaged responses still contain a significant amount of behaviorally-irrelevant signals caused by uninstructed movements (*Musall et al., 2019*), which can lead to a contaminated version of behaviorally-relevant signals. In contrast, our model is capable of extracting clean behaviorally-relevant neural activity for every single trial. At the latent population level, existing latent variable models (*Sani et al., 2021*; *Pandarinath et al., 2018*; *Yu et al., 2008*; *Zhou and Wei, 2020*) focus on modeling some specific properties of latent population representations, such as linear or nonlinear dynamics (*Sani et al., 2021*; *Pandarinath et al., 2018*; *Churchland et al., 2012*), temporal smoothness (*Yu et al., 2008*), and interpretability (*Zhou and Wei, 2020*). Since these models make restrictive assumptions involving characterizing specific neural properties, they fail to capture other parts of behaviorally-relevant signals that do not meet their assumptions, providing no guarantee that the generated signals preserve behavioral information maximally. In contrast, our objective is to extract accurate behaviorally-relevant signals that

closely approximate the ground truth relevant signals as much as possible. To ensure this, we deliberately impose constraints on the model, ensuring that it generates signals that retain neuronal properties while preserving behavioral information to the highest degree possible. Notably, the pivotal operation of striking a balance between the reconstruction and decoding performance of generated signals to extract relevant signals is a distinctive feature absent in other models. At the population level, dimensionality reduction methods aided by task parameters (*Kobak et al., 2016*; *Schneider et al., 2023*) are another important way to discover the latent neural embeddings relevant to task parameters, which may provide new insight into neural representations. In contrast with this class of methods, our model focuses on the signal level, not the latent embedding level.

Although we made every effort, our model is still not able to perfectly extract behaviorally-relevant neural signals, resulting in a small amount of behavioral information leakage in the residuals. Nevertheless, the signals distilled by our model are reliable, and the minor imperfections do not affect the conclusions drawn from our analysis. In the future, better models can be developed to extract behaviorally-relevant signals more accurately, such as incorporating multiple time-step information (*Pandarinath et al., 2018*; *Sani et al., 2021*; *Hurwitz et al., 2021*) and contrastive learning (*Schneider et al., 2023*) or metric learning (*Li et al., 2021*) techniques into models.

Implications for analyzing neural activity by separation

Studying neural mechanisms through noisy signals is akin to looking at flowers in a fog, which is difficult to discern the truth. Thus, removing the interference of irrelevant signals is necessary and beneficial for analyzing neural activity, whether at the single-neuron level or population level.

At the single-neuron level, trial-to-trial neuronal variability poses a significant challenge to identifying the actual neuronal pattern changes. The variability can arise from various sources, including meaningless noise (*Faisal et al., 2008*), meaningful but behaviorally-irrelevant neural processes (*Musall et al., 2019*), and intrinsic components of neural encoding (*Walker et al., 2020*). However, it is still unclear to what extent each source contributes to the variability (*Faisal et al., 2008*). By separating behaviorally-relevant and irrelevant parts, we could roughly determine the extent to which these two parts contribute to the variability and explore which type of variability these two parts may contain. Our results demonstrate that behaviorally-irrelevant signals are a significant contributor to variability, which may include both meaningless noise and meaningful but behaviorally-irrelevant signals as behaviorally-irrelevant signals are not pure noise and may carry some structures (thick blue line, Fig. 4b,f and Supplementary Fig. S6b). Notably, behaviorally-relevant signals also exhibit some variability, which may arise from intrinsic components of neural encoding and provide the neural basis for motor learning (*Dhawale et al., 2017*). Moreover, eliminating the variability caused by irrelevant signals enables us to better observe and compare actual neuronal pattern changes and may facilitate the study of learning mechanisms (*Sadtler et al., 2014*; *Hennig et al., 2021*).

At the population level, determining the neural dimensionality of specific behaviors from raw signals is challenging since it is difficult to discern how many variances correspond to irrelevant signals, which often depend heavily on signal quality. A previous study (*Altan et al., 2021*) demonstrated, through simulation experiments involving different levels of noise, that such noise makes methods overestimate the neural dimensionality. Our results, consistent with theirs, indicate that using raw signals which includes many irrelevant signals will cause an overestimation of the neural dimensionality (Supplementary Fig. S9). These findings highlight the need to filter out irrelevant signals when estimating the neural dimensionality. It is important to note that the dimensionality of neural subspaces encoding behavioral information cannot be accurately determined by the variance they capture. Estimating the dimensionality accurately requires considering the amount of behavioral information encoded by signals distributed within these subspaces. This is because the variance of neural signals does not directly reflect the amount of behavioral information they encode. For example, behaviorally-irrelevant signals occupy some neural subspaces without containing behavioral information. Furthermore, this perspective of signal separation has broader

604 implications for other studies. For instance, researchers can isolate neural signals corresponding
605 to different behaviors and explore their shared and exclusive patterns to uncover underlying com-
606 mon and unique mechanisms of different behaviors (*Gallego et al., 2018*).

607 Implications for exploring neural mechanisms by separation

At the single-neuron level, previous studies (*Carmena et al., 2005*; *Narayanan et al., 2005*) have
shown that neuronal ensembles redundantly encode movement behaviors in the motor cortex.
However, our results reveal a significantly higher level of redundancy than previously reported.
Specifically, prior studies found that the decoding performance steadily declines as neurons drop
out, which is consistent with our results drawn from raw signals. In contrast, our results show that
decoders maintain high performance on distilled signals even when many neurons drop out. Our
findings reinforce the idea that movement behavior is redundantly encoded in the motor cortex
and demonstrate that the brain is robust enough to tolerate large-scale neuronal destruction while
maintaining brain function (*Alstott et al., 2009*).

At the population level, previous studies have proposed that motor control is achieved through
low-dimensional neural manifolds (*Cunningham and Yu, 2014*; *Gallego et al., 2017*). However, our
results challenge this idea by showing that signals composed of smaller variance PCs nonlinearly
encode a significant amount of behavioral information. This suggests that behavioral information
is distributed in a higher-dimensional neural space than previously thought. Interestingly, although
smaller variance PC signals nonlinearly encode behavioral information, their behavioral informa-
tion can be linearly decoded by superimposing them onto larger variance PC signals. This result
is consistent with the finding that nonlinear mixed selectivity can yield high dimensional neural re-
sponses and thus allow linear readout of behavioral information by downstream neurons (*Rigotti*
et al., 2013; *Fusi et al., 2016*). Moreover, we found that smaller variance PC signals can improve
precise motor control, such as lower speed control. Analogously, recent studies have found that
smaller variance PCs of hand postures are task-dependent and relate to the precise and complex
postures (*Yan et al., 2020*). These findings suggest that neural signals composed of lower variance
PCs are involved in the regulation of precise motor control.

In the motor cortex, in what form downstream neurons read out behavioral information is still
an open question. Previous studies have shown that nonlinear readout is superior to linear read-
out on raw signals (*Naufel et al., 2019*; *Glaser et al., 2020*; *Willsey et al., 2022*). However, by filtering
out the interference of behaviorally-irrelevant signals, our study found that accurate decoding per-
formance can be achieved through linear readout, suggesting that the motor cortex may perform
linear readout to generate movement behaviors. Similar findings have been reported in other cor-
tices, such as the inferotemporal cortex (IT) (*Majaj et al., 2015*), perirhinal cortex (PRH) (*Pagan et al.,*
2013), and somatosensory cortex (*Nogueira et al., 2023*), supporting the idea of linear readout as
a general principle in the brain. However, further experiments are needed to verify this hypothesis
across a wider range of cortical regions. While neurons encode significant behavioral information
nonlinearly, our study demonstrates that when neuronal assemblies with diverse firing patterns
collaborate to decode information, they do not necessarily need to fully exert their nonlinear ability.
Instead, a simple linear combination of these assemblies can accomplish the decoding task. This
finding suggests that the complexity of encoding mechanisms underlies the simplicity of decoding
mechanisms.

With regard to studying decoding mechanisms, recent studies (*Pitkow et al., 2015*; *Yang et al.,*
2021) have focused on investigating how the brain decodes task information in the presence of
noise. Unlike their works, we focus on studying the decoding mechanism after removing the noise
(irrelevant signals). Although our research perspectives differ, our results support their idea that
the brain needs nonlinear operations to suppress noise interference (*Yang et al., 2021*). Since the
brain contains both relevant and irrelevant signals, it is reasonable first to separate the relevant
signals and then investigate their inherent encoding and decoding mechanisms. Theoretically, the
process of removing irrelevant signals should not be considered part of the inherent encoding and

decoding mechanisms of the relevant signals. To illustrate this concept, consider a communication system as an example: the signal that the sender transmits has its own decryption rules. However, during transmission, noise is added to the signal. Upon reception, the receiver must first denoise the signal before decrypting it. The denoising operation should not be considered as part of the signal's inherent decryption rules. Additionally, investigating how the brain filters out noise or separates behaviorally-irrelevant factors is a promising research direction (*Schneider et al., 2018*). In this regard, distilled behaviorally-relevant signals can serve as reliable reference signals to facilitate this study. Furthermore, our study reveals that irrelevant signals are the most critical factor affecting accurate and robust decoding, and achieving accurate and robust linear decoding requires weak neural responses. These findings have two important implications for developing accurate and robust BMIs: designing preprocessing filtering algorithms or developing decoding algorithms that include filtering out behaviorally-irrelevant signals, and paying attention to the role of weak neural responses in motor control. More generally, our study provides a powerful framework for separating behaviorally-relevant and irrelevant signals, which can be applied to other cortical data to uncover more hidden neural mechanisms.

Methods

Dataset and preprocessing

Three datasets with different paradigms are employed, including obstacle avoidance task dataset (*Wang et al., 2015*), center-out reaching task dataset (*Dyer et al., 2017*), and self-paced reaching task dataset (*O'Doherty et al., 2017*).

The first dataset (dataset A) is the obstacle avoidance dataset. An adult male Rhesus monkey was trained to use the joystick to move the computer cursor to bypass the obstacle and reach the target. Neural data were recorded from the monkey's upper limb area of the dorsal premotor (PMd) using a 96-electrode Utah array (Blackrock Microsystems Inc., USA). Multi-unit activity (MUA) signals are used in the present study. The corresponding behavioral data (velocity) were simultaneously collected. There are two days of data (20140106 and 20140107), and each day contains 171 trials on average. All animal handling procedures were authorized by the Animal Care Committee at Zhejiang University, China, and conducted following the Guide for Care and Use of Laboratory Animals (China Ministry of Health).

The second dataset (dataset B) is publicly available and provided by Kording Lab (*Dyer et al., 2017*). The monkey was trained to complete two-dimensional 8-direction center-out reaching tasks. We used two days of data from subject C (20161007 and 20161011). Each day contains 190 trials on average. Neural data are spike-sorted PMd signals. The behavioral data were simultaneously collected in instantaneous velocity.

The third dataset (dataset C) is publicly available and provided by Sabes Lab (Zenodo dataset) (*O'Doherty et al., 2017*). An adult male Rhesus monkey was trained to finish self-paced reaching tasks within an 8-by-8 square grid. There are no inter-trial intervals during the experiment. Neural data were recorded from the monkey's primary motor cortex (M1) area with a 96-channel silicon microelectrode array. The neural data are the multi-unit activity (MUA) signals. Hand velocity was obtained from the position through a discrete derivative. The recording period for the data (20170124 01) is about 10 minutes.

For all datasets, the neural signals were binned by a 100ms sliding window without overlap. As a preprocess, we smoothed the neural signals using a moving average filter with three bins. We excluded some electrode activities with low mean firing rates (<0.5 Hz mean firing rates across all bins) and did not perform any other pre-selection to select neurons. For the computation of the Fano factor, we chose twelve and fourteen points as the thresholds of trial length for datasets A and B, respectively; trials with a length less than the threshold were discarded (discard about 7% and 2% trials for datasets A and B), trials longer than the threshold were truncated to threshold length from the starting point. Since dataset C has no trial information, FF is not calculated for

this dataset. For the analysis of datasets A and B, we selected one day of these two datasets for analysis (20140107 for dataset A and 20161011 for dataset B).

The synthetic dataset

The synthetic dataset is used to demonstrate that d-VAE can extract effective behaviorally-relevant signals that are similar to the ground truth signals. The specific process of generating synthetic data is as follows. First, we randomly selected nine larger R^2 neurons from neurons that R^2 is greater than 0.1, and three smaller R^2 neurons from neurons that R^2 is lower than 0.01 of dataset B (20161011). Second, we used deep neural networks to learn the encoding model between movement kinematics (movement velocity of dataset B) and neural signals using one fold train data. The details of the networks are demonstrated as follows. The networks use two hidden layer multilayer perceptron (MLP) with 500 and 500 hidden units. The activation function is ReLU. A SoftPlus activation function follows the last layer of the networks. The reconstruction loss is the Poisson likelihood function. After learning the encoding model, we used the learned encoding model to generate the ground truth of behaviorally-relevant signals from all kinematics data of dataset B. Then we added white Gaussian noise to the behaviorally-relevant signals such that the noisy signals have a signal-to-noise ratio (SNR) of 7dB. After adding noise, the R^2 of the three smaller R^2 neurons is lower than 0.03. We regarded the noisy signals as raw signals and the added Gaussian noise as behaviorally-irrelevant signals. Finally, we separated the synthetic data into five folds for cross-validation model evaluation.

Distill-VAE (d-VAE)

Notations. $\mathbf{x} \in \mathbb{R}^n$ denotes raw neural signals. $\mathbf{x}_r \in \mathbb{R}^n$ represents behaviorally-relevant signals. $\mathbf{x}_i = \mathbf{x} - \mathbf{x}_r \in \mathbb{R}^n$ represents behaviorally-irrelevant signals. $\mathbf{z} \in \mathbb{R}^d$ denotes the latent neural representations. $\mathbf{z}_{prior} \in \mathbb{R}^d$ denotes the prior latent neural representations. $\mathbf{y} \in \mathbb{R}^k$ represents kinematics. $f : \mathbb{R}^n \to \mathbb{R}^d$ represents the inference model (encoder) of VAE. $g : \mathbb{R}^d \to \mathbb{R}^n$ represents the generative model (decoder) of VAE. $m : \mathbb{R}^k \to \mathbb{R}^d$ represents the mapping from kinematics to prior latent representations. $h : \mathbb{R}^d \to \mathbb{R}^k$ represents an affine mapping from latent representations to kinematics.

d-VAE is a generative model based on variational autoencoders (VAEs) (*Kingma and Welling, 2013*), specially designed to extract behaviorally-relevant signals from raw signals. The generative model of d-VAE is

$$p_\theta(\mathbf{x} \mid \mathbf{y}) = \int_\mathbf{z} p_\theta(\mathbf{x}, \mathbf{z} \mid \mathbf{y}) d\mathbf{z} = \int_\mathbf{z} p_m(\mathbf{z} \mid \mathbf{y}) p_g(\mathbf{x} \mid \mathbf{z}) d\mathbf{z}, \tag{1}$$

where $p_m(\mathbf{z} \mid \mathbf{y})$ denotes the conditional prior distribution of latent variables given the kinematics parameterized by feedforward neural networks m, $p_g(\mathbf{x} \mid \mathbf{z})$ denotes the conditional prior distribution of raw signals given the latent variables parameterized by feedforward neural networks g, $p_\theta(\mathbf{x}, \mathbf{z} \mid \mathbf{y})$ represents the joint distribution of raw signals and latent variables given the kinematics parameterized by parameters $\theta = (m, g)$, and $p_\theta(\mathbf{x} \mid \mathbf{y})$ is the marginal distribution of raw signals parameterized by parameters θ.

To learn the model, we need to maximize the evidence lower bound (ELBO) of $p_\theta(\mathbf{x}|\mathbf{y})$:

$$\mathcal{L}_{ELBO}(\mathbf{x}) = \mathbb{E}_{\mathbf{z} \sim q_\phi(\mathbf{z}|\mathbf{x},\mathbf{y})} \left[p_\theta(\mathbf{x} \mid \mathbf{z}) \right] - D_{KL}(q_\phi(\mathbf{z} \mid \mathbf{x}, \mathbf{y}) \mid p(\mathbf{z} \mid \mathbf{y})) \le \log p_\theta(\mathbf{x} \mid \mathbf{y}), \tag{2}$$

where the first term of right hand side of Eq. 2 is called reconstruction term, the second term is called regularization term, $q_\phi(\mathbf{z} \mid \mathbf{x}, \mathbf{y})$ denotes inference model parameterized by parameters ϕ, and $D_{KL}(\cdot \mid \cdot)$ denotes the Kullback-Leibler divergence. In d-VAE, we set $q_\phi(\mathbf{z} \mid \mathbf{x}, \mathbf{y}) = q_f(\mathbf{z} \mid \mathbf{x})$, where f is the inference model parameterized by feedforward neural networks. Because during the test stage, we cannot obtain the ground truth of kinematics, and we need to use only raw signals to extract relevant signals. Note that d-VAE aims to extract behaviorally-relevant signals from raw signals, not generate signals that are too similar to raw signals. Therefore, we modified the objective loss function based on $\mathcal{L}_{ELBO}(\mathbf{x})$ (see Eq. 8).

To distill behaviorally-relevant neural signals, d-VAE utilizes the trade-off between the decoding
and reconstruction abilities of generated behaviorally-relevant signals $\mathbf{x}_r$. The basic assumption
is generated behaviorally-relevant signals that contain behaviorally-irrelevant signals harms their
decoding ability. Our approach for distilling behaviorally-relevant signals consists of three steps,
including identifying latent representations $\mathbf{z}$, generating behaviorally-relevant signals $\mathbf{x}_r$, and de-
coding behaviorally-relevant signals $\mathbf{x}_r$.

Identfiying latent representations

Identifying latent representations containing behaviorally-relevant information is the crucial part
because latent representations influences the subsequent generation. Effective representations
are more likely to generate proper behaviorally-relevant neural signals $\mathbf{x}_r$. d-VAE identifies latent
representations with inference model f, that is, $[\boldsymbol{\mu}; \boldsymbol{\sigma}^2] = f(\mathbf{x})$, where $\boldsymbol{\mu}$ and $\boldsymbol{\sigma}^2$ denote the mean and
variance of latent representations; thus the posterior distribution is $q_f(\mathbf{z} \mid \mathbf{x}) = \mathcal{N}(\mathbf{z}|\boldsymbol{\mu}, \boldsymbol{\sigma}^2)$. Then we
guide latent representations containing behavioral information through an affine map $h : \mathbb{R}^d \to \mathbb{R}^k$
under the loss $\mathcal{L}_{dec1}$,

$$\mathcal{L}_{dec1} = \mathrm{MSE}(h(\boldsymbol{\mu}), \mathbf{y}), \tag{3}$$

762 where $\mathrm{MSE}(\cdot, \cdot)$ denotes mean squared loss. In other words, we encourage latent representations
763 to decode kinematics to distill behaviorally-relevant information. Here we sample from the approx-
764 imation posterior $\mathbf{z} \sim q_f(\mathbf{z} \mid \mathbf{x})$ using $\mathbf{z} \sim \boldsymbol{\mu} + \boldsymbol{\sigma} \odot \boldsymbol{\epsilon}$, where $\boldsymbol{\epsilon} \sim \mathcal{N}(\mathbf{0}, \mathbf{I})$ and $\odot$ denotes element-wise
765 product. This sampling strategy is known as the reparameterization trick.

Generating behaviorally-relevant signals

767 After sampling latent representations $\mathbf{z}$, we send latent representations to the generative model g
768 to generate behaviorally-relevant neural signals $\mathbf{x}_r$, that is, $\mathbf{x}_r = g(\mathbf{z})$. We use following loss to make
769 behaviorally-relevant signals reconstruct raw signals as much as possible:

$$\mathcal{L}_{rec} = \mathrm{Poisson}(\mathbf{x}_r, \mathbf{x}), \tag{4}$$

770 where $\mathrm{Poisson}(\cdot, \cdot)$ denotes Poisson negative log likelihood loss. It is important to note that optimiz-
771 ing the generation of behaviorally-relevant signals to accurately reconstruct noisy raw signals may
772 result in the inclusion of many behaviorally-irrelevant signals in the generated signals, which de-
773 viates from our initial goal of extracting behaviorally-relevant signals. In the following subsection,
774 we will introduce how to avoid generating behaviorally-irrelevant signals.

Decoding behaviorally-relevant signals

As mentioned above, if the generation of behaviorally-relevant signals $\mathbf{x}_r$ is only guided by $\mathcal{L}_{rec}$, gen-
erated signals may contain more behaviorally-irrelevant signals. To avoid generated signals con-
taining behaviorally-irrelevant signals, we introduce decoding loss $\mathcal{L}_{dec2}$ to constrain $\mathbf{x}_r$ to decode
behavioral information. The basic assumption is that behaviorally-irrelevant signals act like noise
for decoding behavioral information and are detrimental to decoding. Thus, there is a trade-off
between neural reconstruction and decoding ability of $\mathbf{x}_r$: the more behaviorally-irrelevant signals
$\mathbf{x}_r$ contains, the more decoding performance $\mathbf{x}_r$ loses. Then we send the $\mathbf{x}_r$ to the encoder f and
obtain the mean and variance of latent representations, that is $[\boldsymbol{\mu}_r; \boldsymbol{\sigma}_r^2] = f(\mathbf{x}_r)$. The decoding loss
$\mathcal{L}_{dec2}$ is as follows:

$$\mathcal{L}_{dec2} = \mathrm{MSE}(h(\boldsymbol{\mu}_r), \mathbf{y}). \tag{5}$$

785 We use the same networks f and h for $\mathbf{x}_r$ and $\mathbf{x}$ in our experiment, because $\mathbf{x}_r$ can act as data
786 augmentation and make f distill robust representations without increasing model parameters. In
787 addition, we combine the two decoding loss as one loss:

$$\mathcal{L}_{dec} = \frac{1}{2}(\mathcal{L}_{dec1} + \mathcal{L}_{dec2}). \tag{6}$$

Learning the prior distribution with behavioral information

The prior distribution of latent representation is crucial because inappropriate prior assumptions can degrade latent representations and generated neural signals. Vanilla VAE uses a Gaussian prior $\mathcal{N}(\mathbf{0}, \mathbf{I})$ to regularize the space of latent representation $\mathbf{z}$. However, in neuroscience, the distribution of latent representations is unknown and may exceed the scope of Gaussian. Therefore we adopt neural networks m to learn the prior distribution with kinematics $\mathbf{y}$, that is, $[\boldsymbol{\mu}_{prior}; \boldsymbol{\sigma}^2_{prior}] = m(\mathbf{y})$ and thus $p_m(\mathbf{z} \mid \mathbf{y}) = \mathcal{N}(\mathbf{z}_{prior} \mid \boldsymbol{\mu}_{prior}, \boldsymbol{\sigma}^2_{prior})$. The prior distribution $p_m(\mathbf{z} \mid \mathbf{y})$ and approximation posterior distribution $q_f(\mathbf{z} \mid \mathbf{x})$ are aligned by the Kullback–Leibler divergence:

$$\mathcal{L}_{KL} = D_{KL}(p_m(\mathbf{z} \mid \mathbf{y}) \mid q_f(\mathbf{z} \mid \mathbf{x})) = D_{KL}(\mathcal{N}(\mathbf{z}|\boldsymbol{\mu}, \boldsymbol{\sigma}^2) \mid \mathcal{N}(\mathbf{z}_{prior} \mid \boldsymbol{\mu}_{prior}, \boldsymbol{\sigma}^2_{prior})). \tag{7}$$

Since $\mathbf{z}_{prior}$ and $\mathbf{z}$ are aligned and the generative network g models the relationship between $\mathbf{z}$ and $\mathbf{x}_r$, this is equivalent to indirectly establishing a neural encoding model from $\mathbf{y}$ to $\mathbf{x}_r$. Thus, we can observe the change of $\mathbf{z}_{prior}$ and $\mathbf{x}_r$ by changing $\mathbf{y}$ and can better understand the encoding mechanism of neural signals.

End-to-end optimization

d-VAE is optimized in an end-to-end manner under the following loss:

$$\mathcal{L} = \mathcal{L}_{rec} + \beta \mathcal{L}_{KL} + \alpha \mathcal{L}_{dec}, \tag{8}$$

where β and α are hyperparameters, β is used to adjust the weight of KL divergence, and α determines the trade-off between reconstruction loss $\mathcal{L}_{rec}$ and decoding loss $\mathcal{L}_{dec}$. Given that the ground truth of latent variable distribution is unknown, even a learned prior distribution might not accurately reflect the true distribution. We found the pronounced impact of the KL divergence would prove detrimental to the decoding and reconstruction performance. As a result, we opt to reduce the weight of the KL divergence term. Even so, KL divergence can still effectively align the distribution of latent variables with the distribution of prior latent variables (see Fig. S13).

In the training stage, we feed raw neural signals into the inference network f to get latent representation $\mathbf{z}$, which is regularized by $\mathbf{z}_{prior}$ coming from kinematics $\mathbf{y}$ and network m. Then we use the mean of $\mathbf{z}$, that is $\boldsymbol{\mu}$, to decode kinematics $\mathbf{y}$ by affine layer h and send $\mathbf{z}$ to the generative networks g to generate neural signals $\mathbf{x}_r$. To ensure that $\mathbf{x}_r$ preserves decoding ability, we send $\mathbf{x}_r$ to f and h to decode $\mathbf{y}$. The whole model is trained in an end-to-end manner under the guidance of total loss. Once the model has been trained, we can feed raw neural signals to it to obtain behaviorally-relevant neural signals $\mathbf{x}_r$, and we can aslo generate behaviorally-relevant neural signals using the prior distribution of $\mathbf{z}_{prior}$.

The identifiability of d-VAE

Recent studies (*Khemakhem et al., 2020*) show that to obtain the identifiability of latent variables, we should either restrict the structures of generating models or introduce some additional constraints on the distribution of latent variables and show that the additive noise models are identifiable under certain assumptions. pi-VAE (*Zhou and Wei, 2020*) has proved that pi-VAE is identifiable under some assumptions. Since d-VAE is a straightforward extension of pi-VAE, it also uses auxiliary variables (kinematics) to constrain the latent variables as pi-VAE did; with the same assumptions, d-VAE is also identifiable.

Differences from pi-VAE

pi-VAE lacks the decoding constraint on latent variables (Eq. 3) and the decoding constraint on generated signals (Eq. 5).

Cross-validation evaluation of models

For each model, we use the five-fold cross-validation manner to assess performance. Specifically, we divide the data into five equal folds. In each experiment, we take one fold for testing and

use the rest for training (taking three folds as the training set and one as the validation set). The reported performance is averaged over test sets of five experiments. The validation sets are used to choose hyperparameters based on the averaged performance of five-fold validation data. To avoid overfitting, we apply the early stopping strategy. Specifically, we assess the criteria (loss for training distillation methods, R^2 for training ANN and KF) on the validation set every epoch in the training process. The model is saved when the model achieves better validation performance than the earlier epochs. If the model cannot increase by 1% of the best performance previously obtained within 30 epochs, we stop the training process.

The strategy for selecting effective behaviorally-relevant signals

As previously mentioned, the hyperparameter α of d-VAE plays a crucial role in balancing the trade-off between reconstruction and decoding loss. Once the appropriate value of α is determined, we can use this value to obtain accurate behaviorally-relevant signals for subsequent analysis. To determine the optimal value of α, we first enumerated different values of α to guide d-VAE in distilling the behaviorally-relevant signals. Next, we used ANN to evaluate the decoding R^2 of behaviorally-relevant (D_{re}) and irrelevant (D_{ir}) signals generated by each α value. Finally, we selected the α value with the criteria formula $0.75 \times D_{re} + 0.25 \times (1 - D_{ir})$. The α value that obtained the highest criteria score on the validation set was selected as the optimal value.

Note that we did not use neural similarity between behaviorally-relevant and raw signals as a criterion for selecting behaviorally-relevant signals. This is because determining the threshold for neural similarity is challenging. However, not using similarity as a criterion does not affect the selection of suitable signals because the decoding performance of behaviorally-irrelevant signals can indirectly reflect the degree of similarity between the generated behaviorally-relevant signals and the raw signals. Specifically, if the generated behaviorally-relevant signals are dissimilar to the raw signals, the behaviorally-irrelevant signals will contain many useful signals. In other words, when the neural similarity between behaviorally-relevant and raw signals is low, the decoding performance of behaviorally-irrelevant signals is high. Therefore, the decoding performance of irrelevant signals is a reasonable alternative to the neural similarity.

For other generative models, we iterate through a range of hyperparameters, generating the corresponding behaviorally-relevant neural signals, and subsequently evaluate these signals using ANN. The hyperparameter associated with the signals that exhibit the highest ANN decoding performance is then selected. In other words, the signals corresponding to this particular hyperparameter are chosen as the selected behaviorally-relevant neural signals.

Implementation details for methods

All the VAE-based models use the Poisson observation function. The details of different methods are demonstrated as follows:

- d-VAE. The encoder f of d-VAE uses two hidden layer multilayer perceptron (MLP) with 300 and 100 hidden units. The activation function of the hidden layers is ReLu. The dimensionality of the latent variable is set to 50. The decoder g of d-VAE is symmetric with the encoder. The last layer of the decoder is followed by a SoftPlus activation function. The prior networks m use one hidden layer MLP with 300 units. The β is set to 0.001. The α is set to 0.3, 0.4, 0.7, and 0.9 for datasets A, B, and C. We perform a grid search for α in $\{0.1, 0.2, 0.3, 0.4, 0.5, 0.6, 0.7, 0.8, 0.9\}$, and β in $\{0.001, 0.01, 0.1, 1\}$, and latent variable dimension in $\{10, 20, 50\}$. For the synthetic dataset A and B experiments, the β and the latent variable dimension are directly set to 0.001 and 50. For synthetic dataset the α is set to 0.9, which is grid searched in $\{0.01–0.09, 0.1–0.9, 1–9\}$, with intervals of 0.01, 0.1, and 1, respectively.

- pi-VAE. The original paper utilizes label information (as shown in Eq. 6) to approximate the posterior of the latent variable and performs Monte Carlo sampling for decoding during the test stage. However, in our signal generation setting, it is inappropriate to use label information (kinematics) for extracting behaviorally-relevant signals during the test stage. As a result,

we modified the model to exclude the use of label information in approximating the posterior. The encoder, decoder, and prior networks of our pi-VAE are kept the same as those in d-VAE.

- LFADS. The hidden units of the encoder for the generator's initial conditions, the controller, the generator are set to 200, 200, 200, and 100 for datasets A, B, and C and the synthetic dataset. The dimensionality of latent factor is set to 50 for all datasets. We perform a grid search for hidden units in $\{100, 200\}$, and latent factor dimensions in $\{10, 20, 50\}$. The dimensionality of inferred inputs is set to 1. The Poisson likelihood function is used. The training strategy follows the practice of the original paper. For datasets A and B, a trial length of eighteen is set. Trials with lengths below the threshold are zero-padded, while trials exceeding the threshold are truncated to the threshold length from their starting point. In dataset A, there are several trials with lengths considerably longer than that of most trials. We found that padding all trials with zeros to reach the maximum length (32) led to poor performance. Consequently, we chose a trial length of eighteen, effectively encompassing the durations of most trials and leading to the removal of approximately 9% of samples. For dataset B (center-out), the trial lengths are relatively consistent with small variation, and the maximum length across all trials is eighteen. For dataset C, we set the trial length as ten because we observed the video of this paradigm and found that the time for completing a single trial was approximately one second. The segments are not overlapped.

- TNDM. The hidden units of the encoder for the generator's initial conditions, the controller, and the generator are set to 64, 64, 100, and 64 for datasets A, B, and C and the synthetic dataset. The dimensionality of relevant latent factors is set to 50, 25, 50, and 50 for datasets A, B, and C and the synthetic dataset. We set the dimensionality of irrelevant latent factors as the same as that of relevant latent factors. The behavior weight is set to 5, 5, 0.2, 0.5 for datasets A, B, and C and the synthetic dataset. We perform a grid search for relevant latent factor dimensionality in $\{10, 25, 50\}$, the hidden units in $\{64, 100, 200\}$, and the behavior weight in $\{0.2, 0.5, 1, 5, 10\}$. The Poisson likelihood function is used. The other hyperparameter setting and the training strategy follow the practice of the original paper. TNDM uses the same trial length and data as LFADS.

- PSID. PSID uses several (horizon size) past neural data to predict behavior at the current time without using neural observations at the current time. For a fair comparison, we let PSID see current neural observations by shifting the neural data one sample into the past relative to the behavior data. We perform a grid search for the horizon hyperparameter in $\{2, 3, 4, 5, 6, 7\}$. Due to the relevant latent dimension should be lower than the horizon times the dimensionality of behavior variables (two-dimensional velocity in this paper), we just set the relevant latent dimension as the maximum. The horizon number of datasets A, B, C, and synthetic datasets is 7, 6, 6 and 5, respectively. And thus the latent variable dimension of datasets A, B, and C and the synthetic dataset is 14, 12, 12 and 10, respectively.

- CEBRA. We use CEBRA-behavior mode. The learning rate is set to 0.003, 0.003, 0.001, and 0.005 for datasets A, B, and C and synthetic dataset. The time offset is set to 15, 15, 10 and 15. The output dimension is set to 10 for all datasets. The number of iterations is set to 5000. The temperature is set to 1, and the temperature mode is set to auto. The batch size is set to 512. We perform a grid search for the learning rate in $\{0.0001, 0.0005, 0.001, 0.003, 0.005\}$, the time offset in $\{5, 10, 15, 20\}$, and the output dimension in $\{5, 10, 15, 20, 50\}$. The optimal hyperparameter is selected based on the lowest averaged loss of five-fold training data.

- ANN. ANN has two hidden layers with 300 and 100 hidden units. The activation function of the hidden layers is ReLu.

- KF. The matrix parameters of observation and state transition process are optimized with the least square algorithm. KF is a linear-Gaussian state-space model designed to provide an optimal estimate of the current state (kinematics in this paper). It does so by considering both the current measurement observations (neural signals in this paper) and the previous

931   state estimate. The KF operates in a recursive and iterative manner, continually updating its
932   state estimate as new observations become available.

Percentage of explained variance captured in a subspace

934 We applied PCA to behaviorally-relevant and irrelevant signals to get relevant PCs and irrelevant
935 PCs. Then we used the percentage variance captured (also called alignment index) to quantify
936 how many variances of irrelevant signals can be captured by relevant PCs by projecting irrelevant
937 signals onto the subspace composed of some relevant PCs and vice versa. The percentage of
938 variance captured is:

$$A = \frac{\mathrm{Tr}\left(\mathbf{D}^{\mathrm{T}}\mathbf{C}\mathbf{D}\right)}{\mathrm{Tr}\left(\mathbf{C}\right)} \times 100\%, \tag{9}$$

939 where $\mathbf{D} \in \mathbb{R}^{N \times d}$ is the top d principal components (PCs) of relevant signals (irrelevant signals).
940 $\mathbf{C} \in \mathbb{R}^{N \times N}$ is the covariance matrix of irrelevant signals (relevant signals), and $\mathrm{Tr}\left(\mathbf{C}\right) = \sum_{i=1}^{N} \lambda_i$,
941 where λ_i is the i^{th} largest eigenvalue for $\mathbf{C}$. The percentage variance is a quantity between 0% and
942 100%.

The composition of raw signals' variance

944 Suppose $\mathbf{x} \in \mathbb{R}^{1 \times T}$, $\mathbf{y} \in \mathbb{R}^{1 \times T}$, and $\mathbf{z} \in \mathbb{R}^{1 \times T}$ are the random variables for a single neuron of
945 behaviorally-relevant signals, behaviorally-irrelevant, and raw signals, where $\mathbf{z} = \mathbf{x} + \mathbf{y}$, T denotes
946 the number of samples. The composition of raw signals' variance is as follows:

$$\begin{aligned}
\mathrm{Var}(\mathbf{z}) = \mathrm{Var}(\mathbf{x} + \mathbf{y}) &= \mathbb{E}\left\{[\mathbf{x} - \mathbb{E}(\mathbf{x})] + [\mathbf{y} - \mathbb{E}(\mathbf{y})]\right\}^2 \\
&= \mathbb{E}[\mathbf{x} - \mathbb{E}(\mathbf{x})]^2 + \mathbb{E}[\mathbf{y} - \mathbb{E}(\mathbf{y})]^2 + 2\mathbb{E}[\mathbf{x} - \mathbb{E}(\mathbf{x})][\mathbf{y} - \mathbb{E}(\mathbf{y})] \\
&= \mathrm{Var}(\mathbf{x}) + \mathrm{Var}(\mathbf{y}) + 2\mathrm{Cov}(\mathbf{x}, \mathbf{y}),
\end{aligned} \tag{10}$$

947 where $\mathbb{E}$, Var, and Cov denote expectation, variance, and covariance, respectively. Thus, the vari-
948 ance of raw signals is composed by the variance of relevant signals $\mathrm{Var}(\mathbf{x})$, the variance of irrelevant
949 signals $\mathrm{Var}(\mathbf{y})$, and the correlation between relevant and irrelevant signals $2\mathrm{Cov}(\mathbf{x}, \mathbf{y})$. If there are N
950 neurons, calculate the composition of each neuron separately and then add it up to get the total
951 composition of raw signals.

Reordered correlation matrix of neurons

The correlation matrix is reordered with a simple group method. The order of reordered neurons
is determined from raw neural signals, which is then used for behaviorally-relevant signals.
The steps of the group method are as follows:
Step 1: We get the correlation matrix in original neuron order and set a list A that contains all
neuron numbers and an empty list B.
Step 2: We select the neuron with the row number of the largest value of the correlation matrix
except for the diagonal line and choose nine neurons in list A that are most similar to the selected
neuron. We selected the value nine because it offers a good visualization of neuron clusters.
Step 3: Remove these selected neurons from list A, and add these selected neurons in descend-
ing order of correlation value in list B.
Step 4: Repeat steps 2 and 3 until list A is empty.

The improvement ratio of lower and higher speed regions

Split lower and higher speed regions
Since the speed ranges of different datasets are different, it is hard to determine a common speed
threshold to split lower and higher speed regions. Here we used the squared error as a criterion
to split the two speed regions. And for the convenience of calculating the absolute improvement
ratio, we need a unified benchmark for comparison. Therefore, we use half of the total squared
error as the threshold. Specifically, first, we calculated all samples' total squared error (E_p) between

actual velocity and predicted velocity obtained by primary signals only. Then we enumerated the speed from 1 to 50 with a step of 0.1 and calculated the total squared error of selected samples whose speed is less than the enumerated speed. Once the total squared error of selected samples is greater than or equal to the half total squared error of all samples ($0.5E_p$), the enumerated speed is set as the speed threshold. The samples whose speed is less than or equal to the speed threshold belong to lower speed regions, and those whose speed is greater than the speed threshold belong to higher speed regions. The squared error of the lower speed part (E_p^{low}) is approximately equal to that of the higher one E_p^{high}, that is, $E_p^{low} \approx E_p^{high} \approx 0.5E_p$ (the difference is negligible).

The absolute improvement ratio

After splitting the speed regions, we calculated the improvement of the two regions by superimposing secondary signals to primary signals, and got the squared error of lower E_{p+s}^{low} and higher E_{p+s}^{high} regions. Then we calculated the absolute improvement ratio (AIR):

$$AIR_{low} = -\frac{E_{p+s}^{low} - E_p^{low}}{E_p^{low}} \approx -\frac{E_{p+s}^{low} - 0.5E_p}{0.5E_p} \tag{11}$$

$$AIR_{high} = -\frac{E_{p+s}^{high} - E_p^{high}}{E_p^{high}} \approx -\frac{E_{p+s}^{high} - 0.5E_p}{0.5E_p} \tag{12}$$

Since the two regions refer to a common standard ($0.5E_p$), the improvement ratio of the two regions can be directly compared, and that's why we call it the absolute improvement ratio.

The relative improvement ratio

The relative improvement ratio (RIR) measures the improvement ratio of each sample relative to itself before and after superimposing secondary signals. The relative improvement ratio is computed as follows:

$$RIR^i = -\frac{E_{p+s}^i - E_p^i}{E_p^i}, \tag{13}$$

where i denotes the ith sample of test data.

Data availability

The datasets are available for research purposes from the corresponding author on reasonable request.

Code availability

The code will be publically available in github (see https://github.com/eric0li/d-VAE).

Acknowledgements

We would like to thank Yuxiao Yang, and Huaqin Sun for valuable discussions. This work was partly supported by grants from the National Key R&D Program of China (2018YFA0701400), Key R&D Program of Zhejiang (no. 2022C03011), the Chuanqi Research and Development Center of Zhejiang University, the Starry Night Science Fund of Zhejiang University Shanghai Institute for Advanced Study (SN-ZJU-SIAS-002), the Fundamental Research Funds for the Central Universities.

Author contributions

Y.G.L. conceived the study, designed the experiments, analyzed the data, and wrote and modified the manuscript. X.Y.Z. designed correlation analysis experiments and modified the manuscript. Y.M.W. and Y.Q. supervised this study.

Competing interests

The authors declare no competing interests.

References

1008

1009 **Alstott J**, Breakspear M, Hagmann P, Cammoun L, Sporns O. Modeling the impact of lesions in the human
1010 brain. PLoS computational biology. 2009; 5(6):e1000408.

1011 **Altan E**, Solla SA, Miller LE, Perreault EJ. Estimating the dimensionality of the manifold underlying multi-
1012 electrode neural recordings. PLoS computational biology. 2021; 17(11):e1008591.

1013 **Azouz R**, Gray CM. Cellular mechanisms contributing to response variability of cortical neurons in vivo. Journal
1014 of Neuroscience. 1999; 19(6):2209–2223.

1015 **Carmena JM**, Lebedev MA, Henriquez CS, Nicolelis MA. Stable ensemble performance with single-neuron vari-
1016 ability during reaching movements in primates. Journal of Neuroscience. 2005; 25(46):10712–10716.

1017 **Churchland MM**, Cunningham JP, Kaufman MT, Foster JD, Nuyujukian P, Ryu SI, Shenoy KV. Neural population
1018 dynamics during reaching. Nature. 2012; 487(7405):51–56.

1019 **Churchland MM**, Yu BM, Cunningham JP, Sugrue LP, Cohen MR, Corrado GS, Newsome WT, Clark AM, Hosseini
1020 P, Scott BB, et al. Stimulus onset quenches neural variability: a widespread cortical phenomenon. Nature
1021 neuroscience. 2010; 13(3):369–378.

1022 **Collinger JL**, Wodlinger B, Downey JE, Wang W, Tyler-Kabara EC, Weber DJ, McMorland AJ, Velliste M, Boninger
1023 ML, Schwartz AB. High-performance neuroprosthetic control by an individual with tetraplegia. The Lancet.
1024 2013; 381(9866):557–564.

1025 **Cunningham JP**, Yu BM. Dimensionality reduction for large-scale neural recordings. Nature neuroscience.
1026 2014; 17(11):1500–1509.

1027 **Dhawale AK**, Smith MA, Ölveczky BP. The role of variability in motor learning. Annual review of neuroscience.
1028 2017; 40:479.

1029 **Dyer EL**, Gheshlaghi Azar M, Perich MG, Fernandes HL, Naufel S, Miller LE, Körding KP. A cryptography-based
1030 approach for movement decoding. Nature biomedical engineering. 2017; 1(12):967–976.

1031 **Elsayed GF**, Lara AH, Kaufman MT, Churchland MM, Cunningham JP. Reorganization between preparatory and
1032 movement population responses in motor cortex. Nature communications. 2016; 7(1):1–15.

1033 **Faisal AA**, Selen LP, Wolpert DM. Noise in the nervous system. Nature reviews neuroscience. 2008; 9(4):292–
1034 303.

1035 **Fusi S**, Miller EK, Rigotti M. Why neurons mix: high dimensionality for higher cognition. Current opinion in
1036 neurobiology. 2016; 37:66–74.

1037 **Gallego JA**, Perich MG, Chowdhury RH, Solla SA, Miller LE. Long-term stability of cortical population dynamics
1038 underlying consistent behavior. Nature neuroscience. 2020; 23(2):260–270.

1039 **Gallego JA**, Perich MG, Miller LE, Solla SA. Neural manifolds for the control of movement. Neuron. 2017;
1040 94(5):978–984.

1041 **Gallego JA**, Perich MG, Naufel SN, Ethier C, Solla SA, Miller LE. Cortical population activity within a preserved
1042 neural manifold underlies multiple motor behaviors. Nature communications. 2018; 9(1):1–13.

1043 **Georgopoulos AP**, Schwartz AB, Kettner RE. Neuronal population coding of movement direction. Science. 1986;
1044 233(4771):1416–1419.

1045 **Glaser JI**, Benjamin AS, Chowdhury RH, Perich MG, Miller LE, Kording KP. Machine learning for neural decoding.
1046 Eneuro. 2020; 7(4).

1047 **Hennig JA**, Oby ER, Golub MD, Bahureksa LA, Sadtler PT, Quick KM, Ryu SI, Tyler-Kabara EC, Batista AP, Chase SM,
1048 et al. Learning is shaped by abrupt changes in neural engagement. Nature Neuroscience. 2021; 24(5):727–
1049 736.

1050 **Hochberg LR**, Bacher D, Jarosiewicz B, Masse NY, Simeral JD, Vogel J, Haddadin S, Liu J, Cash SS, Van Der Smagt
1051 P, et al. Reach and grasp by people with tetraplegia using a neurally controlled robotic arm. Nature. 2012;
1052 485(7398):372–375.

1053 **Hurwitz C**, Srivastava A, Xu K, Jude J, Perich M, Miller L, Hennig M. Targeted neural dynamical modeling. Ad-
1054 vances in Neural Information Processing Systems. 2021; 34:29379–29392.

Inoue Y, Mao H, Suway SB, Orellana J, Schwartz AB. Decoding arm speed during reaching. Nature communications. 2018; 9(1):1–14.

Jiang X, Saggar H, Ryu SI, Shenoy KV, Kao JC. Structure in neural activity during observed and executed movements is shared at the neural population level, not in single neurons. Cell reports. 2020; 32(6):108006.

Keshtkaran MR, Sedler AR, Chowdhury RH, Tandon R, Basrai D, Nguyen SL, Sohn H, Jazayeri M, Miller LE, Pandarinath C. A large-scale neural network training framework for generalized estimation of single-trial population dynamics. Nature Methods. 2022; p. 1–6.

Khemakhem I, Kingma D, Monti R, Hyvarinen A. Variational autoencoders and nonlinear ica: A unifying framework. In: *International Conference on Artificial Intelligence and Statistics* PMLR; 2020. p. 2207–2217.

Kingma DP, Welling M. Auto-encoding variational bayes. arXiv preprint arXiv:13126114. 2013; .

Kobak D, Brendel W, Constantinidis C, Feierstein CE, Kepecs A, Mainen ZF, Qi XL, Romo R, Uchida N, Machens CK. Demixed principal component analysis of neural population data. Elife. 2016; 5:e10989.

Kriegeskorte N, Douglas PK. Interpreting encoding and decoding models. Current opinion in neurobiology. 2019; 55:167–179.

Li Y, Qi Y, Wang Y, Wang Y, Xu K, Pan G. Robust neural decoding by kernel regression with Siamese representation learning. Journal of Neural Engineering. 2021; 18(5):056062.

Majaj NJ, Hong H, Solomon EA, DiCarlo JJ. Simple learned weighted sums of inferior temporal neuronal firing rates accurately predict human core object recognition performance. Journal of Neuroscience. 2015; 35(39):13402–13418.

Moreno-Bote R, Beck J, Kanitscheider I, Pitkow X, Latham P, Pouget A. Information-limiting correlations. Nature neuroscience. 2014; 17(10):1410–1417.

Musall S, Kaufman MT, Juavinett AL, Gluf S, Churchland AK. Single-trial neural dynamics are dominated by richly varied movements. Nature neuroscience. 2019; 22(10):1677–1686.

Narayanan NS, Kimchi EY, Laubach M. Redundancy and synergy of neuronal ensembles in motor cortex. Journal of Neuroscience. 2005; 25(17):4207–4216.

Naufel S, Glaser JI, Kording KP, Perreault EJ, Miller LE. A muscle-activity-dependent gain between motor cortex and EMG. Journal of neurophysiology. 2019; 121(1):61–73.

Nogueira R, Rodgers CC, Bruno RM, Fusi S. The geometry of cortical representations of touch in rodents. Nature Neuroscience. 2023; p. 1–12.

O'Doherty JE, Cardoso M, Makin J, Sabes P. Nonhuman primate reaching with multichannel sensorimotor cortex electrophysiology. Zenodo http://doi org/105281/zenodo. 2017; 583331.

Pagan M, Urban LS, Wohl MP, Rust NC. Signals in inferotemporal and perirhinal cortex suggest an untangling of visual target information. Nature neuroscience. 2013; 16(8):1132–1139.

Pandarinath C, O'Shea DJ, Collins J, Jozefowicz R, Stavisky SD, Kao JC, Trautmann EM, Kaufman MT, Ryu SI, Hochberg LR, et al. Inferring single-trial neural population dynamics using sequential auto-encoders. Nature methods. 2018; 15(10):805–815.

Pitkow X, Liu S, Angelaki DE, DeAngelis GC, Pouget A. How can single sensory neurons predict behavior? Neuron. 2015; 87(2):411–423.

Rigotti M, Barak O, Warden MR, Wang XJ, Daw ND, Miller EK, Fusi S. The importance of mixed selectivity in complex cognitive tasks. Nature. 2013; 497(7451):585–590.

Rouse AG, Schieber MH. Condition-dependent neural dimensions progressively shift during reach to grasp. Cell reports. 2018; 25(11):3158–3168.

Sadtler PT, Quick KM, Golub MD, Chase SM, Ryu SI, Tyler-Kabara EC, Yu BM, Batista AP. Neural constraints on learning. Nature. 2014; 512(7515):423–426.

Sani OG, Abbaspourazad H, Wong YT, Pesaran B, Shanechi MM. Modeling behaviorally relevant neural dynamics enabled by preferential subspace identification. Nature Neuroscience. 2021; 24(1):140–149.

1101 **Saxena S**, Cunningham JP. Towards the neural population doctrine. Current opinion in neurobiology. 2019;
1102 55:103–111.

1103 **Schneider DM**, Sundararajan J, Mooney R. A cortical filter that learns to suppress the acoustic consequences
1104 of movement. Nature. 2018; 561(7723):391–395.

1105 **Schneider S**, Lee JH, Mathis MW. Learnable latent embeddings for joint behavioural and neural analysis. Nature.
1106 2023; p. 1–9.

1107 **Sun G**, Zeng F, McCartin M, Zhang Q, Xu H, Liu Y, Chen ZS, Wang J. Closed-loop stimulation using a mul-
1108 tiregion brain-machine interface has analgesic effects in rodents. Science Translational Medicine. 2022;
1109 14(651):eabm5868.

1110 **Walker EY**, Cotton RJ, Ma WJ, Tolias AS. A neural basis of probabilistic computation in visual cortex. Nature
1111 Neuroscience. 2020; 23(1):122–129.

1112 **Wang F**, Wang Y, Xu K, Li H, Liao Y, Zhang Q, Zhang S, Zheng X, Principe JC. Quantized attention-gated kernel
1113 reinforcement learning for brain–machine interface decoding. IEEE transactions on neural networks and
1114 learning systems. 2015; 28(4):873–886.

1115 **Willsey MS**, Nason-Tomaszewski SR, Ensel SR, Temmar H, Mender MJ, Costello JT, Patil PG, Chestek CA. Real-
1116 time brain-machine interface in non-human primates achieves high-velocity prosthetic finger movements
1117 using a shallow feedforward neural network decoder. Nature Communications. 2022; 13(1):1–14.

1118 **Wodlinger B**, Downey J, Tyler-Kabara E, Schwartz A, Boninger M, Collinger J. Ten-dimensional anthropomorphic
1119 arm control in a human brain- machine interface: difficulties, solutions, and limitations. Journal of neural
1120 engineering. 2014; 12(1):016011.

1121 **Yan Y**, Goodman JM, Moore DD, Solla SA, Bensmaia SJ. Unexpected complexity of everyday manual behaviors.
1122 Nature communications. 2020; 11(1):1–8.

1123 **Yang Q**, Walker E, Cotton RJ, Tolias AS, Pitkow X. Revealing nonlinear neural decoding by analyzing choices.
1124 Nature communications. 2021; 12(1):1–13.

1125 **Yatsenko D**, Josić K, Ecker AS, Froudarakis E, Cotton RJ, Tolias AS. Improved estimation and interpretation of
1126 correlations in neural circuits. PLoS computational biology. 2015; 11(3):e1004083.

1127 **Yu BM**, Cunningham JP, Santhanam G, Ryu S, Shenoy KV, Sahani M. Gaussian-process factor analysis for low-
1128 dimensional single-trial analysis of neural population activity. Advances in neural information processing
1129 systems. 2008; 21.

1130 **Zhang J**, Hughes RN, Kim N, Fallon IP, Bakhurin K, Kim J, Severino FPU, Yin HH. A one-photon endoscope
1131 for simultaneous patterned optogenetic stimulation and calcium imaging in freely behaving mice. Nature
1132 Biomedical Engineering. 2022; p. 1–12.

1133 **Zhou D**, Wei XX. Learning identifiable and interpretable latent models of high-dimensional neural activity using
1134 pi-VAE. Advances in Neural Information Processing Systems. 2020; 33:7234–7247.

 Supplementary Information

Figure S1. Semantic overview of distill-VAE (d-VAE). On the left, we present a set of raw signal examples (depicted by purple lines). The input neural signals fed into the d-VAE consist of single time step samples. Initially, the encoder compresses these input signals into latent variables. We constrain latent variables to decode behaviors to preserve behavioral information. Subsequently, these latent variables are transmitted to the generator, which produces behaviorally-relevant signals (depicted by red lines). To maintain the underlying neuronal properties, we constrain these generated signals to resemble the raw signals closely. At this juncture, relying solely on the constraint for signal resemblance to raw signals makes it challenging to determine the extent of irrelevant signals present within the generated relevant signals. To tackle this hurdle, we introduce the generated signals back into the encoder. We then impose constraints on the resultant latent variables to decode behaviors. This approach is rooted in the assumption that irrelevant signals function as noise relative to relevant signals. Consequently, an excessive presence of irrelevant signals within the generated signals would lead to a degradation in their decoding performance. In essence, there exists a trade-off relationship between the decoding performance and the reconstruction performance of the generated signals. By striking a balance between these two constraints, we can effectively extract behaviorally-relevant signals.

Figure S2. Evaluation of separated signals on the synthetic dataset. a, The temporal neuronal activity of raw signals (the purple line) of an example test trial, which is decomposed into relevant (**b**) and irrelevant (**c**) signals. **b**, Relevant signals (red lines) extracted by d-VAE under three distillation cases, where bold gray lines represent ground truth relevant signals. The hyperparameter α is very important to extracting behaviorally-relevant signals, which balances the trade-off between reconstruction loss and decoding loss. Results show that when $\alpha = 0.09$, the relevant signals are too similar to raw signals but not similar to ground truth; when $\alpha = 0.9$, the relevant signals are well similar to the ground truth; when $\alpha = 9$, the relevant signals are not similar to the ground truth. **c**, Same as **b**, but for irrelevant signals (blue lines). Notably, when $\alpha = 9$, some useful signals are left in irrelevant signals. **d**, The decoding R^2 of distilled relevant signals of three cases. Error bars indicate mean $\pm$ s.d. across five cross-validation folds. Results demonstrate that decoding R^2 increases as α increases. **e**, Same as **d**, but for irrelevant signals. Notably, when $\alpha = 9$, irrelevant signals will contain large behavioral information. **f**, The neural similarity between relevant and raw signals. Results show that the neural R^2 decreases as α increases. **g**, The neural R^2 between relevant signals and the ground truth of relevant signals. Results show that d-VAE can utilize a proper trade-off to extract effective relevant signals that are similar to the ground truth. **h**, The neural R^2 between irrelevant signals and the ground truth of irrelevant signals. Results show that d-VAE can utilize a proper trade-off to remove effective irrelevant signals that are similar to the ground truth. **i**, The decoding R^2 between true velocity and predicted velocity of raw signals (purple bars with slash lines), the ground truth signals (gray) and behaviorally-relevant signals obtained by d-VAE (red), PSID (pink), pi-VAE (green), TNDM (blue), and LFADS (light green). Error bars denote mean $\pm$ standard deviation (s.d.) across five cross-validation folds. Asterisks represent significance of Wilcoxon rank-sum test with $^\star P < 0.05$, $^{\star\star} P < 0.01$. **j**, Same as **i**, but for irrelevant signals. **k**, The neural R^2 between generated relevant signals and raw signals. **l**, Same as **k**, but for the ground truth of relevant signals.

Figure S3. Decoding performance comparison with CEBRA. a, The decoding R^2 comparison between d-VAE and CEBRA on synthetic dataset. The red bar represents the behaviorally-relevant signals extracted by d-VAE, and the light purple bar represents the behaviorally-relevant embeddings extracted by CEBRA. Error bars indicate mean $\pm$ s.d. across five cross-validation folds. Asterisks denote significance of Wilcoxon rank-sum test with $^\star P < 0.05$, $^{\star\star} P < 0.01$. **b-d**, Same as **a**, but for datasets A, B, and C, respectively.

Figure S4. The effect of irrelevant signals on relevant signals at the single-neuron level. a,b Same as Fig. 3, but for dataset C. **a**, The angle difference (AD) of preferred direction (PD) between raw and distilled signals as a function of the R^2 of raw signals. Each black point represents a neuron (n=91). The red curve is the fitting curve between R^2 and AD. Five example larger R^2 neurons' PDs are shown in the inset plot, where the solid line arrows represent the PD of relevant signals, and the dotted line arrows represent the PDs of raw signals. **b**, Comparison of the cosine tuning fit (R^2) before and after distillation of single neurons (black points), where the x-axis and y-axis represent neurons' R^2 of raw and distilled signals.

Figure S5. The firing activity of example neurons. a, Example of three neurons' raw firing activity decomposed into behaviorally-relevant and irrelevant parts using all trials in held-out test sets for four conditions (4 of 8 directions) of center-out reaching task. **b**, Example of three neurons' raw firing activity decomposed into behaviorally-relevant and irrelevant parts using all trials in held-out test sets for four conditions (4 of 12 conditions) of obstacle avoidance task.

Figure S6. The effect of irrelevant signals on analyzing neural activity at the population level. a-d,
Same as Fig. 4, but for dataset C. **a,b**, PCA is separately applied on relevant and irrelevant signals to get
relevant PCs and irrelevant PCs. The thick lines represent the cumulative variance explained for the signals on
which PCA has been performed, while the thin lines represent the variance explained by those PCs for other
signals. Red, blue, and gray colors indicate relevant signals, irrelevant signals, and random Gaussian noise
(for chance level). The cumulative variance explained for behaviorally-relevant (**a**) and irrelevant (**b**) signals
got by d-VAE. **c,d**, PCA is applied on raw signals to get raw PCs. **c**, The bar plot represents the composition of
each raw PC. The inset pie plot shows the overall proportion of raw signals, where red, blue, and purple
colors indicate relevant signals, irrelevant signals, and the correlation between relevant and relevant signals.
The PC marked with a red triangle indicates the last PC where the variance of relevant signals is greater than
or equal to that of irrelevant signals. **d**, The cumulative variance explained by raw PCs for different signals,
where the thick lines represent the cumulative variance explained for raw signals(purple), while the thin lines
represent the variance explained for relevant (red) and irrelevant (blue) signals.

Figure S7. The effect of irrelevant signals obtained by pi-VAE on analyzing neural activity at the population level. a-l, Same as Fig. 4 and Fig. S6, but for pi-VAE. **a,b**, PCA is separately applied on relevant and irrelevant signals to get relevant PCs and irrelevant PCs. The thick lines represent the cumulative variance explained for the signals on which PCA has been performed, while the thin lines represent the variance explained by those PCs for other signals. Red, blue, and gray colors indicate relevant signals, irrelevant signals, and random Gaussian noise (for chance level). The cumulative variance explained for behaviorally-relevant (**a**) and irrelevant (**b**) signals on dataset A. **c,d**, PCA is applied on raw signals to get raw PCs. **c**, The bar plot represents the composition of each raw PC. The inset pie plot shows the overall proportion of raw signals, where red, blue, and purple colors indicate relevant signals, irrelevant signals, and the correlation between relevant and relevant signals. The PC marked with a red triangle indicates the last PC where the variance of relevant signals is greater than or equal to that of irrelevant signals. **d**, The cumulative variance explained by raw PCs for different signals, where the thick line represents the cumulative variance explained for raw signals(purple), while the thin line represents the variance explained for relevant (red) and irrelevant (blue) signals. **e-h, i-l**, Same as **a-d**, but for datasets B and C.

Figure S8. The rotational dynamics of raw, relevant, and irrelevant signals. datasets A and B have twelve and eight conditions, respectively. We get the trial-averaged neural responses for each condition, then apply jPCA to raw, relevant, and irrelevant signals to get the top two jPC, respectively. **a**, The rotational dynamics of raw neural signals. **b**, The rotational dynamics of relevant signals obtained by d-VAE. **c**, The rotational dynamics of irrelevant signals obtained by d-VAE. We can see that the rotational dynamics of behaviorally-relevant signals are similar to that of raw signals, but the rotational dynamics of behaviorally-irrelevant signals are irregular. **d-f**, Same as **a-c**, but for dataset B.

Figure S9. The cumulative variance of raw and behaviorally-relevant signals. a, PCA is applied separately on raw and distilled behaviorally-relevant signals to get raw PCs and relevant PCs. The cumulative variance of raw (purple) and behaviorally-relevant signals (red) on dataset A (n=90). Two upper left corner curves denote the variance accumulation from larger to smaller variance PCs. Two lower right corner curves indicate accumulation from smaller to larger variance PCs. The horizontal lines represent the 10%, and 90% variance explained. The vertical lines indicate the number of dimensions accounted for the last 10% and top 90% of the variance of behaviorally-relevant (red) and raw (purple) signals. Here we call the subspace composed by PCs of capturing top 90% variance the primary subspace, and the subspace composed by PCs of capturing last 10% variance the secondary subspace. We can see that the dimensionality of the primary subspace of raw signals is significantly higher than that of relevant signals, indicating that irrelevant signals make us overestimate the dimensionality of specific behaviors. **b,c**, Same as **a**, but for datasets B (n=159) and C (n=91).

Figure S10. neural responses usually considered useless encode rich behavioral information in complex nonlinear ways. a-c, Same as Fig. 5, but for dataset C (n=91). **d-f**, Same as Fig. 6, but for dataset C. **a**, The comparison of decoding performance between raw (purple) and distilled signals (red) with different neuron groups, including smaller R^2 neuron ($R^2 <= 0.03$), larger R^2 neuron ($R^2 > 0.03$), and all neurons. Error bars indicate mean $\pm$ SD across cross-validation folds. Asterisks denote significance of Wilcoxon rank-sum test with $^\star P < 0.05$, $^{\star\star} P < 0.01$. **b**, The correlation matrix of all neurons of raw and behaviorally-relevant signals. **c**, The decoding performance of KF (left) and ANN (right) with neurons dropped out from larger to smaller R^2. The vertical gray lines indicate the number of dropped neurons at which raw and behaviorally-relevant signals have the greatest performance difference. **d**, The comparison of decoding performance between raw (purple) and distilled signals (red) composed of different raw-PC groups, including smaller variance PCs (the proportion of irrelevant signals that make up raw PCs is higher than that of relevant signals), larger variance PCs (the proportion of irrelevant signals is lower than that of relevant ones). Error bars indicate mean $\pm$ s.d. across five cross-validation folds. Asterisks denote significance of Wilcoxon rank-sum test with $^\star P < 0.05$, $^{\star\star} P < 0.01$. **e**, The cumulative decoding performance of signals composed of cumulative PCs that are ordered from smaller to larger variance using KF (left) and ANN (right). The red patches indicate the decoding ability of the last 10% variance of relevant signals. **f**, Same as **e**, but PCs are ordered from larger to smaller variance. The red patches indicate the decoding gain of the last 10% variance signals of relevant signals superimposing on their top 90% variance signals.

Figure S11. Using synthetic data to demonstrate that conclusions are not a by-product of d-VAE. a, b These results are used to demonstrate that d-VAE can utilize the larger R2 neurons to help the smaller R2 neurons restore their original face. **a**, The decoding R^2 of the ground truth (gray), raw signals (purple), and distilled relevant signals (red) of smaller R^2 neurons of synthetic data. Error bars indicate mean $\pm$ s.d. (n=5 folds). Asterisks denote the significance of Wilcoxon rank-sum test with $^{\star\star}P < 0.01$. We can see that the ground truth of smaller R^2 neurons contain a certain amount of behavioral information, but the behavioral information cannot be decoded from raw signals due to being covered by noise; d-VAE can indeed utilize the larger R^2 neurons to help the smaller R^2 neurons restore their damaged information. **b**, The neural similarity of raw signals and relevant signals to ground truth of smaller R^2 neurons. We can see that d-VAE can obtain effective relevant signals that are more similar to the ground truth compared to raw signals. **c**, The decoding R^2 of the ground truth (gray) and distilled relevant signals (red) of smaller R^2 neurons of synthetic data. These results are used to demonstrate that d-VAE can not make the linear decoder achieve similar performance as the nonlinear decoder. We can see that KF is significantly inferior to ANN on ground truth signals. The KF decoding performance of the ground truth signals is notably low, leaving significant room for compensation by d-VAE. However, after processing with d-VAE, the KF decoding performance of distilled signals does not surpass its ground truth performance. The disparity between KF and ANN remains substantial. These results demonstrate that d-VAE can not make signals that originally require nonlinear decoding linearly decodable.

Figure S12. Smaller variance PC signals preferentially improve lower-speed velocity. a, The comparison of absolute improvement ratio between lower-speed (red) and higher-speed (purple) velocity when superimposing secondary signals on primary signals with KF on dataset A. Error bars indicate mean ± s.d. across five cross-validation folds. Asterisks denote significance of Wilcoxon rank-sum test with $\star P < 0.05$, $\star\star P < 0.01$. **b, c**, Same as **a**, but for datasets B and C. **d**, The comparison of relative improvement ratio between lower-speed (red patch) and higher-speed (no patch) velocity when superimposing secondary signals on primary signals with KF on dataset B. The first-row plot shows five example trials' speed profile of the decoded velocity using primary signals (light blue line) and full signals (dark blue line; superimposing secondary signals on primary signals) and the true velocity (red line). The black horizontal line denotes the speed threshold. The second and third-row plots are the same as the first-row plot, but for X and Y velocity. The fourth-row plot shows the relative improvement ratio for each point in trials.

Figure S13. Visualization of latent variables. a, The velocity samples of one-fold test data. Different colors denote different directions of the eight-direction center-out. **b**, The distribution plot of the top three principal components (PCs) of latent variables. The points on the bottom plane represent the two-dimensional projections of the three-dimensional data. **c**, The distribution plot of the top three PCs of learned prior latent variables. We can see that the distribution of prior latent variables closely resembles that of latent variables, thus illustrating the effectiveness of the KL divergence.