The GLM-Spectrum:
A multilevel framework for spectrum analysis with covariate and confound modelling.

Andrew J Quinn[1, 2†], Lauren Z Atkinson [1], Chetan Gohil [1], Oliver Kohl [1],
Jemma Pitt [1], Catharina Zich [3, 4], Anna C Nobre [1, 5] & Mark W Woolrich[1]

1 Oxford Centre for Human Brain Activity, Wellcome Centre for Integrative Neuroimaging, University Department of Psychiatry, Warneford Hospital, Oxford, UK.
2 Centre for Human Brain Health, School of Psychology, University of Birmingham, UK.
3 Department for Clinical and Movement Neurosciences, UCL Queen Square Institute of Neurology, 33 Queen Square, London, UK
4 FMRIB, Wellcome Centre for Integrative Neuroimaging, Nuffield Department of Clinical Neurosciences, University of Oxford, UK.
5 Department of Experimental Psychology, University of Oxford, UK

† corresponding author: a.quinn@bham.ac.uk

Abstract

The frequency spectrum is a central method for representing the dynamics within electrophysiological data. Some widely used spectrum estimators make use of averaging across time segments to reduce noise in the final spectrum. The core of this approach has not changed substantially since the 1960s, though many advances in the field of regression modelling and statistics have been made during this time. Here, we propose a new approach, the General Linear Model (GLM) Spectrum, which reframes time averaged spectral estimation as multiple regression. This brings several benefits, including the ability to do confound modelling, hierarchical modelling and significance testing via non-parametric statistics.

We apply the approach to a dataset of EEG recordings of participants who alternate between eyes-open and eyes-closed resting state. The GLM-Spectrum can model both conditions, quantify their differences, and perform denoising through confound regression in a single step. This application is scaled up from a single channel to a whole head recording and, finally, applied to quantify age differences across a large group-level dataset. We show that the GLM-Spectrum lends itself to rigorous modelling of within- and between-subject contrasts as well as their interactions, and that the use of model-projected spectra provides an intuitive visualisation. The GLM-Spectrum is a flexible framework for robust multi-level analysis of power spectra, with adaptive covariance and confound modelling.

---

1   Introduction

Frequency-domain analyses of oscillations in electrophysiological recordings of brain activity contain information about the underlying neuronal activity. Both the peaks of specific oscillations and the broader spectral shape are informative about brain function and have inspired a wide literature across neuroscience (Buzsáki and Draguhn, 2004; Kopell et al., 2014). The time-averaged periodogram is the predominant method for spectrum estimation in neuroscience. It computes the average Fourier spectrum across a set of sliding window segments (Bartlett, 1948, 1950; Welch, 1967) based on the premise that the data are comparable over time and that the effect of noise will be attenuated when averaging across segments. This algorithm produces a statistical estimate of a spectrum and has remained largely the same for many decades. Statistical methods have greatly progressed in this time and many newer approaches can be directly applied to the windowed periodogram.

Here, we propose the General Linear Model Spectrum (GLM-Spectrum) framework for analysing time-averaged periodogram estimates of frequency spectra. This reframes the method of averaged periodograms as a regression problem by modelling frequency spectra over successive windows as a linear mixture of a set of user-specified regressors. This links linear spectrum estimation to the GLM analyses that have been developed for a broad range of neuroimaging applications including structural and functional MRI (Friston et al., 1994; Woolrich et al., 2009), event related fields (Smith and Kutas, 2014) and induced responses (Litvak et al., 2013). Specifically, we demonstrate the utility of multi-level models (Friston, 2007; Woolrich et al., 2004), non-parametric permutation testing (Nichols and Holmes, 2001; Winkler et al., 2014), contrast coding and confound regression in the context of spectrum estimation. GLM-Spectrum can be applied to analyse any time series, from Local Field Potentials to multichannel Electro- and Magnetoencephalography (EEG & MEG). It is not dependent on any specific preprocessing methods in sensor- or source- space analyses, beyond what would apply to a typical frequency spectrum analysis. The GLM-Spectrum could also be configured to perform task analyses on the timescale of the sliding windows used in the STFT. For example, a set of 'boxcar' regressors could be defined to contrast different task states. More broadly, the method is applicable to any time series analysis that looks to estimate a Fourier based frequency spectrum.

We illustrate the GLM-Spectrum by analysing EEG recordings alternating between eyes-open and eyes-closed resting-state conditions from a freely available dataset (Babayan et al., 2019). First, the GLM-Spectrum is used to analyse time-series data from a single channel of one individual. The spectrum for the two resting conditions and their difference are computed, whilst a set of covariate and confound regressors account for linear trends over time and a diverse set of potential artefact sources. This approach is generalised to the whole head recording of a single subject to describe the spatial patterns associated with each regressor. Finally, a group-level, whole head analysis explores the GLM-Spectra of specific regressors and contrasts before quantifying how they differ between younger and older participants.

2   Methods

2.1   Time-Averaged Periodogram Estimation

Time-averaged periodogram methods start by estimating a windowed short-time
Fourier transform across time series y using the windowing function w

$$Y_y(f, k) = \sum_{t=1}^{T} w(t)y(t,k)e^{\frac{-i2\pi ft}{fs}} \tag{1}$$

The Fourier transform above is computing the k-th segment of the continuous input
$y(t)$, which we denote with $y(t, k)$. The output matrix $Y(f, k)$ contains the STFT, which
describes how the spectrum changes in power across the K segments. A time-varying
magnitude spectrum S_y or power spectrum P_y can be computed from the STFT.

$$S_y(f, k) = |Y(f, k)| \qquad P_y(f, k) = \frac{|Y(f, k)|^2}{N} \tag{2}$$

Finally, the time-averaged periodogram is then the average of the time-varying
power spectral density across segments.

$$Pwelch_y(f) = \frac{1}{K} \sum_{k=1}^{K} P_y(f, k) \tag{3}$$

If the previous computations included a windowing function $w(t)$ and overlapping
time segments, then this is Welch's power spectral density estimate (Welch, 1967).
Welch's time-averaged periodogram now has the property that the noise level of the
estimate decreases with increased data length, since more input data provides a larger
number of segments for the central averaging step. It is still an imperfect estimator that
has been subject to criticism (Prerau et al., 2017; Thomson, 1982) but it is practical,
straightforward to compute, and in wide use across science and engineering. A detailed
description of these equations is provided in supplemental section 7.1.

2.2   General Linear Model Spectrum

The GLM-Spectrum replaces the averaging step in the time-averaged spectrum
estimation methods with a General Linear Model (also known as multiple regression).
The GLM is widely used in neuroimaging analyses (Friston, 2007; Woolrich et al.,
2009) and the same principles around analysis, model validation and statistics apply
here. The objective is to model the spectrum across the K sliding window segments as a
linear function of a set of regressor variables. The magnitude GLM-Spectrum is defined
as:

$$S_y(f, k) = X(k)B(f) + e(f) \tag{4}$$

Where $S_y(f)$ is the (Kx1) time-varying spectrum estimated at frequency (f) across
all K segments/windows (the STFT computed in 2) computed from a single channel
(timeseries) of data, X is a (KxP) design matrix containing the P regressors of interest
as they vary over time, and e(f) is a (Kx1) vector of residual errors. We model the
whole spectrum using a mass-univariate modelling approach that fits a separate GLM

for each frequency bin in the FFT. The resulting (Px1) vector B(f) contains the   74
estimated regression parameters. We refer to the whole vector of estimates across   75
frequency as the GLM 'beta-spectrum' [1]   76

2.3 Estimating the GLM Parameters   77

Once the design matrix has been specified and the data have been transformed into the   78
STFT, we are ready to fit the regression parameters B in equation 4. Under the   79
assumptions specified above, this can be achieved using Ordinary Least Squares (OLS)   80
to estimate the regression parameters (also known as beta-estimates), $B(f)$, as   81

$$\hat{B}(f) = (X^T X)^{-1} X^T S_y(f) \tag{5}$$

Alternatively, we can pre-multiply the data by the Moore-Penrose pseudo-inverse   82
(MPPI) (Penrose, 1956) of the design matrix, which performs well even when there are   83
multi-collinearities in X (see Section 2.4):   84

$$\hat{B}(f) = X^+ S_y(f) \tag{6}$$

Where the superscript $^+$ denotes the MPPI. More complex fitting routines could be   85
used if the assumptions underlying OLS are inappropriate for a particular application.   86
For example, the rest of the GLM-Spectrum framework would work in the same way if   87
$B(f)$ were estimated using a robust or regularised regression. Similarly, it would be   88
possible to extend the approach to Bayesian regression methods. Here, we use the   89
pseudo-inverse model fitting approach (equation 6) for all GLM estimation.   90

2.4 Assumptions of the GLM-Spectrum   91

The theory of linear regression underlying the GLM-Spectrum uses assumptions that   92
simplify the problem and specify the conditions under which the solution is valid.   93
Typically, five different assumptions are defined: validity, linearity, independence of   94
errors, homoscedasticity of errors and normality of errors. There remains debate about   95
their relative importance (Gelman and Hill, 2007; Knief and Forstmeier, 2021).   96

The first two assumptions are relatively general. *Validity* states that the data being   97
analysed should be an appropriate match to the research question. This apparently   98
simple point is frequently overlooked by researchers (Gelman and Hill, 2007).   99
Linearity is the assumption that the dependent variable can be described as a linear   100
function of the predictors in the model design matrix. This is the central mathematical   101
feature of linear regression models. We cover assumptions about the residuals and the   102
distribution of variables in more detail in the next two sections.   103

2.4.1 Distribution of the residuals.   104

Three commonly reported assumptions relate to the residuals of the fitted model $e(f)$.   105
Independence of errors states that the residuals of the model fit are independent and   106
identically distributed (IID) over observations (over time in the case of GLM-Spectrum).   107
Homoscedasticity of errors states that the variance of the error is consistent across all   108
values of the predictor. Finally, *normality of errors* states that the residuals should have   109

---

[1]The term 'beta' has different uses in the fields of statistics/linear-modelling and neuronal oscillations. In this work, we refer to a 'beta-spectrum' in the statistical sense (a spectrum of linear model parameter estimates) rather than the neuronal sense (a spectrum of beta-oscillation activity).

a normal, Gaussian distribution. Violating these assumptions affects the validity of inferential statistics computed from the model, limiting our ability to generalise results from our data to the population. Parameter estimates are more robust to violations of these assumptions. In most cases, we anticipate that inferential statistics will not be performed on first-level GLM-Spectrum results. Rather the parameter estimates or t-values of many first-level models will be combined into a group model. [110][111][112][113][114][115]

GLMs are relatively robust to violations of *homoscedasticity of errors* and *normality of errors* (Williams et al., 2013). The p-values computed from models with violations of these errors tend to be robust at moderate to large sample sizes, except in datasets with substantial outliers (Knief and Forstmeier, 2021). [116][117][118][119]

A specific issue for first-level statistics is the likely presence of temporal autocorrelation in $e(f)$ indicating a violation of the *independence of errors* assumption. This issue is commonly encountered in other time-series models such as first-level fMRI analyses (Friston et al., 2000; Woolrich et al., 2001; Worsley and Friston, 1995). Future work that requires valid inferential statistics on first-level GLM-Spectra may develop explicit models for this temporal autocorrelation similar to the approach taken in fMRI (Friston et al., 2000; Woolrich et al., 2001). [120][121][122][123][124][125][126]

2.4.2   Distribution of the data and predictor variables. [127]

The ordinary least squares GLM does not make any formal assumptions about the distributions of the data or predictor variables (Williams et al., 2013). Non-normal predictor variables are commonplace in regression analyses. For example, binary variables that 'dummy code' for individual groups of observations are commonly used as predictors. Strongly skewed, fat-tailed or non-normal distributions can still negatively impact the fit by a greater likelihood of influential outlier observations. This may be increasingly problematic with smaller sample sizes, or with increasingly extreme outlier values in the data. [128][129][130][131][132][133][134][135]

Distribution checking is a critical factor in the choice of whether to use the complex, magnitude, power or log-power spectrum as the dependent variable in a GLM-Spectrum. Power is most commonly used for spectrum analysis but power estimates are strictly positive-valued and tend have distributions with a strong positive skew. The magnitude ($S_y(f)$) and log-power ($log(P_y(f))$) spectra are likely to be more Gaussian and both result in similar GLM-Spectrum results (See supplemental section 7.2). Though either of these forms are appropriate, here we use the magnitude spectrum as it is a good compromise between reducing the impact of outliers and maintaining simple visual interpretability of the results. [136][137][138][139][140][141][142][143][144]

Future work could equally use the log-power spectrum or consider expanding the GLM-Spectrum approach to use Generalised Linear Modelling (Nelder and Wedderburn, 1972) to account for specific differences in the distribution of the data being modelled. Finally, we do not consider the complex spectrum due to variability in phase across time segments leading to significant cancellation of the signal. If phase information is critical, and expected to be consistent across time segments, then future work may generalise these statistics to the complex spectrum (for example, Baker (2021). [145][146][147][148][149][150][151][152]

2.5   Design Matrix Specification [153]

2.5.1   Regressor Selection [154]

The regressors in the design matrix X will typically be secondary time-series that are recorded simultaneously with the main data or known *a priori*. The regressors must be prepared in the same manner as the main data, including any filtering and [155][156][157]

segmentation, to ensure correspondence between the design matrix and data. All   158
regressors used in this paper are segmented following the modelled time-series data   159
and summed within each segment to create a vector of values to use as a covariate.   160

The GLM is a highly general method as the design matrix, X, can be adapted   161
depending on the application in question. However, this flexibility can also make the   162
specification and interpretation of the regressors challenging. The addition of a new   163
regressor to an existing GLM design matrix can change the parameter estimates and   164
standard errors of the previous regressors. Therefore, the final choice and   165
interpretation of any regressors is necessarily specific to each individual analysis.   166

Standard time-averaged spectrum estimation methods (such as Welch's   167
Periodogram) model the mean spectrum across time segments. Similarly, most   168
GLM-Spectrum analyses will also want to include regressors that quantify this average. 169
In the simplest case, a single, constant regressor of ones is directly equivalent to the 170
standard method. However, the flexibility of the GLM allows us to build on this and   171
define more sophisticated models with multiple covariates if required.   172

One extension enabled by the GLM-Spectrum is to use confound regression to model   173
the effect of an artefact source and attenuate its contribution to the estimate of the 174
overall mean. The amount of denoising applied by the model is proportional to the   175
effect size of the confound regressor in question. This makes the confound regression   176
adaptive to each individual model; the same potential noise source may be highly   177
predictive of the STFT in one dataset but not the next. Researchers could consider   178
running a formal model comparison to remove ineffective confound regressors from   179
first-level analyses altogether. Here, we have taken the approach of maintaining all   180
first-level regressors to simplify group analysis. Further group-level permutation testing 181
the assesses whether a noise source has a 'significant' effect on the STFT. This is a   182
flexible alternative to removing the artefactual time periods altogether. Confound   183
regression can be performed by including a non-zero mean regressor alongside a   184
constant regressor in the design matrix. With this specification, the constant regressor 185
models the intercept (the average where the value of the artefact regressor is zero)   186
whilst the confound regressor quantifies the artefact effect. This example is explored in 187
more detail in supplemental section 7.6.   188

Covariates can be included into the GLM in several ways. We can use indicator   189
regressors (containing zeros and ones) which assume that the covariates effect will be 190
the same each time it is present. Otherwise, we can use dynamic covariates to model   191
phenomena that dynamically change over time in a continuous way. For example, this   192
might include pupil size, heart rate, or respiration rate. When we include these types of 193
continuous regressors, their regression parameters capture the "slope" effect; in other 194
words, how much does the spectrum change with each increment in the value of the   195
regressor. For example, when including a pupil-size regressor, the spectrum resulting   196
from its regression parameter estimates would indicate how much the power in a   197
particular frequency bin increases or decreases as the pupil-size changes by a certain 198
amount.   199

Another decision is whether to demean a given covariate regressor in the design   200
matrix. Counter intuitively, the interpretation of the regression parameter estimate is 201
unchanged when a covariate is demeaned; in both cases it is modelling the 'slope' effect 202
that quantifies how much the spectrum changes with each increment of the regressor.   203
In contrast, the interpretation of a constant regressor in the same model will change   204
depending on whether a covariate is demeaned or not. A constant regressor will model   205
the mean over all time points if the other covariates are demeaned and will model the   206
intercept if non-zero mean regressors are included. As a result, confound regressors   207
that are intended to remove a given effect from the estimate of the mean will typically 208
have a non-zero mean whilst dynamic covariates that model changes around the mean   209

will be demeaned or z-transformed prior to model fitting. 210

2.5.2 Multicollinearity 211

Finally, while it is not a violation of the model assumptions, one should take care when 212
regressors in X can be expressed, to any extent, as a linear combination of other 213
regressors. This is referred to as multicollinearity and means that there are infinite 214
equally good solutions to the regression equation. Using the MPPI to fit the model 215
parameters can overcome this limitation. If multiple solutions to equation 4 exist, the 216
MPPI will return the regression parameters with the minimum Euclidean norm 217
(Penrose, 1956). Note that when there is partial multicollinearity, the MPPI uses the 218
component of the regressor that is uncorrelated with the rest of the design matrix (i.e. 219
corresponding to any unique variability in that regressor) to find each parameter 220
estimate. This property means the MPPI solution quantifies the unique effect of each 221
regressor that cannot be accounted for by the others. Therefore, it is frequently 222
desirable to proceed with the MPPI solution for a GLM whose design contains some 223
degree of multicollinearity that we wish to eliminate from the results. 224

In addition, the impact of any multicollinearity is naturally accounted for in the 225
variance of the affected regression parameter estimates. For example, when the 226
presence of multicollinearity increases uncertainty about the value of a regression 227
parameter then that parameter estimate's variance (as computed in section 2.6) will be 228
appropriately increased. Nonetheless, even when using the MPPI, we recommend 229
assessing the correlation and singular value spectrum of the design matrix prior to 230
model fitting as well as the variance of the regression parameters (Smith et al., 2007) 231
This ensures that one is aware of the potential impact of multicollinearity on finding a 232
significant result. If these checks identify unexplainable or unintended 233
multicollinearity, perhaps from including too many or inappropriate regressors, then 234
the design should be re-assessed prior to further analysis. 235

2.6 Contrasts and t-statistics 236

Once the design matrix is specified and the model parameters have been estimated, the 237
GLM-Spectrum consists of a beta-spectrum for each regressor. This beta-spectrum 238
contains the regression parameter estimates quantifying the linear effect of that 239
regressor across the frequency range. 240

Next, we can compute simple linear combinations of regression parameter 241
estimates, known as contrasts. Contrasts can be defined to ask questions about the size 242
of these linear combinations, including whether they are significantly different to zero 243
(using t-tests). This approach is commonly applied in neuroimaging applications 244
(Friston, 2007; Woolrich et al., 2009). 245

Each contrast is defined as a vector of values that define the relative weights used to 246
compare different parameter estimates. For example, we could define the following 247
contrasts for a model that contains three regressors in its design matrix: 248

$$c_1 = \begin{bmatrix} 1 \\ 0 \\ 0 \end{bmatrix}, c_2 = \begin{bmatrix} 0 \\ 0.5 \\ 0.5 \end{bmatrix}, c_3 = \begin{bmatrix} 0 \\ 1 \\ -1 \end{bmatrix}, C = [c_1, c_2, c_3] \qquad (7)$$

Where C is a (P x N_c) matrix containing all N_c contrasts. Using terminology 249
common in neuroimaging, these contrasts define a Contrast Of Parameter Estimates, or 250
a cope, which is computed from a matrix multiplication between the contrast and the 251
model parameter estimates: 252

$$cope(f) = C\hat{B}(f) \qquad (8)$$

Here, we refer to the resulting frequency resolved vector of cope values, cope(f), as the GLM cope-spectrum. The individual contrasts are designed to ask specific experimental questions. Using the examples in equation 7, the first contrast asks whether $c_1\hat{B}(f) = 0$. This specifies a t-test that quantifies whether each value in the beta-spectrum of the first regressor is different from zero; regressors two and three are weighted to zero in this specific contrast, but nevertheless still explain variance in the overall model. The second contrast tests if $c_2\hat{B}(f) = 0$ and asks whether the mean of the beta-spectra from regressors two and three is different from zero. Note that setting the values in this contrast to 0.5 ensures that the contrast of the regression parameter estimates can be interpreted as the mean of the two regression parameters involved. When turned into statistics (see below), contrasts c_1 and c_2 are equivalent to one-sample t-tests in classical statistical frameworks.

Finally, testing if $c_3\hat{B}(f) = 0$ tests whether the difference in parameter estimates in the beta-spectrum of regressor 2 minus regressor 3 is different from zero. This is equivalent to an independent samples t-test between the conditions modelled by these regressors. Regressor 1 is set to zero in the second two contrasts and is not directly included in the comparison. However, it is still explaining variance in the model and may be indirectly affecting the outcome of the contrast between regressors 2 and 3.

These contrasts are useful combinations of parameter estimates but we need the associated standard error to complete a formal statistical test. The ratio of the contrast value (cope) and its standard error is a t-statistic that indicates the estimated magnitude of a cope relative to its standard error. To compute the standard errors and subsequent t-statistics for each contrast, we first need to compute the residuals of the model fit:

$$R_y(f) = S_y(f) - \hat{B}(f)X \qquad (9)$$

Note that $R_y(f)$ contains the actual set of residuals for a given dataset and model fit. This is distinct from $e_y(f)$, which denotes a more general white noise process. These residuals are used to compute the variance in the estimate of the cope, also known as a varcope. Firstly, we compute the variance of the residuals:

$$\sigma^2(f) = diag(R_y(f)R_y(f)^T) \qquad (10)$$

And transform this to get the variance of relevant part of the model for this contrast:

$$varcope(f) = diag(C(X^TX)^{-1}C)\sigma^2(f) \qquad (11)$$

$varcope(f)$ now contains the square of the standard error for this contrast. This computation can be costly with large datasets as several matrix multiplications must be performed. However, only the diagonal of the resultant matrix is used for further analysis. Therefore, we speed-up this computation using Einstein summation in numpy[2] to compute only the multiplications which appear in the final diagonal. More information on this and comparisons to alternative computation methods is described in Supplemental section 7.4. The spectrum of t-values corresponding to the contrast

---

[2]https://numpy.org/doc/stable/reference/generated/numpy.einsum.html

can then be computed as the ratio of the cope to its standard error: 289

$$t(f) = \frac{cope(f)}{\sqrt{varcope(f)}} \tag{12}$$

This GLM t-spectrum quantifies the difference of each cope from zero in statistical   290
terms, incorporating both the parameter estimates and their standard errors. Taken   291
together, the GLM beta-spectrum $B(f)$, cope-spectrum $cope(f)$ and t-spectrum $t(f)$ 292
provide an intuitive description of the frequency spectrum of the input data in terms of   293
the specified regressors and contrasts.   294

2.7   Effect Size Computation with Cohen's F^2.   295

Effect sizes represent the strength of a statistical relationship as a complement to   296
hypothesis-based test statistics like t-tests. The effect size of a single variable within the   297
context of a multivariate regression model can be computed with $Cohen's F^2$ (Cohen,   298
1988). The spectrum of effect sizes for a single regressor within a GLM-Spectrum   299
model can be computed as (Selya et al., 2012).   300

$$Cohen's F^2(f) = \frac{R^2_{AB}(f) - R^2_A(f)}{1 - R^2_{AB}(f)} \tag{13}$$

In which B denotes the regressor of interest and A the set of all other regressors.   301
R^2_{AB} is then the proportion of variance explained by the full model and R^2_A is the   302
variance explained by all regressors except B. This metric can be computed for every   303
frequency, channel and regressor within a model to establish a full spectrum of effect   304
sizes. [3]   305
    Here, we compute effect sizes for each covariate by eliminating it from the full   306
model and computing the value in equation 13. For categorical predictors, the effect   307
size is computed by comparing the full model to a model in which separate categorical   308
regressors are combined into a single constant regressor. As an example, this models   309
the effect of modelling two conditions with their own mean term compared to   310
modelling them both with the same mean.   311

2.8   Visualising effects with model projected spectra   312

The GLM beta-, cope- and t-spectra assess parts of the overall time-varying spectrum in   313
relation to the model. As these GLM-Spectra can relate to combinations of effects, their   314
impact on the mean spectrum can be difficult to intuit. We propose computing the   315
model-projected spectra to gain a more immediately intuitive visualisation of effects.   316
This is a visualisation of how the spectrum changes for different values of the regressor   317
of interest. For example, if the GLM-Spectrum of EEG data includes a covariate for   318
pupil size then its beta-spectrum will describe how the spectrum changes as pupil size   319
expands and contracts. The model-projected spectrum could then be used to visualise   320
the predicted spectrum at a specific pupil size.   321
    The model-projected spectrum is typically calculated for a descriptive range of   322
values in the original regressor. In this paper, we use the largest and smallest values   323
from the regressor of interest. For example, to compute the projected spectrum for the   324

---

[3]Cohen's original work suggest that values of $F^2 \geqslant 0.02$, $F^2 \geqslant 0.15$ and $F^2 \geqslant 0.35$ represent small, medium and large effects respectively (Cohen, 1988; Selya et al., 2012). These labels should be interpreted with caution and only used as informal guidelines.

largest and smallest value of a covariate regressor Rv relative to a constant mean term, 325
we use: model-projected spectra 326

$$max\{S_y|Rv\}(f) = max(Rv)\hat{B}_{rv}(f) + \hat{B}_{mean}(f) \qquad (14)$$

$$min\{S_y|Rv\}(f) = min(Rv)\hat{B}_{rv}(f) + \hat{B}_{mean}(f) \qquad (15)$$

$$(16)$$

The max and min model-projected spectrum then describes the range of variability 327
in the spectrum that is described by the regressor. Note that this is only a visualisation 328
method and that any apparent differences in these model projected spectra must be 329
confirmed by statistical significance testing, such as non-parametric permutations (see 330
section 2.10). 331

2.9 Group Models for GLM-Spectrum 332

The GLM-Spectrum described thus far is used to describe continuous data recorded 333
from a single session; we refer to this as the "first-level". We now consider how we can 334
carry out a "group-level" analysis to combine the results across the first-level 335
GLM-Spectra from multiple sessions/subjects using a group-level (or second-level) GLM 336
(Beckmann et al., 2003; Friston et al., 2002; Woolrich et al., 2004). In brief, we create 337
a group-level dependent variable by concatenating the parameter estimates, copes or 338
varcopes from a set of first-level analyses and use another GLM to model how 339
GLM-Spectra vary over sessions/subjects across the group. For example, here we fit a 340
group-level beta-spectrum using the first-level cope-spectra for N subjects and a 341
group-level design matrix: 342

$$\begin{bmatrix} cope^j_{subj1}(f) \\ cope^j_{subj2}(f) \\ \vdots \\ cope^j_{subjN}(f) \end{bmatrix} = X_{group}B_{group}(f) + e_{group}(f) \qquad (17)$$

Where $cope^j_{subj1}(f)$ is the j^{th} first-level cope computed for subject n at frequency 343
bin f, i.e. $cope^j_{subj1}(f) = c_j\hat{B}_{subjn}(f)$ where c_j is the j^{th} first-level contrast and $\hat{B}_{subjn}$ 344
is the first-level contrast regression parameter estimates for subject n. Note that X_{group} 345
is the (NxQ) group-level design matrix and the (Qx1) matrix $B_{group}(f)$ is the 346
group-level regression parameters, where Q is the number of group-level regressors. As 347
with the first-level GLM, the error $e_{group}(f)$ is assumed to be Normal and IID. 348
As with the first-level analysis, the group-level GLM is fitted using OLS with the 349
MPPI; and is computed separately for each frequency, f, (and each channel or voxel – 350
the indexing for which is not shown in the equations) in a mass-univariate manner. In 351
addition, a separate group-level GLM is computed for each first-level cope of interest. 352
As with the first-level GLM, contrasts can be used to ask a range of inference questions 353
from the regression parameter estimates, $\hat{B}_{group}(f)$. A resource showing examples of 354
commonly used group-level design matrices and contrasts is available online[4]. 355
As shown in the equation above, the simplest group-level model carries forward the 356
cope-spectra from a set of first-level analyses. This can be thought of as a fixed-effects 357
group model in which each observation (first-level result) contributes equally to the 358
group effect and the group-level GLM models the between-session/subject variability. 359

---

[4]https://fsl.fmrib.ox.ac.uk/fsl/fslwiki/GLM

This is the approach taken in this manuscript. Future work can extend it to incorporate   360
the information about the first-level standard errors in the varcope-spectra. Both the   361
cope and varcope information could be carried forward to the group-level and fitting a   362
mixed effects model such as the FLAME method in fMRI (Woolrich et al., 2004). In   363
practice, this model is challenging to fit as no simple closed-form estimation is   364
available. Another alternative would be to carry the first-level t-statistics to the   365
group-level. Future work can explore wide range of possibilities for multi-level and   366
mixed-modelling for the GLM-Spectrum.   367

Term	Definition
STFT	The short-time Fourier transform of a time series, containing the spectrum computed within sliding window time segments across the data. Also called a time-varying spectrum.
Design Matrix	A matrix of regressors used to explain variability in observed data with a linear regression model.
Regressor	A single column of a design matrix containing explanatory variables relating to each individual observation.
Beta-estimates	A parameter estimate describing the linear relation between a regressor and the observed data. Also known as regression parameter estimates.
Beta-Spectrum	A vector of parameter estimates for a single regressor across the range of a frequency spectrum.
Contrast	A planned comparison between one or more parameter estimates.
cope	The result of a defined contrast between beta-estimates.
cope-spectrum	A vector of cope estimates for a single contrast across the range of a frequency spectrum.
varcope	The square of the standard error of the cope estimates.
varcope-spectrum	A vector of estimates for a single contrast across the range of a frequency spectrum.
t-statistic	The ratio of the departure of the estimated value of a contrast from its hypothesised value to its standard error.
t-spectrum	A vector of t-statistics for a single contrast across the range of a frequency spectrum.
Model-projected spectrum	A visualisation of a spectrum as predicted by a fitted GLM set at a particular set of covariate values.
First-Level GLM	A linear model for a single data recording that models variability across time segments in a STFT with a specified design- and contrast-matrix resulting in a set of beta-, cope- and t-spectra.
Group-Level GLM	A linear model for a group dataset combining a set of first-level GLM-Spectra. A group-level design- and contrast-matrix models variability in first-level beta or t-spectra across datasets resulting in a set of group-level beta-, cope- and t-spectra.

Table 1. Glossary of definitions for the GLM-Spectrum.

2.10   Non-parametric Permutations for Group GLM-Spectra

Null-hypothesis testing for a given contrast can be carried out with non-parametric permutations (Nichols and Holmes, 2001; Winkler et al., 2014). A null distribution of observed statistics is derived by recomputing the GLM after manipulating the design matrix in line with the null hypothesis. The observed group average is then compared to this null distribution and is 'significant' if it exceeds a pre-set critical threshold, such as the 95th percentile of the null distribution. Here, we perform non-parametric permutation using 'sign-flipping' for categorical regressors and using 'row-shuffling' for parametrically varying regressors.

In all cases, we permute the columns of the design matrix that are directly related to the relevant contrast whilst the remaining regressors are fixed (Draper and Stoneman, 1966; Winkler et al., 2014). The Draper-Stoneman approach can produce erratic results for small sample sizes and may be out-performed by more generally robust methods (Winkler et al., 2014), such as O'Gorman (2005) or Freedman and Lane (1983).

Non-parametric permutation testing could, in principle, be carried out to assess the results of a first-level GLM-Spectrum. In contrast to a group-level analysis, the first-level permutations would only assess whether a particular effect observed within a dataset could be expected to generalise to a wider sample of possible data observations from the same source. Moreover, the time segments in a first-level GLM-Spectrum are likely to exhibit strong autocorrelation (see section 2.4) which would need to be accounted for before any permutation testing could provide a valid result (Friston et al., 2000; Woolrich et al., 2001).

2.11   Software implementation and dependencies

The analyses in this paper were carried out in Python 3.9 with core dependencies of numpy (Harris et al., 2020), scipy (Virtanen et al., 2020) and Matplotlib (Hunter, 2007). MNE python (Gramfort, 2013) was used for EEG/MEG data processing with OSL[5] batch processing tools (Quinn et al., 2022). Python-meegkit[6] was used for the 'zapline' line noise removal algorithm (de Cheveigné, 2020). The spectrum analyses further depend on the Spectrum Analysis in Linear Systems toolbox (Quinn and Hymers, 2020) and glmtools[7]. All code used to run analyses and generate the figures in this paper are available online[8].

2.12   The LEMON Dataset

2.12.1   EEG Preprocessing

All data pre-processing was carried out using MNE-Python and OSL using the OSL batch pre-processing tools. Resting-state EEG recordings from 191 individuals of an open-source dataset (Babayan et al., 2019) were analysed. The raw data for each subject is a resting-state EEG recording from a 62-channel (61 EEG and 1 EOG) using a BrainAmp MR plus amplifier. The channels were in a 10-10 layout and referenced to FCz. Sixteen minutes of data were recorded in one-minute blocks alternating between eyes-closed and eyes-open resting-state. Data were acquired with a bandpass filter between 0.015 Hz and 1 kHz at a sampling frequency of 2500 Hz. The remaining acquisition details are reported in (Babayan et al., 2019).

---

[5]`https://github.com/OHBA-analysis/osl`
[6]`https://github.com/nbara/python-meegkit`
[7]`https://pypi.org/project/glmtools/`
[8]`https://github.com/OHBA-analysis/Quinn2022_GLMSpectrum`

The raw data were first converted from Brainvision files into MNE-Python Raw data   410
objects. The continuous data were bandpass filtered between 0.25 Hz and 125 Hz   411
using an order-5 Butterworth filter. Line noise was suppressed using a spatial filter   412
following the 'zapline' algorithm (de Cheveigné, 2020) as implemented in   413
python-meegkit. Bad channels were automatically identified using the   414
generalised-extreme studentized deviate (G-ESD;Rosner (1983)) routine to identify   415
outliers in the distribution of variance per channel over time. The data were then   416
resampled to 250 Hz to reduce space on-disk and ease subsequent computations.   417
Independent Component Analysis (ICA) denoising was carried out using a 30   418
component FastICA decomposition (Hyvarinen, 1999) on the EEG channels. This   419
decomposition explained an average of 99.2% of variance in the sensor data across   420
datasets. Independent components that contained non-neuronal signals such as blinks   421
were automatically identified by correlation with the simultaneous V-EOG channel. ICA   422
components linked to saccades were identified by correlation with a surrogate H-EOG   423
channel, i.e., the difference between channels F7 and F8. Between 2 and 7 'artefactual'   424
components were identified in each dataset, with an average of 2.66 across all datasets.   425
The two ICs that correlated strongest with the V-EOG and H-EOG channels were   426
separately retained for later use in the GLM design matrix.   427

The continuous sensor data were then reconstructed without the influence of the   428
artefactual V-EOG and H-EOG components. Bad segments were identified by   429
segmenting the ICA-cleaned data into arbitrary 2-second chunks (distinct from the   430
STFT time segments) and using the G-ESD algorithm to identify outlier (bad) samples   431
with high variance across channels. An average of 31 seconds of data (minimum 6   432
seconds and maximum 114 seconds) were marked as bad in this step. This procedure is   433
biased towards low-frequency artefacts due to the $1/f$ shape of electrophysiological   434
recordings. Therefore, to identify bad segments with high-frequency content, the same   435
procedure was repeated on the temporal derivative of the ICA-cleaned data. An average   436
of 27 seconds of data (minimum 2 seconds, maximum 109 seconds) were marked as   437
bad when using the differential of the data.   438

To retain consistent dimensionality across the group, any bad channels were   439
interpolated using a spherical spline interpolation (Perrin et al., 1989) as implemented   440
in MNE-Python. Finally, the spatial gradient between each channel and its distance   441
from the reference sensor (FCz), is attenuated by computing the surface Laplacian (or   442
current source density) of the sensor data. The surface Laplacian data is reference free   443
and has sharper spatial topographies than the raw EEG; though this is a complex   444
computation that is dependent on several hyperparameters, and which may reduce   445
sensitivity to deeper sources (Kayser and Tenke, 2015).   446

2.12.2   First-Level GLM-Spectrum   447

A 'first-level' analysis models the data within each individual participants EEG data.   448
The STFT is computed for each dataset using a 2-second segment length, a 1-second   449
overlap between segments and a Hanning taper. The 2-second segment length at the   450
sample rate of 250Hz gives a resolution of around 2 frequency bins per unit Hertz in   451
the resulting spectrum. The short-time magnitude spectrum is computed from the   452
complex valued STFT and the frequency bins ranging between 0.1Hz and 100Hz taken   453
forward as the dependent variable in the first-level GLM-Spectrum for that dataset. The   454
GLM design matrix is specified with six regressors (Figure 1). Two binary regressors   455
model intercept term for each of the eyes-open and eyes-closed time segments. The   456
third regressor is a z-transformed covariate describing a linear trend over time. This   457
regressor is included to model potential 'time on task' effects over the course of the   458
recording. Previous literature has reported that both alpha power and alpha frequency   459
may change over time within a single EEG recording (Benwell et al., 2019). A non-zero   460

	Eyes Open	Eyes Closed	Linear Trend	Bad Segs	V-EOG	H-EOG
C1: RestMean	0.5	0.5	0.0	0.0	0.0	0.0
C2: Open>Closed	1.0	-1.0	0.0	0.0	0.0	0.0
C3: Eyes Open	1.0	0.0	0.0	0.0	0.0	0.0
C4: Eyes Closed	0.0	1.0	0.0	0.0	0.0	0.0
C5: Linear Trend	0.0	0.0	1.0	0.0	0.0	0.0
C6: Bad Segs	0.0	0.0	0.0	1.0	0.0	0.0
C7: V-EOG	0.0	0.0	0.0	0.0	1.0	0.0
C8: H-EOG	0.0	0.0	0.0	0.0	0.0	1.0

Figure 1. An example first-level design matrix and contrast matrix for a single subject. The top matrix shows the GLM design matrix with individual regressors in columns and single sliding window time segments in rows. The table shows the contrast matrix with corresponding weightings for each regressor. The regressor correlations, singular-value spectrum and variance inflation factors for this design matrix are summarised in Supplemental section 7.5.

mean regressors for bad segments is computed from the sum of the number of 'bad'   461
samples within each STFT time segment. Finally, two further non-zero mean regressors   462
are computed from absolute value of the V-EOG and H-EOG independent component   463
time-courses.   464

A range of contrasts are specified to quantify critical hypothesis tests (see contrast   465
table in Figure 1). The overall mean is modelled by a contrast summing the eyes-open   466
and eyes-closed regressors together weighted by the proportion of ones in each   467
regressor (Contrast 1, Figure 1). A t-test between the spectrum in the eyes-open and   468
eye-closed conditions is specified with a differential contrast (weighted [1, -1], in the   469
direction of eyes-open minus eyes-closed; Contrast 5; Figure 1). Finally, separate   470
one-sample tests are specified for each covariate with contrasts containing a single 1 for   471
a given regressor (Contrasts 3 to 8; Figure 1). The model parameters were estimated   472
using the MPPI and no statistical assessment was carried out at the first-level.   473

2.12.3   Structural MRI Processing   474

Individual anatomical details were extracted from T-weighted structural MRI scans   475
(Babayan et al., 2019). All images were processed using the FMRIB Software Library   476
(Woolrich et al., 2009). Images were reoriented to standard Montreal Neurological   477
Institute (MNI) space, cropped, and bias-field corrected. FMRIB's Linear Registration   478

Tool (FLIRT; Greve and Fischl (2009); Jenkinson et al. (2002); Jenkinson and Smith   479
(2001)) was used to register to standard space before brain extraction was performed   480
using BET (Smith, 2002). Brain images were segmented into different tissue types   481
(grey matter, white matter and CSF) using FMRIB's Automated Segmentation Tool   482
(FAST; Zhang et al. (2001)). The voxel count for each tissue type was extracted and   483
normalised by the individual's total brain volume (also computed by FAST) to create a   484
percentage. The total brain volume and individual percentage of grey matter were   485
carried forward as group-level covariates in the GLM-Spectrum.   486

2.12.4 Group-Level GLM-Spectrum   487

We now carry out a "group-level" analysis to combine the first-level results and describe   488
between subject variability with another GLM. As described in section 2.12.2, the   489
cope-spectra of each first-level GLM was used as the dependent variable in the   490
group-level GLM. The group-level design matrix contained categorical regressors   491
coding the age group of each participant and covariates corresponding to variability in   492
participant sex, head size and relative grey matter volume (Figure 2). We have   493
modelled age as two distinct, categorical regressors as the LEMON dataset contains   494
participants recruited from either a young (20-40 years old) or an old (60-80 years   495
old) group. Age could equally be included as a single parametrically varying regressor   496
in a dataset that recruited from across a broad age range. A contrast was defined to   497
estimate the mean across all participants and a second to estimate the difference   498
between young and old participants. Finally, one-sample t-tests were specified for each   499
covariate to test whether the regression coefficient significantly differed from zero.   500

   The group-level design matrix was used to model each of the first-level contrasts.   501
The group model parameter estimates were computed using the MPPI. Statistical   502
significance in the group-level t-spectra was assessed using cluster-based   503
non-parametric permutations using sign-flipping or row-shuffle permutations. A cluster   504
forming threshold of p=0.001 was used (equivalent to t(205)=3.34) across all tests. A   505
spatial extent threshold of 1 was set to ensure that any cluster has at least 2 adjacent   506
points exceeding the cluster forming threshold.   507

	Young	Old	Sex	TotalBrainVol	GreyMatterVol
C1: Mean	0.69	0.31	0.0	0.0	0.0
C2: Young>Old	1.0	-1.0	0.0	0.0	0.0
C3: Young	1.0	0.0	0.0	0.0	0.0
C4: Old	0.0	1.0	0.0	0.0	0.0
C5: Sex	0.0	0.0	1.0	0.0	0.0
C6: TotalBrainVol	0.0	0.0	0.0	1.0	0.0
C7: GreyMatterVol	0.0	0.0	0.0	0.0	1.0

Figure 2. The group-level design matrix and contrast matrix. The matrix shows the design matrix with regressors in columns and individual first-level datasets in columns. The table shows the contrast matrix with corresponding weightings for each regressor. The regressor correlations, singular-value spectrum and variance inflation factors for this design matrix are summarised in Supplemental section 7.5. This group design matrix was used to to model variability across datasets in each of the first-level contrasts.

3 Results ⁠508

3.1 First-level covariate spectra on a central EEG channel ⁠509

Figure 2 summarises the first-level GLM-Spectrum analysis of a single channel (Pz) ⁠510
from an exemplar resting-state EEG recording. The pre-processed EEG time series ⁠511
(Figure 3A) was split into 2 second time segments with a 50% overlap (Figure 3B), ⁠512
modified by a Hann window (Figure 3C) and transformed into the frequency domain ⁠513
using a Short-Time Fourier Transform (STFT; Figure 3D). Each column of this STFT ⁠514
contains the time course of the magnitude at each frequency and constitutes the ⁠515
dependent variable in a first-level GLM. The first-level GLM (see methods ⁠516
section 2.12.2) models this variability over time in relation to the resting conditions, ⁠517
artefacts detected in the data and the electrooculogram (EOG). The final first-level ⁠518
design matrix had six regressors (Figure 3E) modelling the two resting-state ⁠519
conditions, a linear trend over time and three potential dynamic confounds. The full ⁠520
design matrix and contrast specification for the entire run can be seen in Figure 1. ⁠521

   The first-level GLM was fitted separately for each frequency bin using a standard ⁠522
ordinary least squares routine. The average magnitude spectra for the eyes-open and ⁠523
eyes-closed rest periods are quantified by two cope-spectra (Figure 3F) specified by ⁠524
first-level contrasts 3 and 4 (Figure 1). Both cope-spectra showed a 1/f-type structure ⁠525
and a prominent alpha peak around 9 Hz. The eyes-open > eyes-closed contrast (the ⁠526
regressor was coded to have ones for eyes-open and minus ones for eyes-closed; ⁠527
specified in contrast 5 in Figure 1) had negative values in the cope-spectrum indicating ⁠528
that spectral magnitude was larger in the eyes-closed condition across a range of ⁠529
frequencies, peaking around the alpha range (Figure 3G – top panel). The square of the ⁠530
standard error of the estimates is shown in the varcope-spectrum (Figure 3G – top ⁠531
panel) and indicates where the estimate of the mean was least certain. This roughly ⁠532
followed the shape of the spectra in Figure 3F, showing a clear alpha peak and a weak ⁠533
1/f trend. This is an example of a close relationship between cope and varcope ⁠534
estimates that can lead to large effects in the beta-spectrum being substantially less ⁠535
prominent in the t-spectrum. The final t-spectrum contained a full spectrum of t-values ⁠536
for the contrast between the two resting conditions (Figure 3H). The large magnitude, ⁠537
negative t-values in alpha and surrounding frequencies qualitatively indicated a greater ⁠538
magnitude in the eyes-closed condition. In sum, this shows a full spectrum perspective ⁠539
on the 'alpha reactivity' or 'alpha blocking' effect (Adrian and Matthews, 1934) that is ⁠540
most commonly assessed within a-priori frequency bands (Babiloni et al., 2011; Wan ⁠541
et al., 2018). ⁠542

3.2 First-level spectral analysis on whole head EEG ⁠543

So far GLM-Spectrum method has been applied to univariate data (i.e., single channel ⁠544
EEG data), but it can be readily extended to a full multichannel dataset. To model the ⁠545
GLM-Spectrum across channels, a separate GLM using the same design matrix was ⁠546
fitted to each channel and frequency bin. This provides a description of spectral effects ⁠547
over frequency and space. Accordingly, we extended the resting-state model to the ⁠548
61-channel whole head EEG recording. The design matrix and contrast specification ⁠549
were the same as the single channel analysis. ⁠550

   The beta-spectrum computed from the condition regressors showed the familiar 1/f ⁠551
slope and prominent occipital alpha features in both resting-state conditions. The GLM ⁠552
analysis was identical to the single channel results (Figure 3) but now can include ⁠553
spatial distributions alongside the frequency spectrum. Qualitatively, the eyes-open ⁠554
condition (Figure 4A) had a smaller alpha peak than the eyes-closed condition ⁠555
(Figure 4B). Both conditions had a similar topography in this subject. The t-spectrum ⁠556

Figure 3. First-level (i.e. within-session) GLM-Spectrum description during alternating eyes-open and eyes-closed resting-state from channel Pz in a single EEG recording.

A: A 32-second segment of pre-processed EEG time-course from sensor Pz.

B: EEG time-course segmented into 2-second sliding windows with 50% overlap.

C: Windowed data segments modified by a tapered Hann window function.

D: Short time-Fourier transform computed with the FFT of each windowed data segment. Each column of this matrix (change in magnitude of a single frequency over time) is the dependent variable to be described by the GLM.

E: The GLM design matrix containing condition, covariate and confound regressors. This is zoomed in section of the full design matrix in Figure 1, showing only rows corresponding to the data shown here.

F: The GLM beta-spectra for the two regressors modelling the spectrum during eyes-open and eyes-closed rest (contrasts 3 and 4 in Figure 1).

G: The cope- and varcope-spectrum for a differential contrast between the eyes-open and eyes-closed conditions as specified in contrast 5 in Figure 1.

H: The t-spectrum for the contrast in G.

of the contrast between eyes-open and eyes-closed rest showed a large, negative effect   557
peaking around the alpha range (Figure 4C) as seen in the single channel example   558
(Figure 3G). This difference had a spatial maximum in posterior-central regions,   559
replicating the occipital-parietal location of the alpha reactivity effect widely reported 560
in the literature (Babiloni et al., 2011; Wan et al., 2018).   561

    The linear trend showed substantial t-values around the alpha range, though its   562
model projected spectra suggest that this is a subtle effect (Figure 4D). The bad   563
segment regressor effect (Figure 4E) peaks at relatively low (<4Hz) and high (>25Hz)   564
frequency ranges. The size of this effect is visualised more intuitively in the model   565
projected spectrum (Figure 3F – bottom panel) which showed the substantial increase   566
in both a low- and high-frequency range. Finally, the V-EOG (Figure 4F) and H-EOG   567
(Figure 4G) covariates both showed large t-values in relatively low frequencies (around   568
1Hz). The V-EOG had a large negative effect around the alpha range, suggesting that   569
time segments with high V-EOG activity were associated with lower alpha magnitude.   570
In contrast, the H-EOG showed an additional positive effect in high frequencies   571
suggesting that segments with high H-EOG activity are associated with larger high   572
frequency spectral magnitude. In particular, the complex pattern of effects in the   573
V-EOG t-spectrum manifests as segments with high V-EOG activity showing a decrease   574
in alpha magnitude and an increase in alpha frequency.   575

Figure 4. GLM-Spectrum fits for alternating eyes-open and eyes-closed resting-state EEG for a single participant. Mean magnitude spectrum estimates for each channel and frequency bin. The topography (top right) provides location-colour coding used in the t-spectra throughout the figure. The colour range of each topography is set vary between plus and minus the maximum absolute value of the data plotted. The contrasts shown in this figure are detailed in supplemental section H.
A: Beta-spectrum for the eyes-open condition regressor. The topography shows the spatial distribution of spectral magnitude at 9 Hz
B: Beta-spectrum for the eyes-closed condition regressor, layout is same as in A.
C: t-spectrum for the contrast between the eyes-open and eyes-closed conditions.
D: t-spectrum spectrum for the linear trend covariate (top). Model-predicted magnitude spectra averaged across all sensors for the extrema of the predictor, which in the case of a linear trend regressor corresponds to the start and end of the scan (bottom).
E: t-spectrum spectrum for the bad segment confound (layout same as for D), model-projected spectra are shown for good and bad segments.
F: t-spectrum spectrum for V-EOG confound (layout same as for D), model-projected spectra are shown for the maximum and minimum observed V-EOG activity.
G: t-spectrum spectrum for H-EOG segment confound (layout same as for D), model-projected spectra are shown for the maximum and minimum observed, H-EOG activity.

3.3 Covariate effects are highly variable across datasets. ₅₇₆

Next, we build on the single subject exemplar result by exploring the effect of the ₅₇₇
covariate and confound regressors across 206 EEG recordings from the LEMON ₅₇₈
dataset. Firstly, we show a qualitative description of the model R-squared values and ₅₇₉
related effect sizes for each predictor variable. The group averages here are intended as ₅₈₀
illustrations and are not supported by inferential statistics. Firstly, the GLM-Spectrum ₅₈₁
was able to describe between 60% and 70% of the variance in the STFT, averaged ₅₈₂
across all participants and channels (Figure 5A). This value was highly variable across ₅₈₃
participants, particularly above 50Hz where the R-square values ranges between 20% ₅₈₄
and 80%. Secondly, Cohen's F^2 statistic was used to compute the marginal effect size ₅₈₅
of each predictor within the model (see section 2.7 for details). Modelling the two ₅₈₆
resting conditions separately, as opposed to using a single average, results in a group ₅₈₇
average effect size which peaks around the alpha frequency, though the effect in ₅₈₈
individual datasets was highly variable (Figure 5B). The effect size of the four ₅₈₉
covariates has a low group average but is, again, highly variable in individual datasets ₅₉₀
(Figure 5C). This variability was particularly prominent at higher frequencies and ₅₉₁
indicates the adaptive effects of the covariate regressors. These predictors have strong ₅₉₂
associations with the STFT in some individuals but not others. ₅₉₃

   To further illustrate the effect of including the continuous covariate predictors the ₅₉₄
frequency spectrum was computed for both the full model and a reduced model ₅₉₅
containing only the two condition terms (i.e., eyes-open and eyes-closed), excluding ₅₉₆
other covariates and confounds (Figure 5D). The inclusion of covariate regressors has a ₅₉₇
different pattern of effect across frequencies for each dataset. The difference between ₅₉₈
the full and reduced model is relatively small for datasets i and v indicating that the ₅₉₉
effect of the covariates was minimal for these recordings. In contrast, datasets ii and iv ₆₀₀
show moderate differences in low and high frequencies whilst iii shows a substantial ₆₀₁
difference between the full and reduced model. ₆₀₂

Figure 5. Effect of first-level confound variables on mean spectrum estimates.
A: The proportion of variance explained by the full model for all datasets. The values are averaged across channels and plotted across frequency. The grey lines represent the effect size spectra of individual datasets and the black line is the group average across all datasets.
B: Cohen's f^2 values for the eyes-open > eyes-closed contrast. Plotting style is the same as in A).
C: Cohen's f^2 values for the each of the four covariates. Plotting style is the same as in A).
D: Detailed visualisation of the average beta-spectra across all channels from five example datasets.

3.4   Group-level design matrix and contrasts   603

The GLM-Spectrum framework can be extended to group analyses by carrying a set of   604
first-level results to a second-level GLM (See methods section 2.9). This group-level   605
analysis models between-subject variability across independent first-level GLM-Spectra.   606
These multilevel, hierarchical models are well established in neuroimaging (Beckmann   607
et al., 2003; Friston et al., 2002; Friston, 2007; Woolrich et al., 2004), and the existing   608
theory applies to the GLM-Spectrum.   609

The group-level GLM was fitted to the first-level cope-spectra (Figure 6A) across all   610
datasets separately for each channel, frequency bin and first-level contrast (see   611
methods section 2.12.4). The group-level design matrix contained two condition   612
regressors modelling the mean across subjects for younger and older participants   613
separately and three z-transformed parametric covariates modelling between-subject   614
variability in sex, total brain volume and relative grey matter volume (Figure 6B). Two   615
group contrasts were defined alongside the main effects. One overall average that   616
modelled the sum of the young and old groups (Contrast 1; Figure 6B) weighted by the   617
number of participants in each group. A second contrast quantified the linear group   618
difference (Contrast 2; Figure 6B). Finally, a set of main effect contrasts were also   619
defined for each regressor (Contrasts 3 to 7; Figure 6B). The final fitted model contains   620
a group-level beta-spectrum that describes the linear effect of a group regressor across   621
separate datasets. The group-level GLM returns beta-spectra for the overall mean   622
spectrum (Figure 6C) as well as contrasts and main effects (Figure 6D). At the   623
group-level, the error bars now indicate the standard error of the fitted mean across   624
participants (rather than across STFT time windows, as in the first-level).   625

Figure 6. Group-level GLM-Spectrum describing a group mean and variability associated with two between-subject factors.
A: The data modelled by the group-level GLM are the first-level GLM-Spectra across all participants. A GLM is fit separately for each channel, frequency bin and first-level contrast. **B:** The group-level design matrix. The first and second regressors are categorical predictors coding young and old participants. **C:** The group-level estimate obtained from the first contrast coding for the weighted average of the two regressors (contrast 1). Error bars indicate the varcope of the group contrast. **D:** The group-level effects for the difference between young and old participants (contrast 2, weighted [1, -1]) and the three covariate contrasts (contrasts 5, 6 and 7), quantifying the effect of sex, total brain volume and normalised grey matter volume respectively. Error bars indicate the varcope of the group contrast.

3.5   Group effects of age and eyes-open versus eyes-closed rest

Next, we explored how the GLM-Spectrum varies across resting conditions and participant age. Therefore, two main-effect contrasts and their interaction were explored. Two-tailed, non-parametric, cluster (with clusters formed over frequencies and sensors) permutation tests were used to establish statistical significance for all group-level analyses.

We first computed the group average of the within-subject difference between eyes-open > eyes-closed rest. Specifically, we computed the *Mean* group-level contrast (Contrast 1; Figure 6B) on the *eyes-open > eyes-closed* first-level contrast (Contrast 2; Figure 1). Non-parametric cluster permutation testing indicated two significant clusters (Figure 7A) that together cover the whole frequency range investigated here. The first cluster showed a negative effect with greater magnitude in the eyes-closed condition. This cluster spanned the lower frequency range (approximately 30Hz and lower) across almost all channels, though the effect peaked around the alpha range in occipital channels. The posterior peak within this cluster matched the expected occipito-parietal source of the alpha reactivity effect (Wan et al., 2018). The second cluster showed a positive effect indicating higher magnitude in the eyes-open condition. This cluster spanned the higher frequency range (10-100 Hz) across all channels with the largest effect in bilateral frontal regions. This cluster may partially reflect residual eye movements that have not been accounted for by ICA or the first-level artefact regression. The t-statistics in a low frequency range in frontal sensors are strongly modulated by the inclusion or exclusion of the EOG based confound regressors (see supplemental section 7.7).

Further, we computed the difference in the time-averaged first-level spectra between the younger and older adults. This corresponds to computing the *Young > Old* group-level contrast (Contrast 2; Figure 6B) on the *Overall Mean* first-level contrast's cope-spectrum (Contrast 1; Figure 1). Non-parametric permutations on this showed three significant clusters. The first cluster indicated a positive effect in which younger participants had larger power than older participants. The cluster covered low frequencies (<8 Hz) and all channels peaking in frontal and occipital channels (Figure 7B). The direction of this effect is consistent with previously reported decreases in delta and theta power in older adults (Klimesch, 1999). The second cluster indicates greater beta-frequency magnitude for older adults. The cluster spans between 15 and 30Hz and peaks in bilateral central sensors. This finding replicates literature showing higher beta power in older adults (Xifra-Porxas et al., 2019). Finally, the third cluster indicates greater magnitude for older participants in a cluster between 35 and 100Hz that peaks in frontal sensors. In addition, the change in overall spectral shape qualitatively supports indications that older adults have a flatter 1/f slope in the EEG spectrum (Merkin et al., 2022; Voytek et al., 2015), though we did not explicitly quantify 1/f slope here.

No significant cluster for an age difference was identified in the alpha range, though individual t-statistics reach around 5. This null effect may relate to the choice of sensor normalisation during pre-processing (Klimesch, 1999). In addition, the choice of a 0.5 to 100 Hz frequency range may be too wide to assess any relatively narrow band alpha changes in the presence of large broadband effects in higher frequencies.

Finally, we explored whether the within-subject difference in eyes-open and eyes-closed resting-state changed between the younger and older adults. Specifically, this corresponds to the *Young > Old* group-level contrast (Contrast 2; Figure 6B) computed on the *eyes-open > eyes-closed* first-level contrast (Contrast 5; Figure 1). Non-parametric permutation testing identified a single significant cluster with a negative t-statistic (Figure 7C). This indicates the presence of an interaction effect in which older adults show a larger difference in the eyes-open > eyes-closed contrast.

Figure 7. Higher order GLM-Spectrum group-level results. The topography (top right) provides location-colour coding used in the t-spectra throughout the figure. In all cases, statistical significance is assessed by sensors x frequency cluster permutation testing and is indicated in grey. The colour range of each topography is set to vary between plus and minus the maximum absolute value of the data plotted.
A: The within-subject contrast between eyes-open and eyes-closed conditions, averaged across all participants. Model-predicted magnitude spectra averaged across all sensors for the extrema of the predictor (bottom).
B: The between-subject difference in average magnitude between young and old participants. Layout is the same as for A.
C: The interaction effect exploring whether the eyes-open>eyes-closed contrast varies between young and old participants. Layout is the same as for A.
D: The averaged GLM-Spectra for the two conditions and two groups.

Interestingly, there is no indication of an interaction effect in the low to mid alpha range. The interaction can be qualitatively summarised by plotting the beta-spectrum separately for each of the underlying four mean levels (Figure 7D).

3.6 Group average of first-level cope-spectra.

We explored the group averages of each first-level covariate regressor. The first-level linear trend regressor is expected to be sensitive to slow drifts throughout the recording. The t-spectrum of the *Mean* group-level contrast (Contrast 1; Figure 6B) computed on the *Linear Trend* first-level contrast (Contrast 5; Figure 1) showed four significant clusters (Figure 8I) with a mix of increases and decreases across space and frequency. Broadly these clusters showed a decrease in magnitude over time in both low frequencies (0.5-4Hz) and high frequencies (20-100Hz) peaking in occipital posterior channels. In contrast, an increase in magnitude over time was found in a low theta/alpha range (3-9Hz) and high frequencies (15-100Hz) peaking in frontal sensors. The presence of bad segments was associated with a single, strong positive effect indicating increased magnitude in the EEG during marked bad segments. The *Mean* group-level contrast (Contrast 1; Figure 6B) computed on the *Bad Segments* first-level contrast (Contrast 6; 1) showed a strong positive effect across all frequencies and across all channels (Figure 8B).

Figure 8. Group-level GLM-Spectrum results for each first-level regressor. The topography (top right) provides location-colour coding used in the t-spectra throughout the figure. In all cases, statistical significance is assessed by sensors x frequency cluster permutation testing and is indicated in grey. Topographies for the largest three significant clusters are shown above each plot spectrum. The colour range of each topography is set to vary between plus and minus the maximum absolute value of the data plotted.
A: The group-level average of the first-level linear trend regressor: the group average GLM t-spectrum (top) and model-predicted magnitude spectra averaged across all sensors for the extrema of the regressors (bottom). **B:** The group-level average of the first-level bad segments regressor, layout is the same as in A. **C:** The group-level average of the first-level V-EOG regressor, layout is the same as in A. **D:** The group-level average of the first-level H-EOG regressor, layout is the same as in A.

Finally, we computed the *Mean* group-level contrast (Contrast 1; Figure 6B) computed on the *V-EOG* and *H-EOG* first-level contrasts separately (Contrast 7 and 8; Figure 1). Three clusters indicated that increased variance in the V-EOG is associated with both increases and decreases in magnitude of the EEG (Figure 8C) One positive effect impacted all sensors and all frequencies (though not always simultaneously) showing the wide-ranging impact of eye movements on the spectrum. Two clusters showed negative effects in the alpha range (around 9Hz) and its harmonic (18Hz) in posterior sensors. This effect indicates a decrease in alpha when eye movements are largest. Increased variance in H-EOG time series was associated with increased magnitude across nearly all sensors and frequencies, as summarised in a single, positive statistical cluster (Figure 8D).

These effects demonstrate that the first-level covariates are associated with consistent group-level effects. However, the results must be interpreted in the context of the variability in first-level effect sizes (Figure 5). Each first-level covariate effect was highly variable in the individual datasets, ranging from no effect in some participants to a covariate effect that exceeded the eyes-open > eyes-closed difference in others (Figure 5B and C). As such, we might not expect to see one or more of these effects in a given single dataset, though the group effects are strong.

Figure 9. Between-subject group covariate effects on the overall first-level mean.
The topography (top right) provides location-colour coding used in the t-spectra throughout the figure. In all cases, statistical significance is assessed by sensors x frequency cluster permutation testing and is indicated in grey. The colour range of each topography is set range between plus and minus the maximum absolute value of the data plotted.
A: The between-subject difference effect of sex on the average magnitude between females and males. The model projected spectra visualise the group differences (bottom).
B: Same as A for total brain volume. The model projected spectra visualise the spectrum at the smallest and largest head size.
C: Same as A for normalised grey matter volume. The model projected spectra visualise the spectrum at the smallest and largest grey matter volume.

3.7 Group-level covariate effects

The results so far have combined and contrasted group averages of the first-level results. One possible group-level confound for the age contrast is that the LEMON dataset contains a different number of male and female participants which are not perfectly balanced across age groups. A separate group regressor indicating the reported sex of each participant was included to model between-subject variability relating to this factor, effectively partialling it out from the main age effect of interest in each group contrast. We visualise the overall effect of participant-reported sex on the first-level cope-spectra (averaged across eyes-open and eyes-closed resting-state); this corresponds to the *Sex* group-level contrast (Contrast 5; Figure 6B) computed on the *Overall Mean* first-level contrast (Contrast 1; Figure 1). A single significant cluster identified stronger spectral magnitude in female participants between 1 and 48 Hz, peaking around the alpha and beta frequency ranges (Figure 9A). Increased power in females relative to males has been previously reported in the EEG literature (Aurlien et al., 2004; Zibrandtsen and Kjaer, 2021). Further work is required to distinguish whether this is a true neuronal difference or reflects simpler anatomical differences such as skull thickness.

Between subject variability associated with two anatomical covariates was modelled at the group-level. The total brain volume of each participant and the proportion of grey matter relative to total brain volume. As before, the inclusion of these regressors

ensures that the reported group effects are not biased by these anatomical factors. We   734
separately computed the *TotalBrainVol* and *GrayMatterVol* group-level contrasts   735
(Contrasts 6 and 7; Figure 6B) on the *Overall Mean* first-level contrast (Contrast 1;   736
Figure 1). Non-parametric permutation testing did not identify any significant effects   737
for either overall brain volume or relative grey matter volume (Figure 9B and C).   738
Though these are null effects, the inclusion of these regressors in the group model   739
enables a more refined interpretation of the other results. The inclusion of these   740
confounds means that any variance they might explain can not be attributed to one of   741
the other regressors. Specifically, this increases our confidence that the differences   742
between younger and older adults are not caused by correlated variability in head size   743
or relative grey matter volume.   744

4 Discussion

We have outlined the theory behind the GLM-Spectrum and provided a tutorial overview of its application. We illustrated a practical application for the use of the GLM-Spectrum, using an open EEG dataset to simultaneously quantify and contrast the spectrum of two alternating resting-state conditions whilst regressing out the effect of artefacts including bad segments and eye movements. Both artefact types were associated with a strong group effect but diverse effects at the first-level Of particular interest is the alpha peak in the spectrum of regression coefficients of the V-EOG regressor. This is likely a true neuronal effect linked to blinking that is not removed by ICA but can be explicitly modelled by the GLM-Spectrum. Finally, we extended our analysis to the group-level and explored the spectral differences between older and younger adults, whilst accounting for the effects of sex, brain volume and relative grey matter volume Older adults have lower magnitude in the theta range (3-7 Hz) and higher magnitude in the beta and gamma ranges (>15 Hz). A range of within- and between-subject effects were explored and, crucially, we showed that the reported age effect is robust to differences in participant sex, head size or relative grey matter volume.

4.1 A comprehensive framework for spectrum analysis

The GLM-Spectrum is a practical combination of two well-established methodologies that modernises the statistics underlying the time-averaged periodogram, a long-standing and standard spectral estimation method (Bartlett, 1948, 1950; Welch, 1967). Specifically, we utilise multi-level general linear modelling (Friston, 2007; Woolrich et al., 2004), non-parametric permutation testing (Nichols and Holmes, 2001; Winkler et al., 2014), contrast coding and confound regression to extend the scope of classical time-averaged spectrum estimators.

This approach is generalisable to a huge range of analyses. In principle, the GLM-Spectrum could be used in place of Welch's periodogram or other time-averaged spectrum estimate in any analysis pipeline. A very simple GLM-Spectrum analysis could be configured to be exactly equivalent to these standard approaches. In the simplest case, without first-level covariates the GLM-Spectrum provides a formal framework for multivariate whole head group analysis of power spectra. Moreover, GLM-Spectrum allows for linear denoising of spectrum estimates in datasets where simultaneous recordings of potential artefact sources are available, or artefact time courses can be derived. In addition, covariate effects and contrasts can be readily defined to quickly compute spectra associated with specific external dynamics. For example, an early application of this method has used a GLM-Spectrum to compute power spectra associated with dynamic whole-brain functional networks in MEG (Gohil et al., 2022).

4.2 Covariate and confound regression for spectrum analysis

The GLM-Spectrum can characterise spectral changes associated with covariates and potential artefact sources. Standard ICA denoising removes artefacts that share the time-course of the artefact channel. In contrast, confound regression is exploratory across the spectrum. Denoising can be applied to any frequency band with dynamics associated with the segmented artefact time-course irrespective of the original spectrum. For example, the V-EOG blink artefact has a classic low-frequency response that can be attenuated by removing correlated independent components. However, eye blinks are also associated with relatively prolonged changes in alpha and beta power (Liu et al., 2020). In the context of this paper, we consider this to be an 'indirect'

artefact; it is spatially and spectrally separated from the artefact source and is unlikely   792
to have arisen from volume conduction. The GLM-Spectrum can detect these   793
differences and remove their effect from the overall mean. As such, it could not have   794
been detected or removed by ICA denoising. In another context, this might form the   795
contrast of interest, but in this case, we apply confound regression to minimise the   796
effect of eye movements and blinks on the eyes-open > eyes-closed condition contrast.   797

4.3   Limitations of the GLM-Spectrum model   798

As outlined in the main text, the parameters of a model are only valid if the underlying   799
assumptions are met. The GLM has several relevant assumptions for the spectrum   800
analysis presented here, particularly at the first-level. In detail, the GLM assumes that   801
the residuals of the model are independently and identically distributed. The presence   802
of any temporal autocorrelation in the residuals indicates that the parameter estimates   803
must be interpreted with caution as this assumption has been violated. Future work can   804
account for this shortcoming by building on similar work in fMRI.   805

   The covariate and confound regressors in a GLM-Spectrum model dynamics over   806
time in a highly simplified sense. This approach is appropriate to quantify relatively   807
slow dynamics, on timescales of seconds, in the context of a spectrum estimator that   808
already utilises sliding time segments for spectrum estimation. The sliding windows are   809
tuned for spectral resolution. They have fixed and arbitrary length and may not   810
accurately reflect the true timescale of dynamics in the covariate variables. As such,   811
limited conclusions about underlying dynamics can be made from a GLM-Spectrum.   812
We can only say that a dynamic relationship existed at the specific timescale selected   813
for spectrum estimation. If precise temporal dynamics are of interest, a more advanced,   814
window-free method such as the Hidden Markov Model (Quinn et al., 2019, 2018;   815
Vidaurre et al., 2018, 2016) or Empirical Mode Decomposition (Huang et al., 1998)   816
might be more appropriate.   817

4.4   Conclusion   818

The GLM-Spectrum builds on methodologies that are all well established in the field.   819
The novelty of this work is to bring modern statistics and classical spectrum estimation   820
together into a single framework and to thoroughly explore the theoretical,   821
computational, and practical challenges of its use. The result is an approach for   822
spectrum analysis across the whole head and frequency range with the flexibility to   823
generalise to a huge variety of research and engineering questions.   824

5 Funding & Acknowledgments

This project was supported by the Medical Research Council (RG94383/RG89702) and by the NIHR Oxford Health Biomedical Research Centre. The Wellcome Centre for Integrative Neuroimaging is supported by core funding from the Wellcome Trust (203139/Z/16/Z). A.C.N. is supported by the Wellcome Trust (104571/Z/14/Z) and James S. McDonnell Foundation (220020448). M.W.W. is supported by the Wellcome Trust (106183/Z/14/Z; 215573/Z/19/Z). A.C.N. and M.W.W. are further supported by an EU European Training Network grant (euSSN; 860563). This research was funded in whole, or in part, by the Wellcome Trust . For the purpose of open access, the author has applied a CC BY public copyright licence to any Author Accepted Manuscript version arising from this submission.

The computations described in this paper were performed using the University of Birmingham's BlueBEAR HPC service, which provides a High Performance Computing service to the University's research community. See `http://www.birmingham.ac.uk/bear` for more details.

6 Author Contributions

AQ: Conceptualization, Methodology, Software, Formal analysis, Data Curation, Project administration, Writing - Original Draft, Writing - Review & Editing, Visualization. LA: Conceptualization, Methodology, Writing - Review & Editing. CG: Conceptualization, Methodology, Writing - Review & Editing. OK: Methodology, Writing - Review & Editing. JP: Formal analysis, Writing - Review & Editing. CZ: Formal analysis, Writing - Review & Editing. ACN: Writing - Review & Editing, Supervision. MWW: Conceptualization, Methodology, Writing - Original Draft, Writing - Review & Editing, Supervision.

7 Supporting information

7.1 Time-Averaged Periodogram Estimation

We start by reviewing the definition of the established method for windowed 851
periodogram estimation. The discrete Fourier transform (DFT) can be used to map a 852
series of data points from the time domain into the frequency domain. The frequency 853
domain representation is known as a spectrum and describes how the variance in the 854
data is distributed across frequencies according to a linear basis set. The DFT computes 855
the frequency spectrum $Y(f)$ from an input time series of real values at discrete time 856
points $y(t)$. 857

$$Y(f) = \sum_{t=0}^{N-1} y(t)e^{\frac{-i2\pi ft}{fs}} \tag{18}$$

Where t is a discrete time point, f is a discrete frequency, fs is the sampling 858
frequency in Hz and N is the number of data points. The output, $Y(f)$, is a 859
complex-valued array containing the estimate of the spectrum. In practice, the 860
computationally efficient Fast Fourier Transform (FFT; Cooley and Tukey (1965)) 861
implementation of the DFT is applied by most software packages. We will use the FFT 862
for this section, as it refers to the algorithm that is most commonly used in practice. 863

The mathematics underlying the FFT works with an infinite time series. However, 864
the data from real measurements are finite. Therefore, the FFT must implicitly assume 865
that the time-limited input data, $y(t)$, repeats infinitely many times. The combination 866
of this repetition and the discrete sampling of the time-series $y(t)$ leads to the 867
frequency output of the FFT being a linearly spaced axis of N frequency values 868
spanning between $-\frac{fs}{2}$ to $+\frac{fs}{2}$. In addition, the discontinuities between repetitions 869
lead to an effect known as spectral leakage, which spreads power contained in one 870
frequency bin to its neighbours. Finally, the computational efficiency of the FFT relies 871
on the input data length N being an integer power of 2. If it is not, then the routine 872
will zero-pad the length of the input up to a power of 2. This padding causes further 873
sharp changes and discontinuities that can lead to spectral leakage. 874

The impact of the spectral leakage is reduced by applying a tapered window 875
function designed to flatten the data at the start and end of each segment to minimise 876
discontinuities between repetitions. Here, we modify equation 18 to multiply a window 877
function $w(t)$ with the data (point-by-point) during the FFT: 878

$$Y(f) = \sum_{t=0}^{N-1} w(t)y(t)e^{\frac{-i2\pi ft}{fs}} \tag{19}$$

There is a huge range of possible window functions that provide different profiles of 879
spectral leakage and sensitivity. The Hamming and Hann windows (used by MatLab's 880
'pwelch' function[9] and SciPy's 'scipy.signal.welch' function [10], respectively) are two 881
commonly applied options which offer reasonable narrowband resolution. More 882
advanced tapering can be applied using discrete prolate spheroid sequences (DPSS) to 883
create a Multi-Tapered Spectrum estimate (Prerau et al., 2017; Thomson, 1982). 884

Y(f) is complex-valued, with its real and imaginary parts reflecting the sine and 885
cosine components of the Fourier transform. The phase and magnitude of each 886

---

[9]https://www.mathworks.com/help/signal/ref/pwelch.html
[10]https://docs.scipy.org/doc/scipy/reference/generated/scipy.signal.welch.html

frequency component can be computed from these complex values, though spectrum   887
analyses most commonly use the magnitude. We can take the absolute value of $Y(f)$ to   888
create a *magnitude spectrum* $S_y(f)$.   889

$$S_y(f) = |Y(f)| \tag{20}$$

Similarly, a power spectral density (sometimes just called a power spectrum) can be   890
calculated by taking the squared absolute value normalised by the data length: 891

$$P_y(f) = \frac{|Y(f)|^2}{N} \tag{21}$$

$P_y(f)$ is a real-valued estimate of the spectral density of a signal, sometimes known   892
as a periodogram. This periodogram provides a relatively simple spectrum estimation   893
but has a further shortcoming. Only one estimate for the power at each frequency is   894
calculated, irrespective of the length of $y(t)$. This means that we have no information   895
about the variance around that estimate, and the estimate does not improve if we   896
include more data.   897
A better estimator is the Time-Averaged Periodogram, introduced by Maurice   898
Bartlett (Bartlett, 1948, 1950) and refined by Peter Welch (Welch, 1967). These   899
methods are commonly used and ensure that the noise level in the periodogram   900
reduces as the length of the input data increases by a method of ensemble averaging (at   901
the expense of information about low frequencies). This splits the input into a set of   902
$k = 1, 2, \ldots K$ segments (i.e., time windows) each containing $t = 1, 2, \ldots T$ samples and   903
computes the FFT of each to produce a short time Fourier transform (STFT):   904

$$S_y(f, k) = \sum_{t=1}^{T} w(t) y(t, k) e^{\frac{-i 2 \pi f t}{f s}} \tag{22}$$

The input for each FFT is now the k-th segment of the continuous input $y(t)$, which   905
we denote with $y(t, k)$. The output matrix $Y(f, k)$ contains the STFT, which describes   906
how the spectrum changes in power across the K segments. A time-varying magnitude   907
spectrum can be computed by taking the absolute value of the STFT.   908

$$S_y(f, k) = |Y(f, k)| \tag{23}$$

Similarly, a time-varying power spectral density is computed from the squared   909
absolute of the STFT.   910

$$P_y(f, k) = \frac{|Y(f, k)|^2}{N} \tag{24}$$

Finally, the time-averaged periodogram is then the average of the time-varying   911
power spectral density across segments. If the previous computations included the   912
windowing function $w(t)$ and overlapping time segments, then this is Welch's power   913
spectral density estimate (Welch, 1967).   914

$$Pwelch_y(f) = \frac{1}{K} \sum_{k=1}^{K} P_y(f,k) \qquad (25)$$

Welch's time-averaged periodogram now has the property that the noise level of the estimate decreases with increased data length, since more input data provides a larger number of segments for the central averaging step. It is still an imperfect estimator that has been subject to criticism (Prerau et al., 2017; Thomson, 1982) but it is practical, straightforward to compute, and in wide use across science and engineering.

The real-valued power spectrum may additionally be scaled by a log-transform to produce a log-power spectrum $log(P_y(f,k))$. This can be desirable as the power spectrum is strictly positive and tends to have a strongly non-Gaussian distribution, whereas the log-power spectrum is not strictly positive and tends to have a more Gaussian distribution (See supplemental section 7.2).

Several key parameters must be set by the user when computing a spectrum in this way. These values affect the range and resolution of the spectrum and must be chosen with care. Briefly, there are three main considerations. Firstly, longer segment lengths (T) will increase the frequency resolution (number of bins per Hertz). Secondly, faster data sampling rates allows higher frequencies to be estimated (by increasing the Nyquist range). Finally, increasing the length of the input time-series for a given segment length will increase the number of segments in the average, reducing the impact of noise. These choices are discussed in full in Supplemental section 7.3.

7.2 STFT Data Distributions

The general linear model used here expects the dependent variable (the time-varying spectrum) and residuals to follow a Gaussian distribution. Whilst small deviations are permissible, the model fit and any subsequent statistics may be invalid if either is strongly non-Gaussian. This is a concern for the GLM-Spectrum as power values in a standard PSD tend to be non-Gaussian; they are strictly positive and squared (see equation 24). Figure 10A shows an example power spectrum for a single example subject. The second column shows a strongly skewed distribution of power values over time segments for a single channel and frequency. This skew persists into the distribution of residuals as well, indicating that the model assumptions are likely to be violated for when using PSD estimates as the dependent variable in a GLM.

In this paper, we fix this violation by using the magnitude spectrum rather than the power spectrum. Whilst the magnitude spectrum is less commonly used and has less clear mathematical properties [11], though the distribution of magnitude estimates is more Gaussian than for power estimates. Figure 10B shows an example magnitude spectrum, its data distribution and its residual distribution. All are better distributed than the PSD example in Figure 10A. Another option would have been to use the log-power spectrum, which also has a well-behaved Gaussian distribution Figure 10C.

Here, we restored the GLM model assumptions through a data-transform however a more general solution could be to use a model that is robust to different data and residual distributions. Future work could explore using a Generalised Linear Model which can describe skewed power distributions with an appropriate link function (Nelder and Wedderburn, 1972).

---

[11]The relation between the sum-square of the time-domain data and the integral of the spectrum does not hold for a magnitude spectrum.

Figure 10. Distribution of the magnitude, power and log-power spectra for an example dataset.
A: The power spectrum across frequency and channels, the distribution of power values over time segments and the distribution of residuals after fitting a GLM-Spectrum **B:** As A, for the magnitude spectrum. The data and residual distributions are substantially more Gaussian in shape. **C:** As A for the log-power spectrum. The data and residual distributions are more Gaussian than the power and magnitude spectra.

7.3 Parameter settings and resolution in periodograms ₉₅₆

When estimating power spectra with a time-averaged approach such as Welch's   956
Method, three parameters are of particular interest: the sampling rate, the length of
the window in which the data will be divided, and the length of the data. Changing
these parameters can affect the resolution of the spectrum and how many segments are
included in the average.

Segment Length. The length of the time segments that the data is divided into
influences the resolution of the underlying FFT result. In general, more frequencies are
estimated from longer time segments. So, increasing window length whilst holding
other parameters constant will result in a larger number of frequency bins in the final
spectrum estimate. The resolution in Hz can be computed by dividing the segment
length by the sample rate of the data

$$\delta f = \frac{N}{fs} \tag{26}$$

For example, a time series with 512 data points sampled at 128Hz would have a
frequency resolution of 4Hz. Similarly, the lowest frequencies that can be reliably
extracted from the time-series are also dependent of the window length. Frequencies
that are slower than the window period cannot be extracted. In general, it is
recommended to estimate power of an oscillatory signal across several cycles to reduce
the signal-to-noise ratio of the estimation (Cohen, 2014). Therefore, increasing the
window size will assess lower frequencies more reliably (Figure 11A).

There is an additional subtlety in some implementations of the FFT that means that
the data length does not necessarily equal the length of the computed FFT. For
example, the scipy implementation of Welch's method contains parameters for segment
length (nperseg) and FFT length (nfft). These are assigned equivalent values by
default, but if they are different to the nfft parameter should be used instead of N to
compute the frequency resolution.

Sampling Rate. The FFT returns estimates at equally spaced frequencies from 0Hz
to one half of the sampling rate of the data Nyquist Frequency. The 0Hz component is
known as a 'direct current' or DC offset and contains the average of all samples in the
segment being analysed. The Nyquist frequency is the fastest observable frequency in
the dataset and is one half of the sample rate. As such, increases in the sampling rate,
whilst holding other parameters constant, will in result in larger frequency spacing and
a lower resolution (Figure 11A). The reason for this is that the same number of
frequency bins must cover a larger frequency range. In reverse, this means that
decreasing the sampling rate while holding the window length constant results in a
smaller frequency spacing and higher spectral resolution.

Figure 11. Influence of parameter choice on time-averaged magnitude spectrum estimates.
A: The effect of increasing segment length on the spectrum estimate. Longer segment lengths have a higher frequency resolution. **B:** The effect of increasing sample rate on the spectrum estimate. Faster sample rates have higher Nyquist frequencies and lower frequency resolution. **C:** The effect on increasing the length of the analysed data set. Longer datasets have more segments contributing to the central average and are less affected by noise.

Importantly, increasing the frequency spacing is not always better because smaller bins might result in a noisier estimation of the power spectrum (Figure 11B). Small variations in the (intrinsic) frequency of the oscillatory signals - that are in most cases not of particular interest - might be represented by power in various of these small frequency bins whereas larger frequency bins smooth across these smaller, less relevant variations. This results in a smoother power spectrum.

Length of the overall time-series. The length of the data determines the number of windows in which the time course is divided by Welch's Method before averaging across power spectra. A higher number of windows results in averaging across a larger number of power spectra which in turn results in a better signal-to-noise ratio of the overall power estimation (Figure 11C). In general, considering more data is preferable because the average of a larger number of window-power spectra should result in an estimation closer to the true average power spectrum according to the law of large numbers. Importantly, dynamic fluctuations in oscillatory power over the time course might introduce meaningful variations in the mean power spectrum that cannot be accounted for by Welch's Method and result in more complex, and less peaky power spectra.

7.4   **Fast standard-error estimation.**   1008

The slowest computation in the GLM-Spectrum is obtaining the standard error of the   1009
parameter estimates, known as varcopes. This involves large matrix multiplications that 1010
are typically repeated across many tests. However, only the diagonal output is used in   1011
the eventual varcope estimate. Standard computing approaches will evaluate every   1012
single cell within these matrices even though majority contribute to the off-diagonals   1013
and are eventually discarded. This is not a large computational expense for single tests 1014
but quickly becomes prohibitive when computing large numbers of test together in   1015
matrix form. We use the numpy implementation of Einstein summation conventions   1016
(Numpy.Einsum — NumPy v1.23 Manual,   1017
n.d.)(https://numpy.org/doc/stable/reference/generated/numpy.einsum.html) to   1018
compute the most efficient computational path for the varcope evaluation. In practice,   1019
this avoids carrying out intermediate multiplications which would eventually be   1020
dropped when extracting the diagonal at the final step. The code for the standard   1021
'DotDiag' approach and the new Einsum approache is as follows: 1022

We explore the difference this makes to computation time by running 100 simulated   1023
GLMs with each method for each of four datasets. The first dataset was a single GLM   1024
that might represent a single channel and frequency bin. The second is a full   1025
GLM-Spectrum across 100 frequency bins whilst the third and fourth were   1026
GLM-Spectra across 60 or 204 channels, representing common EEG and MEG data   1027
sizes. The GLM was computed 100 times for each case and the results are summarised   1028
in Figure 12. The computation was equally fast for both methods in the single-test case 1029
but the einsum approach can lead to a 1000x speed up in computation time in the   1030
larger datasets. This is convenient for in any case but is essential for making   1031
non-parametric permutation statistics of GLM-spectra practically feasible.   1032

**Figure 12. Computation times for varcope estimation across different data sizes
with a standard or einsum based method.** Each data size and method was computed
for random data 100 times and the distribution of its timing shows as a boxplot.

7.5   GLM Design Efficiency

Figure 13. The regressor correlations, singular-value spectrum and variance inflation factors for the first-level GLM-Spectrum design matrix for a single dataset. This analysis indicates that there is some indication of co-linearity but not at a problematic level as the smallest singular-values do not reach zero, and the variance inflation factors do not exceed 5.

Figure 14. The regressor correlations, singular-value spectrum and variance inflation factors for the group-level GLM-Spectrum design matrix. This analysis indicates that there is some indication of co-linearity but not at a problematic level as the smallest singular-values do not reach zero, and the variance inflation factors do not exceed 5.

7.6   Confound Regression   1034

Figure 15A shows an example design matrix for this case. The first regressor is a   1035
constant vector of ones and a second regressor tracks the time segments in which the   1036
artefact occurs. In isolation, the constant regressor models the data mean (including   1037
the time periods that the artefact occurs), but this changes when it is alongside a   1038
regressor with non-zero mean in the same model. The constant regressor now models   1039
the intercept; this is the expected value of the data when the artefact regressor is zero   1040
(Figure 15B – contrast 1 'Intercept'). In turn, the artefact regressor can be interpreted   1041
as the difference between the value of the intercept and the mean of the segments   1042
indicated in the artefact regressor (Figure 15B – contrast 2 'Artefact Effect'). We can   1043
recover the mean of the artefact segments by summing the parameter estimates for   1044
both regressors (Figure 15B – contrast 3 'Artefact Mean').   1045

   To illustrate the quantities estimated by the simple model and the confound   1046
regression, we generate a simulation of 128 data points centred around a 'true' mean of   1047
1 with a small number of outliers centred around 4 (Figure 15C). The simple mean   1048
estimated by the 'mean-only' design is biased towards the outlier observations. In   1049
contrast, the confound regression quantifies the 'true mean' of 1 in the intercept term   1050
as the artefact regressor describes the effect of the artefact. In a real data example, this   1051
design could describe the mean spectrum of a resting-state EEG recording whilst   1052
accounting for a set of 'bad segments' annotations identified during pre-processing.   1053
This both provides an estimate of any 'artefact effect' and linearly removes its influence   1054
from the estimate of the mean term.   1055

   We can also specify artefact regressor with the mean removed, i.e. with zero means.   1056
Counter-intuitively, the interpretation of the regression parameter estimate is   1057
unchanged; whereas the interpretation of the constant regressor changes from   1058
modelling the intercept (as in Figure 15B) to modelling the mean over all time points.   1059

Figure 15. GLM-Spectrum design matrix for confound regression. A: A GLM design with a single regressor and contrast modelling a simple mean of the observed data **B:** A GLM design with two regressors and three contrasts illustrating confound regression. The first regressor is a constant term and the second is a sparse, non-zero mean artefact regressor indicating data observations that are possible artefacts. Three contrasts isolate each regressor individually (intercept and artefact effect) and their sum (artefact mean). **C:** Simulated data observations and the quantities estimated by the GLM designs in A and B. The first design estimates the simple mean overall data, though this is heavily influenced by the possible outlier points. The second design models an intercept and an artefact effect. The intercept can be thought of as the mean where the artefact regressor equals zero, and the artefact effect is the distance between the intercept and the artefact mean. Finally, the absolute artefact mean can be reconstructed by the sum of the two parameter estimates as shown in B contrast 3.

7.7 Effect of Confound Regression on Eyes-Open < Eyes-Closed Contrast

Adding covariate and confound regressors to a model can affect the other parameter estimates and contrasts. This effect is particularly strong when there are correlations between any of the new and existing regressors. For example, the current resting-state recordings interleaves periods of eyes-open and eyes close rest so it is likely that eye movements will increase in the eyes-open periods. This correlation means that a some eye movement related effects might leak into contrast between the eyes-open and eyes-closed conditions unless they are explicitly modelled.

    Here, we illustrate this with the group-level average t-spectra for the first-level eyes-open> eyes-closed contrast. This is shown for two different first-level models; a reduced model with no eye movement covariates and a full model with first-level confound modelling. There is a large difference in low frequencies in frontal sensors though the t-spectra are similar in posterior and occipital sensors. Without first-level confound modelling, a large frontal effect can be seen between 1Hz and 4Hz with t-values peaking around 5 (Figure 16A). This is strongly attenuated with the additional confound modelling at the first-level (Figure 16B) which reduces the open > closed contrast t-values in frontal, low frequency regions by around 4.

Figure 16. Effect of first-level confound regressors on group-level eyes-open > eyes-closed contrast. A: A t-spectrum of the contrast between eyes-open and eyes-closed resting-states with no covariate or confound regressors. **B:** A t-spectrum of the same contrast as A from a GLM with an additional confound regressor modelling V-EOG activity. **C:** The difference between A and B.

References

Adrian, E. D. and Matthews, B. H. C. (1934). The berger rhythm: Potential change from the occpital lobes in man. *Brain*, 57(4):355–385.

Aurlien, H., Gjerde, I. O., Aarseth, J. H., Eldøen, G., Karlsen, B., Skeidsvoll, H., and Gilhus, N. E. (2004). EEG background activity described by a large computerized database. *Clinical Neurophysiology*, 115(3):665–673.

Babayan, A., Erbey, M., Kumral, D., Reinelt, J. D., Reiter, A. M. F., Röbbig, J., Schaare, H. L., Uhlig, M., Anwander, A., Bazin, P.-L., Horstmann, A., Lampe, L., Nikulin, V. V., Okon-Singer, H., Preusser, S., Pampel, A., Rohr, C. S., Sacher, J., Thöne-Otto, A., Trapp, S., Nierhaus, T., Altmann, D., Arelin, K., Blöchl, M., Bongartz, E., Breig, P., Cesnaite, E., Chen, S., Cozatl, R., Czerwonatis, S., Dambrauskaite, G., Dreyer, M., Enders, J., Engelhardt, M., Fischer, M. M., Forschack, N., Golchert, J., Golz, L., Guran, C. A., Hedrich, S., Hentschel, N., Hoffmann, D. I., Huntenburg, J. M., Jost, R., Kosatschek, A., Kunzendorf, S., Lammers, H., Lauckner, M. E., Mahjoory, K., Kanaan, A. S., Mendes, N., Menger, R., Morino, E., Näthe, K., Neubauer, J., Noyan, H., Oligschläger, S., Panczyszyn-Trzewik, P., Poehlchen, D., Putzke, N., Roski, S., Schaller, M.-C., Schieferbein, A., Schlaak, B., Schmidt, R., Gorgolewski, K. J., Schmidt, H. M., Schrimpf, A., Stasch, S., Voss, M., Wiedemann, A., Margulies, D. S., Gaebler, M., and Villringer, A. (2019). A mind-brain-body dataset of MRI, EEG, cognition, emotion, and peripheral physiology in young and old adults. *Scientific Data*, 6(1).

Babiloni, C., Lizio, R., Vecchio, F., Frisoni, G. B., Pievani, M., Geroldi, C., Claudia, F., Ferri, R., Lanuzza, B., and Rossini, P. M. (2011). Reactivity of cortical alpha rhythms to eye opening in mild cognitive impairment and alzheimer's disease: an EEG study. *Journal of Alzheimer's Disease*, 22(4):1047–1064.

Baker, D. H. (2021). Statistical analysis of periodic data in neuroscience. *Neurons, Behavior, Data analysis, and Theory*, 5(3).

Bartlett, M. S. (1948). Smoothing periodograms from time-series with continuous spectra. *Nature*, 161(4096):686–687.

Bartlett, M. S. (1950). Perioidogram analysis and continuous spectra. *Biometrika*, 37(1-2):1–16.

Beckmann, C. F., Jenkinson, M., and Smith, S. M. (2003). General multilevel linear modeling for group analysis in FMRI. *NeuroImage*, 20(2):1052–1063.

Benwell, C. S., London, R. E., Tagliabue, C. F., Veniero, D., Gross, J., Keitel, C., and Thut, G. (2019). Frequency and power of human alpha oscillations drift systematically with time-on-task. *NeuroImage*, 192:101–114.

Buzsaki, G. and Draguhn, A. (2004). Neuronal oscillations in cortical networks. *Science*, 304(5679):1926–1929.

Cohen, J. (1988). *Statistical power analysis for the behavioral sciences*. L. Erlbaum Associates, Hillsdale, N.J, 2nd ed edition.

Cohen, M. X. (2014). *Analyzing Neural Time Series Data*. The MIT Press.

Cooley, J. W. and Tukey, J. W. (1965). An algorithm for the machine calculation of complex fourier series. *Mathematics of Computation*, 19(90):297–301.

de Cheveigné, A. (2020). ZapLine: A simple and effective method to remove power line artifacts. *NeuroImage*, 207:116356.

Draper, N. R. and Stoneman, D. M. (1966). Testing for the inclusion of variables in linear regression by a randomisation technique. *Technometrics*, 8(4):695.

Freedman, D. and Lane, D. (1983). A nonstochastic interpretation of reported significance levels. *Journal of Business and Economic Statistics*, 1(4):292–298.

Friston, K., Josephs, O., Zarahn, E., Holmes, A., Rouquette, S., and Poline, J.-B. (2000). To smooth or not to smooth? *NeuroImage*, 12(2):196–208.

Friston, K., Penny, W., Phillips, C., Kiebel, S., Hinton, G., and Ashburner, J. (2002). Classical and bayesian inference in neuroimaging: Theory. *NeuroImage*, 16(2):465–483.

Friston, K. J., editor (2007). *Statistical parametric mapping: the analysis of funtional brain images*. Elsevier/Academic Press, Amsterdam ; Boston, 1st ed edition.

Friston, K. J., Holmes, A. P., Worsley, K. J., Poline, J.-P., Frith, C. D., and Frackowiak, R. S. J. (1994). Statistical parametric maps in functional imaging: A general linear approach. *Human Brain Mapping*, 2(4):189–210.

Gelman, A. and Hill, J. (2007). *Data analysis using regression and multilevel/hierarchical models*. Analytical methods for social research. Cambridge University Press, Cambridge ; New York. OCLC: ocm67375137.

Gohil, C., Roberts, E., Timms, R., Skates, A., Higgins, C., Quinn, A., Pervaiz, U., van Amersfoort, J., Notin, P., Gal, Y., Adaszewski, S., and Woolrich, M. (2022). Mixtures of large-scale dynamic functional brain network modes. *NeuroImage*, 263:119595.

Gramfort, A. (2013). MEG and EEG data analysis with MNE-python. *Frontiers in Neuroscience*, 7.

Greve, D. N. and Fischl, B. (2009). Accurate and robust brain image alignment using boundary-based registration. *NeuroImage*, 48(1):63–72.

Harris, C. R., Millman, K. J., van der Walt, S. J., Gommers, R., Virtanen, P., Cournapeau, D., Wieser, E., Taylor, J., Berg, S., Smith, N. J., Kern, R., Picus, M., Hoyer, S., van Kerkwijk, M. H., Brett, M., Haldane, A., del Río, J. F., Wiebe, M., Peterson, P., Gérard-Marchant, P., Sheppard, K., Reddy, T., Weckesser, W., Abbasi, H., Gohlke, C., and Oliphant, T. E. (2020). Array programming with NumPy. *Nature*, 585(7825):357–362.

Huang, N. E., Shen, Z., Long, S. R., Wu, M. C., Shih, H. H., Zheng, Q., Yen, N.-C., Tung, C. C., and Liu, H. H. (1998). The empirical mode decomposition and the hilbert spectrum for nonlinear and non-stationary time series analysis. *Proceedings of the Royal Society of London. Series A: Mathematical, Physical and Engineering Sciences*, 454(1971):903–995.

Hunter, J. D. (2007). Matplotlib: A 2d graphics environment. *Computing in Science and Engineering*, 9(3):90–95.

Hyvarinen, A. (1999). Fast and robust fixed-point algorithms for independent component analysis. *IEEE Transactions on Neural Networks*, 10(3):626–634.

Jenkinson, M., Bannister, P., Brady, M., and Smith, S. (2002). Improved optimization for the robust and accurate linear registration and motion correction of brain images. *NeuroImage*, 17(2):825–841.

Jenkinson, M. and Smith, S. (2001). A global optimisation method for robust affine registration of brain images. *Medical Image Analysis*, 5(2):143–156. 1164 1165

Kayser, J. and Tenke, C. E. (2015). On the benefits of using surface laplacian (current source density) methodology in electrophysiology. *International Journal of Psychophysiology*, 97(3):171–173. 1166 1167 1168

Klimesch, W. (1999). EEG alpha and theta oscillations reflect cognitive and memory performance: a review and analysis. *Brain Research Reviews*, 29(2-3):169–195. 1169 1170

Knief, U. and Forstmeier, W. (2021). Violating the normality assumption may be the lesser of two evils. *Behavior Research Methods*, 53(6):2576–2590. 1171 1172

Kopell, N. J., Gritton, H. J., Whittington, M. A., and Kramer, M. A. (2014). Beyond the connectome: The dynome. *Neuron*, 83(6):1319–1328. 1173 1174

Litvak, V., Jha, A., Flandin, G., and Friston, K. (2013). Convolution models for induced electromagnetic responses. *NeuroImage*, 64:388–398. 1175 1176

Liu, C. C., Hajra, S. G., Pawlowski, G., Fickling, S. D., Song, X., and D'Arcy, R. C. (2020). Differential neural processing of spontaneous blinking under visual and auditory sensory environments: An EEG investigation of blink-related oscillations. *NeuroImage*, 218:116879. 1177 1178 1179 1180

Merkin, A., Sghirripa, S., Graetz, L., Smith, A. E., Hordacre, B., Harris, R., Pitcher, J., Semmler, J., Rogasch, N. C., and Goldsworthy, M. (2022). Do age-related differences in aperiodic neural activity explain differences in resting EEG alpha? *Neurobiology of Aging*. 1181 1182 1183 1184

Nelder, J. A. and Wedderburn, R. W. M. (1972). Generalized linear models. *Journal of the Royal Statistical Society. Series A (General)*, 135(3):370. 1185 1186

Nichols, T. E. and Holmes, A. P. (2001). Nonparametric permutation tests for functional neuroimaging: A primer with examples. *Human Brain Mapping*, 15(1):1–25. 1187 1188

O'Gorman, T. W. (2005). The performance of randomization tests that use permutations of independent variables. *Communications in Statistics - Simulation and Computation*, 34(4):895–908. 1189 1190 1191

Penrose, R. (1956). On best approximate solutions of linear matrix equations. *Mathematical Proceedings of the Cambridge Philosophical Society*, 52(1):17–19. 1192 1193

Perrin, F., Pernier, J., Bertrand, O., and Echallier, J. (1989). Spherical splines for scalp potential and current density mapping. *Electroencephalography and Clinical Neurophysiology*, 72(2):184–187. 1194 1195 1196

Prerau, M. J., Brown, R. E., Bianchi, M. T., Ellenbogen, J. M., and Purdon, P. L. (2017). Sleep neurophysiological dynamics through the lens of multitaper spectral analysis. *Physiology*, 32(1):60–92. 1197 1198 1199

Quinn, A. and Hymers, M. (2020). SAILS: Spectral analysis in linear systems. *Journal of Open Source Software*, 5(47):1982. 1200 1201

Quinn, A. J., van Ede, F., Brookes, M. J., Heideman, S. G., Nowak, M., Seedat, Z. A., Vidaurre, D., Zich, C., Nobre, A. C., and Woolrich, M. W. (2019). Unpacking transient event dynamics in electrophysiological power spectra. *Brain Topography*, 32(6):1020–1034. 1202 1203 1204 1205

Quinn, A. J., van Es, M., Gohil, C., and Woolrich, M. W. (2022). Ohba software library in python (osl). `https://zenodo.org/record/6875060`. [1206][1207]

Quinn, A. J., Vidaurre, D., Abeysuriya, R., Becker, R., Nobre, A. C., and Woolrich, M. W. (2018). Task-evoked dynamic network analysis through hidden markov modeling. *Frontiers in Neuroscience*, 12. [1208][1209][1210]

Rosner, B. (1983). Percentage points for a generalized ESD many-outlier procedure. *Technometrics*, 25(2):165–172. [1211][1212]

Selya, A. S., Rose, J. S., Dierker, L. C., Hedeker, D., and Mermelstein, R. J. (2012). A practical guide to calculating cohen's f2, a measure of local effect size, from PROC MIXED. *Frontiers in Psychology*, 3. [1213][1214][1215]

Smith, N. J. and Kutas, M. (2014). Regression-based estimation of ERP waveforms: I. the rERP framework. *Psychophysiology*, 52(2):157–168. [1216][1217]

Smith, S., Jenkinson, M., Beckmann, C., Miller, K., and Woolrich, M. (2007). Meaningful design and contrast estimability in FMRI. *NeuroImage*, 34(1):127–136. [1218][1219]

Smith, S. M. (2002). Fast robust automated brain extraction. *Human Brain Mapping*, 17(3):143–155. [1220][1221]

Thomson, D. (1982). Spectrum estimation and harmonic analysis. *Proceedings of the IEEE*, 70(9):1055–1096. [1222][1223]

Vidaurre, D., Hunt, L. T., Quinn, A. J., Hunt, B. A. E., Brookes, M. J., Nobre, A. C., and Woolrich, M. W. (2018). Spontaneous cortical activity transiently organises into frequency specific phase-coupling networks. *Nature Communications*, 9(1). [1224][1225][1226]

Vidaurre, D., Quinn, A. J., Baker, A. P., Dupret, D., Tejero-Cantero, A., and Woolrich, M. W. (2016). Spectrally resolved fast transient brain states in electrophysiological data. *NeuroImage*, 126:81–95. [1227][1228][1229]

Virtanen, P., Gommers, R., Oliphant, T. E., Haberland, M., Reddy, T., Cournapeau, D., Burovski, E., Peterson, P., Weckesser, W., Bright, J., van der Walt, S. J., Brett, M., Wilson, J., Millman, K. J., Mayorov, N., Nelson, A. R. J., Jones, E., Kern, R., Larson, E., Carey, C. J., Polat, İ., Feng, Y., Moore, E. W., VanderPlas, J., Laxalde, D., Perktold, J., Cimrman, R., Henriksen, I., Quintero, E. A., Harris, C. R., Archibald, A. M., Ribeiro, A. H., Pedregosa, F., van Mulbregt, P., Vijaykumar, A., Bardelli, A. P., Rothberg, A., Hilboll, A., Kloeckner, A., Scopatz, A., Lee, A., Rokem, A., Woods, C. N., Fulton, C., Masson, C., Häggström, C., Fitzgerald, C., Nicholson, D. A., Hagen, D. R., Pasechnik, D. V., Olivetti, E., Martin, E., Wieser, E., Silva, F., Lenders, F., Wilhelm, F., Young, G., Price, G. A., Ingold, G.-L., Allen, G. E., Lee, G. R., Audren, H., Probst, I., Dietrich, J. P., Silterra, J., Webber, J. T., Slavič, J., Nothman, J., Buchner, J., Kulick, J., Schönberger, J. L., de Miranda Cardoso, J. V., Reimer, J., Harrington, J., Rodríguez, J. L. C., Nunez-Iglesias, J., Kuczynski, J., Tritz, K., Thoma, M., Newville, M., Kümmerer, M., Bolingbroke, M., Tartre, M., Pak, M., Smith, N. J., Nowaczyk, N., Shebanov, N., Pavlyk, O., Brodtkorb, P. A., Lee, P., McGibbon, R. T., Feldbauer, R., Lewis, S., Tygier, S., Sievert, S., Vigna, S., Peterson, S., More, S., Pudlik, T., Oshima, T., Pingel, T. J., Robitaille, T. P., Spura, T., Jones, T. R., Cera, T., Leslie, T., Zito, T., Krauss, T., Upadhyay, U., Halchenko, Y. O., and and, Y. V.-B. (2020). SciPy 1.0: fundamental algorithms for scientific computing in python. *Nature Methods*, 17(3):261–272. [1230][1231][1232][1233][1234][1235][1236][1237][1238][1239][1240][1241][1242][1243][1244][1245][1246][1247][1248]

Voytek, B., Kramer, M. A., Case, J., Lepage, K. Q., Tempesta, Z. R., Knight, R. T., and Gazzaley, A. (2015). Age-Related Changes in 1/f Neural Electrophysiological Noise. *Journal of Neuroscience*, 35(38):13257–13265. [1249][1250][1251]

Wan, L., Huang, H., Schwab, N., Tanner, J., Rajan, A., Lam, N. B., Zaborszky, L., shan R. Li, C., Price, C. C., and Ding, M. (2018). From eyes-closed to eyes-open: Role of cholinergic projections in EC-to-EO alpha reactivity revealed by combining EEG and MRI. *Human Brain Mapping*, 40(2):566–577.

Welch, P. (1967). The use of fast fourier transform for the estimation of power spectra: A method based on time averaging over short, modified periodograms. *IEEE Transactions on Audio and Electroacoustics*, 15(2):70–73.

Williams, M. N., Grajales, C. A. G., and Kurkiewicz, D. (2013). Assumptions of multiple regression: Correcting two misconceptions.

Winkler, A. M., Ridgway, G. R., Webster, M. A., Smith, S. M., and Nichols, T. E. (2014). Permutation inference for the general linear model. *NeuroImage*, 92:381–397.

Woolrich, M. W., Behrens, T. E., Beckmann, C. F., Jenkinson, M., and Smith, S. M. (2004). Multilevel linear modelling for FMRI group analysis using bayesian inference. *NeuroImage*, 21(4):1732–1747.

Woolrich, M. W., Jbabdi, S., Patenaude, B., Chappell, M., Makni, S., Behrens, T., Beckmann, C., Jenkinson, M., and Smith, S. M. (2009). Bayesian analysis of neuroimaging data in FSL. *NeuroImage*, 45(1):S173–S186.

Woolrich, M. W., Ripley, B. D., Brady, M., and Smith, S. M. (2001). Temporal autocorrelation in univariate linear modeling of FMRI data. *NeuroImage*, 14(6):1370–1386.

Worsley, K. and Friston, K. (1995). Analysis of fMRI time-series revisited—again. *NeuroImage*, 2(3):173–181.

Xifra-Porxas, A., Niso, G., Larivière, S., Kassinopoulos, M., Baillet, S., Mitsis, G. D., and Boudrias, M.-H. (2019). Older adults exhibit a more pronounced modulation of beta oscillations when performing sustained and dynamic handgrips. *NeuroImage*, 201:116037.

Zhang, Y., Brady, M., and Smith, S. (2001). Segmentation of brain MR images through a hidden markov random field model and the expectation-maximization algorithm. *IEEE Transactions on Medical Imaging*, 20(1):45–57.

Zibrandtsen, I. C. and Kjaer, T. W. (2021). Fully automatic peak frequency estimation of the posterior dominant rhythm in a large retrospective hospital EEG cohort. *Clinical Neurophysiology Practice*, 6:1–9.