Extracting electromyographic signals from multi-channel local-field-potentials using independent component analysis without direct muscular recording

Hisayuki Osanai[1], Jun Yamamoto[1], and Takashi Kitamura[1, 2, *]

1. Department of Psychiatry, University of Texas Southwestern Medical Center, Dallas, TX, 75390, USA
2. Department of Neuroscience, University of Texas Southwestern Medical Center, Dallas, TX, 75390, USA
*Correspondence: takashi.kitamura@utsouthwestern.edu

Highlights (85 characters for each)
- EMG signals can be extracted from LFP signals without direct muscular recording   **(81/85)**

- The extracted signal is highly correlated with direct EMG recording signals   **(77/85)**

- The extracted signal is useful in measuring animal behaviors as well as actual EMG **(84/85)**

- This method contributes to precise and stable long-term behavior measurement   **(78/85)**

In brief (44/50 words)
Osanai et al. demonstrate electromyography (EMG) signals can be extracted from multi-channel local field potential (LFP) recordings using blind-source-separation technique without direct measurement of muscle activity. The proposed method adds precise and long-term behavioral measurements with EMG information in wide-ranged in vivo electrophysiology experiments.

Summary (148/150 words)
Electromyography (EMG) has been commonly used for precise identification of animal behavior. However, they are often not recorded together with in vivo electrophysiology due to the need for additional surgeries and setups and the high risk of mechanical wire disconnection. While independent component analysis (ICA) has been used to reduce noise from field potential data, there has been no attempt to proactively use the removed "noise", of which EMG signals are thought to be one of the major sources. Here, we demonstrate that EMG signals can be reconstructed without direct EMG recording, using the "noise" ICA component from local field potentials. The extracted component is highly correlated with directly measured EMG, termed as IC-EMG. IC-EMG is useful for measuring an animal's sleep/wake, freezing response and NREM/REM sleep states consistently with actual EMG. Our method has advantages in precise and long-term behavioral measurement in wide-ranged in vivo electrophysiology experiments.

KEYWORDS
   electromyography, local field potential, multi-channel electrophysiology, independent component analysis, freely moving, fear conditioning, sleep scoring.

Main Text (5429/7000 words)

Introduction

While neural correlates of animal behavior are examined most frequently with video observation of an animal's movement, physiological signals such as electromyography (EMG) are also often used to monitor the small movements of the animal that can be missed in video observation. In neuroscience studies, EMG has been used to accurately assess sleep/wake states [1-6] and freezing behavior [7-9]. However, despite the benefits of accurate behavior assessment, EMG is often not obtained together with brain activity recording because it requires additional surgery and setups [7,10-13]. Furthermore, in the case of implanting a silicon probe, most commercial headstage preamplifiers are not designed with extra pins to obtain EMG signals, thus an additional preamplifier is required which increases total implant weight, potentially interfering with the normal behavior of small animals such as mice. Moreover, a high risk of EMG electrode wire breakage during experiments [14-16] hampers long-term experiments.

Field potentials have been shown to be correlated with an animals' behaviors such as sleep/wake conditions [1,2,17-20] and fear freezing behavior [8,21,22]. Field potential signals are often electrically referenced to one of the electrodes placed in a brain to suppress excessive common noise generated from the outside of the brain [19,23-25]. On the other hand, because the field potential signals can be distorted by the electrical signals at the reference electrode site[24-26], an electric reference is frequently set outside of the brain, (e.g. a skull screw) [27-29]. In this case, in order to minimize the noise arising from the distal reference electrode setting, multiple methods have been proposed such as common average reference [30], current source density analysis [31-33], and application of independent component analysis (ICA) [34].

ICA is a blind source separation technique which isolates temporally independent source signals [35-38]. This technique has been well established for decades in "denoising" recorded neural signals by isolating and deleting the noise components from the field potential data, in which EMG artifacts are considered to be a major noise source [34,39-43]. However, although the putative EMG component isolated by ICA has been the target of noise suppression, it has not yet been investigated to what extent this component correlates with real EMG signals. Thus, the component has not been proactively used as a measurement of animals' behavioral states.

Here, we hypothesized that ICA can reconstruct EMG signals from multichannel local field potential signals obtained by a silicon probe or tungsten wire electrodes without direct measurement of muscular signals. To investigate the correlation between independent component (IC) and EMG signals, we simultaneously implanted a silicon probe into a mouse's hippocampus and wire electrodes into the neck muscles. Local field potentials (LFPs) were recorded referenced to a skull screw over the cerebellum. Next, we obtained ICs from the LFPs using ICA, and demonstrated that EMG-like high frequency components (IC-EMG) could always be obtained from the LFPs. These components were shown to highly correlate with directly measured EMGs. We further demonstrated this IC-EMG can be used to measure sleep/wake activity and freezing behavior. Finally, we demonstrated that IC-EMGs can also be obtained from four-channel multisite brain-areas LFPs obtained by tungsten wire electrodes.

Results

IC-EMG is highly correlated with real EMG signals

LFP signals were obtained from a 32-channel silicon probe implanted in the mouse hippocampus, using a skull screw for electric reference above the cerebellum (Figs. 1A-D). At the same time, EMG signals were obtained from the left and right neck muscles (Fig. 1C, E). The ICs were obtained by ICA from the recorded multichannel LFP signals (Fig. 2A). Figure 2Ab illustrates one of the obtained IC (IC#1) showing EMG-like higher frequency activity than other ICs. The back-

projected reconstructed signals on the original channels using this IC showed that the signals
distributed uniformly along the channels (Fig. 2Ba). Deleting this IC clarified the weaker and
slower activities, which had been previously contaminated with the noise-like large high-frequency
activity in the original waveforms (Fig. 2Bb). Indeed, IC#1 showed a clear peak between 100-200
Hz in the estimated power spectrum density (Fig. 2C) and the weight distribution of this
component was highly uniform compared to other ICs (Fig. 2D). In LFP data obtained from ten
mice, only one IC showing uniform weight distribution (standard deviation (std) < 0.1) was
consistently obtained from individual mice (Fig. 2Ea). To focus on uniformly distributed ICs, we
classified ICs having a minimum std among ICs obtained in individual mice and a std < 0.1 as a
uniform-IC. The uniform-IC also showed the maximum mean value of its weight distribution and
tends to have large amplitude activities (Fig. 2Eb; uniform-IC vs. other ICs: weight mean = 0.97
± 0.007 vs. 0.21 ± 0.013, $t_{(265)}$ = 10.99, p = 2.15e-23; weight std = 0.019 ± 0.003 vs. 0.36 ± 0.009,
$t_{(265)}$ = -7.44, p = 1.42e-12; Amplitude ratio = 0.88 ± 0.090 vs. 0.20 ± 0.013, $t_{(265)}$ = 9.88, p = 8.35e-
20, respectively). In addition, the uniform-IC always had a peak frequency between 100-200 Hz
similar to the real-EMG power spectrum density (Fig. 2F), indicating the uniform-IC reflected EMG
signals.
We next investigated to which extent the uniform-IC correlates with real-EMG signals. Figure
3A illustrates the filtered signals of uniform-IC and the real EMG, and Figure 3B shows the time
course of their amplitude calculated by root-mean-square (RMS) with 100 ms time-windows. As
we expected, the uniform-IC and the real-EMG signals were highly correlated, with correlation
coefficients that were more than 0.9 (Fig. 3C and D). Therefore, EMG signals can be
reconstructed from skull-screw-referenced multichannel LFP data by ICA without direct EMG
recordings. These signals are represented by the uniform-IC, which hereafter we termed IC-EMG.
The EMG-like components were not obtained from brain-referenced LFPs in most cases (eight
out of ten mice), since EMG information was absent due to subtraction (Fig. S1A-C). We observed
the EMG-like components from the brain-referenced LFPs only when the noise-level of LFPs was
different between the recording channels, such that brain-referencing cannot completely reduce
the noise (Fig. S1D-F, S2). Thus, brain-referenced LFP is not ideal for obtaining EMG signals
using ICA.
129
IC-EMG provides behavior measurements
Next, we examined whether the IC-EMG is useful for annotating animal's behavioral states. Mice
were placed into and allowed to move freely in the open field chamber (Fig. 4A). LFPs and EMGs
were recorded while the mice were in the chamber (Fig. 4B), together with video tracking of
animals' positions. We categorized animal behavioral states from video into Sleep, Quiet Awake
(QAW), and Active, classified according to the animals' average head speed (Fig. 4C; see
Methods). Amplitudes of IC-EMG and real-EMG were quantified in ten mice during each
behavioral state. Fig. 4D shows that there were significant differences in the IC-EMG amplitudes,
similarly to the real EMG, between Sleep, QAW, and Active behavioral states (Fig. 4D).
Freezing behavior has been demonstrated as an indicator for fear response in both innate and
conditioned reactions [44-47]. We furthermore demonstrate that IC-EMG is useful for fear freezing
detection, consistent with the previous studies showing that EMG can be used as a measure of
fear freezing behavior [7]. Mice were conditioned in the tone fear conditioning paradigm while their
fear freezing was recorded with video observation, along with LFPs and real EMG signals (Fig.
5A). For conditioning, mice were exposed to three pairings of a 20 s tone and a 2 s foot shock on
Day1. Then, fear freezing behaviors in response to tone were monitored on Day2 in a different
context and scored by animal's motion in the recorded video. At the same time, IC-EMG was
obtained from the recorded LFPs, and the amplitudes of IC-EMG and real EMG were examined
during animals showed freezing and non-freezing behavior (Fig. 5B). The mice actively explored
the recording box before the tone delivery, while they showed increased freezing behaviors after
the first tone delivery (Fig. 5B, C). From the LFP data of five mice, IC-EMG showed a significantly

lower amplitude during the freezing state compared to the non-freezing state, similar to the results
of real EMG signals (Fig. 5D). Together, these results demonstrated that IC-EMG is useful for
annotating animal behavior such as sleep/quiet-awake/active behavioral states and freezing/non-
freezing states.
155
IC-EMG can improve precise REM sleep detection
We examined whether the IC-EMG is useful for precise annotation of the rapid eye movement
(REM) sleep stage. REM/non-REM (NREM) sleep periods are often classified by high/low theta-
to-delta ratio of field potential when the animal shows stationary behavior [48,49]. However, because
many factors can increase theta power during QAW [8,21,22,50-55] (see Discussion), the combination
only of video recording and field potential recording has difficulty in fine discrimination of QAW
and REM sleep stats. The most established sleep scoring method uses a combination of field
potential and EMG [56-60]. In this paradigm, sleep/wake is classified by low/high amplitude EMG
activities in addition to the animal's movements in the recorded video. Here, we demonstrate IC-
EMG can be used for sleep scoring similarly to real-EMG recording.
LFPs and EMGs of the mice were recorded in the open field chamber or their home cages (Fig.
6A). The animal's behaviors were first annotated with the video tracking of animals' positions (Fig.
6Aa). High theta- (6–9 Hz)-to-delta (0.1–4 Hz) ratio periods were observed during the mice were
stationary (Fig. 6Ab, c). In order to separate REM sleep periods from QAW state, the animal
behaviors were further classified using IC-EMG information that the stationary periods with high
IC-EMG amplitudes were re-categorized as being in the awake-state (QAW) (Fig. 6Ad), similarly
to the use of the EMG (Fig. 6Ae). Then, REM/NREM/QAW states were annotated with the
combination of the theta-delta ratio and the animal's speed, or the combination of the theta-delta
ratio, the animal's speed, and the IC-EMG or the EMG (Fig. 6B). Some periods annotated as REM
based only on the video (Fig. 6Ba) were categorized into QAW when the annotation was based
on IC-EMG (Fig. 6Bb), similarly to the result based on the EMG (Fig. 6Bc), because of their large
amplitudes of muscular activities during the periods which are not likely to occur during sleeping
states. The dynamics of IC-EMG and EMG during IC-EMG- and EMG-based categorized REM
periods were consistent with previous studies where EMG shows silent and occasional twitch
activities [61,62], and that body-movement occurs at the end of REM [63]. To evaluate the extent to
which the quality of the video-based and the IC-EMG-based state classification is close to the
EMG-based method, the REM sleep periods were detected from six silicon-probe implanted mice
(Fig. 6C). Because the sleep periods were more strictly annotated, the IC-EMG based method
showed less false-positive rates of REM detection compared to the video-only based method (Fig.
6Da; video: 1.18 ± 0.38%, $t_{(5)}$ = 3.13, p = 0.025; IC-EMG: 0.39 ± 0.20%, $t_{(5)}$ = 1.98, p = 0.104, one-
sample t-test with zero), and negligible levels of false-negative rates in IC-EMG (0.16 ± 0.12%,
$t_{(5)}$ = 1.27, p = 0.260, one-sample t-test with zero). Also, the IC-EMG-based REM period detection
was similar (Cohen's kappa [64-66]) to the EMG-based method while the similarity of the video-only
based method was less (Fig. 6Db; video: 0.91 ± 0.03, $t_{(5)}$ = -2.89, p = 0.035; IC-EMG: 0.96 ± 0.02,
$t_{(5)}$ = -1.93, p = 0.112, one-sample t-test with kappa = 1). Therefore, the use of IC-EMG improves
precise REM sleep detection similarly to the use of real-EMG by decreasing false-positive REM
periods.
193
IC-EMG can be obtained from multisite brain-area recording
Finally, we examined whether IC-EMG can be obtained from multisite brain-area recording data.
We have previously recorded four channel LFPs in ACC, BLA, white matter of dorsal CA1, and
ventral CA1 of mice [67]. We had obtained the LFP signals referenced to the skull screw over the
cerebellum, and ICs were separated by ICA from the recorded LFPs into ICs (Figs. 7A-D). Similar
to the case of silicon-probe recordings (Fig. 2), one of the ICs consistently present in each of the
four mice exhibited a highly uniform weight distribution (Fig. 7E, G). These components also
showed a peak frequency between 100-200 Hz (Fig. 7F, H), which is consistent with the results

of silicon-probe recordings (Fig. 7F), indicating a strong correlation with actual EMG signals. We
examined the amplitude of IC-EMG when the mice explored the open field chamber. Again,
consistent with the results of silicon-probe recordings, IC-EMG amplitudes were significantly
higher during awake states than sleeping states (Fig. 7I). We finally examined IC-EMG amplitudes
during freezing/non-freezing behaviors during the observational fear [68-70]. The recorded mouse,
as an observer, and his cagemate, as a demonstrator, were placed into the two chambers
separated by a transparent plexiglass partition. On the recording day, the foot shock was
delivered to the cagemate demonstrator which produced the observational fear response [67] (Fig.
7Ja). During the freezing period, IC-EMG of 4-channel LFP showed significantly lower amplitudes
compared to the non-freezing state in the observer (Fig. 7Jb). Therefore, IC-EMG can also be
obtained from multisite brain-areas LFP recording, and it provides behavior measurement of
sleep/awake states and fear-freezing/non-freezing states. Moreover, these results also
demonstrate that our method is able to reconstruct EMG signals from data obtained in the past,
so long as an electrical reference was set on the animal's skull screw.
216
217
Discussion
Although previous works have shown good performance of ICA in the reduction of EMG-like
artifacts from field potential data, evidence of to what extent the separated component and the
actual EMG signal correlate was lacking. Thus, no prior attempt was made to use this EMG-like
component proactively. The current study has shown that the EMG component obtained from
multichannel LFP signals by ICA is highly correlated with actual EMG signals. The IC-EMG was
further demonstrated to be useful for measuring animal's sleep/wake and fear freezing behavior
as well as actual EMG. We also showed that EMG component separation could also be performed
by ICA with multisite brain-areas LFP recording. Therefore, the current study demonstrated that
the EMG signal can be reconstructed from multichannel LFP by ICA without any additional
surgery or setup, which can be helpful in the measurement of animal behaviors. In addition, our
method allows re-examining animal behaviors in previously-obtained LFP data.
230
Advantages of IC-EMG
Although techniques used for EMG signal acquisition are simple, simultaneous recording of EMG
with brain activity is not a trivial matter because it requires additional surgeries and setups as we
described in the Introduction. In the current study, the total microdrive weight used for silicon
probe implant and EMG recording was 6.5 g, while the weight would be reduced to 4.7 g in the
case that EMG recording was not needed because the electrical interface board for EMG preamp
can be removed. We did not observe abnormal behaviors in the adult mice used in this study, but
the increased implant weight could interfere with the behavior of more juvenile animals. Stable
EMG recording has also been a challenging problem as the recording wires need to remain
attached to the animal despite the mechanical stress caused by muscular movements. In our
experiments, three out of twelve mice broke the wires; one mouse broke one side of the EMG
wires within a week after the surgery, and another two mice broke one side of the wires while
receiving fear conditioning foot shocks. Reconstructing EMG signals from LFP using ICA does
not require a wire electrode implant. The ground/reference wire used for the LFP recording
connected to the skull screw was fully covered with dental acrylic and did not receive mechanical
stress after surgery, ensuring stable recording. Therefore, our IC-EMG method not only reduces
the requisite effort of additional surgery and setup preparation for EMG recording but also enables
stable simultaneous recording of EMG and LFP with freely moving animals, which allows long-
term behavior experiments without the risk of a wire break.
Up to now, several methods have been proposed to score animal behaviors without EMG.
Video-based sleep scoring has been shown to have a high correlation with EMG-based scoring
[71,72]. The video-based methods, however, have a drawback in identifying the fine sleep structures

because they take 40 seconds of immobility as a threshold to define sleeping, while short sleep bouts of less than 20 seconds have been reported in sleep-deprived rodents [73] and of excessive sleepiness in humans [74,75]. Video recordings systems complemented with infrared beam breaking [76], piezoelectric signals [77,78], and respiration measurement [75] were also proposed; however, these again require additional experimental setups. Sleep has also been often determined based on the oscillatory power of LFP or EEG combined with video-tracking without EMG. In these cases, active awake and REM sleep are identified by prominent theta oscillation (6–9 Hz) while slow-wave sleep is characterized by increased delta oscillation (<4 Hz) [48,49,79] and by the appearance of sharp-wave-ripple and cortical spindles [20,80,81]. Another study further distinguished sleep and quiet awake states using a criterion that delta power is increased during slow-wave sleep than QAW state [82]. However, there is still a limitation of this approach in fine state discrimination of immobility states. Although theta is prominent during REM sleep, theta power during QAW can also increase with many factors including respiration [50], vestibular stimulation [51], sleepiness [52], fear [8,21,22], attention and other cognitive functions [53-55]. In addition, QAW theta becomes less prominent during waking immobility, eating, grooming, and defecation [53,83]. Also, QAW delta power is reported to increase prior to the wake-to-slow-wave-sleep transition onset [84,85]. Thus, EEG-based behavior classification has difficulty in fine discrimination of QAW, slow-wave sleep, and REM sleep. IC-EMG provides the benefit of precise animal state discrimination compared to other conventional methods without utilizing EMG information.

While we demonstrated that IC-EMG can be a measure of sleep/wake and fear freezing behavior, we also observed its amplitude was increased during water-licking, food-chewing, and grooming behavior. Thus, IC-EMG has potential to be a measure of various animal behaviors, although further investigation is needed to clarify to what extent animal behavior types can be scored by IC-EMG.

In this study, we obtained EMG signals from LFP data by ICA. The same methodology has potential to be applied to EEG research, considering that ICA has been a well-established method to eliminate EMG artifacts from EEG data. Recently, several source separation techniques, including empirical mode decomposition [86,87], an improved version of ICA-based separation [88], and others [89-92], have been proposed to have better noise reduction quality for EEG data than conventional ICA with the condition of fewer recording channels. Therefore, utilization of these signal source separation techniques would be possible to improve the quality of EMG-signals isolation from EEG data.

Signal Source of IC-EMG

We obtained IC-EMG from the multichannel LFP signals, which were characterized to have uniform IC weight distribution. Considering neural activity factors surrounding the electrode should contribute to LFP in a more localized manner [24,93], the signal-source of a such uniform distribution component is supposed to be distal volume conduction [94] or a common electrical reference [34]. However, the volume conduction factor is less likely to be the main factor of IC-EMG. First, IC-EMG has a peak power at 130–140 Hz, while power line conduction should generate a peak at a lower frequency range. Second, such a high-frequency neural event in a brain corresponds to sharp wave ripple [20], but it is unlikely to be generated from a uniformly distributed source and its amplitude should be smaller than other slower oscillatory activities. Thus, although both signals were possibly separated by ICA, we assume that the major factor of that uniform component is the electrical reference. In this study, we used the skull screw over the cerebellum as an electrical reference, which can pick up both signals of muscle activities near the screw and cerebellar activity. However, although the precise contribution of cerebellar EEG is unclear, it is reported that overt activity is not seen in a healthy rodent brain [95]. Together with the high correlation with neck-EMG, we assume the head-neck muscular activities surrounding the electrically referenced skull screw is a major signal source of IC-EMG.

Factors that may affect IC-EMG identification

In our method, the high-noise level channels identified by eye were removed prior to running ICA. Such noisy signals can be caused by the degradation of the silicon probe electrode that leads to crosstalk between channels [96] and changes in the frequency-impedance characteristics [97,98], which have a risk of skewing the time-course of LFP traces. Because ICA is a technique to separate temporally maximal independent waveforms, the skewed LFP can generate additional components for which signal-source actually does not exist. Indeed, although only one IC-EMG component was obtained from each mouse in the current study after the removal of bad channels, we have observed two uniform components correlated with EMG (mean weight = 0.97 and 0.95, mean std = 0.02 and 0.03, Amp ratio = 0.65 and 0.46, correlation coefficient = 0.97 and 0.97, respectively) from one mouse when we did not remove the channels of high noise level before the ICA computation. Thus, including unhealthy electrode site signals in ICA may generate "ghost" components, although EMG signals can still be reconstructed from the LFPs.

Benefits of using ICA for reducing noise arising from outside-brain reference electrode setting

In this study, ICA was demonstrated that it can separate muscle activities from multichannel LFP data with a skull screw electric reference. Another advantage of applying ICA to LFP data is, as we demonstrated in Fig. 2Bb, it can obtain noise-cleaned LFP data against a brain-external reference.

There have been multiple methods for reducing the noise arising from the distal reference electrode, which is set to avoid the signal distortion caused by placing the reference electrode close to the recording site. Common average reference is the method to generate a more ideal reference by averaging all the recordings on every electrode site to use as a reference [30]. While the ideal reference can be obtained if the average produces near-zero activity, the average does not often produce zero especially in the case of recording from the local brain area because neural activities at each recording channels are supposed to be correlated each other. Current source density analysis has also been widely used as a reference-independent measure which estimates the strength of extracellular current generators [31-33], which is conducted by calculating a second spatial derivative of the recorded potentials between neighboring electrodes in the standard method. However, because the spatial noise is amplified through the differentiation, it often requires spatial filtering [99-101] which decrease spatial resolution of LFP signals. In addition, this method is not useful in the case of certain recording electrode setups such as those using tungsten wire electrodes because it requires precise electrode site distance information, nor in the case of multi-brain site recording. The ICA-based method, on the other hand, does not depend on the electrode locations, and subtracting electrical reference activity can be interpreted as re-referencing to a zero-activity location [34]. Thus, our method to use ICA to LFP data does not only have an advantage in extracting EMG activities without an EMG electrode implant, but also in obtaining noise-reduced LFP signals avoiding the potential signal distortion that is encountered in the case of a within-brain reference electrode placement.

Conclusion

This study certified EMG signals can be reconstructed from multichannel LFP signals by ICA. Thus, our method provides a physiological measure of animal behavior in LFP data without the extra effort of direct EMG recording. It will be a useful tool in wide-ranged in vivo electrophysiology experiments including investigating neural correlates of animal behavior.

Acknowledgement

We thank Dr. William Marks for his comments on the manuscript, and all other members of the Kitamura laboratory for their support. This work was supported by grants from the Endowed Scholar Program to T.K., Brain Research Foundation to T.K. (BRFSG-2018-04), Faculty Science and Technology Acquisition and Retention Program to T.K., the Whitehall Foundation to T.K. (2019-05-38), the National Institute of Mental Health to T.K. (R01MH120134 and R01MH125916) and Japan Society for the Promotion of Science to H.O. (201860198 and 202101654). (Corresponding author: Takashi Kitamura.)

Author Contribution

H.O. and T.K. contributed to the study design. H.O. conducted all experiments and analysis. H.O., J.Y. and T.K. contributed to the interpretation for data analysis. H.O. and T.K. wrote the manuscript. All authors approved the final manuscript.

Declaration of Interests

The authors declare no competing interests.

372 **Figures**
373
374 Figure 1

375
376
377
378

383   Figure 3

384
385
386

387   Figure 4

388
389
390
391

392   Figure 5

393
394
395
396

397   Figure 6
398

399
400

Figure Legends

Fig. 1. LFPs and EMG recording setups.
(A) A microdrive system for implanting a silicon-probe and EMG electrode wires, placed on a jig (a) and during surgery (b). (B) Skull screw used for an animal's ground and reference. The silicon probe was inserted into the brain in this picture. (C) EMG electrode wires placement. The tips of the coated wires were exposed and looped into the left and right neck muscles. (D) The trace of silicon probe implantation into HPC. The probe was coated with DiI before implantation. (E) Representative LFP traces from a 32-ch silicon probe referencing the skull screw (top), and right (R) and left (L) neck EMG traces (bottom).

Fig. 2. Identification of putative EMG component from LFP by ICA.
(A) Raw LFP traces (a) and their independent components (ICs) separated by ICA (b). Note that IC#1 (black trace) showed higher frequency activity than other ICs (gray traces) similarly to the EMG traces in Fig. 1E. (B) (a) Projection of IC#1 to the original LFP channels. (b) The cleaned LFP obtained by deleting IC#1 from the raw LFP (b). The EMG-like high-frequency activities disappeared in IC#1-deleted LFP. (C) Log-log plots of the normalized power spectrum densities of each IC shown in *A*. IC#1 showed peak power at the range >100 Hz. Black dotted lines indicate the power of aperiodic exponent (see Methods). (D) The weight distribution of ICs shown in *A*. IC#1 had the most-uniform (minimum standard deviation (std)) distribution. (E) (a) Scatter plot of IC's mean weight, std, and amplitude (see Methods), obtained from ten mice. Red circle indicates the ICs classified as uniform-IC in each mouse. (b) Averaged parameters of IC-EMGs and other ICs. Dots of each color indicate different mice. (F) Averaged normalized power spectral density of the uniform-IC (blue) other ICs (red), and raw EMG (black).

Fig. 3. Correlation of uniform-IC and raw EMG signals.
(A) 50-500Hz filtered waveforms of uniform-IC (IC#1 in Fig. 2), right-neck EMG (R-EMG), left-neck EMG (L-EMG) and, Δ(right-to-left) EMG ((R-L)-EMG) which is obtained by subtracting L-EMG from R-EMG to remove the effect of the common reference (skull-screw reference). (B) Root-mean-square (RMS) with 100 ms-bin time windows of each trace in A. (C) Correlation of uniform-IC with each EMG. (a) with R-EMG, (b) L-EMG, and (c) (R-L)-EMG. (R-L)-EMG is less correlated with IC-EMG than R- or L-EMG because the common reference effect is absent due to the subtraction, but still shows high correlation. (D) Average Pearson's correlation coefficient of uniform-IC and real EMG from ten mice. L-EMG data from one mouse is missing due to the wire break during experiments. Correlation between uniform-IC and R-EMG = 0.96±0.008, L-EMG = 0.94±0.016, (R-L)-EMG = 0.93±0.007.

Fig. 4. IC-EMG can provide measurements of animal behaviors.
(A) The recording chamber (a) and head position tracing (b) during LFP and EMG recording. (B) Simultaneous recording of LFP and EMG when the mouse was freely moving in the recording chamber. EMG-IC was obtained from raw-LFP by ICA. (C) Speed of the animal's head, traces of IC-EMG and raw EMG and their amplitudes at the same time. (a) head position speed (black line) and its average during each 15s epoch (red line), (b) z-scored IC-EMG and its RMS amplitude, (c) z-scored raw EMG and its RMS amplitude. Animal behavior was categorized into Sleep (blue), Quiet Awake (QAW, green), and Active (red) based on the video data. (D) Amplitude of IC-EMG (a, n = 10), L- or R-EMG (b, n = 10), and (R-L)-EMG (c, n = 9) during different animal behaviors. Amplitudes between Sleep vs. QAW vs. Active: IC-EMG: 0.54 ± 0.070 vs. 0.84 ± 0.060 vs. 1.17 ± 0.071, p = 0.010 (Sleep/QAW) and p = 0.005 (QAW/Active); L- or R-EMG: 0.52 ± 0.061 vs. 0.86 ± 0.039 vs. 1.24 ±0.090, p = 0.003 (Sleep/QAW) and p = 0.001 (QAW/Active); (R-L)-EMG: 0.55 ± 0.055 vs. 0.91 ± 0.033 vs. 1.26 ±0.100, p = 0.003 (Sleep/QAW) and p = 0.003 (QAW/Active).

Fig. 5. IC-EMG can be measurements of animal's fear freezing.
(A) Schema of the tone fear conditioning task. (B) Animals' freezing behavior at day2, IC-EMG
and raw EMG traces, and their RMS amplitudes during whole sessions (a) and 1 min before and
after the tone onset (b). (C) Freezing rate during habituation session and test sessions (n = 5)
before and after the first tone delivery. Freezing rate before vs. after the tone = 5.4 ± 1.8% vs.
31.7 ± 8.0%, respectively, $t_{(8)}$ = -3.22, p = 0.012. (D) Amplitude of IC-EMG and L- or R-EMG during
animal's active/freezing states. (R-L)-EMG was not analyzed because one side of the EMG wires
was broken during foot-shock delivery in three out of five mice. The z-scored amplitudes during
non-freezing and freezing states: IC-EMG: 0.96 ± 0.079 vs. 0.56 ± 0.043, $t_{(8)}$ = 3.65, p = 0.007;
EMG: 0.98 ± 0.067 vs. 0.57 ± 0.036, $t_{(8)}$ = 3.37, p = 0.001, respectively.
466
Fig. 6. IC-EMG is useful for precise annotation of REM sleep scoring.
(A) Sleep/wake annotation based on the video recording, IC-EMG and EMG. (a) head position
speed (black line) and its average during each 15s epoch (red line). Animal behavior was
categorized into Sleep (blue), QAW (green), and Active (red) based on the head speed. (b)
Spectrogram of LFP at st. lm layer of CA1. (c) Trace of theta (6–9 Hz)-to-delta (0.1–4 Hz) ratio.
Blue dotted line indicates ratio = 4. (d, e) Sleep states categorized based on video recording (a)
were re-annotated into QAW if the amplitudes of the z-scored IC-EMG (d) and (R-L)-EMG (e) are
high (see Methods). Black lines indicate RMS amplitudes of IC-EMG/(R-L)-EMG. Blue dotted lines
indicate z = 1.5. (B) Sleep scoring based on the video recording (a), IC-EMG (b) and (R-L)-EMG
(c). The states were classified into REM when the theta-to-delta ratio is ≥ 4 during Sleep state
(see Methods). Red arrow indicates the REM period which is categorized based on the video was
re-categorized as wake by IC-EMG- and EMG-based annotation due to their high amplitudes. (C)
REM sleep duration from the six mice in the total recording time (a) (percentages based on video
vs. IC-EMG vs. EMG: 9.38 ± 2.75 vs. 8.44 ± 2.68 vs. 8.21 ± 2.67), and in total sleep periods (b)
(percentages based on video vs. IC-EMG vs. EMG: 20.80 ± 5.42 vs. 18.95 ± 5.06 vs. 18.59 ±
5.13). These amounts are consistent with the previous reports [102,103]. (D) The agreement of REM
sleep scoring based on video and IC-EMG versus the scoring based on EMG; False-positive rates
(a), and Cohen's kappa values (b).
485
Fig. 7. IC-EMG can be obtained from multisite brain-areas recording.
(A) Implant device on jig equipped with 4-ch tungsten wire electrodes. (B) The electrode traces.
The electrodes were coated with DiI before implantation. Scale bar: 1 mm. (C) Representative
LFPs from 4-ch electrodes (a), and their ICs (b). The LFP signals were referenced to the skull
screw. (D) The back-projected field potential from IC#1 (a), and the cleaned LFP waveforms
obtained by deleting IC#1 LFP from the raw LFP (b). (E) Weight distribution of ICs. (F) Power
spectrum density of ICs. (G) (a) Scatter plot (a) and bar plots (b) of IC's mean weight, std, and
amplitude ratio, obtained from four mice. Red circle indicates the uniform-ICs (IC-EMG) in each
animal. Averaged parameters were: IC-EMG vs. other ICs: weight mean = 0.96 ± 0.007 vs. 0.20
± 0.033, $t_{(14)}$ = 13.31, p = 2.45e-9; weight std = 0.045 ± 0.011 vs. 0.62 ± 0.033, $t_{(14)}$ = -9.69, p =
1.37e-7; Amplitude ratio = 0.87 ± 0.005 vs. 0.57 ± 0.047, $t_{(14)}$ = 3.53, p = 0.003, respectively. (H)
Average power spectrum density of the IC-EMG (blue) and other ICs (red). (I) IC-EMG from freely
moving animals. Speed of animal's head position (top), 50-500 Hz filtered IC-EMG (middle), and
RMS-amplitude of IC-EMG (bottom). (b) Average amplitude of IC-EMG from four mice.
Amplitudes between Sleep vs. QAW vs. Active: 0.32 ± 0.042 vs. 0.70 ± 0.070 vs. 0.89 ± 0.042, p
= 0.013 (Sleep/QAW) and p = 0.0014 (Sleep/Active). (J) IC-EMG during the observational fear
task. (a) Schema of the task, (b) IC-EMG amplitude during animal's active and freezing states.
The z-scored amplitudes during non-freezing and freezing states: 0.79 ± 0.040 vs. 0.52 ± 0.054,
$t_{(6)}$ = 4.03, p = 0.007.
505

Figure S1

511   Figure S2

Supplementary Figure Legends

Fig. S1. ICs obtained from brain-referenced LFPs, relating to Figs. 2 and 3.
(A-C) Results of ICA to LFPs obtained from a healthy electrode. (A) (a) Skull-screw referenced raw LFPs which are same with Fig. 2Aa. (b) Left, brain-referenced LFPs which are calculated by subtracting ch1 activities of the skull-screw referenced LFPs. Right, noise variance of the brain-referenced LFPs, calculated by variance of 150-500 Hz bandpass filtered LFPs followed by normalizing with the variance at ch2. (c) ICs obtained by ICA to the brain-referenced LFPs (top) and raw EMGs (bottom). EMG-like component was not observed in the ICs. Channel#1 of the brain-referenced LFP was not included in ICA calculation (thus 31-ch LFP data was used for ICA) because it only has zero-values. (B) Log-log plots of the normalized power spectrum densities of each IC shown in *Ac*. Black dotted lines indicate the power of aperiodic exponent. (C) The weight distribution of ICs shown in *Ac*. (D-F) Results of ICA to LFPs obtained from a noisy electrode. (D) (a) Skull-screw referenced raw LFPs. (b) Left, because noise-levels are different depending on the channels, noise remains even in brain (ch1)-referenced LFPs. Red arrows indicate noisy channels compared to the neighboring channels. Right, noise variance of the brain-referenced LFPs obtained similarly to *Ab*, showing even number channels are noisier than odd number channels. (c) ICs obtained by ICA to the brain-referenced LFPs (top) and raw EMGs (bottom). IC#5 and IC#7 show EMG-like activities. (E) Log-log plots of the normalized power spectrum densities of ICs shown in *Dc*. (F) The weight distribution of ICs shown in *Dc*.

Fig. S2. Weight distributions of ICs of brain-referenced LFPs, and correlations with EMG, relating to Figs. 2 and 3.
(A) (a) Scatter plot of IC's mean weight, std, and amplitude, obtained from ICs of the brain-referenced LFPs from ten mice. (b) Averaged parameters of ICs. We could not find clear criteria of EMG-like ICs of the brain-referenced LFPs using these parameters. (B) Average Pearson's correlation coefficient of ICs (50-500Hz filtered) of brain-referenced LFPs and EMGs (R-EMG, L-EMG, and (R-L)-EMG) from ten mice. Dots of each color indicate different mice. Two out of ten mice had ICs that were highly correlated (>0.9) with EMG, which are obtained from LFPs of noisy electrode recordings.

550 **Supplement Material**
551
552 **KEY RESOURCES TABLE**

REAGENT or RESOURCE	SOURCE	IDENTIFIER
Experimental Models: Organisms/Strains		
C57BL/6J	Jackson Labs	Cat#:000664, RRID:IMSR_JAX:000664
Crl:CD1(ICR) (Tg(Sim1-cre)KJ21Gsat/Mmucd)	MMRRC	RRID:MMRRC_034614-UCD
Electrophysiology		
Silicone probe	NeuroNexus	A1x32-6mm-50-177-H32_21mm
Silicone probe	ATLAS Neuroengineering	E32+R-50-S1-L6 NT
Skull screws (.80unm x .060" stainless machine screw)	Antrin	https://antrinminiature.com/shop/ols/products/flat-fillister-head-metric-0-dot-80-unm-thread-050-length-stainless-steel-machine-screw
Tungsten wire (0.001'', 50–150 kΩ)	California Fine Wire	CFW0012081
Digital Lynx 4SX	Neuralynx	https://neuralynx.com/hardware/digital-lynx-sx
Open Ephys Acquisition Board	Open Ephys	https://open-ephys.org/acquisition-system/acquisition-board
Head-stage amplifier	Neuralynx	HS-36; https://neuralynx.com/hardware/hs-36
Head-stage amplifier	Intan Technologies	RHD 32; https://intantech.com/RHD_headstages.html?tabSelect=RHD32ch&yPos=100
PFA-coated silver wire, 0.005''	A-M SYSTEMS	Cat#: 786000
Bare silver wire, 0.005"	A-M SYSTEMS	Cat#: 781500
3-D Printed Custom-Designed Microdrive	This paper	N/A
Software and Algorithms		
MATLAB 2022a	MathWorks	https://www.mathworks.com/products/matlab.html?s_tid=hp_products_matlab
AnyMaze 7.16	Stoelting	https://www.any-maze.com/
Cheetah 6.4.2	Neuralynx	https://neuralynx.com/software/cheetah

Open Ephys GUI v0.6.1	Open Ephys	https://open-ephys.org/gui
EEGLAB toolbox	Delorme, et al., 2004[104]	https://sccn.ucsd.edu/eeglab/index.php
Other		
Behavior monitoring camera	e-con System	See3CAM_CU55_CHL_TC1
DAPI (4',6-Diamidino-2-Phenylindole, Dihydrochloride)	Thermo Fisher Scientific	Cat#D1306, CAS: 28718-90-3
DiI (DiIC18(3); 1,1′-dioctadecyl-3,3,3′,3′-tetramethylindocarbocyanine)	Biotium	Cat#60010, CAS: 41085-99-8
Open field chamber	This paper	N/A
Fear conditioning system	This paper	N/A
Lecia VT1000 S Vibrating Blade Microtome	Leica	VT1000 S
Leica S6E Stereomicroscope	Leica	S6E
Small Animal Stereotaxic Instrument with Digital Display Console	David Kopf Instruments	Model 942
Zeiss AxioImager M2 with Apotome	Zeiss	N/A
Arduino Due	Arduino	https://store-usa.arduino.cc/products/arduino-due?selectedStore=us

553
554
555

Lead Contact and Materials Availability

All data are available in the main text or supplementary materials. Requests for resources and additional information should be directed to and will be fulfilled by the Lead Contact, Dr. Takashi Kitamura (takashi.kitamura@utsouthwestern.edu).

Method details

Animals

All procedures relating to mouse care and experimental treatments conformed to NIH and Institutional guidelines, and were carried out with the approval of the UT Southwestern Institutional Animal Care and Use Committee (IACUC). A total of 16 male mice aged between 2 and 10 months were used. Five C57BL/6J background mice were used for open-field recording. Five Crl:CD1(ICR) background mice crossed to C57BL/6J were used both for open-field and fear conditioning recording. An additional two mice Crl:CD1(ICR) in addition to the four C57BL/6J used above were used to record including REM sleep periods (one mouse was also used for open-field/fear conditioning recording). Another four C57BL/6J background mice were used for open-field and observational fear test with four-channel multisite brain areas tungsten electrode implants, from which data were also used in previous works [67]. All animals were housed on a 12h/12h light schedule.

Electrode implantation surgery

Fabrication of silicon-probe microdrive and implant surgery was based on a previous report [105]. An implant microdrive equipped with a single-shank 32 channel, 50 μm electrode-site spacing silicon probe (A1x32-6mm-50-177-H32_21mm; NeuroNexus, Ann Arbor, MI, USA; or E32+R-50-S1-L6 NT, ATLAS Neuroengineering, Leuven, Belgium) were prepared for implantation into isoflurane-anesthetized mice. The microdrive was also equipped with a custom-made electric interface board for EMG recording (Fig. 1A), which increased the total implant weight to 6.5 g. In the first step, stainless machine screws (Antrin, Fallbrook, CA, USA) were implanted into the skull to anchor the microdrive. One of these skull screws over the center of a cerebellum was attached with bare silver wire, which serves as an electric ground and reference for the LFP recordings (Fig. 1B). Electric connectivity was checked by measuring that the impedance is less than 20 kΩ at 1 kHz between the ground screw and other skull screws. The silicon probe was then implanted into hippocampal CA1 and dentate gyrus (DG) (AP: −1.80 mm, ML: +1.60–1.70 mm, DV: +2.10–2.40 mm), then the microdrive was fixed to the skull screws by applying dental acrylic. For the EMG recording, the tips of two perfluoroalkoxy-coated silver wires (A-M Systems, Sequim, WA, USA) were exposed and tied to the left and right dorsal neck muscles (Fig. 1C) [7,10]. The skin was then covered with dental acrylic.

Implantation of multiple tungsten wire electrodes was reported previously [67]. Briefly, four sets of tungsten wire electrodes were mounted on a custom designed 3D printed microdrive (Fig. 5A), which was implanted targeting anterior cingulate cortex (ACC), basolateral amygdala (BLA), white matter above dorsal hippocampal CA1 (WM), and ventral CA1 (vCA1) (ACC: AP: +1.00 mm; ML: -0.30 mm; DV: -1.50 mm, BLA: AP: -1.40 mm; ML: +3.40 mm; DV: -5.30 mm, White matter: AP: -2.40 mm; ML: +2.00 mm; DV: -1.00 mm; vHPC: AP: -3.18 mm; ML: +3.75 mm; DV: -4.75 mm). LFP data were re-referenced offline to a skull screw above the cerebellum. All mice were allowed to recover for at least seven days after surgery. All electrode placements were histologically verified with brain slices stained with 4′,6-diamidino-2-phenylindole (DAPI) (Fig. 1D and 7B). The probe was coated with 1, 1′-dioctadecyl-3, 3, 3′, 3′-tetramethylindocarbocyanine (DiI) before the implantation.

In Vivo Electrophysiology and Behavior Experiments

LFP and EMG signals (Fig. 1E) were recorded using Neuralynx (Neuralynx, Bozeman, MT, USA)
or Open Ephys (OEPS Tech, Lisbon, Portugal) [106] systems. The wide-band signals were obtained
from the implanted electrodes and the EMG wires at 20 kHz, then band-pass filtered (0.1–500
Hz) and down-sampled to 2 kHz.
The LFPs and EMGs of the ten animals were recorded while exploring in the open field chamber
(70 cm × 38 cm) for 0.5 to 2 hours. Subsequently, five out of the ten animals were recorded during
the tone fear conditioning task using a custom-made fear conditioning box [107]. The box consists
of a 30 cm × 25 cm × 25 cm transparent acrylic box surrounded by white plastic boards, and 3
mm diameter stainless steel bars with a 6.66 mm pitch on the floor. Conditioning foot shock (1.2
mA for 20 kΩ impedance) was designed to be delivered to the bars while animal behaviors were
monitored with a camera (N660 1080P, NexiGo, Beaverton, Oregon, USA) equipped on the side
of the box. Before fear conditioning, all animals were habituated to experimenters for 2 days. On
Day1, mice were placed in the fear conditioning box and allowed to explore for 240 s. Then, a 20
s tone (90 dB, 8 kHz) was played from a speaker (ST304, VIP PRO AUDIO, Brooklyn, NY, USA),
and a 2-s foot shock was delivered to the mice at the end of the tone, and the animals' behaviors
were subsequently monitored for 240 s. This was repeated two more times before the mice were
returned to their home cage. On Day2, the mice were placed in the same box but with a different
context in the form of black plastic boards on the floor and the surrounding walls. Similarly to day1,
the mice explored the box for 240 s, then 20 s tone delivery and 240 s behavior monitoring were
repeated in total three times. LFP and EMG were recorded for the whole period of Day2. The
timing of the tone and the shock delivery is controlled by the triggering signals of Arduino Due
(A000062). The shocker consists of a portable AC power battery (ZeroKor R350), a step-up
transformer (Simran AC-100) and a rectifier (KBP210G, Diodes Incorporated, Plano, Texas, USA)
for shock delivery, and bipolar transistors (BC547BBU, onsemi, Phoenix, Arizona, USA) and
optocouplers (PC817) for shock-timing control. In addition, one mouse used above and two
additional mice were recorded in their home cages (18 × 28 × 12 cm) for 4 to 6 hours to record
LFP data including REM sleep periods.
Another four mice were recorded during the observational fear task in the previous study [67].
Briefly, implanted mice were group housed with their cagemate for one week. On Day1, the
implanted mice received one time 0.5 mA, 2-s foot shock (Med Associates, Fairfax, VT, USA). On
Day2, the implanted mice and their cagemate were placed in the shock and monitoring chambers,
respectively, which were divided by a transparent plexiglass partition. The mice were allowed to
explore the chambers for 5 min, then the implanted mice observed the cagemate receiving 0.5
mA, 2-sec foot shocks with an interval of 15 s for a total of 24 shock trials). LFPs were recorded
from ACC, BLA, WM, and vCA1 during Day2. Due to excessive line and harmonic noises
generated during recording in this shock system, we applied notch filters at 60/120/240 ± 0.1 Hz.
642
643 **Data Analysis**
644 Unless otherwise noted, analysis of electrophysiological data and animal behaviors were
645 performed using custom written scripts in MATLAB (Mathworks, Natick, MA, USA).
646
Independent component analysis of LFPs
To the aim of reconstructing EMG signals without direct EMG recording, we performed ICA on
LFP data [34,108,109]. Before running ICA, we removed unhealthy channels from the LFP data with
two criteria: (1) its waveform is distinct from the neighboring channel (unfunctional channel), (2)
the noise level is larger than the other electrode sites that are observable by eye (degraded
channel).
To separate source signals from LFP data, we used the infomax ICA algorithm [35,110] which is
implemented in the EEGLAB toolbox (*runica.m*) [104]. In ICA, the relationship between signal
sources and the recorded signals is modeled by
656 $$\mathbf{x} = \mathbf{As},$$ (**1**)

657 where **x** is the recorded signals, **s** is the source signals called independent components (ICs),
658 and **A** is the unknown mixing matrix which is to be estimated by the ICA algorithms. The source
659 signals are then obtained by the equation

$$\mathbf{s} = \mathbf{Wx}, \tag{2}$$

where **W** is computed by the inverse of matrix **A**, which is called unmixing matrix. The number of
IC **s** is same with the channel number of the recorded signals **x**. Each column of the mixing matrix
A describes how the source signals distribute along the original channels, which we called "weight
distribution". The reconstruction from the n'th component onto the original data channels is called
inverse ICA, which is accomplished by multiplying the n'th column of the mixing matrix **A** with n'th
IC. For comparing IC's distributions, we normalized their weight distributions so that their
maximum absolute is equal to one and their mean value is positive.
Here, we applied ICA to the first 4-min epoch of 32 channel silicon-probe data or previously
reported 4 channel tungsten-wire data [67] instead of using the full set of data to reduce the
calculation cost. The unmixing matrix **W** was calculated through ICA as described above from the
4-min epoch, and then source signals including outside of the 4-min epoch were obtained using
equation (2). Although data rank reduction using principal component analysis is often applied
before ICA, we did not use it because rank reduction can potentially reduce the quality of
subsequent ICA [111]. While it is known that too many IC separations can cause overfitting, a
problem in which IC waveforms are composed of repeated 'bumps' that do not appear in the
original waveforms [112,113], and indeed we have observed this problem when we have used a 25-
μm-spacing 64-ch silicon probe, this overfitting problem was not observed with our recording
setups in the current study.
679
Analysis of Power Spectral Density, IC Amplitudes, and IC-EMG/EMG Amplitudes
We used Welch's method [114] with a window length of 0.25 s and an overlap of 0.15 s to estimate
the power spectral density of EMG and IC. Aperiodic components of the power spectral density
were parameterized [115] to help find the spectral peaks. To compare the spectral features of EMG
and ICs among different animals, the power spectral densities were normalized by their
summation along all frequency ranges.
For evaluating the amplitudes of each IC, we computed how much the ICs account for the
original LFP. We calculated the amplitude ratio (Amp. ratio) by the maximum variance of the IC's
back-projected (reconstructed) signals among the channels divided by the variance of LFP at the
corresponding channel.
To calculate the time-changing amplitudes of the EEG and the EMG components obtained by
ICA from LFP (IC-EMG), we first applied the zero-phased band-pass filter (50–500 Hz) to the
original waveforms and then their root-mean-squares (RMS) were obtained with 100-ms time
windows. Comparisons of RMS among different animals were conducted with z-scored EMG/IC-
EMG data.
695
Behavioral and Statistical Analysis
During the open-field recordings, the animals' head positions were tracked based on the
position of LEDs mounted on the headstage preamplifier. The head position movements were
then computed with their average in chunks of every 15 seconds. The video-based mouse
behaviors were categorized as Sleep if the head speed was less than 0.2 cm/s lasting more than
40 s [71]. Animal's awake states were further categorized as Active if the velocity is greater than 2.0
cm/s and as Quiet Awake (QAW) if the velocity is less than 2.0 cm/s in every 15 s epoch [82]. In
fear conditioning experiments, animals' freezing behavior was detected by AnyMaze software
(Stoelting, Wood Dale, IL, USA). The detection of freezing response during observational fear
experiments was carried out using the Video Freeze Fear Conditioning System software (Med
Associates) as we previously reported [67].

To detect REM sleep periods (see Fig. 6), theta-to-delta ratio[48,49] and EMG [56-60] amplitude were
used in addition to the video-based criteria stated above. First, spectrogram of LFP at CA1 st. lm
layer was calculated by continuous wavelet transform with Morse wavelet using *cwt.m* function of
Matlab 2022a. LFPs were separated into 10 second epochs to reduce computational cost for the
wavelet transform and subsequently concatenated to calculate theta (6–9 Hz)-to-delta (0.1–4 Hz)
ratio. Next, video-based classified Sleep state period were re-classified using IC-EMG/EMG
amplitude. The 15 seconds chunks are further separated into 5 seconds chunks, then the video-
based Sleep was re-classified into QAW if the EMG amplitudes were above z = 1.5 for more than
20% of the chunk duration and otherwise remained into Sleep. Then, Sleep periods were
classified into REM if theta-to-delta ratio ≥ 4 [60] which continues more than 5 seconds and
otherwise into NREM. The short theta-to-delta < 4 periods which are <5 seconds between REM
states are also categorized as REM state. Only the mice showing >20 mins sleep durations and
showing REM states (six mice) were used for the further analysis. Cohen's kappa values was
calculated by $\kappa = (p_o - p_e)/(1 - p_e)$ [64-66], where p_o is observed agreement rate between video-
based/IC-EMG-based REM periods vs. EMG-based REM periods, and p_e is random agreement
rate between them.
We used Student's t-test after testing normality. Tukey's honest significance tests were
employed for multiple comparisons. $p < 0.05$ was assumed to be statistically significant. *
indicates $p < 0.05$, ** indicates $p < 0.01$, and *** indicates $p < 0.001$. All tests were two-sided. Bar
plots and error bars represent means and standard errors.
727
728

729 **Code availability**
730 The custom Matlab code is available at https://github.com/HisayukiOsanai/IC-EMG.git
731
732

References

1.	Borbély AA, Tobler I, Hanagasioglu M. Effect of sleep deprivation on sleep and EEG power spectra in the rat. *Behavioural brain research*. 1984 Dec 1984;14(3)doi:10.1016/0166-4328(84)90186-4

2.	Vyazovskiy V, Olcese U, Hanlon E, Nir Y, Cirelli C, Tononi G. Local sleep in awake rats. *Nature*. 04/28/2011 2011;472(7344)doi:10.1038/nature10009

3.	Louis R, Lee J, Stephenson R. Design and validation of a computer-based sleep-scoring algorithm. *Journal of neuroscience methods*. 02/15/2004 2004;133(1-2)doi:10.1016/j.jneumeth.2003.09.025

4.	Ji D, Wilson M. Coordinated memory replay in the visual cortex and hippocampus during sleep. *Nature neuroscience*. 2007 Jan 2007;10(1)doi:10.1038/nn1825

5.	Dash M, Douglas C, Vyazovskiy V, Cirelli C, Tononi G. Long-term homeostasis of extracellular glutamate in the rat cerebral cortex across sleep and waking states. *The Journal of neuroscience*. 01/21/2009 2009;29(3)doi:10.1523/JNEUROSCI.5486-08.2009

6.	Kassiri H, Chemparathy A, Salam M, Boyce R, Adamantidis A, Genov R. Electronic Sleep Stage Classifiers: A Survey and VLSI Design Methodology. *IEEE transactions on biomedical circuits and systems*. 2017 Feb 2017;11(1)doi:10.1109/TBCAS.2016.2540438

7.	Steenland H, Zhuo M. Neck electromyography is an effective measure of fear behavior. *Journal of neuroscience methods*. 03/15/2009 2009;177(2)doi:10.1016/j.jneumeth.2008.10.020

8.	Karalis N, Dejean C, Chaudun F, et al. 4-Hz oscillations synchronize prefrontal-amygdala circuits during fear behavior. *Nature neuroscience*. 2016 Apr 2016;19(4)doi:10.1038/nn.4251

9.	Isosaka T, Matsuo T, Yamaguchi T, et al. Htr2a-Expressing Cells in the Central Amygdala Control the Hierarchy between Innate and Learned Fear. *Cell*. 11/19/2015 2015;163(5)doi:10.1016/j.cell.2015.10.047

10.	Okada S, Igata H, Sakaguchi T, Sasaki T, Ikegaya Y. A new device for the simultaneous recording of cerebral, cardiac, and muscular electrical activity in freely moving rodents. *Journal of pharmacological sciences*. 2016 Sep 2016;132(1)doi:10.1016/j.jphs.2016.06.001

11.	Taylor H, Schmiedt J, Carçak N, et al. Investigating local and long-range neuronal network dynamics by simultaneous optogenetics, reverse microdialysis and silicon probe recordings in vivo. *Journal of neuroscience methods*. 09/30/2014 2014;235doi:10.1016/j.jneumeth.2014.06.031

12.	Shikano Y, Sasaki T, Ikegaya Y. Simultaneous Recordings of Cortical Local Field Potentials, Electrocardiogram, Electromyogram, and Breathing Rhythm from a Freely Moving Rat. *Journal of visualized experiments : JoVE*. 04/02/2018 2018;(134)doi:10.3791/56980

13.	Zhu K, Aiani L, Pedersen N. Reconfigurable 3D-Printed headplates for reproducible and rapid implantation of EEG, EMG and depth electrodes in mice. *Journal of neuroscience methods*. 03/01/2020 2020;333doi:10.1016/j.jneumeth.2019.108566

14.	Whelan P. Electromyogram recordings from freely moving animals. *Methods (San Diego, Calif)*. 2003 Jun 2003;30(2)doi:10.1016/s1046-2023(03)00074-4

15.	Liang Y, Shi W, Hu D, Xiang A, Zhang L. Protocol for recording the discharge of locus coeruleus neurons in free-moving mice during different sleep-wake stages. *STAR protocols*. 12/01/2021 2021;2(4)doi:10.1016/j.xpro.2021.100981

16.	Rossetti N, Luthra P, Hagler J, et al. Poly(3,4-ethylenedioxythiophene) (PEDOT) Coatings for High-Quality Electromyography Recording. *ACS applied bio materials*. 11/18/2019 2019;2(11)doi:10.1021/acsabm.9b00809

17.	Buzsáki G, Draguhn A. Neuronal oscillations in cortical networks. *Science (New York, NY)*. 06/25/2004 2004;304(5679)doi:10.1126/science.1099745

18.	Steriade M, McCormick D, Sejnowski T. Thalamocortical oscillations in the sleeping and aroused brain. *Science (New York, NY)*. 10/29/1993 1993;262(5134)doi:10.1126/science.8235588

19.   Buzsáki G, Leung L, Vanderwolf C. Cellular bases of hippocampal EEG in the behaving
rat. *Brain research*. 1983 Oct 1983;287(2)doi:10.1016/0165-0173(83)90037-1
20.   Buzsáki G. Hippocampal sharp wave-ripple: A cognitive biomarker for episodic memory
and planning. *Hippocampus*. 2015 Oct 2015;25(10)doi:10.1002/hipo.22488
21.   Çalışkan G, Stork O. Hippocampal network oscillations at the interplay between innate
anxiety and learned fear. *Psychopharmacology*. 2019 Jan 2019;236(1)doi:10.1007/s00213-018-
5109-z
22.   Pape H, Narayanan R, Smid J, Stork O, Seidenbecher T. Theta activity in neurons and
networks of the amygdala related to long-term fear memory. *Hippocampus*. 2005
2005;15(7)doi:10.1002/hipo.20120
23.   Jones MW, Wilson MA. Theta rhythms coordinate hippocampal-prefrontal interactions in
a spatial memory task. *PLoS Biol*. Dec 2005;3(12):e402. doi:10.1371/journal.pbio.0030402
24.   Kajikawa Y, Schroeder C. How local is the local field potential? *Neuron*. 12/08/2011
2011;72(5)doi:10.1016/j.neuron.2011.09.029
25.   Liu A, Henin S, Abbaspoor S, et al. A consensus statement on detection of hippocampal
sharp wave ripples and differentiation from other fast oscillations. *Nature communications*.
10/12/2022 2022;13(1)doi:10.1038/s41467-022-33536-x
26.   Fein G, Raz J, Brown F, Merrin E. Common reference coherence data are confounded by
power and phase effects. *Electroencephalography and clinical neurophysiology*. 1988 Jun
1988;69(6)doi:10.1016/0013-4694(88)90171-x
27.   Jun JJ, Steinmetz NA, Siegle JH, et al. Fully integrated silicon probes for high-density
recording of neural activity. *Nature*. Nov 8 2017;551(7679):232-236. doi:10.1038/nature24636
28.   Berke J, Okatan M, Skurski J, Eichenbaum H. Oscillatory entrainment of striatal neurons
in freely moving rats. *Neuron*. 09/16/2004 2004;43(6)doi:10.1016/j.neuron.2004.08.035
29.   Mölle M, Yeshenko O, Marshall L, Sara S, Born J. Hippocampal sharp wave-ripples linked
to slow oscillations in rat slow-wave sleep. *Journal of neurophysiology*. 2006 Jul
2006;96(1)doi:10.1152/jn.00014.2006
30.   Ludwig K, Miriani R, Langhals N, Joseph M, Anderson D, Kipke D. Using a common
average reference to improve cortical neuron recordings from microelectrode arrays. *Journal of*
neurophysiology. 2009 Mar 2009;101(3)doi:10.1152/jn.90989.2008
31.   Nicholson C, Freeman JA. Theory of current source-density analysis and determination of
conductivity tensor for anuran cerebellum. *J Neurophysiol*. Mar 1975;38(2):356-68.
32.   Tenke C, Kayser J. Reference-free quantification of EEG spectra: combining current
source density (CSD) and frequency principal components analysis (fPCA). *Clinical*
neurophysiology : official journal of the International Federation of Clinical Neurophysiology. 2005
Dec 2005;116(12)doi:10.1016/j.clinph.2005.08.007
33.   Tenke C, Kayser J. Generator localization by current source density (CSD): implications
of volume conduction and field closure at intracranial and scalp resolutions. *Clinical*
neurophysiology : official journal of the International Federation of Clinical Neurophysiology. 2012
Dec 2012;123(12)doi:10.1016/j.clinph.2012.06.005
34.   Whitmore N, Lin S. Unmasking local activity within local field potentials (LFPs) by
removing distal electrical signals using independent component analysis. *NeuroImage*.
05/15/2016 2016;132doi:10.1016/j.neuroimage.2016.02.032
35.   Bell A, Sejnowski T. An information-maximization approach to blind separation and blind
deconvolution. *Neural computation*. 1995 Nov 1995;7(6)doi:10.1162/neco.1995.7.6.1129
36.   Hyvärinen A, Oja E. Independent component analysis: algorithms and applications. *Neural*
networks. 2000 May-Jun 2000;13(4-5)doi:10.1016/s0893-6080(00)00026-5
37.   Hyvärinen A. Independent component analysis: recent advances. *Philosophical*
transactions Series A, Mathematical, physical, and engineering sciences. 12/31/2012
2012;371(1984)doi:10.1098/rsta.2011.0534

38.   Jutten C, Herault J. Blind separation of sources, part I: An adaptive algorithm based on
neuromimetic   architecture.   *Signal   Processing*.   1991/07/01/   1991;24(1):1-10.
doi:https://doi.org/10.1016/0165-1684(91)90079-X

39.   Makeig S, Bell A, Jung T-P, Sejnowski TJ. Independent component analysis of
electroencephalographic data. *Advances in neural information processing systems*. 1995;8

40.   Jung T, Makeig S, Humphries C, et al. Removing electroencephalographic artifacts by
blind source separation. *Psychophysiology*. 2000 Mar 2000;37(2)

41.   Jung T-P, Humphries C, Lee T-W, et al. Extended ICA removes artifacts from
electroencephalographic recordings. presented at: Proceedings of the 10th International
Conference on Neural Information Processing Systems; 1997; Denver, CO.

42.   Vigário R, Särelä J, Jousmäki V, Hämäläinen M, Oja E. Independent component approach
to the analysis of EEG and MEG recordings. *IEEE transactions on bio-medical engineering*. 2000
May 2000;47(5)doi:10.1109/10.841330

43.   Winkler I, Haufe S, Tangermann M. Automatic classification of artifactual ICA-components
for artifact removal in EEG signals. *Behavioral and brain functions : BBF*. 08/02/2011
2011;7doi:10.1186/1744-9081-7-30

44.   Blanchard D, Blanchard R. Innate and conditioned reactions to threat in rats with
amygdaloid lesions. *Journal of comparative and physiological psychology*. 1972 Nov
1972;81(2)doi:10.1037/h0033521

45.   Kitamura T, Saitoh Y, Takashima N, et al. Adult neurogenesis modulates the
hippocampus-dependent   period   of   associative   fear   memory.   *Cell*.   11/13/2009
2009;139(4)doi:10.1016/j.cell.2009.10.020

46.   Kitamura T, Pignatelli M, Suh J, et al. Island cells control temporal association memory.
Science. Feb 2014;343(6173):896-901. doi:10.1126/science.1244634

47.   Yokose J, Marks W, Yamamoto N, Ogawa S, Kitamura T. Entorhinal cortical Island cells
regulate temporal association learning with long trace period. *Learning & memory (Cold Spring
Harbor, NY)*. 08/16/2021 2021;28(9)doi:10.1101/lm.052589.120

48.   Louie K, Wilson M. Temporally structured replay of awake hippocampal ensemble activity
during   rapid   eye   movement   sleep.   *Neuron*.   2001   Jan   2001;29(1)doi:10.1016/s0896-
6273(01)00186-6

49.   Csicsvari J, Hirase H, Czurkó A, Mamiya A, Buzsáki G. Oscillatory coupling of
hippocampal pyramidal cells and interneurons in the behaving Rat. *The Journal of neuroscience :
the   official   journal   of   the   Society   for   Neuroscience*.   01/01/1999
1999;19(1)doi:10.1523/JNEUROSCI.19-01-00274.1999

50.   Tort A, Ponsel S, Jessberger J, Yanovsky Y, Brankačk J, Draguhn A. Parallel detection of
theta and respiration-coupled oscillations throughout the mouse brain. *Scientific reports*.
04/24/2018 2018;8(1)doi:10.1038/s41598-018-24629-z

51.   Aitken P, Zheng Y, Smith P. The modulation of hippocampal theta rhythm by the vestibular
system. *Journal of neurophysiology*. 02/01/2018 2018;119(2)doi:10.1152/jn.00548.2017

52.   Vyazovskiy V, Tobler I. Theta activity in the waking EEG is a marker of sleep propensity
in the rat. *Brain research*. 07/19/2005 2005;1050(1-2)doi:10.1016/j.brainres.2005.05.022

53.   Harris KD, Thiele A. Cortical state and attention. ReviewPaper. *Nature Reviews
Neuroscience*. 2011-08-10 2011;12(9):509-523. doi:doi:10.1038/nrn3084

54.   Snipes S, Krugliakova E, Meier E, Huber R. The theta paradox: 4-8 Hz EEG oscillations
reflect both sleep pressure and cognitive control. *The Journal of neuroscience : the official journal
of the Society for Neuroscience*. 10/06/2022 2022;doi:10.1523/JNEUROSCI.1063-22.2022

55.   Ward L. Synchronous neural oscillations and cognitive processes. *Trends in cognitive
sciences*. 2003 Dec 2003;7(12)doi:10.1016/j.tics.2003.10.012

56.   Funk C, Honjoh S, Rodriguez A, Cirelli C, Tononi G. Local Slow Waves in Superficial
Layers of Primary Cortical Areas during REM Sleep. *Current biology : CB*. 02/08/2016
2016;26(3)doi:10.1016/j.cub.2015.11.062

57.   Van Gelder R, Edgar D, Dement W. Real-time automated sleep scoring: validation of a
microcomputer-based system for mice. *Sleep*. 1991 Feb 1991;14(1)doi:10.1093/sleep/14.1.48
58.   Willie J, Chemelli R, Sinton C, et al. Distinct narcolepsy syndromes in Orexin receptor-2
and Orexin null mice: molecular genetic dissection of Non-REM and REM sleep regulatory
processes. *Neuron*. 06/05/2003 2003;38(5)doi:10.1016/s0896-6273(03)00330-1
59.   Weber F, Chung S, Beier K, Xu M, Luo L, Dan Y. Control of REM sleep by ventral medulla
GABAergic neurons. *Nature*. 10/15/2015 2015;526(7573)doi:10.1038/nature14979
60.   Kocsis B, Li S, Hajos M. Behavior-dependent modulation of hippocampal EEG activity by
the selective norepinephrine reuptake inhibitor reboxetine in rats. *Hippocampus*. 2007
2007;17(8)doi:10.1002/hipo.20299
61.   Brooks P, Peever J. A Temporally Controlled Inhibitory Drive Coordinates Twitch
Movements   during   REM   Sleep.   *Current   biology   :   CB*.   05/09/2016
2016;26(9)doi:10.1016/j.cub.2016.03.013
62.   Peever J, Fuller P. The Biology of REM Sleep. *Current biology : CB*. 11/20/2017
2017;27(22)doi:10.1016/j.cub.2017.10.026
63.   Kayed K, Hesla P, Røsjø O. The actioculographic monitor of sleep. *Sleep*. 1979
1979;2(2)doi:10.1093/sleep/2.2.253
64.   Sridhar N, Shoeb A, Stephens P, et al. Deep learning for automated sleep staging using
instantaneous heart rate. *NPJ digital medicine*. 08/20/2020 2020;3doi:10.1038/s41746-020-0291-
x
65.   Malafeev A, Laptev D, Bauer S, et al. Automatic Human Sleep Stage Scoring Using Deep
Neural Networks. *Frontiers in neuroscience*. 11/06/2018 2018;12doi:10.3389/fnins.2018.00781
66.   Cohen J. A Coefficient of Agreement for Nominal Scales. *Educational and Psychological
Measurement*. 1960;20(1):37-46. doi:10.1177/001316446002000104
67.   Terranova JI, Yokose J, Osanai H, et al. Hippocampal-amygdala memory circuits govern
experience-dependent   observational   fear.   *Neuron*.   04/20/2022
2022;110(8)doi:10.1016/j.neuron.2022.01.019
68.   Debiec J, Olsson A. Social Fear Learning: from Animal Models to Human Function. *Trends
in cognitive sciences*. 2017 Jul 2017;21(7)doi:10.1016/j.tics.2017.04.010
69.   Keum S, Shin H. Neural Basis of Observational Fear Learning: A Potential Model of
Affective Empathy. *Neuron*. 10/09/2019 2019;104(1)doi:10.1016/j.neuron.2019.09.013
70.   Panksepp J, Lahvis G. Rodent empathy and affective neuroscience. *Neuroscience and
biobehavioral reviews*. 2011 Oct 2011;35(9)doi:10.1016/j.neubiorev.2011.05.013
71.   Fisher S, Godinho S, Pothecary C, Hankins M, Foster R, Peirson S. Rapid assessment of
sleep-wake   behavior   in   mice.   *Journal   of   biological   rhythms*.   2012   Feb
2012;27(1)doi:10.1177/0748730411431550
72.   McShane B, Galante R, Biber M, Jensen S, Wyner A, Pack A. Assessing REM sleep in
mice using video data. *Sleep*. 03/01/2012 2012;35(3)doi:10.5665/sleep.1712
73.   Leemburg S, Vyazovskiy V, Olcese U, Bassetti C, Tononi G, Cirelli C. Sleep homeostasis
in the rat is preserved during chronic sleep restriction. *Proceedings of the National Academy of
Sciences   of   the   United   States   of   America*.   09/07/2010
2010;107(36)doi:10.1073/pnas.1002570107
74.   Blaivas A, Patel R, Hom D, Antigua K, Ashtyani H. Quantifying microsleep to help assess
subjective sleepiness. *Sleep medicine*. 2007 Mar 2007;8(2)doi:10.1016/j.sleep.2006.06.011
75.   Bastianini S, Alvente S, Berteotti C, et al. Accurate discrimination of the wake-sleep states
of mice using non-invasive whole-body plethysmography. *Scientific reports*. 01/31/2017
2017;7doi:10.1038/srep41698
76.   Pack A, Galante R, Maislin G, et al. Novel method for high-throughput phenotyping of
sleep   in   mice.   *Physiological   genomics*.   01/17/2007
2007;28(2)doi:10.1152/physiolgenomics.00139.2006

77.   Mang G, Nicod J, Emmenegger Y, Donohue K, O'Hara B, Franken P. Evaluation of a
piezoelectric system as an alternative to electroencephalogram/ electromyogram recordings in
mouse sleep studies. *Sleep*. 08/01/2014 2014;37(8)doi:10.5665/sleep.3936
78.   Flores A, Flores J, Deshpande H, et al. Pattern recognition of sleep in rodents using
piezoelectric signals generated by gross body movements. *IEEE transactions on bio-medical*
engineering. 2007 Feb 2007;54(2)doi:10.1109/TBME.2006.886938
79.   Montgomery S, Sirota A, Buzsáki G. Theta and gamma coordination of hippocampal
networks during waking and rapid eye movement sleep. *The Journal of neuroscience : the official*
journal of the Society for Neuroscience. 06/25/2008 2008;28(26)doi:10.1523/JNEUROSCI.1227-
08.2008
80.   Pompili M, Todorova R. Discriminating Sleep From Freezing With Cortical Spindle
Oscillations. *Frontiers in neural circuits*. 03/24/2022 2022;16doi:10.3389/fncir.2022.783768
81.   Khodagholy D, Gelinas J, Buzsáki G. Learning-enhanced coupling between ripple
oscillations in association cortices and hippocampus. *Science (New York, NY)*. 10/20/2017
2017;358(6361)doi:10.1126/science.aan6203
82.   Yamamoto J, Tonegawa S. Direct Medial Entorhinal Cortex Input to Hippocampal CA1 Is
Crucial for Extended Quiet Awake Replay. *Neuron*. Sep 27 2017;96(1):217-227.e4.
doi:10.1016/j.neuron.2017.09.017
83.   Vanderwolf C. Hippocampal electrical activity and voluntary movement in the rat.
Electroencephalography and clinical neurophysiology. 1969 Apr 1969;26(4)doi:10.1016/0013-
4694(69)90092-3
84.   Hubbard J, Gent T, Hoekstra M, et al. Rapid fast-delta decay following prolonged
wakefulness marks a phase of wake-inertia in NREM sleep. *Nature communications*. 06/19/2020
2020;11(1)doi:10.1038/s41467-020-16915-0
85.   Adamantidis A, Gutierrez HC, Gent T. Oscillating circuitries in the sleeping brain. *Nature*
reviews Neuroscience. 2019 Dec 2019;20(12)doi:10.1038/s41583-019-0223-4
86.   Chen X, Xu X, Liu A, McKeown MJ, Wang ZJ. The Use of Multivariate EMD and CCA for
Denoising Muscle Artifacts From Few-Channel EEG Recordings. *IEEE Transactions on*
Instrumentation and Measurement. 2018;67(2):359-370. doi:10.1109/TIM.2017.2759398
87.   Mijović B, Vos MD, Gligorijević I, Taelman J, Huffel SV. Source separation from single-
channel recordings by combining empirical-mode decomposition and independent component
analysis.   *IEEE   transactions   on   bio-medical   engineering*.   2010   Sep
2010;57(9)doi:10.1109/TBME.2010.2051440
88.   Rejer I, Górski P. MAICA: an ICA-based method for source separation in a low-channel
EEG recording. *Journal of neural engineering*. 09/11/2019 2019;16(5)doi:10.1088/1741-
2552/ab36db
89.   Zou L, Chen X, Dang G, Guo Y, Wang ZJ. Removing Muscle Artifacts From EEG Data via
Underdetermined Joint Blind Source Separation: A Simulation Study. *IEEE Transactions on*
Circuits and Systems II: Express Briefs. 2020;67(1):187-191. doi:10.1109/TCSII.2019.2903648
90.   Jiang X, Bian G, Tian Z. Removal of Artifacts from EEG Signals: A Review. *Sensors (Basel,*
Switzerland). 02/26/2019 2019;19(5)doi:10.3390/s19050987
91.   Minguillon J, Lopez-Gordo MA, Pelayo F. Trends in EEG-BCI for daily-life: Requirements
for artifact removal. *Biomedical Signal Processing and Control*. 2017/01/01/ 2017;31:407-418.
doi:https://doi.org/10.1016/j.bspc.2016.09.005
92.   Chen X, Xu X, Liu A, et al. Removal of Muscle Artifacts From the EEG: A Review and
Recommendations.   *IEEE   Sensors   Journal*.   2019;19(14):5353-5368.
doi:10.1109/JSEN.2019.2906572
93.   Herreras O, Makarova J, Makarov V. New uses of LFPs: Pathway-specific threads
obtained   through   spatial   discrimination.   *Neuroscience*.   12/03/2015
2015;310doi:10.1016/j.neuroscience.2015.09.054

94. Parabucki A, Lampl I. Volume Conduction Coupling of Whisker-Evoked Cortical LFP in
the Mouse Olfactory Bulb. *Cell reports*. 10/24/2017 2017;21(4)doi:10.1016/j.celrep.2017.09.094
95. Calderon D, Fremont R, Kraenzlin F, Khodakhah K. The neural substrates of rapid-onset
Dystonia-Parkinsonism. *Nature neuroscience*. 2011 Mar 2011;14(3)doi:10.1038/nn.2753
96. McNamara M, Ersöz A, Han M. A Diagnostic Circuit for Crosstalk Detection in
Microelectrode Arrays. *International IEEE/EMBS Conference on Neural Engineering :*
[proceedings] International IEEE EMBS Conference on Neural Engineering. 2021 May
2021;2021doi:10.1109/ner49283.2021.9441164
97. Kozai T, Catt K, Li X, et al. Mechanical failure modes of chronically implanted planar
silicon-based neural probes for laminar recording. *Biomaterials*. 2015 Jan
2015;37doi:10.1016/j.biomaterials.2014.10.040
98. Hara SA, Kim BJ, Kuo JTW, Meng E. An Electrochemical Investigation of the Impact of
Microfabrication Techniques on Polymer-Based Microelectrode Neural Interfaces. *Journal of*
Microelectromechanical Systems. 2015;24(4):801-809. doi:10.1109/JMEMS.2015.2434827
99. Barth D, Sutherling W. Current source-density and neuromagnetic analysis of the direct
cortical response in rat cortex. *Brain research*. 05/31/1988 1988;450(1-2)doi:10.1016/0006-
8993(88)91567-3
100. McFarland D, McCane L, David S, Wolpaw J. Spatial filter selection for EEG-based
communication. *Electroencephalography and clinical neurophysiology*. 1997 Sep
1997;103(3)doi:10.1016/s0013-4694(97)00022-2
101. Rappelsberger P, Pockberger H, Petsche H. Current source density analysis: methods
and application to simultaneously recorded field potentials of the rabbit's visual cortex. *Pflugers*
Archiv : European journal of physiology. 1981 Jan 1981;389(2)doi:10.1007/BF00582108
102. Boyce R, Glasgow S, Williams S, Adamantidis A. Causal evidence for the role of REM
sleep theta rhythm in contextual memory consolidation. *Science (New York, NY)*. 05/13/2016
2016;352(6287)doi:10.1126/science.aad5252
103. Aulehner K, Bray J, Koska I, et al. The impact of tethered recording techniques on activity
and sleep patterns in rats. *Scientific reports*. 02/24/2022 2022;12(1)doi:10.1038/s41598-022-
06307-3
104. Delorme A, Makeig S. EEGLAB: an open source toolbox for analysis of single-trial EEG
dynamics including independent component analysis. *Journal of neuroscience methods*.
03/15/2004 2004;134(1)doi:10.1016/j.jneumeth.2003.10.009
105. Osanai H, Kitamura T, Yamamoto J. Hybrid Microdrive System with Recoverable Opto-
Silicon Probe and Tetrode for Dual-Site High Density Recording in Freely Moving Mice. *Journal*
of visualized experiments : JoVE. 08/10/2019 2019;(150)doi:10.3791/60028
106. Siegle J, López A, Patel Y, Abramov K, Ohayon S, Voigts J. Open Ephys: an open-source,
plugin-based platform for multichannel electrophysiology. *Journal of neural engineering*. 2017
Aug 2017;14(4)doi:10.1088/1741-2552/aa5eea
107. Amaral-Júnior P, Mourão F, Amancio M, et al. A Custom Microcontrolled and Wireless-
Operated Chamber for Auditory Fear Conditioning. *Frontiers in neuroscience*. 11/07/2019
2019;13doi:10.3389/fnins.2019.01193
108. Makarov V, Makarova J, Herreras O. Disentanglement of local field potential sources by
independent component analysis. *Journal of computational neuroscience*. 2010 Dec
2010;29(3)doi:10.1007/s10827-009-0206-y
109. Schomburg EW, Fernandez-Ruiz A, Mizuseki K, et al. Theta phase segregation of input-
specific gamma patterns in entorhinal-hippocampal networks. *Neuron*. Oct 22 2014;84(2):470-85.
doi:10.1016/j.neuron.2014.08.051
110. Lee T, Girolami M, Sejnowski T. Independent component analysis using an extended
infomax algorithm for mixed subgaussian and supergaussian sources. *Neural computation*.
02/15/1999 1999;11(2)doi:10.1162/089976699300016719

111.   Artoni F, Delorme A, Makeig S. Applying dimension reduction to EEG data by Principal
Component Analysis reduces the quality of its subsequent Independent Component
decomposition. *NeuroImage*. 07/15/2018 2018;175doi:10.1016/j.neuroimage.2018.03.016
112.   Sebek J, Bortel R, Sovka P. Suppression of overlearning in independent component
analysis used for removal of muscular artifacts from electroencephalographic records. *PloS one*.
08/14/2018 2018;13(8)doi:10.1371/journal.pone.0201900
113.   Hyvärinen A, Särelä J, Ssrels J, Vigário R. Spikes and bumps: Artefacts generated by
independent component analysis with insufficient sample size. 1999;
114.   Welch PD. The use of fast Fourier transform for the estimation of power spectra: A method
based on time averaging over short, modified periodograms. *IEEE Transactions on Audio and*
Electroacoustics. 1967;15(2):70-73. doi:10.1109/TAU.1967.1161901
115.   Donoghue T, Haller M, Peterson E, et al. Parameterizing neural power spectra into
periodic   and   aperiodic   components.   *Nature*   *neuroscience*.   2020   Dec
2020;23(12)doi:10.1038/s41593-020-00744-x
1049
1050