Supercomputer framework for reverse engineering firing patterns of neuron populations to identify their synaptic inputs

Matthieu K. Chardon[*1,10], **Y. Curtis Wang**[2], **Marta Garcia**[3], **Emre Besler**[4], **J. Andrew Beauchamp**[5], **Michael D'Mello**[6], **Randall K. Powers**[7], **Charles J. Heckman**[1,8,9]

*For correspondence:
m-chardon@northwestern.edu

[1]Department of Neuroscience, Northwestern University, Chicago, IL, USA; [2]Department of Electrical and Computer Engineering, California State University, Los Angeles, Los Angeles, CA, USA; [3]Argonne Leadership Computing Facility, Argonne National Laboratory, Lemont, IL, USA; [4]Department of Electrical Engineering, Northwestern University, Evanston, IL, USA; [5]Department of Biomedical Engineering, Northwestern University, Chicago, IL, USA; [6]Intel Corporation, Santa Clara, CA, USA; [7]Department of Physiology and Biophysics, University of Washington, Seattle, WA, USA; [8]Physical Medicine and Rehabilitation, Shirley Ryan Ability Lab, Chicago, IL, USA; [9]Physical Therapy and Human Movement Sciences, Northwestern University, Chicago, IL, USA; [10]Northwestern-Argonne Institute of Science and Engineering (NAISE), Evanston, IL, USA

Abstract   In this study, we develop new reverse engineering (RE) techniques to identify the organization of the synaptic inputs generating firing patterns of populations of neurons. We tested these techniques *in silico* to allow rigorous evaluation of their effectiveness, using remarkably extensive parameter searches enabled by massively-parallel computation on supercomputers. We chose spinal motoneurons as our target neural system, since motoneurons process all motor commands and have well established input-output properties. One set of simulated motoneurons was driven by 300,000+ simulated combinations of excitatory, inhibitory, and neuromodulatory inputs. Our goal was to determine if these firing patterns had sufficient information to allow RE identification of the input combinations. Like other neural systems, the motoneuron input-output system is likely non-unique. This non-uniqueness could potentially limit this RE approach, as many input combinations can produce similar outputs. However, our simulations revealed that firing patterns contained sufficient information to sharply restrict the solution space. Thus, our RE approach successfully generated estimates of the actual simulated patterns of excitation, inhibition, and neuromodulation, with variances accounted for ranging from 75% to 90%. It was striking that nonlinearities induced in firing patterns by the neuromodulation inputs did not impede RE, but instead generated distinctive features in firing patterns that aided RE. These simulations demonstrate the potential of this form of RE analysis. It is likely that the ever-increasing capacity of supercomputers will allow increasingly accurate RE of neuron inputs from their firing patterns from many neural systems.

Introduction

Array electrodes that allow simultaneous recording of firing patterns of populations of neurons in mammals have transformed understanding of the computations implemented by neural networks during natural behaviors and the utilization of these computations for brain machine interfaces (*Buonomano and Maass, 2009*; *Chandrasekaran et al., 2021*; *Stevenson et al., 2012*; *Stevenson and Kording, 2011*; *Vyas et al., 2020*). However, to understand how a given neural network generates the firing patterns that implement these computations, it is necessary to understand the transformation of inputs to outputs by the constituent neurons. The net effect of ionotropic excitatory inputs in activating a neural circuit is likely to be strongly impacted by the pattern of inhibitory inputs arising from local interneurons and the effects of neuromodulatory inputs acting on G-protein coupled receptors (*Binder et al., 2020*; *Goaillard and Marder, 2021*; *McCormick and Nusbaum, 2014*). In-depth analyses of the resulting complex interactions require intracellular electrode techniques, but these are not yet feasible simultaneously in many neurons during a natural behavior. An alternative is reverse engineering (RE) the firing patterns recorded by arrays to identify the neurons' inputs and properties.

Thus far, RE has been used to achieve several different goals, including estimation of circuit structures within simulations with simple neuron models (*Lim et al., 2011*; *Pisokas, 2021*; *Rostro-Gonzalez et al., 2012*) and estimation local field potentials from measurements of spiking patterns (*Telenczuk et al., 2020*; *Yochum et al., 2019*). In this study, our goal was to harness the computational power provided by implementation of realistic neuron models on a supercomputer to investigate the feasibility of reverse engineering these model firing patterns to identify the underlying organization of their simulated excitatory, inhibitory and neuromodulatory inputs. Successful RE of firing patterns into input organization would greatly advance the effectiveness of array recordings in identifying how neural circuits implement their computations.

RE of neural outputs into inputs faces a formidable barrier. Multiple neural systems have been shown to exhibit non-uniqueness, which is manifest as closely similar outputs being produced by many combinations of parameters specifying neuron properties and inputs (*Edelman and Gally, 2001*; *Marder, 2012*; *Prinz et al., 2004*). This set of parameters forms the "solution space" for that neural system (*Prinz, 2010*). Although likely advantageous for stability and resilience of neurons and circuits (*Goaillard and Marder, 2021*), a large solution space that contain many combinations of excitation, inhibition and neuromodulation may limit the effectiveness of RE. In addition, the parameters within the solution space may interact in complex, nonlinear ways (*Mukunda and Narayanan, 2017*). Neuromodulatory inputs, for example, may have highly nonlinear effects on how neurons process their ionotropic inputs (*Binder et al., 2020*; *Marder, 2012*; *McCormick and Nusbaum, 2014*). On the other hand, when neuronal output behaviors are complex, non-uniqueness may be reduced by the constraints of matching multiple outputs (*Mukunda and Narayanan, 2017*; *Yang et al., 2022*).

To reduce the impact of non-uniqueness, we chose a well-understood neural system for evaluation of RE, the motoneurons that transform all motor commands into signals for control of muscles (*Heckman and Enoka, 2012*). Motoneuron properties and inputs have been extensively studied using in situ voltage clamp methods in animal preparations, with a focus on neuromodulatory actions (*Heckman and Enoka, 2012*; *Henneman and Mendell, 1981*). This data set has enabled us to generate highly realistic motoneuron models (*Powers et al., 2012*; *Powers and Heckman, 2017*), which we have successfully implemented on a supercomputer for the present study. Furthermore, recent advances in flexible array electrode methods now allow measurement of firing patterns of populations of motoneurons in humans, due to the one-to-one relation between motoneuron action potentials and those of its innervated muscle fibers (*Holobar et al., 2010*; *Hug et al., 2021*; *Negro et al., 2016*). Consequently, RE of these population firing patterns may generate deep insights into the synaptic organization of motor commands in humans as well as other animals.

We used an ensemble modeling approach (*Prinz, 2010*) to determine how non-uniqueness and

nonlinearity affected RE identification of the pattern of excitatory, inhibitory and neuromodulatory inputs that produces motor output. All studies were carried out *in silico*, so that both inputs and outputs were known and thus the effectiveness of RE could be accurately quantified. The supercomputer implementation of motoneuron models allowed us to thoroughly explore this input solution space, via more than 300,000 simulations of the effects of many input combinations on firing patterns. Our previous intracellular studies of motoneuron input-output functions suggest that motoneuron firing patterns contain substantial information about their inputs (*Hyngstrom et al., 2008*; *Kuo et al., 2003*; *Lee and Heckman, 1999*, *1998a*,b). We therefore hypothesized that RE of motoneuron firing patterns would effectively deal with the problems of non-uniqueness and would therefore identify a reasonably small solution space of input combinations. To assess the importance of information contained within neuron firing patterns for achieving a small solution space, we compared RE of motoneuron firing patterns to RE of the cumulative spike train (CST), an overall measure of motor output generated by summing all neuron firing patterns together, which has been shown to closely replicate the muscle electromyogram (EMG), which is directly related to muscle force. Our simulation results supported the hypothesis and demonstrated a much smaller solution space for RE of firing of neuron populations than for the CST.

Results

Performance of the motoneuron models for integration of inputs

All simulations are run using a set of 20 model motoneurons designed to closely recreate behaviors documented in our extensive database of current and voltage clamp studies in motoneurons within animal preparations. These models were first developed in NEURON (*Hines and Carnevale, 1997*) for a previous study (*Powers and Heckman, 2017*) and have been implemented on a supercomputer for the present work (see Methods). Our goal of investigating the feasibility of RE of motoneuron firing patterns depends on accuracy of these motoneuron models. *Figure 1* illustrates the performance of our motoneuron models in realistically capturing the integration of excitatory (*Figure 1*A), neuromodulatory (*Figure 1*B) and inhibitory (*Figure 1*C) inputs. Each of these simulated behaviors are considered in the following subsections.

Common input structure, differences in motoneuron properties

A fundamental point in achieving accurate modeling of the outputs of a pool of motoneurons innervating a muscle is that they are subject to "common drive" (*De Luca and Erim, 1994*; *Farina and Negro, 2015*; *Heckman and Enoka, 2012*). As a result, motoneuron firing patterns for a specific task exhibit an overall similarity, which is likely essential for efficient force control (*Farina and Negro, 2015*). This point is important for RE, as common drive precludes independent inputs to each motoneuron. Firing patterns, however, are not identical. As in any biological system, noise is present, though this is relatively low in motoneurons (coefficient of variation during steady firing at about 10-20% (*Heckman and Enoka, 2012*)). We add noise to our excitatory synaptic conductances to match this level, as illustrated in *Figure 1*A1, which illustrates firing patterns of 5 of the 20 motoneuron models in response to a linearly rising and falling excitatory conductance. This figure also shows systematic differences in activation (i.e. recruitment) thresholds. These differences are due to systematic differences in intrinsic electrical thresholds for spiking of motoneurons, which generates an orderly activation (i.e. recruitment) sequence known as Henneman's size principle (*Henneman and Mendell, 1981*). The size principle is essential for effective utilization of the slow (S) vs fast (F) muscle fibers, with motoneurons innervating slow fibers having the lowest thresholds. S units tend to reach higher firing rates than F units, which require more input to reach their higher thresholds so less is available for rate modulation (*Beauchamp et al., 2022*; *De Luca and Contessa, 2012*; *Hu et al., 2013*).

Distribution of excitatory input to S vs F motoneurons

In addition to the pattern and amplitude of excitatory input, there is another important aspect of excitatory motor commands, which is that all excitatory inputs studied thus far project differentially to S vs. F motoneurons (*Powers and Binder, 2001*) (in contrast, inhibition tends to be uniform ((*Powers and Binder, 2001*; *Lindsay and Binder, 1991*) as does neuromodulation (*Lee and Heckman, 1998a*, *1999*). Descending inputs tend to generate larger synaptic currents in the F's, especially the corticospinal input (*Powers and Binder, 2001*) (see Discussion). As yet only one input favors S motoneurons, but it is an essential one, monosynaptic Ia excitation from muscles spindles (*Heckman and Binder, 1988*). These differences, though, do not provide independent control of F motoneurons, much less of individual motoneurons, as common drive still dominates and recruitment still follows the size principle (*Heckman and Binder, 1993*). *Figure 1*A2 however shows that greater relative excitatory synaptic current in high threshold F motoneurons does tend to compress the range of recruitment thresholds and increase the steepness of rate modulation as input levels rise. This compression/steepening may thus provide RE sufficient information to identify the distribution of excitatory input to S vs F motoneurons and provide information on the relative roles of descending versus sensory input.

Neuromodulation and excitatory input

We chose to focus on just one type of neuromodulation (see Methods), the monoaminergic input originating in the brainstem, because this system has proved to have particularly powerful effects on motoneuron excitability (*Heckman et al., 2005*; *Heckman and Enoka, 2012*). These monoaminergic axons form a dense and monosynaptic projection onto motoneurons throughout the spinal cord, with the synapses releasing either 5HT (axons originating in the caudal raphe nuclei) or NE (axons from the locus coeruleus) (*Alvarez et al., 1998*; *Holstege and Kuypers, 1987*; *Maratta et al., 2015*). Both 5HT and NE have multiple effects on motoneuron ion channels, but their strongest action is via facilitation of persistent inward currents (PICs) mediated by dendritic Ca channels (likely CaV 1.3) (*Binder et al., 2020*). Our motoneuron models have been fine tuned to accurately replicate the highly nonlinear interactions between PICs and excitatory inputs (*Powers and Heckman, 2017*). *Figure 1*B shows that, when brainstem neuromodulatory are moderately high and dendritic PICs become strong, three marked nonlinearities become apparent: an initial acceleration (due to PIC activation and consequent amplification of input), followed by attenuation (due to PIC depolarization of dendritic regions, which reduces excitatory driving force) and then hysteresis (offset at a lower level than onset, due to the prolongation of input). In this example, where a pure excitatory drive is applied with no background of inhibition, low threshold motoneurons continue firing long after the input returns to baseline (this is known as self-sustained firing). These nonlinearities are striking in comparison to the nearly linear behavior in the low neuromodulatory state (*Figure 1*A1).

Neuromodulation and inhibition

Our models also accurately capture the very strong interaction of the PIC with inhibition. Even a small background of inhibition reduces PIC amplitudes (*Hyngstrom et al., 2007*; *Kuo et al., 2003*). *Figure 1*C shows that modulation of inhibitory input that is either reciprocally or proportionally organized with respect to excitation also dramatically alters the pattern of rate modulation. Reciprocal inhibition (*Figure 1*C1) tends to allow strong PIC expression with acceleration, attenuation and hysteresis, whereas proportional inhibition (*Figure 1*C2) tends to flatten rate modulation and reduce hysteresis (in fact, of all the patterns shown in *Figure 1*, C1 is closest to that seen in many human muscles (*Beauchamp et al., 2022*; *Heckman and Enoka, 2012*). Thus the nonlinearities in firing patterns are not a straightforward reflection of neuromodulatory input but instead result from a complex interaction between neuromodulation and inhibition.

Given the above effects of the organization of excitation, inhibition and neuromodulation on firing patterns, our RE effort targeted identification of the following aspects of excitation, inhibition

and neuromodulation: amplitude and time course of excitation, distribution of excitation to S versus F motoneurons, amplitude and time course of inhibition (including the baseline level and then whether inhibition was proportional, constant or balanced) and level of neuromodulation from low to high.

Ensemble modeling for Reverse Engineering

The concept for the RE approach we used is illustrated in *Figure 2*. The left portion shows the flow of motor commands from the brain, brainstem and spinal cord to motoneurons, which then activates a muscle. The muscle produces an output force. This force is due to the summed actions of recruited motor units, whose spike trains sum to produce an overall electrical signal (EMG). Our focus is on the spike trains themselves, which can be measured in both animals and humans. The pattern of average firing rate is obtained by summing the rates of all active units (see Methods) and is thus referred to as the cumulative spike train (CST) (righthand side, bottom). We then apply RE methods to both the CST and to individual motor unit firing patterns (right, middle), which, if successful, will allow us to estimate the temporal patterns and amplitudes of the three components of motor commands. Two hypothetical outcomes are illustrated. In both, a triangular form of excitation is applied. The push-pull scheme is a reciprocal organization in which a tonic level of inhibition decreases as excitation increases. The balanced scheme has the opposite organization, inhibition increasing in proportion to excitation. Neuromodulation is assumed to be constant but can varied widely in its level. Although the balanced scheme often is used to drive cortical neurons (*Berg et al., 2007*), it is unknown how these three components interact in motor commands to motoneurons.

The ensemble modeling approach we utilize for RE begins with estimation of the trajectory of the excitatory motor command. The procedure is illustrated in *Figure 3*. We required all simulations to achieve the same overall output, a triangular waveform for CST (upper left; Methods for the match criterion). For each simulation, we specified the following properties of the input organization:

1. Distribution of excitatory input on to S vs F motoneurons (range of 0.5 to 2.5; at 0.5 the highest threshold type F motoneuron received half the average input of lowest threshold type S; at 2.5 the F received 2.5 times the input of the S).
2. Level of neuromodulation: range 0.8 to 1.2, specified in terms of the maximum conductance of the PIC.
3. Baseline level of inhibition: This was set to the lowest level that prevented the PIC from generating self-sustained firing (*Figure 1*B shows an example of motoneurons with strong self-sustained firing due to lack of sufficient inhibitory baseline)
4. Pattern of inhibition relative to excitation: This pattern was set to be linearly proportional to excitation via multipliers ranging from +0.7 to -0.7. *Figure 1*C1 and *Figure 1*C2 illustrate firing patterns resulting from maximum proportional inhibition (multiplier of +0.7) to maximal push-pull (-0.7). At 0.0, the baseline of inhibition remained constant.
5. A physiological level of synaptic noise (see Methods). The RMS value for this noise was the same in all simulations, but was regenerated 30 times to allow estimates of variance for each combination of the above 4 input properties.

Then, for each simulation, we set the input and noise properties as above and then applied a triangular pattern of excitation to the motoneuron models, starting with a purely triangular form and modifying it in an iterative process until the CST of the motoneurons reproduced the linear target CST (*Figure 3*, flow diagram). We repeated these simulations with different sets of input parameters 315,000 times to form the ensemble model of the motor pool (see section Data preparation for parameter combination details). We used the resulting large data set for successful matches to the target CST to assess the feasibility of RE for both the CST and individual motoneuron firing patterns.

Solution space for overall output

We hypothesized that the CST, which contains information only about the overall output trajectory, would have a large solution space. It was nonetheless surprising that our process for modifying the shape of the excitatory input command generated good matches to the target CST for every motor command combination we tried (all 315,000 of them (see section Data preparation)). However, as illustrated in by the progression of input forms in *Figure 2* and further elaborated in *Figure 4*, the potent amplification and large nonlinearities in firing patterns induced by PICs usually resulted in highly nonlinear excitatory commands being required to generate the linear CST. The excitatory conductance input that leads to a good match to the target firing rate typically shows a rapid increase to get recruitment started, followed by a drop off during the acceleration phase due to wide-spread PIC activation across the active motor units, followed by a more rapid increase to keep the average firing rate rising in the face of PIC rate saturation. The falling phase of the command was roughly the mirror image of the rising phase. This general trend is evident in all the examples in *Figure 4*.

As expected, as the level of neuromodulation increased, these nonlinear trends increased, but less excitation is required to achieve the same global output. The examples in upper half of *Figure 4* assumed inhibition was constant. The lower left example in *Figure 4* shows examples of the effects of different organizations of inhibition. Much higher levels of excitation are needed to counteract inhibition when it varies in proportion to the excitatory command (balanced inhibition, red traces), then when it varies inversely (push-pull inhibition, green traces). To quantify the effects of neuromodulation and inhibition on the overall amplitude of excitation, we calculated the area under the curve for the excitation patterns as neuromodulation and inhibition varied. *Figure 5* shows that the amount of excitation required to generate the standard CST target decreased as neuromodulation increased or as inhibition progressively changed from proportional to push-pull. Thus, although the solution space for reproducing the target CST is very wide, encompassing the full range of neuromodulation and inhibition investigated, achieving this wide range required large changes in the pattern and amplitude of the excitatory drive.

The solution space for firing patterns of motor units

If each of patterns of excitation, neuromodulation and inhibition that generated the the standard triangular CST generated highly similar motoneuron firing patterns, then the solution spaces for each set of firing patterns would each be large. This firing pattern similarity however did not occur. The heat map in *Figure 6* provides a quantitative analysis of one of the main differences in motor unit firing patterns, onset-offset hysteresis (this hysteresis was quantified by the ΔF method developed for studies of real motor unit firing patterns in humans (*Gorassini et al., 2002*) (see Methods and *Figure 7*)). The differences in neuromodulation and inhibition produced a huge range of hysteretic firing behaviors, ranging from < 1.0 at low neuromodulation levels coupled to strong proportional inhibition (lower left in *Figure 6*) to > 7.0 for high neuromodulation and strong reciprocal inhibition. Fig. 6 also shows the simulated firing patterns generated by a subset of these combinations (arrows link these patterns to the hysteresis values). As neuromodulation increases, PIC effects (acceleration, attenuation, hysteresis) increase, with push-pull inhibition emphasizing these effects and balanced inhibition suppressing them. These differences for each combination of neuromodulation and inhibition shown in *Figure 6* demonstrate that the solution space for matching a particular set of motor unit firing is much more restricted than for matching the overall CST (see *Figure 4* and *Figure 5*).

Note however there is some degree of trade-off for effects of inhibition and neuromodulation on hysteresis along the diagonals in *Figure 6*. Fortunately, hysteresis is not the only index of motoneuron firing behaviors. *Figure 7* illustrates additional features of motoneuron firing patterns that are easily measured and likely to reflect other effects of excitation, inhibition and neuromodulation. These features include firing rate acceleration and attenuation (which are also driven by actions of neuromodulation and inhibition on PICs – see *Figure 1*C1 and *Figure 1*C2) as well as

recruitment and de-recruitment behaviors (sensitive to the distribution of excitation and S vs F motoneurons – see *Figure 1*A2). Each of these other characteristics had patterns of variation with respect to inhibition and neuromodulation that varied in comparison to each other and to hysteresis. Therefore, to quantify the effectiveness of RE of motor unit firing patterns to predict the organization of synaptic inputs, we next used multiple regression methods to determine how well combinations of these characteristics of simulated firing properties predicted the level of neuromodulation, the patterns of inhibition and the distribution of excitation to low verse high threshold motoneurons.

Regression using motoneuron outputs to predict input organization

We utilized several different types of linear regression techniques (see Methods) and one nonlinear technique (Support Vector Regression using a radial basis function kernel (RBF)). In each case, the regression parameters were calculated from a subset of the data (~70% of the total) and then used to predict the remaining subset (~30%). For neuromodulation, all regression methods were similar in their effectiveness.

*Figure 8*A shows the results for standard linear regression (the dashed red line has slope = 1.0 to indicate perfect predictive performance). For each level of neuromodulation (0.8 to 1.2), the vertical scatter is due to various combinations of the pattern of inhibition (which ranged from 0.7 to -0.7, as is in *Figure 6*) and of the distribution of excitation to low versus high threshold motoneurons (which ranged 0.5 to 2.5). The scatter is considerable, but there is also a tendency for points to cluster near the line. As a result, the regression relation accounts for 76% of the variance (i.e. R^2 = 0.76; *Table 1* shows the R^2 values for all regression methods for prediction of neuromodulation, inhibition and the distribution of excitation). Thus, prediction of the level of neuromodulation is good and indicates that this regression approach can identify the level of neuromodulation with a resolution of about 0.1 units of neuromodulation within the range 0.8 to 1.2.

For inhibition, the nonlinear regression was most effective, giving the results shown in *Figure 8*B. Variance accounted for is 0.85, implying a prediction resolution of about 0.23 units of a range of 1.4 units of inhibition. Finally, *Figure 8*C shows the regression results for prediction of the relative weighting ratio for the motoneuron pool, implying that characteristics of motor unit firing patterns can predict input structure with variances accounted for ranging from 76-91%.

As a final step, we analyzed which motor unit firing characteristics had the most predictive power in identifying each of the three input organizations. *Figure 9* provides two perspectives on this question. The left column shows results of step-wise regression, starting with the characteristic with the strongest predictive power and then progressively adding the others. For neuromodulation, all regression methods behaved similarly, in that the first two characteristics (brace-height and ΔF see *Figure 7*) was highly effective in reducing error in the regression prediction, with little addition benefit from adding the others. For inhibition prediction via the linear regression models, ΔF was most effective, followed by α_{sat}, with all others being ineffective. This is shown in the mutual information ranking (right side) in *Figure 9*, which ranks the characteristics (features) by contribution of new information to the regression model. The left side of *Figure 9* ranks the features by the F-statistic, which does not necessarily imply that new information is introduced into the regression model. This is shown by the very subtle improvements in the error (mean squared error) as features are cumulatively added to the regression model, until t_{drec} and α_{sat} are added to the model.

However, the nonlinear regression method (RBF SVR) was more effective than any of the linear methods. For this method, each of the firing characteristics had a notable effect in reducing error. For linear regression for prediction of excitation, t_{drec} (the average time when units were de-recruited) was the most impactful and adding the other characteristics brought little improvement. The right column in *Figure 9* shows mutual information for each characteristic, which reflects how well each one predicts the input behaviors on its own. As expected, the order of effectiveness of prediction in these plots is identical to that for the step-wise regression.

₃₃₂   Overall, neuromodulation is best predicted by brace-height and ΔF. Inhibition is also predicted
₃₃₃ by ΔF while *brace–height* is ineffective. Excitation (excitatory weight ratio) is best predicted by
₃₃₄ parameters that assess recruitment and derecruitment timings and less informed in prediction by
₃₃₅ ΔF and *brace–height*. These different roles for RE prediction of input make sense in terms of the
₃₃₆ physiological effects of the three types of inputs on motoneuron firing patterns (see Discussion).

Discussion

₃₃₈ Our simulation shows that the solution space for a motor output variable that reflects the net action
₃₃₉ of all active motoneurons is indeed very broad. The variable investigated here, the cumulative spike
₃₄₀ train (CST), has been shown to be closely proportional to muscle EMG and muscle force (***Thompson***
₃₄₁ ***et al., 2018***), which are widely assessed in experimental paradigms in both animals and humans.
₃₄₂ Our simulations however indicate that RE analyses of CSTs, EMGs and forces are likely to fail due to
₃₄₃ the problem of non-uniqueness. In contrast, motoneuron firing patterns provide a much greater
₃₄₄ level of information about motoneuron inputs. Our simulations showed that the solution space for
₃₄₅ a set of motoneuron firing patterns is reasonably small, allowing predictions that account for 75-
₃₄₆ 90% of the variance in the level of neuromodulation, the pattern of inhibition and the distribution
₃₄₇ of excitation to S vs F motoneurons.

Generalization

₃₄₉ Array electrodes are extensively used in many parts of the CNS to record firing patterns of popula-
₃₅₀ tions of neurons in awake behaving animals (see Introduction). Moreover, highly realistic models
₃₅₁ of neurons and their interconnections in many systems are already available and undergoing rapid
₃₅₂ development, including supercomputer implementation (***Einevoll et al., 2019***). Since models and
₃₅₃ firing patterns are the fundamental elements for success of RE in the simulations presented here,
₃₅₄ this same type of approach may be effective in many other neural systems. In each neural sys-
₃₅₅ tem, however, success of RE of firing patterns into input structures as simulated here is likely to
₃₅₆ depend on the particular interactions between neuromodulation, inhibition and excitation. For
₃₅₇ motoneurons the nonlinearities induced by PICs in motoneuron firing patterns have proven to be
₃₅₈ a major advantage for RE. These nonlinearities impart distinctive characteristics to firing patterns
₃₅₉ (acceleration, attenuation, hysteresis – see ***Figure 1***C1, the firing pattern at the upper right in ***Fig-***
₃₆₀ ***ure 6***), which are easy to quantify (see ***Figure 7***). Moreover, because the PIC is highly sensitive to
₃₆₁ inhibition, these same firing characteristics provided effective indices of the temporal pattern of
₃₆₂ inhibition. Furthermore, because these relations between neuromodulation and inhibition were
₃₆₃ different for each firing characteristic (see Supporting Information Figure S1), multiple regression
₃₆₄ using these characteristics was effective. It seems likely that if motoneurons were nearly linear
₃₆₅ input output processors, non-uniqueness would be a much greater problem for RE.

Push-Pull vs Balance Motor Command

₃₆₇ As we defined earlier (see section Ensemble modeling for Reverse Engineering) our model explores
₃₆₈ range of possible combinations of excitatory and inhibitory motor commands from push-pull to
₃₆₉ balanced, for a motoneuron pool to produce a triangular ramp output (***Figure 2***). The push-pull
₃₇₀ scheme is a reciprocal organization in which a tonic level of inhibition decreases as excitation in-
₃₇₁ creases. The balanced scheme has the opposite organization, inhibition increasing in proportion
₃₇₂ to excitation (see ***Powers and Heckman*** (***2017***), ***Johnson et al.*** (***2017***) for full reviews detailing both
₃₇₃ types of schemes). The question remains, which of these schemes is being used in normal human
₃₇₄ motor behavior? Based on our results we would speculate that the most likely scheme would be
₃₇₅ push-pull, as the upper right motoneuron pool discharge pattern shown in ***Figure 6*** seem the most
₃₇₆ realistic when compared to human data from the lower limb (see for example ***Beauchamp et al.***
₃₇₇ (***2022***), ***Afsharipour et al.*** (***2020***)). We have however emphasized that different muscles might re-
₃₇₈ quire different types of motor commands schemes (***Johnson et al., 2017***) and herein lies the power

₃₇₉ of this RE technique as the experimenter can use the RE approach detailed here to identify the
₃₈₀ scheme that best fits their human data.

Muscle EMG versus single motor unit firing patterns

₃₈₂ Muscle EMG is the electrical signal generated by the summed action potentials of the muscle fibers
₃₈₃ of all active motor units. EMG is easy to measure in many types of motor behaviors in humans and
₃₈₄ other animals and provides an effective measurement of the timing and overall pattern of the neu-
₃₈₅ ral output from the spinal cord to muscle. However, the simulations here and in our previous work
₃₈₆ (*Powers et al., 2012*; *Powers and Heckman, 2017*) show that EMG does not provide information
₃₈₇ about the organization of motor commands that produce spinal motor output. On the other hand,
₃₈₈ because motoneurons action potentials are one-to-one with those of their muscle fibers in healthy
₃₈₉ humans and other animals, motor unit firing patterns are equivalent to motoneuron firing patterns.
₃₉₀ While motor unit firing patterns are more technically difficult to measure than whole muscle EMG,
₃₉₁ the accessibility of muscle makes these measurements highly feasible. In fact, motor unit firing
₃₉₂ patterns in humans were recorded at the very onset of single neuron studies, over 90 years ago
₃₉₃ (*Adrian and Bronk, 1929*). The likelihood that this single neuron information provide deep insights
₃₉₄ into the structure of motor commands has thus long been appreciated (*Duchateau and Enoka,*
₃₉₅ *2011*). Many such studies were essential for establishing the prevalence of Henneman's size princi-
₃₉₆ ple of recruitment (reviewed in *Heckman and Enoka* (*2012*)). Many studies also focused on inferring
₃₉₇ the time course of EPSPs and IPSPs driving motoneuron responses to transient ionotropic inputs
₃₉₈ during steady contractions (reviewed in *Türker and Powers* (*2005*)). The distinctive effects of PICs
₃₉₉ on firing have also been a focus, with the ΔF method developed by Gorassini and colleagues for
₄₀₀ quantifying PIC-induced hysteresis having become a standard in the field *Gorassini et al.* (*2002*).
₄₀₁ However, intracellular current and voltage clamp studies have demonstrated that the PIC is highly
₄₀₂ sensitive both to neuromodulatory input (*Hounsgaard et al., 1988*; *Lee and Heckman, 2000*, *1999*)
₄₀₃ and inhibition (*Hyngstrom et al., 2008*; *Kuo et al., 2003*). Consistent with this, ΔF does not provide
₄₀₄ good discrimination of neuromodulation versus inhibition in our simulations (*Figure 9*). In contrast,
₄₀₅ and consistent with our previous study (*Beauchamp et al.* (*2023*)), the brace–height parameter was
₄₀₆ sensitive to neuromodulation but insensitive to inhibition, likely because it is normalized for peak
₄₀₇ firing. In general, our simulations show that no one motor unit firing characteristic is sufficient for
₄₀₈ estimation of input structure and thus a form of RE is necessary.

Limitations

₄₁₀ Ensemble model approaches for RE are obviously reliant on the biological accuracy of the con-
₄₁₁ stituent models. Our models have been carefully tuned to replicate experimental data from years
₄₁₂ of current and voltage clamp studies of the integration of neuromodulatory, inhibitory and exci-
₄₁₃ tatory inputs motoneurons in feline preparations. We made a few adjustments to these models
₄₁₄ to more closely replicate the slow firing rates in human motor units but will likely need to further
₄₁₅ adjust parameters like the spike AHP and the PIC voltage threshold. Our RE was not applied for
₄₁₆ identification of the amplitude or time course of the excitation. The peak excitatory conductance
₄₁₇ for each simulation strongly depends on the level of neuromodulation and the pattern of inhibition
₄₁₈ (*Figure 4*). This correlation was built into our simulations to match the CST for each combination
₄₁₉ of neurmodulation/inhibition and so excitation was not an independent parameter. Further sim-
₄₂₀ ulations in which we relax this constraint or allow inhibition and/or neuromodulation to vary for
₄₂₁ a given pattern of excitation may prove interesting. It will also be interesting to expand our range
₄₂₂ of neuromodulation. At the high end, this expansion will have to be limited, as controlling such
₄₂₃ large PICs is difficult. But exploring whether RE works as at lower neuromodulation levels where
₄₂₄ input-output processing is nearly linear would reveal whether this simpler behavior limits RE effec-
₄₂₅ tiveness.

426 ### Summary & Future Application

427 Although our models likely need modification before we begin RE of human motor unit firing pat-
428 terns, they were well situated to the goal of this study, which was to investigate the feasibility of RE
429 of neuron firing patterns despite the strong tendency for neural systems to be non-unique. In ad-
430 dition, it would seem that the success of our RE approach suggests that this technique can be used
431 to gain insight into the motor commands underlying different motor unit firing patterns associated
432 with different motor tasks with or without disease states (e.g., *Mottram et al.* (*2014*)).

433 ## Methods and Materials

434 ### Motoneuron pool model

435 The motoneuron pool consists of 20 model motoneurons with a range of intrinsic properties. This
436 motonouron pool size was chosen to reflect the typical sample size of motor units discriminated
437 based on surface EMG array recordings. Each model motoneuron consisted of a soma compart-
438 ment and four dendritic compartments, each coupled to the soma. The passive properties of the
439 compartments, such as, size, capacitance and passive conductance were derived from works by
440 described by Kim and colleagues (*Kim et al.* (*2009*); *Kim and Jones* (*2012*)). Spike conductances (g_{Na}
441 and g_K) and conductances mediating the medium AHP were inserted into the soma compartment
442 and a calcium conductance mediating the slowly-activating persistent inward current (PIC) was in-
443 serted into each of the dendritic compartments. In addition, a hyperpolarization-activated mixed-
444 cation (HCN) conductance was inserted into all compartments. Conductance densities, kinetics
445 and steady-state activation curves were originally tuned to recreate the range of input-output be-
446 havior recorded in medial gastrocnemius (MG) motoneurons in decerebrate cats, as described in
447 *Powers and Heckman* (*2017*). We made four modifications to model parameters for the cat MG
448 pool in order to produce the lower firing rates and less than full recruitment typically observed
449 during moderate voluntary contractions in human subjects. First, the range of values governing
450 excitability were restricted to the first 75% of the original recruitment range (i.e., the parameters
451 of motoneuron 20 in the new model corresponded to motoneuron 15 in the original parameter
452 set). Second, AHP durations and amplitudes were increased by increasing the values of the time
453 constant of calcium removal for the calcium-activated potassium conductance (from 60 to 10 ms in
454 the original model to 90 to 57 ms). The larger and longer AHPs acted to oppose early PIC activation
455 during increasing excitatory synaptic drive, so we hyperpolarized the PIC half-activation threshold
456 (from -40 to -37 mV in the original model to -42 to -40.4 mV). Finally, in the original model the
457 slow decay of PICs observed in high threshold MG motoneurons (*Lee and Heckman, 1996*) was
458 replicated by including a voltage-dependent inactivation process. We found that this process lim-
459 ited the firing rate hysteresis to values below those typically seen in human motor unit recordings,
460 so we eliminated PIC inactivation in the present model pool. All simulations were run using the
461 Python interface to the NEURON simulator (*Hines and Carnevale, 1997*). NEURON files specifying
462 motoneuron pool parameters, conductance mechanisms, and protocols on ModelDB with acces-
463 sion number 239582.

464 ### Simulation protocol

465 Inputs to the motoneuron pool

466 The target motoneuron pool output, representing the average firing rate across the entire pool of
467 20 motoneurons was 22 seconds in length and consisted of 1 sec delay followed by a linear rise to
468 a peak value of 16 imp/s over the next 10 sec, and a linear decline back to zero in 10 sec (*Figure 3*,
469 Reference Ref). A scaled version of this command, $I_{ex} = 0.6Ref$, (*Figure 3*, light salmon colored
470 with the value 0 to its bottom left) was used as the first guess of the time course of the excitatory
471 input needed to produce the target output. For each iteration an inhibitory conductance input (I_{in})
472 was also applied according to the following equation:

$$I_{in} = G_{in}I_{ex} + b_{in} \tag{1}$$

473 where the excitatory input I_{ex} is multiplied by a gain G_{in} and biased by b_{in} as defined by:

$$b_{in} = 6.25R_{mod}^2 - 1.25R_{mod} - 1 \tag{2}$$

where R_{mod} is the neuromodulation value, set in this work, from 0.8 to 1.2 at increments of 0.1
(i.e. [0.8:0.1:1.2]). The inhibition is therefore coupled to the neuromodulation through its bias,
b_{in}, and was set to value just sufficient to ensure PIC deactivation at the end of the command.
The inhibitory gain, G_{in}, is varied from -0.7 to 0.7 in increments of 0.1 thus traversing the possible
control schemes push-pull inhibition to balanced inhibition. Example of both control schemes can
be seen in **Figure 2** (green for excitatory and red for inhibitory).

Changes in neuromodulation were simulated by changing the density of dendritic PIC channels:
from 80% to 120% of the standard density in 10% increments. Mathematically, the MN model was
altered by changing the current I_{Ca_L} of the L-type calcium channel according to these equations:

$$I_{Ca_L} = g_{Ca_L}m_{Ca_L}(V - E_{Ca_L}) \tag{3}$$

$$g_{Ca_L} = R_{mod}\bar{g}_{Ca_L} \tag{4}$$

where I_{Ca_L} is the current for L-type calcium channel, g_{Ca_L} is the conductance of the L-type calcium
channel, m_{Ca_L} is the activation gate, V is the compartment voltage, and E_{Ca_L} is the reversal potential
for the L-type calcium channel. R_{mod} is the gain factor that changes the maximum conductance –
$\bar{g}_{Ca_L}$ – of the L-type Calcium channel with the following values $[0.8, 0.9, 1.0, 1.1, 1.2]$.

Finally, filtered Gaussian noise was added to both the excitatory and inhibitory commands with
a standard deviation that varied in proportion to the square root of the mean level and a decay time
constant of 20 ms to reflect the fact that most of the power in the synaptic input to motoneurons
is thought to be in the low frequency (< 10 Hz) range (**Farina et al., 2014**).

Feedback and optimization

We used an iterative optimization procedure to find the motoneuron pool input needed to produce
the "Reference" output as shown in **Figure 3**. We opted for a feedback type of optimization method
to converge onto the solution.

For the feedback to work, an error term is calculated between the output of the MN pool and
the "Reference" (see the "Controller" **Figure 3**). The output of the MN pool is the average of the
20 MN pool calculated by convolving each model spike train with a 2-s Hanning window with unit
area, adding up the result across all 20 spike trains and dividing by 20:

$$I_{ex_n} = \frac{1}{20}\sum_{i}^{20}\left(F(t)_i * H(t)\right) + Ke(t) \tag{5}$$

where I_{ex_n} is the new excitatory input, n is the iteration in the feedback loop, $F(t)_i$ is the firing rate
of a MN $i = [0:20]$ in the 20 MN pool, $H(t)$ is the 2-s Hanning window, $e(t)$ is the error and K is the
proportional gain (usually 20%). The resulting I_{ex_n} (the average firing rate response) plus the error
$e(t)$ is then used as the new excitatory command to the MN Pool. This is shown by the series of
traces leaving the "Plant System - Motoneuron (MN) pool" in **Figure 3**. Using I_{ex_n}, a new inhibitory
command is also calculated using equation 1 and is subsequently used in the new computational
iteration n.

This process was repeated until the mean squared error between the output and the target
was less than 1 Hz^2 (generally less than 0.5 Hz^2). In the case shown in **Figure 3**, good convergence
was reached by the fifth iteration.

This iterative matching procedure was repeated for 225 different input combinations: five levels
of neuromodulation, three different distributions of excitatory input, and fifteen different levels of
inhibition.

512 Excitatory distribution or MN weights

513 The density of the excitatory synaptic conductance was either uniform across all cells, weighted
514 toward low threshold units (synaptic weight onto lowest threshold unit 2 X that of highest threshold
515 unit), or weighted toward high threshold units (high weight 2X low). The parameters governing
516 cell excitability were skewed to produce a greater proportion of low threshold units, so synaptic
517 weighting showed a similar skew according to the following equation:

$$w_{MN\#} = w_{start} + \left(\frac{MN\#}{\#MN - 1}\right)^2 (w_{end} - w_{start}) \tag{6}$$

518 where $w_{MN\#}$ is the weight of the given motoneuron, $\#MN$ is the number of the MN in the pool
519 (e.g. 20), w_{end} and w_{start} are the weight range. For weights favoring low threshold units, $w_{start} = 2.5$
520 and $w_{end} = 1.0$ and for the opposite $w_{start} = 1.0$ and $w_{end} = 2.5$. In total we used 7 different types of
521 weight configurations: $[w_{start}, w_{end}] \iff [1, 1], [1.5, 1], [2, 1], [2.5, 1], [1, 1.5], [1, 2], [2.5, 1]$.

522 Noise Seed

523 We chose to calculate the model using 30 different noise seeds. We assumed that each seed would
524 represent a "unique" individual and allow for the use of averages and variance in our interpretation
525 of the results. *Note*: The noise seed was not reset for each of motoneurons in the pool. The synaptic
526 noise is thus coupled for each of the motoneurons which fits with the "common drive" argument
527 (see section Common input structure, differences in motoneuron properties).

528 **Massively-parallel Data Generation Methods**
529 Since the majority of the simulation is able to operate independently as the simulations for each
530 of the parameter sets (noise seeds, inhibitory gains, and neuromodulation) did not need to feed
531 into each other, we were able to run this simulation in a perfectly parallel way. Each unique param-
532 eter set was simulated using one node (computer) in a supercomputing cluster, which produced a
533 dataset file of the simulation results (see Algorithm 1 in Supporting Information). Each node sim-
534 ulated one motor pool, with the computation of each motoneuron run on each processor on the
535 compute node (see Algorithm 2 in Supporting Information). To implement this setup, we utilized
536 the MPI interface in NEURON 7.7 *Hines and Carnevale* (*1997*) and Python 3.6.7 running on the
537 Bebop supercomputer (Intel Broadwell nodes) at Argonne National Laboratory, (Supplementary
538 *Figure 2*). Each combination tuple tuple_comb contains a particular ginmult, nmmult, ginadd, and
539 random_seed (if noise is used).

540 **Feature Extraction**
541 For each simulation input combination, we analyzed the individual motoneuron discharge patterns
542 to extract 7 features: Recruitment Time (t_{rec}), De-Recruitment Time (t_{drec}), Activation Duration (t_{dur}),
543 Recruitment Range (t_{range}), Firing Rate Saturation (α_{sat}), Firing Rate Hysteresis (ΔF) and brace–height
544 (*brace–height*). The calculation of these quantitative measures is illustrated in *Figure 7*, which shows
545 the instantaneous discharge rates (dots) of a higher (upper panel) and lower threshold (lower
546 threshold) motoneuron, along with the smoothed firing rates calculated by convolving the spike
547 times with a 2-s Hanning window (continuous lines).
548   *Recruitment Time* (t_{rec}): Recruitment time is the time of the first instantaneous discharge rate of
549 a given motorneuron.
550   *De-Recruitment Time* (t_{drec}): De-Recruitment time is the time of the last instantaneous discharge
551 of a given motoneuron.
552   *Activation Duration* (t_{dur}): Activation duration is the difference between de-recruitment time and
553 recruitment time:

$$t_{dur} = t_{drec} - t_{rec} \tag{7}$$

 Recruitment Range (t_{range}): The recruitment range is the difference between the recruitment time of the last and the first motorneuron in the motorpool.

Firing Rate Saturation (α_{sat}): The motorneuron firing rate is characterized by an initial acceleration phase that lasts about 1s followed by partial saturation of firing rate. The degree of this saturation is quantified by calculating the rate of firing rate increase from 1 sec after recruitment to the target peak (11 s):

$$\alpha_{sat} = \frac{f_3 - f_2}{t_3 - t_2} \tag{8}$$

where f_3 is the firing rate at 11 s, f_2 is the firing rate 1 s post recruitment (t_{rec}), t_3 is time at target peak 11 s and t_2 is 1 s post recruitment.

Firing Rate Hysteresis (ΔF): A motorneuron rate hysteresis can be quantified using the ΔF measure introduced by Gorassini and colleagues (*Gorassini et al., 2002*). ΔF is defined as the difference in the smoothed firing rate of a lower threshold reporter motorneuron (*Figure 7* - bottom) at the onset (t_{rec}, f_0) and offset (t_{drec}, f_1) of the higher threshold motorneuron (*Figure 7* - top):

$$\Delta F = f_0 - f_1 \tag{9}$$

brace–height ($brace - height$): Brace height is a measure of the non-linear portion of the rising phase of the firing rate of the motoneuron (see *Figure 7* - top trace). It is the maximum perpendicular distance from the line linking the firing rates at recruitment time (t_{rec}) to t_3, the time at which the triangular "Reference" reaches its maximum (11 s). This distance is calculate by solving the geometric problem of finding the "Distance from a point to a line". This analysis is further detailed by *Beauchamp et al.* (*2023*).

We restricted the calculation to motorneuron pairs for which the recruitment time difference between the two was more than 1 s. This restriction was imposed to ensure that PIC activation in the reporter unit had reached near steady state, so that further changes in reporter discharge rate primarily reflected changes in synaptic drive (cf. *Powers et al.* (*2008*)).

Machine learning inference of motor pool characteristics

Data preparation

We ran the model for a range of neuromodulation (5), inhibition (15), excitatory weights (7) and noise seeds (30) for a total of 15,750 combinations. Given 20 motoneuron per pool and 20 optimization iterations (see *Figure 3* or section Feedback and optimization we ran a grand total of 6,300,000 simulations.

Post simulations, we extracted the features from the firing rates of each motoneuron (see section Feature Extraction and organized them according to the neuromodulation, inhibition, excitatory weight and noise seed. We then first calculated the average of these features accordingly and then took an average of these averages with respect to the noise seed. In final, the was an average of the features grouped by neurmodulation, inhibition and excitatory weight. Supplementary *Figure 1* shows the average of each feature in a heat map configuration for the excitatory weight distribution $[w_{start}, w_{end}] = [1, 1]$. This data was the used subsequently (see section Model fits and Ranking features).

Model fits

One of the goals of our RE approach is to infer the characteristics of the input to the motoneuron pool based on our measures of motor unit output. The numeric features extracted from the discharge patterns are used to create five-dimensional input data for the models. The dimensions were the mean ΔF value, times of recruitment (t_{rec}) and derecruitment (t_{drec}), the firing rate saturation degree (α_{sat}), the recruitment range (t_{range}) and brace–height ($brace - height$). The target values

to predict were the simulation input values, namely level of neuromodulation, inhibition, and excitatory weight. Since all target values to be predicted in this study were continuous numeric values, the RE process was posed as a regression task.

Since the dataset is relatively small (<1000 instances) and has only 5 dimensions, linear methods and kernel methods were chosen for predictive analysis. More complex models, such as tree-based methods and neural networks, were omitted due to inadequate training data instances and interpretability. Linear regression models using standard least-squares, Lasso, Ridge, and ElasticNet methods, and support vector models using linear and radial basis function kernels were created for each simulation input value to be predicted using the mean squared error as the minimization cost function.

Ranking features

To measure the performance of linear regression against the firing features (see section Feature Extraction), we use a greedy approach towards incorporating more and more features into the linear regression model. For this approach, the F-statistic (linear regression test) is used as the scoring function to order-rank the features for incorporation into a linear regression model.

We used mutual information (MI) (*Ross, 2014*; *Kraskov et al., 2004*; *Kozachenko and Leonenko, 1987*) to rank the dependence of the firing rate features (see section Feature Extraction) to the inhibition, neuromodulation and excitatory weight ratio levels of the motoneurons in the pool model.

Acknowledgments

This research used resources of the Argonne Leadership Computing Facility, which is a DOE Office of Science User Facility supported under Contract DE-AC02-06CH11357. We gratefully acknowledge the computing resources provided on Bebop, a high-performance computing cluster operated by the Laboratory Computing Resource Center at Argonne National Laboratory. This research was supported by the National Institute of Neurological Disorders and Stroke of the National Institutes of Health under awards R01NS062200 and R01NS125863. We also gratefully acknowledge Rochelle O. Bright for proofreading this work.

References

Adrian ED, Bronk DW. The discharge of impulses in motor nerve fibres: Part II. The frequency of discharge in reflex and voluntary contractions. The Journal of physiology. 1929; 67(2):i3.

Afsharipour B, Manzur N, Duchcherer J, Fenrich KF, Thompson CK, Negro F, Quinlan KA, Bennett DJ, Gorassini MA. Estimation of self-sustained activity produced by persistent inward currents using firing rate profiles of multiple motor units in humans. Journal of Neurophysiology. 2020; 124(1):63–85.

Alvarez FJ, Pearson JC, Harrington D, Dewey D, Torbeck L, Fyffe RE. Distribution of 5-hydroxytryptamine-immunoreactive boutons on α-motoneurons in the lumbar spinal cord of adult cats. Journal of Comparative Neurology. 1998; 393(1):69–83.

Beauchamp JA, Khurram OU, Dewald JP, Heckman C, Pearcey GE. A computational approach for generating continuous estimates of motor unit discharge rates and visualizing population discharge characteristics. Journal of Neural Engineering. 2022; 19(1):016007.

Beauchamp JA, Pearcey GE, Khurram OU, Chardon M, Wang YC, Powers RK, Dewald JP, Heckman C. A geometric approach to quantifying the neuromodulatory effects of persistent inward currents on individual motor unit discharge patterns. Journal of Neural Engineering. 2023; .

Berg RW, Alaburda A, Hounsgaard J. Balanced inhibition and excitation drive spike activity in spinal half-centers. Science. 2007; 315(5810):390–393.

Binder MD, Powers RK, Heckman C. Nonlinear input-output functions of motoneurons. Physiology. 2020; 35(1):31–39.

Buonomano DV, Maass W. State-dependent computations: spatiotemporal processing in cortical networks. Nature Reviews Neuroscience. 2009; 10(2):113–125.

Chandrasekaran S, Fifer M, Bickel S, Osborn L, Herrero J, Christie B, Xu J, Murphy RK, Singh S, Glasser MF, et al. Historical perspectives, challenges, and future directions of implantable brain-computer interfaces for sensorimotor applications. Bioelectronic medicine. 2021; 7(1):1–11.

De Luca CJ, Contessa P. Hierarchical control of motor units in voluntary contractions. Journal of neurophysiology. 2012; 107(1):178–195.

De Luca CJ, Erim Z. Common drive of motor units in regulation of muscle force. Trends in neurosciences. 1994; 17(7):299–305.

Duchateau J, Enoka RM. Human motor unit recordings: origins and insight into the integrated motor system. Brain research. 2011; 1409:42–61.

Edelman GM, Gally JA. Degeneracy and complexity in biological systems. Proceedings of the National Academy of Sciences. 2001; 98(24):13763–13768.

Einevoll GT, Destexhe A, Diesmann M, Grün S, Jirsa V, de Kamps M, Migliore M, Ness TV, Plesser HE, Schürmann F. The scientific case for brain simulations. Neuron. 2019; 102(4):735–744.

Farina D, Negro F. Common synaptic input to motor neurons, motor unit synchronization, and force control. Exercise and sport sciences reviews. 2015; 43(1):23–33.

Farina D, Rehbaum H, Holobar A, Vujaklija I, Jiang N, Hofer C, Salminger S, van Vliet HW, Aszmann OC. Noninvasive, accurate assessment of the behavior of representative populations of motor units in targeted reinnervated muscles. IEEE Transactions on Neural Systems and Rehabilitation Engineering. 2014; 22(4):810–819.

Goaillard JM, Marder E. Ion channel degeneracy, variability, and covariation in neuron and circuit resilience. Annual review of neuroscience. 2021; 44(1):335–357.

Gorassini M, Yang JF, Siu M, Bennett DJ. Intrinsic activation of human motoneurons: reduction of motor unit recruitment thresholds by repeated contractions. Journal of Neurophysiology. 2002; 87(4):1859–1866.

Heckman C, Binder MD. Analysis of effective synaptic currents generated by homonymous Ia afferent fibers in motoneurons of the cat. Journal of Neurophysiology. 1988; 60(6):1946–1966.

Heckman C, Binder MD. Computer simulations of the effects of different synaptic input systems on motor unit recruitment. Journal of Neurophysiology. 1993; 70(5):1827–1840.

Heckman C, Enoka RM. Motor unit. Comprehensive physiology. 2012; 2(4):2629–2682.

Heckman C, Gorassini MA, Bennett DJ. Persistent inward currents in motoneuron dendrites: implications for motor output. Muscle & Nerve: Official Journal of the American Association of Electrodiagnostic Medicine. 2005; 31(2):135–156.

Henneman E, Mendell L. Handbook of Physiology. The Nervous System. Motor Control. Bethesda, MD: American Physiological Society. 1981; p. 423–507.

Hines ML, Carnevale NT. The NEURON simulation environment. Neural computation. 1997; 9(6):1179–1209.

Holobar A, Minetto MA, Botter A, Negro F, Farina D. Experimental analysis of accuracy in the identification of motor unit spike trains from high-density surface EMG. IEEE Transactions on Neural Systems and Rehabilitation Engineering. 2010; 18(3):221–229.

Holstege J, Kuypers H. Brainstem projections to spinal motoneurons: an update. Neuroscience. 1987; 23(3):809–821.

Hounsgaard J, Hultborn H, Jespersen B, Kiehn O. Bistability of alpha-motoneurones in the decerebrate cat and in the acute spinal cat after intravenous 5-hydroxytryptophan. The Journal of physiology. 1988; 405(1):345–367.

Hu X, Rymer WZ, Suresh NL. Motor unit pool organization examined via spike-triggered averaging of the surface electromyogram. Journal of neurophysiology. 2013; 110(5):1205–1220.

Hug F, Avrillon S, Del Vecchio A, Casolo A, Ibanez J, Nuccio S, Rossato J, Holobar A, Farina D. Analysis of motor unit spike trains estimated from high-density surface electromyography is highly reliable across operators. Journal of Electromyography and Kinesiology. 2021; 58:102548.

689 **Hyngstrom AS**, Johnson MD, Heckman CJ. Summation of excitatory and inhibitory synaptic inputs by motoneu-
690   rons with highly active dendrites. Journal of neurophysiology. 2008; 99(4):1643–1652.

691 **Hyngstrom AS**, Johnson MD, Miller JF, Heckman C. Intrinsic electrical properties of spinal motoneurons vary
692   with joint angle. Nature neuroscience. 2007; 10(3):363–369.

693 **Johnson MD**, Thompson CK, Tysseling VM, Powers RK, Heckman CJ. The potential for understanding the synap-
694   tic organization of human motor commands via the firing patterns of motoneurons. Journal of neurophysi-
695   ology. 2017; 118(1):520–531.

696 **Kim H**, Jones KE. The retrograde frequency response of passive dendritic trees constrains the nonlinear firing
697   behaviour of a reduced neuron model. PLoS One. 2012; .

698 **Kim H**, Major LA, Jones KE. Derivation of cable parameters for a reduced model that retains asymmetric voltage
699   attenuation of reconstructed spinal motor neuron dendrites. Journal of computational neuroscience. 2009;
700   27(3):321–336.

701 **Kozachenko LF**, Leonenko NN. Sample estimate of the entropy of a random vector. Problemy Peredachi
702   Informatsii. 1987; 23(2):9–16.

703 **Kraskov A**, Stögbauer H, Grassberger P. Estimating mutual information. Physical review E. 2004; 69(6):066138.

704 **Kuo JJ**, Lee RH, Johnson MD, Heckman HM, Heckman C. Active dendritic integration of inhibitory synaptic inputs
705   in vivo. Journal of neurophysiology. 2003; 90(6):3617–3624.

706 **Lee R**, Heckman C. Influence of voltage-sensitive dendritic conductances on bistable firing and effective synap-
707   tic current in cat spinal motoneurons in vivo. Journal of neurophysiology. 1996; 76(3):2107–2110.

708 **Lee R**, Heckman C. Bistability in spinal motoneurons in vivo: systematic variations in persistent inward currents.
709   Journal of neurophysiology. 1998; 80(2):583–593.

710 **Lee R**, Heckman C. Bistability in spinal motoneurons in vivo: systematic variations in rhythmic firing patterns.
711   Journal of neurophysiology. 1998; 80(2):572–582.

712 **Lee R**, Heckman C. Enhancement of bistability in spinal motoneurons in vivo by the noradrenergic α1 agonist
713   methoxamine. Journal of neurophysiology. 1999; 81(5):2164–2174.

714 **Lee RH**, Heckman CJ. Adjustable amplification of synaptic input in the dendrites of spinal motoneurons in vivo.
715   Journal of Neuroscience. 2000; 20(17):6734–6740.

716 **Lim HK**, Keniston LP, Cios KJ. Modeling of multisensory convergence with a network of spiking neurons: a
717   reverse engineering approach. IEEE transactions on biomedical engineering. 2011; 58(7):1940–1949.

718 **Lindsay A**, Binder MD. Distribution of effective synaptic currents underlying recurrent inhibition in cat triceps
719   surae motoneurons. Journal of neurophysiology. 1991; 65(2):168–177.

720 **Maratta R**, Fenrich KK, Zhao E, Neuber-Hess MS, Rose PK. Distribution and density of contacts from noradren-
721   ergic and serotonergic boutons on the dendrites of neck flexor motoneurons in the adult cat. Journal of
722   Comparative Neurology. 2015; 523(11):1701–1716.

723 **Marder E**. Neuromodulation of neuronal circuits: back to the future. Neuron. 2012; 76(1):1–11.

724 **McCormick DA**, Nusbaum MP. Editorial overview: neuromodulation: tuning the properties of neurons, net-
725   works and behavior. Current opinion in neurobiology. 2014; 29:iv.

726 **Mottram CJ**, Heckman CJ, Powers RK, Rymer WZ, Suresh NL. Disturbances of motor unit rate modulation are
727   prevalent in muscles of spastic-paretic stroke survivors. Journal of neurophysiology. 2014; 111(10):2017–
728   2028.

729 **Mukunda CL**, Narayanan R. Degeneracy in the regulation of short-term plasticity and synaptic filtering by
730   presynaptic mechanisms. The Journal of Physiology. 2017; 595(8):2611–2637.

731 **Negro F**, Muceli S, Castronovo AM, Holobar A, Farina D. Multi-channel intramuscular and surface EMG decom-
732   position by convolutive blind source separation. Journal of neural engineering. 2016; 13(2):026027.

733 **Pisokas I**. Reverse Engineering and Robotics as Tools for Analyzing Neural Circuits. Frontiers in Neurorobotics.
734   2021; 14:578803.

735 **Powers RK**, Binder MD. Input-output functions of mammalian motoneurons. Reviews of physiology, biochem-
736 istry and pharmacology. 2001; p. 137–263.

737 **Powers RK**, ElBasiouny SM, Rymer WZ, Heckman CJ. Contribution of intrinsic properties and synaptic inputs to
738 motoneuron discharge patterns: a simulation study. Journal of neurophysiology. 2012; 107(3):808–823.

739 **Powers RK**, Heckman CJ. Synaptic control of the shape of the motoneuron pool input-output function. Journal
740 of neurophysiology. 2017; 117(3):1171–1184.

741 **Powers RK**, Nardelli P, Cope TC. Estimation of the contribution of intrinsic currents to motoneuron firing
742 based on paired motoneuron discharge records in the decerebrate cat. Journal of neurophysiology. 2008;
743 100(1):292–303.

744 **Prinz AA**. Computational approaches to neuronal network analysis. Philosophical Transactions of the Royal
745 Society B: Biological Sciences. 2010; 365(1551):2397–2405.

746 **Prinz AA**, Bucher D, Marder E. Similar network activity from disparate circuit parameters. Nature neuroscience.
747 2004; 7(12):1345–1352.

748 **Ross BC**. Mutual information between discrete and continuous data sets. PloS one. 2014; 9(2):e87357.

749 **Rostro-Gonzalez H**, Cessac B, Viéville T. Parameter estimation in spiking neural networks: a reverse-
750 engineering approach. Journal of Neural Engineering. 2012; 9(2):026024.

751 **Stevenson IH**, Kording KP. How advances in neural recording affect data analysis. Nature neuroscience. 2011;
752 14(2):139–142.

753 **Stevenson IH**, London BM, Oby ER, Sachs NA, Reimer J, Englitz B, David SV, Shamma SA, Blanche TJ, Mizuseki
754 K, et al. Functional connectivity and tuning curves in populations of simultaneously recorded neurons. PLoS
755 computational biology. 2012; 8(11):e1002775.

756 **Telenczuk B**, Telenczuk M, Destexhe A. A kernel-based method to calculate local field potentials from networks
757 of spiking neurons. Journal of Neuroscience Methods. 2020; 344:108871.

758 **Thompson CK**, Negro F, Johnson MD, Holmes MR, McPherson LM, Powers RK, Farina D, Heckman CJ. Robust
759 and accurate decoding of motoneuron behaviour and prediction of the resulting force output. The Journal
760 of physiology. 2018; 596(14):2643–2659.

761 **Türker K**, Powers R. Black box revisited: a technique for estimating postsynaptic potentials in neurons. Trends
762 in neurosciences. 2005; 28(7):379–386.

763 **Vyas S**, Golub MD, Sussillo D, Shenoy KV. Computation through neural population dynamics. Annual Review
764 of Neuroscience. 2020; 43:249.

765 **Yang J**, Shakil H, Ratté S, Prescott SA. Minimal requirements for a neuron to coregulate many properties and
766 the implications for ion channel correlations and robustness. Elife. 2022; 11:e72875.

767 **Yochum M**, Modolo J, Mogul DJ, Benquet P, Wendling F. Reconstruction of post-synaptic potentials by reverse
768 modeling of local field potentials. Journal of Neural Engineering. 2019; 16(2):026023.

 Figures

Figure 1. Summary plots showing the performance of the motoneuron pool model with respect to integration of inputs. *A1* - Shows a subset of 6 of the 20 MN in the pool given the same excitatory triangular input, the black trace above. The MN pool follows an orderly activation known as the Henneman's size principle, showing that this MN model can transform a "common drive" into different MN activities (see section Common input structure, differences in motoneuron properties). *A2* - Shows the models ability to favor S-type vs F-type motoneuron within the pool. The orange $[w_{start}, w_{end}] = [1, 2]$ Distribution favors the fast (F-type) motoneuron. The recruitment of theses F-type motoneurons (e.g. MN 11, MN 15 and MN 19) happens sooner and their maximum firing rates are higher with respect to their $[w_{start}, w_{end}] = [1, 1]$ counterparts. For the slow (S-type) motoneurons the recruitment is the same but their max firing rates decrease with respect to their $[w_{start}, w_{end}] = [1, 1]$ counterparts (see section Distribution of excitatory input to S vs F motoneurons). *B* - Shows our models ability to trigger PIC type behavior. For a neuromodulation level of 1.2 (max of range tested) and no inhibition, the motoneurons firing rates show a fast rise time, then attenuation, followed by sustained firing (see section Neuromodulation and excitatory input). *C1 and C2* - Shows the model's ability to modulate the effects of neuromodulation with inhibition. C1 shows a inhibition in the "Push-Pull" or reciprocal configuration. C2 shows inhibition in the balanced configurations (see section Neuromodulation and inhibition).

Figure 2. Reverse Engineering Paradigm. The left side shows a schematic of the input pathway to the MN pool and its subsequent connection to a muscle. The right side shows a schematic of our goal. Can we predict the 3 inputs of the MN pool given the firing pattern of the MN pool used to generate the muscle output? In the push-pull scheme at upper right, inhibition (red) decrease as excitation (green) increases. In contrast, inhibition increases with excitation in the balanced scheme. In this work we show that using the "MN Pool Firing Pattern" one is able to reverse engineer back to the MN pool inputs.

Figure 3. Schematic of the algorithm used to approximate the excitatory input needed to produce the triangular output from the motoneuron pool. The schematic resembles a classic controller schematic. The algorithm starts at the "Input to MN Pool" box where the light pink triangular input is used as the initial guess to the "Plant System" box. Using this initial input guess, the MN pool model calculates it first output, seen in the "System Output" box (light pink trace). This initial output is compared the "Reference" Box and the resulting error $e(t)$ is fed into the "Controller" box. Based on this error the controller calculates a new guess for an input and the cycle is repeated until a satisfactory error is achieved (MSE < 1 Hz^2). The iterations are shown within the "Input to MN Pool" and "System Output" boxes along a left to right diagonal scheme to show the evolution of the traces produced by the algorithm. From iteration 0 to iteration n the input to the MN pool morphs to a highly non linear form to produce a linear output. Finally, this algorithm is repeated over a range of neuromodulation, inhibitory bias, inhibitory gain and exciatatory synaptic weights as shown in the "MN parameters" box. Taking all the iterations and combinations, the model was run at total of 6,300,000 times. See subsection Simulation protocol for details.

Figure 4. *Top Row* – shows the average and std excitatory input to the MN pool to produce the reference command (***Figure 3*** – reference input). Each column has a different neuromodulation value from lowest (0.8) to highest (1.2). For this example, the inhibitory gain is set to zero and the excitatory weight distribution is equal across the pool (111 configuration - see section Excitatory distribution or MN weights). In short, the lower the neuromodulation the more linear the input command becomes however, the higher the excitatory values becomes. *Bottom Row* - shows the average and std excitation (solid) and inhibition (dotted) for the two extremes of inhibitory schemes (Push-Pull in green and Balanced in orange). Neuromodulation is set to 1.0 (middle of range tried) and the excitatory weight distribution is equal across the pool (111 configuration - see section Excitatory distribution or MN weights). The "Push-Pull" inhibitory scheme requires less overall drive to achieve the same output.

Figure 5. Area under the curve for the excitatory inputs calculated by the algorithm (***Figure 3*** and Methods). *Left* - Shows the area under the curve of the excitatory input with respect to neuromodulation and inhibitory levels (color scheme). There inhibitory levels are clearly segregated across the neurmodulation range. The most efficient inhibitory scheme is "Push-Pull" (-0.7) and the least is "Balanced" (0.7). *Right* - shows the area under the curve of the excitatory input with respect to inhibiton for three neurmodulation level. The curves for each neuromodulation level do not intersect across the range of inhibition. The overall trend resembles the results on the left where the most efficent scheme is for high neurmodulation (1.2) and a "Push-Pull" inhibition (-0.7). These curves were calculated using an equally weighted excitatory input.

Figure 6. This figure links the firing rate shapes of the MN pool model to the inhibitory and neuromodulatory search space. *Heat Map* - The central figure is a heat map of the mean ΔF values of the MN pool model calculated using the firing rate patterns of the motoneurons in the MN pool model (see section Feature Extraction). These ΔF values are organized along the neuromodulation (x-axis) and inhibitory values (y-axis) used in the simulations. *Firing Rate Plots* - Emanating from the central figure are a subset of the firing rate plots of the MN pool model given a specific Inhibitory and Neuromodulation set (e.g. (0.2, 0.9)). These plots are linked to a ΔF value with an arrow. For clarity, only a subset of motoneuron firing rates are shown. From visual inspection, the shape of the firing rates differ given the Inhibition and Neuromodulation pair, from more non-linear (e.g. (-0.7, 1.2)) to more linear (e.g. (0.2, 0.9))

Figure 7. Features extracted from the firing rate patterns of each of the motoneurons in the pool. We extracted the following 7 features: Recruitment Time (t_{rec}), De-Recruitment Time (t_{drec}), Activation Duration (t_{dur}), Recruitment Range (t_{range}), Firing Rate Saturation (α_{sat}), Firing Rate Hysteresis (ΔF) and brace–height (*brace–height*). These features are then used to estimate the neuromodulation, inhibition and excitatory weights of the motor pool (see section Machine learning inference of motor pool characteristics and Regression using motoneuron outputs to predict input organization). See subsection Feature Extraction for details on how to extract features.

Figure 8. Residual plots showing the goodness of fit of the different predicted values: (A) Inhibition, (B) Neuromodulation and (C) excitatory Weight Ratio. The summary plots are for the models showing highest R^2 results in ***Table 1***. The predicted values are calculated using the features extracted from the firing rates (see ***Figure 7***, section Machine learning inference of motor pool characteristics and Regression using motoneuron outputs to predict input organization). Diagram (D) shows the multidimensionality of the RE models (see Model fits) which have 7 feature inputs (see Feature Extraction) predicting 3 outputs (Inhibition, Neuromodulation and Weight Ratio).

Figure 9. Shows the impact of the features on the models at predicting Inhibition, Neuromodulation and the excitatory Weight Ratios. The plots are split along two columns showing two types of complementary analysis: F-Statistic (left) and Mutual Information (right). *Left* - The left column shows the impact of the features on the MSE as ranked by their F value. The effect of the features are cumulative along the x-axis such that the value of the MSE at a given position in the x-axis is calculated using the features up to that point. Each of the colored traces represent one of the models used to predict the 3 outcomes and follows the trends found in *Table 1*. *Right* - The right column shows the mutual information of each feature with respect to the outcome: Inhibition, Neuromodulation and exciatory Weight Ratio (Top to Bottom). The features are ranked from best to worst along the x-axis. The ranking matches the MSE ranking in the right column. See section Ranking features to see details on how these techniques were implemented.

Tables

Table 1. R^2 values. Rows are the predicted values. Columns are the models. The R^2 values in bold represents the best model fit: Inhibition is best predicted using the RBF SVM model, Neuromodulation is best predicted by the Ridge model, Excitation Weight Ratio is best predicted by the RBF SVM model.

Name	Linear Regression	Lasso	Ridge	Elastic Net	Linear SVM	RBF SVM
Inhibition	0.36	0.36	0.36	0.36	0.35	**0.85**
Neuromodulation	0.75	0.76	**0.76**	0.75	0.74	0.71
Excitation Weight Ratio	0.72	0.72	0.72	0.72	0.72	**0.91**
Average	0.61	0.61	0.61	0.61	0.60	**0.83**

 Appendix 1

 ## Algorithm 1

 Python pseudocode for reverse engineering proportional controller on each compute node

```python
def mpi_run_proportional_controller(combinations_subset):
    gain = 0.2  # base gain
    for ginmult, ginadd in combinations_subset:
        stim_time, stim_target = load_targets()
        excitatory_input = load_base_excitatory_input()
        for fit_iteration in range(0, 20):
            # setup simulation
            inhibitory_input = excitatory_input * ginmult + ginadd
            inhibitory_input = max(inhibitory_input, 1e-7)
            sim_data = mpi_run_neuron_sims(
                ginmult, ginadd, excitatory_input, inhibitory_input, stim_time)

            # process simulation result
            average_rate = get_average_rate(sim_data)
            mse = mean_squared_error(stim_target, average_rate)
            if mse < 0.5 and mn_recruited == 20:
                return inhibitory_input, mse, fit_iteration
            elif mse < 3:
                gain = 0.5 * gain
            elif mse < 1.5:
                gain = 0.25 * gain
            error = (stim_target - average_rate) * gain
            excitatory_input += error
            excitatory_input = boost_if_needed()
            excitatory_input = max(excitatory_input, 1e-7)
```

 ## Algorithm 2

 Python pseudocode for simulating each motoneuron independently

```python
def mpi_run_motoneuron(tuple_motoneuron):
    motoneuron_h = load_neuron_data(tuple_motoneuron)
    while motoneuron_h.time_elapsed < 22000:
        motoneuron_h.step()
    return motoneuron_h.spike_times_soma

def mpi_run_neuron_sims(ginmult, ginadd, excitatory_input, inhibitory_input):
    params = [(ginmult, ginadd, excitatory_input, inhibitory_input, mn_id)
              for mn_id in range(0, 20)]
    sim_data = mpi_parallel_context.map(mpi_run_motoneuron, params)
    return sim_data
```

Supplementary Figures

779
Appendix 2—figure 1. Heat maps for the different features extracted from the firing rates of the
monotoneurons in the pool model. These heat maps are for the equally distributed excitatory
weights $[w_{start}, w_{end}] = [1, 1]$. Each heat map is organized along the Neuromodulation and Inhibitory
ranges tried in this work. The values within these heat maps show structure with respect to
Neuromodulation and Inhibition and show that this structure can be used to reverse engineer the
Neuromodulation and Inhibition themselves.

Appendix 2—figure 2. Schematic of the parallel architecture used to solve the MN pool model and to find the solution for the input to that pool. Each neuromodulation, inhibition, excitatory input weight and noise seed combination was assigned a node on the computer via the slurm batch scheduler. These "hyper-parameters" were passed to each motoneuron which had a dedicated CPU core using the message passing interface (MPI). This work was done on the Bebop supercomputer at Argonne National Laboratory, Lemont, IL.