Mediodorsal thalamus regulates sensory and mapping uncertainties in flexible decision making

Xiaohan Zhang[1], Michael M. Halassa[2] and Zhe Sage Chen[1,3,4,5] *

1. Department of Psychiatry, New York University Grossman School of Medicine, New York, NY, USA
2. Department of Neuroscience, Tufts University School of Medicine, Boston, MA, USA
3. Neuroscience Institute, New York University Grossman School of Medicine, New York, NY, USA
4. Department of Biomedical Engineering, New York University Tandon School of Engineering, Brooklyn, NY, USA.
5. Lead contact

* Correspondence: zhe.chen@nyulangone.org (Z.S.C.)

SUMMARY (150 words)

The mediodorsal (MD) thalamus is a critical partner for the prefrontal cortex (PFC) in cognitive flexibility. Accumulating evidence has shown that the MD regulates task uncertainty in decision making. However, the mechanism of this cognitive process remains unclear. Here we used a reverse-engineering approach and trained biologically-constrained computational models to delineate these mechanisms. We found that the inclusion of an MD-like feedforward module increased robustness to sensory noise, enhanced working memory and enabled rapid context switching in the recurrent PFC network performing two versions of context-dependent decision-making tasks with sensory and mapping uncertainties. Incorporating genetically identified thalamocortical pathways and interneuron cell types replicated neurophysiological findings of neuronal tuning and uncovered attractor-like population dynamics. Our model revealed key computational mechanisms of context-invariant MD in regulating cueing uncertainty and context switching. It also made experimentally testable predictions linking cognitive deficits with disrupted thalamocortical connectivity, prefrontal excitation-inhibition imbalance and dysfunctional inhibitory cell types.

Keywords: Mediodorsal thalamus, prefrontal cortex, cognitive flexibility, cognitive control, task uncertainty, working memory, context switching, thalamocortical connectivity, cell type

INTRODUCTION

Behavioral flexibility and cognitive control are fundamental in decision making;[1] successful execution of complex decision-making tasks requires identification and processing of multiple sources of uncertainty[2]. Task uncertainty may appear in the form of corrupted or incongruent sensory cues ("sensory uncertainty")[3,4], their mapping onto internal or behavioral variables ("mapping uncertainty")[2,5,6], or their likelihood of resulting in reward ("outcome uncertainty")[7]. Behavioral flexibility to map the same rule under different contexts is critical in decision making. Experiments across multiple species have shown that the MD thalamus is an important partner for the PFC in resolving uncertainty in decision making[8-15]. Human neuroimaging studies have shown that MD activity tracks sensory uncertainty in a multi-attribute attention task[14] and a categorization task[16]. This process generalizes to non-human animals; in mice performing a decision-making task, the MD tracks sensory uncertainty and enables a rapid switching of cue-to-rule transformation[6,17]. Optical manipulations support this notion and delineate their causal roles in cognitive control[5,18]. However, the computational mechanism by which the MD enhances prefrontal activity in context-dependent decision making under sensory and mapping uncertainties remain unclear. In addition, how the newly discovered cellular diversity in MD thalamus contributes to such computations is unexplored. Biologically-inspired computational modeling that incorporates neuronal subtype and circuit pathway knowledge[19-21] may provide an approach to probe these questions and yield mechanistic insight[22-29].

In light of the tenet "structure determines functions", an important circuit computation question arises: how does a feedforward MD-like structure facilitate neural computation in a recurrent PFC network to regulate different task uncertainties? More specifically, how cortical interneuron cell types, intracortical and thalamocortical connectivity may influence task performance and generate emergent task-specific neural representations? To investigate these questions, here we used a reverse-engineering approach and trained biologically-constrained PFC-MD models to perform two versions of context-dependent decision-making tasks, one with sensory uncertainty and the other with both sensory and mapping uncertainties, from which we delineated the roles of interneuron subtype and thalamocortical-projection specificity in prefrontal computation. Our PFC-MD model replicated key behavioral data and neuronal tunings in task-performing mice[5,6], including prefrontal context-invariant rule-tuning and thalamic context tuning, and further made new experimentally testable predictions. The MD subpopulations and cell-type specific MD-to-PFC projections had distinct functional roles in regulating sensory uncertainty driven by cue conflict and sparsity, maintaining working memory, and mediating prefrontal computation in a task-phase specific manner. To accommodate mapping uncertainty, synaptic plasticity of thalamocortical connections enabled rapid context switching to perform rule-invariant prefrontal computation. Our analysis suggests that the feedforward MD regulates recurrent prefrontal computation to improve information integration by increasing intrinsic time constant and controls cue-to-rule remapping by thalamocortical plasticity. Furthermore, the PFC-MD models enabled us to parse cognitive deficits of thalamocortical circuits in flexible decision making with task uncertainty, which are induced by prefrontal excitation-inhibition (E/I) imbalance, dysfunctional inhibitory cell types, and disrupted thalamocortical and corticothalamic connectivity.

RESULTS
Training biologically constrained PFC-MD models to perform decision-making tasks with parameterized sensory uncertainty

We adopted a task-optimized training strategy of computational models to delineate the computational mechanism of context-dependent decision making. We first modeled the PFC with a rate-based excitatory-inhibitory (E/I) recurrent neural network (E/I-RNN) (Methods), where cortical GABAergic inhibitory neurons consisted of parvalbumin (PV), vasoactive

intestinal peptide (VIP)-expressing and somatostatin (SOM) interneuron cell types (**Fig. 1a**). We
assumed structured inhibitory-to-excitatory and inhibitory-to-inhibitory connectivity and
disallowed weak connections that are negligible. Specifically, the VIP interneurons mainly
disinhibit other classes of interneurons[30,31]. We imposed several key biological constraints on
network connectivity. First, we modeled the MD as a feedforward structure devoid of lateral
connectivity, where all MD neurons received excitatory inputs from the PFC and projected back
to excitatory neurons. Second, guided by recent knowledge of genetically identified
thalamocortical projections that differentially target distinct PFC interneuron types[5], we imposed
additional connectivity constraints onto our model. One MD subpopulation, which is termed as
MD_1, projects to prefrontal PV interneurons, while the other subpopulation, MD_2, projects to
cortical VIP interneurons. To translate them to biological terms, $MD_1 \rightarrow$ PV corresponds to the
kainite receptor (GRIK4)-expressing (i.e., MD_{GRIK4}) pathway with preferentially targeted PV+
neurons; $MD_{DRD2} \rightarrow$ VIP projection corresponds to the dopamine receptor (D2)-expressing (i.e.,
MD_{DRD2}) pathway with preferentially targeted VIP$^+$ neurons. We trained both the PFC-MD model,
and a "PFC-alone" model as a control (using identical stimulus inputs and cortical E/I
configuration) to perform a cueing context-dependent decision-making task (**Fig. 1b** and
Methods).
In the first version of context-dependent decision-making task, the task uncertainty
contained sensory uncertainty only and two contexts were learned simultaneously. The two
contexts corresponded to two cue-independent subtasks that mapped different modalities of
sensory cues to one set of rules: attend-to-audition vs. attend-to-vision (**Fig. 1c**). Importantly,
the sensory uncertainty was parameterized in the two subtasks: a random dot motion (RDM)
subtask and a conflicting acoustic cue (CAC) subtask (see Methods). Additionally, the sparsity
of sensory cues, as a generalized form sensory uncertainty, was also parameterized and
controlled. These two subtasks consisted of three common task phases: (i) identifying the rule
by accumulating sensory evidence from ambiguous cues (800-ms cueing period); (ii)
maintaining the rule information during working memory (800-ms task delay period); (iii) making
choices in the presence of both visual and auditory stimuli (200-ms target period). Therefore,
the model first learned to accumulate sensory evidence of conflicting cues to identify the rule,
then learned to preserve the rule information in working memory, and ultimately learned to
attend audition/vision correctly and choose a rule-guided target.
We trained PFC-MD models to learn the RDM and CAC subtasks simultaneously where the
sensory cueing uncertainty was minimal. Upon reaching the desired task accuracy, we tested
the task-optimized PFC-MD models by systematically varying the degree of cue uncertainty. In
the RDM context, this corresponded to changing the coherence of random dot motion; whereas
in the CAC context, it corresponded to changing the congruence levels of low-pass (LP) vs.
high-pass (HP) tones. Namely, the cue-to-rule transformation was determined by motion
direction in the RDM context, whereas cue-to-rule transformation was determined by the tone
majority.

PFC-MD model outperformed PFC-alone model in context-dependent decision-making
under sensory uncertainty
In testing the model's generalization, we produced the model's psychometric curves separately
for two subtasks (**Fig. 1d**). By changing the level of coherence or congruence of the cue signals,
we found that the PFC-MD model outperformed the PFC-alone model in both contexts,
especially in the medium-to-high cue uncertainty ranges. This was consistently observed in
multiple independently performance-optimized models (**Supplementary Fig. 1a**), which
achieved the same performance on similarly constructed training trials. Furthermore, we
examined the percentage of error types in decision making. Given the outcome mismatch
among four choices, task errors could be ascribed by either attending the wrong rule ("rule error"
during the cueing or delay period) or attending the correct rule but with a wrong choice

("sensory error" during the target period). While testing the task-optimized PFC-MD model, the
sensory error was stable regardless of the change in sensory uncertainty, where the rule error
changed according to the level of cue ambiguity (**Fig. 1e, f**).
The signal-to-noise ratio (SNR) of sensory cueing was determined by not only the ratio of
conflicting cues, but also the density of cue signals (or equivalently the sparsity: the higher the
density, the lower the sparsity). For instance, in the CAC context, a 4/2=2:1 ratio of LP/HP
pulses indicates a relatively high level of noise---where signals are conflicting and sparse; an
identical 8/4=2:1 ratio of LP/HP but with more pulses has a higher SNR, where a higher density
of pulses indicates a higher signal level (**Fig. 1g**). Increasing the cue sparsity had a negative
impact on the task performance (**Fig. 1h**), but the PFC-MD model consistently outperformed the
PFC-alone model (**Fig. 1i** and **Supplementary Fig. 1b**). In the RDM context, we changed the
spatial density by varying the number of moving dots with the same cue coherence (**Fig. 1j**).
Similarly, decreasing the signal density or increasing cue sparsity led to a degraded task
performance (**Fig. 1k**), and the PFC-MD model also outperformed the PFC-alone model (**Fig. 1l**
and **Supplementary Fig. 1c**).

PFC and MD units showed diverse tunings and population dynamics according to task
variables, task phase and cue uncertainty
We examined the emergent tuning properties of single units of trained PFC-MD model with
respect to task variables during both cueing and delay periods. A majority (~55-65%) of PFC
excitatory units exhibited tuning preference in rule, but not context; some showed cueing
context-invariant rule tuning during the delay period (**Fig. 2a, 2d**, and **Supplementary Fig. 2a**
for additional examples). Similarly, some (~60%) of PFC inhibitory units encoded rules during
the delay period (**Fig. 2d**). In contrast, ~80% MD units showed modulation selectivity with
respect to the cueing context, but not rule (**Figs. 2b, 2c, 2e** and **Supplementary Fig. 2b** for
additional examples). To simulate an effect of evoked firing activity similar to optogenetic MD
activation, we induced a transient input to the specific MD subpopulation to increase the phasic
firing activity of MD units (Methods). During the baseline (i.e., absence of stimuli), increasing
MD_2 unit firing tended to amplify the firing rate of task-relevant, rule-tuned PFC units, whereas
increasing MD_1 unit firing tended to suppress the firing rate of task-irrelevant PFC units
(especially those with lower firing rates) (**Supplementary Fig. 2c**).
Additionally, during the cueing period, some MD_1 units (25-30%, across subtasks and
multiple test conditions) modulated their firing rates with respect to cue uncertainty (**Fig. 2f** and
Supplementary Fig. 2d). We also found firing modulation with respect to cue sparsity for the
MD_1 subpopulation (**Fig. 2g**), but not for MD_2 units (**Supplementary Fig. 2e**). Among MD_1 units,
tunings with respect to context and cue uncertainty were relatively orthogonal since very few
MD_1 units showed conjunctive coding (**Supplementary Fig. 2f**). Similar cue uncertainty tunings
were also found in PFC inhibitory units (**Fig. 2h**). It is noteworthy that not only these emergent
PFC and MD tuning properties were in line with experimental findings in task-performing mice[5,6],
intensive computer simulations also enabled us to investigate the dependency of these tunings
with respect to thalamocortical connectivity, providing insight into "why" and "how" questions of
MD regulation (see Discussion).
Increasing cue uncertainty or cue sparsity reduced rule selectivity of PFC excitatory units
in working memory (**Supplementary Fig. 3**), suggesting that reducing the SNR of sensory cues
may lead to an information loss during cue-to-rule transformation. During the delay period,
sorting the peak responses of rule-tuned PFC excitatory units produced a rule-specific
sequence[17,24,26,28]; moreover, the neural sequence was context-invariant for RDM and CAC
subtasks (**Fig. 2i**). To further explore the tuning properties of PFC-MD populations, we
employed population decoding analyses to read out either rule or context information on a trial-
by-trial basis based on the mean firing of population (Methods). The rule information could be

reliably decoded from the PFC, but not from the MD (**Fig. 2j**). Increasing cue uncertainty led to a
decrease in the PFC's rule-decoding accuracy, but had no effect on the MD's context-decoding
accuracy (**Fig. 2k**).
Furthermore, dimensionality reduction of the PFC population activity revealed low-
dimensional neural trajectories in the task-specific subspace (**Fig. 3a, d**). Increasing the level of
cue uncertainty or sparsity led to changes of neural trajectories (**Fig. 3b, c, e, f**). Interestingly,
the neural trajectory converged to fixed points faster under the lowest sensory uncertainty, and
the initial velocity was greater while dealing with lower cue uncertainty (**Fig. 3g, h**). All neural
trajectories reached to a steady state where the velocity was close to zero. A fixed-point
analysis on the three-dimensional PC subspace revealed two "line attractor-like" basins, with
each one matching a rule (attend-to-vision vs. attend-to-audition) and aligning sensory
uncertainty from one end to the other (**Fig. 3i**). Collapsing these points could reveal two distinct
line attractor-like profiles with finite line length; the neural trajectory could diverge from the
attractor basins when the sensory cue uncertainty was far too high.

MD enhances working memory maintenance in the PFC-MD network
The neural basis for persistent activity in working memory is thought to involve recurrent
excitation among prefrontal excitatory neurons. During working memory, the rule information is
maintained in thalamocortical communications, but the information may be subject to a loss with
increased task delay duration or noise interference. Therefore, we tested the robustness of task-
optimized PFC-MD model subject to a potential information loss. In so doing, we gradually
increased the duration of delay period from the initial 800 ms to 1200 ms, and found that
increasing delay duration had a negative impact on task performance (**Fig. 4a**; similarly for
PFC-alone network, **Supplementary Fig. 4a**). To demonstrate the role of MD in working
memory maintenance,[17] we increased the firing rate of MD_1 or MD_2 subpopulation during an
elongated 1100-ms delay period (with coherence/congruence of 0.8 in respective RDM/CAC
subtasks), which led to a slight boost in rule maintenance. Notably, it required less firing rate
elevation for MD_2 than MD_1 to achieve the same task improvement (**Fig. 4b, c**), probably
because the $MD_2 \rightarrow$VIP pathway has an amplification effect on increasing the target sensitivity
for working memory maintenance. In contrast, reducing the MD_1 activity during the delay period
had an opposite effect on the task performance (**Supplementary Fig. 4b**). Alternatively, we
strengthened or weakened prefrontal Exc-to-MD corticothalamic connection strengths and
observed similar effects on performance (**Supplementary Fig. 4c-f**). Together, these results
support that reciprocal PFC-MD communications help maintain the rule information through two
functionally distinct thalamocortical//corticothalamic pathways.
To distinguish the role of two specific thalamocortical projections ($MD_1 \rightarrow$PV and $MD_2 \rightarrow$VIP)
in regulating prefrontal computation, we disconnected one of two thalamocortical projections
(i.e., "computational lesion") while keeping the other intact. We found that weakening $MD_1 \rightarrow$PV
connectivity (by setting a small percentage of connections to zeros) reduced the performance
rapidly for RDM and CAC subtasks (**Fig. 4d**). Enhancement of phasic MD_1 activity could boost
task performance, but only within a narrow range (**Fig. 4d**, dashed line within the inset). In
contrast, weakening $MD_2 \rightarrow$VIP connectivity caused task performance to decay slowly (**Fig. 4e**);
however, enhancement of MD_2 activity had little effect on task performance (see inset). This was
possibly because there was no direct VIP$\rightarrow$Exc pathway to prefrontal excitatory neurons.
229
230
231 **Probing mechanistic causes of the PFC-MD circuit in cognitive deficits**
232 Our task-optimized PFC-MD models may serve as a platform to interrogate mechanisms of
233 abnormal neural representations and cognitive deficits in working memory or behavioral

inflexibility. This was achieved by modifying the "normal control" with specific "computational lesion or dysfunction".

Recurrent synaptic excitation among pyramidal neurons is approximately balanced by synaptic inhibition[32]. Thus, we first changed the overall inhibition to excitatory neurons and induced cortical excitation-inhibition (E/I) imbalance; this was done by increasing the sparsity of prefrontal SOM→Exc connections to reduce inhibition. Alternatively, MD inhibition also alters prefrontal E/I balance[33]. Notably, these operations changed the rule tunings of some PFC excitatory units during the delay period and reduced the choice discriminability at the population level during the target period (**Fig. 5a, b** and **Supplementary Fig. 5a, b**). This can be explained by the fact that the prefrontal network dynamics became more unstable and sensitive to external input perturbation, which pushed neural trajectories out of the stable attractor space. Visualizing population dynamics in the PCA subspace showed that E/I imbalance distorted neural trajectories (**Fig. 5c** and **Supplementary Fig. 5a, b**), so that the network might favor one rule over the other (i.e., "cognitive biases" observed in many mental disorders).

We further weakened prefrontal SOM→VIP and SOM→PV connectivity independently and observed a more robust task performance in SOM→PV manipulations (**Fig. 5d**), while a similar manipulation of VIP→SOM connectivity had little impact (**Supplementary Fig. 5c**). For bidirectional SOM-VIP connections, strengthening mutual inhibition between SOM and VIP neurons could amplify the sparse cue signal (grey curves in **Fig. 5e**; note that this was effective for bidirectional SOM-VIP amplification but not for unidirectional manipulation; **Supplementary Fig. 5d**), supporting the role of VIP-SOM motif in gain control[19]. A closer examination of single-unit and population responses revealed that bidirectional SOM-VIP amplification produced emergent rule tunings and enhanced rule discriminability (**Fig. 5f**). Additional MD_2→VIP stimulations further facilitated this SOM-VIP amplification (red curves in **Fig. 5e**), validating the concept of MD amplifier to regulate prefrontal computation[5]. In animal experiments, abnormal cortical GABAergic signaling or deficits in interneuron subtype has been implicated in cognitive impairment in autism spectral disorder (ASD), such as decreased responses to salient stimuli ("hypo-sensitivity") under a low SNR or decreased inhibitory gain control[34,35].

Unbalanced corticothalamic connectivity reshapes MD tunings

Next, we investigated whether modified corticothalamic connectivity could change MD neuronal tunings. Data from previous mouse experiments have suggested that MD_{GRIK4} neurons received dense inputs from L5/6 of the prelimbic cortex, in contrast to MD_{DRD2} neurons that receive sparse prefrontal inputs (experimental data not shown). To incorporate this prior knowledge, we made two modifications to the PFC-MD model. First, we assumed unbalanced MD_1 and MD_2 subpopulations (3:2 ratio in place of the previous 1:1 ratio). Second, we assumed that MD_2 units received a much sparser projection from prefrontal excitatory units than MD_1 units and imposed a sparsity constraint during the course of model training, where Exc→MD_2 connectivity was 75% sparser than Exc→MD_1 connectivity (**Fig. 6a**). Notably, this modified corticothalamic connectivity did not change psychometric curves of the task-optimized PFC-MD model (**Fig. 6b**), but led to emergent weak tunings in some MD_2 units with respect to sensory uncertainty (**Fig. 6c**). Additionally, MD_1 stimulation, but not MD_2 stimulation, improved the performance of two subtasks under cue uncertainty; yet either MD_2 or MD_1 stimulation could improve the task performance under cue sparsity (**Fig. 6d, e**). Furthermore, when cue uncertainty and sparsity were both present, stimulation of both MD subpopulations was required in order to improve task performance (**Fig. 6f**). Together, these findings further suggest distinct modulatory functions imposed by cell type-specific connectivity-dependent thalamocortical projections.

Bidirectional PFC-MD synaptic plasticity enabled rapid learning of context switching

In the second version of context-dependent decision-making task, both sensory and mapping uncertainties were present and two contexts were learned sequentially. Specifically, we introduced cue-to-rule mapping uncertainty and sequential context switching (*Context 1→Context 2→ Context 1'*) using a modified version of CAC subtask (**Fig. 7a** and Methods). Upon learning Context 1, we assumed a prewired intracortical structure and kept the synaptic connectivity intact within the PFC network. Interestingly, PFC inhibitory-to-excitatory connectivity formed two distinct patterns according to the rule tunings of excitatory units (**Supplementary Fig. 6a**); further examination of all presynaptic connections to postsynaptic PFC excitatory units revealed distinct clusters according to the rule-tuning profiles (**Supplementary Fig. 6b**).

   Further, we adapted the MD→PFC and PFC→MD synaptic connections based on inter-trial error feedback to learn context switching in a sequential manner (i.e., on a trial-by-trial basis). Notably, modification of thalamocortical and corticothalamic connections allowed the pretrained PFC-MD network to learn the new cue-to-rule transformation rapidly (**Fig. 7b**). We found that MD→Exc pathways played a critical role in context switching and rule remapping (**Fig. 7c**). The change in thalamocortical connections also mapped to functional cell types in PFC excitatory units, majority of which (>60%) displayed rule-invariant tunings despite context switching (**Fig. 7d**). Some PFC excitatory units did not change firing rates but shifted their peak firing rates temporally during the delay period (**Supplementary Fig. 6c**). Together, the PFC excitatory population displayed robust rule-invariant sequence during the delay period (**Fig. 7e**). Furthermore, the rule-tuning of PFC excitatory units tended to cluster with specific E/I ratio and modified the E/I input accordingly after successful context switching (**Fig. 7f**, left panel); in contrast, the PFC tuning properties would fail to discriminate the rule if context switching was unsuccessful (**Fig. 7f**, right panel).

   On the other hand, MD units showed context-invariant tuning between *Context 1* and *Context 1'* (**Fig. 7h**; and a unit tuning example in **Fig. 7i**). Additionally, the cue-to-rule transformation of the RNN at the steady state are qualitatively similar between *Context 1* and *Context 1'* (**Supplementary Fig 7d** and Methods). Furthermore, a small subset of MD units increased firing with inter-trial error during the course of context-switch learning: they increased the delay-period firing rates during the transient remapping state and resumed the baseline firing when successful context switching was completed (**Fig. 7j**; top: single-unit example; bottom: mean firing rate statistics, n=8 from one trained PFC-MD network). Imbalanced E/I or insufficient MD-to-PFC modulation led to a failure in cue-to-rule remapping at both single-unit and population representations (**Fig. 7f, 7k**).

Theoretical insight on MD feedforward control
Our biologically-constrained computational models have provided a paradigm to test the role of MD in regulating sensory uncertainty in context-dependent decision-making tasks (**Fig. 8a**). The modeling framework also allows us to compare functions and computational efficiency derived from different intracortical, intra-thalamic, thalamocortical and corticothalamic connectivity (**Fig. 8b**). Bilateral interactions between the PFC and MD are critical for cognitive flexibility[6]. A key question is why the combination of a recurrent E/I structure (PFC) and a feedforward excitatory architecture (MD) plus neuron subtype specificity produces more flexible control and robustness in decision making with task uncertainties, as compared to a PFC-alone model that achieves nearly the same computational power? To further probe this question, we systematically varied the size of MD population (N_{MD}=2,8,16,30), retrained the PFC-MD network, and then investigated the impact of MD on the learning speed of context switching and network properties. We found that adding more MD units improved the relative switch speed in trial-by-trial learning (**Fig. 8c**). Therefore, neurobiology may teach us a good reverse-engineering lesson. One specific theoretical insight is that the MD may help "slow down" prefrontal dynamics by increasing the time constant in order to improve information integration during cueing or working

memory (**Fig. 8d** and Methods). Additionally, our computer simulations suggest that the
feedforward MD structure has a lower intrinsic dimensionality than the recurrent PFC structure
in the full-size PFC-MD network (**Fig. 8e**).
Our model provides new insight into the role of MD-PFC connectivity in enabling rapid
context switching to learn a cue-to-rule remapping, and further produces new experimentally
testable hypotheses. As control experiments, in addition to keeping intracortical PFC-to-PFC
connectivity intact, we systematically kept the unilateral or bilateral MD-PFC synaptic
connectivity unchanged during context switching and only allowed synaptic plasticity among the
remaining connectivity (**Fig. 8f**, top panels). Our result showed that the PFC rule invariance
property was lost when MD plasticity was disrupted, and the speed of cue-to-rule remapping
was the slowest when bilateral MD-PFC plasticity was disabled (**Fig. 8f**; compared to the
baseline where intracortical connectivity was intact). In contrast, enabling MD→PFC plasticity
significantly improved the switch speed, suggesting that the crucial role of thalamocortical input
in regulating recurrent prefrontal computation for cognitive flexibility. Based on these results, we
envisioned that the MD acts like an ON/OFF switch that modulates the respective E/I input of
rule-tuned PFC units and changes prefrontal tunings according to the context. If the recurrent
prefrontal circuit is viewed as an attractor network (**Fig. 3i**), the context-encoding MD can play
the role of controller to usher the PFC to a proper attractor space, facilitating noise reduction (for
ambiguous cues) and cue-to-rule remapping (for the same cues) (**Fig. 8g**). If the PFC dynamics
is simplified as a two-dimensional (2D) system, we envisioned that the lower-dimensional (i.e.,
1D) MD is acting like an actuator on the 2D system; rotating the system by 180 degrees through
MD-PFC plasticity may enable cue-to-rule remapping while keeping the original PFC dynamics
intact (**Fig. 8h**). This intuition was confirmed by our computer simulations, where prefrontal
population dynamics under *Context 1* and *Context 2* were projected onto the same subspace
(**Fig. 8i**). Furthermore, the orthogonal relationship of PFC population dynamics was lost if the
PFC-MD network failed to learn the context (**Fig. 8j**, left panel, dashed lines). Additionally, the
MD-impaired model suffered from cognitive inflexibility, and MD-stimulation could rescue the
cognitive deficit (**Fig. 8j**, middle and right panels).

DISCUSSION
The thalamus has various subnetwork motifs and diverse cortical target outputs, the higher-
order thalamic nuclei such as the MD is critical for dynamic regulation of cortical activity in
attention, executive control and perceptual decision-making[9,36,37]. Several computational models
of thalamocortical networks have been developed for the sensory thalamus[38-40] and higher-order
thalamus[22,29,41]. However, it remains unknown how the MD thalamus contributes to decision
making with task uncertainty. Theory and modeling can help unravel key computational
mechanisms that provide new experimental predictions[42]. Motivated by multiple lines of animal
data[5,6,43], we trained biologically inspired PFC-MD models with interneuron subtype and
thalamocortical pathway specificity to perform two versions of context-dependent decision-
making tasks, each with independent sensory and mapping uncertainties. We found that the
PFC-MD model outperformed the PFC-alone model in the presence of sensory uncertainty,
while cell-type and pathway specificity play a vital role in regulating prefrontal computation
during evidence accumulation (cueing period) and working memory (delay period). At different
task phases, the MD regulates prefrontal resources for information transmission and
maintenance to encode the task variables (rule and context) in a coordinated manner. Rule
information is encoded by prefrontal attractor-line dynamics and preserved during the delay
period. We found cell-type specific tunings in the MD subpopulation with respect to cueing
uncertainty and sparsity, and such MD tunings can be influenced by corticothalamic projection.
Additionally, adaptation of MD-PFC connectivity enabled the PFC-MD network to rapidly learn
context switching and maintain invariant rule/context encoding, suggesting the role of MD as an

ON/OFF switch actuator to enable cognitive flexibility. The notion of thalamus as an ON/OFF switch to assist the thalamocortical control is also in line with the concept in the motor system[44,45].

Cognitive flexibility requires PFC-MD coordination to map context to behavior, as well as to regulate sensory and mapping uncertainties. Our computational model provides direct support for circuit mechanisms of PFC-MD network in flexible decision making. Distinct cellular targeting among cortical interneurons underlies differential inhibitory effects on excitatory neurons[46]. Cortical interneuron-specific cells that specialize in synaptic disinhibition of excitatory neurons may shape the way excitatory neurons integrate information, and exhibit context-specific and behavior-relevant responses[32,47]. Optogenetic tagging experiments in mice revealed that $MD_{GRIK4} \rightarrow PV$ projection suppresses prefrontal noise when task inputs are dense but conflicting, and $MD_{DRD2} \rightarrow VIP$ projection amplifies prefrontal signals when task inputs are sparse[5]. The $MD_1 \rightarrow PV$ projection is the primary drive for feedforward thalamic inhibition[48,49]. Cortical PV interneurons have been implied in the mechanisms of gamma oscillations and cognitive function[50]; disturbance in this signaling contributes to altered gamma oscillations and working memory deficits in schizophrenia[51,52]. Thalamocortical and corticothalamic pathways play different roles in decision-making processes[17]. Corticothalamic projection is known to adjust the gain and tuning precision of thalamic neurons as required by behavioral demands[10]. Our analyses of corticothalamic and thalamocortical projections suggest an asymmetric information flow and distinct contributions to decision making in a task phase-dependent manner. The thalamocortical plasticity can potentially modify PFC neuronal correlation[53], and further improve prefrontal SNR (Methods).

At the computational level, low-dimensional representations of the MD may facilitate compression of cortical information and enable predictive coding in the context of cognitive flexibility. Specifically, since the MD modulates with cue uncertainty and context ("prior"), whereas the PFC encodes the rule ("likelihood"), integrating information from both MD and PFC provides a natural paradigm for updating the posterior in a Bayesian framework[54].

The capacity of information transmission between neurons or circuits is fundamentally limited by the SNR. Neuromodulation such as dopamine may enhance the SNR of prefrontal activity[55,56]. Since the MD is known to receive dopaminergic inputs[57], the MD_2 subpopulation in our model may be viewed as performing a similar function relevant to the dopamine type-2 receptor (D2)-expressing projection[5]. This action of dopamine is achieved by D1 and D2-receptor-mediated effects on pyramidal and local circuit neurons, which further mediate neuronal excitability and recurrent inhibition and thus contribute to the stability of cortical representations of external and internal stimuli[58]. Our results are also consistent with the idea that the MD can facilitate GABA shift and change prefrontal functional connectivity and E/I balance[59].

Adaptation to rule or behavior according to the task context is a fundamental property in cognitive control. Cognitive flexibility is facilitated by the inclusion of MD[6]—a feedforward low-dimensional structure that monitors both cue conflicts and task error[5]. We reason that adaptive behaviors are driven by both fast and slow learning, where the feedforward structure is appealing to fast learning and the recurrent cortical structure is involved in slow learning. Our theoretical reasoning and computational simulations have shown that thalamocortical plasticity of a pretrained PFC-MD model through trial-by-trial learning enables a rapid and reversible cue-to-rule remapping for a context switch. Moreover, we found that the feedforward thalamocortical connection plays a more vital role than the feedback corticothalamic connections in the speed of context switching. During remapping, rule information is invariantly preserved by PFC population dynamics, resulting in a geometric rotation of neural trajectories.

What computational insight do our models provide to the studies of cognition in a broader context? First, our PFC-MD model provides a means to identify the role of thalamocortical and corticothalamic signaling and how populations of neurons interact between the source and

target at different decision-making task phases[60]. Second, computer simulations for various task
conditions, which are usually difficult to accomplish in animal experiments due to resource
constraints, may produce experimentally testable predictions on behavior and neural
representations (such as cortical connection motifs, changes in neuronal tunings under
uncertainty). Lastly, our model with cell-type specificity provides a strategy to dissect
computational mechanisms of cognitive deficits (e.g., sensory gating and top-down control)
encountered in neuropsychiatric disorders such as schizophrenia[61-63]. Abnormal dopaminergic
activation and lower cortical SNR have also been implicated in schizophrenia[56]. A lack of
inhibitory control increases hyperexcitability and reduces cognitive flexibility in schizophrenia or
ADHD[12,64,65]. Dysfunction of GABAergic inhibition may impact synaptic E/I balance that is linked
to pathophysiology of a wide range of disease phenotypes such as cognitive deficits and
negative symptoms. Recent results have shown that bidirectional plasticity in PFC-MD
pathways may correct cognitive impairment[66]. Our modeling results have showed that reduced
MD population size or impaired MD→PFC pathway reduce the speed of learning the context
switch, resembling the cognitive deficits in schizophrenia. Finally, a complete dissection of these
computational mechanisms may provide therapeutic insight into thalamic deep brain stimulation
strategies to improve cognitive functions in mental disorders.
454
Methods

Context-dependent cognition with parameterized sensory uncertainty
The computational task was modified from a combination of a version of the two-context two-modality four
alternative forced choice (4AFC) task[17] and a single-modality cue-conflicting two alternative force choice
(2AFC) task[5]. **Fig. 1a** illustrates the two cueing contexts that were mapped to the same rule: attend-to-
audition (rule 1) or attend-to-vision (rule 2). Each trial started with a 40-ms trial initialization period,
followed by 800-ms stimulus cueing. In the cueing period, the neural network received cues from either
visual or auditory modality, each of which had parameterized cue uncertainty or conflicting cues. In the
visual modality context, the random dot motion (RDM) subtask used cues as random dots in motion,
where the coherence of moving dots in time indicates the degree of uncertainty: with 1 meaning all dots
moving with the same direction (rightward, rule 1 vs. leftward, rule 2) and 0 meaning completely random
direction. The default dimensionality of cue input in RDM was 64. In the auditory modality context, the
conflicting acoustic cue (CAC) subtask used cues as a sequence of conflicting pulses: low-pass (LP)
pulse (+1) or high-pass (HP) pulse (-1). The {+1,-1} pulses were task-relevant cues, where the
background was represented by 0. The number of pulses during the 800-ms cueing period was 32 in the
training dataset, giving a signal density 40 s^{-1}. The mixture of sensory cues determined the uncertainty.
Accumulating the sensory evidence (i.e., the total or relative number of LP and HP pulses) would produce
the indication of rule 1 (more -1's) or rule 2 (more +1's). During the cueing period, the neural network first
learned to accumulate the sensory evidence of ambiguous cues to recognize the rule. During the follow-
up 800-ms delay period, the neural network learned to preserve the rule information during working
memory. During the 200-ms target period, the auditory and visual stimuli (which were used differently
from the cueing period) were simultaneously presented (e.g., upsweep/downsweep tone that was
mapped to auditory left/right choice, respectively; yellow/blue light that was mapped to visual left/right
choice, respectively)[16], and each attended target was associated with a unique choice. Therefore, the
network learned to attend to the correct modality and select one of four choices (**Fig. 1a**). Together, the
neural network learned a cross-modal context-dependent working memory and decision-making task,
which mapped the ambiguous cueing signals and rules to decision. As a result, the task error could be
ascribed to either rule error or sensory error, or both. Specifically, errors related to rule encoding was
termed the "rule error" (or "executive error", which occurred in cueing and delay periods), whereas errors
related to target stimulus perception was termed the "sensory error" (which occurred in the post-delay
period) (Table S1).
486
487 **Table S1. Categorization of task errors in the context-dependent 4AFC task.**

	Rule and Context-Dependent Cueing	
	Rule 1: attend-to-audition	Rule 2: attend-to-vision

	Cue: A_{LP} or V_{right}		Cue: A_{HP} or V_{left}	
Response〳Target	Auditory left	Auditory right	Visual left	Visual right
Choice #1 (auditory left)	correct	sensory	rule	both
Choice #2 (auditory right)	sensory	correct	both	rule
Choice #3 (visual left)	rule	both	correct	sensory
Choice #4 (visual right)	both	rule	sensory	correct

488
In theory, the chance-level accuracy for the 4AFC task is 25%. However, the rule error and sensory
error are independent in the task design. For the rule error alone, the chance-level accuracy is 50%. To
introduce a proper degree of sensory error in the target period, we assumed two competing sensory
inputs were stochastic and drawn from normal distributions with two different mean values but the same
variance. Increasing the variance would introduce the task difficulty and increase the sensory error; we
selected a variance value that best matched to the experimental data. In the extreme case where sensory
inputs were deterministic, the model prediction would lead to only rule error and minimal sensory error.
496
497 **Computational models**
498 We first constructed a PFC-alone network as the baseline model. The PFC network is an excitatory-
499 inhibitory (E/I) recurrent neural network (RNN) with N_{PFC}=256 fully interconnected units described by a
500 standard firing-rate model[24,25]. We adopted a continuous-time formulation of RNN dynamics as follows:
501
502 $$\tau \dot{\mathbf{x}}^{PFC} = -\mathbf{x}^{PFC} + \mathbf{W}^{rec}\mathbf{r}^{PFC} + \mathbf{W}^{in}\mathbf{u} + \sigma\boldsymbol{\xi}. \qquad \text{(Equation 1)}$$
503
where τ denotes the time constant (we used τ=20 ms), $\boldsymbol{\xi}$ denotes additive N_{PFC}-dimensional Gaussian
noise, each independently drawn from a standard normal distribution, σ defines the scale of the noise
standard deviation; $\mathbf{W}^{rec}$ is an $N_{PFC} \times N_{PFC}$ matrix of recurrent connection weights, and $\mathbf{W}^{in}$ denotes an
$N_{PFC} \times N_{in}$ matrix of connection weights from the input to network units (N_{in} =72). The network output
consisted a set of linear readout units that produced a 4-dimensional target estimate: $\mathbf{z} = \mathbf{W}^{out}\mathbf{r}$, where
$\mathbf{W}^{out}$ is a $4 \times N_{PFC}$ matrix, and the N_{PFC}-dimensional neuronal firing rate vector $\mathbf{r}$ is defined by a softplus
function: $\mathbf{r} = \phi(\mathbf{x})$. The network selected the maximum mean output from $\mathbf{z}(t)$ to yield one out of four
choices in decision. We assumed 4:1 ratio of the number of excitatory to inhibitory neurons and imposed
Dale's principle on synaptic connectivity. Therefore, the recurrent weight matrix consisted of functionally
distinct connectivity according to the cell types: excitatory-to-excitatory, inhibitory-to-excitatory, excitatory-
to-inhibitory, and inhibitory-to-inhibitory connections. Among cortical inhibitory neurons, we further
considered three major neuron subtypes: parvalbumin (PV), vasoactive intestinal peptide (VIP)-
expressing and somatostatin (SOM) interneurons. The interneuron cell types had distinct inhibitory-to-
excitatory and inhibitory-to-inhibitory connectivity.[26-29] The most common PV interneurons target
excitatory neuronal cell bodies, and the second most common SOM interneurons target the distal
dendrites of postsynaptic excitatory neurons. VIP interneurons preferentially target SOM cells, and to a
lesser extent PV cells, so we did not consider VIP→PV connectivity here; therefore, VIP interneurons can
modulate cortical excitatory neurons through disinhibition of SOM cells (**Fig. 1b**). We further assumed
that the percentages of three interneuron cell types were equal and these subtypes were determined by
the synaptic interconnectivity. To discretize continuous-time dynamics, we used a bin size of Δt=20 ms in
all numerical simulations.
We further constructed a PFC-MD model based on the knowledge of genetically identified
thalamocortical projections and cell type specificity. In light of experimental findings[4], we assumed that
the MD primarily consists of non-recurrent excitatory neurons (N_{MD}=200) and have two specific MD→PFC
pathways: where the MD_1 subpopulation projects to cortical PV interneurons, whereas the MD_2
subpopulation projects to cortical VIP interneurons. Meanwhile, MD neurons received reciprocal
projections from PFC excitatory neurons. We assumed an equal number of excitatory units in both MD_1
and MD_2 subpopulations. The MD and PFC units both received a N_{in}-dimensional stimulus input, but only
the PFC units were used to generate a 4-dimensional choice output. There were fully connected
corticothalamic connections (of size $N_{PFC} \times N_{MD}$) from PFC units to MD_1 and MD_2 subpopulation units,
separately. For convenience, we let $\mathbf{W}^{eff}$ represent the effective PFC-MD connectivity matrix of size

(N_{PFC}+N_{MD})×(N_{PFC}+N_{MD}). In this case, the prefrontal dynamics were controlled by both intracortical weights
and thalamocortical weights[44]

$$\tau\dot{\mathbf{x}}^{PFC} = -\mathbf{x}^{PFC} + \mathbf{W}^{rec}\mathbf{r}^{PFC} + \mathbf{W}^{MD\rightarrow PFC}\mathbf{r}^{MD} + \mathbf{W}^{in}\mathbf{u} + \sigma\boldsymbol{\xi}. \quad \text{(Equation 2)}$$

540 And the MD dynamics were controlled by corticothalamic weights:

$$\tau\dot{\mathbf{x}}^{MD} = -\mathbf{x}^{MD} + \mathbf{W}^{PFC\rightarrow MD}\mathbf{r}^{PFC} + \mathbf{V}^{in}\mathbf{u} + \sigma\boldsymbol{\xi} \quad \text{(Equation 3)}$$

544 where $\mathbf{V}^{in}$ denotes an $N_{MD} \times N_{in}$ matrix. Together, we can rewrite Equations 2 and 3 with a unified
545 equation:

$$\tau\begin{pmatrix}\dot{\mathbf{x}}^{PFC}\\\dot{\mathbf{x}}^{MD}\end{pmatrix} = -\begin{pmatrix}\mathbf{x}^{PFC}\\\mathbf{x}^{MD}\end{pmatrix} + \begin{bmatrix}\mathbf{W}^{rec} & \mathbf{W}^{MD\rightarrow PFC}\\\mathbf{W}^{PFC\rightarrow MD} & 0\end{bmatrix}\begin{pmatrix}\mathbf{r}^{PFC}\\\mathbf{r}^{MD}\end{pmatrix} + \begin{bmatrix}\mathbf{W}^{in} & 0\\0 & \mathbf{V}^{in}\end{bmatrix}\begin{pmatrix}\mathbf{u}\\\mathbf{u}\end{pmatrix} + \sigma\boldsymbol{\xi} \quad \text{(Equation 4)}$$

The output setup was identical to the PFC-alone model, where the readout only depended on the PFC
units but not MD units.
We trained the PFC-alone and PFC-MD models by supervised learning. The two subtasks, CAC and
RDM tasks, were learned separately or simultaneously. The CAC or RDM subtask consisted of a batch
size of 64 simulated trials used for training. The number of training trials for two rules (attend-to-audition
vs. attend-to-vision) was balanced. We used the mean-squared-error (MSE) plus weight decay as the
regularized cost function and optimized the model parameters using a gradient-descent algorithm, with
default configuration of hyperparameters (learning rate parameter 0.0005; weight decay regularization
parameter 0.1). The optimization continued until the desired accuracy was reached. In total, we trained
more than 20 independent PFC-MD networks (and an equally matched number of PFC-alone networks),
and selected their respective best models to present the results (however, the psychometric curves and
neural representations were quite robust among most task-optimized models). In testing, we varied the
degree of cue uncertainty and simulated the 10 independent random test trials per condition in order to
compute the psychometric curve. In the CAC subtask, we changed the ratio of LP/HP pulses for different
cue uncertainties, and varied the timing and order of the LP and HP pulses for a fixed uncertainty (**Fig.
1g**). In the RDM subtask, we varied the percentage of dots moving rightward or leftward for different cue
uncertainties, and selected different subsets of dots in time (**Fig. 1j**). We also observed that some task-
optimized PFC-MD and PFC-alone models did not show good generalization across all tested cue
uncertainty and sparsity conditions (e.g., making more one type of rule-specific error), which we have
excluded in the analyses.

Decision making with mapping uncertainty: switching cue-to-rule transformation in the CAC task
To introduce mapping uncertainty, we considered a switching context task (*Context 1→Context 2→
Context 1'*) using the simulated LP/HP cues in the CAC task (with 800-ms cueing period and 600-ms
delay period). In *Context 1*, more LP (LP>HP) pulses would encode rule 1: attend-to-audition. In *Context
2*, the rule was reverse: more LP pulses would encode rule 2: attend-to-vision (**Fig. 7a**). The cue and
sensory inputs were identical to the previous setup. At the first stage of learning *Context 1*, we trained the
PFC-MD model by batch learning. At the second stage for learning the context switching, we froze
intracortical connection weights $\mathbf{W}^{rec}$, and adapted the other model parameters
$\{\mathbf{W}^{MD\rightarrow PFC}, \mathbf{W}^{PFC\rightarrow MD}, \mathbf{W}^{in}, \mathbf{V}^{in}\}$. on a trial-by-trial basis. After each trial, the correct or error feedback was
used and back-propagated to sequentially update the model parameters. We further learned *Context 2*
under the new cue-to-rule transformation, and then relearned the *Context 1'* based on the original rule. To
speed up computation, we used a smaller size of network, with N_{PFC}=256 and N_{MD}=30 (N_{MD1}=15,
N_{MD2}=15). Additionally, we used a gradually annealing learning rule during online learning.

Behavioral analysis and psychometric curve
The model performance was assessed by a psychometric curve, where the accuracy (percentage of
correct) was calculated with varying degrees of cue uncertainty. In the CAC task, the LP/HP congruence
level (range: [0.5,1.0]) was defined by a ratio: $\max\left\{\frac{\#LP\ pulses}{\#LP\ pulses+\#HP\ pulses}, \frac{\#HP\ pulses}{\#LP\ pulses+\#HP\ pulses}\right\}$, with 0.5 being

maximally uncertain and 1 being maximally certain. In the RDM task, the cue uncertainty was calculated
by the degree of coherence (range: [-1.0, +1.0]) of random dot motion (with absolute coherence of 1
indicating maximal certainty and noise-free, and coherence of 0 being completely uncertain). Furthermore,
we used the algebraic sign to represent the motion direction (with positive/negative values moving
rightward/leftward, respectively).[24] In testing, we generated 10 random realizations of input sequences
and calculated the task errors for producing performance curves (mean ± s.e.m.). Based on the
percentage of correct choices, we further fit a sigmoid-shaped psychometric curve function using
maximum likelihood estimation (**Fig. 1e**). Note that in all psychometric curves, only the rightmost cue
condition in the x-axis (i.e., lowest cue uncertainty) was used for training the models, and the remaining
cue conditions were never used in training.
599
Single-unit tuning curve analysis
We computed the trial-averaged peri-stimulus time histogram (PSTH) from single unit firing activity for
specific task condition (rule/context/cue uncertainty/cue sparsity). We excluded the units with very low
firing rates (lower 5-10 percentiles of population) in tuning curve analysis. We identified rule or context
modulation by comparing their respective mean firing rate as well as temporal PSTH profiles during both
cueing and delay periods (**Fig. 2a-e**). Across trials, mean±SD firing rates of units were calculated, the
rank-sum test was used to compare the statistics to determine significant modulation (p<0.05). To define
the cue uncertainty tuning, we varied the cue coherence or congruence level (high/medium/low) (**Fig. 2f-h**)
and compared the respective PSTH profiles. A unit was called to have cue uncertainty modulation if and
only if the PSTH comparisons were significantly different between all three paired cue uncertainty levels
(high vs. medium, medium vs. low, high vs. low) during the cueing period.
611
612   **Excitatory/inhibition (E/I) input**
613   For each PFC excitatory unit, we compute the total excitatory input and inhibitory input
614
$$I_j^{\text{exc}} = \sum_{j \in \text{Exc}} W_{ij}^{\text{rec}} r_i + \sum_{k \in \text{MD}} W_k^{\text{MD} \to \text{PFC}} r_k$$
615
$$I_j^{\text{inh}} = \sum_{j \in \text{Inh}} W_{ij}^{\text{rec}} r_i \qquad \text{(Equation 5)}$$
616   where the total excitatory input consisted of excitatory units of both cortical and thalamic contributions,
617   and the total inhibitory input consisted of input from cortical inhibitory units.
618
619
Neural sequence analysis
To examine potential neural sequences during the delay period, we normalized the PSTHs of PFC
excitatory units between 0 and 1 and sorted by the latency of their peak firing rates. Units with peak firing
rate smaller than 0.2 during the delay period were excluded in this analysis. We compared the neural
sequence among the selected subpopulation between rules and between contexts using the same rank
order (**Fig. 2i**).
626
627
Population decoding analysis
We employed a binary support vector machine (SVM) classifier to achieve trial-by-trial classification to
decode the task rule or context, based on the simulated population activity of PFC or MD units. The
software was implemented under the Sciket-learn Python environment. The network received an *N*-by-1
input, with each representing the mean firing activity of one unit. Among the total 200 simulated trials, we
divided them into halves: 50% for training and remaining 50% for testing. We reported the average cross-
validation decoding accuracy based on 20 independent Monte Carlo runs. We conducted with decoding
analysis under various cue uncertainty conditions (**Fig. 2j, k**).
636
Dimensionality reduction analysis
To extract low-dimensional representation of population activity from the PFC-MD network, we employed
principal component analysis (PCA) to visualize neural trajectories during the cueing and delay periods.
Briefly, we first defined the task-related axes and grouped neural population activity into a matrix $\mathbf{X} \in$
$\mathbb{R}^{N \times CT}$, where N denotes the number of units, C denotes the number of stimulus conditions, and T denotes
the number of time bins. We performed PCA separately on temporally-binned data matrix $\mathbf{X}$ at specific or
combined task periods, and further extracted two dominant principal subspaces associated with the two

largest eigenvalues. The derived low-dimensional neural trajectory showed task-variable-nonspecific
representations.
To further visualize the neural trajectory in task-variable-axes (e.g., choice of rule, cue, uncertainty),
we further defined the task-relevant state space using a published method[27]. First, we used the 20 largest
principal components (PCs) and denoised the representation of neural activity. Second, we constructed a
regression model for each unit based on task variables for two context-dependent subtasks: cue and
choice of rule. The regression coefficients across units defined an axis in the neural state space
representing each task variable. After performing QR orthogonalization, these axes formed the task-
relevant state space onto which the population response in the 20-dimensional PC subspace was
projected, providing a denoised and demixed task-relevant neural representation. Unless stated
otherwise, we used only correct trials to produce trial-averaged curves in two-dimensional subspace (**Fig.
3a-f**). From a neural trajectory $\boldsymbol{p}(t)$, we further defined the time-varying neural velocity by computing the
change rate in neural trajectory: $v(t) = \|\dot{\boldsymbol{p}}(t)\|$ (**Fig. 3g, h**).

Modeling phasic changes in MD neuronal firing
To model optogenetic activation or suppression effect on the MD neuronal firing, we introduced a
depolarizing or hyperpolarizing single-pulse input to the targeted MD neurons, which led to an increase or
decrease in their phasic firing activities, respectively (**Fig. 6b-d**).

Fixed-point analysis of recurrent network dynamics
Similar to our previous analysis[24,25], we identified fixed-points or slow points of the task-optimized PFC-
MD model by numerically solving the optimization problem (https://github.com/mattgolub/fixed-point-finder)

$$\min_{\tilde{\mathbf{x}}} q(\tilde{\mathbf{x}}), \quad \text{where } q(\tilde{\mathbf{x}}) = \left\| -\tilde{\mathbf{x}} + \mathbf{W}^{\text{eff}}\phi(\tilde{\mathbf{x}}) + [\mathbf{W}^{\text{in}}, \mathbf{V}^{\text{in}}] \cdot \mathbf{u} \right\|^2 \quad \text{(Equation 6)}$$

where $\tilde{\mathbf{x}} = [\mathbf{x}^{\text{PFC}}, \mathbf{x}^{\text{MD}}]$. We collected a set of fixed-points by randomly initializing the network. The
dimensionality of fixed points was the same as dim($\tilde{\mathbf{x}}$)=N_{PFC}+N_{MD}. Once the numerical optimization was
completed, we applied PCA to visualize the fixed points in three-dimensional PC subspace (**Fig. 3i**).

Eigenvalue analysis and time constant estimation
A square matrix $\mathbf{A}$ is non-normal if it satisfies $\mathbf{A}\mathbf{A}^T \neq \mathbf{A}^T\mathbf{A}$. For the non-normal matrix
$\mathbf{W}^{\text{eff}} = \begin{bmatrix} \mathbf{W}^{\text{rec}} & \mathbf{W}^{\text{MD}\rightarrow\text{PFC}} \\ \mathbf{W}^{\text{PFC}\rightarrow\text{MD}} & 0 \end{bmatrix}$ (in the PFC-MD model) or $\mathbf{W}^{\text{rec}}$ (in the MD-lesioned model), we conducted
eigenvalue analysis to analyze the nonlinear dynamics with linear approximation[25,67], where the maximum
of the real (or real-part) eigenvalues characterizes the long-term behavior for the speed of network's
steady state decaying to zero[68]. We further we adapted a published method to estimate the intrinsic time
constant of dynamical systems[69], for both PFC-MD and MD-lesioned structures (**Fig. 8d**):

$$\tau_{\text{intrinsic}} = \max_k \left(-\frac{\Delta t}{\log |\lambda_k|} \right). \quad \text{(Equation 7)}$$

where $|\lambda_k|$ denotes the absolute value of the *k*-th real or complex-valued eigenvalue. Since a large value
of time constant is beneficial for temporal summation, a larger time constant can help information
integration (during the cueing period) and working memory maintenance (during the delay period).

Mathematical analysis of cue-to-rule transformation
In light of Equation 2 and Equation 4, we assumed that the PFC-MD network converged to a steady state
(i.e., the velocity of the state, $|\dot{\mathbf{x}}^{\text{PFC}}|$ and $|\dot{\mathbf{x}}^{\text{MD}}|$ approached to zeros towards the end of task delay period,
see **Fig. 3g, h**). To gain some mathematical intuition, we assumed a linear RNN dynamics and let
$\dot{\mathbf{x}}^{\text{PFC}} = \mathbf{0}$ and $\dot{\mathbf{x}}^{\text{MD}} = \mathbf{0}$. Upon rearranging the terms and assuming $\tau = dt$, we derived the steady-state
solutions for $\tilde{\mathbf{x}} = [\mathbf{x}^{\text{PFC}}, \mathbf{x}^{\text{MD}}]$:

$$\tilde{\mathbf{x}}_{\text{ss}} = \left(\mathbf{I} - \mathbf{W}^{\text{eff}} \right)^{-1} \begin{bmatrix} \mathbf{W}^{\text{in}} & 0 \\ 0 & \mathbf{V}^{\text{in}} \end{bmatrix} \mathbf{u} = \mathbf{\Psi}\mathbf{u} \quad \text{(Equation 8)}$$

where the $(N_{\text{PFC}}+N_{\text{MD}})$-dimensional matrix $\mathbf{\Psi} = \left(\mathbf{I} - \mathbf{W}^{\text{eff}}\right)^{-1}\begin{bmatrix} \mathbf{W}^{\text{in}} & 0 \\ 0 & \mathbf{V}^{\text{in}} \end{bmatrix}$ denotes the cue-to-rule

transformation. Let $\mathbf{\Psi}_{\text{context 1}}$ and $\mathbf{\Psi}_{\text{context 1'}}$ denote the transformation matrices under *Context 1* and

Context 1', respectively; if the cue-to-rule tunings of PFC units are reversibly remapped, we will expect

that these two transformation matrices are similar (**Supplementary Fig. 6d**). Note that if $\mathbf{u}$ is univariate,

$\mathbf{\Psi}$ will reduce to a $(N_{\text{PFC}}+N_{\text{MD}})$-dimensional vector.

From Equation 2, we see that feedforward MD input and cue input jointly influence the prefrontal

neural dynamics $\dot{\mathbf{x}}^{\text{PFC}}$. In the two-dimensional PCA subspace, the MD input can shift the original

prefrontal dynamics and modify the vector field (**Fig. 8f**). Additionally, the cue input can modulate the MD

activity through $\mathbf{V}^{\text{in}}$ (such that the MD can encode cue uncertainty or sparsity). When the MD input is

disconnected or disrupted, the cue-to-rule transformation $\mathbf{\Psi}$ will be written as $\mathbf{\Psi} = (\mathbf{I} - \mathbf{W}^{\text{rec}})^{-1}\mathbf{W}^{\text{in}}$. If the

prefrontal internal connectivity is unchanged in the absence of MD-to-PFC feedforward control, the only

degree-of-freedom in modulation is through the input weights $\mathbf{W}^{\text{in}}$.

Optimal thalamic control

The MD thalamus can be viewed as a controller that operates on the cortical plant, which enables the

context switch. To gain mathematical insight, we assume that the controlled cortical state in *Context 2* at

a fixed point (denoted by $\mathbf{x}^{*,\text{PFC,context2}}$) was a rotated version of state in *Context 1* at the fixed point

(denoted by $\mathbf{x}^{*,\text{PFC,context1}}$; see a two-dimensional cartoon illustration in **Fig. 8h**) during the steady state

(where $\dot{\mathbf{x}}^{\text{PFC}} = 0$ and external input $\mathbf{u}=0$). From Equation 2, the naïve feedforward strategy to achieve the

cortical target state to set the net MD-to-PFC input as[45]

$$\mathbf{W}^{\text{MD}\to\text{PFC}}\mathbf{r}^{\text{MD}} = \left(\mathbf{x}^{*,\text{PFC,context2}} - \mathbf{W}^{\text{rec}}\,\phi(\mathbf{x}^{*,\text{PFC,context2}})\right) \qquad \text{(Equation 9)}$$

Provided that the intracortical connection $\mathbf{W}^{\text{rec}}$ is intact, then the one-shot feedforward control strategy to

learn the context switch (*Context 1→Context 2*) is to set $\mathbf{r}^{\text{MD}}$ as

$$\mathbf{r}^{\text{MD}} = (\mathbf{W}^{\text{MD}\to\text{PFC}})^{-1}\left(\mathbf{x}^{*,\text{PFC,context2}} - \mathbf{W}^{\text{rec}}\,\phi(\mathbf{x}^{*,\text{PFC,context2}})\right) \qquad \text{(Equation 10)}$$

Alternatively, $\mathbf{r}^{\text{MD}}$ can be updated at a slower timescale by modifying the thalamocortical weights

$\mathbf{W}^{\text{MD}\to\text{PFC,context1}}$ as well as the corticothalamic weights $\mathbf{W}^{\text{PFC}\to\text{MD,context1}}$ under *Context 1*. This is relatively

simple since there is no recurrent weights within the feedforward MD structure. The speed of switching

between two contexts depends on the degree-of-freedom of the PFC-MD system and the initial cortical

state.

Intracortical connection motifs and correlation

Cortical networks are known to contain some connectivity motifs.[70] Let us consider a recurrent network

with arbitrary connectivity among *N* PFC neurons. Spike activities of these PFC neurons, denoted by

$\{s(t)\} = \{[s_1(t), s_2(t), \dots, s_N(t)]\}$, were modeled as inhomogeneous Poisson processes with time-varying

rates $\mathbf{\Lambda}(t) = [\lambda_1(t), \lambda_2(t), \dots, \lambda_N(t)]$ and respective baseline rate $\mathbf{\Lambda}_0 = \{\bar{\lambda}_1, \bar{\lambda}_2, \dots, \bar{\lambda}_N\}$. We further modeled

the dynamic evolution of $\mathbf{\Lambda}(t)$ by a matrix equation:

$$\mathbf{\Lambda}(t) = \mathbf{\Lambda}_0 + \int_{-\infty}^{\infty} K(\tau)s(t-\tau)d\tau = \mathbf{\Lambda}_0 + (K*s)(t) \qquad \text{(Equation 11)}$$

where the effect of presynaptic spikes at time $t - \tau$ on postsynaptic rates is characterized by the

interaction kernels in the matrix $K(\tau)$ and depends on the elapsed time τ. In the steady state where the

expectation value of the rate $\lambda_j(t)$ was not dependent on time (i.e.., $\text{E}[\mathbf{\Lambda}(t)] = \mathbf{\Lambda}$), we approximated

Equation 11 as $\mathbf{\Lambda} = \mathbf{\Lambda}_0 + \left(\int_{-\infty}^{\infty} K(\tau)d\tau\right)\mathbf{\Lambda}$ or $\mathbf{\Lambda} = \left(1 - \int_{-\infty}^{\infty} K(\tau)d\tau\right)^{-1}\mathbf{\Lambda}_0$. Let $\mathbf{W} = \int_{-\infty}^{\infty} K(\tau)d\tau$, In light of the

linear response theory, we rewrote the cross-correlation of neuronal population activity as $\mathbf{C} =$

$(\mathbf{I} - \mathbf{W})^{-1}\text{diag}(\mathbf{\Lambda}_0)(\mathbf{I} - \mathbf{W})^{-T}$. Based on the matrix inverse property $(\mathbf{I} - \mathbf{W})^{-1} = 1 + \mathbf{W} + \mathbf{W}^2 + \cdots$, without

loss of generality, we assumed the rate $\mathbf{\Lambda}_0$ as an all-one vector and derived an approximate form of $\mathbf{C}$

using the first four lower-order expansion terms:

$$\mathbf{C}_{\text{approx}} = \mathbf{W} + \mathbf{W}^T + \mathbf{W}\mathbf{W}^T + \mathbf{W}^T\mathbf{W} + \cdots. \qquad \text{(Equation 12)}$$

Therefore, the correlation of neuronal activity is influenced by the sum of a set of connection motifs.

Replacing **W** of Equation 12 with $\mathbf{W}^{\text{eff}}$, and changing MD presynaptic connectivity $\mathbf{W}^{\text{MD}\to\text{PFC}}$ provides a

way to test how presynaptic feedforward MD input may affect postsynaptic recurrent PFC connection

motifs and correlation.

744
745
Data and code availability

747 All the data that supports the plots within this paper and other findings of this study are available.
748 (https://github.com/Xh-Zhang1/pfc-md).

750
751
References

1. Uddin, L.Q. Cognitive and behavioural flexibility: neural mechanisms and clinical considerations.
Nat Rev Neurosci **22,** 167-179 (2021).
2. Bach, D. R., Dolan, R. J. Knowing how much you don't know: a neural organization of uncertainty
estimates. *Nat. Rev. Neurosci.* **13**, 572-586 (2012).
3. Fetsch, C. R., Pouget, A., DeAngelis, G. C., Angelaki, D. E. Neural correlates of reliability-based
cue weighting during multisensory integration. *Nat. Neurosci.* **15,** 146-154 (2012).
4. Zhou, Y., Acerbi, L., Ma, W. J. The role of sensory uncertainty in simple contour integration. *PLoS
Comput. Biol.* **16,** e1006308 (2020).
5. Mukerjee A, Lam NH, Wimmer RD, Halassa MM. Thalamic circuits for independent control of
prefrontal signal and noise. *Nature*, **600,** 100-104 (2021).
6. Rikhye RV, Gilra A, Halassa MM**.** Thalamic regulation of switching between cortical
representations enables cognitive flexibility. *Nat. Neurosci.* **21,** 1753-1763 (2018).
7. O'Neill, M., Schultz, W. Coding of reward risk by orbitofrontal neurons is mostly distinct from
coding of reward value. *Neuron* **68**, 789-800 (2010).
8. Marton TF, Seifikar H, Luongo FJ, et al. Roles of prefrontal cortex and mediodorsal thalamus in
task engagement and behavioral flexibility. *J. Neurosci.* **38**, 2569-2578 (2018).
9. Bolkan SS, Stujenske JM, Parnaudeau S, Spellman TJ, Rauffenbart C, Abbas AI, Harris AZ,
Gordon JA, Kellendonk C. Thalamic projections sustain prefrontal activity during working memory
maintenance. *Nat. Neurosci.* **20,** 987-996 (2017).
10. Halassa MM, Kastner S. Thalamic functions in distributed cognitive control. *Nat. Neurosci.* **20,**
1669-1679 (2017).
11. Wolff M, Vann S.D. The cognitive thalamus as a gateway to mental representations. *J. Neurosci.*
39, 3-14 (2019).
12. Chakraborty S, Kolling N, Walton ME, & Mitchell AS. Critical role for the mediodorsal thalamus in
permitting rapid reward-guided updating in stochastic reward environments. *eLife* **5,** e13588
(2016).
13. Parnaudeau S, Bolkan SS, Kellendonk C. The mediodorsal thalamus: an essential partner of
prefrontal cortex for cognition. *Biol. Psychiatry* **83,** 648-656 (2018).
14. DeNicola AL, Park M-Y, Crowe DA, MacDonald 3rd AW, Chafee MV. Differential roles of
mediodorsal nucleus of the thalamus and prefrontal cortex in decision-making and state
representation in a cognitive control task measuring deficits in schizophrenia. *J. Neurosci.* **40,**
1650-1667 (2020).
15. Kosciessa, J.Q., Lindenberger, U., Garrett, D.D. Thalamocortical excitability modulation guides
human perception under uncertainty. *Nat. Commun.* **12,** 2430 (2021).
16. Grinband, J., Hirsch, J. & Ferrera, V. P. A neural representation of categorization uncertainty in
the human brain. *Neuron* 49, 757-763 (2006).
17. Schmitt LI, Wimmer RD, Nakajima M, Happy M, Mofakham S, Halassa MM. Thalamic
amplification of cortical connectivity sustains attentional control. *Nature* **545,** 219-223 (2017).
18. Alcaraz F, Fresno V, Marchand AR, Kremer EJ, Coutureau E, Wolff M. Thalamocortical and
corticothalamic pathways differentially contribute to goal-directed behaviors in the rat. *eLife* **7**,
e32517 (2018).

19. Hertag L, Sprekeler H. Amplifying the redistribution of somato-dendritic inhibition by the interplay
of three interneuron types. *PLoS Comp. Biol.* **15,** e1006999 (2019).
20. Keller AJ, Dipoppa M, Roth MM, et al. A disinhibitory circuit for contextual modulation in primary
visual cortex. *Neuron*, **108,** 1181-1193 (2020).
21. Pulvermüller, F., Tomasello, R., Henningsen-Schomers, M.R. et al. Biological constraints on
neural network models of cognitive function. *Nat. Rev. Neurosci.* **22,** 488-502 (2021).
22. Jaramillo J, Mejias JF, Wang X-J. Engagement of pulvino-cortical feedforward and feedback
pathways in cognitive computations. *Neuron*, **101,** 321-336 (2019).
23. Song, H.F., Yang, G.R., Wang, X.-J. Training excitatory-inhibitory recurrent neural networks for
cognitive tasks: A simple and flexible framework. *PLoS Comput. Biol.* **12,** e1004792 (2016).
24. Zhang, X., Liu, S., Chen, Z.S. A geometric framework for understanding dynamic information
integration in context-dependent computation. *iScience*, **24,** 102919 (2021).
25. Zhang X, Long X, Zhang S-J, Chen Z.S. Excitatory-inhibitory recurrent dynamics produced robust
visual grids and stable attractors. *Cell Rep.*, **41**, 111777 (2022).
26. Xue, X., Wimmer, R.D., Halassa, M.M., Chen, Z.S. Spiking recurrent neural networks represent
task-relevant neural sequences in rule-dependent computation. *Cogn. Comput.* **15,** 1167-1189
(2023).
27. Mante, V., Sussillo, D., Shenoy, K. et al. Context-dependent computation by recurrent dynamics
in prefrontal cortex. *Nature* **503,** 78-84 (2013).
28. Orhan, A.E., Ma, W.J. A diverse range of factors affect the nature of neural representations
underlying short-term memory. *Nat. Neurosci.* **22,** 275-283 (2019).
29. Hummos A, Wang BA, Drammis S, Halassa MM, Pleger B. Thalamic regulation of frontal
interactions in human cognitive flexibility. *PLoS Computat. Biol.* **18,** e1010500 (2022).
30. Pi, HJ., Hangya, B., Kvitsiani, D. et al. Cortical interneurons that specialize in disinhibitory control.
Nature **503,** 521-524 (2013).
31. Wood KC, Blackwell JM, Geffen MN. Cortical inhibitory interneurons control sensory processing.
Curr. Opin. Neurobiol. **46,** 200-207 (2017).
32. Tao HW, Li Y-T, Zhang LI. Formation of excitation-inhibition balance: inhibition listens and
changes in tune. *Trends Neurosci.* **37,** 528-530.
33. Ferguson BR, Gao W-J. Thalamic control and social behavior via regulation of gamma-
aminobutyric acidergic signaling and excitation/inhibition balance in the medial prefrontal cortex.
Biol. Psychiatry, **83,** 657-669 (2018).
34. Contractor, A., Ethell, I.M., Portera-Cailliau, C. Cortical interneurons in autism. *Nat Neurosci* **24,**
1648-1659 (2021).
35. Fu Y, Tucciarone JM, Espinosa JS, et al. A cortical circuit for gain control by behavioral state. *Cell*
156, 1139-1152 (2014).
36. Halassa MM, Sherman SM. Thalamocortical circuit motifs: a general framework. *Neuron*, **103,**
762-770 (2019).
37. Roy DS, Zhang Y, Halassa MM, Feng G. Thalamic subnetworks as units of function. *Nat.*
Neurosci. **25,** 140-153 (2022).
38. Shine, J.M., Müller, E.J., Munn, B., et al. Computational models link cellular mechanisms of
neuromodulation to large-scale neural dynamics. *Nat Neurosci* **24,** 765-776 (2021).
39. Izhikevich EM, Edelman GM. Large-scale model of mammalian thalamocortical systems. *Proc.*
Natl. Acad. Sci. USA, **105,** 3593-3598 (2008).
40. Krishnan GP, Ghauvette S, Shamie I, et al. Cellular and neurochemical basis of sleep stages in
the thalamocortical network. *eLife*, **5,** e18607 (2016).
41. Quax S, Jensen O, Tiesinga P. Top-down control of cortical gamma-band communication via
pulvinar induced phase shifts in the alpha rhythm. *PLoS Comput Biol* **13,** e1005519 (2017).
42. Levenstein D, Alvarez VA, Amarasingham A, et al. On the role of theory and modeling in
neuroscience. *J. Neurosci.* **43**, 1074-1088 (2023).
43. Anastasiades PG, Collins DP, Carter AG. Mediodorsal and ventromedial thalamus engage
distinct L1 circuits in the prefrontal cortex. *Neuron*, **109,** 314-330 (2021).
44. Logiaco L, Abbott LF, Escola S. Thalamic control of cortical dynamics in a model of flexible motor
sequencing. *Cell Rep.* **35,** 109090 (2021).
45. Kao TC, Sadabadi MS, Hennequin G. Optimal anticipatory control as a theory of motor
preparation: A thalamo-cortical circuit model. *Neuron* **109,** 1567-1581 (2021).

46. Hattori, R., Kuchibhotla, K., Froemke, R. et al. Functions and dysfunctions of neocortical inhibitory neuron subtypes. *Nat. Neurosci*. **20,** 1199-1208 (2017).

47. Guet-McCreight A, Skinner FK, Topolnik L. Common principles in functional organization of VIP/Calretinin cell-driven disinhibitory circuits across cortical areas. *Front. Neural Circuits*, **14,** 32 (2020).

48. Delevich K, Tucciarone J, Huang ZJ, Li B. The mediodorsal thalamus drives feedforward inhibition in the anterior cingulate cortex via parvabumin interneurons. *J. Neurosci*. **35,** 5743-5753 (2015).

49. Delevich K, Jaaro-Peled H, Penzo M, Sawa A, Li B. Parvalbumin interneuron dysfunction in a thalamo-prefrontal cortical circuit in Disc1 locus impairment mice. *eNeuro* **7,** ENEURO.0496-19.2020 (2020).

50. Sohal VS, Zhang F, Yizhar O, Deisseroth K. Paravalbumin neurons and gamma rhythms enhance cortical circuit performance. *Nature*, **459,** 698-702 (2009).

51. Lewis, D., Hashimoto, T., Volk, D. Cortical inhibitory neurons and schizophrenia. *Nat. Rev. Neurosci*. **6,** 312-324 (2005).

52. Dienel SJ, Lewis DA. Alterations in cortical interneurons and cognitive function in schizophrenia. *Neurobiol. Dis*. **131,** 104208 (2019).

53. Nakajima M, Halassa MM. Thalamic control of functional cortical connectivity. *Curr. Opin. Neurobiol*. **44,** 127-131 (2017).

54. Rikhye RV, Wimmer RD, Halassa MM. Toward an integrative theory of thalamic function. *Ann. Rev. Neurosci*. **41,** 163-183.

55. Vander Weele, C.M., Siciliano, C.A., Matthews, G.A. et al. Dopamine enhances signal-to-noise ratio in cortical-brainstem encoding of aversive stimuli. *Nature* **563,** 397-401 (2018).

56. Mininni, C.J., Caiafa, C.F., Zanutto, B.S., et al. Putative dopamine neurons in the ventral tegmental area enhance information coding in the prefrontal cortex. *Sci. Rep.* **8,** 11740 (2018).

57. Garcia-Cabezas MA, Martinez-Sanchez P, Sanchez-Gonzalez MA, et al. Dopamine innervation in the thalamus: monkey versus rat. *Cereb. Cortex* **19,** 424-434 (2009).

58. Winterer G, Weinberger DR. Genes, dopamine and cortical signal-to-noise ratio in schizophrenia. *Trends Neurosci*. **27,** 683-690 (2004).

59. Ferguson BR, Gao W-J. Development of thalamocortical connectivity between the mediodorsal thalamus and the prefrontal cortex and its implication in cognition. *Front. Hum. Neurosci*. **8,** 1027 (2014).

60. Kohn A, Jasper AI, Semedo JD, Gokcen E, Machens CK, Yu BM. Principles of corticocortical communication: proposed schemes and design considerations. *Trends Neurosci.* **43,** 725-737 (2020).

61. DeNicola AL, Park M-Y, Crowe DA, MacDonald 3[rd] AW, Chafee MV. Differential roles of mediodorsal nucleus of the thalamus and prefrontal cortex in decision-making and state representation in a cognitive control task measuring deficits in schizophrenia. *J. Neurosci.* **40,** 1650-1667 (2020).

62. Murray JD, Anticevic A. Toward understanding thalamocortical dysfunction in schizophrenia through computational models of neural circuit dynamics. *Schizophr. Res.* **180,** 70-77 (2017).

63. Mukherjee A, Halassa MM. The associative thalamus: a switchboard for cortical operations and a promising target for schizophrenia. *The Neuroscientist.* (2022) doi:10.1177/10738584221112861

64. Ouhaz Z, Flemming H, Mitchell AS. Cognitive functions and neurodevelopmental disorders involving the prefrontal cortex and mediodorsal thalamus. *Front. Neurosci.* **12,** 33 (2018).

65. Benoit, L.J., Holt, E.S., Posani, L. et al. Adolescent thalamic inhibition leads to long-lasting impairments in prefrontal cortex function. *Nat. Neurosci.* **25,** 714-725 (2022).

66. Bulin SE, Hohl KM, Paredes D, Silva JD, Morilak DA. Bidirectional optogenetically-induced plasticity of evoked responses in the rat prefrontal cortex can impair or enhance cognitive set-shifting. *eNeuro* **7,** ENEURO.0363-19.2019 (2019).

67. Rajakumar A, Rinzel J, Chen ZS. Stimulus-driven and spontaneous dynamics in excitatory-inhibitory recurrent neural networks for sequence representation. *Neural Computat.* **33,** 2603-2645 (2021).

68. Asllani M, Lambiotte R, Carletti T. Structure and dynamical behavior of non-normal networks. *Science Adv.* **4,** sciadv.aau9403 (2018).

905 69. Spitmaan M, Seo H, Lee D, Soltani A. Multiple timescales of neural dynamics and integration of
906    task-relevant signals across cortex. *Proc. Natl. Acad. Sci. USA* **117,** 22522-22531 (2020).
907 70. Le Merre P, Ährlund-Richter S, Carlén M. The mouse prefrontal cortex: Unity in diversity. *Neuron.*
908    **109,** 1925-1944 (2021).

Acknowledgements

We thank N. Lam, A. Mukherjee, R.D. Wimmer and Y. Liu for valuable comments on the manuscript. The work was supported by grants MH118928 (Z.S.C.), DA056394 (Z.S.C.), MH132642 (Z.S.C. and M.M.H.) from the US National Institutes of Health. We thank the Conte Center Team for scientific input and inspiration on cognitive thalamus. A preliminary version of this work has appeared in BioRxiv preprint (https://biorxiv.org/cgi/content/short/2022.12.11.519975v1) and was presented in COSYNE'23.

Author contributions

Z.S.C. conceived and supervised experiments, analyzed and interpreted the data, and wrote the paper. X.Z. developed the computational models, performed experiments, analyzed and interpreted the data. M.M.H. provided experimental data and interpreted the data. Z.S.C. acquired funding.

Competing interests

The authors declare no competing interests.

FIGURE LEGENDS

Figure 1. The task-optimized PFC-MD model in decision making with sensory uncertainty.
(**a**) Excitation-inhibition (E/I) recurrent neural network (RNN) for modeling the PFC-alone network, where three major prefrontal interneuron cell types were specified. The PFC-MD model consisted of two target-specific non-recurrent excitatory MD subpopulations and bidirectional MD-PFC projections.
(**b**) Schematic of a cross-modal, context-dependent decision-making task with working memory and divided attention components. Sensory cues were either conflicting LP/HP pulses or moving random dots.
(**c**) Schematic of context-dependent rule encoding. The RDM and CAC subtasks learned the same rule: attend-to-audition vs. attend-to-vision.
(**d**) Psychometric curves of RDM and CAC subtasks. Error bar was shown in mean ± s.e.m. Each condition was repeated 10 times with different input realizations yet with identical summary statistics. The PFC-MD model outperformed the PFC-alone model in the presence of intermediate-to-high cue conflict.
(**e and f**) Percentage of task error types in two subtasks under various cue uncertainty conditions.
(**g**) Illustration of three types of cues with two congruence levels and two densities in the CAC subtask.
(**h**) Psychometric curve of the PFC-MD model under three different cue sparsity levels in the CAC subtask.
(**i**) Psychometric curve comparison between the PFC-MD and PFC-alone models in the CAC subtask in one cue sparsity condition.
(**j**) Illustration of three types of cues with two coherence levels and two densities in the RDM subtask.
(**k**) Psychometric curve of the PFC-MD model under three different cue sparsity levels in the RDM subtask. (**l**) Psychometric curve comparison between the PFC-MD and PFC-alone models in the RDM subtask in one cue sparsity condition.

Figure 2. Neural representations of PFC and MD units from the task-optimized PFC-MD network.

(**a**) Two representative PFC excitatory units encoding two rules under two contexts. These two units were cue invariant units that encoded the same rule.

(**b**) Two representative PFC inhibitory units encoding the cueing context.

(**c**) Two representative MD units encoding context but not rule.

(**d**) Population statistics of mean firing rates (during the task delay period) of excitatory PFC units and MD units for encoding rule.

(**e**) Population statistics of mean firing rate (during the task delay period) of excitatory PFC units and MD units for encoding context.

(**f**) Two representative MD_1 units that showed firing rate modulation with respect to cue uncertainty during both cueing and delay periods.

(**g**) The same MD_1 units also showed firing rate modulation with respect to cue sparsity.

(**h**) Two representative PFC inhibitory units that showed firing rate modulation with respect to cue uncertainty during both cueing and delay periods.

(**i**) Prefrontal neural sequences showed rule specificity and context invariance. Each heatmap shows the normalized peri-stimulus time histogram (PSTH) of selected prefrontal excitatory units of the task-optimized PFC-MD model during the delay period. In the first row, all units of all panels were sorted by the same order according to attend-to-vision tuning. In the second row, all units of all panels were sorted by the same order according to attend-to-audition tuning. The first and second columns demonstrated rule specificity, whereas the first and third columns demonstrated context invariance.

(**j**) Population decoding analysis showed that the PFC population better encoded rule, whereas the MD population better encoded context. Error bar denotes s.e.m. (n=20).

(**k**) Increased in cue uncertainty caused decreased rule decoding accuracy for the PFC, but did not affect context decoding accuracy for the MD. Error bar denotes SD (n=20). In rule decoding, all paired comparisons were statistically significant (P<7×10^{-8}, two-tailed Wilcoxon rank-sum tests).

Figure 3. Population representations from the task-optimized PFC-MD model.

(**a**) Dynamics of population responses in the CAC subtask. The average population trajectory for a given condition and time was represented as a point in the state space. Responses from correct trials only were shown from the cue onset to the end of target period (80-ms step size), and were projected into the two-dimensional subspace capturing the variance according to the rule (attend-to-audition vs. attend-to-vision) and choice (see Methods). Units are arbitrary. The origin represents the cue onset.

(**b**) Similar to (**a**), except only during the cueing period. For a better illustration, three levels of cue uncertainty were shown by different shades of grey or blue color (dark/intermediate/light shade: low/medium/high cue uncertainty, respectively).

(**c**) Similar to (**b**), except for a fixed cue uncertainty but different levels of cue sparsity. Three levels of sparsity were shown by different shades of grey or blue color (dark/intermediate/light shades: low/medium/high sparsity, respectively).

(**d-f**) Similar to (**a-c**) but for the RDM subtask.

(**g and h**) Comparison of neural velocity during both cueing and delay periods for different levels of cue uncertainty for the CAC and RDM subtasks, respectively. The change of neural activity reduced to a low level during the delay period, reaching a fixed-point regime.

(**i**) Fixed-point analysis in the three-dimensional PCA subspace revealed two "line-attractor-like" basins, with each basin representing a rule. Each cross symbol corresponded to a fixed point (color sorted by cue uncertainty). The red origin represents the cue onset. Inset: rotating the view angle and collapsing these points revealed two "fixed-point-like" attractors.

Figure 4. MD enhances working memory maintenance in the PFC-MD network.

(a) Increasing the duration of task delay period reduced the task performance under cue uncertainty in both subtasks. Figure legend denotes the level of cue coherence or congruence. Error bar denotes SD (n=10). The task condition marked with " " was used in the illustrations of three remaining panels.

(b and c) Increasing the MD_1 or MD_2 population firing rate during an elongated delay period improved the working memory and the psychometric curve in both subtasks. Black curve denotes the baseline, and the number of % denotes the relative increase in subpopulation firing rate.

(d) Weakening $MD_1 \rightarrow PV$ connections (by increasing the percentage of zeros) during the cueing period quickly reduced the task performance in both RDM and CAC subtasks. Inset: increasing MD_1 activity could rescue each subtask performance under a wide range of connectivity conditions (shaded area: 20%-50% of zeros). Error bar denotes SD (n=10).

(e) Weakening $MD_2 \rightarrow PV$ connections only degraded the task performance slowly in both RDM and CAC subtasks, but increasing MD_2 activity had no effect on the change in task performance (see inset).

Figure 5. Parsing cognitive deficits and probing mechanistic causes in the PFC-MD networks.

(A) During the control condition, PFC excitatory units (4 selected units are indicated by different colors) preserved rule tunings in both delay and target periods (left panel). Mean firing rate (FR) comparison of PFC excitatory units between two rules in delay (middle panel) and target (right panel) periods. Four units in the left panels are labeled in the same color in both middle and right panels.

(**B**) In the presence of E/I imbalance (e.g., reduced inhibition), PFC excitatory units shown in (**A**) increased their firing rates but decreased their rule discriminability during the target period.

(**C**) Two-dimensional neural trajectory representations in control and E/I imbalance conditions. Trajectories were generated from all correct and error trials. Orange dots: cue off and start of delay period. Blue and red end points represent two rule representations, whereas dot and star symbols represent left and right choices, respectively.

(D) The task performance decreased with reduced prefrontal SOM$\rightarrow$VIP and SOM$\rightarrow$PV connectivity.

(E) Increasing the mutual inhibition strength between SOM and VIP neurons amplified the gain under a high cue sparsity. Stimulating the $MD_2\rightarrow$VIP pathway further facilitated the amplification and improved the task performance. Two shaded circles indicate the conditions illustrated in (**F**).

(F) In the case of RDM task of (**E**) (with cue sparsity 0.8), comparison of PFC excitatory unit tunings and two-dimensional neural trajectories between scale=1 (light gray, baseline) and scale = 1.2 for bidirectional SOM-VIP connection strengths. In the latter case, single-unit rule tunings emerged and population responses improved rule discriminability.

Figure 6. Modified PFC-MD model with additional sparse corticothalamic connectivity.
(**a**) The modified PFC-MD model that assumed unbalanced MD subpopulations (as shown by two
different circle sizes) and sparser Exc→MD_2 connectivity than Exc→MD_1 connectivity (as shown by a
thinner connection).
(**b**) The psychometric curves of task-optimized modified PFC-MD model in two subtasks. Error bar was
shown in mean $\pm$ s.e.m. (n=10 realizations).
(**c**) Population statistics of mean firing rates (during the cue period) of MD_1 and MD_2 units for encoding
cue uncertainty and cue sparsity.
(**d and e**) MD_1 stimulation, but not MD_2 stimulation, improved task performance under cue uncertainty.
MD_1 or MD_2 stimulation improved task performance under cue sparsity. Error bar denotes SD (n=10). Cue
uncertainty comparison during the RDM (CAC) subtask: baseline vs. MD_2 stimulation, P=0.82 (0.16);
baseline vs. MD_1 stimulation, P=0.00016 (0.00016); MD_2 vs. MD_1 stimulation, P=0.00016 (0.00043). Cue
sparsity comparison during the RDM (CAC) subtask: baseline vs. MD_2 stimulation, P=0.00016 (0.00016);
baseline vs. MD_1 stimulation, P=0.00016 (0.00016); MD_2 vs. MD_1 stimulation, P=0.045 (0.017), two-tailed
Wilcoxon rank-sum tests.
(**f**) When both cue uncertainty and cue sparsity were present, MD_1 or MD_2 stimulation alone couldn't
improve task performance, but simulation of both MD subpopulations could. Baseline vs. stimulation both,
*, P=0.011; ***, P= 0.00015, two-tailed Wilcoxon rank-sum tests. Other paired comparisons were n.s.
1056
1057
1058
1059

Figure 7. Thalamocortical plasticity in the PFC-MD model enabled context switching to tackle mapping uncertainty.

(**a**) Schematic diagram of the context-switching task (Context 1→Context 2→Context 1').

(**b**) Relative learning speed in context switching, where neural plasticity of local MD-PFC connectivity was induced in trial-by-trial learning of Context 2 and Context 1'. Error bar denotes s.e.m. (n=10).

(**c**) Heatmap of connectivity of MD (MD_1 and MD_2) to prefrontal excitatory (Exc) units. Let W denote the MD-to-Exc connection matrix, units were sorted based on the change of $\Delta W = W_{context\ 2} - W_{context\ 1}$. According to the synaptic change ΔW, PFC excitatory units were mapped to two functional cell types: rule tuned (red and blue) vs. non-tuned (green) units.

(**d**) Tuning curve examples of rule tuned (blue) and non-tuned (green) PFC units. Shaded area denotes the task delay period.

(**e**) PFC excitatory units showed context-invariant rule-specific sequential activity during the delay period. Each row of the heatmap corresponded to the normalized trial-averaged firing activity. Units were sorted based on the location of peak firing rates and ranked in the same order in all six panels.

(**f**) The E/I input of PFC excitatory units during the task delay period were clustered according to the PFC rule tuning properties when the PFC-MD network succeeded to learn the context switch (left). The cluster structure was lost when the PFC-MD network failed to learn the context switch (right). Units are color coded using the same color scheme based on rule-tuned (red and blue) or non-tuned (green) property in (**C**).

(**g**) Quantification of average plasticity in bilateral MD-PFC connections during context switching.

(**h**) MD units showed context-invariant firing. Note that some MD units (overlaid "×" symbols) preserved their mean firing rates during the delay period between Context 1 and Context 1'.

(**i**) Turning curve illustrations of one MD unit during context switching. Shaded area denotes the task delay period. Notice the strong context modulation between different contexts, but little modulation with respect to the rule.

(**j**) A subset of MD units (n=8 out of 30 from one trained PFC-MD model) showed increased modulation with respect to decision error during the transient switching stage. The MD firing rate was averaged across the delay period where the change of network state was very small (i.e., steady state). Tuning curves of one MD were shown on the top.

(**k**) Comparison of neural trajectories of PFC population dynamics during cueing and delay periods between conditions where the PFC-MD succeed and failed to learn the context switch. Trajectories were color coded to represent time from the cue onset to the end of delay.

1096
Figure 8. Theoretic insight from computational modeling of the PFC-MD circuit in context-dependent decision making.
(**a**) Schematic summary of cell type and task-phase specific regulatory roles of MD thalamus in decision making under sensory uncertainty.
(**b**) Differential assumptions of intracortical, thalamocortical and corticothalamic connectivity had a direct impact on the MD unit tuning in task-optimized PFC-MD models.
(**c**) Comparison of relative context switch time with different sizes of MD population. All time was normalized with respect to the baseline (MD size of 32). Error bar denotes s.e.m. (n=10).
(**d**) Ratio of explained variance of PFC and MD populations derived from the task-optimized PFC-MD model. Our computer simulations and principal component analysis (PCA) showed that the recurrent PFC structure had a larger intrinsic dimensionality than the feedforward MD structure.
(**e**) Estimated time constant from the nonlinear dynamical systems under different thalamocortical connectivity manipulations. These results suggest that the MD could "slow down" prefrontal dynamics by increasing the time constant for improving information integration during cueing or working memory period. The MD_1 and MD_2 enhancement corresponded to the experiments where respective thalamocortical connections were strengthened during working memory.
(**f**) Comparison of relative context switch time with different assumptions of modifiable connectivity during switch. In the top, unilateral or bilateral PFC, MD and input connectivity is shown ($\varnothing$ denotes no connectivity). In total, there are five unidirectional connections that can be adapted. In the bottom, all time in the y-axis was normalized with respect to the baseline (unchanged intracortical connectivity). Error bar denotes s.e.m. (n=10).
(**g**) Schematic illustration of the MD's role in context switch during cue-to-rule remapping, and the PFC is illustrated as a bistable attractor.
(**h**) Two-dimensional (2D) vector field that illustrates the bistable PFC dynamics as an approximate line attractor. The diagonal dotted line represents an attractor boundary for neutral stimuli (e.g., LP=HP). Rotating the 2D vector field by 180 degrees is equivalent to switching the cue-to-rule transformation while preserving the PFC dynamics.
(**i**) Comparison of PFC population dynamics under *Context 1* and *Context 2* while projecting them onto the same PCA subspace. The neural trajectories were nearly orthogonal to each other. Each color trace represents a single trial with specific cue input (LP>HP or LP<HP). Light to dark color represents the time evolution of the trial.
(**j**) Left panel: Comparison of neural trajectories of PFC dynamics in *Context 1*, *Context 2* with successful context switching, and *Context 2* with unsuccessful context switching. Middle panel: Comparison of neural trajectories of PFC dynamics in *Context 2* with successful context switching and *Context 2* with MD_2 lesion. Right panel: Comparison of neural trajectories of PFC dynamics in *Context 2* with MD_2 lesion and *Context 2* with MD_2 lesion plus MD_1 stimulation.

Figure 1. **The task-optimized PFC-MD model in decision making with sensory uncertainty.**

Figure 2. **PFC and MD single-unit modulation in the performance-optimized PFC-MD model.**

Figure 3. **Population representations from the task-optimized PFC-MD model.**

Figure 4. **MD enhances working memory maintenance in the PFC-MD network.**

Figure 5. **Parsing cognitive deficits and probing mechanistic causes in the PFC-MD networks.**

Figure 6. **Modified PFC-MD model with additional sparse corticothalamic connectivity.**

Figure 7. **Thalamocortical plasticity in the PFC-MD model enabled context switching to tackle mapping uncertainty.**

Figure 8. **Theoretic insight from computational modeling of the PFC-MD circuit in context-dependent decision making.**