Laminar Neural Dynamics of Auditory Evoked Responses:

Computational Modeling of Local Field Potentials in Auditory Cortex

of Non-Human Primates

Vincent S.C. Chien[1], Peng Wang[1,2,3], Burkhard Maess[1], Yonatan Fishman[4], Thomas R. Knösche[1]

[1] Max Planck Institute for Human Cognitive and Brain Sciences, Germany

[2] Institute of Psychology, University of Greifswald, Germany

[3] Institute of Psychology, University of Regensburg, Germany

[4] Departments of Neurology and Neuroscience, Albert Einstein College of Medicine, USA

Abstract

Evoked neural responses to sensory stimuli have been extensively investigated in humans and animal models both to enhance our understanding of brain function and to aid in clinical diagnosis of neurological and neuropsychiatric conditions. Recording and imaging techniques such as electroencephalography (EEG), magnetoencephalography (MEG), local field potentials (LFPs), and calcium imaging provide complementary information about different aspects of brain activity at different spatial and temporal scales. Modeling and simulations provide a way to integrate these different types of information to clarify underlying neural mechanisms.

In this study, we aimed to shed light on the neural dynamics underlying auditory evoked responses by fitting a rate-based model to LFPs recorded via multi-contact electrodes which simultaneously sampled neural activity across cortical laminae. Recordings included neural population responses to best-frequency (BF) and non-BF tones at four representative sites in primary auditory cortex (A1) of awake monkeys. The model considered major neural populations of excitatory, parvalbumin-expressing (PV), and somatostatin-expressing (SOM) neurons across layers 2/3, 4, and 5/6. Unknown parameters, including the connection strength between the populations, were fitted to the data. Our results revealed similar population dynamics, fitted model parameters, predicted equivalent current dipoles (ECD), tuning curves, and lateral inhibition profiles across recording sites and animals, in spite of quite different extracellular current distributions. We found that PV firing rates were higher in BF than in non-BF responses, mainly due to different strengths of tonotopic thalamic input, whereas SOM firing rates were higher in non-BF than in BF responses due to lateral inhibition.

In conclusion, we demonstrate the feasibility of the model-fitting approach in identifying the contributions of cell-type specific population activity to stimulus-evoked LFPs across cortical laminae, providing a foundation for further investigations into the dynamics of neural circuits underlying cortical sensory processing.

Keywords*: auditory processing, cortical microcircuits, lateral inhibition, neural mass model*

1 Introduction

Neural responses to sensory stimuli have been extensively studied in order to elucidate how the brain represents features of the environment. Evoked responses are a specific kind of *event-related* signal that reflect (mostly electrical) brain activity in response to stimuli, such as tactile impulses, images, or sounds. In humans, cortical evoked responses can be recorded noninvasively via electroencephalography (EEG) and magnetoencephalography (MEG), which are widely used methodologies for probing brain function in health and disease. In order to draw valid and informative conclusions from these noninvasively recorded signals, it is important to understand the neural mechanisms underlying their generation. The cortical sources of EEG and MEG are thought to be intracellular currents primarily associated with postsynaptic potentials in pyramidal neurons (Lopes da Silva, 2013; Næss et al., 2021; Vaughan H.G.Jr, 1988). Pyramidal neurons and interneurons constitute multiple distinct populations in different layers of the cortex, which are locally and globally interconnected in a recurrent fashion. Already at the local level, these recurrent networks implement important functions (e.g., Chien et al., 2019; Hahn et al., 2022; Kunze et al., 2019). In order to eventually map the observed evoked responses onto these functions, it is crucial to obtain detailed information about how various neuronal cell types and synaptic connections contribute to their generation.

Invasive studies in animal models can contribute substantially to this aim by allowing the recording/imaging of layer-specific local field potentials (LFP) and cell-type specific neural firing (see Sections 1.1 and 1.2). Such animal model studies have already provided considerable information about lamina-specific neural activity (Bruyns-Haylett et al., 2017; Hajizadeh et al., 2019, 2021, 2022; Kohl et al., 2022; Neymotin et al., 2020; Sumner et al., 2021) and enhanced our understanding of the functional roles of various types of inhibitory interneurons in cortical processing (Aponte et al., 2021; Blackwell & Geffen, 2017; Liu et al., 2019; Liu & Kanold, 2021; Studer & Barkat, 2022). However, to

more thoroughly elucidate the underlying neural generators of evoked responses and their

relationship with information processing in the brain, it is necessary to mechanistically link together

the available information about cell types and local neuronal circuits in the brain, intracranially-

recorded LFPs, and extracranially-measured EEG and MEG signals. This task requires computational

models. Although several efforts in this direction have been made (see Section 1.3), most modeling

studies, such as spiking-based single-column models or rate-based multi-column models, are limited

by being purely forward simulations without fitting the models to actual recordings of brain activity

(e.g., LFPs and EEG/MEG), leaving their proposed theories less mechanistically and empirically

grounded.

1.1 Layer-specific data - local field potentials

Linear-array multi-channel electrodes are a unique methodological tool which allows the simultaneous

recording of LFPs across cortical layers (e.g., Fishman et al., 2001; Schroeder et al., 1998;

Steinschneider et al., 2003). The high spatial resolution of LFPs provides valuable information

regarding the intracranial generators of event-related potentials/fields (ERPs/ERFs) and information

flow within and across cortical layers. Multi-unit activity (MUA), which can be extracted from high-

frequency components of LFPs, reflects the spiking of local neuron populations in the vicinity of each

electrode contact. Current source density (CSD), the second spatial derivative of the LFPs, provides

information about the net transmembrane currents that give rise to the measured LFPs (Mitzdorf,

1985; Pitts, 1952). MUA and CSD provide complementary insights into the dynamics of activity within

local neural circuits, as MUA primarily reflects suprathreshold neuronal firing (output), while CSD

primarily reflects current flow associated with synaptic input, such as excitatory and inhibitory post-

synaptic potentials (EPSPs/IPSPs). However, the disentanglement of meaningful functional

components of MUA and CSD derived from trans-laminar LFP signals is an ill-posed problem. MUA

contains spikes originating from different populations of excitatory and inhibitory neurons, and CSD

is a spatial mixture of extracellular sinks and sources that can be either active (i.e., synaptic activity)

or passive (i.e., return currents). Excitatory synaptic activity results in an active sink and a passive

source, whereas inhibitory synaptic activity results in an active source and a passive sink. Moreover,

the interpretation of activity (especially CSD) at later latencies is more uncertain due to the

involvement of long-range cortical inputs (Happel et al., 2010). So far, evoked CSD and MUA have

been extensively used to characterize tuning curves (Fishman et al., 2000a, 2000b; Fishman &

Steinschneider, 2006, 2009; Steinschneider et al., 1998), differentiate responses to different stimuli

(e.g., best-frequency [BF] vs. non-BF and standard vs. deviant) (Fishman & Steinschneider, 2012;

Lakatos et al., 2020; O'Connell et al., 2011; Schaefer et al., 2015), and compare local neural

population responses in different brain regions (e.g., core vs. belt regions of auditory cortex) (Banno

et al., 2022). Statistical analyses in these studies mostly focused on neuronal activity occurring at

specific latencies (usually within 50ms) in specific cortical layers (usually layer 4 or 2/3). An alternative

approach, called laminar population analysis (LPA), was proposed to decompose the recorded LFP

and MUA into firing rates of multiple neural populations and corresponding spatial profiles (Einevoll

et al., 2007; Głąbska et al., 2014; Głąbska et al., 2016). However, the extracted components were

only mapped to excitatory populations, and the connections between populations were indirectly

estimated by a template-fitting analysis. In short, despite the high spatial specificity provided by LFPs

and CSD analysis, our understanding of the information flow within neural circuits that give rise to

these recorded signals is limited by the underdetermined inverse problem (Tenke & Kayser, 2012).

1.2 Cell type-specific activity in auditory cortex

Calcium imaging and optogenetic techniques make it possible to observe the activity of specific

neuron types in auditory cortex. The activity of pyramidal cells is actively shaped by inhibitory

interneurons (Liu et al., 2019). The major inhibitory interneuron types have specific characteristics

with regard to morphology, targets, electrophysiology, and plasticity (Studer & Barkat, 2022), and

appear to play distinct functional roles in cortical information processing (Blackwell & Geffen, 2017).

Parvalbumin-expressing (PV) interneurons are fast-spiking neurons and mostly show higher spontaneous and tone-evoked firing rates than excitatory neurons. They target the soma, proximal dendrites, and initial segment of the axon of excitatory neurons, providing efficient and strong inhibition to excitatory neurons within the cortical column (a radius of up to 130 µm). PV interneurons receive inputs from both local excitatory neurons and the thalamus (MGBv). Functionally, PV interneurons are thought to contribute to the balance of excitation and inhibition and to the control of bottom-up (feedforward) information flow (Hamilton et al., 2013). Somatostatin-expressing (SOM) interneurons, on the other hand, show lower spontaneous and tone-evoked firing rates than PV interneurons. They target the distal dendrites of excitatory neurons, and their inhibition can reach widely (a radius of up to 300 µm) along the tonotopic axis. SOM interneurons receive excitatory inputs mainly within the cortex and much less from the thalamus (Ji et al., 2016). The synapses from excitatory neurons to SOM interneurons are short-term facilitating, whereas many other classes of synapses (e.g., the excitatory synapses between pyramidal cells and fast-spiking PV neurons) are short-term depressing (Hayut et al., 2011). SOM interneurons show slower activation dynamics and wider lateral inhibition than PV interneurons, which suggests a functional role of SOM neurons in integrating information over temporal and spectral domains (Yavorska & Wehr, 2016). PV and SOM interneurons mutually inhibit each other (Walker et al., 2016; Yavorska & Wehr, 2016). Both PV and SOM interneurons are inhibited by vasoactive-intestinal-peptide-expressing (VIP) interneurons which provide cross-modal modulation of sensory coding (Bigelow et al., 2019). The interaction among these various types of interneurons (with different time scales in spiking pattern and plasticity) can lead to complex dynamics and may implement specific neural computations. Modeling approaches provide a good way to identify the functional roles of each type of interneuron. For example, Park and Geffen built minimal rate-based and spiking models that incorporate a simple PV-SOM compensating mechanism to account for experimental findings in auditory studies, such as stimulus-specific adaptation, forward suppression, and tuning-curve adaptation (Park & Geffen, 2020). Hahn and colleagues used a rate-based mean-field modeling approach to study the interaction between

pyramidal cells as well as SOM, PV, and VIP interneurons in different layers, which implements

ultrasensitive switches toggling pyramidal neurons between high and low firing rate states associated

with oscillations in distinct frequency bands (Hahn et al., 2022). Specifically, the pyramidal upstate is

dominated by PV mediated high-frequency (gamma) activity, while the downstate is characterized by

SOM mediated low-frequency (beta) oscillations.

1.3 Existing biological models

Biological models have been used to bridge the gap between microscopic properties (e.g., neuron

types, single-unit neurophysiology, and morphology) and meso-/macroscopic observations (e.g.,

LFP/EEG/MEG signals). These models vary in their level of detail and scope. For example, a single-

column model of the primary visual cortex (consisting of excitatory and inhibitory neurons in layers

2/3, 4, 5, and 6) was constructed to simulate laminar LFPs under different input conditions (Hagen et

al., 2016, 2018). A single-column model of the primary auditory cortex (consisting of E, PV, SOM, VIP,

and Neurogliaform cells in six layers) was recently constructed to simulate LFP, CSD, and EEG

signals that replicate many experimental observations such as spontaneous neural activity and

evoked responses to speech input (Dura-Bernal et al., 2022). Such detailed single-column models

predict the contribution of layer- and cell-type-specific neuronal populations when the simulations

match experimental observations. Some other, less detailed, models have been constructed to

account for the generation of evoked responses. A single-column model (consisting of excitatory and

inhibitory neurons in layers 2/3 and 5) using Human Neocortical Neurosolver suggests the contribution

of a sequence of bottom-up thalamic inputs (targeting the soma of pyramidal neurons and causing

upward currents) and top-down cortical inputs (targeting dendrites of pyramidal neurons and causing

downward currents) (Kohl et al., 2022; Lakatos et al., 2020). This single-column model relates the

ERP/ERF to intracellular currents in pyramidal long dendrites but leaves the origins of the sequences

of inputs unexplained. This issue was addressed by a rate-based core-belt-parabelt model that

includes an entire network of brain regions comprising auditory cortex (208 cortical columns, each

column consisting of one excitatory and one inhibitory population), where ERFs are considered as the weighted sum of spatially distributed damped harmonic oscillators emerging out of coupled excitation and inhibition (Hajizadeh et al., 2019, 2021, 2022). This model provides a holistic perspective on the generation of ERFs. However, the proposed damped modes are extractions from the whole network dynamics, which can be difficult to link with LFP observations for validation. There remain several principal shortcomings in modeling evoked responses. On the one hand, models that take into account neuronal details (e.g., various types of inhibitory neurons) seemingly lack sufficient consideration of inter-column or inter-area interaction. On the other hand, models that focus on network dynamics and mechanisms currently provide less information about the role of different inhibitory neurons, and the simulations only qualitatively match the LFP/EEG/MEG recordings. Hence, there is a need for biological models that incorporate both a high degree of detail and a broad scope to clarify the neural underpinnings of cortical evoked responses.

1.4 Goals and approach of this study

In this study, we attempt to overcome the above-mentioned limitations by developing a multi-column model of auditory cortex with sufficient detail regarding neural populations and their interconnections to quantitatively reproduce layer-specific intracranial LFP recordings and qualitatively explain extracranially observable evoked responses. We utilized a biological cortical column model accounting for cell-type-specific interactions, which was integrated into a minimalistic multi-column array, representing the most relevant aspects of cortical architecture with respect to the tonotopic processing of auditory stimuli. Model parameters were specified by fitting the model to LFPs of tone-evoked responses simultaneously recorded across the layers of primary auditory cortex (A1) of awake monkeys. We show that the proposed model not only consistently replicates and explains detailed features of tone-evoked LFPs in A1, but also reproduces relevant aspects of extracranially-recorded evoked responses and predicts cell-type specific contributions to these signals.

2 Methods

2.1 Experimental data

2.1.1 Acquisition and preprocessing

Neurophysiological data were obtained from A1 in 3 adult male macaque monkeys (Macaca fascicularis) using previously described methods (Fishman & Steinschneider, 2010; Steinschneider et al., 2003). All experimental procedures were reviewed and approved by the Association for Assessment and Accreditation of Laboratory Animal Care-accredited Animal Institute of Albert Einstein College of Medicine and were conducted in accordance with institutional and federal guidelines governing the experimental use of non-human primates. Animals were housed in our Association for Assessment and Accreditation of Laboratory Animal Care-accredited Animal Institute under daily supervision of laboratory and veterinary staff. Before surgery, monkeys were acclimated to the recording environment and were trained to perform a simple auditory discrimination task (see below) while sitting in custom-fitted primate chairs.

Surgical procedure. Under pentobarbital anesthesia and using aseptic techniques, rectangular holes were drilled bilaterally into the dorsal skull to accommodate epidurally placed matrices composed of 18-gauge stainless steel tubes glued together in parallel. Tubes served to guide electrodes toward A1 for repeated intracortical recordings. Matrices were stereotaxically positioned to target A1 and were oriented to direct electrode penetrations perpendicular to the superior surface of the superior temporal gyrus, thereby satisfying one of the major technical requirements of one-dimensional current source density (CSD) analysis (Müller-Preuss & Mitzdorf, 1984; Steinschneider et al., 1992). Matrices and Plexiglas bars, used for painless head fixation during the recordings, were embedded in a pedestal of dental acrylic secured to the skull with inverted bone screws. Perioperative and

postoperative antibiotic and anti-inflammatory medications were always administered. Recordings

began after at least 2 weeks of postoperative recovery.

Stimuli. Stimuli were generated and delivered at a sample rate of 48.8 kHz by a PC-based system

using an RX8 module (Tucker Davis Technologies). Frequency response functions (FRFs) derived

from responses to pure tones characterized the spectral tuning of the cortical sites. Pure tones used

to generate the FRFs ranged from 0.15 to 18.0 kHz, were 200 ms in duration (including 10 ms linear

rise/fall ramps), and were randomly presented at 60 dB SPL with a stimulus onset-to-onset interval of

658 ms. Resolution of FRFs was 0.25 octaves or finer across the 0.15–18.0 kHz frequency range

tested. All stimuli were presented via a free-field speaker (Microsatellite; Gallo) located 60 degrees

off the midline in the field contralateral to the recorded hemisphere and 1 m away from the animal's

head (Crist Instruments). Sound intensity was measured with a sound level meter (type 2236; Bruel

and Kjaer) positioned at the location of the animal's ears. The frequency response of the speaker was

flat (within 5 dB SPL) over the frequency range tested.

Recordings. Neurophysiological recordings were conducted in an electrically shielded, sound-

attenuated chamber. Monkeys were monitored via video camera throughout each recording session.

To promote alertness and attention to the sounds during the recordings, animals performed a simple

auditory discrimination task (detection of a randomly presented noise burst interspersed among test

stimuli) to obtain liquid rewards.

Local field potentials (LFPs) and multiunit activity (MUA) were recorded using linear-array multi-

contact electrodes, comprising 16 contacts, evenly spaced at 150-micron intervals (U-Probe; Plexon).

Individual contacts were maintained at an impedance of 200 kΩ. An epidural stainless-steel screw

placed over the occipital cortex served as the reference electrode. Neural signals were bandpass

filtered from 3 Hz to 3 kHz (roll-off 48 dB/octave) and digitized at 12.2 kHz using an RA16 PA Medusa

16-channel preamplifier connected via fiber-optic cables to an RX5 data acquisition system (Tucker-Davis Technologies). LFPs time-locked to the onset of the sounds were averaged on-line by computer to yield auditory evoked potentials (AEPs). CSD analyses of the AEPs characterized the laminar distribution of net current sources and sinks within A1 and were used to identify the laminar location of concurrently recorded AEPs and MUA (Steinschneider et al., 1992, 1994). CSD was calculated using a 3-point algorithm that approximates the second spatial derivative of voltage recorded at each recording contact (Freeman & Nicholson, 1975; Nicholson & Freeman, 1975). MUA used to characterize the frequency tuning of each recording site (i.e., electrode penetration) was derived from the spiking activity of neural ensembles recorded within lower lamina 3, as identified by the presence of a large-amplitude initial current sink that is balanced by concurrent superficial sources in mid-upper lamina 3 (Fishman et al., 2001; Steinschneider et al., 1992). This current dipole configuration is consistent with the synchronous activation of pyramidal neurons with cell bodies and basal dendrites in lower lamina 3. Previous studies have localized the initial sink to the thalamorecipient zone layers of A1 (Metherate & Cruikshank, 1999; Müller-Preuss & Mitzdorf, 1984; Steinschneider et al., 1992; Sukov & Barth, 1998). To derive MUA, neural signals (3 Hz to 3 kHz pass-band) were high-pass filtered at 500 Hz (roll-off 48 dB/octave), full-wave rectified, and then low-pass filtered at 520 Hz (roll-off 48 dB/ octave) before averaging of single-trial responses (for a methodological review, see Supèr & Roelfsema, 2005). MUA (referred to as MUA_E in Supèr & Roelfsema, 2005) is a measure of the envelope of summed (synchronized) action potential activity of local neuronal ensembles (Brosch et al., 1997; O'Connell et al., 2011; Schroeder et al., 1998; Supèr & Roelfsema, 2005; Vaughan H.G.Jr, 1988). Thus, whereas firing rate measures are typically based on threshold crossings of neural spikes, MUA, as derived here, is an analog measure of spiking activity in units of response amplitude (e.g., see Kayser et al., 2007). MUA and single-unit activity, recorded using electrodes with an impedance similar to that in the present study, display similar orientation and frequency tuning in primary visual and auditory cortex, respectively (Kayser et al., 2007; Supèr & Roelfsema, 2005). Adjacent neurons in A1 (i.e., within the sphere of recording for MUA) display synchronized responses with similar

spectral tuning, a fundamental feature of local processing that may promote high-fidelity transmission

of stimulus information to subsequent cortical areas (Atencio & Schreiner, 2013).

Positioning of electrodes was guided by online examination of click-evoked AEPs. Pure tone stimuli

were delivered when the electrode channels bracketed the inversion of early AEP components and

when the largest MUA and initial current sink were situated in middle channels. Evoked responses to

40 presentations of each pure tone stimulus were averaged with an analysis time of 500 ms that

included a 100 ms pre-stimulus baseline interval. The BF of each cortical site was defined as the pure

tone frequency eliciting the maximal MUA within a time window of 0-75 ms after stimulus onset. As it

was very consistent across layers (see Fig. S1), we used, for each recording site, the electrode

channel with the maximum MUA for BF determination. The response time window includes the

transient "On" response elicited by sound onset and the decay to a plateau of sustained activity in A1

(e.g., see (Fishman & Steinschneider, 2009)).

The neural responses to pure tones were acquired at the beginning of each recording session, after

which the animals participated in at least three different auditory experiments. Finally, the monkeys

were deeply anesthetized with sodium pentobarbital and transcardially perfused with 10% buffered

formalin. Tissue was sectioned in the coronal plane (80-μm thickness) and stained for Nissl substance

to reconstruct the (Morel et al., 1993) electrode tracks and to identify A1 according to previously

published physiological and histological criteria (Kaas & Hackett, 2000; Merzenich & Brugge, 1973;

Morel et al., 1993). Based upon these criteria, all electrode penetrations considered in this report were

localized to A1, although the possibility that some sites situated near the low-frequency border of A1

were located in field R cannot be excluded.

2.1.2 Preparation for model fitting

The target data for model fitting are comprised of the laminar MUA and CSD profiles of evoked

responses to the best frequency (BF, see an example in Fig. 1) and 4 non-BF tones at four recording

sites (site 1 from monkey A, site 2 from monkey D, sites 3 and 4 from monkey E). The 4 sites were

selected because they display stereotypical features of laminar AEP, MUA, and CSD

neurophysiological response profiles which are characteristic of primary auditory cortex (A1), as

described in previous publications by various investigators (Fishman, 2014; Fishman et al., 2000b;

O'connell et al., 2014). Moreover, the different BFs of these sites lie within the frequency range of

maximum hearing sensitivity in macaques. Hence, we regard these sites as representative of

population responses in A1, which are well-suited for the computational modeling of auditory cortical

responses. See Fig. S2 for further details. For each recording site, the experimental data (BF and 4

non-BF responses) were cropped (time window: 0 to 200 ms, 200 timepoints), concatenated along

the time axis and normalized to their maximum peak, resulting in a target MUA matrix [1000 timepoints

× 16 channels] and a target CSD matrix [1000 timepoints × 12 channels] for model fitting.

Figure 1. Laminar profiles of evoked responses to a BF tone recorded in a representative electrode

penetration into A1. The 16-channel electrode array records local field potentials (LFPs) from

superficial to deep layers (2000 µm), from which current source density (CSD) and multi-unit activity

(MUA) are derived. A schematic of the electrode array is shown on the left of the figure. For

visualization, the values of response amplitude are also color-coded (positive values in blue; negative

 values in red). Tone onset and offset times are indicated by the vertical drop lines.

2.2 Cortical column model

The cortical model consists of two columns. Each column contains 7 neural populations identified by

cell type and laminar location of their cell bodies: excitatory pyramidal neurons (L2/3 E, L4 E, and

L5/6 E), inhibitory PV interneurons (L2/3/4 PV and L5/6 PV), and inhibitory SOM interneurons (L2/3/4

SOM and L5/6 SOM). Each neural population is described by a rate-to-potential operator (Section

2.2.4) and a potential-to-rate operator (Section 2.2.5) as in the Jansen-Rit model (Jansen & Rit, 1995).

Different types of inhibitory interneurons were considered because of their distinct characteristics

regarding morphology, connection motif, target neurons/locations, plasticity, spiking rate, synaptic

time constant, and afferent inputs (Studer & Barkat, 2022), making it likely that they differentially

contribute to the observed MUA and CSD. Thus, the model was designed with the aim of

reconstructing the dynamics of different interneuron types from the LFP data. To reduce model

complexity, VIP interneurons were not included, as VIP interneurons are thought to be involved in

cortico-cortical interaction and neuromodulatory control (Mesik et al., 2015). We would like to note

that, within our model framework, the number of neural populations is flexible, and its modification

would only lead to different degrees of granularity in the spatiotemporal decomposition of MUA and

CSD. In the model, we merge neurons into L2/3, L4, and L5/6 to characterize the dynamics at the

spatial resolution of supragranular, granular, and infragranular layers.

As illustrated in Fig. 2A, column 1 represents the recording site, which does not necessarily respond

optimally to the presented frequency (non-BF site), while column 2 (BF site) represents a location

(cortical column) that responds optimally to the presented tone stimulus. For simplicity, the

configurations of the two columns were set to be identical, and the two columns inhibit each other

through symmetric inter-column E-to-SOM connections. The E and PV populations receive direct

thalamic input with a fixed ratio based on the literature (see Section 2.2.2). Column 2 (BF site) receives

the full strength of thalamic input (in=1), and column 1 (recording site) receives weaker input (in≤1),

based on the tonotopic organization of the auditory pathway. The two-column model is a simplification

of the anatomical and functional organization of A1, where the interactions with other cortical areas

(e.g., non-primary fields of auditory cortex) are not considered. In the case of the BF response, both

columns receive the same input strength (in=1), as they represent the same location and inter-column

connections are in fact intra-column connections. This way, the same model could be used for both

BF and non-BF situations.

The model simulates the time series of latent variables including firing rates, postsynaptic potentials

(PSP), and connectivity efficacy (related to short-term plasticity) under BF and non-BF conditions

given the same model parameter settings but different input configurations. As illustrated in Fig. 2B,

the network dynamics are transformed into simulated MUA and CSD via a forward model (see Section

2.3) to match the target data. The forward model also transforms network dynamics to a simulated

equivalent current dipole (ECD) signal, which is equivalent (up to a scaling factor determined by the

volume conduction of the head) to EEG/MEG signals. Thus, the model could be used to identify the

specific contributions of different cell types to those signals.

Figure 2. Two-column cortical model and forward simulation. (A) The model consists of two identical

columns, where Column 1 represents the cortical area at the recording site, and Column 2 represents

the latent cortical area that responds most strongly to the presented tonal stimulus (at the BF). The

thalamic inputs make synaptic connections with the E and PV populations at L2/3, L4, and L5/6. The

lateral inhibition consists of the connections from L5/6 E to the SOM populations at L2/3 and L5/6.

For clarity, intra-column connections are not shown. Different line widths and circle sizes indicate the

difference in connection strength and contribution to MUA, respectively (details in Tables 1 and 5). (B)

The forward simulation includes two stages. First, the network dynamics are simulated based on the

model parameters and input configurations under BF and non-BF conditions at the recording site.

Second, the observation model translates firing rates and current flows to the observations (i.e., MUA

and CSD) through the spatial profiles calculated by constrained least square fit. The current flows and

CSD can be further translated to dipole signals as model predictions.

355   2.2.1 Thalamic input

356   The thalamic input $i_{th}(t)$ to the two-column model is a decay function with a delay (Eq. (1)). The

357   parameters include thalamic input strength I, decay time constant τ_{in}, decay level α, and delay t_d.

358   This is to mimic the fast decaying firing rate observed in the auditory system (Pérez-González &

359   Malmierca, 2014).

$$i_{th}(t) = \begin{cases} I\left[\alpha + (1-\alpha)e^{\frac{t_d - t}{\tau_{in}}}\right], & t \geq t_d \\ 0, & t < t_d \end{cases} \tag{1}$$

2.2.2 Connectivity

The intra-column connectivity is derived from the reported connection probabilities and synaptic

strengths in the primary visual cortex of mice (Billeh et al., 2020). The calculation is illustrated in Fig.

3, while the exact connectivity values can be found in the supplementary Table S1. The connectivity

is grouped into default connectivity matrices W_{EE}, W_{PE}, W_{SE}, W_{EP}, W_{PP}, W_{SP}, W_{ES}, and W_{PS}, which

can then be separately rescaled by free parameters θ_{1-8} in the optimization. For example, the 2-by-

3 matrix W_{PE} (connections from E1, E2, and E3 to P1 and P2) is rescaled by θ_2. The inter-column

connections only consist of E-to-SOM connections $W_{inter-SE}$ (from E2 in column 1 to SOM1 and

SOM2 in column 2, and vice versa), which can be rescaled by parameters θ_{20-24} that control the

strength of lateral inhibition under BF and non-BF conditions. The scaling parameters also allow

accounting for potential discrepancies between the intra- and inter-columnar connectivity between

mice and primates. Including inter-column E-to-E connections $W_{inter-EE}$ does not significantly

improve model performance and the resulting parameters (as shown in supplementary Fig. S3 that

tests variant models), so we decided to keep the model simple.

Figure 3. Default intra-column connectivity. (A, B) The connection probabilities and synaptic strengths

are taken from (Billeh et al., 2020)*. The numbers in the parentheses stand for the cortical layers. (C,*

D) The probabilities and strengths are merged by averaging into coarser layers matching our model

definitions. (E) The default intra-column connectivity is defined as the product of probabilities and

strengths. Matrices A to E are normalized for visualization. (F) The default intra-column connectivity

is visualized in a graph where the edge widths discretize the normalized connectivity values in matrix

F. Values above 1/2 have the thickest edges, while values lower than 1/16 are not shown in the graph.

For detailed values of connection probabilities, synaptic strengths, and connectivity, please refer to

supplementary Table S1.

The thalamic input is fed only to E and PV populations. The input connectivity across layers (as listed

in Table 1) is based on the normalized peak amplitude of thalamocortical responses and the laminar

pattern of thalamocortical innervation in mouse primary auditory cortex reported in (Ji et al., 2016).

The default thalamic input connectivity matrices W_{Eth} and W_{Pth} refer to connections from the

thalamus to E1, E2, and E3, and to PV1 and PV2, respectively, which can be rescaled by parameters

$\theta_{9,10}$ in the optimization.

392   *Table 1. Thalamic input connectivity across laminar layers (normalized to E3).*

Neural population	(a) Normalized peak amplitude	(b) % Innervated	(a*b) Input connectivity
E1 (L2/3)	129/418=0.3	75%	0.225
E3 (L4)	418/418=1	100%	1
E2 (L5/6)	163/418=0.4	85%	0.34
PV1 (L2/3/4)	615/418=1.47	85%	1.25
PV2 (L5/6)	426/418=1.02	100%	1.02

393   *(a) Thalamocortical input currents (pA). Source: Table 1 in* (Ji et al., 2016)*.*

394   *(b) Percentage of cells exhibiting thalamocortical responses. Source: Figure 4 in* (Ji et al., 2016)*.*

2.2.3 Rate-to-potential operator

The rate-to-potential operator implements the transformation of the firing rate $r_j(t)$ of the *j*th

population to the postsynaptic potential $v_{ij}(t)$ at the *i*th population through an effective connection

strength $w_{ij}(t)$. This transformation is achieved by convolving the weighted firing rate $w_{ij}(t)r_j(t)$ with

a synaptic kernel $h_{ij}(t)$ (Eq. (2), as in Chien et al., 2019; Jansen & Rit, 1995; Wang & Knösche,

2013). Note that the effective connection strength $w_{ij}(t)$ can become a variable, if short-term

plasticity is taken into account (see Section 2.2.5).

$$v_{ij}(t) = \left[w_{ij}(t)r_j(t)\right] \otimes h_{ij}(t) \tag{2}$$

403   The synaptic kernel $h(t)$ is described as a bi-exponential function parameterized by the scaling factor

404   H and the time constants τ_1 and τ_2 (Eq. (3)).

$$h(t) = \begin{cases} H \dfrac{\tau_1 \tau_2}{\tau_1 - \tau_2} \left(e^{\frac{-t}{\tau_1}} - e^{\frac{-t}{\tau_2}} \right), & t \geq 0 \\ 0, & t < 0 \end{cases} \tag{3}$$

406   The convolution in Eq. (2) can be numerically realized by two first-order ordinary differential equations

407   (Eqs. (4) and (5)).

$$\dot{v}(t) = u(t) \tag{4}$$

$$\dot{u}(t) = Hw(t)r(t) - \frac{\tau_1 + \tau_2}{\tau_1 \tau_2} u(t) - \frac{1}{\tau_1 \tau_2} v(t) \tag{5}$$

409   The shape of synaptic kernels depends on pre- and postsynaptic properties of the neurotransmitter-

410   receptor systems, and the respective parameters H, τ_1, and τ_2 are listed in Table 2.

412   *Table 2. Parameters of the synaptic-dendritic kernels for different connections.*

Synaptic type		H	τ_1(ms)	τ_2(ms)	Reference
E→E[1]	AMPA	14400	1	5.3	(Dura-Bernal et al., 2022)
	NMDA	1200	3	70	
E→PV	NMDA	7250	2.1	5.6	(Jouhanneau et al., 2018)
E→SOM	NMDA	3090	4.5	25.2	(Jouhanneau et al., 2018)
PV→E	GABA$_A$	-4000	1	18.2	(Dura-Bernal et al., 2022)
PV→PV	GABA$_A$	-5530	3.5	5.5	(Bacci et al., 2003)
PV→SOM	GABA$_A$	-7380	1.4	101	(Bacci et al., 2003)
SOM→E[2]	GABA$_A$	-1800	2	100	(Dura-Bernal et al., 2022)
	GABA$_B$	-100	25	300	
SOM→PV	GABA$_A$	-1800	2	100	(Dura-Bernal et al., 2022)

(1) AMPA:NMDA=83:17
(2) GABA$_A$:GABA$_B$=50:50

The PSPs $v(t)$ are then used to calculate the current flows $c(t)$. In Eq. (6), a current flow $c_j(t)$
caused by the *j*th input source (from a cortical or a thalamic input) is calculated as the sum of the

absolute values of PSPs $v_{ij}(t)$ at all E populations ($N_E = 3$) at the recording site (i.e., Column 1).

The mapping to MUA and CSD is illustrated in Fig. 4.

$$c_j(t) = \sum_i^{N_E} |v_{ij}(t)| \tag{6}$$

421   2.2.4 Potential-to-rate operator

422   The potential-to-rate operator transforms the overall PSP $v_i(t)$ at the *i*th population into mean firing

423   rate $r_i(t)$ using a sigmoid function (Eqs. (7) and (8)). The overall PSP is the sum of EPSPs and

424   IPSPs caused by N_{cur} presynaptic current sources which include N_{pop} excitatory/inhibitory

425   populations and thalamic input.

$$r_i(t) = Sigm[v_i(t)] = Sigm\left[\sum_j^{N_{cur}} v_{ij}(t)\right] \tag{7}$$

$$Sigm(v) = \begin{cases} \dfrac{1}{1 + e^{r(v_0 - v)}} - \dfrac{1}{1 + e^{rv_0}}, & v \geq 0 \\ 0, & v < 0 \end{cases} \tag{8}$$

The output firing rate is limited to $0 \leq r(t) \leq 1$, where $r = 1$ refers to the max firing rate of the

E/PV/SOM neuron type. The sigmoid function is shifted so that $Sigm(0) = 0$, meaning no change in

the firing rate relative to baseline. To make the fitting process more stable, negative firing rates are

set to 0. The sigmoid functions for the E, PV, and SOM populations have different slopes r and

thresholds v_0 (as listed in Table 3) based on the firing characteristics of the neuron types reported

in (Fanselow et al., 2008).

 Table 3. Parameters of the sigmoid functions

	r (mV^{-1})	v_0 (mV)
E	0.62	6
PV	0.29	15.6
SOM	1.14	2.76

2.2.5 Short-term plasticity

Short-term plasticity (STP) refers to the modulation of synaptic strength based on the history of presynaptic activity. STP can be depressing (STD) or facilitating (STF), which depends on the synaptic type (Blackman et al., 2013; Fino et al., 2013; Ma et al., 2012; Regehr, 2012; Silberberg et al., 2005). STD can be modeled by a synaptic efficacy variable x $(0 \leq x \leq 1)$, which denotes the fraction of remaining neurotransmitters (or synaptic vesicles). STF can be modeled by another synaptic utilization variable u $(0 \leq u \leq 1)$ which denotes the neurotransmitters ready for use (release probability) (Silberberg & Markram, 2007). The two variables then modulate the fixed connection strength w_0 as in Eq. (9).

$$w(t) = x(t)u(t)w_0 \tag{9}$$

The variables $u(t)$ and $x(t)$ depend on the presynaptic firing rate $r(t)$ as in Eqs. (10) and (11). The parameter U is the initial release probability, and parameters τ_f and τ_d denote the decay and recovery time constants, respectively. The parameters κ_f and κ_d are the change rates and are tuned in the optimization procedure.

$$\dot{u}(t) = \frac{U - u(t)}{\tau_f} - \kappa_f U[1 - u(t)]r(t) \tag{10}$$

$$\dot{x}(t) = \frac{1 - x(t)}{\tau_d} - \kappa_d u(t)x(t)r(t) \tag{11}$$

The effect of STP on the dynamics of a network of E, PV, and SOM populations has been studied by

Hayut and colleagues (Hayut et al., 2011). Among the eight synaptic types, only E-to-SOM

connections exhibit STF, while the remaining connections exhibit STD. To simplify the model, we only

consider STF on E-to-SOM connections and STD on E-to-E connections in the model. These are two

most prominent presynaptic plasticities in the neocortex reported in (Kalisman et al., 2005; Silberberg

et al., 2005; Silberberg & Markram, 2007). The parameters of STP are based on (Hayut et al., 2011;

Silberberg & Markram, 2007). See Table 4 for details.

Table 4. Parameters of short-term plasticity.

	U	τ_f (ms)	τ_d (ms)	κ_f	κ_d
E→E	1	-	200	0	20*
E→SOM	0.05	670	-	600*	0

*Note: Values marked by * are default values that will be rescaled by free parameters.*

2.3 Observation model

The observation model includes two spatial profiles which map the network dynamics to MUA and

CSD. To match the target data, the network dynamics are subsampled to $T = 200$ timepoints (i.e.,

firing rates r into S_{rate} [$N_{pop} \times T$], and current flows c into $S_{current}$ [$N_{cur} \times T$], where $N_{pop} = 7$

populations, and $N_{cur} = 8$ input sources.

Figure 4. Forward mapping from network dynamics to observations. (A) The simulated MUA (simMUA) is the sum of individual firing rates (left column) weighted by the non-negative MUA spatial profile (middle column) of the recording site (Column 1). (B) The simulated CSD (simCSD) is the sum of individual current flows (left column) weighted by the CSD spatial profile (middle column) of the recording site (Column 1). (C) The simulated equivalent current dipole (simECD) is the sum of individual current flows (left column) weighted by dipole directions and lengths (red arrows in the middle column) derived from the CSD spatial profile (gray color in the middle column).

2.3.1 Spatial profiles

The MUA spatial profile A_{MUA} $[N_{ch} \times N_{pop}]$ describes the sensitivity of channels ($N_{ch} = 16$) to the firing rates of neural populations (see Section 2.3.2), which is closely related to the spatial distribution of cell bodies (or axonal hillocks, where the spikes are generated). The simulated MUA Φ_{MUA} $[N_{ch} \times T]$ is the multiplication of the mixing matrix A_{MUA} and the firing rates S_{rate} (Eq. (12)).

$$\Phi_{MUA} = A_{MUA} \cdot S_{rate} \tag{12}$$

486 The CSD spatial profile A_{CSD} $[N_{ch'} \times N_{cur}]$ describes the sensitivity of the spatial distribution of sinks

487 and sources along the channels ($N_{ch'} = 12$) to the current flows. The simulated CSD Φ_{CSD} $[N_{ch'} \times T]$

488 is the multiplication of the mixing matrix A_{CSD} and the current flows $S_{current}$ (Eq. (13)).

$$\Phi_{CSD} = A_{CSD} \cdot S_{current} \tag{13}$$

2.3.2 Constraints on the spatial profiles

Both spatial profiles A_{MUA} and A_{CSD} are difficult to determine by measurements. They are estimated

by constrained regression of the network dynamics S_{rate} and $S_{current}$ to the target data Φ_{MUA}^{ref} and

Φ_{CSD}^{ref}. The goal is to find spatial profiles that minimize the distance between simulation Φ and target

Φ^{ref}, while, at the same time, obeying certain plausibility constraints.

The constraint on the MUA spatial profile A_{MUA} $[N_{ch} \times N_{pop}]$ is based on the fact that the sensitivity to

the firing rate of a certain cell type is proportional to the product of cell density and maximal firing rate.

Therefore, the ratio of the column sums of A_{MUA} should be fixed (Table 5). This is a relatively coarse

constraint where the laminar distribution of cell density is not considered.

Table 5. Constraint of MUA spatial profile

Neural population	(a) Proportion of neurons (Keller et al., 2018; Rudy et al., 2011)	(b) Maximal firing rate (Beierlein et al., 2003)	(a*b) Contribution to MUA (normalized to E1)
E1, E2, and E3	1/3 of 80%	59.4 Hz	1
PV1 and PV2	1/2 of 20%*40%	271.7 Hz	0.69
SOM1 and SOM2	1/2 of 20%*30%	120.7 Hz	0.23

The constraint on the CSD spatial profile A_{CSD} [$N_{ch'} \times N_{cur}$] is based on the fact that the

transmembrane currents should be conserved. This means, the sources and the sinks need to match.

Therefore, each column of A_{CSD} should add up to zero (i.e., area of sinks = area of sources).

Additionally, in order to avoid ambiguity with the overall current magnitudes, the norms of all column

vectors of A_{CSD} are constrained to be the same.

2.3.3 Equivalent current dipole

The neuronal generators of EEG/MEG signals are commonly estimated as equivalent current dipoles

(ECDs) by source localization techniques such as dipole fitting and beamforming. The simulated

ECDs provide a theoretical link between LFPs and EEG/MEG signals, by which we can also examine

the contribution of E, PV, and SOM populations to event-related deflections, like P1, N1, and N2.

The model predicts Φ_{ECD} [$1 \times T$] at the recording site once current flows $S_{current}$ and a CSD spatial

profile A_{CSD} are given. As in Eq. (14), Φ_{ECD} is calculated as the multiplication of $\bar{d}$ [$1 \times N_{cur}$] and the

current flows $S_{current}$ [$N_{cur} \times T$], where $\bar{d}$ is the displacement from the mean center of sinks $\bar{d}_{sink}$ to

the mean center of sources $\bar{d}_{source}$ derived from each column of A_{CSD} [$N_{ch'} \times N_{cur}$].

$$\Phi_{ECD} = \bar{d} \cdot S_{current} = \left(\bar{d}_{source} - \bar{d}_{sink} \right) \cdot S_{current} \qquad (14)$$

2.4 Optimization procedure

In general, we use a genetic searching scheme (Eiben & Smith, 2015; García-Martínez et al., 2018;

Katoch et al., 2021) combined with a gradient descent (Gauss-Newton) method to optimize the 28

free parameters θ within a predefined search range (Table 6), in order to minimize the cost function

$f(\theta)$ for each recording site. Since the cost function has a complicated shape with multiple local

minima, we made use of the assumption that the true solutions should yield similar parameters across

recording sites. In order to reliably find these solutions, we iteratively continued the search for each

recording site starting at the solutions for all other recording sites. If our assumption is correct, this

should lead to better fits for the individual recording sites.

Note that this additional similarity criterion is only used to guide the search for the solutions, while the

sole criteria for the goodness of fit are the cost functions for the individual recording sites. The

optimization scheme is detailed in Fig. 5.

The cost function $f(\theta)$ is defined as the sum of squared errors (SSE) between the simulation $\Phi(\theta)$

and target Φ^{ref} (Eq. (15)). The target data Φ^{ref} comprises Φ_{MUA}^{ref} and Φ_{CSD}^{ref} under BF and non-BF

conditions. The benefit of including non-BF conditions in the optimization procedure is two-fold. First,

the amount of target data is increased while the degrees of freedom of spatial profiles remain the

same, which reduces the risk of overfitting. Second, the dynamics of PV and SOM populations under

BF vs. non-BF conditions can be compared.

$$f(\theta) = \left\| \Phi(\theta) - \Phi^{ref} \right\|_2^2 = \sum_i \sum_j \left(\phi_{ij}(\theta) - \phi_{ij}^{ref} \right)^2 \tag{15}$$

The simulated data $\Phi(\theta)$ of an individual recording site comprises of $\Phi_{MUA}(\theta)$ and $\Phi_{CSD}(\theta)$ as in

Eqs. (12) and (13). The forward simulation includes two stages. In the first stage, the default two-

column model and input configuration are rescaled by 28 free parameters θ to generate network

dynamics S_{rate} and $S_{current}$. The 28 free parameters θ rescale intra-column connections W_{EE},

W_{PE}, W_{SE}, W_{EP}, W_{PP}, W_{SP}, W_{ES}, and W_{PS} (θ_{1-8}), thalamic input connectivity matrices W_{Eth} and

W_{Pth} ($\theta_{9,10}$), rates of short-term plasticity $\kappa_{d,EE}$ and $\kappa_{f,SE}$ ($\theta_{11,12}$), synaptic time constants τ (θ_{13}),

slopes of sigmoid functions r (θ_{14}), thalamic input decay levels α_{1-5} for BF and non-BF conditions

(θ_{15-19}), lateral inhibition $W_{inter-SE}$ for BF and non-BF conditions (θ_{20-24}), and thalamic input

strengths to column 1 for non-BF conditions (θ_{25-28}). We chose a reasonably larger range for

connectivity-related free parameters ($\theta_{1-10,20-24}$) to allow enough flexibility of network dynamics. We

chose a narrower range for the rest of the free parameters to adhere to the evidence from the literature.

The search ranges of the 28 free parameters are summarized in Table 6. In the second stage, the

spatial profiles A_{MUA} and A_{CSD} are optimized by regressing the resulting network dynamics S_{rate}

and $S_{current}$ to the target Φ_{MUA}^{ref} and Φ_{CSD}^{ref}, respectively. Multiplication of spatial profiles with network

dynamics then yields the predicted MUA and CSD, which can be compared to the observed MUA and

CSD.

We use the Gauss-Newton (gn) method to approach the minimum of the cost function $f(\theta)$ in Eq.

(15). This method was successfully used in our previous studies for optimization of neural mass

models with large numbers of free parameters (Wang et al., 2019; Wang & Knösche, 2013). The

Jacobian matrix $J = \frac{\partial f}{\partial \theta}$ is numerically approximated with Newton's difference quotient.

The genetic search scheme (see Fig. 5) includes three operating boxes for broadening the exploration

in parameter space. In the 'mutation' box, the solutions are sorted based on the goodness-of-fit (cost).

Then, each parameter of a solution can mutate (i.e., be replaced by a random value) with a chance

that linearly ranges from 10% (for best fit case) to 90% (for worst fit case) based on the ranking of the

solution.

In the 'cross-over' box, we randomly draw two solutions as parent solutions from the outputs of

'selection' and 'mutation' boxes. Then we randomly decide a cross-over point and generate two off-

spring solutions by swapping the same sides of parameters between the parents (i.e., segment-wise

swap). This is repeated to generate N_3 solutions.

In the 'mt_co' box, we run the cross-over operator again. However, instead of swapping the whole

right side of the cross-over point, we only swap the cross-over point (i.e., element-wise swap). This is

repeated to generate N_3 solutions. The parent solutions come from the output of

'selection', 'mutation', and 'cross-over' boxes.

The effect of model parameters on the network dynamics can be highly nonlinear, and a global

minimum in cost function is hard to identify in high-dimensional space. In addition, a global minimum

for a single recording site may still be at risk of overfitting. Therefore, it is important to check the

similarity and stability of the common solutions. We explore the cost function surface by deviating

each parameter at a time, starting from a final solution in the parameter space.

Figure 5. Flow chart of optimization procedure. (A) Optimization for an individual recording site. The

iteration starts with $N_1 = 60$ initial random solutions (parameter sets). The orange box 'selection_gn'

selects the best solution (with highest R^2) and fine-tunes that solution using the Gauss-Newton (gn)

method to the next local minimum. The orange box 'mt_gn' mutates that locally optimal solution, one

parameter at a time, resulting in $N_2 = 28$ modified solutions. These are then fine-tuned again using

the gn method. The white box 'selection' keeps the first N_1 solutions with highest R^2 from the $N_1 +$

$1 + N_2$ solutions. The blue box 'mutation' creates another N_1 solutions, while 'cross-over' and 'mt_co

(mutated_cross-over)' boxes each generate N_3 random solutions ($N_3 = 2000$). The next white box

'selection' again keeps the first (best) N_1 solutions from these $2N_1 + 2N_3$ solutions and replaces the

initial solutions. The best solution for an individual site is selected after 10 iterations. (B) Optimization

across recording sites. The iteration starts with the best solution for each recording site. Noise is

added to these solutions with a uniform distribution (range: $\pm std(i), i \in 1,2,...,28$) to generate $N_4 =$

1000 jittered solutions in the blue box 'pool'. Each of these jittered solutions is then fine-tuned for

each recording site with respect to R^2 using the gn method (the orange boxes). The optimized

solution for each recording site is updated iteratively if a fine-tuned solution with higher R^2 is found.

The iteration ends when there is no update. Then, for each recording site, the best-fitting solution is

selected as the final solution. The number in the parentheses in each box indicates the resulting

number of solutions.

Table 6. Free parameters and the corresponding default model parameters.

Model parameters	Default values of model parameters	Free parameters	Ranges of free parameters [min, max]
Connectivity matrices W_{EE}, W_{PE}, W_{SE}, W_{EP}, W_{PP}, W_{SP}, W_{ES}, and W_{PS}	Table. S1C	θ_{1-8}	[0.1, 15]
Thalamic input connectivity matrices W_{Eth} and W_{Pth}	Table 1	$\theta_{9,10}$	[0.1, 15]
Short-term plasticity $\kappa_{d,EE}$ and $\kappa_{f,SE}$	Table 4	$\theta_{11,12}$	[0.5, 4]
Synaptic kernel time constants τ	Table 2	θ_{13}	[0.5, 1.5]
Sigmoid function slopes r	Table 3	θ_{14}	[0.5, 1.5]
Thalamic input decay levels α_{1-5} (BF and non-BF conditions)	Equal to 1	θ_{15-19}	[0.1, 0.5]
lateral inhibition $W_{inter-SE}$ for (BF and non-BF conditions)	Table. S1C	θ_{20-24}	[0.1, 15]
Thalamic input strengths I_{1-4} to Column 1 (non-BF conditions)	Equal to 1	θ_{25-28}	[0.1, 1]

2.5 Non-negative matrix factorization

We examined whether a blind decomposition approach would yield similar predictions (e.g., ECD) as

our model-fitting approach. The non-negative matrix factorization (a Matlab function *nnmf*) was used

to decompose target MUA Φ_{MUA}^{ref} [$N_{ch} \times T$] into two non-negative matrices A_{MUA}^{nnmf} [$N_{ch} \times N_{pop}$] and

S_{rate}^{nnmf} [$N_{pop} \times T$] where the root mean square residual between Φ_{MUA}^{ref} and $A_{MUA}^{nnmf} \cdot S_{rate}^{nnmf}$ is

minimized. The decomposed firing rates S_{rate}^{nnmf} are then convolved with alpha kernels to generate

current flows $S_{current}^{nnmf}$. The time constants of the alpha kernels are optimized in similar procedure as

in Fig. 5A to minimize the SSE between Φ_{CSD}^{ref} and $A_{CSD}^{nnmf} \cdot S_{current}^{nnmf}$. The ECD Φ_{ECD}^{nnmf} is then

calculated in the same way as in Sections 2.3.3.

3 Results

We fitted the 28 parameters (see Methods section) of our cortical column model, such that the MUA

and CSD derived from the electrophysiological data obtained at each recording site were explained

best in a least squares sense. Concurrently with the parameters of the cortical column model, we also

fitted a set of parameters of the observation model, namely the spatial sensitivity distribution of each

neural population (i.e., MUA spatial profile A_{MUA}) and the spatial distribution of current sinks and

sources on pyramidal dendrites (i.e., CSD spatial profile A_{CSD}). As a result, the fitted model predicted

not only the MUA and CSD that we could compare to the empirically measured values, but also a set

of latent (hidden) variables, namely the mean firing rates and the current flows of the neural

populations.

In Section 3.1, we present the predicted data (Φ_{MUA} and Φ_{CSD}) along with the target data (Φ_{MUA}^{ref} and

Φ_{CSD}^{ref}) for a qualitative and quantitative comparison. In Section 3.2, we show the estimated latent

variables, covering neural population activity (firing rates and current flows), as well as the ECD

magnitude at the recording sites (ECD, Φ_{ECD}). We also compare Φ_{ECD} with the ECD estimated by a

non-negative decomposition approach Φ_{ECD}^{nnmf} to evaluate the advantages of our model-fitting

approach. Section 3.3 reports the estimated parameters of the observation model: MUA spatial profile

A_{MUA} and CSD spatial profile A_{CSD}. In Section 3.4, we finally examine the fitted parameters of the

cortical column model and assess their similarity across the four recording sites (electrode

penetrations).

3.1 Explanation of the target data

The waveforms for measured and predicted MUA and CSD for all 4 recording sites are shown in Fig. 6. These recording sites were selected to cover a wide range in tonotopic space in A1. More detailed depictions, alongside the goodness of fit (R^2), are given in Fig. S4. The target data for model fitting includes the Φ_{MUA}^{ref} and Φ_{CSD}^{ref} of the evoked response to the best frequency (BF) and non-BF tones (see Fig. 6A and B). The BFs of the four recording sites were determined to be 300 Hz, 1000 Hz, 500 Hz, and 6400 Hz, respectively. In Φ_{MUA}^{ref}, L4 (centering around Ch 10) shows higher MUA in BF conditions than in non-BF conditions. This corresponds to the frequency selectivity (tuning curves) of neural population responses that give rise to the tonotopic organization of A1. The BF response may include sustained activity (e.g., 500 Hz at site 3) or a second peak after 150 ms (e.g., 300 Hz at site 1). The non-BF responses at recording site 1 (i.e., 200, 260, 400, and 600 Hz) show negative firing rates (after subtraction of the baseline), reflecting the strong effect of lateral inhibition. In Φ_{CSD}^{ref}, there are early L4 sinks and sources (especially clearly seen at sites 2 and 4) followed by sinks and sources at L2/3 and L5/6. The CSD also revealed longer-lasting sinks (red) and sources (blue) occurring in various channels after 100 ms (especially clearly seen at sites 3 and 4).

The predicted data Φ_{MUA} and Φ_{CSD} capture the general pattern of target data (Fig. 6C and D). The negative firing rate (relative to the pre-stimulus baseline, as at site 1) cannot be reproduced because we only allow non-negative firing rates and a non-negative MUA spatial profile to avoid overfitting (see Discussion). There are some other minor differences between the simulated and target responses. For example, the sustained firing rate (e.g., 500 Hz at site 3) is not well captured by the model. The patterns in Φ_{MUA} and Φ_{CSD} tend to be sharper and do not capture the smooth propagation across layers in Φ_{MUA}^{ref}, and Φ_{CSD}^{ref}, which is due to the limited number of populations ($N_{pop} = 7$) in the model.

Figure 6. Visual comparison of target data and model simulations. (A, B) Target MUA (A) and CSD (B) at the four recording sites. The rows show the responses to different tone frequencies at each recording site. For example, the 1st row shows responses to 200, 260, 300, 400, and 600 Hz at site 1. The middle column (highlighted by the blue rectangle) represents the responses to tones at the BF of each recording site (300, 1000, 500, and 6400 Hz, respectively). The other columns represent non-BF responses. In the target data, the maximum value of each row was normalized to 1. (C, D) The simulated MUA (C) and CSD (D) from the final model solutions. Response amplitudes are color-coded (blue: positive; red: negative).

3.2 Estimated latent variables

3.2.1 Neural activity

The final model solutions provide estimated network dynamics that may underlie the empirical

observations. Fig. 7 shows the firing rates S_{rate} of Column 1 (representing the recording site) as well

as the strength of thalamic inputs based on the common solutions. The network dynamics across the

recording sites, especially sites 1, 2, and 4, share many similarities. The thalamic inputs are stronger

under the BF than the non-BF conditions, which agrees with the tonotopic organization of A1. The

direct input connections lead to stronger early peaks in E and PV activity under the BF than the non-

BF conditions (early intra-column E→PV effect). In contrast, the early peaks in SOM activity are often

weaker under the BF than the non-BF conditions. This is due to the excitatory input from Column 2

via E→SOM connections (lateral inhibition, late inter-column E→SOM effect). Additionally, strong

SOM activity at longer latencies appears to coincide with an increase in short-term facilitation of inter-

column E-to-SOM connections (Fig. 7). The BF and non-BF responses show opposite dynamic

patterns: strong PV inhibits SOM in BF responses, whereas the SOM inhibits PV in non-BF responses.

Figure 7. Estimated firing rates and plasticity of inter-column connections under BF and non-BF

conditions. (A)The estimated firing rates are grouped into layers for visualization. The PV populations

(blue curves) show stronger activity in BF responses (middle column) than in non-BF responses (other

columns), where the peak values seem mainly to be affected by the strength of thalamic input (i.e.,

tonotopy). In contrast, the SOM populations (red curves) show long-lasting activity in non-BF

responses, which reflects the effect of lateral inhibition. (B) The plastic lateral inhibition is reflected by

the short-term plasticity variables $x_{inter-SE} \cdot u_{inter-SE}$ on the inter-column E-to-SOM connections

$W_{inter-SE}$ as in Eq. (9). The lateral inhibition from column 2 (BF site) to column 1 (recording site) is

rising over time (red dashed curves) under non-BF conditions, whereas the lateral inhibition from

column 1 to column 2 is slightly falling (black curves). In the BF conditions, the two curves are identical.

(E1: L23 E population, P1: L234 PV population, S1: L234 SOM population, E3: L4 E population, E2:

L56 E population, P2: L56 PV population, S2: L56SOM population, and Th: thalamic input)

3.2.2 Contribution to EEG/MEG components P1, N1, and P2

The equivalent current dipole (ECD) Φ_{ECD} derived at each recording site provides a link between

intracranially-recorded LFPs and extracranially-recorded EEG/MEG signals. The ECD can be

calculated by Eq. (14), where the current flows associated with activity of specific neural populations

contribute to the ECD by different weights and directions based on the CSD spatial profile A_{CSD}. Fig.

8A shows the predicted ECDs and the contributions of current flows by the E, PV, and SOM

populations at the four recording sites under BF and non-BF conditions. Although there is no ground

truth for verification, the predicted ECDs (the black curves in Fig. 8A) show a pattern of

positive/negative/positive deflections at approximately 25, 40, and 80 milliseconds (site 1 deviates

from that with considerably longer latencies) that can be related to the EEG/MEG components P1,

N1, and P2. These deflections are well-known to occur in humans in response to pure tone stimulation

at latencies of approximately 55, 100, and 160 milliseconds, while corresponding peaks have been

described in macaques at 30, 55, and 70 milliseconds (Itoh et al., 2019). The deflections are the net

result of the summation and cancellation of current flows. To gain insight into cell-type specific

contributions to these deflections, we summed the dipole magnitudes from each of the cell types

(while keeping the thalamic input separate), resulting in only four dipole magnitudes (i.e., $\bar{d}_i \cdot S_{current,i}$

where $i \in \{E, PV, SOM, Th\}$ as in Eq. (14)). For example, the PV dipole signals (yellow curves in Fig.

8A) represent the gross current flow in pyramidal dendrites (i.e., the IPSP on E1, E2, and E3

populations) elicited by the PV neurons (i.e., PV1 and PV2 populations).

In Fig. 8A, we find that the first positive peak of the ECD (related to P1) is consistently due to the

thalamic input (purple curves). The first negative peak of the ECD (related to N1) can be due to either

the E current (blue curves, sites 2, 3, and 4) or the PV current (red curves, site 1), which depends on

the dipole direction derived from the CSD spatial profile. The second positive peak of the ECD (black

line), associated with the P2, is not uniquely attributable to a particular deflection in the cell currents.

For the non-BF condition, it mostly coincides with a positive deflection of the SOM current, except for

site 3, where it coincides with a peak in the E current. For the BF condition, the P2 peak is mostly

associated with a peak in the E current, except for site 1, where we see a positive peak in the PV

current at that latency. Based on these predicted ECDs and cell-type specific contributions, the P1

component is likely to result from the thalamic input (including the BF and non-BF columns). The N1

component is likely to result from the activity of E/PV neurons (also including the BF and non-BF

columns). The origin of the P2 component cannot be identified so clearly. It may be caused by a

change in SOM activity for non-BF columns (not confirmed in site 3) and by a change in E activity in

BF columns (not confirmed in site 1).

The model fitting approach provides a way to decompose the LFP into temporal and spatial

components and predict the ECD at the recording site. We were curious whether a blind

decomposition approach would yield similar predictions. To examine this possibility, we decomposed

the MUA using non-negative matrix factorization (NNMF), determined optimized current flows and

CSD spatial profile, and calculated the dipole signal (Section 2.5). We found that the NNMF approach,

although it leads to improved goodness of fit (Fig. S5) compared with the model fitting approach,

yields implausible time courses of the ECDs (Fig. 8B). The time courses of the magnitude of dipoles

underlying auditory evoked responses usually feature a pattern of alternating peaks and troughs

following that of the respective scalp recordings (see, e.g., Knösche et al., 2002). As the modeling

approach does reproduce an EEG/MEG time course (through the ECD) with the typical peaks of P1,

N1, and P2, it appears to be a promising candidate for realistically accounting for the MUA and CSD.

Note that the precise latencies of these peaks are usually quite variable even in humans and depend

on a number of factors (Picton, 2010).

Figure 8. Simulated equivalent current dipole (ECD) signals. (A) The simulated ECD (black curves)

reflects the contribution of a recording site to the EEG/MEG signal (before considering the orientation

with respect to the MEG sensors). The simulated ECD signal is calculated as the sum of population-

level CD signals (colored curves) representing the effective current flows along the long dendrites of

pyramidal cells induced by individual neural populations or thalamic input (E: E1, E2, and E3; PV:

PV1 and PV2; SOM: SOM1 and SOM2; Th: thalamic input). The vertical lines indicate the deflections

of the ECD signals. (B) Simulated ECD signals obtained by the NNMF approach.

3.2.3 Parameters of the observation model

The observation model contains an MUA spatial profile A_{MUA} and a CSD spatial profile A_{CSD} that

project firing rates S_{rate} and current flows $S_{current}$ to observations Φ_{MUA} and Φ_{CSD}. We now check

the estimated spatial profiles A_{MUA} and A_{CSD} provided by the final solutions. The MUA spatial

profiles A_{MUA} represent the sensitivity of the 16 laminar electrode channels to the firing rates of

neural populations. Fig. 9A shows the MUA spatial profile at each recording site (electrode

penetration). The distributions of E3 center around channel 10, which is consistent with the distribution

of L4 excitatory neurons. However, the distributions of E1 and E2 form one to two clusters, a scenario

which does not agree with the expected distribution of excitatory neurons in L2/3 and L5/6. This

suggests that the definition of neural populations, after model fitting, do not strictly adhere to the initial

laminar definition (i.e., the default connectivity) but changes based on the temporal dynamics of neural

activity. The distributions of E3 center around channel 10, which is consistent with the distribution of

L4 excitatory neurons. However, the distributions of E1 and E2 form one to two clusters, which do not

match the distributions of excitatory neurons in L2/3 and L5/6, as they were assumed in the definition

of the model. Similar observations are made for SOM and PV neurons. This demonstrates that the

best grouping of neurons into a few masses, such that their mean activities explain the measured

effects, does not necessarily coincide with their strict assignment to some layers.

Fig. 9B shows the CSD spatial profile of each recording site, which represents the overall distribution

of current sinks and sources along the dendrites of the excitatory cells (incl. E1, E2, and E3). We

found that the distributions of sinks and sources interlace and spread widely, and differ across

recording sites. This may correspond to the relatively high variability in CSD across recording sites.

This may be also due to the fact that the depth of the 16-channel electrode within the cortex is not

necessarily identical across the 4 electrode penetrations.

Figure 9. Estimated spatial profiles. (A) MUA spatial profiles. Each column represents the laminar

distribution (across electrode channels) of firing rates of neural populations within each recording site.

(B) CSD spatial profiles. Each column represents the corresponding laminar distribution of sinks and

sources. The red arrow indicates the dipole length and direction (from center of sinks to center of

sources).

3.3 Fitted parameters

Next, we checked whether the common solutions for the four recording sites share similar patterns. In Fig. 10, we show parameters related to the tuning curve and lateral inhibition. The tuning curve is characterized by four parameters (θ_{25-28}) which define the strength of thalamic input to the recording site (Column 1) under the four non-BF conditions. The tone frequencies in Fig. 10 are plotted on a log scale. The lateral inhibition is characterized by five parameters (θ_{20-24}) which rescale the default strengths of inter-column E-to-SOM connections. We found M-shape lateral inhibition curves (Fig. 10, lower panel), where lateral inhibition increases as the tone frequency deviates from the BF tone but decreases as the tone frequency deviates further (not reached for site 2). The input strengths under the four non-BF conditions are all weaker than 0.5, and decrease as the tone frequency becomes more distant from the BF of the neurons (Fig. 10, upper panel), which is consistent with features of spectral tuning curves in A1. The lateral inhibition and tuning curves directly affect the activities of PV and SOM populations, respectively, as demonstrated by the firing rates under BF and non-BF conditions in Fig. 7.

We then checked the cost function surface by separately scanning each parameter around the solutions (scanning ranges as listed in Table 6). The surfaces of the four recording sites are shown in Fig. 11. In general, we found that the values of solutions (indicated by triangles) are close to each other in the scan range, and the cost (normalized SSE) increases as the values deviate from the solutions. Hence, at least local minima of the cost function exist, indicating clearly defined solutions. The fact that these solutions are close to each other in parameter space adds to their credibility, based on the assumption that the wiring schemes of cortical columns are similar within the auditory cortex.

Figure 10. Input strength and lateral inhibition in evoked responses. The fitted parameters are plotted

against tone frequency (Hz in log scale). The parameters θ_{25-28} rescale the default thalamic input

strengths I_{1-4} (as illustrated by the red arrow to the cortical column 1, upper left panel) under the four

non-BF conditions (depicted as open circles). Note that the input strength to Column 1 under the BF

condition (solid circles) is always fixed to 1. The parameters θ_{20-24} rescale the default lateral

inhibition $W_{inter-SE}$ (as illustrated by the red arrows between the two cortical columns, lower left

panel) under the BF conditions (solid circles) and four non-BF conditions (open circles). The BFs

corresponding to the four recording sites (300, 1000, 500, and 6400 Hz) are indicated alongside the

solid circles.

Figure 11. Normalized sum of squared errors (nSSE) between predicted and target observations as function of the free parameters. Each plot shows how the nSSE varies as a function of one of the free scaling parameters, while the rest of the parameters are kept constant to their optimal values. These scaling parameters (column 3 of Table 6) are stated on top of each plot together with the scaled model parameter (column 1 of Table 6) in brackets. See Table 6 for an overview of the model parameters, their default values, the free parameters scaling them, and the scaling ranges. The x-axes represent the parameter values normalized to their respective default values. The triangles represent the solutions for the four recording sites.

4 Discussion

In this study, we combined a detailed neural circuit model of the cortex with fine-grained laminar LFP recordings in monkey primary auditory cortex (A1) to estimate cell-type specific contributions to both intracranially- and extracranially-recorded signals. We show that evoked responses at four example recording sites, covering a wide range in tonotopic space in A1, share similar network dynamics (i.e., E, PV, and SOM activity) (Fig. 7), but can show diverse patterns in net transmembrane extracellular current flow, as reflected by CSD analysis, due to the variation in spatial profiles (Fig. 9). The four recording sites also share similar input curves and lateral inhibition curves (Fig. 10) as well as similar intra-column configurations (Fig. 11). These results support the notion of canonical microcircuits (Douglas et al., 1989; Douglas & Martin, 1991, 2004a) and a consistent pattern of neural dynamics and interactions contributing to sensory processing in A1.

We demonstrate the feasibility of our model-fitting approach by transforming laminar profiles of MUA and CSD into products of spatial and temporal components. The fitted model provides insights into neural interactions and cell-type specific activities contributing to equivalent current dipoles (ECDs) underlying typical EEG or MEG recordings (Fig. 8A). This is supported by the plausible ECD signal derived from the estimated current flows and CSD spatial profile. In contrast, an alternative approach based on non-negative matrix factorization, despite a higher goodness of fit to MUA and CSD response profiles (Fig. S5A), is relatively uninformative with regard to elucidating the activities of distinct neural populations (Fig. S5B) and plausible synthesized ECD signals (Fig. 8B).

4.1 PV-SOM interaction

We observed distinct patterns in the estimated activity of PV and SOM interneurons between BF and non-BF responses (Fig. 7). In BF responses, PV interneurons show faster and stronger activity than

SOM interneurons. In non-BF responses, PV interneurons show relatively weak activity, and the

activity of SOM interneurons dominates after around 50 ms. This phenomenon results from various

literature-based settings for PV and SOM neurons in the cortical column model with regard to thalamic

input (no direct input to SOM, Ji et al., 2016), synaptic time constants (slow dynamic in SOM, Dura-

Bernal et al., 2022; Jouhanneau et al., 2018), inter-column connections (only E-to-SOM, considering

a wider spatial distribution of inhibitory innervation by SOM than PV neurons, Kato et al., 2017;

Lakunina et al., 2020), and short-term plasticity (STF on E-to-SOM connections, Hayut et al., 2011;

Silberberg & Markram, 2007). In other words, the early PV activity is directly related to tonotopic

(thalamic) input, and the late SOM activity is directly related to lateral inhibition. Based on this

distinction, the switch between the "BF pattern" and "non-BF pattern" along the tonotopic axis is

sharpened by mutual inhibition between PV and SOM interneurons (Hahn et al., 2022) and should be

observable in possible future experiments involving detailed recordings from different neuron types,

for example, through calcium imaging.

4.2 Generation of P1, N1, and P2 components

Auditory evoked responses recorded via EEG/MEG are typically characterized by a temporal

sequence of positive and negative deflections or waves designated as the P1, N1, and P2

components. Studies based on the Human Neocortical Neurosolver (Kohl et al., 2022; Neymotin et

al., 2020) suggest that the P1 and P2 components are partly generated by upward currents within the

dendrites of cortical pyramidal neurons due to bottom-up inputs, while the N1 component is partly

generated by downward currents associated with top-down inputs. Studies using a multi-column

model of the auditory cortex (Hajizadeh et al., 2019, 2021, 2022) further emphasize the dependence

of current orientation on the cellular location of the active synapses (e.g., apical/somatic), synaptic

type (i.e., excitatory/inhibitory), inter-column connection type (e.g., feedforward, feedback, within-

field), and folding of the cortex (i.e., the neuroanatomical topography of the cortical surface). At the level of a cortical column, our analyses of the cell-specific contributions to ECDs (Fig. 8A) suggests that initial thalamic input primarily contributes to P1, subsequent early activity of E and PV neurons (both BF and non-BF columns) primarily contributes to N1, and late SOM activity (especially in non-BF columns) joins the contribution to P2. We observed variability in peak latencies of the ECD signals at the four recording sites (Fig. 8A), due to the variance in thalamic inputs, intra-column connection strengths, and the CSD laminar spatial profile across cortical columns.

4.3 Patterns of activity propagation

In this study, we were unable to identify a consistent pattern of neural activity propagation across cortical layers and neural populations contributing to the auditory evoked response. Such patterns (e.g., from L4 to L2/3 and to L5) have been assumed in canonical cortical column models of visual and somatosensory areas (e.g., (Douglas & Martin, 2004b)). However, such a stereotypical pattern might not always be the rule. For example, a study using thalamic stimulation suggested that activity in supragranular layers is initiated by infragranular cells and regulated by feed-forward inhibitory cells (Krause et al., 2014). Moreover, specific patterns of information propagation are less likely to be found from a more detailed and complex network derived from existing animal-model databases (Billeh et al., 2020; Campagnola et al., 2022; Ji et al., 2016; Markram et al., 2015). Based on our estimated firing rates (Fig. 7) and MUA spatial profile (Fig. 9A), the three E populations (E1, E2, and E3) show early peaks at similar latencies because they all receive thalamic input. Clear propagation from L4 to L2/3 to L5 is therefore not observed. As for the activity of inhibitory neurons, PV1 activity is in general stronger than PV2 activity in BF responses, and SOM2 activity is stronger than SOM1 activity in non-BF responses. However, this pattern cannot be projected onto specific cortical layers, because the estimated MUA spatial profiles of the same cell type (e.g., PV1 vs. PV2; SOM1 vs. SOM2) are not

spatially exclusive. While our cortical column model was built with default connectivity based on

laminar classification, the neural populations are found to spatially overlap after model fitting. Such

spatial overlap of functional components may provide an alternative framework for understanding the

neural computations underlying sensory processing, for example, the role of lateral inhibition in A1 in

rhythmic masking release (Fishman et al., 2012), spectral resolution (Fishman & Steinschneider,

2006), and complex tone processing (Fishman et al., 2000b).

4.4 Limitations and future directions

Several important limitations of the present work should be noted. First, our model considers only

thalamic and lateral input and disregards inputs from areas outside of primary auditory cortex, e.g.,

frontal and entorhinal cortices (Schaefer et al., 2015). Such input may be increasingly important for

explaining neural activity occurring at longer latencies. Second, the firing rate in our model ranges

from 0 to 1, corresponding to baseline activity and maximum firing rates of each cell type, respectively.

We restricted the sigmoid functions to be non-negative in order to prevent unreasonable cancellation

between negative and positive firing rates in the fitting procedure. This comes with the price of failing

to explain negative (relative to the pre-stimulus baseline) MUA activity. Third, in order to avoid over-

fitting, we reduced model complexity by making a number of simplifying assumptions. For example,

the intra-column settings of the two columns are assumed to be identical. The ratio of thalamic input

to E and PV neurons is assumed to be fixed. The inter-column connections are assumed to be

symmetric. The MUA spatial profile is assumed to have a fixed ratio of sensitivity to E, PV, and SOM

neurons. In general, these assumptions lead to a reduced goodness of fit. We cannot guarantee that

we have found globally optimized solutions, but current best solutions show consistent neural

activities and fitted parameters across the four recording sites examined. The current best solutions

can serve as a prior to improve goodness of fit to data from individual sites using a more flexible

model, or one with a greater number of free parameters.

In this study, we demonstrated the feasibility of our model-fitting approach in estimating cell-type

specific activity across cortical layers based on LFP recordings in A1. So far the target observations

only include tone-evoked responses (BF and non-BF conditions) at four recording sites. Moreover,

our cortical column model was designed with a relatively simple architecture in order to avoid an

underdetermination issue arising from insufficient data constraints. However, our simplified model

could be extended in several ways. For example, VIP interneurons could be included to examine the

modulatory effects of attention on different inhibitory states (Hahn et al., 2022). The matrix thalamic

input (innervating the supragranular cortex) could be included as tone-insensitive input (Müller et al.,

2020) to investigate neural mechanisms underlying other neurophysiological phenomena in auditory

cortex, such as "Off" responses and mismatch responses (e.g., (Fishman, 2014; Fishman &

Steinschneider, 2009)). Corticothalamic pathways (which emanate from L5/6 to the thalamus) could

also be included to model the modulation of thalamic input (Antunes & Malmierca, 2021). Lastly,

spontaneous activity in LFP recordings could be considered in future work to examine the neural

underpinnings of interactions between spontaneous and stimulus-evoked neural activity in auditory

cortex (e.g., Dura-Bernal et al., 2022).

Conclusions

944 We demonstrated the feasibility of a model-fitting approach in estimating cell-type specific population

945 activity from laminar LFPs evoked by sound stimuli, as well as estimating cell-type specific

946 contributions to the P1, N1, and P2 components of extracranial evoked responses. This model-fitting

947 approach provides a foundation for further investigation into the neural dynamics of cortical sensory

948 processing.

Code availability statement

951 The main codes used in this article can be found at https://github.com/vscChien/LFPmodeling.

Acknowledgments

953 Neurophysiological data were obtained in collaboration with Dr. Mitchell Steinschneider (funded under

954 NIH Grant DC00657), with invaluable technical support provided by Jeannie Hutagalung and Shirley

955 Seto.

Supplementary figures

Figure S1. Neural population tuning curves obtained at each of the 16 electrode channels at the 4 recording sites (electrode penetrations) analyzed in this report (represented in panels A-D, respectively). Each colored plot represents the tuning curve of MUA at each electrode channel spanning the laminar extent of A1 (plots have been normalized to the maximum-amplitude response). The tuning curve for the electrode channel at which the maximal-amplitude MUA was recorded is indicated by the arrow. Note that this channel is generally located in the middle of the electrode array and positioned within the middle laminae of A1. The Best Frequency (BF) corresponding to the peak of the tuning curve is indicated by the dashed vertical line. Note the high consistency in BFs across channels displaying the larger-amplitude responses, demonstrating that BF is relatively uniform across layers within a 'cortical column' in A1.

Figure S2. Schematic of matrices used to guide linear-array multi-contact electrodes perpendicularly

into auditory cortex within the left hemisphere in Monkey A, B, and C, as indicated. Circles represent

the tops of guide tubes into which the electrode was inserted during a given recording session.

Numbers within the circles indicate the Best Frequency (BF; in kHz) of the neural population recorded

in each electrode penetration, where a clear and unique BF could be determined based on pure tone

responses. Red circles represent the 4 recording sites selected for analysis in the present report.

These 4 sites were selected because they display stereotypical features of laminar AEP, MUA, and

CSD neurophysiological response profiles which are characteristic of primary auditory cortex (A1).

Note the approximate anterior-lateral to posterior-medial anatomical spatial gradient of low-to-high

BF in all 3 animals, consistent with the tonotopic organization of A1 in macaques.

Goodness of fit (R^2)

Figure S3. Performance of original model (m0), the reduced models (m1-4), and the expanded model (m5). To reveal the relative impact of thalamic input and inter-column connection on the fitting performance, we examine the goodness of fit (R^2) by several variant models (four reduced models and one expanded model) on an exemplary recording site (site 2). The reduced models include m1: thalamic inputs only to L4, m2: no inter-column connectivity, m3: no PV populations, and m4: no SOM populations. Optimization procedures were performed six times for a stability check (standard deviation indicated by error bars). The results show that the reduced models m2-4 perform worse than the original model (m0), and the reduced model m1 has a similar performance. In the expanded model (m5), we include inter-column E-E connections between the L56 E populations, between the L23 E populations, and from the L23 E to L4 E population. The extra current flows by the inter-column E-E connections are included in producing the simulated CSD. Optimization procedures were performed six times with different initial values of inter-column E-E connections. The results show that m5 performs similarly to m0. The estimated firing rates of m5 (not shown here) are very similar to m0, suggesting that the original model (m0) suffices to characterize the network parameters and dynamics.

Figure S4. The target MUA and CSD (red) and the model simulations (black) at sites 1 to 4 (A-D).

1000

Figure S5. The NNMF decomposition approach (site 1 used as example). (A) The target MUA and

CSD (red) and the model simulations (black). (B) The MUA is decomposed by NNMF into firing rates

(rates 2 to 8 in 1st column) and MUA spatial profile (2nd column). The thalamic input (rate1 in 1st

column) and the firing rates are convolved with alpha kernels to generate current flows (3rd column).

The CSD spatial profile is the regression coefficients, and the centers of sinks and sources are shown

in red arrows (4th column).

Table S1A. Connection probabilities after averaging across layers.

To \ From	E1	E2	E3	PV1	PV2	SOM1	SOM2
E1 (L2/3)	0.1600	0.0105	0.1400	0.3305	0.0500	0.3370	0.0845
E2 (L5/6)	0.0415	0.0503	0.0680	0.0395	0.1713	0.0118	0.1192
E3 (L4)	0.0160	0.0035	0.2430	0.2435	0.0500	0.2005	0.0280
PV1 (L2/3/4)	0.2390	0.0250	0.2650	0.2505	0.0340	0.4535	0.0075
PV2 (L5/6)	0.0405	0.0670	0.0505	0.0410	0.1202	0.0075	0.2368
SOM1(L2/3/4)	0.1325	0.0250	0.3355	0.0400	0.0075	0.0660	0.0057
SOM2 (L5/6)	0.0510	0.0508	0.0640	0.0075	0.0425	0	0.0325

1008

1009   *Table S1B. Synaptic strengths (unitary PSP [mV]) after averaging across layers.*

To \ From	E1	E2	E3	PV1	PV2	SOM1	SOM2
E1 (L2/3)	0.3600	0.2350	0.7800	0.5200	0.4050	0.3050	0.1250
E2 (L5/6)	0.3700	0.5800	0.7950	0.2325	0.8100	0.1250	0.2700
E3 (L4)	0.3400	0.1900	0.8300	0.6000	0.4050	0.2950	0.1400
PV1 (L2/3/4)	1.4400	0.6250	1.3400	0.6800	0.3625	0.5000	0.1125
PV2 (L5/6)	0.6600	2.5000	0.6250	0.4325	1.1900	0.1125	0.4000
SOM1(L2/3/4)	0.7750	0.2600	0.6000	0.4200	0.1050	0.1500	0.1675
SOM2 (L5/6)	0.2650	0.5200	0.2600	0.1050	0.4100	0.0700	0.4000

1010

1011   *Table S1C. Intra-column connectivity (connection probability*synaptic strength).*

To \ From	E1	E2	E3	PV1	PV2	SOM1	SOM2
E1 (L2/3)	0.0576	0.0025	0.1092	0.1719	0.0203	0.1028	0.0106
E2 (L5/6)	0.0154	0.0291	0.0541	0.0092	0.1387	0.0015	0.0322
E3 (L4)	0.0054	0.0007	0.2017	0.1461	0.0203	0.0591	0.0039

PV1 (L2/3/4)	0.3442	0.0156	0.3551	0.1703	0.0123	0.2268	0.0008
PV2 (L5/6)	0.0267	0.1675	0.0316	0.0177	0.1431	0.0008	0.0947
SOM1(L2/3/4)	0.1027	0.0065	0.2013	0.0168	0.0008	0.0099	0.0010
SOM2 (L5/6)	0.0135	0.0264	0.0166	0.0008	0.0174	0	0.0130

1012

References

Antunes, F. M., & Malmierca, M. S. (2021). Corticothalamic Pathways in Auditory Processing: Recent Advances and Insights From Other Sensory Systems. In *Frontiers in Neural Circuits* (Vol. 15). https://doi.org/10.3389/fncir.2021.721186

Aponte, D. A., Handy, G., Kline, A. M., Tsukano, H., Doiron, B., & Kato, H. K. (2021). Recurrent network dynamics shape direction selectivity in primary auditory cortex. *Nature Communications*, *12*(1). https://doi.org/10.1038/s41467-020-20590-6

Atencio, C. A., & Schreiner, C. E. (2013). Auditory cortical local subnetworks are characterized by sharply synchronous activity. *Journal of Neuroscience*, *33*(47). https://doi.org/10.1523/JNEUROSCI.2014-13.2013

Bacci, A., Rudolph, U., Huguenard, J. R., & Prince, D. A. (2003). Major Differences in Inhibitory Synaptic Transmission onto Two Neocortical Interneuron Subclasses. *Journal of Neuroscience*, *23*(29). https://doi.org/10.1523/jneurosci.23-29-09664.2003

Banno, T., Shirley, H. W., Fishman, Y. I., & Cohen, Y. E. (2022). Laminar Distribution of stimulus- and task-related variables related to auditory streaming in core and belt auditory cortex. *BioRxiv*, 2022.06.14.496098. https://doi.org/10.1101/2022.06.14.496098

Beierlein, M., Gibson, J. R., & Connors, B. W. (2003). Two Dynamically Distinct Inhibitory Networks in Layer 4 of the Neocortex. *Journal of Neurophysiology*, *90*(5). https://doi.org/10.1152/jn.00283.2003

Bigelow, J., Morrill, R. J., Dekloe, J., & Hasenstaub, A. R. (2019). Movement and VIP interneuron activation differentially modulate encoding in mouse auditory cortex. *ENeuro*, *6*(5). https://doi.org/10.1523/ENEURO.0164-19.2019

Billeh, Y. N., Cai, B., Gratiy, S. L., Dai, K., Iyer, R., Gouwens, N. W., Abbasi-Asl, R., Jia, X., Siegle, J. H., Olsen, S. R., Koch, C., Mihalas, S., & Arkhipov, A. (2020). Systematic Integration of Structural and Functional Data into Multi-scale Models of Mouse Primary Visual Cortex. *Neuron*, *106*(3). https://doi.org/10.1016/j.neuron.2020.01.040

Blackman, A. v., Abrahamsson, T., Costa, R. P., Lalanne, T., & Sjöström, P. J. (2013). Target-cell-specific short-term plasticity in local circuits. In *Frontiers in Synaptic Neuroscience* (Vol. 5, Issue DEC). https://doi.org/10.3389/fnsyn.2013.00011

Blackwell, J. M., & Geffen, M. N. (2017). Progress and challenges for understanding the function of cortical microcircuits in auditory processing. *Nature Communications*, *8*(1). https://doi.org/10.1038/s41467-017-01755-2

Brosch, M., Bauer, R., & Eckhorn, R. (1997). Stimulus-dependent modulations of correlated high-frequency oscillations in cat visual cortex. *Cerebral Cortex*, *7*(1). https://doi.org/10.1093/cercor/7.1.70

Bruyns-Haylett, M., Luo, J., Kennerley, A. J., Harris, S., Boorman, L., Milne, E., Vautrelle, N., Hayashi, Y., Whalley, B. J., Jones, M., Berwick, J., Riera, J., & Zheng, Y. (2017). The neurogenesis of P1 and

N1: A concurrent EEG/LFP study. *NeuroImage*, *146*. https://doi.org/10.1016/j.neuroimage.2016.09.034

Campagnola, L., Seeman, S. C., Chartrand, T., Kim, L., Hoggarth, A., Gamlin, C., Ito, S., Trinh, J., Davoudian, P., Radaelli, C., Kim, M. H., Hage, T., Braun, T., Alfiler, L., Andrade, J., Bohn, P., Dalley, R., Henry, A., Kebede, S., … Jarsky, T. (2022). Local connectivity and synaptic dynamics in mouse and human neocortex. *Science*, *375*(6585). https://doi.org/10.1126/science.abj5861

Chien, V. S. C., Maess, B., & Knösche, T. R. (2019). A generic deviance detection principle for cortical On/Off responses, omission response, and mismatch negativity. *Biological Cybernetics*, *113*(5–6). https://doi.org/10.1007/s00422-019-00804-x

Douglas, R. J., & Martin, K. A. (1991). A functional microcircuit for cat visual cortex. *The Journal of Physiology*, *440*(1), 735–769.

Douglas, R. J., & Martin, K. A. C. (2004a). Neuronal circuits of the neocortex. *Annu. Rev. Neurosci.*, *27*, 419–451.

Douglas, R. J., & Martin, K. A. C. (2004b). Neuronal circuits of the neocortex. In *Annual Review of Neuroscience* (Vol. 27). https://doi.org/10.1146/annurev.neuro.27.070203.144152

Douglas, R. J., Martin, K. A. C., & Whitteridge, D. (1989). A canonical microcircuit for neocortex. *Neural Computation*, *1*(4), 480–488.

Dura-Bernal, S., Griffith, E. Y., Barczak, A., O'Connell, M. N., McGinnis, T., Schroeder, C. E., Lytton, W. W., Lakatos, P., & Neymotin, S. A. (2022). Data-Driven Multiscale Model of Macaque Auditory Thalamocortical Circuits Reproduces in vivo Dynamics. *SSRN Electronic Journal*. https://doi.org/10.2139/ssrn.4219122

Eiben, A. E., & Smith, J. E. (2015). Natural Computing Series Introduction to Evolutionary Computing. In *Natural Computing Series*.

Einevoll, G. T., Pettersen, K. H., Devor, A., Ulbert, I., Halgren, E., & Dale, A. M. (2007). Laminar population analysis: Estimating firing rates and evoked synaptic activity from multielectrode recordings in rat barrel cortex. *Journal of Neurophysiology*, *97*(3). https://doi.org/10.1152/jn.00845.2006

Fanselow, E. E., Richardson, K. A., & Connors, B. W. (2008). Selective, state-dependent activation of somatostatin-expressing inhibitory interneurons in mouse neocortex. *Journal of Neurophysiology*, *100*(5). https://doi.org/10.1152/jn.90691.2008

Fino, E., Packer, A. M., & Yuste, R. (2013). The logic of inhibitory connectivity in the neocortex. In *Neuroscientist* (Vol. 19, Issue 3). https://doi.org/10.1177/1073858412456743

Fishman, Y. I. (2014). The mechanisms and meaning of the mismatch negativity. In *Brain Topography* (Vol. 27, Issue 4). https://doi.org/10.1007/s10548-013-0337-3

Fishman, Y. I., Micheyl, C., & Steinschneider, M. (2012). Neural mechanisms of rhythmic masking release in monkey primary auditory cortex: Implications for models of auditory scene analysis. *Journal of Neurophysiology*, *107*(9). https://doi.org/10.1152/jn.01010.2011

Fishman, Y. I., Reser, D. H., Arezzo, J. C., & Steinschneider, M. (2000a). Complex tone processing in

primary auditory cortex of the awake monkey. I. Neural ensemble correlates of roughness. *The Journal of the Acoustical Society of America*, *108*(1). https://doi.org/10.1121/1.429460

Fishman, Y. I., Reser, D. H., Arezzo, J. C., & Steinschneider, M. (2000b). Complex tone processing in primary auditory cortex of the awake monkey. II. Pitch versus critical band representation. *The Journal of the Acoustical Society of America*, *108*(1). https://doi.org/10.1121/1.429461

Fishman, Y. I., & Steinschneider, M. (2006). Spectral resolution of monkey primary auditory cortex (A1) revealed with two-noise masking. *Journal of Neurophysiology*, *96*(3). https://doi.org/10.1152/jn.00124.2006

Fishman, Y. I., & Steinschneider, M. (2009). Temporally dynamic frequency tuning of population responses in monkey primary auditory cortex. *Hearing Research*, *254*(1–2). https://doi.org/10.1016/j.heares.2009.04.010

Fishman, Y. I., & Steinschneider, M. (2010). Neural correlates of auditory scene analysis based on inharmonicity in monkey primary auditory cortex. *Journal of Neuroscience*, *30*(37). https://doi.org/10.1523/JNEUROSCI.1780-10.2010

Fishman, Y. I., & Steinschneider, M. (2012). Searching for the mismatch negativity in primary auditory cortex of the awake monkey: Deviance detection or stimulus specific adaptation? *Journal of Neuroscience*, *32*(45). https://doi.org/10.1523/JNEUROSCI.2835-12.2012

Fishman, Y. I., Volkov, I. O., Noh, M. D., Garell, P. C., Bakken, H., Arezzo, J. C., Howard, M. A., & Steinschneider, M. (2001). Consonance and dissonance of musical chords: Neural correlates in auditory cortex of monkeys and humans. *Journal of Neurophysiology*, *86*(6). https://doi.org/10.1152/jn.2001.86.6.2761

Freeman, J. A., & Nicholson, C. (1975). Experimental optimization of current source density technique for anuran cerebellum. *Journal of Neurophysiology*, *38*(2). https://doi.org/10.1152/jn.1975.38.2.369

García-Martínez, C., Rodriguez, F. J., & Lozano, M. (2018). Genetic Algorithms. In R. Martí, P. M. Pardalos, & M. G. C. Resende (Eds.), *Handbook of Heuristics* (pp. 431–464). Springer International Publishing. https://doi.org/10.1007/978-3-319-07124-4_28

Głąbska, H., Potworowski, J., Łęski, S., & Wójcik, D. K. (2014). Independent components of neural activity carry information on individual populations. *PLoS ONE*, *9*(8). https://doi.org/10.1371/journal.pone.0105071

Głąbska, H. T., Norheim, E., Devor, A., Dale, A. M., Einevoll, G. T., & Wójcik, D. K. (2016). Generalized laminar population analysis (gLPA) for interpretation of multielectrode data from cortex. *Frontiers in Neuroinformatics*, *10*(JAN). https://doi.org/10.3389/fninf.2016.00001

Hagen, E., Dahmen, D., Stavrinou, M. L., Lindén, H., Tetzlaff, T., van Albada, S. J., Grün, S., Diesmann, M., & Einevoll, G. T. (2016). Hybrid scheme for modeling local field potentials from point-neuron networks. *Cerebral Cortex*, *26*(12). https://doi.org/10.1093/cercor/bhw237

Hagen, E., Næss, S., Ness, T. v., & Einevoll, G. T. (2018). Multimodal modeling of neural network activity: Computing LFP, ECoG, EEG, and MEG signals with LFPy 2.0. *Frontiers in*

Neuroinformatics, *12*. https://doi.org/10.3389/fninf.2018.00092

Hahn, G., Kumar, A., Schmidt, H., Knösche, T. R., & Deco, G. (2022). Rate and oscillatory switching dynamics of a multilayer visual microcircuit model. *ELife*, *11*, e77594. https://doi.org/10.7554/eLife.77594

Hajizadeh, A., Matysiak, A., Brechmann, A., König, R., & May, P. J. C. (2021). Why do humans have unique auditory event-related fields? Evidence from computational modeling and MEG experiments. *Psychophysiology*, *58*(4). https://doi.org/10.1111/psyp.13769

Hajizadeh, A., Matysiak, A., May, P. J. C., & König, R. (2019). Explaining event-related fields by a mechanistic model encapsulating the anatomical structure of auditory cortex. *Biological Cybernetics*, *113*(3). https://doi.org/10.1007/s00422-019-00795-9

Hajizadeh, A., Matysiak, A., Wolfrum, M., May, P. J. C., & König, R. (2022). Auditory cortex modelled as a dynamical network of oscillators: understanding event-related fields and their adaptation. *Biological Cybernetics*, *116*(4), 475–499. https://doi.org/10.1007/s00422-022-00936-7

Hamilton, L. S., Sohl-Dickstein, J., Huth, A. G., Carels, V. M., Deisseroth, K., & Bao, S. (2013). Optogenetic Activation of an Inhibitory Network Enhances Feedforward Functional Connectivity in Auditory Cortex. *Neuron*, *80*(4). https://doi.org/10.1016/j.neuron.2013.08.017

Happel, M. F. K., Jeschke, M., & Ohl, F. W. (2010). Spectral integration in primary auditory cortex attributable to temporally precise convergence of thalamocortical and intracortical input. *Journal of Neuroscience*, *30*(33). https://doi.org/10.1523/JNEUROSCI.0689-10.2010

Hayut, I., Fanselow, E. E., Connors, B. W., & Golomb, D. (2011). LTS and FS inhibitory interneurons, short-term synaptic plasticity, and cortical circuit dynamics. *PLoS Computational Biology*, *7*(10). https://doi.org/10.1371/journal.pcbi.1002248

Itoh, K., Nejime, M., Konoike, N., Nakamura, K., & Nakada, T. (2019). Evolutionary elongation of the time window of integration in auditory cortex: Macaque vs. Human comparison of the effects of sound duration on auditory evoked potentials. *Frontiers in Neuroscience*, *13*(JUN). https://doi.org/10.3389/fnins.2019.00630

Jansen, B. H., & Rit, V. G. (1995). Electroencephalogram and visual evoked potential generation in a mathematical model of coupled cortical columns. *Biological Cybernetics*, *73*(4). https://doi.org/10.1007/BF00199471

Ji, X. Y., Zingg, B., Mesik, L., Xiao, Z., Zhang, L. I., & Tao, H. W. (2016). Thalamocortical Innervation Pattern in Mouse Auditory and Visual Cortex: Laminar and Cell-Type Specificity. *Cerebral Cortex*, *26*(6). https://doi.org/10.1093/cercor/bhv099

Jouhanneau, J. S., Kremkow, J., & Poulet, J. F. A. (2018). Single synaptic inputs drive high-precision action potentials in parvalbumin expressing GABA-ergic cortical neurons in vivo. *Nature Communications*, *9*(1). https://doi.org/10.1038/s41467-018-03995-2

Kaas, J. H., & Hackett, T. A. (2000). Subdivisions of auditory cortex and processing streams in primates. In *Proceedings of the National Academy of Sciences of the United States of America* (Vol. 97, Issue 22). https://doi.org/10.1073/pnas.97.22.11793

Kalisman, N., Silberberg, G., & Markram, H. (2005). The neocortical microcircuit as a tabula rasa.
Proceedings of the National Academy of Sciences of the United States of America, *102*(3).
https://doi.org/10.1073/pnas.0407088102

Kato, H. K., Asinof, S. K., & Isaacson, J. S. (2017). Network-Level Control of Frequency Tuning in
Auditory Cortex. *Neuron*, *95*(2). https://doi.org/10.1016/j.neuron.2017.06.019

Katoch, S., Chauhan, S. S., & Kumar, V. (2021). A review on genetic algorithm: past, present, and
future. *Multimedia Tools and Applications*, *80*(5). https://doi.org/10.1007/s11042-020-10139-6

Kayser, C., Petkov, C. I., & Logothetis, N. K. (2007). Tuning to sound frequency in auditory field
potentials. *Journal of Neurophysiology*, *98*(3). https://doi.org/10.1152/jn.00358.2007

Keller, D., Erö, C., & Markram, H. (2018). Cell densities in the mouse brain: A systematic review. In
Frontiers in Neuroanatomy (Vol. 12). https://doi.org/10.3389/fnana.2018.00083

Knösche, T. R., Lattner, S., Maess, B., Schauer, M., & Friederici, A. D. (2002). Early parallel processing
of auditory word and voice information. *NeuroImage*, *17*(3).
https://doi.org/10.1006/nimg.2002.1262

Kohl, C., Parviainen, T., & Jones, S. R. (2022). Neural Mechanisms Underlying Human Auditory
Evoked Responses Revealed By Human Neocortical Neurosolver. *Brain Topography*, *35*(1).
https://doi.org/10.1007/s10548-021-00838-0

Krause, B. M., Raz, A., Uhlrich, D. J., Smith, P. H., & Banks, M. I. (2014). Spiking in auditory cortex
following thalamic stimulation is dominated by cortical network activity. *Frontiers in Systems*
Neuroscience, *8*. https://doi.org/10.3389/fnsys.2014.00170

Kunze, T., Haueisen, J., & Knösche, T. R. (2019). Emergence of cognitive priming and structure
building from the hierarchical interaction of canonical microcircuit models. *Biological*
Cybernetics, *113*(3), 273–291. https://doi.org/10.1007/s00422-019-00792-y

Lakatos, P., O'Connell, M. N., Barczak, A., McGinnis, T., Neymotin, S., Schroeder, C. E., Smiley, J. F., &
Javitt, D. C. (2020). The Thalamocortical Circuit of Auditory Mismatch Negativity. *Biological*
Psychiatry, *87*(8). https://doi.org/10.1016/j.biopsych.2019.10.029

Lakunina, A. A., Nardoci, M. B., Ahmadian, Y., & Jaramillo, S. (2020). Somatostatin-expressing
interneurons in the auditory cortex mediate sustained suppression by spectral surround.
Journal of Neuroscience, *40*(18). https://doi.org/10.1523/JNEUROSCI.1735-19.2020

Liu, J., & Kanold, P. O. (2021). Diversity of receptive fields and sideband inhibition with complex
thalamocortical and intracortical origin in L2/3 of mouse primary auditory cortex. *Journal of*
Neuroscience, *41*(14). https://doi.org/10.1523/JNEUROSCI.1732-20.2021

Liu, J., Whiteway, M. R., Sheikhattar, A., Butts, D. A., Babadi, B., & Kanold, P. O. (2019). Parallel
Processing of Sound Dynamics across Mouse Auditory Cortex via Spatially Patterned Thalamic
Inputs and Distinct Areal Intracortical Circuits. *Cell Reports*, *27*(3).
https://doi.org/10.1016/j.celrep.2019.03.069

Lopes da Silva, F. (2013). EEG and MEG: Relevance to Neuroscience. *Neuron*, *80*(5), 1112–1128.
https://doi.org/10.1016/J.NEURON.2013.10.017

Ma, Y., Hu, H., & Agmon, A. (2012). Short-term plasticity of unitary inhibitory-to-inhibitory synapses depends on the presynaptic interneuron subtype. *Journal of Neuroscience*, *32*(3). https://doi.org/10.1523/JNEUROSCI.5007-11.2012

Markram, H., Muller, E., Ramaswamy, S., Reimann, M. W., Abdellah, M., Sanchez, C. A., Ailamaki, A., Alonso-Nanclares, L., Antille, N., Arsever, S., Kahou, G. A. A., Berger, T. K., Bilgili, A., Buncic, N., Chalimourda, A., Chindemi, G., Courcol, J. D., Delalondre, F., Delattre, V., … Schürmann, F. (2015). Reconstruction and Simulation of Neocortical Microcircuitry. *Cell*, *163*(2). https://doi.org/10.1016/j.cell.2015.09.029

Merzenich, M. M., & Brugge, J. F. (1973). Representation of the cochlear partition on the superior temporal plane of the macaque monkey. *Brain Research*, *50*(2). https://doi.org/10.1016/0006-8993(73)90731-2

Mesik, L., Ma, W. P., Li, L. Y., Ibrahim, L. A., Huang, Z. J., Zhang, L., & Tao, H. W. (2015). Functional response properties of VIP-expressing inhibitory neurons in mouse visual and auditory cortex. *Frontiers in Neural Circuits*, *9*(May). https://doi.org/10.3389/fncir.2015.00022

Metherate, R., & Cruikshank, S. J. (1999). Thalamocortical inputs trigger a propagating envelope of gamma-band activity in auditory cortex in vitro. *Experimental Brain Research*, *126*(2). https://doi.org/10.1007/s002210050726

Mitzdorf, U. (1985). Current source-density method and application in cat cerebral cortex: Investigation of evoked potentials and EEG phenomena. In *Physiological Reviews* (Vol. 65, Issue 1). https://doi.org/10.1152/physrev.1985.65.1.37

Morel, A., Garraghty, P. E., & Kaas, J. H. (1993). Tonotopic organization, architectonic fields, and connections of auditory cortex in macaque monkeys. *Journal of Comparative Neurology*, *335*(3). https://doi.org/10.1002/cne.903350312

Müller, E. J., Munn, B., Hearne, L. J., Smith, J. B., Fulcher, B., Arnatkevičiūtė, A., Lurie, D. J., Cocchi, L., & Shine, J. M. (2020). Core and matrix thalamic sub-populations relate to spatio-temporal cortical connectivity gradients. *NeuroImage*, *222*. https://doi.org/10.1016/j.neuroimage.2020.117224

Müller-Preuss, P., & Mitzdorf, U. (1984). Functional anatomy of the inferior colliculus and the auditory cortex: current source density analyses of click-evoked potentials. *Hearing Research*, *16*(2). https://doi.org/10.1016/0378-5955(84)90003-0

Næss, S., Halnes, G., Hagen, E., Hagler, D. J., Dale, A. M., Einevoll, G. T., & Ness, T. v. (2021). Biophysically detailed forward modeling of the neural origin of EEG and MEG signals. *NeuroImage*, *225*. https://doi.org/10.1016/j.neuroimage.2020.117467

Neymotin, S. A., Daniels, D. S., Caldwell, B., McDougal, R. A., Carnevale, N. T., Jas, M., Moore, C. I., Hines, M. L., Hämäläinen, M., & Jones, S. R. (2020). Human neocortical neurosolver (HNN), a new software tool for interpreting the cellular and network origin of human MEG/EEG data. *ELife*, *9*. https://doi.org/10.7554/eLife.51214

Nicholson, C., & Freeman, J. A. (1975). Theory of current source density analysis and determination

of conductivity tensor for anuran cerebellum. *Journal of Neurophysiology*, *38*(2). https://doi.org/10.1152/jn.1975.38.2.356

O'connell, M. N., Barczak, A., Schroeder, C. E., & Lakatos, P. (2014). Layer specific sharpening of frequency tuning by selective attention in primary auditory cortex. *Journal of Neuroscience*, *34*(49). https://doi.org/10.1523/JNEUROSCI.2055-14.2014

O'Connell, M. N., Falchier, A., McGinnis, T., Schroeder, C. E., & Lakatos, P. (2011). Dual Mechanism of Neuronal Ensemble Inhibition in Primary Auditory Cortex. *Neuron*, *69*(4). https://doi.org/10.1016/j.neuron.2011.01.012

Park, Y., & Geffen, M. N. (2020). A circuit model of auditory cortex. *PLoS Computational Biology*, *16*(7). https://doi.org/10.1371/journal.pcbi.1008016

Pérez-González, D., & Malmierca, M. S. (2014). Adaptation in the auditory system: An overview. In *Frontiers in Integrative Neuroscience* (Vol. 8, Issue FEB). https://doi.org/10.3389/fnint.2014.00019

Picton, T. W. (2010). *Human auditory evoked potentials*. Plural Publishing.

Pitts, W. (1952). Investigations on synaptic transmission. *Cybernetics, Trans. 9th Conf. Josiah Macy, New York*, 159–162.

Regehr, W. G. (2012). Short-Term Presynaptic Plasticity. *Cold Spring Harbor Perspectives in Biology*, *4*(7), 1–19. https://doi.org/10.1101/CSHPERSPECT.A005702

Rudy, B., Fishell, G., Lee, S. H., & Hjerling-Leffler, J. (2011). Three groups of interneurons account for nearly 100% of neocortical GABAergic neurons. *Developmental Neurobiology*, *71*(1). https://doi.org/10.1002/dneu.20853

Schaefer, M. K., Hechavarría, J. C., & Kössl, M. (2015). Quantification of mid and late evoked sinks in laminar current source density profiles of columns in the primary auditory cortex. *Frontiers in Neural Circuits*, *9*(OCT). https://doi.org/10.3389/fncir.2015.00052

Schroeder, C. E., Mehta, A. D., & Givre, S. J. (1998). A spatiotemporal profile of visual system activation revealed by current source density analysis in the awake macaque. *Cerebral Cortex*, *8*(7). https://doi.org/10.1093/cercor/8.7.575

Silberberg, G., Grillner, S., LeBeau, F. E. N., Maex, R., & Markram, H. (2005). Synaptic pathways in neural microcircuits. In *Trends in Neurosciences* (Vol. 28, Issue 10). https://doi.org/10.1016/j.tins.2005.08.004

Silberberg, G., & Markram, H. (2007). Disynaptic Inhibition between Neocortical Pyramidal Cells Mediated by Martinotti Cells. *Neuron*, *53*(5). https://doi.org/10.1016/j.neuron.2007.02.012

Steinschneider, M., Fishman, Y. I., & Arezzo, J. C. (2003). Representation of the voice onset time (VOT) speech parameter in population responses within primary auditory cortex of the awake monkey. *The Journal of the Acoustical Society of America*, *114*(1). https://doi.org/10.1121/1.1582449

Steinschneider, M., Reser, D. H., Fishman, Y. I., Schroeder, C. E., & Arezzo, J. C. (1998). Click train encoding in primary auditory cortex of the awake monkey: Evidence for two mechanisms

subserving pitch perception. *The Journal of the Acoustical Society of America*, *104*(5). https://doi.org/10.1121/1.423877

Steinschneider, M., Schroeder, C. E., Arezzo, J. C., & Vaughan, H. G. (1994). Speech-evoked activity in primary auditory cortex: effects of voice onset time. *Electroencephalography and Clinical Neurophysiology/ Evoked Potentials*, *92*(1). https://doi.org/10.1016/0168-5597(94)90005-1

Steinschneider, M., Tenke, C. E., Schroeder, C. E., Javitt, D. C., Simpson, G. v., Arezzo, J. C., & Vaughan, H. G. (1992). Cellular generators of the cortical auditory evoked potential initial component. *Electroencephalography and Clinical Neurophysiology/ Evoked Potentials*, *84*(2). https://doi.org/10.1016/0168-5597(92)90026-8

Studer, F., & Barkat, T. R. (2022). Inhibition in the auditory cortex. In *Neuroscience and Biobehavioral Reviews* (Vol. 132). https://doi.org/10.1016/j.neubiorev.2021.11.021

Sukov, W., & Barth, D. S. (1998). Three-dimensional analysis of spontaneous and thalamically evoked gamma oscillations in auditory cortex. *Journal of Neurophysiology*, *79*(6). https://doi.org/10.1152/jn.1998.79.6.2875

Sumner, R. L., Spriggs, M. J., & Shaw, A. D. (2021). Modelling thalamocortical circuitry shows that visually induced LTP changes laminar connectivity in human visual cortex. *PLoS Computational Biology*, *17*(1). https://doi.org/10.1371/journal.pcbi.1008414

Supèr, H., & Roelfsema, P. R. (2005). Chronic multiunit recordings in behaving animals: Advantages and limitations. In *Progress in Brain Research* (Vol. 147, Issue SPEC. ISS.). https://doi.org/10.1016/S0079-6123(04)47020-4

Tenke, C. E., & Kayser, J. (2012). Generator localization by current source density (CSD): Implications of volume conduction and field closure at intracranial and scalp resolutions. In *Clinical Neurophysiology* (Vol. 123, Issue 12). https://doi.org/10.1016/j.clinph.2012.06.005

Vaughan   H.G.Jr. (1988). The neural basis of event-related potentials. *Human Event-Related Potentials*, 45–96. http://ci.nii.ac.jp/naid/10008963195/ja/

Walker, F., Möck, M., Feyerabend, M., Guy, J., Wagener, R. J., Schubert, D., Staiger, J. F., & Witte, M. (2016). Parvalbumin-and vasoactive intestinal polypeptide-expressing neocortical interneurons impose differential inhibition on Martinotti cells. *Nature Communications*, *7*. https://doi.org/10.1038/ncomms13664

Wang, P., & Knösche, T. R. (2013). A realistic neural mass model of the cortex with laminar-specific connections and synaptic plasticity - evaluation with auditory habituation. *PLoS One*, *8*(10). https://doi.org/10.1371/journal.pone.0077876

Wang, P., Kong, R., Kong, X., Liégeois, R., Orban, C., Deco, G., van den Heuvel, M. P., & Yeo, B. T. T. (2019). Inversion of a large-scale circuit model reveals a cortical hierarchy in the dynamic resting human brain. *Tropical and Subtropical Agroecosystems*, *21*(3). https://doi.org/10.1126/sciadv.aat7854

Yavorska, I., & Wehr, M. (2016). Somatostatin-expressing inhibitory interneurons in cortical circuits. In *Frontiers in Neural Circuits* (Vol. 10, Issue SEP). https://doi.org/10.3389/fncir.2016.00076

1316