Building subtraction operators and controllers via molecular sequestration

Christian Cuba Samaniego[1,+], Yili Qian[3,+], Katelyn Carleton[1,+], Elisa Franco[1,2,*]

Abstract— **We show how subtraction can be performed via a simple chemical reaction network that includes molecular sequestration. The network computes the difference between the production rate parameters of the two mutually sequestering species. We benefit from introducing a simple change of variables, that facilitates the derivation of an approximate solution for the differential equations modeling the chemical reaction network, under a time scale separation assumption that is valid when the sequestration rate parameter is sufficiently fast. Our main result is that we provide simple expressions confirming that temporal subtraction occurs when the inputs are constant or time varying. Through simulations, we discuss two sequestration-based architectures for feedback control in light of the subtraction operations they perform.**

Index Terms— **Molecular sequestration, Chemical reactions, Molecular controllers, Biological systems.**

I. Introduction

MOLECULAR sequestration (titration) is a prevalent mechanism in biology that consists of the stoichiometric binding of two species. Sequestration can involve many classes of molecules; examples include RNA-RNA binding, transcription factors binding to promoters, enzymes and their substrates, receptors and their ligands, or antibodies and antigens. This binding process plays a crucial role in various biological processes, including signal transduction, regulation of gene expression, immune response, and metabolic pathways.

Is there an underlying operation being computed by molecular sequestration, that is key to enable a broad variety of functions? This question is difficult to answer in the native context of the cell, but there is evidence that sequestration enables the computation of the difference in the level of participating molecules [1], [2]. In synthetic biology, mathematical modeling has shown how to leverage this property to build molecular controllers [3]–[6], networks for frequency modulation [7], bistable switches with tunable hysteresis [8], [9], gradient detectors [10], [11], and biomolecular perceptrons [12]; some of these ideas have been experimentally demonstrated [13]–[16]. It is abundantly evident that sequestration helps compute the difference of two inputs *at steady-state* [1]–[4], and linear

analysis shows that it works as a sum junction [17]. However it has been challenging to make general statements about whether sequestration can compute differences when the inputs vary over time and in the presence of dilution/degradation. Another limitation that needs to be addressed is the fact that sequestration can only calculate the *positive part of a subtraction operation*, due to the biological nature of the participating components [18]. In this sense, it bears similarity to functions computing an absolute value [7].

Here we provide a complete temporal analysis of a molecular sequestration network, modeled through ordinary differential equations, and we show that it can compute differences in the presence of dilution/degradation, both transiently and at steady state. To come to this conclusion, we introduce a change of variables that makes it easier to apply time scale separation arguments, and decouples the system into a linear and non-linear part. We then find an approximate solution that is proportional to the difference of the molecular inputs, whether they are constant or time varying. We then discuss how sequestration can be used as a low-pass controller within biomolecular feedback loops. Through simulation we also show how low-pass controllers in a "dual rail" architecture improves the response speed of a feedback circuit tracking time-varying inputs. We expect that our modeling results will boost the use of sequestration within complex synthetic biological networks, and that they will facilitate the formulation of hypotheses about the role of sequestration in natural systems.

II. A model for molecular sequestration and its singular perturbation form

Our chemical network for subtraction includes two species, X and Y, that mutually sequester and bind to form a complex C (Fig. 1). We assume that X and Y have zero-order production rate parameters α and β. We model dilution/degradation as a first-order process with rate parameter ϕ, assumed to be the same for simplicity. The sequestration of X and Y happens with a constant rate parameter γ. We postulate that γ can be rescaled [3], [5]. The chemical reactions are:

$$
\begin{array}{lll}
\emptyset \xrightarrow{\alpha} X & \emptyset \xrightarrow{\beta} Y & \text{Production} \\
X \xrightarrow{\phi} \emptyset & Y \xrightarrow{\phi} \emptyset & \text{Decay} \\
X + Y \xrightarrow{\gamma} C & C \xrightarrow{\phi} \emptyset & \text{Sequestration/Decay.}
\end{array}
$$

From these reactions, we derive an Ordinary Differential Equation (ODE) model using the law of mass action:

This work has been partially supported by the BBRSC-NSF/BIO award 2020039 and by NSF CCF/SHF award 2107483 to EF

[1] Department of Mechanical and Aerospace Engineering, University of California at Los Angeles, CA 90095, USA. efranco@seas.ucla.edu, ccubasam@g.ucla.edu
[2] Department of Bioengineering, University of California at Los Angeles, CA 90095, USA.
[3] Department of Biochemistry, University of Wisconsin-Madison, Madison, WI 53706, United States. qian9@wisc.edu
[+] Authors contributed equally.
[*] Corresponding author.

$$\dot{x}(\tau) = \alpha(\tau) - \gamma x(\tau)y(\tau) - \phi x(\tau)$$
$$\dot{y}(\tau) = \beta(\tau) - \gamma x(\tau)y(\tau) - \phi y(\tau) \qquad (1)$$
$$\dot{c}(\tau) = \gamma x(\tau)y(\tau) - \phi c(\tau),$$

where the $\dot{x}$, $\dot{y}$, and $\dot{c}$ indicate derivatives with respect to the time variable. From these chemical reactions, we can immediately provide intuition as to why molecular sequestration realizes a subtraction operator, assuming $\alpha = \beta = 0$. First, sequestration implies there is a 1:1 binding ratio between X and Y (one molecule of X binds to one molecule of Y). Then, in the limit case where $\phi \to 0$, the final concentration of the non-limiting species is the difference between the initial concentrations of the sequestering species [1]. Suppose $x(0) > y(0)$: the final concentration of X (non-limiting species) will be equal to the difference in the initial concentrations $x(0) - y(0)$, given that all free Y (the limiting species) is bound into the complex C.

Chemical reactions of a molecular sequestration module

Fig. 1. Schematic of the reactions occurring in the molecular sequestration network considered here.

In practice, however, matters are made more complex due to the presence of time varying input functions $\alpha(\tau)$ and $\beta(\tau)$, and of degradation and dilution, scaled by parameter ϕ. Next, we illustrate how to examine this case by introducing an approximation valid for constant and time-changing inputs.

We now assume that functions $\alpha(\tau)$ and $\beta(\tau)$ are bounded and have a maximum. To obtain a non-dimensional model, we first rescale time as $t = \phi\tau$, and define new states variables $\hat{x} = \left(\frac{\phi}{m}\right)x$, $\hat{y} = \left(\frac{\phi}{m}\right)y$, $\hat{c} = \left(\frac{\phi}{m}\right)c$, and new rates $\hat{\alpha}(t) = \frac{\alpha(t/\phi)}{m}$, $\hat{\beta}(t) = \frac{\beta(t/\phi)}{m}$ and $\hat{\gamma} = \frac{m}{\phi^2}\gamma$, where $m = \max\left[\max\left[\alpha(\tau/\phi)\right], \max\left[\beta(\tau/\phi)\right]\right]$. Our non-dimensional model is now:

$$\dot{\hat{x}} = \hat{\alpha}(t) - \hat{\gamma}\hat{x}\hat{y} - \hat{x},$$
$$\dot{\hat{y}} = \hat{\beta}(t) - \hat{\gamma}\hat{x}\hat{y} - \hat{y}, \qquad (2)$$
$$\dot{\hat{c}} = \hat{\gamma}\hat{x}\hat{y} - \hat{c}.$$

Next, we apply a coordinate transformation that makes it possible to put the system in its singular perturbation form. We begin by applying a coordinate transformation:

$$\hat{x}^T = \hat{x} + \hat{c}, \qquad \hat{y}^T = \hat{y} + \hat{c}. \qquad (3)$$

The new variables $\hat{x}^T$ and $\hat{y}^T$ represent the total concentration of species X and Y, which includes molecules that are free

or bound to make the complex C, and system (2) becomes:

$$\dot{\hat{x}}^T = \hat{\alpha}(t) - \hat{x}^T,$$
$$\dot{\hat{y}}^T = \hat{\beta}(t) - \hat{y}^T, \qquad (4)$$
$$\dot{\hat{c}} = \hat{\gamma}(\hat{x}^T - \hat{c})(\hat{y}^T - \hat{c}) - \hat{c}.$$

Let $\xi := 1/\hat{\gamma}$, and system (4) can be put into a singular perturbation form:

$$\dot{\hat{x}}^T = \hat{\alpha}(t) - \hat{x}^T,$$
$$\dot{\hat{y}}^T = \hat{\beta}(t) - \hat{y}^T, \qquad (5)$$
$$\xi\dot{\hat{c}} = (\hat{x}^T - \hat{c})(\hat{y}^T - \hat{c}) - \xi\hat{c}.$$

Note that the first two equations of the system above are linear and do not depend on ξ. In the next sections, we use the transformed system (5) to demonstrate its capacity to perform a subtraction operation.

III. THE MOLECULAR SEQUESTRATION NETWORK PERFORMS A SUBTRACTION OPERATION

We will show that the solution $\hat{x}$ of system (2) satisfies:

$$\lim_{\xi \to 0} \hat{x}(t) = \hat{x}_p(t) \triangleq \max\left[0, (\hat{x}^T - \hat{y}^T)\right], \qquad (6)$$

in other words, $\hat{x}(t)$ can be approximated by $\hat{x}_p$, the *non-negative part of the subtraction* of variables $\hat{x}^T$ and $\hat{y}^T$ that capture the total amounts of molecules $\hat{x}$ and $\hat{y}$. It is also possible to prove that $\lim_{\xi \to 0} \hat{y}(t) = \hat{y}_p(t) \triangleq \max\left[0, (\hat{y}^T - \hat{x}^T)\right]$ with a similar approach. For the sake of brevity, we will focus exclusively on demonstrating (6).

To do so, we apply a time scale separation argument to system (5) by assuming that sequestration is significantly faster than the rest of the reactions ($\gamma \to \infty$ implies $\xi \to 0$) [19]. If the dynamics of $\hat{c}$ reach quasi-steady state, then:

$$\left[\hat{x}^T(t) - \hat{c}(t)\right]\left[\hat{y}^T(t) - \hat{c}(t)\right] - \xi\hat{c}(t) = 0. \qquad (7)$$

We now claim that it is possible to neglect term $-\xi\hat{c}(t)$ in equation (7), and we find:

$$\left[\hat{x}^T(t) - \hat{c}(t)\right]\left[\hat{y}^T(t) - \hat{c}(t)\right] = 0. \qquad (8)$$

The factored polynomial in equation (8) implies that $\hat{c}(t)$ should approach either $\hat{x}^T(t)$ or $\hat{y}^T(t)$ for $\xi \to 0$:

$$\hat{c}(t) \to \min\left[\hat{x}^T(t), \hat{y}^T(t)\right] = \begin{cases} \hat{y}^T(t) & \hat{x}^T(t) \geq \hat{y}^T(t) \\ \hat{x}^T(t) & \hat{x}^T(t) < \hat{y}^T(t) \end{cases} \qquad (9)$$

Because $\hat{x}(t) = \hat{x}^T(t) - \hat{c}(t)$, we have that:

$$\lim_{\xi \to 0} \hat{x}(t) = \hat{x}^T - \min\left[\hat{x}^T(t), \hat{y}^T(t)\right]$$
$$= \hat{x}_p(t) = \max\left[0, (\hat{x}^T(t) - \hat{y}^T(t))\right],$$

which is the expression at the beginning of this section. A similar reasoning can be repeated for $\hat{y}(t)$. If this claim holds, then $\hat{x}(t)$, taken as an output to the network, computes the difference between the total amount of $\hat{x}(t)$ and the the total amount of $\hat{y}(t)$. To justify the claim above, we must prove that

$$\hat{c}(t) \to \Gamma(\hat{x}^T, \hat{y}^T) \triangleq \min\left[\hat{x}^T(t), \hat{y}^T(t)\right]$$

as $\xi \to 0$ ($\hat{\gamma} \to \infty$). For this purpose, we define

$$e(t) \triangleq \Gamma(\hat{x}^T, \hat{y}^T) - \hat{c}(t) \qquad (10)$$

and aim to find an upper bound for $|e(t)|$, under certain technical conditions where $\hat{\alpha}(t)$ and $\hat{\beta}(t)$ are bounded. We next find bounds that are valid for constant or time varying inputs $\alpha(t)$ and $\beta(t)$.

Lemma 1. The dynamics of the error (10) satisfy $e(t) \geq 0$ for all $t \geq 0$.

Proof. The dynamics of (2) is positively invariant in the non-negative orthant $\mathbb{R}^3_{\geq 0}$. Since $\hat{x}^T(t) - \hat{c}(t) = \hat{x}(t) \geq 0$ and $\hat{y}^T(t) - \hat{c}(t) = \hat{y}(t) \geq 0$, we have $e(t) = \Gamma(t) - \hat{c}(t) = \min(\hat{x}^T, \hat{y}^T) - \hat{c}(t) \geq 0$. $\square$

The error dynamics can be written as:

$$D^+ e = D^+\Gamma - \frac{1}{\xi}(\hat{x}^T - \Gamma + e)(\hat{y}^T - \Gamma + e) + (\Gamma - e),$$
$$= D^+\Gamma - \frac{1}{\xi}e(\Lambda - \Gamma + e) + (\Gamma - e) \qquad (11)$$

where D^+ indicates right-hand derivative with respect to time and $\Lambda(\hat{x}^T, \hat{y}^T) \triangleq \max(\hat{x}^T, \hat{y}^T)$. We assume that the input signals are bounded and non-negative.

Assumption 1. There exist positive constants $\bar{\alpha}, \bar{\beta}$, independent of ξ, such that $0 \leq \hat{\alpha}(t) \leq \bar{\alpha}$ and $0 \leq \hat{\beta}(t) \leq \bar{\beta}$ for all $t \geq 0$. The initial conditions are such that $\hat{x}^T(0) \leq \bar{\alpha}$ and $\hat{y}^T(0) \leq \bar{\beta}$.

The assumptions on initial conditions $\hat{x}^T(0)$ and $\hat{y}^T(0)$ are for technical convenience and could be relaxed as the set $[0, \bar{\alpha}] \times [0, \bar{\beta}]$ is globally attractive for $(\hat{x}^T, \hat{y}^T)$. As a consequence of Assumption 1, the derivative $D^+\Gamma$ is bounded.

Lemma 2. There exists positive constants M and $\bar{\Gamma}$, independent of ξ, such that $|D^+\Gamma(\hat{x}^T, \hat{y}^T)| \leq M$ and $0 \leq \Gamma \leq \bar{\Gamma}$ for all $t \geq 0$.

Proof. Consider the dynamics of the slow variables $(\hat{x}^T, \hat{y}^T)$ in (5) $\dot{\hat{x}}^T = \hat{\alpha}(t) - \hat{x}^T$, $\dot{\hat{y}}^T = \hat{\beta}(t) - \hat{y}^T$. Given Assumption 1 and by the comparison principle, we have $0 \leq \hat{x}^T(t) \leq \bar{\alpha}$ and $0 \leq \hat{y}^T(t) \leq \bar{\beta}$ for all $t \geq 0$. Hence, we have $\dot{\hat{x}}^T \in [-\bar{\alpha}, \bar{\alpha}]$ and $\dot{\hat{y}}^T \in [-\bar{\beta}, \bar{\beta}]$. For this reason, there exists an ξ-independent constant M such that $|\dot{\hat{x}}^T(t)|, |\dot{\hat{y}}^T(t)| \leq M/2$ for all $t \geq 0$. Because $\Gamma(\hat{x}^T, \hat{y}^T) = \min(\hat{x}^T, \hat{y}^T)$, we have $|D^+\Gamma(\hat{x}^T, \hat{y}^T)| \leq |\dot{\hat{x}}^T(t)| + |\dot{\hat{y}}^T(t)| = M$. The bound on $\Gamma(t)$ is a trivial consequence of Assumption 1. $\square$

We will use comparison principle [20] to develop bounds for the error dynamics (11):

$$D^+ e = D^+\Gamma - \frac{1}{\xi}(\Lambda - \Gamma)e - \frac{e^2}{\xi} + \Gamma - e$$
$$\leq B - \frac{1}{\xi}e^2 - \frac{1}{\xi}\Delta(t)e, \qquad (12)$$

where we applied the results in Lemma 2, and $B \triangleq M + \bar{\Gamma} > 0$ and $\Delta(t) \triangleq \max(\hat{x}^T, \hat{y}^T) - \min(\hat{x}^T, \hat{y}^T)$ are both ξ-independent. The following Theorem states that, pick any $T > 0$ such that $\Delta(t)$ is bounded below by some ξ-independent

constant for all $t \leq T$, there exists a sufficiently small ξ such that $|e(t)| \leq \mathcal{O}(\sqrt{\xi})$ for all $t \geq T$.

Theorem 1. Under Assumption 1 and suppose that there exist ξ-independent constants $T, \delta > 0$ such that $\Delta(t) = \max(\hat{x}^T, \hat{y}^T) - \min(\hat{x}^T, \hat{y}^T) \geq \delta$ for all $0 \leq t \leq T$. Then there exists positive constants ξ^* and p, such that

$$|e(t)| \leq \sqrt{p\xi}, \quad \forall t \geq T, \quad \forall 0 < \xi < \xi^*. \qquad (13)$$

Proof. The proof consists of two parts. First, we show that for any $p > B$ the set $\Omega \triangleq [0, \sqrt{p\xi}]$ is positively invariant. This is because, by (12) and Lemma 1, for any $e \geq p$, we have $D^+ e \leq B - e^2/\xi \leq B - p^2/\xi < 0$. Hence, the set Ω is positively invariant. Next, we show that the set Ω is attractive, and for any $e(0) \notin \Omega$, there exists sufficiently small ξ for $e(t)$ to enter Ω in any chosen T. By inequality (12), we have

$$D^+ e \leq B - \frac{1}{\xi}\Delta(t)e \leq B - \frac{\delta}{\xi}e, \quad \forall t \leq T. \qquad (14)$$

By (14) and the comparison principle [20], we have

$$e(t) \leq \xi\frac{B}{\delta}\left(1 - \exp\left(-\delta t/\xi\right)\right) + e_0 \exp\left(-\delta t/\xi\right),$$
$$\forall t \leq T, \quad e_0 \triangleq e(0).$$

Hence $e(T) \leq \xi B/\delta + e_0 \exp(-\delta T/\xi) \leq 2\xi B/\delta$, if $g(\xi) \triangleq \xi \ln\left(\frac{\delta e_0}{2B\xi}\right) \leq T\delta$. Since $\lim_{\xi\to 0^+} g(\xi) = 0$ and $dg/d\xi(\xi) > 0$ for sufficiently small ξ, there exists an ξ^* such that $g(\xi) \leq T\delta$ for all $0 < \xi \leq \xi^*$. Therefore, $e(T) \in \Omega$ for any $\xi \leq \min\left(\frac{p\delta^2}{4B^2}, \xi^*\right)$. This completes the proof, as we showed that $e(t)$ enters the positively invariant set Ω of size $\mathcal{O}(\sqrt{\xi})$ at $t = T$ for sufficiently small ξ. $\square$

Because we have shown that $e(t)$ converges to zero when $\xi \to 0$, then expression (9) holds and so does our initial equation (6).

Remark 1. Note that the error bound is independent of the derivative of the inputs $\dot{\hat{\alpha}}(t)$ and $\dot{\hat{\beta}}(t)$. This is supported by the simulation in Fig. 2, where we varied the frequencies of the input sinusoidal signals but the error magnitude remains roughly constant. The simulation in Figure 2 shows that $\mathcal{O}(\sqrt{\xi})$ is a tight upper bound of the error dynamics. Simulations are carried out with $\hat{\alpha}(t) = 1.2 \cdot (1.1 + \sin(f \cdot t))$ and $\hat{\beta}(t) = 1.5 \cdot (1.1 + \cos(f \cdot t))$.

Fig. 2. **Error Analysis** Left: The magnitude of the error $e(t) = \min(\hat{x}^T, \hat{y}^T) - \hat{c}$ is plotted as a function of input frequency, f. The simulation is carried out using the setting described in Remark 1 and ξ is kept constant at 0.01. The error is largely independent of the input frequency. Right: the error magnitude is plotted as a function of ξ. The simulation is carried out using the setting described in Remark 1 and input frequency is kept constant at 0.1.

IV. Linear approximation and computational solution of the subtraction network

Building on the result of the previous section we can introduce a linear approximation, which holds for $\xi \to 0$, to the dynamics of the molecular sequestration network (1).

By taking the derivative of the right side of equation (6) (dimensional equations) and substituting the definition of $\dot{x}^T(t)$ and $\dot{y}^T(t)$, we find that:

$$\dot{x}_p(t) = \begin{cases} \alpha(t) - \beta(t) - \phi x_p(t), & x^T(t) \geq y^T(t), \\ 0, & x^T(t) < y^T(t). \end{cases} \quad (15)$$

Similarly, we can derive the approximation for $\hat{y}$:

$$\dot{y}_p(t) = \begin{cases} 0, & x^T(t) \geq y^T(t), \\ \beta(t) - \alpha(t) - \phi y_p(t), & x^T(t) < y^T(t). \end{cases}$$

These piecewise linear ODEs include two species whose dynamics are decoupled and can be solved exactly and independently. We can also map these ODEs to an "equivalent" chemical reaction network sketched in Fig. IV.

Fig. 3. **Equivalent chemical reactions** Left: original sequestration network. Right: equivalent reactions corresponding to the approximated dynamics (15).

When α and β are constant, the dynamics of x^T and y^T are linear (see the first two non dimensional equations in model (4)) and $x_p(t)$ can be found exactly. In Fig. 4A we show that the solution $x(t)$ (blue shades) of the nonlinear model (1) converges to the approximation x_p (black) as $\gamma \to \infty$ ($\xi \to 0$).

When the input rates $\alpha(t)$ and $\beta(t)$ are time varying, equations (15) can be easily integrated to obtain the estimates x_p and y_p without pre-computing x^T and y^T: inequality $x^T(t) < y^T(t)$ can be replaced by $x_p(t) < 0$, and $x^T(t) \geq y^T(t)$ can be replaced by $x_p(t) \geq 0$ (similarly for y and y_p).

We illustrate this with the simulations in Fig. 4B. As a test time-varying input we take $\alpha(t)$ to be a square wave that alternates between high (H) and low (L) values, while input $\beta(t)$ is kept constant. Fig. 4B, top, reports the trajectories for $x^T = x + c$ (red dotted line), $y^T = y + c$ (blue dotted line), and the approximate trajectory $x_p = x^T - y^T$ (15) (black solid line). Fig. 4B, center, compares the trajectories of x (solid blue line) and x_p (solid black line); this plot also shows that y (solid red line) is small but not zero. Fig. 4B, bottom, compares the trajectories of x (solid blue lines) for different values of sequestration constant γ and the ideal trajectory x_p (solid black line): larger γ results in the overlapping of x and x_p. To summarize, for sufficiently large γ (which is equivalent to taking a small ξ) the solution computed for these linear ODEs approaches the full solution of the nonlinear ODEs.

V. Building molecular feedback controllers through the subtraction operator

Network (1) has been used as a molecular feedback controller [21]. In this context, we re-examine the network by

Fig. 4. **Approximated solution of molecular sequestration** Behavior of the sequestration operator under (A) a constant inputs $\alpha = 1$ $\mu M/h$ and $\beta = 0.4$ $\mu M/h$ ($\gamma = 10/\mu M/h$) and (B) when we have a time-varying square wave input where $\alpha(t) = 0.5 \times sgn\left[\sin(\frac{2\pi t}{20} + 1)\right]/2 + 0.4\,\mu M/h$ and $\beta(t) = 0.2\,\mu M/h$. (B), left highlights how we are defining our approximation x_p (black) by the subtraction our new variables $x^T - y^T$. Recall that our new variables represent the total amount of the mutually sequestering species that is either free or bound to the complex c. The center panel compares the approximated dynamics of x_p (black) with the simulated dynamics of x (blue) and y (pink). In the final panel we observe that the simulated dynamics of x (blue) converge to the approximated dynamics x_p (black) as $\gamma \to \infty$.

focusing on its capacity to perform a subtraction operation and by taking advantage of the approximations derived earlier. Our goal is to regulate a standard protein production/degradation process, described by these chemical reactions:

$$X_1 \xrightarrow{\alpha_s} Y \quad Y \xrightarrow{\phi_s} \varnothing \quad \text{Production and Decay of } Y$$

where we do not have direct control over α_s and ϕ_s, while we can manipulate the abundance of species X_1. We want to match the level of the process Y with the level of a reference species R (Fig. 5B and C, gray box).

A low-pass controller (LPC) We begin by applying the analysis described earlier to a leaky molecular sequestration controller [5]: this exercise is useful as it brings out its inherent similarity to a low-pass controller (LPC). We introduce two controller species, X_1 and Z_1. The reference species R produces X_1 at a rate parameter θ_c; to close the loop, we use species Y (process output) to induce the production of species Z_1 at a rate parameter κ_c. The controller species X_1 and Z_1 sequester each other at a rate parameter γ_c (forming a complex C), and they decay at rate parameter ϕ_c. The reactions are summarized below (blue box in Fig. 5A):

$$
\begin{array}{lll}
R \xrightarrow{\theta_c} X_1 & Y \xrightarrow{\kappa_c} Z_1 & \text{Production} \\
X_1 \xrightarrow{\phi_c} \varnothing & Z_1 \xrightarrow{\phi_c} \varnothing & \text{Decay} \\
& X_1 + Z_1 \xrightarrow{\gamma_c} C_1 & \text{Sequestration.}
\end{array}
$$

Through the law of mass action, the closed loop model is:

$$\dot{x}_1 = \theta_c r - \gamma_c x_1 z_1 - \phi_c x_1,$$
$$\dot{z}_1 = \kappa_c y - \gamma_c x_1 z_1 - \phi_c z_1, \qquad (16)$$
$$\dot{c} = \gamma_c x_1 z_1 - \phi_c c.$$
$$\dot{y} = \alpha_s x_1 - \phi_s y,$$

Our previous analysis of molecular sequestration in the parameter regime $\gamma \to \infty$) allows us to derive a simple interpretation of how this controller works. Through a change of variable $x_1^T = x_1 + c$, and $z_1^T = z_1 + c$ we can find the approximated solution to $x_1(t)$:

$$\dot{x}_{1,p}(t) = \begin{cases} \theta_c r(t) - \kappa_c y(t) - \phi_c x_{1,p}(t) & x_1^T(t) \geq z_1^T(t) \\ 0 & x_1^T(t) < z_1^T(t), \end{cases} \quad (17)$$

and similarly we can find the dynamics of $z_{1,p}$. By defining the rescaled error $e = \frac{\theta_c}{\kappa_c} r(t) - y(t)$, it is easy to derive the transfer function mapping e to $x_{1,p}$. When $x_1^T(t) \geq z_1^T(t)$ we have :

$$X_{1,p}(j\omega) = \frac{\kappa_c}{j\omega + \phi_c} E(j\omega) = C(j\omega)\, E(j\omega), \qquad (18)$$

when $x_1^T(t) < z_1^T(t)$, $X_{1,p}(j\omega) = 0$. In expression (18), $C(j\omega)$ is an LPC with gain κ_c and corner frequency $-\phi_c$. At low frequencies ($\omega << \phi_c$), $C(j\omega)$ behaves like a proportional controller with gain κ_c/ϕ_c. For $\phi_c \to 0$, i.e. in the absence of dilution/degradation, $C(j\omega)$ becomes an integrator $C(j\omega) = \kappa_c/j\omega$, consistently with dilution-free sequestration controllers [3]. It is known that ideal integral behavior is possible only in the absence of dilution/degradation [5]. In the presence of degradation, the leaky molecular sequestration controller can only achieve quasi-integral action: fast sequestration and large production rate parameters [5], [15], [16], or input-output ultrasensitivity [5], [22] are required to minimize the steady-state error between reference and output.

A dual-rail controller (DRC) It is apparent that the approximated output $x_{1,p}$ of our controller (17) is non-zero only when $x_1^T(t) \geq z_1^T(t)$, meaning that it only responds to the positive part of the difference between $x_1^T(t)$ and $z_1^T(t)$. When $x_1^T(t) \leq z_1^T(t)$, a positive response could be obtained through $z_{1,p}$ as a second output, or by including a second controller. So we propose a "dual rail" architecture that combines two controllers in parallel and should improve the performance of the single low-pass controller. To build a dual rail controller (DRC), we connect two sequestration networks in parallel and one in series, and we show that this architecture allows a faster response when compared to a single sequestration module. This idea builds on previous work introducing dual rail molecular circuits [18] and feedback controllers [23], [24] in the context of DNA nanotechnology.

The DRC is sketched in the orange box in Fig. 5B: it includes three sequestration reactions, and two outputs, species X_1 that directly regulates the output Y (like in the single rail controller) and species W which removes output Y. The first sequestration reaction is identical to the single rail controller and produces X_1. The second sequestration reaction consists of species X_2 and Z_2: when compare to the single rail controller, the inputs to this reaction are swapped. The reactions are:

$$R \xrightarrow{\theta_c} Z_2 \qquad Y \xrightarrow{\kappa_c} X_2 \qquad \text{Production}$$
$$X_2 \xrightarrow{\phi_c} \varnothing \qquad Z_2 \xrightarrow{\phi_c} \varnothing \qquad \text{Decay}$$
$$X_2 + Z_2 \xrightarrow{\gamma_c} C_2 \qquad \text{Sequestration.}$$

The third sequestration reaction serves as a mechanism to actively produce and remove plant species Y, and includes the reactions:

$$X_1 \xrightarrow{\alpha_s} Y \qquad Y \xrightarrow{\phi_s} \varnothing \qquad \text{Production/Decay}$$
$$X_2 \xrightarrow{\beta_s} W \qquad W \xrightarrow{\phi_s} \varnothing \qquad \text{Production/Decay}$$
$$Y + W \xrightarrow{\gamma_s} C \qquad \text{Sequestration}$$

The closed loop system including the dual rail controller is:

$$\dot{x}_1 = \theta_c r - \gamma_c x_1 z_1 - \phi_c x_1,$$
$$\dot{z}_1 = \kappa_c y - \gamma_c x_1 z_1 - \phi_c z_1,$$
$$\dot{x}_2 = \kappa_c y - \gamma_c x_2 z_2 - \phi_c x_2,$$
$$\dot{z}_2 = \theta_c r - \gamma_c x_2 z_2 - \phi_c z_2, \qquad (19)$$
$$\dot{y} = \alpha_s x_1 - \gamma_c y w - \phi_s y,$$
$$\dot{w} = \beta_s x_2 - \gamma_c y w - \phi_s w.$$

We omit the dynamics of c_1 (formed by binding of x_1 and z_1), c_2 (formed by x_2 and z_2) and c_3 (formed by y and w).

LPC and DRC performance comparison Fig. 5C shows example kinetic traces of the LPC and DRC, showing that the LPC tracks the reference with a larger steady state error. This error may due to the presence of dilution $\phi_c \neq 0$ (non-ideal integral controller), or to poor error computation - intended here as the computation of the positive part of the error only. This controller can actively increase y (positive action), while only dilution/degradation can decrease the amount of y. This type of control strategy with just positive action leads to a trade-off between the controller dynamics (that increases y) and the process dynamics (that removes y). When $\phi_c \neq 0$ the gain κ_c/ϕ_c decreases, contributing to a larger steady state error. Even in the presence of dilution, the DRC shows a reduced error presumably because it actively increases and reduces y (using the full error computation).

Fig. 5D shows the "empirical" frequency response of the two controllers as the sequestration rate γ_c or the decay rate ϕ_c are varied. The controller equations in the LPC model (16) and DRC model (19) were fed a periodic input reference $\theta_c r = 0.5(sin(ft)+1)/2 + 0.3 \ \mu M/h$, and fixed $\kappa_c y = 0.3 \ \mu M/h$. We then numerically integrated the equations, and measured amplitude and frequency of the output x_1 for the LPC, and the difference of $x_1 - x_2$ (these species deliver opposite actuation on the plant) for the DRC. In these simulations (blue for the LPC, orange for the DRC) we vary either the sequestration rate γ_c or the decay rate ϕ_c parameter. Both plots resemble the Bode plot of an LPC with a corner frequency near ϕ_c. In the left panel (ϕ_c=1, γ_c varies), the "DC gain" of the DRC does not depend on the sequestration constant γ_c as the LPC. In the right panel, (ϕ_c varies, $\gamma_c = 10$) the corner frequency moves as the value of ϕ_c. There is a small offset between the LPC and the DRC, that is inversely proportional to ϕ_c: as ϕ_c decreases, passive down-regulation is reduced and the DRC performs better than the LPC.

Finally, Fig. 5E illustrates the closed loop performance when the reference is a sinusoid, as individual parameters are changed. We assume $\theta_c = \kappa_c$ in all cases. Larger values of $\theta_c = \kappa_c$ improve the tracking performance of both LPC and DRC, however the LPC always shows a significant larger error. Increasing or decreasing ϕ_c in the LPC does not improve its tracking behavior, while for $\phi_c \to 0$ the DRC shows error reduction. When γ_c is varied, even at small values the DRC maintains better tracking when compared to the LPC. When the plant parameter α_s is perturbed, the DRC confirms to be better at rejecting this disturbance. When changing the plant dilution constant ϕ_s, the DRC performance improves for smaller values, while the LPC performance deteriorates.

Fig. 5. **Simulations comparing controller performance** Reaction schematics of the LPC (A) and DRC (B). (C) Example trajectories under a square wave input. (D) Empirical frequency analysis. (E) Tracking a sinusoidal reference under variation of individual parameters of the controllers ($\theta_c = k_c$, ϕ_c , γ_c) and of the plant (α_s, ϕ_s). The nominal parameters are $\theta_c = k_c = 10 \ /h$, $\gamma_c = \gamma_s = 10 \ /\mu M/h$, $\alpha_s = \beta_s = \phi_s = \phi_c = 1 \ /h$.

VI. CONCLUSION

We have described an approximation of the dynamic behavior of molecular sequestration that illustrates how sequestration computes the difference between input signals that are constant or time-varying. The approximation we derived is useful to illustrate how leaky molecular sequestration controllers can be considered low-pass controllers that process only one side of the subtraction operation. Through simulations, we showed that a dual rail controller, that completes the subtraction operation, achieves a lower tracking error across parameter variations. We envision that our approximation will help simplify and generalize the design of biomolecular controllers.

REFERENCES

[1] N. E. Buchler and F. R. Cross, "Protein sequestration generates a flexible ultrasensitive response in a genetic network," *Molecular systems biology*, vol. 5, no. 1, p. 272, 2009.

[2] C. Cosentino, R. Ambrosino, M. Ariola, M. Bilotta, A. Pironti, and F. Amato, "On the realization of an embedded subtractor module for the control of chemical reaction networks," *IEEE Transactions on Automatic Control*, vol. 61, no. 11, pp. 3638–3643, 2016.

[3] C. Briat, A. Gupta, and M. Khammash, "Antithetic integral feedback ensures robust perfect adaptation in noisy biomolecular networks," *Cell systems*, vol. 2, no. 1, pp. 15–26, 2016.

[4] D. K. Agrawal, X. Tang, A. Westbrook, R. Marshall, C. S. Maxwell, J. Lucks, V. Noireaux, C. L. Beisel, M. J. Dunlop, and E. Franco, "Mathematical modeling of RNA-based architectures for closed loop control of gene expression," *ACS synthetic biology*, vol. 7, no. 5, pp. 1219–1228, 2018.

[5] Y. Qian and D. Del Vecchio, "Realizing 'integral control' in living cells: how to overcome leaky integration due to dilution?" *Journal of The Royal Society Interface*, vol. 15, no. 139, p. 20170902, 2018.

[6] N. Olsman, A.-A. Baetica, F. Xiao, Y. P. Leong, R. M. Murray, and J. C. Doyle, "Hard limits and performance tradeoffs in a class of antithetic integral feedback networks," *Cell systems*, vol. 9, no. 1, pp. 49–63, 2019.

[7] C. C. Samaniego and E. Franco, "A molecular device for frequency doubling enabled by molecular sequestration," in *2019 18th European Control Conference (ECC)*. IEEE, 2019, pp. 2146–2151.

[8] D. Chen and A. P. Arkin, "Sequestration-based bistability enables tuning of the switching boundaries and design of a latch," *Molecular systems biology*, vol. 8, no. 1, p. 620, 2012.

[9] X. Ren, C. C. Samaniego, R. M. Murray, and E. Franco, "Bistable state switch enables ultrasensitive feedback control in heterogeneous microbial populations," in *2021 American Control Conference (ACC)*. IEEE, 2021, pp. 652–659.

[10] C. C. Samaniego, G. Giordano, and E. Franco, "Practical differentiation using ultrasensitive molecular circuits," in *2019 18th European Control Conference (ECC)*. IEEE, 2019, pp. 692–697.

[11] C. C. Samaniego, J. Kim, and E. Franco, "Sequestration and delays enable the synthesis of a molecular derivative operator," in *2020 59th IEEE Conference on Decision and Control (CDC)*. IEEE, 2020, pp. 5106–5112.

[12] A. Moorman, C. C. Samaniego, C. Maley, and R. Weiss, "A dynamical biomolecular neural network," in *2019 IEEE 58th Conference on Decision and Control (CDC)*. IEEE, 2019, pp. 1797–1802.

[13] E. Franco, G. Giordano, P.-O. Forsberg, and R. M. Murray, "Negative autoregulation matches production and demand in synthetic transcriptional networks," *ACS synthetic biology*, vol. 3, no. 8, pp. 589–599, 2014.

[14] V. Hsiao, E. L. De Los Santos, W. R. Whitaker, J. E. Dueber, and R. M. Murray, "Design and implementation of a biomolecular concentration tracker," *ACS synthetic biology*, vol. 4, no. 2, pp. 150–161, 2015.

[15] H.-H. Huang, Y. Qian, and D. Del Vecchio, "A quasi-integral controller for adaptation of genetic modules to variable ribosome demand," *Nature communications*, vol. 9, no. 1, pp. 1–12, 2018.

[16] S. K. Aoki, G. Lillacci, A. Gupta, A. Baumschlager, D. Schweingruber, and M. Khammash, "A universal biomolecular integral feedback controller for robust perfect adaptation," *Nature*, vol. 570, no. 7762, pp. 533–537, 2019.

[17] H. Steel, A. W. Harris, E. J. Hancock, C. L. Kelly, and A. Papachristodoulou, "Frequency domain analysis of small non-coding rnas shows summing junction-like behaviour," in *2017 IEEE 56th Annual Conference on Decision and Control (CDC)*. IEEE, 2017, pp. 5328–5333.

[18] K. Oishi and E. Klavins, "Biomolecular implementation of linear i/o systems," *IET systems biology*, vol. 5, no. 4, pp. 252–260, 2011.

[19] Y. Qian and D. Del Vecchio, "A singular singular perturbation problem arising from a class of biomolecular feedback controllers," *IEEE Control Systems Letters*, vol. 3, no. 2, pp. 236–241, 2018.

[20] H. K. Khalil, *Nonlinear systems*, 3rd ed. Upper Saddle River, New Jersey: Prentice Hall, 2002.

[21] M. Filo, C.-H. Chang, and M. Khammash, "Biomolecular feedback controllers: from theory to applications," *Current Opinion in Biotechnology*, vol. 79, p. 102882, 2023.

[22] C. C. Samaniego and E. Franco, "Ultrasensitive molecular controllers for quasi-integral feedback," *Cell Systems*, vol. 12, no. 3, pp. 272–288, 2021.

[23] N. M. Paulino, M. Foo, J. Kim, and D. G. Bates, "PID and state feedback controllers using DNA strand displacement reactions," *IEEE Control Systems Letters*, vol. 3, no. 4, pp. 805–810, 2019.

[24] M. Whitby, L. Cardelli, M. Kwiatkowska, L. Laurenti, M. Tribastone, and M. Tschaikowski, "Pid control of biochemical reaction networks," *IEEE Transactions on Automatic Control*, 2021.