Oscillatory waveform shape and temporal spike correlations differ across bat frontal and auditory cortex

Authors: Francisco García-Rosales[1*], Natalie Schaworonkow[1], Julio C. Hechavarria[2].

Affiliations: [1] Ernst Strüngmann Institute (ESI) for Neuroscience in Cooperation with Max Planck Society, 60528 Frankfurt am Main, Germany; [2] Institut für Zellbiologie und Neurowissenschaft, Goethe-Universität, 60438 Frankfurt/M., Germany.

[*] *Corresponding author.*

Mailing address: Francisco García-Rosales, Ernst Strüngmann Institute (ESI) for Neuroscience in Cooperation with Max Planck Society, Deutschordenstraße 46, 60528 Frankfurt am Main, Germany; Tel. (+49) 69 / 96769 123. Email: francisco.garcia-rosales@esi-frankfurt.de

Number of pages: 35

Number of figures: 9

Number of words (Abstract): 211

Number of words (Introduction): 650

Number of words (Discussion): 1425

Conflict of interests: The authors declare no conflicting financial or non-financial interests.

Acknowledgments: This work was supported by the DFG (Grant No. HE 7478/1-1, to J.C.H.), the Joachim-Herz Foundation (fellowship granted to F.G.R.), and a Marie Skłodowska-Curie Actions Postdoctoral Fellowship (grant No. 101062497, to N.S.).

Abstract

Neural oscillations are associated with diverse computations in the mammalian brain. The waveform shape of oscillatory activity measured in cortex relates to local physiology, and can be informative about aberrant or dynamically changing states. However, how waveform shape differs across distant yet functionally and anatomically related cortical regions is largely unknown. In this study, we capitalize on simultaneous recordings of local field potentials (LFPs) in the auditory and frontal cortices of awake, male *Carollia perspicillata* bats to examine, on a cycle-by-cycle basis, waveform shape differences across cortical regions. We find that waveform shape differs markedly in the fronto-auditory circuit even for temporally correlated rhythmic activity in comparable frequency ranges (i.e. in the delta and gamma bands) during spontaneous activity. In addition, we report consistent differences between areas in the variability of waveform shape across individual cycles. A conceptual model predicts higher spike-spike and spike-LFP correlations in regions with more asymmetric shape, a phenomenon that was observed in the data: spike-spike and spike-LFP correlations were higher in frontal cortex. The model suggests a relationship between waveform shape differences and differences in spike correlations across cortical areas. Altogether, these results indicate that oscillatory activity in frontal and auditory cortex possess distinct dynamics related to the anatomical and functional diversity of the fronto-auditory circuit.

Significance statement

The brain activity of many animals displays intricate oscillations, which are usually characterized in terms of their frequency and amplitude. Here, we study oscillations from the bat frontal and auditory cortices on a cycle-by-cycle basis, additionally focusing on their characteristic waveform shape. The study reveals clear differences across regions in waveform shape and oscillatory regularity, even when the frequency of the oscillations is similar. A conceptual model predicts that more asymmetric waveforms result from stronger correlations between neural spikes and electrical field activity. Such predictions were supported by the data. The findings shed light onto the unique properties of different cortical areas, providing key insights into the distinctive physiology and functional diversity within the fronto-auditory circuit.

Introduction

Rhythmic neural activity at various timescales underpins several functions in the mammalian brain. In the frontal cortex, oscillations of local-field potentials (LFPs) in low and high frequencies are implicated in cognitive and executive control (Helfrich and Knight, 2019; Insel et al., 2012; Rajan et al., 2019; Tavares and Tort, 2022; Veniero et al., 2021; Zhang et al., 2016), while rhythmic activity in sensory cortices is linked with the effective encoding of incoming stimuli (Gourevitch et al., 2020; Gross et al., 2007; Kienitz et al., 2021; Lakatos et al., 2007; Tan et al., 2019; Teng et al., 2017; Uran et al., 2022). These oscillations reflect the underlying dynamics of their generating motifs, which determine several of their properties, including waveform shape (Cole and Voytek, 2017). Indeed, waveform shape and related features change in the developing brain (Schaworonkow and Voytek, 2021) and possess atypical characteristics in disease (Cole and Voytek, 2019; Cole et al., 2017; Jackson et al., 2019). Waveform patterns of oscillatory activity can provide important insights into the physiology and function of the neocortex, yet how they differ across cortical regions remains largely unstudied.

In this work, we examine oscillatory waveform shape in the frontal and auditory cortices of a mammalian vocal specialist, the bat *Carollia perspicillata*. The bat auditory cortex (AC) is a well-studied structure that presents both spontaneous and stimulus-driven rhythmic patterns of neuronal activity (Garcia-Rosales et al., 2019; Hechavarria et al., 2016; Medvedev and Kanwal, 2004). As in other mammals (Lakatos et al., 2005; Luo and Poeppel, 2007; Neymotin et al., 2022; Teng et al., 2017), LFPs in the bat AC track the temporal dynamics of acoustic sequences with periodic and quasi-periodic temporal structures (Garcia-Rosales et al., 2018). LFPs in *C. perspicillata*'s AC exhibit clear coupling with neuronal spiking, potentially coordinating single-cell responses to acoustic stimuli and contributing actively to the encoding of multi-syllabic communication sounds (Garcia-Rosales et al., 2018).

In the frontal cortex, we focused on the frontal auditory field (FAF), a structure specialized in auditory-related behaviour (Eiermann and Esser, 2000; Kanwal et al., 2000; Kobler et al., 1987). This region is anatomically connected with the AC, but receives also relatively fast inputs from an alternative pathway bypassing midbrain and cortex (Kobler et al., 1987). Pre- and post-vocal dynamics in the FAF, as well as its functional connectivity patterns with the AC and the striatum, implicate this region in the control of vocalization behaviour (Garcia-Rosales et al., 2022b; Weineck et al., 2020). Furthermore, the FAF is anatomically connected with the superior colliculus, suggesting that it may be involved in coordinating fast movements based on the bat's auditory environment (Casseday et al., 1989; Kobler et al., 1987). The nature of FAF-AC interconnectivity suggests that the FAF plays a crucial role in the integration of auditory feedback for the coordination of rapid auditory-based behaviour (Garcia-Rosales et al., 2022b). These data indicate that, while the AC operates as a classical sensory cortex, the FAF acts as part of a control and integration hub.

While low- and high-frequency oscillatory activities in the bat FAF-AC network are functionally related, it is
unknown how they differ in terms of waveform shape. Characterizing waveform shape differences across
cortical regions could be an informative step towards understanding how neuronal oscillations in these
areas differ, and thus constrain hypotheses about the mechanisms underlying neural activity across
structures. By means of simultaneous electrophysiological recordings and cycle-by-cycle analyses of
neural oscillations, we show that the waveform shape and variability of frontal- and auditory-cortical
oscillations differ markedly in delta and gamma frequencies. We demonstrate a relationship between
waveform shape and spike correlations by modelling and computing spike-field measures. We argue that
these differences reflect physiological disparities in the FAF-AC circuit, and establish a potential link
between spike timing and waveform shape. Our results support the notion of heterogeneity of cortical
rhythms in the mammalian brain, and stress the importance of waveform shape for understanding cortical
physiology and function.

Materials and Methods

<u>Animal preparation and surgical procedures</u>

The study was conducted on two awake *Carollia perspicillata* bats (2 males), which were obtained from a
colony at the Goethe University, Frankfurt. All experimental procedures were in compliance with
European regulation and were approved by the relevant local authorities (Regierungspräsidium
Darmstadt, experimental permit #FU-1126). Animals used in experiments were kept isolated from the
main colony, with a reversed light-dark cycle (i.e. lights off from 12:00 to 00:00; this applies to all bats in
the colony as well).

The data presented in this work were collected as part of a previous study (Garcia-Rosales et al., 2022b),
where a detailed description of the surgical procedures can be found. In brief, bats were anesthetized
with a mixture of ketamine (10 mg*kg^{-1}, Ketavet, Pfizer) and xylazine (38 mg*kg^{-1}, Rompun, Bayer), and
underwent surgery in order to expose the skull in the areas of the frontal and auditory cortices. A metal
rod (ca. 1 cm length, 0.1 cm diameter) was glued onto the bone for head fixation during
electrophysiological recordings. A local anaesthetic (ropivacaine hydrochloride, 2 mg/ml, Fresenius Kabi,
Germany) was applied subcutaneously around the scalp area prior any handling of the wounds. The
precise locations of the FAF and AC were determined by means of well-described landmarks, including
the sulcus anterior and prominent blood vessel patterns (Eiermann and Esser, 2000; Esser and
Eiermann, 1999; Garcia-Rosales et al., 2020). Access to the frontal and auditory regions of the left
hemisphere was gained by cutting small holes (ca. 1 mm^2) with a scalpel blade on the first day of
recordings. Electrophysiological recordings in the AC were made mostly in the high frequency fields
(Esser and Eiermann, 1999).

After the surgery animals were given sufficient time to recover (no less than 2 days) before the beginning

of experimental sessions. A session did not last more than 4 hours per day. Water was offered to the bats

every 1 – 1.5 hours. Experiments were halted if an animal showed any signs of discomfort (e.g. as

excessive movement). No animal was used on two consecutive days for recordings.

Electrophysiological recordings

Electrophysiological measurements were made acutely from fully awake animals in a sound-proofed and

electrically isolated chamber. Inside the chamber, bats were placed on a custom-made holder kept at a

constant temperature of 30 °C using a heating blanket (Harvard, Homeothermic blanket control unit).

Data were acquired simultaneously from the FAF and AC of the left hemisphere using two 16-channel

laminar probes (Model A1x16, NeuroNexus, MI; 50 µm channel spacing, impedance: 0.5–3 MΩ per

electrode). For each paired FAF-AC recording, probes were carefully inserted into the tissue using piezo

manipulators (one per probe; PM-101, Science products GmbH, Hofheim, Germany), perpendicular to the

cortical surface, until the top channel was barely visible above the surface. The typical width of *C.*

perspicillata's cortex, and the total span of the electrodes in the probes (750 μm) allowed us to record

from all six cortical layers at once (see Garcia-Rosales et al. (2022b); Garcia-Rosales et al. (2019)). From

one paired recording to the next in the same experimental session, probes were retracted from the

cortical tissue and moved to a new location within the craniotomy in FAF or AC, as distant as possible

form previous recording sites within that craniotomy. New recording locations were chosen at the

beginning of each experimental session.

Probes in FAF and AC were connected to micro-preamplifiers (MPA 16, Multichannel Systems MCS

GmbH, Reutlingen, Germany), while acquisition was done with a single 32-channel system with

integrated digitization (sampling frequency, 20 kHz; precision, 16 bits) and amplification steps (Multi

Channel Systems MCS GmbH, model ME32 System, Germany). Silver wires were used as references

electrodes for each recording shank (i.e. in FAF and AC) placed at different areas of the brain (for FAF:

non-auditory lateral ipsilateral region; for AC: non-auditory occipital ipsilateral region). The silver wires

were carefully positioned between the skull and the dura matter. The reference and the ground of each

probe were short-circuited, and the ground was ultimately common in the acquisition system (the ME32).

Recordings were monitored online and stored in a computer using the MC_Rack_Software (Multi Channel

Systems MCS GmbH, Reutlingen, Germany; version 4.6.2). Due to technical reasons, the signal from one

FAF channel (depth: 500 μm) was linearly interpolated from its immediate neighbours.

Pre-processing of spiking and LFP signals

All data analyses were made using custom-written Python scripts. Raw data from the recording system

were converted to H5 format using Multichannel System's *McsPyDataTools* package

(https://github.com/multichannelsystems/McsPyDataTools, version 0.4.3), and were then parsed and

handled with *Syncopy* (https://github.com/esi-neuroscience/syncopy, version 2022.8). Local-field

potentials were obtained by filtering the raw data with a low pass Butterworth filter (4th order) with a cut-off

frequency of 300 Hz. For computational convenience, LFP signals were then downsampled to 5 kHz. On

occasions a sharp spectral peak at 100 Hz was present in the recordings, corresponding to a harmonic of

the line noise. We were discouraged to use LFPs close (or above) to 100 Hz in the analyses for the

following reasons: (i) frequencies close to 100 Hz would be affected by the line noise harmonic; and (ii)

high frequency LFPs (> 100 Hz) can be directly influenced by spiking activity in the form of, for example,

spike-bleed through (Ray, 2015). Spike bleed-through constitutes a potential confound that we sought to

avoid.

For the detection of multi-unit activity, the raw data was bandpass filtered between 300 and 3000 Hz with

a 4th order Butterworth filter. Spikes were detected based on threshold crossing: we defined a spike as a

peak with an amplitude of at least 3.5 standard deviations relative all samples in the signal. Only peaks

separated by at least 2 ms were considered.

<u>Spectral analyses</u>

Power spectral densities (PSDs) were computed using Welch's method (segment length 20480 samples,

i.e. 4096 ms) implemented in *scipy* (version 1.9.1). PSDs were calculated independently for each LFP

trace (all channels in the N = 29 recordings in both FAF and AC). LFP traces were typically *circa*, but not

shorter than, 1200 s long (median: 1239.5 s; 25th percentile: 1252.8 s; 75th percentile: 1423.9 s). The

power of each recording was parametrized using a spectral parametrization model (Donoghue et al.,

2020), with which a 1/f fit of the PSD was computed. All fits had an R^2 > 0.93 (mean: 0.9965, s.e.m.:

0.001).

We reasoned that significant deviations of the power spectrum from the 1/f fit potentially represented

oscillatory activity at a given frequency range. Thus, we normalized each power spectrum by its 1/f

component to highlight spectral peaks in FAF and AC. Normalized values would hover around 0 in the

case of no spectral peaks, and would be consistently greater than 0 for frequencies in which LFPs

presented clear deviations from the underlying 1/f trend. For each channel, we considered a significant

deviation from the 1/f if the normalized power at a certain frequency was significantly larger than 0 (FDR-

corrected, two-sided one-sample t-tests, p_{corr} < 0.05). This analysis was done for each individual animal

(Bat-01, N = 15; Bat-02, N = 14), for frequencies ranging from 1 to 120 Hz. From the results in the two

bats, we established the following frequency bands of interest: delta (1–4 Hz) and gamma (65–85 Hz).

<u>Cycle-by-cycle analyses</u>

For detecting oscillatory bursts in the frequencies of interest we used the *bycycle* package ((Cole and

Voytek, 2019), version 1.0.0). The *bycycle* algorithm makes it possible to detect individual cycles in

frequency range of interest (here, the frequency bands outlined above), and then to determine whether

detected cycles belong to so-called "oscillatory bursts". An oscillatory burst consists of a sequence of

cycles (at least 3 in this study) with stable temporal properties that are mainly summarized as follows:

amplitude consistency, period consistency, and monotonicity (rise and decay flanks of cycles in a burst

should be mostly monotonic). Furthermore, one parameter controls for signal-to-noise ratio (SNR): the

amplitude fraction threshold (see **Fig. 2A**). This parameter rejects cycles whose amplitudes are below a

certain percentile relative to the amplitude of all cycles in a given trace. As in (Schaworonkow and Voytek,

2021), we chose the following thresholds for cycle detection: Amplitude fraction threshold, 0.5; Amplitude

consistency threshold, 0.5; Period consistency threshold, 0.5; Monotonicity threshold, 0.5.

Each cycle was characterized according to the following features, which determine waveform shape:

cycle period (i.e. the duration of each cycle), cycle rise-decay asymmetry (the asymmetry between rise

and decay times in the cycle), and cycle peak-trough asymmetry (the asymmetry in duty cycle; see also

(Cole and Voytek, 2019; Schaworonkow and Voytek, 2021)). Bursts were characterized according to their

duration (the sum of the individual duration of each cycle in the burst). Only cycles that were part of

oscillatory bursts were used for further analyses.

To compare cycle features across different recording sites (e.g. between channels in FAF and AC), we

defined the value of a given feature for a certain recording as the median value of that feature across all

detected cycles in the recording. This was made per LFP trace, therefore yielding one value per recording

site (N = 29 paired FAF-AC sites, across 16 channels; data from the two bats were pooled as spectral

and bursting patterns were highly consistent across animals). Given that data from FAF and AC were

acquired simultaneously for each paired recording, the above allowed us to compare across sites using

paired statistics (FDR-corrected Wilcoxon signed-rank tests, significant for $p_{corr} < 0.05$). Only values

derived from simultaneously recorded LFP traces were compared to one another.

A median asymmetry value of 0.5 for a given LFP trace indicates that cycles tend towards a sinusoidal

shape. The farther the value is from 0.5 (above or below) the more asymmetric a waveform is. However,

whether such values lie above or below the 0.5 threshold strongly depends on signal polarity. Note, for

example, that a certain signal and its copy, the latter with inverse polarity, will have values of asymmetry

equally distanced from 0.5, but in opposite directions (as peaks become troughs with a polarity inversion).

Thus, not controlling for signal polarity can be a strong confound when comparing waveform shape

asymmetries, especially if these are calculated from electrodes located in different brain regions which

already have dissimilar cytoarchitectures, such as the frontal and auditory cortices. Since we are unable

to control for signal polarity in the current dataset, we avoid this potential confound by normalizing median

asymmetry values to 0.5. That is, the asymmetry value for a given LFP trace used for comparisons is

given by the absolute value of the difference between its raw asymmetry and 0.5. This approach

measures how far from sinusoidal the waveform shape of an LFP trace is, independently of signal polarity

(Schaworonkow and Voytek, 2021), and is therefore better suited for inter-areal comparisons of waveform
shape asymmetry.

The aforementioned cycle features characterize waveform shape, but they do not quantify to what degree
individual burst cycles in a given LFP trace are similar to one another. This is measured by the dispersion
of the distribution of the cycle features, which was quantified here as the coefficient of variation (CV). The
CV is computed over each LFP trace, therefore quantifying cycle-by-cycle the variability over time; it is
expressed as follows:

$$CV = \frac{\sigma_W}{\mu_W} \qquad , \qquad\qquad [1]$$

where σ_W is the standard deviation of the cycle feature distribution (W), and μ_W its mean.

Every recording in frontal or auditory cortex had a specific CV for a given cycle parameter, channel and
frequency band. As described with median feature values, this enabled us to conduct paired statistics
when comparing CV values between FAF and AC (FDR-corrected Wilcoxon signed-rank tests, significant
for $p_{corr} < 0.05$). The CV was calculated from raw feature values (not normalized to 0.5) across all cycles
in a given signal, given that this metric is not affected by signal polarity as it is self-contained for each LFP
trace. This allows to explore cycle-by-cycle variability over time without affecting the individual asymmetry
values of the cycles involved.

<u>Sensitivity analyses</u>

To evaluate the dependence of significant differences across cortical structures on the burst detection
parameters of the *bycycle* algorithm, bursts were detected as above but detection parameters were
varied in pairs as follows: (i) amplitude fraction threshold vs. amplitude consistency threshold; (ii)
amplitude fraction threshold vs. period consistency threshold; and (iii) amplitude fraction threshold vs.
monotonicity threshold. The same parameter values were used to detect bursts in FAF and AC. However,
we also evaluated to what degree our results were sensitive to different burst detection parameters
across regions, varying the amplitude fraction threshold independently in each area (**Fig. 7**). Parameters
were varied in the range from 0.1 to 0.9, with a step of 0.1. All waveform features were computed as
described above, and the variability of waveform features was measured as the CV. As in the original
analyses, all channels were statistically compared against each other. We then determined the median of
the effect size of comparisons across areas (i.e. the median effect size of the upper-right quadrant of the
comparison matrices in **Figs. 5, 6**; effect sizes of non-significant comparisons were set to 0), and plotted
this median against parameter combinations (**Figs. 7**) to determine how changing detection parameters
affected the reported inter-areal differences.

 Burst co-occurrence analysis

The relationship between the onset of a burst in a specific channel and the cumulative burst co-

occurrence with all other channels was calculated as follows. First, given a certain channel (e.g. channel

A, for convenience) we determined the onset of all bursts detected across all recordings (the data from

the two bats were pooled given that spectral and bursting patterns were highly consistent across

animals). In a time window centred on each burst (spanning from -1000 to 1000 ms for delta frequencies,

and from -250 to 250 ms for the gamma frequencies) we counted and accumulated, for every channel,

the time points at which bursts occurred. Bursts were counted even if their onset or offset were outside

the aforementioned window, as long as at least a segment of the burst occurred within that window. For

every given channel (channel A in this example) this procedure yielded a matrix (dimensions: [channels x

samples]) whose values indicate the accumulated, co-occurring bursting activity in each other electrode,

relative to the times in which a burst onset occurred in the channel of interest (i.e. A in this case). We

referred to this matrix as a channel's burst co-occurrence matrix. Burst co-occurrence matrices were

computed for 8 channels, 4 in the FAF and 4 in the AC (at depths of 50, 250, 450, and 700 μm). This

reduced computational costs and facilitated visualization, while at the same time allowing to explore burst

co-occurrences at various depths in each region including superficial, middle and deep layers of cortex.

In order to evaluate whether the onset of a burst in a given electrode was related to the occurrence of

bursts in other electrodes, the burst co-occurrence matrix for the channel of interest (e.g. channel A) was

normalized following a bootstrapping procedure. We calculated 500 bootstrap burst co-occurrence

matrices, but instead of utilizing burst onsets as a reference, pseudo-random time points were used.

Because the accumulated number of co-occurring bursts across channels depends on the number of

burst onsets used from the reference channel (A), we ensured that the number of randomized time points

was equal to the number of burst onsets individually for each recording. The 500 pseudo-random burst

co-occurrence matrices were used as a baseline distribution, and the values of the burst co-occurrence

matrix for the channel of interest A were then Z-normalized relative to the bootstrap matrices. Absolute Z-

score values ≥ 6 were considered significant. Note that the Bonferroni correction of an alpha of 0.05 over

32 channels, 2 frequency bands, 8 channels of interest and 1000 time points yields a significance

threshold of 9.7×10^{-8}, equivalent to a Z-score of 5.2. In our analysis, negative Z-scores indicate a

suppression of burst activity relative to baseline, while positive values indicate an enhancement. These

procedures are illustrated in **Fig. 4A**.

A conceptual model of spike correlations and LFP waveform shape

Synthetic spike trains were modelled as inhomogeneous Poisson processes with firing rates controlled by

a pulse train with a frequency of 3 Hz. The duty cycle of the pulse train defines a temporal window in

which spiking occurs. Narrow spiking windows (i.e. lower duty cycles) constrain the firing of a neural

population in time, resulting in increased temporal correlations across neurons. By contrast, wider spiking

windows (i.e. higher duty cycles) result in decreased temporal spiking correlations across neurons. By

systematically adjusting the duty cycles we were therefore able to explore how temporal correlations in a

neuronal population (N = 30 neurons in our model) might affect LFP waveform shape.

From the spiking activity we derived synthetic LFP signals as follows. The spike train of each simulated

neuron was convoluted with a synaptic kernel whose rise and decay times were set to 1 and 20 ms,

respectively (function *sim_synaptic_kernel* of the python package NeuroDSP, version 2.2.1; (Cole et al.,

2019)). The sum of all convolutions was taken as the LFP signal. The procedure is illustrated in **Fig. 8A**.

We generated 300 s of spikes and LFPs for several values of duty cycles (5% to 60%, step: 5%). Cycle

features were extracted from the synthetic LFPs by applying of the *bycycle* algorithm described above.

<u>Spike-spike correlations</u>

All detected spiking events (see above) were included to calculate spike train correlations across

channels. Spike trains were binned using 5 ms bins, and the Pearson's correlation coefficient across pairs

of binned spike trains was computed using the *Elephant* toolbox (v. 0.12.0;

https://github.com/NeuralEnsemble/elephant). Correlation coefficients from channels located in the FAF

were averaged, and the same was done for channels located in the AC. This yielded one correlation

value per recording in FAF and AC, which allowed to capitalize on simultaneous recordings in both

regions by means of paired statistical comparisons (Wilcoxon signed-rank test, alpha = 0.05).

<u>Pairwise phase consistency</u>

The pairwise phase consistency (PPC) was computed as described in previous literature (Vinck et al.,

2010). Only spikes that occurred within oscillatory bursts in FAF or AC were considered. If more than

10000 spikes were detected in a given trace, 10000 spikes were randomly selected to calculate PPC

given that analyses were computationally expensive for large spike counts. In order to minimize the risk of

asymmetric signals yielding unclear measurements of phase, spike phases were not obtained by means

of a Hilbert transform or a Fourier analysis. Instead, the timing of a spike was expressed as the time in

which the event occurred relative the onset and offset of a cycle as detected in the time series by the

bycycle algorithm. Thus, each spike timing was between 0 and 1 (0 being the beginning of a burst cycle,

1 being the end), and was converted to a phase by multiplication with 2π. These phases were then used

for PPC calculation, which can be expressed as follows (Vinck et al., 2010):

$$PPC = \frac{2}{N(N-1)} \sum_{j=1}^{N-1} \sum_{k=(j+1)}^{N} f(\phi_j, \phi_k), \qquad [2]$$

where N is the number of spikes, and ϕ_j, ϕ_k represent the phases of spikes *j* and *k*, respectively. The

function $f(\phi_j, \phi_k)$ calculates the dot product between two unit vectors. It can be expressed as follows:

$$f(\phi_j, \phi_k) = \cos(\phi_j)\cos(\phi_k) + \sin(\phi_j)\sin(\phi_k) \qquad [3]$$

PPC values were averaged in FAF and AC, and paired statistical comparisons were made to evaluate

whether significant differences in spike phase consistency existed between regions (Wilcoxon signed-

rank test, alpha = 0.05).

<u>Statistical analyses</u>

All statistical analyses were performed using *scipy* (version 1.9.1), or custom written Python scripts. For

determining significant deviations from a 1/f fitted trend in the LFP spectra one-sample t-tests were

performed. Statistical comparisons of median and CV values across regions (and within regions) were

performed using paired statistics (Wilcoxon signed-rank tests, alpha = 0.05), as recordings in FAF and AC

were performed simultaneously (N = 29). Comparisons of spike-spike and spike-LFP correlation (PPC

values) were also made using paired statistics. Comparisons of burst lengths were made by means of

non-paired statistics (Wilcoxon rank-sum tests, alpha = 0.05). All tests were corrected for multiple

comparisons using the false discovery rate when appropriate (Benjaminin and Hochberg procedure

(Benjamini and Hochberg, 1995)); it is noted in the main text whenever this correction was applied.

Results

<u>Spectral properties of frontal and auditory cortical LFPs</u>

A total of 29 paired recordings (i.e. simultaneous electrophysiological acquisition from each region) in

FAF and AC were performed in two bats: Bat-01 and Bat-02 (N = 15 and N = 14 paired FAF-AC

recordings, respectively). A schematic representation of the laminar probes, channel depths, and

recording locations in the AC are given in **Fig. 1A**. Since a clear map of the FAF does not exist, it was not

possible to map electrode locations in the frontal structure in a similar manner. Example frontal and

auditory cortical LFP traces from both animals are given in **Fig. 1B, K**, across all recording depths.

Typically, LFPs exhibited clear rhythmicity in low and high frequencies in both cortical regions. Evidence

for rhythmic activity was clear in grand-average spectra obtained from all ~20-min long LFP traces (**Fig.**

1C, G, L, M). Observable "bumps" in these spectra are interpretable as deviations from a 1/f power-law (a

property of aperiodic mesoscopic signals such as LFPs (Baranauskas et al., 2012)) and therefore suggest

the presence of oscillatory activity. We performed spectral parametrization by fitting 1/f curves to the

power spectral density of every LFP signal recorded (Donoghue et al., 2020) in order to confirm that such

spectral bumps were in fact significant deviations from an aperiodic spectrum. Representative

parametrized spectra are depicted in **Fig. 1D, H, M, Q**, corresponding to the full ~20-min LFP traces from

which data in **Fig. 1B, K** were selected. The 1/f fit is shown in dashed blue lines. Deviations in the spectra

from the power-law trend were clear in both animals, particularly in the FAF. We tested whether such

deviations were consistently present in all recordings by normalizing the power spectrum of each LFP

trace (N = 15 in Bat-01, N = 14 in Bat-02, per channel) to their fitted 1/f function (**Fig. 1E, I, N, R**). Power

spectral values would hover around 0 in the absence of consistent deviations, but would be significantly

above zero otherwise. Normalized spectral values were significantly above 0 in FAF and AC for both
animals (FDR-corrected one-sample t-tests; $p_{corr} < 1.73 \times 10^{-4}$, $t > 2.25$) at relatively low (~1–5 Hz in FAF
and AC), intermediate (~12–27 Hz in AC), and relatively high (ranging from ~32–105 Hz, but peaking at
70-85 Hz in FAF and AC) frequencies (**Fig. 1F, J, O, S**).

Figure 1. Spectral properties of local-field potentials in FAF and AC. (**A**) *Left*: Schematic representation of the probes used for recordings in FAF
and AC. Depth and channel colours correspond to those in panels **B** and **K**. *Middle*: Location of the FAF and AC in *C. perspicillata*'s cortex.
Right: Schematic representation of recording locations in AC, colour-coded by animal (blue: Bat-01, N = 15; brown: Bat-02, N = 14). The precise
location of one recording in Bat-02 could not be recovered. (**B**) Cortical LFPs (5 s excerpts) recorded simultaneously from the FAF (left) and AC
(right; note that channel depths are colour-coded) of Bat-01. (**C**) Average power spectra in FAF across all recordings (N = 15) in Bat-01 using full
LFP traces (lengths of ~20 minutes), for all channels. The spectrum of each channel is colour-coded according to the depth scheme of panels **A**,
B. (**D**) Parametrization of an exemplary power spectrum obtained from ~20 minutes LFP recordings in the FAF (depth, 700 μm). LFP traces
originate from the same recording shown in **B**. The 1/f fit is depicted as a blue dashed line; power spectrum shown in solid black. (**E**) Normalized
power spectra (to 1/f activity) across all recordings in Bat-01, shown for channels located at 700 μm in FAF. Solid black line indicates average (N

In bats such as *C. perspicillata* (the animal studied here), LFP activity in low and high frequencies is

related to vocal production (e.g. at frequencies delta: 1-4 Hz, beta: 12–30 Hz, and gamma: 60–120 Hz;

see Garcia-Rosales et al. (2022b); Weineck et al. (2020)). Considering the above and the patterns of

deviations from a pure 1/f signal shown in **Fig. 1**, in subsequent analyses we focused on frequency bands

delta (1–4 Hz) and gamma (65–85 Hz). Beta-band frequencies were not included because no clear peaks

in this range were detected in FAF signals (**Fig. 1F, J, O, S**).

<u>Cycle-by-cycle analysis of oscillatory activity in frontal and auditory cortices</u>

To study the characteristics of delta- and gamma-band rhythmic activity in frontal and auditory areas, we

performed a cycle-by-cycle analysis of the recorded LFP. Cycles were considered only if they were part of

consistent oscillatory activity (i.e. they were associated with a putative oscillatory bursts). Bursts of

oscillatory activity were detected using the *bycycle* algorithm (Cole and Voytek, 2019), which capitalizes

on a time-domain approach for quantifying waveform shape (**Fig. 2A**). A burst is detected based on four

parameters, which control for signal-to-noise ratio (SNR) and waveform consistency (see Methods). In

this context, an oscillatory burst occurs if the threshold values of these parameters are exceeded for at

least 3 consecutive cycles.

Representative burst events in delta- and gamma-bands are shown for FAF and AC in **Fig. 2B**. The

waveform shape of oscillatory activity was quantified by measuring three main features on a cycle-by-

cycle basis: cycle period, cycle rise-decay asymmetry, and cycle peak-trough asymmetry (**Fig. 2C**; Cole

and Voytek (2019)). For each LFP trace, the median feature value across all detected cycles was

considered the waveform shape feature for that trace (**Fig. 2D**). The median summarizes a distribution of

feature values, yielding one value per LFP trace (that is, 29 values for each FAF and AC channel). The

median feature value of asymmetry metrics was normalized to 0.5 to account for possible confounds

related to signal polarity differences in FAF and AC (see Methods; (Schaworonkow and Voytek, 2021)).

To determine how and to what extent oscillatory waveform shape differed between recording locations,

we performed systematic channel-by-channel pairwise comparisons. Only values obtained from

simultaneously recorded LFP traces were compared to one another by using paired statistical testing.

Median values for each ~20-minute LFP were quantified from hundreds of cycles. That is, for Bat-01, no

less than 665 and 370 delta-band cycles were used from FAF and AC, respectively, while no less than

829 and 146 gamma-band cycles were used from the same regions. For Bat-02, at least 561 and 468

delta-band cycles were used from FAF and AC, while at least 717 and 241 gamma-band cycles were

used from the same areas.

<u>Bursting dynamics in frontal and auditory cortices</u>

The data shown in **Fig. 1** suggest that the signal-to-noise ratio (SNR) of oscillatory activity in delta- and

gamma bands is higher in FAF than in AC. We quantified SNR independently for each bat in frontal and

auditory regions on a channel-by-channel basis (N = 15 observations for each channel in FAF or AC for

Bat-01, and N = 14 for Bat-02). Distribution of SNR values are shown in **Fig. 3B** (top) for delta

frequencies and in **Fig. 3E** (top) for gamma frequencies. Distributions from Bat-01 are shown with positive

probability densities, whereas data from Bat-02 are given with negative probability densities merely for

illustrative purposes. Note that the colour of each distribution corresponds to a specific channel in the

shank, located at a certain cortical depth (see **Fig. 3A**). Given that the patterns across animals were

highly consistent, we compared SNR values across recording sites by pooling data from the two bats.

Channel-by-channel statistical comparisons revealed significant differences in SNR across recording sites

(FDR-corrected Wilcoxon signed-rank tests, N = 29, significance when $p_{corr} < 0.05$). Comparisons are

summarized in the matrices of **Fig. 3B-G** (bottom). A comparison matrix represents the effect sizes (d) of

pairwise comparisons of SNR values across channels (|d| < 0.5 small, 0.5 <= |d| <= 0.8 medium, |d| > 0.8

large effect sizes; Cohen (2013)). A cell (*r, c*) in a matrix shows the effect size of comparing SNRs from a

channel indexed by row *r*, and a channel indexed by column *c* (i.e. channel *r* vs. channel *c*). The

relationship between a channel index and its relative depth in frontal or auditory cortex is schematized in

Fig. 3A (notice the vertical lines next to channel numbers in **Fig. 3B-G** indicating cortical depths by

following the colour schemes of **Fig. 1** and **Fig. 3A**). The upper right quadrant of each matrix represents

comparisons of channels in FAF vs. those in AC. Only effect size values of significant comparisons (p_{corr} <

0.05) were shown; they were set to 0 otherwise. The matrices in **Fig. 3B** and **Fig. 3E** show strong

differences in SNR between frontal and auditory cortices in the delta and gamma bands.

Typically, SNR values are interpreted solely on the basis of signal amplitude. However, high SNRs

derived from the spectral properties of a signal could also indicate, beyond amplitude, a relatively high

proportion of oscillatory events. We calculated bursting proportion as the ratio of the total time of bursting

in an LFP trace relative to the total duration of that trace. Distribution of bursting proportions are given for

both animals in **Fig. 3C** (top) for delta frequencies and in **Fig. 3F** (top) for gamma frequencies. From

these data it appeared clear that, in both animals, the proportion of bursting events in FAF was higher

than that in AC. Given this consistency, we pooled data across bats and compared on channel-by-

channel basis bursting proportions across sites (FDR-corrected Wilcoxon signed-rank tests, N = 29,

significance when $p_{corr} < 0.05$). These comparisons, summarized in the matrices of **Fig. 3C** (bottom) and

Fig. 3F (bottom), corroborate that the proportion of delta- and gamma-band oscillatory events was

significantly higher in FAF than in AC, with large effect sizes.

Higher proportion of bursting events could be influenced by two factors: more bursts occur in FAF than in

AC, or bursts in FAF are longer than those in the auditory cortex (or both). To elucidate this, we examined

the distributions of burst durations in delta- and gamma-band LFP traces from all channels. Distribution of

burst durations are given independently for each animal in **Fig. 3D** (top) for delta and **Fig. 3G** (top) for

gamma frequencies. To statistically compare burst durations, data across bats were pooled given the

highly similar patterns observed from the two animals. For comparisons, all bursts from any given channel

are considered, so the number of bursts per channel was not always the same (at least 2283 and 1977

bursts were used for delta frequencies from Bat-01 and Bat-02, respectively; in gamma, no less than

2984 and 1991 for each bat). Because of the uneven burst counts, channel-by-channel comparisons were

not paired (FDR-corrected Wilcoxon ranksum tests, N >= 1991, significance when $p_{corr} < 0.05$). As readily

visible from the distributions of burst duration, and as shown in the comparison matrices from **Fig. 3D**

(bottom) and **Fig. 3G** (top), differences in burst durations between FAF and AC were statistically

negligible, indicating that bursts in the FAF were more numerous, but not necessarily longer, than in the

AC. This corresponds well with our initial observation of a very large burst density in frontal regions.

Figure 3. Bursting dynamics and signal-to-noise ratio in frontal and auditory cortices. (**A**) Schematic illustrating the relationship of region and

cortical depth with the channel number markers of panels **B**-**G**. Notice that depths are colour-coded as in **Fig.1**. (**B**) *Top*: Distribution of signal-

to-noise ratio (SNR) shown for each channel (notice colour schemes in panel **A** for the region and depth of each channel), across all recordings

(N = 29 in FAF and AC). Values for Bat-01 are shown with densities > 0; values for Bat-02 are shown with densities < 0 only for illustrative

purposes. *Bottom*: Effect sizes of channel-by-channel, pairwise statistical comparisons of SNR values (FDR-corrected Wilcoxon signed-rank

tests). Effect sizes for comparisons that did not yield significance (i.e. p_{corr} >= 0.05) were set to 0. A cell (r, c) in the effect size matrix indicates

the effect size of the comparison between burst proportion values in channel r and channel c (as per panel **A**). The quadrant spanning rows [0–

15] and columns [16–31] illustrates effect sizes of comparisons between channels in FAF and AC. In this quadrant, red colours indicate higher

proportion values in FAF. (**C**) Same as in **B**, but data shown corresponds to burst proportions across recordings. (**D**) Same as in **C**, but data

shown correspond to burst durations (note the logarithmic scale of the x-axis).

The data shown in **Figs. 1** and **3** demonstrate that spectral and bursting dynamics were highly consistent

between Bat-01 and Bat02. Because of this consistency between animals (**Figs. 1** and **3**), data from the

two bats were pooled in subsequent analyses.

<u>Bursting events in FAF and AC are temporally correlated</u>

Transfer entropy analyses based on the phase of ongoing LFP activity, and direct electrical

microstimulation of the frontal cortex to alter AC responsiveness, show that neural activity in FAF can

significantly modulate its auditory cortical counterpart (Garcia-Rosales et al., 2022b). Given the functional

and anatomical connections in the FAF-AC network, we sought to determine whether oscillatory bursts in

one region are related to bursts occurring in the other. We reasoned that co-occurring bursts across brain

structures could be a fingerprint of functional connectivity complementary to phase correlations (e.g.

coherence), statistical dependencies (e.g. transfer entropy), or invasive approaches (e.g. electrical

microstimulation). We calculated the burst co-occurrence index (**Fig. 4**), a metric that quantifies for any

given channel the relationship between the onset of its own bursts with the occurrence of bursts in other

channels (**Fig. 4A** illustrates how the index was computed). The burst co-occurrence index is shown in

Fig. 4B, C, calculated for eight channels in total, four in each region, at representative depths of 50, 250,

450, 700 μm. Since the index is a cumulative count Z-normalized according to bootstrap distributions (see

Methods), we could use it to evaluate the significance of burst co-occurrence across channels. Thus, red

colours in **Fig. 4** indicate significant, temporally correlated increases in bursting activity in other channels

(Z-values >= 6), while blue colours indicate significant, temporally correlated suppression of bursting

activity in other cahnnels (Z-values <= -6). White colours indicate no significant deviations from baseline

values.

At delta frequencies (**Fig. 4B**), a burst onset in either FAF or AC was typically preceded by a suppression

of bursting activity in channels of the same structure, and succeeded by a within-structure increase in

burst co-occurrence across channels, peaking as trivially expected in the channel from which burst onsets

were chosen. A similar pattern was observable for bursts detected in the gamma frequency range (**Fig.**

4C). However, we observed no clear pre-onset suppression in the gamma band, potentially due to much

shorter durations of gamma bursts compared to delta ones. In gamma frequencies, an interesting pattern

was evident: when burst onsets were taken from FAF channels (top left quadrant of **Fig. 4C**), a periodicity

of burst co-occurrence emerged in the frontal area, with a temporal scale of ~250 ms. This phenomenon

constitutes evidence for strong coupling between gamma-band activity and low-frequency (delta)

rhythms. These data resonate with that of a second study (and a different dataset) demonstrating clear

coupling between the amplitude of gamma-band and the phase of delta-band LFPs in the FAF of *C.*

perspicillata (Garcia-Rosales et al., 2022a).

Figure 4. Burst co-occurrence in the FAF-AC circuit. (**A**) Schematic representation of the analysis for quantifying temporal co-occurrence of bursting events. Note that channels A and B could be drawn from the same or different cortical regions. (**B**) *Left* (shaded green): indicates delta-band burst co-occurrence across all channels, calculated relative to the onset of a burst at four representative depths (50, 250, 450, 700 μm) in the FAF. Matrices in the top row show burst co-occurrence in FAF channels; matrices in the bottom show co-occurrence of bursts in AC channels, aligned to burst onsets in FAF (at t = 0). Burst co-occurrence values were z-normalized relative to a bootstrapped baseline (blue colours: suppression of bursting activity; red colours: increased bursting activity). Only z-normalized values considered significant (|z| > 6, see Methods) are shown. *Right* (shaded pink): similar information, but in this case bursts originate in the AC at the same four representative depths (50, 250, 450, 700 μm). Here, t = 0 is aligned to auditory cortical burst onsets. (**C**) Same as in **B**, but depicting data related to the gamma frequency band. Note that burst co-occurrence matrices corresponding to bursts originating within a specific area (i.e. FAF or AC) are shown with a different colour scale than those corresponding to bursts originating outside a given area.

Remarkably, when a burst onset occurred in frontal or auditory cortex, significant and consistent changes in burst co-occurrence in the other region happened for gamma-band LFPs (**Fig. 4C**). That is, bursts

onsets in FAF were consistently and significantly correlated with gamma-band bursting in the AC, and
vice-versa. Furthermore, **Fig. 4C** suggests a degree of spatial specificity to this relationship, wherein
bursts originating in FAF appear more strongly related to those in middle layers of the AC (depths of 250-
450 μm), while bursts originating in middle layers of the AC yield larger co-activation patterns in the FAF.
Significant inter-areal burst co-occurrence was not equally clear in delta frequencies (**Fig. 4B**), although
clear FAF-AC interactions occur in the delta band when considering transfer entropy analysis or even
electrical stimulation experiments (Garcia-Rosales et al., 2022b). The apparent lack of burst interactions
in the delta band shown in **Fig. 4B**, however, does not necessarily mean the absence of burst co-
occurrence in these frequencies. Rather, this effect is a consequence of the stringency of the
bootstrapping procedure (see Methods) interacting with the ubiquity of bursting activity in the FAF (**Fig.
3**). That is, bootstrap distributions were contaminated with real bursting activity when accumulating burst
counts from the frontal cortex. Taken together, these results (particularly the ones related to gamma-band
LFPs) suggest an intrinsic relationship between elevated bursting activity in frontal and auditory cortices,
supporting the notion of strong functional connectivity in the FAF-AC network.

<u>Oscillatory waveform shape differences between frontal auditory cortices</u>

We have shown the presence of oscillatory activity in delta and gamma frequencies in the frontal and
auditory cortices of *C. perspicillata*. Oscillatory bursts across structures occur more often in the FAF, but
are not necessarily longer than those in the AC. Remarkably, bursts in FAF and AC are temporally
correlated, supporting the notion of concerted activity in the delta and gamma ranges in the FAF-AC
circuit. Such correlated bursting activity occurs in very similar frequencies, yet they occur in functionally
and anatomically distinct areas of the brain. Do these oscillations differ across structures?

A visual inspection of ongoing LFP activity revealed that the oscillatory waveform in the FAF was highly
asymmetric (i.e. less sinusoidal, with more pronounced troughs), something that was not so obvious in
the AC (see, for example, the representative bursts in **Fig. 2B**). The waveform shape of an oscillation was
characterized by three main features (see above): period, rise-decay asymmetry, and peak-trough
asymmetry. The distribution of feature values across recordings is given in **Fig. 5B-D** (top) for delta
frequencies, and in **3E-G** (top) for gamma frequencies for all channels (see **Fig. 5A**; conventions are the
same used for presenting data in **Fig. 3**). Note that the median feature value across all cycles is
considered the feature value for a given LFP trace (**Fig. 2D**), thus yielding 29 feature values for each
electrode either in FAF or AC (i.e. one value per recording). This allowed us to compare between
recording sites using paired statistics, capitalizing on the fact that data in FAF and AC were
simultaneously acquired.

Figure 5. Waveform shape differences between frontal and auditory cortical LFPs. (**A**) Schematic illustrating the relationship of region and cortical
depth with the channel number markers of panels **B**-**G**. Notice that depths are colour-coded as in **Fig. 1**. (**B**) *Top*: Distribution of oscillatory cycle
periods across all recordings (N = 29; for each recording, the median period across all cycles is considered), for all channels (in FAF and AC; see
panel **A** for region and depth according to colour), in the delta band. Vertical lines indicate the median of each distribution. *Bottom*: Effect sizes of
pairwise statistical comparisons of population-level period values across all channels (FDR-corrected Wilcoxon signed-rank tests). Effect sizes for
comparisons that did not yield significance (i.e. p_{corr} >= 0.05) were set to 0. A cell (*r, c*) in the effect size matrix indicates the effect size of the
comparison between values in channel *r* and channel *c* (as per panel **A**). The quadrant spanning rows [0–15] and columns [16–31] illustrates
effect sizes of comparisons between channels in FAF and AC. In this quadrant, blue colours indicate lower periods in FAF. (**C**) Same as in **B**, but
corresponding to values of cycle feature "rise-decay asymmetry". (**D**) Same as in **C**, but related to values of cycle feature "peak-trough
asymmetry". (**E**-**G**) Same as **B**-**D**, but shown for values obtained using gamma-band oscillatory cycles.

Channel-by-channel comparisons revealed significant differences across cortical regions (FDR-corrected
Wilcoxon signed-rank tests, significance when $p_{corr} < 0.05$). These analyses are summarized in the
comparison matrices of **Fig. 5B-G** (bottom; conventions are the same as those of **Fig. 3**). Delta-band
oscillations in frontal and auditory cortices differed in period typically with small-to-medium effect sizes (|d|
<= 0.8; **Fig. 5B**, bottom), but were strongly different in terms of their temporal asymmetries (**Fig. 5C-D**,

bottom; |d| > 0.8 particularly for peak-trough asymmetries). The data in **Fig. 5** corroborates that the

differences visible in **Fig. 2B** were consistent across recordings. Regarding gamma-band LFPs, the

period of gamma-band cycles in FAF and AC differed more markedly than that of delta-band cycles (**Fig.**

3E, bottom; |d| > 0.8), although gamma-band oscillations differed only negligibly in their asymmetry

across structures.

<u>Waveform shape variability is higher in auditory than in frontal cortex</u>

By examining recordings independently we observed that beyond direct differences in waveform shape

features (or lack thereof), feature values across cycles were typically less variable in the FAF than in the

AC. That is, the distribution of feature values (e.g. period) were typically narrower for LFPs recorded in

the frontal cortex. To evaluate the extent of this effect, we quantified for each LFP trace the variability of

waveform shape features as the coefficient of variation (CV; **Fig. 2D**), and compared it across recording

sites. The CV is a measure of dispersion, in the sense that it measures the "broadness" of a distribution.

Thus, larger CVs indicate that cycle features vary over a wider range of possible values, suggesting a

higher variability in the oscillatory processes. As with the median, the CV summarizes a distribution,

yielding one value per LFP trace (see above and **Fig. 2D**). The same cycles used to calculate median

feature values were used to calculate CV values.

The distributions of CV values across cycle features for each channel are given in **Fig. 6B-D** (top) for

delta frequencies, and **Fig. 6E-G** (top) for gamma frequencies. CV values appeared consistently lower for

channels in FAF than for those in AC. This trend was confirmed by statistical, channel-by-channel

pairwise comparisons (FDR-correct Wilcoxon signed-rank tests, N = 29, significance when $p_{corr} < 0.05$),

summarized in comparison matrices similar to those of **Fig. 3**. Statistical comparisons between channels

located in different regions (the upper right quadrants of the comparison matrices) yielded the highest

effect sizes (typically |d| > 0.8, large). CV values were consistently and significantly lower in FAF channels

than in AC channels, in delta- and gamma frequency bands, for all cycle features. Some significant

within-area differences also occurred (e.g. deeper channels in FAF had higher CV values than more

superficial ones), yet effect sizes were typically medium (0.5 < |d| < 0.8) or small (|d| < 0.5). Overall, these

results indicate that, beyond first-order differences in waveform shape, oscillatory activity in the frontal

cortex exhibits a higher degree of cycle-by-cycle regularity (i.e. lower variability over cycles) than that of

the AC. Note that such differences in regularity between regions are unlikely to arise from differences in

the bursting proportions across FAF and AC (**Fig. 3**). Although more bursts result in more cycles

contributing to a distribution, cycle-by-cycle regularity is quantified here using hundreds (sometimes

thousands) of cycles obtained from relatively long LFP traces (ca. 20 minutes). These are well-sampled

distributions whose CV should not be strongly affected by increasing the number of waveform shape

features in them.

Figure 6. The variability of waveform shape features differs between frontal and auditory regions. (**A**) Schematic illustrating the relationship of region and cortical depth with the channel number markers of panels **B-G**. Notice that depths are colour-coded as in **Fig.1**. (**b**) *Top*: Distribution of CV values for oscillatory cycle periods across all recordings (N = 29), for all channels (in FAF and AC; see panel **A** for region and depth according to colour), in the delta band. Vertical lines indicate the median of each distribution. *Bottom*: Effect sizes of pairwise statistical comparisons of population CV values across all channels (FDR-corrected Wilcoxon signed-rank tests). Effect sizes for comparisons that did not yield significance (i.e. $p_{corr} >= 0.05$) were set to 0. A cell (*r, c*) in the effect size matrix indicates the effect size of the comparison between CV values in channel *r* and channel *c* (as per panel **A**). The quadrant spanning rows [0–15] and columns [16–31] illustrates effect sizes of comparisons between channels in FAF and AC. In this quadrant, blue colours indicate lower CV values in FAF. (**C**) Same as in **B**, but corresponding to CV values of cycle feature "rise-decay asymmetry". (**D**) Same as in **C**, but related to CV values of cycle feature "peak-trough asymmetry". (**E-G**) Same as **B-D**, but shown for CV values obtained using gamma-band oscillatory cycles. (Effect sizes can be interpreted as follows: |d| < 0.5 small, 0.5 <= |d| <= 0.8 medium, |d| > 0.8 large).

Differences across regions are robust against burst detection parameters

The data indicate that oscillations in the FAF are more regular than those in the AC. However, the measurements of waveform shape used here can be affected by the SNR of the oscillatory activity used to quantify them. In particular, higher SNR of oscillatory activity in FAF (**Fig. 3B**) could result in narrower distributions of cycle features, because low SNR increases the variability of waveform shape features

(see Schaworonkow and Nikulin (2019)). The SNR for burst detection is controlled by the parameter

amplitude fraction threshold, which discards cycles below a certain amplitude percentile calculated from

all cycles in an LFP trace (Cole and Voytek, 2019; Schaworonkow and Voytek, 2021). Therefore, to test

whether the results shown above can be simply accounted for by different SNR levels in FAF and AC, we

evaluated the sensitivity of the inter-areal differences to different values of amplitude fraction threshold in

each region (**Fig. 7**).

Figure 7. Differences in waveform shape features and their variability are robust against burst detection amplitude threshold. The burst

detection parameter "amplitude fraction threshold" was varied independently in FAF and AC to determine whether SNR critically contributes to

differences in oscillatory regularity between frontal and auditory areas. The difference across regions was measured as the median effect size

obtained from comparing all pairs of channels in FAF and AC (e.g. median of the upper right quadrant in the comparison matrices in **Fig. 5**,

labelled "inter-areal comparisons"). In the absence of significant differences (FDR-corrected Wilcoxon signed rank tests, $p_{corr} < 0.05$), effect size

values were set to 0 ($p_{corr} \geq 0.05$). (**A**) Median effect sizes across all values of amplitude fraction threshold tested in FAF and AC, for delta

frequencies, comparing the median of cycle periods (left), cycle rise-decay asymmetries (middle) and cycle peak-trough asymmetries (right). (**B**)

Same as in **A**, but data corresponds to cycles from gamma-band oscillatory bursts. (**C**, **D**) Same as in **a**, **b**, but the CV was calculated across cycle
periods. Red squares indicate the amplitude fraction threshold values used to detect bursts used in the main results.

The median effect size of inter-areal comparisons was used as a summary metric of differences in

median feature values (**Fig. 7A, B**) and CV values (**Fig. 7C, D**) across cortical regions. This metric

corresponds to the median value of the upper-right quadrant of the comparison matrices in **Figs. 5** and **6**.

We systematically varied the amplitude fraction threshold parameter (range: 0.1 – 0.9, step of 0.1) used

to detect oscillatory bursts independently in the FAF or the AC, and for each iteration we calculated the

median effect size of inter-areal comparisons. As depicted in **Fig. 7A**, period values for delta-band cycles

were different between FAF and AC with typically medium or even low effect sizes ($|d| < 0.5$ for low, 0.5

$<= |d| < 0.8$ for medium), while asymmetries differed with typically strong effect sizes ($|d| > 0.8$)

particularly when considering the peak-trough asymmetry as in **Fig. 5**. In general, observations across a

broad range of threshold values conformed well to the data depicted in **Fig. 5** in delta- and gamma-bands

(**Fig. 7B** for gamma). Those data were obtained with a threshold value of 0.5 (red squares in **Fig. 7**).

Similarly, CVs were consistently lower in FAF than in AC across a wide range of amplitude fraction

threshold values in both delta- and gamma frequencies (**Fig. 7C**, delta; **Fig. 7D**, gamma), for all three

cycle features considered. These data were highly consistent with those shown in **Fig. 6**. These results

indicate that the differences in waveform shape features and their CV values between frontal and auditory

cortices are not trivially accounted for by differences in SNR across regions.

<u>A conceptual model captures patterns of waveform shape differences between FAF and AC</u>

We hypothesized that differences across areas, particularly when considering the CV of waveform

features, might reflect the activity of two distinct cortical generators exhibiting different degrees of

regularity. We illustrate this idea with a conceptual model in which an oscillation occurs as a consequence

of the temporally aligned rhythmic discharge of a population of neurons. This conceptualization makes no

assumption on the nature of the neuronal oscillators themselves (see Discussion); instead, it only

assumes that extracellular oscillatory activity occurs when a sufficiently large neuronal population fires

concertedly (Buzsaki et al., 2012). We reasoned that a highly synchronous population firing would lead to

a strong current at a specific phase of the LFP resulting in relatively asymmetric waveform shapes; by

contrast, a relatively asynchronous population activity would yield less asymmetric temporal features. We

simulated 30 neurons firing rhythmically for 300 seconds at a delta rate (3 Hz, for illustrative purposes;

this can be generalized to other frequencies as well), with varying degrees of synchronicity among them.

The synchronization of the spiking across neurons was manipulated by changing the duty cycle of a

square pulse train determining to the instantaneous rate of an inhomogeneous Poisson process

controlling a neuron's firing rate (see Methods). Lower duty cycles represent narrower spiking windows

and therefore higher synchronicity across neurons. From the neuronal firing in each condition, we

generated a synthetic LFP by convoluting each spike train with a synaptic kernel and adding them over all

neurons (**Fig. 8A**). This synthetic LFP was used to estimate cycle features computed with the *bycycle*

algorithm, analogue to the analyses performed on the empirical data.

Figure 8. A linear model captures the differences in waveform shape between FAF and AC. (**A**) Schematic illustrating how synthetic LFP signals

were derived from the spiking activity of a population of simulated neurons. (**B**) Representative spiking activity of a population of N=30 simulated

neurons. The synchronicity across neurons varies with the duty cycle of a pulse train modulating firing rate (lower duty cycle, more synchronous;

see Methods). A synthetic LFP was calculated for each condition (overlaid traces; see panel **A**). (**C-E**) The period (**C**), rise-decay asymmetry (**D**),

and peak-trough asymmetry (**E**) values across all cycles detected by the *bycycle* algorithm for each duty cycle tested. The black line in panels **D**

and **E** represents no asymmetry (i.e. a value of 0.5). (**F-H**) CV values of features period (**F**), rise-decay asymmetry (**G**), and peak-trough

asymmetry (**H**). In panels **C-H**, values from each duty cycle simulation are colour coded according to panel **B**.

Simulated spiking activity with various degrees of synchronicity (controlled by the duty cycle parameter) is

shown in **Fig. 8B** together with corresponding LFPs. Figure **8C-E** shows the distribution of cycle features

(**Fig. 8C**, period; **Fig. 8D**, rise-decay asymmetry; **Fig. 8E**, peak-trough asymmetry) for each duty cycle

condition. We did not observe changes in the median period across duty cycles. However, we did

observe a consistent change in temporal asymmetries (**Fig. 8D, E**) indicating that a more synchronous

neuronal population (lower duty cycles in the figure) resulted in more asymmetric waveform shapes. Note

that the farther the median feature value is from 0.5 (black line in **Fig. 8D, E**) the more asymmetric LFP

cycles are. In addition, we observed that as the neuronal population became less synchronized (i.e.

higher duty cycles) feature values became more variable, as illustrated by the fact that the CV obtained

from the feature distributions tended to increase together with the duty cycle (**Fig. 8G-H**). These two

cases (higher asymmetry for more synchronized population spiking and more variability for less

synchronized spiking) reflect differences in delta- and gamma-band oscillations in FAF and AC (i.e. higher

asymmetry and less variability for oscillations in FAF), and offer a simple yet plausible account of the

patterns observed across regions.

These results suggest that differences in FAF and AC waveform shape can at least be partially accounted

for by different degrees of synchronicity in the underlying neuronal firing. To test this prediction, we turned

to the spiking activity in frontal and auditory regions (**Fig. 9A**). Since oscillations were more asymmetric

and less variable in FAF, we hypothesized that neuronal spiking would be more highly correlated in

frontal than in auditory cortex and, additionally, more strongly synchronized with LFP oscillations (a

secondary consequence of the model in **Fig. 8**). For each recording, we averaged correlation coefficients

obtained from FAF and AC channels, and tested whether their values were significantly different across

regions. These analyses corroborated that spike train correlations were higher in frontal regions (**Fig. 9B**,

bottom; Wilcoxon signed-rank test, $p = 2 \times 10^{-6}$) with a large effect size ($d = 0.84$).

Because delta-band oscillations exhibited the largest differences in terms of asymmetry (**Fig. 5**), we

studied spike-LFP relationships in this frequency range. Here, only spikes occurring within oscillatory

bursts, as detected by the *bycycle* algorithm, were considered (note that these are the same bursts used

in previous analyses). Spike times were expressed as the points of spike occurrence relative to the period

of the burst cycle in which they occurred (0, spike occurs at beginning of cycle; 1, spike occurs at end of

cycle), and spike phases were obtained by multiplying the relative spike timing by 2π. The distribution of

spike phases from the recordings shown in **Fig. 9A** are depicted in **Fig. 9C** (N = 6760 spikes in FAF, N =

661 spikes in AC), suggesting a tighter clustering of spike phases in FAF. The pairwise phase

consistency (PPC; Vinck et al. (2010)) was computed for all channels across recordings. The PPC

measures how tightly spike phases group together (phase consistency) and constitutes a bias-free

equivalent to the square of the phase locking value. Higher PPC values indicate higher spike-LFP

coherence. To test whether spikes in FAF were more strongly synchronized to delta-band LFPs than

those in the AC, we averaged PPC values across channels in FAF and AC (as described above) and

statistically compared across regions. PPC values were significantly higher in FAF than in AC (**Fig. 9D**,

bottom; Wilcoxon signed-rank test, p = 9.75x10^{-4}) with a large effect size (d = 0.96).

Figure 9. Spiking activity in FAF is more correlated and more strongly synchronized to delta-band oscillatory bursts. (**A**) Representative LFP (top) and spiking (bottom) activity from FAF (purple) and AC (green) electrodes at depths of 700 μm. (**B**) Spike-spike correlation coefficients for each recording in FAF and AC (N = 29; averaged across channels); spike-spike correlation in FAF was significantly larger than in AC (Wilcoxon signed-rank test, p=2x10^{-6}, d = 0.84, large effect size). (**C**) Distribution of spike phases relative to delta LFPs in FAF (left, N = 6760 spikes) and AC (right, N = 661 spikes). Spikes were only those occurring during bursts of delta-band asctivity as detected by the *bycycle* algorithm. Troughs, peaks, rising and falling phases, for any given cycle, are indicated in the figure. (**D**) Average PPC values in FAF and AC were compared across all recordings (N = 29). There was significantly larger spike-phase consistency in FAF than in AC (Wilcoxon signed-rank test, p=9.75x10^{-4}, d = 0.96, large effect size).

Altogether, these results show that differences in waveform asymmetries between FAF and AC in delta

frequencies are accompanied by differences in spike correlations and spike-LFP synchronization between

regions. These observations are in line with predictions derived from the conceptual model illustrated in

Fig. 8, and support a relationship between waveform shape and spike synchronization. Direct correlations

between, for example, peak-trough asymmetry and spike-train correlations were, although significant,

relatively weak (FAF, p = 0.033, adjusted R^2 = 0.13; AC, p = 0.009, adjusted R^2 = 0.2), indicating that

oscillatory waveform shape cannot be trivially explained by local spike synchronization alone.

Discussion

In this work, oscillations in the bat frontal and auditory cortices were studied with respect to their

waveform shape. We show that oscillations present in simultaneously recorded LFPs in the fronto-

auditory circuit differ markedly in waveform shape and in the variability of waveform features across

individual cycles. This heterogeneity is not trivially accounted for by different levels of SNR in frontal and

auditory regions. A conceptual model suggests a relationship between the temporal organization of

neuronal spiking and waveform shape asymmetry, with higher spike temporal correlations leading to

more asymmetric waveforms. In line with the predictions of the model, we demonstrate that spike-spike
and spike-LFP correlations differ significantly in the FAF-AC network.

The bat frontal and auditory cortices are two brain regions with distinct cytoarchitectonic patterns, which
likely accounts for the differences observed in oscillatory waveform shape across areas. *C. perspicillata*'s
AC is a primary sensory region with a well-defined, six-layered columnar structure and clear inter-laminar
boundaries (see Garcia-Rosales et al. (2019) for histology), following a blueprint that is typical across
mammalian species (Douglas and Martin, 2004; Linden and Schreiner, 2003; Mountcastle, 1997). By
contrast, *C. perspicillata*'s FAF lacks clear boundaries between layers (see Garcia-Rosales et al. (2022b);
Weineck et al. (2020)), mirroring instead the stereotypical agranular or slightly agranular architecture of
the mammalian frontal cortex (Beul and Hilgetag, 2014; Camarda and Bonavita, 1985; Shepherd, 2009).
Differences between the bat frontal and auditory regions likely extend to other cytoarchitectonic properties
such as the distribution of cell-type density and overall cellular organization. Beyond anatomy, cortical
cytoarchitecture plays a significant role in defining activity patterns and brain function. Indeed, the
functional characteristics of a given region are well-related to its cytoarchitecture (Badre and D'Esposito,
2009; Pandya and Yeterian, 1996), which includes the nature of incoming and outgoing axonal
connections (Hilgetag et al., 2019; Kritzer et al., 1992; Passingham et al., 2002), cell-type specific
characteristics (e.g. density, morphology; Benavides-Piccione et al. (2002); Beul and Hilgetag (2014)),
and laminar organization (Hooks et al., 2011). Local cytoarchitecture affects neuronal firing patterns,
which are known to vary consistently across functionally and anatomically well-defined regions (Badre
and D'Esposito, 2009; Mochizuki et al., 2016; Shinomoto et al., 2009). Anatomical differences between
granular and agranular cortical areas also result in distinct intra- and inter-laminar connectivity patterns
(Beul and Hilgetag, 2014; Shepherd, 2009), which may also affect the dynamics of the generators of
cortical oscillatory activity. Together, local anatomy, spiking patterns, and connectivity influence
mesoscopic measurements of activity such as LFPs or other signals recorded non-invasively (Buzsaki et
al., 2012; Cole and Voytek, 2017).

Other than local cytoarchitecture, respiration can also affect both single-neuron and oscillatory activities
(Tort et al., 2018). For example, respiratory rhythms in mice entrain single neuron spiking and local
cortical oscillations particularly –but not only- in frontal regions, (Koszeghy et al., 2018; Tort et al., 2018)
with measurable functional consequences (Bagur et al., 2021; Folschweiller and Sauer, 2023). Likewise,
heart rate fluctuations are known to correlate with brain oscillations, particularly during sleep (Mara and
Julian, 2018; Mikutta et al., 2022). Respiratory or cardiac rhythms were not measured in this study, but
their potential effects cannot be directly ruled out given that typical values for *C. perspicillata* lie close to
delta frequencies: respiration rate, ~2.5–4.5 Hz; hear rate: ~8.33 Hz. For example, it is possible that
respiration influences the patterns of rhythmicity and asymmetry overserved in frontal areas by directly
modulating the LFP, by synchronizing neuronal spiking (thereby altering the LFPs), or a combination of

both. Future studies should clarify the roles –if any- of respiration or heart rate in modifying oscillatory

waveform shape dynamics.

Delta-band oscillations differed markedly across regions in terms of their temporal asymmetries,

something that did not occur consistently for gamma-band activity (**Fig. 5**). However, for both frequency

ranges we observed large and consistent inter-areal differences in the variability of shape feature values

across individual cycles (**Fig. 6**). A conceptual model (**Fig. 8**) suggests that temporal asymmetries (i.e.

waveform shape features) and their variability across cycles, could depend on the degree of correlated

activity of the underlying neuronal population. The model in **Fig. 8** suggests that more synchronous

populations yield highly asymmetric waveform shape and lower cycle-by-cycle variability, while less

synchronous populations yield gradually a more sinusoidal shape with more variable cycle-by-cycle

features. That waveforms become less asymmetric can be explained by temporal averaging of the

contribution of each spike to the LFP, akin to the expected effects of spatial averaging in electro- or

magneto-encephalographic recordings (Schaworonkow and Nikulin, 2019). Note that the model does not

make any assumptions about important features of the underlying generators, such as location in the

local circuitry, connectivity patterns, or component cell-types. As discussed above, these factors can

influence both waveform shape and spiking dynamics. Instead, the model provides a parsimonious

account of the empirical data shown in **Fig. 5**, assuming only that spiking is an important contributor to

the LFP (Buzsaki et al., 2012). The model in **Fig. 8**, together with the waveform shape differences across

regions, affords one prediction, namely that spike-spike and spike-LFP correlations should be higher in

the area with more asymmetric signals (i.e. the FAF). Our results in **Fig. 9** corroborate such prediction,

illustrating that the bat frontal cortex exhibits more correlated spiking, which is also more strongly

synchronized the ongoing LFP phase in delta frequencies. As a concept, and supported by our data, the

model draws a relationship between waveform shape asymmetry and the temporal dynamics of neuronal

spiking in the neocortex.

A hypothesis stemming from the above observations is that differences in the variability of cycle features

(measured by the CV) between FAF and AC might be explained by different values of temporal

correlations in the underlying generators. In other words, it could be speculated that putative generators

in the FAF operate with tighter parameters (reflected in higher temporal correlations) than their AC

counterparts. One possible take on the functional implications of such phenomenon would be that frontal

circuits rely more on internal timescales, while auditory circuits exhibit an elevated flexibility and

perturbability. Previous studies have demonstrated that activity patterns in the rodent prefrontal cortex

exhibit less variability than those of sensory regions (Castano-Prat et al., 2017; Ruiz-Mejias et al., 2011),

potentially reflecting a cortical hierarchy of excitability and circuit properties. In such hierarchy, peripheral

areas exhibit more adaptability to sensory stimuli (and therefore more variability), while frontal areas

exhibit higher stimulus independence, yielding activity patterns better related to local network dynamics

(Badre and D'Esposito, 2009; Braun and Mattia, 2010; Ruiz-Mejias et al., 2011)). In the bat brain, the FAF

appears to be a modulation and control structure that may also be involved in the integration of diverse

inputs during echolocation and navigation, as reflected by its internal dynamics and by the anatomical

and functional connectivity patterns with other cortical and subcortical regions (Casseday et al., 1989;

Eiermann and Esser, 2000; Garcia-Rosales et al., 2022b; Kanwal et al., 2000; Kobler et al., 1987;

Weineck et al., 2020). Conversely, the bat AC (as that of other mammals) is primarily tasked with

representing sounds that may unfold in time over nested timescales, typically exhibiting varying degrees

of periodicity which require higher adaptability and flexibility (Doelling et al., 2019; Garcia-Rosales et al.,

2018; Henry and Obleser, 2012; Lakatos et al., 2013; Teng et al., 2017). Indeed, previous modelling work

suggests that neuronal response patterns in FAF and AC can be accounted for by slower synaptic

dynamics in the frontal region (Lopez-Jury et al., 2020), something that could be detrimental for precise

stimulus tracking but that could be important for sensory integration. From the above, we hypothesize that

a higher level of variability in the auditory cortical circuitry (**Fig. 6**) might aid with efficient sensory

representations in AC (see Pittman-Polletta et al. (2021)), while narrower dynamics could be important for

high-level computations in FAF (e.g. sensory integration), closely tied to internal timescales and more

robust against external perturbations.

In conclusion, we have shown that simultaneously recorded oscillatory activity across frontal and auditory

cortices differs markedly in waveform shape. Additionally, a conceptual model, paired with empirical

results, suggests a relationship between waveform shape and local spiking activity. This intriguing

relationship could serve as a tool for constraining generative models of neural oscillations, and can be

used to draw hypotheses after observing waveform shape differences across experimental conditions.

The oscillations studied here in frontal and auditory regions occur in similar frequencies and are

functionally related (**Fig. 4**; (Garcia-Rosales et al., 2022b)), but they nevertheless possess distinct

dynamics that reflect the heterogeneous anatomical and functional properties of the bat fronto-auditory

network.

References

Badre, D., and D'Esposito, M. (2009). Is the rostro-caudal axis of the frontal lobe hierarchical? Nature
Reviews Neuroscience *10*, 659-669.

Bagur, S., Lefort, J.M., Lacroix, M.M., de Lavilleon, G., Herry, C., Chouvaeff, M., Billand, C., Geoffroy, H.,
and Benchenane, K. (2021). Breathing-driven prefrontal oscillations regulate maintenance of conditioned-
fear evoked freezing independently of initiation. Nat Commun *12*, 2605.

Baranauskas, G., Maggiolini, E., Vato, A., Angotzi, G., Bonfanti, A., Zambra, G., Spinelli, A., and Fadiga,
L. (2012). Origins of 1/f2 scaling in the power spectrum of intracortical local field potential. J Neurophysiol
107, 984-994.

Benavides-Piccione, R., Ballesteros-Yanez, I., DeFelipe, J., and Yuste, R. (2002). Cortical area and
species differences in dendritic spine morphology. J Neurocytol *31*, 337-346.

Benjamini, Y., and Hochberg, Y.J.J.o.t.R.s.s.s.B. (1995). Controlling the false discovery rate: a practical
and powerful approach to multiple testing. *57*, 289-300.

Beul, S.F., and Hilgetag, C.C. (2014). Towards a "canonical" agranular cortical microcircuit. Front
Neuroanat *8*, 165.

Braun, J., and Mattia, M. (2010). Attractors and noise: twin drivers of decisions and multistability.
Neuroimage *52*, 740-751.

Buzsaki, G., Anastassiou, C.A., and Koch, C. (2012). The origin of extracellular fields and currents--EEG,
ECoG, LFP and spikes. Nat Rev Neurosci *13*, 407-420.

Camarda, R.M., and Bonavita, V. (1985). The frontal agranular cortex and the organization of purposeful
movements. Ital J Neurol Sci *6*, 287-315.

Casseday, J.H., Kobler, J.B., Isbey, S.F., and Covey, E. (1989). Central acoustic tract in an echolocating
bat: an extralemniscal auditory pathway to the thalamus. J Comp Neurol *287*, 247-259.

Castano-Prat, P., Perez-Zabalza, M., Perez-Mendez, L., Escorihuela, R.M., and Sanchez-Vives, M.V.
(2017). Slow and Fast Neocortical Oscillations in the Senescence-Accelerated Mouse Model SAMP8.
Front Aging Neurosci *9*, 141.

Cohen, J. (2013). Statistical power analysis for the behavioral sciences (Routledge).

Cole, S., Donoghue, T., Gao, R., and Voytek, B.J.J.o.O.S.S. (2019). NeuroDSP: a package for neural
digital signal processing. *4*, 1272.

Cole, S., and Voytek, B. (2019). Cycle-by-cycle analysis of neural oscillations. J Neurophysiol *122*, 849-
861.

Cole, S.R., van der Meij, R., Peterson, E.J., de Hemptinne, C., Starr, P.A., and Voytek, B. (2017).
Nonsinusoidal Beta Oscillations Reflect Cortical Pathophysiology in Parkinson's Disease. J Neurosci *37*,
4830-4840.

Cole, S.R., and Voytek, B. (2017). Brain Oscillations and the Importance of Waveform Shape. Trends
Cogn Sci *21*, 137-149.

Doelling, K.B., Assaneo, M.F., Bevilacqua, D., Pesaran, B., and Poeppel, D. (2019). An oscillator model
better predicts cortical entrainment to music. Proc Natl Acad Sci U S A *116*, 10113-10121.

Donoghue, T., Haller, M., Peterson, E.J., Varma, P., Sebastian, P., Gao, R., Noto, T., Lara, A.H., Wallis,
J.D., Knight, R.T.*, et al.* (2020). Parameterizing neural power spectra into periodic and aperiodic
components. Nat Neurosci *23*, 1655-1665.

Douglas, R.J., and Martin, K.A. (2004). Neuronal circuits of the neocortex. Annu Rev Neurosci *27*, 419-
451.

Eiermann, A., and Esser, K.H. (2000). Auditory responses from the frontal cortex in the short-tailed fruit
bat Carollia perspicillata. Neuroreport *11*, 421-425.

Esser, K.H., and Eiermann, A. (1999). Tonotopic organization and parcellation of auditory cortex in the
FM-bat Carollia perspicillata. Eur J Neurosci *11*, 3669-3682.

Folschweiller, S., and Sauer, J.F. (2023). Behavioral State-Dependent Modulation of Prefrontal Cortex
Activity by Respiration. J Neurosci *43*, 4795-4807.

Garcia-Rosales, F., Beetz, M.J., Cabral-Calderin, Y., Kossl, M., and Hechavarria, J.C. (2018). Neuronal
coding of multiscale temporal features in communication sequences within the bat auditory cortex.
Commun Biol *1*, 200.

Garcia-Rosales, F., Lopez-Jury, L., Gonzalez-Palomares, E., Cabral-Calderin, Y., and Hechavarria, J.C.
(2020). Fronto-Temporal Coupling Dynamics During Spontaneous Activity and Auditory Processing in the
Bat Carollia perspicillata. Front Syst Neurosci *14*, 14.

Garcia-Rosales, F., Lopez-Jury, L., Gonzalez-Palomares, E., Cabral-Calderin, Y., Kossl, M., and
Hechavarria, J.C. (2022a). Phase-amplitude coupling profiles differ in frontal and auditory cortices of bats.
Eur J Neurosci *55*, 3483-3501.

Garcia-Rosales, F., Lopez-Jury, L., Gonzalez-Palomares, E., Wetekam, J., Cabral-Calderin, Y., Kiai, A.,
Kossl, M., and Hechavarria, J.C. (2022b). Echolocation-related reversal of information flow in a cortical
vocalization network. Nat Commun *13*, 3642.

Garcia-Rosales, F., Rohrig, D., Weineck, K., Rohm, M., Lin, Y.H., Cabral-Calderin, Y., Kossl, M., and
Hechavarria, J.C. (2019). Laminar specificity of oscillatory coherence in the auditory cortex. Brain Struct
Funct *224*, 2907-2924.

Gourevitch, B., Martin, C., Postal, O., and Eggermont, J.J. (2020). Oscillations in the auditory system and
their possible role. Neurosci Biobehav Rev *113*, 507-528.

Gross, J., Schnitzler, A., Timmermann, L., and Ploner, M. (2007). Gamma oscillations in human primary
somatosensory cortex reflect pain perception. PLoS Biol *5*, e133.

Hechavarria, J.C., Beetz, M.J., Macias, S., and Kossl, M. (2016). Vocal sequences suppress spiking in
the bat auditory cortex while evoking concomitant steady-state local field potentials. Sci Rep *6*, 39226.

Helfrich, R.F., and Knight, R.T. (2019). Cognitive neurophysiology of the prefrontal cortex. Handb Clin
Neurol *163*, 35-59.

Henry, M.J., and Obleser, J. (2012). Frequency modulation entrains slow neural oscillations and
optimizes human listening behavior. Proc Natl Acad Sci U S A *109*, 20095-20100.

Hilgetag, C.C., Beul, S.F., van Albada, S.J., and Goulas, A. (2019). An architectonic type principle
integrates macroscopic cortico-cortical connections with intrinsic cortical circuits of the primate brain.
Netw Neurosci *3*, 905-923.

Hooks, B.M., Hires, S.A., Zhang, Y.X., Huber, D., Petreanu, L., Svoboda, K., and Shepherd, G.M. (2011).
Laminar analysis of excitatory local circuits in vibrissal motor and sensory cortical areas. PLoS Biol *9*,
e1000572.

Insel, N., Patron, L.A., Hoang, L.T., Nematollahi, S., Schimanski, L.A., Lipa, P., and Barnes, C.A. (2012).
Reduced gamma frequency in the medial frontal cortex of aged rats during behavior and rest: implications
for age-related behavioral slowing. J Neurosci *32*, 16331-16344.

Jackson, N., Cole, S.R., Voytek, B., and Swann, N.C. (2019). Characteristics of Waveform Shape in
Parkinson's Disease Detected with Scalp Electroencephalography. eNeuro *6*.

Kanwal, J.S., Gordon, M., Peng, J.P., and Heinz-Esser, K. (2000). Auditory responses from the frontal
cortex in the mustached bat, Pteronotus parnellii. Neuroreport *11*, 367-372.

Kienitz, R., Cox, M.A., Dougherty, K., Saunders, R.C., Schmiedt, J.T., Leopold, D.A., Maier, A., and
Schmid, M.C. (2021). Theta, but Not Gamma Oscillations in Area V4 Depend on Input from Primary
Visual Cortex. Curr Biol *31*, 635-642 e633.

Kobler, J.B., Isbey, S.F., and Casseday, J.H. (1987). Auditory pathways to the frontal cortex of the
mustache bat, Pteronotus parnellii. Science *236*, 824-826.

Koszeghy, A., Lasztoczi, B., Forro, T., and Klausberger, T. (2018). Spike-Timing of Orbitofrontal Neurons
Is Synchronized With Breathing. Front Cell Neurosci *12*, 105.

Kritzer, M.F., Cowey, A., and Somogyi, P. (1992). Patterns of inter- and intralaminar GABAergic
connections distinguish striate (V1) and extrastriate (V2, V4) visual cortices and their functionally
specialized subdivisions in the rhesus monkey. J Neurosci *12*, 4545-4564.

Lakatos, P., Chen, C.M., O'Connell, M.N., Mills, A., and Schroeder, C.E. (2007). Neuronal oscillations and
multisensory interaction in primary auditory cortex. Neuron *53*, 279-292.

Lakatos, P., Musacchia, G., O'Connel, M.N., Falchier, A.Y., Javitt, D.C., and Schroeder, C.E. (2013). The
spectrotemporal filter mechanism of auditory selective attention. Neuron *77*, 750-761.

Lakatos, P., Shah, A.S., Knuth, K.H., Ulbert, I., Karmos, G., and Schroeder, C.E. (2005). An oscillatory
hierarchy controlling neuronal excitability and stimulus processing in the auditory cortex. J Neurophysiol
94, 1904-1911.

Linden, J.F., and Schreiner, C.E. (2003). Columnar transformations in auditory cortex? A comparison to
visual and somatosensory cortices. Cereb Cortex *13*, 83-89.

Lopez-Jury, L., Mannel, A., Garcia-Rosales, F., and Hechavarria, J.C. (2020). Modified synaptic dynamics
predict neural activity patterns in an auditory field within the frontal cortex. Eur J Neurosci *51*, 1011-1025.

Luo, H., and Poeppel, D. (2007). Phase patterns of neuronal responses reliably discriminate speech in
human auditory cortex. Neuron *54*, 1001-1010.

Mara, M., and Julian, F.T. (2018). How heart rate variability affects emotion regulation brain networks.
Current Opinion in Behavioral Sciences *19*, 98-104.

Medvedev, A.V., and Kanwal, J.S. (2004). Local field potentials and spiking activity in the primary auditory
cortex in response to social calls. J Neurophysiol *92*, 52-65.

Mikutta, C., Wenke, M., Spiegelhalder, K., Hertenstein, E., Maier, J.G., Schneider, C.L., Feher, K.,
Koenig, J., Altorfer, A., Riemann, D.*, et al.* (2022). Co-ordination of brain and heart oscillations during
non-rapid eye movement sleep. J Sleep Res *31*, e13466.

Mochizuki, Y., Onaga, T., Shimazaki, H., Shimokawa, T., Tsubo, Y., Kimura, R., Saiki, A., Sakai, Y.,
Isomura, Y., Fujisawa, S.*, et al.* (2016). Similarity in Neuronal Firing Regimes across Mammalian Species.
J Neurosci *36*, 5736-5747.

Mountcastle, V.B. (1997). The columnar organization of the neocortex. Brain *120 (Pt 4)*, 701-722.

Neymotin, S.A., Tal, I., Barczak, A., O'Connell, M.N., McGinnis, T., Markowitz, N., Espinal, E., Griffith, E.,
Anwar, H., Dura-Bernal, S.*, et al.* (2022). Detecting Spontaneous Neural Oscillation Events in Primate
Auditory Cortex. eNeuro *9*.

Pandya, D.N., and Yeterian, E.H. (1996). Comparison of prefrontal architecture and connections. Philos
Trans R Soc Lond B Biol Sci *351*, 1423-1432.

Passingham, R.E., Stephan, K.E., and Kotter, R. (2002). The anatomical basis of functional localization in
the cortex. Nat Rev Neurosci *3*, 606-616.

Pittman-Polletta, B.R., Wang, Y., Stanley, D.A., Schroeder, C.E., Whittington, M.A., and Kopell, N.J.
(2021). Differential contributions of synaptic and intrinsic inhibitory currents to speech segmentation via
flexible phase-locking in neural oscillators. PLoS Comput Biol *17*, e1008783.

Rajan, A., Siegel, S.N., Liu, Y., Bengson, J., Mangun, G.R., and Ding, M. (2019). Theta Oscillations Index
Frontal Decision-Making and Mediate Reciprocal Frontal-Parietal Interactions in Willed Attention. Cereb
Cortex *29*, 2832-2843.

Ray, S. (2015). Challenges in the quantification and interpretation of spike-LFP relationships. Curr Opin
Neurobiol *31*, 111-118.

Ruiz-Mejias, M., Ciria-Suarez, L., Mattia, M., and Sanchez-Vives, M.V. (2011). Slow and fast rhythms
generated in the cerebral cortex of the anesthetized mouse. J Neurophysiol *106*, 2910-2921.

Schaworonkow, N., and Nikulin, V.V. (2019). Spatial neuronal synchronization and the waveform of
oscillations: Implications for EEG and MEG. PLoS Comput Biol *15*, e1007055.

Schaworonkow, N., and Voytek, B. (2021). Longitudinal changes in aperiodic and periodic activity in
electrophysiological recordings in the first seven months of life. Dev Cogn Neurosci *47*, 100895.

Shepherd, G.M. (2009). Intracortical cartography in an agranular area. Front Neurosci *3*, 337-343.

Shinomoto, S., Kim, H., Shimokawa, T., Matsuno, N., Funahashi, S., Shima, K., Fujita, I., Tamura, H.,
Doi, T., Kawano, K.*, et al.* (2009). Relating neuronal firing patterns to functional differentiation of cerebral
cortex. PLoS Comput Biol *5*, e1000433.

Tan, L.L., Oswald, M.J., Heinl, C., Retana Romero, O.A., Kaushalya, S.K., Monyer, H., and Kuner, R.
(2019). Gamma oscillations in somatosensory cortex recruit prefrontal and descending serotonergic
pathways in aversion and nociception. Nat Commun *10*, 983.

Tavares, L.C.S., and Tort, A.B.L. (2022). Hippocampal-prefrontal interactions during spatial decision-
making. Hippocampus *32*, 38-54.

Teng, X., Tian, X., Rowland, J., and Poeppel, D. (2017). Concurrent temporal channels for auditory
processing: Oscillatory neural entrainment reveals segregation of function at different scales. PLoS Biol
15, e2000812.

Tort, A.B.L., Brankack, J., and Draguhn, A. (2018). Respiration-Entrained Brain Rhythms Are Global but
Often Overlooked. Trends Neurosci *41*, 186-197.

Uran, C., Peter, A., Lazar, A., Barnes, W., Klon-Lipok, J., Shapcott, K.A., Roese, R., Fries, P., Singer, W.,
and Vinck, M. (2022). Predictive coding of natural images by V1 firing rates and rhythmic synchronization.
Neuron *110*, 2886-2887.

Veniero, D., Gross, J., Morand, S., Duecker, F., Sack, A.T., and Thut, G. (2021). Top-down control of
visual cortex by the frontal eye fields through oscillatory realignment. Nat Commun *12*, 1757.

Vinck, M., van Wingerden, M., Womelsdorf, T., Fries, P., and Pennartz, C.M. (2010). The pairwise phase
consistency: a bias-free measure of rhythmic neuronal synchronization. Neuroimage *51*, 112-122.

Weineck, K., Garcia-Rosales, F., and Hechavarria, J.C. (2020). Neural oscillations in the fronto-striatal
network predict vocal output in bats. PLoS Biol *18*, e3000658.

Zhang, S., Xu, M., Chang, W.C., Ma, C., Hoang Do, J.P., Jeong, D., Lei, T., Fan, J.L., and Dan, Y. (2016).
Organization of long-range inputs and outputs of frontal cortex for top-down control. Nat Neurosci *19*,
1733-1742.

Author Contributions

1001 F.G.R, N.S., and J.C.H. conceived and designed the research. F.G.R collected and analysed the data,

1002 produced original figures, and wrote the first draft of the manuscript. F.G.R., N.S, and J.C.H. discussed

1003 analyses and results, interpreted data, and reviewed figures and text.

1004