The insect compass system: From theory to circuitry

Pau Vilimelis Aceituno ⬤, Dominic Dall'Osto ⬤, Ioannis Pisokas ⬤

Abstract

To navigate their environment, insects need to keep track of their orientation. Previous work has shown that insects encode their head direction as a sinusoidal activity pattern around a ring of neurons arranged in an eight-column structure. However, it is unclear whether this sinusoidal encoding of head direction is just an evolutionary coincidence or if it offers a particular functional advantage. We address this question by establishing the basic mathematical requirements for direction encoding and show that several potential circuits with different activity patterns can perform the same function. We prove that among these activity patterns, the sinusoidal one is the most noise-resilient, but only when coupled with a specific connectivity pattern between the encoding neurons. We compare this optimal connectivity pattern with experimental data from the head direction circuits of the locust and the fruit fly, finding a remarkable agreement between our theory and experimental evidence. Furthermore, we demonstrate that our predicted circuit can emerge naturally using Hebbian plasticity, which means the neural connectivity does not need to be explicitly encoded in the genetic program of the insect but rather can emerge during development. Finally, we illustrate that in our theory, the consistent presence of the eight-column organisation of head direction circuits across multiple insect species is not a chance artefact but instead can be explained by basic evolutionary principles.

1 Introduction

Insects exhibit an impressive ability to navigate the world, travelling long distances to migrate, find food or reach places of interest before returning to their nests (Müller and Wehner, 1988; Menzel et al., 1996; Heinze et al., 2013; Collett, 2019), a feat that requires them to keep track of their orientation across long journeys (Mappes and Homberg, 2004; Merlin et al., 2012; Warren et al., 2019; Collett, 2019; Beetz et al., 2022). This orientation tracking is achieved by the use of visual cues as well as integrating angular velocity signals over time to maintain a heading estimate relative to a starting angle (Seelig and Jayaraman, 2015; Taube, 2007), known as *heading integration*.

Electrophysiological and calcium imaging studies have shown that the neural population encoding the head direction in insects has a sinusoid-shaped activation pattern (Labhart, 1988, 2000; Loesel and Homberg, 2001; Pfeiffer et al., 2005; Pfeiffer and Homberg, 2007; Kinoshita et al., 2007; Heinze et al., 2009; Homberg et al., 2011; el Jundi et al., 2014; ElJundi et al., 2019). Furthermore, downstream neural populations also encode velocity signals as sinusoidal activations (Lyu et al., 2022).

Theoretical work has speculated that this recurring motif of sinusoidal activity patterns might be so prevalent because it enables easy elementwise vector addition, where vectors encoded as sinusoidal activity waveforms can be added together to give a sinusoidal waveform encoding the sum of the vectors (Touretzky et al., 1993; Wittmann and Schwegler, 1995; Vickerstaff and Paolo, 2005). This allows the encoded heading to be easily used by downstream circuitry to track the insect's position (Mittelstaedt, 1985; Wittmann and Schwegler, 1995; Vickerstaff and Paolo, 2005; Haferlach et al., 2007; Wessnitzer et al., 2008; Sakura et al., 2008; Stone et al., 2017). Further studies have shown that models closely aligned with biological data can indeed implement heading integration using sinusoidal activity patterns (Pisokas et al., 2020; Turner-Evans et al., 2020), and that such circuits can be learned (Vafidis et al., 2022).

Here we show that enabling easy vector addition cannot be the unique driving factor for the presence of sinusoidal heading encodings, as many other circuits with different activity patterns can perform vector addition in the same way. This finding led us to question whether the sinusoidal activation patterns seen in insect navigation circuits are a coincidence, or if they might offer a particular functional advantage that was selected for during evolution.

To address this question, we consider the basic principles necessary for a circuit encoding direction. Of all the circuits fulfilling these requirements, the sinusoidal activity pattern offers the best resilience

to noise for the encoded information. However, obtaining this activity requires a circuit with a specific connectivity pattern between neurons. Thus, our theory provides a concrete prediction for the most noise-resilient heading integration circuit. We compare our predicted circuit with connectivity data for the desert locust (*Schistocerca gregaria*) and fruit fly (*Drosophila melanogaster*) using network analysis tools, showing a strong agreement. We then ask how an insect brain might develop such a circuit, finding that a simple Hebbian learning rule is sufficient. Finally, we combine ideas from replication dynamics with our theory, which leads us to the conclusion that the eight-column structure is a consequence of basic theoretical principles, rather than an evolutionary coincidence.

2   A theoretical circuit for head integration

We consider a population of N "compass neurons" with an activity that encodes the direction of the insect as an angular variable θ. We represent the activity of this population by a vector where each element corresponds to the activity of one neuron, $\mathbf{a}(\theta) = [\mathbf{a}_1(\theta), \mathbf{a}_2(\theta), ..., \mathbf{a}_N(\theta)]$. We take $N = 8$ neurons, consistent with data from many insect species which possess an eight-column organisation, with each column encoding a different direction (Honkanen et al., 2019; Stone et al., 2017; Pisokas et al., 2020).

Each neuron's activity is updated depending on its current firing rate and the inputs it receives, both from other neurons in the circuit and externally. We formulate this update rule as follows,

$$\dot{\mathbf{a}}(\theta) = -\mathbf{a}(\theta) + \phi \left[\mathbf{W}\mathbf{a}(\theta) + \mathbf{u}(t) \right], \tag{1}$$

where $\mathbf{W}$ is the circuit's weight matrix, representing the connections between neurons; ϕ is the neural activation function, that converts the total neural input into an output firing rate; and $\mathbf{u}(t)$ is the external input that encodes the insect's angular velocity, via the PEN population of neurons (Green et al., 2017; Turner-Evans et al., 2017; Sayre et al., 2021; Pisokas et al., 2020; Turner-Evans et al., 2020; Hulse et al., 2021).

To simplify our derivations we allow the neural activity values to be both positive and negative, interpreting these values as being relative to a baseline neural firing rate. Similarly, we allow the weights to be both positive and negative, a common simplification in computational models (Kadmon and Sompolinsky, 2015; Kriegeskorte and Golan, 2019). This simplification will be addressed in Section 3 where we compare our model with experimental data.

2.1   Mathematical principles for neural heading integration

A circuit capable of performing heading integration must fulfil the requirements outlined in Box 1. The first two requirements allow us to establish the family of possible path integration circuits. We then use the principle of noise minimisation to determine which circuits perform best.

Box 1: Requirements for a heading integration circuit

Circular topology: The activity should have the same topology as the variable it is encoding to prevent discontinuities. To encode heading, the activity should have the topology of a 1D circle.

Rotational Symmetry: The heading integration circuit should work similarly, irrespective of the direction in which the insect travels. There should not be a bias for any direction.

Noise minimisation: The circuit should minimise the noise of the neural representation so the insect can navigate as precisely as possible.

2.2 Constraints on the neural activity

The neural activity should encode the insect's head direction with the matching topology. Because the heading is a single angular variable, the topology of the activity space should be a 1D circle.

Furthermore, the symmetry requirement implies that rotating the heading of the insect should rotate the neural activity vector without changing its shape. Concretely, whether the insect is facing north or east, the activity of the neural population as a whole should be the same, but with the identity of the neuron with each activity value being different.

We can formalise the symmetry requirement by considering a head direction, θ, and a rotation by an integer multiple, k, of the angular spacing between neurons, $\Delta\theta = \frac{2\pi k}{N}$. In this case, individual neuron activities follow the relation

$$\mathbf{a}_n(\theta + \Delta\theta) = \mathbf{a}_{n-k \mod N}(\theta), \tag{2}$$

which enforces that the neural activity vector is circularly rotated as the head direction changes. This relation can be expressed in the Fourier domain where, by the shift property, the circular rotation becomes a multiplication by a complex exponential:

$$\mathcal{F}_f\left[\mathbf{a}(\theta + \Delta\theta)\right] = \mathcal{F}_f\left[\mathbf{a}(\theta)\right] e^{\frac{i2\pi k f}{N}}, \tag{3}$$

where $i = \sqrt{-1}$ and $f \in [0, ..., N-1]$ is the index of the spatial frequency, also called the harmonic. Activity with spatial frequency f has f "bumps" around the ring.

Since the complex exponential has unit norm, the magnitude of the Fourier components remains the same for any rotation, $\|\mathcal{F}[\mathbf{a}(\theta + \Delta\theta)]\| = \|\mathcal{F}[\mathbf{a}(\theta)]\| \;\forall \Delta\theta$. Therefore, the shape of the activity pattern, $\mathbf{a} \equiv \mathbf{a}(0)$, can also be fully specified by its Fourier domain representation, $\mathcal{F}[\mathbf{a}]$, and the phase of this activity profile around the network encodes the heading of the insect:

$$\mathcal{F}_f\left[\mathbf{a}(\theta)\right] = \mathcal{F}_f\left[\mathbf{a}\right] e^{i\theta f}. \tag{4}$$

Taking the inverse Fourier transform with the constraint that the neural activities must be real, we get the following form for the neural activity,

$$\mathbf{a}_n(\theta) = \sum_{f=0}^{N-1} \|\mathcal{F}_f\left[\mathbf{a}\right]\| \cos\left(\frac{2\pi f n}{N} + \theta f\right). \tag{5}$$

It should be noted that the phase offset, θf, of each cosine waveform scales with the spatial frequency. This is because higher frequency waveforms have shorter wavelengths (in terms of number of neurons), so need their phases to rotate more quickly to move at the same speed around the network.

To explain this in more detail, we consider the case where this scaling is not used and the phase offset is the same for all harmonics, shown in Fig. 1 top row. For $f = 1$ (red line in Fig. 1), the waveform has one bump and a wavelength of 8 neurons, so a 180° rotation corresponds to the waveform moving 4 neurons. But for $f = 2$ (blue line in Fig. 1), the waveform has two bumps and a wavelength of 4 neurons, so a 180° rotation corresponds to moving only 2 neurons, while a 4 neuron shift would correspond to a full rotation. That the waveforms for different frequencies move at different speeds through the network implies that, if multiple spatial frequencies are used to independently encode the heading, their positions would not be aligned and the combined waveform would change shape as different angles are encoded (purple line in Fig. 1). This violates the rotational symmetry principle, as the activity would look significantly different when the insect is facing north compared to south.

To solve this problem of misaligned harmonics, we return to the case specified in Eq. 5 where the phase offset is scaled linearly with the spatial frequency so that all waveforms move at the same speed and rotational symmetry is ensured, which is shown in Fig. 1 bottom row. For a network with $N = 8$ neurons, a 180° rotation shifts the activity waveform by 4 neurons. This 4 neuron shift corresponds to a $\frac{4}{8}$ or 180° phase offset for the $f = 1$ waveform, which has a wavelength of 8 neurons, but a $\frac{4}{4}$ or 360° phase offset for the $f = 2$ waveform, which has a wavelength of 4 neurons. While this maintains rotational symmetry, it implies that the $f = 2$ waveform is the same whether the heading angle 0° or 180° is encoded. As a consequence, a higher harmonic waveform (having $f > 1$) cannot on its own specify the encoded angle. The activity in all harmonics must be considered simultaneously to decode the angle, but even then this decoding might not be unique in the presence of noise (see Appendix II). The difficulties associated with multiple harmonic encodings will be further addressed in the following sections.

Figure 1: **Encoding heading with multiple harmonics.** Each panel shows the activity profiles encoding a particular heading value. Curves $f = 1$, $f = 2$, and $f = 1 + f = 2$ respectively denote the waveform of the first harmonic, second harmonic, and the sum of the two. The vertical dashed ($f = 1$ peak) and dotted lines ($f = 2$ peaks) indicate the neurons which respond maximally for the first and second harmonic, respectively. **Top row:** Encoding the heading as the sum of two independent harmonics causes the waveform to change shape as the insect rotates, because the waveform for each harmonic can only rotate a distance of $\frac{360°}{f}$ as the insect rotates a full revolution to ensure an unambiguous representation. **Bottom row:** If all harmonics are aligned to rotate at the same speed, the combined waveform shape does not change. However, this alignment implies that higher harmonic waveforms cannot be uniquely mapped back to a heading: here the $f = 2$ encoding is the same for $\theta = 0°$ and $180°$.

2.3   Constraints on heading integration circuits

The basic assumptions outlined earlier also constrain the possible heading integration circuits – such a circuit should allow activity of the required topology and rotational symmetry to stably exist and propagate. Together, these two principles require that the activity in the circuit should have a constant total magnitude. We consider that this constraint is enforced by the nonlinear neural activation function, ϕ, in Eq. 1, as detailed in Appendix I.

If the network activity is at the desired level, and we consider the external input $\mathbf{u}(t)$ to be projected onto the ring attractor such that it does not alter the total network activity, then we can consider the network dynamics to be linear at this operating point. Therefore, while within the space of possible activities that corresponds to the ring attractor, our circuit dynamics are effectively described as

$$\dot{\mathbf{a}}(\theta) = -\mathbf{a}(\theta) + \mathbf{W}\mathbf{a}(\theta) + \mathbf{u}(t). \tag{6}$$

The rotational symmetry principle also applies to the network. For the same shaped activity waveform to be able to stably exist at any position around the network, the network connectivity should also be rotationally symmetric. For example, the connection strength between the neurons encoding the north and north-east directions should be the same as between those encoding south and south-west. Mathematically, this imposes that the weight matrix, $\mathbf{W}$, is circulant, specifically that $\mathbf{W}_{n,m} = \mathbf{W}_{n+k,m+k}$. This matrix is fully specified by its first row, called the *connectivity profile* and

denoted ω, meaning that we can express the product of the matrix with the neural activity as

$$(\mathbf{W}\mathbf{a}(\theta))_k = \mathbf{W}_k \mathbf{a}(\theta) = \sum_{m=0}^{N-1} \mathbf{W}_{k,m} \mathbf{a}_m(\theta) = \sum_{m=0}^{N-1} \mathbf{W}_{0,m-k} \mathbf{a}_m(\theta) = \sum_{m=0}^{N-1} \omega_{m-k} \mathbf{a}_m(\theta), \qquad (7)$$

which can be simplified in terms of the convolution operation,

$$\mathbf{W}\mathbf{a}(\theta) = \omega * \mathbf{a}(\theta). \qquad (8)$$

Considering the case where the insect is not moving, $\mathbf{u}(t) = 0$, and the network activity is stable, $\dot{\mathbf{a}}(\theta) = 0$, we can combine Eq. 6 and Eq. 8 to get a relation for the stable network activity

$$\mathbf{a}(\theta) = \omega * \mathbf{a}(\theta). \qquad (9)$$

In the Fourier domain, this simplifies into

$$\mathcal{F}_f[\mathbf{a}(\theta)] = \mathcal{F}_f[\omega]\, \mathcal{F}_f[\mathbf{a}(\theta)]. \qquad (10)$$

As for the activity waveform analysis, we note that the Fourier transform is taken on the neural indices, not on the temporal domain.

Here we have N equations that have to be satisfied, since the Fourier transform of an N-dimensional vector is also N-dimensional. For each harmonic frequency f, Eq. 10 has two solutions:

- $\mathcal{F}_f[\omega] = 1$, which implies that activity with this spatial frequency is stable in the network, and so can encode the insect's heading.

- $\mathcal{F}_f[\mathbf{a}(\theta)] = 0$, meaning that the activity in this harmonic is zero, and thus nothing can be encoded in this frequency.

2.3.1 Minimising noise propagation in the circuit

The only constraint on the connectivity weights given by Eq. 10 is that, if a frequency is used for encoding then $\mathcal{F}_f[\omega] = 1$. There is no restriction on the weights for the inactive harmonics – they remain free parameters.

However, non-encoding channels can still propagate noise, which would be prevented by setting $\mathcal{F}_f[\omega] = 0$. To illustrate this, we consider white noise, denoted by ϵ, that is added to the neural activity. When this noisy activity evolves in accordance with the dynamics from Eq. 8, we have

$$\omega * (\mathbf{a}(\theta) + \epsilon) = \omega * \mathbf{a}(\theta) + \omega * \epsilon, \qquad (11)$$

where the term $\omega * \epsilon$ corresponds to noise and should therefore be dampened. We want to minimise the strength of that noise, which is quantified by its variance

$$\mathbf{Var}[\omega * \epsilon] = \mathbf{E}\left[\|\omega * \epsilon\|^2\right] = \|\omega\|^2 \mathbf{Var}[\epsilon]. \qquad (12)$$

Hence the magnitude of the noise that passes from one time interval to the next is modulated by the magnitude of the weight vector. By Parseval's theorem,

$$\sum_f |\mathcal{F}_f[\omega]|^2 = \sum_n |\omega_n|^2 = \|\omega\|^2, \qquad (13)$$

which implies that to minimise noise propagation in the network we should impose $\mathcal{F}_f[\omega] = 0$ for all harmonics, f, where $\mathcal{F}_f[\mathbf{a}(\theta)] = 0$. We show this in simulation in Fig. 2, where only the first harmonic encodes information and we vary the weights of the other harmonics. The noise is indeed minimised if the weights for all non-encoding harmonics are set to zero.

This result establishes that all non-encoding harmonics in the network should be set to 0 to minimise noise propagation, and allows us to recover the circuit connectivity

$$\omega_n = \sum_{f \in \mathbf{F}} \cos\left(\frac{2\pi n}{N} f\right), \qquad (14)$$

where $\mathbf{F}$ is the set of harmonics used to encode the head direction, $\mathbf{F} = \{f \in [1..N-1] : \|\mathcal{F}_f[\mathbf{a}]\| \neq 0\}$. The choice of $\mathbf{F}$ therefore determines both the harmonics used for encoding the angle in the activity, and the connectivity of the circuit that supports this activity.

We leverage the same logic to prove that the number of encoding channels does not affect the signal-to-noise ratio in the network. If we have c encoding channels, each with the same activity, the total activity will grow linearly with c. The noise will also grow with $\|\omega\|^2 = c$, meaning that the signal-to-noise ratio will remain constant.

We now return to the question of whether using one or multiple harmonics is better. As mentioned, the signal-to-noise ratio in the network remains constant as additional encoding channels, c, are used, but these extra encoding channels require a higher total neural activity. If the total activity in the network is limited, the signal-to-noise ratio is in fact *decreased* when using more than one harmonic.

$$\text{SNR} \propto \frac{\|\mathbf{a}\|^2}{\|\omega\|^2} = \frac{\|\mathbf{a}\|^2}{c}. \tag{15}$$

Additionally, as detailed in Section 2.2 and Appendix II, circuits using multiple harmonics perform worse in high noise environments because they are not guaranteed to provide an unambiguous orientation encoding. Finally, as we will discuss in Section 4 and Appendix VII, the use of multiple harmonics also complicates the circuit's development. We therefore only select circuits that use a single harmonic for further analysis, reducing the number of possibilities to N.

Figure 2: **Increased number of harmonics introduces more noise.** Increasing the number of active harmonic frequencies increases the effect of errors in the network. **A:** Weight matrix profiles, ω, for networks with increasing numbers of harmonics. **B:** Normally distributed noise with zero mean and standard deviation 0.3 was added to the network activity, then the network state updated until it reached steady state. Networks with fewer harmonics better filtered out noise. **C:** Noise variance increases linearly as the number of active harmonics increases, as predicted by Eq. 12. Multiple trials were performed with different random noise.

2.4   Determining the optimal circuit

As we consider networks with $N = 8$ neurons, consistent with multiple insect species (Honkanen et al., 2019; Stone et al., 2017; Pisokas et al., 2020), the possible single harmonic circuits are $f = \{1, 2, 3, 4, 5, 6, 7\}$, where the zeroth harmonic is discarded because it only represents the baseline neural activity. This gives the following activities and weights, derived from Eq. 5 and Eq. 14

$$\mathbf{a}_n(\theta) = \cos\left(\frac{2\pi n f}{N} + \theta\right) \quad \omega_n = \cos\left(\frac{2\pi f n}{N}\right). \tag{16}$$

The circuits for the first 4 harmonics are plotted in Fig. 3, but not all of these circuits are valid. In particular, circuits with even spatial frequencies have multiple neurons with identical activity values because they share a common divisor with $N = 8$, as explained in detail in Appendix III.2.

For $f = 4$ there are only 2 unique activity values, $\mathbf{a}_n = \pm \cos(\theta) \; \forall n$, so this circuit can only encode one dimension, not a circular topology (see Fig. 3 D). For $f = 2$ and $f = 6$ (not plotted), there are 4 unique activity values, allowing the angle to be properly encoded. However, these circuits are degenerate because they are actually composed of two independent subcircuits, each encoding one direction (see Fig. 3 B). Because the subcircuits are independent, they cannot constrain the activity to have the required circular topology.

All circuits with odd harmonic frequencies are equivalent. For example, as shown in Fig. 3, the connections in the circuit for $f = 3$ are the same as those for the $f = 1$ circuit after the neuron identities are permuted. As detailed in Appendix III.1, the frequencies $f = \{1, 3, 5, 7\}$ always give the same circuit because the odd frequencies are coprime with the number of neurons $N = 8$.

Since the activities and weights of all the non-degenerate circuits $f = \{1, 3, 5, 7\}$ are the same as the base harmonic $f = 1$ up to a permutation, we choose the lowest harmonic $f = 1$, which gives us the following activity and weights:

$$\mathbf{a}_n(\theta) = \cos\left(\frac{2\pi n}{N} + \theta\right)$$
$$\omega_n = \cos\left(\frac{2\pi n}{N}\right). \tag{17}$$

Figure 3: **Circuits for encoding with different harmonics.** We plot four circuits corresponding to each of the individual harmonics $f = 1, 2, 3, 4$. Excitatory synapses are marked in red and inhibitory in blue. Neurons are shown in yellow with each having a black arrow that marks the direction to which it is tuned from Eq. 16. The $f = 1$ circuit is the simplest and constitutes our baseline. For the other cases we plot the original connectivity in the upper row and the rearranged network in the lower row. We find that the $f = 2$ circuit consists of two independent subnetworks encoding orthogonal directions, the $f = 3$ case is identical to $f = 1$ after permuting neuron indices, and the $f = 4$ case results in two connected groups of neurons inhibiting each other, hence it can only encode one direction. As such, all cases either have a degenerate ring structure ($f = 2, 4$) or are equivalent to $f = 1$ after permutation.

3 Comparing the predicted circuit with biological data

Our theory proposes an optimally noise-resistant circuit for heading integration, and its corresponding activity. The prediction that heading should be encoded as a sinusoidal activity bump is consistent with previous theoretical models (Touretzky et al., 1993; Wittmann and Schwegler, 1995; Hartmann and Wehner, 1995; Zhang, 1996; Vickerstaff and Paolo, 2005; Haferlach et al., 2007; Stone et al., 2017), as well as experimental evidence in both the locust and fruit fly (Heinze et al., 2009; Turner-Evans et al., 2017). In addition to sinusoidal activity, our theory offers the novel proposition that the optimally noise-resilient heading integration circuit should have synaptic weights that follow a sinusoidal pattern. Given that sinusoidal weights are not necessary for producing sinusoidal activity – as discussed in Section 2.3.1 – we sought to validate this prediction using connectivity data from the locust and fruit fly.

However, before we can directly compare our model with biological circuits, we must address a number of modelling simplifications:

- In the model we considered a population of eight neurons, but in insects there are eight neural columns, each with several neuron types (EPG, PEG, PEN, $\Delta 7$). Of these we model only the EPG (known as the compass neurons) which encode the integrated head direction.

- The synaptic connections between neurons in our model can be both positive and negative, while biological neurons follow Dale's law, meaning that a single neuron can either have only positive or only negative synapses.

- The neural activity in the model was centred around zero and could have both positive and negative activity (firing rates), while real neurons only have positive firing rates.

Therefore, we simplified the biological connectivity to produce an equivalent circuit that could be directly compared with our model prediction. The neural population in our theoretical model corresponds to the biological EPG neurons, as these encode the integrated heading. We considered the other three neurons types that are part of the compass circuit (PEG, PEN, $\Delta 7$, see Kakaria and de Bivort (2017); Pisokas et al. (2020)) as just implementing connections between EPG neurons in accordance with biological constraints. We counted the number of different paths between EPG neurons, accounting for the sign of the connections (whether the path passed through an inhibitory $\Delta 7$ neuron), and used the net path count as a proxy for connectivity strength. This process is explained in detail in Appendix IV.

We then computed the average connectivity profile, how each neuron connected to its neighbours around the ring, and compared this profile to the closest fitting sinusoid. Because the neuron gains, absolute synaptic strength and biophysical properties of the neurons are unknown, the units of the net path count are not necessarily equivalent to our abstract connection strength. We therefore fit an arbitrarily scaled and shifted sinusoid to the connection counts:

$$\omega_{m-n} = \beta \cos\left(\frac{2\pi(m-n)}{N}\right) + \gamma, \tag{18}$$

where $m - n$ is the circular distance between two neurons while β and γ are constants that are fit to minimise the precision-weighted mean squared error compared with the experimental connectivity profile (see Appendix VI).

Analysing the data from Pisokas et al. (2020) we consider the shortest excitatory and inhibitory paths between EPG neurons in the locust, which have lengths of 2 and 3, respectively. There are no direct connections of length 1, and all the paths of length ≥ 4 must pass through the same neuron type multiple times. This path counting analysis for the locust is shown in Fig. 4 A, and the procedure is detailed in Appendix IV. We find that the connectivity profile between neurons for the locust is very close to sinusoidal in shape, supporting our theoretical prediction.

For the fruit fly, we used data from Hulse et al. (2021) which provides synapse counts between pairs of neurons. These synapse counts were used as a proxy for connectivity strength, a view that has been validated in previous experiments (Liu et al., 2022; Barnes et al., 2022). After identifying the neurons and connections of interest, we grouped the neurons in eight columns following the logic presented in Pisokas et al. (2020), with detailed methodology explained in Appendix V.

We repeated the path counting analysis for the fruit fly with synapse count data (Fig. 4, B), and found that while the data are noisy, the connectivity profile is more consistent with our predicted single sinusoid pattern than other alternatives (see Appendix VI).

We therefore confirm our prediction of a sinusoidal shaped weight pattern in the navigation circuits of both insect species – using connectivity-level data for the desert locust and synapse-count data for the fruit fly.

Figure 4: **Comparison to biological data.** Biological network models with 4 distinct neural populations were simplified to equivalent networks with 1 population by counting paths of length 1, 2, and 3 between EPG neurons (which encode the integrated heading) and using the net signed path count as a proxy for connectivity strength. The average connectivity profile for each neuron to its neighbours around the ring was compared to the sinusoidal connectivity predicted by our theory. The locust network has no standard deviation because the data in Pisokas et al. (2020) are based on light microscopy which couldn't resolve variations between columns. Excitatory connections are shown in red and inhibitory connections in blue, while the strength of a connection is indicated by the line width.

4 Learning rules and development

Having validated the connectivity of our theoretical circuit by comparing it to experimental data, we ask whether our circuit lends itself to biological development. Specifically, we show that even though our circuit requires precise connection strengths, this connectivity can be developed naturally by a Hebbian learning rule. Previous work has shown that a head direction circuit can emerge from a predictive rule paired with a supervision signal (Vafidis et al., 2022), but here we show that an even simpler rule and circuit suffices.

Because the weight matrix is circulant, its eigenvalues are equal to the Fourier spectrum of its first row, which we derived to only have one nonzero value, for $f = 1$. The network therefore only has a single eigenvalue and so projects activity into a single dimension. This operation is similar to classical dimensionality reduction methods such as principal component analysis, which can be implemented by Hebbian-like learning rules (Dayan and Abbott, 2001). We thus analyse the effects of incorporating Oja's rule into our model, a classical variant of Hebbian learning where the synaptic strength between two neurons grows when both neurons are active simultaneously, and the total synaptic strength is regularised to prevent exploding weight growth,

$$\frac{d\mathbf{W}_{n,m}}{dt} = \eta \left(a_m(t)a_n(t) - a_n^2(t)\mathbf{W}_{n,m} \right), \tag{19}$$

where $\mathbf{W}_{n,m}$ is the synaptic connection strength from neuron m to neuron n, a_m and a_n are the pre- and postsynaptic activities respectively, and η sets the speed of the weight update dynamics relative to the activity dynamics.

For our analysis we integrate the weight updates over some long period of time, after which the insect has visited many directions,

$$\Delta\mathbf{W}_{n,m} = \eta \int_\theta \left[a_m(\theta)a_n(\theta) - a_n(\theta)^2 \mathbf{W}_{n,m} \right] d\theta, \tag{20}$$

where θ is the integration space. We will assume that the insect moves uniformly over the full circle. Applying the activity from Eq. 17, we can find the fixed point of this update rule, when $\Delta\mathbf{W}_{n,m} = 0$:

$$\mathbf{W}_{n,m} = \frac{\eta \int_\theta \cos\left(\theta + \frac{2\pi n}{N}\right) \cos\left(\theta + \frac{2\pi m}{N}\right) d\theta}{\eta \int_\theta \cos^2\left(\theta + \frac{2\pi n}{N}\right) d\theta} \quad = \cos\left(\frac{2\pi(n-m)}{N}\right). \tag{21}$$

Combined with Eq. 7 and Eq. 17, this result means that if there is sinusoidal activity in the network, the weights will naturally converge to the optimal sinusoidal values by way of Oja's rule. This leads to the emergence of sinusoidal activity and weights from self-consistency: initial noisy sinusoidal activity will enforce weights that are close to a sinusoid, and those weights will filter out noise to make the activity even closer to a sinusoid, which will in turn make the weights more sinusoidal. This process will iteratively make the activity and the weights converge to the solution from Eq. 17.

However, this learning rule, or related ones, do not work for combinations of harmonics, because the harmonics would compete in the learning, as explained in Appendix VII. This further supports the choice of a single encoding harmonic.

The finding that the weights will converge to a sinusoidal connectivity with learning has two interesting consequences from a biological standpoint: First, our circuit can emerge even when starting with only very coarse initial weights, without the need for high precision initial connectivity. Second, this simple plasticity rule allows the system to repair or recover from perturbations in its synapses as shown by simulations in Fig. 5.

Figure 5: **Recovery of synaptic weights with a Hebbian learning rule.** The synaptic weights converge to a sinusoidal pattern under Oja's rule when the network activity is dynamic and a sinusoidal input is provided. On the left, the weights start at zero and slowly converge to the prescribed sinusoidal profile, showing that this connectivity can emerge from scratch. On the right, the sinusoidal weights are perturbed by noise but learning ensures that the weight profile is corrected. In both cases the network's initial activity is corrupted with zero mean Gaussian noise. Noisy sinusoidal input is provided to rotate the activity bump around the network at a speed of $1/8$ neurons per timestep. The simulation runs for 100 periods. Parameters: $N = 8$, integration timestep $\Delta t = 0.01, \eta = 0.1, \|\mathbf{a}\| = 1, \sigma_W = 0.2, \sigma_a = 0.2, \sigma_u = 0.2$.

5   Evolution of the eight-column circuit

Having derived and experimentally validated the theoretical circuit, we now address another question: whether there might be a reason that insect head direction circuits typically have an eight-column architecture (Honkanen et al., 2019; Stone et al., 2017; Pisokas et al., 2020). The derivations leading to Eq. 17 are valid for other values of N, so there is no *a priori* reason to expect $N = 8$.

Our reasoning follows recent studies in genetics (Johnston et al., 2022; Dingle et al., 2018), which argue that an observed organism is more likely to have resulted from a simple than a more complex genome: evolution favours simplicity. We note that powers of two are easier to generate with replication dynamics than other numbers, because they just require each cell to divide a set number of times. Other numbers require that, at some point, two cells resulting from a division must behave differently, necessitating more complex signalling mechanisms and rendering this possibility less likely to occur by natural evolution. We therefore expect N to be a power of two unless required to be otherwise.

As we show in Appendix III.3, not all numbers of neurons enable a working circuit. The circuits for $N = 2$ and $N = 4$ are degenerate – either producing a single dimensional encoding, or two disconnected circuits that do not enforce the required circular topology. $N = 8$ is the smallest power of two that could result in a non-degenerate circuit. This hints at the possibility that the eight-column architecture is not a chance evolutionary artefact, but rather that it is the genetically simplest circuit capable of performing heading integration.

6   Discussion

In this work we derived an optimal noise-minimising circuit for encoding heading and verified that this circuit matches experimental data from insects. Finally, we showed that such a circuit can be developed and maintained by a biological learning rule, and proposed a mathematical argument for the eight-column structure found in insect compass circuits. In this section, we discuss the implications and limitations of these contributions, and outline potential future work.

Heading integration circuits in insects have been extensively studied, with models ranging in complexity from simplified conceptual networks (Wittmann and Schwegler, 1995; Cope et al., 2017) to sophisticated models constrained by biological data and featuring multiple neuron types (Kakaria and de Bivort, 2017; Su et al., 2017; Kim et al., 2017; Pisokas et al., 2020; Lyu et al., 2022). Previous theoretical work has argued that a sinusoidal activity encoding is such a common motif in insect navigation because it facilitates elementwise vector addition (Wittmann and Schwegler, 1995). However, this cannot be the full story because we derive a whole family of circuits with different encoding patterns that enable easy vector addition. By showing that the sinusoidal activity emerges from the theoretically most noise-resilient heading integration circuit, and verifying that the corresponding circuit matches experimental data, we close this explanatory gap.

We also show that our proposed circuit can be developed by a simple Hebbian-based learning rule, and that the presence of the eight-column structure can be explained from the perspective of replication dynamics. Both results align with the idea that evolution should be biased towards structures that are easier to encode in the genome (Johnston et al., 2022; Alon, 2007) and learn (Zador, 2019). To the best of our knowledge, this is the first time that such arguments have been put forward in the context of a specific circuit with a specific function.

Our work still has some unaddressed limitations, in particular regarding the topology of the activity. The use of a circular topology to encode the head direction of the insect is valid only in 2D environments. But many species, including the fruit fly, can navigate in a 3D environment. We argue that even if these insects live in a 3D environment, the third dimension (up-down) is different from the other two due to gravity and the existence of a hard boundary (the ground). Further studies would be required to investigate the full effects of 3D motion.

We could also investigate circuits that integrate position, not only heading, which would require the activity to have a 2D plane topology instead of a circle. This would be particularly relevant for foraging insects like bees or ants, whose ability to remember their position with respect to their nest has been the subject of many experimental and computational studies (Collett, 2019; Wehner and Srinivasan, 2003). The position integrating neurons in these insects are also predicted to have sinusoidal activations (Wittmann and Schwegler, 1995; Vickerstaff and Paolo, 2005; Stone et al., 2017).

Finally, another interesting avenue for future work is to compare the encoding of direction in insects with that of mammals, which encode heading in a fundamentally different way that uses many more neurons. This raises a critical question: why would the circuit and encoding be different if navigation follows similar principles across species? We speculate that the difference might lie in the type of navigation that the two classes of animals use. Insects often rely on a reference system that is globally anchored to a certain point or phenomenon, whether it is their nests for ants and bees, the sunlight polarisation pattern for locusts, or the milky way for dung beetles. On the other hand, mammals such as rodents typically do not use global cues but rely on local landmarks that are context-dependent and only occur in specific locations. Therefore, mammals must employ a flexible encoding that can be updated as different environments are explored. Further investigation of this possibility would require a different set of principles than those selected here.

References

Uri Alon. Simplicity in biology. *Nature*, 446(7135):497–497, 2007. doi: 10.1038/446497a.

Christopher L Barnes, Daniel Bonnéry, and Albert Cardona. Synaptic counts approximate synaptic contact area in drosophila. *Plos one*, 17(4):e0266064, 2022. doi: 10.1371/journal.pone.0266064.

M. Jerome Beetz, Christian Kraus, Myriam Franzke, David Dreyer, Martin F. Strube-Bloss, Wolfgang Rössler, Eric J. Warrant, Christine Merlin, and Basil el Jundi. Flight-induced compass representation in the monarch butterfly heading network. *Current Biology*, 32(2):338–349.e5, 2022. ISSN 0960-9822. doi: 10.1016/j.cub.2021.11.009.

Kenneth P Burnham and David R Anderson. Model selection and multimodel inference. *A practical information-theoretic approach*, 2, 2004. doi: 10.1007/b97636.

T. S. Collett. Path integration: how details of the honeybee waggle dance and the foraging strategies of desert ants might help in understanding its mechanisms. *Journal of Experimental Biology*, 222 (11):jeb205187, May 2019. ISSN 1477-9145. doi: 10.1242/jeb.205187.

Alex J. Cope, Chelsea Sabo, Eleni Vasilaki, Andrew B. Barron, and James A.R. Marshall. A computational model of the integration of landmarks and motion in the insect central complex. *PLoS ONE*, 12(2):e0172325, February 2017. ISSN 19326203. doi: 10.1371/journal.pone.0172325.

Peter Dayan and L. F. Abbott. *Theoretical Neuroscience: Computational and Mathematical Modeling of Neural Systems*. Computational Neuroscience. Massachusetts Institute of Technology Press, Cambridge, Mass, 2001. ISBN 978-0-262-04199-7.

Kamaludin Dingle, Chico Q Camargo, and Ard A Louis. Input–output maps are strongly biased towards simple outputs. *Nature communications*, 9(1):761, 2018. doi: 10.1038/s41467-018-03101-6.

Basil el Jundi, Keram Pfeiffer, Stanley Heinze, and Uwe Homberg. Integration of polarization and chromatic cues in the insect sky compass. *Journal of Comparative Physiology A: Neuroethology, Sensory, Neural, and Behavioral Physiology*, 200(6):575–589, Mar 2014. ISSN 14321351. doi: 10.1007/s00359-014-0890-6.

B. ElJundi, E. Baird, M.J. Byrne, and M. Dacke. The brain behind straight-line orientation in dung beetles. *Journal of Experimental Biology*, 222, 2019. doi: 10.1242/jeb.192450.

Jonathan Green, Atsuko Adachi, Kunal K. Shah, Jonathan D. Hirokawa, Pablo S. Magani, and Gaby Maimon. A neural circuit architecture for angular integration in *Drosophila*. *Nature*, 546(7656): 101–106, May 2017. ISSN 14764687. doi: 10.1038/nature22343.

Thomas Haferlach, Jan Wessnitzer, Michael Mangan, and Barbara Webb. Evolving a neural model of insect path integration. *Adaptive Behavior*, 15(3):273–287, 2007. ISSN 1059-7123. doi: 10.1177/1059712307082080.

Georg Hartmann and Rüdiger Wehner. The ant's path integration system: a neural architecture. *Biological cybernetics*, 73(6):483–497, 1995. doi: 10.1007/s004220050204.

Stanley Heinze, Sascha Gotthardt, and Uwe Homberg. Transformation of polarized light information in the central complex of the locust. *The Journal of neuroscience: the official journal of the Society for Neuroscience*, 29(38):11783–93, sep 2009. ISSN 1529-2401. doi: 10.1523/JNEUROSCI.1870-09.2009.

Stanley Heinze, Jeremy Florman, Surainder Asokaraj, Basil el Jundi, and Steven M. Reppert. Anatomical basis of sun compass navigation II: The neuronal composition of the central complex of the monarch butterfly. *Journal of Comparative Neurology*, 521(2):267–298, February 2013. ISSN 00219967. doi: 10.1002/cne.23214.

Uwe Homberg, Stanley Heinze, Keram Pfeiffer, Michiyo Kinoshita, and Basil El Jundi. Central neural coding of sky polarization in insects. *Philosophical Transactions of the Royal Society B: Biological Sciences*, 366(1565):680–687, 2011. ISSN 14712970. doi: 10.1098/rstb.2010.0199.

Anna Honkanen, Andrea Adden, Josiane da Silva Freitas, and Stanley Heinze. The insect central complex and the neural basis of navigational strategies. *Journal of Experimental Biology*, 222(Suppl_1): jeb188854, 2019. doi: 10.1242/jeb.188854.

Brad K Hulse, Hannah Haberkern, Romain Franconville, Daniel B Turner-Evans, Shin-ya Takemura, Tanya Wolff, Marcella Noorman, Marisa Dreher, Chuntao Dan, Ruchi Parekh, Ann M Hermundstad, Gerald M Rubin, and Vivek Jayaraman. A connectome of the drosophila central complex reveals network motifs suitable for flexible navigation and context-dependent action selection. *eLife*, 10, 2021. doi: 10.7554/elife.66039.

Iain G Johnston, Kamaludin Dingle, Sam F Greenbury, Chico Q Camargo, Jonathan PK Doye, Sebastian E Ahnert, and Ard A Louis. Symmetry and simplicity spontaneously emerge from the algorithmic nature of evolution. *Proceedings of the National Academy of Sciences*, 119(11):e2113883119, 2022. doi: 10.1073/pnas.2113883119.

Jonathan Kadmon and Haim Sompolinsky. Transition to chaos in random neuronal networks. *Physical Review X*, 5(4):041030, 2015. doi: 10.1103/PhysRevX.5.041030.

Kyobi S. Kakaria and Benjamin L. de Bivort. Ring attractor dynamics emerge from a spiking model of the entire protocerebral bridge. *Frontiers in Behavioral Neuroscience*, 11:8, February 2017. ISSN 1662-5153. doi: 10.3389/fnbeh.2017.00008.

Sung Soo Kim, Hervé Rouault, Shaul Druckmann, and Vivek Jayaraman. Ring attractor dynamics in the Drosophila central brain. *Science*, 356(6340):849–853, may 2017. ISSN 1095-9203. doi: 10.1126/science.aal4835.

Michiyo Kinoshita, Keram Pfeiffer, and Uwe Homberg. Spectral properties of identified polarized-light sensitive interneurons in the brain of the desert locust schistocerca gregaria. *The Journal of experimental biology*, 210(Pt 8):1350–61, 2007. ISSN 0022-0949. doi: 10.1242/jeb.02744.

Nikolaus Kriegeskorte and Tal Golan. Neural network models and deep learning. *Current Biology*, 29 (7):R231–R236, April 2019. ISSN 09609822. doi: 10.1016/j.cub.2019.02.034.

Thomas Labhart. Polarization-opponent interneurons in the insect visual system. *Nature*, 331(6155): 435–437, 1988. ISSN 0028-0836. doi: 10.1038/331435a0.

Thomas Labhart. Polarization-sensitive interneurons in the optic lobe of the desert ant cataglyphis bicolor. *Naturwissenschaften*, 87(3):133–136, 2000. ISSN 0028-1042. doi: 10.1007/s001140050691.

Tony X. Liu, Pasha A. Davoudian, Kristyn M. Lizbinski, and James M. Jeanne. Connectomic features underlying diverse synaptic connection strengths and subcellular computation. *Current Biology*, 32 (3):559–569.e5, February 2022. ISSN 0960-9822. doi: 10.1016/j.cub.2021.11.056.

Rudi Loesel and Uwe Homberg. Anatomy and physiology of neurons with processes in the accessory medulla of the cockroach leucophaea maderae. *Journal of Comparative Neurology*, 439(2):193–207, 2001. ISSN 0021-9967. doi: 10.1002/cne.1342.

Cheng Lyu, L. F. Abbott, and Gaby Maimon. Building an allocentric travelling direction signal via vector computation. *Nature*, 601(7891):92–97, 2022. ISSN 0028-0836. doi: 10.1038/s41586-021-04067-0.

M. Mappes and U. Homberg. Behavioral analysis of polarization vision in tethered flying locusts. *Journal of Comparative Physiology A*, 190(1):61–68, January 2004. ISSN 1432-1351. doi: 10.1007/s00359-003-0473-4.

R Menzel, K Geiger, L Chittka, J Joerges, J Kunze, and U Müller. The knowledge base of bee navigation. *Journal of Experimental Biology*, 199(1):141–146, 1996. ISSN 1477-9145. doi: 10.1242/jeb.199.1.141.

Christine Merlin, Stanley Heinze, and Steven M Reppert. Unraveling navigational strategies in migratory insects. *Current Opinion in Neurobiology*, 22(2):353–361, April 2012. ISSN 0959-4388. doi: 10.1016/j.conb.2011.11.009.

Horst Mittelstaedt. Analytical cybernetics of spider navigation. In Friedrich G. Barth, editor, *Neurobiology of Arachnids*, pages 298–316. Springer Berlin Heidelberg, 1985. ISBN 978-3-642-70348-5. doi: 10.1007/978-3-642-70348-5_15.

M. Müller and Rüdiger Wehner. Path integration in desert ants, *Cataglyphis fortis. Proceedings of the National Academy of Sciences*, 85(14):5287–5290, 1988. doi: 10.1073/pnas.85.14.5287.

Keram Pfeiffer and Uwe Homberg. Coding of azimuthal directions via time-compensated combination of celestial compass cues. *Current Biology*, 17(11):960–965, jun 2007. ISSN 0960-9822. doi: 10.1016/J.CUB.2007.04.059.

Keram Pfeiffer, Michiyo Kinoshita, and Uwe Homberg. Polarization-sensitive and light-sensitive neurons in two parallel pathways passing through the anterior optic tubercle in the locust brain. *Journal of neurophysiology*, 94(6):3903–15, 2005. ISSN 0022-3077. doi: 10.1152/jn.00276.2005.

Ioannis Pisokas, Stanley Heinze, and Barbara Webb. The head direction circuit of two insect species. *eLife*, 9:e53985, July 2020. ISSN 2050-084X. doi: 10.7554/eLife.53985.

Midori Sakura, Dimitrios Lambrinos, and Thomas Labhart. Polarized skylight navigation in insects: model and electrophysiology of e-vector coding by neurons in the central complex. *Journal of neurophysiology*, 99(2):667–82, 2008. ISSN 0022-3077. doi: 10.1152/jn.00784.2007.

Marcel Ethan Sayre, Rachel Templin, Johanna Chavez, Julian Kempenaers, and Stanley Heinze. A projectome of the bumblebee central complex. *eLife*, 10:e68911, 2021. doi: 10.7554/elife.68911.

Johannes D. Seelig and Vivek Jayaraman. Neural dynamics for landmark orientation and angular path integration. *Nature*, 521(7551):186–191, May 2015. ISSN 14764687. doi: 10.1038/nature14446.

Thomas Stone, Barbara Webb, Andrea Adden, Nicolai Ben Weddig, Anna Honkanen, Rachel Templin, William Wcislo, Luca Scimeca, Eric Warrant, and Stanley Heinze. An anatomically constrained model for path integration in the bee brain. *Current Biology*, 27(20):3069–3085, 2017. ISSN 0960-9822. doi: 10.1016/j.cub.2017.08.052.

Ta Shun Su, Wan Ju Lee, Yu Chi Huang, Cheng Te Wang, and Chung Chuan Lo. Coupled symmetric and asymmetric circuits underlying spatial orientation in fruit flies. *Nature Communications*, 8(1), 2017. ISSN 20411723. doi: 10.1038/s41467-017-00191-6.

Jeffrey S Taube. The head direction signal: origins and sensory-motor integration. *Annu. Rev. Neurosci.*, 30:181–207, 2007. doi: 10.1146/annurev.neuro.29.051605.112854.

David S. Touretzky, A. David Redish, and Hank S. Wan. Neural representation of space using sinusoidal arrays. *Neural Computation*, 5(6):869–884, nov 1993. ISSN 0899-7667. doi: 10.1162/neco.1993.5.6.869.

Daniel Turner-Evans, Stephanie Wegener, Hervé Rouault, Romain Franconville, Tanya Wolff, Johannes D Seelig, Shaul Druckmann, and Vivek Jayaraman. Angular velocity integration in a fly heading circuit. *eLife*, 6:2112–2126, May 2017. ISSN 2050-084X. doi: 10.7554/elife.23496.

Daniel B. Turner-Evans, Kristopher T. Jensen, Saba Ali, Tyler Paterson, Arlo Sheridan, Robert P. Ray, Tanya Wolff, J. Scott Lauritzen, Gerald M. Rubin, Davi D. Bock, and Vivek Jayaraman. The neuroanatomical ultrastructure and function of a biological ring attractor. *Neuron*, 108(1): 145–163.e10, 2020. ISSN 10974199. doi: 10.1016/j.neuron.2020.08.006.

Pantelis Vafidis, David Owald, Tiziano D'Albis, and Richard Kempter. Learning accurate path integration in ring attractor models of the head direction system. *Elife*, 11:e69841, 2022. doi: 10.7554/eLife.69841.

R. J. Vickerstaff and E. A. Di Paolo. Evolving neural models of path integration. *Journal of Experimental Biology*, 208(17):3349–3366, 2005. doi: 10.1242/jeb.01772.

Timothy L T.L. Warren, Ysabel M Y.M. Giraldo, and M.H. Michael H Dickinson. Celestial navigation in *Drosophila*. *Journal of Experimental Biology*, 222:jeb186148, February 2019. ISSN 1477-9145. doi: 10.1242/jeb.186148.

Rüdiger Wehner and Mandyam V. Srinivasan. Path integration in insects. In K.J. Jeffery, editor, *The Neurobiology of Spatial Behaviour*, pages 9–30. Oxford University Press, November 2003. ISBN 978-0-19-851524-1. doi: 10.1093/acprof:oso/9780198515241.003.0001.

Jan Wessnitzer, Thomas Haferlach, Michael Mangan, and Barbara Webb. Path integration using a model of e-vector orientation coding in the insect brain: Reply to vickerstaff and di paolo. *Adaptive Behavior*, 16(4):277–280, 2008. doi: 10.1177/1059712308094947.

Thomas Wittmann and Helmut Schwegler. Path integration - a network model. *Biological Cybernetics*, 73(6):569–575, 1995. ISSN 3401200. doi: 10.1007/bf00199549.

Anthony M Zador. A critique of pure learning and what artificial neural networks can learn from animal brains. *Nature communications*, 10(1):3770, 2019. doi: 10.1038/s41467-019-11786-6.

Kechen Zhang. Representation of spatial orientation by the intrinsic dynamics of the head-direction cell ensemble: a theory. *Journal of Neuroscience*, 16(6):2112–2126, 1996. doi: 10.1523/JNEUROSCI.16-06-02112.1996.

Author contributions

P.V.A. and I.P. designed and conceptualised the project. D.D. performed the simulations. P.V.A. and D.D. performed the analytical calculations. P.V.A. and I.P. designed the data analysis and D.D. implemented it. All authors wrote the manuscript.

Code availability

We make the code used for all analysis and figure generation available at https://github.com/Dominic-DallOsto/insect-navigation-sinusoidal-optimality.

Acknowledgements

We would like to thank Benjamin F. Grewe for his support and helpful comments.

I Path integration dynamics for heading and position

Here we make more precise statements about the dynamics of the circuit. The topology of the activity is a circular line attractor, so that any perturbation falls back into a circle and the position of the activity around the circle represents an angle. In our circuit with the dynamics from Eq. 1, this circular line attractor is achieved by setting

$$
\begin{aligned}
\|\phi'\left[\mathbf{Wa}\right]\| = 1 \quad &\forall \|\mathbf{a}\| = r \\
\|\phi'\left[\mathbf{Wa}\right]\| < 1 \quad &\forall \|\mathbf{a}\| > r \\
\|\phi'\left[\mathbf{Wa}\right]\| > 1 \quad &\forall \|\mathbf{a}\| < r.
\end{aligned}
\tag{22}
$$

where r is the radius of the attractor. Effectively we can write the original dynamics around the line attractor directly in the spatial Fourier basis,

$$
\dot{\mathcal{F}_f}[\mathbf{a}] = -\mathcal{F}_f[\mathbf{a}] + (1 + \alpha(r - \|\mathbf{a}\|))\mathcal{F}_f[\omega](\mathcal{F}_f[\mathbf{a}] + \delta\mathcal{F}_f[\mathbf{a}]),
\tag{23}
$$

where $\alpha(r - \|\mathbf{a}\|)$ is some non-linear smooth function with a single minimum.

As the activity always falls back to the circular line attractor, the heading integration is linear along the circle. This implies that any small movement of the animal or the perception of a sensory clue is projected onto the circle then linearly integrated. Notice that in our framework, the linearity in the circular line is not a computational assumption, but rather it emerges from the principle of symmetry.

In more intuitive terms, the neurons have a saturating nonlinearity where they reduce their gain as they fire more, implying that any deviation from the circular line attractor will return back to it. As the activity of the network goes beyond that of the line attractor, the gain reduces and the activity decreases, and when the activity of the network is smaller than that of the line attractor the gain is larger and the activity increases.

II Ambiguities in multiple harmonic decoding with drift

We consider the case where multiple harmonics are used, and their phases have drifted. For example, we consider the harmonics f_1 and f_2. The activity is given by Eq. 5

$$
\mathbf{a}_n(\theta) = \cos\left(\frac{2\pi f_1 n}{N} + f_1\theta\right) + \cos\left(\frac{2\pi f_2 n}{N} + f_2\theta\right).
\tag{24}
$$

If the phase of the second harmonic drifts by $\delta\theta$,

$$
\mathbf{a}_n^{\delta\theta}(\theta) = \cos\left(\frac{2\pi f_1 n}{N} + f_1\theta\right) + \cos\left(\frac{2\pi f_2 n}{N} + f_2\theta + \delta\theta\right)
\tag{25}
$$

We can calculate the alignment between the activity with drift and the activity without as a dot product of the activity vectors,

$$
\frac{\langle \mathbf{a}(\theta), \mathbf{a}^{\delta\theta}(\theta)\rangle}{\|\mathbf{a}(\theta)\|\|\mathbf{a}^{\delta\theta}(\theta)\|} = \frac{1}{\|\mathbf{a}(\theta)\|^2}\sum_n \mathbf{a}_n(\theta)\mathbf{a}_n^{\delta\theta}(\theta) = 1 + \cos(\delta\theta).
\tag{26}
$$

However, there are other angles where the alignment is better. For example, we can consider an estimate angle, $\hat{\theta}$, with its corresponding activity, $\mathbf{a}(\hat{\theta})$, which gives

$$
\frac{\langle \mathbf{a}(\hat{\theta}), \mathbf{a}^{\delta\theta}(\theta)\rangle}{\|\mathbf{a}(\hat{\theta})\|\|\mathbf{a}^{\delta\theta}(\theta)\|} = \frac{1}{\|\mathbf{a}(\theta)\|^2}\sum_n \mathbf{a}_n(\hat{\theta})\mathbf{a}_n^{\delta\theta}(\theta) = \cos(\theta - \hat{\theta}) + \cos(\theta - \hat{\theta} + \delta\theta).
\tag{27}
$$

For small $\delta\theta$, this is maximised when $\hat{\theta} = \theta + \delta\theta/2$. However, since θ is circular, if the drift is π then there are two possible positions given by $\hat{\theta} = \theta \pm \pi/2$.

This implies that an encoding using multiple harmonic does not necessarily offer a unique decoding in the presence of noise.

III Equivalent circuits and degeneracies

III.1 Equivalence under permutation

The activity of neurons given by Eq. 5 implies that the preferred angle of neuron n is given by

$$\varphi_n = 2\pi \frac{fn \mod N}{N} \tag{28}$$

where in our case $N = 8$. Table S.1 shows $nf \mod (N)$ evaluated for all neurons in the network using different harmonics. We notice that for $f = \{1, 3, 5, 7\}$ all the numbers from zero to seven appear, while for $f = \{2, 6\}$ we only get the even numbers, for $f = 4$ we get only zero and four, and for $f = 8$ there is only zero.

The explanation is based on number theory. If f and N have the greatest common divisor $\gcd(N, f) = d$, then $nf \mod N = 0$ for $n = N/d$. This implies that the preferred angle of neuron $n = 0$ is the same as that of $n = N/d$. When N, f are co-prime $d = 1$, n goes from 0 to $N - 1$ without repeating any value. However, when $d > 1$, the neuron $n = N/d$ has the same tuning as the neuron $n = 0$, the neuron $n = N/d + 1$ has the same tuning as the neuron $n = 1$ and so on. In other words, the angular tuning of the neurons has a period of $\gcd(N, f)$.

This divides the possible circuits into the following groups:

- $f = \{1, 3, 5, 7\}$ which contain $N = 8$ angular tunings with values $[0, \pi/4, \pi/2, 3\pi/4, \pi, 5\pi/4, 3\pi/2, 7\pi/4]$ because every odd number is coprime with 8 and thus the $\gcd(N, f) = 1$.

- $f = \{2, 6\}$ which cycle through 4 possible directions $[0, \pi/2, \pi, 3\pi/2]$ because $\frac{N}{\gcd(N,f)} = 4$

- $f = 4$ which can only represent 2 possible directions $[0, \pi]$.

- $f = 8$ which can only represent the direction 0

	$n = 0$	$n = 1$	$n = 2$	$n = 3$	$n = 4$	$n = 5$	$n = 6$	$n = 7$	$\gcd(8, f)$
$f = 1$	0	1	2	3	4	5	6	7	1
$f = 2$	0	2	4	6	0	2	4	6	2
$f = 3$	0	3	6	1	4	7	2	5	1
$f = 4$	0	4	0	4	0	4	0	4	4
$f = 5$	0	5	2	7	4	1	6	3	1
$f = 6$	0	6	4	2	0	6	4	2	2
$f = 7$	0	7	6	5	4	3	2	1	1
$f = 8$	0	0	0	0	0	0	0	0	8

Table S.1: Distribution of neural activity phases for different harmonics: We computed $fn \mod 8$ for $n = \{1, 2, 3, 4, 5, 6, 7\}$ and $f = \{1, 2, 3, 4, 5, 6, 7, 8\}$ and found that all possible phases appear for any odd number. This happens because the $\mod 8$ operation imposes an abelian group structure, namely $\mathbb{Z}/8$ and any coprime with 8 will be a generator of the whole group. If we use instead $f = 2$ or $f = 6$ we have that we can divide the $N = 8$ and f by 2 and we get the abelian group $\mathbb{Z}/4$ which has four elements. The same argument applies to $f = 4$, leaving only two elements, and for $f = 8$ we get a single element.

III.2 Degenerate circuits

Given the groupings presented in the previous subsection, we notice that not all of them allow the encoding of a full range of angles, $(0, 360]$. Notably, for $f = 8$ the neurons only encode one angle, and for $f = 4$ only two complementary angles are encoded, 0 and π. This means that we cannot represent a full circle, because we need two different dimensions to do so, but in both of these cases we can only encode one.

For $f = 2, 6$ we obtain two groups of neurons, and in each group there are two neurons that encode two opposing directions, thus it is possible to cover a full circle. However, the circuit is degenerate, as shown in Fig. 3. In this case there are no connections between even and odd neurons. Thus, we have

two groups of neurons that are disconnected, and each group encodes only one direction (either north-south or east-west). While the encoding could work in principle, the circuit is decoupled, meaning that there is nothing in this circuit that prevents the activity from having activities outside the circular topology: as the two circuits are disconnected, a given value of activity in one group does not restrict the activity in the other.

III.3 Circuits with different neuron counts

We evaluate the viability of circuits with other values of N. From findings in the the previous appendix, we note that choosing N to be a prime number implies that all frequencies will be coprime with N, and thus that all the neurons will have a different tuning.

For $N = 2$, the two angles are $0, \pi$, in which case the circuit can only encode one dimension and thus cannot encode a full circle, as was the case for $N = 8, f = 4$ in Appendix III.2.

For $N = 4$, if $f = 2$ the circuit can encode only the angles $0, \pi$ and we have the same case as for $N = 2$. But if $f = 1$ or $f = 3$, the neurons are tuned to the angles $0, \pi/2, \pi, 3\pi/2$ which can encode a circle. However, by looking at the connectivity matrix from Eq. 16, we find that neurons $1, 3$ are connected to one another, but not to $2, 4$, as was the case for $N = 8, f = 4$ in Appendix III.2. This implies that the circuit does not enforce a circular topology, and thus it does not work.

Notice that we could think of another structure where each neuron encodes a different direction. Intuitively, we would have a north-south neuron and an east-west neuron, as we would have in Cartesian coordinates. However, this would have the same problem as $N = 4$, where the two neurons would not interact and thus the topology would be wrong. Additionally, when the insect heads north, the north-south neuron would be very active, while when it heads south it would be very inactive. This means that the circuit as a whole would have a different firing rate depending on the direction, breaking the symmetry assumption.

IV Path counting

We counted the number of different paths between EPG neurons, accounting for the sign of the connections (whether the path passed through an inhibitory $\Delta 7$ neuron), and used the net path count as a proxy for connectivity strength. The results of this analysis are shown in Section 3, but we will detail the process here using the locust network from Pisokas et al. (2020) as an example, shown in Fig. S.1.

We consider the shortest excitatory and inhibitory pathways between EPG neurons, which have lengths of 2 and 3 respectively. There are no direct paths between EPG neurons in the locust circuit. In this case there are two paths of length 2 that implement self-excitatory connections for EPG_1:

- $EPG_1 \rightarrow PEG_1 \rightarrow EPG_1$

- $EPG_1 \rightarrow PEN_1 \rightarrow EPG_1$

And there is one connection of path length 2 that connects EPG_1 to each of its nearest neighbours:

- $EPG_1 \rightarrow PEN_1 \rightarrow EPG_2$

- $EPG_1 \rightarrow PEN_1 \rightarrow EPG_8$

For inhibitory connections there are four paths of length 3 that connect EPG_1 to the neuron on the opposite side of the ring, EPG_5. These are:

- $EPG_1 \rightarrow \Delta 7_5 \rightarrow PEN_5 \rightarrow EPG_5$

- $EPG_1 \rightarrow \Delta 7_5 \rightarrow PEG_5 \rightarrow EPG_5$

- $EPG_1 \rightarrow \Delta 7_4 \rightarrow PEN_4 \rightarrow EPG_5$

- $EPG_1 \rightarrow \Delta 7_6 \rightarrow PEN_6 \rightarrow EPG_5$

There are three connections of path length 3 connecting EPG_1 to EPG_4:

- $EPG_1 \rightarrow \Delta 7_4 \rightarrow PEN_4 \rightarrow EPG_4$

- $EPG_1 \to \Delta 7_4 \to PEG_4 \to EPG_4$

- $EPG_1 \to \Delta 7_5 \to PEN_5 \to EPG_4$

Finally, there is one path of length 3 connecting EPG_1 to the neuron perpendicular to it around the ring, EPG_3:

- $EPG_1 \to \Delta 7_4 \to PEN_4 \to EPG_3$

We then add these connections together to obtain the net path count profile for the network. Because the network is rotationally symmetric, the connections from EPG_1 are the same as the connections from EPG_2 but with the neurons indices incremented by 1. The generalised profile is shown in Table S.2.

$EPG_n \to$	$n-4$	$n-3$	$n-2$	$n-1$	n	$n+1$	$n+2$	$n+3$
Excitatory path count	0	0	0	1	2	1	0	0
Inhibitory path count	4	3	1	0	0	0	1	3
Net path count	-4	-3	-1	1	2	1	-1	-3

Table S.2: Net path count profile between EPG neurons in the locust circuit.

Supplementary Figure S.1: The full locust connectivity network from Pisokas et al. (2020) (left), and the connections with path lengths 2 and 3 from EPG_1 to all other EPG neurons in the network (right). Because the network is rotationally symmetric these path counts generalise to all EPG neurons as shown in Table S.2.

V   Data preprocessing

The following section details our data preprocessing to produce a central complex circuit for the fruit fly similar to that in Pisokas et al. (2020) using synaptic counts from the fruit fly connectome data set (Hulse et al., 2021). Full details are shown in our available code.

We first identified the 6 neuron types which corresponded to the neurons of interest in the central complex (Table S.3).

Neuron class	Number
PEN_a(PEN1)	20 neurons
PEN_b(PEN2)	22 neurons
PEG	18 neurons
EPG	46 neurons
EPGt	4 neurons
Delta7	42 neurons

Table S.3: Neuron types and their numbers in the fruit fly connectome data set (Hulse et al., 2021).

We grouped the two PEN and two EPG populations together for further analysis.

From the connectome data we created a connectivity matrix (Fig. S.2) containing the number of synapses between all pairs of neurons of the above mentioned types. This contained 129473 synapses between 152 neurons in total.

Next, neurons in the same glomerulus were grouped together. The EPG neurons were divided between 18 glomeruli, L1-L9 and R1-R9. The PEN neurons were also divided between 16 glomeruli, L2-L9 and R2-R9. The PEG neurons were divided into 18 glomeruli with only 1 neuron in each, L1-L9 and R1-R9. The Delta7 neurons had 10 unique sub-types (Table S.4) which were grouped into 8 glomeruli based on their left glomerulus index – i.e. L4R5_R and L4R6_R were grouped in L4.

Delta7 neuron sub-types	Glomerulus group
Delta7(PB15)_L1L9R8_R	Delta7 L1
Delta7(PB15)_L2R7_R	Delta7 L2
Delta7(PB15)_L3R6_R	Delta7 L3
Delta7(PB15)_L4R5_R	Delta7 L4
Delta7(PB15)_L4R6_R	Delta7 L4
Delta7(PB15)_L5R4_L	Delta7 L5
Delta7(PB15)_L6R3_L	Delta7 L6
Delta7(PB15)_L6R4_L	Delta7 L6
Delta7(PB15)_L7R2_L	Delta7 L7
Delta7(PB15)_L7R3_L	Delta7 L7
Delta7(PB15)_L8R1R9_L	Delta7 L8

Table S.4: List of the Delta7 neuron sub-types in the fruit fly connectome data set (Hulse et al., 2021). These differ in the glomeruli their pre- and post-synaptic terminals innervate. We are referring to those altogether as Delta7 neurons in the present account.

After this grouping we had a connectivity matrix of 60 neurons in total (Fig. S.3).

For the EPG, PEN, and PEG neurons we then grouped glomeruli mirrored in the two hemispheres together – i.e. L1 and R1 were grouped into glomerulus 1. This resulted in a connectivity matrix of 34 neurons (Fig. S.4).

Finally, as in (Pisokas et al., 2020) we grouped the PEG9 and PEG1 neurons and EPG9 and EPG1 neurons together. The former because they both output to the same ellipsoid body segment, and the latter because they both receive common input. This resulted in a connectivity matrix with 32 neurons (Fig. S.5) which we used for the analysis in Fig. 4 as this network had the 8-fold rotational symmetry compatible with our theoretical model.

VI Fitting weights

Having calculated the paths or synaptic strengths between EPG neurons in the network, we next computed the average connectivity profile for the network – how each EPG neuron connected to its neighbours a certain distance around the ring. We then compared this connectivity profile to the closest fitting sinusoid to quantify to what degree our prediction of sinusoidal weights was consistent with biological data.

We use the vector

$$\hat{\omega}_d = \beta \cos\left(\frac{2\pi d}{N}\right) + \gamma, \tag{29}$$

where $d = ((m-n)+4 \mod 8) - 4 \in [-4..3]$ is the signed circular distance from neuron m to neuron n.

In the networks from Pisokas et al. (2020) the weights are rotationally symmetric, so we minimise the mean squared error between the sinusoidal profile and the biological connectivity profile,

$$\beta^*, \gamma^* = \arg\min_{\beta,\gamma} \frac{1}{N} \sum_{d=-N/2}^{N/2-1} \left(\hat{\omega}_d(\beta,\gamma) - \omega_d\right)^2, \tag{30}$$

by using least squares. The network derived from the synaptic count data in Hulse et al. (2021) is not rotationally symmetric so each value in the average connectivity profile, ω_d, has a corresponding standard deviation, σ_d. In this case we minimise the precision-weighted mean squared error, which emphasises fitting connectivity profile values that are more consistently seen in the network:

$$\beta^*, \gamma^* = \arg\min_{\beta,\gamma} \frac{1}{N} \sum_{d=-N/2}^{N/2-1} \left(\frac{\hat{\omega}_d(\beta,\gamma) - \omega_d}{\sigma_d}\right)^2. \tag{31}$$

The result of fitting sinusoidal profiles to the data is shown in Section 3. Since the fit for the fruit fly is not as clear as for the locust, we also compared the quality of the fit with harmonics $f = 2$ and a combination of $f = 1$ and $f = 2$, which gives us worse results as shown in Fig. S.6 and Table S.5.

For completeness we also fit the observed weights in the fruit fly by a Gaussian curve. Since Gaussians (and most unimodal curves) also have parameter specifying a width, this requires an extra parameter to fit, which yields

$$\beta_g e^{-\frac{n^2}{\sigma_g}} + \gamma \tag{32}$$

where $\beta_g, \sigma_g, \gamma_g$ are parameters to fit. We find a good agreement with the weights in Fig. S.6, and a lower root mean square error (RMSE) than with any combination of harmonics. However, we note that our sinusoidal model has two parameters instead of three, so to make a fair comparison we use the Akaike Information Criterion (AIC) (Burnham and Anderson, 2004), which is given by

$$\text{AIC} = 2p - 2\ln(L) = 2p - 16\text{MSE}, \tag{33}$$

where p is the number of parameters and L is the log-likelihood, which in this case is the sum of squared errors, or 8MSE with $N = 8$. Note that it is common to add a correction to the AIC when the number of samples is small (Burnham and Anderson, 2004), which is given by

$$\text{AICc} = \text{AIC} + \frac{2p^2 + 2p}{N - p - 1}, \tag{34}$$

where N is the number of samples (equivalent to the number of neurons). We find that the lowest AIC and AICc (corresponding to the best model) corresponds to the harmonic $f = 1$ (Table S.5).

Supplementary Figure S.6: The weight profile with sinusoidal weights of frequency 1 provides the best fit to the experimental data when also accounting for the number of model parameters, compared to the second frequency, the combination of the first two frequencies, or a Gaussian profile. Note that the -4 and 4 neuron indices are the same and just duplicated for visualisation purposes.

Curve	RMSE	AIC	AICc
$f = 1$	0.3213	5.65	8.15
$f = 1, 2$	0.4409	7.11	9.61
$f = 2$	0.8478	15.50	18
Gaussian	0.1941	6.60	12.60

Table S.5: Quality of fit for different possible weight structures. The Root Mean Square Error is weighted by the variance attached to each connection (in units of standard deviations). The Akaike Information Criterion (AIC) and its sample-size correction (AICc) for the weight profiles in Fig. S.6. The best fit after correcting for model size is $f = 1$.

VII   Convergence of Oja's rule with multiple harmonics

Integrating Oja's learning rule updates (Eq. 19) over all angles in the position space gives us the following:

$$\Delta\omega = \mathbf{a} * \mathbf{a} - \|\mathbf{a}\|^2 \omega, \tag{35}$$

which we can transform into the Fourier domain:

$$\mathcal{F}_f[\Delta\omega] = \mathcal{F}_f[\mathbf{a}]^2 - \|\mathbf{a}\|^2 \mathcal{F}_f[\omega]. \tag{36}$$

The steady state solution when the weight update is 0 is:

$$\mathcal{F}_f[\omega] = \frac{\mathcal{F}_f[\mathbf{a}]^2}{\|\mathbf{a}\|^2}. \tag{37}$$

By Parseval's theorem, $\|\mathbf{a}\|^2 = \sum_f \|\mathcal{F}_f[\mathbf{a}]\|^2$ so the Fourier spectrum of the steady state weights is just the normalised Fourier spectrum of the input:

$$\mathcal{F}_f[\omega] = \frac{\mathcal{F}_f[\mathbf{a}]^2}{\sum_f \|\mathcal{F}_f[\mathbf{a}]\|^2}. \tag{38}$$

From this we can see that the stable L_1 norm of $\mathcal{F}[\omega]$ is 1,

$$\sum_f |\mathcal{F}_f[\omega]| = \frac{1}{\sum_f \|\mathcal{F}_f[\mathbf{a}]\|^2} \sum_f |\mathcal{F}_f[\mathbf{a}]^2| = 1. \tag{39}$$

If we combine this result with Eq. 10, we find that in the case of a single encoding frequency, $\mathcal{F}_{f^*}[\mathbf{a}] > 0$, Oja's rule will result in a single stable harmonic with $\mathcal{F}_{f^*}[\omega] = 1$ because $\sum_f \mathcal{F}_f[\mathbf{a}]^2 = \mathcal{F}_{f^*}[\mathbf{a}]^2$.

If Oja's rule has a normalising factor added to account for the number of encoding harmonics used, $|\mathbf{F}|$,

$$\Delta\omega = \mathbf{a} * \mathbf{a} - \frac{1}{|\mathbf{F}|}\|\mathbf{a}\|^2\omega, \tag{40}$$

then the steady state solution for the weights becomes

$$\mathcal{F}_f[\omega] = |\mathbf{F}|\frac{\mathcal{F}_f[\mathbf{a}]^2}{\sum_f \mathcal{F}_f[\mathbf{a}]^2}, \tag{41}$$

where the L_1 norm of $\omega = |\mathbf{F}|$. In this case multiple harmonics could develop stable values of $\mathcal{F}_f[\omega] = 1$, but only if the activity magnitudes for these harmonics are identical. If any perturbation affects the activities, the harmonic which happens to have the larger activity will begin to dominate the other by the dynamics of Eq. 40, until only one remains.

Therefore, the only case where Oja's rule results in a stable solution robust to perturbations is when only one harmonic is used.

Supplementary Figure S.2: The connectivity matrix for the fruit fly containing all 152 neurons. On the horizontal axis are the names of the pre-synaptic neurons while on the vertical axis the names of the post-synaptic neurons. Neurons within each cell type are ordered by the glomerulus they innervate and arbitrarily within glomerulus.

Supplementary Figure S.3: The connectivity matrix for the fruit fly neurons grouped by innervated glomerulus so containing 60 groups. On the horizontal axis are the names of the pre-synaptic neurons while on the vertical axis the names of the post-synaptic neurons. Neuron groups are ordered by the glomerulus they innervate.

Supplementary Figure S.4: The connectivity matrix for the fruit fly neurons grouped by glomerulus and aggregated from both hemispheres, so containing 34 groups. On the horizontal axis are the names of the pre-synaptic neuron groups while on the vertical axis are the names of the post-synaptic neuron groups. Neuron groups are ordered by the glomerulus they innervate.

Supplementary Figure S.5: The connectivity matrix for the fruit fly neurons grouped by glomerulus and aggregated from both hemispheres, with PEG9 & PEG1 neurons and EPG9 & EGP1 neurons grouped, so containing 32 groups in total. On the horizontal axis are the names of the pre-synaptic neuron groups while on the vertical axis the names of the post-synaptic neuron groups. Neuron groups are ordered by the glomerulus they innervate.