Detection and localization of conspecifics in ghost knifefish are influenced by the relationship between the spatial organization of receptors and signals.

Keshav L Ramachandra[1], Oak E Milam[1], Federico Pedraja[3], Jenna Cornett[1] & Gary Marsat[1,2]

[1]Department of Biology & [2]Department of Neuroscience, West Virginia University, Morgantown, USA

[3]Department of Neuroscience, Zuckerman Mind Brain Behavior Institute, Columbia University, New York, USA

Corresponding author:

Gary Marsat

Gary.marsat@mail.wvu.edu

53 Campus Dr,

WVU Biology Dept,

Morgantown, WV, 26506

Acknowledgments: The authors would like to thank Dr. Alexandra Schmidt for assistance with fluorescence microscopy. Note that a previous version of this paper was included in the PhD thesis of Ramachandra (2023) and Milam (2023)

Funding: This research was supported by the NSF's CAREER grant IOS-1942960 to GM and made use of the Super Computing System funded by NFS grant MRI-1726534 and WVU.

ABSTRACT

The detection and localization of signals rely on arrays of receptors, and their spatial organization plays a key role in determining the accuracy of the system. Weakly electric ghost knifefish rely on a distributed array of electroreceptors to detect spatially diffuse electric signals from conspecifics. While we know that spatial resolution for small objects, such as prey, is enhanced near the head due to a high receptor density, it is not clear how receptor organization influences the processing of global and diffuse signals from conspecifics. Using spatially realistic modeling, we quantified how receptor density influences detection and localization accuracy for conspecific signals across varying distances.

Our main result demonstrates that receptor density markedly enhances detection accuracy in frontal regions at intermediate distances (35-50 cm) yet surprisingly contributes minimally to improving localization accuracy. This highlights a fundamental principle: receptor convergence primarily benefits signal detection when dealing with spatially diffuse stimuli, even though higher receptor density can enhance localization accuracy for spatially delineated signals. Our findings extend beyond the electrosensory modality, drawing parallels with other sensory systems, and offer broader insights into spatial processing principles.

INTRODUCTION

Accurate detection and localization of sensory signals is fundamental to animal behavior,

influencing predator avoidance, mating decisions, and resource acquisition. Signal detection and

localization typically rely on an array of sensory receptors; their sensitivity, number, and spatial

organization play a key role in setting the accuracy of the system. Therefore, understanding how

receptor arrays are spatially structured to optimize these sensory tasks remains a central question

in sensory neuroscience. For example, visual resolution is enhanced by the high receptor density

in the retina's fovea, sound localization is largely enabled by the binaural configuration of the

auditory system, and moths can detect the presence of just a few pheromone molecules due to the

number and convergence of olfactory receptors (Ashida and Carr, 2011; Provis et al., 2013;

Rospars et al., 2014). While the spatial structure and size of the receptor array influence the

system's sensitivity, it is not always clear how the configuration of the receptors relates to

detection accuracy versus localization. This is particularly true for diffuse signals that affect most

of the sensory array, such as a luminosity gradient in the environment, a distant heat source, or

the Earth's magnetic field.

The electrosensory system in fish is a remarkable example of sensitivity. In ghost

knifefish, in particular, survival depends on navigating, detecting prey, and communicating

through this active sense. They generate a constant weak electric field with their electric organ

(EO), and any distortions of this field by preys or objects in their environment are picked up by

an array of receptors covering the skin of the fish (Nelson et al., 1997; Pedraja et al., 2014).

Distortions from an object or prey will impact only a spatially defined subset of receptors on the

corresponding portion of skin onto which the electric image (EI) of the object is projected. By

activating the corresponding portions of the topographic maps higher in the sensory system,

spatial information is encoded in a sort of labeled-line code reminiscent of the way the visual or

somatosensory system is organized. Similar to these modalities (i.e., fovea of the retina), regions

of higher receptor density towards the head and snout of the fish provide a higher spatial

resolution particularly useful in the last stage of prey capture, as the target approaches the fish's

mouth (MacIver et al., 2001; Nelson and Maciver, 1999). They also detect and communicate

with one another through this electric sense (Allen & Marsat, 2018; Knudsen, 1975; Petzold et

al., 2016). The ongoing electric organ discharge (EOD) is a spatially diffuse signal that can reach

globally all the receptors of the other fish's body. Localization of such signals would thus have to

rely on differences in the signal strength at different input locations, similar to the way the

auditory system compares binaural inputs to localize sound sources (see Milam et al., 2019, for

review). While it is clear that the high rostral density of receptors can enhance the spatial

accuracy for objects, it is not clear how it influences the processing of diffuse and global signals

from another fish's EOD. More specifically, we are interested in determining how the spatial

organization and density of receptors interact with the spatial structure of EOD signals to

influence the detection and localization of conspecific signals.

The EOD generated by the long EO located in the caudal 2/3 of the fish can be

approximated as a dipole whose polarity switches during each EOD cycle (Rasnow et al., 1993).

The resulting signal is a quasi-sinusoidal output with frequencies between 500 Hz and 1000 Hz

(in *A. leptorhynchus*, the focal species in this paper; (Zupanc and Maler, 1993). Although weak,

this signal will travel several tens of cm and will permit the long-range detection of the

conspecific (Pedraja et al., 2016). Behavior studies demonstrated that frequent interactions occur

at distances of 30 cm or less, but there is evidence from field studies that these fish might be able

to detect and navigate toward one another at distances in the 1-meter range (this upper limit has

not been quantified systematically; (Henninger et al., 2018; Stamper et al., 2012; Stamper et al.,

2013; Zupanc et al., 2006). These distant signals will reach the receptors with low intensity as

the strength of electric signals decreases exponentially with distance. The signal from a distant

fish will combine with the signal of the fish's own EOD, resulting in a combined electric field

with sinusoidal amplitude modulations designated as the beat. If the distant fish's signal reaches

the focal fish with an amplitude $1/10^{th}$ the strength of the self-generated EOD, this beat

modulation will have an amplitude of $1/10^{th}$ the undisturbed EOD. These weak beat contrasts are

the signals that must be encoded to detect a conspecific, and differences in contrast at receptors'

locations across the fish's body constitute the localization cues. The mathematical framework to

estimate the strength and structure of the electric field during social interactions has been

detailed in previous studies (Caputi and Budelli, 2006; Castello et al., 2000; Gómez-Sena et al.,

2014; Kelly et al., 2008). It can be used to quantify the strength of the signal as it reaches each

receptor to obtain a complete characterization of the sensory input structure due to an

approaching conspecific.

Ghost knifefish possess several types of electroreceptors; we focus here on p-unit

tuberous receptors, which constitute the vast majority of electroreceptors, are tuned specifically

to encode conspecific signals, and are responsible for encoding the amplitude of these beat

contrasts (Bennett et al., 1989). Previous estimates of p-units receptor density range from 9-15

per mm^2 on the head region to 0.6-3.4 over the trunk area (Carr et al., 1982). A thorough

quantification of receptor density as a function of dorso-ventral/rostro-caudal location in *A.*

leptorhynchus is not yet available. Receptor sensitivity and response properties have been

extensively studied, and several neural models of p-units are available (Benda et al., 2005;

Chacron et al., 2005; Goense and Ratnam, 2003; Gussin et al., 2007; Nelson et al., 1997; Ratnam

and Nelson, 2000). This large population of several thousand receptors converges to the primary

sensory area in the hindbrain, the electrosensory lateral line lobe, and the information is then

transmitted down the sensory pathway (Lannoo et al., 1989; Maler et al., 1991). To estimate the

information carried by the population of receptors about realistic signals, two key elements must

be considered. First, we must consider the response properties of the receptors, including their

sensitivity and noise levels, as well as their heterogeneity across the population. Second, we must

consider the structure of the stimuli and how signals from different locations will result in input

strengths that vary across receptor positions.

In this paper, we aim to clarify how spatially realistic signals from conspecifics are

encoded by the population of electroreceptors. Our approach includes using a model of the fish's

electric field to quantify the EI strength at each receptor location. This input drives a model of

the p-unit population consisting of heterogeneous leaky-integrate-and-fire units calibrated based

on the extensively documented properties of this population. We then use a decoding analysis to

estimate the information that can be extracted from the receptor population and provide a

conservative estimate of the expected detection and localization accuracy. We specifically

hypothesize that the high density of receptors rostrally will enhance detection and localization

accuracy, particularly in the frontal quadrant. We tested this hypothesis by altering the structure

and density of the receptor population and confirming that detection accuracy depends on

receptor density. Surprisingly, we demonstrate that localization is relatively less influenced by

receptor density, and that high rostral density does not enhance localization accuracy for frontal

azimuth. Our results reveal the intricate relationship between the spatial structure of signals and

the spatial organization of sensory receptors, highlighting broader sensory processing strategies

relevant across modalities and taxa.

METHODS

Quantification of electroreceptor distribution

Weakly electric brown ghost knifefish, *Apteronotus leptorhynchus*, were obtained from a

tropical fish supplier (Segrest Farms, FL, USA). Fish care and use were approved by West

Virginia University IACUC.

Fish were euthanized, then fixed in a 50mL aliquot containing a 40mL solution of 4%

paraformaldehyde and preserved for up to 7 days. After the tissues were completely fixed, 5mg

of eosin Y was added to the aliquot containing the preserved fish. Stained fish were analyzed

under a fluorescent microscope with a light wavelength of 530nm. A stereotaxic system was

used to move the fish and place a 1 mm² sampling grid at different locations along the fish's

body. Tuberous receptors inside the grid were visually identified and counted. We collected 581

samples from 18 fish measuring, on average, 14 cm in length.

A coarse 3D mesh model of the fish was created using Maya 2019 (Autodesk, Inc.) based

on average measurements of our fish and images of the rostral, dorsal, and lateral profiles. The

quadrangle mesh model has 218 planar faces. For each face, the corresponding measured

receptor densities were averaged. Average receptor densities for each face were mapped along a

rostro-caudal and dorsal-ventral plane. A 3-dimensional 5th-degree polynomial was fitted to

obtain a smooth, interpolated estimate of receptor density as a function of body location. Using a

mesh model with triangular faces (the same used for EI calculation; see below), we randomly

generated receptor locations for each face according to our density function.

EI model

The electric image model used in this study was based on the established methods developed

by Caputi and Budelli (Caputi and Budelli, 1995; Caputi and Budelli, 2006; Caputi et al., 1998)

and implemented using software developed by Rother (Rother et al., 2003). More details on the

model can be found in the following publications, and a brief description is provided here. The

EI model requires the creation of a reconstruction of the geometry and electrical properties of the

fish bodies and their placement in the surrounding water. This information is used to calculate

the transcutaneous voltage at specific nodes along the skin of the fish. The model makes the

following assumptions:

1. All the media are ohmic. Therefore, $J(x) = \sigma(x)E(x), \sigma(x) > 0$ (1)

Where J(x) is the current density at point x and E(x) is the electric field at the same point.

2. There are no capacitive effects, so at no point in space is there an accumulation of charge.

$\frac{\delta p(x)}{\delta(t)} = 0$ (2)

3. The model is an electrostatic approximation (Bacher, 1983)

4. The fish and other objects that make up the environment are immersed in an infinite

water medium. Each object in the environment is covered by a thin resistive layer (the

skin in the case of the fish), which can be homogeneous or heterogeneous.

The model is based on the charge density equation, which, under the above assumptions, implies

that the charge generated by the sources f(x) is equal to the charge diffusion:

$\frac{\delta p(x)}{\delta(t)} = f(x) - \nabla.J(x)$ (3)

Combining equations 1 and 2, we get

$\nabla.J(x) = f(x) \Rightarrow \sigma\nabla.E(x) = f(x)$ (4)

The electric field E(x) can be expressed as $E(x) = -\nabla\varphi$ therefore:

$\sigma\nabla^2\varphi(x) = -f(x)$ (5)

Equation (5) is a partial differential equation known as the Poisson equation, which can be

solved for every point in space, in this case, the fish boundaries, using the boundary element

method (BEM) as proposed by Assad (Assad and Bower, 1997). The method determines the

boundary conditions by solving a linear system of M•N equations for M poles and N nodes, with

the unknown variables being the transepithelial current density and voltage at each node (Pedraja

et al., 2014). The shape of the 3D fish mesh model consists of 49 ellipses composed of 17 nodes

each (i.e., 835 nodes), defining 1,666 triangular faces between the nodes (Rother et al., 2003).

The size of the fish was kept constant at 14 cm in length in this paper, the water conductivity was

set to 300 μS, and the skin and internal conductivity of the fish were 100 and 10,000 μS,

respectively. The two poles for each fish were positioned 9.3 and 10.5 cm from the rostral tip of

our 14 cm fish. We use the middle of this dipole (i.e., the center of our "electric organ") to define

the position from which the signal originates.

Calculations of signal strength at receptor locations

We calculate the transdermal voltage when only the focal fish is present (*Vf*) or when

both focal and sender fish are present (*Vfs*), in which case the peak voltage is determined at the

top of the beat cycle (EODs in phase). The strength of the EI caused by the sender fish at each

node *i* on the surface of the focal fish was defined as a contrast *c*:

$$c = \frac{Vfs_i - Vf_i}{Vf} \qquad (6)$$

The contrast value for receptor location within each triangular face was interpolated
from the values at the nodes that define the face using a barycentric coordinates system.
Considering a triangle with values N at the nodes (vertices) and coordinates X, Y, Z. A receptor
inside the triangle will have a contrast value R according to the weighted value of the nodes. The
weights W can be found by solving:

$$X_R = W1 \cdot X_{N1} + W2 \cdot X_{N2} + W3 \cdot X_{N3} \qquad (7)$$

$$Y_R = W1 \cdot Y_{N1} + W2 \cdot Y_{N2} + W3 \cdot Y_{N3} \qquad (8)$$

$$Z_R = W1 \cdot Z_{N1} + W2 \cdot Z_{N2} + W3 \cdot Z_{N3} \qquad (9)$$

Contrast at the receptor location is calculated as:

$$R = W1 \cdot N1 + W2 \cdot N2 + W3 \cdot N3 \qquad (10)$$

Although the EI model was thoroughly calibrated based on experimental recordings on actual
fish (Pedraja et al., 2014; Pedraja et al., 2016), we performed transcutaneous recordings on three
pairs of fish and verified that the transdermal voltage contrast values that we calculated
correspond to the range of values that can be measured experimentally (data not shown).

Receptor Modelling
We used a leaky integrate-and-fire (LIF) framework to model the receptors. The model
includes noise σ and adaptation current with conductance g_α, reversal potential E_α, and is driven
by an input I. The membrane voltage is calculated as:

$$\tau_m \frac{dV}{dt} = E_m - V + R_m(I + \sigma - g_\alpha(V - E_\alpha)) \qquad (11)$$

The initial parameters of the model were based on existing models (Benda et al., 2005;
Carlson and Kawasaki, 2006; Chacron et al., 2001; Nelson et al., 1997). Particularly, the noise
was the product of a strength variable A_σ and a random process (specifically, two Ornstein–
Uhlenbeck processes (refer to Chacron et al., 2001, for details). Adaptation current α was
adjusted to match the time course of adaptation described experimentally (Benda et al., 2005).
Conductance g_α is augmented by Δ_α after each spike and decays with time constant τ_α. When the
membrane voltage reaches the threshold V_T it is reset to V_R and kept constant during a refractory

period t_R. The input I to these p-unit model neurons replicates the input they would receive from

receptor cells during social interactions. A sinusoidal EOD carrier signal with amplitude A_{EOD}

was created with a frequency of 1000 Hz (the upper range of the naturally occurring EOD

frequencies in this species was used for convenience) and modulated with a sinusoidal amplitude

modulation (the "beat") of 30 Hz (other AM envelopes are used to validate our model, see

Supplementary Material). This AM envelope signal was adjusted to a specific contrast as

specified in the Results. A contrast of 0% indicates that the baseline EOD is unmodulated,

whereas a beat contrast of 100% causes the EOD amplitude to be zero during the trough and

twice the baseline EOD amplitude at the peak of the beat. To emulate the current direction and

sensitivity as the signal passes through the receptor cells before it reaches the p-unit neurons, the

modulated EOD is halfwave rectified after a baseline bias β was subtracted.

Parameters were adjusted to create a prototypical neuron with response properties

matched to published data (Bastian, 1981; Benda et al., 2005; Chacron et al., 2005; Grewe et al.,

2017; Gussin et al., 2007b; Nelson et al., 1997; Ratnam and Nelson, 2000). We used a wide

range of response parameters to validate our model, including firing rate, coefficient of variation,

response sensitivity to random amplitude modulations, response sensitivity and time course to

steps, and responses to beat stimuli (see Supplementary Figure S1). This prototypical neuron,

with response properties matched to the average experimental values, served as our original seed;

the set of parameter values is given in Supplementary Information Table S1.

We then used this original seed to create a heterogeneous population that replicates the

range of response properties observed experimentally through an iterative process of diversifying

the population and constraining the response properties. A heterogeneous array of parameter sets

was created (8,000 sets) from the original seed values by randomly varying slightly several

parameters: t_R, R_m, τ_m, V_T, A_σ, τ_α, Δ_α, and β. From this array, 12 seeds were selected by choosing

sets of parameters that, again, best replicate the average response properties. These sets were

further diversified randomly, and from these new arrays, 26 seeds were chosen by selecting

neurons that replicate the average coding properties but that span the range of spontaneous firing

rates measured experimentally (Chacron et al., 2001; Gussin et al., 2007; Ratnam and Nelson,

2000). From these 26 seeds, the parameter sets were further diversified, and we retained 9,200

sets of parameters by rejecting sets for which the response properties did not fit in the range of

response properties determined experimentally. Therefore, our pool of neurons replicates the

average and range of response properties measured experimentally. From this pool, five

equivalent but different populations of 8,195 receptors were created by randomly assigning one

of the 9,200 neurons to each receptor location. All data shown in the results reflect averages

across these five populations.

Decoding analysis

264   Population responses to different stimuli were compared with our decoding analysis to

determine how accurately signals could be detected or discriminated, considering the differences

in response patterns for these stimuli. The framework used for our decoder has been described

and thoroughly validated in previous publications (Marsat et al., 2023; Allen and Marsat, 2018;

Allen and Marsat, 2019; Allen et al., 2021; Marsat and Maler, 2010). It was shown that this

analysis measure is directly correlated with the information content of the responses about the

stimuli. We describe the method briefly here. Importantly, the only difference with the

established measure described in Marsat et al. (2023) is that we do not use the detailed time

course of each neural response (i.e., the full spike trains) but use the peak-to-though firing rate to

quantify the response of the neuron. To calculate the peak-to-trough firing rate, the binarized

spike trains are smooth with a sliding square window of 16.67 ms (half a beat cycle) to obtain an

instantaneous firing rate. For each beat cycle, the difference between the maximum of the

instantaneous firing rate and the minimum gives us our measure of peak-to-through firing rate.

These peak-to-trough measures can be averaged over several cycles of the beat, or we can use

the values for single beat cycles as specified in the different Results section. When no beat

stimulus is provided, the analysis is unchanged, and the peak-to-trough is calculated over each

consecutive 33.34 ms segment of response (i.e., a 30 Hz period).

281   The analysis compares pairs of responses: responses to stimuli from two different

azimuths are compared in the angular resolution analysis; while in the detection analysis, the

response to the sender fish's signal is compared to the response when no second fish is present

(i.e., baseline firing due to the focal fish's own signal). For each individual neuron i (out of n

total neurons), the similarity between the probability distributions $P(x)$ of responses (the peak-to-

trough firing rate x) to the two stimuli (R and B) is calculated based on the area difference

$\Omega_{(P_R, P_B)}$ between the two distributions:

288             $$\Omega_{(P_{Ri}, P_{Bi})} = \sum_x |P_{Ri}(x) - P_{Bi}(x)| \qquad\qquad (12)$$

AD values are normalized to 1 across the n neurons to obtain a weight W:

$$W_i = H_0(\Omega_{(P_{Ri},P_{Bi})} - \frac{1}{n}\Sigma_n \Omega_{(P_{Rn},P_{Bn})} + 1)$$ (13)

where H_0 is the Heaviside step function. The peak-to-trough firing rates for each neuron are

multiplied with these weights before being used in our Euclidean distance calculations (see

below). As a consequence of this weighting, the neurons that respond very differently to the two

stimuli will contribute more to the Euclidean distance between the population responses, and the

neurons that respond similarly to the two stimuli will contribute little to the Euclidean distance.

Since the sum of the weight for a population is 1, the overall firing rate of the population is

unchanged by the weighting procedure.

The Euclidean distance D between pairs of weighted responses (R_a and R_b) is calculated

between responses to the same stimulus or between responses to the two different stimuli being

compared:

$$D = \sqrt{\Sigma_{nt}(R_a - R_b)^2}$$ (14)

These Euclidean distances are used to determine how well an ideal observer could discriminate

between responses to the two stimuli. The distribution of distances between responses to the

same stimulus, $D_{xx,}$ and the distribution of distances between responses to the two different

stimuli, D_{xy}, are used for an ROC analysis. In this analysis, a threshold distance T is varied. For

each threshold, the probability of non-discrimination (P_D) is calculated as the sum of $P(D_{xy}>T)$,

and the probability of false discrimination (P_F) is calculated as the sum of $P(D_{xx}>T)$. The error

rate E is taken as the minimum error across threshold according to:

$$E = \frac{1}{2}P_F + \frac{1}{2}(1 - P_D)$$ (15)

This error rate is used in the various parts of the result as specified therein, and we consider that

reliable detection or discrimination happens when the error rate is below 0.05.

314   **RESULTS**

Since ghost knifefish can detect and localize each other based on the electric signals they

continuously emit, both fish are thus senders and receivers at the same time. To simplify the

description of our results, we describe the fish for which we describe the electric image (EI) and

sensory responses as the focal fish. The "other" fish that needs to be detected and localized by

the focal fish is designated as the sender fish. A number of studies have characterized the EI that

one fish causes on another fish's body (Kelly et al., 2008; Pedraja et al., 2016). The results

presented in these papers are not always easily related to electrophysiological studies because

many experiments on the responses of sensory neurons in this system calibrate the signals as a

relative contrast in the measured voltage. For example, many studies present the response

properties to a conspecific signal of 5-10% contrast (Fotowat et al., 2013; Metzen et al., 2018).

Since our goal is to use the estimate of signal strength as an input to neuron models that match

their known response properties, we quantify the EI strength as a relative contrast in the

transdermal potential difference. If the signal from the sender is as strong as the focal fish's own

baseline signal at a given point on their body, the signal strength will be 100%, and the EOD will

vary from close to 0 mV (at the trough of the beat) to twice the baseline EOD strength (at the

peak of the beat cycle).

Expressing the signal as a contrast highlights the challenges that the fish encounters when

interacting with a conspecific due to the rapid decay of signal strength with distance. Figure 1

displays the signal strength during a common scenario: a sender fish approaching and then

moving away from the focal fish. When the fish are separated by only a few centimeters

(position 2), the EI has a strong gradient that goes from a strong signal (25% contrast) on

portions of the body closest to the sender to a very weak signal close to 0% contrast. For

convenience, we will refer to the region of the electric image with the strongest signal as the hot

spot. While this hotspot is well-defined when the sender is close by, the EI is much more diffuse

when the sender is further away, and there is a weaker gradient between the hotspot and the areas

with a weaker signal. For example, in Fig 1B, the difference between the hot spot near the head

(position 1) or tail (position 3) is less than 1% stronger than the portions with the weakest signal.

The positions 1 and 3 depicted here correspond to a distance (30 cm) at which we know fish can

detect each other and display active interactions (Henninger et al., 2018; Zupanc and Maler,

1993; Zupanc et al., 2006). The known extreme sensitivity of this system is thus highlighted

here, as detecting the sender 30 cm away involves detecting a 1% modulation, and localizing this

signal requires deciphering a gradient in the signal of less than 1% across the body surface.

The EI stimulates an array of receptors covering the fish's skin, and the spatial structure

of this sensory array will dictate how the spatial structure of the signal is captured. Receptor

density for different portions of the fish's body has been characterized in a closely related species
(Carr et al., 1982), but we needed a more detailed quantification of variations in receptor density
across the fish's body (Fig 2A). Our data confirm the general organization of receptor density: a
region of high density on the snout and head, of medium density on the dorso-rostral portion of
the trunk that decreases both ventrally and caudally (Fig 2B). Based on this spatially precise
empirical data, we incorporated a population of p-unit receptor locations on the 3D mesh model
used for EI calculations that varies smoothly in density as a function of rostro-caudal and dorso-
ventral position (Fig 2C). In the rest of this study, we will use an "average" fish that measures 14
cm long and includes ~8,195 receptor locations.

We calculated the stimulus intensity for each receptor location for the various iterations
of the EI calculation; the result for the three positions illustrated in Fig 1 is shown in Fig 3A
(note that for this figure, the blue-red color scale covers the contrast range for each position). We
wanted to quantify how the strength of the EI changes with the position of the sender relative to
the focal fish. To do so, we ran the model for 864 relative positions, where the two fish are at 12
distances that vary from nearly touching to 75 cm apart, and for 72 different azimuths around the
focal fish while always having the sender fish's heading towards the focal fish. To estimate the
maximal strength of the signal for each location, we used the strength of the signal at the center
of the hot spot on the focal fish. We plot this value as a color scale at the position of the middle
of the electric organ of the sender fish (Fig 3B). We can see that the signal strength decreases
sharply with distance, as expected. The portions of the figure with contrast above 20% (yellow-
white shades) represent positions where the fish are nearly touching (with the sender fish head-
on). The decrease in signal strength with distance follows the expected power law, such that
contrast drops to 10% by 10-15 cm and is only a few percent when the sender is 20-30 cm away
(Fig. 3C).

The EI model helps us quantify the cues that the sensory system can use to detect and
localize the source of these signals. To better understand the accuracy with which detection and
localization could occur, the strength of these signals must be compared with the noise that the
sensory system experiences. We therefore use the deterministic model of EI signal strength
described above as an input to a population of model neurons that includes realistic noise. We
based our receptor model on established parameters of leaky-integrate-and-fire, which include

adaptation, noise, and a refractory period, to replicate the response properties of p-units (Benda
et al., 2005; Chacron et al., 2005; Grewe et al., 2017; Gussin et al., 2007; Nelson et al., 1997).
Based on this prototype p-unit model, with properties matched to the average characteristics of
p-units, we diversified the model parameters to create a heterogeneous population matching the
range of properties observed experimentally (see Methods for details). For the model to provide
a biologically reasonable estimate of how accurately this population encodes spatial cues, it is
vital to calibrate the sensitivity, heterogeneity, and noisiness of the responses to reflect the
measured properties of the neurons. Our calibration involved matching the model responses to
published values for a range of stimulus types and analysis methods (see Methods and
Supplementary Figure S1). The population is then stimulated with conspecific signals (beat
stimuli) at intensity levels that are dictated by the EI image for various relative fish positions.
Figure 4 shows the response pattern of the population for two of the positions used in Figures 1
and 3. Response strength is quantified as the difference between the peak and trough of the
instantaneous firing rate during each stimulus cycle (here normalized relative to spontaneous
activity). We can observe differences in response strength due to the spatial contrast in the EI, as
well as differences across receptors resulting from heterogeneity that makes some neurons more
sensitive.

Firing rate modulation across one stimulus cycle replicates the experimentally measured
sensitivity (Fotowat et al., 2013; Henninger et al., 2018; Pedraja et al., 2014; Pedraja et al., 2016;
Zupanc et al., 2006) The strength of the electric image quickly decreases with distances and
reaches levels below 1% contrast at ranges where the fish still detect and interact with each other
(e.g., 30 cm). Our model replicates the fact that for these weak signals, the response modulation
is barely above variations in firing rate that naturally occur in the absence of a second fish (Fig
5). Figure 5C shows that, although the responses for nearby fish (14 cm and 22.5 cm in this
figure) are visibly different from the spontaneous response, signals from more distant fish (40
cm, 75 cm in this figure) cause much more subtle differences in response strength. This is true
when looking at the distribution of responses for cycles of the beat, for responses averaged
across time (grey or color portion of the distribution plots), or overall responses averaged across
time and neurons (white lines).

The sensitivity with which a conspecific signal would be detected will depend on the
coding and decoding mechanisms implemented by the nervous system. It is beyond the scope of
this article to explore all possible coding and decoding algorithms that could contribute to the
system's sensitivity, but as a first step towards understanding the system's sensitivity, we aim to
provide a lower bound on accuracy. To do so, we only consider peak-to-trough firing rate to
quantify response strength as it is the most salient aspect of the response that varies with stimulus
strength. The responses of individual receptors will be combined at higher levels of the nervous
system, and this can help average out noise in the responses. However, the way these responses
are combined would require various assumptions matched to the architecture of high brain areas,
which would lead to a complex modeling effort and speculation about the decoding procedure.
For this reason, and to remain within a "lower-bound" perspective, we map each population
response in Euclidean space, where each dimension represents the response strength of a neuron
(i.e., response strength is not averaged across neurons). Reliable detection would occur if the
strength of the population response is markedly different from the response when no signal is
present; in other words, when the stimulus-response is far from the baseline-response in this
Euclidean space representation. Our analysis, therefore, uses a weighted Euclidean distance
followed by a ROC analysis to quantify the reliability with which stimulus responses can be
differentiated from baseline. This analysis could be conducted on "instantaneous responses,"
considering the response of the population (peak-to-trough for each receptor) for a single cycle
of the stimulus, which would give us a response accuracy (i.e., probability of error) for each fish
position. Behavioral responses typically occur after attending the signal for a certain period of
time, and more accurate detection occurs after several seconds of the stimulus than after the first
cycle. We therefore integrate the response of each neuron across time (averaging the peak-to-
trough across several beat cycles) to estimate how detection accuracy changes as information is
accumulated over time. We consider that accurate detection occurs when less than 5% detection
error would occur and plot in Figure 6 the amount of time that accurate detection would require.
Our analysis shows that accurate detection could occur within a single cycle of the stimulus for
fish that are within 20 cm of the focal fish (Fig 6A, 6C). Detection accuracy decreases with
distance, and thus, it takes more time to detect the stimulus reliably. As a result, a fish 60-70 cm
away would require integrating the signal for several seconds to be able to tell reliably that
another fish is present.

Detection accuracy is undoubtedly influenced by the fact that thousands of receptors

contribute to transmitting this information. The distribution of these receptors is not uniform

across the fish's body. In particular, the rostral end of the fish (head region) has a density of

receptors 5-10 times higher than the caudal end (tail region). We hypothesize that this foveal

organization supports an enhanced sensitivity in the frontal quadrant relative to the fish.

Alternatively, the increased density in receptors plays an important role in localizing small

objects, like prey, with higher resolution but does not enhance the perception of conspecifics in

specific regions of space. This is a plausible alternative because conspecific signals cause a more

diffuse EI that stimulates a majority of the receptors over the receiver's body. To test our

hypothesis, we reduced the density of receptors to make it uniform over the entire body and

equal to the low density found at the caudal end of the fish (Supplementary Figure S2). Our

resulting population has 2,770 receptors compared to 8,195 for the full population. The

difference in detection sensitivity is displayed in Figure 6B and reveals the enhancement in

sensitivity afforded by the increased density in the rostral portion of the body. The difference is

negligible when the sender is very close because accuracy is high, and a decrease in the number

of receptors encoding the stimulus is not sufficient to affect performance. For very distant signals

(e.g., 75 cm), the lower rostral density causes a decrease in sensitivity that is fairly uniform

across azimuth (see also Supplementary Figure S3). This can be explained by the fact that distant

signals cause diffuse EI patterns that vary by less than 1% across the body (e.g., see Figure 1).

As a result, the head region is stimulated at a level nearly identical to the tail region, even if the

sender fish is located behind the focal fish. There is, however, a clear difference as a function of

azimuth for medium distances (35-50 cm; Figure 6B and Supplementary Figure S3). The higher

density of receptors on the head provides a clear advantage in detection accuracy in the frontal

quadrants (i.e., it requires less time until accurate detection occurs). We further verified the idea

that having a larger population of receptors allows the population to encode the presence of the

stimulus more reliably by decreasing the density of our uniform population of receptors by 2-, 4-,

and 8-fold (resulting in population sizes of 1,385, 693, and 347 receptors, respectively). Our

analysis confirms that a higher density of receptors allows more accurate detection for distances

where the signal is faint (Figure 6C).

We next inquire about the spatial information about the angular position of the sender

fish relative to the focal fish: its azimuth (in front=0°; behind= 180°). To do so, we compare the

responses to stimuli at various positions and quantify how reliably these responses could be

discriminated based on the same weighted Euclidean distance analysis used above. Error

probability will thus depend on two factors: the angular separation between the two stimuli and

the duration of the stimulus evaluated, whereas in our previous detection analysis, the latter was

the only factor considered. To display our results conveniently, we chose to keep the duration of

the stimulus integration at 1 second. This value is a compromise between expecting accurate

angular discrimination instantaneously (~1 cycle) and expecting the sender fish to remain in a

relatively fixed position for seconds in order for the angular position to be accurately estimated.

Using this 1s integration time, we determined the angle that needed to separate two stimuli to

lead to reliable discrimination (<5% error) and refer to this value as angular resolution (Figure

7). Our results show that angular resolution is accurate to a few degrees (<5°) when the sender is

within 10-20 cm and decreases sharply between 20 and 40 cm such that beyond 40 cm, azimuth

could not be reliably determined (angular resolution>180°). If we repeat the analysis using

different integration times (Fig 7B), as expected, the sharp decrease in angular resolutions moves

from being for positions 20 cm away when a single cycle of the beat is considered to being 40-50

cm away when 3.3s of the stimulus is being averaged. Our analysis suggests that for the most

distant positions tested (75 cm), the angular position could not be resolved, even when the

stimulus was integrated for several seconds. Together with the results of Figure 6, these findings

suggest that for more distant signals, only detection would occur, and the position of the sender

would not be accurately determined without relying on additional behavioral or neural

mechanisms (see Discussion).

The angular resolution does not appear to be equally good for a given distance as a

function of the azimuth of the sender (e.g., front vs. side vs. back). This can be seen in Figure

7A, where the color patterns around the focal fish are not perfectly circular. In particular, worse

angular resolution occurs at a shorter distance in the back quadrant compared to the front. We

suspected that the way we equalized distance across angles could cause a bias. The center of the

focal fish is taken as the average receptor position, and the center of the sender as the middle

between the two emitting poles that constitute the EOD source. Center-to-center distance and

azimuth were used to set our relative positions. In this arrangement, a fish at 130° (in the back

quadrant, see fish illustrated in Fig 7A) rotating 5° would not only change azimuth but also come

closer to the focal fish if we consider the two closest points on each fish's bodies. Note that this

is not an issue in our detection analysis since our accuracy measure does not depend on the

comparisons between two stimuli locations but only on the absolute location of a single stimulus.

We therefore repeated our angular resolution analysis by comparing angular resolutions where

the distance between the rostral tip of the sender and the closest point on the body of the receiver

is kept constant (the dots in Fig 8A show the positions of the rostral tip of the sender used in our

analysis). We found that angular resolution is better in the frontal quadrants than at the back (Fig

8A, 8C). Surprisingly, it is not best directly in front of the focal fish (0°) but rather on the side

(90°). Since we expected the high density of receptors on the head of the fish to help enhance

localization accuracy, we hypothesize that angular resolution is particularly good as the edge of

the hotspot caused by the sender sweeps across the region of high receptor density (which could

correspond to sender positions around ~90°). To test the contribution of higher receptor density

towards the head, we repeated the analysis using the "uniform" receptor population from the

previous section, which has an equally low receptor density across the whole body. This uniform

population of receptors did not perform much worse than our full population, and in particular,

there is no striking difference directly in front (0°) or the side (90°) of the fish where resolution

is best. Azimuth determination was not possible (angular resolution > 180°) when the fish were

two body lengths apart (28 cm), but at one body length, the higher density of receptors provided

a small advantage. Specifically, there are only a few spots at ~45° and ~125° where the higher

receptor density on the rostral portion of the body helps to enhance angular resolution (Fig 8B,

8C). We confirm that decreasing the population density further decreases angular resolution, and

this is particularly evident for more distant stimuli (one body length), where localization is still

possible but the angular resolution is not great (Fig. 8D).

Our results demonstrate that the angular resolution is relatively poor at the back and is

slightly better on the side than at the front. This effect cannot be attributed to the higher density

of receptors towards the head. Therefore, we questioned whether this effect could be due to the

geometry of the fish's body and how it interacts with the geometry of the electric field. We

hypothesize that a small change in angle on the side will cause a relatively bigger change in the

electric image than a similar angle difference at the back. A sender fish at 90° azimuth would

have its EI hotspot centered on the flat surface of the side of the focal fish, whereas for frontal

(0°) or caudal (180°) azimuth, the EI hotspots are centered on the pointy rostral and caudal ends

of the fish. We quantified how much difference in EI a sender at various azimuths would cause

on the focal fish and integrated this difference across the body surface. We found that it

correlates strongly with the differences in angular resolution that we have estimated for various

azimuths and distances (Figure 8E). Our analysis supports the conclusion that differences in

angular resolution as a function of azimuth are, in part, due to the geometry of the fish and their

electric fields.

538   **DISCUSSION**

By using a model of weakly electric fish EI and carefully normalizing how we calculate

the distance between the relevant points on the two fish, we presented a clear quantification of

the strength of the EI as a function of distance. Our results suggest that strong signals of more

than a few percent beat contrast occur only at distances below 15-20 cm. This finding is in

agreement with empirical data and consistent with the fact that when two fish actively interact

(e.g., chasing each other and courtship), they are typically in close proximity (Fotowat et al.,

2013; Zupanc and Maler, 1993). The relationship we show is quantitatively informative only in a

simplified case: a given fish size (and EOD strength) with a fixed heading angle (sender head-on

towards focal fish). The strength of the electric image as a function of distance will depend on

environmental factors (water conductivity), the individuals interacting (their size and EOD

strength), and moment-by-moment changes in the relative heading angle of each fish. All these

factors could be taken into account in a more extensive analysis of EI during social interactions,

but it is beyond the scope of our paper. It is also important to note that further improvements to

the model could provide additional details on the structure and dynamics of the EI, such as

replicating the bending of the fish's body or modeling the EO with more spatio-temporal details

rather than being a simple fixed dipole. We note that since the strength of the EI at a given

receptor location depends on distance and relative heading angles, the strength of the beat AM

(its envelope) cannot serve as a reliable indicator of distance or movement towards/away. Rather,

reliable spatial information must take into account the differences in EI strength over the body of

the receiver. This is obvious for localizing the azimuth of the target but can also help resolve the

distance since a fish close by will cause EIs with sharper contrasts across the body, while distant

fish will elicit more uniform EIs.

We used, for the first time in this system, a model of the full population of receptors,

replicating their heterogeneous response properties and their spatially realistic input patterns.

This allowed us to provide a conservative estimate of the detection range that this sensory input

could support. We found that, depending on how the information is extracted, detection would

still be possible at 75 cm. This range is comparable to behavioral interactions that report

instances where a fish detected and moved towards another, or simply interacted electrically,t

ranges above 60 cm (Henninger et al., 2018; Stamper et al., 2012; Yu et al., 2012). Our

sensitivity estimates might, in fact, come short of the sensitivity observed behaviorally, but this

might be because we intentionally provide a conservative estimate. Our estimate relies on a

decoding analysis that does not try to replicate sophisticated decoding procedures that the

nervous system could implement. Our analysis uses a "Euclidean distance" perspective to

quantify similarity in responses where the response of each neuron is kept as separate

dimensions. The nervous system will, in various steps of its pathway, combine neural responses

and thereby average out noise. An optimized procedure (e.g., using a principal component

approach) could be implemented, but it would need to be tailored to each stimulus/task being

considered. Any realistic attempt to leverage the convergence of receptor input performed by

higher sensory areas would be a major undertaking that could not be simply added to this study.

We also use a simple measure of response strength (peak-to-trough firing rate), and although it is

likely one of the key elements of the response, other aspects could be considered. Particularly,

synchrony among receptors has been shown to encode frequency modulations that occur during

communication (Benda et al., 2006; Metzen et al., 2020). Changes in synchrony may occur as the

stimulus strength changes and encode information that could enhance the detection and

localization accuracy. Further experiments are required to better understand the importance of

population synchrony in this context. Other neural mechanisms could be present and enhance the

system's sensitivity. We know, for example, that the presence of negative correlations in inter-

spike intervals suppresses noise at low frequencies and could enhance the coding of low-

frequency stimuli (lower than the frequency we use in this paper; (Chacron et al., 2001). For this

reason, we propose that our sensitivity estimates are conservative, serving as a starting point for

estimating the limits in detection and localization abilities.

Our analysis suggests that reliable detection or localization would require the integration

of signals over a certain period by higher brain areas. This is a realistic perspective, as behavioral

performance in various systems is more accurate for ongoing stimuli than for brief ones(Dizon

and Litovsky, 2004; Gai et al., 2013). For example, estimates of the direction of motion in a

"random dot display" integrate over time in the visual system of primates to reach a reliable

decision after seconds of attending the stimulus (Ditterich et al., 2003; Kim and Shadlen, 1999).

Spatial memory and navigation in sharks and turtles involve prolonged signal integration (Fagan

et al., 2013). Furthermore, long-range search behavior in Diptera also relies on dynamic

integration of spatial information (Kaushik et al., 2020), and directional coding in insect brains

underscores the broad applicability of spatial integration strategies (Beetz & el Jundi, 2023). For

weakly electric fish, it is not unrealistic to assume that the stimulus can be integrated over

several hundred ms to support accurate detection and localization. However, it is not clear that

this integration could occur over tens of seconds, particularly when relative movement requires

the location estimate to be updated frequently. As a first step, our analysis considered spatially

fixed signals; however, it will be imperative in future studies to take into account both the spatial

and temporal dynamics of the conspecific signals. According to this perspective, localization

accuracy, and thus behavioral decisions, depends on the spatial dynamic during the interaction.

Moreover, this spatial dynamic can be leveraged as a means to collect spatial information.

Various behavioral strategies can contribute to localizing a stimulus. For example, when

localization is difficult, movements toward the target increase signal strength and help confirm

the position of the second fish (Fagan et al., 2013; Kaushik et al., 2020). Lateralization, rather

than precise azimuth localization, can be used while a fish moves towards a target: if a stimulus

is perceived as coming from the left or right, corrective turns realign the target. The individual

would therefore move toward the target in a zig-zag pattern; this mechanism has been proposed

to contribute to behavior in various systems (Beetz and el Jundi, 2023; Gerhardt et al., 2023;

Pollack et al., 1984).

Detection could rely on the convergence of the whole population of receptors, thereby

efficiently averaging out noise. Furthermore, the high receptor density rostrally improves

detection for frontal azimuth because the EI hotspot is centered on this high receptor density

area, leading to a high convergence of strong responses. Localization, however, must rely on a

comparison of the EI strength across the body. When comparing the responses to stimuli from

different azimuths, our analysis focuses on the neural responses that differ between the stimuli,

weighing heavily the contribution of these neurons. This procedure to optimize the extraction of

spatial information is essential because the EI might differ only slightly between two stimuli, and

thus, the responses of most neurons will be identical across the stimuli locations. For

localization, it is thus the convergence of the responses of a subset of neurons that differ in

activation between the locations being compared that can support the accurate discrimination of

azimuth. Surprisingly, we found that the high density of receptors on the rostral portion of the

fish does not lead to a better discrimination of the frontal azimuth. This result could reflect the

fact that the receptors on the head will have a stronger difference in response at the edge of the

hot spot elicited by the sender moving across these receptor locations. We suggest that this

would occur as the leading or trailing edge of the hotspot sweeps across the high-density areas.

This could explain the modest increases in spatial resolution due to the increased rostral receptor

density that we observed around $60°$ and $120°$. This is in contrast with the contribution of the

high density of receptors during prey capture (i.e., small objects), where localization accuracy is

enhanced for the head and snout regions. The structure and convergence of receptors thus play

different roles in the detection and localization of objects and conspecifics: while high density

and convergence contribute markedly to the spatial coding of objects, they mostly contribute to

the detection accuracy of conspecific signals.

In other systems, regions of high receptor density are typically associated with high

spatial resolution. It is the case of the foveal region of the retina and of high receptor density

regions of the somatosensory system like the fingers or lips in humans (Catania and Catania,

2015; Dacey, 1994; Nakamura et al., 1998). In other systems faced with spatially diffuse signals,

like the auditory or olfactory systems, the extraction of spatial information typically relies on the

comparisons between a limited number of inputs (e.g., two ears) and high convergence of

receptors is more tightly involved with the accurate detection, rather than localization, of the

signals (Carr and MacLeod, 2010; Chapman, 1982; Okada and Toh, 2006; Schnupp and Carr,

2009). Our results on the electrosensory system suggest that this is a general principle guiding

the relationship between signal structure and the organization of sensory arrays. We argue that

for signals that are spatially diffuse, receptor density and convergence will benefit detection

abilities, and spatial information is extracted by comparing inputs at different locations without

relying on a higher number of inputs to enhance localization. For signals that are spatially

localized, a topographic mapping system is advantageous, and localization accuracy directly

depends on the spatial resolution of the input array. This perspective invites speculation about

the evolutionary pressures that shape sensory receptor distributions. Spatially diffuse signals may

drive sensory system evolution towards maximizing detection through receptor convergence,

whereas localized signals might select for heightened spatial resolution. Since both types of

signals are relevant in the electrosensory system of knifefish, it would be shaped by different

evolutionary pressures that do not automatically require the same optimal solution. Investigating

these evolutionary implications could further illuminate sensory processing adaptations across

diverse ecological niches. The electrosensory system provides a powerful way to compare these

systems and reveal organizing principles because it processes both localized and diffuse signals

for which receptor organization and convergence play distinct roles.

REFERENCES

Allen, K. M. and Marsat, G. (2018). Task-specific sensory coding strategies are matched to detection and discrimination performance. *J Exp Biol* **221**, jeb170563.

Allen, K. M. and Marsat, G. (2019). Neural Processing of Communication Signals: The Extent of Sender–Receiver Matching Varies across Species of Apteronotus. *eNeuro* **6**,.

Allen, K. M., Salles, A., Park, S., Elhilali, M. and Moss, C. F. (2021). Effect of background clutter on neural discrimination in the bat auditory midbrain. *J Neurophysiol* **126**, 1772–1782.

Ashida, G. and Carr, C. E. (2011). Sound localization: Jeffress and beyond. *Curr Opin Neurobiol* **21**, 745–751.

Assad, C. and Bower, J. M. (1997). Electric field maps and boundary element simulations of electrolocation in weakly electric fish. *Engineering and Applied Science* **PhD**,.

Bacher, M. (1983). A new method for the simulation of electric fields, generated by electric fish, and their distorsions by objects. *Biol Cybern* **47**, 51–58.

Beetz, M. J. and el Jundi, B. (2023). The influence of stimulus history on directional coding in the monarch butterfly brain. *J Comp Physiol A Neuroethol Sens Neural Behav Physiol*.

Benda, J., Longtin, A. and Maler, L. (2005). Spike-Frequency Adaptation Separates Transient Communication Signals from Background Oscillations. *Journal of Neuroscience* **25**, 2312–2321.

Benda, J., Longtin, A. and Maler, L. (2006). A synchronization-desynchronization code for natural communication signals. *Neuron* **52**, 347–358.

Bennett, M. V. L., Sandri, C. and Akert, K. (1989). Fine structure of the tuberous electroreceptor of the high-frequency electric fish,Sternarchus albifrons (gymnotiformes). *J Neurocytol* **18**, 265–283.

Caputi, A. and Budelli, R. (1995). The electric image in weakly electric fish: I. A data-based model of waveform generation in Gymnotus carapo. *J Comput Neurosci* **2**, 131–147.

Caputi, A. A. and Budelli, R. (2006). Peripheral electrosensory imaging by weakly electric fish.
Journal of Comparative Physiology A **192**, 587–600.

Caputi, A. A., Budelli, R., Grant, K. and Bell, C. C. (1998). The electric image in weakly
electric fish: physical images of resistive objects in Gnathonemus petersii. *J Exp Biol* **201**,
2115–28.

Carlson, B. A. and Kawasaki, M. (2006). Ambiguous Encoding of Stimuli by Primary Sensory
Afferents Causes a Lack of Independence in the Perception of Multiple Stimulus Attributes.
Journal of Neuroscience **26**, 9173–9183.

Carr, C. E. and MacLeod, K. M. (2010). Microseconds Matter. *PLoS Biol* **8**, e1000405.

Carr, C. E., Maler, L. and Sas, E. (1982). Peripheral organization and central projections of the
electrosensory nerves in gymnotiform fish. *J Comp Neurol* **211**, 139–153.

Castello, M. E., Aguilera, P. A., Trujillo-Cenoz, O. and Caputi, A. A. (2000).
Electroreception in Gymnotus carapo: pre-receptor processing and the distribution of
electroreceptor types. *Journal of Experimental Biology* **203**,.

Catania, K. C. and Catania, E. H. (2015). Comparative studies of somatosensory systems and
active sensing. *Sensorimotor Integration in the Whisker System* 7–28.

Chacron, M. J., Longtin, A. and Maler, L. (2001). Negative interspike interval correlations
increase the neuronal capacity for encoding time-dependent stimuli. *J Neurosci* **21**, 5328–
43.

Chacron, M. J., Maler, L. and Bastian, J. (2005). Electroreceptor neuron dynamics shape
information transmission. *Nat Neurosci* **8**, 673–678.

Chapman, R. F. (1982). Chemoreception: the significance of receptor numbers. *Adv Insect*
Physiol **16**, 247–356.

Dacey, D. M. (1994). Physiology, Morphology and Spatial Densities of Identified Ganglion Cell
Types in Primate Retina. *Ciba Found Symp* **184**, 12–34.

Ditterich, J., Mazurek, M. E. and Shadlen, M. N. (2003). Microstimulation of visual cortex
affects the speed of perceptual decisions. *Nature Neuroscience 2003 6:8* **6**, 891–898.

Dizon, R. M. and Litovsky, R. Y. (2004). Localization dominance in the median-sagittal plane:
Effect of stimulus duration. *J Acoust Soc Am* **115**, 3142–3155.

Fagan, W. F., Lewis, M. A., Auger-Méthé, M., Avgar, T., Benhamou, S., Breed, G., Ladage,
L., Schlägel, U. E., Tang, W. W., Papastamatiou, Y. P., et al. (2013). Spatial memory
and animal movement. *Ecol Lett* **16**, 1316–1329.

Fotowat, H., Harrison, R. R. and Krahe, R. (2013). Statistics of the Electrosensory Input in
the Freely Swimming Weakly Electric Fish Apteronotus leptorhynchus. *Journal of*
Neuroscience **33**, 13758–13772.

Gai, Y., Ruhland, J. L., Yin, T. C. T. and Tollin, D. J. (2013). Behavioral and modeling
studies of sound localization in cats: Effects of stimulus level and duration. *J Neurophysiol*
110, 607–620.

Gerhardt, H. C., Bee, M. A. and Christensen-Dalsgaard, J. (2023). Neuroethology of sound
localization in anurans. *J Comp Physiol A Neuroethol Sens Neural Behav Physiol* **209**, 115–
129.

Goense, J. B. M. and Ratnam, R. (2003). Continuous detection of weak sensory signals in
afferent spike trains: The role of anti-correlated interspike intervals in detection
performance. *J Comp Physiol A Neuroethol Sens Neural Behav Physiol* **189**, 741–759.

Gómez-Sena, L., Pedraja, F., Sanguinetti-Scheck, J. I. and Budelli, R. (2014). Computational
modeling of electric imaging in weakly electric fish: Insights for physiology, behavior and
evolution. *Journal of Physiology-Paris* **108**, 112–128.

Grewe, J., Kruscha, A., Lindner, B. and Benda, J. (2017). Synchronous spikes are necessary
but not sufficient for a synchrony code in populations of spiking neurons. *Proc Natl Acad*
Sci U S A **114**, E1977–E1985.

Gussin, D., Benda, J. and Maler, L. (2007). Limits of Linear Rate Coding of Dynamic Stimuli
by Electroreceptor Afferents. *J Neurophysiol* **97**, 2917–2929.

Henninger, J., Krahe, R., Kirschbaum, F., Grewe, J. and Benda, J. (2018). Statistics of
natural communication signals observed in the wild identify important yet neglected
stimulus regimes in weakly electric fish. *J Neurosci* 0350–18.

Kaushik, P. K., Renz, M. and Olsson, S. B. (2020). Characterizing long-range search behavior
in Diptera using complex 3D virtual environments. *Proc Natl Acad Sci U S A* **117**, 12201–
12207.

Kelly, M., Babineau, D., Longtin, A. and Lewis, J. E. (2008). Electric field interactions in
pairs of electric fish: Modeling and mimicking naturalistic inputs. *Biol Cybern* **98**, 479–490.

Kim, J. N. and Shadlen, M. N. (1999). Neural correlates of a decision in the dorsolateral
prefrontal cortex of the macaque. *Nature Neuroscience 1999 2:2* **2**, 176–185.

Knudsen, E. I. (1975). Spatial aspects of the electric fields generated by weakly electric fish.
Journal of Comparative Physiology ? A **99**, 103–118.

Lannoo, M. J., Maler, L. and Tinner, B. (1989). Ganglion cell arrangement and axonal
trajectories in the anterior lateral line nerve of the weakly electric fish Apteronotus
leptorhynchus (Gymnotiformes). *Journal of Comparative Neurology* **280**, 331–342.

MacIver, M. A., Sharabash, N. M. and Nelson, M. E. (2001). Prey-capture behavior in
gymnotid electric fish: motion analysis and effects of water conductivity. *Journal of*
Experimental Biology **204**,.

Maler, L., Sas, E., Johnston, S. and Ellis, W. (1991). An atlas of the brain of the electric fish
Apteronotus leptorhynchus. *J Chem Neuroanat* **4**, 1–38.

Marsat, G. and Maler, L. (2010). Neural Heterogeneity and Efficient Population Codes for
Communication Signals Marsat G, Maler L. Neural heterogeneity and efficient population
codes for communication signals. *J Neurophysiol* **104**, 2543–2555.

Marsat, G., Daly, K. C. and Drew, J. A. (2023). Characterizing neural coding performance for
populations of sensory neurons: comparing a weighted spike distance metrics to other
analytical methods. *bioRxiv* 778514.

Metzen, M. G., Huang, C. G. and Chacron, M. J. (2018). Descending pathways generate
perception of and neural responses to weak sensory input. *PLoS Biol* **16**, e2005239.

Metzen, M. G., Hofmann, V. and Chacron, M. J. (2020). Neural Synchrony Gives Rise to
Amplitude- and Duration-Invariant Encoding Consistent With Perception of Natural
Communication Stimuli. *Front Neurosci* **14**, 79.

Milam, O.E. (2023). Spatial processing of conspecific signals in weakly electric fish: from
sensory image to neural population coding. *Doctoral dissertation, West Virginia University*.
researchrepository.wvu.edu/etd/12120.

Milam, O. E., Ramachandra, K. L. and Marsat, G. (2019). Behavioral and Neural Aspects of
the Spatial Processing of Conspecifics Signals in the Electrosensory System. *Behavioral*
Neuroscience **133**, 282–296.

Nakamura, A., Yamada, T., Goto, A., Kato, T., Ito, K., Abe, Y., Kachi, T. and Kakigi, R.
(1998). Somatosensory Homunculus as Drawn by MEG. *Neuroimage* **7**, 377–386.

Nelson, M. E. and Maciver, M. A. (1999). Prey capture in the weakly electric fish Apteronotus
albifrons: sensory acquisition strategies and electrosensory consequences. *J Exp Biol* **202**,
1195–203.

Nelson, M. E., Xu, Z. and Payne, J. R. (1997). Characterization and modeling of P-type
electrosensory afferent responses to amplitude modulations in a wave-type electric fish.
Journal of Comparative Physiology A **181**, 532–544.

Okada, J. and Toh, Y. (2006). Active tactile sensing for localization of objects by the
cockroach antenna. *J Comp Physiol A Neuroethol Sens Neural Behav Physiol* **192**, 715–
726.

Pedraja, F., Aguilera, P., Caputi, A. A., Budelli, R. and Nobel, S. (2014). Electric Imaging
through Evolution, a Modeling Study of Commonalities and Differences. *PLoS Comput*
Biol **10**, e1003722.

Pedraja, F., Perrone, R., Silva, A. and Budelli, R. (2016). Passive and active electroreception
during agonistic encounters in the weakly electric fish Gymnotus omarorum. *Bioinspir*
Biomim **11**, 065002.

Petzold, J. M., Marsat, G. and Smith, G. T. (2016). Co-adaptation of electric organ discharges
and chirps in South American ghost knifefishes (Apteronotidae). *J Physiol Paris* **110**, 200–
215.

Pollack, G. S., Huber, F. and Weber, T. (1984). Frequency and temporal pattern-dependent
phonotaxis of crickets (Teleogryllus oceanicus) during tethered flight and compensated
walking. *Journal of Comparative Physiology A* **154**, 13–26.

Provis, J. M., Dubis, A. M., Maddess, T. and Carroll, J. (2013). Adaptation of the central
retina for high acuity vision: Cones, the fovea and the avascular zone. *Prog Retin Eye Res*
35, 63–81.

Ramachandra, K.L. (2023). Sense and sensitivity: spatial structure of conspecific signals
during social interaction. *Doctoral dissertation, West Virginia University*.
researchrepository.wvu.edu/etd/12111.

Rasnow, B., Assad, C. and Bower, J. M. (1993). Phase and amplitude maps of the electric
organ discharge of the weakly electric fish, Apteronotus leptorhynchus. *Journal of*
Comparative Physiology A **172**, 481–491.

Ratnam, R. and Nelson, M. E. (2000). Nonrenewal statistics of electrosensory afferent spike
trains: implications for the detection of weak sensory signals. *J Neurosci* **20**, 6672–83.

Rospars, J. P., Grémiaux, A., Jarriault, D., Chaffiol, A., Monsempes, C., Deisig, N., Anton,
S., Lucas, P. and Martinez, D. (2014). Heterogeneity and Convergence of Olfactory First-
Order Neurons Account for the High Speed and Sensitivity of Second-Order Neurons. *PLoS*
Comput Biol **10**, e1003975.

Rother, D., Migliaro, A., Canetti, R., Gómez, L., Caputi, A. and Budelli, R. (2003). Electric
images of two low resistance objects in weakly electric fish. *Biosystems* **71**, 169–177.

Schnupp, J. W. H. and Carr, C. E. (2009). On hearing with more than one ear: lessons from
evolution. *Nat Neurosci* **12**, 692–697.

Stamper, S. A., Madhav, M. S., Cowan, N. J. and Fortune, E. S. (2012). Beyond the Jamming
Avoidance Response: weakly electric fish respond to the envelope of social electrosensory
signals. *Journal of Experimental Biology* **215**, 4196–4207.

Stamper, S. A., Fortune, E. S. and Chacron, M. J. (2013). Perception and coding of envelopes
in weakly electric fishes. *Journal of Experimental Biology* **216**,.

Yu, N., Hupé, G., Garfinkle, C., Lewis, J. E., Longtin, A. and Fortune, E. (2012). Coding
Conspecific Identity and Motion in the Electric Sense. *PLoS Comput Biol* **8**, e1002564.

Zupanc, G. K. H. and Maler, L. (1993). Evoked chirping in the weakly electric fish
Apteronotus leptorhynchus : a quantitative biophysical analysis. *Can J Zool* **71**, 2301–2310.

Zupanc, G. K. H., Sîrbulescu, R. F., Nichols, A., Ilies, I., Sirbulescu, R. F., Nichols, A., Ilies,
I., Sîrbulescu, R. F., Nichols, A., Ilies, I., et al. (2006). Electric interactions through
chirping behavior in the weakly electric fish, Apteronotus leptorhynchus. *J Comp Physiol A*
Neuroethol Sens Neural Behav Physiol **192**, 159–173.

FIGURES

Figure 1: Model of the electric image during social interactions. The model takes into account the relative position of the two fish to estimate the strength of the EI caused by one fish (designated as "sender") onto the body of the other ("focal" fish). **A.** Three relative positions are illustrated here, representing different phases of a fish approaching the focal fish. **B.** The EI is quantified based on the strength of the transdermal voltage at the peak of the beat AM caused by the interaction of the fish's EODs. The strength of this AM is then normalized to the baseline EOD strength (i.e., EOD amplitude when only the focal fish is present) to obtain an EI strength expressed as percent contrast. 0% contrast indicates that the signal from the sender fish has no impact on the receiver, and 100% contrast indicates that the sender's signal is as strong as the focal fish's own EOD. We can see that for the two more distant positions, the signal strength is weak (<1%), and there are only minute differences in signal strength across the receiver's body. When the sender is very close, however, a salient "hot spot" has a much stronger EI strength than other portions of the body (note the different color scales for each image). We show, as an inset on the right, the electric field with current lines (grey lines) and the iso-potential lines, depicted as a color gradient (red or blue depending on polarity), for the near-field range. The perspective in this inset is from the top as in A), while the EI illustrations in B) present a perspective of the side of the focal fish being approached by the sender.

Figure 2: Spatial structure of the receptor array. A. Receptor density across the body of the fish was determined experimentally. Eosin Y stained specimens were examined, and cutaneous receptors of different types were identified (e.g., Neuromast labeled N, ampullary labeled A, or tuberous receptors labeled T in the inset on the top right). The number of tuberous receptors in $1mm^2$ areas was averaged across samples for each face of a coarse 3D mesh model of the fish (**B**). Receptor density as a function of body position was then smoothed by fitting a 5th-degree polynomial and mapped onto the fine mesh model used in the EI model (**C**). For each face of this 3D mesh, random receptor positions were selected according to the receptor density attributed to each face. The receptor positions that we generated are marked by the dots in B) and C), and their color reflects the density of receptors for the corresponding position.

Figure 3: EI strength as a function of the relative position of the two fish. A. The strength of the EI from the sender was calculated for each receptor position. It is displayed here for the three relative fish positions illustrated in Figure 1 (note the difference in color scale for positions two vs. one and 3). The focal fish are presented here from a top perspective. **B.** The strength of the electric image is characterized as a function of distance and azimuth. The EI for 864 relative positions (12 distances x 72 azimuths) was calculated, and the strength of the signal in the "hot spot" (HS; taken as the average of the 5% most strongly activated receptors) is depicted by the color scale. The position of the sender fish is based on the center of the EO, and the data points have been repositioned to reflect the distance between the center of the HS on the focal fish and the EO of the sender rather than the center

920   of the focal fish. The EI strength values

921   (contrast %) have been interpolated between data points. **C.** Average contrast values in the HS

922   across azimuth and for fish displayed as a function of the distance between the hot spot and EO

923   centers. The relationship follows a cubic power law (red best-fit curve: $c=1.6 \cdot 10^4 \cdot x^{-3}$).

Figure 4: Heterogeneous population response in modeled receptors. A. LIF models
with heterogeneous response properties were stimulated with realistic inputs that match the
spatio-temporal structure of conspecific signals. In the color map (top), each receptor's response
is quantified as the peak-to-trough firing rate modulation and normalized relative to spontaneous
modulations in firing rate occurring when no second fish is present (i.e., a relative response of 1
reflects modulations in firing rate similar to spontaneous activity). The two raster plot insets on
the left show the response patterns of two individual neurons from portions of the fish's body that
are more or less strongly stimulated. The raster plot on the right shows the population response,
where we display a stack of 800 randomly selected receptor responses, ordered from weakest
peak-to-trough responses (bottom) to strongest responses (top). B. We display the same elements
as in panel A, but the position of the sender fish is more distant (position 1 of Figure 1)
compared to the nearby relative position used in A. (position 2 from Figure 1).

Figure 5: Sensitivity of the receptor model replicates responses to beat stimuli. A. Mean firing rate (averaged across all receptors) during a single cycle of a 30 Hz AM beat stimulus for different contrast intensities. The model produced modulations in firing of just a few spikes/s peak-to-through for the weakest intensities and of a few hundred spikes/s for the stronger intensities. **B.** F-I curves display the strength of the response as a function of the stimulus intensity (mean across the population ± s.d.). Average peak-to-through firing rate quantified in a similar way; spontaneous activity (no sender fish) is displayed (grey dashed line), and we can see that for the weakest stimuli the average response is similar to spontaneous activity. Response sensitivity has been calibrated to match published data (Bastian, 1981; Nelson et al., 1997; see also Methods and Supplementary Figure S1). **C.** The distribution of response strength across the population of receptors is displayed for sender

fish positioned at different distances (azimuth 90º). The outer distributions (black violin plots)

show the variability of peak-to-through firing rate on single cycles of the beat for single neurons.

The inner distributions (colored violin plots) show the variability across neurons; however, for

each neuron, the peak-to-trough firing rate is averaged across the entire stimulus (900 cycles, 30

s). The mean of this distribution (i.e., also averaged across neurons) is displayed as a white line.

Dotted grid lines (in grey) are provided in the background to help notice minute differences in

the distributions. The fact that only subtle differences between the distributions for stimuli at

distances of 40 cm or more compared to responses in the absence of second fish highlights the

difficulty in detecting these distant signals.

Figure 6: Estimates of detection sensitivity as a function of relative fish position and the influence of receptor density distribution. A. Detection sensitivity is quantified as the time it would take to reliably detect the presence of the sender's signal and is displayed as a function of the relative position of the sender. For each position (12 distances x 72 azimuth), the peak-to-trough responses of the population are compared to spontaneous responses. As peak-to-trough is averaged across cycles of the beat (increased time to detection), detection becomes more reliable because noise is averaged out. We display the stimulation time required for our decoder to reach reliable detection (<5% error; see Methods for more details). Each position is defined by the distance and azimuth between the center of the receptor positions in the focal fish and the center of the EO in the sender fish. Values for each data point are then interpolated across space to obtain the smoothly varying color plots.

B. Decrease in detection sensitivity (increased time to detection) caused by reducing the density of receptors in dense areas (i.e., making it uniformly low like the density in the caudal portion of the body). The decrease in density makes uniformly no difference nearby (black region). It uniformly increases the time to detection when the sender is very distant (distant black area in panel A). It has a most pronounced effect at mid-distance (40-50 cm) in the frontal azimuth (yellow area) where time to detection increases from 1-2 s to 2-6 s (see also Supplementary Figure S3) showing that the rostral high density of receptors can increase detection sensitivity in

1004   the frontal quadrant. C. The overall detection sensitivity (time to detection averaged across

1005   azimuth) decreased markedly at distances above 30 cm when receptor density was made

1006   uniformly low (black line compared to red line) and decreased further when receptor density was

1007   made even sparser (1/2, 1/4 or 1/8 the size of the uniform population; grey curves).

1008

Figure 7: Estimates of angular resolution supported by the receptors' response accuracy. A. Angular resolution estimated as a function of distance and azimuth of the sender. The analysis is based on the average peak-to-trough firing rate (30 cycles average, i.e., 1 s) of each receptor for a given stimulus location. Population responses for a sender at a given test azimuth were compared by our decoder to responses for a sender at various angular displacements (clock-wise or counter-clock-wise; distance kept fixed). The smallest angle that allows 95% accurate discrimination between the responses was taken as the angular resolution. Failure to discriminate responses for stimuli locations 180º apart (black regions on the graph) indicates an inability to reliably localize the azimuth of the sender's location. Data points for 72 test azimuths and 12 distances (i.e., 864 positions) were generated, taking the center of receptors location for the focal fish and the center of the EO for the sender fish as position values. Data values are then interpolated to obtain the smoothly varying color plot. **B.** The angular resolution (mean ± s.d. across azimuth) can be calculated based on peak-to-trough responses of the receptors to a single cycle of the stimulus or on the peak-to-trough averaged across several cycles. Averaging the response across cycles corresponds to a decoder that integrates the response across time to get a more accurate estimate of response strength. Consequently, the angular resolution improves as the decoder integrates over more time; however, in all cases, we still observe a sharp change in resolution from very accurate (e.g., at distances below 20 cm) to very poor (e.g., above 50 cm).

1036

Figure 8: Receptor density and angular resolution as a function of azimuth. A.
Angular resolution for a sender fish at various positions around the focal fish was calculated as in
Figure 7, but the way distance is normalized across angles is different. We still compare, with
our decoder, positions at different angles while keeping the distance equal. Here, distance is set
by the distance between the rostral tip of the sender and the closest point on the surface of the
focal fish. The fish are thus separated by a fixed gap set to 1/4, 1/2, 1, or 2 body lengths (i.e., 3.5,
7, 14, and 28 cm, respectively). In Figure 7, the gap between the fish was not consistent across
azimuth since the distance was set between the center of receptor locations in the focal fish and
the center of the EO in the sender. For example, the rostral tip of the sender was closer to the
skin of the receiver when it was at 180° than when it was at 0°. The positions of the rostral tip of
the sender, for the 72 angles and four distances, are marked with dots on this figure. Datapoints
for various positions are still mapped on the color graph at the position of the middle of the EOD

of the sender, and the color gradient interpolated between datapoints. **B.** Decreasing the density

of receptors in dense areas (i.e., making receptor density uniformly as low as density in the

caudal portion of the body) causes decreases in angular resolution. This resolution decrease is

strongest in the red area of the graph. We note that this decrease is relatively limited and not

concentrated in the frontal quadrant. **C.** Angular resolution as a function of azimuth, distance,

and receptor density. This is the same data used to generate Panels A and B but presented here in

2D. The change in resolution as a function of azimuth is clearly visible even when receptor

density is uniform across the body **D.** Angular resolution averaged across azimuths for different

receptor density patterns. The full population is compared to a uniform lower-density population

or to populations made even sparser (1/2, 1/4, or 1/8 of the uniform population). Decreasing the

receptor density decreases the angular resolution. **E.** Changes in EI for small angular

displacements (averaged across 5°, 10°, and 15° displacements) are compared across azimuth

and related to the angular resolution of the system. For a given displacement, the difference in EI

was characterized by integrating the difference in EI strength across the body surface. This EI

difference was calculated for various azimuths and at the two distances (1 or 1/2 body length

apart) that give medium angular resolutions. We show that the EI difference correlates with

angular resolution with an exponential relationship (black best-fit curve, $r^2=0.98$).

1066

1067

1068   **SUPPLEMENTARY INFORMATION**

1069

1070   **Table S1: Model parameters used for the prototypic seed neuron (see Methods for details).**

Description	Name	Value	Description	Name	Value
Membrane time constant (s)	τ_m	$15 \cdot 10^{-4}$	Noise strength (A)	A_σ	$15 \cdot 10^{-9}$
Lean reversal potential (V)	E_m	$-70 \cdot 10^{-3}$	Adaptation reversal potential (V)	E_α	$-80 \cdot 10^{-3}$
Membrane resistance (Ω)	R_m	$15 \cdot 10^5$	Adaptation increment (V)	Δ_α	$14.5 \cdot 10^{-8}$
Spiking threshold (V)	V_T	$-49 \cdot 10^{-3}$	Adaptation time constant (s)	τ_α	$50 \cdot 10^{-3}$
Reset potential (V)	V_R	$-70 \cdot 10^{-3}$	EOD amplitude (A)	A_{EOD}	$1.7 \cdot 10^{-7}$
Refractory period (s)	t_R	$9 \cdot 10^{-4}$	EOD baseline bias (A)	β	$3 \cdot 10^{-8}$

1071

1072

1073

1074

Figure S1: Average response properties of the heterogeneous population of modeled

receptors.

A. an example of the membrane potential and spiking pattern of a model response (spontaneous

activity). **B.** Inter-spike intervale histogram of 2 different model neurons (spontaneous activity)

showing phase locking to the EOD period and different firing tendencies. Note that the x-axis is

expressed in multiples of the EOD period but since we used an EOD frequency of 1,000 Hz for

simplicity, this also corresponds to ms. **C.** Distribution of spontaneous firing rate across our

entire population. This distribution was achieved by selecting 26 seed neurons with firing rates

unevenly distributed along this range and diversifying model parameters based on these seeds

(see Methods). This range and distribution replicates published data (Bastian, 1981; Grewe et al.,

2017; Ratnam and Nelson, 2000). In particular, the mean spontaneous firing rate was 251 spk/s

with a CV of 0.45. **D.** Responses to step increases in EOD intensity. The strength of the peak

response, the steady-state response, and the adaptation time course were matched to published

data (Benda et al., 2005). **E.** Response gain to beat stimuli of different AM frequencies.

Although we did not explore systematically the response of our model at different beat

frequencies in the results section, we calculated the gain for a range of AM frequencies. This

analysis helps us to evaluate the sensitivity of the neurons (see the absolute scale on the left) and

it also helps to assert that the adaptation dynamic replicates some of the tuning properties of the

neurons (see the relative scale on the right; gain for an AM of 1 Hz is normalized to 1). This

average gain curve is comparable to experimental data (Chacron et al., 2005; Nelson et al.,

1997). **F.** Relative firing rate during random amplitude modulations. We replicated a published

analysis of receptor sensitivity (Gussin et al., 2007a) that measures the relative firing rate

(relative to average) in successive 32 ms windows during the response to a low frequency (0 to 4

Hz) random amplitude modulation. We note that our scale is different from theirs: our $\pm$ 5%

values correspond to the absolute contrast of the stimulus (i.e. s.d. of 10% contrast) whereas the

scale in their Fig 3 has $\pm$ 50% being the min-to-max of their 10% contrast stimulus. When

converted to the same scale, we find a gain slope of 23.7 spk/s/% ($\pm$ 5.8 s.d.) comparable to the

17.7 spk/s/% (range 3.2 to 40.2) they found. **G.** Mean coherence at 10-30 Hz for random

amplitude modulations (0-100 Hz) of different overall intensities (contrast). We qualitatively

matched the coherence to values found in previous publications (Chacron et al., 2005; Grewe et

al., 2017). **H.** Firing rate modulation in response to random amplitude modulations (0-300 Hz).

We replicated the analysis in Grewe et al. (2017; see their figure S1A) which plots the standard

deviation of the response (averaged over trials) as a function of stimulus contrast. Their

population averages go from approximately 100 spk/s at 2.5% contrast to 200 spk/s at 20%

contrast with a large variability among the population; we have a population average between 90

spk/s and 250 spk/s respectively.

1111

1112

1113

1114 **Figure S2: Receptor density compared between our full population (A) and our uniformly**
1115 **low-density population (B)**. Each dot shows the position of a receptor and the color reflects the
1116 density of receptors at this location. The uniform population was created by selecting, for each
1117 face of the mesh model, a subset of receptors from the full population to match the density of 2
1118 receptors per mm^2.

1119

1120

Figure S3: Detection performance as a function of source location and receptor structure. We compare a full population of receptors that includes a high density in rostral regions with a population that has a uniform density across the body matching the low density of the caudal region of the body (see Figure S2B). We present here the results for distances above 25 cm where we can see differences across azimuth and population structures. Our decoder considers that the response strength of receptors can be integrated across time and thus more noisy, weak responses require integration across longer periods to reach a reliable detection performance. We plot here the integration time required for our decoder to reach 95% detection accuracy and plot this here as a function of stimulus location.

1130

1131

1132