The rapid decline in interaural-time-difference sensitivity for pure tones is explained by a single frequency-channel model

Matthew J. Goupell[1,2] (ORCID: 0000-0003-2662-3057)

G. Cristopher Stecker[3]

Brittany T. Williams[3]

Anhelina Bilokon[1]

Daniel J. Tollin[4] (ORCID: 0000-0001-6790-1290)

[1] Department of Hearing and Speech Sciences, University of Maryland, College Park, MD 20742, USA

[2] Neuroscience and Cognitive Science Program, University of Maryland, College Park, MD 20742, USA

[3] Center for Hearing Research, Boys Town National Research Hospital, 555 N 30th St Omaha, NE 68131, USA

[4] Department of Physiology & Biophysics, University of Colorado School of Medicine, Aurora, CO 80045, USA

Corresponding Author:
Matthew J. Goupell
Department of Hearing and Speech Sciences
University of Maryland
College Park, MD 20742
(301) 405-8552
goupell@umd.edu

AUTHOR CONTRIBUTIONS
Conceptualization, methodology, software, investigation, data visualization, formal analysis, writing – original draft, funding acquisition, M.J.G.
Conceptualization, methodology, software, writing – review & editing, funding acquisition, G.C.S.
Methodology, investigation, writing – review & editing, B.T.W.
Methodology, investigation, writing – review & editing, A.B.
Conceptualization, methodology, investigation, data analysis, writing – review & editing, funding acquisition, D.J.T.

DECLARATION OF INTERESTS
The authors declare no competing interests.

CLASSIFICATION: Major: Biological Sciences; **Minor:** Neuroscience, Psychological and Cognitive Sciences

KEYWORDS: Spatial Hearing, Interaural Time Difference, Binaural Models, Binaural Physiology, Binaural Display

FUNDING: Research reported in this publication was supported by the National Institute on Deafness and Other Communication Disorders of the National Institutes of Health under Award Number R01DC014948 (M.J.G.), R01DC016643 (G.C.S.), R01DC01155 (D.J.T.). The content is solely the responsibility of the authors and does not necessarily represent the official views of the National Institutes of Health.

ABSTRACT

The interaural time difference (ITD) is a primary horizontal-plane sound localization cue computed in the auditory brainstem. ITDs are accessible in the temporal fine structure of pure tones with a frequency of no higher than about 1400 Hz. Explaining how listeners' ITD sensitivity transitions from very best sensitivity near 700 Hz to impossible to detect within 1 octave currently lacks a clear physiological explanation. Here, it was hypothesized that the rapid decline in ITD sensitivity is dictated not to a central neural limitation but by initial peripheral sound encoding, specifically, the low-frequency edge of the cochlear excitation pattern produced by a pure tone. To test this hypothesis, ITD sensitivity was measured in 16 normal-hearing listeners as a joint function of frequency (900-1500 Hz) and level (10-50 dB sensation level). Performance decreased with increasing frequency and decreasing sound level. The slope of performance decline was 90 dB/octave, consistent with the low-frequency slope of the cochlear excitation pattern. Consequently, fine-structure ITD sensitivity near 1400 Hz may be conveyed primarily by "off-frequency" activation of neurons tuned to lower frequencies near 700 Hz. Physiologically, this could be realized by a single narrow channel near 700 Hz that conveys fine-structure ITDs. Such a model is a major simplification and departure from the classic formulation of the binaural display, which consists of a matrix of neurons tuned to a wide range of relevant frequencies and ITDs.

(Number of words: 230/250)

SIGNIFICANCE STATEMENT

Human sensitivity to fine-structure interaural time differences declines with increasing frequency at an incredible rate of 90 dB/octave above 1200 Hz. This is best explained by initial peripheral processing (auditory filtering and off-frequency processing), not a central neural limitation such as a decline phase locking. A binaural model with a single dominant channel near 700 Hz can explain these data, which contradicts the classic formulation of binaural display that utilizes a matrix of neurons tuned to a range of best frequencies and interaural time differences.

(Number of words: 85/120)

INTRODUCTION

Humans can precisely localize sounds in the horizontal plane. When a sound is located away from the midline, the extra distance that the sound travels to the far ear generates an interaural time difference (ITD) (1). There is an obvious central physiological substrate for ITD processing in the medial superior olivary complex of the mammalian auditory brainstem, which consists of neurons that primarily respond to low frequencies and receive bilateral frequency-matched inputs from the anteroventral cochlear nucleus from cells that have short-latency and secure synaptic connections with superior temporal precision (2-5).

The most important ITD cues for sound localization occur at frequencies below 1500 Hz (6, 7) and are conveyed in the acoustic waveform's temporal fine structure, the temporal aspects of the rapid variation in pressure that the auditory nerve can precisely

encode. There are two notable features to ITD frequency dependence below 1500 Hz.

First, the best sensitivity in ITD discrimination for pure tones is exquisitely good, on the

order of 10 µs. This occurs for pure tones near 700 Hz (8-10), which coincides with the

often-called ITD frequency "dominant region" (i.e., a region of very high relative weight)

for lateralization of narrowband noises, transients, and complex tones that exceed a single

peripheral cochlear filter width (11-15). Second, ITD discrimination sensitivity for pure

tones declines at a remarkable slope previously estimated to be at least 46-78 dB/octave

as frequency is increased from 1200 to 1400 Hz (10, 16). This is much steeper than the

12 dB/octave decline in temporal information conveyed by auditory nerve phase locking

(17) (i.e., the ability to generate action potentials during a preferred phase of the

waveform), making the decline in neural phase locking a relatively poor explanation for

this phenomenon. The question posed in this study is whether the dominant region and

the upper limit of fine-structure ITD processing are related. This could be a result of

some unique aspect of binaural processing at 700 Hz that allows for very effective

conveyance of fine-structure ITD.

Most studies that investigate the frequency dependence of ITD discrimination

sensitivity present stimuli at a fixed level, for example 65 dB SPL (9) or 70 dB SPL (10,

16), comparable to the level of conversational speech. Lower level sounds (e.g., 10 dB

sensation level, SL) are perceived relatively nearer the midline (18) and have worse ITD

discrimination thresholds (19). For low-frequency pure tones, Zwislocki and Feldman (8)

measured ITD discrimination thresholds in up to six normal-hearing listeners as a

function of level (10-110 dB SL) and frequency (250, 500, 1000, and 1250 Hz). ITD

performance decreased as the frequency increased from 1000 to 1250 Hz, and as the level

decreased from 70 to 10 dB SL. At 10 dB SL and 1250 Hz, the ITD discrimination

threshold was not measurable, which places the upper limit of fine-structure ITD

processing at a frequency that is much lower than the typically reported 1400 Hz for

higher level tones (10).

121   (Figure 1 about here)

123   Another stage of the auditory system that shows an incredibly steep slope occurs

at the auditory periphery in the cochlea (inner ear), where there is a high-resolution

frequency decomposition of sound; in the cochlea, sound is effectively passed through a

bank of narrowly tuned bandpass filters (20). The low-frequency edge of the cochlear

excitation pattern (i.e., the representation of the effective amount of excitation produced

by a stimulus or internal spectral representation of a stimulus) (21) generated by one of

these peripheral bandpass auditory filters is approximately 100 dB/octave at 1000 Hz (20,

22). This means that tonal excitation at a frequency just above the ITD frequency

dominant region extends downward to induce activity in dominant region neurons tuned

near 700 Hz, but this activity would decrease rapidly with increasing tone frequency and

decreasing tone level (Fig. 1). Moreover, at some frequency near 1400 Hz, activity of

neurons in the dominant region would cease altogether regardless of the tone level due to

the exceptionally steep cochlear excitation pattern. That expectation is consistent with the

abrupt cessation of the ability to use fine-structure ITDs near 1400 Hz. Such a

relationship can be understood if the upper limit of fine-structure ITD processing was

investigated as a function of level. Such measurements, however, have not been made

with adequate resolution to quantify the slope of ITD sensitivity decline with adequate

precision. Therefore, this study measured this upper limit as a function of frequency and

sound level. It was hypothesized that the upper limit of fine-structure ITD processing

decreases with decreasing level with a slope near 100 dB/octave, suggesting it is a

consequence of peripheral auditory filtering, the low-frequency edge of the cochlear

excitation pattern. Through the confirmation of this hypothesis, we have shown that these

data are best explained by the initial peripheral encoding, and that fine-structure ITD is

conveyed through responses of a single dominant channel tuned near 700 Hz,

contradicting the classic formulation of the binaural display.

RESULTS AND DISCUSSION

The upper limit of fine-structure ITD sensitivity decreases from 1400 to 900 Hz with decreasing sound level

Individual ITD discrimination data are shown in Fig. 2 for all 16 normal-hearing

human listeners. The average performance across all tested conditions is reported in each

panel. While there is variability in the overall performance, the patterns in the data are

consistent across listeners and testing sites. Two listeners (M6 and B3) had great

difficulty with this task, with an average performance <60%. These two listeners were

removed from subsequent group analyses. For all other listeners, ITD discrimination

performance decreased systematically with increasing frequency and decreasing sound

level.

(Figure 2 about here)

The average ITD discrimination data are shown in Fig. 3(A) for 14 listeners. A

three-way repeated-measures analysis of variance was performed on ITD discrimination

performance transformed to rationalized arcsine units (23) with factors frequency (7

levels: 900-1500 Hz), level (4 levels: 10, 20, 30, 50 dB SL), and testing location (3

levels: Maryland, Nebraska, Colorado). The Greenhouse-Geisser correction was used to

address sphericity assumption violations. There were significant effects of frequency

[$F(2.8,5.6)=73.7$, $p<0.0001$, $\eta_p^2=0.87$] and level [$F(1.6,3.2)=99.4$, $p<0.0001$, $\eta_p^2=0.90$].

There was a significant frequency×level interaction [$F(4.4,8.8)=13.9$, $p<0.0001$,

$\eta_p^2=0.56$]. The effect of testing location was not significant [$F(2,11)=0.265$, $p=0.772$,

$\eta_p^2=0.05$], and there were no significant interactions with testing location ($p>0.05$ for all).

(Figure 3 about here)

The upper limit of fine-structure ITD processing (defined as 75% correct ITD

discrimination performance) was found for each presentation level and for each listener

by fitting the data with a logistic regression (24). The frequency boundaries are shown in

Fig. 3(B). These data generally agree with others that show that the upper limit of fine-

structure ITD processing is near 1400 Hz for sound levels above 50 dB SPL.(8-10, 16)

Across listeners, the frequency that yielded 75% correct ITD discrimination was

1264.8±95.4 Hz (range=1168–1483) for 50 dB SL tones. For better comparison to past

studies estimating the upper frequency boundary at higher levels, the data in Fig. 3(B)

were fit by a three-parameter exponential rise to maximum function. The best fitting

equation (r=0.74, $p<0.0001$) was $y = 775.9 + 587.6 \times (1 - e^{-0.039x})$, where y is the

frequency boundary and x is the sensation level. Evaluating this function at 70 dB SL

yielded an estimated upper frequency boundary of 1326 Hz with a 95% confidence

interval from 1212 to 1437 Hz, the latter which encompasses the upper frequency

boundary measured in other studies (8-10, 16).

Any other small discrepancies in the upper limit of fine-structure ITD processing

between the current study and others can be explained by methodological differences. For

example, our stimuli had slow diotic ramps minimizing contributions from onset ITD

(25). We also tested more listeners than previous studies, and thus may have included

more listeners that were not operating at a point near the absolute limits of human

binaural processing, including two that were middle aged (26, 27). Similarly, Klug and

Dietz (10) and Best and Swaminathan (28) tested a relatively large number of normal-

hearing listeners (n=9), and reported relatively larger ITD thresholds compared to some

studies with relatively smaller (potentially more selective) samples. It may also be that

more extensive training would improve ITD discrimination performance to the levels of

the best listeners in this study (29), including the two who had <60% total correct

responses and were omitted from the average data and slope calculations (described

below).

These data also agree with other studies that show declines in ITD discrimination

performance with decreasing sound level (8, 19, 28). This decrease in performance with

decreasing level causes the 75% correct performance point to shift from about 1400 to

900 Hz [Fig. 3(B)]. It is notable that changing the stimulus level from 50 to 30 SL

produces a marked change in the upper limit given that both stimuli are clearly audible;

this result is difficult to reconcile with a phase locking explanation, which reaches a

maximum within ~20 dB of neural threshold (30). Hence, it is important to account for

the stimulus sound level when considering the upper limit of fine-structure ITD

processing.

213   The rate of fine-structure ITD sensitivity decline is 90 dB/octave, best

214   explained by peripheral cochlear filtering

A linear fit between the sound level (in dB SL) and the frequency boundary (in

octaves relative to 1000 Hz) determined the slope of the ITD performance change. The

10 dB SL point was omitted from the calculation for 2 of the 14 listeners (M3 and C2)

because they did not have an estimate of the frequency boundary at 75% correct (i.e.,

they were guessing in this condition). The resulting fit slopes are shown in Fig. 3(C). The

median slope was 90.5 dB/octave (range=40.7–244.6). The linear fits explained a median

of 88% in the variance of the data points (range=74–99.8).

The most important addition to our knowledge that results from this study is that

the slope of ITD discrimination performance decline was measured to be 90 dB/octave

[Fig. 3(C)]. Such a steep slope of decline limits the possible explanations for the

physiological mechanisms that are involved in the upper limit of fine-structure ITD

processing. For example, Klug *et al*. showed that phase locking in the auditory nerve

across animal models declines at approximately 12 dB/octave (17). Therefore, the decline

in phase locking by itself cannot account for these data because the slopes are so

different. In contrast, one well-known stage of the auditory system that does have such a

steep slope is the low-frequency edge of the cochlear excitation pattern, which is

approximately 100 dB/octave near 1000 Hz (20, 22).

Fine-structure ITD sensitivity as a function of frequency appears to be a

result of off-frequency listening to a single channel near 700 Hz

If the peripheral cochlear filtering interpretation of these data is correct, it has a

further important corollary. It suggests that ITD sensitivity for stimulus frequencies

between 1000-1500 Hz are primarily driven by lower-frequency neurons, such as those

tuned between 500-1000 Hz–in other words, the region where the best ITD sensitivity is

observed (9) and location of the ITD frequency dominant region for ITD (Fig. 1) (13).

There could be a narrow band of neurons near 700 Hz in humans that is responsible for

conveying fine-structure ITD, which in turn yields the exquisite sensitivity to fine-

structure ITDs and carries most of the localization weight for broadband stimuli. Indeed,

examination of the functional form of ITD sensitivity as a function of frequency [see Fig.

9 in Klug and Dietz (10)] resembles the neural response area of a high level tone (i.e., a

shallow low-frequency portion, a minimum at 700 Hz, a sharp high-frequency portion;

the inverse of the excitation patterns shown in Fig. 1), which would suggest the

possibility of a single dominant channel for fine-structure ITD processing. To the extent

that neurons tuned to 1000-1500 Hz contribute to fine-structure ITD sensitivity, they are

clearly less important than those between 500-1000 Hz because the observed transition

slope does not extend near the high-frequency edge of their tuning, which would be 2

kHz or higher. They may, in fact, not contribute at all. In other words, the dominant

region neurons are highly weighted even for pure tones.

Future behavioral and physiological experiments that examine ITD sensitivity as a

function of frequency and level are required to better understand the properties of the

neurons that convey fine-structure ITD information. Such experiments include animal

studies in mammalian models to determine if they have a single dominant fine-structure

ITD channel and its location in frequency. For example, primates may have a dominant

channel near the same frequency region as humans but in animals with smaller heads like

cats, ferrets, and chinchillas, it could be higher, if it exists at all. (31)

The proposed "dominant channel theory," having only a single narrow band of

ITD sensitive neurons near 700 Hz, is starkly different than the classic binaural display

proposed by Jeffress (11, 32, 33), which consists of a matrix of frequency- and ITD-tuned

neurons. Such a reimagining of human ITD processing overlaps with past discussions

about mammalian vs avian binaural-processing models, the distribution and length of

neural delay lines, and how the binaural system processes physiologically plausible and

implausible ITDs (2, 4, 33-35). This dominant channel theory can be formulated to be

consistent with the idea that the binaural system evolved in a manner to emphasize

ecologically valid range of ITDs that provide unambiguous location information(36),

helping to reconcile the discrepant interpretation of data from several past binaural-

hearing studies.

In summary, the rapid 90 dB/octave rate of decline in fine-structure ITD

sensitivity is best explained by initial peripheral cochlear filtering. This suggests that

listeners are performing off-frequency listening to a single dominant channel tuned near

700 Hz. Such a model contradicts the classic binaural display that utilizes a matrix of

neurons that yield maximum firing rates at their best frequency and best interaural time
difference.

METHODS

Listeners and Equipment

Sixteen young to middle-aged (mean=30.1 years, range=20-51 yrs) normal-
hearing listeners (10 female) were tested in this study. Hearing thresholds were measured
at octave frequencies from 0.25-8 kHz. Hearing thresholds were ≤20 dB hearing level
(HL) for all listeners except C1, who had slightly higher thresholds ≥6 kHz. Interaural
asymmetry in hearing thresholds was ≤10 dB except it was 15 dB at 1000 Hz for listener
M5. Data from the authors (listeners M1, B1, B2, and C1) were included.

The testing was done at three locations (Maryland, Nebraska, and Colorado),
three to seven listeners at each location. Each location used the same testing software and
type of circumaural headphones (HD280 Pro, Sennheiser; Hannover, Germany). Stimuli
were generated and the experiment was conducted on a personal computer using MATLAB
(the Mathworks; Natick, MA). Procedures were reviewed and approved by the University
of Maryland, Boys Town National Research Hospital in Nebraska, and the University of
Colorado School of Medicine Multiple Institutional Review Boards for use of human
subjects.

In Maryland, testing was performed in a double-walled sound booth (IAC; North
Aurora, IL). Stimuli were presented to listeners via an external sound card (Sound Blaster
PLAY! 3, Creative Labs; Milpitas, California). In Nebraska, testing was performed in a
double-walled electromagnetically shielded sound booth (ETS-Lindgren; Cedar Park,

TX). Stimuli were presented to listeners via USB audio interface (RME Fireface UFX;

Haimhausen, Germany). In Colorado, testing was performed in a single-walled custom-

built sound booth. Stimuli were presented to listeners via an external digital-to-analog

converter (Schitt Modi, Schitt Audio; Newhall, CA) and headphone amplifier (Schitt

Magni 3+, Schitt Audio; Newhall, CA).

Stimuli

The stimuli were pure tones that were 250 ms in duration, with frequencies of

900-1500 Hz in 100-Hz steps. For audiometric threshold measurements, tones were

presented diotically. For ITD discrimination testing, tones started with the left channel in

sine (0°) phase and the right channel had the same phase or a phase that yielded ±167-µs

ITDs. Then a diotic raised-cosine temporal ramp applied that had a 100-ms rise-fall time.

In other words, ITD was applied in only the temporal fine structure. The tone amplitude

was 10-, 20-, 30-, and 50-dB SL.

Procedure

<u>Pure-Tone Audiometric Threshold Measurements</u>

Pure tones were presented diotically. An experimenter controlled the timing of

presentation and level of the stimulus by using buttons that could adjust the level by 0,

±1, ±2, or ±6 dB. Listeners indicated when they heard a tone. Experimenters adjusted the

sound level above and below the level that produced threshold (transition from response

to no response) at least twice to determine a final threshold level (TL), which defines 0

dB SL, at each test frequency. The frequencies were tested in increasing order. The

threshold at each frequency was tested twice for most listeners. If the two thresholds

differed by >5 dB, additional threshold levels were measured and the average of the last

two measurements were used. Across-frequency averaging was implemented to smooth

out small variations in TL during later periods of testing (listeners M6, B4, B5, B6): the

average TL at each frequency was computed as the average of levels from the target and

adjacent frequencies, rounded to the nearest integer. For example, the TL at 1200 Hz was

based on the six measurements from 1100, 1200, and 1300 Hz. Adjustments due to

averaging were small–generally, less than 2 dB; on average <1 dB over all listeners and

frequencies–and yielded comparable results to unsmoothed TLs used for other listeners.

<u>Left-right ITD Discrimination</u>

Listeners performed a two-interval forced-choice discrimination task based on the

task described by Füllgrabe and Moore (26). Each interval presented a sequence of four

250-ms tone bursts with sinusoidal envelopes. In the reference interval, all four tone

bursts had zero ITD. In the target interval, the ITD alternated twice between right and left

leading ±167-µs ITDs (i.e., right-left-right-left). This ITD magnitude was chosen because

it corresponds to one-quarter of the stimulus period at 1500 Hz, which was the highest

frequency tested in this study. Hence, this ITD should yield the maximum performance at

1500 Hz and avoids the descending portion of the cyclical psychometric function. There

was a 200-ms silent interval between the target and reference intervals. The order of the

intervals was randomized with a probability of 50%. The task of the listener was to

identify which interval contained the target alternating ITD.

The task was self-paced because listeners initiated each trial. After the stimulus

was presented, the listener indicated the target interval by pressing a button on the screen.

Pre-experiment training was performed to ensure the listener understood the task

and had no apparent problems with binaural processing. Listeners were initially presented

with 10 trials at 500 Hz and 70 dB SL. Training in 10-trial blocks continued until

performance was 100% correct. Almost all the listeners needed only the initial 10

practice trials to proceed.

For the main experiment, a method of constant stimuli was performed where all

combinations of frequency and level were presented in random order, consisting of seven

frequencies (900–1500 Hz in 100-Hz steps) and four levels (10, 20, 30, and 50 dB SL).

Therefore, there were 112 trials per block (7 frequencies×4 level×4 trials), and each block

took ~10 minutes to complete. Testing breaks were provided between blocks as needed.

Listeners performed 60 trials/condition, which took ~3 hours. Three listeners were

provided less than 60 trials (minimum of 56 trials) for at least one condition and four

listeners were provided more than 60 trials (maximum of 83 trials) for at least one

condition because of computer or experimenter error. Correct answer feedback was

provided after each trial, which helped keep the listener attentive during testing blocks.

ACKNOWLEDGMENTS

We thank Taylor Beinke for assistance with data collection.

REFERENCES

1. W. M. Hartmann, "Localization and Lateralization of Sound" in Binaural Hearing, R.

Y. Litovsky, M. J. Goupell, R. R. Fay, A. N. Popper, Eds. (Springer International

Publishing, Cham, Switzerland, 2021), vol. 73, pp. 9-45.

2. R. Y. Litovsky, M. J. Goupell, R. R. Fay, A. N. Popper, *Binaural Hearing*, Springer

Handbook of Auditory Research (Springer International Publishing, Cham

Switzerland, 2021), vol. 73, pp. 424.

3. D. A. Blanks, J. M. Roberts, E. Buss, J. W. Hall, D. C. Fitzpatrick, Neural and

behavioral sensitivity to interaural time differences using amplitude modulated tones

with mismatched carrier frequencies. *J. Assoc. Res. Otolaryngol.* **8**, 393-408 (2007).

4. T. C. T. Yin, P. H. Smith, P. X. Joris, Neural mechanisms of binaural processing in

the auditory brainstem. *Compr. Physiol.* **9**, 1503-1575 (2019).

5. M. Müller, Quantitative comparison of frequency representation in the auditory

brainstem nuclei of the gerbil, Pachyuromys duprasi. *Exp. Brain Res.* **81**, 140-149

(1990).

6. E. A. Macpherson, J. C. Middlebrooks, Listener weighting of cues for lateral angle:

The duplex theory of sound localization revisited. *J. Acoust. Soc. Am.* **111**, 2219-2236

(2002).

7. F. L. Wightman, D. J. Kistler, The dominant role of low-frequency interaural time

differences in sound localization. *J. Acoust. Soc. Am.* **91**, 1648-1661 (1992).

8. J. Zwislocki, R. S. Feldman, Just noticeable differences in dichotic phase. *J. Acoust.*

Soc. Am. **28**, 860-864 (1956).

9. R. G. Klumpp, H. R. Eady, Some measurements of interaural time difference

thresholds. *J. Acoust. Soc. Am.* **28**, 859-860 (1956).

10. J. Klug, M. Dietz, Frequency dependence of sensitivity to interaural phase differences

in pure tones. *J. Acoust. Soc. Am.* **152**, 3130-3141 (2022).

11. R. M. Stern, A. S. Zeiberg, C. Trahiotis, Lateralization of complex binaural stimuli: A

weighted-image model. *J. Acoust. Soc. Am.* **84**, 156-165 (1988).

12. T. M. Shackleton, R. Meddis, M. J. Hewitt, Across frequency integration in a model

of lateralization. *J. Acoust. Soc. Am.* **91**, 2276-2279 (1992).

13. M. L. Folkerts, G. C. Stecker, Spectral weighting functions for lateralization and

localization of complex sound. *J. Acoust. Soc. Am.* **151**, 3409-3425 (2022).

14. D. J. Tollin, G. B. Henning, Some aspects of the lateralization of echoed sound in

man. II. The role of the stimulus spectrum. *J. Acoust. Soc. Am.* **105**, 838-849 (1999).

15. M. J. Goupell, A. V. Bilokon (2022) Support for the frequency dominance region

explanation of lateralization of larger than physiologically possible interaural time

differences. in *International Symposium on Hearing* (Lyon, France), pp 1-19.

16. A. Brughera, L. Dunai, W. M. Hartmann, Human interaural time difference

thresholds for sine tones: The high-frequency limit. *J. Acoust. Soc. Am.* **133**, 2839-

2855 (2013).

17. J. Klug, J. Encke, M. Dietz, Characterization of the decline in auditory nerve phase

locking at high frequencies. *JASA Express Lett.* **3**, 074403 (2023).

18. A. Ihlefeld, N. Alamatsaz, R. M. Shapley, Population rate-coding predicts correctly

that human sound localization depends on sound intensity. *Elife* **8** (2019).

19. M. Dietz, L. R. Bernstein, C. Trahiotis, S. D. Ewert, V. Hohmann, The effect of

overall level on sensitivity to interaural differences of time and level at high

frequencies. *J. Acoust. Soc. Am.* **134**, 494-502 (2013).

20. A. J. Oxenham, C. A. Shera, Estimates of human cochlear tuning at low levels using

forward and simultaneous masking. *J. Assoc. Res. Otolaryngol.* **4**, 541-554 (2003).

21. B. C. Moore, B. R. Glasberg, Suggested formulae for calculating auditory-filter

bandwidths and excitation patterns. *J. Acoust. Soc. Am.* **74**, 750-753 (1983).

22. K. L. Whiteford, H. A. Kreft, A. J. Oxenham, The role of cochlear place coding in the

perception of frequency modulation. *Elife* **9** (2020).

23. G. A. Studebaker, A 'rationalized' arcsine transform. *J. Speech Hear. Res.* **28**, 455-

462 (1985).

24. F. A. Wichmann, N. J. Hill, The psychometric function: II. Bootstrap-based

confidence intervals and sampling. *Percept. Psychophys.* **63**, 1314-1329 (2001).

25. G. C. Stecker, J. M. Bibee, Nonuniform temporal weighting of interaural time

differences in 500 Hz tones. *J. Acoust. Soc. Am.* **135**, 3541-3547 (2014).

26. C. Füllgrabe, B. C. J. Moore, The association between the processing of binaural

temporal-fine-structure information and audiometric threshold and age: A meta-

analysis. *Trends Hear.* **22**, 2331216518797259 (2018).

27. B. Ross, T. Fujioka, K. L. Tremblay, T. W. Picton, Aging in binaural hearing begins

in mid-life: Evidence from cortical auditory-evoked responses to changes in interaural

phase. *J. Neurosci.* **27**, 11172-11178 (2007).

28. V. Best, J. Swaminathan, Revisiting the detection of interaural time differences in

listeners with hearing loss. *J. Acoust. Soc. Am.* **145**, EL508-EL513 (2019).

29. B. A. Wright, M. B. Fitzgerald, Different patterns of human discrimination learning

for two interaural cues to sound-source location. *Proc. Natl. Acad. Sci. USA* **98**,

12307-12312 (2001).

30. A. R. Palmer, I. J. Russell, Phase-locking in the cochlear nerve of the guinea-pig and

its relation to the receptor potential of inner hair-cells. *Hear. Res.* **24**, 1-15 (1986).

31. E. Verschooten *et al.*, The upper frequency limit for the use of phase locking to code

temporal fine structure in humans: A compilation of viewpoints. *Hear Res* **377**, 109-

121 (2019).

32. L. A. Jeffress, A place theory of sound localization. *J. Comp. Physiol. Psychol.* **41**,

35-39 (1948).

33. R. M. Stern, H. S. Colburn, L. R. Bernstein, C. Trahiotis, The fMRI data of

Thompson et al. (2006) do not constrain how the human midbrain represents

interaural time delay. *J. Assoc. Res. Otolaryngol.* **20**, 305-311 (2019).

34. B. Grothe, M. Pecka, D. McAlpine, Mechanisms of sound localization in mammals.

Physiol. Rev. **90**, 983-1012 (2010).

35. S. K. Thompson *et al.*, Representation of interaural time delay in the human auditory

midbrain. *Nat. Neurosci.* **9**, 1096-1098 (2006).

36. W. M. Hartmann, E. J. Macaulay, Anatomical limits on interaural time differences:

An ecological perspective. *Front. Neurosci.* **8**, 34 (2014).

Figures and Captions:

Fig. 1: Illustration of the transformation of input acoustic tones into their effective neural spectral representations (i.e., their excitation patterns, which have a steep low-frequency slope and shallow high-frequency slope) and their relationship to the experimental hypothesis. If fine-structure ITD is primarily conveyed by neurons in the ITD frequency dominant region near 700 Hz, decreasing the stimulus level will decrease the highest frequency that demonstrates fine-structure ITD sensitivity at approximately the same slope as the low-frequency edge of the cochlear excitation pattern, about 100 dB/octave.

460 Fig. 2: Percent correct as a function of frequency and level (in dB SL) for 16 listeners.

461 Error bars show 95% confidence intervals. The average percent correct over all

462 conditions is reported in each panel.

Fig. 3: (A) Percent correct as a function of frequency and sensation level for 14 listeners. Error bars represent ±1 standard error. Some conditions had error bars that were smaller than the symbol. (B) Frequency boundaries that yield 75% correct ITD discrimination performance. Small closed symbols show individual data. Large open symbols show the data averaged over listeners. The error bars represent ±1 standard deviation. (C) Linear slope estimates between sound level (in dB SL) and frequency (in octaves). Small closed symbols show the slope for the individual listeners. The box length represents the interquartile range, and the median is shown within the box. Whiskers extend to 10th and 90th percentiles.