The rapid decline in interaural-time-difference sensitivity for pure tones is explained by a single frequency-channel model

Matthew J. Goupell[1,2] (ORCID: 0000-0003-2662-3057)
G. Christopher Stecker[3] (ORCID: 0000-0003-1442-9839)
Brittany T. Williams[3] (ORCID: 0000-0002-6779-8331)
Anhelina Bilokon[1]
Daniel J. Tollin[4] (ORCID: 0000-0001-6790-1290)

[1] Department of Hearing and Speech Sciences, University of Maryland, College Park, MD 20742, USA
[2] Neuroscience and Cognitive Science Program, University of Maryland, College Park, MD 20742, USA
[3] Center for Hearing Research, Boys Town National Research Hospital, 555 N 30th St Omaha, NE 68131, USA
[4] Department of Physiology & Biophysics, University of Colorado School of Medicine, Aurora, CO 80045, USA

Corresponding Author:
Matthew J. Goupell
Department of Hearing and Speech Sciences
University of Maryland
College Park, MD 20742
(301) 405-8552
goupell@umd.edu

AUTHOR CONTRIBUTIONS
Conceptualization, methodology, software, investigation, data visualization, formal analysis, writing – original draft, funding acquisition, M.J.G.
Conceptualization, methodology, software, writing – review & editing, funding acquisition, G.C.S.
Methodology, investigation, writing – review & editing, B.T.W.
Methodology, investigation, writing – review & editing, A.B.
Conceptualization, methodology, investigation, data analysis, writing – review & editing, funding acquisition, D.J.T.

STATEMENTS AND DECLARATIONS
The authors declare no competing interests.

KEYWORDS: Spatial Hearing, Interaural Time Difference, Binaural Models, Binaural Physiology, Binaural Display

FUNDING: Research reported in this publication was supported by the National Institute on Deafness and Other Communication Disorders of the National Institutes of Health under Award Number R01DC014948 (M.J.G.), R01DC016643 (G.C.S.), R01DC01155 (D.J.T.). The content is solely the responsibility of the authors and does not necessarily represent the official views of the National Institutes of Health.

ABSTRACT

Purpose: The interaural time difference (ITD) is a primary horizontal-plane sound

localization cue computed in the auditory brainstem. ITDs are accessible in the temporal

fine structure of pure tones with a frequency of no higher than about 1400 Hz. Explaining

how listeners' ITD sensitivity transitions from very best sensitivity near 700 Hz to

impossible to detect within 1 octave currently lacks a clear physiological explanation.

Here, it was hypothesized that the rapid decline in ITD sensitivity is dictated not to a

central neural limitation but by initial peripheral sound encoding, specifically, the low-

frequency edge of the cochlear excitation pattern produced by a pure tone.

Methods: ITD sensitivity was measured in 16 normal-hearing listeners as a joint function

of frequency (900-1500 Hz) and level (10-50 dB sensation level).

Results: Performance decreased with increasing frequency and decreasing sound level.

The slope of performance decline was 90 dB/octave, consistent with the low-frequency

slope of the cochlear excitation pattern.

Conclusion: Fine-structure ITD sensitivity near 1400 Hz may be conveyed primarily by

"off-frequency" activation of neurons tuned to lower frequencies near 700 Hz.

Physiologically, this could be realized by a single narrow channel near 700 Hz that

conveys fine-structure ITDs. Such a model is a major simplification and departure from

the classic formulation of the binaural display, which consists of a matrix of neurons

tuned to a wide range of relevant frequencies and ITDs.

(Number of words: 229/250)

INTRODUCTION

Humans can precisely localize sounds in the horizontal plane. When a sound is

located away from the midline, the extra distance that the sound travels to the far ear

generates an interaural time difference (ITD) (Hartmann, 2021). There is an obvious

central physiological substrate for ITD processing in the medial superior olivary complex

of the mammalian auditory brainstem, which consists of neurons that primarily respond

to low frequencies and receive bilateral frequency-matched inputs from the anteroventral

cochlear nucleus from cells that have short-latency and secure synaptic connections with

superior temporal precision (Müller, 1990; Blanks et al., 2007; Yin et al., 2019; Litovsky

et al., 2021).

The most important ITD cues for sound localization occur at frequencies below

1500 Hz (Wightman and Kistler, 1992; Macpherson and Middlebrooks, 2002) and are

conveyed in the acoustic waveform's temporal fine structure, the temporal aspects of the

rapid variation in pressure that the auditory nerve can precisely encode. There are two

notable features to ITD frequency dependence below 1500 Hz. First, the best sensitivity

in ITD discrimination for pure tones is exquisitely good, on the order of 10 μs. This

occurs for pure tones near 700 Hz (Klumpp and Eady, 1956; Zwislocki and Feldman,

1956; Klug and Dietz, 2022), which coincides with the often-called ITD frequency

"dominant region" (i.e., a region of very high relative weight) for lateralization of

narrowband noises, transients, and complex tones that exceed a single peripheral cochlear

filter width (Stern et al., 1988; Shackleton et al., 1992; Tollin and Henning, 1999;

Folkerts and Stecker, 2022; Goupell and Bilokon, 2022). Second, ITD discrimination

sensitivity for pure tones declines at a remarkable slope previously estimated to be at

least 46-78 dB/octave as frequency is increased from 1200 to 1400 Hz (Brughera et al.,

2013; Klug and Dietz, 2022). This is much steeper than the 12 dB/octave decline in

temporal information conveyed by auditory nerve phase locking (Klug et al., 2023) (i.e.,

the ability to generate action potentials during a preferred phase of the waveform),

making the decline in neural phase locking a relatively poor explanation for this

phenomenon. The question posed in this study is whether the dominant region and the

upper limit of fine-structure ITD processing are related. This could be a result of some

unique aspect of binaural processing at 700 Hz that allows for very effective conveyance

of fine-structure ITD.

Most studies that investigate the frequency dependence of ITD discrimination

sensitivity present stimuli at a fixed level, for example 65 dB SPL (Klumpp and Eady,

1956) or 70 dB SPL (Brughera et al., 2013; Klug and Dietz, 2022), comparable to the

level of conversational speech. Lower level sounds (e.g., 10 dB sensation level, SL) are

perceived relatively nearer the midline (Ihlefeld et al., 2019) and have worse ITD

discrimination thresholds (Dietz et al., 2013). For low-frequency pure tones, Zwislocki

and Feldman (Zwislocki and Feldman, 1956) measured ITD discrimination thresholds in

up to six normal-hearing listeners as a function of level (10-110 dB SL) and frequency

(250, 500, 1000, and 1250 Hz). ITD performance decreased as the frequency increased

from 1000 to 1250 Hz, and as the level decreased from 70 to 10 dB SL. At 10 dB SL and

1250 Hz, the ITD discrimination threshold was not measurable, which places the upper

limit of fine-structure ITD processing at a frequency that is much lower than the typically

reported 1400 Hz for higher level tones (Klug and Dietz, 2022).

(Figure 1 about here)

Another stage of the auditory system that shows an incredibly steep slope occurs

at the auditory periphery in the cochlea (inner ear), where there is a high-resolution

frequency decomposition of sound; in the cochlea, sound is effectively passed through a

bank of narrowly tuned bandpass filters (Oxenham and Shera, 2003). The low-frequency

edge of the cochlear excitation pattern (i.e., the representation of the effective amount of

excitation produced by a stimulus or internal spectral representation of a stimulus)

(Moore and Glasberg, 1983) generated by one of these peripheral bandpass auditory

filters is approximately 100 dB/octave at 1000 Hz (Oxenham and Shera, 2003; Whiteford

et al., 2020). This means that tonal excitation at a frequency just above the ITD frequency

dominant region extends downward to induce activity in dominant region neurons tuned

near 700 Hz, but this activity would decrease rapidly with increasing tone frequency and

decreasing tone level (Fig. 1). Moreover, at some frequency near 1400 Hz, activity of

neurons in the dominant region would cease altogether regardless of the tone level due to

the exceptionally steep cochlear excitation pattern. That expectation is consistent with the

abrupt cessation of the ability to use fine-structure ITDs near 1400 Hz. Such a

relationship can be understood if the upper limit of fine-structure ITD processing was

investigated as a function of level. Such measurements, however, have not been made

with adequate resolution to quantify the slope of ITD sensitivity decline with adequate

precision. Therefore, this study measured this upper limit as a function of frequency and

sound level. It was hypothesized that the upper limit of fine-structure ITD processing

decreases with decreasing level with a slope near 100 dB/octave, suggesting it is a

consequence of peripheral auditory filtering, the low-frequency edge of the cochlear

excitation pattern. Through the confirmation of this hypothesis, we have shown that these

data are best explained by the initial peripheral encoding, and that fine-structure ITD is

conveyed through responses of a single dominant channel tuned near 700 Hz,

contradicting the classic formulation of the binaural display.

METHODS

Listeners and Equipment

Sixteen young to middle-aged (mean=30.1 years, range=20-51 yrs) normal-

hearing listeners (10 female) were tested in this study. Hearing thresholds were measured

at octave frequencies from 0.25-8 kHz. Hearing thresholds were ≤20 dB hearing level

(HL) for all listeners except C1, who had slightly higher thresholds ≥6 kHz. Interaural

asymmetry in hearing thresholds was ≤10 dB except it was 15 dB at 1000 Hz for listener

M5. Data from the authors (listeners M1, B1, B2, and C1) were included.

The testing was done at three locations (Maryland, Nebraska, and Colorado),

three to seven listeners at each location. Each location used the same testing software and

type of circumaural headphones (HD280 Pro, Sennheiser; Hannover, Germany). Stimuli

were generated and the experiment was conducted on a personal computer using MATLAB

(the Mathworks; Natick, MA). Procedures were reviewed and approved by the University

of Maryland, Boys Town National Research Hospital in Nebraska, and the University of

Colorado School of Medicine Multiple Institutional Review Boards for use of human

subjects.

In Maryland, testing was performed in a double-walled sound booth (IAC; North

Aurora, IL). Stimuli were presented to listeners via an external sound card (Sound Blaster

PLAY! 3, Creative Labs; Milpitas, California). In Nebraska, testing was performed in a

double-walled electromagnetically shielded sound booth (ETS-Lindgren; Cedar Park,

TX). Stimuli were presented to listeners via USB audio interface (RME Fireface UFX;

Haimhausen, Germany). In Colorado, testing was performed in a single-walled custom-

built sound booth. Stimuli were presented to listeners via an external digital-to-analog

converter (Schitt Modi, Schitt Audio; Newhall, CA) and headphone amplifier (Schitt

Magni 3+, Schitt Audio; Newhall, CA).

Stimuli

The stimuli were pure tones that were 250 ms in duration, with frequencies of

900-1500 Hz in 100-Hz steps. For audiometric threshold measurements, tones were

presented diotically. For ITD discrimination testing, tones started with the left channel in

sine (0°) phase and the right channel had the same phase or a phase that yielded ±167-µs

ITDs. Then a diotic raised-cosine temporal ramp applied that had a 100-ms rise-fall time.

In other words, ITD was applied in only the temporal fine structure. The tone amplitude

was 10-, 20-, 30-, and 50-dB SL.

Procedure

<u>Pure-Tone Audiometric Threshold Measurements</u>

Pure tones were presented diotically. An experimenter controlled the timing of

presentation and level of the stimulus by using buttons that could adjust the level by 0,

±1, ±2, or ±6 dB. Listeners indicated when they heard a tone. Experimenters adjusted the

sound level above and below the level that produced threshold (transition from response

to no response) at least twice to determine a final threshold level (TL), which defines 0

dB SL, at each test frequency. The frequencies were tested in increasing order. The

threshold at each frequency was tested twice for most listeners. If the two thresholds

differed by >5 dB, additional threshold levels were measured and the average of the last

two measurements were used. Across-frequency averaging was implemented to smooth

out small variations in TL during later periods of testing (listeners M6, B4, B5, B6): the

average TL at each frequency was computed as the average of levels from the target and

adjacent frequencies, rounded to the nearest integer. For example, the TL at 1200 Hz was

based on the six measurements from 1100, 1200, and 1300 Hz. Adjustments due to

averaging were small–generally, less than 2 dB; on average <1 dB over all listeners and

frequencies–and yielded comparable results to unsmoothed TLs used for other listeners.

<u>Left-right ITD Discrimination</u>

Listeners performed a two-interval forced-choice discrimination task based on the

task described by Füllgrabe and Moore (Füllgrabe and Moore, 2018). Each interval

presented a sequence of four 250-ms tone bursts with sinusoidal envelopes. In the

reference interval, all four tone bursts had zero ITD. In the target interval, the ITD

alternated twice between right and left leading ±167-µs ITDs (i.e., right-left-right-left).

This ITD magnitude was chosen because it corresponds to one-quarter of the stimulus

period at 1500 Hz, which was the highest frequency tested in this study. Hence, this ITD

should yield the maximum performance at 1500 Hz and avoids the descending portion of

the cyclical psychometric function. There was a 200-ms silent interval between the target

and reference intervals. The order of the intervals was randomized with a probability of

50%. The task of the listener was to identify which interval contained the target

alternating ITD.

The task was self-paced because listeners initiated each trial. After the stimulus

was presented, the listener indicated the target interval by pressing a button on the screen.

Pre-experiment training was performed to ensure the listener understood the task

and had no apparent problems with binaural processing. Listeners were initially presented

with 10 trials at 500 Hz and 70 dB SL. Training in 10-trial blocks continued until

performance was 100% correct. Almost all the listeners needed only the initial 10

practice trials to proceed.

For the main experiment, a method of constant stimuli was performed where all

combinations of frequency and level were presented in random order, consisting of seven

frequencies (900–1500 Hz in 100-Hz steps) and four levels (10, 20, 30, and 50 dB SL).

Therefore, there were 112 trials per block (7 frequencies×4 level×4 trials), and each block

took ~10 minutes to complete. Testing breaks were provided between blocks as needed.

Listeners performed 60 trials/condition, which took ~3 hours. Three listeners were

provided less than 60 trials (minimum of 56 trials) for at least one condition and four

listeners were provided more than 60 trials (maximum of 83 trials) for at least one

condition because of computer or experimenter error. Correct answer feedback was

provided after each trial, which helped keep the listener attentive during testing blocks.

RESULTS

The upper limit of fine-structure ITD sensitivity decreases from 1400 to

900 Hz with decreasing sound level

Individual ITD discrimination data are shown in Fig. 2 for all 16 normal-hearing

human listeners. The average performance across all tested conditions is reported in each

panel. While there is variability in the overall performance, the patterns in the data are

consistent across listeners and testing sites. Two listeners (M6 and B3) had great

difficulty with this task, with an average performance <60%. These two listeners were

removed from subsequent group analyses. For all other listeners, ITD discrimination

performance decreased systematically with increasing frequency and decreasing sound

level.

236   (Figure 2 about here)

The average ITD discrimination data are shown in Fig. 3(A) for 14 listeners. A

three-way repeated-measures analysis of variance was performed on ITD discrimination

performance transformed to rationalized arcsine units (Studebaker, 1985) with factors

frequency (7 levels: 900-1500 Hz), level (4 levels: 10, 20, 30, 50 dB SL), and testing

location (3 levels: Maryland, Nebraska, Colorado). The Greenhouse-Geisser correction

was used to address sphericity assumption violations. There were significant effects of

frequency [$F(2.8,5.6)=73.7$, $p<0.0001$, $\eta_p^2=0.87$] and level [$F(1.6,3.2)=99.4$, $p<0.0001$,

$\eta_p^2=0.90$]. There was a significant frequency×level interaction [$F(4.4,8.8)=13.9$,

$p<0.0001$, $\eta_p^2=0.56$]. The effect of testing location was not significant [$F(2,11)=0.265$,

p=0.772, η_p^2=0.05], and there were no significant interactions with testing location

(p>0.05 for all).

250   (Figure 3 about here)

The upper limit of fine-structure ITD processing (defined as 75% correct ITD

discrimination performance) was found for each presentation level and for each listener

by fitting the data with a logistic regression (Wichmann and Hill, 2001). The frequency

boundaries are shown in Fig. 3(B). These data generally agree with others that show that

the upper limit of fine-structure ITD processing is near 1400 Hz for sound levels above

50 dB SPL.(Klumpp and Eady, 1956; Zwislocki and Feldman, 1956; Brughera et al.,

2013; Klug and Dietz, 2022) Across listeners, the frequency that yielded 75% correct

ITD discrimination was 1264.8±95.4 Hz (range=1168–1483) for 50 dB SL tones. For

better comparison to past studies estimating the upper frequency boundary at higher

levels, the data in Fig. 3(B) were fit by a three-parameter exponential rise to maximum

function. The best fitting equation (r=0.74, p<0.0001) was $y = 775.9 + 587.6 \times (1 -$

$e^{-0.039x})$, where y is the frequency boundary and x is the sensation level. Evaluating this

function at 70 dB SL yielded an estimated upper frequency boundary of 1326 Hz with a

95% confidence interval from 1212 to 1437 Hz, the latter which encompasses the upper

frequency boundary measured in other studies (Klumpp and Eady, 1956; Zwislocki and

Feldman, 1956; Brughera et al., 2013; Klug and Dietz, 2022).

Any other small discrepancies in the upper limit of fine-structure ITD processing

between the current study and others can be explained by methodological differences. For

example, our stimuli had slow diotic ramps minimizing contributions from onset ITD

(Stecker and Bibee, 2014). We also tested more listeners than previous studies, and thus

may have included more listeners that were not operating at a point near the absolute

limits of human binaural processing, including two that were middle aged (Ross et al.,

2007; Füllgrabe and Moore, 2018). Similarly, Klug and Dietz (Klug and Dietz, 2022) and

Best and Swaminathan (Best and Swaminathan, 2019) tested a relatively large number of

normal-hearing listeners (n=9), and reported relatively larger ITD thresholds compared to

some studies with relatively smaller (potentially more selective) samples. It may also be

that more extensive training would improve ITD discrimination performance to the levels

of the best listeners in this study (Wright and Fitzgerald, 2001), including the two who

had <60% total correct responses and were omitted from the average data and slope

calculations (described below).

These data also agree with other studies that show declines in ITD discrimination

performance with decreasing sound level (Zwislocki and Feldman, 1956; Dietz et al.,

2013; Best and Swaminathan, 2019). This decrease in performance with decreasing level

causes the 75% correct performance point to shift from about 1400 to 900 Hz [Fig. 3(B)].

It is notable that changing the stimulus level from 50 to 30 SL produces a marked change

in the upper limit given that both stimuli are clearly audible; this result is difficult to

reconcile with a phase locking explanation, which reaches a maximum within ~20 dB of

neural threshold (Palmer and Russell, 1986). Hence, it is important to account for the

stimulus sound level when considering the upper limit of fine-structure ITD processing.

292 **The rate of fine-structure ITD sensitivity decline is 90 dB/octave, best**

293 **explained by peripheral cochlear filtering**

A linear fit between the sound level (in dB SL) and the frequency boundary (in

octaves relative to 1000 Hz) determined the slope of the ITD performance change. The

10 dB SL point was omitted from the calculation for 2 of the 14 listeners (M3 and C2)

because they did not have an estimate of the frequency boundary at 75% correct (i.e.,

they were guessing in this condition). The resulting fit slopes are shown in Fig. 3(C). The

median slope was 90.5 dB/octave (range=40.7–244.6). The linear fits explained a median

of 88% in the variance of the data points (range=74–99.8).

The most important addition to our knowledge that results from this study is that

the slope of ITD discrimination performance decline was measured to be 90 dB/octave

[Fig. 3(C)]. Such a steep slope of decline limits the possible explanations for the

physiological mechanisms that are involved in the upper limit of fine-structure ITD

processing. For example, Klug *et al.* showed that phase locking in the auditory nerve

across animal models declines at approximately 12 dB/octave (Klug et al., 2023).

Therefore, the decline in phase locking by itself cannot account for these data because the

slopes are so different. In contrast, one well-known stage of the auditory system that does

have such a steep slope is the low-frequency edge of the cochlear excitation pattern,

which is approximately 100 dB/octave near 1000 Hz (Oxenham and Shera, 2003;

Whiteford et al., 2020).

DISCUSSION

The upper limit of human fine-structure ITD processing was determined by perceptual ITD discrimination measurements that sampled frequency and sound level with a high resolution. It was found that ITD discrimination sensitivity decreases with decreasing level with a slope of 92 dB/octave. Such a steep slope suggests it is a consequence of peripheral auditory filtering, the low-frequency edge of the cochlear excitation pattern, rather than the decay in phase-locking at the level of the auditory nerve.

If the peripheral cochlear filtering interpretation of these data is correct, it has a further important corollary. It suggests that ITD sensitivity for stimulus frequencies between 1000-1500 Hz are primarily driven by lower-frequency neurons, such as those tuned between 500-1000 Hz–in other words, the region where the best ITD sensitivity is observed (Klumpp and Eady, 1956) and location of the ITD frequency dominant region for ITD (Fig. 1) (Folkerts and Stecker, 2022). There could be a narrow band of neurons near 700 Hz in humans that is responsible for conveying fine-structure ITD, which in turn yields the exquisite sensitivity to fine-structure ITDs and carries most of the localization weight for broadband stimuli. Indeed, examination of the functional form of ITD sensitivity as a function of frequency [see Fig. 9 in Klug and Dietz (Klug and Dietz, 2022)] resembles the neural response area of a high level tone (i.e., a shallow low-frequency portion, a minimum at 700 Hz, a sharp high-frequency portion; the inverse of the excitation patterns shown in Fig. 1), which would suggest the possibility of a single dominant channel for fine-structure ITD processing. To the extent that neurons tuned to 1000-1500 Hz contribute to fine-structure ITD sensitivity, they are clearly less important

than those between 500-1000 Hz because the observed transition slope does not extend

near the high-frequency edge of their tuning, which would be 2 kHz or higher. They may,

in fact, not contribute at all. In other words, the dominant region neurons are highly

weighted even for pure tones.

Future behavioral and physiological experiments that examine ITD sensitivity as a

function of frequency and level are required to better understand the properties of the

neurons that convey fine-structure ITD information. Such experiments include animal

studies in mammalian models to determine if they have a single dominant fine-structure

ITD channel and its location in frequency. For example, primates may have a dominant

channel near the same frequency region as humans but in animals with smaller heads like

cats, ferrets, and chinchillas, it could be higher, if it exists at all. (Verschooten et al.,

2019)

The proposed "dominant channel theory," having only a single narrow band of

ITD sensitive neurons near 700 Hz, is starkly different than the classic binaural display

proposed by Jeffress (Jeffress, 1948; Stern et al., 1988; Stern et al., 2019), which consists

of a matrix of frequency- and ITD-tuned neurons. Such a reimagining of human ITD

processing overlaps with past discussions about mammalian vs avian binaural-processing

models, the distribution and length of neural delay lines, and how the binaural system

processes physiologically plausible and implausible ITDs (Thompson et al., 2006; Grothe

et al., 2010; Stern et al., 2019; Yin et al., 2019; Litovsky et al., 2021). This dominant

channel theory can be formulated to be consistent with the idea that the binaural system

evolved in a manner to emphasize ecologically valid range of ITDs that provide

unambiguous location information(Hartmann and Macaulay, 2014), helping to reconcile

the discrepant interpretation of data from several past binaural-hearing studies.

In summary, the rapid 90 dB/octave rate of decline in fine-structure ITD

sensitivity is best explained by initial peripheral cochlear filtering. This suggests that

listeners are performing off-frequency listening to a single dominant channel tuned near

700 Hz. Such a model contradicts the classic binaural display that utilizes a matrix of

neurons that yield maximum firing rates at their best frequency and best interaural time

difference.

ACKNOWLEDGMENTS

We thank Taylor Beinke for assistance with data collection.

REFERENCES

Best V, Swaminathan J (2019) Revisiting the detection of interaural time differences in

listeners with hearing loss. J Acoust Soc Am 145:EL508-EL513.

Blanks DA, Roberts JM, Buss E, Hall JW, Fitzpatrick DC (2007) Neural and behavioral

sensitivity to interaural time differences using amplitude modulated tones with

mismatched carrier frequencies. J Assoc Res Otolaryngol 8:393-408.

Brughera A, Dunai L, Hartmann WM (2013) Human interaural time difference thresholds

for sine tones: The high-frequency limit. J Acoust Soc Am 133:2839-2855.

Dietz M, Bernstein LR, Trahiotis C, Ewert SD, Hohmann V (2013) The effect of overall

level on sensitivity to interaural differences of time and level at high frequencies. J

Acoust Soc Am 134:494-502.

Folkerts ML, Stecker GC (2022) Spectral weighting functions for lateralization and

localization of complex sound. J Acoust Soc Am 151:3409-3425.

Füllgrabe C, Moore BCJ (2018) The association between the processing of binaural

temporal-fine-structure information and audiometric threshold and age: A meta-

analysis. Trends Hear 22:2331216518797259.

Goupell MJ, Bilokon AV (2022) Support for the frequency dominance region explanation

of lateralization of larger than physiologically possible interaural time differences. In:

International Symposium on Hearing, pp 1-19. Lyon, France.

Grothe B, Pecka M, McAlpine D (2010) Mechanisms of sound localization in mammals.

Physiol Rev 90:983-1012.

Hartmann WM (2021) Localization and Lateralization of Sound. In: Binaural Hearing

(Litovsky RY, Goupell MJ, Fay RR, Popper AN, eds), pp 9-45. Cham, Switzerland:

Springer International Publishing.

Hartmann WM, Macaulay EJ (2014) Anatomical limits on interaural time differences: An

ecological perspective. Front Neurosci 8:34.

Ihlefeld A, Alamatsaz N, Shapley RM (2019) Population rate-coding predicts correctly

that human sound localization depends on sound intensity. Elife 8.

Jeffress LA (1948) A place theory of sound localization. J Comp Physiol Psychol 41:35-

39.

Klug J, Dietz M (2022) Frequency dependence of sensitivity to interaural phase

differences in pure tones. J Acoust Soc Am 152:3130-3141.

Klug J, Encke J, Dietz M (2023) Characterization of the decline in auditory nerve phase

locking at high frequencies. JASA Express Lett 3:074403.

Klumpp RG, Eady HR (1956) Some measurements of interaural time difference

thresholds. J Acoust Soc Am 28:859-860.

Litovsky RY, Goupell MJ, Fay RR, Popper AN (2021) Binaural Hearing. Cham

Switzerland: Springer International Publishing.

Macpherson EA, Middlebrooks JC (2002) Listener weighting of cues for lateral angle:

The duplex theory of sound localization revisited. J Acoust Soc Am 111:2219-2236.

Moore BC, Glasberg BR (1983) Suggested formulae for calculating auditory-filter

bandwidths and excitation patterns. J Acoust Soc Am 74:750-753.

Müller M (1990) Quantitative comparison of frequency representation in the auditory

brainstem nuclei of the gerbil, Pachyuromys duprasi. Exp Brain Res 81:140-149.

Oxenham AJ, Shera CA (2003) Estimates of human cochlear tuning at low levels using

forward and simultaneous masking. J Assoc Res Otolaryngol 4:541-554.

Palmer AR, Russell IJ (1986) Phase-locking in the cochlear nerve of the guinea-pig and

its relation to the receptor potential of inner hair-cells. Hear Res 24:1-15.

Ross B, Fujioka T, Tremblay KL, Picton TW (2007) Aging in binaural hearing begins in

mid-life: Evidence from cortical auditory-evoked responses to changes in interaural

phase. J Neurosci 27:11172-11178.

Shackleton TM, Meddis R, Hewitt MJ (1992) Across frequency integration in a model of

lateralization. J Acoust Soc Am 91:2276-2279.

Stecker GC, Bibee JM (2014) Nonuniform temporal weighting of interaural time

differences in 500 Hz tones. J Acoust Soc Am 135:3541-3547.

Stern RM, Zeiberg AS, Trahiotis C (1988) Lateralization of complex binaural stimuli: A

weighted-image model. J Acoust Soc Am 84:156-165.

Stern RM, Colburn HS, Bernstein LR, Trahiotis C (2019) The fMRI data of Thompson et

al. (2006) do not constrain how the human midbrain represents interaural time delay.

J Assoc Res Otolaryngol 20:305-311.

Studebaker GA (1985) A 'rationalized' arcsine transform. J Speech Hear Res 28:455-462.

Thompson SK, von Kriegstein K, Deane-Pratt A, Marquardt T, Deichmann R, Griffiths

TD, McAlpine D (2006) Representation of interaural time delay in the human

auditory midbrain. Nat Neurosci 9:1096-1098.

Tollin DJ, Henning GB (1999) Some aspects of the lateralization of echoed sound in

man. II. The role of the stimulus spectrum. J Acoust Soc Am 105:838-849.

Verschooten E, Shamma S, Oxenham AJ, Moore BCJ, Joris PX, Heinz MG, Plack CJ

(2019) The upper frequency limit for the use of phase locking to code temporal fine

structure in humans: A compilation of viewpoints. Hear Res 377:109-121.

Whiteford KL, Kreft HA, Oxenham AJ (2020) The role of cochlear place coding in the

perception of frequency modulation. Elife 9.

Wichmann FA, Hill NJ (2001) The psychometric function: II. Bootstrap-based

confidence intervals and sampling. Percept Psychophys 63:1314-1329.

Wightman FL, Kistler DJ (1992) The dominant role of low-frequency interaural time

differences in sound localization. J Acoust Soc Am 91:1648-1661.

Wright BA, Fitzgerald MB (2001) Different patterns of human discrimination learning

for two interaural cues to sound-source location. Proc Natl Acad Sci USA 98:12307-

12312.

Yin TCT, Smith PH, Joris PX (2019) Neural mechanisms of binaural processing in the

auditory brainstem. Compr Physiol 9:1503-1575.

Zwislocki J, Feldman RS (1956) Just noticeable differences in dichotic phase. J Acoust

Soc Am 28:860-864.

Figures and Captions:

Fig. 1: Illustration of the transformation of input acoustic tones into their effective neural

spectral representations (i.e., their excitation patterns, which have a steep low-frequency

slope and shallow high-frequency slope) and their relationship to the experimental

hypothesis. If fine-structure ITD is primarily conveyed by neurons in the ITD frequency

dominant region near 700 Hz, decreasing the stimulus level will decrease the highest

frequency that demonstrates fine-structure ITD sensitivity at approximately the same

slope as the low-frequency edge of the cochlear excitation pattern, about 100 dB/octave.

Fig. 2: Percent correct as a function of frequency and level (in dB SL) for 16 listeners.

Error bars show 95% confidence intervals. The average percent correct over all

conditions is reported in each panel.

Fig. 3: (A) Percent correct as a function of frequency and sensation level for 14 listeners. Error bars represent ±1 standard error. Some conditions had error bars that were smaller than the symbol. (B) Frequency boundaries that yield 75% correct ITD discrimination performance. Small closed symbols show individual data. Large open symbols show the data averaged over listeners. The error bars represent ±1 standard deviation. (C) Linear slope estimates between sound level (in dB SL) and frequency (in octaves). Small closed symbols show the slope for the individual listeners. The box length represents the interquartile range, and the median is shown within the box. Whiskers extend to 10[th] and 90[th] percentiles.