Analytical strength-duration curve for spiking response of the LIF neuron to an alpha-function shaped excitatory current pulse

Alexander Paraskevov

Institute of Science and Technology Austria, 3400 Klosterneuburg, Austria

Institute for Information Transmission Problems, 127051 Moscow, Russia

Abstract

Whether or not the neuron emits a spike in response to stimulation by an excitatory current impulse is determined by a strength-duration curve (SDC) for the impulse parameters. Excitatory neurons affect the others through impulses of excitatory postsynaptic current. A simple yet plausible approximation for the time course of such an impulse is the alpha function, with linear rise at the start and exponential decay at the end. However, an exact analytical SDC for this case is unknown even for the leaky integrate-and-fire (LIF) neuron, the simplest spiking neuron model used in practice. This paper contains the solution: the exact analytical SDC has been found for the spiking response of the LIF neuron stimulated by an excitatory current pulse in the form of alpha function. In addition, we have derived general SDC equations for an arbitrary shape of the stimulating pulse. For comparison, we have also re-derived SDCs in a unified way for (i) a standard rectangular pulse, (ii) ascending ramp pulse, and (iii) instantly rising and exponentially decaying pulse. In the limit of no leakage, for all considered cases the SDC is reduced to the classical hyperbola. The obtained SDC formulas can be of use for theoretical and computational neuroscience studies, as well as for patch-clamp experiments in neuronal electrophysiology.

Keywords: Integrate-and-fire neuron, Spiking response, Excitatory current impulse, Alpha function, Strength-duration curve, Rheobase

1. Introduction

For modeling biological neuronal networks, an adequate choice of the amplitude and duration values for impulses of excitatory postsynaptic current (EPSC) is crucial [1]. No less crucial is the impulse waveform. The same can be said for the stimulating electrical impulses in precision neuroprosthetics [2–4]. Whether or not the neuron emits a spike in response to an excitatory current impulse (synaptic or externally-stimulated via sealed microelectrode in the current-clamp mode of whole-cell patch-clamp technique) is determined by the so-called strength-duration curve (SDC). SDC is the dependence of minimal impulse amplitude, which is sufficient for spiking response, on either the impulse duration or, as in our case, the impulse rising time, provided that the neuron's initial state is unaltered.

Leaky Integrate-and-Fire (LIF) neuron is the simplest dynamic model of a spiking neuron that is widely used in theoretical studies and large-scale simulations of spiking activity in biological neuronal networks. The analytical SDC for the LIF neuron stimulated by rectangular current impulse was derived by Lapicque just after the seminal LIF model definition [5].

However, the rectangular impulse is poorly suitable both for modeling an EPSC impulse and for artificial pulse stimulation of biological neurons in neuroprosthetics [2]. In turn, the alpha-function, with the linear rise at the start and exponential decay at the end (see the inset on the right graph in Fig. 1), is a simple yet plausible approximation for the time course of an EPSC impulse. Based on relatively recent advances in special mathematical functions, we have analytically derived a SDC for the LIF neuron stimulated by a single alpha-function-shaped current impulse.

We have shown that for the above case the exact analytical SDC (Fig. 1, right graph) can be expressed through the branches of the special Lambert W function [6, 7] (Fig. 1, left graph) that gives the solution $y = W(x)$ of transcendental equation [7] $y \exp(y) = x$. The SDC depends on two compound parameters of the LIF model: minimal 'critical' (or 'rheobase') direct current I_c for periodic spike generation and the 'membrane' relaxation time constant τ_m. Notably, these are standardly accessible in patch-clamp experiments. We assume that the obtained result can be used for calibrating neuroprosthetic systems and tuning the parameters of network models with LIF neurons. In addition, these can be used in theoretical studies of synaptic plasticity, e.g., for analyzing the influence of spike-timing-

Figure 1. Left graph: Lambert function $W(x)$ with its two branches highlighted and standardly denoted. Both branches are essential for the SDC computation. Right graph: Analytically derived SDC (blue curve) for the LIF neuron stimulated by a single EPSC impulse with the alpha function waveform (see the inset). Numerically calculated SDC matches accurately the analytical one. $I_c = 150$ pA and $\tau_m = 20$ ms are constant parameters of the LIF neuron model, see Sec. 2.

dependent plasticity (STDP) on integrative properties of the LIF neuron. In particular, the multiplicative version of the classical pair-based STDP rule [8] explicitly contains a maximal synaptic weight; it is also implicitly introduced in the additive version. A difficult question for a modeler of biological neuronal networks is that from what considerations one should take the maximal weight value, implying that the synaptic weight is either the EPSC amplitude or EPSC upward slope. One can suggest determining the maximal weight value from the analytical SDC for the EPSC impulse, provided that its typical duration is known. Indeed, any higher weight value is hardly meaningful while considering integrative excitation of the postsynaptic neuron: having such a 'strong' incoming synapse activated, the neuron will generate a spike regardless of other incoming excitatory signals, provided that inhibitory signals do not come for a while.

2. Standard LIF neuron model

Subthreshold dynamics of transmembrane potential V for the LIF neuron is described by equation

$$\tau_m dV/dt = V_{rest} - V(t) + I(t)R_m, \tag{1}$$

where V_{rest} is the neuron's resting potential, $\tau_m = C_m R_m$ is the characteristic time for relaxation of $V(t)$ to V_{rest}, C_m and R_m are the capacity and resistance of the neuron's membrane, $I(t)$ is the total incoming synaptic current, which, as a function of time t, depends on the choice of the synapse dynamic model and the number of incoming synapses.

When the transmembrane potential reaches a threshold value $V_{th} = V(t_{sp})$, it is supposed that the neuron emits a spike, then V abruptly drops to V_{rest} and retains this value during the absolute refractory period τ_{ref},

$$V(t) \geq V_{th} \rightarrow spike, \ V(t + t') = V_{rest}, \ 0 \leq t' \leq \tau_{ref}, \tag{2}$$

and afterwards the potential dynamics is again described by Eq. (1). The result of the LIF neuron dynamics is a sequence of spike generation moments $\{t_{sp}^{(1)}, t_{sp}^{(2)}, \ldots\}$.

If the total incoming current in Eq. (1) is a positive constant, $I(t) = I > 0$, and exceeds 'rheobase' or 'critical' value $I_c = (V_{th} - V_{rest})/R_m$, then the LIF neuron emits spikes regularly, with period

$$T = \tau_{ref} + \tau_m \ln[1/(1 - I_c/I)]. \tag{3}$$

Finally, the numerical values of parameters for the LIF neuron are as follows: $\tau_m = 20$ ms, $C_m = 200$ pF, $R_m = 0.1$ GΩ, $V_{rest} = -65$ mV, $V_{th} = -50$ mV. These give the critical current value $I_c = 150$ pA. A typical value for the refractory period τ_{ref} is 2 or 3 ms, though it will not be used further, as we study a single spiking response.

In addition, to make an accurate comparison with the earlier results, where the strength-duration curve was fitted by a hyperbola, it is also worth outlining the Perfect Integrate-and-Fire (PIF) neuron, which has no leakage current due to formally infinite resistance R_m. The PIF neuron dynamics is described by equation

$$dQ/dt = C_m dV/dt = I(t), \tag{4}$$

Here $Q = C_m(V - V_{rest})$ is excessive transmembrane electric charge, and all other notations are the same as those for the LIF neuron. Instead of the critical current I_c, which is formally zero for the PIF neuron, it has the critical charge value $Q_c = C_m(V_{th} - V_{rest})$ at which the PIF neuron emits a spike. The after-spike dynamics for the PIF model is the same as for the LIF one, see Eq. (2). We used the same numerical values of corresponding parameters as for the LIF neuron, resulting in the critical charge value $Q_c = 3$ pC.

At last, suppose we have a formula derived for the LIF neuron, e.g., the period T of regular spiking, Eq. (3). How to transform the formula for describing the PIF neuron case? To this end, one should concurrently turn τ_m to infinity and I_c to zero such that their product $I_c\tau_m = Q_c$ would hold a finite non-zero value, which is the critical charge. Following this way, the spiking period T for the PIF neuron stimulated by constant depolarising current $I > 0$ is given by $T = \tau_{ref} + Q_c/I$.

3. General equations for the strength-duration curve (SDC)

By its definition, the SDC is a dependence of minimal spike-triggering amplitude I_a of the stimulation current impulse on its characteristic duration τ_a. Assuming that the neuron is initially at rest, the corresponding evoked impulse of the membrane potential must have the amplitude equal to V_{th}. In other words, the impulse maximum is reached at $V(t_{sp}) = V_{th}$, giving the second condition for SDC: $dV/dt = 0$ at $t = t_{sp}$. Together, one gets the system of two algebraic equations

$$
\begin{cases}
V(t = t_{sp}) = V_{th}, \\
\dfrac{dV}{dt}(t = t_{sp}) = 0.
\end{cases}
\tag{5}
$$

The solutions of the system are I_a and the moment t_{sp} of spike generation, as functions of τ_a. The SDC is function $I_a(\tau_a)$.

For the LIF neuron, a straightforward integration of Eq. (1) with arbitrary current $I(t)$ and the initial condition $V(t = t_0) = V_0$ results in

$$
V(t) = V_{rest} + \exp(-\frac{(t - t_0)}{\tau_m})[(V_0 - V_{rest}) + \frac{R_m}{\tau_m}\int_{t_0}^{t} \exp(\frac{(t' - t_0)}{\tau_m})I(t')dt'],
\tag{6}
$$

where $t_0 \leq t \leq t_{sp}$ and t_{sp} is the moment of the first spike since t_0.

In what follows, we use $t_0 = 0$ and $V_0 = V_{rest}$. Assuming $I(t)$ being a stimulating impulse of amplitude I_a and characteristic duration τ_a, the system (5) is then as follows

$$
\begin{cases}
V_{th} = V_{rest} + \dfrac{R_m}{\tau_m} \exp(-\dfrac{t}{\tau_m})\int_{0}^{t_{sp}} \exp(\dfrac{t'}{\tau_m})I(t')dt', \\
0 = V_{rest} - V_{th} + I(t_{sp})R_m.
\end{cases}
\tag{7}
$$

Using the standard notation for the critical current $I_c = (V_{th} - V_{rest})/R_m$ and denoting

$x = t_{sp}/\tau_m$, we get

$$\begin{cases} I_c = \exp(-x) \int_0^x \exp(y) I(y\tau_m) dy, \\ \\ I_c = I(x\tau_m), \end{cases} \quad (8)$$

where x is the dimensionless moment of the first spike after the stimulation begins.

4. SDC for the alpha-function shaped pulse

Let us consider that the stimulation pulse $I(t)$ has a shape determined by the alpha function,

$$I(t) = I_a \frac{(t - t_0)}{\tau_a} \exp(1 - (t - t_0)/\tau_a), \ t \geq t_0, \quad (9)$$

which is the solution of equations (where $\delta(t - t_0)$ is the Dirac delta function)

$$\begin{cases} dI/dt = S - I/\tau_a, \\ \tau_a dS/dt = -S + I_a \delta(t - t_0), \end{cases} \quad (10)$$

at $I(t \leq t_0) = 0$ and $S(t < t_0) = 0$. Setting $t_0 = 0$, we get Eqs. (8) in the form

$$\begin{cases} I_c = I_a \dfrac{\tau_m}{\tau_a} \exp(1 - x) \int_0^x y \exp(y(1 - \tau_m/\tau_a)) dy, \\ \\ I_c = I_a x \dfrac{\tau_m}{\tau_a} \exp(1 - x\tau_m/\tau_a). \end{cases} \quad (11)$$

Denoting $k = 1 - \tau_m/\tau_a$ and, for $k \neq 0$, integrating

$$\int_0^x y \exp(ky) dy = \frac{1}{k^2} \left[\exp(kx)(kx - 1) + 1 \right], \quad (12)$$

we get

$$\begin{cases} I_c = I_a \dfrac{(1 - k)}{k^2} \exp(1 - x) \left[\exp(kx)(kx - 1) + 1 \right], \\ \\ I_c = I_a x(1 - k) \exp(1 - x(1 - k)), \end{cases} \quad (13)$$

from where, combining both equations, it follows that

$$x(k^2 - k) + 1 = \exp(-kx), \quad (14)$$

resulting in

$$(kx - 1/(1 - k)) \exp(kx - 1/(1 - k)) = -\exp(-1/(1 - k) - \ln(1 - k)). \quad (15)$$

The latter equation can be directly solved using the Lambert W function definition: $y = W(b)$ is the solution of $y \exp(y) = b$, respecting the W function branches [6, 7]:

$$kx - 1/(1 - k) = W(-\exp(-1/(1 - k) - \ln(1 - k))), \tag{16}$$

$$x = \frac{1}{k(1 - k)} + \frac{1}{k}W\left(\frac{\exp(1/(k - 1))}{k - 1}\right). \tag{17}$$

In turn, from the 2nd equation of system (13) one straightforwardly gets

$$\frac{I_c}{I_a \exp(1)} = x(1 - k) \exp(-x(1 - k)), \tag{18}$$

$$x = -\frac{1}{1 - k}W\left(-\frac{I_c}{I_a \exp(1)}\right). \tag{19}$$

Comparing solutions (17) and (19), we get

$$W\left(-\frac{I_c}{I_a \exp(1)}\right) = -\frac{1}{k} - \frac{1 - k}{k}W\left(\frac{\exp(1/(k - 1))}{k - 1}\right) \equiv -K, \tag{20}$$

and, again using the definition of Lambert W function, only inside out now, we finally get

$$I_a = I_c\frac{\exp(K - 1)}{K}, \tag{21}$$

where

$$K = \frac{1}{k} + \frac{1 - k}{k}W\left(\frac{\exp(1/(k - 1))}{k - 1}\right) = \frac{\tau_a + \tau_m W\left(-\frac{\tau_a}{\tau_m}\exp\left(-\frac{\tau_a}{\tau_m}\right)\right)}{\tau_a - \tau_m}. \tag{22}$$

From Eq. (17) it follows that $K = t_{sp}/\tau_a$, i.e., K is simply the 1st spike time, in units of τ_a.

If $k = 0$, i.e. $\tau_a = \tau_m$, system (11) is reduced to

$$\begin{cases} I_c = I_a \exp(1 - x)\displaystyle\int_0^x ydy = I_a \exp(1 - x)\frac{1}{2}x^2, \\ I_c = I_a x \exp(1 - x), \end{cases} \tag{23}$$

from where $x = 2$ and $I_a = I_c/(x \exp(1 - x)) = I_c \exp(1)/2$. Notably, this result can be obtained from formula (21) by setting $K = 2$ there.

Taking into account the W function branches, the final formula for SDC is given by

$$I_a = I_c\frac{\exp(K - 1)}{K}, \tag{24}$$

where K is the following function of τ_a,

$$K = t_{sp}/\tau_a = \begin{cases} \dfrac{\tau_a + \tau_m W_{-1}\left(-\frac{\tau_a}{\tau_m}\exp\left(-\frac{\tau_a}{\tau_m}\right)\right)}{\tau_a - \tau_m}, & \tau_a < \tau_m, \\[3mm] \dfrac{\tau_a + \tau_m W_0\left(-\frac{\tau_a}{\tau_m}\exp\left(-\frac{\tau_a}{\tau_m}\right)\right)}{\tau_a - \tau_m}, & \tau_a > \tau_m, \\[3mm] 2, & \tau_a = \tau_m. \end{cases} \tag{25}$$

Here $W_{-1}(...)$ and $W_0(...)$ are the lower and upper branches of the Lambert W function (see Fig. 1, left graph), respectively.

Notably, at $\tau_a \to +\infty$ one gets $K \to 1$ in Eq. (25) and, according to Eq. (24),

$$I_a(\tau_a \to +\infty) = I_c \qquad (26)$$

that is a general limiting case for the SDC, regardless of a specific shape of the stimulation pulse.

For the PIF neuron case, the corresponding SDC formula can be directly obtained from Eqs. (24) and (25) by turning there $\tau_m \to +\infty$ and $I_c \to 0$, with $I_c\tau_m = Q_c$ (see details in Sec. 2). In particular, denoting $\tau_a/\tau_m = z \to 0$, from Eq. (25) we asymptotically get $K = -W_{-1}(-z\exp(-z))$, which is equivalent to $-K\exp(-K) = -z\exp(-z)$, according to the Lambert W function definition. Substituting the latter expression into Eq. (24), we get

$$I_a = I_c\frac{-\exp(-1)}{(-K)\exp(-K)} = I_c\frac{\exp(-1)}{z\exp(-z)} \to \frac{Q_c}{\tau_m}\frac{\exp(-1)}{\tau_a/\tau_m} = \frac{Q_c}{\tau_a}\exp(-1). \qquad (27)$$

This result is exact for the PIF neuron and coincides with the classic SDC fitting by a hyperbola.

5. Comparison with other pulse shapes

It seems advisable to compare the obtained SDC formula with the results for (i) a standard rectangular pulse, (ii) linearly-increasing ramp pulse, and (iii) instantly rising and exponentially decaying pulse. For the first two shapes, parameter τ_a stands for the pulse duration, and, for the latter, τ_a is the time constant of exponential decay.

1. For the rectangular pulse

$$I(t) = I_a H(t_0 + \tau_a - t)H(t - t_0), \qquad (28)$$

where $H(x)$ is the Heaviside unit-step function

$$H(x) = \begin{cases} 1, & x \geq 0, \\ 0, & x < 0, \end{cases} \qquad (29)$$

the first spike time t_{sp} for the LIF neuron (at $t_0 = 0$ and $V(t_0) = V_{rest}$) is given by Eq. (3), where $\tau_{ref} = 0$,

$$t_{sp} = \tau_m \ln[1/(1 - I_c/I_a)]. \qquad (30)$$

The spike must occur before the end of stimulating pulse, i.e. $t_{sp} \leq \tau_a$. The limiting equality $t_{sp} = \tau_a$ determines the SDC,

$$I_a = \frac{I_c}{1 - \exp(-\tau_a/\tau_m)}. \tag{31}$$

It is widely accepted that this formula was first reported by L. Lapicque in 1907 [5] (cp. [9]). Limiting cases $\tau_a \gg \tau_m$ and $\tau_a \ll \tau_m$ for Eq. (31) give $I_a \approx I_c$ and $I_a \approx I_c \tau_m/\tau_a$, respectively. For the PIF neuron, Eq. (31) is transformed to $I_a = Q_c/\tau_a$.

2. For the ramp pulse given by

$$I(t) = I_a \left(t/\tau_a\right) H(t_0 + \tau_a - t) H(t - t_0), \tag{32}$$

with the same initial conditions ($t_0 = 0$, $V(t_0) = V_{rest}$) one gets the first spike condition for the LIF neuron

$$I_a = \frac{\tau_a}{\tau_m} \frac{I_c}{\exp(-\frac{t_{sp}}{\tau_m}) + \frac{t_{sp}}{\tau_m} - 1}, \tag{33}$$

where, as previously, $t_{sp} \leq \tau_a$, and the SDC is determined by $t_{sp} = \tau_a$, resulting in

$$I_a = \frac{\tau_a}{\tau_m} \frac{I_c}{\exp(-\frac{\tau_a}{\tau_m}) + \frac{\tau_a}{\tau_m} - 1}. \tag{34}$$

Limiting cases $\tau_a \gg \tau_m$ and $\tau_a \ll \tau_m$ for Eq. (34) give $I_a \approx I_c$ and $I_a \approx 2I_c\tau_m/\tau_a$, respectively. For the PIF neuron, Eq. (34) is transformed to $I_a = 2Q_c/\tau_a$.

3. Finally, for the instantly rising and exponentially decaying pulse,

$$I(t) = I_a \exp(-(t - t_0)/\tau_a) H(t - t_0), \tag{35}$$

from Eqs. (8) we get

$$\begin{cases} I_c = I_a \exp(-x) \int\limits_0^x \exp(ky) dy, \\ I_c = I_a \exp(x(k-1)), \end{cases} \tag{36}$$

where, as before, $x = t_{sp}/\tau_m$ and $k = 1 - \tau_m/\tau_a$. If $k = 0$, the solution of Eqs. (36) is $x = 1$ and $I_a = I_c \exp(1)$. If $k \neq 0$,

$$\begin{cases} I_c = (I_a/k)[\exp(x(k-1)) - \exp(-x)], \\ I_c = I_a \exp(x(k-1)), \end{cases} \tag{37}$$

from where one gets $k = 1 - (I_c/I_a)^{k/(1-k)}$ and $I_a = I_c(1-k)^{-(1-k)/k}$. In usual notations, the SDC reads

$$I_a = \begin{cases} I_c(\tau_m/\tau_a)^{\tau_m/(\tau_m-\tau_a)}, & \tau_a \neq \tau_m, \\ I_c \exp(1), & \tau_a = \tau_m. \end{cases} \tag{38}$$

At $\tau_a \to +\infty$, taking into account that

$$\lim_{y \to 0}(y^{-y}) = 1, \tag{39}$$

where $y = \tau_m/\tau_a$, one gets the standard value $I_a(\tau_a \to +\infty) = I_c$. The case $\tau_a \ll \tau_m$ for Eq. (38) gives $I_a \approx I_c(\tau_m/\tau_a)^{1+\tau_a/\tau_m} \approx I_c\tau_m/\tau_a$. For the PIF neuron, Eq. (38) is transformed to $I_a = Q_c/\tau_a$, which is exactly the same as for the rectangular pulse case.

Summarizing, we have explicitly shown that different pulse shapes lead to significant functional differences in the SDC for the LIF neuron, however, up to a numerical factor, they are completely insignificant for the case of the PIF neuron, which has a relatively universal SDC in the form of a hyperbola. That universality can be explained as follows: for the PIF neuron the SDC comes from the condition that, for initiating a spike, the total electric charge Q_{tot} delivered by the incoming excitatory pulse, i.e.

$$Q_{tot} = \int\limits_{0}^{+\infty} I(t)dt = I_a\tau_a\eta, \tag{40}$$

where η is a numerical constant determined by the pulse shape, should be equal to the critical charge Q_c (see Sec. 2). All the above results for the SDC in the PIF neuron case follow directly from equality $Q_{tot} = Q_c$.

6. Conclusion

For the LIF neuron stimulated by an excitatory current pulse in the form of alpha function, analytical strength-duration curve (SDC) for the spiking response has been accurately found. The SDC is expressed through the Lambert W function, a well-studied and widely-implemented special function. In addition, general SDC equations for an arbitrary shape of the stimulating pulse have been obtained. For comparison, we have also re-derived in a unified way the analytical SDCs for (i) a standard rectangular pulse, (ii) ascending ramp pulse, and (iii) instantly rising and exponentially decaying pulse. In the limit of no leakage, it has been shown that for all considered cases the SDC is reduced to the classical hyperbola.

Data and code availability

The Supplementary Material for this article contains (i) the data for graphs in Figure 1 and (ii) ready-to-use MATLAB codes for reproducing the data. It is available online at `https://doi.org/10.6084/m9.figshare.24081849`.

Declaration of competing interests

The author declares no competing interests.

Acknowledgments

The author thanks T.S. Zemskova and N.D. Efimova for verifying some of the results.

---

[1] L.F. Abbott, W.G. Regehr, Synaptic computation, Nature **431**, 796-803 (2004).
https://doi.org/10.1038/nature03010

[2] M. Sahin, Y. Tie, Non-rectangular waveforms for neural stimulation with practical electrodes,
J. Neural Eng. **4**, 227-233 (2007). https://doi.org/10.1088/1741-2560/4/3/008

[3] T.J. Foutz, C.C. McIntyre, Evaluation of novel stimulus waveforms for deep brain stimulation,
J. Neural Eng. **7**, 066008 (2010). https://doi.org/10.1088/1741-2560/7/6/066008

[4] A. Wongsarnpigoon, J.P. Woock, W.M. Grill, Efficiency analysis of waveform shape for electrical
excitation of nerve fibers, IEEE Trans. Neural Syst. Rehabil. Eng. **18**, 319-328 (2010).
https://doi.org/10.1109/TNSRE.2010.2047610

[5] N. Brunel, M.C.W. van Rossum, Quantitative investigations of electrical nerve excitation treated
as polarization, Biol. Cybern. **97**, 341-349 (2007).
https://doi.org/10.1007/s00422-007-0189-6

[6] R.M. Corless et al., On the Lambert W function, Adv. Comput. Math. **5**, 329-359 (1996).
https://doi.org/10.1007/BF02124750

[7] J.P. Boyd, Solving Transcendental Equations (Society for Industrial and Applied Mathematics,
2014). https://doi.org/10.1137/1.9781611973525

[8] A. Morrison, M. Diesmann, W. Gerstner, Phenomenological models of synaptic plasticity based
on spike timing, Biol. Cybern. **98**, 459-478 (2008).
https://doi.org/10.1007/s00422-008-0233-1

[9] J.L. Hoorweg, Ueber die elektrische Nervenerregung, Pflügers Arch. **52**, 87-108 (1892).
https://doi.org/10.1007/BF01661875