Continuous Tracking using Deep Learning-based Decoding for Non-invasive Brain-Computer Interface

Dylan Forenzo#, Hao Zhu#, Jenn Shanahan, Jaehyun Lim, and Bin He*, *Fellow, IEEE*

Abstract— Brain-computer interfaces (BCI) using electroencephalography (EEG) provide a non-invasive method for users to interact with external devices without the need for muscle activation. While noninvasive BCIs have the potential to improve the lives of both healthy and motor impaired individuals, they currently have limited applications due to inconsistent performance and low degrees of freedom. In this study, we use deep-learning (DL)-based decoders for online Continuous Pursuit (CP), a complex BCI task requiring the user to track an object in 2D space. We developed a new labelling system to use CP data for supervised learning, trained DL-based decoders based on two architectures, including a newly proposed adaptation of the PointNet architecture, and evaluated the performance over several online sessions. We rigorously evaluated the DL-based decoders in a total of 28 human subjects, and found that the DL-based models improved throughout the sessions as more training data became available and significantly outperformed a traditional BCI decoder by the last session. We also performed additional experiments to test an implementation of transfer learning by pre-training models on data from other subjects, and mid-session training to reduce inter-session variability. The results from these experiments show that pre-training did not significantly improve performance, but updating the models mid-session may have some benefit. Overall, these findings support the use of DL-based decoders for improving BCI performance in complex tasks like CP, which can expand the potential applications of BCI devices and help improve the lives of both healthy individuals and motor-impaired patients.

*Index Terms—*BCI, Brain-Computer Interface, Deep Learning, Continuous Pursuit, Motor Imagery, EEG

I. INTRODUCTION

BRAIN-computer interfaces (BCIs) are devices that allow users to interact with computers or other devices by determining their intentions directly from their recorded brain signals. These fast-growing devices have the potential to help patients suffering from motor or speech disorders by allowing them to control devices such as prosthetic limbs or perform everyday tasks like sending emails or turning on lights. Successful BCIs also have the potential to improve the quality of lives of healthy individuals by allowing them to interact directly with electronics such as cell phones or computers without the need for muscle activation or speech.

The brain recording methods used for BCIs can be generally split into two main categories based on whether they require an invasive procedure or not. Invasive BCIs can often get closer to the source of the brain activity and generally offer good quality signals. Non-invasive brain recording methods such as electroencephalography (EEG) record neural signals from outside the brain and do not require any invasive procedures. Although they carry less risk, the signals from these methods can be limited in either temporal or spatial resolution compared to invasive recording techniques.

BCI applications that require the best available signal quality may be able to justify the medical procedures required for invasive BCIs, but so far invasive BCIs have only been implanted in several dozens of patients. For other applications, non-invasive BCIs provide a safer and more widely available alternative. Among non-invasive methods, EEG is particularly well suited for BCI systems due to its high temporal resolution, portability, and relatively low cost [1]. An example of an EEG-BCI setup is shown in Figure 1A. These systems have been used to control devices such as robotic arms [2]–[4], wheelchairs [5], [6], and a virtual [7], [8] or even physical quadcopter drone [9] and could one day be used to control advanced devices like lower limb prostheses [10]. Although these EEG-based BCIs have been studied for several decades [11], recent advances in hardware, software, and available computing power have opened up new possibilities for this technology.

One of the common ways to control an EEG-based BCI is the Motor Imagery (MI) paradigm. To perform MI, the user imagines the feeling or sensation of moving a body part, without executing the movement [12]. Since this method does not require muscle activation, it can be used by both healthy individuals and patients with some motor impairments [13]. In addition, previous studies have shown that MI-based BCIs may be able to help the rehabilitation process for stroke-affected patients [14]–[16].

At rest, healthy individuals have neural activity in the sensorimotor area of their cortex that oscillates at around 8-13 Hz. These oscillations are typically referred to as the mu or alpha rhythm, and are likely caused by synchronized activity of neurons in the sensorimotor area. When users perform or imagine movements, they reduce this synchronized activity and the amplitude of these oscillations decreases in what is known as Event-Related Desynchronization (ERD) [12], [17]. Changes

D. Forenzo, Hao Zhu, J. Shanahan, J Lim, and B. He* are with the Department of Biomedical Engineering at Carnegie Mellon University, Scott Hall 4N115, 5000 Forbes Avenue, Pittsburgh, PA. # D.F. and H.Z. contributed equally to the work.

Fig. 1. Schematic illustration of EEG BCI. A) A BCI setup, where the user is interacting with a computer with their intention recorded and decoded from EEG. B) An example MI control paradigm for BCI. C) Illustrations of the DT and CP BCI tasks.

in this frequency band can be detected in the EEG signal, which have also been correlated with BOLD fMRI signals [18], and used to infer when users are imaging the movement of their body parts, allowing them to control a BCI device.

Traditionally, BCI experiments have involved subjects performing MI, or another control paradigm, to produce a specified task or output. In one common setup, subjects are shown a target on one side of a screen and are asked to perform MI to move a virtual cursor to hit the target using predetermined controls (Figure 1B and 1C) [19]–[21]. These experiments, which we will refer to as Discrete Trial or DT tasks, have allowed subjects to achieve effective control over BCI systems as they are intuitive, and users only have to focus on one target outcome in each trial. However, while subjects can obtain good performance in DT tasks, these systems can often take several seconds to produce a single output and may not be suitable for real-world applications that require dynamic control.

A new type of BCI task, Continuous Pursuit (CP), has been recently explored for EEG-based BCIs [2], [22]. In this task, subjects are tasked with continuously tracking a target that randomly moves throughout a trial, instead of having only a single target movement (Figure 1C). This task is more complex than similar DT tasks, since subjects need to move their cursor in many different directions throughout a single trial to get closer to the randomly moving target, instead of only having to move in a single direction each trial. Although it is more difficult, this task requires dynamic and continuous control, bringing it closer to the requirements of real-world applications like controlling robotic devices.

One of the other major advances in BCI technology in recent years is the development of more complex decoders. In particular, deep learning (DL) models have been applied to BCI decoding with some success and have been shown to improve performance beyond the abilities of conventional decoders [23]–[29]. This technology has seen rapid growth due to successful applications in many other fields that require

complex modelling, such as computer vision and machine translation [30]. These models can extract features and model relationships from large and complex datasets, making them an excellent candidate for decoding EEG signals and particularly well suited for taking advantage of subject-specific features. The success of these decoders has been generating increasing interest from the field, and many different DL architectures and paradigms have been recently proposed for BCI decoding [23].

While DL models have the potential to improve BCI performance, there are also several challenges that need to be addressed compared to conventional decoders. Training DL models can require large amounts of training data to achieve better results [24]. In other fields that DL has been used successfully, such as image processing, training data is relatively easy to acquire or is already available in large amounts [31]. However, BCI data is costly and time consuming to collect and data can be collected with different parameters that may not be compatible such as different sampling frequencies or number of EEG channels [32], [33]. In addition, large variances in BCI features between subjects or even different sessions from the same subject can lead to overfitting problems when models are trained extensively on limited data.

Even with these challenges, the potential performance improvements offered by DL-based decoders make them a promising signal processing method for future BCI systems. In addition, methods are being developed to overcome these challenges and take advantage of the strengths of DL. Subject-specific models are commonly trained to reduce the effects of inter-subject variability. Transfer learning is a method used in other fields where DL has been applied to reduce the amount of training data needed for effective models [34]. This method, which can involve training at least part of a model on data from a different but related task, has seen increasing interest from the BCI field as DL becomes more popular [35]–[38]. With these methods, and the ability to extract features from complex data like EEG signals, DL-based decoding has the potential to improve BCI systems beyond conventional methods, especially in complex tasks like CP.

In this work, we aimed to improve BCI performance in the CP task by implementing DL-based BCI decoders for online experiments. To accomplish this, we developed a system to label CP data for supervised learning and used it to train several DL models for BCI decoding. We then evaluated decoders based on two different DL architectures in online BCI experiments over several sessions and studied the effects of increasing amounts of training data. We also evaluated additional decoders that used methods that could potentially improve performance even further such as transfer learning, to potentially reduce the amount of training data needed, and calibration, to reduce the effects of inter-session variability.

Overall, the CP task is challenging and requires both continuous and dynamic control of the BCI system. However, improving performance in this task through advanced decoding methods like DL can help bring non-invasive BCI devices closer to real-world applications like continuous control of robotic devices. In turn, these advances have the potential to

improve the lives of both healthy individuals and motor-impaired patients by offering a direct line of communication with their electronic devices.

II. MATERIALS AND METHODS

In this work, we focused on studying EEG-BCI systems based around the MI paradigm. To control the BCI system with this method, subjects were seated in front of a computer monitor and asked to imagine the feeling or sensation of moving their hands (Figure 1A). Performing hand MI causes ERD in the alpha band of the EEG signal (8-13 Hz, this is sometimes referred to as the mu rhythm, but we will use the term alpha rhythm throughout this manuscript) in the contralateral sensorimotor area, usually around either C3 or C4 [39]. This modulation of brain activity can be detected and used to infer the user's intentions using signal processing methods that we refer to as decoders. The output from these decoders can then be used to control applications such as robotic devices or, in this case, a virtual cursor.

In the CP task, subjects are asked to use MI to control a virtual cursor to move around a 2D screen. They are instructed to imagine moving their left hand to move the cursor to the left, their right hand to move it right, both hands simultaneously to go upwards, and to rest without performing any MI to move the cursor down (Figure 1B). In this paradigm, a virtual circle acts as the target, which randomly drifts around the screen area. The subjects' goal for the CP task is to move their cursor using the MI controls to track the target as close as possible (Figure 1C).

A. Subject Recruitment

This study consists of two experimental parts. In the first sub-study, we recruited 15 healthy human subjects (average age: 25.2, 14 right-handed, 8 male) for 8 sessions of CP BCI and fourteen subjects completed all 8 sessions. In the second sub-study, we recruited an additional 15 healthy human subjects (average age: 22.13, 13 right-handed, 8 male) for two BCI training sessions and 4 CP sessions. Fourteen of these subjects completed the 6 total sessions. The subjects in each sub-study were unique and no subject participated in both.

Fliers were placed around Carnegie Mellon University campus and the greater Pittsburgh area to recruit subjects. This study was approved by the Institutional Review Board at Carnegie Mellon University and each subject provided written consent to the protocol before participating. For the first sub-study, all participants were required to have completed at least two previous sessions of BCI before beginning the experiment. If a subject was recruited with less than two sessions of experience, they performed discrete trial BCI sessions to meet this requirement before beginning this study. For the second sub-study, all subjects recruited had no prior BCI experience.

B. Signal Acquisition

EEG signals were recorded using the Neuroscan Quik-Cap with 64 channels and amplified with the SynAmps 2/RT system from Compumedics Neuroscan. The electrode caps were configured in a modified version of the international 10/20 system, with the reference electrode in the center between Cz and CPZ electrodes. At the beginning of each session, all electrode impedances were reduced to below 5 kΩ. Data were collected using the Neuroscan Acquire application at a sampling rate of 1kHz, low-pass filtered under 200Hz with a notch filter at 60Hz to remove potential interference from AC electronic devices.

The BCI2000 program [40] was used to run the BCI experiments and cursor control application. Data packets were streamed from the acquisition software and processed at 40ms intervals for signal processing. The amount of data used to make a classification was different for each decoder, but all but each decoding method produced an output every 40ms to update the cursor velocity.

C. Continuous Pursuit Task

The continuous pursuit task was run using custom python scripts made for BCPy2000, part of the BCI2000 program. In this paradigm, the subject is tasked with moving their cursor, displayed on the screen as a circle, in two dimensions to track a virtual target as closely as possible. The subjects used the motor imagery paradigm described above to move the cursor, and each decoder provided two outputs: one for the horizontal axis and another for the vertical.

The virtual target in this task was also a circle with the same size as the cursor. The target was made to randomly drift around the screen in each trial by applying accelerations chosen from a normal distribution every 40 milliseconds. Following the paradigm from later experiments in the original CP study [2], we chose to not allow the cursor or target to wrap around the screen to be consistent with controlling a physical object. To deter the target from remaining on the boundary of the screen for long periods, we applied a repulsion acceleration to the target if it drifted towards the edge of the screen.

D. Traditional Decoder

To provide a baseline performance for comparing the DL models studied in this work, and to obtain the initial training data for supervised learning, subjects completed several runs of the CP task each session using a traditional online BCI decoder. For this purpose, we chose to use the AR Signal Processing module, part of the standard BCI2000 software. This class of decoder is very well established for BCI experiments [20], [41]–[44] and does not require any training data before use, allowing us to implement it for each subject's first session.

The EEG signal for the traditional decoder was processed in 160ms windows shifted every 40ms. First, a small surface Laplacian filter was applied to channels C3 and C4 by subtracting the average signal from the four surrounding electrodes. The filtered signals were then processed in an autoregressive spectral estimation model to extract a 3 Hz band from 10.5 to 13.5 Hz, the upper portion of the alpha (or mu) band. The sum of this band in C3 and C4 was then used in a linear classifier to produce an output in the horizontal (C4-C3) or vertical (-C3-C4) direction. Lastly, the most recent 30 seconds of classifier outputs were saved to estimate the mean and standard deviation of the control signal and to normalize the decoder output to around zero mean and unit standard deviation for each axis independently. This normalized signal was then used as the output to control the cursor velocity.

Fig. 2. DL architectures. A) The implementation of EEGNet used in this study. B) Our proposed PointNet architecture, adapted for BCI decoding.

E. DL Training Paradigm

Supervised learning is one of the standard paradigms for training DL models. This method requires the training data to be labelled with corresponding ground truth outputs. For BCI tasks, these labels can be things such as the desired direction when moving a cursor or device, or a selected letter in a speller. BCI tasks with only a single target in each trial, such as DT tasks, have a clear label for each trial and are well-suited for supervised learning. In contrast, the CP task does not have one clear target or direction for each trial that can be used as the label so additional steps are required to use this data for supervised learning.

The subjects' primary goal in the CP task is to move their cursor as close to the target as possible throughout the trial. Therefore, the optimal direction for them to move their cursor to reduce this distance is the vector from the cursor position to the target position (example shown in Figure 3A). Although this vector may not be the exact direction that the subject is intending to move at any point in time, it should be a close estimate if the subject is attempting the task correctly.

To calculate this label, we took the average cursor position and target position for each data window and found the vector from the cursor to the target. This vector, normalized to unit length, was then used as the label for the corresponding data window to train the DL-based decoders.

The DL models were implemented and trained using custom python scripts and the Pytorch framework, details on model training can be found in the supplemental materials. Preprocessing was different for each DL architecture and more information can be found in the corresponding sections.

In addition to designing a labelling system for the CP task, we also needed to find a way to evaluate CP performance in offline experiments. Cursor-target distance and correlation are informative metrics for evaluating online experiments, where the cursor and target positions are available, but they are more difficult to calculate in offline situations where the positions

must be simulated. In an offline task, such as evaluating one set of weights for a DL-based decoder, the outputs from the offline model could be used to simulate a cursor moving, just like in the online task. However, the EEG data is recorded from the online experiment, so when the cursor and target in the offline simulation are in different positions than they were during the online task, the subjects' intentions during the EEG recordings may not match up with the correct direction for the offline simulation.

To evaluate the DL models' performance without using the cursor-target positions, we chose to use the angle between the models' predictions and the labels as a performance metric (Figure 3A). Here, a lower average angle indicates that the prediction is closer to the true label suggesting the model will perform better in an online CP experiment. This method, which we refer to as the Average Difference Angle (ADA), does not rely on cursor or target positions, only the labels which are available from the dataset. This means that the method can be calculated offline without having to simulate a CP trial, and can be used to evaluate DL model performance during training.

F. EEGNet

Following the increasing interest in DL-based decoding for BCI, there have been a number of DL architectures developed specifically for EEG BCIs [23], [27]. Our previous work compared several of these models on two offline datasets and found that they performed similarly overall, but one model in particular, EEGNet [45], outperformed the others on one of the datasets. Due to EEGNet's performance in this offline study and well-established use, we chose to implement this model for the online CP experiments.

The details of the EEGNet architecture can be found in the original publication: [45]. Our implementation of EEGNet is shown in Figure 2A. Instead of applying a SoftMax to the output, our implementation of EEGNet performed regression and produced two numbers, one corresponding to the horizontal

Fig. 3. Study Design A) Labelling system for CP data. The vector between the cursor and target positions is used as the label for supervised learning. The angle between a model prediction and true label is used as an offline performance metric: Average Difference Angle (ADA). B) Breakdown of a CP run. Each trial lasts 60 seconds. Each run consists of five trials and lasts about 5 minutes. C) The main study design. Subjects performed eight sessions of BCI experiments, each with 12 BCI runs split between various decoders and 1 additional run to estimate chance level. D) The study design to evaluate transfer learning and calibration. The setup is like Panel C, but subjects performed two training sessions of DT BCI and four sessions of CP.

component of the cursor-to-target vector, and another for the vertical component.

A window of 1 second of EEG data is used as the input as a 62 channel by 250-time points array (1 second of data at 250 Hz). The data in this window is downsampled by a factor of 4 (from 1 kHz to 250 Hz) and common average re-referenced. This preprocessing is done in both online experiments and offline training. In the online experiment, new data blocks arrive every 40ms, so the input window consists of the most recent 1 second of data, updated every 40ms. In the offline setting, data windows are sliding windows 1 second long, sliding every 40ms to stay consistent with the online setting.

G. PointNet

In addition to implementing EEGNet for the CP task, we also chose to test another architecture in online experiments as well. For this purpose, we adapted the PointNet architecture for

BCI decoding [46], [47]. The PointNet architecture is designed around point cloud representations of the task as inputs to extract spatial patterns or features. In other fields, this point cloud can be a collection of points that make up a 3D scene, but here we used the collection of electrodes and their 3D locations in space (relative to each other) as the point cloud.

Unlike the EEGNet implementation, for PointNet we use a spectral domain representation of the EEG signal for the input to the model. The same data windows described above for EEGNet are used, but are passed through a Fast Fourier Transform (FFT) to yield an estimation of the frequency spectrum of the signal for each electrode. The input to the PointNet model is the array of 62 frequency spectrums (one for each channel), and a 62 x 3 vector containing the 3D locations of each electrode relative to one another. The positions were a set of standard electrode positions for the Neuroscan Quik-Cap, and were not recorded experimentally. The same electrode positions were used for every subject.

Our implementation of the PointNet architecture is shown in Figure 2B. The model begins with the frequency spectrum input, which is passed through three successive set abstraction layers, a fully connected layer, batch normalization, a RELU activation function, dropout (40%), and a final fully connected layer. The implementations of both the EEGNet and PointNet architectures used in this study will be made public via GitHub when paper is accepted for publication.

H. Study Design

Two of the main goals of this study were to establish DL-based BCI decoders for the CP task, and to evaluate their performance in human subjects to evaluate the effects of additional training data. To accomplish this, we developed the study design shown in Figure 3. Subjects completed 8 sessions of CP BCI experiments. Each session consisted of 12 CP runs, where each run had 5 one-minute trials, with an additional run used to calculate the chance level (Figure 3B). Since the DL-based decoders require subject-specific training data before they can be used, the first session consisted entirely of runs using the traditional decoder. Each session after the first had four runs each of the traditional decoder, PointNet model, and EEGNet model (Figure 3C). The order of decoders was randomized for each session, but all four runs of each decoder were completed together as a block.

Chance level is a commonly used benchmark in BCI studies to show the performance level when subjects have no control over the system [48]. To estimate the chance level for our implementation of the CP paradigm, we ran an additional run in each session of the study where the screen was turned off and subjects were instructed not to perform any motor imagery. Subjects were also asked to relax and limit their movements to reduce any motion artifacts in the data. Since the subjects could not see the cursor or target and should not have performed any motor imagery, the performance from these runs should be random and can be used to estimate a chance level for this task.

Subjects were required to have at least two sessions of BCI experience before starting this experiment. This requirement helped to ensure that subjects had some control over the BCI system, reduce the effects of training on performance in the first few sessions, and prepare subjects for the more complex CP

task. In addition, the speed of the cursor and target was reduced for the first session of this experiment (Session 'T' in Figure 3B) to help introduce subjects to the CP task. The speed was then increased and kept consistent for the remaining 7 sessions (Sessions 1-7 in Figure 3B).

I. Statistical Analysis

Cursor and target position data were recorded using BCI2000 every 40ms and processed offline using custom MATLAB scripts. Statistical analysis was performed using custom R scripts. For offline analysis, the data was downsampled by a factor of 4 to 250 Hz and common average re-referencing was applied.

Performance in the CP task is primarily quantified using either the error between the cursor and target, or the correlation between their positions. Here, we report cursor-target distance using the Mean Squared Error (MSE) between the two positions, normalized by the screen size (diagonal distance of the square workspace). The Pearson correlation coefficients are used to report the linear relationship between cursor and target positions throughout the trial.

For each of the MSE, correlation, and ADA performance metrics, statistical analyses were performed by fitting linear mixed effects models. For these models, the session number, decoder, and session-decoder interaction were considered fixed effects while subjects were classified as random effects. ANOVAs performed on each of the models for MSE, correlation (x and y), and ADA showed significant effects for session, decoder, and session-decoder interactions. Estimated marginal means, calculated from the R library *emmeans*, were used to perform pairwise t-tests to compare decoders in specific sessions (example Figure 4B). Unless noted otherwise, the Holm method was used to adjust p-values for multiple comparisons.

The ADA metric was primarily used to compare DL models offline to choose the best architectures and weights for online experiments. To investigate how similar the ADA metric compares to cursor-target MSE, we calculated the Pearson correlation coefficient between the two metrics for all trials. Furthermore, a linear model was fitted to the data with the MSE as the dependent variable and ADA as the independent. The resulting parameters and linear fit are shown as results in Figure 4I.

To study the lag between target and cursor movements and the effect on performance, we constructed histograms of trials whose best performance was achieved at specific time-lags. To create these plots, we shifted the cursor position vector relative to the target position vector, with the difference between vector positions called the *lag*. Since the cursor and target positions were sampled every 40ms, each shift of the cursor position vector represents a lag of 40ms. After each shift, the MSE between the cursor and target positions was calculated and recorded for that specific lag. The lag that produced the best MSE for each trial was recorded and the trials were binned based on their best lag to construct histograms. Finally, the average MSE across trials was found for each decoder at each lag and used to determine which lag resulted in the best average performance for each decoder.

J. Transfer Learning

We designed a second sub-study to investigate the potential benefits of using transfer learning to reduce the amount of training data needed for DL-based decoders. For this experiment, we chose to test only the EEGNet architecture to allow us to collect more data for each experimental condition instead of having to split the runs between EEGNet and PointNet. We designed the study as shown in Figure 3C, similar to the original study design with 12 CP runs and an additional chance run for each session. Here, we recruited only subjects with no prior BCI experience and ran two sessions of DT BCI as training before moving on to the CP tasks. All of the subjects recruited for this experiment were different from those who participated in the previous CP experiment. We also chose to reduce the cursor speed by 25% and the variance of the random accelerations applied to the target by 33% for this experiment after seeing that some subjects struggled with the faster speeds in the first part of this study.

For this follow-up experiment, we tested the original EEGNet DL-decoder paradigm (DL) along with two new DL-based paradigms: transfer learning (TL) and calibration (CL). Details on the on our implementation of transfer learning can be found in the supplemental materials.

K. Calibration

The second new decoding paradigm we evaluated was calibrating the DL decoders. By calibrating the DL-based decoders mid-session with data from the current BCI session, we hypothesized that we could reduce the effects of inter-session variance in the data and achieve higher performance in the CP task.

In this method, subjects first performed 4 runs with TL decoder as normal. We then used those 4 runs from the current session to update the TL decoder mid-session. To do this, we created a new EEGNet model and initialized the model weights as the weights from the current TL decoder. We then trained the new model for 5 epochs using only the 4 runs of TL data from the current session as training data. To make the most of the data from the current session, all of the data from these 4 TL runs was used as training data and no validation was performed. The model weights at the end of the fifth epoch were used as the final weights for the calibrated model (CL).

To train the CL model mid-session, we ran the random chance runs directly following the TL runs each session. While the chance runs were ongoing, the data from the TL runs were uploaded to a remote server, used to train the CL model, and then the resulting model weights were downloaded to the local computer to be used for the CL runs. Training the CL models with this setup took a similar amount of time as the chance-level run, so there was minimal interruption in the sessions.

III. RESULTS

There are several different methods that can be used to quantify BCI performance in the CP task. The primary metric for online experiments is the MSE between the cursor and the target. To make this number more intuitive, we use the normalized MSE throughout this manuscript. The normalized MSE is the squared distance between the cursor and target, divided by the diagonal length of the square task area. Using

this metric, the best performance is 0, where the cursor and target are in the same spot, and the worst possible performance is 1, where they are in opposite corners.

trials from this sub-study of two different subjects using EEGNet, and one of the subjects using the PointNet architecture.

Fig. 4. Results of DL decoding in online CP experiments. A) Decoder performance throughout sessions of the study in terms of Mean Square Error (MSE). A lower MSE indicates better performance. B) MSE performance of decoders in the first session. C) MSE performance of decoders in the last session (Session 7). D) Horizontal correlation between cursor and target positions (Pearson Correlation Coefficients) over sessions throughout the study. E) Vertical correlation throughout the study. F) Performance of each decoder over sessions in terms of ADA. G) ADA performance in the first session. H) ADA performance in the last session (Session 7). I) Scatter plot of each trial in terms of ADA vs. MSE. A strong correlation was found between the two and a linear fit is shown in red.

A. Group-level Results

Figure 4 shows the group level results in terms of cursor-target position MSE. Figure 4A shows the overall results throughout each session of the experiment. The Traditional decoder performs better than both DL models in the first session, but each of the DL models improves throughout the experiment. Both the Traditional decoder and the Chance runs do not have a clear trend over sessions.

Panels B and C of Figure 4 show the results from the first and last sessions individually. In Session 1, all three decoders perform better than chance level, and the Traditional decoder outperforms PointNet but not EEGNet. In the final session, Session 7, both DL models outperformed the Traditional decoder and there was no significant difference between EEGNet and PointNet. EEGNet improved by 0.43 per session (%screen size^2) while PointNet improved by 0.56. Supplementary Videos SV1, SV3, and SV5 show reconstructed

Another way to evaluate the performance in the CP task is through the correlation between the cursor and target position. This metric measures the relationship between the cursor and target positions and will be higher when they tend to be in similar locations of the task area throughout the trial. A correlation close to zero implies that there is no substantial relationship between the cursor and target movements, making this an intuitive benchmark for a random baseline performance. As expected, the experimental chance level results fluctuate around zero correlation in both the horizontal and vertical directions.

The correlation results were split into each axis, with the correlation between horizontal cursor and target positions shown in Figure 4D, and the vertical results in Figure 4E. In both plots, the traditional decoder remains relatively level across the sessions, while both DL decoders improve over time. In both cases, the EEGNet performance reaches a higher performance than PointNet by the last session, and seems to be

Fig. 5. Cursor position lag. A-E) Histograms of the cursor position lag that results in the best performance for each trial. The large spikes around 1-2 seconds suggest that there is a short delay between a change in target direction and the decoder output. F) CP performance in cursor-target distance for each lag duration. The low points in each curve show the estimated BCI performance from removing the delay.

continuing on an upward trend while PointNet starts to plateau over the final few sessions.

Figure 4F illustrates the group-level CP results in terms of the ADA metric over each of the sessions. Here, all three of the decoders tested in this study perform similarly in Session 1, but both DL models improve over time and outperform the traditional decoder by the last session. The results specific to Session 1 and Session 7 are shown in Figures 4G and 4H respectively.

We chose to use ADA for training and evaluating the DL models offline since this metric can be obtained without simulating a cursor path in an offline CP trial (see Materials and Methods for more information). However, the cursor-target MSE remains the primary metric for quantifying online performance and may be more intuitive than ADA. To study how well ADA may substitute for MSE in offline analysis, we looked at the correlation between the two metrics. Figure 4I shows a scatter plot of each online CP trial comparing the distance and ADA results, along with a linear fit. The result over all online trials was a correlation of 0.81 between distance and ADA, showing a strong relationship between the two metrics.

B. Cursor-Target Lag

During the CP task, BCI decoders can suffer from the delay period between when the cursor-target direction changes and when the decoder can update accordingly. This delay period can have several contributing factors including: the subject's reaction time and ability to change their motor imagery quickly, as well as the ability of the decoder to detect changes in motor imagery features and modify its output in a timely manner. While this lag period can be a challenge for the CP task, it may not have a substantial effect on traditional BCI tasks that have a single target, and therefore intention, in each trial.

To investigate this delay, or lag, between changing target directions and decoder output, we shifted the cursor positions over time and calculated the cursor-target distance at each lag. The lag that produced the best performance (lowest cursor-target MSE) was recorded for each trial. Figure 5A shows a histogram of the results over all the decoders. The large spike after a few seconds shows that the performance in most trials is better using the target position from a few seconds in the past, rather than the current target position. Figures 5B, 5C, 5D, and 5E show the same histogram for the experimental 'chance' runs, the traditional model, EEGNet, and PointNet, respectively. Similar spikes around 1.5 seconds are present in each of the decoders, while the chance level runs do not have any spike, showing that the delay is not present in runs without any BCI control.

Figure 5F shows the grand-average MSE over all sessions for each decoder as a function of lag. The performance of each BCI decoder improves with the delay, up to a peak between 1-2 seconds, while the 'chance' level performance remains steady throughout any lag. The traditional model performed best after a lag of 1.28 seconds and the MSE was improved by 0.8 (%screen size^2). EEGNet's best lag was 1.2 seconds and improved by 1.6, while PointNet was later at 1.48 seconds and improved by 1.7. Supplementary Videos SV2, SV4, and SV6 show the same trials from SV1, SV3, and SV5, but with the lag adjusted for by shifting the cursor position forward in time.

C. Transfer Learning and Calibration

One of the main disadvantages of deep learning-based decoders is that they can require a larger amount of training data to achieve optimal performance compared to other methods. Transfer learning (TL) is a method used in some deep learning applications that could potentially reduce the amount of training data needed for these models by pre-training them on data from previously studied subjects. We hypothesized that pre-training

Fig. 6. Transfer learning results. B) Overall results from sessions 1-4 in terms of MSE B) Results from the first CP session, Session 1. C) Results from Session 4 of the CP experiments.

DL-based decoders on the data from the first part of this study could help the resulting TL-based models perform well in early sessions for new subjects, even with the limited subject-specific training data available in the first few sessions.

In addition to needing enough training data, DL-based decoders are also prone to overfitting on the training dataset. The large variances in BCI data between subjects, and even between sessions for the same subject, may cause reduced performance when models are fit too heavily on training data that is from a different subject or day than the online testing session. To help models adapt to the current task, we hypothesized that calibrating the models using data from the current testing session could help improve performance.

We used the study design in Fig. 3D to compare both TL and calibration (CL) to the same EEGNet paradigm we used in the first sub-study (DL). Like the first part of the study, the DL model requires subject-specific training data and could not be used until Session 2. We chose to include 4 runs from the traditional decoder in Session 1 to compare with the TL decoder

in the first session, where the TL model has not been trained on any subject-specific data.

The results over the first 4 sessions are shown in Fig. 6A. All three models performed similarly at the group level, and both TL and DL saw improvements each session from Session 2-4. Interestingly, the TL models did not improve from Session 1 to Session 2 at the group level (average across all subjects). Both the TL and DL training methods achieved similar performances throughout Session 2-4.

Looking at the results from Session 1 (Fig. 6B), the traditional decoder and TL models reach similar performance, and the CL models had a similar median but larger variance. In the final session (Fig. 6C) had similar results where each of the three training methods achieved similar performances, but CL had a large variance with some subjects benefiting substantially.

Lastly, we compared the performance of the first sub-study with the faster speed to the second sub-study using the slower speeds (Supplementary Fig. S1). For this analysis, we compared only the runs using EEGNet without TL since this was the only condition in both sub-studies. Although we lowered the cursor and target speed to make the task easier for subjects, the results show that the performance using both speeds was not substantially different.

Furthermore, we looked at the effects of lag on both speeds (Supplementary Fig. S2) and found that the lag affected performance more using the faster speed. Although the slower speed performance was less affected, the optimal lag was longer than the faster settings (2.04s vs. 1.34s). This may be because the slower cursor speed required more time for subjects to correct their course.

IV. DISCUSSION

In this study, we designed a framework to train deep learning-based EEG decoders for the continuous pursuit (CP) task and evaluated the performance of two different DL architectures and a traditional decoder over 7 BCI sessions. We found that both DL-based decoders improved throughout the study and outperformed the traditional decoder by the final session. Both the EEGNet- and PointNet- based decoders performed similarly across several metrics including cursor-target distance, correlation, and ADA. When we implemented a transfer learning technique by pre-training DL-based decoders on data from previous subjects, we found that the pre-training did not significantly improve BCI performance in early sessions compared to training from scratch. However, calibrating models by training on small data samples from the current online session helped to improve outcomes in some situations. Overall, using DL-based decoders improved their performance throughout the course of the study and outperformed the traditional decoder once enough training data became available.

While DL-based decoders have been implemented for other BCI tasks, the CP paradigm lacks a clear label for the data to use for supervised learning purposes. This makes training DL models using the conventional methods more difficult compared to discrete trial BCI tasks, where there is a single target for each trial and therefore a clear label. To solve this problem, we developed a CP task labelling method, described

above in the Materials and Methods section, that uses the vector between the cursor and target positions as a label.

Although this paradigm allows us to apply a label to the CP data for supervised learning, it also creates two potential problems for the decoders. First, the labelling system assumes that the subject is always trying to move in the optimal direction towards the target. Although this is the best direction for the cursor to get closer to the target, subjects may not always be trying to move in this direction during the actual experiment, which could generate inaccurate labels. Second, the MI paradigm that the subjects were instructed to move only consisted of four cardinal directions (left, right, up, and down). To move in other directions, the subjects had to perform a combination of these MI tasks, and it was up to each subject to determine their best strategy for combining the movements. How subjects chose to integrate these movements could make the difference between producing decodable features for multiple directions, or just the four cardinal directions.

Even with these challenges, This work shows that the models were able to capture some relationship between the label and subjects' EEG recordings and provides evidence that the labelling system is suitable for training supervised learning models for the CP task.

The overall group results in Figure 4 show the development of each decoder throughout the study sessions. In the first session, all three decoders perform better than chance level, showing that the DL-based decoders can perform even when trained using only a single session of subject-specific data. However, the traditional AR-based decoder had the best average performance and statistically outperformed the PointNet model. Throughout the study, both DL-based decoders improved when given increasing amounts of training data and outperform the traditional decoder by the final session (Fig. 4C). Overall, these results show that DL-based decoders improve when given increasing amounts of training data and may even keep improving past the 7 sessions studied here.

Interestingly, the performance of the traditional decoder seemed to stay consistent throughout the study instead of improving as subjects got more experienced. One reason that we did not see an improvement in performance due to learning may be that all the subjects recruited for this study were experienced and had already participated in at least 2 BCI sessions prior to this experiment. This means that any performance improvements from learning in sessions that subjects completed before this study are not shown in the results here.

Another potential factor could be that subjects may be able to tell the difference between the three decoders during the experiment (subjects were not told which decoder was being used for each run) based on the cursor movement and their observed performance. If there is a large difference in performance, as is the case in later sessions, subjects might become discouraged when using the worse performing method which is more difficult to control. This could have caused the performance of the traditional method to suffer and could negate any benefits from learning, even though subjects were encouraged to try their best for every trial.

Since the cursor-target MSE is the primary metric for the CP task but cannot be readily used offline, it is important to determine if ADA can be a used as an offline approximation of MSE. To study this, we looked at the correlation between cursor-target MSE and ADA shown in Figure 4I. The high correlation (0.81) shows that both ADA and distance follow a similar trend and that a low ADA offline suggests that a similar online setup would achieve a good MSE. However, there is still a large variance off the linear trend, meaning that ADA is not a perfect predictor for online performance.

During the experiments with this faster speed, we noticed a substantial lag between the target position and cursor movement. We hypothesized that this lag could be caused by both subject reaction times and the decoder's ability to change its output. The results in Figure 5 show an analysis of shifting the cursor position vector in time. The histograms in panels A-E show how frequently each time-shift resulted in the best cursor-target distance for each trial. The large peaks around 1-2 seconds for each BCI decoder show that the MSE improves by shifting the cursor position forward 1-2 seconds in time suggesting that the cursor position lags the target by about 1-2 seconds. Figure 5F shows the average cursor-target MSE across trials for each decoder as a function of lag. Here, all three decoders see peak performance after a short delay.

This lag between target movement and decoder output presents a unique challenge for the CP paradigm. While real-time and dynamic control is desired for continuous tasks, the subjects' reaction time and the internal buffers of decoders could limit the ability of BCI systems to react quickly. This is even more pronounced in higher speed CP tasks, where subject is likely to have to change their intention more often and decoders will have less time to modify their output.

One of the primary drawbacks of deep learning-based decoders is that they can require large amounts of training data before they can perform well. This issue is especially relevant for BCI tasks, where collecting data can be costly in both time and money for researchers. In this study, we implemented a transfer learning paradigm to reduce the amount of training data needed by using data from the 14 subjects studied in the first part of this work to pre-train DL models for new subjects. In addition, we attempted to further improve performance for these new subjects by fine-tuning models mid-way through each session using data collected from the current session. Since we hypothesized that the TL models would outperform the standard DL training paradigm, we performed this calibration step on the TL models.

The overall results from this second set of experiments (Figure 6A) follow a similar trend to the original experiments. Each of the DL-based decoders improved in successive sessions as more subject-specific training data became available. Overall, the TL and DL models reached similar performance in sessions 2-4, showing that our specific implementation of transfer learning did not benefit performance in early sessions. Interestingly, the TL decoders reached a similar performance to the traditional decoder in the first session (Figure 6B), when no subject-specific data was available. Since the TL models had no subject-specific training data at this point, it makes sense that they would not be able to take advantage of any subject-specific features which could be one explanation for the similar performance. Both these results suggest that the main benefits

of DL-based decoding lie in the models' ability to extract subject-specific features.

The results of same-session calibration are interesting, but not conclusive. The calibrated models reached a better average performance than the TL models that they are based upon in each session after the first, but do not reach statistical significance. Our current implementation of calibration uses only data from four runs to update the models mid-session, and we do not have any way to choose the best model weights among the five training epochs. Future iterations of this method could include a validation set, or use a different way to update the model weights, such as a different learning rate or only updating specific layers. The calibration results shown here suggest that some method of updating the models mid-session may help to reduce inter-session variance and warrant further investigation.

This study demonstrates the potential of using DL-based decoders for online BCI decoding in difficult tasks and shows that subjects can achieve very strong performance with these models. However, additional work could be done to further improve performance and help optimize the training process. First, we used two different DL architectures in this study, including the popular EEGNet and our original implementation of the PointNet architecture. Although the models performed similarly in this case, other DL architectures could be designed specifically for the CP task and could produce better outcomes. The experiments from this work produced over 150 hours of CP BCI recordings that could be used as a rich training dataset for developing such models.

In both parts of this study, the DL model performance is still improving between the second to last and final session studied, suggesting that the models could still benefit from additional training data. A long-term study with many sessions for each subject could help to further characterize the relationship between DL-based decoder performance and training data and may be able to determine the full potential of these models.

Lastly, transfer learning and calibration were studied briefly here, but each method could warrant a study of its own. Although our implementation of TL did not seem to benefit the DL-based decoders, transfer learning has a strong foundation and has seen success in other fields and even some BCI applications [35]–[37]. The calibration method here did improve performance in some cases but could be limited by the amount of calibration data available and there may be better ways of fine-tuning the models mid-session.

V. Conclusion

In this study, we have developed a novel labelling paradigm and offline performance metric that allowed us to train DL-based decoders for the continuous pursuit (CP) BCI tasks, and rigorously evaluated the DL-based CP BCI in a group of 28 human subjects. Two different DL-based decoders were evaluated over 7 BCI sessions and both models were found to improve throughout the study when additional sessions of training data became available and outperformed a traditional BCI decoder after just a few sessions. A transfer learning paradigm and mid-session calibration technique were also evaluated and show the potential to benefit performance, although more work is needed to optimize these methods. This

study introduces online, DL-based decoding to the CP task and shows how these decoders have the potential to improve subjects' control in continuous BCI systems. Although the CP is challenging, strong performance in this task can open the door to more complex and intricate BCI systems with real-time dynamic control and can help move non-invasive BCIs closer to real-world and clinical applications.

VI. Acknowledgment

The authors thank Jeehyun Kim for assistance with data collection.

Author Contributions: Conceptualization – D.F., H.Z., B.H.; Investigation: D.F., H.Z., B.H.; Data Acquisition: D.F., H.Z., J.S., J.L.; Analysis: D.F., H.Z.; Writing of Original Manuscript: D.F.; Manuscript Revision: B.H.; Supervision: B.H.

Formatted: No underline

VII. References

[1] B. He, J. Yuan, J. Meng, and S. Gao, "Brain-Computer Interfaces," in *Neural Engineering*, 3rd ed., Springer International Publishing, Cham, 2020, pp. 131–183.

[2] B. J. Edelman *et al.*, "Noninvasive neuroimaging enhances continuous neural tracking for robotic device control," *Science Robotics*, vol. 4, no. 31, p. eaaw6844, Jun. 2019, doi: 10.1126/scirobotics.aaw6844.

[3] J. Meng, S. Zhang, A. Bekyo, J. Olsoe, B. Baxter, and B. He, "Noninvasive Electroencephalogram Based Control of a Robotic Arm for Reach and Grasp Tasks," *Sci Rep*, vol. 6, no. 1, Art. no. 1, Dec. 2016, doi: 10.1038/srep38565.

[4] B. Xu *et al.*, "Continuous Hybrid BCI Control for Robotic Arm Using Noninvasive Electroencephalogram, Computer Vision, and Eye Tracking," *Mathematics*, vol. 10, no. 4, Art. no. 4, Jan. 2022, doi: 10.3390/math10040618.

[5] F. Galán *et al.*, "A brain-actuated wheelchair: Asynchronous and non-invasive Brain–computer interfaces for continuous control of robots," *Clinical Neurophysiology*, vol. 119, no. 9, pp. 2159–2169, Sep. 2008, doi: 10.1016/j.clinph.2008.06.001.

[6] R. Leeb, D. Friedman, G. R. Müller-Putz, R. Scherer, M. Slater, and G. Pfurtscheller, "Self-Paced (Asynchronous) BCI Control of a Wheelchair in Virtual Environments: A Case Study with a Tetraplegic," *Computational Intelligence and Neuroscience*, vol. 2007, p. e79642, Sep. 2007, doi: 10.1155/2007/79642.

[7] A. J. Doud, J. P. Lucas, M. T. Pisansky, and B. He, "Continuous Three-Dimensional Control of a Virtual Helicopter Using a Motor Imagery Based Brain-Computer Interface," *PLOS ONE*, vol. 6, no. 10, p. e26322, Oct. 2011, doi: 10.1371/journal.pone.0026322.

[8] A. S. Royer, A. J. Doud, M. L. Rose, and B. He, "EEG Control of a Virtual Helicopter in 3-Dimensional Space Using Intelligent Control Strategies," *IEEE Transactions on Neural Systems and Rehabilitation Engineering*, vol. 18, no. 6, pp. 581–589, Dec. 2010, doi: 10.1109/TNSRE.2010.2077654.

[9] K. LaFleur, K. Cassady, A. Doud, K. Shades, E. Rogin, and B. He, "Quadcopter control in three-dimensional space using a noninvasive motor imagery based brain-computer interface," *J Neural Eng*, vol. 10, no. 4, p. 10.1088/1741-2560/10/4/046003, Aug. 2013, doi: 10.1088/1741-2560/10/4/046003.

[10] F. Barberi, E. Anselmino, A. Mazzoni, M. Goldfarb, and S. Micera, "Toward the development of user-centered neurointegrated lower limb prostheses," *IEEE reviews in biomedical engineering*, vol. PP, Aug. 2023, doi: 10.1109/RBME.2023.3309328.

[11] J. J. Vidal, "Toward Direct Brain-Computer Communication," *Annual Review of Biophysics and Bioengineering*, vol. 2, no. 1, pp. 157–180, 1973, doi: 10.1146/annurev.bb.02.060173.001105.

[12] G. Pfurtscheller and C. Neuper, "Motor imagery and direct brain-computer communication," *Proceedings of the IEEE*, vol. 89, no. 7, pp. 1123–1134, Jul. 2001, doi: 10.1109/5.939829.

[13] V. Kaiser, I. Daly, F. Pichiorri, D. Mattia, G. R. Müller-Putz, and C. Neuper, "Relationship Between Electrical Brain Responses to Motor Imagery and Motor Impairment in Stroke," *Stroke*, vol. 43, no. 10, pp. 2735–2740, Oct. 2012, doi: 10.1161/STROKEAHA.112.665489.

[14] K. K. Ang *et al.*, "A Randomized Controlled Trial of EEG-Based Motor Imagery Brain-Computer Interface Robotic Rehabilitation for Stroke," *Clin EEG Neurosci*, vol. 46, no. 4, pp. 310–320, Oct. 2015, doi: 10.1177/1550059414522229.

[15] R. Foong *et al.*, "Assessment of the Efficacy of EEG-Based MI-BCI With Visual Feedback and EEG Correlates of Mental Fatigue for Upper-Limb Stroke Rehabilitation," *IEEE Transactions on Biomedical Engineering*, vol. 67, no. 3, pp. 786–795, Mar. 2020, doi: 10.1109/TBME.2019.2921198.

[16] C. S. Choy, S. L. Cloherty, E. Pirogova, and Q. Fang, "Virtual Reality Assisted Motor Imagery for Early Post-Stroke Recovery: A Review," *IEEE Reviews in Biomedical Engineering*, vol. 16, pp. 487–498, 2023, doi: 10.1109/RBME.2022.3165062.

[17] M. Jeannerod, "Mental imagery in the motor context," *Neuropsychologia*, vol. 33, no. 11, pp. 1419–1432, Nov. 1995, doi: 10.1016/0028-3932(95)00073-C.

[18] H. Yuan, T. Liu, R. Szarkowski, C. Rios, J. Ashe, and B. He, "Negative covariation between task-related responses in alpha/beta-band activity and BOLD in human sensorimotor cortex: An EEG and fMRI study of motor imagery and movements," *NeuroImage*, vol. 49, no. 3, pp. 2596–606, Feb. 2010, doi: 10.1016/j.neuroimage.2009.10.028.

[19] B. He, B. Baxter, B. J. Edelman, C. C. Cline, and W. W. Ye, "Noninvasive Brain-Computer Interfaces Based on Sensorimotor Rhythms," *Proceedings of the IEEE*, vol. 103, no. 6, pp. 907–925, Jun. 2015, doi: 10.1109/JPROC.2015.2407272.

[20] J. R. Stieger, S. Engel, H. Jiang, C. C. Cline, M. J. Kreitzer, and B. He, "Mindfulness Improves Brain–Computer Interface Performance by Increasing Control Over Neural Activity in the Alpha Band," *Cereb Cortex*, vol. 31, no. 1, pp. 426–438, Sep. 2020, doi: 10.1093/cercor/bhaa234.

[21] J. R. Wolpaw and D. J. McFarland, "Control of a two-dimensional movement signal by a noninvasive brain-computer interface in humans," *Proceedings of the National Academy of Sciences*, vol. 101, no. 51, pp. 17849–17854, Dec. 2004, doi: 10.1073/pnas.0403504101.

[22] V. Martínez-Cagigal, R. J. Kobler, V. Mondini, R. Hornero, and G. R. Muller-Putz, "Non-linear online low-frequency EEG decoding of arm movements during a pursuit tracking task," in *2020 42nd Annual International Conference of the IEEE Engineering in Medicine & Biology Society (EMBC)*, Jul. 2020, pp. 2981–2985. doi: 10.1109/EMBC44109.2020.9175723.

[23] A. Craik, Y. He, and J. L. Contreras-Vidal, "Deep learning for electroencephalogram (EEG) classification tasks: a review," *J. Neural Eng.*, vol. 16, no. 3, p. 031001, Apr. 2019, doi: 10.1088/1741-2552/ab0ab5.

[24] I. H. Sarker, "Deep Learning: A Comprehensive Overview on Techniques, Taxonomy, Applications and Research Directions," *SN Comput Sci*, vol. 2, no. 6, p. 420, 2021, doi: 10.1007/s42979-021-00815-1.

[25] R. T. Schirrmeister *et al.*, "Deep learning with convolutional neural networks for EEG decoding and visualization," *Human Brain Mapping*, vol. 38, no. 11, pp. 5391–5420, 2017, doi: 10.1002/hbm.23730.

[26] J. R. Stieger, S. A. Engel, D. Suma, and B. He, "Benefits of deep learning classification of continuous noninvasive brain–computer interface control," *J Neural Eng*, vol. 18, no. 4, p. 10.1088/1741-2552/ac0584, Jun. 2021, doi: 10.1088/1741-2552/ac0584.

[27] H. Zhu, D. Forenzo, and B. He, "On the Deep Learning Models for EEG-Based Brain-Computer Interface Using Motor Imagery," *IEEE Trans Neural Syst Rehabil Eng*, vol. 30, pp. 2283–2291, 2022, doi: 10.1109/TNSRE.2022.3198041.

[28] D. Zhang, L. Yao, K. Chen, S. Wang, X. Chang, and Y. Liu, "Making Sense of Spatio-Temporal Preserving Representations for EEG-Based Human Intention Recognition," *IEEE Transactions on Cybernetics*, vol. 50, no. 7, pp. 3033–3044, Jul. 2020, doi: 10.1109/TCYB.2019.2905157.

[29] J.-H. Cho, J.-H. Jeong, and S.-W. Lee, "NeuroGrasp: Real-Time EEG Classification of High-Level Motor Imagery Tasks Using a Dual-Stage Deep Learning Framework," *IEEE Transactions on Cybernetics*, vol. 52, no. 12, pp. 13279–13292, Dec. 2022, doi: 10.1109/TCYB.2021.3122969.

[30] L. Alzubaidi *et al.*, "Review of deep learning: concepts, CNN architectures, challenges, applications, future directions," *Journal of Big Data*, vol. 8, no. 1, p. 53, Mar. 2021, doi: 10.1186/s40537-021-00444-8.

[31] "ImageNet." Accessed: Apr. 03, 2023. [Online]. Available: https://www.image-net.org/

[32] M. Kaper, P. Meinicke, U. Grossekathoefer, T. Lingner, and H. Ritter, "BCI competition 2003-data set IIb: support vector machines for the P300 speller paradigm," *IEEE Transactions on Biomedical Engineering*, vol. 51, no. 6, pp. 1073–1076, Jun. 2004, doi: 10.1109/TBME.2004.826698.

[33] J. R. Stieger, S. A. Engel, and B. He, "Continuous sensorimotor rhythm based brain computer interface learning in a large population," *Sci Data*, vol. 8, no. 1, Art. no. 1, Apr. 2021, doi: 10.1038/s41597-021-00883-1.

[34] F. Zhuang *et al.*, "A Comprehensive Survey on Transfer Learning," *Proceedings of the IEEE*, vol. 109, no. 1, pp. 43–76, Jan. 2021, doi: 10.1109/JPROC.2020.3004555.

[35] J. Li, S. Qiu, Y.-Y. Shen, C.-L. Liu, and H. He, "Multisource Transfer Learning for Cross-Subject EEG Emotion Recognition," *IEEE Transactions on Cybernetics*, vol. 50, no. 7, pp. 3281–3293, Jul. 2020, doi: 10.1109/TCYB.2019.2904052.

[36] D. Wu, Y. Xu, and B.-L. Lu, "Transfer Learning for EEG-Based Brain–Computer Interfaces: A Review of Progress Made Since 2016," *IEEE Transactions on Cognitive and Developmental Systems*, vol. 14, no. 1, pp. 4–19, Mar. 2022, doi: 10.1109/TCDS.2020.3007453.

[37] J. G. Makin, D. A. Moses, and E. F. Chang, "Machine translation of cortical activity to text with an encoder–decoder framework," *Nat Neurosci*, vol. 23, no. 4, Art. no. 4, Apr. 2020, doi: 10.1038/s41593-020-0608-8.

[38] O.-Y. Kwon, M.-H. Lee, C. Guan, and S.-W. Lee, "Subject-Independent Brain–Computer Interfaces Based on Deep Convolutional Neural Networks," *IEEE Transactions on Neural Networks and Learning Systems*, vol. 31, no. 10, pp. 3839–3852, Oct. 2020, doi: 10.1109/TNNLS.2019.2946869.

[39] H. Yuan and B. He, "Brain–Computer Interfaces Using Sensorimotor Rhythms: Current State and Future Perspectives," *IEEE Transactions on Biomedical Engineering*, vol. 61, no. 5, pp. 1425–1435, May 2014, doi: 10.1109/TBME.2014.2312397.

[40] G. Schalk, D. J. McFarland, T. Hinterberger, N. Birbaumer, and J. R. Wolpaw, "BCI2000: A General-Purpose Brain-Computer Interface (BCI) System," *IEEE Trans. Biomed. Eng.*, vol. 51, no. 6, pp. 1034–1043, Jun. 2004, doi: 10.1109/TBME.2004.827072.

[41] D. Forenzo, Y. Liu, J. Kim, Y. Ding, T. Yoon, and B. He, "Integrating Simultaneous Motor Imagery and Spatial Attention for EEG-BCI Control," *IEEE Trans Biomed Eng*, vol. PP, Jul. 2023, doi: 10.1109/TBME.2023.3298957.

[42] J. Kim *et al.*, "Immediate effects of short-term meditation on sensorimotor rhythm-based brain–computer interface performance," *Frontiers in Human Neuroscience*, vol. 16, 2022, doi: 10.3389/fnhum.2022.1019279.

[43] D. Krusienski, D. McFarland, and J. Wolpaw, "An Evaluation of Autoregressive Spectral Estimation Model Order for Brain-Computer Interface Applications".

[44] J. Meng, T. Streitz, N. Gulachek, D. Suma, and B. He, "Three-Dimensional Brain–Computer Interface Control Through Simultaneous Overt Spatial Attentional and Motor Imagery Tasks," *IEEE Transactions on Biomedical Engineering*, vol. 65, no. 11, pp. 2417–2427, Nov. 2018, doi: 10.1109/TBME.2018.2872855.

[45] V. J. Lawhern, A. J. Solon, N. R. Waytowich, S. M. Gordon, C. P. Hung, and B. J. Lance, "EEGNet: a compact convolutional neural network for EEG-based brain–computer interfaces," *J. Neural Eng.*, vol. 15, no. 5, p. 056013, Jul. 2018, doi: 10.1088/1741-2552/aace8c.

[46] C. R. Qi, H. Su, K. Mo, and L. J. Guibas, "PointNet: Deep Learning on Point Sets for 3D Classification and Segmentation." arXiv, Apr. 10, 2017. doi: 10.48550/arXiv.1612.00593.

[47] C. R. Qi, L. Yi, H. Su, and L. J. Guibas, "PointNet++: Deep Hierarchical Feature Learning on Point Sets in a Metric Space." arXiv, Jun. 07, 2017. Accessed: Apr. 15, 2023. [Online]. Available: http://arxiv.org/abs/1706.02413

[48] G. Müller-Putz, R. Scherer, C. Brunner, R. Leeb, and G. Pfurtscheller, "Better than random? A closer look on BCI results," *International Journal of Bioelectromagnetism*, vol. 10, no. 1, pp. 52–55, 2008.