Title: Phase Resetting Curves Determine Stability of Synchrony in One and Two

Clusters of Pulse Coupled Oscillators with Delays

Authors: Ananth Vedururu Srinivas and Carmen C Canavier

Affiliation: Louisiana State University Health Sciences Center, Department of Cell

Biology and Anatomy, New Orleans, LA, 70112

Corresponding Author: Ananth Vedururu Srinivas - avedur@lsuhsc.edu

Abstract

Previously, our group used phase response curves under a pulsatile coupling assumption

to determine the stability of synchrony within a cluster of neural oscillators and between

two clusters of oscillators. The interactions of the within and between cluster terms were

considered, demonstrating how an alternating firing pattern between clusters could

stabilize within cluster synchrony- even in clusters unable to synchronize themselves in

isolation. In addition, criteria were derived for synchrony between two pulse coupled

oscillators with synaptic delays. In this study, we update our previous work on one and

two clusters of coupled oscillators to include delays and demonstrate the validity of the

results using a map of the firing intervals based on the phase resetting curve. We use

self-connected neurons to represent clusters and derive conditions under which an

oscillator can phase-lock itself with a delayed input. Although this analysis only strictly

applies to identical neurons receiving identical synapses from the same number of

neurons, the principles are general and can be used to understand how to promote or

impede synchrony in physiological networks of neurons. Heterogeneity can be interpreted

as a form of frozen noise, and approximate synchrony can be sustained despite

heterogeneity. The pulse-coupled oscillator model can not only be used to describe

biological neuronal networks but also cardiac pacemakers, lasers, fireflies, artificial neural

networks, social self-organization, and wireless sensor networks.

Keywords: Pulse-Coupled Oscillators; Phase Response Curve; Synchronization; Phase-

Locking; Phase resetting.

1. Introduction

Three mathematical methods that are commonly utilized for studying synchronization

between neural oscillators [1,2] include weak coupling [3,4], firing time maps [5,6], and

mean field methods, which often use leaky integrate-and-fire neurons [7]. The first two

methods can only apply to repetitively firing neurons in which a baseline oscillation period

can be measured, whereas the third method is most useful in the case in which individual

neurons are not oscillators but instead emit spikes randomly. The first two methods

employ different variants of phase response curves (PRCs). A phase response curve

measures the change in length of the oscillation period caused by an input received during

an oscillatory cycle. Weak coupling assumes that each oscillator remains very near its

unperturbed trajectory, and the effects of multiple inputs are summed to get the averaged

effect over one (unperturbed) oscillation cycle. In weak coupling, the infinitesimal phase

response curve is obtained in the limit as the strength and duration of the synaptic input

current both go to zero.

Here we focus on firing time maps under the assumption that coupling between neurons

is pulsatile, meaning that the effect of the coupling is brief compared to the period of the

neural network. The perturbation is not required to be small, but the oscillator is assumed

to return to its unperturbed, free-running trajectory prior to receiving any additional inputs.

In contrast to infinitesimal PRCs, phase response curves used for the firing maps are

analogous to spike time response curves [8,9]; the perturbation used to measure the PRC

is a post-synaptic conductance waveform, often assumed to be biexponential. Neural

oscillators are nonlinear; therefore, the effect of a perturbation is not time invariant, but

rather periodic with the same period as the neural oscillator. The PRC is the normalized

change in cycle length plotted as a function of the phase of the oscillator. In a network in

which each neuron receives N synaptic inputs, any given neuron can receive up to N

simultaneous inputs. Since multiple inputs are not assumed to be additive, the PRC to n

out of N inputs must be measured for each $n \in [0, N]$.

*1.1 Forced Oscillato*r: The simplest case of phase locking in pulse-coupled oscillators is

that of a single oscillator forcing another oscillator in a one-to-one locking in which the

driven oscillator receives an input on each cycle at a phase of φ. The criterion derived by

[10] was stated in terms of the slope of the PRC at the locking phase φ. The slope $f'(φ)$ is

simply the compensation in the direction back toward a steady phase locking normalized

by the size of the perturbation away from the steady locking. For perfect compensation

such that the locking is restored within a single cycle, the ratio of the compensation to the

perturbation should be one; the stability criterion is $|1 - f'(φ)| < 1$. The perturbation away

from the locking is multiplied by the factor *1 − f'(φ)* on each cycle, therefore a slope of 1

results in a multiplier of 0. For stability, the perturbation must decay to zero, therefore for

stability the absolute value of the factor must be less than one.

1.2 Synchrony Between Two Coupled Oscillators with and without delays: Previous work

has derived the criterion for synchrony between two identical, reciprocally pulse-coupled

oscillators in terms of the slope of the PRC at the phases of 0 and 1. Mapping the phases

from 0 to around a circle, both 0 and 1 correspond to an upward threshold crossing that

initiates an action potential, and is the phase at which an input is received by both neurons

in a network with no delays. However, because of the definition of a cycle length as being

between two action potentials threshold events, the PRC may have discontinuities. An

input applied just before an action potential may delay that action potential, but an input

applied after the action potential has already been initiated cannot. Therefore, the left and

right slopes at the phase at which an input is received in the case with no delays can be

different. The criterion for stability is [11] $|(1 - f'(0^+)) (1 - f'(1^-))| < 1$. If inputs are received

in different intervals, then they are multiplicative. However, if multiple inputs are received

in the interval between a spike in one neuron and a spike in another neuron, then the

compensations are additive; for a two neuron network the inputs are received by different

neurons. Therefore with small delays (less than a network period), the criterion for stability

of synchrony in reciprocally coupled identical neurons [12] becomes $|1 - f'(δ/P_i) - f'(δ/P_i)|$

< 1, or equivalently $|1 - 2 f'(δ/P_i)| < 1$, where $δ$ is the delay and P_i is the intrinsic period

of the free running oscillator.

1.3 Alternating firing pattern in two neuron networks. The general criterion for stability of

an alternating firing pattern between two neurons of neurons [13,14] A and B is $|(1 -$

$f'_{A,B}(φ_A)) (1 - f'_{B,A}(φ_B))| < 1$ where $φ_A$ is the phase at which neuron A receives an input

from neuron B and φ_B is the phase at which neuron B receives an input from neuron A in

a one-to-one phase-locked mode. The neurons are not presumed to be identical. The

criterion is unchanged for short delays [12].

2. Methods

2.1 Model Neurons:

2.2.1 Fast-Spiking Inhibitory interneurons

For illustrative purposes we examined a model of a representative fast spiking

parvalbumin (PV+) inhibitory interneuron in layers 2/3 of the medial entorhinal cortex [15].

This model was calibrated based on data the passive and active properties of these

neurons, which have Hodgkin's class 2 excitability [16] meaning they cannot sustain

repetitive firing below a threshold frequency. The single compartment model neurons

have five state variables: the membrane potential, *V*, and four gating variables (m, h, n,

and a) which use the same kinetic equations as the original Hodgkin-Huxley model

[17,18], but with different parameters tuned to replicate the dynamics of fast spiking

neurons in the medial entorhinal cortex and given in Table 1 of [15]. We also included two

delayed rectifier K$^+$ currents (I_{Kv1} and I_{Kv3}), consistent with other models of fast-spiking

interneurons [19,20]. All the synaptic parameters except one (synaptic decay constant)

were calibrated according to [21] with a biexponential waveform in conductance with time

constants of 0.3 and 0.45 ms and a peak conductance of 1.65 nS. The synaptic decay

constant was 2.0 ms in [21] but was reduced to 0.45ms to reduce second order resetting.

Two values for the synaptic reversal potential (-75 mV and -55 mV) were used to produce

two very different phase resetting curves and the synaptic delay was varied to correspond

to phases from 0.05 to 0.95 to test our stability criteria.

2.1.2 Excitatory Neurons

114   To understand the role of excitation on the network of fast-spiking inhibitory

115   interneurons, we used the Reduced-Traub-Miles model (RTM model) [22,23] of an

116   excitatory neuron in the rat hippocampus with a slight modification. Instead of applying a

Fig. 1. Phase Response Curve Under Pulsatile Coupling Assumption. A. A single output waveform from one oscillator (red) is used to perturb the other at phases ranging from 0 (spike onset) to 1 (onset of the next spike). The phase φ is the stimulus interval (ts) normalized by the unperturbed period P_0. B. The phase resetting f(φ) is the normalized change in the cycle length caused by the perturbation (P_1-P_0)/P_0. The response interval tr is determined by the phase resetting tr= P_0(1-φ+f(φ)). C. The PRC defines an interval map in a two-neuron network with delays. The response interval in one neuron determines the stimulus interval in the other, which determines the next response interval in the same neuron. D. Depiction of the Emulator (map with no pre-determined firing order). Two neurons are shown to be driven towards synchrony. We can observe that the phase of each neuron increases linearly except when reaches its threshold value φ = 1 or when it has its phase reset after receiving a delayed input from the other neuron.

constant current to induce repetitive firing as in [23] we used a constant excitatory

conductance to simulate channel rhodopsin drive as in [15].

2.2 Phase response curves: In Fig. 1AB we generated PRCs of the Via model for fast

spiking neurons discussed in the Methods section, in response to hyperpolarizing

inhibitory postsynaptic potentials. Except in the criterion for self-locking of an oscillator,

we neglect resetting that occurs in cycles after the one in which the perturbation is

received, for example second order resetting [14]. The first order phase response $f_{i,j}(\varphi)$ is

defined as the normalized difference between the perturbed cycle period P_1 and the

free-running intrinsic cycle period P_0 when a input from neuron j to neuron i is applied at

a phase φ: $f_{i,j}(\varphi)=(P_1-P_0)/P_0$. The second order phase response $f_{2,i,j}(\varphi)$ is defined as

the normalized difference between the period of the cycle P_2 following the perturbed

cycle and the free-running period P_0 when a input from neuron j to neuron i is applied at

a phase φ: $f_{2,i,j}(\varphi)=(P_2-P_0)/P.$ Figure 1A defines the stimulus and response intervals

based on the open loop PRC.

2.3 Stability Proofs: The basic idea is to assume a firing pattern (as the alternating firing

pattern with delays in Fig. 1C) and create a discrete system of difference equations (a

map or coupled set of maps) that characterize the dynamics in response to a perturbation.

Then we linearize the map about the fixed point of the map and find the eigenvalues of

the Jacobian matrix. These eigenvalues must have an absolute value less than 1 for

stability. The maps rely upon the definition of stimulus and response intervals as defined

in Fig.1. The stimulus interval *$ts_i[n]$* in cycle *n* is the interval between when neuron *i* fires

and when it next receives an input: $ts_i[n] = P_i\varphi_i[n]$, where P_i is the intrinsic period of neuron

1 and *$\varphi_i[n]$* is the phase at which an input is received on cycle *n*. If two inputs are received

in the same cycle, the resetting due to the first input is assumed to be complete by the

time the second input is received and the second stimulus interval is

$ts_{i,2}[n] = P_i(\varphi_{i,2}[n] - \varphi_i[n] + f(\varphi_i[n]))$, where $\varphi_{i,2}$ is the phase at which the second input is

received, and $f(\varphi_i)$ is the phase resetting due to the first input. The response interval $tr_i[n]$

is the interval between the receipt of the last input and the next spike in neuron i:

$tr_i[n] = P_i(1 - \varphi_i[n] + f(\varphi_i[n]))$ if there has only been one input in the cycle and

$tr_i[n] = P_i(1 - \varphi_{i,2}[n] + f(\varphi_{i,2}[n]))$ if there have been two.

2.4 Emulator (Map with no predetermined firing order [6]): The concept of a hybrid

oscillator that updates its phase linearly between events but discontinuously when an

input is received, or its threshold is crossed was pioneered by Winfree [24] and extended

by others [25,26] . In this study, we present the modified Winfree Model for pulsatile

coupling with delays:

$$\frac{d\varphi_i}{dt} = \omega - \sum_{j,k} D(t = t - t_{j,k} + \delta) f_{i,j}(\varphi_i) - D(\varphi_i = 1)$$

where ω is the angular frequency, φ_i is the phase of the i^{th} neuron, $t_{j,k}$ is the time the k^{th}

input is received from neuron j, $f_{i,j}(\varphi_i)$ is the phase response of neuron i at time $t_{j,k}$ to in

input from neuron j and the phase is reset to zero when the phase reaches 1. In this

modified Winfree Model represented by the equation above, the function D() represents

a unit impulse at the time the condition in parentheses is true and δ represents the

synaptic delay. Since PRCs are not additive, at the time two neurons synchronize their

input to neuron i, for strict accuracy the appropriate PRC corresponding to the joint input

must be substituted for the two separate PRCs. We utilize the emulator to test our proofs

because the pulsatile coupling assumptions are honored exactly, whereas in simulations

using conductance-based models we cannot ensure that the assumption of pulsatile

coupling is strictly honored. Figure 1D shows two coupled PRCs converging to synchrony,

using the emulator. The input given to this map is the intrinsic period and phase resetting

curve of each neuron.

3. Results

3.1 Assumptions of Pulsatile Coupling. The phase response curve is measured under

open loop conditions, meaning that there is no feedback to the rest of the circuit during

the measurement. In order for the phase response curve measured under those

conditions to apply to a closed loop circuit with feedback from other circuit elements,

several assumptions must be honored: 1) The trajectory of each oscillator must be near

enough to its unperturbed limit cycle when an input is received for the phase response

curve to predict the timing of the next spike by subtracting the first order resetting from

the current phase. 2) If there are multiple inputs within a network period, then the

trajectory should be near the limit cycle at the time that each input is received. It is not

required that the trajectory be near the limit cycle when a spike is emitted. 3) The second

order resetting can be non-negligible only for the last input received within a network

period. The second order resetting is assumed to be complete between the spike time

and the receipt of the first input within a network period (the stimulus interval). 4) Third

order resetting should be negligible. 5) There should be no non-negligible cumulative

effect of multiple inputs such as firing rate adaptation or acceleration.

3.2 Self-connected oscillator with delay:

Previously, a self-connected oscillator has been taken as the equivalent to a network of

identical, synchronized, mutually connected neurons [27]. One study derived existence

and stability criteria for a periodically spiking neuron forcing itself with a feedback input at

a fixed delay after each spike [28]. Their rationale was that excitatory pyramidal cells

receive feedback from inhibitory interneurons, such that there were two conduction and

synaptic delays in the feedback loop. They only considered delays longer than the

network period and neglected second order resetting. However, the case of delays

shorter than a network period has not previously been addressed. We formulated a simple

existence criterion for a stable phase locking of an oscillator with intrinsic period P_i by

feedback at a fixed delay (δ) after each spike is emitted.

Lemma: For the phase locked mode to exist, the stimulus interval at phase locking should

be equal to the delay $\delta = P_i(\varphi^* + f_2(\varphi^*))$, where φ^* is the phase at which an input would

arrive at phase locking.

Proof: If there is no second order resetting, the existence of a phase-locked mode is

guaranteed at every delay less than the network period $\delta < P_i(1+ f_1(\varphi^*))$. This is because

at the steady state, the phase defined by $\varphi^* = (ts[\infty]/P_i)$ at which the oscillator receives

the input due to self-connection would be just the normalized delay δ/P_i.

However, if the delay δ is such that the input from the self-connection arrives late in the

cycle, then the effect of second-order resetting becomes significant, especially in the case

of the model neurons considered in this study.

Therefore, with the second order resetting, the phase at which the input from the self-

connection is received is determined by the second order resetting. As a result, the

Fig. 2. A. Interval map for the self-connected oscillator. The sub-cluster of N-1 neurons from a cluster of N neurons receive N-2 inputs after a delay δ. B. Plot of predicted and observed periods for various delays at which the inputs from self-connection arrive. C. Plot of the steady-state stimulus interval ts[∞] = φ^* + $f_2(\varphi^*)$ versus the phase φ , to check the existence of phase-locking in self-connected oscillator. D. Trace of the membrane potential when δ = 5.1 ms. B (Inset): * denotes the case for the dashed red line in C for a delay of 5.1ms. In this case, the prediction is that there would no phase-locking in the self-connected oscillator. As a result, predicted period is not plotted for this delay. † denotes the case when the delay is 4.8 ms where the existence is predicted by the intersection (not shown here) and hence the predicted network period is plotted, but the numerical simulations of the model of the oscillator do not show periodicity in spiking. Thus, there is no observed period in the figure.

steady-state stimulus interval ts[∞] becomes a function of the second order resetting:

$$ts[\infty] = P_i(\varphi^* + f_2(\varphi^*))$$

where φ^* is the steady-state phase. But the input due to self-connection would arrive at a

phase of δ/P_i. So, for phase locking to exist, these two quantities must be equal to each

other:

$$\delta/P_i = P_i(\varphi^* + f_2(\varphi^*))$$

For the model neurons, we established existence using graphical method. We used a

fast-spiking model neurons with intrinsic period $P_i = 5.97$ ms. As described in the Methods

section, we varied the synaptic from $0.05^* P_i$ ($\delta = 0.3$ ms) to $0.95 {}^*P_i$ ($\delta = 5.7$ms). Figure

2C depicts the case with $\delta = 5.1$ ms such that $\delta/P_i \sim 0.90$. The green curve in the figure

represents $P_i(\varphi^* + f_2(\varphi^*))$ whereas the red dashed line is the constant value $\delta/P_i \sim 0.9$. In

this case, due to discontinuity in the second order resetting (figure 1B), we see that there

is no intersection of the two curves, and hence, we conclude that the phase-locking does

not exist for a delay of 5.1ms. For other delays we find that the curves intersect (not shown

here) thereby establishing the existence of phase locking. If phase-locking exists, then

the period of the self-connected oscillator can be predicted using the relation: $P^*_{N-1} = (1 +$

$f_1(\varphi^*) + f_2(\varphi^*))$. In figure 2B, we plotted the periods predicted through this relation for each

delay in the arrival of input stimulus due to self-connection versus the delay. We also

plotted the periods observed from simulating these oscillators using systems of ODEs for

various delays. Two cases are to be noted (see Figure 2B):

1. * in the inset of the figure denotes the case for which the delay is 5.1ms and

existence is not predicted, thus we have not indicated any predicted period in that

case.

2. For the case in which the input from the self-connection arrives at a delay of 4.8ms,

we observe a special case in which the existence is established by the intersection

of curves but from the ODE simulations we do not observe a one-to-one locking of

the neuron by itself. Assumption 3 above is violated because the second order

resetting is not completed in the stimulus interval but instead continues into the

response interval, rendering the prediction invalid indicated by † in figure 2B.

In a network of identical identically connected neurons, synchrony always exists due to

the symmetry [29]. Fig. 1D shows that synchrony need not be periodic.

The stability criterion for phase locking in self-connected oscillators is identical for self-

forcing as for external forcing: $-1 < 1 - f'_1(\varphi^*) - f'_2(\varphi^*) < 1$ [30].

3.3 Extension of the results for synchrony in an N neuron network without delay to include

delays:

For a network of neurons each receiving N-1 identical pulse-coupled inputs, the criteria

for synchrony in a network with no delays, under the assumption that the most

destabilizing perturbation is to perturb a single neuron from a synchronous cluster, are

$\left|(1 - f'_{1,N}(0^+))(1 - f'_{N-1,1}(1^-))\right| < 1$ and $\left|(1 - f'_{N-1,1}(0^+))(1 - f'_{1,N-1}(1^-))\right| < 1$ (Canavier and Achuthan,

2010). Here, the synchronous cluster is assumed to have N-2 self-connections

representing the inputs from all the neurons in the presumed synchronous cluster. There

are indices *i,j* on the phase resetting curve, where *i* is 1 for the PRC of the single neuron

in response to a *j* equal to N-1 inputs from the presumed synchronous cluster and i is N-

1 for the PRC of presumed synchronous cluster in response to a *j* equal to 1 inputs from

N-1 the single neuron.

In this study, we extend this criterion by analogy with the two-neuron case with delays as

studied in [12]. Figures 3A and 3B depict the perturbations with synaptic delays. In the

representation of the synchronous cluster, we incorporate inputs due to self-connections

but not autapses (synapses from an individual neuron onto itself). However, the results

that we will prove can be easily extended to include autapses. Connections need not be

all to all as long as each neuron receives the same number of identical inputs [15].

Fig. 3. Stability of Synchrony in a Network of N identical neurons each receiving N-1 identical inputs. A. Schematic firing pattern in which a single neuron is perturbed from synchrony. These intervals are used in the proof of stability. B. Reduction of the network to two oscillators. The larger group is assumed to receive delayed synchronous feedback from itself. Autapses are not considered.

Let P_i be the intrinsic period of the single perturbed neuron and let P_{N-1} denote the network period of the N-1 unperturbed neurons assumed to be oscillating synchronously (*Lemma*). We are interested in the stability of synchrony of the network, where,

following the perturbation of a single neuron, the two resulting oscillators synchronize as

a single network of N oscillators. To obtain a criterion that describes the stability of

synchrony we first define synchrony as a steady-state equilibrium for a discrete linear

map based on perturbation. The stability would then be determined using the eigen value

of the discrete map. Figure 3A shows the intervals that we will use to define the discrete

map. Using the definitions of stimulus interval and response interval, the two main

constraints that are used to construct the discrete map are:

276
$$ts_{N-1}[n] + tr_{N-1}[n] + ts_{N-1}[n+1] = \delta + tr_1[n] + \delta$$

277
$$ts_1[n] + tr_1[n] + ts_1[n+1] = \delta + tr_{N-1}[n] + \delta$$

278 At synchrony, the steady-state intervals (if steady-state exists) would be:

279
$$ts_{N-1}[\infty] + tr_{N-1}[\infty] + ts_{N-1}[\infty] = 2\delta + tr_1[\infty]$$

280
$$ts_1[\infty] + tr_1[\infty] + ts_1[\infty] = 2\delta + tr_{N-1}[\infty]$$

Note that the two constraints have common terms and so we would get a one-dimensional

discrete map.

We also define the phase in the n^{th} cycle as a perturbation from the fixed point φ^*: $\varphi[n] =$

$\varphi^* + \Delta\varphi[n]$. Using the definition of the response interval in terms of the PRC and

linearizing the PRC around the fixed point at the locking phase as $f(\varphi[n]) = f(\varphi^*) +$

$f'(\varphi^*)\Delta\varphi[n]$. Continuing with substitutions along these lines we get a one-dimensional

discrete map as:

288
$$\Delta\varphi_1[n+1] = \left(1 - f'_{1,N-1}(\varphi_1^*) - f'_{N-1,1}(\varphi_{N-1}^*)\right)\Delta\varphi_1[n]$$

where $f'_{i,j}$ are the slopes of the respective PRCs. The detailed derivation of this map can

be found in Appendix A.

For synchrony as a fixed point of this map to be stable, the perturbation must decay

$\Delta\varphi_1[n+1] \to 0$ as n → ∞. To that end, the eigenvalue for the map $\lambda =$

$\left(1 - f'_{1,N-1}(\varphi_1^*) - f'_{N-1,1}(\varphi_{N-1}^*)\right)$ must have an absolute value less than 1. Since the

oscillators are all identical and we know the intrinsic period of a single oscillator, we can

obtain the steady-state phases for each case. Also, since the PRCs are simulated for

each oscillator are computed through simulations, the PRC for the self-connected

unperturbed network $f_{N-1,1}$ becomes a function of the synaptic delay. Thus, we get the

stability criterion:

Eq. 1

300
$$\left| 1 - f'_{1,N-1}\left(\frac{\delta}{P_i}\right) - f'_{N-1,1,\delta}\left(\frac{\delta}{P_i\left(1 + f_{1,N-2}\left(\frac{\delta}{P_i}\right)\right)}\right) \right| < 1$$

The above discussion can be summarized as the following theorem:

Theorem 1: *Stability of Synchrony in a Single Cluster*

If a network of N identical neurons with synaptic delays and each receiving N-1 inputs

achieves synchrony as a steady-state phase-locking mode in the case of a single-neuron

perturbation, then the synchrony is stable if the following criterion holds:

Eq. 1 $\left| 1 - f'_{1,N-1}\left(\frac{\delta}{P_i}\right) - f'_{N-1,1,\delta}\left(\frac{\delta}{P_i\left(1 + f_{1,N-2}\left(\frac{\delta}{P_i}\right)\right)}\right) \right| < 1$

Figure 4 addresses an all-to-all network of 25 identical Via model inhibitory neurons as

described in the Methods. This network was chosen to correspond loosely to the sparsely

connected homogeneous network from [15]. Delays were sampled at intervals of 5 percent

of the period both in the emulator and to apply the stability criterion in Eq. 1.

Fig. 4. Predicted and Observed Periods for Global Synchrony. A. PRC of a single oscillator (blue) in response to a population spike in all other oscillators with E_{GABA} = -75 mV and of a self-connected oscillator representing the rest of the network. The set of points depicted in red color corresponds to three points from each PRC $f_{1,N-1,\delta}$ (φ) parameterized by the delay (equal to the locking phase) to give the slope at each delay δ. * and † indicate the special cases with delays 4.8 ms and 5.1 ms, discussed in the case of existence of self-locking. B. Same as A with shunting reversal potential. C and D. Plots of predicted versus observed time-lags in cases where synchrony was predicted to be stable using Eq.1.

Figs. 4A (E_{GABA} = -75 mV) and 4B (E_{GABA} = -55 mV) depict the PRCs of both oscillators

in Fig. 3B due to perturbation by each other (Fig. 3B). The curve in blue represents the

PRC of the single perturbed neuron due to the self-connected cluster $f_{1,N-1}$ (φ)

representing the rest of he network. Since the PRCs for the self-connected oscillator are

parametrized by the delay, the sets of points depicted in red color correspond to three

points sampled around the locking phase (equal to the normalized feedback delay) in

order to calculate the slope of the PRC $f_{1,N-1,\delta}(\varphi)$ for each delay δ.

Fig. 4C and 4D show that the time lags between the firing of oscillators predicted by the

criterion Eq.1 match with the time lags observed from the emulator simulations when

synchrony is predicted. To the right of the dashed line in Fig. 4A and C, we have not used

the emulator map to test due one of the following reasons:

1. *Unstable synchrony predicted:* For the cases with delays 5.4 ms and 5.7 m, the

eigen value of the discrete map calculated using Eq. 1 is greater than 1, indicating

that the synchrony, if exists, is unstable. This means that unless the oscillators are

initialized to be already in synchrony, they would not fire in synchrony and any

perturbation would disrupt their synchrony. The reason is that the respective

slopes of PRCs are negative. Therefore, although the respective PRCs $f_{1,N-1,\delta}(\varphi)$

have been calculated and plotted (red point-traces in Fig 4C), the predicted and

observed periods are not plotted since synchrony is not observed when tested in

the emulator.

2. *Phase-locking did not exist:* For the case with delay 5.1 ms, we saw from the

lemma that the self-connected oscillator would not be able to phase-lock. The

discontinuity in the second-order resetting is the cause for this situation. Periodicity

of spiking was not observed and as a result the PRC $f_{1,N-1,\delta}(\varphi)$ could not be

measured for this case. Therefore, the criterion in Eq. 1 is not applicable to this

case. This is denoted by * in Fig. 4A.

3. Phase-locking was predicted to exist, but periodicity was not observed: For the

case with delay 4.8 ms, we saw that even though the existence of self-locking was

predicted, periodicity was not observed in simulations. As a result, here too the

PRC $f_{1,N-1,\delta}$ (φ) could not be measured and therefore the criterion in Eq. 1 is not

applicable to this case. This is denoted by a dagger **†** in Fig. 4A.

In case of the figures 4B and 4D, the existence of self-locking was established for all

delays (data not shown). The dashed-line dividers in figures 4B and 4D only indicate the

delays where the stability criterion given by Eq. 1 has an eigen value greater than 1. The

reason for this is the negative slope in PRCs.

Although both reversal potential values are physiologically plausible [31], they result in

vastly different phase resetting curves. In contrast to the hyperpolarizing case, for

shunting inhibition there is both a lower and an upper bound on the delays that support

stable synchrony because there are two regions of negative slope in the PRC, which

make synchrony unstable. In the regions that did not support stable synchrony, we did

not observe synchrony when tested in the emulator.

Fig 5. Multiple-Neuron Perturbation and Eigen Values. A. Depiction of the two oscillators when M neurons are perturbed. Both the clusters are assumed to receive delayed synchronous feedback from themselves without autapses. B. For a fixed delay of 0.3 ms in the example where shunting inhibition is used, the figure shows slopes and eigenvalues plotted against the number of neurons perturbed from the network (M).

3.4 Extension of the results for perturbation of more than one neuron:

Instead of perturbing just a single neuron, if we perturb more than one, the second

oscillator becomes another self-connected cluster. Figure 5A shows the two oscillators

and their connections when M neurons are perturbed from a cluster of N neurons. The

unperturbed cluster contains N-M neurons with N-M-1 self-connections, whereas the

perturbed cluster with M neurons receives M-1 inputs due to self-connections. Extending

Eq.1 to the perturbation for M neurons ($1 \leq M \leq N$), we get a generalized criterion:

Eq. 2

362
$$\left| 1 - f'_{M,N-M,\delta}\left(\frac{\delta}{P_i\left(1 + f_{1,M-1}(\delta/P_i)\right)} \right) - f'_{N-M,M,\delta}\left(\frac{\delta}{P_i\left(1 + f_{1,N-M-1}(\delta/P_i)\right)} \right) \right| < 1$$

From the equation above, we see that in the multiple-neuron perturbation case, the PRCs

of both oscillators are functions of the delay. Further, we wanted to check if the

assumption that the single neuron perturbation from the network is the most destabilizing

(Canavier and Achuthan, 2010) holds even in the presence of delays and self-

connections. To that end, we took the specific case from the model (considered above)

with shunting inhibition and a delay of 0.3 ms which had the greatest eigenvalue greater

than 1 for a single neuron perturbation case. To this, we varied the number of perturbed

Fig 6. Firing intervals for perturbation of Two Cluster Network. Schematic firing pattern in which a single neuron is perturbed from one cluster in the two-cluster case. These intervals are used to derive the discrete map through which a stability criterion of the two-cluster solution is established.

neurons from the network of 25 between M = 2 and M = 12. In each case, we used Eq. 2

to obtain the eigen value of the discrete map that suggests stability. The plot of slopes

and eigenvalues in each case can be found in Figure 5B. From the empirical observations,

we see that for all perturbations including 1 till 12, the eigenvalues do not drastically

change, indicating that for this case, the perturbing any number of neurons could

determine the stability of synchrony of the all-to-all network.

3.5 Extension of the results for alternating firing of two nonidentical clusters without delay

to include delays:

Previously, we showed how an alternating firing pattern between two clusters, A and B,

can enforce synchrony within each cluster, even if neither cluster is capable of

synchronizing in isolation [32]. The key is the multiplicative nature of the factors that scale

the perturbation in separate intervals. We assume once again that the perturbation of a

single neuron from a fully synchronized cluster is the most destabilizing perturbations

(one such perturbation is illustrated in Fig. 6.) A two-cluster mode cannot be presumed to

exist but must satisfy the existence criteria determined by the firing intervals in Fig. 5.

The existence criterion is simply that [12] $tr_A[\infty] + 2\delta = ts_B[\infty]$ and $tr_B[\infty] + 2\delta = ts_A[\infty]$,

where the stimulus and response intervals in the steady 1:1 phase locked mode are

determined by the phase response curves.

Unlike global synchrony, this system cannot be reduced to a single coupled map. Instead,

due to the presence of three oscillators, we get a two-dimensional discrete map leading

to two eigen values. Based on figure 6, like the global synchrony case, the constraints

that lead to the map are:

$$2\delta + tr_{A-1}[n] = ts_{B,1}[n] + ts_{B,A-1}[n] \qquad (1)$$

$$ts_{B,1}[n] = \delta + tr_{A-1}[n] + ts_{A-1,1}[n+1] \qquad (2)$$

394
$$ts_{A-1,B}[n+1] = ts_{B,A-1}[n] + tr_B[n] + \delta \quad (3)$$

395
$$ts_{1,B}[n+1] = tr_B[n] + \delta \quad (4)$$

396
$$ts_{B,1}[n] = 2\delta + tr_1[n] \quad (5)$$

397
$$ts_{1,A-1}[n+1] = \delta + ts_{B,A-1}[n] \quad (6)$$

The derivation of the 2-dimensional discrete map and the discussion leading up to the

eigen values can be found in Appendix -B. Based on the two eigenvalues, we get two

criteria. For a perturbation of a single neuron from cluster A (illustrated in Fig. 4), one

criterion is

Eq. 3 $$-1 < (1 - f'_{A,B}(\varphi_A))\left(1 - f'_{1,A-1}\left(\frac{\delta}{P_1}\right) - f'_{A-1,1}\left(\frac{\delta}{P_{A-1}}\right)\right) < 1$$

in which the large parentheses enclose the within cluster synchrony term for cluster A

and is scaled by the term representing forcing of cluster A by cluster B: $1 - f'_{A,B}(\varphi_A)$.

Another criterion, consisting solely of between cluster terms is

Eq. 4 $$-1 < (1 - f'_{A,B}(\varphi_A))(1 - f'_{B,A-1}(\varphi_B))(1 - f'_{B,1}(\varphi_B)) < 1$$

To test the predictions in the two-cluster case, we considered the inhibitory neurons used

in the global synchrony case as one cluster, and the RTM model of excitatory neurons

described in methods as the second cluster. Unlike the network of inhibitory neurons, the

excitatory neurons are not assumed to be self-connected, as is the case for excitatory

neurons in layer 2/3 entorhinal cortex [33]. Therefore, we consider the whole cluster of

excitatory neurons as a single oscillator that is firing in synchrony (denoted by B in Fig.

6). Since this testing is essentially meant to understand the

influence of the second cluster on the existing cluster that cannot

synchronize by itself, we considered the inhibitory neurons with

shunting reversal potential at a delay of 0.3ms, which denotes

the most destabilizing case for the cluster of inhibitory neurons.

Figures 7A1 shows the output from the emulator depicting how

the oscillators do not synchronize when a single neuron is

perturbed from the inhibitory cluster at the aforementioned delay.

The arrows in the figure 7A2 of PRCs show how the negative

slopes of the PRCs influence the eigenvalue (Eq.1) to be 1.75

(greater than 1 denotes unstable synchrony).

However, when we add the cluster of excitatory neurons, from

the emulator results shown in figure 7B1, we see that the two

oscillators of the inhibitory cluster fire synchronously. The PRCs

as shown in figure 7B2 in fact show that the phase at which the

excitatory input reaches the inhibitory neurons is highly

stabilizing (with its slope almost 1). Thus, from Eq.3, we see that

the forcing term dominates the effect of the single-neuron

perturbation within the cluster.

Figure 7. **Two cluster synchrony A**. A self-connected cluster of A neurons (red) cannot synchronize itself when one neuron (blue) is perturbed because the slopes of the PRCs at the locking point are negative. **B**. Mutual coupling to a population of excitatory cells (green) enforces synchrony.

4. Discussion

4.1 Generality: The results presented herein generalize to any system of pulse-coupled

oscillators with delays including synchronization of fireflies [5], cardiac pacemaker cells

[34–36], circadian rhythms [24] and in the engineering application of pulse-coupled

sensor networks [37–40].

4.2 Role of Delays in Neuronal Networks: In the nervous system, there is always a delay

between an action potential in the pre-synaptic neuron and the postsynaptic potential

observed at chemical synapses, due to the time required for an action potential to

propagate from the axon initial segment to the axonal terminal and for the

neurotransmitter to diffuse across the synaptic cleft and bind to the post-synaptic

ionotropic receptors [41]. Delays in synchronization of inhibitory networks have previously

been shown to promote synchrony [42,43]. The innovation herein is to use delayed self-

connections to represent breaking the network into smaller clusters to rigorously

determine the stability of one and two-cluster synchrony.

4.3 *Discontinuity in the PRC:* Discontinuous PRCs have been previously observed

[44,45]. Although the dynamical system representing the oscillator is continuous, the use

of events such as the action potential to define the windows within which phase resetting

occurs allows for discontinuities in the PRC. For example, the discontinuity at late phases

in Fig. 1B occurs at the phase at which the perturbation cannot hyperpolarize the neuron

sufficiently to stop the action potential from occurring, and the bulk of its effect occurs in

the next oscillation cycle, resulting in second order resetting instead. The curves for both

first and second order resetting are discontinuous. Basically, the PRC function become

discontinuous for inputs that arrive at a later phase. We can observe that for such inputs,

the second order resetting is greater than the first order resetting. However, this increase

in second order resetting also is after a discontinuity. In fact, this discontinuity accounts

for the non-existence of phase-locking of self-connected oscillator when the inputs arrive

after a delay of 5.1 ms. As a result the slope of the PRC becomes undefined at those

points and so phase locking does not exist at phases that fall in the discontinuity.

However, it is clear that this discontinuity is highly repelling [43,46].

4.4 Higher-Order Phase Resetting: In the criterion for existence of phase-locking in a self-

connected oscillator, we included second order resetting into the stimulus interval of the

first cycle following the perturbation [11]. Otherwise, here we ignore the second-order

resetting, or any other higher order resetting. It does not seem possible to incorporate

third and higher order resetting into our simple pulsatile coupling framework, which is a

limitation our methods. Others [47] have considered the case in which an oscillator does

not return to its original limit cycle by the time the next input is received .

4.5 Perturbation of a single neuron from a cluster versus multiple neurons: From the

empirical results in Fig. 5 for the case of all-to-all network synchrony, we saw that the

eigenvalues of the discrete map did not depend strongly on the the number of neurons

perturbed from global synchrony.   In order to guarantee stability, in some small

neighborhood around the fixed point of the map, synchrony must be robust to all possible

perturbations. Therefore, if any specific perturbation is predicted to grow rather than

decay, synchrony is unstable. However, the simplest perturbation (Eq. 1), that of a single

neuron from a stable cluster, may provide useful insights regarding whether a system can

synchronize, although technically Eq. 2 must also be considered.

4.6 Applications to Neural Oscillations: There are numerous examples in the literature

about how populations of excitatory neurons can synchronize themselves via mutual

coupling with populations of inhibitory neurons [48–51] in a type of brain rhythm called

pyramidal interneuronal network gamma (PING). Many of these mechanisms assume

that the excitatory neurons are driven above threshold (mean driven) but inhibitory

neurons are quiescent in the absence of excitation via their local excitatory neuron

partners [52], whereas other assume that both populations are in the fluctuation driven

regime below threshold [53–55]. We propose a third mechanism by which the excitatory

cells can synchronize tonically firing interneurons that cannot synchronize themselves, as

in Fig. 7. During theta oscillations, the firing rate of fast spiking interneuron increases [56],

thus it is possible that interneurons are in the mean driven regime during theta nested

gamma. In optogenetically-driven theta-nested gamma in a slice preparation [57], the

interneurons are indeed tonically active during the peak of theta with excitation blocked.

In that study, the interneurons only synchronized with excitation intact. Under similar

optogenetic drive, we have observed some gamma synchrony in the absence of

excitation; however, recruiting excitatory cells into optogenetically-driven theta nested

gamma [58] increases gamma power, perhaps by a similar mechanism as in Fig. 7.

5. Conclusions

We extended our previous criteria for stability of one and two cluster synchrony in

networks of pulse-coupled oscillators to include conduction delays shorter than the

intrinsic period using self-connected oscillators to represent perturbed clusters of

oscillators. We also showed that second order resetting can prevent the existence of self-

locked synchrony, which is a prerequisite for the application of the stability criteria we

present.

Acknowledgements

This work was funded by NIH R01NS054281 to CCC. The funding agency had no role in

the collection, analysis and interpretation of data, in the writing of the report or in the

decision to submit the article for publication.

Conflict of Interest

The authors declare no conflict of interest.

509
References

[1] G.B. Ermentrout, C.C. Chow, Modeling neural oscillations, Physiol. Behav. 77
(2002) 629–633.
[2] F. Núñez, Y. Wang, A.R. Teel, F.J. Doyle, Synchronization of pulse-coupled
oscillators to a global pacemaker, Syst. Control Lett. 88 (2016) 75–80.
https://doi.org/10.1016/j.sysconle.2015.11.007.
[3] G.B. Ermentrout, N. Kopell, Multiple pulse interactions and averaging in systems of
coupled neural oscillators, J. Math. Biol. 29 (1991) 195–217.
https://doi.org/10.1007/BF00160535.
[4] J. Rinzel, G.B. Ermentrout, Analysis of neural excitability and oscillations, Methods
Neuronal Model. Ions Netw. 2 (1998) 251–291.
[5] R.E. Mirollo, S.H. Strogatz, Synchronization of Pulse-Coupled Biological
Oscillators, SIAM J. Appl. Math. 50 (1990) 1645–1662.
https://doi.org/10.1137/0150098.
[6] C.C. Canavier, S. Achuthan, Pulse coupled oscillators and the phase resetting
curve, Math. Biosci. 226 (2010) 77–96. https://doi.org/10.1016/j.mbs.2010.05.001.
[7] N. Brunel, D. Hansel, How Noise Affects the Synchronization Properties of
Recurrent Networks of Inhibitory Neurons, Neural Comput. 18 (2006) 1066–1110.
[8] C.D. Acker, N. Kopell, J.A. White, Synchronization of strongly coupled excitatory
neurons: relating network behavior to biophysics, J. Comput. Neurosci. 15 (2003)
71–90. https://doi.org/10.1023/a:1024474819512.
[9] P. Malerba, N. Kopell, Phase resetting reduces theta–gamma rhythmic interaction
to a one-dimensional map, J. Math. Biol. 66 (2013) 1361–1386.
https://doi.org/10.1007/s00285-012-0534-9.
[10] D.H. Perkel, J.H. Schulman, T.H. Bullock, G.P. Moore, J.P. Segundo,
PACEMAKER NEURONS: EFFECTS OF REGULARLY SPACED SYNAPTIC
INPUT, Science. 145 (1964) 61–63. https://doi.org/10.1126/science.145.3627.61.
[11] S. Achuthan, C.C. Canavier, Phase-Resetting Curves Determine Synchronization,
Phase Locking, and Clustering in Networks of Neural Oscillators, J. Neurosci. 29
(2009) 5218–5233. https://doi.org/10.1523/JNEUROSCI.0426-09.2009.

[12] M.M. Woodman, C.C. Canavier, Effects of conduction delays on the existence and
stability of one to one phase locking between two pulse-coupled oscillators, J.
Comput. Neurosci. 31 (2011) 401–418. https://doi.org/10.1007/s10827-011-0315-2.
[13] R.O. Dror, C.C. Canavier, R.J. Butera, J.W. Clark, J.H. Byrne, A mathematical
criterion based on phase response curves for stability in a ring of coupled
oscillators, Biol. Cybern. 80 (1999) 11–23. https://doi.org/10.1007/s004220050501.
[14] S.A. Oprisan, A.A. Prinz, C.C. Canavier, Phase resetting and phase locking in
hybrid circuits of one model and one biological neuron, Biophys. J. 87 (2004)
2283–2298. https://doi.org/10.1529/biophysj.104.046193.
[15] G. Via, R. Baravalle, F.R. Fernandez, J.A. White, C.C. Canavier, Interneuronal
network model of theta-nested fast oscillations predicts differential effects of
heterogeneity, gap junctions and short term depression for hyperpolarizing versus
shunting inhibition, PLOS Comput. Biol. 18 (2022) e1010094.
https://doi.org/10.1371/journal.pcbi.1010094.
[16] A.L. Hodgkin, The local electric changes associated with repetitive action in a non-
medullated axon, J. Physiol. 107 (1948) 165–181.
[17] A.L. Hodgkin, A.F. Huxley, A quantitative description of membrane current and its
application to conduction and excitation in nerve, J. Physiol. 117 (1952) 500–544.
[18] D.A. Baxter, C.C. Canavier, J.H. Byrne, CHAPTER 7 - Dynamical Properties of
Excitable Membranes, in: J.H. Byrne, J.L. Roberts (Eds.), Mol. Netw., Academic
Press, Burlington, 2004: pp. 161–196. https://doi.org/10.1016/B978-012148660-
0/50008-1.
[19] A. Erisir, D. Lau, B. Rudy, C.S. Leonard, Function of Specific K+ Channels in
Sustained High-Frequency Firing of Fast-Spiking Neocortical Interneurons, J.
Neurophysiol. 82 (1999) 2476–2489. https://doi.org/10.1152/jn.1999.82.5.2476.
[20] D. Golomb, K. Donner, L. Shacham, D. Shlosberg, Y. Amitai, D. Hansel,
Mechanisms of Firing Patterns in Fast-Spiking Cortical Interneurons, PLOS
Comput. Biol. 3 (2007) e156. https://doi.org/10.1371/journal.pcbi.0030156.
[21] F.R. Fernandez, G. Via, C.C. Canavier, J.A. White, Kinetics and Connectivity
Properties of Parvalbumin- and Somatostatin-Positive Inhibition in Layer 2/3 Medial
Entorhinal Cortex, eNeuro. 9 (2022). https://doi.org/10.1523/ENEURO.0441-
21.2022.
[22] R.D. Traub, R. Miles, Neuronal Networks of the Hippocampus, Cambridge
University Press, 1991.
[23] C. Börgers, Three Simple Models of Neurons in Rodent Brains, in: C. Börgers
(Ed.), Introd. Model. Neuronal Dyn., Springer International Publishing, Cham, 2017:
pp. 31–37. https://doi.org/10.1007/978-3-319-51171-9_5.
[24] A.T. Winfree, The Geometry of Biological Time, Springer London, Limited, 1990.
[25] V.V. Klinshov, V.I. Nekorkin, The map with no predetermined firing order for the
network of oscillators with time-delayed pulsatile coupling, Commun. Nonlinear Sci.
Numer. Simul. 18 (2013) 973–977. https://doi.org/10.1016/j.cnsns.2012.09.012.
[26] R. Goebel, R.G. Sanfelice, A.R. Teel, Hybrid Dynamical Systems: Modeling,
Stability, and Robustness, Princeton University Press, 2012.
http://www.barnesandnoble.com/w/hybrid-dynamical-systems-rafal-
goebel/1120733646 (accessed April 1, 2015).

[27] J.A. White, C.C. Chow, J. Ritt, C. Soto-Treviño, N. Kopell, Synchronization and
586    oscillatory dynamics in heterogeneous, mutually inhibited neurons, J. Comput.
587    Neurosci. 5 (1998) 5–16.
588 [28] J. Foss, J. Milton, Multistability in recurrent neural loops arising from delay, J.
589    Neurophysiol. 84 (2000) 975–985. https://doi.org/10.1152/jn.2000.84.2.975.
590 [29] M. Golubitsky, I. Stewart, Nonlinear dynamics of networks: the groupoid formalism,
591    Bull. Am. Math. Soc. 43 (2006) 305–365. https://doi.org/10.1090/S0273-0979-06-
592    01108-6.
593 [30] C.C. Canavier, S. Achuthan, History of the application of the phase resetting curve
594    to neurons coupled in a pulsatile manner, in: N.W. Schultheiss, A.A. Prinz, R.J.
595    Butera (Eds.), Phase Response Curves Neurosci., Springer New York, New York,
596    NY, 2012: pp. 73–91. http://link.springer.com/10.1007/978-1-4614-0739-3
597    (accessed September 25, 2015).
598 [31] Y. Otsu, F. Donneger, E.J. Schwartz, J.C. Poncer, Cation–chloride cotransporters
599    and the polarity of GABA signalling in mouse hippocampal parvalbumin
600    interneurons, J. Physiol. 598 (2020) 1865–1880. https://doi.org/10.1113/JP279221.
601 [32] L. Chandrasekaran, S. Achuthan, C. Canavier, Stability of two cluster solutions in
602    pulse coupled networks of neural oscillators, J. Comput. Neurosci. 30 (2011) 427–
603    445.
604 [33] J.J. Couey, A. Witoelar, S.-J. Zhang, K. Zheng, J. Ye, B. Dunn, R. Czajkowski, M.-
605    B. Moser, E.I. Moser, Y. Roudi, M.P. Witter, Recurrent inhibitory circuitry as a
606    mechanism for grid formation, Nat. Neurosci. 16 (2013) 318–324.
607    https://doi.org/10.1038/nn.3310.
608 [34] C.S. Peskin, Mathematical aspects of heart physiology, Courant Institute of
609    Mathematical Sciences, New York University, 1975.
610 [35] M.R. Guevara, A. Shrier, L. Glass, Phase resetting of spontaneously beating
611    embryonic ventricular heart cell aggregates, Am. J. Physiol. 251 (1986) H1298-
612    1305. https://doi.org/10.1152/ajpheart.1986.251.6.H1298.
613 [36] M.R. Guevara, L. Glass, Phase locking, period doubling bifurcations and chaos in a
614    mathematical model of a periodically driven oscillator: a theory for the entrainment
615    of biological oscillators and the generation of cardiac dysrhythmias, J. Math. Biol.
616    14 (1982) 1–23. https://doi.org/10.1007/BF02154750.
617 [37] J. Nishimura, E.J. Friedman, Robust convergence in pulse-coupled oscillators with
618    delays, Phys. Rev. Lett. 106 (2011) 194101.
619    https://doi.org/10.1103/PhysRevLett.106.194101.
620 [38] Y. Wang, F. Nunez, F.J. Doyle, Statistical analysis of the pulse-coupled
621    synchronization strategy for wireless sensor networks, IEEE Trans. Signal Process.
622    61 (2013) 5193–5204. https://doi.org/10.1109/TSP.2013.2275511.
623 [39] Y. Wang, K. Mosalakanti, F. Núñez, S. Deligeorges, F.J. Doyle, A kernel module
624    for pulse-coupled time synchronization of sensor networks, Comput. Netw. 127
625    (2017) 161–172. https://doi.org/10.1016/j.comnet.2017.08.009.
626 [40] F. Núñez, Y. Wang, A.R. Teel, F.J. Doyle, Synchronization of pulse-coupled
627    oscillators to a global pacemaker, Syst. Control Lett. 88 (2016) 75–80.
628    https://doi.org/10.1016/j.sysconle.2015.11.007.
629 [41] E.R. Kandel, J.H. Schwartz, T.M. Jessell, Principles of Neural Science, 4 edition,
630    McGraw-Hill Medical, New York, 2000.

631   [42] N. Roohi, A. Valizadeh, Role of Interaction Delays in the Synchronization of
632   Inhibitory Networks, Neural Comput. 34 (2022) 1425–1447.
633   https://doi.org/10.1162/neco_a_01500.
634   [43] R.A. Tikidji-Hamburyan, C.A. Leonik, C.C. Canavier, Phase Response Theory
635   Explains Cluster Formation in Sparsely but Strongly Connected Inhibitory Neural
636   Networks and Effects of Jitter due to Sparse Connectivity, J. Neurophysiol. (2019).
637   https://doi.org/10.1152/jn.00728.2018.
638   [44] L. Glass, A.T. Winfree, Discontinuities in phase-resetting experiments, Am. J.
639   Physiol. 246 (1984) R251-258.
640   [45] T. Krogh-Madsen, L. Glass, E.J. Doedel, M.R. Guevara, Apparent discontinuities in
641   the phase-resetting response of cardiac pacemakers, J. Theor. Biol. 230 (2004)
642   499–519. https://doi.org/10.1016/j.jtbi.2004.03.027.
643   [46] C.C. Canavier, R.A. Tikidji-Hamburyan, Globally attracting synchrony in a network
644   of oscillators with all-to-all inhibitory pulse coupling, Phys. Rev. E. 95 (2017)
645   032215. https://doi.org/10.1103/PhysRevE.95.032215.
646   [47] V. Klinshov, S. Yanchuk, A. Stephan, V. Nekorkin, Phase response function for
647   oscillators with strong forcing or coupling, Europhys. Lett. 118 (2017) 50006.
648   https://doi.org/10.1209/0295-5075/118/50006.
649   [48] M.A. Whittington, R.D. Traub, J.G. Jefferys, Synchronized oscillations in
650   interneuron networks driven by metabotropic glutamate receptor activation, Nature.
651   373 (1995) 612–615.
652   [49] A. Fisahn, F.G. Pike, E.H. Buhl, O. Paulsen, Cholinergic induction of network
653   oscillations at 40 Hz in the hippocampus in vitro, Nature. 394 (1998) 186–189.
654   https://doi.org/10.1038/28179.
655   [50] M. Bartos, I. Vida, P. Jonas, Synaptic mechanisms of synchronized gamma
656   oscillations in inhibitory interneuron networks, Nat. Rev. Neurosci. 8 (2007) 45–56.
657   https://doi.org/10.1038/nrn2044.
658   [51] P. Tiesinga, T.J. Sejnowski, Cortical enlightenment: are attentional gamma
659   oscillations driven by ING or PING?, Neuron. 63 (2009) 727–732.
660   https://doi.org/10.1016/j.neuron.2009.09.009.
661   [52] C. Börgers, N. Kopell, Synchronization in networks of excitatory and inhibitory
662   neurons with sparse, random connectivity, Neural Comput. 15 (2003) 509–538.
663   https://doi.org/10.1162/089976603321192059.
664   [53] N. Brunel, X.-J. Wang, What determines the frequency of fast network oscillations
665   with irregular neural discharges? I. Synaptic dynamics and excitation-inhibition
666   balance, J. Neurophysiol. 90 (2003) 415–430.
667   https://doi.org/10.1152/jn.01095.2002.
668   [54] C. Geisler, N. Brunel, X.-J. Wang, Contributions of intrinsic membrane dynamics to
669   fast network oscillations with irregular neuronal discharges, J. Neurophysiol. 94
670   (2005) 4344–4361. https://doi.org/10.1152/jn.00510.2004.
671   [55] G. Buzsáki, X.-J. Wang, Mechanisms of gamma oscillations, Annu. Rev. Neurosci.
672   35 (2012) 203–225. https://doi.org/10.1146/annurev-neuro-062111-150444.
673   [56] D. Lapray, B. Lasztoczi, M. Lagler, T.J. Viney, L. Katona, O. Valenti, K. Hartwich,
674   Z. Borhegyi, P. Somogyi, T. Klausberger, Behavior-dependent specialization of
675   identified hippocampal interneurons, Nat. Neurosci. 15 (2012) 1265–1271.
676   https://doi.org/10.1038/nn.3176.

[57] H. Pastoll, L. Solanka, M.C.W. van Rossum, M.F. Nolan, Feedback inhibition
enables θ-nested γ oscillations and grid firing fields, Neuron. 77 (2013) 141–154.
https://doi.org/10.1016/j.neuron.2012.11.032.
[58] B. Williams, F.R. Fernandez, C.C. Canavier, J.A. White, Synaptic mechanisms of
theta-nested gamma oscillations in the medial entorhinal cortex, (2023).
https://www.abstractsonline.com/pp8/#!/10892/presentation/33250 (accessed
December 1, 2023).

Appendix A: Derivation for Stability of Synchrony in an All-to-All Network

Let P_1 and P_{N-1} be the intrinsic periods of the two pulse-coupled oscillators. Figure 3A and 3B describe the nature, connections and intervals of both the oscillators. Based on the figure, the cluster with $N-1$ neurons is treated as a single oscillator labelled $N-1$ as it is assumed to be oscillating in synchrony, in which case, P_{N-1} denotes the network period at which each neuron oscillates. A necessary condition for stability of synchrony in a network of N oscillators is that it be robust to perturbing even one of them. Perturbing a single neuron from a synchronous cluster introduces the perturbation into all affected intervals (Figure 3B). The goal is to define a discrete linear map and arrive at the stability criterion based on the eigen values of this map.

As defined earlier, $ts_i[k]$ stands for the *Stimulus Interval* of the i^{th} oscillator in its k^{th} cycle. $tr_i[k]$ stands for the *Response Interval* of the i^{th} oscillator in its k^{th} cycle. The *Phase* of the oscillator i in its k^{th} cycle is defined as

$$\varphi_i[k] = \frac{ts_i[k]}{P_i}$$

Thus, from the definitions given earlier, the *Stimulus Interval* of the i^{th} oscillator in its k^{th} cycle can be expanded as:

$$ts_i[k] = P_i \varphi_i[k]$$

and, the *Response Interval* of the i^{th} oscillator in its k^{th} cycle as

$$tr_i[k] = P_i(1 - \varphi_i[k] - f_{i,j}(\varphi_i[k])$$

706 where $f_{i,j}(\varphi_i[k])$ is the *Phase Resetting Curve* of the i^{th} oscillator due to the input from

707 j^{th} oscillator in its k^{th} cycle. We ignore second order resetting for this criterion. Figure 3A

708 shows schematically the perturbation and the intervals defined for each of the oscillators

709 in their n^{th} cycle.

710 From the figure 3A above, the two main constraints that relate the intervals of the two

711 oscillators can be written as

712
$$ts_{N-1}[n] + tr_{N-1}[n] + ts_{N-1}[n+1] = \delta + tr_1[n] + \delta \text{ (1)}$$

713
$$ts_1[n] + tr_1[n] + ts_1[n+1] = \delta + tr_{N-1}[n] + \delta \qquad \text{(2)}$$

714 Further, based on the figure, we get an additional constraint given by:

715
$$ts_{N-1}[n] + tr_{N-1}[n] + \delta = \delta + tr_1[n] + ts_1[n+1] \qquad \text{(3)}$$

716 Simplifying the above constraint (3),

717
$$ts_{N-1}[n] + tr_{N-1}[n] = tr_1[n] + ts_1[n+1]$$

718 Now, expanding the intervals in the above equation using the definitions of the stimulus

719 and response intervals of each oscillator, we get

720
$$P_{N-1}\left(1 + f_{N-1,1}(\varphi_{N-1}[n])\right) = P_1\left(1 - \varphi_1[n] + f_{1,N-1}(\varphi_1[n])\right) + P_1\varphi_1[n+1] \text{ (4)}$$

721 As mentioned earlier, we consider the synchrony to be the equilibrium state or steady

722 state of the discrete map and thus using the definitions of phase at steady state, equation

723 (4) becomes

724
$$P_{N-1}\left(1 + f_{N-1,1}(\varphi_{N-1}^*)\right) = P_1\left(1 + f_{1,N-1}(\varphi_1^*)\right) \qquad \text{(5)}$$

Now, using the phase approximation from the steady state and the linearized PRC about

the steady state, equation (5) becomes

$$P_{N-1}\big(1 + f_{N-1,1}(\varphi_{N-1}^*) + f_{N-1,1}'(\varphi_{N-1}^*)\Delta\varphi_{N-1}[n]\big)$$

$$= P_1\big(1 - \varphi_1^* - \Delta\varphi_1[n] + f_{1,N-1}(\varphi_1^*) + f_{1,N-1}'(\varphi_1^*)\Delta\varphi_1[n]\big) + P_1\varphi_1^*$$

$$+ P_1\Delta\varphi_1[n+1]$$

Denoting $m_1 = f_{1,N-1}'(\varphi_1^*)$, $m_{N-1} = f_{N-1,1}'(\varphi_{N-1}^*)$, and cancelling the terms and using the

steady state equation (5), we get

$$\Delta\varphi_{N-1}[n] = \frac{P_1}{P_{N-1}}\frac{1}{m_{N-1}}\big[(m_1 - 1)\Delta\varphi_1[n] + \Delta\varphi_1[n+1]\big] \quad (6)$$

Now, let us consider the main constraint (2). Rearranging the equation, we get

$$ts_1[n+1] = tr_{N-1}[n] + 2\delta - (ts_1[n] + tr_1[n])$$

Expressing the intervals in the above equation using phases and PRCs, we get

$$P_1(\varphi_1[n+1]) = P_{N-1}\Big(1 - \varphi_{N-1}[n] + f_{N-1,1}(\varphi_{N-1}[n])\Big) + 2\delta - P_1\Big(1 + f_{1,N-1}(\varphi_1[n])\Big)$$

At steady state, the above equation would be

$$P_1(\varphi_1^*) = P_{N-1}\Big(1 - \varphi_{N-1}^* + f_{N-1,1}(\varphi_{N-1}^*)\Big) + 2\delta - P_1\Big(1 + f_{1,N-1}(\varphi_1^*)\Big)$$

Now, approximating the phases about the steady state and linearizing the PRCs we get

$$P_1(\varphi_1^* + \Delta\varphi_1[n+1])$$

$$= 2\delta$$

$$+ P_{N-1}\big(1 - \varphi_{N-1}^* - \Delta\varphi_{N-1}[n] + f_{N-1,1}(\varphi_{N-1}^*) + f_{N-1,1}'(\varphi_{N-1}^*)\Delta\varphi_{N-1}[n]\big)$$

$$- P_1\big(1 + f_{1,N-1}(\varphi_1^*) + f_{1,N-1}'(\varphi_1^*)\Delta\varphi_1[n]\big)$$

Again, using the steady state equation and cancelling the terms, and denoting the

slopes of the PRCs using m_1 and m_{N-1}, we get

$$P_1(\Delta\varphi_1[n+1]) = P_{N-1}(m_{N-1}-1)\Delta\varphi_{N-1}[n] - P_1 m_1 \Delta\varphi_1[n]$$

Rearranging, we get

$$\Delta\varphi_1[n+1] = \frac{P_{N-1}}{P_1}(m_{N-1}-1)\Delta\varphi_{N-1}[n] - m_1\Delta\varphi_1[n] \quad (9)$$

Now, substituting the expression for $\Delta\varphi_{N-1}[n]$ from equation (6) into equation (9), we

get

$$\Delta\varphi_1[n+1] = \frac{P_{N-1}}{P_1}(m_{N-1}-1)\left\{\frac{P_1}{P_{N-1}}\frac{1}{m_{N-1}}\left((m_1-1)\Delta\varphi_1[n] + \Delta\varphi_1[n+1]\right)\right\} - m_1\Delta\varphi_1[n]$$

The periods get cancelled and multiplying the term m_{N-1} to the whole equation we get

$$m_{N-1}\Delta\varphi_1[n+1] = (m_{N-1}-1)[(m_1-1)\Delta\varphi_1[n] + \Delta\varphi_1[n+1]] - m_{N-1}m_1\Delta\varphi_1[n]$$

Rearranging the terms, we get

$$\Delta\varphi_1[n+1] = (m_{N-1}-1)(m_1-1)\Delta\varphi_1[n] - m_{N-1}m_1\Delta\varphi_1[n]$$

Simplifying the terms, we finally get the discrete linear map for the perturbation of the

single oscillator that is perturbed:

$$\Delta\varphi_1[n+1] = (1 - m_1 - m_{N-1})\Delta\varphi_1[n] \quad (10)$$

The delay for a synchronous network can be calculated by substituting the delay δ for

both the delays in equations (1) and (2) and solving for δ. Thus, we get,

763
$$\varphi_1^* = \frac{ts_1[\infty]}{P_1} = \frac{\delta}{P_1}$$

764
$$\varphi_{N-1}^* = \frac{ts_{N-1}[\infty]}{P_{N-1}} = \frac{\delta}{P_1\left(1 + f_{1,N-2}(\delta/P_1)\right)}$$

765   Substituting the values for the slopes of the PRCs, the map at a synchronous state is

766   given by

767
$$\Delta\varphi_1[n+1] = 1 - f'_{1,N-1}\left(\frac{\delta}{P_i}\right) - f'_{N-1,1}\left(\frac{\delta}{P_1\left(\left(1 + f_{1,N-2}(\delta/P_1)\right)\right)}\right)$$

768   Since the PRC $f_{N-1,1}$ is measured by simulating the unperturbed cluster using self-

769   connections and delay, the slope $f'_{N-1,1}$ becomes a function of delay and thus the map

770   becomes:

771
$$\Delta\varphi_1[n+1] = 1 - f'_{1,N-1}\left(\frac{\delta}{P_i}\right) - f'_{N-1,1,\delta}\left(\frac{\delta}{P_1\left(\left(1 + f_{1,N-2}(\delta/P_1)\right)\right)}\right)$$

          Appendix B: Derivation for Stability of Clusters with Delays

From figure 5, we see that oscillators denoted by 1 and $A - 1$ fire using the scheme where

1 fires first followed by $A - 1$. After both have fired, their firing causes perturbation as

input stimuli in the other cluster denoted by B in the order of their firing. However, between

the two clusters A and B, the input perturbation due to one cluster follows immediately

after firing, before the other cluster fires. Thus, when clusters 1 and $A - 1$ fire one after

the other, the phase of the oscillator B is linearly increasing until it receives both inputs

after respective delays. Once B has received inputs from both sub-clusters, B fires,

leading to input perturbations to sub-clusters 1 and $A - 1$ after delay.

For convenience, we assume that the delays are small and are equal. We also assume

that the periods P_1, P_{A-1} and P_B are equal. Even if we don't assume that the periods are

same, at some point in the derivation of the map, they would cancel out. Hence, for

convenience, we assume it early in the process.

Now, based on the figure 5, we write the necessary constraints to define the discrete map:

789
$$2\delta + tr_{A-1}[n] = ts_{B,1}[n] + ts_{B,A-1}[n] \qquad (1)$$

790
$$ts_{B,1}[n] = \delta + tr_{A-1}[n] + ts_{A-1,1}[n+1] \qquad (2)$$

791
$$ts_{A-1,B}[n+1] = ts_{B,A-1}[n] + tr_B[n] + \delta \qquad (3)$$

792
$$ts_{1,B}[n+1] = tr_B[n] + \delta \qquad (4)$$

793
$$ts_{B,1}[n] = 2\delta + tr_1[n] \qquad (5)$$

794
$$ts_{1,A-1}[n+1] = \delta + ts_{B,A-1}[n] \qquad (6)$$

Using the equation (1), and plugging in the expressions for stimulus and response

intervals (and using the equality of intrinsic periods), we get

$$2\delta + \left(1 - \varphi_{A-1,B}[n] + f\left(\varphi_{A-1,B}[n]\right)\right) = \varphi_{B,1}[n] + \left(\varphi_{B,A-1}[n] - \varphi_{B,1}[n] + f\left(\varphi_{B,1}[n]\right)\right)$$

Here, as discussed in the results section, the steady state is the two-cluster solution,

where each cluster has neurons that fire synchronously, but the two clusters need not

necessarily synchronize with each other. With that as the steady-state, using the steady-

state intervals and phases, and linearizing the PRCs about this fixed point, we get

$$\left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] = \Delta\varphi_{B,A-1}[n] + m_{B,1}\Delta\varphi_{B,1}[n]$$

Rearranging the above equation, we get:

$$\Delta\varphi_{B,A-1}[n] = \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] - m_{B,1}\Delta\varphi_{B,1}[n] \qquad (7)$$

Now, using equation (5), we get a relation between $\Delta\varphi_{B,1}[n]$ and $\Delta\varphi_{1,B}[n]$. Thus,

substituting for the phases in (5), we get

$$\varphi_{B,1}[n] = 2\delta + \left(1 - \varphi_{1,B}[n] + f\left(\varphi_{1,B}\right)[n]\right)$$

Linearizing about the fixed points, we get

$$\Delta\varphi_{B,1}[n] = \left(m_{1,B} - 1\right)\Delta\varphi_{1,B}[n] \qquad (8)$$

Substituting equation (8) in equation (7), we get

$$\Delta\varphi_{B,A-1}[n] = \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] - m_{B,1}\left(m_{1,B} - 1\right)\Delta\varphi_{1,B}[n] \qquad (9)$$

Now, using equation (2), we get an expression for $\Delta\phi_{A-x,x}[n+1]$. Substituting phases in

(2), we get

814
$$\varphi_{B,1}[n] = \delta + \left(1 - \varphi_{A-1,B}[n] + f\left(\varphi_{A-1,B}[n]\right)\right) + \varphi_{A-1,1}[n+1]$$

815 Linearizing about the fixed points, we get

816
$$\Delta\varphi_{B,1}[n] = \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] + \Delta\varphi_{A-1,1}[n+1]$$

817 Rearranging the above expression, we get

818
$$\Delta\varphi_{A-1,1}[n+1] = \Delta\varphi_{B,1}[n] - \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n]$$

819 Substituting for $\varphi_{B,1}[n]$ in the above equation from (8), we get

820
$$\Delta\varphi_{A-1,1}[n+1] = \left(m_{1,B} - 1\right)\Delta\varphi_{1,B}[n] - \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] \qquad (10)$$

821 Now, using equation (6), we get an expression for $\Delta\varphi_{1,A-1}[n+1]$. Substituting phases in

822 (6), we get

823
$$\varphi_{1,A-1}[n+1] = \delta + \varphi_{B,A-1}[n] - \varphi_{B,1}[n] + f\left(\varphi_{B,1}[n]\right)$$

824 Linearizing the PRC about the fixed points, we get

825
$$\Delta\varphi_{1,A-1}[n+1] = \Delta\varphi_{B,A-1}[n] + \left(m_{B,1} - 1\right)\Delta\varphi_{B,1}[n]$$

826 Substituting for $\Delta\varphi_{B,A-1}[n]$ in the above equation from equation (9), we get

827
$$\Delta\varphi_{1,A-1}[n+1] = \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] - m_{B,1}\left(m_{1,B} - 1\right)\Delta\varphi_{1,B}[n] + \left(m_{B,1} - 1\right)\Delta\varphi_{B,1}[n]$$

828 Now, substituting for $\Delta\varphi_{B,1}[n]$ in the above equation from equation (8), we get

829
$$\Delta\varphi_{1,A-1}[n+1]$$

830
$$= \left(m_{A-1,B} - 1\right)\Delta\varphi_{A-1,B}[n] - m_{B,1}\left(m_{1,B} - 1\right)\Delta\varphi_{1,B}[n]$$

831
$$+ \left(m_{B,1} - 1\right)\left(m_{1,B} - 1\right)\Delta\varphi_{1,B}[n]$$

Rearranging and cancelling the terms, we get

$$\Delta\varphi_{1,A-1}[n+1] = (m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n] - (m_{1,B}-1)\Delta\varphi_{1,B}[n] \qquad (11)$$

Now, let us consider equation (3) to get an expression for $\Delta\varphi_{A-1,B}[n+1]$. Substituting

phases in (3), we get

$$\varphi_{A-1,B}[n+1] - \varphi_{A-1,1}[n+1] + f(\varphi_{A-1,1}[n+1])$$

$$= \varphi_{B,A-1}[n] + \left(1 - \varphi_{B,A-1}[n] + f(\varphi_{B,A-1}[n])\right) +$$

After cancelling and linearizing the PRCs about the fixed points, we get

$$\Delta\varphi_{A-1,B}[n+1] + (m_{A-1,1}-1)\Delta\varphi_{A-1,1}[n+1] = (m_{B,1}-1)\Delta\varphi_{B,1}[n] + m_{B,A-1}\Delta\varphi_{B,A-1}[n]$$

Rearranging the above equation, we get

$$\Delta\varphi_{A-1,B}[n+1] = (m_{B,1}-1)\Delta\varphi_{B,1}[n] - (m_{A-1,1}-1)\Delta\varphi_{A-1,1}[n+1] + m_{B,A-1}\Delta\varphi_{B,A-1}[n]$$

Substituting for $\Delta\varphi_{A-1,1}[n+1]$ in the above equation from equation (10), we get

$$\Delta\varphi_{A-1,B}[n+1]$$

$$= m_{B,A-1}\Delta\varphi_{B,A-1}[n] + (m_{B,1}-1)\Delta\varphi_{B,1}[n]$$

$$- (m_{A-1,1}-1)\{(m_{1,B}-1)\Delta\varphi_{1,B}[n] - (m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n]\}$$

Substituting for $\Delta\varphi_{B,1}[n]$ in the above equation from equation (8), we get

$$\Delta\varphi_{A-1,B}[n+1]$$

$$= m_{B,A-1}\Delta\varphi_{B,A-1}[n] + (m_{B,1}-1)(m_{1,B}-1)\Delta\varphi_{1,B}[n]$$

$$- (m_{A-1,1}-1)\{(m_{1,B}-1)\Delta\varphi_{1,B}[n] - (m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n]\}$$

Rearranging and simplifying, we get the following steps:

$\Delta\varphi_{A-1,B}[n+1]$

$= m_{B,A-1}\Delta\varphi_{B,A-1}[n] + (m_{1,B}-1)[(m_{B,1}-1)-(m_{A-1,1}-1)]\Delta\varphi_{1,B}[n]$

$+ (m_{A-1,1}-1)\{(m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n]\}$

$\Delta\varphi_{A-1,B}[n+1]$

$= m_{B,A-1}\Delta\varphi_{B,A-1}[n] + (m_{1,B}-1)[m_{B,1}-m_{A-1,1}]\Delta\varphi_{1,B}[n]$

$+ (m_{A-1,1}-1)(m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n]$

Now, we substitute for $\Delta\varphi_{B,A-1}[n]$ in the above equation from equation (9)

$\Delta\varphi_{A-1,B}[n+1]$

$= m_{B,A-1}\{(m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n] - m_{B,1}(m_{1,B}-1)\Delta\varphi_{1,B}[n]\}$

$+ (m_{1,B}-1)[m_{B,1}-m_{A-1,1}]\Delta\varphi_{1,B}[n] + (m_{A-1,1}-1)(m_{A-1,B}-1)\Delta\varphi_{A-1,B}[n]$

Rearranging the terms in the above equation, we get

$\Delta\varphi_{A-1,B}[n+1]$

$= \{m_{B,A-1}(m_{A-1,B}-1) + (m_{A-1,1}-1)(m_{A-1,B}-1)\}\Delta\varphi_{A-1,B}[n]$

$+ \{[m_{B,1}-m_{A-1,1}](m_{1,B}-1) - m_{B,A-1}m_{B,1}(m_{1,B}-1)\}\Delta\varphi_{1,B}[n]$

Further rearranging the terms in the above equation gives us

$\Delta\varphi_{A-1,B}[n+1]$

$= (m_{A-1,B}-1)\{m_{B,A-1}+m_{A-1,1}-1\}\Delta\varphi_{A-1,B}[n]$

$+ (m_{1,B}-1)\{[m_{B,1}-m_{A-1,1}]-m_{B,A-1}m_{B,1}\}\Delta\varphi_{1,B}[n]$

$\Delta\varphi_{A-1,B}[n+1]$

$$= (m_{A-1,B} - 1)\{m_{B,A-1} + m_{A-1,1} - 1\}\Delta\varphi_{A-1,B}[n]$$

$$+ (m_{1,B} - 1)\{m_{B,1}(1 - m_{B,A-1}) - m_{A-1,1}\}\Delta\varphi_{1,B}[n]$$

Thus, we get the first equation of the map:

$\Delta\varphi_{A-1,B}[n+1]$

$$= (m_{A-1,B} - 1)\{m_{B,A-1} + m_{A-1,1} - 1\}\,\Delta\varphi_{A-1,B}[n]$$

$$+ (m_{1,B} - 1)\{m_{B,1}(1 - m_{B,A-1}) - m_{A-1,1}\}\Delta\varphi_{1,B}[n] \quad (12)$$

Now, we use the constraint (4) to obtain the equation for $\varphi_{1,B}[n+1]$. Substituting the

phases for the equation (4), we get

$\varphi_{1,B}[n+1] - \varphi_{1,A-1}[n+1] + f(\varphi_{1,A-1}[n+1]) = 1 - \varphi_{B,A-1}[n] + f(\varphi_{B,A-1}[n]) + \delta$

Linearizing the PRCs about the fixed points and cancelling the steady state terms, we get

$\Delta\varphi_{1,B}[n+1] + (m_{1,A-1} - 1)\Delta\varphi_{1,A-1}[n+1] = (m_{B,A-1} - 1)\Delta\varphi_{B,A-1}[n]$

Rearranging the above equation, we get

$\Delta\varphi_{1,B}[n+1] = (m_{B,A-1} - 1)\Delta\varphi_{B,A-1}[n] - (m_{1,A-1} - 1)\Delta\varphi_{1,A-1}[n+1]$

Substituting for $\varphi_{B,A-1}[n]$ from equation (9) and for $\varphi_{A-1,1}[n]$ from equation (11), we get

$\Delta\varphi_{1,B}[n+1] = (m_{B,A-1} - 1)\{(m_{A-1,B} - 1)\Delta\varphi_{A-1,B}[n] - m_{B,1}(m_{1,B} - 1)\Delta\varphi_{1,B}[n]\}$

$- (m_{1,A-1} - 1)\{(m_{A-1,B} - 1)\Delta\varphi_{A-1,B}[n] - (m_{1,B} - 1)\Delta\varphi_{1,B}[n]\}$

Rearranging the terms, we get

$\Delta\varphi_{1,B}[n+1] = \{(m_{B,A-1}-1)(m_{A-1,B}-1)-(m_{1,A-1}-1)(m_{A-1,B}-1)\}\Delta\varphi_{A-1,B}[n]$

889               $+ \{(m_{1,A-1}-1)(m_{1,B}-1)-(m_{B,A-1}-1)m_{B,1}(m_{1,B}-1)\}\Delta\varphi_{1,B}[n]$

890   Cancelling the terms and rearranging, we finally get the second equation of the map

891      $\Delta\varphi_{1,B}[n+1] = (m_{A-1,B}-1)\{m_{B,A-1}-m_{1,A-1}\}\Delta\varphi_{A-1,B}[n] + (m_{1,B}-1)\{(m_{1,A-1}-1)-$

892               $(m_{B,A-1}-1)m_{B,1}\}\Delta\varphi_{1,B}[n]$ (13)

893   Like the results in the work of Chandrasekaran et.al, perhaps the intrinsic periods would

894   have cancelled out even if we did not assume them to be equal. However, finally, the

895   system (12) - (13) gives us a two-dimensional discrete linear system of the form:

896                                $\Delta[n+1] = S\Delta[n]$ (14)

897   where S can be expressed as

898                                $S = \begin{bmatrix} s_{11} & s_{12} \\ s_{21} & s_{22} \end{bmatrix}$ (15)

The terms s_{11}, s_{12}, s_{21} and s_{22} are defined as

$s_{11} = (m_{A-1,B}-1)\{m_{B,A-1}+m_{A-1,1}-1\}$

$s_{12} = (m_{1,B}-1)\{m_{1,B,1}(1-m_{1,B,A-1})-m_{A-1,1}\}$

$s_{21} = (m_{A-1,B}-1)\{m_{B,A-1}-m_{1,A-1}\}$

$s_{22} = (m_{1,B}-1)\{(m_{1,A-1}-1)-(m_{B,A-1}-1)m_{B,1}\}$

Based on this, the characteristic polynomial for the matrix (15) is given by

905                 $\lambda^2 - \lambda(s_{11}+s_{22}) + s_{11}s_{22} - s_{21}s_{12} = 0$ (16)

The stability of this cluster mode is determined by the eigen values of the characteristic

polynomial given in equation (16). If $|\lambda_{\max}| < 1$, then we can conclude that the clustered

solution is stable, implying that the applied perturbation decays to zero.

Analysis of the Cluster Interaction Terms

The perturbed sub-cluster 1 and the sub-cluster $A - 1$ receive the same input from the

other unperturbed cluster B. The sub-cluster $A - 1$ is comprised of neurons identical to

the neurons in the perturbed sub-cluster 1, but the response of each of the sub-clusters

to an input from cluster B could differ because of other neurons on each other within each

sub-cluster. We approximate the PRC for a cluster of identical neurons with that of an

individual neuron. We presume that all post-synaptic oscillators comprised of identical

neurons will have the same resetting irrespective of their composition in terms of the sub-

cluster. Thus, the phase resetting for the sub-clusters 1 and $A - 1$ for an input from B

would be the same. Hence, we get the equality:

919
$$f_{A-1,B}\left(\varphi_{A-1,B}\right) = f_{1,B}\left(\varphi_{1,B}\right) = f_{A,B}(\varphi_A^*) \qquad (17)$$

920   This would result in the slopes being equal and we therefore get

921
$$m_{A-1,B} = m_{1,B} = m_{A,B}$$

922   Substituting these values in the 2-dimensional map (14), and solving the characteristic

923   polynomial (15) for eigen values, we get the factorized characteristic polynomial as

924
$$(\lambda - \lambda_1)(\lambda - \lambda_2) = 0 \qquad (18)$$

925   where the λ_1 and λ_2 evaluated at phase-locked points are given by

926
$$\lambda_1 = \left(1 - f'_{A,B}(\varphi_A^*)\right)\left(1 - f'_{B,1}(\varphi_B^*)\right)\left(1 - f'_{B,A-1}(\varphi_B^*)\right) \quad (19)$$

927
$$\lambda_2 = \left(1 - f'_{A,B}(\varphi_A^*)\right)\left(1 - f'_{A-1,1}(\varphi_{A-1}^*) - f'_{1,A-1}(\varphi_1^*)\right) \quad (20)$$

928   λ_2 in equation (20) has the term $\left(1 - f'_{A,B}(\varphi_A^*)\right)$ that represents the effect of between

929   cluster interactions on within cluster synchrony. Substituting the values of phases at

930   steady state, we get

931
$$\lambda_1 = \left(1 - f'_{A,B}\left(\frac{ts^*_A}{P_A}\right)\right)\left(1 - f'_{B,1}\left(\frac{ts^*_{B,1}}{P_B}\right)\right)\left(1 - f'_{B,A-1}\left(\frac{ts^*_{B,A-1}}{P_B}\right)\right)$$

932
$$\lambda_2 = \left(1 - f'_{A,B}\left(\frac{ts^*_A}{P_A}\right)\right)\left(1 - f_{A-1,1}\left(\frac{ts^*_{A-1,1}}{P_{A-1}}\right) - f_{1,A-1}\left(\frac{ts^*_{1,A-1}}{P_1}\right)\right)$$