# Representational dissimilarity component analysis (ReDisCA)

**Alexei Ossadtchi**[*,1,2] **, Ilia Semenkov** [1,3]**, Anna Zhuravleva** [1,3]**,**
**Oleg Serikov** [4]**, Ekaterina Voloshina** [3]

1 Higher School of Economics, Moscow, Russia
[2] LIFT, Life Improvement by Future Technologies Institute, Moscow, Russia
[3] AIRI, Artificial Intelligence Research Institute, Moscow, Russia
[4] AI Initiative, King Abdullah University of Science and Technology, KSA
* the corresponding author, `ossadtchi@gmail.com`

**Abstract.**

The principle of Representational Similarity Analysis (RSA) posits that neural representations reflect the structure of encoded information, allowing exploration of spatial and temporal organization in brain information processing. Traditional RSA when applied to EEG or MEG data faces challenges in accessing activation timeseries at the brain source level due to modeling complexities and insufficient geometric/anatomical data.

To address this, we introduce Representational Dissimilarity Component Analysis (ReDisCA), a method for estimating spatial-temporal components in EEG or MEG responses aligned with a target representational dissimilarity matrix (RDM). ReDisCA yields informative spatial filters and associated topographies, offering insights into the location of "representationally relevant" sources. Applied to evoked response timeseries, ReDisCA produces temporal source activation profiles with the desired RDM. Importantly, while ReDisCA does not require inverse modeling its output is consistent with EEG and MEG observation equation and can be used as an input to rigorous source localization procedures.

Demonstrating ReDisCA's efficacy through simulations and comparison with conventional methods, we show superior source localization accuracy and apply the method to a real EEG dataset, revealing physiologically plausible representational structures without inverse modeling. ReDisCA adds to the family of inverse modeling free methods such as independent component analysis (Makeig et al., 1995), Spatial spectral decomposition (Nikulin et al., 2011) and Source power comodulation (Dähne et al., 2014) designed for extraction sources with desired properties from EEG or MEG data. Extending its utility beyond EEG and MEG analysis, ReDisCA is likely to find application in fMRI data analysis and exploration of representational structures emerging in multilayered artificial neural networks.

## 1. Introduction

Representational Similarity Analysis (RSA) now stands as a pivotal technique within cognitive neuroscience, offering a profound lens into the organization and representation

of information in the human brain. This method has revolutionized our capacity to comprehend the neural bases of cognitive processes by elucidating the relationships between neural representations of stimuli or concepts and relating them to behavioral variables and computational modeling (Edelman, 1998; Kriegeskorte et al., 2008a). The largely philosophical concept of representational similarity later received its practical implementation in the field of both invasive electrophysiological (Op de Beeck et al., 2001; Hung et al., 2005; Tsao et al., 2006) and non-invasive functional magnetic resonance imaging(fMRI) based neuroimaging (Carlson et al., 2003; Cox and Savoy, 2003) followed by explicitly matching similarity patterns of neural activity to the theoretically presupposed representational structure (Aguirre, 2007) including the attempts to match representational structure of neural activity across species (Kriegeskorte et al., 2008b). Capitalizing on the success of the early application of the RSA principle, a seminal paper by Kriegskorte et al. (Kriegeskorte et al., 2008a), provided a step-by-step guide for the use of RSA to link the three whales of modern neuroscience: neuronal activity, behavior and computational models. Since then a number of informative studies emerged that utilize the notion of representation (Shea, 2018) and employ RSA as an instrument to explore informational structure embodied in the neural substrate (Kriegeskorte and Kievit, 2013).

RSA was extended to merge fMRI and magnetoencephalography (MEG) non-invasive functional neuroimaging modalities (Cichy et al., 2016). This approach aimed to leverage the typically acknowledged high spatial resolution of fMRI alongside the high temporal resolution of MEG. MEG channels were used as features for constructing a classifier to yield the representational dissimilarity matrices (RDMs) corresponding to specific time intervals. These RDMs were then matched against those computed from spatial region of interest (ROI) activity patterns as measured by fMRI. This study revealed intriguing patterns of temporally persistent and recurrent representations (King and Dehaene, 2014) across visual processing stream reflecting both bottom-up and top-down informational flows highlighting the concept of predictive coding implemented by our brain.

Several years later, MEG alone combined with cortical ROI multivariate pattern analysis (MVPA) and powered by the RSA framework (Kozunov et al., 2018) managed to provide both temporally and spatially informative maps highlighting the ventral vs. dorsal bifurcation of the visual pathway related to processing images of faces and tools contrasted against meaningless textures. Methodologically, this paper is significant as to the best of our knowledge that was the first attempt to apply RSA to MEG data in the source-space. To this end the authors first computed a fine-grained distributed inverse solution using sLORETA technique (Pascual-Marqui et al., 2002). Applying it to each time slice in the MEG sensor data they obtained cortical distribution of activity for each vertex on the cortical mesh model. Then, they combined vertices into spatially extended coarse ROIs and retained only three principal components of activities in each cortical ROI. Then, a series of region and time-window specific linear discriminant analysis (LDA) classifiers were trained to distinguish between stimulus classes and to

form regional RDMs. These regional RDMs were then employed within the standard RSA framework and compared against theoretical RDMs.

It is important to realize that in case of fMRI the source-space signals are readily available after application of a more or less standard collection of analysis steps including data preprocessing and calculation of the appropriate contrasts. Things are significantly less transparent and standardized in the EEG or MEG cases. Here, in order to obtain the individual voxel or ROI activity profiles the inverse modeling approaches are used to convert sensor signals into the source-space activation timeseries. This is typically done by applying an inverse operator matrix to EEG / MEG sensor measurements. The inverse operator directly depends on the forward model (FM). The latter approximates the way the source activity is mapped to the sensors and is computed by solving Maxwell equations within the head volume which typically requires approximating the head with a set of concentric surfaces bounding the regions of constant conductivity. The accuracy of the FM depends on the extent to which the geometry as well as conductivity and permeability properties of the model align with their real counterparts. Generally unknown conductivity profiles of the tissues comprising the head, the associated anisotropy of the conductivity tensor and the limited coregistration accuracy of the sensor array to the volume conductor model are the sources of the FM inaccuracies especially pronounced when dealing with EEG data. The precision of modeling magnetic fields from neuronal sources tends to yield accurate MEG forward models, showcasing an impressive fidelity with an estimated error rate of around 10% (Mosher and Leahy, 1999). Yet, despite this advantage, MEG systems are notably less accessible compared to their EEG counterparts. Even if the FM is accurate enough the task of estimating neuronal sources from non-invasively collected EEG or MEG data is inherently ill-posed. Fundamentally, for a given set of measurements there exist an infinite number of cortical source distributions that perfectly fit the measurements. This problem is resolved and a unique solution is guaranteed by regularization which makes the results depend heavily on the *apriori* assumptions about source distributions. Taken together, all this limits RSA applications in the realm of time-resolved neuroimaging furnished by the EEG and MEG, the techniques that offer a unique time-resolved window into the speedy neuronal processes.

To circumvent this problem and broaden the potential applications of the powerful RSA principle here we propose novel representational dissimilarity component analysis (ReDisCA) - an inverse modeling free method designed to estimate the spatial-temporal components in the evoked responses that adhere to a specific target (or theoretical) representational dissimilarity matrix (RDM). The output of this method is a set of spatial filters and the associated topographies (or patterns) that appear informative of location of "representationally relevant" sources whose activity exhibits the sought representational profiles. Application of the discovered spatial filters to the evoked response timeseries matrix yields temporal source activation profiles with the desired RDM over the selected time window.

While ReDisCA doesn't necessitate inverse modeling, its foundation lies in the

classical linear EEG/MEG observation equation. It exercises the concept of spatial filtering, akin to already established techniques like Independent Component Analysis (ICA) (Makeig et al., 1995), Spatial-Spectral Decomposition (SSD) (Nikulin et al., 2011), or Source Power Co-modulation (SPoC) (Dähne et al., 2014). This ensures that the discovered spatial patterns are suitable for implementing a rigorous source localization procedure based on the notion of signal subspace (Mosher et al., 1992) as described for example in (Ossadtchi et al., 2014) in application to ICA.

This compatibility with the linear model positively distinguishes ReDisCA from the purely sensor space applications of RSA to EEG or MEG data. For example, (Mensen et al., 2017) used high density EEG and were able to highlight the detailed spatial and temporal patterns of responses underlying various aspects of meaningfulness in the presented visual stimuli. They achieved this using newly proposed differentiation analysis (DA) and computed temporal and spatial profiles of the category differentiation index (CDI) that can be used to make judgments about time windows and approximate spatial locations of the pivotal sources. However, due to their empirical nature the obtained spatial CDI maps can not be rigorously fitted with the electromagnetic model of the head and therefore are only tangentially related to the underlying distribution of cortical sources with target representational properties. Therefore, the approach proposed here can be considered as a link between the existing purely sensor-space applications of RSA to EEG and MEG data and fully fledged inverse modeling based technique described in (Kozunov et al., 2018).

In what follows we first describe a classical RSA formulation and then proceed to the presentation of ReDisCA. As it will become clear, ReDisCA utilizes formally the same optimization strategy as that used by SPoC, a well established technique for extracting spatial-temporal components corresponding to neuronal sources of rhythmic activity whose power is co-modulated with the user supplied behavioral variable. To illustrate this connection we provide a table of explicit correspondence between the quantities defined in this paper and those used in SPoC and then describe the optimization strategy based on solving the generalized eigenvalue problem with appropriately formed matrices. Next we evaluate ReDisCA's performance and compare it against several versions of the source space RSA implementations in the two simulated scenarios, with either a single source or with four simultaneously active sources each with its own RDM. Finally, we apply ReDisCA to the analysis of a real EEG dataset that lacks the information necessary for source localization, a prerequisite for the source space RSA analysis. We show how the new method can be used to discover representationally relevant structure in the EEG evoked responses without the use of inverse modeling. We conclude with the discussion of ReDisCA's strengths and weaknesses and relate it to the existing modifications of RSA including accommodation of advanced dissimilarity measures (Walther et al., 2016) and the data-driven estimation of the theoretical RDM (Khaligh-Razavi et al., 2017; Kaniuth and Hebart, 2022).

## 2. Methods

### 2.1. Problem statement

Consider a collection of data matrices denoted as $\mathbf{X}_i^c$, each with dimensions $N \times T$. These matrices represent recordings of brain activity, specifically EEG, MEG, or potentially ECoG or sEEG, performed with $N$ channels over $T$ time stamps. The length of the time segment of interest (tSOI) within the entire response is $T$ samples, corresponding to the number of columns in $\mathbf{X}_i^c$. These recordings are obtained during the $i$-th trial out of a total of $I_c$ trials, corresponding to the experimental condition $c \in 1, \ldots, C$.

Averaged evoked response is one of the informative features extracted from electrophysiological recordings obtained in the event-related paradigms. It can be calculated simply by averaging $\mathbf{X}_i^c$ over $I_c$ trials to get $\mathbf{X}^c = \frac{1}{I_c} \sum_{i=1}^{I_c} \mathbf{X}_i^c$. $\mathbf{X}^c$ emphasizes phasic components of the response, i.e. those whose activity phase is consistent with the stimulus onset.

Our objective is using a set of $\mathbf{X}^c$ observed over $C$ conditions to identify spatial and temporal components or subsequently brain regions whose temporal activity profiles exhibit the target differences among the $C$ experimental conditions. The target differences in our case are defined by a predefined theoretical or model-based $C \times C$ representational dissimilarity matrix (RDM) $\mathbb{D}$.

### 2.2. Source space representational similarity analysis (RSA)

For EEG and MEG scenarios, we can achieve this by the two step spot-light procedure. First we use an $M \times N$ inverse operator denoted as $\mathbf{W}_M$ whose $m$-th row denoted as $\mathbf{w}_m^T$, $m \in 1, \ldots, M$, acts as a spatial filter tuned to the $m$-th voxel.

This precomputed spatial filter aids in estimating the $1 \times \tau$ vector of the $m$-th voxel activity during condition $c$ as $\mathbf{s}_m^{cT} = \mathbf{w}_m^T \mathbf{X}^c$, allowing us to derive the time-series corresponding to every voxel in the predefined volumetric grid based on the sensor-space averaged evoked response measurements $\mathbf{X}^c$ defined above. Note that here and in the subsequent expressions horizontally oriented vectors are marked with transpose superscript, i.e. $\mathbf{s}_m^{cT}$.

Next, once we have obtained regional timeseries vectors $\mathbf{s}_m^{cT}$ we can evaluate the dissimilarity measure of choice in order to obtain the $m$-th region specific dissimilarity matrix $\mathbf{D}_m = \{d_m^{ij}\}$, $m = 1, \ldots, M$. In what follows we will stick to the square of the Euclidean distance as a measure of response dissimilarity that can be readily extended to Mahalanobis distance once the covariance matrix describing the dependencies between the time samples of the regional response is available. Thus

$$\mathbf{D}_m = \{d_m^{ij}\} = \|\mathbf{s}_m^{c_iT} - \mathbf{s}_m^{c_jT}\|^2, \; i, j = 1, \ldots, C. \tag{1}$$

Once the regional RDMs are prepared, following the standard RSA procedure, we will employ the correlation coefficient $\rho_m$ to assess the similarity between regional RDMs ($\mathbf{D}_m$) indexed by $m$ and the theoretical RDM $\mathbb{D} = \{d^{ij}\}$ typically supplied by the user.

Figure 1: Source space RSA diagrams. a) RSA applied to the averaged evoked response (AV). The inverse operator is applied to already averaged evoked response data $\mathbf{X}^p$ observed during condition $p$, $p = 1, \ldots, C$, then the empirical RDM entry is calculated as the quadratic difference between the evoked source timeseries in conditions $c_i = p$ and $c_j = q$. b) RSA applied to single trials (S.T.). The inverse operator is applied to each single $l - th$ trial in the data, followed by computing the quadratic difference that gets then averaged over trials within each condition. In both cases different inverse operators ($\mathbf{W}_M = \{\mathbf{w}_m\}$) can be used. We experimented with two inverse solvers - MNE and LCMV BF.

$$\rho_m^{RSA} = corr\left(d^{ij}, d_m^{ij}\right) = \frac{2}{C(C-1)} \sum_{i=1}^{C} \sum_{j=i+1}^{C} \tilde{d}^{ij} \tilde{d}_m^{ij} \tag{2}$$

where the tilde represents standardized upper triangular elements of the respective RDM matrices.

The scores $\rho_m^{RSA}$ reflect similarity between the theoretical and regional RDMs. They can be visually represented on the cortical surface or within the brain volume by interpolating the scores associated with each of the $M$ voxels or cortical mesh nodes. Then, to identify the spots of significant similarity, a statistical testing procedure is applied. This procedure should consider the limited spatial resolution inherent in EEG and MEG-based inverse mapping, and correction should be made for the effective number of multiple comparisons. This may be accomplished using, for example, the cluster-based permutation testing procedure (Maris and Oostenveld, 2007) where the surrogate data are obtained by permuting the labels of $C$ conditions which essentially corresponds to computing $\rho_m^{RSA}$ but for randomly reshuffled upper triangle of the theoretical RDM.

The diagrams in Figure 1 schematically show the described process for the two cases. In the first case illustrated in panel Figure 1.a the inverse operator is applied to already averaged evoked response data $\mathbf{X}^p$ observed during condition $p$, $p = 1, \ldots, C$ and then the empirical RDM entry is calculated as the quadratic difference between the evoked source timeseries in condition $p$ and $q$. In Figure 1.b we show an alternative approach where the inverse operator is applied to the single ($l - th$) trial data, followed by computing the quadratic difference that then gets averaged over trials within each condition. In our experiments with source space RSA we will also distinguish between the use of two different inverse solvers - Minimum norm estimator (MNE) and Linearly constrained minimum variance beamformer (LCMV BF). This gives us in total four versions of the source space RSA that we will compare our new approach with.

### 2.3. Representational dissimilarity component analysis (ReDisCA)

Here we propose an alternative method for identifying brain activity components with the desired representational dissimilarity. Instead of using the precomputed inverse operator $\mathbf{W}_M = \{\mathbf{w}_m\}$, $m = 1, \ldots, M$ and conducting an exhaustive search over all $M$ cortical vertices (or voxels) as in the spotlight source space RSA illustrated in Figure 1, we analytically seek a vector of coefficients $\mathbf{w}$ such that the empirical RDM of spatially filtered data $\mathbf{s}_w^{cT} = \mathbf{w}^T\mathbf{X}^c$, $c \in 1, \ldots, C$, closely approximates the target RDM $\mathbb{D}$. Note that this analytically found spatial filter weights vector $\mathbf{w}$ conceptually plays the same role as the rows $\mathbf{w}_m$ of the inverse operator in the source space RSA.

To implement this we posit and solve the following optimization problem

$$\mathbf{w} = argmax\ corr\left(d_w^{ij}, d^{ij}\right) = argmax\ corr\left(\|\mathbf{s}_w^{c_iT} - \mathbf{s}_w^{c_jT}\|, d^{ij}\right), \tag{3}$$

where in accordance with (1) to gauge similarity between the emprirical RDM $\mathbf{D}_w =$
$\{d_w^{ij}\}$ of the spatially filtered data $\mathbf{s}_w^{cT} = \mathbf{w}^T\mathbf{X}^c$ and the target RDM matrix $\mathbb{D}$ we use the
Pearson correlation coefficient between the two RDMs upper triangular elements indexed
by $(i,j)$. Also, as a representational dissimilarity measure we employ Euclidean distance
between condition specific spatially filtered temporal activation profiles. However, in this
case the spatial filter $\mathbf{w}$ is unknown and needs to be found by solving this optimization
problem. Once the weights are found they can be turned into source topographies in
order to apply inverse modeling and localize the corresponding neuronal sources. Note
that we used subscript $w$ to denote the elements of the empirical RDM corresponding
to the spatial filter $\mathbf{w}$ that we are about to identify, see (2) for comparison.

To solve optimization problem (3) we use the fact that $\mathbf{s}_w^{c_iT} = \mathbf{w}^T\mathbf{X}^{c_i}$ and rewrite
(3) as an explicit function of $\mathbf{w}$:

$$\mathbf{w} = argmax\ corr\left(\mathbf{w}^T\left(\mathbf{X}^{c_i} - \mathbf{X}^{c_j}\right)\left(\mathbf{X}^{c_i} - \mathbf{X}^{c_j}\right)^T\mathbf{w}, d^{ij}\right). \tag{4}$$

246 For compactness we denote $\mathbf{R}^{ij} = \left(\mathbf{X}^{c_i} - \mathbf{X}^{c_j}\right)\left(\mathbf{X}^{c_i} - \mathbf{X}^{c_j}\right)^T$ to obtain the following
247 optimization problem

$$\mathbf{w}_{max} = argmax\ corr\left(\mathbf{w}^T\mathbf{R}^{ij}\mathbf{w}, d^{ij}\right),\ i = 1,\ldots,C,\ j = 1,\ldots,C\ , \tag{5}$$

$$s.t.\ \mathbf{w}^T\left(\sum_{i=1}^{C}\sum_{j=i+1}^{C}\mathbf{R}^{ij}\right)\mathbf{w} = const$$

In Equation (5), $N \times N$ matrix $\mathbf{R}^{ij}$ represents the unscaled correlation matrix of the
sensor-space timeseries differences recorded between condition $i$ and condition $j$. This
expression formally exactly matches the optimization problem solved in SPoC (Dähne
et al., 2014) where the role of $\mathbf{R}^{ij}$ is played by the time-segment specific sensor data
correlation matrix.

SPoC deals with a collection of time segments (or epochs) indexed by $e$ in the
original paper, and aims to find a spatial filter for isolating a source whose power
follows the desired temporal profile $z(e)$. In our approach we work with a collection
of condition pairs $(i,j)$ and seek a source whose RDM $\mathbf{D}_w = \{d_w^{ij}\}$ matches the target
RDM $\mathbb{D} = \{d^{ij}\}$. While SPoC computes correlation matrices $\mathbf{C}(e)$ specific to the $e$-th
epoch of EEG(MEG) data, in our approach we calculate correlation matrices $\mathbf{R}^{ij}$ of the
difference of EEG (MEG) time series observed during the pairs of conditions indexed by
$(i,j)$. The role of index $e$ in the original SPoC is played by the pair of indices $(i,j)$ whose
combinations enumerate the collection of the upper triangular elements of the RDM.
One may also express this correspondence as $e = (i-1)C + j,\ i > j,\ i = 1,\ldots,C,\ j =$
$1,\ldots,C$. Essentially, the $e$-th segment timeseries in SPoC is replaced by the timeseries
of the difference between condition pair $(i,j)$. The role of the desired power profile $z(e)$
from the original SPoC is played by the elements $d^{ij}$ of the theoretical RDM $\mathbb{D}$ driving

the proposed here representational dissimilarity components analysis (ReDisCA). This correspondence is summarized in Table 1 below.

| Var. SPoC | Var. ReDisCA | Role in SPoC | Role in ReDisCA |
|-----------|--------------|--------------|-----------------|
| $e$ | $(i,j)$ | time window index | conditions pair index |
| $\mathbf{C}(e)$ | $\mathbf{R}^{ij}$ | data correlation matrix | data diff. corr. matrix |
| $z(e)$ | $d^{ij}$ | desired response pattern | desired RDM pattern |

Table 1: Correspondence between main SPoC variables as defined in Dähne et al. (2014) and the variables used to define ReDisCA in this manuscript.

There are two ways to solve the optimization problem (5). The first one is to use the
gradient descent and to identify $\mathbf{w}$ as the solution for (5) in order to achieve maximum
correlation coefficient between the empirical and the desired theoretical RDM profiles.
While this is entirely possible, SPoC paper describes a more attractive alternative to
approximate the correlation coefficient with covariance which allows for a closed form
solution.

In order to ensure that optimization of covariance (the non-normalized version of the
correlation coefficient) is a good approximator of the correlation coefficient optimization
we

• use standardized elements of the RDM $\tilde{d}^{ij}$

• use the constraint $\mathbf{w}^T\bar{\mathbf{R}}\mathbf{w}^T = 1$ where

$$\bar{\mathbf{R}} = \frac{2}{C(C-1)} \sum_{i=1}^{C} \sum_{j=i+1}^{C} \mathbf{R}^{ij} \tag{6}$$

279 is the average correlation matrix.

280 For compactness we also denote the weighted average correlation matrix

$$\bar{\mathbf{R}}^d = \sum_{i=1}^{C} \sum_{j=i+1}^{C} d^{ij}\mathbf{R}^{ij} \tag{7}$$

281 The resulting optimization problem can then be written as

$$\mathbf{w} = argmax \ \left(\mathbf{w}^T\bar{\mathbf{R}}^d\mathbf{w}\right), \ s.t. \ \mathbf{w}^T\bar{\mathbf{R}}\mathbf{w} = 1 \tag{8}$$

and can be analytically solved using the method of Lagrange multipliers.

The problems formally identical to (8) often arise in the domain of multivariate
signal processing, see beamforming (Van Veen et al., 1997), common spatial patterns
(Pfurtscheller et al., 1999), spatial spectral decomposition (SSD) (Nikulin et al., 2011)
and SPoC (Dähne et al., 2014) as EEG (MEG) specific examples. The optimal $\mathbf{w}$ is
found as the solution to the following generalized eigenvalue problem corresponding to
the largest eigenvalue

$$\bar{\mathbf{R}}^d \mathbf{w} = \lambda \bar{\mathbf{R}} \mathbf{w} \tag{9}$$

When solving this problem for an $N$-channel data we will arrive at an $N \times N$ matrix $\mathbf{W}$ whose columns are the eigenvectors of matrix pair $(\bar{\mathbf{R}}^d, \bar{\mathbf{R}})$ or in other words

$$\bar{\mathbf{R}}^d \mathbf{W} = \mathbf{\Lambda} \bar{\mathbf{R}} \mathbf{W} \tag{10}$$

Then, the square matrix $\mathbf{W}$ can be inverted in order to obtain the matrix $\mathbf{A} = \{\mathbf{a}_n^T\} = \mathbf{W}^{-1}$ whose rows $\mathbf{a}_n^T$ are the topographies of sources with the desired representational properties. In our case the rows corresponding to the largest eigenvalues forming the diagonal of $\mathbf{\Lambda}$ are the topographies of the sources whose RDMs most closely approximate the desired theoretical RDM $\mathbb{D}$. The similarity between the empirical and the theoretical RDM is reflected by the corresponding generalized eigenvalue.

We call these topographies $\mathbf{a}_n^T$ combined with the corresponding data derived RDM profiles $\hat{\mathbf{D}}_n = \{\hat{d}_n^{ij}\} = \{\mathbf{w}_n^T \mathbf{R}^{ij} \mathbf{w}_n\}$ the *representational dissimilarity components* and the described process of obtaining them the *REpresentational DISsimilarity Component Analysis* or ReDisCA.

The significance of similarity between the component specific data-derived RDMs $\hat{\mathbf{D}}_n$, $n = 1, \ldots, N$ and the theoretical RDM $\mathbb{D}$ can be established by the permutation testing procedure suggested in SPoC. The idea of this approach is to solve a large number of surrogate problems of the form (10) but based on the matrices created from the data with permuted condition labels. The mutual correspondence between the set of difference correlation matrices $\mathbf{R}^{ij}$ and the condition pair labels $(i, j)$ is destroyed and the corresponding asymptotic $p-$values are calculated as a fraction of cases when the surrogate generalized eigenvalue exceeds that obtained on the original data.

The collection of $K$ topographies $\mathbf{A}_K = [\mathbf{a}_1, \ldots, \mathbf{a}_K]$ corresponding to the components with significantly high similarity between the data-derived and the theoretical RDM spans *representational dissimilarity subspace, ReDisS*. These topographies together with the corresponding spatially filtered ERP timeseries furnish the decomposition of the evoked response potential (ERP) data into a set of *relevant* constituents with respect to the used theoretical RDM.

Technically this completes ReDisCA's description whose result is a set of spatial component topographies $\mathbf{a}_k$ and the corresponding spatial filters $\mathbf{w}_k$ that can be used to obtain component specific response timeseries vectors $\mathbf{u}_k^{cT}$ in the $c$-th condition as $\mathbf{u}_k^{cT} = \mathbf{w}_k^T \mathbf{X}^c$. More generally, one can write this in a matrix form as

$$\mathbf{U}^{cT} = \mathbf{W}^T \mathbf{X}^c. \tag{11}$$

From the above and given that the matrix of spatial filters $\mathbf{W}^T$ is invertible we can write

$$\mathbf{X}^c = \mathbf{W}^{-1} \mathbf{U}^{cT} = \mathbf{A} \mathbf{U}^{cT} = \sum_{k=1}^{N} \mathbf{a}_k \mathbf{u}^{cT} k, \tag{12}$$

which shows that after obtaining ReDisCA components the sensor data in the $c$-th condition can be reconstructed as a superposition of rank-1 contributions $\mathbf{a}_k \mathbf{u}_{kc}$ of ReDisCA components.

Figure 2: Representational dissimilarity component analysis (ReDisCA) diagram. The problem of finding the spatial components whose output ERP follow the desired RDM is reduced to SPoC covariance optimization. Instead of time-window covariance matrices $\mathbf{C}(e)$ and the associated values of behavioral variable $z(e)$ observed for a set of latency values $e = 1, \ldots E$ ReDisCA uses activation difference covariance matrices $\mathbf{R}^{pq}$ and the elements $d^{pq}$ of the theoretical RDM correspondingly, see also Table 1.

Note that using ReDisCA there's no need for explicit electromagnetically informed inverse modeling to identify the spatial components within multichannel EEG (MEG) data that exhibit the desired representational properties aligned with the user supplied theoretical RDM.

However, in order to align ReDisCA's results to those obtained with the more conventional source space RSA approaches we apply the electromagnetic inverse modeling to the identified spatial topography vectors $\mathbf{a}_k$. This allows us to quantitatively assess locations of sources underlying each of the components. The simplest way to associate ReDisCA results with neuronal sources is to compute the cosine similarity score between each forward model-based topography vector $\mathbf{g}_m$ corresponding to the $m-$th vertex of the cortical mesh and the ReDisCA derived pattern $\mathbf{a}_1$ corresponding to the largest generalized eigenvalue $\lambda_1$, i.e.

$$\rho_m^{CS} = \frac{\mathbf{g}_m^T \mathbf{a}_1}{\|\mathbf{g}_m\| \|\mathbf{a}_1\|} \tag{13}$$

To localize sources corresponding to the entire $K-$dimensional ReDisS spanned by the topographies of statistically significant components stored in $\mathbf{A}_K$ we can perform a simple multiple signal classification (MUSIC) scan using subspace correlation metric as

$$\rho_m^{MUSIC} = subcorr\left(\mathbf{g}_m^T, \mathbf{A}_K\right) \tag{14}$$

Similarly to $\rho_m$ used in the classical RSA setting, the scores $\rho_m^{MUSIC}$ and $\rho_m^{CS}$ can be visually represented on the cortical surface or within the brain volume by interpolating the scores associated with each of the $M$ voxels or cortical mesh nodes. Note also that $\rho_m^{MUSIC}$ is a more general measure of similarity between the subspaces of the arbitrary dimensions and reduces to $\rho_m^{CS}$ for $K = 1$.

### 2.4. Simulations setting

To validate the proposed ReDisCA approach, we conducted two sets of simulations. The best way to ensure that ReDisCA derived components are informative with respect to the underlying sources is to actually find these sources given the components estimated by ReDisCA. Therefore in both simulations we mapped the obtained topographies to the source space using (14) and assessed the location of the MUSIC scan's peak with respect to the location of simulated source(s).

### 2.4.1. Generation of source activation timeseries with desired representational structure

In both simulations we used the following strategy to generate the source activation timeseries for each of the $C$ conditions and associate them with the representational structure across $C$ conditions.

- For each source generate a random mixing matrix $\mathbf{M}$ by sampling its elements from zero mean and unit variance Gaussian distribution $\mathcal{N}(0, 1)$
- Generate $C \times T$ matrix $\mathbf{S} = \{\mathbf{s}^{cT}\}$, $c = 1, \ldots, C$ of condition specific source evoked response potentials as $\mathbf{S} = \mathbf{MZ}$ where $\mathbf{Z}$ is a $C \times T$ matrix of Gaussian random variables whose rows are low-pass filtered by the 6-th order Butterworth filter with cut off frequency 2 Hz.
- Compute the resultant dissimilarity profile matrix $\mathbb{D}^0$ from the obtained condition-specific timeseries vectors $\mathbf{S}$ according to equation (1).

As described later the noisy version of $\mathbb{D}^0$ will be supplied to the tested here RSA approaches as a theoretical RDM. For each Monte-Carlo iteration we generated a new matrix $\mathbf{Z}$, and thus a new set of condition specific source timeseries $\mathbf{S}$. In the first set of simulations where we generated only one active source we kept the mixing matrix $M$ constant over all Monte-Carlo iterations. In the second set of simulations with $P = 4$ source we used $P = 4$ mixing matrices $\mathbf{M}_p$ that remained unchanged over the course of Monte-Carlo trials.

2.4.2. *ReDisCA vs. source space RSA*    First, we compared ReDisCA against the source space RSA using a single source scenario. In this comparison, in order to generate the observed EEG (MEG) data we placed a single source iteratively (one at a time) in the node of the cortical mesh whose index was randomly generated and activated the source with condition specific timeseries. Here we used $C = 5$ conditions and generated condition-specific ERP timeseries. For each source position (iteration) the timeseries were randomly regenerated from a newly sampled matrix of random variables according to the procedure described above.

At each Monte-Carlo iteration corresponding to a specific source location in the $m_0$-th node of the cortical mesh we obtained condition specific source time series observed in the $l-$th trial as

$$\mathbf{X}_l^c = (\mathbf{g}_{m_0} + \boldsymbol{\delta}) \, \mathbf{s}^{cT} + \gamma \mathbf{\Upsilon}_{xl}, \tag{15}$$

where $\mathbf{g}_{m_0}$ is the $N \times 1$ forward model vector (or topography) corresponding to the source located in the $m_0$-th vertex of the cortical mesh with coordinate $\mathbf{r}_{m_0}$, $\boldsymbol{\delta}$ is the source model noise vector to avoid the inverse crime that we set to have variance equal to 15% of $\mathbf{g}_{m_0}$'s norm, $\mathbf{s}^{cT}$ is the $c$-th row of $\mathbf{S}$ and $\mathbf{\Upsilon}_{xl}$ is the realistic brain noise matrix generated by 1000 randomly seeded cortical sources activated with $1/f$ noise, similarly to the way it was done in (Ossadtchi et al., 2018) with factor $\gamma$ controlling the signal-to-noise ratio in the simulated data. Note that each trial had different realization of the spatially correlated noise $\mathbf{\Upsilon}_{xl}$.

We then use the simulated noisy sensor data $\mathbf{X}_l^c$ for $l = 1, \ldots, I_c$ and $c = 1, \ldots, C$ and our aim is using the approximate RDM of a specific source find spatial component(s) whose timeseries, see (11), exhibits the desired representational structure defined by the approximate RDM. The approximate RDM is used to simulate the real-world scenario where we naturally lack precise knowledge of the dissimilarity profile. To this end we incorporate a random $C \times C$ noise matrix $\mathbf{\Upsilon}_d$ at each Monte-Carlo iteration. This addition modifies the theoretical RDM $\mathbb{D}^0$ to $\mathbb{D} = \mathbb{D}^0 + \mathbf{\Upsilon}_d$.

To verify the result we then apply source localization procedure to the discovered component(s) in order to determine the location $\hat{\mathbf{r}}$ of a source (or its index, denoted as $\hat{m}$) the discovered spatial component pertains to and whose activity exhibits the intended theoretical similarity profile. We then use the obtained location to calculate the performance metrics as described in Section 3.1. When source-space RSA is applied to this simulated data our goal is to directly identify the cortical source of interest using the procedures outlined in Figure 1.

In our simulations we have chosen $T = 200$ ms as the length of the window to which RSA is applied. The spectral profiles of the source evoked activity occupied frequency range below 2 Hz to impose the smoothness characteristic of the real evoked responses. As we will show in the example of applying ReDisCA to real EEG data the method can be applied in a sliding window mode and remains operable at $T = 150$ ms. The constraint on the length of the time interval is dictated primarily by the condition

number of the resultant correlation matrices (4) and can be further reduced with proper regularization and/or dimension reduction procedures.

To evaluate the performance of ReDisCA in comparison to the four versions of the source space RSA, we employed the Receiver Operating Characteristic (ROC) curve. This measure, devoid of specific thresholds, gauges the overall informational capacity in the output of these approaches with respect to the detection task. For a detailed explanation of how the ROC curve is calculated, please refer to Section 3.1.

*2.4.3.    Realistic simulations with multiple sources* Another simulation scenario reproduces the situation when the observed evoked responses are generated by a superposition of several sources each with its own representational dissimilarity matrix. To this end we experimented with $P = 4$ sources and their corresponding dissimilarity matrices $\mathbb{D}^{0p}$ and $\mathbb{D}^{p}$, $p = 1, \ldots, \mathcal{P}$. The ideal RDMs of the evoked responses for each of the four sources among $C = 6$ conditions are shown in Figure 3. To evaluate the RSA's robustness we have also experimented with $C = 3, 4, 5$, conditions.

At each Monte-Carlo iteration we have randomly seeded four sources over the cortical mantle with the restriction of no source be closer than $\delta_{min} = 2$ $cm$ to any of the other sources. This gave us $P = 4$ true source location vectors $\mathbf{r}_p^{true}$ and true source topography vectors $\mathbf{g}_p^{true}$, $p = 1, \ldots, P$. We have then noised these true source topographies, projected source activation timeseries to the sensors and added realistic $1/f$ brain noise similarly to (15) as

$$\mathbf{X}^c = \sum_{p=1}^{P} \left( \mathbf{g}_p^{true} + \boldsymbol{\delta}_p \right) \mathbf{s}_p^{cT} + \gamma \boldsymbol{\Upsilon}_x, \tag{16}$$

Overall the approach to constructing the simulated data in this second experiment matched that of the first one with the exception that in the current experiment the simulated data contained the superposition of activity of $P = 4$ simultaneously active task-related sources each with its own RDM.

## 3. Performance metrics

As we described in Section 2 ReDisCA itself does not require the electromagnetic inverse modeling, see also Figure 2. At the same time the source space RSA applied to EEG(MEG) data explicitly uses inverse modeling as highlighted by the diagrams shown in Figure 1. Therefore in order to evaluate ReDisCA's performance and match it against the source space RSA we use components discovered by ReDisCA and fit them with electromagnetic model as described in Section 2 and equations (13, 14).

### 3.1. ROC curves

Within the first set of simulations we evaluated methods' performance using area under ROC curve (ROC AUC) metrics. To compute the ROC curves we first determine

Figure 3: Theoretical RDM matrices for each of the four simulated sources generated within an exemplar Monte-Carlo trial.

the counts of true positives (TP), false positives (FP), true negatives (TN) and false negatives (FN).

To this end as described in Section 2.4 at each $k$-th Monte-Carlo iteration corresponding to a neuronal source placed at a randomly chosen location $\mathbf{r}_k$ we use the scans $\rho_m$, $m = 1, \ldots, M$ described in Section 2 and for each threshold value $\theta$ we find a set of indices $\mathcal{M}_>$ of cortical vertices $m$ for which $\rho_m \geq \theta$. Then, we count the number of vertices in $\mathcal{M}_>$ that fall within a sphere with $r_{max} = 0.01$ m centered around the true source location $\mathbf{r}_k$ simulated during the $k$-th Monte-Carlo iteration and save it to the corresponding true positives count array $TP_k(\theta)$. The count of vertices from $\mathcal{M}_>$

that fall outside the sphere with radius $r_{max}$ is added to the false-positives count array $FP_k(\theta)$.

Next we find a complementary set $\mathcal{M}_<$ of cortical vertex indices $m$ such that $\rho_m < \theta$. We then count the number of vertices from $\mathcal{M}_<$ that appear within the sphere with $r_{max} = 0.01$ m centered around the true source location $\mathbf{r}_k$ and save it to the corresponding false negatives count array $FN_k(\theta)$. The count of vertices from $\mathcal{M}_<$ outside the sphere with radius $r_{max}$ is saved to the true-negatives count array $TN_k(\theta)$.

Then, for each threshold value $\theta$ we compute the average true positive rate ($TPR(\theta)$) or sensitivity and the average false positive rate $FPR(\theta)$ equal to $1 - specificity$ as

$$TPR(\theta) = \frac{\sum_{k=1}^{N_{mc}} TP_k(\theta)}{\sum_{k=1}^{N_{mc}} TP_k(\theta) + FN_k(\theta)} \tag{17}$$

$$FPR(\theta) = \frac{\sum_{k=1}^{N_{mc}} FP_k(\theta)}{\sum_{k=1}^{N_{mc}} FP_k(\theta) + TN_k(\theta)} \tag{18}$$

The pair $(FPR(\theta), TPR(\theta))$ parameterized by $\theta$ forms the ROC curve that we use to compare between different RSA approaches studied in this paper.

## 3.2. Performance gauges for realistic simulations

In the realistic simulations with multiple sources described in Section 2.4.3 we created $P = 4$ simultaneously active sources placed randomly on the cortex during each Monte-Carlo iteration, each with the specific theoretical RDM $\mathbb{D}^p$. In this case we gauged the performance based on the distance between the simulated source locations and those that were estimated using ReDisCA and the two source space RSA implementations that performed best during first set of simulations with a single source, see Section 2.4.2.

To compute this metric at each Monte-Carlo iteration we used the scans $\rho_m^p$, $m = 1, \ldots, M$, $p = 1, \ldots, P$ corresponding to the $p-$th source RDM $\mathbb{D}^p$ and identified the cortical vertex index $m^*$ corresponding to the maximum of $\rho_m^p$ as $m^* = argmax(\rho_m^p)$. We then used the coordinates vector $\mathbf{r}^*$ of the $m^*$ vertex and computed the distance between it and the true location of the $p$-th source $\mathbf{r}_p^{true}$, see Section 2.4.3 as $\delta \mathbf{r}_p = \|\mathbf{r}_p^{true} - \mathbf{r}^*\|$. We then plotted the histograms $\delta \mathbf{r}_p$ observed in the Monte-Carlo trials for each of the compared methods.

At each Monte-Carlo iteration we have also computed the correlation coefficients between spatial topography vector $\mathbf{a}_1^p$ of the first ReDisCA component and the corresponding true source topography vectors $\mathbf{g}_{true}^p$, $p = 1, \ldots, P$. Having performed a set of Monte-Carlo trials we summarized the observed correlation coefficient distributions in the form of histograms.

Finally, we have compared the target RDMs $\mathbb{D}^p = \{d_{ij}^p\}$ from the $p$-th source to the empirical RDMs $\hat{\mathbf{D}}^p$. These empirical RDMs can be obtained from spatially filtered data using ReDisCA-derived filters $\mathbf{w}^p$ as $\hat{\mathbf{D}}^p = \{\hat{d}_{ij}^p\} = \{\mathbf{w}_p^T \mathbf{R}^{ij} \mathbf{w}_p\}$, where $\mathbf{R}_{ij}$ is the

487 $i$-th and $j - th$ condition difference timeseries covariance matrix as desribed in section
488 2.3. Then, we have measured the correlation coefficients between the vectors derived
489 from the upper triangular elements of $\mathbb{D}^p$ and $\hat{\mathbf{D}}^p$ for each $p-$th source, $p = 1, \ldots, P$.
490 Using multiple Monte-Carlo trials, we summarized the distributions of these correlation
491 coefficients in histograms.

## 4. Results

### 4.1. Simulations

In Figure 4, we illustrate the outcomes of the first set of our simulations where we
compared ReDisCA with four versions of the source space RSA, see Figure 1 for their
detailed diagram. As describe before, the aim here was to detect a single neuronal
source using a noisy version of its specific RDM. In Figure 4.a, the blue curve represents
ReDisCA's performance in detection of the representational dissimilarity subspace using
the averaged evoked response data. This method significantly outperforms four different
versions of the source space RSA that employ two different inverse operators: the
minimum norm estimator and the LCMV beamformer. Out of the four source space RSA
approaches LCMV beamformer based on single trials (BF S.T.) approach appears to
perform best. Importantly, ReDisCA yields better ROC AUC values in detecting spatial
component linked to the targeted neuronal source without relying on electromagnetic
inverse modeling and with significantly fewer computations as compared to the source
space RSA. In order to make this conclusion and enable the comparison we employed the
electromagnetic inverse modeling to align ReDisCA's results with those of conventional
RSAs that operate explicitly in the space of neuronal sources, see expressions (13) and
14). Figure 4.b illustrates noisy (blue) and noise free (red) averaged ERP timeseries
and the theoretical dissimilarity matrix used in simulations is shown in the bottom.
Figures 4.c and 4.d show similar results but for SNR = 0.1. As we can see, in this
atypically low SNR case ReDisCA's performance only slightly deteriorates and remains
superior to that of the other methods. ReDisCA appears capable of accurately locating
the target source in nearly 85% cases at almost zero false alarms rate. Comparing the
curves of classical RSA approaches (MNE AV RSA, MNE S.T. RSA, BF AV RSA,
BF S.T. RSA) across two SNR values (panels a) and c) in Figure 4), an interesting
finding emerges. We notice an improvement in the performance of the source space
RSA methods under low SNR conditions compared to higher SNR scenarios in this
single-source simulation. Our analysis reveals that this seeming paradox arises due to a
decrease in false positives in the traditional RSA outputs as SNR decreases. Despite the
use of a realistic brain noise model with spatial correlations, the resulting data matrix
appears 'empty'. This results in the situation where despite the inverse modeling the
sole persistent component of the single source remains spread across numerous cortical
vertices in the source timeseries estimates, which leads to a surplus of high correlations
between the observed and theoretical RDMs. The increased noise levels, however, rectify

Figure 4: Results of 100 MC trials of simulations in single source detection scenario. a) and c) the ROC curves for ReDisCA and four source space RSA versions, see Section 2 for two different SNR levels. b) and d) - noisy (blue) and noise free (red) averaged ERP timeseries for the two SNR values and the theoretical dissimilarity matrix used in the simulations.

this issue, rendering RDM correlation scans more specific which in turn improves the corresponding ROC curves.

This observation aligns with the lower ROC-AUC values observed in the source space RSAs based on the averaged ERP data (BF AV and MNE AV) compared to their single-trial counterparts (BF S.T. and MNE S.T.). In the latter case, dissimilarity scores are computed on individual trials before averaging, while in the former the averaging precedes computation of the vertex-specific between-condition dissimilarity scores based

on the inverse modeling of these averaged ERP data (refer to Figure 1). This paradoxical behavior, however, does not manifest in more realistic simulations involving multiple cortical sources, as described next.

Figure 5: Results of 100 MC trials of realistic simulations with $M = 4$ randomly seeded sources and $C = 6$ conditions: a) Distribution of the true topography and ReDisCA derived pattern correlation coefficient, b) Distribution of the true topography and ReDisCA spatial filter weight vector correlation coefficient, c) Distribution of the correlation coefficient of true RDM and RDMs derived from the multichannel data with the first ReDisCA derived spatial filter, d) Distribution of ReDisCA source localization error, e) Distribution of the MNE spotlight RSA source localization error.

Next we describe the results of more realistic simulations where at each Monte Carlo trial we randomly seeded $M = 4$ sources each with its own RDM, see Section 2.4.3 for details. The results from 100 Monte Carlo trials of these realistic simulations for $C = 5$ conditions are presented in Figure 5 for two SNR values.

In Figure 5.a we show the distribution of source localization errors for four sources (different colors) for the three methods: ReDisCA, BF S.T. RSA and MNE S.T. RSA. Out of compactness considerations we have chosen to present here the results of only

two best performing source space RSA methods, BF S.T. and MNE S.T. As one can see ReDisCA's distribution appears to have the largest proportion of cases where all four source are localized with errors below 1 cm. The distributions of source localization errors delivered by BF S.T. and MNE S.T. are increasingly shifted to the right and result into greater median source localization error as compared to ReDisCA.

Panel b) shows ReDisCA specific metrics described in Section 3.2. From top to bottom we show the distributions of 1) topography correlation coefficient between ReDisCA identified $\mathbf{a}_1$ and the true simulated source topography $\mathbf{g}_p^{true}$, 2) ReDisCA weights $\mathbf{w}_1$ and the true topography $\mathbf{g}_p^{true}$ correlation coefficient and finally 3) correlation coefficient between the target $\mathbb{D}^p$ and observed RDMs $\hat{\mathbf{D}}^p$ for $p = 1, \ldots, 4$.

Since the spatial filters derived by ReDisCA get not only tuned to the target source but also attempt to tune away from the interfering sources (Haufe et al., 2014; Petrosyan et al., 2021) the true source topographies appear to be much better aligned with ReDisCA derived topographies (patterns) than with the corresponding weight vectors. As evident from the bottom plot in Figure 5.b the observed RDMs appear to correlate well with the target RDMs for all four sources. Panels c) and d) of Figure 5 show similar plots but for the decreased Signal-to-Noise Ratio (SNR) equal to 0.2 which allows us to observe that ReDisCA remain operable in these harsh conditions. It is important to note that in simulations by combining noiseless sensor data with noise data matrices, see equation (16), we effectively control the SNR based on the ratio of root mean powers between these two matrices. Therefore, as the number of sources within the noiseless data matrix increases, the SNR per individual source automatically decreases. Hence, in the case of four sources, the SNR of 0.2 represents a notably more challenging task compared to a single-source scenario with the SNR of 0.1.

Finally, we explore the dependence of localization error on the number of conditions employed in RSA analysis. It is intuitive to expect that the increase in the number of conditions should lead to the improved source localization performance in the classical RSA scenario and to better identification of the representationally relevant components by ReDisCA. As before, in order to align ReDisCA's results with those of source space RSA approaches we fitted a dipole to ReDisCA derived source topography vectors $\mathbf{a}_1^p$, $p = 1, \ldots, 4$. The results are presented in Figure 6 in the form of three graphs corresponding to the average median localization error achieved by the three techniques. As expected the increase in the number of conditions leads to the decrease of source localization error. ReDisCA furnishes the best performance for all $C$, the mean median error appears to be less than 2 cm for $C = 6$ conditions.

## 4.2. Real data analysis example

To demonstrate ReDisCA in application to real data we have selected a publicly available low density EEG N170 dataset available at https://osf.io/pfde9/ and described in (Kappenman et al., 2021). In that data the N170 was elicited in a face perception task with stimuli from from (Rossion and Caharel, 2011). In this task, an image of a

Figure 6: Average median localization error of 4 simultaneously active sources (each with its own RDM) as a function of the conditions count $C$ for three methods ReDisCA, beamformer powered single trial RSA and MNE powered single trial RSA. As expected the increase in the number of conditions leads to the decrease of source localization error. ReDisCA furnishes the best performance for all $C$, the mean median error appears to be less than 2 cm for $C = 6$ conditions.

face, car, scrambled face, or scrambled car was presented on each trial in the center of the screen, and participants responded whether the stimulus was an "object" (face or car) or a "texture" (scrambled face or scrambled car). The data were preprocessed and three ICA components corresponding to ocular and cardiac artifacts were removed from the data. Then, the ERP were computed by averaging responses within each of the stimulus types.

We first applied ReDisCA to exploring the spatial-temporal structure of the response to meaningful versus meaningless stimuli that were formed as the scrambled versions of the original images. For that we formed the theoretical RDM shown in Figure 7.a. Then, scanning over time windows of duration $T = 150$ ms and calculating the $p$-

values we obtain their color-coded map shown in Figure 7.b with rows corresponding to the components and columns encode time. We then visualized $p$-values corresponding to the first two components and identify the time interval corresponding to a continuous segment of $p < 0.05$. As can be seen from Figure 7.d we found such a segment at around $t = 400$ ms. The corresponding pattern is visualized in panel c) and has highly pronounced occipital topography. This result is in agreement with observations made in a high density EEG-based study (Mensen et al., 2017) that demonstrates statistically significant difference between meaningful and meaningless stimuli occurring in the time-window around 300-500 ms and is localized to the occipital area of the scalp. ReDisCA missed the first peak at around 100 ms reported in (Mensen et al., 2017) but that could be explained by a smaller number of electrodes in the current dataset as compared to the one analyzed in (Mensen et al., 2017).

The presence of the theoretical meaningful vs. meaningless RDM was observed over 3 adjacent time windows. Figure 8 shows the discovered topographic patterns of the first ReDisCA component, the corresponding timecourses of this component observed within the four different conditions as well as the observed (or empirical) color coded RDM in the bottom most panel. As we can see the yellow and violet timecourses corresponding to the meaningless stimuli appear clearly disentangled from the red and blue ones observed during the presentation of meaningful pictures. The topography of the first significant ReDisCA component ($p < 0.05$) remains highly similar over the three consecutive time windows. Interestingly, the timeseries of this ERP component observed during the presentation of faces (blue) exhibits longer lasting traces as compared to that corresponding to the activity during the presentation of cars (red curve) which is consistent with the findings reported in several studies exploring neural correlates of face perception in humans. Consequently, the observed RDMs indeed appear to closely resemble the target RDM, see Figure 7.a used for the described inquiry. Comparing the evolution of the topography of the first (the only one found significant) ReDisCA component we can observe its gradual displacement in the sagital plane moving downwards with time followed by deepening (the topography widens) of the source at the last time stamp. This may correspond to the traveling wave patterns found in the visual area (Sato et al., 2012; Benigno et al., 2023).

We proceeded by examining the activity associated with particular meaningful stimuli using the RDMs displayed in Figure 9.a for faces and Figure 9.b for cars, respectively. These RDMs guide our search towards a component with a distinct activity in one condition (face or car) different from that observed in the remaining three conditions. Additionally, unlike it may be the case in the decoding based MBPA approaches the RDMs prescribe the activity during the remaining three conditions to be similar.

According to the large volume of studies N170 ERP component is considered to be face specific and occurs at around 170 ms latency. We have therefore selected the time window of duration $T = 100$ ms centered at 200 ms and applied ReDisCA to it using the theoretical RDM shown in Figure 9.a. Figure 10 shows ReDisCA's output and as we

Figure 7: Meaningful vs meaningless stimuli perception analysis. a) Theoretical RDM contrasting the two type of stimuli. b) Color-coded map of component $p$-values, each row corresponds to a component and columns encode time. c) Topography (pattern) of the first and the only significant component during the time interval around $t = 400$ ms. d) Temporal profiles of the $p$-values corresponding to the first two components. The signifcant segmant is marked with asterisks.

can see from the top panel of 10 the first and the only significant ReDisCA component has topography corresponding to a source in the right fusiform gyrus, the area known to be crucial to perception of facial information and differentially activated in response to regular or scrambled face stimuli (Haist and Anzures, 2017; Kozunov et al., 2018).

The corresponding ERP components obtained by filtering the multichannel ERP with a spatial filter derived by ReDisCA are presented in the panel below the topography. We indeed can observe a burst of activity around 170 ms in the "face" condition while

Figure 8: Meaningful vs. meaningless stimuli perception analysis. Topography, spatially filtered timecourses and the observed RDMs for the three consecutive time slices at around $t = 400$ ms, see also Figure 7.d

Figure 9: Theoretical RDMs corresponding to faces (a) and cars (b)

in the other three conditions the response curves do not have such a burst and are very closely aligned implementing the requirement imposed by the RDM matrix. In agreement with other studies the discovered face-related ERP components remains active over a long duration of response. The observed RDM is shown in the bottom most panel. We can see that it aligns well with the theoretical RDM and exhibits high correlation coefficient of 0.82.

Finally, we performed similar processing but using the theoretical RDM from Figure 9.b designed to highlight response components specific to processing of car images. We have found two signifcant components with $p < 0.01$ shown in Figure 11. The first components appear to have a lower occipital topography with the time course exhibiting deflection at around 150 ms that is specific to the second condition (car images). This reflects activity in the ventral visual pathway during the image perception task. The traces of this ReDisCA component appear to be remarkably similar in the other three conditions not only during the target interval but also over the entire response duration. The observed and the theoretical RDM appear highly correlated with correlation coefficient greater than 0.99.

Interestingly, the second component has a pronounced topography that may reflect the activity in the dorsal visual pathway that is known to accompany visual perception of objects and is hypothesized to reflect the neural processes of formation of spatial relations between the objects within the scene that is then fed to the ventral visual stream (Ayzenberg and Behrmann, 2022). It may also be related to identifying the car as a graspable tool as far as the steering wheel is concerned (Almeida et al., 2010).

Figure 10: ReDisCA of face specific responses using the RDM depicted in Figure 9.a. The top panel shows the topography (pattern) of the first and the only significant ReDisCA component. The topography corresponds to a source in the right fusiform gyrus, the area pivotal to perception of facial information. In the central panel the corresponding ERP components in the four conditions are displayed. The observed RDM is shown in the bottom most panel and exhibits high correlation coefficient of 0.82 with the theoretical RDM.

Based on the above we can conclude that the reported real data analysis results obtained with a direct application of ReDisCA to the averaged ERP data appear to align well with the existing knowledge in the field of neuroimaging related to visual perception of faces and cars and differentiation between meaningful and meaningless stimuli including not only spatial but also temporal structure of this process.

Figure 11: Two significant components discovered by ReDisCA using car detector RDM (Figure 9.b) applied at $t = 170$ ms latency.

These findings obtained with ReDisCA appear be inline with what's already known in the field of neuroimaging regarding the brain processes underlying visual perception. This includes distinguishing between meaningful and meaningless stimuli, delineation of face specific and cars specific activations considering both the spatial and temporal aspects of this cognitive process. The superiority of ReDisCA over the source space RSA methods, as demonstrated in simulations, combined with low computational costs and its promising performance in real data analysis, suggests the need for further exploration of this new tool. ReDisCA not only democratizes the application of the powerful RSA principle to the cases where explicit inverse modeling is not possible or desired but also significantly reduces computational costs, making ReDisCA a valuable tool for future

679 neuroimaging research.

## 5. Discussion

Conceptually, ReDisCA extends the family of the previously developed methods for
decomposing multichannel EEG and MEG data and extracting the spatial-temporal
components with desired properties. One popular example is the Spatial Spectral
Decomposition (SSD) technique (Nikulin et al., 2011). SSD seeks to maximize the
power at a frequency band of interest while simultaneously minimizing it within the
side bands. For each specific triplet of frequency bands (one central and two flanking)
the SSD results in a set of spatial components whose timeseries exhibit the frequency
band selective property. In particular, the timecourses of the SSD-derived spatial
components are characterized by the maximal ratio of power within the central band
to that within the two flanking sub-bands which justifies the use of SSD for extracting
rhythmic components from multichannel EEG or MEG timeseries. Another popular
method is the Source Power Comodulation, or SPoC (Dähne et al., 2014). SPoC
aims to find spatial filters and patterns by using in the decomposition process a target
behavioral variable in order to emphasize the components whose instantaneous power
profile correlates with the target variable. Typically SPoC targets rhythmic activity and
extracts its sources whose envelope aligns well with the target variable. Notably, neither
SSD nor SPoC or their early forerunner ICA require forward and inverse modeling
machinery to extract target component timeseries. Theoretically speaking, the design
of either of these methods does not require that the obtained components correspond
to a specific neuronal source with a well defined location. In practice, however, the
obtained patterns that pertain to individual components exhibit remarkable alignment
with the appropriate dipolar electromagnetic model and allow for pinpointing a specific
cortical location as a source of activity with the desired property.

In its current version ReDisCA operates with evoked response data recorded over
several experimental conditions and aims at finding spatial components (each potentially
corresponding to a distinct neuronal source) whose activation timeseries exhibit the
expected representational structure. We have started with the Euclidean norm as
a measure of similarity between component activation timeseries. This continuous
measure of dissimilarity not only allows for an analytic solution of the subsequent
optimization problem but appears superior (Walther et al., 2016; Guggenmos et al.,
2018) to the simplest forms of more intricate classification accuracy based distances.
Based on this and using the standard notion of spatial filtering of multichannel EEG or
MEG data we devised ReDisCA as the approach for dissecting the evoked responses into
a set of spatial components with activation timeseries that adhere to the user supplied
target (or theoretical) representational dissimilarity structure.

To achieve this we have formulated the specific constrained optimization problem
(5). Its solution gives us the spatial filters whose application to the multichannel
evoked response yields component activation timeseires with the expected target

representational structure encoded by the prespecified target RDM. These timeseries combined with the spatial patterns corresponding to each of the spatial filters (Haufe et al., 2014; Petrosyan et al., 2021; Kay, 1993) give us spatial decomposition of the multichannel evoked responses observed over the range of experimental conditions. The goodness of fit is given by the corresponding generalized eigenvalue.

In contrast to the source space RSA (Kozunov et al., 2018) ReDisCA does not require inverse modeling and does not perform an explicit and exhaustive scan over brain sources in the attempt to pinpoint those whose empirical RDM is close enough to the target RDM. Conceptually the role of inverse modeling in ReDisCA is similar to that in the MVPA analysis of EEG or MEG data, see for example (Clarke et al., 2015). While the inverse modeling can be applied to the patterns (Haufe et al., 2014; Kay, 1997) obtained from the regression weights it is not the essential step in the analysis.

In order to compare ReDisCA to the source space RSA we fitted an electromagnetic model to the signal subspace spanned by the topographies of the statistically significant ReDisCA components, see equation (14) and compared the obtained locations to those of simulated sources. This allowed us to rigorously compare ReDisCA against the explicit inverse modeling driven RSA. ReDisCA has successfully identified the signal subspace corresponding to the simulated sources and provided higher ROC AUC scores as compared to the source space RSA based on the exhaustive scan. Note that in our implementation of the source space RSA we analyzed each cortical source separately, used MNE and LCMV beamformer as inverse solvers and employed the L2-norm as the dissimilarity measure instead of sLORETA and LDA classifier used in (Kozunov et al., 2018). However, when matching these two techniques against each other one has to keep in mind that ReDisCA uses less information and does not require inverse modeling which makes it applicable to a broader collection of datasets and modalities. For example, ReDisCA may be an interesting option to employ for analysis of ECoG data where forward and inverse modeling are less straightforward than it is with non-invasive EEG or MEG data. Also, ReDisCA is directly applicable to the averaged evoked responses timeseries and does not require the presence of the single trial data.

Any RSA implementation benefits from the increase in the number of experimental conditions. Although we demonstrated that ReDisCA outperformed conventional RSA approaches for all tested counts of conditions (3,4,5,6), the practically useful results can be obtained from datasets with no less than four conditions. MNE inverse solver appeared to be a better option as compared to the LCMV beamformer for the number of conditions less than 6. ReDisCA yielded almost 2-fold reduction in the mean source localization error as compared to the exhaustive scanning source space RSA. The approach reported in (Kozunov et al., 2018) where voxel timeseries obtained with sLORETA are combined into ROIs followed by dimension reduction and LDA classification. This combination may potentially improve accuracy of the exhaustive scan based RSA however, requires significantly more computations and in contrast to ReDisCA is not directly applicable to the averaged evoked responses timeseries.

As we show, ReDisCA's optimization problem is mathematically similar to that

of SPoC but is based on the modified input data matrices computed as the difference between the evoked responses registered in each pair of conditions. The role of behavioral variable is played by the entries of the theoretical RDM, see Table 1.

In the future, ReDisCA can potentially adopt cross-validated Euclidean distances (Walther et al., 2016). To cope with the inherent asymmetry one can use a symmetric version of it as $d_{c.v.}^{ij} = \frac{1}{2}\mathbf{w}^T\left(\mathbf{R}_{[A][B]}^{ij} + \mathbf{R}_{[B][A]}^{ij}\right)\mathbf{w}$, where $\mathbf{R}_{[A][B]}^{ij} = \left(\mathbf{X}_{[A]}^{c_i} - \mathbf{X}_{[A]}^{c_j}\right)\left(\mathbf{X}_{[B]}^{c_i} - \mathbf{X}_{[B]}^{c_j}\right)^T$ and $\mathbf{R}_{[B][A]}^{ij} = \left(\mathbf{X}_{[B]}^{c_i} - \mathbf{X}_{[B]}^{c_j}\right)\left(\mathbf{X}_{[A]}^{c_i} - \mathbf{X}_{[A]}^{c_j}\right)^T$ with $\mathbf{X}_{[A]}^{c_i}$ representing averaged responses corresponding to condition $c_i$ and obtained using base data partition A and $\mathbf{X}_{[B]}^{c_i}$ - using validation partition B. Investigation of the utility of this cross-validated distance in the ReDisCA setting is a separate topic that needs to be addressed by the future studies.

Feature-weighted RSA is a modification of RSA that allows to better align the observed and the theoretical RDMs (Kaniuth and Hebart, 2022). This is achieved by mixing the RDMs that pertain to the individual features, e.g. voxels comprising an ROI, with optimal weights maximizing the similarity of this mixed RDM and its theoretical target. In application to EEG and MEG data the role of individual features is played by individual channels and therefore the adaptively tuned weights may be considered as some sort of spatial filtering. At the same time, since the weighted RDM matrix entries appear in the form of non-linearly transformed channel data (squared distances, functions of classification accuracy, etc.) the coefficients of such a mixing can not be transformed into electromagnetically meaningful patterns and are therefore difficult to interpret (Foged et al., 2022).

In contrast, ReDisCA by design seeks for a linear spatial filter applied directly to the channel data to isolate a source with the desired representational pattern. Because of this, the weights vector can be easily converted to source topography, or pattern (Kay, 1997; Haufe et al., 2014), that takes into account the spatial correlation structure present in the data. This guarantees that the discovered spatial patterns can be used for implementing a rigorous source localization procedure based on the notion of signal subspace as described for example in (Mosher et al., 1992). This property positively distinguishes ReDisCA from the sensor space RSA approach described in (Mensen et al., 2017) where the authors using high density EEG were able to highlight the detailed spatial and temporal patterns of responses underlying various aspects of meaningfulness in the presented visual stimuli. They achieved this using newly proposed differentiation analysis (DA) and computed temporal and spatial profiles of the category differentiation index (CDI) that can be used to make judgments about time windows and approximate spatial locations of the pivotal sources. However, due to their empirical nature the obtained spatial CDI maps can not be rigorously fitted with an electromagnetic model and therefore are only tangentially related to the underlying distribution of cortical sources whose activity exhibits the desired representational properties.

ReDisCA is formulated to search for a single spatial vector, as indicated by Equation (5), and evaluates the similarity of activation in the temporal dimension. This places

specific constraints on the size of the temporal window $T$ to ensure ReDisCA's proper functioning. It's crucial to recognize that the size of this window is contingent upon the frequency content of the investigated evoked response. Faster-changing signals permit more information (pertaining to similarity/dissimilarity) within shorter time intervals.

Additionally, the window size is influenced by the number of sensors employed. In theory, larger sensor arrays necessitate longer windows to ensure the correlation matrices are full rank. Note however, that typically, EEG and MEG data are projected into smaller subspaces with dimensions 10-100. All subsequent operations are conducted within this reduced dimensional space to guarantee the full rank of the resulting matrices. An alternative or additional approach involves employing the Tikhonov regularization strategy when computing the inverse of the correlation matrix $\bar{\mathbf{R}}$. It's evident that reducing the subspace size and increasing the regularization parameter, in addition to enhancing stability, adversely impacts ReDisCA's spatial resolution. Guidelines detailing these trade-offs must be developed in the future, drawing upon both simulations and theoretical analyses followed by verification with real data.

The approaches such as SSD, SPoC and now ReDisCA are designed to be applied to a single subject. When the conclusion needs to be drawn from a cohort of subjects, special steps need to be undertaken. For example, in the source space RSA approach reported in (Kozunov et al., 2018) pooling across subjects is performed using the standard in MEG approach based on warping individual cortex geometries onto the canonical cortex followed by calculation of the group level statistics. Given the demonstrated here superiority of ReDisCA as compared to the explicit scan in detecting sources with given RDMs, see Figures 4 and 5, the source space estimates can be obtained by applying the individual inverse modeling to the patterns discovered by ReDisCA followed by warping these individual results onto the canonical brain. It is potentially possible to consider development of group-level approaches, conceptually similar to those reported in (Kozunov and Ossadtchi, 2015; Janati et al., 2020) and driven by ReDisCA functional (5).

ReDisCA's applications extend beyond EEG and MEG data analysis to potentially include the ROI-based examination of fMRI data. Interpreting the weights that scale individual voxel RDMs, as introduced in (Kaniuth and Hebart, 2022), poses challenges in converting it into a pattern, as discussed in (Haufe et al., 2014). Here, the difficulty arises because the weights in (Kaniuth and Hebart, 2022) are applied to the Representational Dissimilarity Matrices (RDMs) of individual voxels and not to the actual voxel activations. Since the RDM elements are non-linear functions of voxel activation, the weights in (Kaniuth and Hebart, 2022) can not be converted into within ROI activation patterns highlighting the voxels that contribute most to the target RDM.

Employing ReDisCA within each ROI may resolve this challenge, by applying weights to the activation of individual voxels rather than to their non-linear functions. This would enable the subsequent transformation of ReDisCA weights into patterns (Haufe et al., 2014; Parra et al., 2003) which could enhance the spatial resolution of fMRI-based functional mapping by clarifying the delineation of an extended ROI into

subregions contributing to the improved alignment with the target RDM.

Moreover, ReDisCA can advance the methodology outlined in (Laakso and Cottrell, 2000), where the RSA principle was used to analyze representations emerging in the layers of an artificial neural network. An intriguing possibility arises when ReDisCA-derived weights align with those of a subsequent neuron connected to the analyzed layer, signifying that the individual neuron appears to be tuned to track the representational structure encoded in the target RDM.

## 6. Conclusion

In conclusion, this study introduces and applies the novel technique of Representational Dissimilarity Component Analysis (ReDisCA) to overcome challenges associated with classical Representational Similarity Analysis (RSA), particularly in EEG and MEG data. By estimating spatial-temporal components aligned with a target representational dissimilarity matrix (RDM), ReDisCA produces spatial filters and associated topographies that reveal "representationally relevant" sources. The application of these spatial filters to evoked response timeseries demonstrates superior performance in terms of source localization accuracy compared to conventional source space RSA, with significantly fewer computations. Our approach does not require forward modeling and any geometric information but if these are available the obtained components permit rigorous fits with electromagnetic model by means of a plethora of methods for solving the inverse problem. The methodology is validated through realistic simulations and applied to a real EEG dataset, showcasing its potential for discovering representational structures without relying on inverse modeling. In the discussion, we highlighted the limitations of ReDisCA, outlined potential directions for its further development, and identified novel applications.

## 7. Funding

The article was prepared within the framework of the Basic Research Program at HSE University.

## 8. Conflict of interest statement

The authors declare that they have no conflicts of interest regarding the publication of this article.

## References

Aguirre, G. K. (2007). Continuous carry-over designs for fmri. *Neuroimage*, 35(4):1480–1494.

Almeida, J., Mahon, B. Z., and Caramazza, A. (2010). The role of the dorsal visual processing stream in tool identification. *Psychological science*, 21(6):772–778.

Ayzenberg, V. and Behrmann, M. (2022). The dorsal visual pathway represents object-centered spatial relations for object recognition. *Journal of Neuroscience*, 42(23):4693–4710.

Benigno, G. B., Budzinski, R. C., Davis, Z. W., Reynolds, J. H., and Muller, L. (2023). Waves traveling over a map of visual space can ignite short-term predictions of sensory input. *Nature Communications*, 14(1):3409.

Carlson, T. A., Schrater, P., and He, S. (2003). Patterns of activity in the categorical representations of objects. *Journal of cognitive neuroscience*, 15(5):704–717.

Cichy, R. M., Pantazis, D., and Oliva, A. (2016). Similarity-based fusion of meg and fmri reveals spatio-temporal dynamics in human cortex during visual object recognition. *Cerebral Cortex*, 26(8):3563–3579.

Clarke, A., Devereux, B. J., Randall, B., and Tyler, L. K. (2015). Predicting the time course of individual objects with meg. *Cerebral cortex*, 25(10):3602–3612.

Cox, D. D. and Savoy, R. L. (2003). Functional magnetic resonance imaging (fmri) "brain reading": detecting and classifying distributed patterns of fmri activity in human visual cortex. *Neuroimage*, 19(2):261–270.

Dähne, S., Meinecke, F. C., Haufe, S., Höhne, J., Tangermann, M., Müller, K.-R., and Nikulin, V. V. (2014). Spoc: a novel framework for relating the amplitude of neuronal oscillations to behaviorally relevant parameters. *NeuroImage*, 86:111–122.

Edelman, S. (1998). Representation is representation of similarities. *Behavioral and brain sciences*, 21(4):449–467.

Foged, M. T., Scherg, M., Fabricius, M., and Beniczky, S. (2022). Learn to interpret voltage maps: an atlas of topographies. *Epileptic Disorders*, 24(2):229–248.

Guggenmos, M., Sterzer, P., and Cichy, R. M. (2018). Multivariate pattern analysis for meg: A comparison of dissimilarity measures. *Neuroimage*, 173:434–447.

Haist, F. and Anzures, G. (2017). Functional development of the brain's face-processing system. *Wiley Interdisciplinary Reviews: Cognitive Science*, 8(1-2):e1423.

Haufe, S., Meinecke, F., Görgen, K., Dähne, S., Haynes, J.-D., Blankertz, B., and Bießmann, F. (2014). On the interpretation of weight vectors of linear models in multivariate neuroimaging. *Neuroimage*, 87:96–110.

Hung, C. P., Kreiman, G., Poggio, T., and DiCarlo, J. J. (2005). Fast readout of object identity from macaque inferior temporal cortex. *Science*, 310(5749):863–866.

Janati, H., Bazeille, T., Thirion, B., Cuturi, M., and Gramfort, A. (2020). Multi-subject meg/eeg source imaging with sparse multi-task regression. *NeuroImage*, 220:116847.

Kaniuth, P. and Hebart, M. N. (2022). Feature-reweighted representational similarity analysis: A method for improving the fit between computational models, brains, and behavior. *NeuroImage*, 257:119294.

Kappenman, E. S., Farrens, J. L., Zhang, W., Stewart, A. X., and Luck, S. J. (2021). Erp core: An open resource for human event-related potential research. *NeuroImage*, 225:117465.

Kay, S. M. (1993). *Fundamentals of statistical signal processing: estimation theory*. Prentice-Hall, Inc.

Kay, S. M. (1997). *Fundamentals of Statistical Signal Processing: Estimation Theory*. Prentice Hall.

Khaligh-Razavi, S.-M., Henriksson, L., Kay, K., and Kriegeskorte, N. (2017). Fixed versus mixed rsa: Explaining visual representations by fixed and mixed feature sets from shallow and deep computational models. *Journal of Mathematical Psychology*, 76:184–197.

King, J.-R. and Dehaene, S. (2014). Characterizing the dynamics of mental representations: the temporal generalization method. *Trends in cognitive sciences*, 18(4):203–210.

Kozunov, V., Nikolaeva, A., and Stroganova, T. A. (2018). Categorization for faces and tools—two classes of objects shaped by different experience—differs in processing timing, brain areas involved, and repetition effects. *Frontiers in Human Neuroscience*, 11:650.

Kozunov, V. V. and Ossadtchi, A. (2015). Gala: group analysis leads to accuracy, a novel approach for solving the inverse problem in exploratory analysis of group meg recordings. *Frontiers in Neuroscience*, 9:107.

Kriegeskorte, N. and Kievit, R. A. (2013). Representational geometry: integrating cognition, computation, and the brain. *Trends in cognitive sciences*, 17(8):401–412.

Kriegeskorte, N., Mur, M., and Bandettini, P. A. (2008a). Representational similarity analysis-connecting the branches of systems neuroscience. *Frontiers in systems neuroscience*, page 4.

Kriegeskorte, N., Mur, M., Ruff, D. A., Kiani, R., Bodurka, J., Esteky, H., Tanaka, K., and Bandettini, P. A. (2008b). Matching categorical object representations in inferior temporal cortex of man and monkey. *Neuron*, 60(6):1126–1141.

Laakso, A. and Cottrell, G. (2000). Content and cluster analysis: assessing representational similarity in neural systems. *Philosophical psychology*, 13(1):47–76.

Makeig, S., Bell, A., Jung, T.-P., and Sejnowski, T. J. (1995). Independent component analysis of electroencephalographic data. *Advances in neural information processing systems*, 8.

Maris, E. and Oostenveld, R. (2007). Nonparametric statistical testing of eeg-and meg-data. *Journal of neuroscience methods*, 164(1):177–190.

Mensen, A., Marshall, W., and Tononi, G. (2017). Eeg differentiation analysis and stimulus set meaningfulness. *Frontiers in psychology*, 8:1748.

Mosher, J. C. and Leahy, R. M. (1999). Source localization using recursively applied and projected (rap) music. *IEEE Transactions on signal processing*, 47(2):332–340.

Mosher, J. C., Lewis, P. S., and Leahy, R. M. (1992). Multiple dipole modeling and localization from spatio-temporal meg data. *IEEE transactions on biomedical engineering*, 39(6):541–557.

Nikulin, V., Nolte, G., and Curio, G. (2011). A novel method for reliable and fast extraction of neuronal EEG/MEG oscillations on the basis of spatio-spectral decomposition. *Neuroimage*.

Op de Beeck, H., Wagemans, J., and Vogels, R. (2001). Inferotemporal neurons represent low-dimensional configurations of parameterized shapes. *Nature neuroscience*, 4(12):1244–1252.

Ossadtchi, A., Altukhov, D., and Jerbi, K. (2018). Phase shift invariant imaging of coherent sources (psiicos) from meg data. *NeuroImage*, 183:950–971.

Ossadtchi, A., Pronko, P., Baillet, S., Pflieger, M. E., and Stroganova, T. (2014). Mutual information spectrum for selection of event-related spatial components. application to eloquent motor cortex mapping. *Frontiers in Neuroinformatics*, 7:53.

Parra, L., Alvino, C., Tang, A., Pearlmutter, B., Yeung, N., Osman, A., and Sajda, P. (2003). Single-trial detection in eeg and meg: Keeping it linear. *Neurocomputing*, 52:177–183.

Pascual-Marqui, R. D. et al. (2002). Standardized low-resolution brain electromagnetic tomography (sloreta): technical details. *Methods Find Exp Clin Pharmacol*, 24(Suppl D):5–12.

Petrosyan, A., Sinkin, M., Lebedev, M., and Ossadtchi, A. (2021). Decoding and interpreting cortical signals with a compact convolutional neural network. *Journal of Neural Engineering*, 18(2):026019.

Pfurtscheller, G., Guger, C., and Ramoser, H. (1999). Eeg-based brain-computer interface using subject-specific spatial filters. In *Engineering Applications of Bio-Inspired Artificial Neural Networks: International Work-Conference on Artificial and Natural Neural Networks, IWANN'99 Alicante, Spain, June 2–4, 1999 Proceedings, Volume II 5*, pages 248–254. Springer.

Rossion, B. and Caharel, S. (2011). Erp evidence for the speed of face categorization in the human brain: Disentangling the contribution of low-level visual cues from face perception. *Vision research*, 51(12):1297–1311.

Sato, T. K., Nauhaus, I., and Carandini, M. (2012). Traveling waves in visual cortex. *Neuron*, 75(2):218–229.

Shea, N. (2018). *Representation in cognitive science*. Oxford University Press.

Tsao, D. Y., Freiwald, W. A., Tootell, R. B., and Livingstone, M. S. (2006). A cortical region consisting entirely of face-selective cells. *Science*, 311(5761):670–674.

Van Veen, B., Van Drongelen, W., Yuchtman, M., and Suzuki, A. (1997). Localization of brain electrical activity via linearly constrained minimum variance spatial filtering. *IEEE Transactions on Biomedical Engineering*, 44(9):867–880.

995   Walther, A., Nili, H., Ejaz, N., Alink, A., Kriegeskorte, N., and Diedrichsen, J. (2016).
996       Reliability of dissimilarity measures for multi-voxel pattern analysis. *Neuroimage*,
997       137:188–200.