Phase delays between mouse globus pallidus neurons entrained by common

oscillatory drive arise from their intrinsic properties, not their coupling

<u>Short title</u>: Phase locking and correlations in globus pallidus

<u>Authors:</u> Erick Olivares[1], Charles J. Wilson[1] and Joshua A. Goldberg[1,2*]

[1]Department of Neuroscience, Developmental and Regenerative Biology, University of Texas at San

Antonio, San Antonio, Texas 78249, USA

[2]Department of Medical Neurobiology, Institute of Medical Research Israel – Canada, Faculty of

Medicine, The Hebrew University of Jerusalem 9112102, Israel

*Corresponding author

E-mail: joshua.goldberg2@mail.huji.ac.il

Abstract

A hallmark of Parkinson's disease is the appearance of correlated oscillatory discharge throughout the cortico-basal ganglia (BG) circuits. In the primate globus pallidus (GP), where the discharge of GP neurons is normally uncorrelated, pairs of GP neurons exhibit oscillatory spike correlations with a broad distribution of pairwise phase delays in experimental parkinsonism. The transition to oscillatory correlations is considered an indication of the collapse of the normally segregated information channels traversing the BG, and the large phase delays are thought to reflect pathological changes in synaptic connectivity in the BG. Here we study the structure and phase delays of correlations measured from independent neurons in the mouse external GP (GPe) subjected to an identical 1-100 Hz sinusoidal drive. We find that spectral modes of a GPe neuron's empirical instantaneous phase response curve (iPRC), elucidate at what phases of the oscillatory drive the GPe neuron locks when it is entrained, and the distribution of phases at which it fires when it is not. We show, mathematically, that the spike cross-intensity function (CIF) is the cross-correlation function of the spike phase distributions of a neuronal pair. Moreover, the distribution of GPe CIF phase delays arises from the diversity of iPRCs, and is broadened when the neurons become entrained. Modeling GPe networks with realistic intranuclear connectivity demonstrates that the connectivity decorrelates GPe neurons without affecting CIF phase delays. Thus, common oscillatory drive gives rise to GPe correlations whose diverse structure and pairwise phase delays reflect their intrinsic properties as captured by their iPRCs.

Author's summary

The external globus pallidus (GPe) is a hub in the basal ganglia, whose neurons impose a barrage of inhibitory synaptic currents on neurons of the subthalamic nucleus, substantia nigra and internal globus pallidus. GPe neurons normally fire independently, but in experimental parkinsonism, they become correlated in the frequency range associated with the pathological rhythms seen in human Parkinson's disease, raising the possibility that they may be generators of the pathological oscillation. We drove individual pallidal neurons with an oscillatory input over a wide range of frequencies. Cross-correlations of these neurons reproduced many of the features seen in parkinsonism, suggesting that their correlated oscillations might derive from a shared input rather than internal interconnections.

Introduction

Anatomical convergence is a key feature of the cortico-basal ganglia (BG) circuit [1,

2, 3]. Much of this convergence occurs in the striatopallidal projection, in which millions of

striatal projection neurons converge in rodents onto tens of thousands of external globus

pallidus (GPe) neurons, each of which is densely covered with a mosaic of synapses arising

from a large number of striatal neurons [1, 4, 5, 6]. Despite the converging innervation of

GPe neurons [4, 7, 8, 9], the firing of GPe neurons remains uncorrelated under normal

conditions [4, 9, 10, 11, 12, 13, 14, 15]. The uncorrelated nature of GPe firing is thought to be

important for maintaining independent channels of information flow via the cortico-BG

circuit [16, 17], which is necessary for effective action selection [18, 19].

In experimental parkinsonism, the firing of GPe neurons becomes correlated, with

their pairwise correlations showing oscillations in the beta frequency range [10, 11, 13, 14,

15, 20, 21]. Beta-range oscillations throughout the cortico-BG circuits are a hallmark of

parkinsonian pathophysiology both in animal models [13, 15, 22, 23] and in humans [24, 25,

26]. The GPe may even be the source of the beta oscillations [27].

How do oscillatory correlations appear specifically in the GPe in the parkinsonian

state? Possibly there are changes in striatopallidal or pallidopallidal synaptic connectivity that

enhance shared inputs [28, 29, 30]. Alternatively, or additionally, there may be an oscillatory

correlation among the neurons presynaptic to the GPe neurons. In this scenario, pairs of GPe

neurons are conditionally correlated, meaning that the common input is the only source of

correlation between the neurons [23].

There are synaptic changes in GPe [31, 32, 33] and other BG nuclei [34, 35, 36, 37,

38] in parkinsonian animals, but these changes have not been shown to produce correlated

oscillations. On the other hand, if the GPe neurons were simply being driven by common

input in the beta frequency, intuition suggests that their oscillations should be synchronous,

because the striatopallidal axonal and synaptic delays would be comparable for all neurons

receiving the common inputs [39]. However, the experimentally measured pairwise spiking

correlations in parkinsonian animals were not synchronous but had broad distribution of

delays [10, 11, 40]. What could cause the differences in the phases of oscillations in GPe

neurons? Possibly, there could be some undiscovered heterogeneity in the oscillatory input,

so that otherwise similar GPe neurons are driven by different inputs at the same frequency

but different phase. It is also possible that differences among neurons in the phase of

oscillations might arise somehow from the inhibitory synaptic interactions between GPe

neurons. Finally, there could be a heterogeneity of cellular properties that could cause GPe

neurons to fire at different phases of a shared common input.

In the present study, we examine the structure of correlations between pallidal

neurons driven by a common oscillation. GPe neurons are autonomous pacemakers whose

firing becomes entrained by oscillatory inputs over a wide frequency range of 10-70 Hz [28,

41, 42]. We therefore addressed the following questions. What determines the distribution of

stimulus phases at which each GPe neuron fires, and how does this change with the frequency

of the input? Can the delays in the correlations among pairs of neurons be predicted from the

differences in these spike phase distributions? Can common drive generate a broad range of

phase differences even when the two GPe neurons are entirely independent of each other?

How might the known intrinsic connectivity among GPe neurons influence the correlations

among them both in term of their strength and phase differences?

86   **Results**

87   **GPe neurons driven periodically exhibit phase locking**

GPe neurons ($n = 16$) were recorded in acute brain slices (from $N = 14$ mice) in the

perforated patch configuration to preserve their autonomous firing over the long recording

duration. Each neuron was subjected to a sequence of 100 ten-second-long sinusoidal current

waveforms at frequencies 1, 2, 3, …, 100 Hz, each with an amplitude of 20 pA. This

amplitude, although small in comparison to *in vivo* synaptic currents, proved to be sufficient

for inducing rate modulation and spike entrainment in our experimental setup. In 3 of the 16

neurons the cell did not survive all 100 trials, but all neurons were recorded up to 50 Hz. As

we reported previously [42], the sinusoidal drive influences the timing of the spikes (Fig. 1A)

causing the spike times to distribute non-uniformly across the phases of the sinusoidal

waveform in a frequency-dependent manner. We call this distribution the *spike phase*

distribution and denote it $P_j(\phi; f)$ of the j^{th} neuron for driving frequency f. In the example

depicted in Fig. 1B, for low and high driving frequencies (top and bottom panels), the GPe

spikes distributed broadly across phases – the spike phase distribution itself was sinusoidal –

and peaked at phase 0.25, which corresponds to the peak of the sinusoidal waveform.

However, when the driving frequency was close to the intrinsic firing rate of the neuron, the

spike phase distribution became narrower and peaked at a later phase that varied among

neurons (approximately 0.4 in Fig. 1B, middle). The degree of phase locking is captured by

the vector strength (VS, Fig. 1D, see Materials and Methods), which increases as the

distribution in Figure 1B is more sharply peaked (and unimodal). The VS increased as the

driving frequency approached the intrinsic firing rate of the neuron, indicating that the neuron

was more strongly entrained when driven by a frequency similar to its own intrinsic rate. As

the driving frequency approached the intrinsic rate of the GPe neurons, the cyclic averaged

phase angle of firing (VA, Fig. 1E) shifted away from stimulus phase 0.25 (the peak of the

sinusoidal driving current) towards larger phase shifts. What determines the stimulus phase at

which the GPe neurons became maximally entrained, and why does this phase vary among

neurons?

Figure 1. GPe neurons driven periodically exhibit phase locking. A) Voltage trace of one example cell
driven by a periodic current input at three different frequencies. Spike times were mapped to stimulus
phase, and the distributions of spike phases are shown in B. C) Mean firing rate of the neuron during the
100 periods of stimulation. Red arrows indicate the stimulation frequencies shown in A and B. Dashed
lines indicate a 1:1 ratio of firing rate to driving frequency (left) and a 1:2 ratio (right). D) Vector strength
and E) vector angle as a function of stimulus frequency for the example cell.

Fourier modes of the iPRC dictate the phase at which phase locking occurs

We hypothesized that the diversity of stimulus phases at which different GPe neurons

entrain is related to the heterogeneity of the their iPRCs. To see why, we first digress with a

simplified iPRC. Consider a triangular iPRC (of unity height) that is driven by a sinusoidal

input whose frequency matches the neuron's intrinsic firing rate. The iPRC is parameterized

by a single parameter θ, which is the location (between 0 and 1) at which the triangle peaks

(Fig. 2A). As described in the Materials and Methods section, the iPRC can be decomposed

into (a constant term plus) an infinite series of cosine functions each with: 1) a frequency that

is an integer ($n = 1,2,3$...) multiple (or harmonic) of the fundamental frequency; 2) an

amplitude; and c) and angle, between 0 and 1 (eq. 1 in Materials and Methods). Figure 2B

depicts the first four cosine functions, or *modes*, of the triangular iPRC. Their amplitude is

indicated with a black vertical line and their angle is the distance of that line from 1

(indicated by a red line) *divided* by the period of that mode (indicated by a magenta line). The

amplitudes of the modes decrease like $1/n^2$ (see Materials and Methods) and their angles

increase linearly (Fig. 2C). Figure 2A includes a sequence of curves, each representing a

partial sum of the first N terms (with $N = 0, 1, 2, 3, 4$). As the number of modes used in the

partial sum is increased the approximation of the iPRC improves.

In order to calculate the phase of the sinusoidal input at which the neuron will lock to

its sinusoidal input, we will consider two different triangular iPRCs, a skewed one ($\theta = 0.9$)

and a symmetrical one ($\theta = 0.5$) (Fig. 2D). We need to first calculate the return map that

represents the phase of the next spike on the input, ϕ_{next}, as a function of the previous spike's

phase, ϕ_{prev} (Fig. 2E). This is achieved by integrating the phase equation of the neuron

driven by sinusoidal input (eq. 2 in Materials and Methods) for all values of ϕ_{prev} between 0

and 1, and plotting the resultant ϕ_{next} (e.g. [43]). The phase locking occurs at the phase at

which the return map crosses the identity line (diagonal in Fig. 2E) with a slope below 1 (that

guarantees that this fixed point on the return map is stable). Note that the stimulus phase of

locking depends on the shape of the iPRC. For the rightward skewed iPRC (red) the phase

locking occurs slightly above 0.25 and for the symmetrical iPRC (blue) it occurs at

approximately 0.5 (Fig. 2E).

Figure 2. Fourier modes of the iPRC dictate the phase of spikes on the sine wave input at locking. A)

Triangular iPRCs with θ value of (i.e., location of peak at) 0.9 (solid black) and sequences of curves

representing a partial sum of the first *N* terms or modes of the Fourier decomposition (with *N = 0, 1, 2, 3, 4*,

gray lines). B) First four modes of the iPRC shown in A, black vertical line show the mode amplitude and their

angle is the represented by the fraction of the horizontal red line in proportion to the period of that mode,

indicated by a magenta line. C) Amplitudes (black exes) and angles (red diamonds) of the first 10 modes of the

iPRC shown in A. E) Triangular iPRCs with θ values of 0.5 (blue) and 0.9 (red), dashed lines shows the

first Fourier mode component of each iPRCs. F) Predicted return map indicating the phases of sequential

spikes when each of the iPRCs shown in A is driven by a sinusoidal stimulus at the neuron's natural

frequency; diamonds and dashed lines show the stable locking phase (ψ) for each iPRC. F) Phase at

locking (ψ) closely matches the Fourier first mode of the iPRC (Δ_1) as predicted by the theoretical

approximation. G) Relationship between the sinusoidal input (black solid line), the iPRC (solid colored

line), its first Fourier mode (dashed colored line), and the orthogonal function to the stimulus (cosine,

dashed black line). The iPRC and its first Fourier mode are aligned with the stimulus phase at two

sequential spike times (ψ & $1 + \psi$, vertical lines). It is apparent that the Fourier mode of the iPRC nearly

merges with the cosine function orthogonal to the sine wave stimulus. All curves are normalized for easy

comparison. H) Two examples of iPRCs estimated from GPe neurons; filled symbols and error bars show

the iPRC estimated by the multilinear regression method, solid lines show the parameterized fit to each

iPRC and dashed lines shows the first Fourier mode component of the iPRCs. I) Solid lines show return

maps predicted by the phase model. Colored dots show ϕ_{next} vs. ϕ_{prev} in the experimental data. Locking

phases indicated by horizontal dashed lines are calculated as the vector angle. J) Correspondence between

the phase of the first mode of the iPRC and the phase of locking, calculated as the vector angle for the

spikes at the locking frequency for all 16 cells in the sample (r = 0.887, P < 10^{-5}).

To gain an intuitive understanding of what determines the phase locking, we sought an

approximate solution of the phase equation (eq. 2 in Materials and Methods) under the

assumption that the phase φ that appears as the argument of the iPRC [$Z(\varphi)$] can be replaced

with the solution of the unperturbed phase equation (namely that $\varphi(t) = \frac{t}{T}$). Although this is

never strictly true because it assumes the stimulus does not alter cell phase, it is a useful

approximation when the stimulus amplitude is small and the driving is at precisely the

intrinsic frequency of the neuron (so the period is not expected to change). In this

approximation, the phase locking occurs at the phase ψ that equals the phase Δ_1 of the

fundamental mode of the iPRC when it is written as $\cos(2\pi[\varphi + \Delta_1])$. For the triangular

iPRC, we found (see Materials and Methods) that $\Delta_1 = \frac{3}{4} - \frac{\theta}{2}$. Indeed, if we plot the phase ψ

at which phase-locking occurs based on the numerical solution of the full phase equation,

against Δ_1, we find that the points lie very close to the identity line (Fig. 2F). Fig. 2G clarifies

why this is. When driving the neuron with a sinusoid described by $\sin\left(2\pi\left[\frac{t}{T} + \phi\right]\right)$,

integration of its product with the term $\cos(2\pi[\varphi(t) + \Delta_1]) = \cos\left(2\pi\left[\frac{t}{T} + \Delta_1\right]\right)$ (in the

approximated solution of eq. 2) equals zero if $\phi = \Delta_1$ (because sine and cosine functions of

the same frequency are orthogonal if their phase shifts equal each other). Geometrically, this

means that if we plot the iPRC so that it spans from one phase-locked spike to the next

(vertical dashed lines in Fig. 2G) along the sine wave input (solid black sinusoid in Fig. 2G),

then the fundamental Fourier mode of the iPRC (dashed sinusoids in Fig. 2G) will very

nearly merge with the cosine wave (dotted black sinusoid in Fig. 2G) that corresponds (i.e.,

that is shifted to the left by 0.25 relative) to that sine wave. In the approximate solution,

where $\psi = \Delta_1$, the fundamental mode of the iPRC merges precisely with the cosine wave.

The discrepancy between the approximate and full solutions of the phase equation depends

on the shape of the PRC (compare red and blue dots in Fig. 2F, see below) and on the

amplitude of the oscillatory driving (which determines to what extent the dotted solutions

bulge away from the unity line in Fig. 2F).

Note that in this simplified model the more skewed red empirical iPRC leads to phase

locking at a smaller phase shift than the more symmetrical blue empirical iPRC. Thus, the

fundamental Fourier mode of the iPRC generates an "equivalence class" among neurons, in

the sense that neurons whose iPRCs' fundamental modes shares the same angle will all lock

at the same phase when driven at a frequency equal to their intrinsic firing rate. Conversely,

any difference between neurons in the fine structure of their iPRCs that does not affect the

fundamental mode will not impact this entrainment and phase locking. Another corollary of

this finding is that if the neuron is driven at the n^{th} harmonic of its intrinsic rate, then the

phase locking will occur at the phase of the n^{th} Fourier mode of the iPRC (see Materials and

Methods). In line with a previous study of ours [44], these findings underscore the

importance of the iPRCs' Fourier modes in understanding how pacemaker neurons respond to

periodic inputs (see Discussion).

These results were based on a highly idealized iPRC, and on the $Z(\varphi) = Z\left(\frac{t}{T}\right)$

approximation, which is valid only for vanishingly small stimuli (see Materials and

Methods). To determine whether the results apply more broadly, we tested the results using

the empirical iPRCs of all 16 of our recorded neurons (Fig 2H), and numerically integrated

the phase model of each neuron to generate return maps (Fig. 2I). These reproduced the

correspondence between the phase Δ_1 of the first mode of the iPRC and the stimulus phase ψ

of locking, calculated as the vector angle for the neurons' spikes at the locking frequency

(Fig. 2J, Pearson correlation $r = 0.887$, $P < 10^{-5}$). Note the similarity between the phase of

the fundamental modes of the empirical iPRCs (dotted lines in Fig. 2H) and that of the

triangular iPRCs (dotted lines in Fig. 2D), which demonstrates the notion of the "equivalence

class" of the skewed iPRCs and of the symmetrical ones, and clarifies that it is the

fundamental mode that mostly influences the shape of the return maps and their stable fixed

points.

Figure 3. Return maps determine the shape of the spike phase distributions across frequencies. A)
Examples illustrating the alignment between a neuron's return maps and its spike phases at three different
frequencies of sinusoidal driving input (8, 52 and 80 Hz). The blue line shows the return map generated by
the phase model using the neuron's iPRC, while red dots depict recorded pairs of consecutive spike phases
on the sinusoidal input. B) The spike phase histograms (red) correspond to the density of red points in A.
The black line in B shows the predicted density from the return maps for the same three frequencies. C)
Pearson correlations between the predicted (black steps) and empirical phase distributions (red bars) were
calculated across all GPe neurons and plotted as a function of the driving frequency.

Return maps determine the shape of the spike phase distributions across frequencies

The formalism of using the return maps (which are calculated from the phase equation and using the GPe neurons' empirical iPRC) to predict the spike phase distributions $P_j(\phi; f)$ is not restricted to the case of phase locking. In Fig. 3A, we depict (in red) the scatter plot of all the empirical pairs $\left(\phi_{prev}, \phi_{next}\right)$ representing consecutive phases of the sinusoidal input at which the GPe neuron spiked. In Fig. 3B, we depict the spike phase histograms (red), which correspond to the density of points on the scatter plot for each frequency. The deterministic return maps predicted from the empirical iPRC for the same three frequencies (Fig. 3A, blue) correspond closely to the red scatter plots. Moreover, if we assume a certain degree of additive noise to the deterministic return maps (see Materials and Methods for how the noise level was determined) than we find that the resulting spike phase distributions (black lines in Fig. 3B) match the empirical histograms (red bars in Fig. 3B). To estimate the goodness-of-fit, we calculated the average across all GPe neurons of the Pearson correlations between the predicted and empirical phase distribution (Fig. B, blue steps vs. red bars, respectively) as a function of the driving frequency (Fig. 3C) and found a high degree of correlation of approximately 0.75 across all frequencies.

Pairwise CIFs during sinusoidal driving are predicted from the phase distributions across all frequencies

We have seen that the iPRCs and phase maps can give rise to diverse spike phase distributions, and the modes of these distributions can occur at various phase delays in a frequency-dependent fashion. Can the heterogeneity of iPRC shape among neurons give rise to the diversity of their pairwise CIFs? Intuitively this seems correct. Consider two GPe neurons whose spike phase distributions (at a specific frequency) possess modes (e.g., where they peak) at different phases. The maximal value of their pairwise CIF should be located at the phase difference between these respective modes. In the Materials and Methods, we present the general derivation that shows that the structure of the pairwise CIF of two neurons is equal to the cross-correlation function of their respective spike phase distributions. In Figs. 4A-C, we depict several examples of empirical pairwise CIFs (green curve) with the CIF that is predicted from the two empirical spike phase distributions (purple curve) that are shown to the left (blue and orange distributions). The correspondence is impressive, with even some of the fine structure of the CIF being explained by cross-correlating the phase distributions. To estimate the goodness-of-fit between the predicted and empirical CIFs, we calculated the

average across all (*16×15/2 =*) 120 GPe neuron pairs of the Pearson correlations between the

predicted and empirical CIFs (purple vs. green, respectively) as a function of the driving

frequency (Fig. 4D) and found a high degree of correlation of approximately 0.6 across all

frequencies. Moreover, because the Pearson correlations are independent of amplitude, we

also determined that the amplitudes of the empirical CIFs were highly correlated the

amplitude of predicted CIFs (Fig. 4E).

Figure 4. Pairwise CIFs during sinusoidal driving are predicted from the spike phase distributions across
all frequencies. A-C) Left: Examples of spike phase distributions for two neurons (blue and orange), with
cell pairs and stimulus frequencies shown in the plots. Right: Corresponding empirical pairwise CIFs
(green curve) and CIFs predicted from the same neurons' spike phase distributions (purple curve). A)
Stimulation at low frequencies (8-11 HZ), B) Stimulation at frequencies near neurons' firing rates (38-55
HZ), C) Stimulation at high frequencies (79-86 HZ). D) Goodness-of-fit evaluated by Pearson correlations
between predicted and empirical CIFs across all GPe neuronal pairs in the sample as a function of driving
frequency. E E) Predicted CIFs reliably predict the amplitude of empirical CIFs.

What is striking about the various pairwise CIFs (Figs 4A-C) is that they exhibit diverse

delays between the neurons, that depend on their iPRCs, firing rates and stimulus frequencies.

This occurs even though each neuron was recorded separately on different brain slices in

different mice, and neurons are therefore entirely independent of each other.

288   In summary, our analysis demonstrates that the iPRCs beget the return maps, which

289 beget the phase distributions, which beget the pairwise CIFs. In other words, the

290 heterogeneity in iPRCs is sufficient to explain the diversity of pairwise CIFs. Of particular

291 relevance to previous interpretations of GPe neuron cross-correlations, our analysis shows

292 that neurons driven by common input are not generally expected to produce CIFs with zero

293 phase delay.

294   The two main features of CIFs of pairs of neurons subjected to common drive are

295 their amplitude and their phase delay (or just "phase"). The amplitude indicates the strength

296 of association between the neurons. In order to characterize how the amplitude of the CIFs

297 calculated for the pairs of independent, sinusoidally-driven GPe neurons depends on the

298 driving frequency, we plotted the maximal amplitude of the pairwise CIFs as a function of

299 two parameters: the driving frequency and the geometric mean of the intrinsic firing rates of

300 the two neurons (Fig. 5A). The first salient feature of this rendition is the large amplitudes at

301 high driving frequencies particularly for the pairs with the lower intrinsic firing rates. The

302 reason for this is that when the driving frequency is high, all spiking for all neurons tends to

303 occur at the peaks of the stimulus that is closest to the end of the intrinsic period of the

304 neurons (e.g., Fig. 1A, bottom). On the one hand, this input does not entrain the much slower

305 neuron. Nevertheless, the rapid upswing closest to the end of the intrinsic period will recruit

306 the next spike, and so the spiking for both cells occurs tightly around the phase of the peak

307 (i.e., 0.25) of the stimulus cycle (Fig. 4C). The peak of the CIF will be high because it is the

308 cross-correlation function of two unimodal, narrow distributions located around phase 0.25 of

309 the input. The second salient property of the surface plot in Fig. 5A is the ridge of large

310 amplitudes that runs diagonally along the curve where the driving frequency equals the

311 geometric mean firing rate. This is intuitively clear, because it represents the case where one

312 or both of the GPe neurons are being driven near their intrinsic firing rate. This too will give

313 rise to narrow, unimodal phase distributions, which in turn will contribute to a prominent

314 peak in the CIF.

315   To characterize how the diversity of phase delays between neurons depends on the

316 driving frequency, we plotted the probability distribution functions (PDFs) of the CIFs' phase

317 delays across all pairs of GPe neurons as a function of the driving frequency (Fig. 5B). This

318 plot reveals that the broadest distribution of phase differences occurs for frequencies near the

319 intrinsic firing rates of the GPe neurons (approximately 30 spikes/s) and at roughly double

320 that frequency, which are the frequencies at which the strongest phase locking occurs. Note

321 that in Fig. 5B there is a truncated large and narrow peak located at very low driving

322 frequencies and at zero phase delay. At these very low driving frequencies the spiking of both

323 neurons is rate modulated (*e.g.,* Fig. 1A, top), which means that the CIF is a cross-

324 correlations of the *rates* of two GPe driven by an identical sinusoidal input, so naturally both

325 rates will peak at the same phase and the cross-correlation function will always peak at zero.

328 Figure 5: Experimental CIFs show frequency-dependent amplitude and broad distributions of phase delays.
329 A) Amplitude of CIF as a function of two parameters: the driving frequency and the geometric mean of the
330 intrinsic firing rates of the two neurons. B) Probability distribution function (PDF) of the CIFs' phase
331 delays across all pairs of GPe neurons as a function of the driving frequency, asterisk denotes occurrence
332 of antiphase CIFs in the beta range. These data show that pairs of GPe neurons had a broad distribution of
333 phase delays, particularly in response to driving frequencies in the beta range.

335   This analysis also demonstrates that beta-frequency periodic driving of completely

336 independent GPe neurons is expected to generate CIFs with a broad distribution of non-zero

337 phase delays.

Intranuclear connectivity decorrelates entrained GPe neurons without changing phase

delays

We found that unconnected GPe neurons, driven by the same stimulus frequency,

exhibit broad distributions of phase delays in their CIFs, and the amplitudes of these CIFs

depend on the cells' firing rates and the stimulus frequency. To investigate the impact of local

connectivity within the GPe on the CIFs of neurons receiving common sinusoidal inputs, we

employed a network of simulated phase model GPe neurons.

As a preliminary step, we examined whether unconnected phase model neurons could

replicate the behavior observed in uncoupled neurons in our experiments. Similar to the

experimental data, unconnected phase model neurons were subjected to sinusoidal inputs

ranging from 1 to 100 Hz. The stimuli were presented to a set of 1000 GPe model neurons

with iPRCs and firing rates comparable to those in the experimental sample. We applied the

same CIF analysis used for the experimental data to the resulting spike trains (see Fig. 6).

The amplitude of the pairwise CIFs in unconnected phase model neurons was

reminiscent of the profile observed in the experimental data (compare Fig. 5A and Fig. 6A),

including the ridge of large amplitudes running diagonally on the stimulation frequency

versus pairwise geometric mean plane. The mean and standard deviation of CIF amplitudes

for every stimulation frequency in the set of unconnected phase model neurons were similar

to those observed in the experimental data (see Fig. 6C). Furthermore, the CIF phase delay

angles across the stimulus frequencies for unconnected phase model neurons closely matched

the distributions observed in the experimental data (compare Fig. 5B and Fig. 6B).

Figure 6: Unconnected *in silico* phase model neurons produce CIF amplitude and phase delay distributions that closely resemble the experimental data. A) Amplitude of CIF as a function of two parameters: the driving frequency and the geometric mean of the intrinsic firing rates of the two neurons. B) Probability distribution function (PDF) of the CIFs' phase delays across all pairs of GPe neurons in the unconnected network as a function of the driving frequency. Mean ± SD of CIF amplitude (C) and angle (D) as a function of stimulation frequency for experimental data (red) and unconnected model neurons (blue).

Next, we utilized the network model to study the impact of neuronal connectivity on CIFs. When connected, GPe neurons constantly receive a barrage of synaptic inputs from other GPe neurons. This barrage of inhibitory synaptic inputs decreases the regularity of inter-spike intervals and thereby alters the response to external inputs [45]. To quantify the specific contribution of local connectivity, we compared the CIFs from the connected network with those from an equivalent ensemble of unconnected phase model neurons, and a separate ensemble of unconnected neurons receiving a steady inhibitory barrage that approximated the average inhibition of the connected network but without its correlated temporal structure. To facilitate a direct comparison of CIFs, a constant depolarizing current was applied in both scenarios to offset the inhibition-induced reduction in firing rate. The same set of phase model neurons was used in all three configurations.

Figure 7: Impact of local neuronal connectivity on CIFs in GPe neurons. CIF amplitude as a function of stimulation frequency and the geometric mean rate of the neuron pair in the connected network (A) and for the unconnected network with the inhibitory barrage (B). C) Probability density functions of CIF amplitudes at selected stimulation frequencies (8 Hz, 35 Hz, and 80 Hz). Black, red, and green lines represent unconnected neurons, unconnected neurons with barrage, and connected neurons, respectively. D) Probability density functions of CIF angles at same stimulation frequencies as in C. E1 & E2) Example CIFs from two pairs of neurons at different stimulation frequencies for each model configuration.

The principal effect of local connectivity on neurons' CIFs is a dramatic decrease in

CIF amplitude across all frequencies of stimulation studied, as shown in Fig. 7A. This

reduction can be partly attributed to the irregularity induced by the synaptic barrage (Fig.

7B). To clarify this, we plotted the distribution of CIF amplitudes for all pairs in the sample

[$N{\times}(N\text{-}1)/2$ pairs, $N = 1000$] at three stimulation frequencies (8, 35, and 80 Hz, Fig. 7C).

Here, connected neurons (green) display a distribution skewed toward lower CIF amplitudes

at all frequencies compared to unconnected neurons (black), while the unconnected neurons

with barrage (red) show a similar skew, but only at the high frequency of 80 Hz. The

influence of synaptic coupling on CIF phase delays is subtler (Fig. 7D); connected neurons

and those receiving the barrage (green and red, respectively) exhibit distributions that are

slightly skewed toward in-phase angles compared to unconnected neurons (black). It is worth

mentioning the bimodal distribution of CIF phase delays at 35 Hz in neurons receiving the

inhibitory barrage (red line 7D, middle panel). The origin of this distribution is explained by

the neurons firing rates. The peak near zero delay is populated by neurons pairs whose rates

are both above or below the stimulation frequency. The peak near 0.3 is populated by neurons

pairs whose rates are one above and one below the stimulation frequency. The bimodal

distribution is also present in connected and unconnected neurons (green and black lines) but

with a greater overlap. The effect of CIF amplitude and subtler effect on CIF phase are also

evident in the examples shown in Figs. 7E1 and E2, where we present CIFs of two neuron

pairs at different stimulation frequencies. It is evident that the connected neurons (green)

exhibit a reduced CIF amplitude at all frequencies, compared to the unconnected neurons

(black), and this is true for the unconnected barrage configuration (red) only at the high

stimulation frequency of 80 Hz. The CIF phase delay angle remained relatively stable across

configurations but tended to gravitate toward antiphase angles as the stimulation frequency

was increased.

These results were not dependent on the specific structure of the iPRCs in the GPe

network, because repeating the same simulations with an identical iPRC for each neuron

resulted in CIFs with similar amplitudes and phases (not shown). Thus, the attenuation of CIF

amplitudes by local GPe connectivity is robust to changes in the intrinsic properties of the

GPe neurons that alter their iPRCs. These findings suggest that local synaptic connections in

the GPe decorrelates GPe neurons when they are driven by common input, by reducing CIF

amplitudes without notably altering their phase delays.

Discussion

Phase models of GPe neurons fully predict their entrainment to oscillatory drive

We combined experiments and modeling to investigate the phase delays among GPe

neurons subjected to a common oscillatory drive. We first addressed the question of how

oscillatory drive determines the nature of the entrainment of an individual GPe neuron. For

this, we recorded mouse GPe neurons in the perforated patch configuration while driving

them with oscillatory current injections in the frequency range of 1-100 Hz. As described in

previously [43, 46], we found that as the driving frequency approaches the neuron's intrinsic

frequency the neuron tracks the driving frequency. This tracking is accompanied by an

increase in the VS, which reflects a sharpening of the spike phase distributions. The present

study adds to these previous studies by revealing that the shape of the neuron's iPRC

determines the particular stimulus phase around which the spike phase distribution centers. In

particular, by measuring the iPRC of each of the GPe neurons that were subjected to the

oscillatory driving, we were able to show that the phase at which a neuron phase locks to its

input, when driven at or around its intrinsic firing rate, is determined primarily by the angle

of the fundamental Fourier mode of the iPRC. More generally, we found that by integrating

the neuron's phase equation (which takes the neuron's intrinsic firing rate and its iPRC into

account) to produce a return map, then with appropriate additive noise, we were able to

reconstruct the spike phase distribution at all frequencies, even in the absence of entrainment.

The phase model of GPe neurons explains their temporal correlations in the presence of common oscillatory drive

After showing how the spike phase distribution can be derived from the individual

neurons' iPRC and phase equation, we showed that the structure of the CIF estimated for a

pair of independent GPe neurons driven by a common oscillatory drive can be derived from

the cross-correlation function of their corresponding spike phase distributions. Importantly,

our analyses show that the phase delays of these CIFs can distribute broadly, particularly

when the neurons are driven at frequencies approaching their intrinsic firing rates. To see

why this is, note that the cross-correlation function of two distributions of random variables is

essentially the distribution of the difference between these random variables. Therefore, the

mode of the distribution of the CIF phase delays of a given pair of neurons, will be located at

the difference between the modes of their respective spike phase distributions. We saw that as

the driving frequency approached the intrinsic firing rate of a GPe neuron there was an

increase in the stimulus phase at which the neuron phase locked (VS angle in Fig. 1E).

Consequently, when one of two GPe neurons becomes entrained the differences between the

modes of their spike phase distributions will become larger.

Local connections between GPe neurons decorrelate them

The conclusion from these experiments is that connectivity among GPe neurons is not

necessary to account for the broad distribution of phase differences among these cells seen in

their CIFs, for example, in parkinsonian primates [10, 11]. We therefore asked, how would

connectivity among GPe neurons affect the structure of their pairwise CIFs. To this end, we

used an *in silico* approach, and found that when modeling the known connectivity between

GPe neurons, the amplitudes of the pairwise CIFs were reduced. This finding agrees with

previous studies of ours that have shown the local connectivity among GPe neurons serves to

reduce the strength of their pairwise correlations, or "decorrelate" them [6, 47]. It is not clear

whether GPe collaterals are the primary influence that decorrelates GPe neurons, or whether

their lack of pairwise correlation *in vivo* [10, 11] is caused by the absence of overlap in joint

input that neighboring GPe neurons receive [6]. Regardless, our simulation study suggests

that even when (model) GPe neurons receive common oscillatory input, their local

connectivity serves to decorrelate them. Importantly, this *in silico* result was robust to a

battery of variations we applied to the iPRCs used in the simulation, indicating that

decorrelation is a general outcome of the presence of local GPe connectivity.

An additional conclusion from this study is that in contrast to the amplitudes of the

CIFs, which are attenuated by the collaterals, the phase delays among GPe neurons are

essentially unaffected by the local connectivity. Thus, we can summarize that, while the

amplitudes of the GPe CIFs are controlled by their local connectivity, the phase differences

result from the intrinsic properties of the individual GPe neurons, which shape their

respective iPRCs.

Consistent phase relationships among neurons do not imply a direct interaction between

them

There is a large body of work on phase relationships among GPe neurons (and other

basal ganglia neurons) during oscillatory brain activity, whether they arise pathologically, as

in various models of parkinsonism where beta oscillations dominate [10, 11, 15, 22, 23] or

under more physiological conditions such as sleep [48, 49] and anesthesia [30, 50, 51]. In

these studies, while acknowledging that correlation does not imply causation, finding

consistent phase relationships among various neurons or neuronal populations was often

interpreted as an indication of some direct or indirect interaction or influence between these

neurons or populations [39]. For example, if two populations are anti-phase, then one inhibits

the other [15, 30, 50, 52, 53, 54]. Our findings provide a clear counterexample to this line of

reasoning. In our data there is no interaction between the various GPe neurons recorded

(because they are recorded separately on different brain slices from various animals), yet

when subjecting them to the same oscillatory drive they give rise to a rich slew of CIFs with

various amplitudes and phase delays spanning all the way from in-phase to anti-phase (in a

frequency dependent manner). Thus, it is important to consider that when a particular

postsynaptic neuron exhibits a consistent phase with respect to some global oscillatory input,

this phase may be best explained by the intrinsic properties of the neuron, as captured by its

iPRC, which dictate the phase at which it entrains.

The spectral decomposition of the iPRC

Our study underscores the spectral decomposition of the iPRC to its Fourier modes as

an important property that elucidates how the iPRC interacts with oscillatory input. While the

full solution of the phase model is needed in order to produce a return map, which in turn

determines the precise phase at which locking occurs, we found mathematically that this

phase is very nearly the angle of the fundamental Fourier mode of the iPRC. This means that

two iPRCs that share the same fundamental mode will phase lock at roughly the same phase

of the oscillatory drive. The higher harmonics of the iPRCs are irrelevant, because when they

integrate with the input they contribute a vanishing change in phase, because they are

orthogonal to the waveform of the input.

iPRCs are typically thought of (and defined as) a way to characterize the responsivity

of a neuron to a brief perturbation occurring at specific phase of the neuron's firing cycle.

Until recently it was also usually measured that way empirically [55]. However, iPRCs also

dictate how the phase of the oscillator will be impacted by extended perturbations that span

the entire cycle (or more) by integrating the product of the input and the iPRC. In this case,

because the oscillator and the iPRC are both periodic, the natural way to analyze the system

is through its Fourier spectral decomposition [44]. In our case, this analysis demonstrates that

it is these modes that determine the properties of the entrainment.

Relevance to beta oscillations in parkinsonian primates

Our study may shed light on the structure of the CIFs observed among GP neurons in

parkinsonian primates [10, 11]. It suggests that the oscillatory CIFs exhibited in these animals

are the result of a global beta oscillation that entrains GPe neurons. It also suggests that the

appearance of oscillatory CIFs does not imply a change in the connectivity among GPe

neurons. Moreover, the broad distribution of phase delays observed in the CIFs of GPe

neurons in parkinsonian primates may reflect the intrinsic properties of these neurons with

little bearing on the coupling between them. It should be mentioned that in our experiments

the frequency ranges in which the CIFs exhibited the broadest distribution of phase delays

(calculated for completely independent neurons) were close to the intrinsic firing rates of the

GPe neurons, which were in the 10-40 spikes/s range. In primate GPe, the firing rates may be

considerably higher than the beta frequency in which the pairwise CIFs of GPe neurons from

parkinsonian primates exhibit a broad distribution of phase delay angles. One way to

determine whether our explanation for the broad distribution of CIF delays applies to the

broad distribution of phase delays observed in parkinsonian primates would be to estimate the

global oscillatory signal present in those animals, for example, through recording of the local

field potentials (LFPs) and constructing the spike phase distribution with respect to the

phases of the oscillatory LFP. One could then test whether the convolution of these

distributions gives rise to the empirical CIFs, which is reminiscent of a previous study

showing the GPe CIFs in parkinsonian primates can be predicted from the LFP [23].

Materials and Methods

Institutional approval

All experiments were conducted in accordance with the National Institutes of Health

guidelines and were approved by the Institutional Animal Care and Use Committee of The

University of Texas at San Antonio.

Animals

The animal subjects used in this research have been detailed previously [42]. The

study involved 14 mice aged between 74 to 193 days. Out of these, 10 were PV-Cre, 2 were

Npas1-Cre-tdTomato mice, and 2 were wildtype C57BL/6 mice without any genetic

modifications. In total, 16 GPe neurons were examined, all classified as prototypic cells using

the electrophysiological criterion of Jones et al. (2023) [56]. Eleven of these were confirmed

as parvalbumin-positive (PV+) either through fluorescence or via a distinct light-induced

Archaerhodopsin-3 (Arch) hyperpolarization. The remaining neurons were identified in slice

preparations that lacked any PV reporter.

Acute brain slices

Mice were deeply anesthetized with isoflurane and killed by decapitation. Parasagittal

brain slices of 300 μm that included the GPe were obtained using a vibrating microtome

(Leica) in an ice-cold cutting solution. This solution consisted of the following (in mM): 110

choline chloride, 2.5 KCl, 1.25 NaH_2PO_4, 0.5 $CaCl_2$, 7 $MgSO_4$, 25 glucose, 11.6 Na

ascorbate, 3.1 Na pyruvate, and 26 $NaHCO_3$, and was saturated with 95% O_2 and 5% CO_2.

The slices were then transferred to ACSF, which contained (in mM): 126 NaCl, 2.5 KCl, 1.25

NaH_2PO_4, 2 $CaCl_2$, 1 $MgSO_4$, and 10 glucose, also bubbled with 95% O_2 and 5% CO_2. The

ACSF used for storing the slices, but not for recording, additionally included (in mM): 0.005

glutathione, 1 Na ascorbate, and 1 Na pyruvate. The slices were subsequently heated to 34°C

for 30 minutes and then permitted to cool to room temperature before being used.

Perforated patch recordings

The slices were continuously superfused with ACSF oxygenated and heated to

between 33°C and 35°C. Neurons were imaged using an Olympus BX51WI microscope

equipped with a 40X water-immersion lens and Dodt gradient contrast optics. Recordings of

neurons were made using the perforated patch-clamp method. Recording pipettes made from

filamented borosilicate glass (G150F-4; Warner Instruments) were pulled to have resistances

of 3-7 MΩ using a Flaming-Brown pipette puller (model P-97; Sutter Instruments). The

pipette tip was initially filled with a solution containing (in mM): 140 $KMeSO_4$, 10 HEPES,

7.5 NaCl, and then back-filled with the same solution plus 1 μM Gramicidin-D (MP

Biomedicals). After achieving a gigaohm seal, a period of 10-30 minutes was allowed for the

gramicidin to perforate the cell membrane, ensuring adequate electrical access (40-70 MΩ).

Recordings were obtained using a MultiClamp 700B amplifier (Molecular Devices),

connected to an ITC-18 A/D converter (HEKA Instruments), and managed on a Macintosh

computer with custom software written for Igor Pro (WaveMetrics).

Oscillatory driving and vector strength

Neurons were driven by sinusoidal currents with frequencies ranging from 1 to 100

Hz in 1 Hz steps. Each frequency was presented for 10 s. Spike times t_j were converted to

phases using $\phi_j = ft_j \mod 1$ where f is the driving frequency. To assess spike entrainment

to the stimulus at each frequency, we calculated the vector strength (VS) as:

$$VS = \frac{1}{N}\sqrt{\left(\sum_j \sin(2\pi\phi_j)\right)^2 + \left(\sum_j \cos(2\pi\phi_j)\right)^2}$$

where N is the number of spikes. Additionally, the vector angle (VA) was computed as:

$$VA = \frac{1}{2\pi}\arctan\frac{\sum_j \sin(2\pi\phi_j)}{\sum_j \cos(2\pi\phi_j)}$$

The VA provides an estimate of the average phase on the input oscillation at which

the neuron fired, while the VS indicates the reliability of firing at that angle. A vector

strength of zero signifies firing at random with respect to the oscillation, while a value of one

denotes firing consistently at the same exact phase on the oscillation on every cycle.

iPRC measurements

The infinitesimal PRC was estimated as described previously [57]. The intrinsic

oscillation of the neuron was perturbed by a barrage of contiguous brief pulses of injected

current (0.25 ms) with amplitudes drawn from a Gaussian distribution (mean = 0, standard

deviation (SD) = 40 pA). A total of 40 episodes, each lasting 4 s, were applied to each

neuron. Each inter-spike interval (ISI) was divided into 50 equal-length bins, and the charge

applied in each bin was calculated. The resulting matrix of applied charges was subjected to

multiple regression analysis to estimate the iPRC values at each bin.

$$\frac{ISI_\alpha}{\langle ISI \rangle} = 1 + Q_{\alpha,1}Z(\varphi_1) + Q_{\alpha,2}Z(\varphi_2) + \cdots + Q_{\alpha,n}Z(\varphi_n) + \epsilon_\alpha$$

The resulting iPRCs were parameterized as in Olivares et al. (2022) [47] using an *ad*

hoc function with 7 free parameters that has proven capable of capturing the shape and size of

the GPe iPRC. The parameterized iPRC was used to simulate the phase equation (see below)

and obtain the iPRC Fourier components.

Representation of the iPRC as a Fourier series

The autonomous pacemaking of a GPe neuron is described as an oscillator whose

intrinsic phase is $\varphi \in [0,1)$ and whose intrinsic frequency is f. Consequently, the neuron's

iPRC is also a periodic function of phase. According to Fourier theory any periodic function

can be represented as an infinite series of cosine functions with integer frequencies plus a

constant term. Additionally, the cosine function of frequency n, which is also called the n^{th}

Fourier *mode*, is shifted by a specific angle, which we denote Δ_n. Thus, we have [44, 58].

602
$$Z(\varphi) = \tilde{Z}_0 + \sum_{n=1}^{\infty} \tilde{Z}_n \cos(2\pi[n\varphi + \Delta_n]) \quad \text{(eq. 1)}$$

The formulas for the prefactors $\tilde{Z}_n$ are: $\tilde{Z}_0 = \int_0^1 Z(\phi)d\phi$ (the temporal average of the

iPRC) and $\tilde{Z}_n = \sqrt{Z_n^{C^2} + Z_n^{S^2}}$, where $Z_n^C = 2\int_0^1 Z(\phi)\cos(2\pi n\phi)d\phi$ and

$Z_n^S = 2\int_0^1 Z(\phi)\sin(2\pi n\phi)d\phi$. $Z_n{}^C$ and $Z_n{}^S$ are called the n^{th} cosine and sine Fourier

transforms of $Z(\varphi)$, and are essentially the correlation between the iPRC and n^{th} cosine and

sine functions, respectively. The angles are given by the formula $\Delta_n = -\frac{1}{2\pi}\arctan\frac{Z_n^S}{Z_n^C}$. On a

practical level, summing a finite number of modes in the above series (e.g., beginning with

modes 0,1,2, and so on) up to some N^{th} mode results in an ever-improving approximation of

the iPRC as N is increased.

Relationship between the phase of the iPRC modes and the stimulus phase of locking

612   In order to gain insight into the phase at which a GPe neurons will phase lock to an

613   oscillatory drive, it is informative to consider how the phase oscillator representing the GPe

614   neuron is affected by sinusoidal driving at the same intrinsic frequency f of the oscillator (or

615   integer n multiples of f). In this case, the dynamics of the phase oscillator are governed by the

616   following phase equation

617
$$\frac{d\varphi}{dt} = f + A\sin(2\pi n[ft + \phi])Z(\varphi) \qquad \text{(eq. 2)}$$

Because the oscillator is being driven at its intrinsic frequency, it stands to reason that the

oscillator will continue to oscillate at its intrinsic frequency when driven, so we use the

approximation that phase advances linearly, i.e., $\varphi(t) = \frac{t}{T}$, where $T (= 1/f)$ is the period of

the oscillator. In this approximation, we can now integrate the phase equation (eq. 2) between

0 and *T*. In the case of phase locking at the intrinsic frequency the sinusoidal driving should

add no net phase change when averaged over the neuron's period, so that the neuron will

spike at the same phase of the input on every period of driving. In other words, we are

looking for a stimulus phase ψ such that

626
$$\varphi(T) = fT + A \int_0^T \sin(2\pi n[fs + \psi])Z\left(\frac{s}{T}\right) ds = 1$$

627 Because $fT = 1$ we have

628
$$\int_0^T \sin(2\pi n[fs + \psi])Z\left(\frac{s}{T}\right) ds = 0$$

629 While this equation can be solved directly, it is instructive to expand the left-hand-

630 side of this equation using Fourier representation of the iPRC (eq. 1).

631
$\int_0^T \sin(2\pi[nfs + \psi])\{\tilde{Z}_0 + \sum_{m=1}^{\infty} \tilde{Z}_m \cos(2\pi[mfs + \Delta_m])\}ds = 0$ (eq. 3)

632 The first term in eq. 3 vanishes because the integral of a sinusoidal function over one

633 period is zero (multiplication by the constant $\tilde{Z}_0$ does not change that). The rest of the infinite

634 number of terms in eq. 3 all have the following structure

635
$$\int_0^T \sin(2\pi[nfs + \psi]) \cos(2\pi[mfs + \Delta_m]) ds$$

Using trigonometric identities (plus, again, the useful result that the integral of a

sinusoidal function over one period vanishes) demonstrates that for all iPRC modes for which

$m \neq n$ the integral vanishes. Only when $m = n$, does the integral equal $\sin(2\pi[\psi - \Delta_n])$ (up

to a scale factor). This underscores the finding that when you drive an oscillator at an integer

multiple (n), or harmonic, of its fundamental frequency you are only affecting (or interacting

with) the corresponding n^{th} mode of its iPRC [44]. All other modes are unaffected, and are

said to be *orthogonal* to the input. Additionally, all Fourier modes are orthogonal to each

other because

$\int_0^1 \cos(2\pi[n\phi + \Delta_n]) \cos(2\pi[m\phi + \Delta_m]) d\phi = \begin{cases} 0 & m \neq n \\ 0.5 & m = n \end{cases}$

Thus, eq. 3 reduces to $\sin(2\pi[\psi - \Delta_n]) = 0$, or in other words, $\psi = \Delta_n$. The

meaning of this result is that the sine wave perturbation needs to be shifted exactly by the

angle of the n^{th} mode of the iPRC when driven by n times the fundamental frequency in order

to create zero phase perturbation and therefore stable locking (the other solution

$\psi = 0.5 + \Delta_n$ is unstable). In other words, even when the phase oscillator is driven at

precisely one of its harmonic frequencies, there are specific phases at which the input would

still be orthogonal to the corresponding mode and not drive any phase change.

Parameterization of a triangular iPRC

653   It is instructive to consider the triangular iPRC (of unity height) that is parameterized

654   by the location θ of its peak (also because it is a good first approximation for some empirical

655   iPRCs [46]. The sine and cosine Fourier modes of the triangular iPRC are given by $\tilde{Z}_0^C = \frac{1}{2}$

656   and for all $n > 0$ by

$$Z_n^C = \frac{\cos(2\pi n\theta) - 1}{2\pi^2\theta(1-\theta)n^2}$$

$$Z_n^S = \frac{\sin(2\pi n\theta)}{2\pi^2\theta(1-\theta)n^2}$$

658   In this model, a straightforward calculation shows that the angle of the iPRC's

659   fundamental frequency (and hence the phase at which an oscillator with the same frequency

660   will stably lock) is $\Delta_1 = \frac{3}{4} - \frac{\theta}{2}$.

Numerical integration of the phase equation and additive noise

Neurons' return maps (RMap) were obtained by numerically integrating the phase

model equation (eq. 1) using Euler's method with a constant time step of 0.05 ms. For each

stimulus frequency f, we performed 400 independent simulations starting at equidistant

stimulus phases (relative to a preceding spike) in the range [0, 1]. For each starting phase

ϕ_{prev}, a deterministic simulation was initialized with the neuron phase $\varphi = 0$. The stimulus

was run until the neuron spiked ($\varphi = 1$), and the stimulus phase at the moment of the spike

was recorded as ϕ_{next}. The return map is fully determined by the neuron's iPRC, intrinsic rate,

and the stimulus frequency and amplitude.

We used the calculated return map to obtain a sample of neurons' spike phases. The

sample was obtained by iterations in the return map, discarding the first 100 iterations. In

every iteration, additive noise was introduced to account for the neurons' intrinsic spike

variability. The iteration rule was defined as:

$$\phi_{next} = RMap(\phi_{prev}) + \xi(f) \quad \mod 1$$

Where $\xi(f)$ is additive Gaussian noise that depends on the stimulus frequency f with

zero mean and SD of $\beta\sqrt{f}$. β was tuned to match the spread of spike phases when the neuron

is driven by a stimulus frequency closer to the neuron's intrinsic spike rate (i.e., when locking

occurs). We adjusted the standard deviation in proportion to the square root of the stimulation

frequency. This adjustment was necessary because as the frequency increases, the stimuli

period becomes shorter, making the return map predictions less precise.

GPe neural network model

The GPe neural network was simulated as described in Olivares et al. (2022) [47].

One thousand model neurons were connected using a small-world architecture; each neuron

was connected in a ring-like organization to its ten closest neighbors, and then 1% of the

synapses were randomly rewired. The degree of connectivity is consistent with experimental

data [56, 59, 60, 61]. Neurons in the network were heterogeneous with respect to their iPRCs

and intrinsic firing rates; both neuron properties were drawn from distributions that

qualitatively represent experimental data from GPe neurons. The unitary inhibitory synaptic

conductance for the local synaptic connections was modeled with an instantaneous rise and

an exponential decay with a time constant of 2.4 ms. The peak amplitude of each local

synaptic conductance varied independently from spike to spike to represent quantal synaptic

fluctuations and was drawn from a normal distribution with a mean of 2.5 nS and a SD of

1.75 nS. The reversal potential was set at -73 mV. These values were chosen to match those

of spontaneous unitary synaptic conductances observed in voltage clamp recordings from

GPe neurons [61].

When unconnected, the network was simulated with all synapses removed, and the

neurons were driven solely by the sinusoidal input (20 pA amplitude) and an additive noise

tuned to each cell using the theoretical approximation in [62] to generate an inter-spike

interval coefficient of variation of 0.08. When connected, we compensated for the decrease in

rate due to the local inhibitory inputs using an excitatory direct current tuned to each neuron

individually. To discriminate the effect of connectivity from the effect of the barrage of

inhibitory synaptic inputs produced by the local network in the absence of external drive, we

simulate a disconnected network in which every neuron received a barrage of synaptic inputs

with a mean rate equal to the one received in the connected configuration, but without the

temporal structure produced by synaptic interactions and sinusoidal drive.

Network simulations were conducted using a C++ package originally designed for

continuous-time recurrent neural networks [63], accessible at https://rdbeer.pages.iu.edu. We

made modifications to the package, introducing the phase model and incorporating our

synaptic events. The model was numerically integrated using Euler's method, employing a

fixed time step of 0.1 ms. Common external stimuli were applied, covering frequencies from

1 to 100 Hz, and each frequency was simulated for a duration of 100 seconds.

Deriving the cross-intensity function (CIF) from the spike phase distribution of neurons

driven by a common sinusoidal input

Assume we have two spike trains that are driven by common sinusoidal input of

frequency f

716
$$s_1(t) = \sum_{j=1}^{N} \delta(t - t_j^1)$$

717 and

718
$$s_2(t) = \sum_{k=1}^{M} \delta(t - t_k^2)$$

719 where t_j^1 and t_k^2 are the spike times of the two neurons, respectively.

720 The cross-intensity function (CIF), which is the spike cross-correlation function [39, 64], is

721 given by

722
$$R_{12}(\tau) = \frac{1}{\Delta} \int_0^\Delta s_1(t) s_2(t + \tau) dt = \frac{1}{\Delta} \int_0^\Delta \sum_{j=1}^{N} \sum_{k=1}^{M} \delta(t - t_j^1) \delta(t + \tau - t_k^2) \, dt$$

723
$$= \frac{1}{\Delta} \sum_{j=1}^{N} \sum_{k=1}^{M} \delta(\tau - [t_k^2 - t_j^1])$$

If we restrict ourselves to $\tau < T = \frac{1}{f}$, then the only pairs of spikes t_j^1, t_k^2 that contribute to the

sum are those that appear in the same period of the sinusoidal input. But in this case, we can

define probability distributions $P_1(\phi; f)$ and $P_2(\phi; f)$ of the phase at which the spikes t_j^1, t_k^2

occur, which we will refer to as the *spike phase distributions*, and use the ergodic theorem to

replace the time average ($1/\Delta$) by averages on these distributions of the Dirac delta function.

This yields

731
$$R_{12}(\tau; f) = T \int_0^1 d\varphi P_1(\varphi; f) \int_0^1 d\psi P_2(\psi; f) \delta\left(\tau - \frac{[\psi - \varphi]}{f}\right)$$

732
$$= fT \int_0^1 d\varphi P_1(\varphi; f) P_2(f\tau + \varphi; f)$$

where the pre-factor T is because we averaged over time Δ for the spikes of the first neuron

and averaged a neighborhood of T for the spikes of the second (so we need to multiply back

by T). Then according to the algebra of the Dirac delta function we need to multiply times f.

But because $fT = 1$ we get

$$R_{12}(\tau; f) = \int_0^1 d\varphi P_1(\varphi; f) P_2(\varphi + f\tau; f)$$

This means that the CIF of spikes between *0* and *T* is equal to the cross-correlation function

of the probability distribution functions.

Statistics

We used Pearson correlation (*r*) to measure the linear association between variables, and

Wald's test to determine the statistical significance of the association. Calculations were done

using SciPy.Stats Python library. The null hypothesis of no linear association was rejected if

the P value was smaller than 0.05.

Data availability

All data and code used in this work will be made available on a public repository upon

publication.

Acknowledgments

This work was supported by National Institute of Neurological Disorders and Stroke Grant

R35NS097185 to C.J.W. The authors would like to thank Rostislav Likhotvorik for his

excellent technical support, and Drs. Lior Tiroshi, Matthew Higgs and Hitoshi Kita for

helpful advice and comments on the manuscript. J.A.G. was on sabbatical at UTSA during

the performance of this work.

Conflict of Interest Statement

The authors declare no competing financial interests.

References

1. Oorschot DE. c. Journal of Comparative Neurology.1996;366(4):580–599.

2. Zheng T, Wilson C. Corticostriatal combinatorics: the implications of corticostriatal axonal

arborizations. Journal of neurophysiology.2002;87(2):1007–1017.

3. Bar-Gad I, Morris G, Bergman H. Information processing, dimensionality reduction and

reinforcement learning in the basal ganglia. Progress in neurobiology. 2003;71(6):439–473.

4. Goldberg JA, Bergman H. Computational physiology of the neural networks of the primate

globus pallidus: function and dysfunction. Neuroscience.2011;198:171–192.

5. Jaeger D, Kita H. Functional connectivity and integrative properties of globus pallidus

neurons. Neuroscience. 2011;198:44–53.

6. Wilson CJ. Active decorrelation in the basal ganglia. Neuroscience.2013;250:467–482.

7. Yelnik J, Percheron G, François C. A Golgi analysis of the primate globus pallidus. II.

Quantitative morphology and spatial orientation of dendritic arborizations. Journal of

Comparative Neurology. 1984;227(2):200–213.

8. Shink E, Smith Y. Differential synaptic innervation of neurons in the internal and external

segments of the globus pallidus by the GABA-and glutamate-containing terminals in the

squirrel monkey. Journal of Comparative Neurology. 1995;358(1):119–141.

9. Kita H, Nambu A, Kaneda K, Tachibana Y, Takada M. Role of ionotropic glutamatergic

and GABAergic inputs on the firing activity of neurons in the external pallidum in awake

monkeys. Journal of neurophysiology.2004;92(5):3069–3084.

10. Nini A, Feingold A, Slovin H, Bergman H. Neurons in the globus pallidus do not show

correlated activity in the normal monkey, but phase-locked oscillations appear in the MPTP

model of parkinsonism. Journal of neurophysiology.1995;74(4):1800–1805.

11. Raz A, Vaadia E, Bergman H. Firing patterns and correlations of spontaneous discharge

of pallidal neurons in the normal and the tremulous1-methyl-4-phenyl-1, 2, 3, 6-

tetrahydropyridine vervet model of parkinsonism. Journal of Neuroscience.

2000;20(22):8559–8571.

12. Bar-Gad I, Heimer G, Ritov Y, Bergman H. Functional correlations between neighboring

neurons in the primate globus pallidus are weak or nonexistent. Journal of Neuroscience.

2003;23(10):4012–4016.

13. Goldberg JA, Boraud T, Maraton S, Haber SN, Vaadia E, Bergman H. Enhanced

synchrony among primary motor cortex neurons in the 1-methyl-4-phenyl-1, 2, 3,6-

tetrahydropyridine primate model of Parkinson's disease. Journal of Neuroscience.

2002;22(11):4639–4653.

14. Heimer G, Bar-Gad I, Goldberg JA, Bergman H. Dopamine replacement therapy reverses

abnormal synchronization of pallidal neurons in the 1-methyl-4-phenyl-1,2, 3, 6-

tetrahydropyridine primate model of parkinsonism. Journal of Neuroscience.

2002;22(18):7850–7855.

15. Mallet N, Pogosyan A, Márton LF, Bolam JP, Brown P, Magill PJ. Parkinsonian beta

oscillations in the external globus pallidus and their relationship with subthalamic nucleus

activity. Journal of neuroscience. 2008;28(52):14245–14258.

16. Alexander GE, DeLong MR, Strick PL. Parallel organization of functionally segregated

circuits linking basal ganglia and cortex. Annual review of neuroscience. 1986;9(1):357–381.

17. Foster NN, Barry J, Korobkova L, Garcia L, Gao L, Becerra M, et al. The mouse cortico–

basal ganglia–thalamic network. Nature. 2021;598(7879):188–194.

18. Mink JW. The basal ganglia: focused selection and inhibition of competing motor

programs. Progress in neurobiology. 1996;50(4):381–425.

19. Boraud T, Brown P, Goldberg JA, Graybiel AM, Magill PJ. Oscillations in the basal

ganglia: the good, the bad, and the unexpected. In: The basal ganglia VIII. Springer; 2005. p.

1–24.

20. Heimer G, Rivlin-Etzion M, Bar-Gad I, Goldberg JA, Haber SN, Bergman H. Dopamine

replacement therapy does not restore the full spectrum of normal pallidal activity in the 1-

methyl-4-phenyl-1, 2, 3, 6-tetra-hydropyridine primate model of Parkinsonism. Journal of

Neuroscience. 2006;26(31):8101–8114.

21. Plotkin JL, Goldberg JA. Thinking outside the box (and arrow): current themes in striatal

dysfunction in movement disorders. The Neuroscientist.2019;25(4):359–379.

22. Raz A, Feingold A, Zelanskaya V, Vaadia E, Bergman H. Neuronal synchronization of

tonically active neurons in the striatum of normal and parkinsonian primates. Journal of

neurophysiology. 1996;76(3):2083–2088.

23. Goldberg JA, Rokni U, Boraud T, Vaadia E, Bergman H. Spike synchronization in the

cortex-basal ganglia networks of parkinsonian primates reflects global dynamics of the local

field potentials. Journal of Neuroscience.2004;24(26):6003–6010.

24. Brown P. Bad oscillations in Parkinson's disease. Journal of neural transmission

Supplementum. 2006;70:27.

25. Hammond C, Bergman H, Brown P. Pathological synchronization in Parkinson's disease:

networks, models and treatments. Trends in neurosciences.2007;30(7):357–364.

26. Cagnan H, Mallet N, Moll CK, Gulberti A, Holt AB, Westphal M, et al. Temporal

evolution of beta bursts in the parkinsonian cortical and basal ganglia network. Proceedings

of the National Academy of Sciences.2019;116(32):16095–16104.

27. Crompe Bdl, Aristieta A, Leblois A, Elsherbiny S, Boraud T, Mallet NP. The globus

pallidus orchestrates abnormal network dynamics in a model of Parkinsonism. Nature

communications. 2020;11(1):1570.

28. Chan CS, Shigemoto R, Mercer JN, Surmeier DJ. HCN2 and HCN1 channels govern the

regularity of autonomous pacemaking and synaptic resetting in globus pallidus neurons.

Journal of Neuroscience. 2004;24(44):9921–9932.

29. Chan CS, Surmeier DJ, Yung WH. Striatal information signaling and integration in

globus pallidus: timing matters. Neurosignals. 2006;14(6):281–289.

30. Magill PJ, Pogosyan A, Sharott A, Csicsvari J, Bolam JP, Brown P. Changes in

functional connectivity within the rat striatopallidal axis during global brain activation in

vivo. Journal of Neuroscience. 2006;26(23):6318–6329.

31. Ingham C, Hood S, Mijnster M, Baldock R, Arbuthnott G. Plasticity of striatopallidal

terminals following unilateral lesion of the dopaminergic nigrostriatal pathway: a

morphological study. Experimental brain research.1997;116:39–49.

32. Baufreton J. Arkypallidal neuron: a new player in the basal ganglia circuitry. Movement

Disorders: Official Journal of the Movement Disorder Society.2012;27(14):1740–1740.

33. Miguelez C, Morin S, Martinez A, Goillandeau M, Bezard E, Bioulac B, et al. Altered

pallido-pallidal synaptic transmission leads to aberrant firing of globus pallidus neurons in a

rat model of Parkinson's disease. The Journal of physiology.2012;590(22):5861–5875.

34. Fan KY, Baufreton J, Surmeier DJ, Chan CS, Bevan MD. Proliferation of external globus

pallidus-subthalamic nucleus synapses following degeneration of midbrain dopamine

neurons. Journal of Neuroscience. 2012;32(40):13718–13728.

35. Cui Q, Pitt JE, Pamukcu A, Poulin JF, Mabrouk OS, Fiske MP, et al. Blunted mGluR

activation disinhibits striatopallidal transmission in parkinsonian mice. Cell reports.

2016;17(9):2431–2444.

36. Glajch KE, Kelver DA, Hegeman DJ, Cui Q, Xenias HS, Augustine EC, et al. Npas1+

pallidal neurons target striatal projection neurons. Journal of Neuroscience.

2016;36(20):5472–5488.

37. Chu HY, McIver EL, Kovaleski RF, Atherton JF, Bevan MD. Loss of hyperdirect

pathway cortico-subthalamic inputs following degeneration of midbrain dopamine neurons.

Neuron. 2017;95(6):1306–1318.

38. Ji YW, Zhang X, Fan JP, Gu WX, Shen ZL, Wu HC, et al. Differential remodeling of

subthalamic projections to basal ganglia output nuclei and locomotor deficits in 6-OHDA

induced hemiparkinsonian mice. Cell Reports.2023;42(3).

39. Perkel DH, Gerstein GL, Moore GP. Neuronal spike trains and stochastic point processes:

II. Simultaneous spike trains. Biophysical journal. 1967;7(4):419–440.

40. Raz A, Frechter-Mazar V, Feingold A, Abeles M, Vaadia E, Bergman H. Activity of

pallidal and striatal tonically active neurons is correlated in MPTP-treated monkeys but not in

normal monkeys. The Journal of Neuroscience.2001;21(3):RC128.

41. Deister CA, Dodla R, Barraza D, Kita H, Wilson CJ. Firing rate and pattern heterogeneity

in the globus pallidus arise from a single neuronal population. Journal of neurophysiology.

2013;109(2):497–506.

42. Wilson CJ, Jones JA. Propagation of Oscillations in the Indirect Pathway of the Basal

Ganglia. Journal of Neuroscience. 2023;43(35):6112–6125.

43. Wilson CJ. Predicting the response of striatal spiny neurons to sinusoidal input. Journal of

neurophysiology. 2017;118(2):855–873.

44. Goldberg JA, Atherton JF, Surmeier DJ. Spectral reconstruction of phase response curves

reveals the synchronization properties of mouse globus pallidus neurons. Journal of

neurophysiology. 2013;110(10):2497–2506.

45. Simmons DV, Higgs MH, Lebby S, Wilson CJ. Indirect pathway control of firing rate and

pattern in the substantia nigra pars reticulata. Journal of neurophysiology. 2020;123(2):800–

814.

46. Tiroshi L, Goldberg JA. Population dynamics and entrainment of basal ganglia

pacemakers are shaped by their dendritic arbors. PLOS Computational Biology.

2019;15(2):e1006782.

47. Olivares E, Higgs MH, Wilson CJ. Local inhibition in a model of the indirect pathway

globus pallidus network slows and deregularizes background firing, but sharpens and

synchronizes responses to striatal input. Journal of computational neuroscience.

2022;50(2):251–272.

48. Salih F, Sharott A, Khatami R, Trottenberg T, Schneider G, Kupsch A, et al. Functional

connectivity between motor cortex and globus pallidus in human non-REM sleep. The

Journal of physiology. 2009;587(5):1071–1086.

49. Mizrahi-Kliger AD, Kaplan A, Israel Z, Bergman H. Desynchronization of slow

oscillations in the basal ganglia during natural sleep. Proceedings of the National Academy of

Sciences. 2018;115(18):E4274–E4283.

50. Magill PJ, Sharott A, Bolam JP, Brown P. Brain state–dependency of coherent oscillatory

activity in the cerebral cortex and basal ganglia of the rat. Journal of neurophysiology.

2004;92(4):2122–2136.

51. Slovik M, Rosin B, Moshel S, Mitelman R, Schechtman E, Eitan R, et al. Ketamine

induced converged synchronous gamma oscillations in the cortico-basal ganglia network of

nonhuman primates. Journal of neurophysiology. 2017;118(2):917–931.

52. Goldberg JA, Kats SS, Jaeger D. Globus pallidus discharge is coincident with striatal

activity during global slow wave activity in the rat. Journal of Neuroscience.

2003;23(31):10058–10063.

53. Mallet N, Micklem BR, Henny P, Brown MT, Williams C, Bolam JP, et al. Dichotomous

organization of the external globus pallidus. Neuron. 2012;74(6):1075–1086.

54. Abdi A, Mallet N, Mohamed FY, Sharott A, Dodson PD, Nakamura KC, et al. Prototypic

and arkypallidal neurons in the dopamine-intact external globus pallidus. Journal of

Neuroscience. 2015;35(17):6667–6688.

55. Reyes AD, Fetz EE. Two modes of interspike interval shortening by brief transient

depolarizations in cat neocortical neurons. Journal of neurophysiology. 1993;69(5):1661–

1672.

56. Jones JA, Higgs MH, Olivares E, Pe˜na J, Wilson CJ. Spontaneous activity of the local
GABAergic synaptic network causes irregular neuronal firing in the external globus pallidus.
Journal of Neuroscience. 2023;43(8):1281–1297.

57. Wilson CJ, Barraza D, Troyer T, Farries MA. Predicting the responses of repetitively
firing neurons to current noise. PLoS computational biology. 2014;10(5):e1003612.

58. Morales JC, Higgs MH, Song SC, Wilson CJ. Broadband entrainment of striatal low-
threshold spike interneurons. Frontiers in Neural Circuits. 2020;14:36.

59. Sadek AR, Magill PJ, Bolam JP. A single-cell analysis of intrinsic connectivity in the rat
globus pallidus. Journal of Neuroscience. 2007;27(24):6352–6362.

60. Bugaysen J, Bar-Gad I, Korngreen A. Continuous modulation of action potential firing by
a unitary GABAergic connection in the globus pallidus in vitro. Journal of Neuroscience.
2013;33(31):12805–12809.

61. Higgs MH, Jones JA, Chan CS, Wilson CJ. Periodic unitary synaptic currents in the
mouse globus pallidus during spontaneous firing in slices. Journal of neurophysiology.
2021;125(4):1482–1500.

62. Ermentrout GB, Beverlin B, Troyer T, Netoff TI. The variance of phase-resetting curves.
Journal of computational neuroscience. 2011;31:185–197.

63. Beer RD. On the dynamics of small continuous-time recurrent neural networks. Adaptive
Behavior. 1995;3(4):469–509.

64. Cox DR, Lewis PAW. The statistical analysis of series of events. Methuen's monographs
on applied probability and statistics. London: Methuen; 1966.