FREQuency-resolved brain Network Estimation via Source Separation (FREQ-NESS)

Rosso, M.[1,2]*, Fernández-Rubio, G.[1], Keller, P.[1], Brattico, E.[1,3], Vuust, P.[1], Kringelbach, M. L.[1,4,5], Bonetti, L.[1,4,5]*

[1] *Center for Music in the Brain, Department of Clinical Medicine, Aarhus University & The Royal Academy of Music, Aarhus/Aalborg, Aarhus, Denmark*

[2] *IPEM Institute for Systematic Musicology, Ghent University, Ghent, Belgium*

[3] *Department of Education, Psychology, Communication, University of Bari Aldo Moro, Italy*

[4] *Centre for Eudaimonia and Human Flourishing, Linacre College, University of Oxford, Oxford, United Kingdom*

[5] *Department of Psychiatry, University of Oxford, Oxford, United Kingdom*

*Corresponding authors: Mattia.Rosso@UGent.be and leonardo.bonetti@psych.ox.ac.uk

Abstract

The brain is a dynamic system whose network organisation is often studied by focusing on specific frequency bands or anatomical regions, leading to fragmented insights, or by employing complex and elaborate methods that hinder straightforward interpretations. To address this issue, we introduce a novel method called *FREQuency-resolved Network Estimation via Source Separation* (FREQ-NESS). This method is designed to estimate the activation and spatial configuration of simultaneous brain networks across frequencies by analysing the frequency-resolved multivariate covariance between whole-brain voxel time series. We applied FREQ-NESS to source-reconstructed magnetoencephalography (MEG) data during resting state and isochronous auditory stimulation. Results revealed simultaneous, frequency-specific brain networks in resting state, such as the default mode, alpha-band, and motor-beta networks. During auditory stimulation, FREQ-NESS detected: (1) emergence of networks attuned to the stimulation frequency, (2) spatial reorganisation of existing networks, such as alpha-band networks shifting from occipital to sensorimotor areas, (3) stability of networks unaffected by auditory stimuli. Furthermore, auditory stimulation significantly enhanced cross-frequency coupling, with the phase of attuned auditory networks modulating the gamma band amplitude of medial temporal lobe networks. In conclusion, FREQ-NESS effectively maps the brain's spatiotemporal dynamics, providing a comprehensive view of brain function by revealing simultaneous, frequency-resolved networks and their interaction.

Keywords

Brain networks, Generalised Eigendecomposition (GED), Cross-frequency coupling (CFC), Magnetoencephalography (MEG), Resting state, Auditory processing

Introduction

The ultimate goal of cognitive neuroscience is to understand how the human brain functions as an interface with the external world [1]. This endeavour involves characterising the brain's intrinsic dynamics [2–4] and their interaction with continuous streams of information sampled from the environment [5–8]. In this pursuit, the field faces the major challenge of solving a source separation problem: whether the brain is at rest, stimulated, or actively interacting with its surroundings, distinct cognitive processes simultaneously unfold, producing mixed neurophysiological signals that are not readily disentangled [9,10]. Thus, developing a robust and interpretable method to isolate distinct yet simultaneous brain networks from high-dimensional neural data is key to advancing the field of cognitive neuroscience.

Decades of research have provided effective multivariate solutions for separating brain processes that overlap in time, frequency, and space, allowing for independent examination. Yet, most studies to date still pre-define regions of interest, canonical frequency bands, or time-windows, often based on stimulus characteristics, a priori hypotheses, or previous research (see [10,11]). While this approach can yield informative results into individual features of the data and in explaining how the brain reacts to simple, controlled stimuli, it involves many assumptions and commonly overlooked the complex, multivariate nature of brain data [10,12]. Thus, it offers a limited comprehensive understanding of the brain because they do not consider these features together.

To address this challenge, recent advancements in both data acquisition (e.g., state-of-the-art magnetoencephalography (MEG) and magnetic resonance imaging (MRI) systems) and computational algorithms have pushed the field forward, providing new insights into collecting, handling, and interpreting multivariate neural data. For example, decoding via multivariate pattern analysis [13,14] has enabled the classification of experimental conditions by leveraging the multivariate interactions between multiple brain sources and processes. Although this method provides opportunities to understand the contribution of each source in an integrative manner, by definition it cannot disentangle different brain processes. Furthermore, it performs best with broadband or low-frequency data but is less effective for studying different frequency bands, which are crucial for characterising brain functioning both at rest and during tasks [15–20].

To this goal, notable insights came from other multivariate methods such as generalised eigendecomposition (GED), which stands out for its flexibility in defining assumptions and

criteria for source and frequency separation [21]. Among other applications [10,22,23], GED can

decompose multivariate signals into components exhibiting activity at a defined frequency

that characterises the process of interest [23–28]. This feature makes it an ideal framework to

investigate the brain in resting state and its processing of naturalistic stimuli such as music

and speech as they continuously unfold over time. This occurs because the temporal structure

of these stimuli triggers neural activation at matching frequencies [29–31], and the associated

domain-specific brain networks are characterised by unique spectral fingerprints [15].

While previous applications of GED have demonstrated its reliability in separating sources

related to distinct cognitive processes within specific frequency bands, its contributions to

understanding the spatial extent of these processes and the interactions among the underlying

brain networks operating at different frequencies have been limited. This limitation primarily

arose because GED was predominantly applied to EEG sensor data matrices (e.g., [27,28,32–35]),

which provide limited spatial information about the distinct contributions of different brain

regions to the various cognitive processes captured by the multivariate neurophysiological

data.

To address the challenge of tracing the data back to their neuroanatomical sources, MEG

stands at the forefront of non-invasive methods for the excellent trade-off between temporal

and spatial resolution, since its use in combination with MRI scans [36,37] enables the

reconstruction of the specific brain sources which generated the MEG signal [38–40]. Yet, due to

the high-dimensional nature of brain voxel activation matrices produced by source

reconstruction, studies have traditionally used a priori parcellations based on anatomical

atlases [41] to define brain regions of interest (e.g., [37,42–45]). Narrowing the focus on parcellated

regions comes with the same biases as selecting clusters of sensors a priori, which has been

shown suboptimal by previous research (see, e.g., [28]).

In this study, we introduce a novel framework called *Network Estimation via Source*

Separation (NESS), specifically focusing on its *FREQuency-resolved* variant, FREQ-NESS.

This analytical approach synthesises insights from previous scientific literature into a

comprehensive framework, yielding physiologically meaningful and accessible interpretation

of brain processes. We demonstrated that applying GED directly to MEG reconstructed brain

voxel data for a large sample of narrow frequency bands enabled us to derive the spectral,

spatial, and temporal organisation of simultaneous, frequency-resolved brain networks.

Initially, we applied this methodology during resting state to concurrently capture classical

brain networks commonly associated with it (e.g., default-mode network, alpha-band

network, beta-band network, gamma-band network [42,48]). Subsequently, we recorded
participants' brain activity during continuous periodic auditory stimulation at a frequency of
2.4 Hz to investigate how their brain networks were reshaped by such low-effort task. At a
conceptual level, this characterisation of brain networks mirrors how experimental physicists
test the resonance properties of physical systems such as vibrating structures, first assessing
the intrinsic properties of the system and then its changes in response to basic external
perturbations [1].

Remarkably, since FREQ-NESS operates in narrow frequency bands and produces a time
series for each of the frequency-resolved brain networks, we were also able to model the
between-network dynamics in a framework based on cross-frequency coupling (CFC) [2,21].
Among a set of CFC metrics (see [3,49]), phase-to-amplitude coupling provides a parsimonious
measure with substantial explanatory power, provided that each estimated network is
dominated by one frequency [50]. This approach allowed us not only to distinguish intrinsic
frequency-resolved brain networks and their rearrangement in response to auditory stimuli,
but also to explore the dynamics of multivariate networks beyond traditional pairwise
functional connectivity between single brain regions.

In short, FREQ-NESS aims to provide a comprehensive framework for estimating the
activation and configuration of concurrent, frequency-resolved brain networks using non-
invasive multivariate neurophysiology. The approach was optimised for analysing source-
reconstructed MEG recordings in continuous time, particularly focusing on simultaneous
processes operating within one or more defined frequencies, whether endogenously generated
or driven by temporally structured auditory stimulation. Our overarching objective is to
extend the application of widely adopted multivariate methods beyond spatial filtering and
dimensionality reduction, to derive physiologically meaningful and accessible interpretations
of how the brain attunes its network in frequency and space with the external world.

Results

Experimental design

Twenty-nine (n = 29) participants underwent five minutes of MEG recording in conditions of resting state (RS) and passive listening (PL) to an isochronous auditory tone sequence stimulus presented at a rate of 2.4 Hz (**Figure 1a** and **b**). Two participants did not undergo the PL recording, and one participant was discarded due to technical issues during the data collection, leaving us with twenty-six (n = 26) participants eligible for within-subject comparisons in both conditions.

FREQ-NESS was used to characterise the temporal and spatial configuration of brain networks operating at specific frequencies, and to investigate their rearrangement as a result of continuous auditory stimulation. To this aim, we performed GED on the entire brain voxel data matrix as reconstructed via beamforming. We iterated the procedure for both conditions, for each participant, and for the entire frequency spectrum from 0.2 to 97.6 Hz, in intervals of 1.2 Hz (for a similar scanning procedure, see also [51]). For the sake of consistency with previous literature, we will often refer to the canonical division in frequency bands when reporting our results [11]: delta (0.2 – 4 Hz), theta (4 – 8 Hz), alpha (8 – 13 Hz), beta (13 – 30 Hz), and gamma (30 – 97.6 Hz). However, our primary focus is on specific frequencies within these ranges.

For each frequency, we computed the eigenvectors to decompose the multivariate signal in its components carrying the most narrowband activity at the specified frequencies, as contrasted with broadband activity. The same eigenvectors were used to filter the covariance matrix of narrowband activity, computing the spatial activation patterns of the respective component. Given 3559 voxels time series, 3559 components were extracted and sorted in descending order by explained variance. This resulted in a network landscape consisting of the eigenvalue distribution over the frequency spectrum and the associated spatial activation patterns. The associated network activation time series were used at a subsequent stage to perform cross-frequency coupling analysis between networks.

167

168

169 *Figure 1: FREQuency-resolved network estimation via source separation (FREQ-NESS).*

170 *The figure provides an overview of the FREQ-NESS methodology. **a -** MEG was used to collect*

171 *neurophysiological data during the experimental conditions, while structural MRI was acquired in a separate*

172 *session. **b -** Participants underwent MEG recordings during two experimental conditions: resting state (5*

173 *minutes) and passive listening to isochronous auditory tone sequence (5 minutes) at a rate of 2.4 Hz. **c** – To*

174 *compute MEG source reconstruction, we performed co-registration between MEG data and individual MRI*

175 *anatomical scans, forward model (single shell), and inverse solution using beamforming. **d** – The source*

176 *reconstruction generated one time series for each of the 3559 brain voxels from an 8-mm grid parcellation of*

177 *the brain. **e -** The covariance matrices R and S were computed from the broadband voxel data matrix (R) and*

178 *from the narrowband filtered voxel data matrix (S); the procedure was repeated for a sample of 86 frequencies,*

179 *computing a new S covariance matrix upon each iteration. **f -** Generalised eigendecomposition (GED) was*

180 *computed by solving the eigenequation $RW\Lambda = SW$ for the eigenvectors (W) to find the weighted combinations*

181 *of brain voxels to separate frequency-specific networks; the associated eigenvalues (Λ) express the amount of*

182 *variance explained by each network component. **g -** Network activation time series and spatial patterns were*

183 *computed. The spatial filters (W) were applied to the broadband voxel data matrix (X_{broad}) via matrix*

184 *multiplication to reconstruct its components (Y) as network activation time series; the same spatial filters were*

*applied to the narrowband covariance matrix S to compute the spatial activation patterns (A) as the components' projections in voxel space. **h** - The phase of the bandpass filtered time series of the 2.4 Hz components of interest (brain networks) is extracted via Hilbert transform for subsequent cross-frequency coupling (CFC) analysis. **i** - To investigate the modulation of network interactions (phase of the 2.4 Hz brain networks modulating the amplitude over all the frequency bins), the modulation of frequency-specific brain networks as a function of the low-frequency modulating network was quantified as amplitude modulation. **j** - For each network, mean power values were calculated for all the phase bins, resulting in an amplitude distribution over the 2.4 Hz network's phase. **k** – For each frequency-specific network, an index of modulation strength was computed by fitting a sinewave to the modulation curves and computing its amplitude; this enabled the identification of significant interactions across networks operating at specific frequencies (here, phase of the 2.4 Hz brain networks modulating the amplitude over all the frequency bins).*

Variance explained by the brain networks in resting state and passive listening

To assess changes in the network landscape associated with the auditory stimulation in PL against RS, we conducted a series of Wilcoxon signed-rank tests. Considering the exponential decay observed for the eigenvalues returned by GED, we focused our statistics on the top 10 eigenvalues (i.e. the eigenvalues corresponding to the 10 GED components which explained the highest variance). We contrasted PL vs RS over the entire frequency spectrum and applied False Discovery Rate (FDR) correction for multiple comparisons. In this context, every normalised eigenvalue expresses the percentage of total variance explained by the respective signal components in GED space [10]. Positive z-values emerging from the Wilcoxon test were interpreted as the emergence of frequency-resolved networks of PL against the RS baseline, whereas negative z-values were interpreted as their suppression. To increase readability of the results, we report statistical tests for only the top three eigenvalues up to 40.9 Hz in **Figure 2**, while detailed depiction of full statistical test outcomes for the full range (top 10 eigenvalues over the spectrum up to 97.6 Hz) is provided in **Figure S1**.

212
213

214 *Figure 2: Network landscape: eigenspectrum and spatial activation patterns during rest and passive listening.*

*This figure illustrates the frequency-resolved brain networks estimated via FREQ-NESS in two experimental conditions: (a) resting state and (b) passive listening. The first element of the network landscape is the **eigenspectrum**, which consists of the eigenvalues expressing the percentage of variance explained by the associated GED components, plotted over the frequencies. The solid lines indicate the mean normalised eigenvalues across participants, while the shaded areas represent the standard error of the mean (SEM). The second element displays the **spatial activation patterns** associated with the top GED components for the frequencies exhibiting the highest explained variance. Each pattern highlights the extent of each brain voxel's contribution to the respective network. To improve visualisation, the eigenspectra are shown here for the first three GED components (sorted by explained variance) over a portion of the frequency spectrum (0.2 to 40.9 Hz), while the topographies of the first two components are shown for the frequencies with the highest explained variance. For an extended version of the network landscape, see **Figure S1**. **a - Resting state (R)**: The network landscape reveals a 1/f exponential decay of explained variance in the low delta range and local maxima in the alpha (10.9 Hz) and beta (22.9 Hz) frequency ranges. The spatial activation patterns show the typical topographies expected from the brain at rest, namely the broad mesial distribution associated with the DMN for low frequencies not engaged in stimulus processing (2.4 Hz and 4.8 Hz), parieto-occipital distribution for the alpha network (10.9 Hz), and sensorimotor involvement for the beta network (22.9 Hz). Notably, while frequencies on the left side of the alpha peak exhibit parieto-occipital activation (8.4 Hz and 9.6 Hz), the higher end of the range is characterized by sensorimotor activation (12.1 Hz). In the beta range, the explained variance peaks at 22.9 Hz, and the spatial pattern shows activation limited to sensorimotor regions. **b – Passive Listening (PL)**: Significant reorganisation of brain networks occurs in response to auditory stimulation. The eigenspectrum exhibits a pronounced peak at the stimulation frequency of 2.4 Hz and its first harmonic at 4.8 Hz, reflecting the emergence of brain networks attuned to the rhythmic auditory stimulus. The spatial activation patterns at 2.4 Hz show focal engagement of the right auditory cortex, particularly in Heschl's gyrus, with additional involvement of broader medial temporal regions in the 4.8 Hz component, indicative of secondary auditory processing. Another key change observed in this condition is the shift in the alpha peak from 10.9 Hz in the resting state to 12.1 Hz during listening, accompanied by a posterior-to-anterior shift in spatial activation from parieto-occipital to sensorimotor regions. This reorganisation suggests that auditory stimulation induces a rearrangement of alpha networks, likely reflecting increased readiness for action and sensory processing in response to the rhythmic stimulus. The arrangement of beta remains stable across conditions, both in terms of eigenspectrum and spatial patterns.*

Significant changes in the first two eigenvalues were found for the following frequencies: 2.4 Hz (1st component: $p < 0.001$, FDR-corrected; 2nd component: $p < 0.001$, FDR-corrected), 4.8 Hz (1st component: $p < 0.001$, FDR-corrected; 2nd component: $p < 0.001$, FDR-corrected), and 9.6 Hz (1st component: $p < 0.001$, FDR-corrected; 2nd component: $p < 0.001$, FDR-corrected).

The prominent peaks at 2.4 Hz indicate a strong attunement of the brain to the frequency of the auditory stimulation. By 'attunement', we mean that the spectral content of a network

component becomes highly concentrated around a specific frequency as a direct result of the

stimulation. The term is conceptually and operationally different from 'entrainment' as the

latter assumes a specific phase-based mechanism leading to the match in the stimulation

frequency [52,53]. Whilst a possibility [24,54], we do not claim that entrainment is the mechanism

underlying our result. As a qualitative observation, we note that this attunement also reshaped

the 1/f exponential decay on the left end of the spectrum. Specifically, we observed a

suppression of the aperiodic components of the brain signal in the background [55], caused by

the emergence of primary and secondary frequency-resolved auditory networks. Based on the

harmonic relationship with the stimulation frequency and the associated spatial activation

pattern, we interpret the emergence of the 4.8 Hz as attunement of auditory networks

alongside the 2.4 Hz components.

The significant change at 9.6 Hz is the result of a rearrangement in the alpha region of the

landscape. Specifically, the peak of the top components shifted from 10.9 Hz in RS to 12.1

Hz in PL, biasing the symmetry of the Gaussian-shaped distributions observed for RS to the

right. The result indicates an imbalance between alpha ranges across conditions, with

auditory stimulation resulting in a suppression of the lower and an enhancement of the higher

alpha range. We interpret this finding as indicative of a re-attunement of the alpha networks

during rhythmic auditory processing.

Beta and gamma ranges did not exhibit any significant change between experimental

conditions in terms of explained variance. Detailed statistical results for all components over

the frequency spectrum are reported in **Table S1**.

After detecting statistically significant changes in the variance explained by the GED

components across experimental conditions, we computed the spatial activation patterns to

provide complementary qualitative information, as typically done in multivariate methods for

neuroimaging (see [10,12,24]). As shown in **Figure 2** and described in detail in the Methods

section, spatial activation patterns were computed for each eigenvalue associated to the GED

components (i.e. brain networks) to produce their topographical projection in brain voxel

space. Please note that in all the figures in this article, only the most meaningful activation

patterns are shown. Specifically, only the activation patterns that exceeded the mean by more

than one standard deviation were displayed on the brain template (see [37]).

The entire delta range (0.2 – 4 Hz) in RS was characterised by the spatial distribution

typical of the default-mode network (DMN) [48]. At 2.4 Hz, in absence of stimulation, both the

first and the second component matched this configuration. Conversely, in PL, the first
component involved primarily the right auditory cortex with a major focus on the Heschl's
gyrus [54], while the second component recruited a larger brain network previously connected
to secondary auditory processing [37,55] and including regions of the medial temporal lobe such
as hippocampal regions, inferior temporal cortex, insula, ventromedial prefrontal cortex, as
well as the cingulate gyrus. Taken together, these spatial changes show the unequivocal
involvement of early and late stages of auditory processing, marking a transition from DMN
to auditory networks associated to the frequency attunement. This physiological
interpretation is corroborated by the observation that, over the whole delta range, both the
frequency attunement and the spatial clustering during PL occurred prominently and
selectively for the stimulation frequency.

In the theta range (4-8 Hz), a similar pattern was observed for the first harmonic of the
stimulation frequency 4.8 Hz, showing prominent auditory networks and cingulate gyrus in
PL and DMN in RS. Given the harmonic relationship and significant overlap with
fundamental auditory networks, we interpret the attunement of the 4.8 Hz network as being
functionally related to auditory processing.

In the alpha range (8-13 Hz), the spatial activation patterns displayed a relevant
reorganisation across conditions. In RS, the maximally attuned network at 10.9 Hz showed a
spatial distribution of the first two GED components centred in the parieto-occipital regions,
while higher alpha frequencies showed a strong recruitment of sensorimotor regions. In PL,
the alpha peak shifted to 12.1 Hz, and sensorimotor regions replaced parieto-occipital regions
across the entire alpha range. Overall, the rearrangement of alpha networks consisted of a
focal cluster of neighbouring regions shifting from parieto-occipital areas at RS to
sensorimotor regions during PL. Interestingly, **Figure 2** demonstrates a posterior-to-anterior
spatial gradient in the alpha frequency range, which shifts as frequency increases. While this
gradient is present in both conditions, indicating that these are inherent brain dynamics, the
significant change in eigenvalues suggests that attunement to a preferred peak frequency is
task dependent. This spatial reorganisation is qualitatively different from the transitions away
from the DMN observed at lower frequencies, where the emergence of frequency-resolved
networks over aperiodic background activity was linked to a focal convergence from a
broader spatial distribution.

In the beta range (13 – 30 Hz), the spatial activation patterns were consistent across both RS and PL, pointing to a primarily involvement of sensorimotor regions for the first two components in both experimental conditions.

In the gamma range (30 – 97.6 Hz), similar to beta, the spatial activation patterns remained consistent across conditions. Here, gamma activity was broadly distributed, encompassing bilateral insula, inferior temporal cortex, hippocampal regions, frontal operculum and inferior frontal gyrus. The topographies of the gamma networks are shown in **Figure 3** and **Figure S1**.

Cross-frequency coupling

To investigate the dynamics of interaction across the separated networks, we analysed the cross-frequency coupling (CFC) between selected combinations of their activation time series. Specifically, we assessed whether activation in networks across all frequencies was modulated by the auditory networks attuned to the stimulation frequency. To do so, we calculated the power distribution of all frequency-resolved components over the phase time series [56–58] of the first component of the 2.4 Hz modulator. Given the responses elicited in the secondary auditory network, we repeated the procedure for the second component of the 2.4 Hz modulator. Motivated by the empirical observation that the power distributions are well approximated by a sinusoidal function, we fitted a sinewave to each distribution and used its amplitude as an index of modulation strength [25].

Figure 3: Network landscape: cross-frequency coupling during rest and passive listening.

The figure shows the interaction between each of the two low-frequency 2.4 Hz auditory networks and all the

higher-frequency networks during resting state (R) and passive listening (PL). The plots display the modulation

strength, a measure of how the phase of the low-frequency network component modulates the amplitude of the

other network components. The shaded areas represent the standard error of the mean (SEM) across

*participants. **a - Component #1 (2.4 Hz)**: The left panel shows the spatial activation patterns for component #1*

at 2.4 Hz in both resting state and listening conditions. In R, the activation is concentrated in medial temporal

regions, including the hippocampus, while during listening, it shifts towards primary auditory areas,
particularly Heschl's gyrus, indicating the auditory network's engagement with the rhythmic stimulus. The right
panel displays the PAC results, showing significant modulation of high gamma band activity (70-90 Hz) by the
2.4 Hz component during listening. This modulation is notably stronger than in the resting state, suggesting
*enhanced cross-frequency coupling driven by auditory processing. **b - Component #2 (2.4 Hz)**: The left panel*
shows the spatial activation patterns for component #2 at 2.4 Hz, which involve a broader network during both
conditions, including auditory and medial temporal regions. In the listening condition, this component also
recruits additional prefrontal regions, indicating a higher-level integration of auditory information. The right
panel shows that, similar to component #1, the modulation of gamma band activity by component #2 is
significantly stronger during listening, particularly in the 60-80 Hz range, reinforcing the finding that auditory
stimulation enhances the coupling between low-frequency auditory rhythms and high-frequency gamma
oscillations. These results highlight the dynamic reconfiguration of cross-frequency interactions in response to
auditory stimulation, with a clear enhancement of PAC between low-frequency auditory components and high-
frequency gamma networks. The enhanced modulation of gamma band activity by the low-frequency auditory
networks during listening suggests heightened cross-frequency coupling, indicative of increased interaction
across neural networks in response to external stimuli. This underscores that gamma oscillations play a key role
in processing rhythmic auditory stimuli, mediated by the interaction with auditory networks attuned to the
stimulation frequency.

As illustrated in **Figure 3**, we tested the hypothesis that PL would result in a significantly stronger modulation than RS over the networks landscape. We performed a Wilcoxon signed-rank test on the modulation strength of PL vs RS, over the entire frequency spectrum and independently for the first two 2.4 Hz GED components. The results were corrected for multiple comparisons using FDR.

The statistical tests returned the following main significant frequency windows for the first 2.4 Hz component (**Figure 3a**): 71.0 – 73.5 Hz; 77.0 – 81.9 Hz; 84.3 – 87.9 Hz ($p < 0.01$, false-discovery rate FDR-corrected; for an extensive report of the exact statistics, see **Table S2**). **Figure 3b** shows the results of the same test for the modulation by the second 2.4 Hz component, which resulted in the following main significant frequency windows: 63.8 – 81.9 Hz; 84.3 – 89.1 Hz; 92.7 – 96.3 Hz ($p < 0.02$, false-discovery rate FDR-corrected; for an extensive report of the exact statistics, see **Table S2**).

These results indicate that cross-frequency coupling was significantly stronger in PL compared to RS, selectively for the gamma band. Specifically, the phase fluctuations of oscillations at 2.4 Hz modulated the power of higher-frequency components to a larger extent during auditory stimulation, suggesting a heightened state of interaction across networks driven by the external rhythmic stimulus. This level of analysis provides further insight into

the interplay between different neural oscillations during auditory processing and how it
relates to the configuration of different networks. Importantly, it showed that the role of the
gamma network in sensory processing is mediated by the coupling with primary auditory
networks rather than by an internal frequency attunement.

Detailed statistical results for the modulation of all components over the frequency
spectrum are reported in **Table S2**.

Randomisations

In order to systematically test the principle of dissociation between the temporal and
spatial dimensions of FREQ-NESS, we performed two types of randomisations on our RS
data in voxel space, and iterated GED on the same data in the four shuffled conditions. This
was done only in RS since it was superfluous to conduct the same procedure in both
experimental conditions. The randomisation strategies were carried out as follows, operating
on a matrix of brain voxels with two dimensions (space and time): (1) *label randomisation*:
the brain voxel indexes were shuffled, in a consistent manner over the entire time series (i.e.
no changes were made to the time series but the time series were entirely reassigned to
different brain voxels); (2) *point-wise label randomisation*: the voxel indexes were shuffled
row-wise, independently for each timepoint.

By applying these randomisation techniques, we sought to disrupt the temporal and spatial
structures of the data independently. **Figure 4** show the effects of the randomisation
strategies on the network landscape in RS. Label randomisation (1) disrupted the spatial
activation patterns without altering the eigenspectrum. This preserved the frequency content
of the time series and the variance explained by the GED components but returned
physiologically meaningless activation patterns. Point-wise label randomisation (2) disrupted
both the spatial activation patterns and the eigenspectrum, indicating that reshuffling the
voxels for every time-point disrupted the temporal structure of the multivariate signal and,
therefore, the frequency content of the estimated networks. Here, the variance explained by
the first GED components decreased to an average of 0.06% across frequencies, flattening the
exponential decrease in the variance explained by progressive GED components at each
frequency and providing insights into the variance explained by GED components which
might be attributable to chance.

Figure 4: Network landscape of randomised resting state data: eigenspectrum and spatial activation patterns.

*This figure illustrates the frequency-resolved brain networks obtained using FREQ-NESS applied to the original data, randomised with two different strategies. 1)Label randomisation: The brain voxel indices were shuffled consistently across the entire time series, meaning the temporal data remained intact but was reassigned to different brain voxels; 2)Point-wise label randomisation: The voxel indices were shuffled independently for each time point, disrupting the temporal structure. As shown in **Figure 2**, first element of the network landscape is the eigenspectrum, which shows the eigenvalues representing the percentage of variance explained by the GED components across frequencies. Solid lines denote the mean normalised eigenvalues across participants, with shaded areas indicating the standard error of the mean (SEM). The second element depicts spatial activation patterns associated with the top GED components at frequencies with the highest explained variance. Each pattern illustrates the contribution of each brain voxel to the corresponding network. For enhanced visualisation, the eigenspectra are presented for the first three GED components (sorted by explained variance) across a frequency range of 0.2 to 40.9 Hz. The spatial topographies of the first two components are shown for frequencies with the highest explained variance. **a – Original data**: To allow an easier comparison, we report the same results for resting state data shown in **Figure 2**. **b – Randomisation 1 (Label)** preserved the eigenspectrum but disrupted the spatial activation patterns, maintaining the frequency content and variance explained by GED components but yielding physiologically meaningless patterns. **c – Randomisation 2 (Point-wise label)** disrupted both the eigenspectrum and spatial activation patterns, flattening the exponential decrease in variance explained by subsequent GED components. This suggests that reshuffling voxels for each time point disrupts the temporal structure of the signal and reduces the variance explained by GED components to approximately 0.06% across frequencies, highlighting potential variance contributions attributable to chance.*

Discussion

Scientific research has long established that the brain is a complex, dynamic system organised into networks [1,2,46,59–61]. However, much of the existing evidence has arisen from studies that narrowly focused on specific frequency bands or brain regions, resulting in fragmented insights. Additionally, the use of complex methods often hindered straightforward interpretations. While these approaches have yielded valuable findings, they also present challenges in integrating the brain's temporal and spatial dynamics into a cohesive framework that is based on minimal assumptions and allows for clear interpretations. To address these challenges, we developed the *FREQuency-resolved Network Estimation via Source Separation* (FREQ-NESS) method and applied it to MEG recordings during both resting state and continuous auditory rhythmic stimulation. This flexible, data-driven approach is based on three main assumptions supported by previous evidence: (1) a brain network exists when independent brain voxels covary over time [62–64], (2) during both resting state and tasks involving external rhythmic stimulation, brain networks operate at different frequency bands [3,42,43], and (3) the GED components generated by FREQ-NESS are directly interpretable as brain networks. Here, the variance explained by these components indicates the relative significance of the networks for each frequency band and experimental condition, while the associated activation patterns and time series provide insights into the spatial and temporal extent of the networks.

As expected by a successful source separation [10,24], we observed a pronounced exponential decay in the variance explained by the GED components within each frequency band and experimental condition. This pattern indicates that only the first three to five components are meaningful, as they explain a significantly larger proportion of the variance compared to the remaining components. Additionally, these components showed markedly higher variance than those obtained from applying GED to randomised data whose covariance patterns were disrupted (see **Figure 4b** and **4d**). In resting state, the variance explained by these GED components showed an exponential decay from the slow to high frequencies in the delta range, a prominent alpha peak at 10.9 Hz, and a reduced yet relevant beta peak at 22.9 Hz (see **Figure 2a**). During listening, we instead observed an outstanding peak at the stimulation frequency of 2.4 Hz and its first harmonic 4.8 Hz, along with a prominent alpha peak at 12.1 Hz, and beta peak at 22.9 Hz (see **Figure 2b**).

In this study, the 2.4 Hz frequency within the delta range was of particular interest because it matched the adopted stimulation frequency. During resting state, the variance explained by

the GED components exhibited an exponential decay with increasing frequency, with no

prominent peaks at 2.4 Hz. However, the spatial activation patterns across all delta band

components, including at 2.4 Hz, were highly comparable and displayed the characteristic

configuration of the DMN (**Figure 2**). The DMN is widely recognised as the dominant

activation mode of the brain at rest, primarily involved in self-referential and introspective

activities rather than external stimulus processing (for a review, see [65]). Notably, no

prominent eigenvalue associated with this network emerged from the spectrum, indicating

that the DMN exhibits low frequency-specificity according to our criteria for source

separation. This finding suggests that the DMN's spatial activation pattern persists across

different frequency bins within the delta band when the brain is not engaged in a specific

task, underscoring its role in basal brain activity [66].

Beyond resting state, when GED was attuned to 2.4 Hz in the listening condition, the

eigenspectrum was dominated by one eigenvalue explaining 18% and a second eigenvalue

explaining 7% of the total variance (see **Figure 2b**). This finding indicates that two

components of the brain voxel signal maximally attuned to the stimulation frequency, based

on their narrow spectral density. Inspection of their spatial projections onto voxel space

revealed focal patterns in auditory areas, providing a clear physiological explanation for the

frequency attunement of brain activity to the stimulation. To elaborate, we inferred that two

brain networks were recruited to process the rhythmic stimuli, coherent with low- and higher-

level processing of auditory stimuli previously reported in the literature [37,67–70]. The focal

activation in the Heschl's gyrus observed in the first network, with asymmetry favouring the

right hemisphere previously reported observed in healthy adults [68,71], is associated with early

components of auditory processing [37,67,72]. The activation of the second network appeared

more widespread, prominently involving medial temporal regions such as hippocampal

regions, insula, inferior temporal cortex as well as cingulate gyrus and ventro-medial

prefrontal cortex, which were previously connected to later stages of auditory processing [55,73].

Although the second network partially overlaps with the DMN on a spatial level, its narrow

attunement suggests its genuine involvement in auditory processing rather than being a

residual of the DMN operating in the background.

The second frequency of interest in relation to our results falls within the alpha range,

which is not surprising since alpha activity is ubiquitous in the brain and therefore prominent

in most M/EEG sensors [74]. Interestingly, the peak and distribution of the variance explained

by the top alpha networks differed across resting state and sound listening. At rest, it

approximated a symmetric Gaussian curve peaking at 10.9 Hz. During listening, the left side of the curve flattened, and the peak shifted higher to 12.1 Hz. In resting state, the spatial activation pattern of the peak components displayed the stereotypical parieto-occipital activation characteristic of the brain at rest [42–45]. In contrast, during listening, the focal activation was centred in the sensorimotor areas, highlighting the involvement of alpha mu-rhythms typically observed in these regions [45,75,76].

Notably, a more fine-grained inspection of the left- and right-sides of the eigenvalues' distribution in the alpha range revealed that even during resting state, the focus of the spatial extent of the alpha network transitions anteriorly towards the pre-central gyrus and sensorimotor regions with increasing frequency (see **Figure 2**). Indeed, while not as dominant in the distribution, higher alpha is still spatially concentrated in sensorimotor areas such as supplementary motor area (SMA). What occurred during listening is that the sensorimotor alpha network at 12.1 Hz became more prominent relative to the same network at rest. We interpret this spatial rearrangement of the alpha network as underpinning readiness for action, given the natural human inclination to synchronise with periodic auditory stimuli [77–79]. This is particularly true for the involvement of the SMA, which is thought to inform expectations of auditory periodic stimuli by representing cyclic sensorimotor processes, enabling sensory predictions in absence of movement and ultimately overt behavioural synchronisation with a beat [80].

The third frequency of interest was found in the beta range, peaking at 22.9 Hz and exhibiting the same spatial activation patterns in both conditions. The focal activation over the precentral gyrus aligns with the expected topography at rest, as beta is a dominant spectral mode of motor cortices [42,45,75]. Interestingly, the same pattern was observed during the listening condition, where different outcomes might have been anticipated. For example, given the contribution of motor beta dynamics to auditory processing [81–83], one might reasonably expect either a significant change in the explained variance of this motor network or the emergence of an additional auditory network dominated by beta activity [83–85]. At the same time, beta oscillations in sound and music processing are associated with processes such as internal representation, prediction, and hierarchical subdivision of sounds, making it sensitive to the task and complexity of the stimuli [83,85–87]. In light of our results and given the extreme simplicity of the isochronous tone sequences presented to our participants, we conclude that the emergence of a prominent beta network was likely unnecessary to process the stimulation in our experimental condition. Furthermore, fluctuations in beta power

induced by rhythmic stimuli are dissociable by the overall level of beta power [25], which may
have left the variance explained by the beta network unchanged across conditions.

To summarise, FREQ-NESS captured a dissociation between temporal and spatial
dimensions in brain activity, successfully identifying the classical networks commonly
associated with the resting state, such as the default mode network, alpha-band network, and
motor-beta network [42,43,46,88]. Notably, FREQ-NESS offers advances beyond earlier research
by providing a comprehensive overview of simultaneous brain networks at rest and revealing
three scenarios resulting from auditory stimulation compared to the resting state baseline: (1)
emergence of prominent networks attuned to the stimulation frequency (e.g., transition from
DMN to auditory networks attuned to the stimulation frequency); (2) topographical
rearrangement of endogenous oscillations already prominent in the brain activity at rest (e.g.,
rearrangement of alpha networks); (3) maintenance of the status quo for networks operating
at frequencies not relevant to stimulus processing (e.g., invariance of the beta motor
network).

While FREQ-NESS offers a novel framework for studying brain networks, it is grounded
in well-established concepts and analytical methods commonly used in neuroscience
[10,12,22,32,89]. Indeed, over the last decade, GED has been applied to sensor data matrices
measured by M/EEG with the explicit purpose of separating latent processes in the brain
projecting and mixing to the recording at the scalp level (e.g., [24–28,32–35]). However, a major
limitation of such approaches arises from the fact that brain dipoles are postulated to be
inaccessible latent sources, and therefore the physiological interpretability of spatial
activation patterns is limited to a model of diffusion across sensors due to volume conduction
(for an extensive discussion on the interpretability of the eigenvectors, see [12]). One major
insight behind FREQ-NESS is that applying GED on a data matrix of reconstructed brain
voxels enables a direct and physiologically meaningful estimation of brain networks. In
addition to GED, other methods have been previously explored for separating sources and
deriving insights into brain networks. For instance, some studies gathered insights about
network configurations in the brain by using Independent Component Analysis (ICA) [64,90–92]
and Principal Component Analysis (PCA) [63,93–95], especially in relation to fMRI data.
However, while valuable, the signal measured by fMRI has very low temporal resolution on
the order of seconds and does not directly capture the neurophysiological signal produced by
the brain. This means it lacks the ability to capture relevant frequency information and cannot
make inferences on the fast-scale neurophysiological processes occurring in the brain at rest

and during stimulus processing. As a result, when applied to fMRI data, ICA and PCA cannot

identify frequency-resolved brain networks using detailed, temporally rich

neurophysiological signals. In neurophysiology, the use of linear decompositions to derive

brain networks is relatively rare. An interesting example is the study by Brooks et al., where

ICA was applied to MEG data across canonical broad frequency ranges, resulting in network

configurations comparable to those observed in fMRI during resting state [96]. While valuable,

ICA is not specifically designed to separate frequency-resolved networks, lacking the

flexibility to define criteria for source separation, such as contrasting broadband and

narrowband frequencies. Additionally, ICA does not provide information about the variance

explained by the components, making it challenging to select the most relevant ones.

Moreover, the study did not employ a systematic frequency-resolved approach.

In contrast, we have presented evidence that FREQ-NESS is an effective method to

separate brain networks in a data-driven manner based on their frequency-specificity, under

three fundamental assumptions which widely align with existing research. The first

assumption is that the multivariate time series characterising the brain voxels is a linear

combination of sources mixed with noise, and that a brain network exists when independent

brain voxels covary over time. This allows the estimation of brain networks via

eigendecomposition of the covariance matrices computed on the broadband and frequency-

resolved voxel data. The second assumption is that oscillatory dynamics are the dynamics of

interest, whereas broadband aperiodic components of brain activity are technically treated as

noise to enhance contrast with a reference covariance matrix [97]. This assumption constrains

the solution space, gives the researcher control over the criteria for separating the sources and

elects GED as an ideal tool to perform frequency-resolved blind source separation [21] (but see

[98], for other approaches accounting for aperiodic components of brain activity). Furthermore,

this second assumption is also backed by substantial evidence that preferred frequency modes

characterise cognitive processes [99] and dominate the activity of specific brain regions [42]. The

third assumption is that the GED components generated by FREQ-NESS are directly

interpretable as brain networks. Here, the variance explained by these components indicates

the relative significance of the networks for each frequency band and experimental condition,

while the associated activation patterns and time series provide insights into the spatial and

temporal extent of the networks [12].

In addition, FREQ-NESS not only delivers insights into brain network estimation but also

offers flexibility for integration with other analytical methods, enhancing their capabilities.

For example, FREQ-NESS enables the study of cross-frequency coupling (CFC) between
entire brain networks, rather than between individual pairs of brain regions. More
specifically, computing CFC between the narrowband filtered time series of different brain
networks enables the quantification of their interactions in the form of phase-to-amplitude
coupling [2,21,48,100]. To test the hypothesis that high-frequency network activity is modulated
by a low-frequency oscillation attuned to the stimulation frequency (2.4 Hz), we computed an
index of modulation based on the distribution of high-frequency power values over low-
frequency phase [25,56–58] . Our results revealed that power in gamma networks between 63.8
and 96.3 Hz is significantly modulated by low-frequency oscillators in the two main auditory
networks attuned to the 2.4 Hz stimulation frequency. This result is coherent with the
established notion that oscillations in the gamma band are induced by the presentation of
repetitive auditory stimuli and are associated with their bottom-up processing [84,101–104].
Notably, our study did not highlight a specific role for the auditory cortex in the gamma
network dynamics, which instead primarily recruited insula, inferior temporal cortex,
hippocampal regions, frontal operculum and inferior frontal gyrus. This suggests that
modulated gamma activity may not originate directly in the auditory cortex but rather be
mediated by interactions within low-frequency auditory networks.

This work presents several implications and potential future perspectives. A key
implication is that FREQ-NESS is designed for use with continuous MEG recordings co-
registered with MRI data. This tool is valuable for researchers who have a specific hypothesis
about activity at a particular frequency of interest and for those who aim to explore the entire
network landscape without the a priori assumptions previously discussed. Consequently,
FREQ-NESS can be particularly useful in analysing datasets involving continuous stimuli
such as music or speech to uncover neural responses and connectivity patterns, where the
temporal structure of the stimulus can be decomposed in frequency components and mapped
to neurophysiology [6,29,31] and domain-specific networks are characterised by spectral
fingerprints [15].

In absence of stimulation, other datasets of interest include the investigation of states of
consciousness, involving continuous resting state recording carried out in conditions of
meditation or psychedelics, where altered states of consciousness have been associated with
changes in the power spectral density over the whole brain [90,105–108]. Along this line, large-
scale comparisons of resting state recordings across populations in a between-subject design

would enable to establish a normative landscape of frequency-resolved networks at rest and,
eventually, during tasks.

FREQ-NESS demonstrated high reliability even when analysing data from individual
participants, as evidenced by the low standard errors in our statistics. This reliability allows
FREQ-NESS to obtain robust results from small sample sizes, facilitating the generation of
individualised data. Such data could be crucial for clinical applications that aim to diagnose
pathological changes in the frequency-specific brain network patterns of clinical populations
compared to healthy individuals.

Provided a successful separation, another future direction consists of deploying tasks to
elicit dynamics in networks of interest. One concrete example comes from perturbation
paradigms in the context of sensorimotor synchronisation. As previously pointed out [24], the
network estimation at the level of the anatomical sources could potentially solve the long-
standing problem of neural entrainment (see [69]), disentangling the different networks
underlying endogenous oscillations and periodic evoked responses within critical time
windows of frequency alignment in response to tempo changes [24].

To conclude, the current study demonstrated the effectiveness of FREQ-NESS as a
multivariate framework to provide a comprehensive and physiologically interpretable
perspective on the brain functioning, in terms of a landscape of frequency-resolved brain
networks.

Methods

Participants

A total of 29 participants (N = 29) took part in the study (17 females, 12 males). The age of the participants ranged from 19 to 50 years (mean age = 26.45 ± 7.37). The group consisted of four first-year music students and 25 non-musicians. With the exception of one participant in the latter group, all participants had less than two years of formal musical theory training (mean age = 0.23 ± 0.47) and less than five years of formal musical instrument training (mean years = 0.59, ± 1.10). None of the participants have been diagnosed with any neurological or psychiatric disease, nor had hearing impairment. All participants except one were right-handed. Of the 14 countries represented by our sample, Danish was the largest national group (24%). Participants were compensated for their time with vouchers for online-shopping. To be noted, two participants did not undergo the passive listening (PL) recording, and one participant was discarded due to technical issues during the data collection, leaving us with twenty-six (n = 26) participants eligible for within-subject comparisons in both conditions.

Experimental procedure

Upon arrival, participants were instructed about the experimental procedures before signing the informed consent form. They were given the possibility to withdraw their participation in the study at any time. A researcher was present at all times to provide assistance or clarifications when needed. Participants underwent MEG recordings under two conditions. In the PL condition, participants listened to rhythmic auditory stimulation while watching a silent movie. The stimuli consisted of an isochronous sequence of 300 Hz sine tones of 100 ms duration, with 10 ms fade-in and 10 ms fade-out, presented at a rate of 2.4 Hz (400 ms inter-onset interval) for a total duration of five minutes. Prior to the measurements, the sound intensity was set at 50 dB above the minimum hearing threshold of each participant. In the resting state RS condition, no auditory stimulation was presented while participants watched the same silent movie for a total duration of 10 minutes. Only the first five minutes of the resting state recording were analysed, in order to match the passive listening condition. The present study was conducted on a subset of a larger dataset acquired at Aarhus University and approved by the Ethics Committee of the Central Denmark Region (De Videnskabsetiske Komiteer for Region Midtjylland) (ref. 1-10-72-411-17). The experimental procedure was carried out according to the Declaration of Helsinki.

Data Acquisition

The MEG data was collected in a magnetically shielded room at Aarhus University

Hospital (AUH) in Aarhus, Denmark, using an Elekta Neuromag TRIUX MEG scanner with

306 channels (Elekta Neuromag, Helsinki, Finland). The recordings were sampled at 1000 Hz

with analog filtering set between 0.1 and 330 Hz. Prior to recording, the participants' head

shapes and the positions of four Head Position Indicator (HPI) coils were registered relative

to three anatomical landmarks using a 3D digitizer (Polhemus Fastrak, Colchester, VT,

USA). This information was later used to align the MEG data with MRI anatomical scans in

co-registration. During the MEG sessions, the HPI coils continuously tracked head position

for movement correction during pre-processing. Additionally, two sets of bipolar electrodes

recorded cardiac rhythm and eye movements, which facilitated the removal of

electrocardiography (ECG) and electrooculography (EOG) artifacts during pre-processing.

MRI scans were obtained using a CE-approved 3T Siemens MRI scanner at AUH, with

structural T1 (mprage with fat saturation) data recorded at a spatial resolution of 1.0 x 1.0 x

1.0 mm. The sequence parameters were set as follows: echo time (TE) = 2.61 ms; repetition

time (TR) = 2300 ms; reconstructed matrix size = 256 x 256; echo spacing = 7.6 ms;

bandwidth = 290 Hz/Px. The MEG and MRI recordings were conducted on separate days.

MEG Data Pre-Processing

The raw MEG sensor data, consisting of 204 planar gradiometers and 102 magnetometers,

were initially pre-processed using MaxFilter 69 [109] to reduce external interferences. Signal

space separation was applied with the following MaxFilter parameters: spatiotemporal signal

space separation (SSS); down-sampling from 1000 Hz to 250 Hz; movement compensation

with cHPI coils (default step size: 10 ms); and correlation limit of 0.98 between inner and

outer subspaces to reject intersecting signals during spatiotemporal SSS. As commonly

practiced in the literature [36,110], data was downsampled by a factor of four to facilitate the

computational feasibility of our analyses without significant data loss. Frequencies up to 97.6

Hz were explored in our analysis, a boundary which is still well below the Nyquist frequency

of 125Hz given a sampling rate of 250 Hz. The data was then converted to Statistical

Parametric Mapping (SPM) format for further pre-processing and analysis in MATLAB

(MathWorks, Natick, MA, USA) using custom-built codes (LBPD,

https://github.com/leonardob92/LBPD-1.0.git) and the Oxford Centre for Human Brain

Activity (OHBA) Software Library (OSL) [111], which builds on Fieldtrip [112], FSL [113], and

SPM [114] toolboxes. The continuous MEG data was visually inspected using the OSLview tool

to identify and remove the artifacts. Independent component analysis (ICA) (OSL

implementation) was used to eliminate eye-blink and heart-beat artifacts from the brain data

[115]. The original signal was decomposed into independent components (ICs), and then

correlated each IC with activity recorded by the EOG and ECG channels. ICs showing a

correlation at least three times higher than the others with either the EOG or the ECG were

labelled for removal. To ensure the accuracy of this procedure, we also visually inspected the

activation timeseries and the topographic scalp distribution of the labelled ICs, to confirm the

expected stereotyped patterns generated by eyeblinks and heartbeats. When both the

correlations and visual inspections indicated that an ICA component was due to eyeblink or

heartbeat activity, those components were discarded. The signal was then reconstructed by

back-projecting the remaining components in the MEG sensor space. The continuous

recordings of each experimental condition were segmented in one single 5-minute epoch

starting from the first trigger detected in the recording.

Anatomical Source Reconstruction

MEG is highly effective in detecting whole-brain activity with excellent temporal

resolution. However, in order to provide a physiologically interpretable characterisation of

the brain networks, it was crucial to estimate the anatomical sources projecting their

activation at the scalp level. Since MEG records neural signals outside the head without

directly indicating their specific brain sources, these have to be reconstructed by tackling an

inverse problem. For this purpose, we used the established beamforming method [38–40] (**Figure**

1b), which integrates custom-built code with routines from OSL, SPM, and FieldTrip.

Beamforming algorithms consist of two main steps: (1) creating a forward model for the

projection of the brain sources to the sensors and (2) computing the inverse solution. The

forward model treats each brain source as an active dipole (brain voxel) and predicts how the

unitary strength of each dipole is reflected across all MEG sensors. Here, we used only the

magnetometer channels with an 8-mm grid, yielding 3559 dipole locations (voxels)

throughout the brain. This choice was based on magnetometers' better detection of deep brain

activity compared to gradiometers, which are more sensitive to cortical activity near each

gradiometer [36,110]. After co-registering individual structural T1 data with fiducial points (head

landmarks), we computed the forward model using the widely adopted "Single Shell" method

detailed by Nolte 83. The result, called the "leadfield model," was stored in matrix L (sources

x MEG channels). For the participants lacking structural T1 data, we used a template

(MNI152-T1 with 8-mm spatial resolution) for leadfield computation. Next, we computed the

inverse solution using beamforming. This process sequentially applies different weights to

source locations to isolate each source's contribution to the MEG signal at every time point.

The beamforming inverse solution involves several steps. The MEG sensor data (B) at time t

is described by the equation:

$$\mathbf{B}_{(t)} = \mathbf{L} * \mathbf{Q}_{(t)} +$$

771 where L is the leadfield model, Q is the dipole matrix containing each dipole's activity over

772 time, and $\square$ represents noise (see [40] for details). To solve for Q, the weights (W) must be

773 computed, and then applied to the MEG sensors at each time point:

$$\mathbf{q}_{(t)} = \mathbf{W}^{\mathbf{T}} * \mathbf{B}_{(t)}$$

776   To obtain q, the weights W are calculated as shown in equation:

$$\mathbf{W}_{(n)} = (\mathbf{L}_{(n)}^{\mathbf{T}} * \mathbf{C}^{-\mathbf{1}} * \mathbf{L}_{(n)})^{-\mathbf{1}} * \mathbf{L}_{(n)}^{\mathbf{T}} * \mathbf{C}^{-\mathbf{1}}$$

779 where I is the covariance matrix between MEG sensors, calculated from the single 5-minute

780 epoch. Leadfield model computation was performed for three main orientations of each brain

781 source (dipole) according to Nolte [116], but orientations were reduced to one using the singular

782 value decomposition algorithm to simplify the beamforming output [117,118].

$$\mathbf{L} = \mathrm{svd}(\mathbf{l}^{\mathbf{T}} * \mathbf{C}^{-\mathbf{1}} * \mathbf{l})^{-\mathbf{1}}$$

Here, l represents the leadfield model with three orientations, while L is the simplified

one-orientation model used in the equation above. The weights were applied to each brain

source and time point, with the covariance matrix computed from the continuous signal

estimated by concatenating trials of all experimental conditions. Weights were normalised

according to Luckhoo et al. [119] to counterbalance reconstruction bias towards the centre of the

head. Weights were applied to neural activity from the single epoch, resulting in a time series

known as the neural activity index [38,119] for each of the 3559 brain sources over five minutes

of recording. The procedure was applied to PL and RS MEG sensor data, separately.

Generalised Eigendecomposition

Generalised eigendecomposition (GED) [10] was applied to the 3559 reconstructed brain

sources, in order to separate brain networks operating at specific frequencies. Given a

frequency of interest, this technique identifies the weighted combination of voxels which best

separates narrow oscillatory activity from broadband background activity, by maximising the

contrast between patterns of covariance in input data [24–26,97]. A major novelty of our approach

consists of applying the technique to a highly dense set of reconstructed brain sources, which

we argued would yield physiologically interpretable estimations of connectivity within brain

networks identified based on a criterion of frequency-specificity.

On a first iteration, we attuned the analysis to the stimulation frequency of 2.4 Hz, with the

goal of identifying brain networks attuned to process the auditory stimulus. The first step

consisted of narrow filtering the multivariate signal in voxel space, for which we designed a

wavelet kernel as a Gaussian function in the frequency domain, with centre at 2.4 Hz and

width of 0.3 Hz at half of the maximum gain. The settings were based on previous

applications of GED to EEG data in the context of neural entrainment to isochronous auditory

stimuli presented at a similar frequency [24,26]. We then filtered the broadband voxel data via

element-wise multiplication between the broadband spectrum and the wavelet kernel in

frequency domain, and transformed the resulting tapered spectrum in the time domain via

inverse fast Fourier transform.

Subsequently, we repeated the analysis for a large sample of 86 frequencies ranging from

0.2 to 97.6 Hz, equally spaced in intervals of 1.2 Hz for the 80 frequencies above the

stimulation frequency and 0.2 for the six frequencies below. In order to compare in the

sample elements with and without a harmonic ratio with respect to the stimulation,

frequencies were defined as an evenly spaced series where every second number was a

multiple integer of the stimulation frequency (harmonic), and an evenly spaced halving series

where every second number was a divisor of the stimulation frequency (sub-harmonic). The

width of the filters used to compute the narrow signals was optimised for every frequency,

log10-spaced scale.

For each frequency, the components of interest were separated by applying a spatial filter

to the voxels data matrix. In practice, spatial filtering consists of weighting the contribution

of all 3559 voxels to the narrow activity. The set of vectors W (weights) was calculated by

solving the following equation:

$$RW\Lambda = SW$$

where R is the reference covariance matrix of the broadband signal in voxel space and S is the

covariance matrix of the narrow signal in voxel space filtered at the frequency of interest.

GED identifies the set of eigenvectors W associated with the eigenvalues Λ, containing the

weights to best separate the signal (S) covariance from the reference (R) covariance matrix.

The S and R covariance matrices were computed in one step via matrix multiplication of the

mean-centred narrow and broadband voxel data, respectively.

$$S = X_{narrow} * X_{narrow}^{T}$$

$$R = X_{broad} * X_{broad}^{T}$$

To improve the numerical stability of the GED performance in case of rank deficiency,

regularisation was applied to both covariance matrices by adding a small constant to their

diagonal [10,120]. For S, the constant was 10^{-6}, whereas for R it was 1% of its average

eigenvalues.

The eigenvectors associated to the 10 largest eigenvalues were taken as spatial filters,

individually transposed and multiplied by the broadband voxel data matrix to reconstruct the

time series of our target signal components. When applying this spatial filter to the voxel data

matrix, the resulting signal component is physiologically interpretable as a *network activation*

timeseries (Y).

$$Y = w^{T} X_{broad}$$

In support to our interpretation, we computed the spatial projection of the components in

voxel space. To do so, we multiplied the raw weights w by the S covariance matrix and

computed its absolute value, obtaining the absolute voxel activation strengths associated with

the estimated latent factors (i.e., the networks) [12]. In order to facilitate comparisons across

components and frequencies, we normalised the scale of all activation patterns between 0 and

1 by dividing each vector by its maximum value. The resulting topographical distribution of

the components were interpreted as *network activation patterns (A)*.

$$A = w^T S$$

Randomisations

The entire GED procedure was applied to PL and RS reconstructed brain voxel data,

separately. In some aspects, the resting state worked as physiological control condition to

compare the networks' engagement in auditory processing with the networks in the same

frequency band at rest. However, the intrinsic dynamics of the brain at rest are still in

principle identifiable as frequency-specific networks via GED.

In order to systematically test the sensitivity of FREQ-NESS to the temporal and spatial

dimensions of latent brain networks, we independently disrupted their temporal and spatial

organisation by performing two types of randomisations on our voxel data in the RS

condition. The randomisation strategies were designed as follows: (1) *label randomisation*:

the voxel indexes were shuffled row-wise; (2) *point-wise label randomisation*: the voxel

indexes were shuffled row-wise, independently for each timepoint. Importantly, note that the

randomisations were performed after filtering in the narrowband data in order not to alter the

filtering procedure. The selective effects of each randomisation strategy on the GED

performance are presented in **Figure 4**.

Cross-frequency coupling (CFC)

By their nature, the frequency-resolved network activations estimated via GED are

maximally expressed in a defined narrow frequency band. This feature makes cross-

frequency coupling (CFC) an optimal approach to investigate interactions across networks

since narrowband activity accounts for the largest part of the variance in each network. For

each frequency, the first component was narrowband filtered using the same parameters

previously defined for GED. Subsequently, the narrowband component was Hilbert-

transformed to produce an analytic signal.

The first two components attuned to the stimulation frequency at 2.4 Hz were processed as

low-frequency modulators. The phase timeseries were extracted from the analytic signal and

divided into 36 bins (bin size = 10°) [56]. For each frequency, the first component was

processed as a carrier signal. Power time series were computed as the squared magnitude of

the analytic signal, and the mean power within each phase bin was computed to produce

power distributions over the modulators' phase [58]. Finally, a sine wave was fitted to each

distribution using the sineFit MATLAB function [121], and its amplitude was used as an index

of modulation strength [25].

Statistical testing

Signed-rank tests were performed to test for significant differences in the network

landscapes across experimental conditions. A two-tailed test of the eigenvalues was

performed testing PL against RS, for each component and each frequency. For this test, we

assumed that significant changes could be found in both directions, due to the possible

attunement or suppression of frequency-specific brain networks resulting from the auditory

stimulation.

A right-tailed test of the strength of the modulation by the low-frequency auditory

components was performed testing PL against RS. The test was repeated for the first and the

second low-frequency modulators, for each component and each frequency. For this test, we

hypothesised that PL would result in stronger modulation due to the fact that no auditory

network was expected to be attuned to the stimulation frequency in Rest.

False-discovery rate (FDR) correction was applied to all statistical tests to define a

significance threshold adjusted for multiple comparisons.

Data availability

The pre-processed neuroimaging data generated in this study will be made available upon reasonable requests.

Code availability

The MEG data was first pre-processed using MaxFilter 2.2.15. Then, the data was further pre-processed using Matlab R2016a or later (MathWorks, Natick, Massachusetts, United States of America). Specifically, we used codes from the Oxford Centre for Human Brain Activity Software Library (OSL), FMRIB Software Library (FSL) 6.0, SPM12, and Fieldtrip.

The full analysis pipeline used in this study as well as the code developed within the FREQ-NESS framework are available in the following GitHub:

https://github.com/mattiaRosso92/Frequency-resolved_brain_network_estimation_via_source_separation_FREQ-NESS

References

1. Deco, G., Tononi, G., Boly, M. & Kringelbach, M. L. Rethinking segregation and integration: contributions of whole-brain modelling. *Nat. Rev. Neurosci.* **16**, 430–439 (2015).

2. Deco, G. *et al.* Single or multiple frequency generators in on-going brain activity: A mechanistic whole-brain model of empirical MEG data. *Neuroimage* **152**, 538–550 (2017).

3. Engel, A. K., Gerloff, C., Hilgetag, C. C. & Nolte, G. Intrinsic coupling modes: multiscale interactions in ongoing brain activity. *Neuron* **80**, 867–886 (2013).

4. Buzsáki, G., Logothetis, N. & Singer, W. Scaling brain size, keeping timing: evolutionary preservation of brain rhythms. *Neuron* **80**, 751–764 (2013).

5. Nobre, A. C. & van Ede, F. Anticipated moments: temporal structure in attention. *Nat. Rev. Neurosci.* **19**, 34–48 (2018).

6. Giraud, A.-L. & Poeppel, D. Cortical oscillations and speech processing: emerging computational principles and operations. *Nat. Neurosci.* **15**, 511–517 (2012).

7. Lakatos, P. *et al.* The spectrotemporal filter mechanism of auditory selective attention. *Neuron* **77**, 750–761 (2013).

8. Lakatos, P., Karmos, G., Mehta, A. D., Ulbert, I. & Schroeder, C. E. Entrainment of neuronal oscillations as a mechanism of attentional selection. *Science* **320**, 110–113 (2008).

9. Cohen, M. X. Where does EEG come from and what does it mean? *Trends Neurosci.* **40**, 208–218 (2017).

10. Cohen, M. X. A tutorial on generalized eigendecomposition for denoising, contrast enhancement, and dimension reduction in multichannel electrophysiology. *Neuroimage* **247**, 118809 (2022).

11. Cohen, M. X. A data-driven method to identify frequency boundaries in multichannel electrophysiology data. *J. Neurosci. Methods* **347**, 108949 (2021).

12. Haufe, S. *et al.* On the interpretation of weight vectors of linear models in multivariate neuroimaging. *Neuroimage* **87**, 96–110 (2014).

13. Cichy, R. M. & Pantazis, D. Multivariate pattern analysis of MEG and EEG: A comparison of representational structure in time and space. *Neuroimage* **158**, 441–454 (2017).

14. King, J.-R. & Dehaene, S. Characterizing the dynamics of mental representations: the temporal generalization method. *Trends Cogn. Sci.* **18**, 203–210 (2014).

15. Te Rietmolen, N., Mercier, M. R., Trébuchon, A., Morillon, B. & Schön, D. Speech and music recruit frequency-specific distributed and overlapping cortical networks. *Elife* **13**, (2024).

16. Womelsdorf, T., Valiante, T. A., Sahin, N. T., Miller, K. J. & Tiesinga, P. Dynamic circuit motifs
underlying rhythmic gain control, gating and integration. *Nat. Neurosci.* **17**, 1031–1039 (2014).

17. Buzsáki, G. & Draguhn, A. Neuronal oscillations in cortical networks. *Science* **304**, 1926–1929 (2004).

18. Buzsáki, G. & Watson, B. O. Brain rhythms and neural syntax: implications for efficient coding of
cognitive content and neuropsychiatric disease. *Dialogues Clin. Neurosci.* **14**, 345–367 (2012).

19. Siegel, M., Donner, T. H. & Engel, A. K. Spectral fingerprints of large-scale neuronal interactions. *Nat.*
Rev. Neurosci. **13**, 121–134 (2012).

20. Wang, S.-J., Hilgetag, C. C. & Zhou, C. Sustained activity in hierarchical modular neural networks: self-
organized criticality and oscillations. *Front. Comput. Neurosci.* **5**, 30 (2011).

21. Cohen, M. X. Multivariate cross-frequency coupling via generalized eigendecomposition. *Elife* **6**, (2017).

22. de Cheveigné, A. & Parra, L. C. Joint decorrelation, a versatile tool for multichannel data analysis.
Neuroimage **98**, 487–505 (2014).

23. Zuure, M. B. & Cohen, M. X. Narrowband multivariate source separation for semi-blind discovery of
experiment contrasts. *J. Neurosci. Methods* **350**, 109063 (2021).

24. Rosso, M., Moens, B., Leman, M. & Moumdjian, L. Neural entrainment underpins sensorimotor
synchronization to dynamic rhythmic stimuli. *Neuroimage* **277**, 120226 (2023).

25. Rosso, M., Heggli, O. A., Maes, P. J., Vuust, P. & Leman, M. Mutual beta power modulation in dyadic
entrainment. *Neuroimage* **257**, 119326 (2022).

26. Rosso, M., Leman, M. & Moumdjian, L. Neural Entrainment Meets Behavior: The Stability Index as a
Neural Outcome Measure of Auditory-Motor Coupling. *Front. Hum. Neurosci.* **15**, 668918 (2021).

27. Zuure, M. B., Hinkley, L. B., Tiesinga, P. H. E., Nagarajan, S. S. & Cohen, M. X. Multiple Midfrontal
Thetas Revealed by Source Separation of Simultaneous MEG and EEG. *J. Neurosci.* **40**, 7702–7713
(2020).

28. Cohen, M. X. & Gulbinaite, R. Rhythmic entrainment source separation: Optimizing analyses of neural
responses to rhythmic sensory stimulation. *Neuroimage* **147**, 43–56 (2017).

29. Lenc, T. *et al.* Mapping between sound, brain and behaviour: four-level framework for understanding
rhythm processing in humans and non-human primates. *Philos. Trans. R. Soc. Lond. B Biol. Sci.* **376**,
20200325 (2021).

30. Nozaradan, S., Peretz, I., Missal, M. & Mouraux, A. Tagging the neuronal entrainment to beat and meter. *J.*
Neurosci. **31**, 10234–10240 (2011).

31. Nozaradan, S., Keller, P. E., Rossion, B. & Mouraux, A. EEG frequency-tagging and input-output

978   comparison in rhythm perception. *Brain Topogr.* **31**, 153–160 (2018).

979   32. Nikulin, V. V., Nolte, G. & Curio, G. A novel method for reliable and fast extraction of neuronal

980   EEG/MEG oscillations on the basis of spatio-spectral decomposition. *Neuroimage* **55**, 1528–1535 (2011).

981   33. Duprez, J., Gulbinaite, R. & Cohen, M. X. Midfrontal theta phase coordinates behaviorally relevant brain

982   computations during cognitive control. *Neuroimage* **207**, 116340 (2020).

983   34. Gulbinaite, R., Roozendaal, D. H. M. & VanRullen, R. Attention differentially modulates the amplitude of

984   resonance frequencies in the visual cortex. *Neuroimage* **203**, 116146 (2019).

985   35. Gulbinaite, R., van Viegen, T., Wieling, M., Cohen, M. X. & VanRullen, R. Individual Alpha Peak

986   Frequency Predicts 10 Hz Flicker Effects on Selective Attention. *J. Neurosci.* **37**, 10173–10184 (2017).

987   36. Hansen, P., Kringelbach, M. & Salmelin, R. *MEG: An Introduction to Methods*. (Oxford University Press,

988   2010).

989   37. Bonetti, L. *et al.* Spatiotemporal brain hierarchies of auditory memory recognition and predictive coding.

990   *Nat. Commun.* **15**, 4313 (2024).

991   38. Brookes, M. J. *et al.* Beamformer reconstruction of correlated sources using a modified source model.

992   *Neuroimage* **34**, 1454–1465 (2007).

993   39. Hillebrand, A. & Barnes, G. R. Beamformer analysis of MEG data. *Int. Rev. Neurobiol.* **68**, 149–171

994   (2005).

995   40. Huang, M. X., Mosher, J. C. & Leahy, R. M. A sensor-weighted overlapping-sphere head model and

996   exhaustive head model comparison for MEG. *Phys. Med. Biol.* **44**, 423–440 (1999).

997   41. Tzourio-Mazoyer, N. *et al.* Automated anatomical labeling of activations in SPM using a macroscopic

998   anatomical parcellation of the MNI MRI single-subject brain. *Neuroimage* **15**, 273–289 (2002).

42. Keitel, A. & Gross, J. Individual Human Brain Areas Can Be Identified from Their Characteristic Spectral

Activation Fingerprints. *PLoS Biol.* **14**, e1002498 (2016).

43. Keitel, A., Ince, R. A. A., Gross, J. & Kayser, C. Auditory cortical delta-entrainment interacts with

oscillatory power in multiple fronto-parietal networks. *Neuroimage* **147**, 32–42 (2017).

44. Florin, E. & Baillet, S. The brain's resting-state activity is shaped by synchronized cross-frequency

coupling of neural oscillations. *Neuroimage* **111**, 26–35 (2015).

45. Hillebrand, A., Barnes, G. R., Bosboom, J. L., Berendse, H. W. & Stam, C. J. Frequency-dependent

functional connectivity within resting-state networks: an atlas-based MEG beamformer solution.

Neuroimage **59**, 3909–3921 (2012).

46. Hansen, E. C. A., Battaglia, D., Spiegler, A., Deco, G. & Jirsa, V. K. Functional connectivity dynamics:

modeling the switching behavior of the resting state. *Neuroimage* **105**, 525–535 (2015).

47. Helfrich, R. F., Herrmann, C. S., Engel, A. K. & Schneider, T. R. Different coupling modes mediate

cortical cross-frequency interactions. *Neuroimage* **140**, 76–82 (2016).

48. Canolty, R. T. & Knight, R. T. The functional role of cross-frequency coupling. *Trends Cogn. Sci.* **14**, 506–

515 (2010).

49. de Cheveigné, A. & Arzounian, D. Scanning for oscillations. *J. Neural Eng.* **12**, 066020 (2015).

50. Lakatos, P., Gross, J. & Thut, G. A New Unifying Account of the Roles of Neuronal Entrainment. *Curr.*

Biol. **29**, R890–R905 (2019).

51. Haegens, S. & Zion Golumbic, E. Rhythmic facilitation of sensory processing: A critical review. *Neurosci.*

Biobehav. Rev. **86**, 150–165 (2018).

52. Doelling, K. B., Assaneo, M. F., Bevilacqua, D., Pesaran, B. & Poeppel, D. An oscillator model better

predicts cortical entrainment to music. *Proc. Natl. Acad. Sci. U. S. A.* **116**, 10113–10121 (2019).

53. Samaha, J. & Cohen, M. X. Power spectrum slope confounds estimation of instantaneous oscillatory

frequency. *Neuroimage* **250**, 118929 (2022).

54. Zatorre, R. J. & Belin, P. Spectral and temporal processing in human auditory cortex. *Cereb. Cortex* **11**,

946–953 (2001).

55. Brattico, E. & Delussi, M. Making sense of music: Insights from neurophysiology and connectivity

analyses in naturalistic listening conditions. *Hear. Res.* **441**, 108923 (2024).

56. Zhou, G., Bourguignon, M., Parkkonen, L. & Hari, R. Neural signatures of hand kinematics in leaders vs.

followers: A dual-MEG study. *Neuroimage* **125**, 731–738 (2016).

57. Seeber, M., Scherer, R. & Müller-Putz, G. R. EEG oscillations are modulated in different behavior-related

networks during rhythmic finger movements. *Journal of Neuroscience* (2016).

58. Tort, A. B. L., Komorowski, R., Eichenbaum, H. & Kopell, N. Measuring phase-amplitude coupling

between neuronal oscillations of different frequencies. *J. Neurophysiol.* **104**, 1195–1210 (2010).

59. Tewarie, P. *et al.* How do spatially distinct frequency specific MEG networks emerge from one underlying

structural connectome? The role of the structural eigenmodes. *Neuroimage* **186**, 211–220 (2019).

60. Tewarie, P. *et al.* Integrating cross-frequency and within band functional networks in resting-state MEG: A

multi-layer network approach. *Neuroimage* **142**, 324–336 (2016).

61. Kringelbach, M. L. *et al.* Dynamic coupling of whole-brain neuronal and neurotransmitter systems. *Proc.*

Natl. Acad. Sci. U. S. A. **117**, 9566–9576 (2020).

62. Zhang, Z. *et al.* Resting-state brain organization revealed by functional covariance networks. *PLoS One* **6**,

e28817 (2011).

63. Zhong, Y. *et al.* Detecting functional connectivity in fMRI using PCA and regression analysis. *Brain*

Topogr. **22**, 134–144 (2009).

64. Mantini, D., Perrucci, M. G., Del Gratta, C., Romani, G. L. & Corbetta, M. Electrophysiological signatures

of resting state networks in the human brain. *Proc. Natl. Acad. Sci. U. S. A.* **104**, 13170–13175 (2007).

65. Mak, L. E. *et al.* The Default Mode Network in Healthy Individuals: A Systematic Review and Meta-

Analysis. *Brain Connect.* **7**, 25–33 (2017).

66. Chen, A. C. N., Feng, W., Zhao, H., Yin, Y. & Wang, P. EEG default mode network in the human brain:

spectral regional field powers. *Neuroimage* **41**, 561–574 (2008).

67. Haumann, N. T. *et al.* Extracting human cortical responses to sound onsets and acoustic feature changes in

real music, and their relation to event rate. *Brain Res.* **1754**, 147248 (2021).

68. Bonetti, L. *et al.* Brain recognition of previously learned versus novel temporal sequences: a differential

simultaneous processing. *Cereb. Cortex* **33**, 5524–5537 (2023).

69. Novembre, G. & Iannetti, G. D. Tagging the musical beat: Neural entrainment or event-related potentials?

Proceedings of the National Academy of Sciences of the United States of America vol. 115 E11002–

E11003 (2018).

70. Di Liberto, G. M. *et al.* Cortical encoding of melodic expectations in human temporal cortex. *Elife* **9**,

(2020).

71. Bonetti, L. *et al.* Whole-brain computation of cognitive versus acoustic errors in music: A mismatch

negativity study. *Neuroimage: Reports* **2**, 100145 (2022).

72. Paavilainen, P., Alho, K., Reinikainen, K., Sams, M. & Näätänen, R. Right hemisphere dominance of

different mismatch negativities. *Electroencephalogr. Clin. Neurophysiol.* **78**, 466–479 (1991).

73. Bonetti, L. *et al.* Spatiotemporal whole-brain activity and functional connectivity of melodies recognition.

Cereb. Cortex **34**, (2024).

74.   Mathewson, K. E. *et al.* Pulsed out of awareness: EEG alpha oscillations represent a pulsed-inhibition of
ongoing cortical processing. *Front. Psychol.* **2**, 99 (2011).

75.   Ramkumar, P., Parkkonen, L. & Hyvärinen, A. Group-level spatial independent component analysis of
Fourier envelopes of resting-state MEG data. *Neuroimage* **86**, 480–491 (2014).

76.   Pfurtscheller, G., Stancák, A., Jr & Neuper, C. Event-related synchronization (ERS) in the alpha band--an
electrophysiological correlate of cortical idling: a review. *Int. J. Psychophysiol.* **24**, 39–46 (1996).

77.   Large, E. W. On synchronizing movements to music. *Hum. Mov. Sci.* **19**, 527–566 (2000).

78.   Matthews, T. E., Witek, M. A. G., Lund, T., Vuust, P. & Penhune, V. B. The sensation of groove engages
motor and reward networks. *Neuroimage* **214**, 116768 (2020).

79.   Grahn, J. A. & Brett, M. Rhythm and beat perception in motor areas of the brain. *J. Cogn. Neurosci.* **19**,
893–906 (2007).

80.   Cannon, J. J. & Patel, A. D. How Beat Perception Co-opts Motor Neurophysiology. *Trends Cogn. Sci.* **25**,
137–150 (2021).

81.   Morillon, B., Arnal, L. H., Schroeder, C. E. & Keitel, A. Prominence of delta oscillatory rhythms in the
motor cortex and their relevance for auditory and speech perception. *Neurosci. Biobehav. Rev.* **107**, 136–
142 (2019).

82.   Morillon, B. & Baillet, S. Motor origin of temporal predictions in auditory attention. *Proc. Natl. Acad. Sci.*
U. S. A. **114**, E8913–E8921 (2017).

83.   Fujioka, T., Trainor, L. J., Large, E. W. & Ross, B. Internalized Timing of Isochronous Sounds Is
Represented in Neuromagnetic Beta Oscillations. *J. Neurosci.* **32**, 1791–1802 (2012).

84.   Fujioka, T., Trainor, L., Large, E. & Ross, B. Beta and gamma rhythms in human auditory cortex during
musical beat processing. *Ann. N. Y. Acad. Sci.* (2009).

85.   Fujioka, T., Ross, B. & Trainor, L. J. Beta-Band Oscillations Represent Auditory Beat and Its Metrical
Hierarchy in Perception and Imagery. *J. Neurosci.* **35**, 15187–15198 (2015).

86.   Criscuolo, A., Schwartze, M., Henry, M. J., Obermeier, C. & Kotz, S. A. Individual neurophysiological
signatures of spontaneous rhythm processing. *Neuroimage* **273**, 120090 (2023).

87.   Biau, E. & Kotz, S. A. Lower Beta: A Central Coordinator of Temporal Prediction in Multimodal Speech.
Front. Hum. Neurosci. **12**, (2018).

88.   Cabral, J., Kringelbach, M. L. & Deco, G. Exploring the network dynamics underlying brain activity
during rest. *Prog. Neurobiol.* **114**, 102–131 (2014).

89. Haufe, S., Dähne, S. & Nikulin, V. V. Dimensionality reduction for the analysis of brain oscillations.

Neuroimage **101**, 583–597 (2014).

90. Timmermann, C. *et al.* Human brain effects of DMT assessed via EEG-fMRI. *Proceedings of the National*

Academy of Sciences **120**, e2218949120 (2023).

91. Greicius, M. D., Srivastava, G., Reiss, A. L. & Menon, V. Default-mode network activity distinguishes

Alzheimer's disease from healthy aging: evidence from functional MRI. *Proc. Natl. Acad. Sci. U. S. A.*

101, 4637–4642 (2004).

92. McKeown, M. J. & Sejnowski, T. J. Independent component analysis of fMRI data: examining the

assumptions. *Hum. Brain Mapp.* **6**, 368–372 (1998).

93. Carbonell, F., Bellec, P. & Shmuel, A. Global and system-specific resting-state fMRI fluctuations are

uncorrelated: principal component analysis reveals anti-correlated networks. *Brain Connect.* **1**, 496–510

(2011).

94. Leonardi, N. *et al.* Principal components of functional connectivity: a new approach to study dynamic brain

connectivity during rest. *Neuroimage* **83**, 937–950 (2013).

95. McKeown, M. J. *et al.* Spatially independent activity patterns in functional MRI data during the Stroop

color-naming task. *Proceedings of the National Academy of Sciences* **95**, 803–810 (1998).

96. Brookes, M. J. *et al.* Investigating the electrophysiological basis of resting state networks using

magnetoencephalography. *Proc. Natl. Acad. Sci. U. S. A.* **108**, 16783–16788 (2011).

97. Cohen, M. X. Comparison of linear spatial filters for identifying oscillatory activity in multichannel data. *J.*

Neurosci. Methods **278**, 1–12 (2017).

98. Donoghue, T. *et al.* Parameterizing neural power spectra into periodic and aperiodic components. *Nat.*

Neurosci. **23**, 1655–1665 (2020).

99. Cannon, J. *et al.* Neurosystems: brain rhythms and cognitive processing. *Eur. J. Neurosci.* **39**, 705–719

(2014).

100. Hyafil, A., Giraud, A.-L., Fontolan, L. & Gutkin, B. Neural Cross-Frequency Coupling: Connecting

Architectures, Mechanisms, and Functions. *Trends Neurosci.* **38**, 725–740 (2015).

101. Parciauskaite, V., Bjekic, J. & Griskova-Bulanova, I. Gamma-Range Auditory Steady-State Responses and

Cognitive Performance: A Systematic Review. *Brain Sci* **11**, (2021).

102. Brugge, J. F. *et al.* Coding of repetitive transients by auditory cortex on Heschl's gyrus. *J. Neurophysiol.*

102, 2358–2374 (2009).

103. Pantev, C. *et al.* Human auditory evoked gamma-band magnetic fields. *Proc. Natl. Acad. Sci. U. S. A.* **88**,

8996–9000 (1991).

104. Galambos, R., Makeig, S. & Talmachoff, P. J. A 40-Hz auditory potential recorded from the human scalp.

Proc. Natl. Acad. Sci. U. S. A. **78**, 2643–2647 (1981).

105. Muthukumaraswamy, S. D. *et al.* Broadband cortical desynchronization underlies the human psychedelic

state. *J. Neurosci.* **33**, 15171–15183 (2013).

106. Carhart-Harris, R. L. *et al.* Neural correlates of the LSD experience revealed by multimodal neuroimaging.

Proc. Natl. Acad. Sci. U. S. A. **113**, 4853–4858 (2016).

107. Schartner, M. M., Carhart-Harris, R. L., Barrett, A. B. & Seth, A. K. Increased spontaneous MEG signal

diversity for psychoactive doses of ketamine, LSD and psilocybin. *Sci. Rep.* (2017).

108. Wong, W. P., Camfield, D. A., Woods, W., Sarris, J. & Pipingas, A. Spectral power and functional

connectivity changes during mindfulness meditation with eyes open: A magnetoencephalography (MEG)

study in long-term meditators. *Int. J. Psychophysiol.* **98**, 95–111 (2015).

109. Taulu, S. & Simola, J. Spatiotemporal signal space separation method for rejecting nearby interference in

MEG measurements. *Phys. Med. Biol.* **51**, 1759–1768 (2006).

110. Gross, J. *et al.* Good practice for conducting and reporting MEG research. *Neuroimage* **65**, 349–363

(2013).

111. Woolrich, M., Hunt, L., Groves, A. & Barnes, G. MEG beamforming using Bayesian PCA for adaptive

data covariance matrix regularization. *Neuroimage* **57**, 1466–1479 (2011).

112. Oostenveld, R., Fries, P., Maris, E. & Schoffelen, J.-M. FieldTrip: Open source software for advanced

analysis of MEG, EEG, and invasive electrophysiological data. *Comput. Intell. Neurosci.* **2011**, 156869

(2011).

113. Woolrich, M. W. *et al.* Bayesian analysis of neuroimaging data in FSL. *Neuroimage* **45**, S173-86 (2009).

114. Penny, W. D., Friston, K. J., Ashburner, J. T., Kiebel, S. J. & Nichols, T. E. *Statistical Parametric*

Mapping: The Analysis of Functional Brain Images. (Elsevier, 2011).

115. Mantini, D. *et al.* A signal-processing pipeline for magnetoencephalography resting-state networks. *Brain*

Connect. **1**, 49–59 (2011).

116. Nolte, G. The magnetic lead field theorem in the quasi-static approximation and its use for

magnetoencephalography forward calculation in realistic volume conductors. *Phys. Med. Biol.* **48**, 3637–

3652 (2003).

1154 117. Afnan, J. *et al.* Validating MEG source imaging of resting state oscillatory patterns with an intracranial

1155    EEG atlas. *Neuroimage* **274**, 120158 (2023).

1156 118. Tukey, J. W. Comparing individual means in the analysis of variance. *Biometrics* **5**, 99–114 (1949).

1157 119. Luckhoo, H. T., Brookes, M. J. & Woolrich, M. W. Multi-session statistics on beamformed MEG data.

1158    *Neuroimage* **95**, 330–335 (2014).

1159 120. Lotte, F. & Guan, C. Regularizing common spatial patterns to improve BCI designs: unified theory and

1160    new algorithms. *IEEE Trans. Biomed. Eng.* **58**, 355–362 (2011).

1161 121. Seibold, P. *Sine Fitting (Https://Www.Mathworks.Com/Matlabcentral/Fileexchange/66793-Sine-Fitting),*

1162    *MATLAB Central File Exchange.* (2021).

1163

1164

Acknowledgements

The Center for Music in the Brain (MIB) is funded by the Danish National Research Foundation (project number DNRF117).

M.R. is supported by IPEM Institute for Systematic Musicology, Ghent University, Belgium, with a Methusalem grant awarded by the Flemish Government, Belgium, to Professor Marc Leman.

L.B. is supported by Lundbeck Foundation (Talent Prize 2022), Carlsberg Foundation (CF20-0239), Center for Music in the Brain, Linacre College of the University of Oxford and Nordic Mensa Fund.

M.L.K. is supported by Center for Music in the Brain and Centre for Eudaimonia and Human Flourishing, which is funded by the Pettit and Carlsberg Foundations.

We thank Simjon Radloff, Anastasiia Popova and Antonieta Martínez-Guerrero for their extensive and tireless work during the data collection.

Author contributions statement

M.R. and L.B. conceived the hypotheses. L.B. and E.B. designed the experiment and collected the data. L.B., M.L.K., E.B., and P.V. recruited the resources for the experiment. M.R. and L.B. performed pre-processing, signal processing, statistical analysis and implemented the code for the FREQ-NESS framework. P.K., M.L.K., E.B., and P.V. provided essential help to interpret and frame the results within the neuroscientific literature. M.R., G.F.R. and L.B. wrote the first draft of the manuscript. G.F.R., M.R., and L.B. prepared the figures. All the authors contributed to and approved the final version of the manuscript.

Competing interests statement

1189

1190   The authors declare no competing interests.

1191 **Supplementary Material**

1192

1193 The supplementary tables are available at the following link:

1194 https://drive.google.com/drive/folders/1f5sZvXhQRPuh7YtjfjdxiZB5PTfdu2iT?usp=sharing

1195

1196

1197 **Table S1. Complete statistical results – variance explained**

1198 The table reports the results of the sing-ranked Wilcoxon tests (n = 26) contrasting the variance explained by the
1199 first two generalised eigendecomposition (GED) components for passive listening (PL) versus resting state
1200 (RS). Z-values and p-values are reported, along with the threshold for the p-values computed by the False
1201 Discovery Rate (FDR) correction for multiple comparisons.

1202

1203

Table S2. Complete statistical results – cross-frequency coupling

The table reports the results of the sing-ranked Wilcoxon tests (n = 26) contrasting the cross-frequency coupling
between the phase of the first two generalised eigendecomposition (GED) components over the amplitude of the
first component of all frequencies (starting at 14.9 Hz). This was done independently for both passive listening
(PL) and resting state (RS). Z-values and p-values are reported, along with the threshold for the p-values
computed by the False Discovery Rate (FDR) correction for multiple comparisons.

1210
1211

a Resting state
Frequency-resolved GED components

b Passive listening
Frequency-resolved GED components

1212

Figure S1: Network landscape: eigenspectrum and spatial activation patterns during rest and passive
*listening (**full spectrum**). This figure illustrates the frequency-resolved brain networks estimated via FREQ-*
NESS in two experimental conditions: (a) resting state and (b) passive listening. The first element of the network
*landscape is the **eigenspectrum**, which consists of the eigenvalues expressing the percentage of variance*
explained by the associated GED components, plotted over the frequencies. The solid lines indicate the mean
normalised eigenvalues across participants, while the shaded areas represent the standard error of the mean
*(SEM). The second element displays the **spatial activation patterns** associated with the top GED components for*
the frequencies exhibiting the highest explained variance. Each pattern highlights the extent of each brain
*voxel's contribution to the respective network. This is the same as **Figure 2**, but it shows the full spectrum of*
frequencies, highlighting no significant peak of variance explained is visible in the large gamma range.
1223
1224