Elucidating the Selection Mechanisms in Context-Dependent Computation through Low-Rank Neural Network Modeling

Yiteng Zhang[1,2], Jianfeng Feng[1,3,4,*], Bin Min[2,*]

1. School of Data Science, Fudan University, Shanghai 200443, China.

2. Lingang Laboratory, Shanghai 200031, China

3. Institute of Science and Technology for Brain-Inspired Intelligence, Fudan University, Shanghai 200443, China.

4. Key Laboratory of Computational Neuroscience and Brain-Inspired Intelligence, Fudan University, Ministry of Education, Shanghai, China.

*Correspondence: jianfeng64@gmail.com(J.F.), minbin@lglab.ac.cn (B.M.)

Abstract

Humans and animals exhibit a remarkable ability to selectively filter out irrelevant information based on context. However, the neural mechanisms underlying this context-dependent selection process remain elusive. Recently, the issue of discriminating between two prevalent selection mechanisms— input modulation versus selection vector modulation—with neural activity data has been highlighted as one of the major challenges in the study of individual variability underlying context-dependent decision-making (CDM). Here, we investigated these selection mechanisms through low-rank neural network modeling of the CDM task. We first showed that only input modulation was allowed in rank-one neural networks and additional dimensions of network connectivity were required to endow neural networks with selection vector modulation. Through rigorous information flow analysis, we gained a mechanistic understanding of why additional dimensions are required for selection vector modulation and how additional dimensions specifically contribute to selection vector modulation. This new understanding then led to the identification of novel neural dynamical signatures for selection vector modulation at both single neuron and population levels readily testable in experiments. Together, our results provide a rigorous theoretical framework linking network connectivity, neural dynamics and selection mechanisms, paving the way towards elucidating the circuit mechanisms when studying individual variability in context-dependent computation.

Introduction

Imagine you are playing a card game. Depending on your opponents' actions, you may change the way you organize the cards and adjust your strategy to increase your chance of winning. This example exemplifies the context-dependent nature of most decisions we made in our daily life (Miller & Cohen, 2001; Roy et al., 2010; Mante et al., 2013; Saez et al., 2015; Siegel et al., 2015; Bernardi et al., 2020; Takagi et al., 2021; Flesch et al., 2022; Barbosa et al., 2023). However, how the brain performs such context-dependent computation remains elusive (Fusi et al., 2016; Cohen, 2017; Badre et al., 2021; Okazawa & Kiani, 2023).

Using a monkey context-dependent decision-making (CDM) behavioral paradigm, together with neurophysiological recordings and recurrent neural network modeling, an influential work uncovered a novel context-dependent selection mechanism, namely selection vector modulation (Mante et al., 2013), distinct from the early sensory input modulation counterpart (Desimone & Duncan, 1995; Noudoost et al., 2010). More recently, aided by a high-throughput animal training approach, a large number of rats were trained to perform a similar CDM task (Pagan et al., 2022). The obtained neural and behavioral data then supported a new theoretical framework revealing a spectrum of possible network mechanisms for the context-dependent selection process, opening the door towards addressing the important issue of individual variability in higher cognition. Critically, this theoretical framework pointed out that current neurophysiological data fell short of distinguishing between selection vector modulation and sensory input modulation, calling for rethinking what kind of evidence is required for differentiating different selection mechanisms.

Here, we investigated these two selection mechanisms through low-rank neural network modeling (Landau & Sompolinsky, 2018; Mastrogiuseppe & Ostojic, 2018; Kadmon et al., 2020; Schuessler et al., 2020; Beiran et al., 2021, 2023; Dubreuil et al., 2022; Valente et al., 2022; Ostojic & Fusi, 2024), with the aim of generating experimentally testable predictions for selection mechanism

differentiation. Through introducing novel pathway-based information flow analysis afforded by the

low-rank network modeling, we gained a parsimonious pathway-based understanding of selection

vector modulation and explained where the two types of selection modulations can occur along

different pathways. Critically, our results led to the identification of novel experimentally testable

neural dynamical signatures for selection vector modulation at both the single-neuron and population

levels. Together, our work provides a theoretical basis for resolving the challenging issue of

distinguishing different selection mechanisms with neural activity data, shedding new light on the

study of individual variability in neural computation underlying the ubiquitous context-dependent

behaviors.

Results

Task paradigm, key concept and modeling approach

The task paradigm we focused on is the pulse-based context-dependent decision-making (CDM) task

(Pagan et al., 2022), a novel rat-version CDM paradigm inspired by the previous monkey CDM work

(Mante et al., 2013). In this paradigm, rats were presented with sequences of randomly-timed

auditory pulses that varied in both location and frequency (Figure 1A). In alternating blocks of trials,

rats were cued by an external context signal to determine the prevalent location (in the "LOC"

context) or frequency (in the "FRQ" context). Note that compared to the continuous sensory input

setting in previous works (e.g., Mante et al., 2013), this pulse-based sensory input setting allowed the

experimenters to better characterize both behavioral and neural responses (Pagan et al., 2022). We

will also demonstrate the unique advantage of this pulse-based input setting later in the present study

(e.g., Fig. 7).

Figure 1. Prevalent candidate selection mechanisms in CDM cannot be dissociated by classical neural dynamics analysis.

(A) A pulse-based context-dependent decision-making task (adapted from Pagan et al., 2022). In each trial, rats were first cued by sound to indicate whether the current context was the location (LOC) context or the frequency (FRQ) context. Subsequently, rats were presented with a sequence of randomly-timed auditory pulses. Each pulse could come from either the left speaker or right speaker and could be of low frequency (6.5 kHz, light blue) or high frequency (14 kHz, dark blue). In the LOC context, rats were trained to turn right (left) if more pulses are emitted from the right (left) speaker. In the FRQ context, rats were trained to turn right (left) if there are more (fewer) high-frequency pulses compared to low-frequency pulses.

(B) Two prevalent candidate mechanisms for context-dependent decision-making. *Top*: The input modulation mechanism. In this scenario, while the selection vector remains invariant across contexts, the stimulus input representation is altered in a way such that only the relevant stimulus input representation (i.e., the location input in the LOC context and the frequency input in the FRQ context) is well aligned with the selection vector, thereby fulfilling the requirement of

context-dependent computation. *Bottom*: The selection vector modulation mechanism. In this
scenario, although the stimulus input representation remains constant across different contexts,
the selection vector itself is altered by the context input to align with the relevant sensory input.
Red line: line attractor (choice axis). Green arrow: selection vector. Thick grey and blue arrows
stand for the projections of the location and frequency input representation directions on the
space spanned by the line attractor and selection vector, respectively. The small grey arrows stand
for direction of relaxing dynamics.
(C) Networks with distinct selection mechanisms may lead to similar trial-averaged neural dynamics
(adapted from Pagan et al., 2022). In a model with pure input modulation, the irrelevant sensory
input can still be represented by the network in a direction orthogonal to the selection vector.
Therefore, using the classical targeted dimensionality reduction method (Mante et al., 2013), both
the input modulation model (top) and the selection vector modulation model (bottom) would
exhibit similar trial-averaged neural dynamics as shown in Pagan et al., 2022.
(D) The setting of low-rank RNN modeling for the CDM task. The network has four input channels.
Input 1 and input 2 represent two sensory inputs, while the other two channels indicate the
context. The connectivity matrix J is constrained to be low-rank, expressed as $\frac{1}{N}\sum_{r=1}^{R}\boldsymbol{m}_r\boldsymbol{n}_r^T$,
where N is the number of neurons, R is the matrix's rank, and $\boldsymbol{m}_r\boldsymbol{n}_r^T$ is a rank-1 matrix
formed by the outer product of two N-dimensional connectivity vectors $\boldsymbol{m}_r$ and $\boldsymbol{n}_r$.
110
To solve this task, rats had to select the relevant information for the downstream evidence

accumulation process based upon the context. There were at least two different mechanisms capable

of performing this selection operation, i.e., selection vector modulation and input modulation (Mante

et al., 2013; Pagan et al., 2022). To better introduce these mechanisms, we first reviewed the classical

linearized dynamical systems analysis and the concept of selection vector (Figure 1B; Mante et al.,

2013; Sussillo & Barak, 2013; Maheswaranathan et al., 2019; Maheswaranathan & Sussillo, 2020;

Nair et al., 2023). In the linearized dynamical systems analysis, the neural dynamics around the

choice axis (Figure 1B, red line) is approximated by a line attractor model. Specifically, the dynamics

in the absence of external input can be approximated by the following linear equation $\frac{d\boldsymbol{r}}{dt} = M\boldsymbol{r}$,

where M is a matrix with one eigenvalue being equal to 0 and all other eigenvalues having a negative

real part. For brevity, let us denote the left eigenvector of the 0 eigenvalue as $\boldsymbol{s}$. In this linear

dynamical system, the effect of any given perturbation can be decomposed along the directions of

different eigenvectors: the projection onto the $\boldsymbol{s}$ direction will remain constant while the projections

onto all other eigenvectors will exponentially decay to zero. Thus, for any given input $\boldsymbol{I}$, only the

component projecting onto the $\boldsymbol{s}$ direction (i.e., $\boldsymbol{I} \cdot \boldsymbol{s}$) can be integrated along the line attractor (see

Methods for more details). In other words, $\boldsymbol{s}$ serves as a vector selecting the input information,

which is known as the "selection vector" in the literature (Mante et al., 2013).

Two distinct selection mechanisms can then be introduced based upon the concept of selection vector

(Pagan et al., 2022). Specifically, to perform the CDM task, the stimulus input (LOC input, for

example) must have a larger impact on evidence accumulation in the relevant context (LOC context)

than in the irrelevant context (FRQ context). That is, $\boldsymbol{I} \cdot \boldsymbol{s}$ must be larger in the relevant context

than in the irrelevant context. The difference between these two can be decomposed into two

components:

$$\Delta(\boldsymbol{I} \cdot \boldsymbol{s}) = \Delta\boldsymbol{I} \cdot \overline{\boldsymbol{s}} + \overline{\boldsymbol{I}} \cdot \Delta\boldsymbol{s}, \qquad (Eq.\,1)$$

where the Δ symbol denotes difference across two contexts (relevant – irrelevant) and the bar

symbol denotes average across two contexts (see Methods for more details). The first component

$\Delta\boldsymbol{I} \cdot \overline{\boldsymbol{s}}$ is called input modulation in which the change of input information across different contexts

is emphasized (Figure 1B, top). In contrast, the second component $\overline{\boldsymbol{I}} \cdot \Delta\boldsymbol{s}$ is called selection vector

modulation in which the change of selection vector across contexts is instead highlighted (Figure 1B,

bottom).

While these two selection mechanisms were clearly defined, recent work showed that it is actually

challenging to differentiate them through neural dynamics (Pagan et al., 2022). For example, both

input modulation and selection vector modulation can lead to similar trial-averaged neural dynamics

through targeted dimensionality reduction (Figure 1C; Pagan et al., 2022). Take the input modulation

as an example (Figure 1C, top). One noticeable aspect we can observe is that the input information

(e.g., location information) is preserved in both relevant (LOC context) and irrelevant contexts (FRQ

context), which seems contradictory to the definition of input modulation. What is the mechanism

underlying this counterintuitive result? As Pagan et al. pointed out earlier, input modulation is not the

input change (ΔI) per se. Rather, it means the change of input multiplied by selection vector (i.e.,

$\Delta I \cdot \bar{s}$). Therefore, for the input modulation, while input information indeed is modulated by context

along the selection vector direction, input information can still be preserved across contexts along

other directions orthogonal to the selection vector, which explains the counterintuitive result and

highlights the challenge of distinguishing input modulation from selection vector modulation in

experiments (Pagan et al., 2022).

In this study, we sought to address this challenge using the low-rank RNN modeling approach. In

contrast to the "black-box" vanilla RNN approach (e.g., Mante et al., 2013), the low-rank RNN

approach features both well-controlled model complexity and mechanistic transparency, potentially

providing a fresh view into the mechanisms underlying the intriguing selection process. Specifically,

the low-rank RNNs we studied here implemented an input-output task structure similar to the

classical RNN modeling work of CDM (Figure 1D; Mante et al., 2013). More concretely, the hidden

state $\boldsymbol{x}$ of a low-rank RNN with N neurons evolves over time according to

162
$$\tau \frac{d\boldsymbol{x}}{dt} = -\boldsymbol{x} + J\phi(\boldsymbol{x}) + \sum_{s=1}^{2} \boldsymbol{I}_s u_s(t) + \sum_{s=1}^{2} \boldsymbol{I}_s^{ctx} u_s^{ctx}(t), \qquad (Eq.\,2)$$

where $J = \sum_{r=1}^{R} \boldsymbol{m}_r \boldsymbol{n}_r^T / N$ is a low-rank matrix with R output vectors $\boldsymbol{m}_r, r = 1, \cdots, R$ and R

input-selection vectors $\boldsymbol{n}_r, r = 1, \cdots, R,$ τ is the time constant of single neurons, ϕ is the nonlinear

activation function, $u_s(t), s = 1, 2$ embedded into the network through $\boldsymbol{I}_s$ mimic the location and

frequency click inputs, and $u_s^{ctx}(t), s = 1, 2$ embedded through $\boldsymbol{I}_s^{ctx}$ indicate whether the current

context is location or frequency. The output of the network is a linear projection of neural activity

(see Methods for more model details). Under this general architectural setting, on one hand, through

controlling the rank R of the matrix J during backpropagation training, we can determine the

minimal rank required for performing the CDM task and reverse-engineer the underlying mechanism,

which will be demonstrated in Figure 2. On the other hand, recent theoretical progress of low-rank

RNNs (Beiran et al., 2021, 2021; Dubreuil et al., 2022) enabled us to explicitly construct neural

network models with mechanistic transparency, complementing the reverse-engineering analysis

(Mante et al., 2013; Sussillo & Barak, 2013), which will be shown in Figure 3.

No selection vector modulation in rank-one models

In the literature, it was found that rank-one RNN models suffice to solve the CDM task (Dubreuil et

al., 2022). Here, we further asked whether selection vector modulation can occur in rank-one RNN

models. To this end, we trained many rank-1 models (see Methods for details) and found that indeed

having rank-1 connectivity (e.g., with the overlap structure listed in Figure 2A; for the detailed

connectivity structure, see Figure 2-figure supplement 1) is sufficient to perform the CDM task,

consistent with the earlier work. As shown in Figure 2B, in context 1, the decision was made based

on input-1 evidence, ignoring input-2 evidence, indicating that the network can effectively filter out

irrelevant information. To answer what kind of selection mechanisms underlies this context-

dependent computation, we computed the selection vector in two contexts through linearized

dynamical systems analysis (Sussillo & Barak, 2013). Cosine angle analysis revealed that selection

vectors kept invariant across different contexts (Figure 2C, left), indicating no selection vector

modulation. This result was preserved across different hyperparameter settings (such as different

regularization coefficients or activation functions) and we also provide a mathematical proof in

Methods (see also Pagan et al., 2023).

Figure 2. No selection vector modulation in rank-1 neural network models.

(A) Illustration of rank-1 connectivity matrix structure. *Left*: a rank-1 matrix can be represented as the outer product of an output vector $\boldsymbol{m}_{dv}$ and an input-selection vector $\boldsymbol{n}_{dv}$, of which the input-selection vector $\boldsymbol{n}_{dv}$ played the role of selecting the input information through its overlap with the input embedding vectors $\boldsymbol{I}_1$ and $\boldsymbol{I}_2$. The context signals are fed forward to the network with embedding vectors $\boldsymbol{I}_1^{ctx}$ and $\boldsymbol{I}_2^{ctx}$. Since the overlap between the context embedding vectors and input-selection vector $\boldsymbol{n}_{dv}$ are close to 0, for simplicity, we omitted the context embedding vectors here. *Right*: an example of the trained rank-1 connectivity structure characterized by the cosine angle between every pair of connectivity vectors (see Figure 2-figure supplement 1 and Methods for details).

(B) The psychometric curve of the trained rank-1 RNNs. In context 1, input 1 strongly affects the choice, while input 2 has little impact on the choice. In context 2, the effect of input 1 and input 2 on the choice is exchanged. The shaded area indicates the standard deviation. Ctx. 1, context 1. Ctx. 2, context 2.

(C) Characterizing the change of selection vector as well as input representation direction across contexts using cosine angle. The selection vector in each context is computed using linearized dynamical system analysis. The input representation direction is defined as the elementwise multiplication between the single neuron gain vector and the input embedding vector (see

Methods for details). *** p<0.001, one-way ANOVA test, n=100. Inp., input. Rep.,
representation.
(D) Characterizing the overlap between the input representation direction and the selection vector.
*** p<0.001, one-way ANOVA test, n=100. Dir., direction.
(E) The state space analysis for example trained rank-1 RNN. The space is spanned by the line
attractor axis (red line) and the selection vector (green arrow).
(F) Trial-averaged dynamics for example rank-1 RNN. We applied targeted dimensionality reduction
(TDR) to identify the choice, input 1 and input 2 axes. The neuron activities were averaged
according to input 1 strength, choice and context and then projected onto the choice and input 1
axes to obtain the trial-averaged population dynamics.
219

While the selection vector was not altered by contexts, the direction of input representations changed

significantly across different contexts (Figure 2C, left; see Methods for the definition of input

representation direction). Further analysis revealed that the overlap between the input representation

direction and the unchanged selection vector is large in the relevant context and small in the

irrelevant context, supporting the input modulation mechanism (Figure 2D). These results indicate

that while a rank-1 network can perform the task, it can only achieve flexible computation through

input modulation (Figure 2E). Importantly, when applying a similar targeted dimensionality

reduction method to this rank-1 model, we found that the irrelevant sensory input information was

indeed well-represented in neural activity state space (Figure 2F), supporting the conclusion made in

the Pagan et al. paper that the presence of irrelevant sensory input in neural state space cannot be

used as a reliable indicator for the absence of input modulation (Figure 1C).

In summary, we conclude that to study the mechanism of selection vector modulation, instead of

limiting to the simplest model of CDM task, it is necessary to explore network models with higher

ranks.

A low-rank model with pure selection vector modulation

To study the mechanism of selection vector modulation, we designed a rank-3 neural network model,

with one additional rank for each sensory input feature (i.e., $\boldsymbol{m}_{iv_1}\boldsymbol{n}_{iv_1}^T$ for input 1 and $\boldsymbol{m}_{iv_2}\boldsymbol{n}_{iv_2}^T$ for

input 2; Figure 3A, left). Specifically, we ensured that I_1 (I_2) has a positive overlap with n_{iv_1}

(n_{iv_2}) and zero overlap with n_{dv}, while m_{iv1} (m_{iv_2}) has a positive overlap with n_{dv} (Figure 3A,

right; see Figure 3-figure supplement 1 and Methods for more details). This configuration implies

that the stimulus input 1 (2) is first selected by $n_{iv_1}(n_{iv_2})$, represented by $m_{iv_1}(m_{iv_2})$, and

subsequently selected by n_{dv} before being integrated by the accumulator. In principle, this

sequential selection process enables more sophisticated contextual modulations.

We confirmed that a model with such connectivity structure can perform the task (Figure 3B) and

then conducted an analysis similar to that performed for rank-1 models. Unlike the rank-1 model, the

selection vector for this rank-3 model changes across contexts while the input representation

direction remains invariant (Figure 3C). Further analysis revealed that the overlap between the

selection vector and the unchanged input representation direction is large in the relevant context and

small in the irrelevant context (Figure 3D), supporting a pure selection vector modulation mechanism

(Figure 3E) distinct from the input modulation counterpart shown in Figure 2D. When applying a

similar targeted dimensionality reduction method to this rank-3 model, as what we expected, we

found that both relevant and irrelevant sensory input information was indeed well-represented in

neural activity state space (Figure 3F), which was indistinguishable from the input modulation

counterpart (Figure 2F).

Figure 3. A rank-3 neural network model with pure selection vector modulation.

(A) Illustration of the utilized rank-3 connectivity matrix structure. *Left*: the rank-3 matrix can be represented as the summation of three outer products, including the one with the output vector $\boldsymbol{m}_{dv}$ and the input-selection vector $\boldsymbol{n}_{dv}$, the one with the output vector $\boldsymbol{m}_{iv_1}$ and the input-selection vector $\boldsymbol{n}_{iv_1}$, and the one with the output vector $\boldsymbol{m}_{iv_2}$ and the input-selection vector $\boldsymbol{n}_{iv_2}$, of which the input-selection vectors $\boldsymbol{n}_{iv_1}$ and $\boldsymbol{n}_{iv_2}$ played the role of selecting the input information from $\boldsymbol{I}_1$ and $\boldsymbol{I}_2$, respectively. *Right*: the connectivity structure of the handcrafted RNN model characterized by the cosine angle between every pair of connectivity vectors (see Figure 3-figure supplement 1 and Methods for more details).

(B) The psychometric curve of the handcrafted rank-3 RNN model.

(C) Characterizing the change of selection vector as well as input representation direction across contexts using cosine angle. The selection vector in each context is computed using linearized dynamical system analysis. The input representation direction is defined as the elementwise multiplication between the single neuron gain vector and the input embedding vector (see Methods for details). *** $p<0.001$, one-way ANOVA test, n=100.

(D) Characterizing the overlap between the input representation direction and the selection vector.

*** p<0.001, one-way ANOVA test, n=100.

(E) The state space analysis for example rank-3 RNN. The space is spanned by the line attractor axis

(red line, invariant across contexts), selection vector in context 1 (green arrow, top panel) and

selection vector in context 2 (green arrow, bottom panel).

(F) Trial-averaged dynamics for example rank-3 RNN.

Together, through investigating these two extreme cases—one with pure input modulation and the

other with pure selection vector modulation, we not only reconfirm the challenge of distinguishing

input modulation from selection modulation based on neural activity data (Pagan et al., 2022) but

also point out the previously unknown link between selection vector modulation and network

connectivity dimensionality.

Understanding context-dependent modulation in Figs. 2 and 3 through pathway-based

information flow analysis

What is the machinery underlying this link between selection vector modulation and network

connectivity dimensionality? One possible way to address this issue is through linearized dynamical

systems analysis: first computing the selection vector and the sensory input representation direction

through reverse-engineering (Barak & Sussillo, 2013) and then calculating both selection vector

modulation and input modulation according to Eq. 1. However, the connection between the network

connectivity dimensionality and the selection vector obtained through reverse-engineering is implicit

and in general non-trivial (Pagan et al., 2023), hindering further investigation of the underlying

machinery. Here, building on recent theoretical progress in low-rank RNNs (Mastrogiuseppe &

Ostojic, 2018; Dubreuil et al., 2022), we introduced a novel pathway-based information flow analysis

approach, providing an explicit link between network connectivity, neural dynamics and selection

mechanisms.

To start with, the low-rank RNN dynamics (i.e., Eq. 2) can be described by an information flow

graph, with each task variable as a node and each effective coupling between task variables as an

edge (Mastrogiuseppe & Ostojic, 2018; Dubreuil et al., 2022). Take the rank-1 RNN in Figure 2 as

an example. A graph with three nodes, including two input variables $\kappa_{inp_s}(t), s = 1, 2$ and one

decision variable $\kappa_{dv}(t)$, suffices (Figure 4A; see Methods for more details). In this graph, the

dynamical evolution of the task variable κ_{dv} can be expressed as:

$$\tau \frac{d\kappa_{dv}}{dt} = -\kappa_{dv} + E_{inp_1 \to dv}\kappa_{inp_1} + E_{inp_2 \to dv}\kappa_{inp_2} + E_{dv \to dv}\kappa_{dv} \qquad (Eq.3)$$

where the effective coupling $E_{inp_s \to dv}$ from the input variable κ_{inp_s} to the decision variable κ_{dv} is

equal to the overlap between the input representation direction $\tilde{I}_s$ (each element is defined by $\tilde{I}_{s,i} =$

$\phi'(x_i)I_{s,i}$) and the input-selection vector $\boldsymbol{n}_{dv}$. More precisely, $E_{inp_s \to dv} = \langle \tilde{I}_s, \boldsymbol{n}_{dv} \rangle$, where $\langle \boldsymbol{a}, \boldsymbol{b} \rangle$

is defined as $\frac{1}{N}\sum_1^N a_i b_i$ for two length-N vectors. Since the input representation direction $\tilde{I}_s$

depends on the single neuron gain ϕ' and the context input can modulate this gain, the effective

coupling $E_{inp_s \to dv}$ is context-dependent. Indeed, as shown in Figure 4A and Figure 4-figure

supplement 1A, $E_{inp_1 \to dv}$ exhibited a large value in context 1 but was negligible in context 2 while

$E_{inp_2 \to dv}$ exhibited a large value in context 2 but was negligible in context 1. In other words,

information from the input variable can arrive at the decision variable only in the relevant context,

which exactly is the computation required by the CDM task.

To get a more intuitive understanding of the underlying information flow process, we discretized the

equation and followed the information flow step by step. Specifically, by discretizing Eq. 3 using

Euler's method with a time step equal to the time constant τ of the system, we get

$$\kappa_{dv}(t + \tau) = E_{inp_1 \to dv}\kappa_{inp_1}(t) + E_{inp_2 \to dv}\kappa_{inp_2}(t) + E_{dv \to dv}\kappa_{dv}(t) \qquad (Eq.4)$$

Take context 1 as an example (Figure 4B, top panel). Initially, there is no information in the system.

In step 1, pulse inputs of size A_1 and A_2 are placed in the inp_1 and inp_2 slots, respectively. The

information from these slots, after being multiplied by the corresponding effective coupling, then

flows to the dv slot. In context 1, $E_{inp_2 \to dv} \approx 0$, meaning only the content from the inp_1 slot can

arrive at the dv slot. Consequently, in step 2, the information content in the dv slot would

be $E_{inp_1 \to dv} A_1$. The following steps will replicate step 2 due to the recurrent connectivity of the dv

slot. The scenario in context 2 is similar to context 1, except that only the content from the inp_2 slot

arrives at the dv slot (Figure 4B, bottom panel). The continuous dynamics for each task variable

given pulse input is displayed in Figure 4-figure supplement 2, A-C.

Figure 4. Pathway-based information flow analysis.
(A) The information flow graph of the rank-1 model presented in Figure 2. In this graph, nodes
represented task variables communicating with each other through directed connections (denoted
as $E_{sender \to receiver}$) between them. Note that $E_{sender \to receiver}$ is the overlap between the
representation direction of the sender variable (e.g., the representation directions of input variable
and decision variable $\tilde{I}_{inp}$ and $\tilde{m}_{dv}$) and the input-selection vector of the receiver variable (e.g.,
the input-selection vector of decision variable n_{dv}). As such, $E_{sender \to receiver}$ naturally inherits
the context dependency from the representation direction of task variable: while $E_{inp_1 \to dv}$

exhibited a large value and $E_{inp_2 \to dv}$ was negligible in context 1, the values of these two

exchanged in context 2.

(B) Illustration of information flow dynamics in (A) through discretized steps. At step 1, sensory

information A_1 and A_2 were placed in $inp1$ and $inp2$ slots, respectively. Depending on the

context, different information contents (i.e., $E_{inp_1 \to dv}A_1$ in context 1 and $E_{inp_2 \to dv}A_2$ in context

2) entered into the dv slot at step 2 and were maintained by recurrent connections in the

following steps, which is desirable for the context-dependent decision-making task.

(C) The information flow graph of the rank-3 model presented in Figure 3. Different from (A), here

to arrive at the dv slot, the input information has to first go through an intermediate slot (e.g.,

the $inp_1 \to iv_1 \to dv$ pathway in context 1 and the $inp_2 \to iv_2 \to dv$ pathway in context 2).

(D) Illustration of information flow dynamics in (C) through discretized steps.

The same pathway-based information flow analysis can also be applied to the rank-3 model (Figure

4C and 4D). In this model, similar to the rank-1 models, there are input variables (k_{inp_1} and k_{inp_2})

and decision variable (k_{dv}). Additionally, it includes intermediate variables (k_{iv_1} and k_{iv_2})

corresponding to the activity along the $\boldsymbol{m}_{iv_1}$ and $\boldsymbol{m}_{iv_2}$ axes. In this scenario, instead of flowing

directly from the input to the decision variable, the information flows first to the intermediate

variables and then to the decision variable. These intermediate variables act as intermediate nodes.

Introducing these nodes does more than simply increase the steps from the input variable to the

decision variable. In the rank-1 case, the context signals can only modulate the pathway from the

input to the decision variable. However, in the rank-3 case, context signals can modulate the system

in two ways: from the input to the intermediate variables and from the intermediate variables to the

decision variable.

Take the rank-3 model introduced in Figure 3 as an example. Context signals did not alter the

representation of input signals, leading to constant effective couplings (i.e., constant $E_{inp_1 \to iv_1}$ and

$E_{inp_2 \to iv_2}$) from input to intermediate variables across contexts. Instead, it changed the effective

coupling from the intermediate variables to the decision variable (i.e., large $E_{iv_1 \to dv}$ in context 1 and

near zero $E_{iv_1 \to dv}$ in context 2; Figure 4C and Figure 4-figure supplement 1B). Consider the context

1 scenario in the discrete case. In step 1, pulse inputs of size A_1 and A_2 are placed in the inp_1 and

inp_2 slots, respectively. In step 2, information flows to the intermediate slots, with $E_{inp_1 \to iv_1} A_1$ in

the iv_1 slot and $E_{inp_2 \to iv_2} A_2$ in the iv_2 slot. In step 3, only the information in the iv_1 slot flows

to the dv slot, with the information content being $E_{inp_1 \to iv_1} E_{iv_1 \to dv} A_1$ (Figure 4D, top panel). The

scenario in context 2 is similar to context 1, except that only the content from the iv_2 slot reaches

the dv slot in the third step, with the content being $E_{inp_2 \to iv_2} E_{iv_2 \to dv} A_2$ (Figure 4D, bottom panel).

The continuous dynamics for each task variable given pulse input is displayed in Figure 4-figure

supplement 2, D and E.

Together, this pathway-based information flow analysis provides an in-depth understanding of how

the input information can be routed to the accumulator depending on the context, laying the

foundation for a novel pathway-based information flow definition of selection vector and input

contextual modulations.

Information flow-based definition of selection vector modulation and selection vector for more

general cases

Based on the understanding gained from the pathway-based information flow analysis, we now

provide a novel definition of input modulation and selection vector modulation distinct from the one

in Eq. 1. To begin with, we first considered a model with mixed input and selection vector

modulation (Figure 5A, left), instead of studying extreme cases (i.e., one with pure input modulation

in Figure 2 and the other with pure selection vector modulation in Figure 3). In this more general

model, input information can either go directly to the decision variable (with effective coupling

$E_{inp \to dv}$) or first pass through the intermediate variables before reaching the decision variable (with

effective coupling $E_{inp \to iv}$ and $E_{iv \to dv}$ respectively). Applying the same information flow analysis,

we see that a pulse input of unit size will ultimately reach the dv slot with a magnitude of

$E_{inp \to dv} + E_{inp \to iv} E_{iv \to dv}$ (Figure 5A, right; see Methods for more details). In other words, the total

effective coupling E_{tol} from the input to the decision variable is equal to $E_{inp \to dv} + E_{inp \to iv} E_{iv \to dv}$.

Now, it is straightforward to decompose the context-dependent modulation of E_{tol} in terms of input

or selection vector change:

$$\Delta E_{tol} = \left(\Delta E_{inp \to dv} + \Delta E_{inp \to iv} \bar{E}_{iv \to dv} \right) + \left(\bar{E}_{inp \to iv} \Delta E_{iv \to dv} \right), \qquad (Eq. 5)$$

in which the first component $\Delta E_{inp \to dv} + \Delta E_{inp \to iv} \bar{E}_{iv \to dv}$ stands for the change of input

representation (termed as input modulation) and the second component $\bar{E}_{inp \to iv} \Delta E_{iv \to dv}$ is the one

without changing the stimulus input representation (termed as selection vector modulation).

We then asked if this pathway-based definition is equivalent to the one in Eq. 1 based on linearized

dynamical system analysis (Figure 5B; Pagan et al., 2022). To answer this question, we numerically

compared these two definitions using a family of models with both input and selection vector

modulations (Figure 5C; see Methods for model details) and found that these two definitions

produced the same proportion of selection vector modulation across a wide range of parameter

regimes (Figure 5D). Together with theoretical derivation of equivalence (see Methods), this

consistency confirmed the validity of our pathway-based definition of contextual modulation

decomposition.

Having elucidated the pathway-based definitions of input and selection vector modulation, we next

provide a novel pathway-based definition of selection vector. For the network depicted in Figure 5A,

the total effective coupling $E_{inp \to dv} + E_{inp \to iv} E_{iv \to dv}$ can be rewritten as $\langle \tilde{I}, n_{tol} \rangle$, where $\tilde{I}$ is the

input representation direction and $n_{tol} = n_{dv} + \langle \tilde{m}_{iv}, n_{dv} \rangle n_{iv}$. This reformulation aligns with the

insight that the amount of input information that can be integrated by the accumulator is determined

by the dot product between the input representation direction $\tilde{I}$ and the selection vector. Thus, n_{tol}

is the selection vector of the circuit in Figure 5A.

Figure 5. A novel pathway-based definition of selection vector modulation.

(A) A pathway-based decomposition of contextual modulation in a model with both input and selection vector modulations. This definition is based on an explicit formula of the effective connection from the input variable to the decision variable in the model (i.e., $E_{inp \to dv} + E_{inp \to iv}E_{iv \to dv}$; see Method for details). The input modulation component is then defined as the modulation induced by the change of the input representation direction across contexts. The remaining component is then defined as the selection vector modulation one.

(B) Illustration of contextual modulation decomposition introduced in Pagan et al., 2022. In this definition, the selection vector has to be first reverse-engineered through linearized dynamical systems analysis. The input modulation component is then defined as the modulation induced by

the change of input representation direction across contexts while the selection vector modulation
component is defined as the one induced by the change of the selection vector across contexts.
(C) A family of handcrafted RNNs with both input and selection vector modulations. α, β, and η
represent the associated effective coupling between task variables. In this model family, the
$inp \to dv$ pathway, susceptible to the input modulation, is parameterized by α while the $inp \to$
$iv \to dv$ pathway, susceptible to the selection vector modulation, is parameterized by β and η.
As such, the ratio of the input modulation to the selection vector modulation can be conveniently
controlled by adjusting α, β, and η.
(D) Comparison of pathway-based definition in (A) with the classical definition in (B) using the
model family introduced in (C).

To better understand why selection vector has such a formula, we visualized the information

propagation from input to the choice axis using a low-rank matrix (Figure 6A). Specifically, it

comprises two components, each corresponding to a distinct pathway. For the first component, input

information is directly selected by $\boldsymbol{n}_{dv}$. For the second component, input information is sent first to

the intermediate variable and then to the decision variable. This pathway involves two steps: in the

first step, the input representation vector is selected by $\boldsymbol{n}_{iv}$, and in the second step, to arrive at the

choice axis, the selected information has to be multiplied by the effective coupling $E_{iv \to dv} =$

$\langle \widetilde{\boldsymbol{m}}_{iv}, \boldsymbol{n}_{dv} \rangle$. By concatenating these two steps, information propagation from the input to the choice

axis in this pathway can be effectively viewed as a selection process mediated by the vector

$\langle \widetilde{\boldsymbol{m}}_{iv}, \boldsymbol{n}_{dv} \rangle \boldsymbol{n}_{iv}$ (termed as the second-order selection vector component). Therefore, $\boldsymbol{n}_{tol}$ provides a

novel pathway-based definition of selection vector in the network. We further verified the

equivalence between this pathway-based definition and the linearized-dynamical-systems-based

classical definition (Mante et al., 2013) in our simple circuit through theoretical derivation (see

Methods) and numerical comparison (Figure 6B).

Figure 6. An explicit pathway-based formula of selection vector.
(A) Illustration of how an explicit pathway-based formula of selection vector is derived. In a model
with both the first-order selection pathway (i.e., $inp \to dv$) and the second-order selection
pathway (i.e., $inp \to iv \to dv$), the second-order pathway can be reduced to a pathway with the
effective selection vector $\langle \widetilde{m}_{iv}, n_{dv} \rangle n_{iv}$ that exhibited the contextual dependency missing in
rank-1 models.
(B) Comparison between this pathway-based selection vector and the classical one (Mante et al.,
2013) using 1,000 RNNs.
(C) The connection between our understanding and the classical understanding in neural state space.
Based upon the explicit formula of selection vector in (A), the selection vector modulation has to
rely on the contextual modulation of additional representation direction (i.e., $\widetilde{m}_{iv}$) orthogonal to
both the input representation direction ($\widetilde{I}_{inp}$) and decision variable representation direction ($\widetilde{m}_{dv}$,
line attractor). Therefore, it requires at least three dimensions (i.e., $\widetilde{I}_{inp}$, $\widetilde{m}_{dv}$, and $\widetilde{m}_{iv}$) to
account for the selection vector modulation in neural state space.

To visualize the pathway-based selection vector in neural activity state space, we found that a

minimum of three dimensions is required, including the input representation direction, the decision

variable representation direction and the intermediate variable representation direction (Figure 6C,

left). This geometric visualization highlighted the role of extra-dimensions beyond the classical two-

dimensional neural activity space spanned by the line attractor and selection vector (Figure 6C, right)

in accounting for the selection vector modulation. This is simply because only the second-order

selection vector component, which depends on the existence of the intermediate variable, is subject

to contextual modulation. In other words, without extra-dimensions to support intermediate variable

encoding, there will be no selection modulation.

Together, this set of analysis provided a parsimonious pathway-based understanding for both

selection vector and its contextual modulation.

Model prediction verification with vanilla RNN models

The new insights obtained from our new framework enable us to generate testable predictions for

better differentiating selection vector modulation from input modulation, a major challenge

unresolved in the field (Pagan et al., 2022).

Figure 7. The correlation between the dimensionality of neural dynamics and the proportion of selection vector modulation is confirmed in vanilla RNNs.

(A) A general neural circuit model of CDM. In this model, there are multiple pathways capable of propagating the input information to the decision variable slot, of which the blue connections are susceptible to the input modulation while the green connections are susceptible to the selection vector modulation (see Methods for details).

(B) The explicit formula of both the effective connection from the input variable to the decision variable and the effective selection vector for the model in (A).

(C) The setting of vanilla RNNs trained to perform the CDM task. See Methods for more details.

(D) Positive correlation between effective connectivity dimension and proportion of selection vector modulation. Given a trained RNN with matrix J, the effective connectivity dimension, defined by

$\sum_{i=1}^{n} \sigma_i^2 / \sigma_1^2$ where $\sigma_1 \geq \sigma_2 \geq \cdots \geq \sigma_n$ are singular values of J, is used to quantify the

connectivity dimensionality. Spearman's rank correlation, r=0.919, p<1e-3, n=3,892. The x-axis

is displayed in log-scale.

(E) Single neuron response kernels for two example RNNs. The neuron response kernels were

calculated using a regression method (Pagan et al., 2022; see Methods for details). For simplicity,

only response kernels for input 1 are displayed. *Top*: Response kernels for two example neurons

in the RNN with low effective dimension (indicated by a star marker in panel D). Two typical

response kernels, including the decision variable profile (left) and the sensory input profile

(right), are displayed. *Bottom*: Response kernels for three example neurons in the RNN with high

effective dimension (indicated by a square marker in panel D). In addition to the decision

variable profile (left) and sensory input profile (middle), there are neurons whose response

kernels initially increase and then decrease (right). Gray lines, response kernels in context 1 (i.e.,

rel. ctx.). Blue lines, response kernels in context 2 (i.e., irrel. ctx.).

(F) Principal dynamical modes for response kernels in the population level extracted by singular

value decomposition. *Left*: Shared dynamical modes including one persistent choice mode (grey)

and three transient modes (blue, orange, green) are identified across both RNNs. *Right*:   For the

i-th transient mode, the normalized percentage of explained variance (PEV) is given by

$\sigma_i^2 / \sum_{j=1}^{39} \sigma_j^2$, where $\sigma_1 \geq \sigma_2 \geq \cdots \geq \sigma_{39}$ are singular values for each transient mode (see

Methods for details).

(G) Positive correlation between response-kernel-based index and proportion of selection vector

modulation. For a given RNN, PEV of extra dynamical modes is defined as the accumulated

normalized PEV of the second and subsequent transient dynamical modes (see Methods for

details). Spearman's rank correlation, r=0.902, p<1e-3, n=3,892. The x-axis is displayed in log-

scale.

First, we predict that it is more likely to have a large proportion of selection vector modulation for a

neural network with high-dimensional connectivity. To better explain the underlying rationale, we

can simply compare the number of potential connections contributing to the input modulation with

those contributing to the selection vector modulation for a given neural network model. For example,

in the network presented in Figure 5, there are three connections (including light blue, dark blue and

green ones) while only one connection (i.e., the green one) supporting selection vector modulation.

For a circuit with many higher-order pathways (e.g., Figure 7A), only those connections with the

input as the sender is able to support input modulation. In other words, there exist far more

connections potentially eligible to support the selection vector modulation (Figure 7B), thereby

leading to a large selection vector modulation proportion. We then tested this prediction on vanilla

RNNs trained through backpropagation (Figure 7C; Mante et al., 2013; Song et al., 2016; Yang &

Wang, 2020). Using effective dimension (see Methods for a formal definition; Rudelson &

Vershynin, 2007; Sanyal et al., 2020) to quantify the dimensionality of the connectivity matrix, we

found a strong positive correlation between the effective dimension of connectivity matrix and the

selection vector modulation (Figure 7D, left panel and Figure 7-figure supplement 1A).

We then asked if we could generate predictions to quantify the proportion of selection vector

modulation purely based on neural activities. To this end, as what has been performed in Pagan et al.,

we took advantage of the pulse-based sensory input setting to calculate the single neuron response

kernel (see Methods for details). For a given neuron, the associated response kernel is defined to

characterize the influence of a pulse input on its firing rate in later times. For example, for a neuron

encoding the decision variable, the response kernel should exhibit a profile accumulating evidence

over time (Figure 7E, top left). In contrast, for a neuron encoding the sensory input, the response

kernel should exhibit an exponential decay profile with time constant τ (Figure 7E, top right). For

each RNN trained through backpropagation, we then examined the associated single neuron response

kernels. We found that for the model with low effective dimension (denoted by a star marker in

Figure 7D), there were mainly two types of response kernels, including sensory input profile and

decision variable profile (Figure 7E, top). In contrast, for the model with the highest effective

dimension (denoted by a square marker in Figure 7D), aside from the sensory input and decision

variable profiles, richer response kernel profiles were exhibited (Figure 7E, bottom). In particular,

there was a set of single neuron response kernels with peak amplitudes occurring between the pulse

input onset and the choice onset (Figure 7E, bottom right). These response kernels cannot be

explained by the combination of sensory input and decision variable. Instead, the existence of these

response kernels signifies neural dynamics in extra-dimensions beyond the subspaces spanned by the

input and decision variable, the genuine neural dynamical signature of the existence of selection

vector modulation (Figure 6C).

While single neuron response kernels are illustrative in highlighting the model difference, they lack

explanatory power at the population level. Therefore, we employed the singular value decomposition

method to extract the principal dynamical modes of response kernels at the population level (see

Methods for details). We found that similar dynamical modes, including one persistent choice mode

(grey) and three transient modes (blue, orange, green), were shared across both the low and high

effective dimension models (Figure 7F, left). The key difference between these two models lies in the

percentage of explained variance (PEV) of the second transient mode (orange): while there is near-

zero PEV in the low effective dimension model (Figure 7F, top right), there is a substantial PEV in

the high effective dimension model (Figure 7F, bottom right), consistent with the single neuron

picture shown in Figure 7E. This result led us to use the PEV of extra dynamical modes (including

the orange and green ones; see Methods for details) as a simple index to quantify the amount of

selection vector modulation in these models. As expected, we found that the PEV of extra dynamical

modes can serve as a reliable index reflecting the proportion of selection vector modulation in these

models (Figure 7G, right panel and Figure 7-figure supplement 1, B and C). Similar results for

vanilla RNNs trained with different hyperparameter settings are displayed in Figure 7-figure

supplement 2.

Together, we identified novel neural dynamical signatures of section vector modulation at both the

single neuron and population level, suggesting that the potential great utility of these neural

dynamical signatures in distinguishing the contribution of selection vector modulation from input

modulation in experimental data.

Discussion

Using low-rank RNNs, we provided a rigorous theoretical framework linking network connectivity,

neural dynamics, and selection mechanisms, and gained an in-depth algebraic and geometric

understanding of both input and selection vector modulation mechanisms, and accordingly uncovered

a previously unknown link between selection vector modulation and extra-dimensions in neural state

space. This gained understanding enabled us to generate novel predictions linking novel neural

dynamic modes with the proportion of selection vector modulation, paving the way towards

addressing the intricacy of neural variability across subjects in context-dependent computation.

A pathway-based definition of selection vector modulation

In their seminal work, Mante, Sussillo, and their collaborators developed a numerical approach to

compute the selection vector for trained RNN models (Mante et al., 2013). Based on this concept of

selection vector, recently, Pagan et al. proposed a new theoretical framework to decompose the

solution space of context-dependent decision-making, in which input modulation and selection vector

modulation were explicitly defined (i.e., Eq. 1). Here, taking the theoretical advantage of low-rank

RNNs (Mastrogiuseppe & Ostojic, 2018; Dubreuil et al., 2022), we went beyond numerical reverse-

engineering and provided a complementary pathway-based definition of both selection vector and

selection vector modulation (i.e., Eq. 5). This new definition gained us a novel geometric

understanding of selection vector modulation, revealed a previously unknown link between extra

dimensions and selection vector modulation (Figure 6C), and eventually provided us experimentally

identifiable neural dynamical signature of selection vector modulation at both the single neuron and

population levels (Figure 7, E-G).

Individual neural variability in higher cognition

One hallmark of higher cognition is individual variability, as the same higher cognition problem can

be solved equally well with different strategies. Therefore, studying the neural computations

underlying individual variability is no doubt of great importance (Hariri, 2009; Parasuraman & Jiang,

2012; Keung et al., 2020; Nelli et al., 2023). Recent experimental advances enabled researchers to

investigate this important issue in a systematic manner using delicate behavioral paradigms and large-

scale recordings (Pagan et al., 2022). However, the computation underlying higher cognition is largely

internal, requiring discovering novel neural activity patterns as internal indicators to differentiate

distinct circuit mechanisms. In the example of context-dependent decision-making studied here, to

differentiate selection vector modulation from input modulation, we found the PEV in extra dynamical

modes is a reliable index for a wide variety of RNNs (Figure 7D and Figure 7-figure supplement 2).

However, cautions have be made here as we can conveniently construct counter-examples deviating

from the picture depicted by this index. In fact, in the extreme scenario, we can construct two models

with distinct circuit mechanisms (selection vector modulation and input modulation, respectively) but

having the same neural activities (Figure 7-figure supplement 3), suggesting that any activity-based

index alone would fail to make this differentiation. Therefore, our modeling work suggests that, to

address the intricacy of individual variability of neural computations underlying higher cognition,

integrative efforts incorporating not only large-scale neural activity recordings but also activity

perturbations, neuronal connectivity knowledge and computational modeling may be inevitably

required.

Beyond context-dependent decision making

While we mainly focused on context-dependent decision-making task in this study, the issue of

whether input or selection vector modulation prevails is not limited to the domain of decision-making.

For instance, recent work (Chen et al., 2024) demonstrated that during sequence working memory

control (Botvinick & Watanabe, 2007; Xie et al., 2022), sensory inputs presented at different ordinal

ranks first entered into a common sensory subspace and then were routed to the corresponding rank-

specific working memory subspaces in monkey frontal cortex. Here, similar to the decision-making

case (Figure 1C), the same issue arises: where is the input information selected by the context (here,

the ordinal rank)? Can the presence of a common sensory subspace (similar to the presence of location

information in both relevant and irrelevant contexts in Figure 1C) preclude the input modulation? The

pathway-based understanding of input and selection vector modulation gained from CDM in this study

may be transferable to address these similar issues.

The role of transient dynamics in extra-dimensions in context-dependent computation

In this study, we linked the selection vector modulation with transient dynamics (Aoi et al., 2020;

Soldado-Magraner et al., 2023) in extra-dimensions. While the transient dynamics in extra-dimensions

is not necessary in context-dependent decision-making here (Dubreuil et al., 2022; Figure 2), more

complex context-dependent computation may require its presence. For example, recent work (Tian et

al., 2024) found that transient dynamics in extra subspaces is required to perform the switch operation

(i.e., exchanging information in subspace 1 with information in subspace 2). Understanding how

transient dynamics in extra-dimensions contribute to complex context-dependent computation

warrants further systematic investigation.

In summary, through low-rank neural network modeling, our work provided a parsimonious

mechanistic account for how information can be selected along different pathways, making

significant contributions towards understanding the intriguing selection mechanisms in context-

dependent computation.

Aoi, M. C., Mante, V., & Pillow, J. W. (2020). Prefrontal cortex exhibits multidimensional dynamic encoding during decision-making. *Nature Neuroscience*, *23*(11), 1410–1420. https://doi.org/10.1038/s41593-020-0696-5

Badre, D., Bhandari, A., Keglovits, H., & Kikumoto, A. (2021). The dimensionality of neural representations for control. *Current Opinion in Behavioral Sciences*, *38*, 20–28. https://doi.org/10.1016/j.cobeha.2020.07.002

Barbosa, J., Proville, R., Rodgers, C. C., DeWeese, M. R., Ostojic, S., & Boubenec, Y. (2023). Early selection of task-relevant features through population gating. *Nature Communications*, *14*(1), 6837. https://doi.org/10.1038/s41467-023-42519-5

Beiran, M., Dubreuil, A., Valente, A., Mastrogiuseppe, F., & Ostojic, S. (2021). Shaping Dynamics With Multiple Populations in Low-Rank Recurrent Networks. *Neural Computation*, *33*(6), 1572–1615. https://doi.org/10.1162/neco_a_01381

Beiran, M., Meirhaeghe, N., Sohn, H., Jazayeri, M., & Ostojic, S. (2023). Parametric control of flexible timing through low-dimensional neural manifolds. *Neuron*, 111(5), 739-753.e8. https://doi.org/10.1016/j.neuron.2022.12.016

Bernardi, S., Benna, M. K., Rigotti, M., Munuera, J., Fusi, S., & Salzman, C. D. (2020). The Geometry of Abstraction in the Hippocampus and Prefrontal Cortex. *Cell*, *183*(4), 954-967.e21. https://doi.org/10.1016/j.cell.2020.09.031

Botvinick, M., & Watanabe, T. (2007). From Numerosity to Ordinal Rank: A Gain-Field Model of Serial Order Representation in Cortical Working Memory. *The Journal of Neuroscience*, *27*(32), 8636–8642. https://doi.org/10.1523/JNEUROSCI.2110-07.2007

Chen, J., Zhang, C., Hu, P., Min, B., & Wang, L. (2024). Flexible control of sequence working memory in the macaque frontal cortex. *Neuron*, 112, 1-13. https://doi.org/10.1016/j.neuron.2024.07.024

Cohen, J. D. (2017). Cognitive Control: Core Constructs and Current Considerations. In T. Egner (Ed.),

The Wiley Handbook of Cognitive Control (1st ed., pp. 1–28). Wiley.

https://doi.org/10.1002/9781118920497.ch1

Desimone, R., & Duncan, J. (1995). Neural mechanisms of selective visual attention. *Annual Review*

of Neuroscience, *18*, 193–222. https://doi.org/10.1146/annurev.ne.18.030195.001205

Dubreuil, A., Valente, A., Beiran, M., Mastrogiuseppe, F., & Ostojic, S. (2022). The role of population

structure in computations through neural dynamics. *Nature Neuroscience*, *25*(6), 783–794.

https://doi.org/10.1038/s41593-022-01088-4

Flesch, T., Juechems, K., Dumbalska, T., Saxe, A., & Summerfield, C. (2022). Orthogonal

representations for robust context-dependent task performance in brains and neural networks.

Neuron, *110*(7), 1258-1270.e11. https://doi.org/10.1016/j.neuron.2022.01.005

Fusi, S., Miller, E. K., & Rigotti, M. (2016). Why neurons mix: High dimensionality for higher

cognition. *Current Opinion in Neurobiology*, *37*, 66–74.

https://doi.org/10.1016/j.conb.2016.01.010

Hariri, A. R. (2009). The Neurobiology of Individual Differences in Complex Behavioral Traits.

Annual Review of Neuroscience, *32*, 225–247.

https://doi.org/10.1146/annurev.neuro.051508.135335

Kadmon, J., Timcheck, J., & Ganguli, S. (2020). Predictive coding in balanced neural networks with

noise, chaos and delays. *Advances in Neural Information Processing Systems*, *33*, 16677–

16688.

https://proceedings.neurips.cc/paper/2020/hash/c236337b043acf93c7df397fdb9082b3-

Abstract.html

Keung, W., Hagen, T. A., & Wilson, R. C. (2020). A divisive model of evidence accumulation explains

uneven weighting of evidence over time. *Nature Communications*, *11*(1), 2160.

https://doi.org/10.1038/s41467-020-15630-0

Landau, I. D., & Sompolinsky, H. (2018). Coherent chaos in a recurrent neural network with structured connectivity. *PLOS Computational Biology*, *14*(12), e1006309. https://doi.org/10.1371/journal.pcbi.1006309

Maheswaranathan, N., & Sussillo, D. (2020). How recurrent networks implement contextual processing in sentiment analysis. *Proceedings of the 37th International Conference on Machine Learning*, 6608–6619. https://proceedings.mlr.press/v119/maheswaranathan20a.html

Maheswaranathan, N., Williams, A., Golub, M., Ganguli, S., & Sussillo, D. (2019). Reverse engineering recurrent networks for sentiment classification reveals line attractor dynamics. *Advances in Neural Information Processing Systems*, *32*. https://proceedings.neurips.cc/paper_files/paper/2019/hash/d921c3c762b1522c475ac8fc0811 bb0f-Abstract.html

Mante, V., Sussillo, D., Shenoy, K. V., & Newsome, W. T. (2013). Context-dependent computation by recurrent dynamics in prefrontal cortex. *Nature*, *503*(7474), 78–84. https://doi.org/10.1038/nature12742

Mastrogiuseppe, F., & Ostojic, S. (2018). Linking Connectivity, Dynamics, and Computations in Low-Rank Recurrent Neural Networks. *Neuron*, *99*(3), 609-623.e29. https://doi.org/10.1016/j.neuron.2018.07.003

Miller, E. K., & Cohen, J. D. (2001). An Integrative Theory of Prefrontal Cortex Function. *Annual Review of Neuroscience*, *24*(1), 167–202. https://doi.org/10.1146/annurev.neuro.24.1.167

Nair, A., Karigo, T., Yang, B., Ganguli, S., Schnitzer, M. J., Linderman, S. W., Anderson, D. J., & Kennedy, A. (2023). An approximate line attractor in the hypothalamus encodes an aggressive state. *Cell*, *186*(1), 178-193.e15. https://doi.org/10.1016/j.cell.2022.11.027

Nelli, S., Braun, L., Dumbalska, T., Saxe, A., & Summerfield, C. (2023). Neural knowledge assembly in humans and neural networks. *Neuron*, *111*(9), 1504-1516.e9. https://doi.org/10.1016/j.neuron.2023.02.014

Noudoost, B., Chang, M. H., Steinmetz, N. A., & Moore, T. (2010). TOP-DOWN CONTROL OF
VISUAL ATTENTION. *Current Opinion in Neurobiology*, *20*(2), 183–190.
https://doi.org/10.1016/j.conb.2010.02.003

Okazawa, G., & Kiani, R. (2023). Neural Mechanisms That Make Perceptual Decisions Flexible.
Annual Review of Physiology, *85*(1), 191–215. https://doi.org/10.1146/annurev-physiol-
031722-024731

Ostojic, S., & Fusi, S. (2024). Computational role of structure in neural activity and connectivity.
Trends in Cognitive Sciences, *28*(7), 677–690. https://doi.org/10.1016/j.tics.2024.03.003

Pagan, M., Tang, V. D., Aoi, M. C., Pillow, J. W., Mante, V., Sussillo, D., & Brody, C. D. (2022). *A*
new theoretical framework jointly explains behavioral and neural variability across subjects
performing flexible decision-making [Preprint]. Neuroscience.
https://doi.org/10.1101/2022.11.28.518207

Pagan, M., Valente, A., Ostojic, S., & Brody, C. D. (2023). *Brief technical note on linearizing recurrent*
neural networks (RNNs) before vs after the pointwise nonlinearity (arXiv:2309.04030). arXiv.
http://arxiv.org/abs/2309.04030

Parasuraman, R., & Jiang, Y. (2012). Individual differences in cognition, affect, and performance:
Behavioral, neuroimaging, and molecular genetic approaches. *NeuroImage*, *59*(1), 70–82.
https://doi.org/10.1016/j.neuroimage.2011.04.040

Roy, J. E., Riesenhuber, M., Poggio, T., & Miller, E. K. (2010). Prefrontal Cortex Activity during
Flexible Categorization. *Journal of Neuroscience*, *30*(25), 8519–8528.
https://doi.org/10.1523/JNEUROSCI.4837-09.2010

Rudelson, M., & Vershynin, R. (2007). Sampling from large matrices: An approach through geometric
functional analysis. *Journal of the ACM*, *54*(4), 21. https://doi.org/10.1145/1255443.1255449

Saez, A., Rigotti, M., Ostojic, S., Fusi, S., & Salzman, C. D. (2015). Abstract Context Representations in Primate Amygdala and Prefrontal Cortex. *Neuron*, *87*(4), 869–881. https://doi.org/10.1016/j.neuron.2015.07.024

Sanyal, A., Dokania, P. K., & Torr, P. H. (2020). *STABLE RANK NORMALIZATION FOR IMPROVED GEN- ERALIZATION IN NEURAL NETWORKS AND GANS*.

Schuessler, F., Dubreuil, A., Mastrogiuseppe, F., Ostojic, S., & Barak, O. (2020). Dynamics of random recurrent networks with correlated low-rank structure. *Physical Review Research*, *2*(1), 013111. https://doi.org/10.1103/PhysRevResearch.2.013111

Siegel, M., Buschman, T. J., & Miller, E. K. (2015). Cortical information flow during flexible sensorimotor decisions. *Science (New York, N.Y.)*, *348*(6241), 1352–1355. https://doi.org/10.1126/science.aab0551

Soldado-Magraner, J., Mante, V., & Sahani, M. (2023). Inferring context-dependent computations through linear approximations of prefrontal cortex dynamics. *Neuroscience*. https://doi.org/10.1101/2023.02.06.527389

Song, H. F., Yang, G. R., & Wang, X.-J. (2016). Training Excitatory-Inhibitory Recurrent Neural Networks for Cognitive Tasks: A Simple and Flexible Framework. *PLOS Computational Biology*, *12*(2), e1004792. https://doi.org/10.1371/journal.pcbi.1004792

Sussillo, D., & Barak, O. (2013). Opening the Black Box: Low-Dimensional Dynamics in High-Dimensional Recurrent Neural Networks. *Neural Computation*, *25*(3), 626–649. https://doi.org/10.1162/NECO_a_00409

Takagi, Y., Hunt, L. T., Woolrich, M. W., Behrens, T. E., & Klein-Flügge, M. C. (2021). Adapting non-invasive human recordings along multiple task-axes shows unfolding of spontaneous and over-trained choice. *eLife*, *10*, e60988. https://doi.org/10.7554/eLife.60988

Tian, Z., Chen, J., Zhang, C., Min, B., Bo, X., & Wang, L. (2024). Mental Programming of Spatial Sequences in Working Memory in Macaque Frontal Cortex. Science, in press

Valente, A., Ostojic, S., & Pillow, J. W. (2022). Probing the Relationship Between Latent Linear

Dynamical Systems and Low-Rank Recurrent Neural Network Models. *Neural Computation*,

34(9), 1871–1892. https://doi.org/10.1162/neco_a_01522

Xie, Y., Hu, P., Li, J., Chen, J., Song, W., Wang, X.-J., Yang, T., Dehaene, S., Tang, S., Min, B., &

Wang, L. (2022). Geometry of sequence working memory in macaque prefrontal cortex.

Science, *375*(6581), 632–639. https://doi.org/10.1126/science.abm0204

Yang, G. R., & Wang, X.-J. (2020). Artificial Neural Networks for Neuroscientists: A Primer. *Neuron*,

107(6), 1048–1070. https://doi.org/10.1016/j.neuron.2020.09.005

The general form of RNNs

We investigated networks of N neurons with S input channels, described by the following temporal evolution equation

$$\tau \frac{dx_i(t)}{dt} = -x_i(t) + \sum_{j=1}^{N} J_{ij}\phi\left(x_j(t)\right) + \sum_{s=1}^{S} I_{si}\, u_s(t) + \epsilon_i(t). \tag{1}$$

In this equation, $x_i(t)$ represents the activation of neuron i at time t, τ denotes the characteristic time constant of a single neuron, and ϕ is a nonlinear activation function. Unless otherwise specified, we use the tanh function as the activation function. The coefficient J_{ij} represents the connectivity weight from neuron j to neuron i. The input $u_s(t)$ corresponds to the s-th input channel at time t, with feedforward weight I_{si} to neuron i, and $\epsilon_i(t)$ represents white noise at time t. The network's output is obtained from the neuron's activity $\phi(x)$ through a linear projection:

$$z(t) = \frac{1}{N} \sum_{i=1}^{N} w_i \phi(x_i). \tag{2}$$

The connectivity matrix J, specified as $J = \{J_{ij}\}, i = 1, \ldots, N, j = 1, \ldots, N$, can be a low-rank or a full-rank matrix. In the low-rank case, J is restricted to a low-rank matrix $\frac{1}{N}\sum_{r=1}^{R} \boldsymbol{m}_r \boldsymbol{n}_r^T$, in which $\boldsymbol{m}_r$ is the r-th *output vector*, and $\boldsymbol{n}_r$ is the r-th *input-selection vector*, with each element of $\boldsymbol{m}_r$ and $\boldsymbol{n}_r$ considered an independent parameter (Dubreuil et al., 2022). In this paper, we set the time constant τ to be 100 ms, and use Euler's method to discretize the evolution equation with a time step $\Delta t = 20$ ms.

Task setting

We modeled the click-version CDM task recently investigated by (Pagan et al., 2022). The task involves four input channels $u_1(t)$, $u_2(t)$, $u_1^{ctx}(t)$, and $u_2^{ctx}(t)$, where $u_1(t)$ and $u_2(t)$ are stimulus inputs and $u_1^{ctx}(t)$ and $u_2^{ctx}(t)$ are context inputs. Initially, there is a fixation period lasting for $T_{fix} = 200$ ms. This is followed by a stimulus period of $T_{sti} = 800$ ms and then a decision period of $T_{decision} = 20$ ms.

For trial k, at each time step, the total number of pulse inputs (#pulse) is sampled from a Poisson distribution with a mean value of $40\Delta t = 0.8$. Each pulse has two properties: location and frequency. Location can be either left or right, and frequency can be either high or low. We randomly sample a pulse to be right with probability p_{right}^k (hence left with probability $1 -$

p_{right}^k) and to be high with probability p_{high}^k (hence low with probability $1 - p_{high}^k$). The

values of p_{right}^k and p_{high}^k are independently chosen from the set {39/40, 35/40, 25/40, 15/40,

5/40, 1/40}. The stimulus strength for the location input at trial k is defined as $2 \times p_{right}^k - 1$,

and for the frequency input, it is defined as $2 \times p_{high}^k - 1$. The input $u_1(t)$ represents location

evidence, calculated as 0.1 times the difference between the number of right pulses and the

number of left pulses (#right-#left) at time step t. The input $u_2(t)$ represents frequency

evidence, calculated as 0.1 times the difference between the number of high-frequency pulses

and the number of low-frequency pulses (#high-#low) at time step t.

The context is randomly chosen to be either the location context or the frequency context. In the

location context, $u_1^{ctx} = 1$ and $u_2^{ctx} = 0$ throughout the entire period. The target output z_k is

defined as the sign of the location stimulus strength (1 if $p_{right}^k > 0.5$, otherwise -1). Thus, in

this context, the target output z_k is independent of the frequency stimulus input. Conversely, in

the frequency context, $u_1^{ctx} = 0$ and $u_2^{ctx} = 1$. The target output z_k is defined as the sign of

the frequency stimulus strength (1 if $p_{high}^k > 0.5$, otherwise -1). Thus, in this context, the target

output is independent of the location stimulus input.

Linearized dynamical system analysis (Figure 1)

To uncover the computational mechanism enabling each RNN to perform context-dependent

evidence accumulation, we utilize linearized dynamical system analysis to "open the black box"

(Mante et al., 2013). The dynamical evolution of an RNN in context c is given by:

$$\tau \frac{d\boldsymbol{x}}{dt} = -\boldsymbol{x} + J\boldsymbol{r} + \boldsymbol{I}_1 u_1 + \boldsymbol{I}_2 u_2 + \boldsymbol{I}_c^{ctx}, \tag{3}$$

811   where $\boldsymbol{r} = \phi(\boldsymbol{x})$ is the neuron activity. First, we identify the slow point of each RNN in each

812   context using an optimization method (Mante et al., 2013). Let $\boldsymbol{x}^*$ be the discovered slow point,

813   i.e., $\boldsymbol{x}^* \approx J\boldsymbol{r}^* + \boldsymbol{I}_c^{ctx}$ where $\boldsymbol{r}^* = \phi(\boldsymbol{x}^*)$. We define a diagonal matrix $G = \text{diag}(\phi'(\boldsymbol{x}^*))$, with

814   the i-th diagonal element representing the sensitivity of the i-th neuron at the slow point. Near

815   the slow point, we have $\Delta\boldsymbol{r} = \boldsymbol{r} - \boldsymbol{r}^* \approx G\phi'(\Delta\boldsymbol{x})$. Then, we can derive:

$$\tau \frac{d\Delta\boldsymbol{r}}{dt} \approx \tau G \frac{d\Delta\boldsymbol{x}}{dt} = -\Delta\boldsymbol{r} + GJ\Delta\boldsymbol{r} + G\boldsymbol{I}_1 u_1 + G\boldsymbol{I}_2 u_2. \tag{4}$$

817   Thus, the dynamics of neuron activity around the slow point can be approximated by a linear

818   dynamical system:

$$819 \qquad \tau\frac{d\Delta r}{dt} = M\Delta r + \tilde{I}_1 u_1 + \tilde{I}_2 u_2, \qquad (5)$$

$$820 \qquad M = -E + GJ, \qquad (6)$$

where E is the identity matrix, M denotes the state transition matrix of the dynamical system,

and $\tilde{I}_r = GI_r, r = 1,2$ are stimulus *input representation directions*. Similar to previous work

(Mante et al., 2013), we find that for every network, the linear dynamical system near the slow

point in each context is roughly a linear attractor. Specifically, the transition matrix M has a

single eigenvalue close to zero, while all other eigenvalues have negative real parts. The right

eigenvector of M associated with the eigenvalue close to zero defines the stable direction of the

dynamical system, forming the line attractor ρ (unit norm). The left eigenvector of M

associated with that eigenvalue defines the direction of the selection vector s. The norm of

selection vector s is chosen such that $s \cdot \rho = 1$. Previous work (Mante et al., 2013) has shown

that a perturbation Δr_0 from the line attractor will eventually converge to the line attractor, with

the distance from the starting point being $s \cdot \Delta r_0$.

Based on linearized dynamical systems analysis, Pagan et al. recently defined **input modulation**

and **selection vector modulation** (Pagan et al., 2022) as:

$$834 \qquad mod_{inp} = \Delta GI \cdot \bar{s}, \qquad (7)$$

$$835 \qquad mod_{sel} = \overline{GI} \cdot \Delta s. \qquad (8)$$

Specifically, the input modulation and selection vector modulation for stimulus input 1 are

defined as $(s^{ctx_1} + s^{ctx_2})/2 \cdot (\tilde{I}_1^{ctx_1} - \tilde{I}_1^{ctx_2})$ and $(s^{ctx_1} - s^{ctx_2}) \cdot (\tilde{I}_1^{ctx_1} + \tilde{I}_1^{ctx_2})/2$,

respectively. Similarly, the input modulation and selection vector modulation for stimulus input 2

are defined as $(s^{ctx_1} + s^{ctx_2})/2 \cdot (\tilde{I}_2^{ctx_2} - \tilde{I}_2^{ctx_1})$ and $(s^{ctx_2} - s^{ctx_1}) \cdot (\tilde{I}_2^{ctx_1} + \tilde{I}_2^{ctx_2})/2$,

respectively.

Training of rank-1 RNNs using backpropagation (Figure 2)

The rank-1 RNNs in Figure 2 are trained using backpropagation-through-time with the PyTorch

framework. These networks are trained to minimize a loss function defined as:

$$844 \qquad L = \sum_{k,t} M_t \left(\hat{z}_{k,t} - z_k\right)^2 + L_{reg}. \qquad (9)$$

Here, z_k is the target output, $\hat{z}_{k,t}$ is the network output, and the indices t and k represent

time and trial, respectively. M_t is a temporal mask with value $\{0, 1\}$, where M_t is 1 only

during the decision period. L_{reg} is the L2 regularization loss. For full-rank RNNs (Figure 7),

$L_{reg} = w_{reg} \sum_{ij} J_{ij}^2$ and for low-rank RNNs, $L_{reg} = w_{reg} \sum_r (\|\boldsymbol{m}_r\|_2^2 + \|\boldsymbol{n}_r\|_2^2)$. The loss

function is minimized by computing gradients with respect to all trainable parameters. We use

Adam optimizer in PyTorch with the decay rates for the first and second moments set to 0.9 and

0.99, respectively, and a learning rate of 10^{-3}. Each RNN is trained for 5000 steps with a batch

size of 256 trials.

For Figure 2, we trained 100 RNNs of $N = 512$ neurons with the same training

hyperparameters. The rank of the connectivity matrix is constrained to be rank-1, represented as

$J = \frac{1}{N} \boldsymbol{m}_{dv} \boldsymbol{n}_{dv}^T$. We trained the elements of the input vectors $\boldsymbol{I}_1, \boldsymbol{I}_2, \boldsymbol{I}_1^{ctx}, \boldsymbol{I}_2^{ctx}$, connectivity vector

$\boldsymbol{m}_{dv}, \boldsymbol{n}_{dv}$, and the readout vector $\boldsymbol{w}$. All trainable parameters were initialized with random

independent Gaussian weights with a mean of 0 and a variance of $1/N^2$. The regularization

coefficient w_{reg} is set to 10^{-4}.

Proof of no selection vector modulation in rank-1 RNNs (Figure 2)

The transition matrix of neuron activity in the rank-1 RNN is given by:

$$M = -E + \frac{1}{N} G \boldsymbol{m}_{dv} \boldsymbol{n}_{dv}. \tag{10}$$

862 Multiplying M^T on the right by $\boldsymbol{n}_{dv}$, we obtain

$$M^T \boldsymbol{n}_{dv} = -\boldsymbol{n}_{dv} + \langle \widetilde{\boldsymbol{m}}_{dv}, \boldsymbol{n}_{dv} \rangle \boldsymbol{n}_{dv} \approx 0, \tag{11}$$

where the $\langle \cdot, \cdot \rangle$ symbol is defined as $\langle \boldsymbol{a}, \boldsymbol{b} \rangle = \frac{1}{N} \sum_{i=1}^N a_i b_i$ for two vectors of length-N. The

requirement for the linear attractor approximation, $\langle \widetilde{\boldsymbol{m}}_{dv}, \boldsymbol{n}_{dv} \rangle \approx 1$, is met by all our trained and

handcrafted RNNs (Figure 4-supplement figure 1). This demonstrates that $\boldsymbol{n}_{dv}$ is the left

eigenvector of the transition matrix, and hence $\frac{1}{N} \|\widetilde{\boldsymbol{m}}_{dv}\|_2 \boldsymbol{n}_{dv}$ is the selection vector in each

context. Therefore, the direction of the selection vector is invariant across different contexts for

the rank-1 model, indicating no selection vector modulation and this is consistent with the

training results shown in Figure 2.

Handcrafting rank-3 RNNs with pure selection vector modulation (Figure 3)

First, we provide the implementation details of the rank-3 RNNs used in Figure 3. The network

consists of 30,000 neurons divided into three populations, each with 10,000 neurons. The first

population (neurons 1-10,000) receives stimulus input, accounting for both the information flow

from the stimulus input to the intermediate variables and the recurrent connection of the decision

variable. The second (neurons 10,001-20,000) and third populations (neurons 20,001-30,000)

handle the information flow from the intermediate variables to the decision variable and are

modulated by the context signal. To achieve this, we generate three Gaussian random matrices

$(M^{(1)}, M^{(2)}, M^{(3)})$ of shape $10,000 \times 3$. Let $M_{:,r}^{(p)}$ denote the r-th column of matrix $M^{(p)}$. The

stimulus input I_1 is given by the concatenation of three length-10,000 vectors $\left[M_{:,1}^{(1)}; \mathbf{0}; \mathbf{0}\right]$,

where $\mathbf{0}$ denotes a length-10,000 zero vector. The stimulus input I_2 is given by $\left[M_{:,2}^{(1)}; \mathbf{0}; \mathbf{0}\right]$.

The context input I_1^{ctx} is given by $\left[\mathbf{0}; M_{:,1}^{(2)}; \mathbf{0}\right]$. The context input I_2^{ctx} is given by

$\left[\mathbf{0}; \mathbf{0}; M_{:,1}^{(3)}\right]$. The connectivity vectors $\boldsymbol{m}_{iv1}, \boldsymbol{m}_{iv2}$ and $\boldsymbol{m}_{dv}$ are given by $\left[\mathbf{0}; M_{:,2}^{(2)}; M_{:,2}^{(3)}\right]$,

$\left[\mathbf{0}; M_{:,3}^{(2)}; M_{:,3}^{(3)}\right]$ and $\left[M_{:,3}^{(1)}; \mathbf{0}; \mathbf{0}\right]$, respectively. The input-selection vectors $\boldsymbol{n}_{iv1}, \boldsymbol{n}_{iv2}$, and $\boldsymbol{n}_{dv}$

are given by $\left[10M_{:,1}^{(1)}; \mathbf{0}; \mathbf{0}\right]$, $\left[10M_{:,2}^{(1)}; \mathbf{0}; \mathbf{0}\right]$, and $\left[3M_{:,3}^{(1)}; -gM_{:,2}^{(2)} + M_{:,3}^{(2)}; M_{:,2}^{(3)} - gM_{:,3}^{(3)}\right]$,

respectively, where $g = \int_{-\infty}^{+\infty} \frac{1}{\sqrt{2\pi}} e^{-x^2/2} \phi'(x) dx$ represents the average gain of the second

population in context 1 or the third population in context 2. The readout vector $\boldsymbol{w}$ is given by

$\left[4M_{:,3}^{(1)}; \mathbf{0}; \mathbf{0}\right]$. We generate 100 RNNs based on this method to ensure that the conclusions in

Figure 3 do not depend on the specific realization of random matrices. Linearized dynamical

system analysis reveals that all these RNNs perform flexible computation through pure selection

vector modulation. Please see the section "**The construction of rank-3 RNN models**" for a

mean-field-theory-based understanding.

Pathway-based information flow graph analysis of low-rank RNNs (Figure 4)

The dynamical evolution equation for low-rank RNN with R ranks and S input channels in

context c is given by

896
$$\frac{d\boldsymbol{x}}{dt} = -\boldsymbol{x} + \frac{1}{N}\sum_{r=1}^{R} \boldsymbol{m}_r \boldsymbol{n}_r^T \phi(\boldsymbol{x}) + \sum_{s=1}^{S} I_s u_s + I_c^{ctx} \tag{12}$$

897   Assuming $\boldsymbol{x}(0) = I_c^{ctx}$ at $t = 0$, the dynamics of $\boldsymbol{x}(t) - \boldsymbol{x}(0)$ are always constrained in the

898   subspace spanned by $\{\boldsymbol{m}_r, r = 1, \dots, R\}$ and $\{I_s, s = 1, \dots, S\}$. Therefore, $\boldsymbol{x}(t)$ can be

899   expressed as a linear combination of these vectors: $\boldsymbol{x}(t) = I_c^{ctx} + \sum_{r=1}^{R} k_r(t)\boldsymbol{m}_r + $

900    $\sum_{s=1}^{S} k_{inp_s}(t) I_s$, leading to the following evolving dynamics of task variables:

901
$$\tau \frac{dk_{inp_s}(t)}{dt} = -k_{inp_s}(t) + u_s(t), \tag{13}$$

$$\tau \frac{dk_r(t)}{dt} = -k_r(t) + \frac{1}{N} \boldsymbol{n}_r^T \phi \left(\boldsymbol{I}_c^{ctx} + \sum_{j=1}^{R} k_j(t) \boldsymbol{m}_j + \sum_{s=1}^{S} k_{inp_s}(t) \boldsymbol{I}_s \right), \tag{14}$$

903 where $k_{inp_s}(t)$ denotes activation along the s-th input vector, termed the input task variable

904 and $k_r(t)$ denotes activation along the j-th output vector, termed the internal task variable.

905 **The rank-1 RNN case.** Therefore, for rank-1 RNNs, the latent dynamics of decision variable

906 (internal task variable associated with $\boldsymbol{m}_{dv}$) in context c is given by

$$\tau \frac{dk_{dv}(t)}{dt} = -k_{dv}(t) + \frac{1}{N} \boldsymbol{n}_{dv}^T \phi \left(\boldsymbol{I}_c^{ctx} + k_{dv}(t) \boldsymbol{m}_{dv} + \sum_{s=1}^{2} k_{inp_s}(t) \boldsymbol{I}_s \right). \tag{15}$$

908 Similar to the linearized dynamical systems analysis introduced earlier, we linearized equation

909 (15) around $\boldsymbol{I}_c^{ctx}$, obtaining the following linearized equation:

$$\tau \frac{dk_{dv}(t)}{dt} = -k_{dv}(t) + \frac{1}{N} \left(\boldsymbol{n}_{dv}^T \phi(\boldsymbol{I}_c^{ctx}) + \boldsymbol{n}_{dv}^T \widetilde{\boldsymbol{m}}_{dv}^{ctx_c} k_{dv}(t) + \sum_{s=1}^{2} \boldsymbol{n}_{dv}^T \widetilde{\boldsymbol{I}}_s^{ctx_c} k_{inp_s}(t) \right), \tag{16}$$

911 where $\widetilde{\boldsymbol{m}}_{dv}^{ctx_c} = G_c \boldsymbol{m}_{dv}$ (termed as the decision variable representation direction) and $\widetilde{\boldsymbol{I}}_s^{ctx_c} =$

912 $G_c \boldsymbol{I}_s$ (termed as the input representation direction), with G_c equal to $\text{diag}(\phi'(\boldsymbol{I}_c^{ctx}))$. By

913 denoting $\frac{1}{N} \boldsymbol{n}_{dv}^T \widetilde{\boldsymbol{m}}_{dv}^{ctx_c}$ and $\frac{1}{N} \boldsymbol{n}_{dv}^T \widetilde{\boldsymbol{I}}_s^{ctx_c}$ as $E_{dv \to dv}^{ctx_c}$ and $E_{inp_s \to dv}^{ctx_c}$, respectively, together with the

914 fact that $\frac{1}{N} \boldsymbol{n}_{dv}^T \phi(\boldsymbol{I}_c)$ is close to zero for all trained rank-1 RNNs, we obtain

$$\tau \frac{dk_{dv}(t)}{dt} = -k_{dv}(t) + E_{dv \to dv} k_{dv}(t) + E_{inp_1 \to dv}^{ctx_c} k_{inp_1}(t) + E_{inp_2 \to dv}^{ctx_c} k_{inp_2}(t), \tag{17}$$

916 which is Eq. 3 in the main text.

917 **The rank-3 RNN case.** Using a similar method, we can uncover the latent dynamics of rank-3

918 RNNs shown in Figure 5. Note that the rank-3 RNN in Figure 3 is a special case of this more

919 general form. The latent dynamics for internal task variables in context c can be written as:

$$\tau \frac{dk_{iv_s}}{dt} = -k_{iv_s}(t) + \frac{1}{N} \boldsymbol{n}_{iv_s}^T \phi \left(\boldsymbol{I}_c^{ctx} + k_{dv} \boldsymbol{m}_{dv} + \sum_{s=1}^{2} k_{iv_s} \boldsymbol{m}_{iv_s} + \sum_{s=1}^{2} k_{inp_s} \boldsymbol{I}_s \right), \tag{18}$$

$$\tau \frac{dk_{dv}}{dt} = -k_{dv}(t) + \frac{1}{N} \boldsymbol{n}_r^T \phi \left(\boldsymbol{I}_c^{ctx} + k_{dv} \boldsymbol{m}_{dv} + \sum_{s=1}^{2} k_{iv_s} \boldsymbol{m}_{iv_s} + \sum_{s=1}^{2} k_{inp_s} \boldsymbol{I}_s \right). \tag{19}$$

922 By applying the same first-order Taylor expansion, we obtain the following equations:

$$\tau \frac{dk_{iv_s}}{dt} = -k_{iv_s} + \frac{1}{N} \boldsymbol{n}_{iv_s}^T \left(\widetilde{\boldsymbol{m}}_{dv}^{ctx_c} k_{dv} + \sum_{s=1}^{2} \widetilde{\boldsymbol{m}}_{iv_s}^{ctx_c} k_{iv_s} + \sum_{s'=1}^{2} \widetilde{\boldsymbol{I}}_{s'}^{ctx_c} k_{inp_{s'}} \right), \tag{20}$$

$$\tau \frac{dk_{dv}}{dt} = -k_{dv} + \frac{1}{N} \boldsymbol{n}_r^T \left(\widetilde{\boldsymbol{m}}_{dv}^{ctx_c} k_{dv} + \sum_{s=1}^{2} \widetilde{\boldsymbol{m}}_{iv_s}^{ctx_c} k_{iv_s} + \sum_{s=1}^{2} \widetilde{\boldsymbol{I}}_s^{ctx_c} k_{inp_s} \right). \tag{21}$$

925   We consider the case in which the intermediate variables ($k_{iv_s}, s = 1,2$, internal task variables

926   associated with $\boldsymbol{m}_{iv_s}, s = 1,2$, respectively) only receive information from the corresponding

927   stimulus input, and the effective coupling of the recurrent connection is 1 in both contexts.

928   Specifically, we assume:

929
$$\langle \tilde{\boldsymbol{I}}_{iv_{s'}}^{ctx_c}, \boldsymbol{n}_{iv_s} \rangle = 0, s \neq s', c = 1,2, \tag{22}$$

930
$$\langle \tilde{\boldsymbol{m}}_{iv_{s'}}^{ctx_c}, \boldsymbol{n}_{iv_s} \rangle = 0, s, s' \in \{1,2\}, c = 1,2, \tag{23}$$

931
$$\langle \tilde{\boldsymbol{m}}_{dv}^{ctx_c}, \boldsymbol{n}_{dv} \rangle = 1, c = 1,2. \tag{24}$$

932   Our construction methods for rank-3 RNNs in Figures 3 and 5 guarantee these conditions when

933   the network is large enough (for example, $N = 30,000$ in our setting). Under these conditions,

934   equations (20) and (21) can be simplified to:

935
$$\tau \frac{dk_{iv_s}}{dt} = -k_{iv_s} + E_{inp_s \to iv_s}^{ctx_c} k_{inp_s}, \tag{25}$$

936
$$\tau \frac{dk_{dv}}{dt} = E_{inp_1 \to dv}^{ctx_c} k_{inp_1} + E_{inp_2 \to dv}^{ctx_c} k_{inp_2} + E_{iv_1 \to dv}^{ctx_c} k_{iv_1} + E_{iv_2 \to dv}^{ctx_c} k_{iv_2}. \tag{26}$$

937   Suppose at $t = 0$, the network receives a pulse from input 1 with size A_1 and a pulse from

938   input 2 with size A_2, which correspond to $u_1(t) = A_1 \tau \delta(t),\ u_2(t) = A_2 \tau \delta(t)$. Under this

939   condition, the expression for k_{dv} is given by

940
$$k_{dv}(t) = \sum_{s=1}^{2} A_s \left(E_{inp_s \to dv}^{ctx_c} (1 - e^{-t/\tau}) + E_{inp_s \to iv_s}^{ctx_c} E_{iv_s \to dv}^{ctx_c} \left(1 - e^{-t/\tau} - \frac{t}{\tau} e^{-t/\tau} \right) \right). \tag{27}$$

From equation (27), as $t \to \infty$, k_{dv} will converge to $\sum_{s=1}^{2} A_s \left(E_{inp_s \to dv}^{ctx_c} + E_{inp_s \to iv_s}^{ctx_c} E_{iv_s \to dv}^{ctx_c} \right)$,

providing a theoretical basis for the pathway-based information flow formula presented in

Figures 4 and 5.

Building rank-3 RNNs with both input and selection vector modulations (Figure 5)

Understanding low-rank RNNs in the mean-field limit. The dynamics of task variables in low-

rank RNNs can be mathematically analyzed under the mean-field limit ($N \to +\infty$) when each

neuron's connectivity component is randomly drawn from a multivariate Gaussian mixture

model (GMM) (Beiran et al., 2021; Dubreuil et al., 2022). Specifically, we assume that, for the

i-th neuron, the connectivity component vector $\{I_s^{(i)}, s = 1, \ldots, S, (I_c^{ctx})^{(i)}, c = 1,2, m_r^{(i)}, r =$

$1, \ldots, R, n_r^{(i)}, r = 1, \ldots, R\}$ is drawn independently from a GMM with P components. The

weight for the j-th component is α_j, and this component is modeled as a Gaussian distribution

with mean zero and covariance matrix $\Sigma^{(j)}$. Let $\Sigma_{Im}^{(j)}$ denote the upper-left $(S + R + 2) \times (S + $

$R + 2)$ submatrix of $\Sigma^{(j)}$, which represents the covariance matrix of $\{I_s^{(i)}, s = $

$1, \dots, S, (I_c^{ctx})^{(i)}, c = 1,2, m_r^{(i)}, r = 1, \dots, R\}$ within the j-th component. Let $\sigma_{ab}^{(p)}, a, b \in$

$\{I_s, s = 1, \dots, S, I_c^{ctx}, c = 1,2, m_r, r = 1, \dots, R, n_r, r = 1, \dots, R\}$ denote the covariance of $a^{(i)}$

and $b^{(i)}$, where the i-th neuron belongs to the p-th component.

Given these assumptions, under the mean-field limit $(N \to +\infty)$, equation (14) can be expressed

as

$$\tau \frac{dk_r(t)}{dt} = -k_r(t) + \sum_{j=1}^{R} \sum_{p=1}^{P} \alpha_p \langle \phi' \rangle_p \, \sigma_{m_j n_r}^{(p)} k_j(t)$$

$$+ \sum_{s=1}^{S} \sum_{p=1}^{P} \alpha_p \langle \phi' \rangle_p \, \sigma_{I_s n_r}^{(p)} k_{inp_s} + \sum_{p=1}^{P} \alpha_p \langle \phi' \rangle_p \, \sigma_{I_c^{ctx} n_r}^{(p)}, \qquad (28)$$

960
$$\langle \phi' \rangle_p = \int_{-\infty}^{\infty} \frac{1}{\sqrt{2\pi}} e^{-\frac{x^2}{2}} \phi'(\Delta_p x) dx, \qquad (29)$$

$\Delta_p^2 = [k_{inp_1}, \dots, k_{inp_S}, k_{ctx_1}, k_{ctx_2}, k_1, \dots, k_R] \Sigma_{Im}^{(p)} [k_{inp_1}, \dots, k_{inp_S}, k_{ctx_1}, k_{ctx_2}, k_1, \dots, k_R]^T, \quad (30)$

where $k_{ctx_i} = 1$ if $i = c$, otherwise $k_{ctx_i} = 0$. Under the condition of small task variables

$(k_{inp_s}, s = 1, \dots, S$ and $k_r, r = 1, \dots, R)$, Δ_p^2 is approximately equal to $\sigma_{I_c^{ctx}, I_c^{ctx}}^{(p)}$ and the

quantities $\langle \phi' \rangle_p, p = 1, \dots, P$ are determined solely by the covariance of the context c signal

input within each population. Clearly, the effective coupling from the input task variable k_{inp_s}

to the internal task variable k_r is given by $\sum_{p=1}^{P} \alpha_p \langle \phi' \rangle_p \, \sigma_{I_s n_r}^{(p)}$, and the effective coupling

between the internal task variables k_j and k_r is given by $\sum_{p=1}^{P} \alpha_p \langle \phi' \rangle_p \, \sigma_{m_j n_r}^{(p)}$.

Mean-field-theory-based model construction. Utilizing this theory, we can construct RNNs

tailored to any given ratio of input modulation to selection vector modulation by properly setting

the connectivity vectors (I_1, I_2, I_1^{ctx}, I_2^{ctx}, m_{iv1}, m_{iv2}, m_{dv}, n_{iv1}, n_{iv2}, and n_{dv}). The

RNN we built consists of 30,000 neurons divided into three populations. The first population

(neurons 1-10,000) receives the stimulus input, accounting for information flow from stimulus

input to intermediate variables (the connection strength is controlled by β) and the recurrent

connection of the decision variable. The second (neurons 10,001-20,000) and third populations

(neurons 20,001-30,000) receive the stimulus input, accounting for the information flow from the

stimulus input to the decision variable (the connection strength is controlled by α) and the

information flow from the intermediate variables to the decision variable (the connection

strength is controlled by η), and are modulated by contextual input. To achieve this, we generate

three Gaussian random matrices ($M^{(1)}, M^{(2)}, M^{(3)}$) of shape $10{,}000 \times 3$, $10{,}000 \times 5$ and

$10{,}000 \times 5$, respectively. Let $M^{(p)}_{:,r}$ denote the r-th column of matrix $M^{(p)}$. The stimulus input

I_1 is given by the concatenation of three length-10,000 vectors $\left[M^{(1)}_{:,1}; M^{(2)}_{:,1}; M^{(3)}_{:,1}\right]$. The stimulus

input I_2 is given by $\left[M^{(1)}_{:,2}; M^{(2)}_{:,2}; M^{(3)}_{:,2}\right]$. The context input I^{ctx}_1 is given by $\left[0; M^{(2)}_{:,3}; 0\right]$. The

context input I^{ctx}_2 is given by $\left[0; 0; M^{(3)}_{:,3}\right]$. The connectivity vectors $\boldsymbol{m}_{iv1}, \boldsymbol{m}_{iv2}$, and $\boldsymbol{m}_{dv}$ are

given by $\left[0; M^{(2)}_{:,4}; M^{(3)}_{:,4}\right]$, $\left[0; M^{(2)}_{:,5}; M^{(3)}_{:,5}\right]$ and $\left[M^{(1)}_{:,3}; 0; 0\right]$, respectively. The input-selection

vectors $\boldsymbol{n}_{iv_1}$ and $\boldsymbol{n}_{iv_2}$ are given by $\left[3\beta M^{(1)}_{:,1}; 0; 0\right]$, $\left[3\beta M^{(1)}_{:,2}; 0; 0\right]$, respectively. $\boldsymbol{n}_{dv}$ is given

by $\left[3M^{(1)}_{:,3}; -\frac{3\alpha g}{1-g^2}M^{(2)}_{:,1} + \frac{3\alpha}{1-g^2}M^{(2)}_{:,2} - \frac{3\eta g}{1-g^2}M^{(2)}_{:,4} + \frac{3\eta}{1-g^2}M^{(2)}_{:,5}; \frac{3\alpha}{1-g^2}M^{(3)}_{:,1} - \frac{3\alpha g}{1-g^2}M^{(3)}_{:,2} + \right.$

$\left. \frac{3\eta}{1-g^2}M^{(3)}_{:,4} - \frac{3\eta g}{1-g^2}M^{(3)}_{:,5}\right]$, where $g = \int_{-\infty}^{+\infty} \frac{1}{\sqrt{2\pi}}e^{-x^2/2}\phi'(x)dx$ is the average gain of the second

population in context 1 or third population in context 2. The readout vector $\boldsymbol{w}$ is given by

$\left[4M^{(1)}_{:,3}; 0; 0\right]$.

For the network, in context 1, $\langle\phi'\rangle_p$ is only determined by the covariance of the context 1

signal. That is,

$$\langle\phi'\rangle_p = \int_{-\infty}^{\infty} \frac{1}{\sqrt{2\pi}}e^{-\frac{x^2}{2}}\phi'\left(\sqrt{\sigma^{(p)}_{I^{ctx}_1 I^{ctx}_1}}x\right)dx. \tag{31}$$

993 Our construction method guarantees that $\sigma^{(p)}_{I^{ctx}_1 I^{ctx}_1} = 0,1,0$ for $p = 1,2,3$, respectively. Hence,

994 $\langle\phi'\rangle_p = 1, g, 1$ for $p = 1,2,3$, respectively. Then the effective coupling from input variable

995 k_{inp_1} to k_{iv_1} in context 1 is given by

$$E^{ctx_1}_{inp_1 \to iv_1} = \sum_{p=1}^{P} \frac{1}{3}\langle\phi'\rangle_p \sigma^{(p)}_{I_1 n_{iv_1}} = \frac{1}{3} \times 3 \times \beta = \beta. \tag{32}$$

997 Similarly, we can get that:

$$E^{ctx_1}_{inp_2 \to iv_2} = \beta, \tag{33}$$

$$E^{ctx_1}_{inp_1 \to dv} = \alpha, E^{ctx_1}_{inp_2 \to dv} = 0, \tag{34}$$

$$E^{ctx_1}_{iv_1 \to dv} = \eta, E^{ctx_1}_{iv_2 \to dv} = 0. \tag{35}$$

1001 Other unmentioned effective couplings are zero. Similarly, the effective couplings in context 2

1002 are given by

1003
$$E_{inp_1 \to iv_2}^{ctx_2} = E_{inp_2 \to iv_2}^{ctx_2} = \beta, \tag{36}$$

1004
$$E_{inp_1 \to dv}^{ctx_2} = 0, E_{inp_2 \to dv}^{ctx_2} = \alpha, \tag{37}$$

1005
$$E_{iv_1 \to dv}^{ctx_2} = 0, E_{iv_2 \to dv}^{ctx_2} = \eta. \tag{38}$$

Thus, for each input, the input modulation is α and the selection vector modulation is $\beta \times \eta$.

Therefore, any given ratio of input modulation to selection vector modulation can be achieved by

varying the parameters $\alpha, \beta,$ and η. The example in Figure 3 with pure selection vector

modulation is a special case with $\alpha = 0, \beta = \frac{10}{3},$ and $\eta = (1 - g^2)/3$.

Pathway-based definition of selection vector (Figure 6)

Next, we will consider the rank-3 RNN with latent dynamics depicted in equations (18) and (19).

The input representation produced by a pulse input $u_s = \tau A_s \delta(t), s = 1,2$ in a certain context

at $t = 0$ is given by $A_1 \tilde{I}_1 + A_2 \tilde{I}_2$. We have proven that this pulse input will ultimately reach

the dv slot with a magnitude of $\sum_{s=1}^{2} A_s (E_{inp_s \to dv} + E_{inp_s \to iv_s} E_{iv_s \to dv})$. This equation can be

rewritten as

1016
$$\frac{1}{N} (A_1 \tilde{I}_1 + A_2 \tilde{I}_2) \cdot (\boldsymbol{n}_{dv} + E_{iv_1 \to dv} \boldsymbol{n}_{iv_1} + E_{iv_2 \to dv} \boldsymbol{n}_{iv_2}) \tag{39}$$

1017 Therefore, we define $\boldsymbol{n}_{tol} = \boldsymbol{n}_{dv} + E_{iv_1 \to dv} \boldsymbol{n}_{iv_1} + E_{iv_2 \to dv} \boldsymbol{n}_{iv_2}$ as the pathway-based definition

1018 of the selection vector. Through calculations, we can prove that this pathway-based definition of

1019 the selection vector is equivalent to the classical definition based on linearized dynamical

1020 systems. In fact, the transition matrix of neuron activity in this rank-3 RNN is given by:

1021
$$M = -E + \frac{1}{N} G (\boldsymbol{m}_{iv_1} \boldsymbol{n}_{iv_1}^T + \boldsymbol{m}_{iv_2} \boldsymbol{n}_{iv_2}^T + \boldsymbol{m}_{dv} \boldsymbol{n}_{dv}^T)$$
$$= -E + \frac{1}{N} (\tilde{\boldsymbol{m}}_{iv_1} \boldsymbol{n}_{iv_1}^T + \tilde{\boldsymbol{m}}_{iv_2} \boldsymbol{n}_{iv_2}^T + \tilde{\boldsymbol{m}}_{dv} \boldsymbol{n}_{dv}^T). \tag{40}$$

1022 Multiplying M^T on the right by $\boldsymbol{n}_{tol}$, we obtain:

1023
$$M^T \boldsymbol{n}_{tol} = 0. \tag{41}$$

1024 Moreover, under the condition that the choice axis is invariant across contexts, i.e., $\tilde{\boldsymbol{m}}_{dv}$ is

1025 invariant across contexts (Mante et al., 2013; Pagan et al., 2022),

1026
$$\frac{\tilde{\boldsymbol{m}}_{dv}}{\|\tilde{\boldsymbol{m}}_{dv}\|_2} \cdot \left(\frac{1}{N} \|\tilde{\boldsymbol{m}}_{dv}\|_2 \boldsymbol{n}_{tol}\right) = \langle \tilde{\boldsymbol{m}}_{dv}, \boldsymbol{n}_{tol} \rangle = 1. \tag{42}$$

This demonstrates that $\frac{1}{N} \|\tilde{\boldsymbol{m}}_{dv}\|_2 \boldsymbol{n}_{tol}$ is indeed the left eigenvector of the transition matrix as

well as the classical selection vector of the linearized dynamical systems.

The equivalence between two definitions of selection vector modulation (Figure 5)

Here, we use the rank-3 RNN and input 1 as an example to explain why there is an equivalence

between our definition of selection vector modulation and the classical one (Pagan et al., 2022).

In the previous section, we have proven that the input representation direction and selection

vector are given by $\tilde{I}_1$ and $s = \frac{1}{N}\|\tilde{m}_{dv}\|_2(n_{dv} + E_{iv_1 \to dv}n_{iv_1} + E_{iv_2 \to dv}n_{iv_2})$, respectively.

According to the classical definition (Pagan et al., 2022), the input modulation and selection

vector modulation are given by $mod_{inp} = \Delta\tilde{I}_1 \cdot \bar{s}$ and $mod_{sel} = \bar{\tilde{I}}_1 \cdot \Delta s$, respectively. Since

$\tilde{m}_{dv}, n_{iv_1}, n_{iv_2}$ and n_{dv} are invariant across different contexts, we have:

$$\bar{s} = \frac{1}{N}\|\tilde{m}_{dv}\|_2(n_{dv} + \bar{E}_{iv_1 \to dv}n_{iv_1} + \bar{E}_{iv_2 \to dv}n_{iv_2}), \tag{43}$$

$$\Delta s = \frac{1}{N}\|\tilde{m}_{dv}\|_2(\Delta E_{iv_1 \to dv}n_{iv_1} + \Delta E_{iv_2 \to dv}n_{iv_2}). \tag{44}$$

1039 Substituting these into equations (7) and (8) yields:

$$mod_{inp} = \|\tilde{m}_{dv}\|_2(\Delta E_{inp_1 \to dv} + \Delta E_{inp_1 \to iv_1}\bar{E}_{iv_1 \to dv}), \tag{45}$$

$$mod_{sel} = \|\tilde{m}_{dv}\|_2(\bar{E}_{inp_1 \to iv_1}\Delta E_{iv_1 \to dv}), \tag{46}$$

a result fully consistent with the pathway-based definition in Eq. 5 of the main text.

Pathway-based analysis of higher order low-rank RNNs (Figures 7, A and B)

In this section, we will consider RNNs with more intermediate variables (Figure 7A). Here, we

consider only one stimulus modality for simplicity and use the same notation convention in the

previous sections. The network consists of one input variable k_{inp}, L intermediate variables

$k_{iv_i}, i = 1, \dots, L$, and one decision variable k_{dv}. For simplicity, we let k_{iv_0} be an alias for the

input variable and $k_{iv_{L+1}}$ be an alias for the decision variable. We use the shorthand $E_{i \to j}$ and

$E_{i \to dv}$ to denote the effective coupling $E_{iv_i \to iv_j}$ and $E_{iv_i \to dv}$, respectively. The dynamics of

these task variables are given by

$$\tau\frac{dk_{inp}}{dt} = -k_{inp} + u, \tag{47}$$

$$\tau\frac{dk_{iv_i}}{dt} = -k_{iv_i} + \sum_{j=0}^{i-1} E_{j \to i}k_{iv_j}, i = 1, \dots, L, \tag{48}$$

$$\tau\frac{dk_{dv}}{dt} = \sum_{j=0}^{L} E_{j \to L+1}k_{iv_j}. \tag{49}$$

1054 Consider the case when, at time $t = 0$, the network receives a pulse input with unit size (i.e.,

1055 $u(t) = \tau\delta(t)$). Then, we have

1056
$$k_{inp} = e^{-\frac{t}{\tau}}, \tag{50}$$

1057
$$k_{iv_i} = \sum_{j=1}^{i} \frac{K_j^i}{j!} e^{-\frac{t}{\tau}} \left(\frac{t}{\tau}\right)^j \quad i = 0, \dots, n, \tag{51}$$

1058
$$k_{dv} = k_{iv_{L+1}} = \sum_{j=1}^{L+1} K_j^{L+1} \left(1 - \frac{\Gamma\left(j,\frac{t}{\tau}\right)}{(j-1)!}\right), \tag{52}$$

where $K_j^i = \sum_{0=a_1<a_2<\cdots<a_j<i} E_{a_1 \to a_2} \cdot E_{a_2 \to a_3} \cdot \dots \cdot E_{a_j \to i}$. In equation (52), Γ stands for the

incomplete Gamma function and $\Gamma\left(j,\frac{t}{\tau}\right) = \int_{t/\tau}^{\infty} x^{j-1} e^{-x} dx$. These expressions tell us that, as

time goes to infinity, all intermediate task variables $k_{iv_i}, i = 1, \dots, L$ will decay to zero and the

decision variable will converge to $\sum_{j=1}^{L+1} K_j^{L+1}$, which means that a pulse input of unit size will

ultimately reach the dv slot with a magnitude of $\sum_{j=1}^{L+1} K_j^{L+1}$. Therefore, we define the total

effective coupling from the input variable to the decision variable in this higher-order graph as

1065
$$E_{tol} = \sum_{j=1}^{L+1} \sum_{0=a_1<a_2<\cdots<a_j\le L} E_{a_1 \to a_2} \cdot E_{a_2 \to a_3} \cdot \dots \cdot E_{a_j \to dv}. \tag{53}$$

1066 The difference of the total effective coupling between relevant context and irrelevant context can

1067 be decomposed into:

1068
$$\Delta E_{tol} = \sum_{j=1}^{L+1} \sum_{0=a_1<a_2<\cdots<a_j\le L} \Delta\left(E_{a_1 \to a_2}\right) \cdot \overline{E_{a_2 \to a_3} \cdot \dots \cdot E_{a_j \to dv}} +$$
$$\sum_{j=1}^{L+1} \sum_{0=a_1<a_2<\cdots<a_j\le L} \overline{E_{a_1 \to a_2}} \cdot \Delta\left(E_{a_2 \to a_3} \cdot \dots \cdot E_{a_j \to dv}\right). \tag{54}$$

1069 The first term, caused by changing of stimulus input representation, is defined as the input

1070 modulation. The second term, the one without changing the stimulus input representation, is

1071 defined as the selection vector modulation.

1072 Using a similar method in rank-3 RNNs, the selection vector for RNNs of higher order is given

1073 by:

$$1074 \qquad n_{dv} + \sum_{j=1}^{L} \sum_{0 < a_1 < \cdots < a_j \leq L} \left(E_{a_1 \to a_2} \cdot \ldots \cdot E_{a_j \to dv} \right) n_{iv_{a_1}}. \qquad (55)$$

Training of full-rank vanilla RNNs using backpropagation (Figure 7)

For Figure 7, we trained full-rank RNNs of $N = 128$ neurons. We trained the elements of the

input vectors, the connectivity matrix, and the readout vector. We tested a large range of

regularization coefficients ranging from 0 to 0.1. For each r_{reg} chosen from the set {0, 0.001,

0.002, 0.003, 0.004, 0.005, 0.006, 0.007, 0.008, 0.009, 0.01, 0.02, 0.03, 0.04, 0.05, 0.06, 0.07,

0.08, 0.09, 0.1}, we trained 100 full-rank RNNs. A larger w_{reg} value results in trained

connectivity matrix J with lower rank, making the network more similar to a rank-1 RNN. All

trainable parameters were initialized with random independent Gaussian weights with a mean of

0 and variance of $1/N^2$. Only trained RNNs with their largest eigenvalue of the activity

transition matrix falling within the -0.05 to 0.05 range in both contexts were selected for

subsequent analysis.

To ensure that the conclusions drawn from Figure 7 are robust and not dependent on specific

hyperparameter settings, we conducted similar experiments under different model

hyperparameter settings. First, we trained RNNs with the softplus activation function and

regularization coefficients chosen from {0.1, 0.09, 0.08, 0.07, 0.06, 0.05, 0.04, 0.03, 0.02, 0.01,

0.008, 0.004, 0.002, 0.001} (Figure 7-figure supplement 2A). Unlike tanh, softplus does not

saturate on the positive end. Additionally, we tested the initialization of trainable parameters

with a variance of $1/N$ (Figure 7-figure supplement 2B). Together, these experiments

confirmed that the main results do not depend on the specific model hyperparameter settings.

Estimating matrix dimension and extra-dimension (Figure 7)

Effective dimension of connectivity matrix (Figure 7D). Let $\sigma_1 \geq \sigma_2 \geq \cdots \geq \sigma_n$ be the singular

values of the connectivity matrix. Then, the effective dimension of matrix J is defined as its

stable rank (Sanyal et al., 2020):

$$1098 \qquad \sum_{i=1}^{n} \frac{\sigma_i^2}{\sigma_1^2}. \qquad (56)$$

1099 *Single neuron response kernel for pulse input (Figure 7E)*. We apply pulse-based linear

1100 regression (Pagan et al., 2022) to access how pulse input affects neuron activity. The activity of

1101 neuron i in trial k at time step t is given by:

1102
$$r_{i,t}(k) = \beta_{choice;i,t} choice(k) + \beta_{context;i,t} context(k) + \beta_{time;i,t} + \\ \beta_{inp_1,ctx_c;i} * u_{1,k} + \beta_{inp_2,ctx_c;i} * u_{2,k},$$ (57)

where $choice(k)$ is the RNN's choice on trial k defined as the sign of its output during the

decision period, $context(k)$ is the context of trial k (1 for context 1 and 0 for context 2), $u_{i,k}$

indicates signed input i evidence as defined previously in Methods. The first three regression

coefficients, $\beta_{choice;i,t}$, $\beta_{context;i,t}$ and $\beta_{time;i,t}$, capture the influent of choice, context, and

time on the neuron's activity at each time step, each being a 40-dimension vector. The remaining

coefficient, $\beta_{inp_1,ctx_1;i}$, $\beta_{inp_1,ctx_2;i}$, $\beta_{inp_2,ctx_1;i}$, and $\beta_{inp_2,ctx_2;i}$, reflect the impact of pulse input

on the neuron activity in specific context, each also a 40-dimension vector. The asterisk ($*$)

indicates the convolution operation between the response kernel and input evidence, described

by:

1112
$$\left(\beta_{inp_1,ctx_c;i} * u_{1,k}\right)(t) = \sum_{s=1}^{t} u_{1,k}(s) \, \beta_{inp_1,ctx_c;i}(t-s).$$ (58)

Therefore, there are a total of 280 regression coefficients for each neuron. We obtained these

coefficients using ridge regression with 1000 trails for each RNN. The coefficient $\beta_{inp_i,ctx_c;i}(t)$

is termed the single neuron response kernel for input i in context c (Figure 7E).

Response kernel modes and normalized percentage of explained variance (PEV) (Figure 7F). For

each RNN, we construct a matrix B with shape $N_t \times (2N)$ from neuron response kernels for

input 1 (or input 2) across both contexts, where $N_t = 40$ represents time steps and N is the

number of neurons, with each column as a neuron's response kernel in a context. Then we apply

singular value decomposition (SVD) to the matrix:

1121
$$B = USV^T$$ (59)

1122 where S is a diagonal square matrix of size N_t, with diagonal element $\sigma_1 \geq \sigma_2 \geq \cdots \geq \sigma_{N_t}$

1123 being the singular value of the matrix. The first column of U serves as a persistent mode (mode

1124 0), while the second and following columns are transient modes (transient dynamical modes 1, 2,

1125 etc.). The normalized PEV of transient dynamical mode $r, r \geq 1$ is defined as:

1126
$$PEV_{mode_r} = \frac{\sigma_{r+1}^2}{\sum_{i=2}^{40} \sigma_i^2}.$$

1127 *PEV of extra dynamical modes*. The PEV of extra dynamical modes for input 1 (or 2) is defined

1128 based on the normalized PEV of transient dynamical mode:

$$1129 \qquad PEV_{ED}(inp_1) = \sum_{r=1}^{N_t-1} PEV_{mode_r}. \qquad (60)$$

The counterintuitive extreme example (Figure 7-figure supplement 3)

We can manually construct two models (RNN1 and RNN2) with distinct circuit mechanisms

(input modulation versus selection vector modulation) but showing the same neural activities.

Specifically, we generated three Gaussian random matrices $(M^{(1)}, M^{(2)}, M^{(3)})$ of shape

$10,000 \times 5$, $10,000 \times 5$ and $10,000 \times 1$, respectively. Let $M^{(p)}_{:,r}$ denote the r-th column of

matrix $M^{(p)}$. The two models have the same input vectors, output vectors, and input-selection

vectors for intermediate task variables ($\boldsymbol{n}_{iv_1}$ and $\boldsymbol{n}_{iv_2}$), given by:

$$1137 \qquad \boldsymbol{I}_1 = \left[M^{(1)}_{:,1}; M^{(2)}_{:,1}; \boldsymbol{0} \right], \boldsymbol{I}_2 = \left[M^{(1)}_{:,2}; M^{(2)}_{:,2}; \boldsymbol{0} \right] \qquad (61)$$

$$1138 \qquad \boldsymbol{I}_1^{ctx} = \left[M^{(1)}_{:,5}; \boldsymbol{0}; \boldsymbol{0} \right], \boldsymbol{I}_2^{ctx} = \left[\boldsymbol{0}; M^{(2)}_{:,5}; \boldsymbol{0} \right] \qquad (62)$$

$$1139 \qquad \boldsymbol{m}_{iv_1} = \left[M^{(1)}_{:,3}; M^{(2)}_{:,3}; \boldsymbol{0} \right], \boldsymbol{m}_{iv_2} = \left[M^{(1)}_{:,4}; M^{(2)}_{:,4}; \boldsymbol{0} \right], \boldsymbol{m}_{dv} = \left[\boldsymbol{0}; \boldsymbol{0}; M^{(3)}_{:,1} \right] \qquad (63)$$

$$1140 \qquad \boldsymbol{n}_{iv_1} = \left[\frac{3}{1+g} M^{(1)}_{:,1}; \frac{3}{1+g} M^{(2)}_{:,1}; \boldsymbol{0} \right], \boldsymbol{n}_{iv_2} = \left[\frac{-3g}{1-g^2} M^{(1)}_{:,1}; \frac{3}{1-g^2} M^{(2)}_{:,1}; \boldsymbol{0} \right], \qquad (64)$$

1141 where $g = \int_{-\infty}^{+\infty} \frac{1}{\sqrt{2\pi}} e^{-x^2/2} \phi'(x) dx$. The difference between these two RNNs lies in their input-

1142 selection vector $\boldsymbol{n}_{dv}$ for the decision variable. For RNN1, $\boldsymbol{n}_{dv}$ is given by

$$1143 \qquad \boldsymbol{n}_{dv} = \left[\frac{3}{1+g} M^{(1)}_{:,4}; \frac{3}{1+g} M^{(2)}_{:,4}; \boldsymbol{0} \right] + \left[\frac{3}{1-g^2} M^{(1)}_{:,2}; \frac{-3g}{1-g^2} M^{(2)}_{:,2}; \boldsymbol{0} \right] + \left[\boldsymbol{0}; \boldsymbol{0}; 3M^{(3)}_{:,1} \right]. \qquad (65)$$

1144 For RNN2, $\boldsymbol{n}_{dv}$ is given by:

$$1145 \qquad \boldsymbol{n}_{dv} = \left[\frac{-3g}{1-g^2} M^{(1)}_{:,3}; \frac{3}{1-g^2} M^{(2)}_{:,3}; \boldsymbol{0} \right] + \left[\frac{3}{1-g^2} M^{(1)}_{:,2}; \frac{-3g}{1-g^2} M^{(2)}_{:,2}; \boldsymbol{0} \right] + \left[\boldsymbol{0}; \boldsymbol{0}; 3M^{(3)}_{:,1} \right]. \qquad (66)$$

In this construction, the information flow graphs from input 1 to the decision variable (dv) in

each context for the two RNNs are shown in Figure 7-figure supplement 3A.

Although the connectivity matrices of the two networks are different (Figure 7-figure supplement

3B), when provided with the same input, the neuron activity of the i-th neuron in RNN1 is

exactly the same as that of the i-th neuron in RNN2 at the same time point (Figure 7-figure

supplement 3C). The statistical results of similarity between all neuron pairs are given in Figure

7-figure supplement 3D.

1153
1154

A

1155
1156 **Figure 2-figure supplement 1: Connectivity structure for the example rank-1 RNN.**
1157 (A) Projection of the connectivity space for the example rank-1 RNN. Each dot denotes a neuron.
1158   On each panel, the x and y coordinates of the i-th dot represent the i-th entry of the
1159   corresponding connectivity vectors.

1160
Figure 3-figure supplement 1: Connectivity structure for the example rank-3 RNN.
(A) Projection of the connectivity space for the example rank-3 RNN. This RNN has 30,000
neurons divided into three populations. Dots of the same color represent neurons within the
same population. The inset in the top right corner shows the projection on the two context
input axes. For brevity, we did not include the projections onto the context input axis and
other connectivity vectors. Within each population, the context input axis is independent of
the other connectivity vectors. This independence implies that the context signal only affects
the average sensitivity of each neuron population, thereby serving a modulatory function.

1169

1170
Figure 4-figure supplement 1: Effective coupling between task variables for rank-1 and
rank-3 RNNs.
(A) Effective coupling between task variables for 100 trained rank-1 RNNs (Figure 2) in each
context. Effective coupling between two task variables is defined as the overlap between the
corresponding representation vector and input-selection vector. For example, the effective
coupling from input 1 to decision variable $E_{inp_1 \to dv}$ is the overlap between $\tilde{I}_1$ and $\mathbf{n}_{dv}$
($\langle \tilde{I}_1, \mathbf{n}_{dv} \rangle$). As can be seen, the effective couplings of recurrent connection ($E_{dv \to dv}$) are close
to 1 in both contexts. The effective coupling from input task variables to decision variable is
large in the relevant context (i.e. $E_{inp_1 \to dv}$ in context 1 and $E_{inp_2 \to dv}$ in context 2) and are
negligible in the irrelevant context.
(B) Effective coupling between task variables for 100 trained rank-3 RNNs (Figure 3) in each
context. The effective coupling for recurrent connectivity ($E_{dv \to dv}$, $i.e.$ overlap between $\widetilde{m}_{dv}$
and $\mathbf{n}_{dv}$) is close to 1 in both contexts. There is no direction connectivity from the input task
variable to the decision variable since $E_{inp_s \to dv}, s = 1, 2$ are zero in both contexts. The
difference between $E_{iv_s \to dv}$ in the two contexts leads to selection vector modulation.

1186
Figure 4-figure supplement 2: Neural activity and task variable dynamics for single pulse
input.
(A) Task setting for single pulse input. We study the neural activity dynamics for low-rank RNN
when they receive pulse input. For simplicity, only the RNNs' neural activity given a pulse
from input 1 in context 1 is considered.
(B) Illustration of neural activity for rank-1 RNN given pulse input. For rank-1 RNN (Figure 2),
dynamics of $\boldsymbol{x}(t) - \boldsymbol{I}_1^{ctx}$ is always constrained in the subspace spanned by $\{\boldsymbol{I}_1, \boldsymbol{m}_{dv}\}$, with
the corresponding coefficients being the input task variable (k_{inp_1}) and decision variable
(k_{dv}), respectively. Moreover, the neural activity $\boldsymbol{x}(t)$ is always constrained in a line
(dashed line) orthogonal to the selection vector.
(C) Task variable dynamics for rank-1 RNN given pulse input. We run the example RNN for a
given input and project the results onto each axis to obtain the dynamics of each task variable
(solid line). The analytical expressions for the dynamics of each task variable are provided in

the methods section (dotted line). The simulated RNN results closely match the theoretical

values.

(D) Illustration of neural activity for rank-3 RNN given pulse input. For rank-3 RNN (Figure 3),

dynamics of $\boldsymbol{x}(t) - \boldsymbol{I}_1^{ctx}$ are always constrained in the subspace spanned by $\{\boldsymbol{I}_1, \boldsymbol{m}_{iv}, \boldsymbol{m}_{dv}\}$,

with the corresponding coefficients being input task variable (k_{inp_1}), intermediate task

variable (k_{iv_1}) and decision variable (k_{dv}), respectively.

(E) Task variable dynamics for rank-3 RNN given pulse input. Solid lines denote task variable

dynamics calculated numerically by RNN simulation and dotted lines denote theoretical

results.

1209

1210
Figure 7-figure supplement 1: Training vanilla RNNs with different regularization
coefficients.
(A) The influence of regularization coefficient to effective connectivity dimension of trained
RNNs. For each regularization coefficient, we trained 100 full-rank RNNs (Figure 7, panel
D). Larger regularization results in connectivity matrices with lower rank, leading to a
smaller effective connectivity dimension.
(B) The influence of regularization coefficient on selection vector modulation of trained RNNs
Distribution of selection vector modulation for networks trained with different regularization
coefficients. Larger regularization leads to networks that favor the input modulation strategy.
(C) The relationship between the proportion of explained variance (PEV) in extra-dimensions
and effective connectivity dimension. There is a strong positive correlation between the PEV
in extra dimensions and the effective connectivity dimension in both contexts. In each panel,
each dot denotes a trained RNN, with different colors denoting different regularization
coefficients.
1225

1226
Figure 7-figure supplement 2: Verification correlation results using vanilla RNNs trained
with different hyper-parameter settings.
(A) Similar results in trained vanilla RNNs with a softplus activation function. *Left*: Spearman's
rank correlation, r= 0.945, p<1e-3, n= 2564. *Right*: Spearman's rank correlation, r=0.803,
p<1e-3, n=2564. The x-axes are displayed in log-scale for both panels.
(B) Similar results in trained vanilla RNNs initialized with a variance of $1/N$. *Left*: Spearman's
rank correlation, r=0.973, p<1e-3, n=2630. *Right*: Spearman's rank correlation, r=0.976,
p<1e-3, n=2630. The x-axes are displayed in log-scale for both panels.
1235

1236
Figure 7-figure supplement 3: Two RNNs with distinct modulation strategies produce the
same neural activities.
(A) Information flow graph for the two RNNs. The black arrows denote that the effective
coupling from the head to the tail is 1. For RNN1, the closure of $inp_1 \rightarrow iv_2$ on the pathway
$inp_1 \rightarrow iv_2 \rightarrow dv$ prevents inp_1 from reaching iv_2 and subsequently the decision variable
(dv), indicating that RNN1 uses solely input modulation strategy for input 1. For RNN2, the
closure of $iv_1 \rightarrow dv$ on the pathway $inp_1 \rightarrow iv_1 \rightarrow dv$ means that although inp_1 can
reach iv_1, the subsequent step of iv_1 reading dv is blocked. This indicates RNN2 uses
solely the selection vector modulation strategy for input 1.
(B) Connectivity weight among three example neurons in the two RNNs. Each neuron belongs to
one of the three neuron populations (see Method for more details). Notice that the
connectivity weights from n_1 (neuron 1) to n_3 (or n_2 to n_3) are different between the
two RNNs.
(C) Neural activities for the three neurons in three example trials. Orange lines denote activities
for RNN1 and blue lines denote activities for RNN2. The neural activity is approximately
equal between the two RNNs.
(D) Histogram of the single neuron activity similarity between the two RNNs. We calculated the
similarity between the activity of the i-th neuron in RNN1 and the i-th neuron in RNN2
during trial k ($r2\_score$ function in the *sklearn* package of Python). Averaging over the
batches provides the similarity between corresponding neurons (neuron i in RNN1 and
neuron i in RNN2).
1258