Illumination mediates a switch in both active sensing and control in weakly electric fish

Huanying Yeh[1,†], Yu Yang[2,3,*,†], Debojyoti Biswas[3], and Noah J. Cowan[2,3,*]

[1]Department of Electrical and Computer Engineering, Johns Hopkins University, 3400 N. Charles Street, Baltimore, MD 21218, USA

[2]Department of Mechanical Engineering, Johns Hopkins University, 3400 N. Charles Street, Baltimore, MD 21218, USA

[3]Laboratory for Computational Sensing and Robotics, Johns Hopkins University, 3400 N. Charles Street, Baltimore, MD 21218, USA

[*]Author for correspondence: yangyuharbin@gmail.com (Y.Y.), ncowan@jhu.edu (N.J.C.)

[†]These authors contributed equally to this work

Abstract

Animals integrate multiple sensory inputs to explore environments and execute locomotor behaviors. To carry out these behaviors, the nervous system internally reweights controller gains, putting more emphasis on those with the least uncertainty, e.g. in a Bayesian framework. Meanwhile, as sensory uncertainty increases, animals produce more vigorous active sensing movements. To better understand the link between these two complementary processes—multisensory reweighting and active sensing—we studied how the weakly electric glass knifefish *Eigenmannia virescens* alters its movement dynamics under parametric manipulations of illumination. We hypothesized a concomitant switch in both active sensing (an overt behavior) and multisensory reweighting (an internal control computation). To test this, we varied illumination levels from 0.1 to 210 lx as fish tracked a moving refuge. We discovered that in a neighborhood of a critical threshold (on the order of 1 to 10 lx), small increases in illumination led to dramatic changes in both active sensing and multisensory control, specifically in 1) steep reductions in fish head and tail movements and 2) decreased refuge tracking phase lag. Outside of this threshold, large changes in illumination only caused mild changes in behavior. A control-theoretic model that dynamically modulates the weights of vision and electrosense due to illumination changes explains the changes in closed-loop behavior in our experiments. Our findings enhance our understanding of active sensing, multisensory reweighting, and locomotor control.

Keywords: active sensing, multisensory reweighting, locomotion, control theory

Introduction

When navigating the natural environment, animals gather information from various senses, such as visual, tactile, and auditory cues [1–4]. During such navigational behaviors, animals also *internally reweight* streams of sensory information so that larger sensorimotor gains are applied to the sensory streams with the least uncertainties [5–8]. For instance, humans adjust the relative weights of vision, proprioception, and vestibular sensory information to maintain balance under different scenarios, such as when their eyes are closed or when the proprioception of their legs are perturbed [9, 10]. Likewise, electric fish can reweight streams of visual and electrosensory information [11].

Critically, uncertainties in sensing do not only lead to a passive, internal reweighting of streams of sensory information; they can also lead to dramatic changes in *overt active sensing behavior*, where animals induce ancillary movements to improve sensory perception in one or more modalities [3, 12–14]. For example, when crepuscular hawkmoths search for nectar under dim light, they use their proboscis to actively probe a flower's surface to sense its shape and texture and, critically, the temporal dynamics of the active sensing behavior depends on the salience of mechanical features of the flower [15]. While station-keeping inside a refuge, electric fish actively control their back and forth movements to enforce non-zero relative movement between their receptors and the refuge [16]; these active sensing movements maintain the variance of the sensory error signal in a manner that resembles stochastic resonance [17] but at the behavioral level [18]. Rapid active movements are thought to enhance sensing [19, 20] and feedback control [21]. In addition to fore-aft oscillations, these fish also actively bend their tails in response to changes in sensory conditions [13], likely another form of active sensation. Computational models based on information theory [14, 22] and control theory and state estimation [21, 23, 24] have emerged recently that may help explain the genesis of these active movements.

Active sensing (an overt behavior) and multisensory reweighting (an internal computation) are not mutually exclusive. Thus, we take the next step of investigating how these processes are modulated simultaneously under perturbations to the available sensory information using the weakly electric glass knifefish *Eigenmannia virescens*. *Eigenmannia* relies heavily on its two exteroceptive senses, vision and electrosense, [11, 25, 26] to navigate its environment. These fish also excel at a locomotor tracking behavior: by actuating the anal ribbon fin [27, 28], they swim forward and backward nearly equally well. Without prior training, these fish readily hover inside a moving refuge with precise positional and temporal coordination (Fig. 1A) [29]. The robust tracking performance, as well as illumination-dependent movement strategies [13, 16], has made *Eigenmannia* an ideally suited model organism for sensorimotor control studies [30, 31].

In this study, we parametrically examined the effect of illumination on both active sensing and multisensory control as *Eigenmannia* tracked a pseudo-randomly moving refuge under a broad range of lighting conditions (0.1 to 210 lx). We discovered that illumination mediated a switch at a threshold (on the order of 1 to 10 lx, in which slight increases or decreases in illumination produced large decreases or increases, respectively, in active sensing movements. We also discovered a similar threshold in the fish refuge tracking dynamics, especially the phase lags which rose sharply at frequencies above 1 Hz when illumination was decreased near the

threshold. We formulated a control-theoretic multisensory reweighting model (Fig. 1B) that recapitulates our findings, indicating that *Eigenmannia* dynamically changed the relative sensory weights between electrosense and vision in a manner that appears similar to hawkmoths that dynamically reweight visual and mechanosensory information when feeding from a moving flower [32].

The illumination threshold we discoverd, which simultaneously and abruptly alters both internal sensory reweighting and overt active sensing behavior, could foster further investigation on how animals respond to sensory conflicts [11, 33] under different sensory weights, and on how animals solve the explore-vs.-exploit problem [21] under a range of sensory conditions.

Results

We recorded tracking responses of untethered fish inside a moving refuge using a camera that imaged the fish from below (Fig. 1A). We digitized the horizontal position and 2D body shape of five individual fish in 20 s trial duration for 8–20 trials per condition. Experiments were performed for illumination levels ranging from 0.1 to 210 lx on a logarithmic scale (Table S1). This illumination range, from a dark to a well-lit aquarium, enabled us to test the parametric effects of illumination on active sensing and locomotor control (Fig. 1B) during refuge tracking. Lighting levels were randomized across trials. The refuge movement followed a pseudo-random sum-of-sines stimulus comprising 12 frequency components (see Material and Methods) [34, 35].

Fish exhibit an illumination-dependent switch in fore-aft active sensing

Across illumination levels, the frequencies present in fish movement aligned with those of the refuge (Fig. 1D,F,H). The averaged movement traces of fish and refuge were highly correlated (Fig. S1A). Together, this implies that fish consistently tracked the refuge across all tested illumination levels.

We observed an increase in the variability in fish fore-aft movements (along the rostrocaudal axis) under decreasing illumination (see progression in Fig. 1C,E,G). The fore-aft movements were composed of the refuge-tracking movements (sharp peaks in the frequency response at the 12 refuge stimulus frequencies) as well as ancillary active sensing movement which can be observed most clearly as highly variable movement in the time domain (Fig. 1C,E,G).

The fore-aft movement variance as a function of illumination of one representative fish (Fig. 1I) and that of the population (Fig. 1J) indicated an increase in fore-aft active sensing movements as a function of decreased sensory salience as would be expected from prior literature [13, 16, 21]. Building on prior work, we examined active sensing in relation to paremetrically varied illumination levels, revealing that the variance of fish fore-aft movement changed in a sigmoidal pattern [36–38], suggesting the presence of an illumination-mediated switch. To fully characterize the transition, we fitted a sigmoidal function to the movement variance as a function of the log of the illumination level (see Material and Methods and Table S2). The sigmoidal fit was also better than polynomial fits, as evidenced by both adjusted R^2 and the Akaike Information Criterion (AIC), shown in Fig. S1B,C. The sigmoidal fit of the combined fish data indicated the presence of an illumination-dependent

Fig. 1. Illumination-dependent behavioral transitions in fish head movements. (A) Schematic of the experimental setup with the following components: 1) linear actuator, 2) LED strip, 3) refuge, 4) first surface mirror, 5) infrared (IR) lights, and 6) high-speed camera. (B) Block diagram of the closed-loop refuge-tracking system in fish. The refuge is actuated with a pre-designed sum-of-sines reference stimulus, $r(t)$, along the rostrocaudal axis. To track the refuge, fish use vision and electrosense to integrate the "sensory slip" $e(t)$, which is the difference between the refuge movement $r(t)$ and the fish's own movement $y(t)$. The central nervous system processes the sensory slip and generates the necessary actuation to control swimming mechanics. Experimental manipulation of lighting conditions affects the sensory processing of the sensory slip, which in turn influences the refuge-tracking behavior. (C-H) Fish head movement traces (C,E,G) under low (0.1 lx, $n = 17$), medium (2.0 lx, $n = 20$) and high (150 lx, $n = 13$) illumination, and the corresponding discrete Fourier transforms (D,F,H) from a single representative fish (blue) tracking the refuge movement (red). Lighter shades: individual position traces. Darker shades: average fish head movements. The solid lines and the shaded regions in (D,F,H) denote mean and the standard error of mean (s.e.m), respectively. (I) Fish head movement variance of the same fish vs. illumination. Each marker represents the mean across trials, while the shaded region denotes the s.e.m. The dashed black line denotes the sigmoidal fit to the data. (J) Combined fish head movement variance for all individuals ($N = 5$) vs. illumination. Different colors represent different fish; each marker is the mean of 8–20 trials. The dashed black line and the gray-shaded region denote the sigmoidal fit to the combined data and 95% prediction interval, respectively. See Table S2 and Fig. S1B,C for fitting details.

threshold. At 0.95 lx the fish head movement variance in the rostrocaudal axis began to decrease sharply with respect to the illumination, until reaching 5.32 lx (Fig. 1J, Table S2). Outside this illumination range, the rate of change in variance became largely insensitive to illumination changes.

In addition to fore-aft active sensing movements, *Eigenmannia* also bends its body and tail to enhance active sensing [13]. Here, we analyzed whole-body bending motion as a parametric function of illumination from 0.1 to 210 lx by tracking 12 equally spaced points along the center line of the fish's body, from the head tip b_0 to the tail end b_{11} (Fig. 2A,B). We analyzed body bending and tail movements relative to the fish's body frame by establishing a body frame at the head position b_1, with orientation given by best-fit line through the three points b_0, b_1, and b_2 (see Material and Methods and Fig. S4).

We found that the tail beat amplitude (b_{11}) decreased under higher illumination (Fig. 2A–F) as did the corresponding Fourier spectrum amplitude (Fig. 2G, Fig. S2). The Fourier spectrum of the velocity revealed a prominent peak between 1.0 and 1.5 Hz that also decreased with increasing illumination (Fig. 2H, Fig. S2). We observed a pronounced illumination-dependence in tail movement, again following a sigmoidal trend (Adj $R^2 \geq 0.9$) in four out of five fish (Fig. 2J, sampled fish in Fig. 2I and Fig. S1D). However, one fish's (orange) decrease in variance was better fit by a quadratic (Adj $R^2 = 0.79$) than the sigmoidal model (Adj $R^2 = 0.62$), shown in Fig. 2J. Taken together, these findings demonstrate that fish actively regulate their body movements in response to changing illumination during refuge-tracking tasks in such a way that the intensity of these active sensing movements declines sharply once illumination surpasses a certain threshold.

Tracking phase lag decreases sharply near the illumination threshold

As fish actively moved for sensing, they simultaneously tracked the trajectories of the refuge, as can be seen in the time-domain tracking response (Fig. 1C–H) [31]. How does illumination mediate performance during this refuge tracking task? We answered this question by applying a sum-of-sines refuge stimulus [34] and applying traditional frequency domain system identification approaches to quantify fish refuge tracking performance over the frequency range of 0.1 to 2.05 Hz [34, 35, 39, 40]. We found that at low frequencies (< 0.2 Hz), fish performance approached perfect tracking across illumination conditions, with a gain close to 1 and a phase lag

Fig. 2. Fish body dynamics changed in response to illumination. (A-F) Fish body movements over 20 seconds are depicted by 12 colored markers overlaid on the fish bottom view images (A,C,E). The corresponding temporal traces of the transverse fish body movements in time domain are shown in (B,D,F) under three illuminations (0.4, 2.0 and 150 lx). **(G,H)** Average discrete Fourier transform (DFT) magnitude of transverse tail movement (G) and the corresponding velocity (H) across trials under different illumination conditions from one sampled fish (fish 1). Different colors denote different illumination levels. **(I)** Variance of transverse tail movement across different illumination from one sampled fish (fish 1). The markers and shaded regions denote the mean and the standard error of mean, respectively. The dashed black line denotes the sigmoidal fit to the data. See Table S2 for fitting details. The data corresponding to 0.1 lx, 1 lx and 12 lx are omitted in (G–I) due to small sample size ($n \leq 3$); see Fig. S1D, Fig. S2 for full version. **(J)** Combined transverse tail movement variance for all individuals ($N = 5$) under different illumination. Different colors represent different fish; each marker is the mean of 2–17 trials. Except for one of the fish (orange, Adj R^2(sigmoid) = 0.62, Adj R^2(quadratic) = 0.79) all other fish showed sigmoidal trend (Adj R^2(sigmoid) $\geq$ 0.9, $N = 4$). The black dashed line and the gray-shaded region denote the sigmoidal fit to the combined data and 95% prediction interval, respectively. See Table S2 fitting details.

near 0° (Fig. 3A,B). At higher frequencies, the gain and phase "rolled off" to lower values, as expected. Notably, there were no significant differences in gain across illumination levels, but a clear increase in phase (decrease in phase lag) as illumination increased, especially at high frequencies greater than 1.55 Hz. The three highest sum-of-sines frequencies (1.55 Hz, 1.85 Hz, and 2.05 Hz) displayed the most prominent illumination dependence. To quantify this trend, we averaged the tracking phase values for these frequencies and observed a sigmoidal trend in tracking phase (Fig. 3C) that bears striking simililarity to the trend in active sensing movements of the head position (Fig. 1I,J) and tail movement (Fig. 2I,J). For all five fish, the sigmoidal trend was better compared

to the polynomial fits (Table S2). This combined data exhibits a threshold region between 3.56 lx and 18.17 lx, and within this range phase lag decreased sharply as illumination increased. Outside of this range, the phase lag was generally insensitive to changes in illumination. It is possible that this change in phase lag arises from an illumination dependent delay [41] or perhaps a more complex multisensory reweighting [32], which we examine in the next section.

Fig. 3. The closed-loop frequency responses of fish tracking.
(A,B) Representative Bode gain (A) and phase (B) plot of fish frequency responses v.s. illumination. Bode gains tightly distribute over the refuge frequency range (0.1 – 2.05 Hz), whereas Bode phase values, initially tightly grouped, become more dispersed at higher frequencies (> 0.5 Hz). Different colors denote the illumination scale. See Fig. S3 for results from all five fish. **(C)** Closed-loop high frequency tracking phase vs. illumination for all individuals ($N = 5$), computed by averaging the phase in the 1.55 – 2.05 Hz frequency range (shaded region in (B)). Each color represents a subject; each marker is the mean of 4 – 17 trials. The dashed black line and the gray-shaded region denote the sigmoidal fit to the combined data and 95% prediction interval, respectively. See Table S2 for details on fitting.

Fish dynamically reweight vision and electrosense under changes in illumination

Eigenmannia primarily uses its visual and electrosensory systems to process environmental cues. How does it tune these sensing modalities to bring about the illumination-mediated behavioral transitions? To address this question, we proposed a control-theoretic model involving these two sensory systems. We modeled the dynamics as a closed-loop system (Fig. 1B), including distinct sensory dynamics for vision, S_V, and electrosense, S_E. In the model, the controller, C, represents the sensorimotor transform performed by the nervous system, and the musculoskeletal plant, P, represents how the swimming dynamics transforms motor commands into fish movement (Fig. 1B).

Previous work explored the role of illumination on flower-tracking behavior in hawkmoths [41, 42]. In an illumination-dependent control system model, a single temporal processing delay was sufficient to explain the moth flower tracking behavior in different illumination conditions [41, 42]. However, we found that simply adding a delay block (Fig. 4A) with the transfer function $e^{-s\tau(\lambda)}$, where λ is the illumination level and $\tau(\lambda)$ is the illumination-dependent time delay, failed to explain the fish behavior (Fig. 4B,C).

Fig. 4. Illumination-dependent sensory reweighting explains the observed behavior in fish.
(A) A schematic showing the candidate heuristic of illumination-dependent sensory delay. The sensory system is represented by $S(s)$ (purple dashed box), containing the illumination-dependent sensory delay, $\tau(\lambda)$, visual system $S_V(s)$, and electrosensory system $S_E(s)$. This heuristic is under the assumption that more sensory delay τ is needed as illumination level λ decreases. The central nervous system and the swimming dynamics of fish are depicted as the controller, $C(s)$, and plant, $P(s)$, respectively. The open-loop sensory system, controller, and plant cascade is depicted as $G(s)$ (pale pink dashed box). This process is under feedback control. **(B)** Bode plots of open-loop sensory system, controller, and plant cascade $G(s)$, generated from the experimental data of a representative fish (fish 1) under high (210 lx, peach squares) illumination condition. The best fit of data in high (210 lx) illumination obtained from the variable delay model is shown in peach colored line. **(C)** Bode plots of $G(s)$ generated from the experimental data of the same representative fish in (B) under low (0.1 lx, black circles) illumination condition. Adding a pure delay to the fitting in high (210 lx) illumination in (B) (black line) does not predict data in low (0.1 lx, black circles) illumination condition well, providing the differences in gain and phase at low frequencies below 0.55 Hz (blue shaded region). **(D)** Schematic showing the proposed sensory reweighting model, where "sensory slip" $e(t)$ is processed by the sensory system $S(s)$ (purple dashed box), containing visual pathway $S_V(s)$ and electrosensory pathway $S_E(s)$ with sensory weights, $\alpha(\lambda)$ and $1 - \alpha(\lambda)$, respectively. α is a variable depending on illumination level λ. **(E)** Bode plot of the averaged $G(s)$, from bootstrapped datasets (black) and the corresponding fitted result (red) from the sensory reweighting model for a representative fish (fish 4) at 7.1 lx. The lines and shaded regions denote the corresponding mean and standard deviation of the 100 bootstrapped data and their corresponding fitted results, respectively. **(F)** Sensory weights of the visual pathway, $\alpha(\lambda)$ across different illumination levels are presented for all individuals ($N = 5$). Different colors represent different fish. The dashed black line and the gray-shaded region denote the sigmoidal fit to the combined data and 95% prediction interval, respectively. See Table S2 for fitting details. The characteristic "S" shape denotes that above a certain illumination threshold, fish began to rely more on vision, resulting in higher visual weight. **(G)** The hypothetical "electrosense only" pathway (top, deep aquamarine color dashed box) with transfer function $G_E(s)$ and "vision only" pathway (bottom, yellow dashed box) with transfer function $G_V(s)$. **(H)** Bode gain (G, top) and phase (G, bottom) plots for the open-loop sensory system, controller, and plant cascade of a representative fish (fish 1) under the "electrosense only" (deep aquamarine) and "vision only" (golden yellow) conditions. In the "vision only" condition, there is a notably lower phase lag and a flatter gain roll-off compared with "electrosense only" condition. **(I)** Frequency vs. frequency domain tracking error plots of the experimental data from a representative fish (fish 1) at 0.1 lx and 210 lx, placed adjacent to the "vision only" and "electrosense only" simulated results from the experimental data for the same fish. The similar trends align with experimental observations, where higher electrosensory weights correspond to higher tracking error, especially at frequencies > 0.55 Hz.

The time-domain and frequency-domain analyses presented earlier suggest an illumination-mediated switching behavior in fish. Below a certain illumination value, fish engaged in more ancillary active sensing movements, while above a certain higher illumination value, fish movement variance decreased. At low visual salience conditions, the extraneous movements enhance active sensing with electrosense, whereas in well-lit conditions, such movements attenuated, suggesting a heavier reliance on vision. Based on these observations, we propose an alternative illumination-dependent sensory reweighting model, where the error signal "sensory slip" $e(t)$ is processed by the visual and electrosensory pathways with illumination-dependent sensory weights, $\alpha(\lambda)$ and $1 - \alpha(\lambda)$, respectively, in a manner similar to a model recently proposed for hawkmoths [32]. In this model, we assume that the transfer functions for vision $S_V(s)$, electrosense $S_E(s)$, the controller $C(s)$, and the plant $P(s)$ are all illumination-invariant (Fig. 4D). Thus, the impact of illumination is solely captured by the sensory weights, $\alpha(\lambda)$ for vision and $1 - \alpha(\lambda)$ for electrosense, in which a single illumination-dependent parameter α serves to complementarily reweigh vision and electrosense.

To test the model, we first computed the open-loop frequency response function (FRF), $G(j\omega)$, from the experimental data. After that, we derived an optimal $G_V(j\omega)$, $G_E(j\omega)$, and a set of α for each illumination condition tested which minimized the cumulative mean-squared error (MSE) between model $\hat{G}(j\omega)$ and data $G(j\omega)$ at frequencies of interests from all $9 - 14$ illumination levels (see Material and methods and Supplemental Methods for further details). The fitted open-loop FRFs, based on the sensory reweighting model, dramatically improved the fit when compared with the "sensory delay" model (Fig. 4A-C), matching the experimental gain

and phase responses (e.g. Fig. 4E). However, the fitting quality declined for low illuminations, due to greater trial-by-trial variance in the data. Interestingly, the computed visual weight α presented similar sigmoidal trend across different fish (Fig. 4F) as found for other parameters of active sensing and control.

The proposed sensory reweighting model allows us to compute the open-loop transfer function from error to movement as follows:

$$\hat{G}(s) = P(s)C(s)[(1-\alpha)S_E(s) + \alpha S_V(s)]$$

$$= (1-\alpha)\underbrace{P(s)C(s)S_E(s)}_{G_E(s)} + \alpha\underbrace{P(s)C(s)S_V(s)}_{G_V(s)}, \tag{1}$$

Here, the terms $G_E(s)$ and $G_V(s)$ can be thought of as the "electrosense only" and "vision only" pathways, respectively (Fig. 4G), as would be found in a hypothetical sensory ablation experiment [43]. We found the illumination-invariant open-loop system transfer function for the "electrosense only" condition $G_E(s)$ has greater phase lag and a sharper gain roll-off (Fig. 4H) compared to that of "vision only" $G_V(s)$. Moreover, fish exhibited a significantly lower frequency domain tracking error across the frequency range of $0.1 - 2.05$ Hz in "vision only" hypothetical condition compared with that in the "electrosense only" hypothetical condition (Fig. 4I). The experimental frequency domain tracking error at the lowest (0.1 lx) and highest (210 lx) illumination conditions were between the two hypothetical extreme conditions (Fig. 4I) as expected. Taken together, these data indicate a complementary illumimance-dependent sensory switch in the gains applied to vision and electrosense.

Discussion

In this study, we applied a single-parameter change in visual salience to evaluate refuge tracking of weakly electric fish. Under a broad range of illumination levels, we examined the body motion and frequency responses of the fish. At lower illumination levels, fish not only presented higher head-position variance across trials and more vigorous tail-bending movements, but also presented higher phase lag in the high-frequency responses. The former implied more active movements for electrosense, while the latter implied the outcome of multisensory control. Notably, we observed a similar threshold on the order of 1 to 10 lx for various locomotion metrics, namely trial-by-trial variance in head locations, tail bending, and refuge tracking phase lag. Around this threshold, small changes of illumination level brought about significant changes in the outputs. This illumination threshold suggested a switch from a "electrosense dominant" sensing mode to a "vision dominant" mode. Then, we proposed a control theoretic sensory reweighting model that captured this illumination-dependent switch. This research sheds new light on illumination-dependent sensing and control in object tracking tasks, enhancing our understanding of animal active sensing, multi-sensory integration, and locomotor control.

Active movements enhances sensory processing

We observed that as the lighting intensity decreased, the trial-by-trial variance in fish head movement trajectories and the tail-bending magnitudes both increased. This supports earlier findings that *Eigenmannia* engages in more vigorous movements to enhance electrosense and compensate for the lack of vision [13, 16, 44, 45] to prey-capture [46–48]. In low light, weakly electric fish usually generate high frequency fore-aft movements [13, 14, 21, 44] and actively bend the trunk and tail [13, 46, 48–50]. Such movements, the hallmarks of active sensing, not only increase the overall sensory volume of fish [20], but may also serve to "up-modulate" frequency content to match the spatial-temporal properties of neural circuits [13] and prevent perceptual fading [51]. Specifically, tail bending induces changes in the relative geometry between the electrosensory organ and the electroreceptor, which generally causes an amplitude modulation: a stronger electric field on the ipsilateral side of bending while a weaker stimulation on the contralateral side [52, 53]. The principal frequency-domain velocity amplitude of tail bending centered at around $1.0 - 1.5$ Hz across illumination levels (Fig. 2H, Fig. S2F– J). Such modulation might be extracted in the neurons that are selective for amplitude modulation at the same frequency band in fish mid-brain [54, 55]. Tail bending also affects electrosense by retuning neurophysiological activities; the repeated tail beating could be canceled by descending feedback sent to the Pyramidal cells in the electrosensory lateral line lobe (ELL), a cerebellar-like structure of fish [13, 56, 57].

Indeed, whole body fore-aft active movements driven by the ribbon fin [27, 28] and active tail bending [13] likely help fish obtain sensory information. However, at the same time, these motions incur energetic costs [20]. Several theories have been proposed recently for rationalizing these movements in the face of the associated costs [14, 21, 23] and future work could extend these theories to allow for parametric manipulations of salience in one modalitity (i.e. illumination) to examine which (if any) of the models predict the switches in active sensing and control we observed experiemntally.

The significance of the illumination threshold

The illumination threshold on the order of 1 to 10 lx observed in this study reflects an intricate feature of animal sensorimotor control systems. Sensory movement strategies were rapidly adjusted in response to changes of illumination throughout the threshold, then "saturated" as illumination level surpassed around the order of 10 lx (Fig. 1I,J, Fig. 2I,J). Note that across experimental trials, the illumination conditions were applied in a pseudo-randomized order, so it was unlikely for the fish to adapt to certain patterns of illumination change. Instead, the results suggested that within the neighborhood of illumination threshold, visual receptors of *E. virescens* seem to be more sensitive to illumination change so that fish can gather adequate quantity of visual information and quickly reweight vision and other senses. The threshold range occurs at relatively low illumination, which could be result from *E. virescens*' evolutionary context; as a nocturnal species living in turbid water and in complex root and littoral habitats in South America, *E. virescens* may have visual receptors more suitable for relatively low light intensities [58, 59].

Furthermore, even though weakly electric fish assemble convergent evolution trends [60], different species

have different visual and electrosensory systems. Thus, it is likely that the illumination threshold would vary for different species. For instance, the black ghost knifefish *Apteronotus albifrons* has smaller and less developed eyes compared to other species of Gymnotiformes that rely relatively more heavily on vision [61,62]. Another species, the blind cavefish *Eigenmannia vicentespelea*, inhabits in completely dark caves in central Brazil with poorly-developed or missing eyes [63,64]. Compared with nearby epigean (surface) relatives *Eigenmannia trilineata* in the same river system but with well-developed eyes and distinctive markings, *E. vicentespelea* generates stronger electric discharges [64]. Therefore, it is possible that *E. vicentespelea* would even be less sensitive to the variations light intensity changes described in this study, but rather be sensitive to electrosensory manipulations, such as inhibiting fish electric organ discharge (EOD) through jamming [14, 65, 66] or increasing water conductivity [13, 48]. Further investigation on species comparison can relate the sensing and locomotion strategies to the evolutionary context, as well as further explore energy optimization and performance improvements across species.

Sensory reweighting and integration in sensorimotor control

We proposed a control-theoretic sensory reweighting model for the refuge tracking task of weakly electric fish that captured responses over a broad range of illumination levels. Under the assumption that fish dynamically integrates visual and electrosensory pathways, our model suggested that as illumination levels decreased, fish tended to adjust the weights of two sensory pathways and put more weight on the electrosensory pathway than the visual one. From Fig. 4H, we see that electrosensory pathway possesses larger phase lag than that in visual pathway, thus requiring longer integration time than visual pathway. This was surprising to us and the reasons for this are not entirely clear. One speculative possibility is that electrosense relies on whole-body active sensing movements which, by their nature, require time to complete. In any case, the increased phase lag in lower illumination appears to be due to the increased weight of electrosense and the intrinsically larger phase lag of the electrosensory pathway.

We applied linear time-invariant (LTI) control theory tools to construct our model, i.e., a linear combination of illumination-independent transfer functions of visual and electrosensory pathways multiplied by their corresponding illumination-dependent weights. It is critical to note, however, that the sensory reweighting process itself is fundamentally a nonlinear one. Our application of LTI theory inherently assumes that the nonlinear sensory reweighting process was sufficiently *fast* that, during any given trial, the weights for each sensory pathway were time-invariant after a brief reweighting process. This is, in a sense, opposite to the assumption by Yang et al. (2021) [67] and Yang et al. (2024) [35] in which LTI models were used to study learning, wherein the assumption was that the learning rate was sufficiently *slow*.

Sensory reweighting is commonly studied across taxa. For instance, in human balancing control which integrates visual, vestibular, and proprioceptive sensory information, researchers usually apply sensory perturbations in the environments and test the relative contribution that different sensory systems make for completing the task [9, 68, 69]. In cross-modal object recognition of weakly electric fish *Gnathonemus petersii*, fish were

trained to use either vision or electrosense to discriminate two objects and could accomplish the task using only the untrained sense [70]. Results showed that they dynamically reweighted the object-related sensory input based on reliability of the sensory inputs to minimize the uncertainty and optimize sensory integration [70]. Researchers also found that rats and humans dynamically adjusted weights assigned to each sensing modality based on their reliability to help decision-making [71]. Theories such as nonlinear adaptive control models [10] and Bayesian framework [72] have been applied to model the multisensory reweighting.

Researchers also introduce sensory conflicts, i.e., perturbing the system simultaneously with different sensory inputs, to test how different sensing modalities of animals integrate in sensorimotor behaviors such as refuge tracking of weakly electric fish (vision and electrosense) [11], wing steering in fruit flies (vision and haltere mechanosense) [73], and flower tracking of hawkmoths (vision and proboscis mechanosense) [32, 43]. Although neural systems adopt complex encoding/decoding mechanisms possessing nonlinearity [74–77], many studies have found that sensory information integrated approximately linearly under conflicts across different sensorimotor behaviors [11, 32, 43]. There are also examples showing that linearity does not hold for sensory integration. For instance, linear superposition of haltere-driven and visually driven responses predicted wing steering responses but failed to predict gaze responses of *Drosophila* [73]. These studies illustrate that despite that the elements in nervous systems are intrinsically nonlinear, at least within a certain range of conditions for behaviors, the combined activity often presents itself linearity [78]. Further investigation from both behavioral level and circuit level can reveal more insights on the integration of various sensing modalities across animals.

Acknowledgment

We thank Eric S. Fortune for helpful discussions and suggestions; we also thank Calvin Yeh for contributions to the machine learning-based image processing pipeline. This work was supported by the Office of Naval Research under grant no. N00014-21-1-2431 (N.J.C), the National Science Foundation under grant no. 2011619 (N.J.C), and the Provost's Undergraduate Research Award (PURA) at Johns Hopkins University (H.Y.).

Author Contributions

H.Y., Y.Y., and N.J.C. co-designed the experiments; H.Y. and Y.Y. developed analysis methods; H.Y. collected data; H.Y., Y.Y., and D.B., processed and analyzed data; N.J.C. oversaw data analysis, supervised the project, and obtained funding; H.Y., Y.Y., D.B., and N.J.C. interpreted results; H.Y., Y.Y., D.B. and N.J.C wrote the original draft.

Data and software availability

An archived version of raw and processed datasets and the analysis code will be available through the Johns Hopkins University Data Archive in final submission.

Material and methods

Subjects

Adult glass knifefish *Eigenmannia virescens* (length 12 – 15 cm) were purchased from a commercial vendor and housed according to published guidelines [79]. The water temperature and conductivity in fish tank were maintained at 27 °C and 150 – 250 μS/cm. Fish was transferred to the experimental tank at least 12 hours before experiments. Animal care and experimental procedures were approved by the Johns Hopkins Animal Care and Use Committee and were in accordance with guidelines from the National Research Council and the Society for Neuroscience.

Experimental apparatus

The experimental apparatus was similar to those in previous work [16, 21, 35]. The setup included a linearly actuated PVC refuge, a 17-gallon rectangular, clear glass tank, a mirror, infrared (IR) lights, and a video camera (Fig. 1A). This system controlled a standardized input trajectory of the refuge, and recorded refuge and fish motion with live video footage.

A 122 cm RGB LED strip (Aclorol, Cincinnati, Ohio, USA) was secured around the tank at about 5 cm below water surface, providing approximately equal amount of illumination within the tank environment. The LED strip was controlled via Arduino Uno (Arduino, Turin, Italy) command running on a computer, providing a maximum illumination of 500 lx. The experimental conditions spanned a wide spectrum on the logarithmic scale. To minimize additional sources of lighting, the experimental space was blocked off with black curtains that spanned from the ceiling down to the floor. The computer monitor was at the minimum brightness level and turned away from the fish tank.

A 30.48 cm × 45.72 cm first surface mirror (FSM first surface mirror LLC, Toledo, OH, USA) was installed at about 45° slanted under the experimental tank, reflecting images of the bottom view of the fish and refuge. Videos were captured by a high-speed camera (pco.1200, PCO AG, Kelheim, Germany) through mirror reflection. Two infrared (IR) lights (CMVision Technologies Inc., Houston, TX, USA) were installed under the experimental tank. These IR lights, invisible to the fish, helped enhance the image quality when recording videos in low light intensities. A 15 cm PVC refuge was attached from the linear actuator to the bottom of the fish tank.

Stimulus

We designed a pseudo-random periodic sum-of-sines stimulus to control the refuge movements. The input signal was constructed with the following equation, inspired from previous work [34, 35] for system identification of the fish's frequency-domain tracking responses:

$$r(t) = \sum_{i=1}^{12} \frac{1}{2\pi f_i} \cdot \cos(2\pi f_i t + \phi_i). \tag{2}$$

Here, $f_i = 0.05 \times [2, 3, 5, 7, 11, 13, 19, 23, 29, 31, 37, 41]$ Hz. The phases ϕ_i were randomly chosen to create a unique phase shift for each frequency component. The amplitude of each sinusoidal component was modulated so that the velocity amplitude of each component was kept constant to prevent saturation in tracking high frequencies. Since the sum-of-sines signal contains prime multiples of basis frequency at 0.05 Hz, the period for the stimulus was 20 seconds. With 12 distinct frequency peaks, the time-domain input would be computationally infeasible for the fish to predict [34].

Experimental Procedure

During experiments, each fish received 5 trials of 9 to 14 illumination stimuli profiles (Table S1). Data was collected with pseudo-randomized trials, where all five fish experienced similar randomization orders, despite slight changes in the numbers of illumination conditions tested between different fish. Before starting each trial, the illumination level was adjusted using an Arduino program. For verification, we put a light meter (LATNEX LM-50KL, Toronto, Ontario, Canada) close to the refuge position near fish tank to measure the illumination level. Each trial lasted for 70 seconds total with a 10-second ramp-up signal at the beginning followed by three 20-second periods of the input signal. Between every two trials, there was a 60-second break with the refuge system paused to prevent fish fatigue.

The linear actuator drove the refuge movement controlled by a custom LabVIEW program [16]. To rule out the effect of fish head direction, we applied the refuge motion trajectory in Equation 2 when the fish head pointed to the right in camera view, and applied the inverted signal of Equation 2 when the fish head pointed to the left. This allows the fish to experience the same tracking task in all trials.

During experiments, we visually inspected real-time tracking plots and identified large events of tracking loss, and then re-ran trials when needed. When it was not possible to keep more than one out of three 20-second repetitions, more follow-up trials were conducted in the original pseudo-randomized order. A video was saved at the end of each trial, capturing the bottom view of refuge and fish at 25 frames per second (FPS). Each video contains 1777 frames (640 pixels × 190 pixels).

Each subject's data was collected within two consecutive days in up to two experiment sessions, with each illumination level having five trials (15 repetitions total). Some conditions may have more raw data than others, depending on the difficulty of data collection. The same procedure was standardized and repeated across $N = 5$ subjects.

Data Preparation

After all data collections, we obtained about 45–52 trial folders for each fish. We then processed videos with custom DeepLabCut [80] machine learning models, MATLAB, and Python OpenCV to obtain 1) the refuge and fish head position, used for system identification; 2) pixel coordinates along the entire fish body for analysis on fish tail bending dynamics. After obtaining time-series pixel coordinates of the fish head, we shifted each video frame so that the fish head was fixed at a designated "anchor point" at $x = 220$ pixels and $y = 110$ pixels.

Another image processing step ensured horizontal alignment of the fish body axis in all frames. This minimized error in tail position analysis due to whole-body rotations. Then, we obtained body-frame position data as shown in Fig. 2A-F. See method details in Supplementary Materials (Fig. S4).

Data Analysis

Data Clean-up

The data outliers mainly include: 1) failure of trackers (tracking losses), 2) failure in data collection (i.e. fish left the refuge during experiments), and 3) other trials that fish were in the refuge but did not follow the sum-of-sines trajectory. We first referred to experiment notes and excluded trials in which the fish left the camera view. The time-domain position data (20 seconds each) was plotted in MATLAB for further inspection. Trials with tracking losses were then identified and excluded. We finally identified and excluded other outliers, in which the fish were in the refuge but not tracking the sum-of-sines trajectory. For all trials in the same condition, we measured statistical distributions of the frequency domain data, mainly on the sum of square error (SSE) and Mahalanobis distances of each complex-numbered frequency response. Then, we formulated a conservative and fair metric to exclude outliers and preserved 80% of the data. The procedure details can be found in Supplemental Materials.

For body dynamics analysis, we captured pixel coordinates along the entire body up to the tail point. Visual inspection of the original videos and body-frame time-domain data were conducted. If the DeepLabCut pixel coordinates of the body exceeded the maximum possible x value ($x = 640$), then the trial was excluded. This makes sure that all the fish body data points are within the camera frame.

Frequency Response Function Estimation

Following similar system identification process described in Yang [40], we applied discrete Fourier transform (DFT) to the time-domain refuge position $r(t)$ and fish position $y(t)$ across all conditions for $N = 5$ fish, resulting in the refuge position $R[\omega]$ and fish position $Y[\omega]$ in the frequency domain.

After that, the frequency response function (FRF) of fish refuge tracking $H(j\omega)$ was estimated using empirical transfer function estimate (ETFE) [39]:

$$\hat{H}(j\omega) = \frac{Y[\omega]}{R[\omega]}, \tag{3}$$

where $\hat{H}(j\omega)$ is the estimated fish FRF $H(j\omega)$ using ETFE. Note that this computation is only defined at the 12 frequencies that the sum-of-sine stimulus contains, since $R[\omega] = 0$ at all other frequencies.

For the results shown in Fig. 3A-C, we applied the MATLAB `smooth` function to the FRF gain and phase data on across the frequency scale. The `smooth(z)` function smooths the data in column vector z using a

moving average filter like so:

$$zz(1) = z(1)$$
$$zz(2) = \frac{z(1) + z(2) + z(3)}{3}$$
$$zz(3) = \frac{z(1) + z(2) + z(3) + z(4) + z(5)}{5}$$
$$zz(4) = \frac{z(2) + z(3) + z(4) + z(5) + z(6)}{5}$$
$$\vdots$$

where $zz(\cdot)$ denotes the smoothed data points.

Frequency-Domain Tracking Error

To examine how the illumination affects refuge tracking performance of fish, we computed the frequency domain tracking error $\varepsilon(\omega)$ by the distance between $\hat{H}(j\omega)$ over 12 stimulus frequencies and the perfect tracking point $(1, j0)$ on the complex plane, where gain $= 1$ and phase $= 0°$, i.e.,

$$\varepsilon(\omega) = \|\hat{H}(j\omega) - (1, j0)\|, \tag{4}$$

where $j = \sqrt{-1}$.

Proposed Computational Model for Sensory Reweighting

We proposed a computational model for sensory reweighting in different illumination conditions based on the assumption that changes in illumination levels would result in reweighting in visual and electrosensory processing.

In our model, we proposed that the "sensory slip" $e(t)$ went to two frequency dependent open-loop transfer functions: "$S_E(s)$" (open-loop transfer function to electrosense) and "$S_V(s)$" (open-loop transfer function to vision). Two transfer functions were weighed by illumination-dependent weights $1-\alpha(\lambda)$ and $\alpha(\lambda)$, respectively, where λ is the illumination level in lx. The resulting electrosensory and visual signals were combined and processed into commands by the central nervous system, $C(s)$, and swimming dynamics $P(s)$. Thus, the open-loop transfer function was modeled as $(1 - \alpha)P(s)C(s)S_E(s) + \alpha P(s)C(s)S_V(s)$.

Since the FRFs of the closed-loop system were estimated already from experimental data, to open the feedback loop and obtain open-loop FRFs, we followed methods as described in [81]. Using algorithms in Supplemental Materials, we were able to find illumination-invariant $G_V(s)$, $G_E(s)$, and a set of α values in all illumination scales that minimize the fitting error to open-loop FRFs $G(s)$ computed from experimental data across all illumination conditions.

Statistical Analysis

All the statistical analysis was performed using custom codes written in R version: 4.3.0, R Core Team, and MATLAB R2024a, MathWorks. The statistical tests performed are: sign test, Mann-Kendall test, Augmented Dickey-Fuller test. The significance level was set to 0.05 for all tests. The experimental and simulation data are provided as either mean plus or minus the standard deviation ($\mu \pm$ s.d.) or mean plus or minus the standard error of the mean ($\mu \pm$ s.e.m).

References

[1] G. H. Jacobs, J. A. Fenwick, and G. A. Williams, "Cone-based vision of rats for ultraviolet and visible lights," *J. Exp. Biol.*, vol. 204, no. 14, pp. 2439–2446, 2001.

[2] N. J. Cowan, J. Lee, and R. J. Full, "Task-level control of rapid wall following in the american cockroach," *J. Exp. Biol.*, vol. 209, no. 9, pp. 1617–1629, 2006.

[3] R. A. Grant, P. M. Itskov, R. B. Towal, and T. J. Prescott, "Active touch sensing: finger tips, whiskers, and antennae," *Front. behav. neurosci.*, vol. 8, p. 50, 2014.

[4] J. B. Kelly, "Effects of auditory cortical lesions on sound localization by the rat," *J. Neurophysiol.*, vol. 44, no. 6, pp. 1161–1174, 1980.

[5] D. C. Knill and A. Pouget, "The bayesian brain: the role of uncertainty in neural coding and computation," *Trends Neurosci.*, vol. 27, no. 12, pp. 712–719, 2004.

[6] D. C. Knill, "Robust cue integration: A bayesian model and evidence from cue-conflict studies with stereoscopic and figure cues to slant," *J. Vis.*, vol. 7, no. 7, pp. 5–5, 2007.

[7] W. J. Ma, "Signal detection theory, uncertainty, and poisson-like population codes," *Vis. Res.*, vol. 50, no. 22, pp. 2308–2319, 2010.

[8] R. J. van Beers, C. M. van Mierlo, J. B. Smeets, and E. Brenner, "Reweighting visual cues by touch," *J. Vis.*, vol. 11, no. 10, pp. 20–20, 2011.

[9] J. H. Pasma, T. A. Boonstra, S. F. Campfens, A. C. Schouten, and H. Van der Kooij, "Sensory reweighting of proprioceptive information of the left and right leg during human balance control," *J. Neurophysiol.*, vol. 108, no. 4, pp. 1138–1148, 2012.

[10] S. Carver, T. Kiemel, and J. J. Jeka, "Modeling the dynamics of sensory reweighting," *Biol. Cybern.*, vol. 95, no. 2, pp. 123–134, 2006.

[11] E. E. Sutton, A. Demir, S. A. Stamper, E. S. Fortune, and N. J. Cowan, "Dynamic modulation of visual and electrosensory gains for locomotor control," *J. R. Soc. Interface.*, vol. 13, no. 118, p. 20160057, 2016.

[12] R. A. Grant, B. Mitchinson, C. W. Fox, and T. J. Prescott, "Active touch sensing in the rat: anticipatory and regulatory control of whisker movements during surface exploration," *J. Neurophysiol.*, vol. 101, no. 2, pp. 862–874, 2009.

[13] S. A. Stamper, E. Roth, N. J. Cowan, and E. S. Fortune, "Active sensing via movement shapes spatiotemporal patterns of sensory feedback," *J. Exp. Biol.*, vol. 215, no. 9, pp. 1567–1574, 2012.

[14] C. Chen, T. D. Murphey, and M. A. MacIver, "Tuning movement for sensing in an uncertain world," *eLife*, vol. 9, p. e52371, 2020.

[15] T. Deora, M. A. Ahmed, T. L. Daniel, and B. W. Brunton, "Tactile active sensing in an insect plant pollinator," *J. Exp. Biol.*, vol. 224, no. 4, p. jeb239442, 2021.

[16] D. Biswas, L. A. Arend, S. A. Stamper, B. P. Vágvölgyi, E. S. Fortune, and N. J. Cowan, "Closed-loop control of active sensing movements regulates sensory slip," *Curr. Biol.*, vol. 28, no. 24, pp. 4029–4036, 2018.

[17] K. Wiesenfeld and F. Moss, "Stochastic resonance and the benefits of noise: from ice ages to crayfish and squids," *Nature*, vol. 373, no. 6509, pp. 33–36, 1995.

[18] D. F. Russell, L. A. Wilkens, and F. Moss, "Use of behavioural stochastic resonance by paddle fish for feeding," *Nature*, vol. 402, no. 6759, pp. 291–294, 1999.

[19] M. J. Lannoo and S. J. Lannoo, "Why do electric fishes swim backwards? an hypothesis based on gymnotiform foraging behavior interpreted through sensory constraints," *Environ. Biol. Fishes*, vol. 36, pp. 157–165, 1993.

[20] M. A. MacIver, N. A. Patankar, and A. A. Shirgaonkar, "Energy-information trade-offs between movement and sensing," *PLoS Comput. Biol.*, vol. 6, no. 5, p. e1000769, 2010.

[21] D. Biswas, A. Lamperski, Y. Yang, K. Hoffman, J. Guckenheimer, E. S. Fortune, and N. J. Cowan, "Mode switching in organisms for solving explore-versus-exploit problems," *Nat. Mach. Intell.*, vol. 5, no. 11, pp. 1285–1296, 2023.

[22] S. C.-H. Yang, D. M. Wolpert, and M. Lengyel, "Theoretical perspectives on active sensing," *Curr. Opin. Behav. Sci.*, vol. 11, pp. 100–108, 2016.

[23] O. K. Karagoz, A. Kilic, E. Y. AYDIN, M. M. Ankarali, and I. Uyanik, "Predictive uncertainty in state-estimation drives active sensing in weakly electric fish," *bioRxiv*, pp. 2023–11, 2023.

[24] E. D. Sontag, D. Biswas, and N. J. Cowan, "An observability result related to active sensing," *arXiv*, 2022.

[25] C. Assad, B. Rasnow, and P. K. Stoddard, "Electric organ discharges and electric images during electrolocation," *J. Exp. Biol.*, vol. 202, no. 10, pp. 1185–1193, 1999.

[26] J. Bastian, "Vision and electroreception: integration of sensory information in the optic tectum of the weakly electric fish *Apteronotus albifrons*," *J. Comp. Physiol. A*, vol. 147, no. 3, pp. 287–297, 1982.

[27] S. Sefati, I. D. Neveln, E. Roth, T. R. Mitchell, J. B. Snyder, M. A. MacIver, E. S. Fortune, and N. J. Cowan, "Mutually opposing forces during locomotion can eliminate the tradeoff between maneuverability and stability," *Proc. Natl. Acad. Sci. U.S.A.*, vol. 110, no. 47, pp. 18798–18803, 2013.

[28] I. Uyanik, S. Sefati, S. A. Stamper, K.-A. Cho, M. M. Ankarali, E. S. Fortune, and N. J. Cowan, "Variability in locomotor dynamics reveals the critical role of feedback in task control," *eLife*, vol. 9, p. e51219, 2020.

[29] C. RoseGJ, "Longitudinal tracking responses of *Eigenmannia* and *Sternopygus*," *J. Comp. Physiol. A Neuroethol Sens Neural Behav Physiol*, vol. 173, pp. 698–700, 1993.

[30] N. J. Cowan, M. M. Ankarali, J. P. Dyhr, M. S. Madhav, E. Roth, S. Sefati, S. Sponberg, S. A. Stamper, E. S. Fortune, and T. L. Daniel, "Feedback control as a framework for understanding tradeoffs in biology," *Integr. Comp. Biol.*, vol. 54, no. 2, pp. 223–237, 2014.

[31] J.-M. Mongeau, Y. Yang, I. Escalante, N. Cowan, and K. Jayaram, "Moving in an uncertain world: robust and adaptive control of locomotion from organisms to machine intelligence," *Integr. Comp. Biol.*, p. icae121, 2024.

[32] V. P. Sharma and S. Sponberg, "Context dependent multisensory integration: Mechanosensation depends on luminance for robust performance," *bioRxiv*, pp. 2023–09, 2023.

[33] A. Demirel and İ. Uyanık, "Investigation of sensory reweighting in weakly electric fish during multisensory integration.," *Anatomy: International Journal of Experimental & Clinical Anatomy*, vol. 16, 2022.

[34] E. Roth, K. Zhuang, S. A. Stamper, E. S. Fortune, and N. J. Cowan, "Stimulus predictability mediates a switch in locomotor smooth pursuit performance for *Eigenmannia virescens*," *J. Exp. Biol.*, vol. 214, no. 7, pp. 1170–1180, 2011.

[35] Y. Yang, D. G. Yared, E. S. Fortune, and N. J. Cowan, "Sensorimotor adaptation to destabilizing dynamics in weakly electric fish," *Curr. Biol.*, vol. 34, no. 10, pp. 2118–2131, 2024.

[36] A. Mahboobin, P. Loughlin, C. Atkeson, and M. Redfern, "A mechanism for sensory re-weighting in postural control," *Med. Biol. Eng. Comput.*, vol. 47, pp. 921–929, 2009.

[37] N. Blüthgen and H. Herzel, "How robust are switches in intracellular signaling cascades?," *J. Theo. Biol.*, vol. 225, no. 3, pp. 293–300, 2003.

[38] J. E. Ferrell Jr, J. R. Pomerening, S. Y. Kim, N. B. Trunnell, W. Xiong, C.-Y. F. Huang, and E. M. Machleder, "Simple, realistic models of complex biological processes: positive feedback and bistability in a cell fate switch and a cell cycle oscillator," *FEBS Lett.*, vol. 583, no. 24, pp. 3999–4005, 2009.

[39] L. Ljung, "System identification," in *Signal analysis and prediction*, pp. 163–173, Springer, 1998.

[40] Y. Yang, "A comparison of system identification techniques for refuge tracking behavior in *Eigenmannia virescens*," Master's thesis, Johns Hopkins University, 2020.

[41] S. Sponberg, J. P. Dyhr, R. W. Hall, and T. L. Daniel, "Luminance-dependent visual processing enables moth flight in low light," *Science*, vol. 348, no. 6240, pp. 1245–1248, 2015.

[42] A. L. Stöckl, K. Kihlström, S. Chandler, and S. Sponberg, "Comparative system identification of flower tracking performance in three hawkmoth species reveals adaptations for dim light vision," *Philos. Trans. R. Soc. Lond. B Biol. Sci.*, vol. 372, no. 1717, p. 20160078, 2017.

[43] E. Roth, R. W. Hall, T. L. Daniel, and S. Sponberg, "Integration of parallel mechanosensory and visual pathways resolved through sensory conflict," *Proc. Natl. Acad. Sci. U.S.A.*, vol. 113, no. 45, pp. 12832–12837, 2016.

[44] I. Uyanik, S. A. Stamper, N. J. Cowan, and E. S. Fortune, "Sensory cues modulate smooth pursuit and active sensing movements," *Front. Behav. Neurosci.*, vol. 13, p. 59, 2019.

[45] M. S. Comertler and I. Uyanik, "Salience of multisensory feedback regulates behavioral variability," *Bioinspir. Biomim.*, vol. 17, no. 1, p. 016006, 2021.

[46] M. E. Nelson and M. A. MacIver, "Prey capture in the weakly electric fish apteronotus albifrons: sensory acquisition strategies and electrosensory consequences," *J. Exp. Biol.*, vol. 202, no. 10, pp. 1195–1203, 1999.

[47] P. Nanjappa, L. Brand, and M. J. Lannoo, "Swimming patterns associated with foraging in phylogenetically and ecologically diverse american weakly electric teleosts (Gymnotiformes)," *Environ. Biol. Fishes*, vol. 58, pp. 97–104, 2000.

[48] M. A. MacIver, N. M. Sharabash, and M. E. Nelson, "Prey-capture behavior in gymnotid electric fish: motion analysis and effects of water conductivity," *J. Exp. Biol.*, vol. 204, no. 3, pp. 543–557, 2001.

[49] M.-J. Toerring and P. Moller, "Locomotor and electric displays associated with electrolocation during exploratory behavior in mormyrid fish," *Behav. Brain Res.*, vol. 12, no. 3, pp. 291–306, 1984.

[50] S. E. Clarke, A. Longtin, and L. Maler, "Contrast coding in the electrosensory system: parallels with visual computation," *Nat. Rev. Neurosci.*, vol. 16, no. 12, pp. 733–744, 2015.

[51] A. Kunapareddy and N. J. Cowan, "Recovering observability via active sensing," in *Proc. Amer. Control Conf.*, (Milwaukee, WI, USA), pp. 2821–2826, IEEE, 2018.

[52] J. Bastian, "Pyramidal-cell plasticity in weakly electric fish: a mechanism for attenuating responses to reafferent electrosensory inputs," *J. Comp. Physiol. A*, vol. 176, pp. 63–78, 1995.

[53] L. Chen, J. L. House, R. Krahe, and M. E. Nelson, "Modeling signal and background components of electrosensory scenes," *J. Comp. Physiol. A*, vol. 191, pp. 331–345, 2005.

[54] E. S. Fortune and G. J. Rose, "Passive and active membrane properties contribute to the temporal filtering properties of midbrain neurons in vivo," *J. Neurosci.*, vol. 17, no. 10, pp. 3815–3825, 1997.

[55] E. Fortune and G. Rose, "Temporal filtering properties of ampullary electrosensory neurons in the torus semicircularis of eigenmannia: evolutionary and computational implications," *Brain Behav. Evol.*, vol. 49, no. 6, pp. 312–323, 1997.

[56] J. Bastian, "Plasticity in an electrosensory system. I. general features of a dynamic sensory filter," *J. Neurophysiol.*, vol. 76, no. 4, pp. 2483–2496, 1996.

[57] A. Wallach and N. B. Sawtell, "An internal model for canceling self-generated sensory input in freely behaving electric fish," *Neuron*, vol. 111, no. 16, pp. 2570–2582, 2023.

[58] K. O. Winemiller, A. A. Agostinho, and É. P. Caramaschi, "Fish ecology in tropical streams," in *Tropical stream ecology* (D. Dudgeon, ed.), pp. 107–III, Elsevier, 2008.

[59] M. S. Madhav, R. P. Jayakumar, A. Demir, S. A. Stamper, E. S. Fortune, and N. J. Cowan, "High-resolution behavioral mapping of electric fishes in amazonian habitats," *Sci. Rep.*, vol. 8, no. 1, p. 5830, 2018.

[60] K. O. Winemiller and A. Adite, "Convergent evolution of weakly electric fishes from floodplain habitats in Africa and South America," *Environ. Biol. Fishes*, vol. 49, pp. 175–186, 1997.

[61] E. Sas and L. Maler, "Retinofugal projections in a weakly electric gymnotid fish (*Apteronotus leptorhynchus*)," *Neurosci.*, vol. 18, no. 1, pp. 247–259, 1986.

[62] T. Takiyama, V. Luna da Silva, D. Moura Silva, S. Hamasaki, and M. Yoshida, "Visual capability of the weakly electric fish *Apteronotus albifrons* as revealed by a modified retinal flat-mount method," *Brain Behav. Evol.*, vol. 86, no. 2, pp. 122–130, 2015.

[63] M. E. Bichuette and E. Trajano, "Morphology and distribution of the cave knifefish eigenmannia vicentespelaea triques, 1996 (Gymnotiformes: Sternopygidae) from central brazil, with an expanded diagnosis and comments on subterranean evolution," *Neotrop. Ichthyol.*, vol. 4, pp. 99–105, 2006.

[64] E. S. Fortune, N. Andanar, M. Madhav, R. P. Jayakumar, N. J. Cowan, M. E. Bichuette, and D. Soares, "Spooky interaction at a distance in cave and surface dwelling electric fishes," *Front. mol. neurosci.*, vol. 14, p. 561524, 2020.

[65] A. Watanabe and K. Takeda, "The change of discharge frequency by ac stimulus in a weak electric fish," *J. Exp. Biol.*, vol. 40, no. 1, pp. 57–66, 1963.

[66] J. Bastian, "Electrolocation in the presence of jamming signals: behavior," *J. Comp. Physiol. A*, vol. 161, pp. 811–824, 1987.

[67] C. S. Yang, N. J. Cowan, and A. M. Haith, "*De novo* learning versus adaptation of continuous control in a manual tracking task," *eLife*, vol. 10, p. e62578, 2021.

[68] T. Mergner, "A neurological view on reactive human stance control," *Annu. Rev. Control*, vol. 34, no. 2, pp. 177–198, 2010.

[69] L. Assländer and R. J. Peterka, "Sensory reweighting dynamics in human postural control," *J. Neurophysiol.*, vol. 111, no. 9, pp. 1852–1864, 2014.

[70] S. Schumacher, T. Burt de Perera, J. Thenert, and G. von der Emde, "Cross-modal object recognition and dynamic weighting of sensory inputs in a fish," *Proc. Natl. Acad. Sci. U.S.A.*, vol. 113, no. 27, pp. 7638–7643, 2016.

[71] J. P. Sheppard, D. Raposo, and A. K. Churchland, "Dynamic weighting of multisensory stimuli shapes decision-making in rats and humans," *J. Vis.*, vol. 13, no. 6, pp. 4–4, 2013.

[72] C. R. Fetsch, A. H. Turner, G. C. DeAngelis, and D. E. Angelaki, "Dynamic reweighting of visual and vestibular cues during self-motion perception," *J. Neurosci.*, vol. 29, no. 49, pp. 15601–15612, 2009.

[73] M. J. Rauscher and J. L. Fox, "Haltere and visual inputs sum linearly to predict wing (but not gaze) motor output in tethered flying *Drosophila*," *Proc. R. Soc. Lond. Ser. B, Biol. Sci.*, vol. 288, no. 1943, p. 20202374, 2021.

[74] M. H. Dickinson, "Linear and nonlinear encoding properties of an identified mechanoreceptor on the fly wing measured with mechanical noise stimuli," *J. Exp. Biol.*, vol. 151, no. 1, pp. 219–244, 1990.

[75] L. Paninski, J. Pillow, and J. Lewi, "Statistical models for neural encoding, decoding, and optimal stimulus design," *Prog. Brain Res.*, vol. 165, pp. 493–507, 2007.

[76] S. J. Huston and H. G. Krapp, "Nonlinear integration of visual and haltere inputs in fly neck motor neurons," *J. Neurosci.*, vol. 29, no. 42, pp. 13097–13105, 2009.

[77] U. B. Sikandar, H. Choi, J. Putney, H. Yang, S. Ferrari, and S. Sponberg, "Predicting visually-modulated precisely-timed spikes across a coordinated and comprehensive motor program," in *2023 International Joint Conference on Neural Networks (IJCNN)*, pp. 1–8, IEEE, 2023.

[78] J. L. Fox and M. A. Frye, "Figure–ground discrimination behavior in *Drosophila*. II. visual influences on head movement behavior," *J. Exp. Biol.*, vol. 217, no. 4, pp. 570–579, 2014.

[79] É. M. Hitschfeld, S. A. Stamper, K. Vonderschen, E. S. Fortune, and M. J. Chacron, "Effects of restraint and immobilization on electrosensory behaviors of weakly electric fish," *ILAR J.*, vol. 50, no. 4, pp. 361–372, 2009.

[80] A. Mathis, P. Mamidanna, K. M. Cury, T. Abe, V. N. Murthy, M. W. Mathis, and M. Bethge, "DeepLabCut: Markerless pose estimation of user-defined body parts with deep learning," *Nat. Neurosci.*, vol. 21, no. 9, pp. 1281–1289, 2018.

[81] E. Roth, S. Sponberg, and N. J. Cowan, "A comparative approach to closed-loop computation," *Curr. Opin. Neurobiol.*, vol. 25, pp. 54–62, 2014.

Supplemental Materials

Supplemental Figures

Fig. S1. Illumination-mediated switching transition in fish head and tail movements.
(A) Spearman rank correlation coefficient between the refuge trace and the average fish head movement traces from the same fish from Fig. 1 (fish 1) for different illuminations. High correlation coefficients (> 0.78) observed across all tested illumination levels indicate that the fish consistently followed the refuge. Furthermore, the atypical "S" shape conforms to the switching behavior. The dashed black line and the gray-shaded region denote the sigmoidal fit to the combined data and 95% prediction interval, respectively. The sigmoidal fit to the data was obtained by excluding 0.1 lx data point (red marker) as an outlier. **(B,C)** Adjusted R^2 and small sample corrected AIC score substantiate that the sigmoidal model (solid line) is a better fit for the data compared to the polynomial model (markers with dashed line). **(D)** Mean profile for transverse tail movement variance across different illumination for the same fish from Fig. 2I (fish 1). The open circles represent the data corresponding to the neglected outliers from Fig. 2I.

Fig. S2. Illumination dependence in transverse tail movement.
Average discrete Fourier Transform (DFT) magnitude of transverse tail movement (A–E) and the corresponding velocity (F–J) across trials under different illumination conditions for each fish ($N = 5$). Different colors denote different illumination levels. The dashed lines in (A) and (F) represent the data corresponding to the neglected outliers from Fig. 2G,H.

Fig. S3. Closed-loop frequency response shows illumination dependent transitions.
Bode gain (A–E) and phase (F–J) plots for all individuals ($N = 5$). Different colors represent different illumination levels. The results show that for four out of five fish (except for fish 2), Bode gains tightly distribute over the refuge frequency range (0.1 – 2.05 Hz), whereas for all five fish, Bode phase values are initially tightly grouped but become more dispersed at higher frequencies (> 0.5 Hz).

Supplemental Tables

Supplemental Table 1: The measured illumination levels (lx) of each fish subject. There are slight fluctuations across subjects, due to slight changes in water level of the experimental tank which caused the LED lights to reflect differently.

	Fish 1	Fish 2	Fish 3	Fish 4	Fish 5
Condition 1	0.1	0.1	0.1	0.1	0.1
Condition 2	0.4	0.4	0.4	0.4	0.4
Condition 3	1.0	2.5	2.6	2.3	3.5
Condition 4	2.0	7.8	3.6	4.1	4
Condition 5	3.5	12.5	5.1	7.1	7
Condition 6	5.5	14.6	8.5	10.3	9.5
Condition 7	7	19.7	12.6	14.5	15
Condition 8	9.5	60	14.5	57	55
Condition 9	12	210	20	181	157.6
Condition 10	15	–	68	–	–
Condition 11	30	–	218	–	–
Condition 12	60	–	–	–	–
Condition 13	150	–	–	–	–
Condition 14	210	–	–	–	–

Supplemental Table 2: Fitting details for the sigmoidal function, $f(x) = a/(1 + e^{-b(x-c)}) + d$ to the data. The fitting parameters, locations of change points in terms of illumination levels (Change Pts, lx), adjusted R^2 (Adj R^2), and small-sample corrected Akaike Information Criterion (AICc) are listed below. ΔAdj R^2 = Adj R^2(sigmoidal) – Adj R^2(best polynomial fit) whereas, ΔAICc = AICc(best polynomial fit) – AICc(sigmoidal). n denotes the order of the best fitted polynomial model for that criterion.

	a	b	c	d	Change Pts (lx)	Adj R^2	AICc	ΔAdj R^2 (n)	ΔAICc (n)
Fig. 1I	2.729	−2.079	−0.063	0.083	[0.66, 3.40]	0.99	−68.95	−0.001(4)	1.08(4)
Fig. 1J	1.691	−2.015	0.192	0.093	[0.95, 5.32]	0.81	−140.91	0.003(3)	0.81(3)
Fig. 2I	1.9	−4.21	0.732	0.175	[3.46, 9.46]	0.99	−46.10	-1.27×10^{-5}(4)	5.62(4)
Fig. 2J	0.606	−3.183	0.845	0.453	[3.46, 12.81]	0.69	−196.5	−0.02(7)	−0.24(3)
Fig. 3C	33.87	2.289	0.968	−166.9	[3.56, 18.17]	0.86	159.38	0.003(5)	2.09(3)
Fig. 4F	0.252	2.064	0.558	0.351	[1.77, 9.76]	0.83	−340.38	−0.004(6)	0.64(3)
Fig. S1A	0.100	8.374	0.973	0.792	[7.09, 12.51]	0.98	−122.98	0.003(7)	18.48(3)

Supplemental Methods

Using computational tools to obtain tracked data points from fish video footage

For tracking the fish head positions in time series, we prepared a training dataset of 200 video frames, collected from all subjects under all illumination levels. In each frame, the fish's head point, h_0, roughly located between the eyes, and one point on the refuge, s_0, were labeled by hand with the DeepLabCut graphic user interface [80] (Fig. S4A).

Fig. S4. Illustrations of the procedure of tracking fish position and fish body motion. (A) The raw video with two points labeled manually: the fish head point and one point on the refuge. **(B)** The pre-processed video with the fish orienting to the left, head pinned at $x = 220$ pixel and $y = 110$ pixel, with the bright rims of the refuge masked out with pixel brightness $= 0$. **(C)** The DeepLabCut tracked output, with 8 hand-labeled points along the fish body. **(D)** The re-interpolated video output with 12 points, including a red line that connects all the points for visual inspection purposes.

Then, we trained a ResNet-50 machine learning model and analyzed videos to obtain the fish head and refuge positions. The x and y positions were saved as .csv files in pixel units for each 70-second trial.

To accurately track the entire fish body, we developed an image pre-processing procedure. After obtaining the head position data, we loaded the original videos into a MATLAB script, and then shifted the frame image to pin the fish head point h_0 to the same coordinate: $x = 220$ pixels and $y = 110$ pixels. To follow the MATLAB image coordinates convention, we standardize the fish orientation to left-pointing. This ensures that the tail always points to the right, where x coordinates along the body strictly increase (Fig. S4B).

To minimize chances of image mislabeling in the DeepLabCut model, we masked black rectangles to cover the bright refuge boundaries in each frame, since the fish body would not appear in these regions.

From the pre-processed videos, another 200 frames were selected among all trials to train one network with data from all 5 fish. For each frame, we manually plotted 8 points that are roughly equally spaced along the fish body. Then, we trained another ResNet-50 model in DeepLabCut. This new model labeled all videos, labeling 8 points along the fish body for each video frame, each at likelihood above 99% (Fig. S4C).

As the manual plotting and fish body-length variability introduced errors in the point spacing, the fish's body-length curve was re-interpolated again with 12 points. We first bisect the curve, then equally spaced 5 points at the first half and 7 points on the second half. This arrangement helps better capture tail curvature. A Python OpenCV script read the original 8 data points, interpolated a 4th order polynomial to those data points, and segmented the curve into the 12 points mentioned above (Fig. S4D). This ensured that each data point

labeled the exact same location on the fish body in every frame; across different fish, this point also labeled the same position with respect to the whole-body length.

Aligning fish body orientations across video frames

After obtaining the fish head coordinates from the head tip b_0 to the tail end b_{11}, we aligned the fish's general body directions across frames. As the fish head positions can be considered rigid (not curving along the body), we fitted a line with the first 3 points from fish head, b_0, b_1, and b_2 and calculated its angle with the horizontal line, θ. Then, we rotated all points, b_0 through b_{11}, around the the head point b_2. This operation ensured consistencies in the body-frame movement analysis, such as the tail-beat motion comparisons shown in (Fig. 2A,C,E).

Using statistical methods to exclude data outliers

To exclude outliers within each experimental condition, we implemented a statistical heuristic on both the time-domain head movement data and the frequency-domain tracking responses. To identify outliers, the following rules provided a fair metric for data clean-up.

First, if among all trials in a given condition (around 15 trials), a trial's sum of squared errors (SSE) has a absolute-valued z-score greater than 2.2 (98.6% percentile), then it is considered an outlier.

Alternatively, outliers in frequency-domain responses are also considered. With the discrete Fourier transform, each trial would have 12 complex data points for the 12 frequency components. For each frequency component, we fitted a Gaussian distribution of all trials with the Mahalanobis distance (Fig. S5A). With the 12 z-scores per trial, we applied the following logic: if 1) any one frequency component has $z > 2.5$ (99.4% percentile), this trial was flagged as an outlier. 2) if there were at least three frequency components with $z > 1.5$ (93.4% percentile), then we also marked the trial as an outlier. Fig. S5B,C illustrates the outliers identified with the above method, which are indeed categorically different from the rest of the trials. Our data clean-up method ensure that enough data (76% – 100%) remains after excluding outliers, and that the statistical comparisons are fair, since they only compare among trials of the same condition and the same fish. This clean-up process preserved accurate and representative data for further processing.

Fig. S5. Illustrations of the data clean-up process. (A) Within the 18 trials of the same fish and under the same illumination, we plotted the Mahalanobis distances of the tracking responses at a certain frequency peak. 12 such plots were produced. Then, we examined the 12 z-scores from each trial to identify outliers. **(B)** Considering the frequency-domain z-scores as well as the time-domain SSE z-scores, we identified 3 outlier trials with this example. The FRF amplitudes of the outlier trials were labeled in red. **(C)** The corresponding time-domain traces of the outliers identified above.

Control-theoretic sensory reweighting model algorithm

We applied an optimization algorithm in MATLAB to obtain illumination-dependent sensory weights in each illumination level tested in this research and the estimated illumination-invariant non-parametric open-loop transfer functions $G_V(s)$ and $G_E(s)$ in our proposed sensory reweighting model (see Fig. 4D, G). The estimated non-parametric illumination-invariant open-loop transfer functions, i.e. $G_V(j\omega)$ and $G_E(j\omega)$ as $s = j\omega$, are both 12 complex numbers since there are 12 frequencies in the FRF estimation. Here we note them as follows:

$$G_V(j\omega) = P(j\omega)C(j\omega)S_V(j\omega) = \left[m_1 + jn_1, m_2 + jn_2, \ldots, m_{12} + jn_{12}\right], \tag{5}$$

$$G_E(j\omega) = P(j\omega)C(j\omega)S_E(j\omega) = \left[p_1 + jq_1, p_2 + jq_2, \ldots, p_{12} + jq_{12}\right]. \tag{6}$$

Thus, to determine either $G_V(j\omega)$ or $G_E(j\omega)$ over the frequencies we tested in our experiments, we need to determine 24 free parameters, i.e., 12 real parameters m_l or p_l, and 12 imaginary parameters jn_l or jq_l ($l = 1, 2, ..., 12$). In our model, we also determined the sensory weights: $\alpha(\lambda)$ for vision (and $1 - \alpha(\lambda)$ for electrosense) in each of 9 to 14 illumination levels of λ. Therefore, depending on the number of illumination levels λ we tested on each fish, there were $57 - 62$ (24×2 + the number of illumination conditions) parameters need to be determined.

Given 500 randomly generated initial conditions for each parameter, we used the `fmincon` function in MATLAB to find a set of free parameters for each initial condition that minimized a cost function, i.e., the cumulative mean-squared-error (MSE) between model and averaged data at frequencies of interests from all 9 – 14 illumination levels for the specified fish:

$$\text{cost function} = \sum_{k=1}^{n} \left[\frac{1}{12} \sum_{i=1}^{12} \left| \omega_i \Big(G(j\omega_i)_k - \hat{G}(j\omega_i)_k \Big) \right|^2 \right], \tag{7}$$

where k represents the illumination condition; n is the total number of illumination levels ($n = 9 - 14$); i represents the frequency of interests; terms in $[\cdot]$ is the MSE between averaged data and model in each illumination level; $G(j\omega_i)_k$ is the estimated open-loop FRF from experimental data at frequency ω_i in the k^{th} illumination level λ_k; $\hat{G}(j\omega_i)_k$ is the fitted open-loop FRF from our sensory reweighting model at frequency ω_i in the k^{th} illumination level λ_k, and

$$\hat{G}(j\omega_i)_k = \beta(\lambda_k) \underbrace{P(j\omega_i)C(j\omega_i)S_1(j\omega_i)}_{G_1(j\omega_i)} + [1 - \beta(\lambda_k)] \underbrace{P(j\omega_i)C(j\omega_i)S_2(j\omega_i)}_{G_2(j\omega_i)}, \tag{8}$$

where $\beta(\lambda_k)$ and $1 - \beta(\lambda_k)$, $G_1(j\omega_i) = P(j\omega_i)C(j\omega_i)S_1(j\omega_i)$ and $G_2(j\omega_i) = P(j\omega_i)C(j\omega_i)S_2(j\omega_i)$ are candidates for sensory weights and open-loop FRF from different sensory pathways, respectively. Due to the fact that fitting result is generally worse at higher frequencies compared with lower frequencies, we multiplied data and model difference $G(j\omega_i)_k - \hat{G}(j\omega_i)_k$ by frequency ω_i itself so that the cost function put higher weights on error at higher frequencies.

Although the form of Equation 8 is similar to that of the sensory reweighting model in Equation 1, we need to further determine whether $\alpha(\lambda_k) = \beta(\lambda_k)$ or $\alpha(\lambda_k) = 1 - \beta(\lambda_k)$, and which one of $G_1(j\omega)$ and $G_2(j\omega)$ is $G_E(j\omega)$ and which one is $G_V(j\omega)$ since the optimization algorithm itself treated each sensory pathway the same and could only gave us candidates for sensory weights and open-loop FRF from different sensory pathways. Therefore, we used another algorithm to determine each item by checking the trend of $\beta(\lambda_k)$. In the lowest illumination level 0.1 lx, it makes sense that fish is "electrosense dominated", i.e., they put lower weights on vision since they cannot see very well and put higher weights on electrosense. Thus, α at 0.1 lx should be relatively small and $1 - \alpha$ should be relatively high. As illumination increased, the weight α in visual pathway should be increasing and $\alpha(\lambda_1) < \alpha(\lambda_n)$. Therefore, if $\beta(\lambda_k)$ obtained from the optimization algorithm satisfies $\beta(\lambda_1) < \beta(\lambda_n)$, then

$$\alpha(\lambda_k) = \beta(\lambda_k),$$
$$G_V(j\omega) = G_1(j\omega),$$
$$G_E(j\omega) = G_2(j\omega);$$

otherwise,

$$\alpha(\lambda_k) = 1 - \beta(\lambda_k),$$
$$G_V(j\omega) = G_2(j\omega),$$
$$G_E(j\omega) = G_1(j\omega).$$

Note that sensory weights for vision α and that for electrosense $1 - \alpha$ depend on illumination levels λ_k, while

visual and electrosensory pathways $G_V(j\omega)$ and $G_E(j\omega)$ are illumination-invariant. In the end, among all 500 best fitted parameter sets corresponding to each initial conditions, we selected the set of parameters that gave the least fitting error as the final parameters for each fish.

Comparing the bootstrapped experimental data with the sensory reweighting model

To better quantify the fitting quality of our model, we conducted bootstrapping analysis for each fish ($N = 5$). The procedure is as follows: in each illumination condition, we created a sampled dataset by sampling trials from the actual dataset with replacements. After repeating this step for all illumination conditions, we created a bootstrapped dataset. Following those steps, we finally generated 100 bootstrapped datasets for each fish ($N = 5$). And for each bootstrapped dataset, we applied sensory reweighting control model algorithm to obtain the corresponding $G_E(j\omega)$ and $G_V(j\omega)$ and a set of illumnation-dependent visual weight α. Thus, for each fish, we finally obtained 100 bootstrapped datasets and their corresponding fitted models in each illumination. All code for this bootstrap analysis was run in MATLAB R2024a.