Rhythms and Background (RnB): The Spectroscopy of Sleep Recordings

J. Dubé [1,2], M. Foti [3], S. Jaffard [4], V. Latreille [5], B. Frauscher [6], J. Carrier
[1,2], J.M. Lina [2,3,7]

1. Department of Psychology, Université de Montréal, Montreal, QC, H3C 1J7, Canada

2. Center for Advanced Research in Sleep Medicine, Hop. Sacré-Cœur de Montréal, Montreal, QC,

H4J 1C5, Canada

3. Electrical Eng. Dep., École de Technologie Supérieure, Montreal, QC, H3C 1K3, Canada

4. LAMA, Univ. Paris-Est-Créteil, France

5. Department of Neurology and Neurosurgery, Montreal Neurological Institute Hospital, McGill

University, Montreal, QC, H3A 2B4, Canada.

6. Department of Neurology, Analytical Neurophysiology Lab., Duke University, North Carolina,

27708, United States.

7. Centre de Recherches Mathématiques, Université de Montréal, Montreal, QC, H3C 1J7, Canada

Corresponding author: jean-marc.lina@etsmtl.ca

Number of pages (with figure and tables in-text): 70

Number of figures: 11

Number of tables: 1

Number of words: Abstract: 248; Significance Statement: 119; Introduction**:** 630; Methods**:**

3382**;** Results: 1925; Discussion:1439; Figure legends ; 1535

The authors declare no competing financial interests.

Abstract

Non-rapid eye movement (NREM) sleep is characterized by the interaction of multiple coupled oscillations essential for various functions such as memory consolidation, alongside a pervasive and dynamic arrhythmic 1/f scale-free background that may also contribute to these functions. Although recent spectral parametrization methods such as FOOOF (Fitting-One-and-Over-f) allowed to dissociate rhythmic and arrhythmic components in the spectral domain, they fail to resolve these processes in the time domain, where instantaneous measures of frequency, amplitude, and phase-amplitude coupling are still confounded by arrhythmic activity. This limitation represents a significant pitfall for studies of NREM sleep, which often rely on phase-based analyses of specific oscillations. To address this limitation, we introduce 'Rhythms & Background' (RnB), a novel wavelet-based methodology designed to dynamically denoise time-series data by correcting for arrhythmic interference. This enables the extraction of a purely rhythmic time-series suitable for enhanced time-domain analyses of sleep rhythms. We first validate RnB through simulations, demonstrating its robust performance in accurately estimating spectral profiles of individual and multiple oscillations across a range of arrhythmic conditions. We then apply RnB to publicly available intracranial EEG sleep recordings, showing that it provides an improved spectral and time-domain representation of hallmark NREM rhythms. Finally, we demonstrate that RnB significantly enhances the assessment of phase-amplitude coupling between cardinal NREM oscillations, outperforming traditional methods that conflate rhythmic and arrhythmic components. This methodological advance

offers a substantial improvement in the analysis of sleep oscillations, providing

greater precision in the study of rhythmic activity critical to NREM sleep functions.

SIGNIFICANCE STATEMENT

The Rhythms and Background (RnB) algorithm introduces a novel approach to

signal processing in electrophysiology by isolating rhythmic activity from the

arrhythmic background at the time-series level. Unlike existing spectral

decomposition methods, RnB enables more precise analysis of brain rhythms in

both the time and spectral domains, providing clearer insights into cerebral

oscillatory processes. This breakthrough has direct applications in studying brain

connectivity and oscillation dynamics during sleep. Additionally, its application in

clinical populations where pathological changes in arrhythmic activity are common,

such as neurodevelopmental and neurodegenerative disorders, will help to better

understand abnormal oscillatory processes. By improving the accuracy of rhythmic

signal analysis, RnB opens new avenues for understanding brain function and

dysfunction in research and clinical settings.

Introduction

Brain rhythms from bioelectric activity reflect synchronization of neuronal assemblies and are often inventoried using the Fourier analysis of electrophysiological brain recordings (Buzsáki, 2004). A noteworthy case is non-rapid eye movement (NREM) sleep, which is characterized by cardinal rhythms critically involved in overnight information processing such as sleep slow waves (SSW, 0.5-4 Hz), theta bursts (6-10 Hz), sleep spindles (8-16 Hz), and sharp-wave ripples (100-200 Hz). These rhythms are organized in complex wave sequences, with sporadic phase-amplitude coupling across frequencies, which occur locally and between remote brain regions (Klinzing et al., 2016; Helfrich et al., 2019). For instance, sleep spindles usually occur after SSWs down states, within the transition period towards their upstate. The loss of specificity of this phase coupling in aging may contribute to impaired memory consolidation (Helfrich et al., 2018).

New hypotheses suggest that arrhythmic brain activity plays complementary roles to brain rhythms in NREM sleep functions (Helfrich et al., 2021). Arrhythmic activity recruits a broad range of frequencies and is usually expressed as $1/f^\beta$ decay in the power spectral density (He, 2014). This "scale-free" arrhythmic component is usually estimated using the spectral slope (β) expressed in the log-log power spectrum. The steepness of β has been shown to closely follow shift in the excitation-inhibition balance during sleep (Lendner et al., 2020; Helfrich et al., 2021; Niethard et al., 2021; Kozhemiako et al., 2022), and to show age-dependent changes which can predict ulterior cognitive impairment (Finley et al., 2024;

Hernandez et al., 2024). Furthermore, arrhythmic differences in β alter the spectral peaks' characteristics in the Fourier domain which are typically attributed to brain rhythms (i.e. width, height, central frequency). Spectral parametrization methods, such as *Fitting-Oscillations-One-and-Over-F (FOOOF),* have been recently introduced to robustly assess rhythmic (peaks) and arrhythmic (β) components in the power spectrum (Wen and Liu, 2016; Donoghue et al., 2020). Such methods are increasingly used to report rhythmic and arrhythmic changes in neuroscience (Donoghue et al., 2022; Ostlund et al., 2022).

Arrhythmicity is also evident at the signal level, manifesting as a ubiquitous 'desynchronized' background activity that nonlinearly interferes with transient oscillatory events (Helfrich et al., 2021). This interplay introduces noise in time-domain analyses, reducing the reliability of phase and amplitude estimates typically associated to brain rhythms (Jurkiewicz et al., 2021; Donoghue et al., 2022). Such metrics are crucial for investigating oscillation-dependent coupling and connectivity in neurodegenerative disorders such as Alzheimer's and Parkinson's disease (Nimmrich et al., 2015). Therefore, correcting the phase and amplitude instantaneous estimates for differences in arrhythmicity — which is now increasingly documented across various brain dysfunctions (Pani et al., 2022) — is imperative. However, no existing methods currently address this challenge.

The present work addresses this critical gap by introducing a novel wavelet-based algorithm, **Rhythms & Background (*RnB*)**. This algorithm accounts for the arrhythmic background in NREM sleep's electrophysiological time series by

denoising rhythmic activity at the level of wavelet coefficients in the 'time scale' domain. By synthesizing corrected wavelet coefficients, RnB extracts a 'rhythmic time series' in which arrhythmic activity is attenuated. RnB thus allows an accurate representation of brain rhythms, effectively performing a 'spectroscopy' of NREM sleep recordings.

The method section begins by presenting the mathematical framework that allows the transition from the spectral to the wavelet paradigm. This section also outlines the key methodological tools—such as a slow-wave detector, time-frequency analyses, and amplitude-phase coupling—employed in subsequent analyses of rhythmic time series derived from NREM sleep recordings. Next, we validate the algorithm's ability to estimate background and rhythmic components using a simulation paradigm. Following this, we apply the RnB algorithm to intracranial NREM sleep recordings to conduct a detailed spectroscopy and inventory of NREM sleep rhythms. Finally, we demonstrate that the RnB-derived rhythmic time series enable the detection of rhythmic sleep slow waves during NREM sleep, which exhibit robust coupling to other NREM rhythms.

1 Materials and Methods

2 *From the spectral to the wavelet paradigm of rhythms and background*

3 Spectral approaches characterize rhythms and background from the spectral

4 power in the Fourier domain. Without loss of generality, we considered the

5 following model of the power spectral density $\Gamma(f)$

6
$$\Gamma(f) = P(f)\, e^{R(f)} \tag{1}$$

7 where the factor $P(f) = c/f^{\beta}$ accounts for arrhythmicity (as a constant c and a

8 slope β also called scaling exponent) and $R(f)$ represents rhythms. Expanding the

9 exponential, this multiplicative model can accommodate the usual additive model,

10
$$\Gamma(f) \approx \frac{c}{f^{\beta}} + c\, f^{-\beta} R(f) + \cdots \tag{2}$$

where the first term accounts for the arrhythmic background, and the second term

is a resonance, if $R(f)$ is sufficiently decaying at low frequency to compensate the

infrared divergence. This expansion can explain the possible modulation of narrow

band power peaks. To extract the arrhythmic factor, we follow the IRASA approach

(Wen and Liu, 2016), considering a random sequence of power spectrums

obtained from a series of rescaling transforms $f \to af$,

17
$$\Gamma(f) \to \Gamma_a(f) = \frac{c}{f^{\beta}}\, a^{-\beta}\, e^{R(af)} \tag{3}$$

where $0 < a < 2$ will be chosen in pair, a and $1/a$. Then, from n randomly selected values for a, the geometric average

$$Q(f) = \left(\prod_{a_1}^{a_n} \Gamma_a(f)\, \Gamma_{1/a}(f) \right)^{\frac{1}{2n}} = P(f)\, e^{\mathcal{E}(f)} \tag{4}$$

exhibits the arrhythmic factor $P(f) = c/f^\beta$ since a large number of random rescaling will not preserve narrowband rhythmic processes present in the spectrum as previously demonstrated, and $\mathcal{E}(f) = 1/2n \sum_{a_i}(R(a_i f) + R(a_i^{-1} f)) \approx 0$.

Thus, $Q(f)^{-1} \approx P(f)^{-1}$ is a spectral filter able to whiten the arrhythmic component of the individual power spectrums on an epoch-per-epoch basis. The rhythmic factor $e^{R^*(f)}$ is estimated from the average of this residual spectra across all epochs 'i',

$$e^{R^*(f)} = \langle Q_i(f)^{-1}\, \Gamma_i(f) \rangle \tag{5}$$

which reliably estimates the spectral signature of simulated oscillations (see Fig.1, E1 and E2). It is worth noting that the spectral slope can be estimated from a log-log regression of (3) applied for each epoch, leading to a spectrum of the scaling exponent as shown in Fig.1(D1 and D2).

As for all current spectral approaches, this filtering approach cannot restore the underlying rhythmic signal. To disentangle rhythms from arrhythmicity in the time domain, a signal processing approach mixing time *and* frequency is mandatory. This is precisely the wavelet paradigm developed in RnB.

FIGURE 1 (Legend provided below for ease of reference, also available after the References section)

Fig.1. Spectral estimation of arrhythmic background and rhythms. (A1, A2). Examples of two simulated time series (see simulations section for methodological details). (A1) show pure background arrhythmic activity (β =1.70; arrhythmic background). (A2) shows a mixture of the same arrhythmic activity as in A1**,** with the addition of a four second alpha oscillation (10.5 Hz). (B1, B2). Fourier power spectra of (A1) and (A2), respectively. The estimated arrhythmic spectrum $Q_i(f)$, as described above, is shown in red. (C1, C2). Averaged standard power spectra over 250 simulations for each type of simulation as shown in (B1) and (B2). Even though the added oscillation in the signal (A2) is unnoticeable in the individual Fourier spectrum (B2), its signature is apparent in the averaged standard spectrum (C2). (D1, D2)**.** Probability density of estimated scale-free exponents obtained from $Q_i(f)$ in the two sets of 250 simulations, without (D1) and with (D2) the alpha 10.5 Hz oscillation. (E1, E2). the residual 'rhythmic factor' $\exp(R^*(f))$ controlled for the presence of arrhythmic background for the two sets of simulations, respectively without (E1**)** and with (E2) the alpha 10.5 Hz oscillation.

1   *Wavelet and arrhythmicity*

2   Although the scale-free arrhythmic process is usually addressed in the Fourier

3   power spectrum, the 'time – scale decomposition' is an appropriate representation

4   of such a process (Rocca et al., 2018; Abry et al., 2019). This representation

5   amounts to expand the signal in terms of 'transient little wave' called wavelets,

6
$$s(t) = \sum_{j} \sum_{k=1}^{n_j} w_{j,k} \; \psi_{j,k}^{(\alpha)}(t) \tag{6}$$

7   In this expansion, each wavelet has a temporal scale $\approx 2^j$ and is timely located at

8    $t = k \, 2^j$ where k and j are integer,

9
$$\psi_{j,k}^{(\alpha)}(t) = \; 2^{-\frac{j}{2}} \, \psi^{(\alpha)}\big(2^{-j} \, t - k\big)$$

The smoothness of the 'mother wavelet' $\psi^{(\alpha)}(t)$ is controlled by the regularity

parameter α. This 'little wave' oscillates with a frequency f_0 that depends on the

parameter α. Therefore, the main frequency of the wavelets at scale j in expansion

(6) is $\approx 2^{-j} \, f_0$.

The multiresolution 'time - scale' representation of a signal in such a basis is a

collection of wavelet coefficients at various discrete time and scales as is illustrated

in Fig.2C.

1   The previous log-log regression allowing to estimate the scaling exponents in the

2   spectral domain, $\log \Gamma(f) \approx -\beta \log f$, can be reformulated in the wavelet domain

3   as follows

4
$$\beta^* = \frac{\sum_{j_1}^{j_2} n_j \ \sum_{j_1}^{j_2} j \ n_j \ D_j \ - \ \sum_{j_1}^{j_2} j \ n_j \ \sum_{j_1}^{j_2} n_j \ D_j}{\sum_{j_1}^{j_2} n_j \ \sum_{j_1}^{j_2} n_j \ j^2 - \left(\sum_{j_1}^{j_2} j \ n_j\right)^2} \tag{7}$$

5   with the second-order statistics of the wavelet coefficients,

6
$$D_j = \log\left(\frac{1}{n_j} \sum_k w_{j,k}^2\right)$$

Fig.2. **The analysis of an original signal and synthesis of a rhythmic signal using fractional spline wavelets.** (A) An

example of fractional spline wavelet that could be used for analysis of an NREM sleep signal as illustrated in (B). (C) 'time-

scale' decomposition of $s(t)$ displayed in (B) using wavelet basis generated with (A). Each boxes represents a wavelet

coefficient $\langle s, \psi_{j,k}^{(4)} \rangle$ at a particular scale (j) and discrete time ($k\, 2^j$). Real time is indicated on the x-axis. To help the reading

of the time-scale representations, visible boxes account for 99% of the overall wavelet power of the signal. Gray intensity

(globally normalized) indicates the amplitude of the largest wavelet coefficient. (D) Logarithmic wavelet power of (B) with

respect to the dyadic scale parameter. The linear regression will provide the scaling exponent as given in (6). (E) 'time-

scale' decomposition of the rhythmic signal resulting from processing (B). Notice the lacunar representation as compared

to the analysis of the original signal in (C). The rhythmic decomposition exhibits coefficients at high scale (low frequencies)

that seem to account for oscillatory pattern localized in time (confirmed with an inspection of (B)). (F) Wavelet power of

multiple NREM rhythmic signals (dashed grey lines) and the mean (dark bold line).

The regression, illustrated on Fig. 2D is done across scales ranging from j_1 (high

frequencies) to j_2 (low frequencies). Thus, the range from j_1 to j_2 should cover the

spectral domain of interest with respect to the rhythms to be further extracted. This

estimate must also be reliable with respect to the second order statistics involved

in (7). There is a compromise between the number of scales to be used and the

duration of the epochs in which the statistics are computed. The lowest scales

(high frequencies) should not include dominant noisy activity, whereas the largest

scales (low frequencies) are limited by epoch duration and edge effects. Our

GitHub illustrates the choice of this interval in the algorithm we propose (see RnB

algorithm).

In summary, our approach bridges the gap between fully time-resolved continuous

wavelet transforms (unsuitable for signal processing) and Fourier analysis

(unsuitable for time-resolved analysis). The balance between the accuracy of the

scale-free model and temporal precision is the key strength of the multi-scale

representation of the signal that we introduce.

Wavelet denoising and extraction of the rhythmic timeseries

To extract the rhythmic activity, wavelet coefficients should be adjusted for the

scale-free activity previously described. To do so, we consider the 'fractional spline

wavelet' bases (Blu and Unser, 2000) to handle the regularity of the original signal,

quantified with the parameter $\alpha = \alpha_0 + \beta^*/2$' in which α_0 represents the regularity

of the rhythmic signal to be extracted and β is the scaling exponent of the signal

estimated in the previous section. We exploited the property of fractional differentiation of this wavelet family,

$$\langle s, \psi_{j,k}^{(\alpha)} \rangle \approx 2^{j\,(\alpha+3/2)}\; \partial^{\alpha+1} s\!\left(k\,2^j\right) \tag{8}$$

where the partial differentiation operator ∂^r corresponds to the product with f^r in the Fourier domain. The following equality can be further shown,

$$\langle \partial^{\frac{\beta^*}{2}} s, \psi_{j,k}^{(\alpha_0)} \rangle = \mathcal{K}\!\left(\alpha_0 + \tfrac{\beta^*}{2}, \alpha_0\right)\; 2^{-j\,\beta^*/2}\; \langle s, \psi_{j,k}^{(\alpha_0+\beta^*/2)} \rangle \tag{9}$$

Where,

$$\mathcal{K}(\alpha', \alpha) = (4\pi)^{\alpha'-\alpha}\; \frac{2^\alpha - 1}{2^{\alpha'} - 1}\; \frac{\zeta(\alpha+1)}{\zeta(\alpha'+1)} \tag{10}$$

Equation (9) shows that a whitening correction combined with a change of wavelet basis allows to synthetize a time-resolved fractional differentiation, able to reduce the arrhythmicity from the original signal,

$$s_R(t) \stackrel{\text{def}}{=} \sum_j \sum_{k=1}^{n_j} \langle \partial^{\frac{\beta^*}{2}} s, \psi_{j,k}^{(\alpha_0)} \rangle\; \psi_{j,k}^{(\alpha_0)}(t) \tag{11}$$

Notice that the fractional differentiation $\partial^{\beta^*/2}$ of the original signal is precisely the whitening filtering of the power expressed by $Q(f)^{-1}\,\Gamma(f)$ previously described in the spectral domain (4). Formula (11) thus expresses this 'spectral operation' in the time domain. To summarize, the 'rhythmic signal' is defined by

$$s_R(t) = \sum_j \sum_{k=1}^{n_j} w_{j,k}^*\; \psi_{j,k}^{(\alpha_0)}(t) \tag{12}$$

with

$$w^*_{j,k} = \mathcal{K}\left(\alpha_0 + \frac{\beta^*}{2}, \alpha_0\right) \, 2^{-j\,\beta^*/2} \, \mathcal{S}(w_{j,k}) \tag{13}$$

where the $w_{j,k}$'s were computed from the wavelet analysis of the original signal,

$$s(t) = \sum_j \sum_{k=1}^{n_j} w_{j,k} \, \psi^{(\alpha_0 + \beta^*/2)}_{j,k}(t) \tag{14}$$

A denoising shrinkage $\mathcal{S}$ has also been introduced to keep the significant largest wavelet coefficients. It is worth mentioning that each epoch will be analyzed with its appropriate wavelet basis parametrized with a specific β^* whereas the synthesis is performed in a unique wavelet basis parametrized with α_0. In practice, the regularity of the rhythmic signal is accomplished with $\alpha_0 > 2$.

The wavelet analysis of an original signal and the synthesis of a rhythmic signal is illustrated respectively on Fig. 2C and Fig. 2E. The discrete wavelet coefficients displayed in Fig. 2C illustrate the stationary gaussian process that governs the wavelet coefficients at each scale. In neural time series, these values are highly influenced by the scale-free process which contributes power in all frequencies. The wavelet coefficients synthetized through fractional differentiation of the original signal are thus corrected for this scale-free process (Fig. 2E).

Although the arrhythmic characteristic of the original discrete wavelet coefficients is attenuated in the discrete wavelet representation of the rhythmic time series (Fig. 2E), the wavelet power of the rhythmic signal does not exhibit the details of the

oscillatory content since its representation is driven by scales (Fig. 2F). However,

the Fourier power spectrum of the synthetized rhythmic signals will be appropriate

to extract the oscillatory components (Fig. 3). The average of the spectral power

densities from equivalent rhythmic signal provides an inventory of rhythms that we

call 'spectroscopy', as illustrated on Fig.3C for epochs collected in sleep. In

addition to this spectral signature, we have the distribution of the β-exponent that

characterizes the arrhythmicity of the rhythm's background (Fig. 3B).

Fig.3. **The 'rhythmic spectroscopy'.** (A) The rhythmic signal corresponding to (B) in

Fig.2. The value of the β-exponent of the removed arrhythmic component is indicated in

parenthesis. (B) From 300 epochs in NREM3 from the Anterior Cingulate (see upcoming

NREM sleep section), we display the probability distribution of the β-exponents. (C) The

individual rhythmic spectrums resulting from the Fourier analyses of the rhythmic time

series and the 'rhythmic spectroscopy' provided with the mean (bold line; see the sleep

spectroscopy section for a definition).

The RnB algorithm

In the next sections, the RnB algorithm will be used to extract rhythmic timeseries

from simulations and intracranial sleep recordings. Description on how to use this

algorithm on user-provided data can be found in a publicly available GitHub

(https://github.com/michaelcfoti/RnB-Wavelet/). Code for this algorithm is available

as a Matlab package licensed by an Apache 2.0 license. The module supports

Matlab2021a or later, with dependencies upon the 'Signal Processing' toolbox. The

package is openly developed and maintained. The project's repository includes the

codebase, a demo which allows to illustrate use of the algorithm on publicly

available and user-provided data and the documentation materials. This pipeline

allows to process user-provided timeseries, to extract a rhythmic timeserie and

perform basic spectroscopy. The rhythmic time series is extracted as a matrix that

can be used by the user to perform time-resolved analyses in other pipelines.

Two parameters need to be set to use the algorithm on user-provided data (see

the *wRnBMain* script in Github). The parameters linked to the β' estimation relate

to the $j1$ and $j2$ scale range to estimate the scale-free process (described in Eq.7).

The parameter J refers to the highest scales (lower frequency) upon which the

wavelet analysis/synthesis operations are performed to obtain the rhythmic signal,

similarly to a high-pass filter. These parameters can be changed according to the

input data properties and the documentation on GitHub allows us to understand

the impact of such changes. As default parameters used in this work, the scale run

from 1 to 9 to determine the arrhythmic β's and the parameter J was set to 8.

Simulation of arrhythmic background and rhythms

Simulations were conducted to assess RnB performance in characterizing

background and rhythms. These simulations combined various scale-free

backgrounds with transient oscillations. Considering a fractional Brownian motion

(fBm) kind of signals, the backgrounds were obtained by filtering a white-noise time

series in the frequency domain to obtain a power law $1/f^{\beta}$ of the spectral power,

while keeping random the Fourier phase. To introduce variability in the

background, each simulation trial used a β-exponent randomly sampled around a

predefined mean value, with a standard deviation of 0.1.

Alpha oscillations were added to these backgrounds using a classical

phenomenological neural mass model (Jansen and Rit, 1995; Pinotsis et al.,

2012). This model simulates the dynamics of coupled inhibitory and excitatory

neuronal populations interacting with a pyramidal cell. The canonical temporal and

spectral responses of the model are presented in Fig. 4. These neural mass

responses were superimposed onto pure scale-free backgrounds to construct

realistic time series.

1 **FIGURE 4**

4   Fig.4. **Neural mass oscillation**. (A) A four second oscillation produced by a standard neural

5   mass model (with the original parameters). (B) The Fourier power spectrum of the response

6   (A). The alpha peak is accompanied with a lower frequency content that corresponds to the

7   first seconds of the oscillation that does not reach a 'pure' harmonic oscillation.

Two batches of simulations were conducted to assess RnB's accuracy in estimating the maximal rhythmic amplitude from the rhythmic time series and of the scaling exponent.

1. The first batch tested the robustness of RnB estimation for an alpha oscillation (10.5 Hz) with a four second duration simulated at 15 amplitude levels within three arrhythmic background conditions (β = 1.7, 2.1 and 2.5).
2. A second batch of simulations assessed the ability of RnB to perform accurate estimations in the context of two concurrent oscillations (delta at 3 Hz delta and alpha at 13 Hz). The amplitude of the delta oscillation was varied across 15 levels and the alpha amplitude remained constant.

For both batches, 300 pure 'scale-free' epochs of eight seconds were generated for each amplitude level of the simulated oscillation, with scaling exponent randomly defined around the preceding defined scaling exponents, i.e. 1.7 with a standard deviation of 0.1. Then, 200 randomly chosen time series were selected to incorporate oscillatory activity. Finally, 60 epochs were randomly selected among the 300 epochs per amplitude level for statistical analyses. For each epoch, RnB estimates of maximal rhythmic amplitudes and of the scaling exponents were extracted and included in statistical analyses.

Statistical testing of the simulation's parameters

Linear regressions were used to assess the relationship between simulation parameters and RnB estimates (estimation of maximal rhythmic amplitude and

1 arrhythmic scaling exponents). Simulations parameters and their interactions were

2 entered as predictors of RnB outcomes in SPSS Statistics 26 software.

NREM sleep analyses

Our main objectives for NREM analyses were to show that rhythmic time series

exhibit characteristics of fundamental NREM sleep rhythms, notably their spectral

signature and inter-frequency coupling between delta and sigma rhythms. To do

so, we first evaluated how the rhythmic time series extracted from intracranial

recordings of NREM sleep provided a reliable representation of cardinal rhythms.

Second, we detected sleep slow waves in the rhythmic time series and

characterized how these events locally group and synchronize other rhythms in

the theta and sigma frequency bands. Finally, we compared delta-sigma coupling

between rhythmic and original time series.

Intracranial recordings

The intracranial recordings used in this work are extracted from the MNI-open

iEEG atlas (https://mni-open-ieegatlas.research.mcgill.ca) (Ellenrieder et al.,

2020). From this multicentric database providing physiological activity in non-

lesional tissues of the sleeping brain, we used the recordings of 16 patients with

epilepsy. Analyses were performed on NREM2 and NREM3 sleep recordings and

included all the electrodes (200 Hz) localized in the precuneus and the anterior

cingulate. All recordings were segmented in 20 seconds epochs. Duration of

recordings in each region and sleep stage are described in Table 1.

Table 1.

Region	Sleep stage	# epochs	Total duration (min)
Precuneus	NREM2	967	322.33
	NREM3	951	317
Ant. Cingulate	NREM2	821	273.66
	NREM3	809	269.66

2
3   **Table 1. Dataset for the intracranial sleep recordings.** Total number of 20s
4   epochs and total duration of each sleep stage are shown.
5
6

Spectroscopy of NREM recordings

All NREM sleep epochs were processed with the RnB algorithm to extract rhythmic time series and estimate the distribution of scaling exponents in the time-scale domain. From RnB outputs, we estimated the distribution of scaling exponents and the power spectral density from the rhythmic timeseries separately in NREM2 and NREM3 sleep, what will be referred to as 'NREM sleep spectroscopy' (alike Fig. 3B and Fig. 3C). We compared this spectroscopy in each sleep stage to a standard spectral parameterization method (FOOOF). FOOOF was applied on the original intracranial recordings from same NREM epochs that were processed using RnB. For all analyses, FOOOF extracted 3 peaks in the 1-45 Hz range using a fixed aperiodic mode.

Slow waves detection in the rhythmic signals

We used a proof-of-concept approach to detect sleep slow waves (SSWs) in the rhythmic time series from NREM3 sleep, aiming to demonstrate that the rhythmic time series produced by RnB exhibit the characteristic oscillatory features of SSWs in the time domain.

Rhythmic SSWs (rSSW) were detected in two steps. First, we used a standard SSWs intracranial detection on the rhythmic time series, with an initial delta low-pass filter (0.5-4 Hz), followed by detection of high frequency activity (>32Hz) to define the polarity of the slow waves (Ellenrieder et al., 2016). Second, we performed another detection pass using similar polarity criteria, but now with a

band-pass filter adapted to the specific delta found in the spectroscopy of each

region and sleep stage (Fig. 7). This adaptive filtering enabled us to focus on the

oscillatory content specifically expressed in each region, like recent approaches

(Donoghue et al., 2022). The rSSW inventory was defined as the non-redundant

union of events detected in both passes. For analyses involving the rhythmic time

series (spectroscopy, time-frequency analyses, and PAC), four-second time

windows were extracted around the maximal hyperpolarization peak of each

rSSW.

For comparative PAC analyses using the original NREM recordings, an additional

inventory of SSWs was produced from the original NREM sleep recordings using

standard intracranial detection criteria (Ellenrieder et al., 2016) We then extracted

four-seconds time windows centered around the hyperpolarisation peak of each

detected original SSW.

As in our previous work (Bouchard et al., 2021), we characterized the transition

frequency of each SSWs and rSSWs by measuring the time delay (τ) between the

down phase (hyperpolarization) and up phase (depolarization) maxima. We used

an unsupervised Gaussian mixture model (EM algorithm) to estimate each event's

latent 'switcher' class (fast or slow) based on the distribution of transition

frequencies in each region.   Events in the rhythmic signal are referred to as

rhythmic slow switchers (rSlowS) and rhythmic fast switchers (rFastS).

Spectroscopy analyses of rSSWs

We analyzed the spectroscopy of rSSWs during NREM3 sleep. The spectroscopy of all rSSWs was compared to an equivalent number of four seconds NREM3 time windows without detected rSSWs (baseline). Second, we directly compared the spectroscopy of rSlowS to rFastS, as SSWs with a slower transition frequency are known to synchronize NREM sigma rhythms (Nicolas et al., 2022).

Statistical analyses – impact of the transition frequency on rSSWs spectroscopy

The impact of switcher type on arrhythmic and rhythmic estimates from RnB was assessed using tests computed in SPSS 26. Wilcoxon tests were used to test switcher difference (rSlowS vs rFastS) in the distribution of scaling exponents from RnB. Bilateral t-test were used to test for difference between rSlowS and rFastS for the integrated rhythmic power in frequency bands locally modulated per brain region (delta: 0.5-4 Hz in both regions, sigma: 8-14 Hz in anterior cingulate, 11.5-14.5 Hz in precuneus, theta: 5-9 Hz in precuneus).

Time-domain analyses of rSSWs

To examine the organization of NREM rhythmic activity around rSSWs, we performed time-frequency analyses (scalograms) around two distinct characteristic markers of rSSWs. For analyses that included all rSSWs (regardless of switcher type), the peak of hyperpolarization was used as the central landmark, consistent with previous studies (Cox et al., 2014). When comparing rSlowS and rFastS specifically, we centered the scalogram on the zero-crossing point between

hyperpolarization and depolarization, which represents the midpoint of the

transition phase for both types.

We computed two types of scalograms: the standard 'induced power' scalogram,

which represents the cumulative amplitude of wavelet coefficients and was applied

to all rSSWs, and a 'phase-locked' scalogram to specifically assess in-phase

synchrony of rhythmic signals for switcher comparisons (Tallon-Baudry et al.,

1999). For all analyses, we calculated the time-frequency wavelet transform within

a one-second window around each central landmark (indicated as t=0 in Fig. 8 and

Fig. 9). The scalograms were calculated using the continuous wavelet transform

with the Morse analytic wavelet (default parameters: $\beta = 20$ and $\gamma = 3$). For

visualization only, each scalogram is renormalized using an analytic variant of the

Taeger-Kaiser power normalization and each display is individually rescaled

between 0 and 1.

Phase-Amplitude Coupling analyses of rSSWs

To demonstrate that the rhythmic timeseries is sensitive to the phase-coupling of

delta and sigma rhythms during NREM sleep, we computed phase-amplitude

coupling (PAC) from the original NREM recordings using the SSW inventory and

compared it to estimates computed on the rhythmic time series using the rSSWs

inventory (rhythmic PAC; rPAC).

For SSWs, we used the phase $\varphi(t)$ of the SSW (from the Hilbert transform in the

delta band) and the amplitude of the simultaneous sigma activity (10 - 16 Hz) in

the original signal. For rPAC, we considered the phase $\varphi(t)$ of the rSSW (from the

Hilbert transform in the delta band) and the amplitude of the simultaneous sigma

activity in the rhythmic timeseries. For rPAC, we adapted the sigma frequency

band as defined by the RnB spectroscopy in each region (Fig. 7; Anterior

Cingulate: 8-14 Hz; Precuneus: 11.5-14.5 Hz).

For each SSW or rSSWs, the PAC is defined by:

8
$$PAC = \left| \frac{1}{T}\sum_t A(t)\, e^{i\,\varphi(t)} - \frac{1}{T}\sum_t A(t)\ \frac{1}{T}\sum_t e^{i\,\varphi(t)} \right| \qquad (15)$$

where T is the SSW or rSSW duration across which the summation is running.

Detection of theta bursts associated to rSSWs in the rhythmic timeseries

PAC from the rhythmic timeseries was investigated according to the presence of

'theta burst' (TBs) in the precuneus because preceding analyses highlighted that

the transition of rSSWs in this region were transiently associated with theta. To do

so, we adapted an existing NREM TB detection algorithm to be applied on the

rhythmic timeseries (Jiang et al., 2019). We adapted the theta-band filter using our

sleep spectroscopy i.e. the theta mode obtained from the rhythmic spectrum in the

precuneus (7.02 $\pm$ 2.4 Hz in NREM3). The detected events needed to have peaks

above ± 3 standard deviation of the average power across the epochs with start

and stop times defined with ± 1 standard deviation. The final TBs inventory kept

events with a duration between 0.4 and 1 second. We then extracted 4-sec

windows centered around rSSWs co-occurring with TBs (<500ms; rSSWs+TBs

events) and around rSSWs that did not (rSSWs-TBs events).

Statistical analyses of PAC associated with slow waves

PAC were averaged for SSWs detected in the original and rhythmic signal

separately for rSlowS and rFastS in each region (anterior cingulate and

precuneus). PAC was also investigated according to TB specifically in the

precuneus irrespective of switcher type (rSSWs+TBs and rSSWs-TBs).

Mann-Whitney U-tests were used to test for difference in PAC between the original

and rhythmic timeseries separately for both type of switchers in the anterior

cingulate and precuneus. The impact of switchers type on PAC was also

investigated separately in each region for original and rhythmic timeseries

separately. Finally, PAC differences between rSSWs according to the presence of

a TB (rSSWs+TBs vs rSSWs-TBs) were investigated in the precuneus.

Results

Simulations and validation of RnB

We first used realistic simulations to assess RnB estimations of both rhythmic and arrhythmic parameters. First, we considered an alpha (10.5 Hz) oscillation in an arrhythmic background (Fig. 5). The signal from this simulation was processed by RnB to produce a rhythmic time series (Fig. 5C). The arrhythmic drift which dominated the original time series (Fig. 5A) is removed in the reconstructed signal (Fig. 5C). The spectral density of the rhythmic component provided by RnB (Fig. 5D) exhibits a clear signature of the oscillation in comparison with the original Fourier spectrum (Fig. 5B).

FIGURE 5

Fig.5. *RnB* **estimation in the wavelet domain. A.** Example of a simulated time series containing

a mixture of a scale-free activity ($\beta = 2.2$; arrhythmic background) and an alpha oscillation (four

seconds 10.5 Hz rhythm). **B.** The Fourier spectra of the original time series $s(t)$ displayed in (A),

mostly dominated by the dominant arrhythmic background. **C.** The output $s_R(t)$ of the *RnB*

algorithm, revealing the rhythmic features of the time series synthesized from the wavelet's

coefficients filtered for the arrhythmic factor. **D.** The Fourier spectra of a single $s_R(t)$ epoch (in (C))

highlight a clear signature of the simulated oscillation that was added to the arrhythmic background,

with a marginal "arrhythmic" contribution. This averaged across multiple epochs define the rhythm's

spectroscopy for further analyses (methods). The black dotted line is the original spectra of the

simulated oscillation, without the addition of an arrhythmic background. The 'expected power'

indicates the maximal power of the simulated oscillation.

Regression analyses were performed to investigate the validity of RnB estimations

at different amplitude levels of the simulated oscillations and different arrhythmic

background (Fig. 6B). Analyses showed that the rhythmic estimations of the alpha

oscillation (amplitude out) scaled remarkably linearly with the amplitude of the

simulation (amplitude in) (b=0.99, p<0.0001, R^2=0.98). Rhythmic estimations

differed slightly between the three arrhythmic conditions (interaction: t=8.58,

p<0.0001; R^2<0.01), although they remained strongly associated with the

amplitude of the simulated rhythm in each of the background conditions (b=0.99 to

b=0.94 from lower to higher scale-free exponents, p<0.0001 in the three arrhythmic

conditions).

FIGURE 6

3   Fig.6. **RnB estimation of rhythms and arrhythmic background**. (A1, A2, A3). Examples

4   of simulated arrhythmic time series with three different values of arrhythmic background (β)

(1.69, 2.11, 2.49); 300 simulations were generated for each arrhythmic condition. For a

random set of 200 arrhythmic simulations, an alpha oscillation (10.5 Hz) was added, varying

its amplitude at 15 fixed amplitude levels (x-axis on the B plot). For each amplitude level,

RnB is applied 60 times on a random selection among all epochs, enforcing a realistic

approach where an oscillation may or may not be systematically present. (B). Estimated

maximal rhythmic amplitude measured by RnB (Y-axis) plotted against simulated alpha

oscillation amplitudes (X axis). Colors of the dots represent the arrhythmic conditions (red:

β=1.69; blue: β=2.11; yellow: β=2.49). (C). Estimated scaling exponents out (Y axis) with

respect to the simulated alpha oscillation amplitudes (X axis) for the three simulated

arrhythmic backgrounds. The dashed line indicates the value in the simulation. (D). An

example of rhythmic oscillations to be added to (A3). (E). Spectral signature of the rhythmic

component from (D). (F1). Maximal rhythmic amplitude of RnB in the delta range with respect

to varying amplitude of this oscillatory component. (F2). Maximal rhythmic amplitude at 13

Hz, varying amplitude of the 3 Hz-oscillation. (G). Response of the RnB algorithm for the

scale-free exponent estimation, varying amplitude of the 3Hz-oscillatory component.

Second, we evaluated the accuracy of RnB estimates of the arrhythmic

background (scaling exponent) and whether they were impacted by the amplitude

of the simulated alpha oscillation (Fig. 6 C). As expected, the three simulated

arrhythmic background conditions were strongly associated with RnB estimates of

the arrhythmic background (β; change in constant, t=663.3, p<0.0001, R^2=0.99).

In addition, higher amplitude of the simulated alpha oscillation was associated with

higher estimates of the arrhythmic background (β; change in slope; b=0.10, t=91.1,

p<0.001, R^2<0.01), although this relationship differed slightly between the three

background conditions (interaction; t=9.47, p<0.001; R^2<0.001; b=0.10 to b=0.11

across the three background conditions).

Third, we investigated whether the presence of a concurrent delta and alpha

oscillation affected the accuracy of RnB estimations (Fig. 6 D to G). As expected,

the rhythmic amplitude estimation for the delta oscillation (amplitude out) scaled

linearly with the amplitude of the simulated delta oscillation (amplitude in; Fig. 6

F1, b=0.87, p<0.0001, R^2=0.85). There was no significant relationship between the

amplitude of the simulation delta oscillation (amplitude in) and the estimated

maximal alpha amplitude (Fig. 6 F2; b=-0.01, p=0.27, R^2 < 0.01). RnB slightly

overestimated the scaling exponent in presence of multiple oscillations, but this

does not scale with the amplitude of the simulated delta oscillation (Fig. 6 G,

constant=2.7, p<0.001, b=-0.03, p=0.31, R^2=0.001).

Overall, the RnB outputs of rhythmic amplitude and scaling exponents are reliable

to assess single or concurrent oscillations (alpha and delta), with minor caveats.

First, rhythmic amplitude is slightly underestimated in arrhythmic conditions with

high scaling exponents. Second, RnB marginally overestimate the scaling

exponents when a high amplitude oscillation is present. In both cases, the error

from RnB is marginal and represents less than 10% of the variance for either of

their rhythmic or arrhythmic outputs.

The spectroscopy of sleep recordings

Given that rhythmic time series provided by RnB are corrected for arrhythmicity,

we now demonstrate their potential to characterize genuine NREM sleep rhythms.

Our analyses focused on the anterior cingulate and the precuneus, two key regions

involved in NREM cardinal delta and sigma rhythms (Murphy et al., 2009; Zerouali

et al., 2014).

To better interpret our spectroscopy of NREM sleep recordings, we first illustrated

how the NREM sleep power spectrum is decomposed using FOOOF (Donoghue

et al., 2020). We then assessed the contribution of the spectroscopy provided by

RnB. As expected, NREM2 and NREM3 sleep spectra were characterized by a 1/f

arrhythmic background (Fig. 7 A1 and A2). FOOOF confirmed significant sigma

peaks in the average NREM spectrum in both stages and regions, with an

additional theta peak in the precuneus during NREM2 and NREM3 sleep (Fig. 7

B1 and B2). FOOOF did not reveal peaks below 4Hz, which fits with previous

findings indicating the limitations of spectral parametrization methods to identify

delta residual spectral power (Gerster et al., 2022).

FIGURE 7

Fig. 7. **The spectroscopy of NREM sleep recordings**. Results from spectral factorization (top

row) and the spectroscopy (bottom row) of NREM sleep recordings in the anterior cingulate (two

left columns) and precuneus (two right columns). (A1, A2). Standard spectral density per region in

NREM2 (blue) and NREM3 (pink) sleep, highlighting a significant arrhythmic 1/f background

alongside spectral peaks. (B1, B2). Residual periodic power estimated by FOOOF in NREM2 and

NREM3 sleep. Dashed vertical lines indicate found spectral peaks. (C1, C2). Probability density of

observed scaling exponents as assessed by *RnB* wavelet coefficients during NREM2 and NREM3.

(D1, D2). Spectral analysis from the rhythmic timeseries, highlighting distinctive peaks in each

region. Dashed horizontal lines in the delta band indicate the frequency bands to be used for the

detection of sleep slow waves in the rhythmic timeseries.

Next, we assessed whether our NREM sleep spectroscopy provides a reliable representation of NREM cardinal rhythms. Interestingly, the NREM sleep spectroscopy highlighted higher delta power in NREM3 as compared to NREM2 sleep, although the specific frequency bands varied between the two regions (Fig. 7 D1 and D2). In the anterior cingulate, a low-frequency delta rhythmic peak ($1.17 Hz$) predominated in NREM3 as compared to NREM2 sleep, whereas two delta rhythmic delta peaks (1.95 and 3.71 Hz) were found in the precuneus during NREM3 and NREM2 sleep. A rhythmic theta peak ($\approx 7 Hz$) was also found specifically in the precuneus during NREM2 and NREM3 sleep. Additionally, rhythmic sigma peaks were found in both regions, with slightly faster frequencies in the anterior cingulate (12.5 Hz) as compared to the precuneus (13.5 Hz), and lower maximal power in NREM3 compared to NREM2. RnB also provided distributions of scaling exponents β in each region (Fig. 7 C1 and C2), with higher scaling exponents (higher persistence) in NREM3 as compared to NREM2 sleep in both regions. Thus, RnB spectroscopy reveals a more exhaustive NREM sleep spectral content as compared to FOOOF.

Rhythmic sleep slow waves modulate rhythmic and arrhythmic activity

Given that delta activity was higher in NREM3 in both regions, we detected sleep

slow waves (SSWs) in the rhythmic time series (rSSWs), cardinal NREM rhythms,

and assessed how they modulate other rhythms during NREM3 sleep. The

analysis of rSSWs showed an expected biphasic shape, with a suppression of

higher frequency during their downstate (Fig. 8 A1 and A2). Interestingly, time-

frequency analyses of the rhythmic timeseries associated with rSSWs in NREM3

showed that rSSWs in the anterior cingulate were specifically associated with

sigma activity in their depolarization period during NREM3 sleep (Fig. 8 B1 and

B2).

Spectroscopy-based analyses of rSSWs were also performed to assess how

rSSWs transiently modulate rhythmic and arrhythmic NREM activity. As compared

to baseline NREM epochs (epochs without rSSWs), most epochs with rSSWs had

lower scaling exponents (lower persistence), although this effect was predominant

in the anterior cingulate (Fig. 8 C1 and C2). Epochs with rSSWs also showed

higher delta and lower sigma rhythmic power than baseline epochs in both regions,

although the anterior cingulate showed a stronger increase in rhythmic delta and

a wider rhythmic sigma (Fig. 8 D1 and D2). The theta peak previously observed in

the precuneus also showed lower power during rSSWs as compared to the

baseline.

FIGURE 8

Fig. 8. **SSWs in rhythmic time series from the anterior cingulate and precuneus during**

NREM3 sleep. (A1, A2). Average waveforms of rSSWs detected during NREM3 in the anterior

cingulate (top) and precuneus (bottom). (B1,B2). Induced scalograms of the rhythmic time series

associated with SSWs coregistered with respect to the hyperpolarization phase. Red/yellow

indicate higher normalized power than blue. (C1,C2). Distribution of scaling exponents across

epochs with rSSW (plain) and without rSSW (dashed lines). (D1,D2). Spectroscopy of epochs with

rSSWs (plain) and without rSSWs (dashed lines) during NREM3 sleep.

The spectroscopy of SSWs differ according to their transition period

SSWs can be categorized as slow or fast switchers, depending on the duration of

the *transition period* between their hyperpolarization and depolarization phase

(Bouchard et al., 2021). Interestingly, sigma rhythms are preferentially nested in

the transition of SSWs with longer transition periods (slow switchers), as compared

to fast switchers during NREM sleep (Nicolas et al., 2022). We thus evaluated

whether sigma activity after rSSWs was due to slow switchers.

We categorized each rSSW during NREM3 as a rhythmic slow switcher (rSlowS)

or rhythmic fast switcher (rFastS; methods; Fig. 9). We reproduced the clustering

of rSSWs between rSlowS and rFastS in the rhythmic time series, with a

distribution skewed toward rFastS in both regions (Fig. 9 A1 and A2). The

spectroscopy of rSlowS differed from rFastS particularly in the anterior cingulate.

In this region, rSlowS showed a bimodal distribution of scaling exponents with

persistent and antipersistent modes, whereas rFastS showed a distribution of

scaling exponents with a clear persistent mode (Fig. 9 C1; Wilcoxon test : z-

statistic: -4.49, p<0.001). Compared to rFastS, rSlowS also showed significantly

higher rhythmic delta and higher rhythmic sigma power in the anterior cingulate

(Fig. 8 D1, t-test p<0.05). In the precuneus, arrhythmic and rhythmic estimates

were superposable between rFastS and rSlowS (Fig.9 C2 and D2).

FIGURE 9

Fig. 9. **The spectroscopy of slow (rSlowS) and fast switchers (rFastS) during NREM3.** (A1,

A2). The probability density of rSSWs according to their transition frequency is shown for the

anterior cingulate (A1) and precuneus (B1), highlighting a bimodal distribution in both regions. The

transition frequency to cluster rFastS and rSlowS is shown as a dashed vertical line. (B1, B2).

Average waveform of rSlowS and rFastS, with respect to the separation frequency are defined in

(A1) and (A2) respectively. Averages are centered around the zero-crossing markers. (C1, C2).

Probability density of the scale-free exponents is estimated by *RnB* for rSlowS and rFastS in each

region. (D1, D2). Spectroscopy of the rhythmic switchers in NREM3 are shown for both regions.

The horizontal bold vertical bars depict local frequency bands which were considered for further

PAC analyses. Bilateral T-tests were performed in each region to investigate switcher-related

differences in the integrated rhythmic power for each region (anterior cingulate: delta between 0.5

and 4 Hz, sigma between 8-14; precuneus: delta between 0.5 and 4 Hz, theta between 5-9 Hz, and

sigma between 11.5 – 14.5 Hz). Significance is depicted using stars (p-values: * <0.05; **<0.01).

rSlowS and rFastS regroup differently transient sigma and theta rhythms

To evaluate how rSSWs synchronize NREM rhythms with respect to their transition period, we assessed the scalograms of rSlowS and rFastS derived from the rhythmic time series (Fig. 10). Induced and phase-locked rhythmic power were both considered to assess how rSSWs group or synchronize rhythmic activity, respectively. As sigma rhythms occur specifically during the transition from hyperpolarization to depolarization particularly for slow waves with slower transition (Nicolas et al., 2022), we hypothesized that rSlowS would show higher phase-locked sigma power during their transition as compared to rFastS.

Induced sigma power was observed across rSlowS and rFastS in both regions (Fig. 10 A1, A2, C1, C2). The precuneus also showed induced theta power around the transition phase of rFastS and rSlowS (Fig. 10 A2, C2). As expected, rSlowS in the anterior cingulate showed phase-locked sigma rhythmic power in their transition, with increasing frequency and reaching maximal power synchronously with their depolarizing peak (Fig.10 B1). Although induced 'theta bursts' (TBs) in the precuneus were not sufficiently synchronized around the transition to produce a theta signature in the locked scalogram, phase-locked rhythmic sigma power occurred later with a delay around 400 msec preferentially for rFastS (Fig.10 B2, D2).

Fig.10. **Induced and phase-locked rhythmic power synchronized with the transition of**

rSlowS and rFastS during NREM3 sleep. Scalograms of induced (A1, A2, C1, and C2) and

phase-locked (B1, B2, D1, and D2) power for the rSlowS (Left panels) and the rFastS (Right

panels), co-registered around their zero crossing, in the anterior cingulate (top panels) and the

precuneus (bottom panels). Vertical lines indicate the transition markers for rSlowS and rFastS

(zero-crossing in bold; the depolarization 'max. peak' as estimated from the averaged signal in

Fig.9 B1 and B2). The arrows in top panels (anterior cingulate) indicate phase-locked power around

the transition of rSlowS, whereas arrows in bottom panels (precuneus) emphasize the temporal

relationship between the induced theta and phase-locked sigma activity predominantly for rFastS.

Each plane is individually normalized for visualization (hot colors for higher power).

rSlowS and TBs promote SSW-sigma coupling specifically in rhythmic time series

To evaluate how sigma amplitude is systematically modulated by the phase of delta rhythms in NREM sleep, we computed delta-sigma phase-amplitude coupling (PAC) during SSWs in NREM3. We considered PAC from SSWs in the original EEG signal and from rSSWs detected in the rhythmic time series (rhythmic PAC: rPAC). rPAC was computed using delta frequencies which stood out locally in each region's spectroscopy (Fig. 7, see methods), whereas PAC was computed using standard SSW (0.5-4Hz) and sigma (12-16Hz) frequencies. We hypothesized higher PAC for rSlowS and rFastS detected in the rhythmic time series as compared to events detected in the original signal since arrhythmic interferences should be minimized.

As shown in Fig. 11 (A and B), rPAC values were significantly higher than PAC values for both types of switchers in the two brain regions (Mann-Whitney U-tests: $p < 0.001$ for all events). These results suggest that phase interferences are reduced in the rhythmic time series, revealing higher phase coupling between delta and sigma rhythms. Additionally, rPAC was significantly higher for rSlowS as compared to rFastS in the anterior cingulate during NREM3 (Fig. 11 A, U=2.82, p=0.005), as expected. This difference between SlowS and FastS in the anterior cingulate was not significant with standard PAC (U= 1.85, p-value=0.06). In the precuneus, no significant differences in rPAC were found between switchers (Fig. 11 B, U=0.18, p>0.1).

FIGURE 11

Fig.11. **Delta-sigma PAC from original and rhythmic time series.** Average

values and standard error of the mean for rPAC (rhythmic) and PAC (raw), for slow

and fast switchers during NREM3 sleep in the anterior cingulate (A) and in the

precuneus (B). In the precuneus, rPAC values are shown in (C) for all rSSWs

without TBs (rSSW-TBs) and for rSSWs co-detected with a TBs (rSSW+TBs). For

each event type, arrows indicate significant differences between PAC and rPACs

values. Stars indicate significance value (*: p≤0.01).

Since previous literature suggests that NREM TBs precede slow-wave-spindle complexes and facilitate delta-sigma PAC (Gonzalez et al., 2018), we explored the effects of TBs on rPAC during rSSWs in the precuneus. This analysis is prompted by the specific theta peak and induced theta found in the precuneus spectroscopy and with the transition of rSlowS and rFastS in the precuneus scalogram analyses (Fig.10). We designed a rhythmic TBs detector that used the theta peak found in the precuneus spectroscopy. Then, we identified rSSWs co-occurring with TBs (<500ms; rSSWs+TBs events) and rSSWs that did not (rSSWs-TBs). We hypothesized higher delta-sigma rPAC for rSSWs+TBs events as compared to rSSWs-TB in the precuneus.

As shown in Fig. 11 C, delta-sigma rPAC was higher for rSSWs+TBs compared to rSSWs-TBs (U=2.46, p=0.01). Importantly, rSSW+TBs events represented around 6% of all rSSWs in NREM3 (116/1815 rSSWs). Although rSSW+TBs are rare, they constitute a significant modulator of rPAC in NREM3. Thus, the rhythmic time series shows globally higher delta-sigma coupling. Furthermore, rPAC was higher for rSlowS in the anterior cingulate and was significantly amplified with TBs in the precuneus.

Discussion

Interference between background and rhythms in the time domain is a challenge that current spectral parametrization methods cannot address. We introduce a wavelet-based method able to disentangle the rhythmic time series from the arrhythmic background. We showed that rhythmic time series adequately extract rhythmic activity in either simulations or in NREM sleep, with enhanced coupling estimates.

RnB allows time-domain analyses of brain rhythms free from arrhythmicity, whereas spectral methods focus on properties of "periodic" peaks and aperiodic background (Wen and Liu, 2016; Donoghue et al., 2020). Usually characterized as a 1/f slope (i.e., a scaling exponent) varying over time, arrhythmicity indicates fluctuations of scale-free brain dynamics (He et al., 2010; Miskovic et al., 2019). Pure arrhythmic EEG (i.e., without cardinal oscillations) represents around 80% of the recording time in NREM2 and more than 50% in NREM3 sleep (Helfrich et al., 2021). This ubiquitous background also interferes with spectral and temporal estimates of brain rhythms: time series with higher scaling exponents are characterized by slower fluctuations contributing to delta power in standard spectral analyses which may, for instance, be confounded for sleep slow waves (Donoghue et al., 2022; Gerster et al., 2022). As previously reported (Lendner et al., 2020; Bódizs et al., 2021; Horváth et al., 2022), our results showed higher scaling exponents in deeper NREM sleep. We also showed that scaling exponents fluctuate across sleep epochs, which was previously reported in multifractal

analyses (Lina et al., 2019). This overnight variability in arrhythmicity may reflect time-dependent changes in multiple neurophysiological parameters during sleep, such as the excitation-inhibition balance (Niethard et al., 2016; Gao et al., 2017) and the dynamics of brain networks (Brake et al., 2024). So far, amplitude and phase estimates of oscillatory activity remained unaccounted for arrhythmicity. RnB allows to extract phase and amplitude estimates of rhythmic activity underlying genuine NREM sleep oscillations in the time domain, controlling for 'instantaneously' differences in the arrhythmic backgrounds.

Recent simulation studies pinpointed limitations in spectral methods to reveal rhythmic delta due to interferences between arrhythmicity and low frequencies in the Fourier domain (Gerster et al., 2022). Hence, previous sleep studies using such methods mostly focused on sigma periodic peaks (Bódizs et al., 2021; Schneider et al., 2022). Interestingly, our simulations showed that RnB robustly estimate concurrent delta and sigma rhythms across different scale-free scenarios. Furthermore, RnB detected delta, theta, and sigma differences between NREM2 and NREM3 in the anterior cingulate, which correspond to changes expected in NREM sleep (Steriade, 2006). We argue that RnB allows an accurate spectroscopy of NREM rhythms due to the wavelet based 'punctual' estimations and corrections in the time-scale domain. This allows to synthesize rhythmic delta activity in the time-scale domain, which otherwise overlaps with the scale-free process in the Fourier domain.

Compared to the precuneus, the anterior cingulate spectroscopy showed stronger differences in arrhythmic and rhythmic activities between NREM2 and NREM3 sleep. Specifically, rhythmic timeseries from the anterior cingulate showed higher rhythmic delta power in NREM3 as compared to NREM2 sleep, consistent with the well-known anterior predominance of NREM delta power and of sleep slow waves (Vyazovskiy et al., 2007; Hubbard et al., 2020). This facilitated the detection of sleep slow waves (SSWs) in the rhythmic time series (rSSWs) from NREM3 sleep using spectroscopy-adapted criteria, aligning with recent guidelines to adapt detection criteria to local frequency content (Muehlroth and Werkle-Bergner, 2020; Donoghue et al., 2022).

rSSWs in the anterior cingulate were associated with higher rhythmic delta power and lower scaling exponents compared to baseline. Lower scaling exponents during rSSWs in the anterior cingulate resonate with a recent study reporting a flatter slope (lower scaling exponent) during the depolarization phase of SSWs in anterior regions, suggesting higher excitation in this phase (Lendner et al., 2020). This is consistent with the anterior predominance of the slow oscillation, during which neurons are strongly depolarized in the active phase (Steriade, 2006). Furthermore, rSSWs modulated sigma power differentially the anterior cingulate and precuneus, consistent with previous EEG findings on SSWs (Cox et al., 2014). This anterior specificity may reflect the cortico-genesis of SSWs, as these waves originate in the anterior cingulate before spreading in other regions (Murphy et al., 2009). Thus, we hypothesize that rSSWs, expressed above the arrhythmic background, result from the underlying slow oscillation during NREM sleep.

We reproduced the 'fast-slow' switchers classification of the rSSWs observed in

scalp EEG sleep recordings (Bouchard et al., 2021). In the anterior cingulate,

rSSWs with slower transitions (rSlowS) displayed distinct characteristics

compared to those with faster transitions (rFastS), including higher delta and sigma

rhythmic power. These differences align with evidence that SSWs with longer

depolarization periods show larger amplitudes, higher sigma synchronization and

sleep spindle occurrence (Botella-Soler et al., 2012; Cox et al., 2018, 2020;

Chylinski et al., 2022). Furthermore, rhythmic sigma power was phase-locked

specifically after rSlowS transition in the anterior cingulate, and these events

exhibited higher delta-sigma rPAC compared to rFastS. Together, these findings

suggest that rSlowS from the anterior cingulate play a pivotal role in mediating

interactions between rSSWs and NREM sigma rhythms.

Supporting this, previous findings indicated that sleep spindles in anterior regions

did not show a clear relationship to fast switchers and preferentially occurred

during the depolarization phase of a subset of slow switchers (Chylinski et al.,

2022). Consistently, we observed a bimodal distribution of scaling exponents

specific to rSlowS in the anterior cingulate, with a subset exhibiting lower values

(i.e. antipersistence). Recent work suggests that such arrhythmic properties reflect

local network dynamics involved in long-range connectivity (Brake et al., 2024).

Interestingly, slow switchers coupled with sleep spindles are known to show higher

frontal EEG connectivity (Bouchard et al., 2021). Thus, we hypothesize that the

antipersistent arrhythmic regime linked to rSlowS in the anterior cingulate may

contribute to the emergence of cortical networks associated with sleep spindles.

Interestingly, while the coupling between rSSWs and sigma in the anterior cingulate depended on the transition frequency of rSSWs, it relied instead on the co-occurrence of TBs and rSSWs in the precuneus. TBs have been identified as an "early" down state when the slow oscillation is less synchronized, facilitating subsequent SSWs up states and the later occurrence of sleep spindle (Gonzalez et al., 2018; Jiang et al., 2019). Thus, TBs could help to drive sigma synchronization in posterior regions, where the cortical slow oscillations are usually less synchronized. Furthermore, we can hypothesize that transient sigma rhythms associated to rTBs or rSlowS could synchronize across brain regions to form "global" spindles. Interestingly, EEG "global" spindles involve progressive synchronization of MEG sigma rhythms from the precuneus to the anterior cingulate (Zerouali et al., 2014). Thus, transient rSlowS and TBs could be local cortical features contributing to sigma synchronization during global spindles.

Delta-sigma PAC was higher for SSWs detected in the rhythmic as compared to the original signal. A few reasons could account for this. First, it is possible that the spectroscopy-improved rSSW detection criteria increased the representation of genuine slow oscillations, which led to better disclose delta-sigma coupling (Aru et al., 2015). The rhythmic time series might also better estimate the inherent phases of the cardinal rhythms, as arrhythmic interferences have been attenuated (Donoghue et al., 2022). In any case, it is likely that coupling in the rhythmic time series provides a better insight into the oscillatory-dependent hippocampo-thalamo-cortical interactions altered in numerous disease (Helfrich et al., 2019; Mendes et al., 2021). Currently, PAC metrics express high heterogeneity and are

often low, preventing their clinical use (Mander et al., 2017; Jurkiewicz et al., 2021).

By jointly improving the detection of NREM rhythms and the assessment of their

coupling, RnB could decrease the heterogeneity of PAC or phase-based findings.

RnB represents a significant paradigm shift in EEG signal processing. It constitutes

a crucial step towards disentangling electrophysiological rhythms from

arrhythmicity in brain time series. However, further refinements could help to

estimate rhythmic processes even more accurately. Specifically, our current

rhythmic signal may not be considered as a "sparse representation" in terms of

oscillatory events and future work could improve its classification. For instance,

instead of using standard detection criteria into the rhythmic time series, previously

proposed matching pursuit methods could be applied to the rhythmic signal to

better identify basic patterns corresponding to NREM rhythms (rSSWs, TBs, sigma

rhythms). This would allow the development of detectors relaxing the need of prior

detection criteria (Durka and Blinowska, 1995; Krstulović and Gribonval, 2006;

Durka et al., 2024). Alternatively, previously proposed cycle-by-cycle analysis

could also be used directly in the rhythmic signal to identify periods where such

events manifest. Thus, the application and refinement of our '*sleep spectroscopy*'

could be crucial to provide updated detection criteria for NREM sleep transient

events across the lifespan and clinical conditions.

References

Abry P, Wendt H, Jaffard S, Didier G (2019) Multivariate scale-free temporal

dynamics: From spectral (Fourier) to fractal (wavelet) analysis. C R Phys

20:489–501.

Aru J, Aru J, Priesemann V, Wibral M, Lana L, Pipa G, Singer W, Vicente R

(2015) Untangling cross-frequency coupling in neuroscience. Curr Opin

Neurobiol 31:51–61.

Blu T, Unser M (2000) The fractional spline wavelet transform: definition end

implementation. 2000 IEEE Int Conf Acoust, Speech, Signal Process Proc

(Cat 00CH37100) 1:512–515 vol.1.

Bódizs R, Szalárdy O, Horváth C, Ujma PP, Gombos F, Simor P, Pótári A,

Zeising M, Steiger A, Dresler M (2021) A set of composite, non-redundant

EEG measures of NREM sleep based on the power law scaling of the Fourier

spectrum. Sci Rep 11:2041.

Botella-Soler V, Valderrama M, Crépon B, Navarro V, Quyen MLV (2012) Large-

Scale Cortical Dynamics of Sleep Slow Waves. PLoS ONE 7:e30757.

Bouchard M, Lina J-M, Gaudreault P-O, Lafrenière A, Dubé J, Gosselin N,

Carrier J (2021) Sleeping at the switch. Elife 10:e64337.

Brake N, Duc F, Rokos A, Arseneau F, Shahiri S, Khadra A, Plourde G (2024) A

neurophysiological basis for aperiodic EEG and the background spectral

trend. Nat Commun 15:1514.

Buzsáki G (2004) Large-scale recording of neuronal ensembles. Nat Neurosci

7:446–451.

Chylinski D, Egroo MV, Narbutas J, Muto V, Bahri MA, Berthomier C, Salmon E,

Bastin C, Phillips C, Collette F, Maquet P, Carrier J, Lina J-M, Vandewalle G

(2022) Timely coupling of sleep spindles and slow waves linked to early

amyloid-β burden and predicts memory decline. eLife 11:e78191.

Cox R, Driel J van, Boer M de, Talamini LM (2014) Slow oscillations during sleep

coordinate interregional communication in cortical networks. J Neurosci

34:16890–16901.

Cox R, Mylonas DS, Manoach DS, Stickgold R (2018) Large-scale structure and

individual fingerprints of locally coupled sleep oscillations. SLEEP 41:zsy175.

Cox R, Rüber T, Staresina BP, Fell J (2020) Phase-based coordination of

hippocampal and neocortical oscillations during human sleep. Commun

Biology 3:176.

Donoghue T, Haller M, Peterson EJ, Varma P, Sebastian P, Gao R, Noto T, Lara

AH, Wallis JD, Knight RT, Shestyuk A, Voytek B (2020) Parameterizing neural

power spectra into periodic and aperiodic components. Nat Neurosci 23:1655–

1665.

Donoghue T, Schaworonkow N, Voytek B (2022) Methodological considerations

for studying neural oscillations. Eur J Neurosci 55:3502–3527.

Durka P, Dovgialo M, Duszyk-Bogorodzka A, Biegański P (2024) Two-Stage

Atomic Decomposition of Multichannel EEG and the Previously Undetectable

Sleep Spindles. Sensors 24:842.

Durka PJ, Blinowska KJ (1995) Analysis of EEG transients by means of matching

pursuit. Ann Biomed Eng 23:608–611.

Ellenrieder N, Frauscher B, Dubeau F, Gotman J (2016) Interaction with slow

waves during sleep improves discrimination of physiologic and pathologic

high-frequency oscillations (80–500 Hz). Epilepsia 57:869–878.

Ellenrieder N, Gotman J, Zelmann R, Rogers C, Nguyen DK, Kahane P, Dubeau

F, Frauscher B (2020) How the Human Brain Sleeps: Direct Cortical

Recordings of Normal Brain Activity. Ann Neurol 87:289–301.

Finley AJ, Angus DJ, Knight EL, Reekum CM van, Lachman ME, Davidson RJ,

Schaefer SM (2024) Resting EEG Periodic and Aperiodic Components Predict

Cognitive Decline Over 10 Years. J Neurosci 44:e1332232024.

Gao R, Peterson EJ, Voytek B (2017) Inferring synaptic excitation/inhibition

balance from field potentials. NeuroImage 158:70–78.

Gerster M, Waterstraat G, Litvak V, Lehnertz K, Schnitzler A, Florin E, Curio G, Nikulin V (2022) Separating Neural Oscillations from Aperiodic 1/f Activity: Challenges and Recommendations. Neuroinformatics 20:991–1012.

Gonzalez CE, Mak-McCully RA, Rosen BQ, Cash SS, Chauvel PY, Bastuji H, Rey M, Halgren E (2018) Theta Bursts Precede, and Spindles Follow, Cortical and Thalamic Downstates in Human NREM Sleep. J Neurosci 38:9989–10001.

He BJ (2014) Scale-free brain activity: past, present, and future. Trends Cogn Sci 18:480–487.

He BJ, Zempel JM, Snyder AZ, Raichle ME (2010) The Temporal Structures and Functional Significance of Scale-free Brain Activity. Neuron 66:353–369.

Helfrich RF, Lendner JD, Knight RT (2021) Aperiodic sleep networks promote memory consolidation. Trends Cogn Sci 25:648–659.

Helfrich RF, Lendner JD, Mander BA, Guillen H, Paff M, Mnatsakanyan L, Vadera S, Walker MP, Lin JJ, Knight RT (2019) Bidirectional prefrontal-hippocampal dynamics organize information transfer during sleep in humans. Nat Commun 10:3572.

Helfrich RF, Mander BA, Jagust WJ, Knight RT, Walker MP (2018) Old Brains Come Uncoupled in Sleep: Slow Wave-Spindle Synchrony, Brain Atrophy, and Forgetting. Neuron 97:221-230.e4.

Hernandez J, Lina J-M, Dubé J, Lafrenière A, Gagnon J-F, Montplaisir J-Y,

Postuma RB, Carrier J (2024) EEG rhythmic and arrhythmic spectral

components and functional connectivity at resting state may predict the

development of synucleinopathies in idiopathic REM sleep behavior disorder.

SLEEP:zsae074.

Horváth CG, Szalárdy O, Ujma PP, Simor P, Gombos F, Kovács I, Dresler M,

Bódizs R (2022) Overnight dynamics in scale-free and oscillatory spectral

parameters of NREM sleep EEG. Sci Rep 12:18409.

Hubbard J, Gent TC, Hoekstra MMB, Emmenegger Y, Mongrain V, Landolt H-P,

Adamantidis AR, Franken P (2020) Rapid fast-delta decay following prolonged

wakefulness marks a phase of wake-inertia in NREM sleep. Nat Commun

11:3130.

Jansen BH, Rit VG (1995) Electroencephalogram and visual evoked potential

generation in a mathematical model of coupled cortical columns. Biol Cybern

73:357–366.

Jiang X, Gonzalez-Martinez J, Halgren E (2019) Posterior Hippocampal Spindle

Ripples Co-occur with Neocortical Theta Bursts and Downstates-Upstates,

and Phase-Lock with Parietal Spindles during NREM Sleep in Humans. J

Neurosci 39:8949–8968.

Jurkiewicz GJ, Hunt MJ, Żygierewicz J (2021) Addressing Pitfalls in Phase-

Amplitude Coupling Analysis with an Extended Modulation Index Toolbox.

Neuroinformatics 19:319–345.

Klinzing JG, Mölle M, Weber F, Supp G, Hipp JF, Engel AK, Born J (2016)

Spindle activity phase-locked to sleep slow oscillations. NeuroImage 134:607–

616.

Kozhemiako N, Mylonas D, Pan JQ, Prerau MJ, Redline S, Purcell SM (2022)

Sources of Variation in the Spectral Slope of the Sleep EEG. eNeuro

9:ENEURO.0094-22.2022.

Krstulović S, Gribonval R (2006) MPTK: Matching Pursuit Made Tractable. 2006

IEEE Int Conf Acoust Speech Signal Process Proc 3:III-496-III–499.

Lendner JD, Helfrich RF, Mander BA, Romundstad L, Lin JJ, Walker MP,

Larsson PG, Knight RT (2020) An electrophysiological marker of arousal level

in humans. eLife 9:e55092.

Lina J-M, O'Callaghan EK, Mongrain V (2019) Scale-Free Dynamics of the

Mouse Wakefulness and Sleep Electroencephalogram Quantified Using

Wavelet-Leaders. Clocks Sleep 1:50–64.

Mander BA, Winer JR, Walker MP (2017) Sleep and Human Aging. Neuron

94:19–36.

Mendes RAV, Zacharias LR, Ruggiero RN, Leite JP, Moraes MFD, Lopes-Aguiar

C (2021) Hijacking of hippocampal–cortical oscillatory coupling during sleep in

temporal lobe epilepsy. Epilepsy Behav 121:106608.

Miskovic V, MacDonald KJ, Rhodes LJ, Cote KA (2019) Changes in EEG

multiscale entropy and power-law frequency scaling during the human sleep

cycle. Hum Brain Mapp 40:538–551.

Muehlroth BE, Werkle-Bergner M (2020) Understanding the interplay of sleep

and aging: Methodological challenges. Psychophysiology 57:e13523.

Murphy M, Riedner BA, Huber R, Massimini M, Ferrarelli F, Tononi G (2009)

Source modeling sleep slow waves. Proc National Acad Sci 106:1608–1613.

Nicolas J, King BR, Levesque D, Lazzouni L, Coffey E, Swinnen S, Doyon J,

Carrier J, Albouy G (2022) Sigma oscillations protect or reinstate motor

memory depending on their temporal coordination with slow waves. eLife

11:e73930.

Niethard N, Brodt S, Born J (2021) Cell-Type-Specific Dynamics of Calcium

Activity in Cortical Circuits over the Course of Slow-Wave Sleep and Rapid

Eye Movement Sleep. J Neurosci 41:4212–4222.

Niethard N, Hasegawa M, Itokazu T, Oyanedel CN, Born J, Sato TR (2016)

Sleep-Stage-Specific Regulation of Cortical Excitation and Inhibition. Curr Biol

26:2739–2749.

Nimmrich V, Draguhn A, Axmacher N (2015) Neuronal Network Oscillations in

Neurodegenerative Diseases. NeuroMolecular Med 17:270–284.

Ostlund B, Donoghue T, Anaya B, Gunther KE, Karalunas SL, Voytek B, Pérez-

Edgar KE (2022) Spectral parameterization for studying neurodevelopment:

How and why. Dev Cogn Neurosci 54:101073.

Pani SM, Saba L, Fraschini M (2022) Clinical applications of EEG power spectra

aperiodic component analysis: A mini-review. Clin Neurophysiol 143:1–13.

Pinotsis DA, Moran RJ, Friston KJ (2012) Dynamic causal modeling with neural

fields. NeuroImage 59:1261–1274.

Rocca DL, Zilber N, Abry P, Wassenhove V van, Ciuciu P (2018) Self-similarity

and multifractality in human brain activity: A wavelet-based analysis of scale-

free brain dynamics. J Neurosci Methods 309:175–187.

Schneider B, Szalárdy O, Ujma PP, Simor P, Gombos F, Kovács I, Dresler M,

Bódizs R (2022) Scale-free and oscillatory spectral measures of sleep stages

in humans. Front Neuroinformatics 16:989262.

Steriade M (2006) Grouping of brain rhythms in corticothalamic systems.

Neuroscience 137:1087–1106.

Tallon-Baudry C, Bertrand O, Tallon-Baudry C, Bertrand O (1999) Oscillatory

gamma activity in humans and its role in object representation. Trends Cogn

Sci 3:151–162.

Vyazovskiy VV, Riedner BA, Cirelli C, Tononi G (2007) Sleep Homeostasis and

Cortical Synchronization: II. A Local Field Potential Study of Sleep Slow

Waves in the Rat. Sleep 30:1631-S1.

Wen H, Liu Z (2016) Separating Fractal and Oscillatory Components in the

Power Spectrum of Neurophysiological Signal. Brain Topogr 29:13–26.

Zerouali Y, Lina J-M, Sekerovic Z, Godbout J, Dubé J, Jolicoeur P, Carrier J

(2014) A time-frequency analysis of the dynamics of cortical networks of sleep

spindles from MEG-EEG recordings. Front Neurosci-switz 8:310.

Legends

Fig.1. Spectral estimation of arrhythmic background and rhythms. (A1, A2).

Examples of two simulated time series (see simulations section for methodological

details). (A1) show pure background arrhythmic activity (β =1.70; arrhythmic

background). (A2) shows a mixture of the same arrhythmic activity as in A1**,** with

the addition of a four second alpha oscillation (10.5 Hz). (B1, B2). Fourier power

spectra of (A1) and (A2), respectively. The estimated arrhythmic spectrum $Q_i(f)$,

as described above, is shown in red. (C1, C2). Averaged standard power spectra

over 250 simulations for each type of simulation as shown in (B1) and (B2). Even

though the added oscillation in the signal (A2) is unnoticeable in the individual

Fourier spectrum (B2), its signature is apparent in the averaged standard spectrum

(C2). (D1, D2)**.** Probability density of estimated scale-free exponents obtained from

$Q_i(f)$ in the two sets of 250 simulations, without (D1) and with (D2) the alpha 10.5

Hz oscillation. (E1, E2). the residual 'rhythmic factor' $\exp(R^*(f))$ controlled for the

presence of arrhythmic background for the two sets of simulations, respectively

without (E1**)** and with (E2) the alpha 10.5 Hz oscillation.

Fig.2. **The analysis of an original signal and synthesis of a rhythmic signal**

using fractional spline wavelets. (A) An example of fractional spline wavelet that

could be used for analysis of an NREM sleep signal as illustrated in (B). (C) 'time-

scale' decomposition of $s(t)$ displayed in (B) using wavelet basis generated with

(A). Each boxes represents a wavelet coefficient $\langle s, \psi_{j,k}^{(4)} \rangle$ at a particular scale (j)

and discrete time ($k\, 2^j$). Real time is indicated on the x-axis. To help the reading

of the time-scale representations, visible boxes account for 99% of the overall wavelet power of the signal. Gray intensity (globally normalized) indicates the amplitude of the largest wavelet coefficient. (D) Logarithmic wavelet power of (B) with respect to the dyadic scale parameter. The linear regression will provide the scaling exponent as given in (6). (E) 'time-scale' decomposition of the rhythmic signal resulting from processing (B). Notice the lacunar representation as compared to the analysis of the original signal in (C). The rhythmic decomposition exhibits coefficients at large scale (low frequencies) that seem to account for oscillatory pattern localized in time (confirmed with an inspection of (B)). (F) Wavelet power of multiple rhythmic signals (dashed grey lines) and the mean (dark bold line).

Fig.3.   **The 'rhythmic spectroscopy'.** (A) The rhythmic signal corresponding to (B) in Fig.2. The value of the β-exponent of the removed arrhythmic component is indicated in parenthesis. (B) From 300 epochs in NREM3 from the Anterior Cingulate (see upcoming NREM sleep section), we display the probability distribution of the β-exponents. (C) The individual rhythmic spectrums resulting from the Fourier analyses of the rhythmic time series and the 'rhythmic spectroscopy' provided with the mean (bold line; see the sleep spectroscopy section for a definition).

Fig.4. **Neural mass oscillation**. (A) A four second oscillation produced by a standard neural mass model (with the original parameters). (B) The Fourier

power spectrum of the response (A). The alpha peak is accompanied with a lower frequency content that corresponds to the first seconds of the oscillation that does not reach a 'pure' harmonic oscillation.

Fig.5. ***RnB* estimation in the wavelet domain.** **A.** Example of a simulated time series containing a mixture of a scale-free activity ($\beta = 2.2$; arrhythmic background) and an alpha oscillation (four seconds 10.5 Hz rhythm). **B.** The Fourier spectra of the original time series $s(t)$ displayed in (A), mostly dominated by the dominant arrhythmic background. **C.** The output $s_R(t)$ of the *RnB* algorithm, revealing the rhythmic features of the time series synthesized from the wavelet's coefficients filtered for the arrhythmic factor. **D.** The Fourier spectra of a single $s_R(t)$ epoch (in (C)) highlight a clear signature of the simulated oscillation that was added to the arrhythmic background, with a marginal "arrhythmic" contribution. This averaged across multiple epochs define the rhythm's spectroscopy for further analyses (methods). The black dotted line is the original spectra of the simulated oscillation, without the addition of an arrhythmic background. The 'expected power' indicates the maximal power of the simulated oscillation.

Fig.6. **RnB estimation of rhythms and arrhythmic background**. (A1, A2, A3). Examples of simulated arrhythmic time series with three different values of arrhythmic background (β) (1.69, 2.11, 2.49); 300 simulations were generated for each arrhythmic condition. For a random set of 200 arrhythmic simulations, an alpha oscillation (10.5 Hz) was added, varying its amplitude at 15 fixed amplitude levels (x-axis on the B plot). For each amplitude level,

RnB is applied 60 times on a random selection among all epochs, enforcing a realistic approach where an oscillation may or may not be systematically present. (B). Estimated maximal rhythmic amplitude measured by RnB (Y-axis) plotted against simulated alpha oscillation amplitudes (X axis). Colors of the dots represent the arrhythmic conditions (red: $\beta=1.69$; blue: $\beta=2.11$; yellow: $\beta=2.49$). (C). Estimated scaling exponents out (Y axis) with respect to the simulated alpha oscillation amplitudes (X axis) for the three simulated arrhythmic backgrounds. The dashed line indicates the value in the simulation. (D). An example of rhythmic oscillations to be added to (A3). (E). Spectral signature of the rhythmic component from (D). (F1). Maximal rhythmic amplitude of RnB in the delta range with respect to varying amplitude of this oscillatory component. (F2). Maximal rhythmic amplitude at 13 Hz, varying amplitude of the 3 Hz-oscillation. (G). Response of the RnB algorithm for the scale-free exponent estimation, varying amplitude of the 3Hz-oscillatory component.

Fig. 7. **The spectroscopy of NREM sleep recordings**. Results from spectral factorization (top row) and the spectroscopy (bottom row) of NREM sleep recordings in the anterior cingulate (two left columns) and precuneus (two right columns). (A1, A2). Standard spectral density per region in NREM2 (blue) and NREM3 (pink) sleep, highlighting a significant arrhythmic 1/f background alongside spectral peaks. (B1, B2). Residual periodic power estimated by FOOOF in NREM2 and NREM3 sleep. Dashed vertical lines indicate found spectral peaks. (C1, C2). Probability density of observed scaling exponents as assessed by *RnB* wavelet

coefficients during NREM2 and NREM3. (D1, D2). Spectral analysis from the rhythmic timeseries, highlighting distinctive peaks in each region. Dashed horizontal lines in the delta band indicate the frequency bands to be used for the detection of sleep slow waves in the rhythmic timeseries.

Fig. 8. **SSWs in rhythmic time series from the anterior cingulate and precuneus during NREM3 sleep**. (A1, A2). Average waveforms of rSSWs detected during NREM3 in the anterior cingulate (top) and precuneus (bottom). (B1,B2). Induced scalograms of the rhythmic time series associated with SSWs coregistered with respect to the hyperpolarization phase. Red/yellow indicate higher normalized power than blue. (C1,C2). Distribution of scaling exponents across epochs with rSSW (plain) and without rSSW (dashed lines). (D1,D2). Spectroscopy of epochs with rSSWs (plain) and without rSSWs (dashed lines) during NREM3 sleep.

Fig. 9. **The spectroscopy of slow (rSlowS) and fast switchers (rFastS) during NREM3.** (A1, A2). The probability density of rSSWs according to their transition frequency is shown for the anterior cingulate (A1) and precuneus (B1), highlighting a bimodal distribution in both regions. The transition frequency to cluster rFastS and rSlowS is shown as a dashed vertical line. (B1, B2). Average waveform of rSlowS and rFastS, with respect to the separation frequency are defined in (A1) and (A2) respectively. Averages are centered around the zero-crossing markers. (C1, C2). Probability density of the scale-free exponents is estimated by *RnB* for rSlowS and rFastS in each region. (D1, D2). Spectroscopy of the rhythmic

switchers in NREM3 are shown for both regions. The horizontal bold vertical bars depict local frequency bands which were considered for further PAC analyses. Bilateral T-tests were performed in each region to investigate switcher-related differences in the integrated rhythmic power for each region (anterior cingulate: delta between 0.5 and 4 Hz, sigma between 8-14; precuneus: delta between 0.5 and 4 Hz, theta between 5-9 Hz, and sigma between 11.5 – 14.5 Hz). Significance is depicted using stars (p-values: * <0.05; **<0.01).

Fig.10. **Induced and phase-locked rhythmic power synchronized with the transition of rSlowS and rFastS during NREM3 sleep.** Scalograms of induced (A1, A2, C1, and C2) and phase-locked (B1, B2, D1, and D2) power for the rSlowS (Left panels) and the rFastS (Right panels), co-registered around their zero crossing, in the anterior cingulate (top panels) and the precuneus (bottom panels). Vertical lines indicate the transition markers for rSlowS and rFastS (zero-crossing in bold; the depolarization 'max. peak' as estimated from the averaged signal in Fig.9 B1 and B2). The arrows in top panels (anterior cingulate) indicate phase-locked power around the transition of rSlowS, whereas arrows in bottom panels (precuneus) emphasize the temporal relationship between the induced theta and phase-locked sigma activity predominantly for rFastS. Each plane is individually normalized for visualization (hot colors for higher power).

Fig.11. **Delta-sigma PAC from original and rhythmic time series.** Average values and standard error of the mean for rPAC (rhythmic) and PAC (raw), for slow and fast switchers during NREM3 sleep in the anterior cingulate (A) and in the

1   precuneus (B). In the precuneus, rPAC values are shown in (C) for all rSSWs

2   without TBs (rSSW-TBs) and for rSSWs co-detected with a TBs (rSSW+TBs). For

3   each event type, arrows indicate significant differences between PAC and rPACs

4   values. Stars indicate significance value (*: p≤0.01).