Cumulative dose responses for adapting biological systems*

Ankit Gupta[1] and Eduardo D. Sontag[2]

[1]Department of Biosystems Science and Engineering, ETH Zurich, Basel, Switzerland
[2]Department of Electrical and Computer Engineering and Department of Bioengineering, Northeastern University, Boston, Massachusetts, United States

Abstract

This paper introduces the notion of cumulative dose response (cDR). The cDR is the area under the plot of a response variable, an integral taken over a fixed time interval and seen as a function of an input parameter. This work was motivated by the accumulation of cytokines resulting from T cell stimulation, where a non-monotonic cDR has been observed experimentally. However, the notion is of general applicability. A surprising conclusion is that incoherent feedforward loops studied in the systems biology literature, though capable of non-monotonic dose responses, can be mathematically shown to always result in monotonic cDR.

Keywords: dose response, perfect adaptation, systems biology, incoherent feedforward loops, integral feedback, immunology, T cells

1 Introduction

The capability to adapt and to formulate appropriate responses to environmental cues is a key factor for the survival of life at every level, from individual cells to organisms [1, 2, 3, 4]. A delicate balance is needed in this process: organisms maintain tightly regulated levels of vital quantities, even in the face of variations to be counteracted upon, a property sometimes called homeostasis or adaptation, all the while being able to detect and react to changes in the environment. Underlying adaptation at the cellular level are dynamical signal transduction and gene regulatory networks that measure and process external and internal chemical, mechanical, and physical conditions (ligand, nutrient, oxygen concentrations, pressure, light, temperature) eventually leading to changes in metabolism, gene expression, cell division, motility, and other characteristics. These mechanisms enable organisms to display transient responses that gradually return to a baseline activity level when presented with relatively constant input stimulation, a phenomenon usually called "perfect" or "exact" adaptation [5].

1.1 Cumulative dose responses

In this paper, we continue the study of adaptation mechanisms, with an emphasis on monotonicity properties of an output or reporter variable as a function of an input. We are concerned with ordinary

---

*timestamp: 2024-11-22:15:15:32

differential equation systems that model the interactions of several species, and where there is an "input" (which might represent the dose of a drug or of a genetic inducer), whose level is quantified by the variable u, and an "output" that is time dependent, and whose magnitude at time t is represented by $y(t)$. The input u will be assumed to be constant, and we write $y_u(t)$ to emphasize the dependence of the output on the input as well as time. The dependence on the initial state will not be indicated explicitly; the initial values of all the species will be fixed at values to be discussed. The notions that we introduce are general, but for concreteness in our examples there will only be two variables.

By definition, in an adapting system the numerical value of $y_u(t)$ for large t (that is, $\lim_{t\to\infty} y_u(t)$) does not depend on the specific value of the input u. Adaptation is by definition an *asymptotic* property. On the other hand, one often is interested in *transient* behaviors, and specifically on how $y_u(T)$ depends on u, for a fixed time T. (What is be the concentration of a drug in a tumor microenvironment, after 1hr, as a function of the drug dose? What is the size of a tumor after 60 days of the start of therapy, as function of the drug dose? What is the size of the pool of infected individuals in an epidemic population model, as a function of transmission parameters?) We will call $y_u(T)$ the *dose response* and denote it as DR(u, T). If the turnover of $y(t)$ is slow, this species may accumulate (in a particular tissue or in blood circulation, for example). Often, as described in the motivational work discussed below that arose from our previous work reported in [6], one can only directly measure this accumulated value, the integral $\int_0^T y_u(t)dt$, which we call the *cumulative dose response* and denote by cDR(u, T).

1.2   Motivation: T cell recognition

Adaptation is central to immunity. In particular, T cells must react to stimulation by pathogens and cancers, yet limit their response in order to maintain self-tolerance and avoid autoimmune reactions. T cell activation is triggered by the binding to T cell receptors (TCRs) to peptide major-histocompatibility complex (pMHC) antigens. Activation results in the production of signaling molecules (cytokines) which in turn may recruit other immune components.

The paper [6] studied the response of immune CD8+ T cells to external antigen inputs, showing perfect adaptation over many orders of magnitude in antigen affinity. Specifically, in the experiments reported in that paper, primary human CD8+ T cells (with c58c61 TCR) were stimulated with recombinant pMHC antigen 9V immobilized on plates, seen here as the input u, at different constant concentrations. This antigen is a cancer peptide routinely used in studies of T-cell binding and antigen discrimination. The cumulative amount of cytokine TNF-α (the output $y(t)$) secreted into the culture medium was measured. Figure 1 shows the cDR when one averages the results of three biological replicates. It shows the average cumulative TNF-α abundance ($z(t) = \int_0^t y(s)\,ds$) plotted against several constant concentrations u, measured at various times ($t = 1$ to 8 hours). Note the non-monotonic, and even somewhat oscillatory, behavior.

The work in [6] thus raises the question of what network motifs are capable, at least for suitable parameters, to exhibit perfect adaptation as well as non-monotonic cDR as seen in these experiments. It was speculated, on the basis of numerical exploration, that incoherent feedforward loops cannot result in non-monotonic cDR and thus cannot explain T cell adaptation as measured by accumulated cytokines, unless a thresholding mechanism is imposed. Our main results in this paper confirm in a mathematically rigorous way that, indeed, the main two common types feedforward loops ("IFFL1" and "IFFL2" below) can *never* exhibit such behaviors, because their cDR is always monotonic. This is very surprising for one of them ("IFFL1") because the DR itself can be non-monotonic in that case. Consider the

Figure 1: Cumulative dose response based on average of three experiments, plotted from data in [6]. The same data was plotted in the top left panel of Figure 1 in that paper. Horizontal axis denotes concentrations of the input (in units of ligand in ng/well).

following system of two differential equations:

$$\dot{x} = -x + u \tag{1}$$

$$\dot{y} = -10\,xy + u\,. \tag{2}$$

This is an adapting system: for any given constant input $u > 0$, the steady states are $\bar{x} = u$ and $\bar{y} = 1/10$, which is independent of u. Figure 2 shows plots of DR (non-monotonic) and cDR (monotonic).

Figure 2: Plots of DR ($y(t)$) and cDR ($\int_0^T y(t)dt$) for the example in Equation 1. The initial conditions are $x(0) = 0$, $y(0) = 1/10$, and the time horizon is $T = 1.5$.

On the other hand, the standard integral feedback for adaptation ("IFB" below) is indeed capable of showing non-monotonic cDR, as we discuss in this paper.

Back to the experimental data, one may ask whether the T cell experiments point to adaptation, that is, if $y_u(t)$ is independent of u for large t. Since only $z(t) = \int_0^t y(s)\,ds$ is experimentally available, we need

to estimate the output $y(t)$ by taking time-derivatives of $z(t)$. To obtain a more meaningful estimate than would be obtained from the averages shown in Figure 1, we consider instead the separate plots of $z(t)$ from each experiment. The top panel in Figure 3 shows again the cumulative dose responses for various times ($t = 1$ to 8 hours), but now with separate plots from each experiment, starting from the data that was used to generate Figure 1 in the SI of [6].

Figure 3: Top: cDR plots of individual experiments, and measured at different times. Bottom: Adaptation behavior in individual experiments. Output $y(t)$ is estimated from individual cumulative $z(t)$ plots in respective top panels.

Using first-order differences, and imposing a zero value at the start of the experiment: $y(0) = 0$, we then derived estimates of $y(t)$ for the various input values and the three experimental replicates shown in Figure 3. See the bottom panel of Figure 3. These estimates are very rough, because the time steps are large (1 hour), and in any event experimental data is subject to noise. Nonetheless, this data strongly suggests that adaptation, in the sense that the output $y(t)$ approaches as time increases a value (in this case $y = 0$) which is the same no matter what the input (drug dose). The estimated negative values of $y(t)$ at certain time points are likely due to numerical errors or to the fact that there is some cytokine present in the experimental wells which does not arise from the stimulation, so that the values shown are relative to this baseline.

1.3 Review: network motifs for adaptation

As discussed, ("perfect") adaptation to constant inputs means that, no matter the value of an input, the value of $y_u(t)$ for large t will be the same. In engineering terms, one has a "high pass filter" that essentially acts on a derivative of the input. Generally speaking, adaptation requires one of two mechanisms for adaptation: incoherent feedforward or negative feedback [7, 8, 9].

Incoherent feedforward loops (IFFL) are a type of network motifs that are capable of adaptation [10, 11]. In an IFFL, the input u induces formation of the reporter y but also acts as a delayed inhibitor, through one or more intermediary control variables. Feedforward motifs are statistically overrepresented in biological systems from bacterial to mammalian cells [12, 13]. IFFL's have been argued to underlie mechanisms involved in such varied contexts as microRNA-mediated loops [14], MAPK pathways [15, 16], insulin release [17, 18], intracellular calcium release [19, 20], *Dictyostelium* and neutrophil chemotaxis [21, 22], NF-κB activation [23], and microRNA regulation [24], as well as metabolic regulation of bacterial carbohydrate uptake and other substrates [25, 26]. IFFL's may also play a role in immunology, enabling the recognition of dynamic changes in antigen presentation [27], and have been employed in synthetic biology in order to control protein expression under DNA copy variability [28, 29]. The paper [30] provided a large number of additional references, and carried out a computational exploration of IFFLs that lead to non-monotonic dose responses and/or adaptation.

In *integral feedback loops (IFB)*, the intermediate variable or variables provide a type of memory that integrates the "error" between $y(t)$ and a steady-state value y_0. IFB's arise in biological systems ranging from *E. coli* chemotaxis [31] and regulation of tryptophan [32] to human physiological control such as blood calcium homeostasis [33] or neuronal control of the prefrontal cortex [34] to synthetic circuits for adaptation [35, 36, 37]. We remark that integral feedback is in a sense universal for adaptation, because nonlinear changes of coordinates can recast IFFLs that adapt into integral feedback form [38], but these coordinate changes may have no physical interpretation and hence lack interpretability. Moreover, IFBs are known to provide extra degrees of robustness to the adaptation property because, unlike the IFFL, the underlying mechanism can sense and correct for perturbations to the output variable $y(t)$. This theme is explored in greater detail in recent papers, where it is shown that IFBs arise naturally when one considers adapting circuits that exhibit a *maximal* form of robustness [39] or robustness that is independent of the reaction kinetics [40]. The results in these papers apply to arbitrarily-sized networks, and they explicitly identify the network species that create the integral feedback required for adaptation.

1.4 Three paradigmatic examples of adapting systems

In this paper, we will consider three types of two-species systems, shown schematically in Figure 4. These are the systems studied in [41, 42]. In all these examples, u refers to a positive constant input, x is the concentration of a "controller" species, and the output variable y is the concentration of the "regulated" or output species.

1.5 Steady states, perfect adaptation, and scale-invariance

Let us compute the steady states, obtained by setting the right-hand sides of the differential equations to zero, for the systems shown in Figure 4. For the IFFL1 system (a) we have:

$$\bar{x} = \frac{\alpha}{\delta}u\,, \quad \bar{y} = \frac{\beta}{\gamma\bar{x}}u = \frac{\beta}{\gamma}\frac{\delta}{\alpha u}u = \frac{\beta\delta}{\gamma\alpha}\,.$$

$$\begin{array}{ll} \text{(a) IFFL1} & \text{(b) IFFL2} \qquad\qquad \text{(c)} \qquad\qquad \text{(d) IFB} \end{array}$$

$$
\begin{aligned}
\dot{x} &= \alpha u - \delta x \\
\dot{y} &= \beta u - \gamma x y
\end{aligned}
\qquad
\begin{aligned}
\dot{x} &= \alpha u - \delta x \\
\dot{y} &= \beta \frac{u}{K+x} - \gamma y
\end{aligned}
\qquad
\begin{aligned}
\dot{x} &= x(\alpha y - \delta) \\
\dot{y} &= \beta \frac{u}{K+x} - \gamma y
\end{aligned}
$$

Figure 4: Three examples of systems: (a) is an IFFL with degradation enhancement, (b) is an IFFL with production inhibition, and (d) is an integral feedback system. The input u is assumed to be a positive constant, and x, y are abundances of a quantity of interest such as concentration of a protein or mRNA. Arrows "$\rightarrow$" indicate positive effect (activation) and blunt edges $\dashv$ denote negative effects (inhibition). Both (a) and (b) have the same qualitative relation, schematically represented by diagram in (c), between activation of x and y by the input u, and inhibition of y by x, but their dynamical properties are very different. Dynamics can be described by pairs of differential equations for the abundances $x(t)$ and $y(t)$ as a function of time, as shown below the diagrams. State variables $x(t)$ and $y(t)$ are taken to be nonnegative. When $K = 0$, it is assumed that $x(t) > 0$ for all t. In these equations, α, β, γ, δ, and K are all positive constants.

For the IFFL2 system (b) we have:

$$
\bar{x} = \frac{\alpha}{\delta} u \,, \quad \bar{y} = \frac{\beta}{\gamma(K+\bar{x})} u = \frac{\beta}{\gamma} \frac{\delta}{(\delta K + \alpha u)} u = \frac{\beta \delta}{\gamma \alpha} \text{ when } K = 0 \,.
$$

Finally, for the IFB system (c) we have that there are two types of steady states:

$$
(\bar{x}, \bar{y}) = \left(0, \frac{\beta u}{\gamma K} \right)
$$

and, for nonzero $\bar{x}$ and assuming $K < \frac{\beta \delta}{\gamma \alpha} u$ (for example, if $K = 0$):

$$
(\bar{x}, \bar{y}) = \left(\frac{\beta \alpha}{\delta \gamma} u - K, \frac{\delta}{\alpha} \right)
$$

In all three cases, if $K = 0$, the system is perfectly adapting. In addition, when $K = 0$ both systems IFFL2 and IFB have the scale-invariance (or "fold-change detection") property [41, 42]. This means that the output variable $y(t)$ satisfies the same differential equation, independently of rescalings of the input u by any constant factor p, as shown by the following simple calculation:

$$
\begin{aligned}
\dot{x} &= \alpha u - \delta x \\
\dot{y} &= \beta \frac{u}{x} - \gamma y \\
\Rightarrow (\dot{px}) &= \alpha(pu) - \delta(px) \\
\dot{y} &= \beta \frac{\cancel{p} u}{\cancel{p} x} - \gamma y
\end{aligned}
\qquad\qquad
\begin{aligned}
\dot{x} &= \alpha x y - \delta x \\
\dot{y} &= \beta \frac{u}{x} - \gamma y \\
\Rightarrow (\dot{px}) &= \alpha(px)y - \delta(px) \\
\dot{y} &= \beta \frac{\cancel{p} u}{\cancel{p} x} - \gamma y
\end{aligned}
$$

System IFFL1, in contrast, admits no such symmetries.

1.6 Stability

For both systems IFFL1 (a) and IFFL2 (b) in Figure 4, the respective steady states $(\bar{x}, \bar{y})$ are globally asymptotically stable with respect to initial conditions in the positive quadrant $x > 0$, $y > 0$. This is very simple to show. The variable $x(t)$ is the solution of a one-dimensional stable linear system, hence converges exponentially to $\frac{\alpha}{\delta} u$. The variable y is the solution of a time-dependent linear system, with a constant negative rate $-\gamma$ for IFFL2, and a rate for IFFL1 which converges to the strictly negative number $-\frac{\alpha\gamma}{\delta} u$, and hence also exponentially converges to its steady state value. (See [11] for details, as well as similar results for other IFFL configurations.)

The proof of stability for the feedback system IFB (d) in Figure 4 requires more work. We proceed by extending the proof from [42], which covered only the case $K = 0$. We will assume that $K < \frac{\beta\delta}{\gamma\alpha} u$, which holds in particular if $K = 0$. We want to global asymptotic stability with respect to initial conditions with $x(0)$ positive and $y(0)$ non-negative (or even arbitrary), when u is a positive constant, for the two-dimensional system IFB evolving on $\mathbb{R}_{>0} \times \mathbb{R}$ with equations $\dot{x} = x(\alpha y - \delta)$, $\dot{y} = \beta \frac{u}{K+x} - \gamma y$.

It is convenient to change coordinates $\tilde{x} := \ln x$ and $\tilde{y} = \alpha y - \delta$, so that we reduce to the study of the system in $\mathbb{R}^2$ with equations (dropping tildes):

$$\dot{x} = y$$
$$\dot{y} = \frac{\alpha\beta u}{K + e^x} - \gamma(y + \delta)$$

and we wish to prove the global asymptotic stability of the unique steady state

$$\bar{x} = \ln\left(\frac{\alpha\beta u}{\gamma\delta} - K\right), \quad \bar{y} = 0.$$

Introducing $c := \gamma\delta = \frac{\alpha\beta u}{K+e^{\bar{x}}}$, $f(x) = -\frac{\alpha\beta u}{K+e^x} + c$, and $k(y) = \gamma(y + \delta) - c = \gamma y$, we can write our system as

$$\dot{x} = y$$
$$\dot{y} = -f(x) - k(y)$$

with $f(\bar{x}) = 0$ and $k(\bar{y}) = 0$. In other words, we have a mass-spring system $\ddot{x} + k(\dot{x}) + f(x) = 0$ with nonlinear damping $k(\dot{x})$ and nonlinear spring constant $f(x)$. This suggests the use of energy as a Lyapunov function. The map f is strictly increasing, positive for $x > \bar{x}$ and negative otherwise, and similarly for k with respect to $\bar{y} = 0$. Let us define

$$V(x, y) := \int_{\bar{x}}^{x} f(r)\, dr + \frac{y^2}{2}.$$

By definition, $V(\bar{x}, 0) = 0$ and $V(x, y) > 0$ for all $(x, y) \neq (\bar{x}, 0)$. We also have that $\frac{\partial^2 V}{\partial^2 x} = f'(x) > 0$, and $\frac{\partial^2 V}{\partial^2 y} = 1 > 0$, (and mixed partial derivatives are zero), V is a strictly convex, and thus a proper (also called radially unbounded or coercive) function, thus a Lyapunov function candidate. The derivative of V along trajectories is

$$f(x)\, y + y\, [-f(x) - k(y)] = \gamma y^2 \leq 0$$

for all (x, y), and if this derivative only vanishes identically along a trajectory, then $y(t) \equiv 0$, which in turn implies, when substituted into $0 = \dot{y} = -f(x) - 0$ that $f(x(t)) \equiv 0$, i.e. that $x(t) \equiv \bar{x}$. The LaSalle Invariance Principle (see e.g. [43]) then allows us to conclude global asymptotic stability.

1.7 Outline of paper

Denoting the input-dependent dynamics as $(x_u(t), y_u(t))$ for $t \geq 0$, we define the **dose response (DR)** and the **cumulative dose response (cDR)** at time T as

$$\mathrm{DR}(u, T) = y_u(T) \qquad \text{and} \qquad \mathrm{cDR}(u, T) = \int_0^T y_u(t) dt.$$

In each example, our aim is to determine whether the mapping $u \mapsto \mathrm{cDR}(u, T)$ is monotonically increasing. If this monotonicity does not hold universally, we seek to identify sufficient conditions under which it does. It is straightforward to note that if the map $u \mapsto \mathrm{DR}(u, T)$ is monotonically increasing, then the same holds for the map $u \mapsto \mathrm{cDR}(u, T)$.

Let us review the specific examples that we consider. The first is the IFFL1 system shown in Figure 4(a) with equations given by

$$\dot{x} = \alpha u - \delta x \tag{3}$$
$$\dot{y} = \beta u - \gamma x y, \tag{4}$$

with initial state $x(0) = x_0$ and $y(0) = \frac{\beta \delta}{\alpha \gamma}$. The initial state for x is arbitrary nonnegative, while the initial state for y is its steady-state value which is independent of $u > 0$.

The second example is the IFFL2 system (see Figure 4(b)) given by

$$\dot{x} = \alpha u - \delta x \tag{5}$$
$$\dot{y} = \beta \frac{u}{K + x} - \gamma y \tag{6}$$

where the initial states $x_u(0) = x_0 > 0$ and $y_u(0) = y_0 > 0$ are arbitrary.

As the final example we have the IFB system (see Figure 4(c)) given by

$$\dot{x} = x(\alpha y - \delta) \tag{7}$$
$$\dot{y} = \beta \frac{u}{K + x} - \gamma y \tag{8}$$

with initial states $x(0) = x_0 > 0$ (arbitrary) and $y(0) = \frac{\delta}{\alpha}$, which is the steady-state for y which is independent of u.

The rest of this paper is organized as follows. In Section 2 we prove that for IFFL1, even though the map $u \mapsto \mathrm{DR}(u, T)$ may not be monotonic, the map $u \mapsto \mathrm{cDR}(u, T)$ is always monotonically increasing, irrespective of the values of T, x_0, δ and γ. In Section 3 we show that the situation is much simpler for IFFL2, in the sense that both $\mathrm{DR}(u, T)$ and $\mathrm{cDR}(u, T)$ are monotonically increasing functions of u, regardless of the choice of T, initial states and the model parameters. Lastly, in Section 4 we show that for the IFB system the map $u \mapsto \mathrm{cDR}(u, T)$ is not monotonic in general and find a sufficient condition under which monotonicity holds.

2 Unconditional monotonicity of the cDR for IFFL1

We shall prove the monotonicity of map $u \mapsto \mathrm{cDR}(u, T)$ in multiple steps.

1. Simplifying the system: As the first step, we simplify the system (3)-(4) to make it more amenable to analysis. Let $(x_u(t), y_u(t))$ be the solution of this system for $t \geq 0$. We scale time by δ^{-1} and the state values by a suitable ratio to define

$$\hat{x}(t) = \frac{\gamma}{\delta}x(\delta^{-1}t) \qquad \text{and} \qquad \hat{y}(t) = \frac{\gamma}{\delta}\frac{\alpha}{\beta}y(\delta^{-1}t).$$

Then the dynamics of this rescaled system are given by

$$\dot{\hat{x}}(t) = \frac{\gamma}{\delta^2}\dot{x}(\delta^{-1}t) = \frac{\gamma}{\delta^2}\left(-\delta x(\delta^{-1}t) + \alpha u\right) = -\frac{\gamma}{\delta}x(\delta^{-1}t) + \frac{\gamma}{\delta^2}\alpha u$$

$$= -\hat{x}(t) + \frac{\gamma}{\delta^2}\alpha u$$

$$\dot{\hat{y}}(t) = \frac{\gamma}{\delta^2}\frac{\alpha}{\beta}\dot{y}(\delta^{-1}t) = \frac{\gamma}{\delta^2}\frac{\alpha}{\beta}\left(-\gamma x(\delta^{-1}t)y(\delta^{-1}t) + \beta u\right) = -\frac{\gamma^2}{\delta^2}x(\delta^{-1}t)\frac{\alpha}{\beta}y(\delta^{-1}t) + \frac{\gamma}{\delta^2}\alpha u$$

$$= -\hat{x}(t)\hat{y}(t) + \frac{\gamma}{\delta^2}\alpha u.$$

Therefore if we define

$$\hat{u} = \frac{\gamma}{\delta^2}\alpha u$$

then $(\hat{x}(t), \hat{y}(t))$ satisfies the ODEs

$$\dot{\hat{x}}(t) = -\hat{x}(t) + \hat{u}$$
$$\dot{\hat{y}}(t) = -\hat{x}(t)\hat{y}(t) + \hat{u}.$$

with initial states $\hat{x}(0) = \frac{\gamma}{\delta}x_0$ and $\hat{y}(0) = 1$. Let $(\hat{x}_{\hat{u}}(t), \hat{y}_{\hat{u}}(t))$ be the solution of this system. To prove the result it suffices to show that the map

$$\hat{u} \mapsto \int_0^T \hat{y}_{\hat{u}}(t)dt$$

is monotonically increasing for any $T > 0$.

Henceforth we shall drop the hats for notational convenience and suppose that the dynamics is given by

$$\dot{x}(t) = -x(t) + u \tag{9}$$
$$\dot{y}(t) = -x(t)y(t) + u \tag{10}$$

with initial state $x(0) = x_0$ (arbitrary) and $y(0) = 1$. Letting $(x_u(t), y_u(t))$ be the solution of this system, we shall show that the cDR map

$$u \mapsto \int_0^T y_u(t)dt$$

is monotonically increasing for any $T > 0$. In order to prove this we will prove that for any T and u

$$\int_0^T \partial_u y_u(t)dt \geq 0 \tag{11}$$

where ∂_u denotes the partial derivative w.r.t. u.

2. Deriving explicit expressions: As the second step, we develop explicit expressions for $x_u(t)$, $y_u(t)$, $\int_0^T y_u(t)dt$, and $\int_0^T \partial_u y_u(t)dt$. It is easy to see that

$$x_u(t) = x_0 e^{-t} + (1 - e^{-t})u = u - (u - x_0)e^{-t}, \tag{12}$$

which also implies that

$$\partial_u x_u(t) = 1 - e^{-t}. \tag{13}$$

Note that ODE (10) can be written as

$$\dot{y}_u + x_u y_u = u.$$

Multiplying with the integrating factor $e^{\int_0^t x_u(s)ds}$ on both sides we obtain

$$\frac{d}{dt} e^{\int_0^t x_u(s)ds} y_u(t) = u e^{\int_0^t x_u(s)ds}.$$

Integrating both sides and using $y_u(0) = 1$ we get the usual variation of parameters formula:

$$y_u(t) = e^{-\int_0^t x_u(s)ds} + u \int_0^t e^{-\int_s^t x_u(w)dw} ds.$$

From (9) we know that

$$\int_s^t x_u(w)dw = u(t - s) - (x_u(t) - x_u(s)) = u(t - s) - (u - x_0)e^{-t}(e^{t-s} - 1),$$

where the second relation follows from (12). Plugging this in the previous expression for $y_u(t)$ we get

$$y_u(t) = e^{(u-x_0)(1-e^{-t})-ut} + u \int_0^t e^{(u-x_0)e^{-t}(e^{t-s}-1)-u(t-s)} ds$$

$$= e^{(u-x_0)(1-e^{-t})-ut} + u \int_0^t e^{(u-x_0)e^{-t}(e^s-1)-us} ds, \tag{14}$$

where to derive the last expression we have made a change of variable from $(t - s)$ to s.

Note that by changing the order to integration in the second term in the r.h.s. below we obtain

$$\int_0^T y_u(t)dt = \int_0^T e^{(u-x_0)(1-e^{-t})-ut} dt + u \int_0^T \int_0^t e^{(u-x_0)e^{-t}(e^s-1)-us} ds dt$$

$$= \int_0^T e^{(u-x_0)(1-e^{-t})-ut} dt + u \int_0^T e^{-us} \left(\int_s^T e^{(u-x_0)e^{-t}(e^s-1)} dt \right) ds.$$

Making the change of variable $t \mapsto (u - x_0)e^{-t}(e^s - 1)$ we see that

$$\int_s^T e^{(u-x_0)e^{-t}(e^s-1)} dt = \int_{(u-x_0)(e^{s-T}-e^{-T})}^{(u-x_0)(1-e^{-s})} \frac{e^t}{t} dt$$

$$= \mathrm{Ei}\left((u - x_0)(1 - e^{-s})\right) - \mathrm{Ei}\left((u - x_0)(e^{s-T} - e^{-T})\right)$$

where $\mathrm{Ei}(t)$ is the special *Exponential Integral* function defined as

$$\mathrm{Ei}(t) = \int_{-\infty}^t \frac{e^w}{w} dw. \tag{15}$$

Plugging this in we obtain

$$\int_0^T y_u(t)dt = \int_0^T e^{(u-x_0)(1-e^{-t})-ut} dt + u \int_0^T e^{-us} \mathcal{I}(s, T) ds. \tag{16}$$

where
$$\mathcal{I}(s,T) = \mathrm{Ei}\left((u-x_0)(1-e^{-s})\right) - \mathrm{Ei}\left((u-x_0)(e^{s-T}-e^{-T})\right).$$

Observe that at $s \to T^-$ we have $\mathcal{I}(s,T) \to \mathcal{I}(T,T) = 0$ and we claim that as $s \to 0^+$, we have $\mathcal{I}(s,T) \to T$. To see this note that as $s \to 0^+$, both $(1-e^{-s})$ and $(e^{s-T}-e^{-T})$ approach 0 and close to 0 we have

$$\mathrm{Ei}\left((u-x_0)(1-e^{-s})\right) - \mathrm{Ei}\left((u-x_0)(e^{s-T}-e^{-T})\right)$$
$$= \int_{(u-x_0)(e^{s-T}-e^{-T})}^{(u-x_0)(1-e^{-s})} \frac{e^t}{t} dt$$
$$\approx \int_{(u-x_0)(e^{s-T}-e^{-T})}^{(u-x_0)(1-e^{-s})} \frac{1}{t} dt$$
$$= \log((u-x_0)(1-e^{-s})) - \log((u-x_0)(e^{s-T}-e^{-T}))$$
$$= \log\left(\frac{(u-x_0)(1-e^{-s})}{(u-x_0)e^{s-T}(1-e^{-s})}\right)$$
$$= T - s$$

which is just T as $s \to 0+$. By the definition of the Exponential Integral function (15)

$$\frac{d}{ds}\mathrm{Ei}(s) = \frac{e^s}{s}$$

and hence by the chain rule

$$\frac{d}{ds}\mathrm{Ei}\left((u-x_0)(1-e^{-s})\right) = \frac{e^{(u-x_0)(1-e^{-s})}}{(u-x_0)(1-e^{-s})}(u-x_0)e^{-s} = e^{(u-x_0)(1-e^{-s})}\frac{e^{-s}}{1-e^{-s}}$$

and

$$\frac{d}{ds}\mathrm{Ei}\left((u-x_0)(e^{s-T}-e^{-T})\right) = \frac{e^{(u-x_0)(e^{s-T}-e^{-T})}}{(u-x_0)(e^{s-T}-e^{-T})}(u-x_0)e^{s-T}$$
$$= e^{(u-x_0)(e^{s-T}-e^{-T})}\frac{e^{s-T}}{e^{s-T}-e^{-T}}$$
$$= e^{(u-x_0)(e^{s-T}-e^{-T})}\frac{1}{1-e^{-s}}.$$

Using these expressions we can write the derivative of $\mathcal{I}(s,T)$ as

$$\frac{d}{ds}\mathcal{I}(s,T) = \frac{d}{ds}\mathrm{Ei}\left((u-x_0)(1-e^{-s})\right) - \frac{d}{ds}\mathrm{Ei}\left((u-x_0)(e^{s-T}-e^{-T})\right)$$
$$= e^{(u-x_0)(1-e^{-s})}\frac{e^{-s}}{1-e^{-s}} - e^{(u-x_0)(e^{s-T}-e^{-T})}\frac{1}{1-e^{-s}}.$$

Therefore applying integration by parts to the second term in the r.h.s of (16) we get

$$u\int_0^T e^{-us}\mathcal{I}(s,T)ds = \lim_{s\to 0^+}\mathcal{I}(s,T) - \lim_{s\to T^-}\mathcal{I}(s,T) + \int_0^T e^{-us}\frac{d}{ds}\mathcal{I}(s,T)ds$$
$$= T + \int_0^T e^{-us}\left(e^{(u-x_0)(1-e^{-s})}\frac{e^{-s}}{1-e^{-s}} - e^{(u-x_0)(e^{s-T}-e^{-T})}\frac{1}{1-e^{-s}}\right)ds.$$

Upon substituting this term in the r.h.s. of (16) we obtain

$$\int_0^T y_u(t)dt = \int_0^T e^{(u-x_0)(1-e^{-t})-ut}dt + T$$
$$+ \int_0^T e^{-us}\left(e^{(u-x_0)(1-e^{-s})}\frac{e^{-s}}{1-e^{-s}} - e^{(u-x_0)(e^{s-T}-e^{-T})}\frac{1}{1-e^{-s}}\right)ds. \qquad (17)$$

Note that by rearranging and simplifying, (17) can be expressed as

$$\int_0^T y_u(t)dt = T + \int_0^T \frac{e^{-us}}{1-e^{-s}}\left(e^{(u-x_0)(1-e^{-s})} - e^{(u-x_0)(e^{s-T}-e^{-T})}\right)ds. \qquad (18)$$

Differentiating (18) w.r.t. u we obtain

$$\int_0^T \partial_u y_u(t)dt = -\int_0^T s\frac{e^{-us}}{1-e^{-s}}\left(e^{(u-x_0)(1-e^{-s})} - e^{(u-x_0)(e^{s-T}-e^{-T})}\right)ds$$
$$+ \int_0^T e^{-us}\left(e^{(u-x_0)(1-e^{-s})} - e^{(u-x_0)(e^{s-T}-e^{-T})}e^{s-T}\right)ds$$

which can be rewritten as

$$\int_0^T \partial_u y_u(t)dt = \int_0^T e^{-us}\left(e^{(u-x_0)(1-e^{-s})}\left(1-\frac{s}{1-e^{-s}}\right)\right.$$
$$\left. +e^{(u-x_0)(e^{s-T}-e^{-T})}\left(\frac{s}{1-e^{-s}} - e^{s-T}\right)\right)ds. \qquad (19)$$

3. Two useful results: We now establish a couple of useful results that will help us in proving the monotonicity property of the cDR.

Lemma 1. *Fix any positive T and κ, and for $s \in [0, T]$ define functions*

$$\rho(s) = (1 - e^{-s})(1 - e^{s-T})$$

and

$$f_\kappa(s) = e^{-\kappa\rho(s)}\left(\frac{s}{1-e^{-s}} - e^{s-T}\right) - \left(\frac{s}{1-e^{-s}} - 1\right). \qquad (20)$$

Then the function $f_\kappa(s)$ can cross the x-axis only once in the interval $[0, T]$.

Proof. Note that $\rho(s) = (1 - e^{-s})(1 - e^{s-T}) = 1 + e^{-T} - e^{-s} - e^{s-T}$. Setting $f_\kappa(s) = 0$ we get

$$s + e^{-s} - 1 = e^{-\kappa\rho(s)}(s - e^{s-T} + e^{-T}) = e^{-\kappa\rho(s)}(s + e^{-s} - 1 + \rho(s)),$$

which upon re-arranging yields

$$s + e^{-s} - 1 = \frac{\rho(s)}{e^{\kappa\rho(s)} - 1}.$$

Let $g_\kappa(s)$ be the function

$$g_\kappa(s) = (s + e^{-s} - 1) - \frac{\rho(s)}{e^{\kappa\rho(s)} - 1}.$$

To prove the lemma it suffices to show that the function $g_\kappa(s)$ is monotonically increasing, which we shall show by proving that $g'_\kappa(s) \geq 0$ for all $s \in [0, T]$. For convenience let us define a function

$$\phi(z) = \frac{z}{e^z - 1}.$$

Then we can write $g_\kappa(s)$ as

$$g_\kappa(s) = (s + e^{-s} - 1) - \frac{1}{\kappa}\phi(\kappa\rho(s))$$

which shows that

$$g'_\kappa(s) = 1 - e^{-s} - \phi'(\kappa\rho(s))\rho'(s) = 1 - e^{-s} - \phi'(\kappa\rho(s))(e^{-s} - e^{s-T}).$$

Suppose we can show that

$$-1 \leq \phi'(z) \leq 0 \qquad \text{for all} \qquad z \geq 0. \tag{21}$$

Then for $s \in [0, \frac{T}{2}]$ we have $(e^{-s} - e^{s-T}) > 0$ and so $g'_\kappa(s) \geq 1 - e^{-s} \geq 0$. On the other hand for $s \in [\frac{T}{2}, T]$, $(e^{-s} - e^{s-T}) < 0$ and using $\phi'(z) \geq -1$, we obtain

$$g'_\kappa(s) \geq 1 - e^{-s} + (e^{-s} - e^{s-T}) = 1 - e^{s-T} \geq 0.$$

Hence to prove the lemma we just need to prove the inequality (21) to which we come to now. Note that

$$\phi'(z) = \frac{1}{e^z - 1} - \frac{ze^z}{(e^z - 1)^2} = \frac{e^z - 1 - ze^z}{(e^z - 1)^2} = -\frac{e^z(z + e^{-z} - 1)}{(e^z - 1)^2}.$$

Since $z + e^{-z} - 1 \geq 0$ for any $z \geq 0$, we would have that $\phi'(z) \leq 0$. Since the function $\phi(z)$ is monotonically decreasing for $z \geq 0$ we must have

$$\sup_{z>0} \phi(z) = \lim_{z \to 0^+} \phi(z) = 1. \tag{22}$$

Observe that we can write $\phi'(z)$ as

$$\phi'(z) = \frac{e^z - 1 - z}{(e^z - 1)^2} - \phi(z)$$

As the first term is always positive, we have $\phi'(z) \geq -\phi(z)$, which along with (22) shows that

$$\inf_{z>0} \phi'(z) \geq -\sup_{z>0} \phi(z) = -1.$$

This completes the proof of the inequality (21) and concludes the proof of this lemma. □

Proposition 1. *For any $u > 0$, the integral*

$$\int_0^\infty e^{-us}\left(\frac{s}{1 - e^{-s}} - e^{u(1-e^{-s})}\left(\frac{s}{1 - e^{-s}} - 1\right)\right)ds \tag{23}$$

has a positive value.

Proof. Define a function

$$w(s) = s + e^{-s} - 1.$$

Note that the integral (23) can be rewritten as

$$I(u) = \int_0^\infty \left(\frac{se^{-us} - w(s)e^{-uw(s)}}{1 - e^{-s}} \right) ds = \frac{d}{du} G(u)$$

where

$$G(u) = \int_0^\infty \left(\frac{e^{-uw(s)} - e^{-us}}{1 - e^{-s}} \right) ds.$$

Hence in order to prove that $I(u)$ is positive, we just need to prove that the function $G(u)$ is monotonically increasing. This is what we show next.

Using the fact that

$$\frac{e^x - 1}{x} = \sum_{n=0}^\infty \frac{x^n}{(n+1)!},$$

we obtain

$$G(u) = \int_0^\infty e^{-us} \left(\frac{e^{u(1-e^{-s})} - 1}{1 - e^{-s}} \right) ds$$

$$= \sum_{n=0}^\infty \frac{u^{n+1}}{(n+1)!} \int_0^\infty e^{-us}(1 - e^{-s})^n ds.$$

Applying the change of variable $t = 1 - e^{-s}$, we get

$$G(u) = \sum_{n=0}^\infty \frac{u^{n+1}}{(n+1)!} \int_0^1 (1 - t)^{u-1} t^n dt.$$

The integral on the right can be expressed in terms of the Gamma function $\Gamma(x)$ as

$$\int_0^1 (1 - t)^{u-1} t^n dt = \frac{\Gamma(n+1)\Gamma(u)}{\Gamma(n+1+u)} = \frac{n!\Gamma(u)}{\Gamma(n+1+u)}.$$

Substituting this we obtain

$$G(u) = \sum_{n=0}^\infty \frac{u^{n+1}}{(n+1)} \frac{\Gamma(u)}{\Gamma(n+1+u)}.$$

Since $\Gamma(x+1) = x\Gamma(x)$ we can express $G(u)$ as

$$G(u) = \sum_{n=0}^\infty \frac{1}{(n+1)} L_n(u).$$

where

$$L_n(u) = \prod_{i=1}^n \left(\frac{u}{u+j} \right).$$

As each $L_n(u)$ is a product of positive monotonically increasing functions, the function $G(u)$ is also monotonically increasing. This completes the proof of this proposition. $\square$

4. Proving monotonicity of the cDR: Finally we now prove the monotonicity of the cDR by proving (11). For this we shall use the integral expression (19).

Let us first deal with the case $u \leq x_0$. In this scenario $(u - x_0) \leq 0$ and since $e^{s-T} \leq 1$ we have

$$e^{(u-x_0)(e^{s-T}-e^{-T})} = e^{(u-x_0)e^{s-T}(1-e^{-s})} \geq e^{(u-x_0)(1-e^{-s})}.$$

Therefore the integrand on the r.h.s. of (19) can be bounded below

$$e^{(u-x_0)(1-e^{-s})} \left(1 - \frac{s}{1-e^{-s}} \right) + e^{(u-x_0)(e^{s-T}-e^{-T})} \left(\frac{s}{1-e^{-s}} - e^{s-T} \right)$$
$$\geq e^{(u-x_0)(1-e^{-s})} \left(1 - e^{s-T} \right) \geq 0.$$

Hence the integrand in (19) is always non-negative which establishes the monotonicity of cDR for $u \leq x_0$.

We now consider the case $u > x_0$. Note that in this case $x_u(t)$ (see (12)) is monotonically increasing from x_0 to u. Hence $y_u(0) = 1$ and

$$\dot{y}_u(t) = -x_u(t)y_u(t) + u \geq -uy_u(t) + u$$

which allows us to conclude that $y_u(t) \geq 1$ for all $t \geq 0$, by a simple comparison argument we now provide. Suppose that $x_0 \leq 1$. In this case we prove that for any positive u, the trajectory $t \mapsto \partial_u y_u(t)$ can only change its sign once, to go from positive to negative, and then it will stay negative and asymptotically approach 0. To see this define

$$z_u(t) = (1 - e^{-t})y_u(t) - 1$$

and then

$$\dot{z}_u(t) = e^{-t}y_u(t) + (1 - e^{-t})\dot{y}_u(t)$$
$$= e^{-t}y_u(t) + (1 - e^{-t})(-x_u(t)y_u(t) + u)$$
$$= e^{-t}y_u(t) + (1 - e^{-t})u - x_u(t)(1 - e^{-t})y_u(t)$$
$$= e^{-t}y_u(t) + (1 - e^{-t})u - x_u(t) - x_u(t)z_u(t)$$
$$= e^{-t}(y_u(t) - x_0) - x_u(t)z_u(t).$$

Since we have assumed $x_0 \leq 1$ we have the differential inequality

$$\dot{z}_u(t) \geq -x_u(t)z_u(t).$$

Hence, by the comparison argument, if there exists a t_1 such that $z_u(t_1) \geq 0$, then for all $t \geq t_1$ we have $z_u(t) \geq 0$ which also implies that

$$y_u(t) \geq \frac{1}{1 - e^{-t}}.$$

Now let t_1 be the first zero of the trajectory $\partial_u y_u(t)$. Observe that

$$\partial_u \dot{y}_u(t) = -y_u(t)\partial_u x_u(t) - x_u(t)\partial_u y_u(t) + 1$$
$$= -(1 - e^{-t})y_u(t) - x_u(t)\partial_u y_u(t) + 1$$
$$= -z_u(t) - x_u(t)\partial_u y_u(t).$$

As t_1 is the first zero of the trajectory $\partial_u y_u(t)$ we have $\partial_u y_u(t) > 0$ for $t < t_1$, and $\partial_u \ddot{y}_u(t_1) \leq 0$ and $\partial_u y_u(t_1) = 0$. Hence we must have $z_u(t_1) \geq 0$ and by previous arguments $z_u(t) \geq 0$ for all $t \geq t_1$. Therefore in this interval $t \in (t_1, \infty)$ we have the inequality

$$\partial_u \dot{y}_u(t) \leq -x_u(t) \partial_u y_u(t) = -(1 - e^{-t}) \partial_u y_u(t)$$

and since $\partial_u y_u(t_1) = 0$, the comparison argument shows that $\partial_u y_u(t) \leq 0$ for all $t \geq t_1$. Hence the trajectory $t \mapsto \partial_u y_u(t)$ can only change its sign once, to go from positive to negative. Therefore in order to prove $\int_0^T \partial_u y_u(t) dt \geq 0$ for any T, it suffices to prove that this holds in the limit $T \to \infty$. Letting $T \to \infty$ in (19) we arrive at

$$\int_0^\infty \partial_u y_u(t) dt = \int_0^\infty e^{-us} \left(\frac{s}{1 - e^{-s}} - e^{(u-x_0)(1-e^{-s})} \left(\frac{s}{1 - e^{-s}} - 1 \right) \right) ds.$$

Since $\frac{s}{1-e^{-s}} \geq 1$ for all $s > 0$, in order to prove the positivity of this integral it suffices to prove its positivity for $x_0 = 0$, i.e.

$$\int_0^\infty \partial_u y_u(t) dt = \int_0^\infty e^{-us} \left(\frac{s}{1 - e^{-s}} - e^{u(1-e^{-s})} \left(\frac{s}{1 - e^{-s}} - 1 \right) \right) ds > 0, \qquad (24)$$

which holds due to Proposition 1.

We now come to the case where $1 < x_0 < u$. Set $\kappa = (u - x_0)$ and let $\rho(s)$ and $f_\kappa(s)$ be the functions defined in the statement of Lemma 1. Note that (19) can be written in terms of this function as

$$\int_0^T \partial_u y_u(t) dt = \int_0^T e^{-us} e^{\kappa(1-e^{-s})} f_\kappa(s) ds. \qquad (25)$$

Moreover

$$\lim_{s \to 0+} f_\kappa(s) = 1 - e^{-T} > 0 \qquad \text{and} \qquad f_\kappa(T) = 0.$$

Lemma 1 proves that the function $f_\kappa(s)$ can only cross the x-axis at most once in the interval $[0, T]$. If it does cross then it goes from positive to negative and it stays negative till it becomes 0 at $s = T$. The same holds for the function $e^{-\kappa s} e^{\kappa(1-e^{-s})} f_\kappa(s)$. Hence if we can prove that

$$\int_0^T e^{-\kappa s} e^{\kappa(1-e^{-s})} f_\kappa(s) ds > 0 \qquad (26)$$

then, as $\kappa < u$, it automatically implies that

$$\int_0^T \partial_u y_u(t) dt = \int_0^T e^{-us} e^{\kappa(1-e^{-s})} f_\kappa(s) ds > 0. \qquad (27)$$

To see this let s^* be the time in $[0, T]$ where the function $f_\kappa(s)$ crosses the x-axis. Then (26) implies that

$$\int_0^T e^{-\kappa s} e^{\kappa(1-e^{-s})} f_\kappa(s) ds$$

$$= \int_0^{s^*} e^{-\kappa s} e^{\kappa(1-e^{-s})} f_\kappa(s) ds + \int_{s^*}^T e^{-\kappa s} e^{\kappa(1-e^{-s})} f_\kappa(s) ds$$

$$= \int_0^{s^*} e^{-\kappa s} e^{\kappa(1-e^{-s})} |f_\kappa(s)| ds - \int_{s^*}^T e^{-\kappa s} e^{\kappa(1-e^{-s})} |f_\kappa(s)| ds$$

$$> 0.$$

Therefore, using that $e^{-us} \geq e^{-(u-\kappa)s^*}e^{-\kappa s}$ for $s \leq s^*$ and $e^{-us} \leq e^{-(u-\kappa)s^*}e^{-\kappa s}$ for $s \geq s^*$, we get

$$
\int_0^T e^{-us}e^{\kappa(1-e^{-s})}f_\kappa(s)ds
$$
$$
= \int_0^{s^*} e^{-us}e^{\kappa(1-e^{-s})}|f_\kappa(s)|ds - \int_{s^*}^T e^{-us}e^{\kappa(1-e^{-s})}|f_\kappa(s)|ds
$$
$$
\geq e^{-(u-\kappa)s^*}\left(\int_0^{s^*} e^{-\kappa s}e^{\kappa(1-e^{-s})}|f_\kappa(s)|ds - \int_{s^*}^T e^{-\kappa s}e^{\kappa(1-e^{-s})}|f_\kappa(s)|ds\right)
$$
$$
> 0.
$$

This shows that to prove the monotonicity result it suffices to prove (26), which is of course equivalent to proving the positivity of (19) for $u = \kappa$ and $x_0 = 0$. As mentioned above, this positivity follows from (24) which is shown in Proposition 1. This completes the proof of the cDR monotonicity result for IFFL1.

3 Unconditional monotonicity of both DR and cDR for IFFL2

Recall the description of IFFL2 from equations (5)-(6). Here we can easily prove that DR map $u \mapsto y_u(t)$ is a monotonically increasing function of input u, and hence, the same holds for the cDR map.

In order to prove this monotonicity it suffices to show that the partial derivative $\partial_u y_u(t)$ is nonnegative for any u and t. Since $x_u(t)$ satisfies the linear ODE (5) we can solve for it explicitly to obtain

$$
x_u(t) = x_0 e^{-\delta t} + \frac{u\alpha}{\delta}(1 - e^{-\delta t})
$$

which also implies that

$$
\partial_u x_u(t) = \frac{\alpha}{\delta}(1 - e^{-\delta t}) = \frac{x_u(t) - x_0 e^{-\delta t}}{u}. \tag{28}
$$

As $y_u(t)$ satisfies the ODE (6) we can differentiate it w.r.t. u to obtain an ODE for $\partial_u y_u(t)$ as

$$
\partial_u \dot{y}_u = \frac{\beta}{K + x_u(t)} - \frac{\beta u}{(K + x_u(t))^2}\partial_u x_u(t) - \gamma\,\partial_u y_u(t).
$$

Substituting $\partial_u x_u(t)$ from (28) and re-arranging we get

$$
\partial_u \dot{y}_u = \frac{\beta}{K + x_u(t)} - \frac{\beta u}{(K + x_u(t))^2}\left(\frac{x_u(t) - x_0 e^{-\delta t}}{u}\right) - \gamma\,\partial_u y_u(t)
$$
$$
= \frac{\beta}{K + x_u(t)}\left(1 - \frac{x_u(t)}{K + x_u(t)} + \frac{x_0 e^{-\delta t}}{K + x_u(t)}\right) - \gamma\,\partial_u y_u(t).
$$

Since $K \geq 0$, it is immediate that $\frac{x_u(t)}{K + x_u(t)} \leq 1$, and so we have the differential inequality

$$
\partial_u \dot{y}_u(t) \geq -\gamma\,\partial_u y_u(t).
$$

As $\partial_u y_u(0) = 0$, by the comparison argument it follows that $\partial_u y_u(t) \geq 0$ for all t and u. This concludes the proof of the monotonicity result for IFFL2.

4   Conditional monotonicity of the cDR for IFB

Recall the description of IFB from equations (7)-(8). We shall assume that $K = 0$ for convenience. We scale time by γ^{-1} and the state values by a ratio to define

$$\hat{x}(t) = x(\gamma^{-1}t) \qquad \text{and} \qquad \hat{y}(t) = \frac{\alpha}{\gamma}y(\gamma^{-1}t).$$

Then we can write this system as

$$\dot{\hat{x}}(t) = \gamma^{-1}\dot{x}(\gamma^{-1}t) = \gamma^{-1}x(\gamma^{-1}t)(\alpha y(\gamma^{-1}t) - \delta) = \hat{x}(t)\left(\hat{y}(t) - \frac{\delta}{\gamma}\right)$$

$$\dot{\hat{y}}(t) = \frac{\alpha}{\gamma^2}\left(\frac{\beta u}{x(\gamma^{-1}t)} - \gamma y(\gamma^{-1}t)\right) = \frac{\alpha\beta u}{\gamma^2\hat{x}(t)} - \hat{y}(t)$$

Therefore if we define

$$\hat{u} = \frac{\alpha\beta}{\gamma^2}u \qquad \text{and} \qquad p = \frac{\delta}{\gamma}$$

then $(\hat{x}(t), \hat{y}(t))$ satisfies the ODEs

$$\dot{\hat{x}}(t) = \hat{x}(t)(\hat{y} - p)$$

$$\dot{\hat{y}}(t) = \frac{\hat{u}}{\hat{x}} - \hat{y}.$$

with initial values $\hat{x}(0) = x(0) = x_0$ and $\hat{y}(0) = \frac{\alpha}{\gamma}y(0) = \frac{\alpha}{\gamma}\frac{\delta}{\alpha} = \frac{\delta}{\gamma} = p$. Henceforth we shall drop the hats for notational convenience and suppose that the dynamics is given by

$$\dot{x} = x(y - p) \tag{29}$$

$$\dot{y} = \frac{u}{x} - y \tag{30}$$

with initial values $x(0) = x_0$ and $y(0) = p$.

Note that p is both the initial state and the steady-state value of the output variable $y_u(t)$. We shall reformulate the dynamics in terms of the "error"

$$\tilde{y}_u(t) = y_u(t) - p$$

and variable $z_u(t)$ defined as

$$z_u(t) = \frac{u}{x_u(t)}.$$

Then dynamics of $z_u(t)$ is given by

$$\dot{z}_u(t) = -\frac{u}{x_u^2(t)}\dot{x}_u(t) = -\frac{u}{x_u(t)}(y_u(t) - p) = -z_u(t)\tilde{y}_u(t).$$

Hence we can solve for $z_u(t)$ as

$$z_u(t) = \frac{u}{x_0}e^{-\int_0^t \tilde{y}_u(s)ds} \tag{31}$$

and the dynamics of the error is given by

$$\dot{\tilde{y}}_u(t) = \dot{y}_u(t) = z_u(t) - y_u(t) = z_u(t) - p - \tilde{y}_u(t). \tag{32}$$

Henceforth, instead of examining the monotonicity of the original cDR map, we shall equivalently examine the monotonicity of the error cDR map given by

$$u \mapsto \int_0^T \tilde{y}_u(t)dt.$$

1. Steady-state analysis:

We proved earlier that the steady state is stable. Thus $\lim_{t\to\infty} \tilde{y}_u(t) = 0$ and so $\lim_{t\to\infty} z_u(t) = p$. Therefore expression (31) implies that

$$\int_0^\infty \tilde{y}_u(t)dt = \log(u) - \log(px_0) \tag{33}$$

which is a monotonically increasing function of u. In particular, by differentiating w.r.t. u we obtain

$$\int_0^\infty \partial_u \tilde{y}_u(t)dt = \frac{1}{u} > 0. \tag{34}$$

If this positivity holds for any finite time-interval then we shall have the monotonicity of the error cDR map. We shall show that this monotonicity does not always hold and identify a sufficient condition under which it does. For this we shall connect this problem to a harmonic oscillator with a time-varying frequency.

2. Connection to a harmonic oscillator: Differentiating the error equation (32) w.r.t. t and using that $\dot{z}_u(t) = -z_u(t)\tilde{y}_u(t)$ we get

$$\ddot{\tilde{y}}_u(t) = \dot{z}_u(t) - \dot{\tilde{y}}_u(t) = -z_u(t)\tilde{y}_u(t) - \dot{\tilde{y}}_u(t)$$

which means that the error $\tilde{y}_u(t)$ satisfies the equation for a 'damped' harmonic oscillator with a non-constant frequency

$$\ddot{\tilde{y}}_u(t) + \dot{\tilde{y}}_u(t) + z_u(t)\tilde{y}_u(t) = 0, \tag{35}$$

with initial conditions $\tilde{y}_u(0) = 0$ and $\dot{\tilde{y}}_u(0) = z_u(0) - p = \frac{u}{x_0} - p$. Let us define the 'frequency' and Hamiltonian for this oscillator as

$$\omega(t) = \sqrt{z_u(t)} \quad \text{and} \quad \mathcal{H}(t) = (\tilde{y}_u(t))^2 + \left(\frac{\dot{\tilde{y}}_u(t)}{\omega(t)}\right)^2$$

respectively. Then their dynamics can be derived as

$$\dot{\omega}(t) = \frac{1}{2\omega(t)}\dot{z}_u(t) = -\frac{1}{2\omega(t)}z_u(t)\tilde{y}_u(t) = -\frac{\tilde{y}_u(t)}{2}\omega(t). \tag{36}$$

Using (35) we obtain

$$\dot{\mathcal{H}}(t) = 2\tilde{y}_u(t)\dot{\tilde{y}}_u(t) + 2\frac{\dot{\tilde{y}}_u(t)\ddot{\tilde{y}}_u(t)}{z_u(t)} - \left(\frac{\dot{\tilde{y}}_u(t)}{z_u(t)}\right)^2 \dot{z}_u(t)$$

$$= 2\tilde{y}_u(t)\dot{\tilde{y}}_u(t) - 2\frac{\dot{\tilde{y}}_u(t)}{z_u(t)}(\dot{\tilde{y}}_u(t) + z_u(t)\tilde{y}_u(t)) + \frac{(\dot{\tilde{y}}_u(t))^2}{z_u(t)}\tilde{y}_u(t)$$

$$= -2\left(\frac{\dot{\tilde{y}}_u(t)}{\omega(t)}\right)^2 \left(1 - \frac{\tilde{y}_u(t)}{2}\right). \tag{37}$$

Observe that the error $\tilde{y}_u(t) = y_u(t) - p$ in our adapting circuit goes to 0 as $t \to \infty$. Equation (37) shows that when this error is below 2, the Hamiltonian is decreasing. Note that the initial value of this Hamiltonian is

$$\mathcal{H}(0) = \frac{(u - px_0)^2}{ux_0}.$$

This brings us to a proposition that shows that if this value is less than 4, then the error $\tilde{y}_u(t)$ remains below 2 at all times.

Proposition 2. *Suppose that the following holds*

$$(u - px_0)^2 \leq 4ux_0. \tag{38}$$

Then we must have that $\tilde{y}_u(t) \leq 2$ for all $t \geq 0$.

Proof. Condition (38) implies that $\mathcal{H}(0) \leq 4$. Recall that $\tilde{y}_u(0) = 0$. Let t_1 be the first time $\tilde{y}_u(t)$ reaches 2, i.e. $\tilde{y}_u(t_1) = 2$ and $\tilde{y}_u(t) < 2$ for all $t < t_1$. Then due to (37) the Hamiltonian must be decreasing in the interval $[0, t_1]$, and so $\mathcal{H}(t_1) < \mathcal{H}(0) \leq 4$. But this is a contradiction since $\tilde{y}_u(t_1) = 2$ and so by definition $\mathcal{H}(t_1) \geq 4$. Hence $t_1 = \infty$ which means that $\tilde{y}_u(t) \leq 2$ for all $t \geq 0$. $\qquad \square$

3. Conditional monotonicity result: Now let us substitute $z_u(t)$ from (31) into eqn. (32) to obtain

$$\dot{\tilde{y}}_u(t) = \frac{u}{x_0}e^{-\int_0^t \tilde{y}_u(s)ds} - p - \tilde{y}_u(t). \tag{39}$$

Differentiating this w.r.t. u we get

$$\begin{aligned}
\partial_u \dot{\tilde{y}}_u(t) &= \frac{1}{x_0}e^{-\int_0^t \tilde{y}_u(s)ds} - \frac{u}{x_0}e^{-\int_0^t \tilde{y}_u(s)ds} \int_0^t \partial_u \tilde{y}_u(s)ds - \partial_u \tilde{y}_u(t) \\
&= \frac{u}{x_0}e^{-\int_0^t \tilde{y}_u(s)ds} \left(\frac{1}{u} - \int_0^t \partial_u \tilde{y}_u(s)ds \right) - \partial_u \tilde{y}_u(t) \\
&= z_u(t)\left(\frac{1}{u} - \int_0^t \partial_u \tilde{y}_u(s)ds \right) - \partial_u \tilde{y}_u(t).
\end{aligned}$$

This shows that if we define $\beta(t)$ as

$$\beta(t) = 1 - u \int_0^t \partial_u \tilde{y}_u(s)ds,$$

then $\beta(t)$ also satisfies the following second-order ODE for the damped harmonic oscillator (35) with initial conditions $\beta(0) = 1$ and $\dot{\beta}(0) = 0$. To prove the monotonicity we need to show that

$$\int_0^t \partial_u \tilde{y}_u(s)ds \geq 0$$

which is equivalent to proving that

$$\beta(t) \leq 1 \qquad \text{for all} \qquad t \geq 0. \tag{40}$$

Again we can definite the Hamiltonian as

$$\mathcal{H}_\beta(t) = (\beta(t))^2 + \left(\frac{\dot{\beta}(t)}{\omega(t)} \right)^2 \tag{41}$$

and it will have the same dynamics as before

$$\dot{\mathcal{H}}_\beta(t) = -2\left(\frac{\dot{\beta}(t)}{\omega(t)}\right)^2\left(1 - \frac{\tilde{y}_u(t)}{2}\right) \tag{42}$$

which we can also write as

$$\dot{\mathcal{H}}_\beta(t) = -\mathcal{H}_\beta(t)(2 - \tilde{y}_u(t)) + (\beta(t))^2(2 - \tilde{y}_u(t)). \tag{43}$$

We now come to our main result for the IFB example, which proves monotonicity of the error cDR under condition (38).

Proposition 3. *Suppose that condition* (38) *holds. Then the map*

$$u \mapsto \int_0^T \tilde{y}_u(t)dt$$

is monotonically increasing for any $T > 0$.

Proof. When (38) holds, we have that the error $\tilde{y}_u(t) \le 2$ for all $t \ge 0$ due to Proposition 2. This fact along with (42) implies that $\mathcal{H}_\beta(t) \le \mathcal{H}_\beta(0) = 1$ for $t \ge 0$. Therefore (40) holds which proves the required monotonicity property. □

4. Numerical illustration of non-monotonicity: When condition (38) does not hold, we do not have any analytical approach for checking the monotonicity property. Therefore we need to rely on numerical simulations. For any given u, the monotonicity condition (40) can fail at any $t \ge 0$. However as we cannot check this condition for all $t \ge 0$, we first show that if this monotonicity fails then it has to fail in the finite time-interval $[0, T_u]$ where T_u is defined by

$$T_u = \inf\{t \ge 0 : \mathcal{H}(t) \le 4 \quad \text{and} \quad \mathcal{H}_\beta(t) \le 1\}. \tag{44}$$

Note that T_u is finite because both $\mathcal{H}(t)$ and $\mathcal{H}_\beta(t)$ are nonnegative quantities converging to zero as $t \to \infty$. This is due to stability and the fact that (34) implies that $\beta(t) \to 0$ as $t \to \infty$.

Proposition 4. *Let T_u be the finite time defined by* (44). *Then we must have $\beta(t) \le 1$ for all $t \ge T_u$ which is the same as saying that $u \int_0^t \partial_u y(s)ds \ge 0$ for all $t \ge T_u$.*

Proof. Pick a small $\epsilon > 0$ and define

$$T_u^\epsilon = \inf\{t \ge 0 : \mathcal{H}(t) \le 4 - \epsilon \quad \text{and} \quad \mathcal{H}_\beta(t) \le 1 - \epsilon\}.$$

Note that for the same reason that T_u is finite, T_u^ϵ must also be finite. Moreover as ϵ decreases the set $\{t \ge 0 : \mathcal{H}(t) \le 4 - \epsilon \quad \text{and} \quad \mathcal{H}_\beta(t) \le 1 - \epsilon\}$ gets bigger and consequently its infimum, which is T_u^ϵ, gets smaller. Therefore T_u^ϵ decreases monotonically as ϵ decreases and since $\mathcal{H}(t)$ and $\mathcal{H}_\beta(t)$ are continuous functions of time we must have

$$\lim_{\epsilon \searrow 0} T_u^\epsilon = T_u. \tag{45}$$

By the definition of T_u^ϵ we have that $\mathcal{H}(T_u^\epsilon) < 4$ which implies that $\tilde{y}_u(T_u^\epsilon) < 2$. Let t_1^ϵ be the first time after T_u^ϵ such that $\tilde{y}_u(t_1^\epsilon) = 2$ and consequently $\mathcal{H}(t_1^\epsilon) \ge 4$. On the open interval $(T_u^\epsilon, t_1^\epsilon)$, $\mathcal{H}(t)$ must be decreasing due to (37) and so we should have $\mathcal{H}(t_1^\epsilon) \le \mathcal{H}(T_u^\epsilon)$. However this leads to a contradiction because $\mathcal{H}(T_u^\epsilon) < 4 \le \mathcal{H}(t_1^\epsilon)$. Therefore $t_1^\epsilon = \infty$ which means that $\tilde{y}_u(t) < 2$ for all $t \ge T_u^\epsilon$. This also means that $\mathcal{H}_\beta(t)$ in decreasing in the interval $[T_u^\epsilon, \infty]$ due to (42). Since $\mathcal{H}_\beta(T_u^\epsilon) < 1$ this implies that $\beta(t) < 1$ for all $t \ge T_u^\epsilon$. Using the continuity of β and the limit (45) we can conclude that $\beta(t) \le 1$ for all $t \ge T_u$. This completes the proof of this proposition. □

Figure 5 illustrates this proposition for three values of u. One can observe that $u \int_0^t \partial_u y(s) ds \geq 0$ holds for all $t \geq T_u$ for each u-value.

Figure 5: Plot of the map $t \mapsto u \int_0^t \partial_u y(s) ds$ for three values of u. Note that for each u, we have $u \int_0^t \partial_u y(s) ds \geq 0$ for all $t \geq T_u$.

We can now numerically solve the system $(z_u(t), y_u(t), \beta(t))$ in the interval $[0, T_u]$ and check if $\beta(t)$ exceeds 1 or not. For any t such that $\beta(t) > 1$ we would have $\int_0^t \partial_u \tilde{y}_u(s) ds < 0$ which would imply non-monotonicity. For any given u we define the non-monotonicity score as

$$\mathcal{S}(u) = \int_0^{T_u} (\beta(t) - 1)^+ dt = u \int_0^{T_u} \left(\int_0^t \partial_u \tilde{y}_u(s) ds \right)^- dt, \tag{46}$$

where a^+ (resp. a^-) denotes the positive (resp. negative) part of a. In Figure 6 we plot the non-monotonicity score $\mathcal{S}(u)$ and the time T_u for a range of u-values for $x_0 = p = 1$. Notice that T_u is monotonically increasing with u, while the non-monotonicity score $\mathcal{S}(u)$ stays at zero till $u \approx 220$ and then it gradually starts increasing. This shows that for higher values of u the map

$$u \mapsto \int_0^T \tilde{y}_u(t) dt$$

is always non-monotonic for some T which will increase as u increases. Figure 7 illustrates this non-monotonicity for some values of p and T.

Figure 6: Plot of the maps $u \mapsto \mathcal{S}(u)$ and $u \mapsto T(u)$ with $x_0 = p = 1.0$.

Figure 7: Plot of the map $u \mapsto \int_0^T \tilde{y}_u(t)dt$ for some values of p and T. Note that this map exhibits non-monotonicity in these cases.

5   Conclusions

We introduced the notion of cDR, and went on to show mathematically that both the incoherent feedback loop IFFL1 and IFFL2 motifs can only produce monotonic cumulative dose responses, even if (for IFFL1) the dose response itself may be non-monotonic. On the other hand, we also established conditions under which the integral feedback mechanism IFB can produce a non-monotonic cDR.

One may view our study of the cDR work as an addition to the toolkit of mathematical methods for model discrimination and invalidation, in a spirit similar to the work in [44] that infers the existence of IFFLs or negative feedback loops when time responses are non-monotonic, or to the work in [8] on using periodic inputs in order to rule out IFFLs as the basis of adaptation.

6   Acknowledgments

EDS's research was supported in part by grant AFOSR FA9550-21-1-0289. AG's research was supported in part by the Swiss National Science Foundation (SNSF) grant no. 216505.

References

[1] N. Barkai and S. Leibler. Robustness in simple biochemical networks. *Nature*, 387(6636):913–917, Jun 1997.

[2] Graeme W. Davis. Homeostatic control of neural activity: From phenomenology to molecular design. *Annual Review of Neuroscience*, 29(Volume 29, 2006):307–323, 2006.

[3] B. Wark, B. N. Lundstrom, and A. Fairhall. Sensory adaptation. *Current Opinion in Neurobiology*, 17(4):423–429, 2007. Sensory systems.

[4] D. Muzzey, C. A. Gómez-Uribe, J. T. Mettetal, and A. van Oudenaarden. A systems-level analysis of perfect adaptation in yeast osmoregulation. *Cell*, 138(1):160–171, Jul 2009.

[5] M.H. Khammash. Perfect adaptation in biology. *Cell Systems*, 12(6):509–521, Jun 2021.

[6] N. Trendel, P. Kruger, S. Gaglione, J. Nguyen, J. Pettmann, E.D. Sontag, and O. Dushek. Perfect adaptation of CD8+ T cell responses to constant antigen input over a wide range of affinity is overcome by costimulation. *Science Signaling*, 14:eaay9363, 2021.

[7] W. Ma, A. Trusina, H. El-Samad, W. A. Lim, and C. Tang. Defining network topologies that can achieve biochemical adaptation. *Cell*, 138(4):760–773, 2009.

[8] S. J. Rahi, J. Larsch, K. Pecani, N. Mansouri, A. Y. Katsov, K. Tsaneva-Atanasova, E. D. Sontag, and F. R. Cross. Oscillatory stimuli differentiate adapting circuit topologies. *Nature Methods*, 14:1010–1016, 2017.

[9] P. Yu and E.D. Sontag. A necessary condition for non-monotonic dose response, with an application to a kinetic proofreading model. In *Proc. 2024 63rd IEEE Conference on Decision and Control (CDC)*, 2024. To appear. Note: Extended version in arXiv.

[10] J.J. Tyson, K. Chen, and B. Novak. Sniffers, buzzers, toggles, and blinkers: dynamics of regulatory and signaling pathways in the cell. *Curr. Opin. Cell. Biol.*, 15:221–231, 2003.

[11] E.D. Sontag. Remarks on feedforward circuits, adaptation, and pulse memory. *IET Systems Biology*, 4:39–51, 2010.

[12] U. Alon. *An Introduction to Systems Biology: Design Principles of Biological Circuits*. Chapman & Hall, 2006.

[13] S. Semsey, S. Krishna, K. Sneppen, and S. Adhya. Signal integration in the galactose network of Escherichia coli. *Mol. Microbiol.*, 65:465–476, Jul 2007.

[14] F.-D. Xu, Z.-R. Liu, Z.-Y. Zhang, and J.-W. Shen. Robust and adaptive microRNA-mediated incoherent feedforward motifs. *Chinese Physics Letters*, 26(2):028701–3, February 2009.

[15] S. Sasagawa, Y. Ozaki, K. Fujita, and S. Kuroda. Prediction and validation of the distinct dynamics of transient and sustained ERK activation. *Nat. Cell Biol.*, 7:365–373, Apr 2005.

[16] T. Nagashima, H. Shimodaira, K. Ide, T. Nakakuki, Y. Tani, K. Takahashi, N. Yumoto, and M. Hatakeyama. Quantitative transcriptional control of ErbB receptor signaling undergoes graded to biphasic response for cell differentiation. *J. Biol. Chem.*, 282:4045–4056, Feb 2007.

[17] P. Menè, G. Pugliese, F. Pricci, U. Di Mario, G. A. Cinotti, and F. Pugliese. High glucose level inhibits capacitative Ca2+ influx in cultured rat mesangial cells by a protein kinase C-dependent mechanism. *Diabetologia*, 40:521–527, May 1997.

[18] R. Nesher and E. Cerasi. Modeling phasic insulin release: immediate and time-dependent effects of glucose. *Diabetes*, 51 Suppl 1:S53–59, Feb 2002.

[19] M. P. Mahaut-Smith, S. J. Ennion, M. G. Rolf, and R. J. Evans. ADP is not an agonist at P2X(1) receptors: evidence for separate receptors stimulated by ATP and ADP on human platelets. *Br. J. Pharmacol.*, 131:108–114, Sep 2000.

[20] S. Marsigliante, M. G. Elia, B. Di Jeso, S. Greco, A. Muscella, and C. Storelli. Increase of [Ca(2+)](i) via activation of ATP receptors in PC-Cl3 rat thyroid cell line. *Cell. Signal.*, 14:61–67, Jan 2002.

[21] L. Yang and P.A. Iglesias. Positive feedback may cause the biphasic response observed in the chemoattractant-induced response of *dictyostelium* cells. *Systems Control Lett.*, 55(4):329–337, 2006.

[22] A. Levchenko and P.A. Iglesias. Models of eukaryotic gradient sensing: Application to chemotaxis of amoebae and neutrophils. *Biophys J.*, 82:50–63, 2002.

[23] L. A. Ridnour, A. N. Windhausen, J. S. Isenberg, N. Yeung, D. D. Thomas, M. P. Vitek, D. D. Roberts, and D. A. Wink. Nitric oxide regulates matrix metalloproteinase-9 activity by guanylyl-cyclase-dependent and -independent pathways. *Proc. Natl. Acad. Sci. U.S.A.*, 104:16898–16903, Oct 2007.

[24] J. Tsang, J. Zhu, and A. van Oudenaarden. MicroRNA-mediated feedback and feedforward loops are recurrent network motifs in mammals. *Mol. Cell*, 26:753–767, Jun 2007.

[25] A. Kremling, K. Bettenbrock, and E. D. Gilles. A feed-forward loop guarantees robust behavior in escherichia coli carbohydrate uptake. *Bioinformatics*, 24:704–710, 2008.

[26] E. Voit, A. R. Neves, and H. Santos. The intricate side of systems biology. *Proc. Natl. Acad. Sci. U.S.A.*, 103:9452–9457, Jun 2006.

[27] E.D. Sontag. A dynamical model of immune responses to antigen presentation predicts different regions of tumor or pathogen elimination. *Cell Systems*, 4:231–241, 2017.

[28] L. Bleris, Z. Xie, D. Glass, A. Adadey, E.D. Sontag, and Y. Benenson. Synthetic incoherent feed-forward circuits show adaptation to the amount of their genetic template. *Molecular Systems Biology*, 7:519–, 2011.

[29] T.H. Segall-Shapiro, E. D. Sontag, and C. A. Voigt. Engineered promoters enable constant gene expression at any copy number in bacteria. *Nature Biotechnology*, 36:352–358, 2018.

[30] D. Kim, Y. K. Kwon, and K. H. Cho. The biphasic behavior of incoherent feed-forward loops in biomolecular regulatory networks. *Bioessays*, 30:1204–1211, Nov 2008.

[31] T. M. Yi, Y. Huang, M. I. Simon, and J. Doyle. Robust perfect adaptation in bacterial chemotaxis through integral feedback control. *Proc. Natl. Acad. Sci. U.S.A.*, 97:4649–4653, 2000.

[32] K. V. Venkatesh, S. Bhartiya, and A. Ruhela. Mulitple feedback loops are key to a robust dynamic performance of tryptophan regulation in *Escherichia coli*. *FEBS Letters*, 563:234–240, 2004.

[33] H. El-Samad, J. P. Goff, and M. Khammash. Calcium homeostasis and parturient hypocalcemia: An integral feedback perspective. *J. Theor. Biol.*, 214:17–29, 2002.

[34] P. Miller and X. J. Wang. Inhibitory control by an integral feedback signal in prefrontal cortex: A model of discrimination between sequential stimuli. *Proc. Natl. Acad. Sci.*, 103:201–206, 2006.

[35] D.K. Agrawal, R. Marshall, V. Noireaux, and E.D. Sontag. In vitro implementation of robust gene regulation in a synthetic biomolecular integral controller. *Nature Communications*, 10:1–12, 2019.

[36] S. K. Aoki, G. Lillacci, A. Gupta, A. Baumschlager, D. Schweingruber, and M. Khammash. A universal biomolecular integral feedback controller for robust perfect adaptation. *Nature*, 570(7762):533–537, Jun 2019.

[37] C. Briat, A. Gupta, and M. Khammash. Antithetic integral feedback ensures robust perfect adaptation in noisy biomolecular networks. *Cell systems*, 2(1):15–26, 2016.

[38] M. Bin, J. Huang, A. Isidori, L. Marconi, M. Mischiati, and E. D. Sontag. Internal models in control, bioengineering, and neuroscience. *Annual Review of Control, Robotics, and Autonomous Systems*, 5:20.1–20.25, 2022.

[39] A. Gupta and M. Khammash. Universal structural requirements for maximal robust perfect adaptation in biomolecular networks. *Proceedings of the National Academy of Sciences*, 119(43):e2207802119, 2022.

[40] Y. Hirono, A. Gupta, and M. Khammash. Complete characterization of robust perfect adaptation in biochemical reaction networks. *arXiv preprint arXiv:2307.07444*, 2023.

[41] O. Shoval, L. Goentoro, Y. Hart, A. Mayo, E.D. Sontag, and U. Alon. Fold change detection and scalar symmetry of sensory input fields. *Proc Natl Acad Sci USA*, 107:15995–16000, 2010.

[42] O. Shoval, U. Alon, and E.D. Sontag. Symmetry invariance for adapting biological systems. *SIAM Journal on Applied Dynamical Systems*, 10:857–886, 2011. (See here for a small typo: http://www.sontaglab.org/FTPDIR/shoval.alon.sontag.erratum.pdf).

[43] E.D. Sontag. *Mathematical Control Theory. Deterministic Finite-Dimensional Systems*, volume 6 of *Texts in Applied Mathematics*. Springer-Verlag, New York, second edition, 1998.

[44] J.A. Ascensao, P. Datta, B. Hancioglu, E.D. Sontag, M.L. Gennaro, and O.A. Igoshin. Non-monotonic response dynamics of glyoxylate shunt genes in mycobacterium tuberculosis. *PLoS Computational Biology*, 12:e1004741, 2016.