Temporal dose inversion properties of adaptive biomolecular circuits

Eiji Nakamura[1], Franco Blanchini[2], Giulia Giordano[3], Alexander Hoffmann[4], and Elisa Franco[1*]

[1]Department of Mechanical and Aerospace Engineering, University of California, Los Angeles, USA

[2]Department of Mathematics, Computer Science and Physics, University of Udine, Italy

[3]Department of Industrial Engineering, University of Trento, Italy

[4]Department of Microbiology, Immunology, and Molecular Genetics, University of California, Los Angeles, USA

[*]Correspondence: efranco@seas.ucla.edu

SUMMARY

Cells have the capacity to encode and decode information in the temporal features of molecular signals. Many pathways, for example, generate either sustained or pulsatile responses depending on the context, and such diverse temporal behaviors have a profound impact on cell fate. Here we focus on how molecular pathways can convert the temporal features of dynamic signals, in particular how they can convert transient signals into persistent downstream events and vice versa. We refer to this type of behavior as temporal dose inversion, and we demonstrate that it can be achieved through adaptive molecular circuits. Using a cell-free synthetic gene circuit implementing an incoherent feedforward loop (IFFL), we experimentally demonstrate the temporal dose inversion. To understand the design principles of the temporal dose inversion, we analyze adaptive circuit motifs including incoherent feedforward loops (IFFLs) and negative feedback loops (NFLs). Through numerical simulations with expensive parameter exploration, we identify parametric regimes in which these circuits exhibit temporal dose inversion. We further examine more detailed biological models of the IFFL and NFL circuits, including enzymatic signaling models and gene regulatory network models, showing that the IFFL circuits is more likely to exhibit temporal dose inversion compared with the NFL circuits. Finally, we analyze a generalized IFFL topology, and we find that both the time delay in the inhibition pathway and the relative signal intensities of the activation and inhibition signals are key determinants for temporal dose inversion. Together, our results establish a design principle of temporal dose inversion on the adaptive biomolecular circuits and provide mechanistic insight into how molecular networks process temporal information in dynamic signals.

KEYWORDS

temporal coding, pulse signaling, duration filtering, systems biology, incoherent feedforward loop

INTRODUCTION

Biological systems sense and respond to various physiological inputs, such as hormones, cytokines, and growth factors, by processing these signals through complex signaling pathways. These pathways lead to specific biological outcomes not only by producing or eliminating biomolecular components, but also by introducing temporal fluctuations of their concentration or activity[1–4]. A well-known example is the extracellular signal-regulated kinase (ERK), which can take different temporal characteristics and accordingly induce different biological outcomes in the mitogen-activated protein kinase (MAPK) network. ERK signals show either a transient or sustained behavior, depending on the input identity[5–8]. Epidermal growth factor (EGF) induces transient ERK activity, which triggers proliferation, whereas nerve growth factor (NGF) induces sustained ERK activity, which is translated to differentiation. ERK also plays an essential role in animal development. In the early Drosophila embryo, a high-dose ERK pulse induces gut endoderm differentiation, while a low-dose ERK pulse triggers cells to adopt neurogenic ectoderm[6]. The importance of temporal features has become evident in many biological contexts, including but not limited to neuronal activity[9] and hormonal signaling[10–12], leading to the notion of "temporal signaling" or "temporal coding"

by which living organisms encode and interpret information based on the timing, duration, frequency, and amplitude of signals over time.

Here we consider a broad question pertaining to temporal coding: what signaling networks can enable cells to select transient inputs based on their duration and amplitude? It is known that sustained signals and transient signals can be discriminated by simple network motifs such as the incoherent feedforward loop (IFFL) and the negative feedback loop (NFL)[13–18]. The IFFL and NFL are well-known for their adaptive behavior, which means they respond only transiently to changes in their input signal, typically taken to be a sustained amplitude input change. After a transient, the circuit eventually recovers its original state, unless the input perturbs the system beyond its tolerance. Intriguingly, we found that the IFFL and NFL can also produce a sustained output in response to a transient input, indicating their ability to discriminate inputs based on temporal features, and to process them to generate outputs with opposite temporal patterns. Building on these observations, we introduce the notion of temporal dose inversion which occurs if a system produces a sustained output when stimulated with a short-lived input, and vice-versa the system produces a short-lived output in response to a sustained input, as illustrated in Figure 1A and B.

The IFFL is a versatile motif that features one activation pathway and one inhibition pathway in parallel[17,19–23]. The behavior of the IFFL has typically been studied using step input functions: in this case, the expected response is a transient pulse owing to the presence of a delayed inhibition branch in the circuit[24,25]. The output initially increases and then is repressed, approaching an equilibrium that, in some cases, is identical or sufficiently close to its pre-stimulus state (perfect adaptation)[26]. Under certain assumptions, the output level directly depends on the ratio of the new input level to the pre-stimulus input level (fold-change detection)[27–31]. Furthermore, the IFFL has attracted growing interest as a circuit for processing dynamic signals, especially for detecting and decoding pulsatile signals[13–17]. Some of these studies (computational and experimental) demonstrated that the IFFL circuit or its variants, such as an interlocked IFFL[14,15], can be utilized as pulse detectors that respond to pulsatile inputs with specific temporal features. Finally, the IFFL can work as a band-pass circuit[14,32,33].

The NFL is a circuit motif with an inhibitory feedback loop, which is known as a core motif for generating pulses and oscillations in a variety of contexts, including the circadian clock[34], feedback circuit governing nuclear NF-κB localization[35], and the p53/Mdm2 network[36]. In addition, under certain conditions the NFL is known for its capability of adaptation and fold-change detection[37–40], both of which are essential for maintaining the robust operation of cellular functions in noisy environments.

We begin our study by considering simple IFFL and NFL circuit models to investigate the requirements for temporal dose inversion through numerical simulations. Next, we experimentally validate the temporal dose inversion property of an IFFL circuit built using *in vitro* transcriptional gene networks. We then examine whether temporal dose inversion property arises from specific biological mechanisms or emerges purely from network topology by analyzing more complex models meant to capture enzymatic signaling and gene regulatory networks. Finally, we consider a generalized IFFL architecture that is parameterized by the lengths of the activation and inhibition pathways to extract design rules of temporal dose inversion, showing that delayed inhibition is essential for temporal dose inversion. Together, these computational and experimental results provide insights that help us understand how adaptive biomolecular networks decode temporal information, specifically signal duration.

RESULTS

1 IFFL and NFL Models Exhibit Temporal Dose Inversion

Reduced order models for IFFL and NFL motifs Numerous models have been proposed to describe IFFL-based circuits[27,41–43]. Here, we adopt the typical circuit topology of an IFFL composed of an input signal U, an intermediate chemical species X and an output chemical species Y (Figure 1C). We use lowercase letters to indicate concentrations; u is the amplitude of input signal U, and x and y represent the concentrations of the species X and Y respectively. Temporarily denoting the input amplitude by $\bar{u}$,

Figure 1: (A) Illustrations of input-output circuit behaviors that maintain or invert the input temporal dose. (B) In a directly correlated dose response, the output dose increases as input dose increases. In an inversely correlated dose response, the output duration decreases as the input dose increases. (C, D) Our simple models for the incoherent feedforward loop (IFFL) and the negative feedback loop (NFL) circuits exhibit temporal dose inversion. Circuit diagrams, and temporal dynamics of (C) IFFL and (D) NFL, responding to pulsatile inputs with varied duration D_{in} from 0.2 to 1.00, with $a = 2$, $b = 20$, $c = 0.1$, and $p = 2$. Input duration versus output duration or output AUC for (C) IFFL and (D) NFL with c in the range from 0.05 to 1.00 is indicating that IFFL exhibits inverse dose duration (IDD) and inverse dose AUC (IDA) for a certain range of D_{in}, and NFL exhibits IDD in the whole evaluated range of D_{in}.

we introduce a simple model to describe the IFFL as follows:

$$\frac{dx(s)}{ds} = \alpha\bar{u}(s) - \beta x(s) \tag{1}$$

$$\frac{dy(s)}{ds} = \gamma\bar{u}(s) - \delta x^p(s)y(s) - \epsilon y(s) \tag{2}$$

where α and γ are the input activation rate constants for species X and Y; β and ϵ are self-degradation rate constants for species X and Y; δ is the rate constant associated with inhibition of Y mediated by X, and p represents the effective order of the inhibitory reaction, capturing nonlinearities arising from cooperative interactions, multimer formation, or embedded multi-step reaction cascades, while s is the time variable. We note that it is essential for our model to be nonlinear, as linear systems do not admit temporal dose inversion (Supplemental information).

To reduce the number of parameters, we rescale time in Equations 1 and 2, obtaining the updated model, which we will analyze in the following without loss of generality:

$$\dot{x}(t) = u(t) - x(t) \tag{3}$$

$$\dot{y}(t) = au(t) - bx^p(t)y(t) - cy(t) \tag{4}$$

where $t = \beta s$, $u = \alpha\bar{u}/\beta$, $a = \gamma/\alpha$, $b = \delta/\beta$ and $c = \epsilon/\beta$, while $\dot{x}(t) = \frac{dx(t)}{dt}$ and $\dot{y}(t) = \frac{dy(t)}{dt}$. Using Equations 3 and 4, we can evaluate the circuit dynamics with respect to parameters a, b, c, and p. We examine the response of the model to a rectangular input function of finite duration D_{in} with amplitude u_0:

$$u(t) = \begin{cases} u_0 & 0 \leq t \leq D_{in} \\ 0 & t > D_{in} \end{cases} \tag{5}$$

For the NFL, we adopt the simple circuit topology (Figure 1D) and obtain the corresponding equations with rescaled time as follows:

$$\dot{x}(t) = y(t) - x(t) \tag{6}$$

$$\dot{y}(t) = au(t) - bx^p(t)y(t) - cy(t) \tag{7}$$

The detailed derivation of Equations 6 and 7 is described in STAR Methods 4. The only difference from the IFFL model is that the first term of Equation 6 is $y(t)$ instead of $u(t)$. Throughout numerical simulations using these IFFL and NFL models, the initial conditions are $x(0) = 0$ and $y(0) = 0$. Responses of the simple IFFL model and the simple NFL model for different input durations D_{in} (from 0.2 to 1.0) are evaluated (Figure 1C and 1D).

Measuring temporal inversion properties To quantify whether the IFFL and NFL have the capacity to invert the temporal features of the input, we measure the output response with two metrics: signal duration and temporal dose. Temporal dose is broadly intended as the area under the curve (AUC, i.e. the integral) of a transient signal, which depends on both its amplitude and its duration. Accordingly, we define two types of temporal dose inversion properties: inverse dose duration (IDD) and inverse dose AUC (IDA). An IDD circuit converts a short pulse into a longer pulse and vice versa, functioning as a duration inverter. An IDA circuit converts a small-AUC input into a large-AUC output and vice versa, functioning as a temporal dose amplifier. When a circuit specifically detects a transient signal, it is expected that the circuit shows the temporal dose inversion properties. Through computational methods, we characterize the temporal dose inversion properties of IFFL and NFL circuits by considering pulsatile inputs of varying duration, and derive parametric and topological conditions for implementing inversion properties.

The IFFL exhibits a long-lasting response to a shorter input duration (e.g. $D_{in} = 0.2$), and thus shows the capacity for IDD (Figure 1C). To quantitatively evaluate its temporal dose inversion properties, we computed the output duration D_{out} and the area under the curve (AUC). D_{out} is calculated as the square root of the variance in the time domain, where the variance is derived as the difference between the second moment ($\int_0^\infty t^2 y(t)dt / \int_0^\infty y(t)dt$) and the square of the mean ($\int_0^\infty ty(t)dt / \int_0^\infty y(t)dt$). This approach is analogous to the calculation of the standard deviation in probability distributions. AUC is the

integration of the output signal $y(t)$ from $t = 0$ to $t = 80$, as described in detail in STAR Methods 4. D_{out} and AUC are evaluated as a function of D_{in} (lower left panels of Figure 1C and D). D_{out} monotonically decreases as D_{in} increases: D_{out} and D_{in} are inversely correlated, and therefore the system has the inverse dose duration (IDD) property. Conversely, AUC increases when $0 < D_{in} < 0.25$, has a peak at $D_{in} = 0.25$, and decreases when $D_{in} > 0.25$. Hence, we argue that the IFFL exhibits the inverse dose AUC (IDA) property just in a range of D_{in} values ($D_{in} > 0.25$). The NFL circuit also exhibits IDD, as D_{out} is monotonically decreasing with respect to D_{in}, while it does not exhibit IDA, since AUC increases for increasing D_{in} (Figure 1D). We will compare the likelihood of the IDA property for IFFL and NFL in Section 3.

Parametric regimes enabling temporal dose inversion To understand how each parameter shapes the circuit dynamics and temporal dose inversion, we first identify a set of nominal parameter values that exhibit temporal dose inversion through trial and error. We then vary a, b and c individually by one order of magnitude around their nominal values, taking input durations $D_{in} = 0.1$ and $D_{in} = 1$ (Figure 6). The activation parameter a mostly changes the amplitude of the output, without significantly affecting its duration. The inhibition parameter b and the degradation parameter c change the output response more drastically. As b or c increases, the output duration decreases, because a larger value of b or c brings the output level more quickly back to its basal level. However, when $D_{in} = 1$, the output duration does not perceptibly decrease as c increases; this happens because, owing to the longer input duration, the effect of the inhibition term $bx^p y$ is dominant.

Heat maps of D_{out} and AUC displayed in the D_{in}-a, D_{in}-b and D_{in}-c planes reveal the emergence of temporal dose inversion and the influence of each parameter (Figure 2). When there is a cross-section at a fixed parameter value along which D_{out} decreases over a range of D_{in} (e.g., $b = 20$ in the left middle panel of Figure 2B), the circuit exhibits the IDD property for that parameter set. Similarly, a decrease in AUC at a cross-section indicates the IDA property.

To systematically assess the IDD and the IDA property, we calculate an IDD score (S_{IDD}) and an IDA score (S_{IDA}) as follows. Given an input duration interval $D_{in,1} < D_{in} < D_{in,2}$ for which the function $D_{out}(D_{in})$ has a negative derivative,

$$S_{IDD} = \frac{D_{out}(D_{in,1})}{D_{out}(D_{in,2})} - 1. \tag{8}$$

If there are multiple input duration intervals in which the function $D_{out}(D_{in})$ has a negative derivative, we choose our score S_{IDD} as the maximum value of $\frac{D_{out}(D_{in,1})}{D_{out}(D_{in,2})} - 1$. If the function $D_{out}(D_{in})$ is monotonically increasing or constant, $S_{IDD} = 0$, which means that no IDD property is observed in the considered parameter set. S_{IDA} is computed analogously for the function $AUC(D_{in})$. By computing S_{IDD} and S_{IDA} values for each parameter set, we can quantify to which degree the IDD and IDA properties hold within that parameter set. More details on the mathematical computation of S_{IDD} and S_{IDA} are provided in STAR Methods 18.

The IFFL shows both the IDD and IDA properties within a certain range of each parameter (Figure 2A and B). While the activation parameter a does not change D_{out} (and therefore does not affect the IDD property), a higher value of a favors an apparent IDA property. The inhibition parameter b and the degradation parameter c significantly affect both D_{out} and AUC; as b or c increases, the circuit dynamics accelerates, which can be seen in the fact that the region with large D_{out} expands as b or c decreases. The dependence of AUC on b is more complicated than that of D_{out}. Although AUC increases as b decreases because of a smaller inhibition effect, decreasing b leads to the loss of the IDA property: for instance, along a cross-section with $b = 2$ (Figure 2B middle), AUC monotonically increases as D_{in} increases (hence, there is no IDA property). Therefore, b should not be too small to obtain the IDA property at least for a range of D_{in} values, whereas a larger value of a and lower value of c are preferable to ensure the IDA property at least in some ranges of D_{in}.

The NFL can also exhibit the IDD and IDA properties, but for a smaller set of parameters with respect to the IFFL (Figure 2C). Concerning the IDD property, differently from the IFFL circuit, the NFL shows a strong dependence on the activation parameter a; in fact, the inhibitory feedback from X has to be triggered by Y and a determines how quickly Y activates X, which eventually affects D_{out}. Concerning the IDA property, it is worth pointing out that the color scales of the heat maps in Figure 2C (right) are

smaller than those in Figure 2B (right), suggesting that, in the NFL, it is more difficult to identify a cross-section at a parameter value along which we see an apparent IDA property. Here is an explanation as to why the IFFL is more likely to exhibit the IDA property. In the IFFL, the activation and inhibition pathways can be tuned independently, so we can choose the parameters so that the output node Y is immediately activated, while X is activated with a certain (tunable) delay. Therefore, if D_{in} is smaller than a threshold, input U only activates Y, without activating the inhibition signal from X. Once D_{in} exceeds the threshold, both the activation and inhibition pathways are triggered, which eventually decreases AUC. This is the mechanism that allows us to attain the IDA property in the IFFL. In contrast, in the NFL, the activation pathway and the inhibition pathways acting on Y are not independent, and are stimulated simultaneously in most cases; in fact, it is relatively difficult to find a condition in which only Y is activated, keeping the inhibition feedback from X not significantly stimulated, because active Y stimulates X. This does not mean that the NFL does not exhibit the IDA property for any choice of the parameters, but provides us with a qualitative understanding of why IFFL is more likely than NFL to exhibit the IDA property.

Figure 2: Evaluating the inverted dose-response as a function of individual parameters related to output production (a), inhibition (b), and degradation (c). (A) Time evolution of the output y with $D_{in} = 0.1$, $D_{in} = 0.5$, $D_{in} = 1$. Each output curve corresponds to the data point indicated with the same Roman numeral in the heat maps in panel B. (B,C) Heat maps showing the values of D_{out} (blue heat maps) and AUC (red heat maps) for the outputs of the IFFL (B) and the NFL (C) in the D_{in}-a, D_{in}-b, D_{in}-c planes respectively. Here, D_{in} is linearly varied from 0.1 to 1 in steps of 0.05. In the same row or the same column, heat maps have the same axes units (only shown in the leftmost or bottom panels). Each row shows heat maps for a different parameter: a, top; b, center; c, bottom.

Parameter p, the order of the inhibition term, also affects the IDD and IDA properties. D_{out} and AUC are shown as heat maps in the D_{in}-u_0 plane (Figure 2D and E). For both IFFL and NFL, the IDA property is reinforced as p increases, namely, the ranges of D_{in} and u_0 where an apparent inverse relationship occurs and the corresponding dynamic ranges of the AUC expand, while the IDD property is not apparently reinforced for both circuits. When $p = 3$, both the IFFL and NFL do not exhibit the IDD and the IDA properties for small u_0 (such as $u_0 = 0.5$), while they do exhibit the properties for larger u_0. This happens because, when $x < 1$, the inhibition term $bx^p y$ decreases as p increases.

Varying the input amplitude u_0 can also lead to temporal dose inversion (Figure 2D and E). This can be explained by noting that the x variable of the IFFL responds to an input (starting from the initial condition $x(0) = 0$) by increasing monotonically and asymptotically reaching its equilibrium $x_{eq} = u_0$. Therefore, if $u_0 < 1$, then it is always $x(t) < 1$, which reduces the effect of the inhibition term $bx^p y$. However, if $u_0 > 1$, the degree p of the inhibition term reinforces the IDD and IDA properties. Interestingly, all heat maps are symmetric with respect to the diagonal line in the D_{in}-u_0 plot (which is not the bisector, since the two axes have different scales).

2   Cell-free demonstration of Temporal Dose Inversion

We experimentally demonstrate that temporal dose inversion occurs in a synthetic IFFL circuit built using cell-free transcriptional components known as "genelets"[21,44,45].

Transcriptional genelet circuits A genelet is a linear, double-stranded DNA construct that contains a T7 promoter with a nick in its template strand (Figure 3A). Transcription from a genelet depends on whether an activator strand (dA) is bound (genelet transcription on) or not (genelet off) to the promoter region, which operates as an input domain. The output of a genelet is its RNA transcript, whose sequence content is completely decoupled from the input. Thus, a genelet can be graphically represented as a node characterized by its independent inputs and outputs (Figure 3A, bottom). In this system, transcription is achieved using bacteriophage T7 RNA polymerase, and RNA is degraded by introducing RNase H[44], which targets RNA in DNA-RNA complexes. We measure the on/off state of a genelet by labeling genelet templates with a fluorophore (labeled F in Figure 3A), and DNA activators with a quencher (Q in Figure 3A).

Binding of an activator to its input domain is competitively regulated by the presence of a DNA blocker (dB). Activator and blocker DNA strands can themselves be sequestered by external regulatory RNAs, an RNA co-activator (rC) and an RNA repressor (rR), to provide an additional layer of regulation (Figure 3B). Genelets can easily be interconnected in a cascade, where the genelet upstream can transcribe a coactivator or a repressor RNA for the downstream genelet (Figure 3C). Furthermore, because input domains and regulatory-RNA sequences can be freely recombined, it is possible to realize nearly arbitrary network topologies. These networks can be represented as graphs where nodes are associated with genelets, and arcs with the RNA input/output molecules functionally interconnecting the genelets[21] (Figure 3C,D).

A genelet-based IFFL Figure 3D shows our IFFL circuit, which is consistent with previous work by Schaffter and coauthors[21]. Two input genelets, $G_{in}C_{out}$ and $G_{in}C_r$, share an identical input domain; thus a single DNA activator (dA_{in}) activates both input genelets, and a single DNA repressor (dR_{in}) represses both of them. The circuit implements an IFFL, in which one pathway directly activates the output genelet ($G_{in}C_{out} \rightarrow G_{out}S$), while the other pathway indirectly inhibits the output node through the intermediate node ($G_{in}C_r \rightarrow G_rR_{out} \dashv G_{out}S$). We tuned the dynamics of the circuit to achieve a desired operating point by varying the concentrations of the individual genelets and the enzymes T7 RNA polymerase and RNase H. All working concentrations used in our experiments are listed in the Supplemental Information. These values were established through a set of preliminary experiments so that the timescale of experimentally observed on/off transitions of input, intermediate, and output genelets (measured through fluorescence spectroscopy) would be consistent with the timescale of computational simulations discussed in the previous sections. For a detailed discussion of how genelet and enzyme concentrations shape circuit dynamics, we refer the reader to the work by Schaffter and coauthors[21].

Experimental Validation of Temporal Dose Inversion We generated a finite-duration stimulus for the genelets by manually adding DNA activator and a complementary DNA repressor for the input genelets.

The repressor displaces the activator due to the presence of a toehold, and turns the input genelets off, a reaction that equilibrates within minutes (Figure 3E, top). Thus, the time at which the DNA repressor is added determines the input duration, which we define as the time interval during which the two input genelets ($G_{in}C_{out}$ and $G_{in}C_r$) remain active. We measured the responses of the IFFL genelets to varying input durations (10, 20, 30, 40, 60, and $240\,\text{min}$). In Figure 3E we report the corresponding active fraction of one input genelet, of the intermediate repressor genelet, and of the output for the average of three experimental replicate (all the individual replicates are shown in Figure 12). We found that the active fraction of the intermediate repressor gene G_rR_{out} increased with longer input pulses, and persisted after the inputs were repressed. Consequently, the response of the output node $G_{out}S$ evolved from sustained to transient as the input duration increased. (A slight decay in the active fraction of $G_{in}C_{out}$ during this window arises from genelet auto-inhibition, as reported previously[21]).

In this experimental validation, we focus on the evaluation of the inverse dose-AUC (IDA) property, as AUC provides a more biologically relevant metric. To quantify the IDA property of the circuit, we evaluated the AUC of $G_{out}S$ response to varying input durations and input node concentrations, as shown in Figure 3F. The AUC of $G_{out}S$ (Figure 3F) was inversely correlated with both input duration and input node concentration, indicating that the genelet-based IFFL exhibits the IDA property.

The sustained activation of the output node in response to short input durations arises from the accumulation of a substantial amount of rC_{out} prior to the shutdown of the input nodes. This accumulated rC_{out} remains sufficient to sustain output activation over the timescale of the experiment, even in the presence of RNase H. In contrast, repression by rR_{out} is delayed because it requires the activation of G_rR_{out} and the accumulation of rR_{out} to a level sufficient to effectively repress the output node. Consequently, the circuit exhibits a regime in which activation persists before repression becomes dominant.

Around the transition from sustained to transient output (30 - $40\,\text{min}$), the standard deviation (indicated by the error bar) among three replicates was larger, probably reflecting increased sensitivity to experimental variations of concentration and activity of T7 RNA polymerase and RNase H, which is well-documented in the literature[45]. We also computationally confirmed that variations in enzymatic parameters affect the behavior of our circuit (the Supplemental Figure 14). Overall, these experiments confirm that a genelet-based IFFL can realize the IDA property *in vitro*.

IDA critically depends on the speed and strength of activation and inhibition We experimentally characterized how key parameters affect the IDA property (Figure 3G and H). We varied three conditions: (i) the total concentration of $G_{in}C_r$, which determines the speed of the inhibition pathway; (ii) the toehold length of dA_{out}, which determines the binding strength between rR_{out} and dA_{out} (inhibition), and (iii) the toehold length of dB_{out}, which determines the binding strength between rC_{out} and dB_{out} (activation). Varying these conditions enables us to explore how temporal dose inversion depends on the relative speed and strength of activation and inhibition pathways. These individual parameter variations monotonically changed AUC, which eventually eliminated the IDA property, showing that balanced activation and inhibition strength are essential.

A complete mathematical model of the genelet-based IFFL (Supplemental Information), fitted to the data, generally reproduces experimental observations (dashed lines in Figure 3 E, F, H). The model includes 32 variables, indicating that while the system's behavior is predictable, it is also much more complex than what is depicted in the schematic.

3   Temporal Dose Inversion In Signaling and Regulatory Networks

We next ask whether temporal dose inversion arises from specific biological mechanisms or instead solely from network topology. We consider more detailed IFFL and NFL models based on enzymatic signaling and gene regulatory networks (GRNs). In the enzymatic signaling models, the input U represents a transient upstream signal or kinase activity, whereas in gene regulatory networks it represents transient transcription factor availability. These two models capture distinct biological mechanisms of activation and inhibition: direct post-translational regulation versus transcriptional regulation. Comparing these two models allows us to test whether temporal dose inversion depends on specific biochemical implementation or instead arise from the underlying IFFL topology. Although real signaling dynamics are not strictly

Figure 3: A genelet-based incoherent feedforward loop (IFFL) exhibits the inverse dose-AUC (IDA) property. (A) Schematic of a genelet, in which the T7 promoter (domain in yellow) has a nick on the template strand. The non-template strand of the genelet has a fluorophore (F) on its 5' end, and dA has a quencher (Q) on its 3' end. (B) Genelet regulation through toehold-mediated strand displacement. The DNA activator (dA) has a toehold domain that enables its displacement by an RNA repressor (rR), repressing transcription from the genelet. Transcription can also be prevented in the presence of a DNA blocker (dB) due to the incomplete T7 promoter. The DNA blocker also has a toehold domain, which enables its removal by an RNA coactivator (rC). (C) We represent genelet networks with nodes (genelets) interconnected by arcs (regulatory interactions). Each genelet node is depicted by a circle separated into two parts: the left half shows the input domain, and the right half shows the output domain. Arcs are represented with the symbol "→" when associated with an RNA coactivator, and with "⊣" if the associated signal is a repressor. (D) Schematic of our genelet-based incoherent feedforward loop (IFFL). The input is received by two separate genelets ($\mathrm{G_{in}C_{out}}$ and $\mathrm{G_{in}C_r}$) with the same activation domain. Transcription from the input nodes is turned on by a single DNA activator ($\mathrm{dA_{in}}$), and repressed by a single DNA repressor ($\mathrm{dR_{in}}$). Not shown in this schematic is one additional genelet, G1I1, at very low concentration ($1\,\mathrm{nM}$), which suppresses the transcription leakage of $\mathrm{G_rR_{out}}$. Genelets meant to be activated by RNA coactivators are initially in blocked states. A fully-detailed schematic of the system is provided in the Supplemental Information (Figure4). (E) Responses of the genelet IFFL to varying input durations. The three graphs display normalized active levels of the three genelets: $\mathrm{G_{in}C_{out}}$ (top), $\mathrm{G_rR_{out}}$ (middle), and $\mathrm{G_{out}S}$ (bottom) responding to to six different input durations (10, 20, 30, 40, 60, and 240 min). Each plot shows the result of a single replicate. Additional replicates are shown in the Supplemental Figure 12. $\mathrm{G_{in}C_{out}}$ and $\mathrm{G_{in}C_r}$ are initially in ON state, and T7 RNA polymerase is added at $t = 0$ to initiate the circuit operation. The active levels of $\mathrm{G_{in}C_{out}}$ and $\mathrm{G_{in}C_r}$ are shaped into pulses by adding $\mathrm{dR_{in}}$ at specific time points (indicated by "↓"), which determine the pulse durations (only $\mathrm{G_{in}C_{out}}$ is monitored). (F) Areas under the curves of the circuit responses depend on the input durations and input node concentrations. AUC of $\mathrm{G_{out}S}$ versus input duration (top) and AUC of $\mathrm{G_{out}S}$ versus input node concentrations (bottom). Panel F (top) was generated from the trajectories shown in (E) and additional replicates shown in the Supplemental Information, while Panel F (bottom) was generated from the trajectories shown in the Supplemental Figure 12 and 13. Throughout the experiments we maintained a ratio of $[\mathrm{G_{in}C_{out}}]$ to $[\mathrm{G_{in}C_r}]$ equal to five. Thus, in Panel F (bottom), $[\mathrm{G_{in}C_r}]$ also varies accordingly. For each data point, we visualize the mean ± standard deviation ($n = 3$). (G, H) The IDA behavior of the circuit was modulated by varying (i) $[\mathrm{G_rR_{out}}]$, (ii) the binding rate of rR_{out}, and (iii) the binding rate of rC_{out}. (G) shows a schematic indicating where these parameters act in the circuit. (H) shows AUC of $\mathrm{G_{out}S}$ versus input duration.

rectangular, approximating transient inputs as finite-duration pulses is effective in capturing temporal dose $_{290}$
inversion, which depends primarily on nonlinear dynamics and time-integrated features rather than the $_{291}$
precise input shape. $_{292}$

Our signaling model for the IFFL is based on the work by Gerardin et al.[46]: $_{293}$

$$\dot{x}(t) = \alpha_x \frac{u(t)[1-x(t)]}{K_{M,ux} + u(t) + [1-x(t)]} - \gamma_x \frac{p_x x(t)}{K_{M,px} + p_x + x(t)}, \tag{9}$$

$$\dot{y}(t) = \alpha_y \frac{u(t)[1-y(t)]}{K_{M,uy} + u(t) + [1-y(t)]} - \beta_y \frac{x(t)y(t)}{K_{M,xy} + x(t) + y(t)} - \gamma_y \frac{p_y}{K_{M,py} + p_y + y(t)}. \tag{10}$$

All reactions assume enzymatic signaling and involve two species, X and Y, and one input, U. Each $_{294}$
species is either in an active or inactive state. Activation and deactivation are scaled by reaction param- $_{295}$
eters α and β; K_M parameters are Michaelis-Menten constants; p_x and p_y are the concentrations of two $_{296}$
basal deactivators, while γ_x and γ_y are the corresponding deactivation rate constants. Subscripts indicate $_{297}$
the species associated with a particular parameter: for example, α_x is the activation rate constant of X $_{298}$
and $K_{M,xy}$ is the Michaelis-Menten constant of enzyme X acting on substrate Y. To simplify the model, $_{299}$
we assume that the total concentration of each species is conserved and normalized to 1. Further, we $_{300}$
assume total quasi-steady-state approximation (tQSSA), which is valid for a wider range of parameter $_{301}$
spaces than the conventional QSSA[47]. $_{302}$

The gene regulatory network (GRN) model of the IFFL is as follows: $_{303}$

$$\dot{x}(t) = \delta_x \frac{[u(t)/K_{D,ux}]^{h_{ux}}}{1 + [u(t)/K_{D,ux}]^{h_{ux}}} - \epsilon_x x(t) \tag{11}$$

$$\dot{y}(t) = \delta_y \frac{[u(t)/K_{D,uy}]^{h_{uy}}}{1 + [u(t)/K_{D,uy}]^{h_{uy}} + [x(t)/K_{D,xy}]^{h_{xy}}} - \epsilon_y y(t) \tag{12}$$

where x and y denote concentrations of proteins (transcription factors). Parameters δ are maximal activa- $_{304}$
tion rates, while rate constants ϵ are associated with protein dilution/degradation. K_D is the dissociation $_{305}$
constant and h is the Hill coefficient of a transcription factor from its target promoter. $_{306}$

The NFL models based on enzymatic signaling and gene regulatory networks are reported in the $_{307}$
STAR Methods 4. $_{308}$

We evaluate the likelihood of the IDD or IDA properties of these four models in response to a rect- $_{309}$
angular input function as in Equation 5, with a constant amplitude ($u_0 = 0.01$ for the signaling model, $_{310}$
and $u_0 = 1$ for the GRN model), and varying duration D_{in}, assuming zero initial conditions. We examine $_{311}$
10000 parameter sets randomly sampled from a log uniform distribution (STAR Methods 4, reported in $_{312}$
Table 4), and we count the sets for which the system exhibits IDD or IDA. $_{313}$

We find that the emergence of temporal dose inversion depends on both biological mechanism and $_{314}$
network topology. Signaling models exhibit higher IDD and IDA scores when compared to the GRN $_{315}$
models, suggesting a strong dependence on mechanism (Figure 4). At the same time, the IDA property is $_{316}$
consistently observed more frequently in the IFFL than in the NFL across both model classes, indicating $_{317}$
a dependence on topology. The signaling IFFL model exhibits a particularly high likelihood of achieving $_{318}$
large IDA scores, likely due to the independent activation and inhibition pathways inherent to the IFFL $_{319}$
motif. Note that a large fraction of parameter sets with positive IDD scores does not necessarily imply $_{320}$
robust IDD behavior, as strong IDD (e.g., $S_{IDD} > 0.1$) is less prevalent and depends on the range of input $_{321}$
durations. Therefore, these fractions should not directly be interpreted as a probability of robust temporal $_{322}$
dose inversion. $_{323}$

IDD and IDA scores of the GRN models are consistently low (below 0.1, marked as a dashed line) when $_{324}$
compared to signaling models. A possible explanation is that the GRN inhibitory interaction reduces the $_{325}$
production rate of the output species, rather than eliminating the output species; in addition, the output $_{326}$
decay does not depend on X. Another possible reason is that our model does not capture delays that may $_{327}$
occur during translation. If we allow additional intermediate nodes to introduce additional time delay in the $_{328}$
GRN model, the IDD and IDA properties can be achieved (Figure S 9).These observations suggest that, $_{329}$
within the simplified GRN framework considered here, transcriptional gene regulation alone is less likely $_{330}$
to realize temporal dose inversion without additional protein–protein interactions or explicit time delays. $_{331}$

In the Supplement, Figure 15, we explore two additional signaling circuits, one that combines the IFFL and NFL topology (hereinafter, referred to as IFFL+NFL), and one that includes an antithetic integral feedback controller[40,48]. The IFFL+NFL circuit exhibits an intermediate behavior between the IFFL and NFL, suggesting that combining these two motifs does not produce a synergistic effect in terms of temporal dose inversion. The circuit with the antithetic integral feedback controller exhibits temporal dose inversion with a frequency comparable to that of the IFFL. Investigating the relationship between temporal dose inversion and adaptation in circuits with antithetic integral feedback would be an interesting direction for future work, although it is beyond the scope of the present study.

Figure 4: The IDA property is more likely to emerge in the IFFL motif. Histograms of IDD and IDA scores for 10000 randomly-chosen parameter sets. Each parameter is chosen from a log-uniform distribution in the interval specified in STAR Methods 4. For the IFFL signaling model, (A) IDD score histogram and (C) IDA score histogram. For the NFL signaling model, (B) IDD score histogram and (C) IDA score histogram. (E, F) IDD score histograms of gene regulatory model of the (E) IFFL and (F) NFL; IDA scores for these circuits are not shown because a negligible number of parameter sets present a positive score.

4 Signal Amplification and Time Delay Enable Temporal Dose Inversion in Generalized IFFLs

Given that IFFL models show the IDA property more frequently than NFL models, we examine generalized IFFL architectures with varying pathway lengths to assess whether temporal dose inversion depends on topological parameters, seeking to extract design principles to achieve IDA (the analysis can be readily extended to IDD using the same methods). Our generalized IFFL model is:

$$\dot{x}_1(t) = \alpha_{x_1} \frac{u(t)[1-x_1(t)]}{K_{M,ux} + u(t) + [1-x_1(t)]} - \gamma_{x_1} \frac{p_{x_1} x_1(t)}{K_{M,px} + p_{x_1} + x_1(t)} \tag{13}$$

$$\dot{y}_1(t) = \alpha_{y_1} \frac{u(t)[1-y_1(t)]}{K_{M,uy} + u(t) + [1-y_1(t)]} - \gamma_{y_1} \frac{p_{y_1} y_1(t)}{K_{M,py} + p_{y_1} + y_1(t)} \tag{14}$$

$$\dot{x}_i(t) = \alpha_{x_i} \frac{x_{i-1}(t)[1-x_i(t)]}{K_{M,x_i} + x_{i-1}(t) + [1-x_i(t)]} - \gamma_{x_i} \frac{p_{x_i} x_i(t)}{K_{M,px_i} + p_{x_i} + x_i(t)} \quad (i = 2,3,...,m) \tag{15}$$

$$\dot{y}_j(t) = \alpha_{y_j} \frac{y_{j-1}(t)[1-y_j(t)]}{K_{M,y_j} + y_{j-1}(t) + [1-y_j(t)]} - \gamma_{y_j} \frac{p_{y_j} y_j(t)}{K_{M,py_j} + p_{y_j} + y_j(t)} \quad (j = 2,3,...,n) \tag{16}$$

$$\dot{z}(t) = \alpha_z \frac{x_m(t)[1-z(t)]}{K_{M,xz} + x_m(t) + [1-z(t)]} - \beta_z \frac{y_n(t)z(t)}{K_{M,yz} + y_n(t) + z(t)} - \gamma_z \frac{p_z z(t)}{K_{M,pz} + p_z + z(t)} \tag{17}$$

Parameters are labeled consistently with the IFFL signaling model in the previous section, and we introduce a variable pathway length defined by n and m. Species X_i ($i = 1,...,m$) are in the activation pathway, and Y_i ($i = 1,...,n$) are in the inhibition pathway. Node Z is the output node, activated by X_m

and inhibited by Y_n. To simplify the analysis, we assume $\alpha_{x_i} = \alpha_x$ for all i, and $\alpha_{y_j} = \alpha_y$ for all j. The initial conditions of all variables are set to zero.

We investigate the dependence of IDA on the pathway length by varying m, n) and pathway strength by changing α_x, α_y, α_z and β_z (Figure 5).

First, we fix α_z and β_z and consider three different parameter sets of γ_{y_j} ($j \in \{1, 2, \ldots, n\}$) (Figure 5A to C). For $\gamma_{y_j} = 1$, $m < n$ results in a higher IDA score because short input durations D_{in} activate the output more quickly than they inhibit it (Figure 5A). However, increasing the inhibition pathway length n is not always advantageous. For example, when $a_y = 2$, the inhibition pathway amplifies the signal, so longer pathways strengthen inhibition relative to activation regardless of D_{in}. In this regime, the IDA score decreases once n exceeds a threshold (e.g., $n = 4$ when $m = 1$). Thus, strong inhibition leads to an optimal inhibition pathway length for a given activation pathway.

When $\gamma_{y_j} = 0.1$ for all $j \in \{1, 2, \ldots, n\}$, the decay dynamics of the inhibitory pathway are slower, resulting in more sustained inhibition (Figure 5C). As a result, the IDA score becomes negligible for long pathways ($n \geq 2$). Because inhibition is already strong, the cases $a_y = 1$ and $a_y = 2$ show little difference. Thus, as in the case $a_y = 2$ in Figure 5A, excessively strong inhibition makes long inhibitory pathways unfavorable. When $a_x = 2$, the optimal activation pathway length is $m = 3$ (Figure 5C).

This non-monotonic trend arises from the balance between activation and inhibition strengths (Supplemental Figure 7). For long inputs, increasing m mainly extends the output duration with little change in amplitude. For short inputs, increasing m initially increases both amplitude and duration, but the response saturates at $m = 3$, after which further increases only prolong the output. Consequently, $m = 3$ yields the highest IDA score.

The previous cases show that comparable activation and inhibition intensities promote higher IDA scores (Figure 5A and 5C). If activation is too strong, both small and large D_{in} produce long, high-amplitude outputs, lowering the IDA score. If inhibition is too strong, both small and large D_{in} values produce outputs with small AUC, which also reduces the IDA score. When activation and inhibition are more balanced, a more complex pattern emerges, as when $\gamma_{y_1} = 0.1$, $\gamma_{y_j} = 1$ for $j \in \{2, \ldots, n\}$ (Figure 5B), representing an intermediate case between Figures 5A and 5C.

Figure 5D and E show two circuits with different combinations of γ_j ($j = 1, \ldots, n$), each evaluated with four sets of (α_z, β_z) (additional cases are shown in Supplemental Figure 10). Comparing $\alpha_z = 10$ (top row) and $\alpha_z = 100$ (bottom row), the latter produces broader regions with high IDA scores, indicating that a high IDA score requires rapid activation of the output node over a relatively short input duration D_{in}. Among the four β_z values, $\beta_z = 1, 10$ yield high IDA scores for cases (E), whereas case (D) favors $\beta_z = 10, 100$. Overall, these results highlight the need for a balanced strength between activation and inhibition pathways to obtain the IDA property.

Finally, Figure 5F–I present simulations with a parameter set yielding high IDA and IDD scores ($S_{IDA} = 7.1$, $S_{IDD} = 17.8$). The parameters, listed in the figure caption, were obtained through random search and are not necessarily optimal. When $D_{in} = 1$ min, X_2 activates rapidly while Y_3 remains weak, producing a long-lasting, high-amplitude output. In contrast, when $D_{in} = 20$ min, both X_2 and Y_3 activate strongly, generating a pulse with slightly lower amplitude and much shorter duration. A similar response occurs for an even longer input ($D_{in} = 100$ min; Supplemental Figure 8). These results suggest that the IFFL acts as a dose filter, selectively responding to transient signals or producing distinct outputs for pulsatile versus sustained inputs[13–17].

Strictly speaking, the circuit in Figure 5F is a band-pass filter, in the sense that AUC as a function of D_{in} attains a maximum between $D_{in} = 0$ and $D_{in} = 1$, because the circuit does not produce any output if $D_{in} = 0$ (i.e., if there is no input signal). When the input amplitude u_0 is varied instead of D_{in}, $AUC(u_0)$ and $D_{out}(u_0)$ behave analogously to $AUC(D_{in})$ and $D_{out}(D_{in})$ ((the Supplemental Figure 8). Therefore, this circuit behaves as a band-pass filter with respect to both D_{in} and u_0. This observation is consistent with previous studies reporting that the IFFL circuit can implement a band-pass function and thus detect a certain range of the input dose by producing a larger steady-state response for a certain dose range of a sustained input[14,32,33,49,50].

Figure 5: Generalized IFFL circuits show that temporal dose inversion depends on the relative strength of activation and inhibition pathways. (A to C) Each panel shows the circuit diagram of a generalized IFFL network, along with heat maps of IDA scores S_{IDA} in the m-n plane for different values of α_x and α_y, reported above each heat map. The basal deactivation rates are reported next to each node in the circuit diagram: in all three cases, $\gamma_{x_i} = 1$ for all $i = 1, \ldots, m$, and moreover (A) $\gamma_{y_j} = 1$ for all $j = 1, \ldots, n$; (B) $\gamma_{y_1} = 0.1$, and $\gamma_{y_j} = 1$ for $j = 2, \ldots, n$; (C) $\gamma_{y_j} = 0.1$ for all $j = 1, \ldots, n$. Other parameters are kept constant at their nominal values listed in Table 1. The input amplitude is set at $u_0 = 0.1$; D_{in} is logarithmically varied from $D_{in} = 0.1$ to $D_{in} = 10$. (D, E) Similarly, heat maps of IDA scores S_{IDA} in the m-n plane are shown for different values of α_z and β, reported above each heat map. (F to I) An example of a circuit with a remarkably high IDA score. (F) Circuit diagram of a generalized IFFL network with $m = 2$ and $n = 3$. (G to I) Time evolution of the output responses of the circuit shown in (F) to input pulses of $u_0 = 0.005$ with two different input durations: $D_{in} = 1$ min (left), and $D_{in} = 20$ min (right). Parameter values are listed in Table 3. (H,I) Plots of AUC as a function of D_{in} (H) and D_{out} (I) as a function of D_{in} obtained from numerical simulations for the circuit shown in (F). D_{in} was linearly increased from 0 to 20 minutes with steps of 0.25 min. Note that $D_{out}(D_{in} = 0)$ is not included in the plot (G) because $D_{in} = 0$ gives $y(t) = 0$, with which D_{out} cannot be calculated by Equation 42. When not varied, the parameters are kept constant at their nominal values listed in Table 1, 2 and 3

DISCUSSION

We showed that adaptive biomolecular circuits can invert the temporal dose of input signals, producing sustained responses to transient inputs and transient responses to sustained inputs. Analyzing incoherent feedforward loop (IFFL) and negative feedback loop (NFL) motifs, we distinguish two forms of temporal dose inversion: inverse dose duration (IDD) and inverse dose AUC (IDA). While both motifs readily exhibit IDD, IDA arises more frequently in the IFFL due to topology: its activation and inhibition pathways can be tuned independently, enabling low-dose inputs to activate the output without strongly triggering inhibition. In contrast, the NFL couples inhibition to output activation through feedback, limiting such selective responses. Cell-free experiments with a genelet-based IFFL demonstrated IDA behavior. Extending our computational analysis to a broader class of IFFL circuits revealed design rules for temporal dose inversion based on the relative strength of activation and inhibition pathways, and inhibition delay. This insight is consistent with our cell-free experimental findings: changing parameters that modulate output activation and inhibition has a dramatic effect on IDA. Together, these results indicate that temporal dose inversion is a general property of adaptive architectures determined primarily by network topology, while also depending on underlying biochemical implementations and parameter values. Our experimental demonstration uses a genelet-based IFFL[21], but other programmable *in vitro* platforms, such as the polymerase-exonuclease-nickase (PEN) toolbox[51] and cell-free gene networks[52], could be adopted for the same purpose. Such components could expand synthetic signaling systems capable of processing and decoding pulsatile inputs[50,53,54].

Our finding that the IFFL motif acts as a dose filter aligns with several studies suggesting its capacity to detect pulsatile signals[13–17]. However, prior work did not systematically examine how dose–response inversion arises or how it enables pulse detection. Moreover, pulse detection principles outlined in previous work differ from those we identified here. For example, Lormeau et al.[15] detected single pulses using an interlocked IFFL, and Benzinger et al.[14] detected pulse trains with a diamond-shaped IFFL. Both rely on falling-edge detection: while the input is present, the output remains minimal because activation and inhibition are triggered simultaneously; once the input disappears, the output increases as the activation signal decays more slowly. In contrast, in our mechanism the output rises immediately after input onset and decays once the inhibition pathway dominates. Because triggering the inhibition pathway requires a sufficient input dose, shorter or weaker inputs stimulate the output more effectively, producing dose filtering through temporal dose inversion. A related strategy was proposed for pulse-train detection in[17], although that model relied on an extremely high Hill coefficient, limiting its biological realism.

The ability of IFFL motifs to generate temporal dose inversion relates to their well-known band-pass filtering properties[32,33,50,55], where independently tuned activation and inhibition thresholds restrict responses to a defined input range. In contrast, temporal dose inversion evaluates dose through time-dependent input features. Our simulations reveal a "duality" between input duration and amplitude (Figure 2D): temporal dose inversion emerges both when duration varies at constant amplitude, and when amplitude varies at constant duration. Accordingly, dose filtering can be interpreted as duration filtering or amplitude filtering when one input dimension is held constant. This duality may underlie the broad utility of IFFL motifs, including circuits that detect regions where molecule concentrations fall within a specific range leading to spatial patterning in bacteria[32] and mammalian cells[33].

The concept of temporal dose inversion may help describe and interpret behaviors associated with temporal coding in natural living systems[4,56]. For example, tumor necrosis factor (TNF)-induced NF-κB signaling exhibits responses that depend on the temporal properties of TNF pulses. First, TNF stimulates both the pro-apoptotic caspase pathway and the pro-survival NF-κB-driven gene transcription pathway, which in turn inhibits some steps in the pro-apoptotic caspase signaling, leading to a topology consistent with the IFFL motif. Lee et al.[57] reported that a 1-min TNF pulse induces apoptosis more effectively than a 1-hour TNF pulse. This behavior may be related to temporal dose inversion. More broadly, cells interpret multiple temporal features of inputs, such as amplitude, duration, and frequency[3]. Exploring temporal dose inversion across various input features may provide insights into how biological systems decode temporally varying signals.

Temporal dose inversion circuits could expand and simplify the combinatorial recognition of multiple temporal features of a signal, similar to strategies observed in living systems. For example, Benzinger

et al.[14] demonstrated pulse-train signal processing based on the amplitude and duty cycle using two readouts. Temporal dose-response may simplify the design of circuits that detect duty cycle or perform complex temporal signal processing. Libraries of circuits for temporal coding and detection may expand our knowledge of molecular communication, with potential relevance for diagnostics[58], therapeutics[59], and material development[60].

Supplemental information

Linear systems do not exhibit temporal dose inversion

We consider causal linear time invariant systems with input $u(t)$ and state/output $y(t)$, characterized by a non-negative impulse response function $h(t)$. This class of systems is relevant to our study, because any physically plausible biological model must present non-negative variables at all times.
Assume $y(0) = 0$ and $u(t) = 0$ for $t < 0$. The forced response of this type of system is:

$$y(t) = \int_0^t h(t - \tau)u(\tau)d\tau.$$

Consider a finite-duration step input $u_T(t)$:

$$u_T(t) = \begin{cases} 1 & 0 \leq t < T, \\ 0 & \text{otherwise.} \end{cases}$$

The response to the step input with $u(t) = 0$ for $t < 0$ and $u(t) = 1$ for $t \geq 0$ is

$$S(t) = \int_0^t h(\tau)d\tau$$

and it is non-decreasing, because h is non-negative.
Input u_T can be seen as the difference between the unit step at zero ($u(t) = 0$ for $t < 0$ and $u(t) = 1$ for $t \geq 0$) and the unit step at T ($u(t) = 0$ for $t < T$ and $u(t) = 1$ for $t \geq T$). In view of linearity, the response to the difference of the two signals is difference of the responses to the two signals:

$$y_T(t) = S(t) - S(t - T);$$

note that, for $t < T$, we have $y_T(t) = S(t)$.
Now, consider two inputs u_{T_1} and u_{T_2}, with $T_1 < T_2$. Since S is non-decreasing, we have that $S(t - T_1) \geq S(t - T_2)$. Hence

$$y_{T_1}(t) = S(t) - S(t - T_1) \leq S(t) - S(t - T_2) = y_{T_2}(t)$$

This means that the magnitude of the response $y(t)$ scales with the duration of the input signal. In other words, this kind of system does not admit temporal dose inversion.

Figure 6: Evaluating the influence of individual parameter variations on the temporal response of the IFFL and NFL circuits. Temporal responses of (A) the IFFL and of (B) the NFL circuit to a rectangular input with amplitude $u_0 = 1$ when $D_{in} = 0.1$ (left) and when $D_{in} = 1$ (right). The values of varying parameters are indicated in the legends. All other parameters are kept constant at their nominal value $a = 2$, $b = 20$, $c = 0.1$, $p = 2$.

Figure 7: Dynamics of the circuit associated with the model in Equations 13-17 with different combinations of (m, n). (A) Behaviour of the circuit in Figure 5A, having $\gamma_{y_j} = 1$ for all j, with $m = 1$ and different values of n. (B) Behaviour of the circuit in Figure 5C, having $\gamma_{y_j} = 0.1$ for all j, with $n = 1$ and different values of m.

Figure 8: Details of the signaling IFFL circuit shown in Figure 5F to I. (A) Diagram of the signaling IFFL circuit. The circuit has the parameters listed in Table 3. (B) Dynamics of each node with $D_{in} = 1\,\text{min}$ (left), $D_{in} = 20\,\text{min}$ (center) and $D_{in} = 100\,\text{min}$ (right). (C) Output duration and AUC as a function of D_{in} with $u_0 = 0.005$. (D) Dynamics of each node with $u = 0.005\,\mu\text{Mmin}^{-1}$ (left), $u = 0.1\,\mu\text{Mmin}^{-1}$ min (center) and $u = 0.5\,\mu\text{Mmin}^{-1}$ (right). (E) Output duration and AUC as a function of u with $D = 1\,\text{min}$

A GRN circuit showing the IDA property

Figure 9: A GRN IFFL circuit showing the IDA property; the mathematical model is described in STAR Methods 4. (A) Diagram of the GRN IFFL circuit. (B) Dynamics of each node with $D_{in} = 4$ min (left) and $D_{in} = 80$ min (right). The input amplitude was kept at $u_0 = 0.5$ (C) AUC as a function of D_{in}. Parameter values are listed in Table 4.

Activation and inhibition rates on the output node affects IDA property

In the main text, we evaluated how the parameters of node X_i $(i = 1, ..., m)$ and Y_j $(i = 1, ..., n)$ affect the IDA property of generalized IFFL circuits. Here, we see how the parameters of the output node Z affect the IDA property of the same circuit motifs. Figure 10 shows three cases (different combinations of γ_j $(j = 1, ..., n)$) as evaluated in Section 4. For each case, eight different sets of (α_z, β_z) are evaluated. When we compare $\alpha_z = 10$ (top row) and $\alpha_z = 100$ (bottom row) for each case, $\alpha_z = 100$ gives broader areas with high IDA score for all the cases. These results suggest that, for obtaining a high IDA score, the output node has to be quickly activated during a relatively shorter period with a smaller D_{in}. Among four different values of β_z, $\beta_z = 1, 10$ give high IDA scores for case (B) and (C), while case (A) prefers $\beta_z = 10, 100$. These results supports the argument that relative balance of the activation and inhibition determines the IDA property, which was stated in the main text.

Figure 10: Parameters of the output node Z affects the IDA property of the generalized IFFL circuits. (A to C) Each panel shows the circuit diagram of a generalized IFFL network, along with heat maps of IDA scores S_{IDA} in the m-n plane for different values of α_z and β_z, reported above each heat map. The basal deactivation rates are reported next to each node in the circuit diagram: in all three cases, $\gamma_{x_i} = 1$ for all $i = 1, \ldots, m$, and moreover (A) $\gamma_{y_j} = 1$ for all $j = 1, \ldots, n$; (B) $\gamma_{y_1} = 0.1$, and $\gamma_{y_j} = 1$ for $j = 2, \ldots, n$; (C) $\gamma_{y_j} = 0.1$ for all $j = 1, \ldots, n$. When not varied, the parameters are kept constant at their nominal values: $\alpha_x = 1$, $\alpha_y = 1$, $\gamma_z = 0.1$, $K_{M,x} = K_{M,y} = K_{M,z} = 1.0$, $p_x = p_y = 1.0$, $p_z = 0.2$, $u_0 = 0.1$; D_{in} is logarithmically varied from $D_{in} = 0.1$ to $D_{in} = 10$.

Detailed architecture of the genelet-based IFFL circuit

Our genelet-based IFFL is derived from the design originally developed by Schaffter and coworkers[21]. We modified their design by incorporating an additional genelet, $G_{out}I_{out}$, at a low conentration ($1\,\mathrm{nM}$) to suppress the effect of transcription leakage from G_rR_{out}, adjusting component concentrations to reinforce the temporal dose inversion, and employing a different set of input genelet nodes to enable sharper ON/OFF switching. In the original genelet notation of Schaffter et al., the genelets $G_{in}C_{out}$, $G_{in}C_r$, G_rR_{out}, $G_{out}I_{out}$, $G_{out}S$ in our implementation correspond to $G8C1$, $G8C3$, $G3R1$, $G1I1$, $G1S$, respectively. A detailed schematic of the resulting circuit architecture is shown in the Supplemental Figure 11.

Figure 11: A detailed schematic of the genelet-based IFFL circuit. Each genelet node is depicted either as a circle (input and intermediate nodes: $G_{in}C_{out}$ or $G_{in}C_r$, G_rR_{out}) or as a rounded rectangle (output node: $G_{out}S$). Genelets are switched ON (red arrows) or OFF (blue arrows) mediated by RNA coactivators or repressors respectively, which are indicated by colored circles. Single-stranded DNA species are indicated by gray rounded rectangles.

Complete experimental dataset of genelet IFFL experiments

All the replicates for the genelet IFFL experiments with varying input durations are shown in the Supple- 496
mental Figure 12. We have conducted separate experiments to measure responses of the genelet-based 497
IFFL circuit to six different input durations: $10, 20, 30, 40, 60, 240$ min. For each input duration, we obtained 498
three replicates to evaluate the variance of the experiment. 499

Figure 12: All the replicates of the genelet IFFL experiments with varying input durations. We have separate experiments for six different input durations: $10, 20, 30, 40, 60, 240$ min. Experiments for each input duration have three replicates, and the active fractions of $G_{in}C_{out}$, G_rR_{out}, and $G_{out}S$ are shown for each replicate.

All the replicates for the genelet IFFL experiments with varying input genelet concentrations are shown 500
in the Supplemental Figure 13. We have conducted separate experiments for three different sets of 501
$[G_{in}C_{out}]$ / $[G_{in}C_r]$: $10\,nM$ / $2\,nM$, $25\,nM$ / $5\,nM$, $50\,nM$ / $10\,nM$. The input duration was fixed at $30\,min$. For 502
each input concentration, we obtained three replicates to evaluate the variance of the experiment. 503

For both experiments, the variation of $G_{out}S$ active level is correlated with the variation of G_rR_{out} active 504
level; the higher active fraction of G_rR_{out} is, the lower the active fraction of $G_{out}S$. The variation of G_rR_{out} 505
is most likely due to the fluctuation of enzyme concentrations and activities. 506

Figure 13: All the replicates of the genelet IFFL experiments with varying input genelet concentrations. We have separate experiments for three different sets of $[G_{in}C_{out}]/[G_{in}C_r]$: 10 nM / 2 nM, 25 nM / 5 nM, 50 nM / 10 nM. Experiments for each input genelet concentrations have three replicates, and the active fractions of $G_{in}C_{out}$, G_rR_{out}, and $G_{out}S$ are shown for each replicate.

A mathematical model of the genelet IFFL

Here we describe the detailed mathematical model of the genelet IFFL that we designed for the biological realization of the IDA property in Section 2. We use the following mathematical model for the genelet IFFL, which is exactly the same as the model established by Schaffter et al.[21]:

$$\frac{d[G_{in}C_{out}:dA_{in}]}{dt} = k_{GA}[G_{in}C_{out}][dA_{in}] - k_{GAB}[G_{in}C_{out}:dA_{in}][dB_{in}]$$
$$- k_{GAR}[G_{in}C_{out}:dA_{in}][rR_{in}]$$
$$- k_{GAR,d}[G_{in}C_{out}:dA_{in}][dR_{in}]$$

$$\frac{d[G_{in}C_{out}:dB_{in}]}{dt} = k_{GB}[G_{in}C_{out}][dB_{in}] + k_{GAB}[G_{in}C_{out}:dA_{in}][dB_{in}]$$
$$- k_{GBC}[G_{in}C_{out}:dB_{in}][rC_{in}]$$

$$\frac{d[G_{in}C_r:dA_{in}]}{dt} = k_{GA}[G_{in}C_r][dA_{in}] - k_{GAB}[G_{in}C_r:dA_{in}][dB_{in}]$$
$$- k_{GAR,d}[G_{in}C_r:dA_{in}][dR_{in}]$$

$$\frac{d[G_{in}C_r:dB_{in}]}{dt} = k_{GB}[G_{in}C_r][dB_{in}] + k_{GAB}[G_{in}C_r:dA_{in}][dB_{in}]$$
$$- k_{GBC}[G_{in}C_r:dB_{in}][rC_{in}]$$

$$\frac{d[G_rR_{out}:dA_r]}{dt} = k_{GA}[G_rR_{out}][dA_r] - k_{GAB}[G_rR_{out}:dA_r][dB_r]$$
$$- k_{GAR}[G_rR_{out}:dA_r][rR_r]$$

$$\frac{d[G_rR_{out}:dB_r]}{dt} = k_{GB}[G_rR_{out}][dB_r] + k_{GAB}[G_rR_{out}:dA_r][dB_r]$$
$$- k_{GBC}[G_rR_{out}:dB_r][rC_r]$$

$$\frac{d[G_{out}S:dA_{out}]}{dt} = k_{GA}[G_{out}S][dA_{out}] - k_{GAB}[G_{out}S:dA_{out}][dB_{out}]$$
$$- k_{GAR}[G_{out}S:dA_{out}][rR_{out}]$$

$$\frac{d[G_{out}S:dB_{out}]}{dt} = k_{GB}[G_{out}S][dB_{out}] + k_{GAB}[G_{out}S:dA_{out}][dB_{out}]$$
$$- k_{GBC}[G_{out}S:dB_{out}][rC_{out}]$$

$$\frac{d[dA_{in}]}{dt} = k_{DR}[dA_{in}:rR_{in}] - k_{GA}([G_{in}C_{out}] + [G_{in}C_r])[dA_{in}]$$
$$+ k_{GAB}([G_{in}C_{out}:dA_{in}] + [G_{in}C_r:dA_{in}])[dB_{in}]$$
$$- k_{AR}[dA_{in}]([rR_{in}] + [dR_{in}])$$

$$\frac{d[dA_r]}{dt} = k_{DR}[dA_r:rR_r] - k_{GA}[G_rR_{out}][dA_r] + k_{GAB}[G_rR_{out}:dA_r][dB_r]$$
$$- k_{AR}[dA_r][rR_r]$$

$$\frac{d[dA_{out}]}{dt} = k_{DR}[dA_{out}:rR_{out}] - k_{GA}[G_{out}S][dA_{out}] - k_{AR}[dA_{out}][rR_{out}]$$
$$+ k_{GAB}[G_{out}S:dA_{out}][dB_{out}]$$

$$\frac{d[dB_{in}]}{dt} = k_{DC}[dB_{in}:rC_{in}] - k_{GB}([G_{in}C_{out}] + [G_{in}C_r])[dB_{in}]$$
$$- k_{BC}[dB_{in}][rC_{in}] - k_{GAB}([G_{in}C_{out}:dA_{in}] + [G_{in}C_r:dA_{in}])[dB_{in}]$$

$$\frac{d[dB_r]}{dt} = k_{DC}[dB_r:rC_r] - k_{GB}[G_rR_{out}][dB_r] - k_{BC}[dB_r][rC_r]$$
$$- k_{GAB}[G_rR_{out}:dA_r][dB_r]$$

$$\frac{d[dB_{out}]}{dt} = k_{DC}[dB_{out}:rC_{out}] - k_{GB}[G_{out}S][dB_{out}] - k_{BC}[dB_{out}][rC_{out}]$$
$$- k_{GAB}[G_{out}S:dA_{out}][dB_{out}]$$

$$\frac{d[rC_{in}]}{dt} = k_{auto}[dA_{in}] - k_{GBC}([G_{in}C_{out}:dB_{in}] + [G_{in}C_r:dB_{in}])[rC_{in}]$$
$$- k_{BC}[dB_{in}][rC_{in}]$$

$$\frac{d[rC_r]}{dt} = k_{auto}[dA_r] + k_{PC}[G_{in}C_r:dA_{in}] - k_{GBC}[G_rR_{out}:dB_r][rC_r]$$
$$- k_{BC}[dB_r][rC_r] + k_{leak}[G_{in}C_r]$$

$$\frac{d[rC_{out}]}{dt} = k_{auto}[dA_{out}] + k_{PC}[G_{in}C_{out}:dA_{in}] - k_{GBC}[G_{out}S:dB_{out}][rC_{out}]$$
$$- k_{BC}[dB_r][rC_r] + k_{leak}[G_{in}C_{out}]$$

$$\frac{d[rR_{out}]}{dt} = k_{auto}[dB_{out}] + k_{PR}[G_rR_{out}:dA_r] - k_{GAR}[G_{out}S:dA_{out}][rR_{out}]$$
$$- k_{AR}[dB_{out}][rC_{out}] + k_{leak}[G_rR_{out}]$$

where k_{GA}, k_{GAB}, k_{GAR}, k_{GBC}, k_{AR}, k_{BC} are the binding constants between genelets and DNA activators, activated genelets and RNA repressors, blocked genelets and RNA coactivators, DNA activators and RNA repressors, DNA blockers and RNA coactivators respectively; $k_{GAR,d}$ is the binding constant between activated genelets and DNA repressor; k_{PC}, k_{PR} are the production rates of RNA coactivators and repressors respectively; k_{DC}, k_{DR} are the degradation rates of DNA-RNA complexes. Here we assume binding constants and rate constants are identical for all the genelet nodes; k_{auto} is the production rate of RNA repressor or coactivator from their corresponding DNA activator or DNA blocker. The produced RNAs cause auto-inhibition or auto-activation, which has been reported by Schaffter et al.[21]; k_{leak} is the production rate of RNA repressor or RNA coactivator from their corresponding genelets at OFF state or BLOCKED state.

We also have the following mass balance equations:

$$[G_{in}C_r] = [G_{in}C_r]_{tot} - [G_{in}C_r : dA_{in}] - [G_{in}C_r : dB_{in}]$$

$$[G_{in}C_{out}] = [G_{in}C_{out}]_{tot} - [G_{in}C_{out} : dA_{in}] - [G_{in}C_{out} : dB_{in}]$$

$$[G_rR_{out}] = [G_rR_{out}]_{tot} - [G_rR_{out} : dA_r] - [G_rR_{out} : dB_r]$$

$$[G_{out}S] = [G_{out}S]_{tot} - [G_{out}S : dA_{out}] - [G_{out}S : dB_{out}]$$

$$[dB_{in} : rC_{in}] = [dB_{in}]_{tot} - [dB_{in}] - [G_{in}C_{out} : dB_{in}] - [G_{in}C_r : dB_{in}]$$

$$[dB_r : rC_r] = [dB_r]_{tot} - [dB_r] - [G_rR_{out} : dB_r]$$

$$[dB_{out} : rC_{out}] = [dB_{out}]_{tot} - [dB_{out}] - [G_{out}S : dB_{out}]$$

$$[dA_{in} : rR_{in}] = [dA_{in}]_{tot} - [dA_{in}] - [G_{in}C_{out} : dA_{in}] - [G_{in}C_r : dA_{in}]$$

$$[dA_r : rR_r] = [dA_r]_{tot} - [dA_r] - [G_rR_{out} : dA_r]$$

$$[dA_{out} : rR_{out}] = [dA_{out}]_{tot} - [dA_{out}] - [G_{out}S : dA_{out}]$$

The parameter values fitted based on the experimental results are listed in Table 9,10, 11 and 12.

Sample-to-sample variability induced by enzymatic parameter fluctuations

We hypothesize that the experimental fluctuations observed in Figure 3 is primarily originated from pipetting variability specifically for enzyme solutions, as the enzyme solution contains a high concentration of glycerol, which alters its viscosity and wetting properties compared to aqueous buffers, making it more prone to pipetting variability. To support this hypothesis, we performed a Monte Carlo analysis in which enzymatic parameters were stochastically varied.

Specifically, we considered variability in two groups of kinetic parameters: (i) transcription-related parameters k_{pc}, k_{pr}, k_{pi} and (ii) RNA degradation-related parameters k_{dc}, k_{dr}. For each group, parameters are scaled by its common perturbation factor, which is associated with the pipetting fluctuation and batch-to-batch activity variation of T7 RNA polymerase and RNase H, which are independent of genelet nodes. We defined the perturbation factor as follows:

$$s = exp(\sigma Z), \quad Z \sim \mathcal{N}(0,1) \tag{18}$$

$$\sigma = \sqrt{\log(1 + CV^2)} \tag{19}$$

where σ is the standard deviation of the underlying normal distribution in log space, and CV is the coefficient of variation of the resulting perturbation factor s. CV was set to 0.1. All remaining parameters are fixed at the nominal parameter set (Table 6), and at the fitted circuit parameters (Table 9, 10, and 11). Input pulse durations of $10, 20, 30, 40, 60, 240\,\mathrm{min}$ were tested. For each Monte Carlo sample, the ODE model of the genelet-based IFFL was simulated for four hours, and the area under the curve (AUC) of $G_{out}S$ was computed from the obtained time evolution. For each input duration, 500 independent simulations were performed. The obtained results are shown in Figure 14. The simulated standard deviations are compared with those observed experimentally, supporting the hypothesis that the experimental fluctuation can be explained by the fluctuations of the enzymatic activity derived from pipetting and preparation variability.

Analysis of additional adaptive circuits

In the main text, our focus was on the IFFL and NFL. However, there are other types of adaptive circuit motifs. Here, we briefly evaluate two additional circuit motifs: IFFL combined with NFL (hereinafter, referred to as IFFL+NFL), and an antithetic integral feedback (Figure 15). Circuit motifs in real biological networks are often intertwined, which suggests evaluating combined circuit motifs[20,61]. Here, we only evaluate IFFL+NFL as a combined motif because it is the only circuit pattern of two circuit nodes (not including the input node) that has both IFFL and NFL motif. The ODE model of IFFL+NFL is defined as

Figure 14: Monte Carlo analysis quantifies the sample-to-sample variability of the output AUC of the genelet-based IFFL induced by the fluctuations in enzymatic parameters.

$$\dot{x}(t) = \alpha_{ux} \frac{u(t)[1 - x(t)]}{K_{M,ux} + u(t) + [1 - x(t)]} + \alpha_{yx} \frac{y(t)[1 - x(t)]}{K_{M,yx} + y(t) + [1 - x(t)]} - \gamma_x \frac{p_x x(t)}{K_{M,px} + p_x + x(t)} \tag{20}$$

$$\dot{y}(t) = \alpha_y \frac{u(t)[1 - y(t)]}{K_{M,uy} + u(t) + [1 - y(t)]} - \beta_y \frac{x(t)y(t)}{K_{M,xy} + x(t) + y(t)} - \gamma_y \frac{p_y}{K_{M,py} + p_y + y(t)} \tag{21}$$

In the parameter set evaluated here, IFFL+NFL showed an intermediate histogram between IFFL and NFL. We also evaluated the effect of an antithetic integral feedback. The antithetic integral feedback is a powerful controller that realizes a robust perfect adaptation. Even though it is still unclear how adaptation and the dose inversion properties are related, it is an intriguing question how the antithetic integral feedback affects the dose inversion properties. In the antithetic integral feedback controller, we introduce two additional species, z_1 and z_2, to regulate the system of interest. z_1 is constitutively produced at a constant rate μ, whereas the production of z_2 is activated by the inactive form of y with rate constant θ. Species z_1 and z_2 bind to each other to form an inactive complex. Both z_1 and z_2 are also subject to basal degradation. In this study, the antithetic integral feedback controller was applied only to the signaling model, because the binding reaction between z_1 and z_2 can be naturally interpreted as a protein-protein interaction. Although it is possible to combine gene regulation with the antithetic integral feedback controller, exploring such implementation is beyond the scope of this work. The ODE model of the antithetic integral feedback circuit is as follows:

$$\dot{y}(t) = \alpha_y \frac{u(t)[1 - y(t)]}{K_{M,uy} + u(t) + [1 - y(t)]} - \beta_y \frac{x(t)y(t)}{K_{M,xy} + x(t) + y(t)} - \gamma_y \frac{p_y}{K_{M,py} + p_y + y(t)} \tag{22}$$

$$\dot{z}_1(t) = \mu - \eta z_1 z_2 - \gamma_{z_1} z_1 \tag{23}$$

$$\dot{z}_2(t) = \theta(1 - y) - \eta z_1 z_2 - \gamma_{z_2} z_2 \tag{24}$$

Figure 15: Histograms showing the occurrence of positive IDD and IDA scores in the IFFL+NFL circuit and the antithetic integral feedback circuit. The selected input amplitudes are $u = 0.01$ for the signaling IFFL+NFL, $u = 1$ for the GRN IFFL+NFL, and $u = 0.01$ for the antithetic integral feedback.

The occurrence of temporal dose inversion properties depends on input amplitude

Figure 16 shows a complete set of histograms of IDD and IDA scores obtained by the random parameter sampling for the signaling and the GRN models of the IFFL and NFL.

Figure 16: Histograms showing the fraction of parameter sets with positive IDD or IDA scores for the signaling and gene regulatory network (GRN) models of IFFL and NFL at different input amplitudes.

Figure 17: Histograms showing the fraction of parameter sets with positive IDD or IDA scores for the signaling and gene regulatory network (GRN) models of IFFL+NFL and the signaling model of the antithetic integral feedback circuit at different input amplitudes.

Acknowledgments

E.N. and E.F acknowledge support from National Science Foundation through award NSF-CCF 2107483. F.B. and G.G. have been partly supported by the European Union through the Next Generation EU, Mission 4, Component 2, PRIN 2022 grant PRIDE (project number 2022LP77J4, CUP E53D2300072000); G.G. also acknowledges support from the European Union through the ERC INSPIRE grant (project number 101076926); views and opinions expressed are however those of the authors only and do not necessarily reflect those of the European Union, the European Research Council Executive Agency or the European Council; neither the European Union nor the granting authority can be held responsible for them. A.H. was supported by National Institutes of Health (R01AI173214). The authors thank all members of the labs for their support.

Author contributions

Conceptualization, E.N., A.H., and E.F.; mathematical model development, E.N., F.B., G.G., and E.F.; numerical simulations, E.N.; mathematical analysis, F.B., G.G., and E.F.; experiments, E.N.; writing – original draft, E.N.; writing – review & editing, E.N., F.B., G.G, A.H., and E.F.; funding acquisition, E.F.; supervision, E.F.

Declaration of interests

The authors declare no competing interests.

DECLARATION OF GENERATIVE AI AND AI-ASSISTED TECHNOLOGIES

During the preparation of this work, the authors used ChatGPT from OpenAI in order to refactor and write MATLAB code and to revise grammatical errors in the text. After using this tool, the authors reviewed and edited the content as needed and take full responsibility for the content of the publication.

References

1. Hoffmann, A., Levchenko, A., Scott, M. L., and Baltimore, D. (2002). The IκB-NF-κB signaling module: temporal control and selective gene activation. Science *298*, 1241–1245. 591 592

2. Purvis, J. E., and Lahav, G. (2013). Encoding and decoding cellular information through signaling dynamics. Cell *152*, 945–956.

3. Adelaja, A., Taylor, B., Sheu, K. M., Liu, Y., Luecke, S., and Hoffmann, A. (2021). Six distinct NFκB signaling codons convey discrete information to distinguish stimuli and enable appropriate macrophage responses. Immunity *54*, 916–930.e7.

4. Behar, M., and Hoffmann, A. (2010). Understanding the temporal codes of intra-cellular signals. Current opinion in genetics & development *20*, 684–693.

5. Gillies, T. E., Pargett, M., Minguet, M., Davies, A. E., and Albeck, J. G. (2017). Linear integration of ERK activity predominates over persistence detection in fra-1 regulation. Cell systems *5*, 549–563.e5.

6. Johnson, H. E., and Toettcher, J. E. (2019). Signaling dynamics control cell fate in the early drosophila embryo. Developmental cell *48*, 361–370.e3.

7. Uhlitz, F., Sieber, A., Wyler, E., Fritsche-Guenther, R., Meisig, J., Landthaler, M., Klinger, B., and Blüthgen, N. (2017). An immediate-late gene expression module decodes ERK signal duration. Molecular systems biology *13*, 928.

8. Ryu, H., Chung, M., Dobrzyński, M., Fey, D., Blum, Y., Lee, S. S., Peter, M., Kholodenko, B. N., Jeon, N. L., and Pertz, O. (2015). Frequency modulation of ERK activation dynamics rewires cell fate. Molecular systems biology *11*, 838.

9. Panzeri, S., Brunel, N., Logothetis, N. K., and Kayser, C. (2010). Sensory neural codes using multiplexed temporal scales. Trends in neurosciences *33*, 111–120.

10. Walker, J. J., Terry, J. R., Tsaneva-Atanasova, K., Armstrong, S. P., McArdle, C. A., and Lightman, S. L. (2010). Encoding and decoding mechanisms of pulsatile hormone secretion. Journal of neuroendocrinology *22*, 1226–1238.

11. Dalkin, A. C., Haisenleder, D. J., Ortolano, G. A., Ellis, T. R., and Marshall, J. C. (1989). The frequency of gonadotropin-releasing-hormone stimulation differentially regulates gonadotropin subunit messenger ribonucleic acid expression. Endocrinology *125*, 917–924.

12. Stamatiades, G. A., and Kaiser, U. B. (2018). Gonadotropin regulation by pulsatile GnRH: Signaling and gene expression. Molecular and cellular endocrinology *463*, 131–141.

13. Ravindran, P. T., McFann, S., Thornton, R. H., and Toettcher, J. E. (2021). A synthetic gene circuit for imaging-free detection of signaling pulses. Cell systems.

14. Benzinger, D., Ovinnikov, S., and Khammash, M. (2022). Synthetic gene networks recapitulate dynamic signal decoding and differential gene expression. Cell systems *13*, 353–364.e6.

15. Lormeau, C., Rudolf, F., and Stelling, J. (2021). A rationally engineered decoder of transient intracellular signals. Nature communications *12*, 1886.

16. O'Brien, J., and Murugan, A. (2019). Temporal pattern recognition through analog molecular computation. ACS synthetic biology *8*, 826–832.

17. Zhang, C., Tsoi, R., Wu, F., and You, L. (2016). Processing oscillatory signals by incoherent feedforward loops. PLoS computational biology (1–16).

18. Luecke, S., Sheu, K. M., and Hoffmann, A. (2021). Stimulus-specific responses in innate immunity: Multilayered regulatory circuits. Immunity *54*, 1915–1932.

19. Mangan, S., Itzkovitz, S., Zaslaver, A., and Alon, U. (2006). The incoherent feed-forward loop accelerates the response-time of the gal system of escherichia coli. Journal of molecular biology *356*, 1073–1081.

20. Alon, U. (2007). Network motifs: Theory and experimental approaches. Nature reviews. Genetics *8*, 450–461.

21. Schaffter, S. W., Chen, K.-L., O'Brien, J., Noble, M., Murugan, A., and Schulman, R. (2022). Standardized excitable elements for scalable engineering of far-from-equilibrium chemical networks. Nature chemistry.

22. Ryan, J., Hong, S., Foo, M., Kim, J., and Tang, X. (2022). Model-based investigation of the relationship between regulation level and pulse property of I1-FFL gene circuits. ACS synthetic biology *11*, 2417–2428.

23. Westbrook, A., Tang, X., Marshall, R., Maxwell, C. S., Chappell, J., Agrawal, D. K., Dunlop, M. J., Noireaux, V., Beisel, C. L., Lucks, J., and Franco, E. (2019). Distinct timescales of RNA regulators enable the construction of a genetic pulse generator. Biotechnology and bioengineering *116*, 1139–1151.

24. Basu, S., Mehreja, R., Thiberge, S., Chen, M. T., Weiss, R., and Modeling, D. (2004). Spatiotemporal control of gene expression with pulse-generating networks. Proceedings of the National Academy of Sciences of the United States of America *101*, 6355–6360.

25. Guo, S., and Murray, R. M. (2019). Construction of incoherent feedforward loop circuits in a cell-free system and in cells. ACS synthetic biology *8*, 606–610.

26. Sontag, E. D. (2010). Remarks on feedforward circuits, adaptation, and pulse memory. IET systems biology *4*, 39–51.

27. Goentoro, L., Shoval, O., Kirschner, M. W., and Alon, U. (2009). The incoherent feedforward loop can provide fold-change detection in gene regulation. Molecular cell *36*, 894–899.

28. Shoval, O., Alon, U., and Sontag, E. (2011). Symmetry invariance for adapting biological systems. SIAM journal on applied dynamical systems *10*, 857–886.

29. Lee, R. E. C., Walker, S. R., Savery, K., Frank, D. A., and Gaudet, S. (2014). Fold change of nuclear NF-κB determines TNF-induced transcription in single cells. Molecular cell *53*, 867–879.

30. Wong, V. C., Bass, V. L., Bullock, M. E., Chavali, A. K., Lee, R. E. C., Mothes, W., Gaudet, S., and Miller-Jensen, K. (2018). NF-κb-chromatin interactions drive diverse phenotypes by modulating transcriptional noise. Cell Reports *22*, 585–599.

31. Wong, V. C., Mathew, S., Ramji, R., Gaudet, S., and Miller-Jensen, K. (2019). Fold-change detection of NF-κb at target genes with different transcript outputs. Biophysical Journal *116*, 709–724.

32. Basu, S., Gerchman, Y., Collins, C. H., Arnold, F. H., and Weiss, R. (2005). A synthetic multicellular system for programmed pattern formation. Nature *434*, 1130–1134.

33. Greber, D., and Fussenegger, M. (2010). An engineered mammalian band-pass network. Nucleic acids research *38*, e174.

34. Takahashi, J. S. (2017). Transcriptional architecture of the mammalian circadian clock. Nature reviews. Genetics *18*, 164–179.

35. Mitchell, S., Vargas, J., and Hoffmann, A. (2016). Signaling via the NFκB system. Wiley interdisciplinary reviews. Systems biology and medicine *8*, 227–241.

36. Batchelor, E., Mock, C. S., Bhan, I., Loewer, A., and Lahav, G. (2008). Recurrent initiation: a mechanism for triggering p53 pulses in response to DNA damage. Molecular cell *30*, 277–289.

37. Shoval, O., Goentoro, L., Hart, Y., Mayo, A., Sontag, E., and Alon, U. (2010). Fold-change detection and scalar symmetry of sensory input fields. Proceedings of the National Academy of Sciences of the United States of America *107*, 15995–16000.

38. Adler, M., Szekely, P., Mayo, A., and Alon, U. (2017). Optimal regulatory circuit topologies for fold-change detection. Cell Systems *4*, 171–181.e8.

39. Ma, W., Trusina, A., El-Samad, H., Lim, W. A., and Tang, C. (2009). Defining network topologies that can achieve biochemical adaptation. Cell *138*, 1–55.

40. Aoki, S. K., Lillacci, G., Gupta, A., Baumschlager, A., Schweingruber, D., and Khammash, M. (2019). A universal biomolecular integral feedback controller for robust perfect adaptation. Nature *570*, 533–537.

41. Mangan, S., and Alon, U. (2003). Structure and function of the feed-forward loop network motif. Proceedings of the National Academy of Sciences of the United States of America *100*, 11980–11985.

42. Tyson, J. J., Chen, K. C., and Novak, B. (2003). Sniffers, buzzers, toggles and blinkers: dynamics of regulatory and signaling pathways in the cell. Current opinion in cell biology *15*, 221–231.

43. Wall, M. E., Dunlop, M. J., and Hlavacek, W. S. (2005). Multiple functions of a feed-forward-loop gene circuit. Journal of molecular biology *349*, 501–514.

44. Kim, J., White, K. S., and Winfree, E. (2006). Construction of an in vitro bistable circuit from synthetic transcriptional switches. Molecular systems biology *2*, 68.

45. Weitz, M., Kim, J., Kapsner, K., Winfree, E., Franco, E., and Simmel, F. C. (2014). Diversity in the dynamical behaviour of a compartmentalized programmable biochemical oscillator. Nature chemistry *6*, 295–302.

46. Gerardin, J., Lim, W. A., Reddy, N. R., and Lim, W. A. (2019). The design principles of biochemical timers: Circuits that discriminate between transient and sustained stimulation - supplemental. Cell Systems *9*, 297–308.e2.

47. Tzafriri, A. R., and Edelman, E. R. (2004). The total quasi-steady-state approximation is valid for reversible enzyme kinetics. Journal of theoretical biology *226*, 303–313.

48. Briat, C., Gupta, A., and Khammash, M. (2016). Antithetic integral feedback ensures robust perfect adaptation in noisy biomolecular networks. Cell systems *2*, 15–26.

49. Yu, P. Y., and Sontag, E. D. (2024). A necessary condition for non-monotonic dose response, with an application to a kinetic proofreading model – extended version. arXiv [q-bio.MN].

50. Gao, X. J., Chong, L. S., Kim, M. S., and Elowitz, M. B. (2018). Programmable protein circuits in living cells. Science (New York, N.Y.) *361*, 1252–1258.

51. Aubert-Kato, N., and Cazenille, L. (2020). Designing dynamical molecular systems with the pen toolbox. New Generation Computing *38*, 341–366.

52. Dupin, A., and Simmel, F. C. (2019). Signalling and differentiation in emulsion-based multi-compartmentalized in vitro gene circuits. Nature chemistry *11*, 32–39.

53. Gordley, R. M., Williams, R. E., Bashor, C. J., Toettcher, J. E., Yan, S., and Lim, W. A. (2016). Engineering dynamical control of cell fate switching using synthetic phospho-regulons. Proceedings of the National Academy of Sciences of the United States of America *113*, 13528–13533.

54. Yang, X., Rocks, J. W., Jiang, K., Walters, A. J., Rai, K., Liu, J., Nguyen, J., Olson, S. D., Mehta, P., Collins, J. J., Daringer, N. M., and Bashor, C. J. (2023). Engineering synthetic phosphorylation signaling networks in human cells. bioRxiv (2023.09.11.557100). [716][717][718]

55. Shui, S., Scheller, L., and Correia, B. E. (2023). Protein-based bandpass filters for controlling cellular signaling with chemical inputs. Nature chemical biology. [719][720]

56. Levine, J. H., Lin, Y., and Elowitz, M. B. (2013). Functional roles of pulsing in genetic circuits. Science *342*, 1193–1200. [721][722]

57. Lee, R. E. C., Qasaimeh, M. A., Xia, X., Juncker, D., and Gaudet, S. (2016). NF-κB signalling and cell fate decisions in response to a short pulse of tumour necrosis factor. Scientific reports *6*, 39519. [723][724]

58. Gong, X., Wei, J., Liu, J., Li, R., Liu, X., and Wang, F. (2019). Programmable intracellular DNA biocomputing circuits for reliable cell recognitions. Chemical science (Royal Society of Chemistry: 2010) *10*, 2989–2997. [725][726][727]

59. Lienert, F., Lohmueller, J. J., Garg, A., and Silver, P. A. (2014). Synthetic biology in mammalian cells: next generation research tools and therapeutics. Nature reviews. Molecular cell biology *15*, 95–107. [728][729]

60. Kumar, S., and Khammash, M. (2022). Platforms for optogenetic stimulation and feedback control. Frontiers in bioengineering and biotechnology *10*, 918917. [730][731]

61. Wan, Y., Cohen, J., Szenk, M., Farquhar, K. S., Coraci, D., Krzysztoń, R., Azukas, J., Van Nest, N., Smashnov, A., Chern, Y.-J., De Martino, D., Nguyen, L. C., Bien, H., Bravo-Cordero, J. J., Chan, C.-H., Rosner, M. R., and Balázsi, G. (2023). Nonmonotone invasion landscape by noise-aware control of metastasis activator levels. Nature chemical biology *19*, 887–899. [732][733][734][735]

62. Heinrich, R., Neel, B. G., and Rapoport, T. A. (2002). Mathematical models of protein kinase signal transduction. Molecular cell *9*, 957–970. [736][737]

STAR METHODS

Resource availability

Lead contact

Requests for further information and resources should be directed to and will be fulfilled by the lead contact, Elisa Franco (efranco@seas.ucla.edu).

Materials availability

This study did not generate new materials.

Data and code availability

- All the numerical simulation data used for the figures are publicly available as of the date of publication at https://github.com/enaka74/IDR.

- All original code has been deposited at https://github.com/enaka74/IDR and is publicly available as of the date of publication.

- All the raw data and the MATLAB scripts for analyzing the data have been deposited at https://zenodo.org/records/15385324.

Method details

Mathematical models for the negative feedback loop (NFL) circuit

Temporarily denoting the concentration of species Y as $\bar{y}$, we introduce the simple NFL model as follows:

$$\frac{dx(s)}{ds} = \alpha\bar{y}(s) - \beta x(s) \tag{25}$$

$$\frac{d\bar{y}(s)}{ds} = \gamma u(s) - \delta x^p(s)\bar{y}(s) - \epsilon\bar{y}(s) \tag{26}$$

where α and γ are the activation rate constants for species X and Y respectively; β and ϵ are the self-degradation rate constants for species X and Y respectively; δ is the rate constant associated with inhibition of Y mediated by X, and p represents the order (i.e., cooperativity) of the reaction, while s is the time variable. To reduce the number of parameters, we rescale time in Equations 25 and 26 and obtain the new ODE model, which we will analyze in the following without loss of generality:

$$\dot{x}(t) = y(t) - x(t) \tag{27}$$

$$\dot{y}(t) = au(t) - bx^p(t)y(t) - cy(t) \tag{28}$$

where $t = \beta s$, $y = \alpha\bar{y}/\beta$, $a = \gamma/\beta$, $b = \delta/\alpha$, $c = \epsilon\beta/\alpha$, while $\dot{x}(t) = \frac{dx(t)}{dt}$ and $\dot{y}(t) = \frac{dy(t)}{dt}$. Note that variable y is rescaled here. Using Equations 27 and 28, we can evaluate the circuit dynamics with respect to a, b, c, and p, as done in the main text.

The signaling model of NFL is as follows:

$$\dot{x}(t) = \alpha_x\frac{y(t)[1-x(t)]}{K_{M,yx} + y(t) + [1-x(t)]} - \gamma_x\frac{p_x x(t)}{K_{M,px} + p_x + x(t)} \tag{29}$$

$$\dot{y}(t) = \alpha_y\frac{u(t)[1-y(t)]}{K_{M,uy} + u(t) + [1-y(t)]} - \beta_y\frac{x(t)y(t)}{K_{M,xy} + x(t) + y(t)} - \gamma_y\frac{p_y}{K_{M,py} + p_y + y(t)} \tag{30}$$

The gene regulatory model of NFL is as follows:

$$\dot{x}(t) = \delta_x \frac{[u(t)/K_{D,ux}]^{h_{ux}}}{1 + [u(t)/K_{D,ux}]^{h_{ux}}} - \epsilon_x x(t) \tag{31}$$

$$\dot{y}(t) = \delta_y \frac{[u(t)/K_{D,uy}]^{h_{uy}}}{1 + [u(t)/K_{D,uy}]^{h_{uy}} + [x(t)/K_{D,xy}]^{h_{xy}}} - \epsilon_y y(t) \tag{32}$$

The parameters for each model are defined in the same way as those for IFFL.

Gene regulatory network model for the generalized incoherent feedforward loop (IFFL) circuit

We consider the following gene regulatory network model for the generalized incoherent feedforward loop:

$$\dot{x}_1(t) = \delta_{x_1} \frac{[u(t)/K_{D,ux}]^{h_{ux}}}{1 + [u(t)/K_{D,ux}]^{h_{ux}}} - \epsilon_{x_1} x_1(t) \tag{33}$$

$$\dot{y}_1(t) = \delta_{y_1} \frac{[u(t)/K_{D,uy}]^{h_{uy}}}{1 + [u(t)/K_{D,uy}]^{h_{uy}}} - \epsilon_{y_1} y_1(t) \tag{34}$$

$$\dot{x}_i(t) = \delta_{x_i} \frac{[x_{i-1}(t)/K_{D,x_i}]^{h_{x_i}}}{1 + [x_{i-1}(t)/K_{D,x_i}]^{h_{x_i}}} - \epsilon_{x_i} x_i(t) \quad (i = 2, ..., m) \tag{35}$$

$$\dot{y}_j(t) = \delta_{y_j} \frac{[y_{j-1}(t)/K_{D,y_j}]^{h_{y_j}}}{1 + [y_{j-1}(t)/K_{D,y_j}]^{h_{y_j}}} - \epsilon_{y_j} y_j(t) \quad (j = 2, ..., n) \tag{36}$$

$$\dot{z}(t) = \delta_z \frac{[x_m(t)/K_{D,xz}]^{h_{xz}}}{1 + [x_m(t)/K_{D,xz}]^{h_{xz}} + [y_n(t)/K_{D,yz}]^{h_{yz}}} - \epsilon_z z(t) \tag{37}$$

where δ is the activation rate and ϵ is the dilution/degradation rate for an expressed protein, while K_D is the dissociation constant of a transcription factor on its target promoter. The subscripts indicate the species in which a constant is involved; for example, δ_{x_i} is the activation rate of X and K_{D,y_j} is the dissociation constant between the transcription factor expressed from the gene Y_{j-1} and the targeted promoter for gene Y_j.

Parameter values for the detailed mathematical models

Table 1: Nominal parameter values for the mathematical models evaluated in Figure 5A to C

Parameter	Unit	Value		
		x	y	z
α	min^{-1}	Varied	Varied	100
β	min^{-1}	—	—	10
γ	min^{-1}	Varied	Varied	0.1
K_M	$\mu\mathrm{M}$	1	1	1
$K_{M,p}$	$\mu\mathrm{M}$	1	1	1
p_x	$\mu\mathrm{M}$	1	1	0.2

Table 2: Nominal parameter values for the mathematical models evaluated in Figure 5D and E

Parameter	Unit	Value		
		x	y	z
α	min^{-1}	1	1	Varied
β	min^{-1}	—	—	Varied
γ	min^{-1}	Varied	Varied	0.1
K_M	μM	1	1	1
$K_{M,p}$	μM	1	1	1
p_x	μM	1	1	0.2

Table 3: Nominal parameter values for the mathematical models evaluated in Figure 5F and I

Parameter	Unit	Value					
		x_1	x_2	y_1	y_2	y_3	z
α	min^{-1}	50	50	0.5	1.5	2.5	5
β	min^{-1}	—	—	—	—	—	5
γ	min^{-1}	0.5	0.5	0.1	0.1	0.1	0.1
K_M	μM	1	1	5	5	5	
$K_{M,xz}$	μM	—	—	—	—	—	100
$K_{M,yz}$	μM	—	—	—	—	—	1
$K_{M,p}$	μM	0.2	0.2	0.2	0.2	0.2	10
p	μM	0.3	0.3	0.3	0.3	0.3	0.3

Table 4: Nominal parameter values for the mathematical models evaluated in the Supplemental Figure 9

Parameter	Unit	Value						
		x_1	x_2	x_3	y_1	y_2	y_3	z
δ	nM hr^{-1}	20	0.2	0.3	2.5	45	10	0.01
ϵ	hr^{-1}	0.02	0.0003	0.0003	0.0004	0.0004	0.0003	0.001
K	nM	0.5	60	0.6	2.2	5	13	—
K_{xz}	nM	—	—	—	—	—	—	8
K_{yz}	nM	—	—	—	—	—	—	0.15
h	—	2	3	3	3	4	2	—
h_{xz}	—	—	—	—	—	—	—	2
h_{yz}	—	—	—	—	—	—	—	4

Quantification of the inverse properties

We introduce several mathematical formulae from Heinrich's work [62] to evaluate the transient dynamics of a signal. With the formulae, we can quantify temporal features of a signal of an arbitrary shape. Given the function $f(t)$ of time, which can be the temporal signal obtained as the output response of a biological circuit, the formulae are as follows.

$$I = \int_0^\infty f(t)dt \tag{38}$$

$$T = \int_0^\infty tf(t)dt \tag{39}$$

$$\tau = T/I \tag{40}$$

$$Q = \int_0^\infty t^2 f(t)dt \tag{41}$$

$$D_{out} = \sqrt{Q/I - (T/I)^2} \tag{42}$$

I is the integral of the signal, also referred to as the area under the curve or AUC, i.e. the integrated response. T is the time-weighted integrated response, while the *signaling time* τ is the average time required to activate the response. Q is the squared-time-weighted integrated response. The signal duration is denoted by D_{out}. The quantities τ and D_{out} are analogous to the mean and standard deviation, respectively, of a continuous statistical distribution. Throughout the present study, we evaluate the signal duration of an output response by computing D_{out} as in Equation 42. It should be noted that D_{out} is undefined when $f(t) = 0$ due to division by zero. Specifically, $D_{in} = 0$ results in no response across all the models evaluated in the main text. Therefore, $D_{out}(D_{in} = 0)$ is not considered in this study.

Next we define and quantify the IDD property. We suppose $D_{out}(D_{in})$, namely the output signal duration as a function of the input signal duration, can have an arbitrary functional form, as shown in Fig. 18. The steps to compute the IDD score S_{IDD} are as follows: First, we locate all the local maxima, D_{out,M_i}, and local minima, D_{out,m_j}. D_{in,M_i} and D_{in,m_j} are the input pulse durations that give D_{out,M_i} and D_{out,m_j} (i.e., $D_{out,M_i} = D_{out}(D_{in,M_i})$, $D_{out,m_j} = D_{out}(D_{in,m_j})$). Next we consider all combinations of D_{out,M_i} and D_{out,m_j}. Finally, we determine the combination that gives the maximum value of $\frac{D_{out,M_i}}{D_{out,m_j}} - 1$, satisfying $D_{in,M_i} < D_{in,m_j}$, which guarantees the IDD property is maintained for all $D_{in,M_i} \leq D_{in} \leq D_{in,m_j}$. The following definition mathematically represents the IDD score S_{IDD} determined through the above steps:

$$S_{ij} = \frac{D_{out,M_i}}{D_{out,m_j}} - 1 \quad (i = 1, ..., N_M, j = 1, ..., N_m) \tag{43}$$

$$S_{IDD} = max\{S_{ij} \quad s.t. \quad D_{in,M_i} < D_{in,m_j}\} \tag{44}$$

where N_M and N_m are the total number of maxima and minima, respectively. If $D_{out}(D_{in})$ is a non-decreasing function, then S_{IDD} is defined as zero. Because a constant function can be considered to have $D_{out,M} = D_{out,m}$, which gives $S_{IDD} = 0$, this extension of the definition is reasonable. This expression can quantify the IDD property of an arbitrary shape of $D_{out}(D_{in})$ curve. Based on this definition, if a response has an interval of D_{in} values for which $D_{out}(D_{in})$ locally decreases, the response has a positive S_{IDD}; otherwise, $S_{IDD} = 0$. An IDA score S_{IDA} is calculated in the same way, just considering function $I(D_{in})$, namely $AUC(D_{in})$.

Computational simulations and random parameter sampling for the biological network models

All the numerical simulations were performed using MATLAB. The ode23s solver was used for the signaling models, and the ode15s solver was used for the GRN models. For random parameter sampling, each parameter (except for the Hill coefficient h) was sampled from the log-uniform distribution in the interval specified by the lower and upper limits listed in Table 5 using the MATLAB $rand$ function. The Hill coefficient was sampled from a discrete uniform distribution over the integer values defined by the corresponding bounds in Table 5. The selected parameter ranges are biologically plausible and consistent in

Figure 18: A schematic example of function $D_{out}(D_{in})$ and steps to find the $(D_{out,M_i}, D_{out,m_j})$ pair to compute the IDD score.

units, and are comparable to those used in previous modeling studies of biological circuits[46]. The input amplitude was varied among $u_0 = 0.001$, 0.01, 0.1, $1\,\mu M$ for the signaling models, and $u_0 = 0.1$, 1, 10, $100\,nM$ for the GRN models. The histograms selected for Figure 4 were generated using $u_0 = 0.01\,\mu M$ for the signaling model and $u_0 = 1\,nM$ for the GRN model. The remaining histograms are provided in the Supplemental Figure 16.

For the GRN models, additional time-scaling was conducted to improve the stability of the numerical simulations. To obtain a rough estimate of the overall time scale of the system with a given parameter set, we the following scaling factor:

$$\tau = \sum_{i,j} \frac{1}{\epsilon_{i,j}} \tag{45}$$

This scaling factor was applied to the time steps, absolute tolerance, and input durations.

For each sampled parameter set, simulations were performed over a range of input durations. For the signaling model, D_{in} was logarithmically swept over the interval $[1, 100]$, and whereas for the GRN model, D_{in} was logarithmically swept over the interval $[0.1, 10] \times \tau$. Note that, for the generalized IFFL networks with fixed parameter values and varying numbers of intermediate nodes, simulations were performed with D_{in} logarithmically swept over the interval $[0.1, 10]$ in order to capture the range of durations over which the inversion property emerges.

Table 5: Parameter ranges for the random parameter sampling.

Parameter	Unit	Lower limit	Upper limit
α	min^{-1}	1×10^{-1}	1×10^{2}
β	min^{-1}	1×10^{-1}	1×10^{2}
γ	min^{-1}	1×10^{-1}	1×10^{2}
K_M	μM	1×10^{-2}	1×10^{2}
P	μM	0.1	1
δ	$nM\,hr^{-1}$	1×10^{0}	1×10^{2}
ϵ	hr^{-1}	1×10^{-2}	1×10^{0}
K_D	nM	1×10^{-2}	1×10^{2}
h	-	1	4

Experimental Methods

Oligonucleotide sequences All DNA was purchased from Integrated DNA Technologies (IDT, Coralville, Iowa, USA). The DNA sequences used for the genelet IFFL experiments are listed in Table 7. All sequences were adapted from genelets established by Schaffter et al.[21]. Specifically, $G_{in}C_{out}$, $G_{in}C_r$,

G_rR_{out}, $G_{out}S$, and $G_{out}I_{out}$ were derived from G8C1, G8C3, G3R1, G1S1, and G1I1, respectively, as reported in their study.

Genelet preparation Each genelet was annealed separately in 1X NEB RNAPol Reaction Buffer (New England Biolabs, Ipswich, MA, USA; catalog no. B9012SVIAL). Annealing protocol is as follows: heated to $90\,°C$ for $5\,min$ and cooled to $20\,°C$ at a rate of $1\,°C\,min^{-1}$. The initially blocked genelets, G_rR_{out}, $G_{out}S$, and $G_{out}I_{out}$, were annealed with a template strand, a non-template strand, and a DNA blocker at a 1.5-fold concentration. In contrast, the initially active genelets, $G_{in}C_{out}$ and $G_{in}C_r$, were annealed with only a template and a non-template strand.

Circuit preparation Annealed IFFL genelets were combined in a single reaction containing NTPs (New England Biolabs; catalog no. N0450L), MgCl$_2$, pyrophosphatase (New England Biolabs; catalog no. M2403L), and dithiothreitol (Promega, distributed by VWR, Radnor, PA, USA; catalog no. PAP1171) at the concentrations listed in Table 6.

Fluorescence spectroscopy Fluorescence was measured by a spectrofluorometer (HORIBA Instruments Incorporated, Irvine, CA, USA; catalog no. FL3-11) or plate reader (), both of which are equipped with a temperature control system that maintained the sample temperature at $37\,°C$. . The spectrofluorometer was used for the experiment shown in Figure 3E and F, and the plate reader was used for the experiments shown in Figure 3H.

For spectroflurometer measurements, samples were loaded into quartz cuvettes, and covered with $50\,\mu L$ hexadecane to prevent evaporation. Cuvettes were placed in thespectrofluorometer. Fluorescence signals were recorded every two minutes at excitation/emission wavelengths of 495/520 nm for 6FAM dye, 549/565 nm for TYE563 dye, and 596/615 nm for TEX615 dye.

For plate reader measurements, samples were loaded into 384 Well Black Plate, Non-Treated Surface, Non-Sterile (Thermo Fisher Scientific, Waltham, MA, USA; catalog no. 262260), and covered with a VWR polyester film (Avantor, Radnor, PA, USA; catalog no. 60941-062) to prevent evaporation. Fluorescence signals were recorded every two minutes at excitation/emission wavelengths of 490/530 nm for 6FAM dye, 539/569 nm for TYE563 dye, and 590/621 nm for TEX615 dye.

Transcription reaction Samples including all the IFFL genelets were loaded in the fluorimeter to collect baseline off fluorescence. After equilibration, a mixture of dA_{in}, dA_r, dA_{out}, dB_r, and dB_{out} was added. The amounts of dB_r and dB_{out} were adjusted such that the total concentrations of $[dB_r]$ and $[dB_{out}]$, including the contributions from dB_r and dB_{in} added during annealing, matched the values listed in Table 6. At this point, only $G_{in}C_{out}$ and $G_{in}C_r$ are active because the remaining genelets are in a blocked state. After the fluorescence signals stabilized, RNase H (Thermo Fisher Scientific, Waltham, MA, USA; catalog no. EN0202) and T7 Enzyme mix from MEGAshortscript T7 Transcription Kit (Invitrogen, Thermo Fisher Scientific; catalog no. AM1354) were added. The final concentrations correspond to those in Table 6 with a total reaction volume of $60\,\mu L$ for fluorometer measurement and $20\,\mu L$ for plate reader measurement. After a predetermined time interval, the DNA repressor dR_{in} was introduced to repress the input genelets ($G_{in}C_{out}$ and $G_{in}C_r$), resulting in the pulsatile activation of the input genelets.

Fluorescence normalization The active level of a fluorescently tagged genelet was calculated based on the maximum fluorescence F_M (fluorescence provided by fluorescently tagged genelets only) and the minimum fluorescence F_m (fluorescence from a fully-quenched genelet). Note that both F_M and F_m are time-course trajectories obtained from control experiments, so hereinafter we denote $F_M(t)$ and $F_m(t)$ for clarity. First, in control samples, two trajectories were obtained: $F_{ctr,M}(t)$ a trajectory reflecting the maximum fluorescence value, and $F_{ctr,m}(t)$, a trajectory reflecting the minimum fluorescence value. $F_{ctr,M}$ was obtained from a sample to which no activators were added, and $F_{ctr,m}$ was obtained by adding excess amount of activators to a sample that has no blockers (Figure 19). Therefore, $F_{ctr,M}$ and $F_{ctr,m}$ are supposed to show the maximum and minimum fluorescence signals corresponding to $0\,\%$ activation and $0\,\%$ activation, respectively. However, $F_{ctr,M}$ and $F_{ctr,m}$ have to be adjusted based on sample-to-sample intensity variation. Therefore, F_M and F_m were calculated by multiplying a scaling factor f_M and f_m. f_M and f_M is calculated based on a relative fluorescent intensity at a specified time point, t_{ref}. Thus

$$f_M = F(t_{ref,M})/F_{ctr,M}(t_{ref,M}) \tag{46}$$

$$f_m = F(t_{ref,m})/F_{ctr,m}(t_{ref,m}) \tag{47}$$

Thus, adjusted trajectories of the maximum and minimum fluorescence are:

$$\bar{F_M}(t) = f_M * F_M(t) \tag{48}$$
$$\bar{F_m}(t) = f_m * F_m(t) \tag{49}$$

Finally, the active level of a genelet at time t, $[G]_{on}(t)$, is calculated as follows:

$$[G]_{on}(t) = \frac{\bar{F_M}(t) - F(t)}{\bar{F_M}(t) - \bar{F_m}(t)} \tag{50}$$

For spectrofluorometer data, fluorescence signal was also scaled based on volume change every time additional reagents (e.g., DNA activators and enzymes) are added, as the spectrofluorometer measurement is more sensitive to dilution than the plate reader measurement.

The whole normalization procedure is visualized in Figure 19 with example data. The spectrofluorometer has much larger signal-to-noise ratio, enabling dana analysis without any smoothing. Furthermore, the fluorometer data is showing more reasonable normalization results: for instance, $G_{in}C_r$ active fraction shows complete shut off after DNA repressor was added.

Table 6: Concentration of genelets and buffer components in the experiments shown in Figure 3, Supplemental Figure 12 and 13.

Component	Concentration
$G_{in}C_{out}$	25 nM (10 nM, 25 nM, 50 nM in the experiments for the Supplemental Figure 13)
$G_{in}C_r$	5 nM (2 nM, 5 nM, 10 nM in the experiments for the Supplemental Figure 13)
dA_{in}	150 nM
dR_{in}	250 nM
G_rC_{out}	5 nM
dA_r	50 nM
dB_r	125 nM
$G_{out}S$	25 nM
$G_{out}I_{out}$	1 nM
dA_{out}	100 nM
dB_{out}	37.5 nM
NTP	7.5 mM each
MgCl$_2$	30 mM
Pyrophosphatase	1.35 mU μL^{-1}
Dithiothreitol	5 mM
RNase H	0.01 U μL^{-1}
T7 Enzyme Mix	2.9 U μL^{-1}

Table 7: A list of the DNA sequences for the genelet IFFL experiments

Sequence ID	DNA Sequence (5' to 3')
$G_{in}C_{out}$-nt	/5TYE563/CAGAGGGTTAGCAGAACCCAGATAATACGACTCACTATAGGG AGATTCGTCTCCCAAATCCTTCCATGAACGCCAAACCGTGGCGACGAC
C_{out}-t	GAGTAGGTCGTCGCCACGGTTTGGCGTTCATGGAAGGATTTGGGAGACGAA TCTCCCTATAGTGAGTCG
$G_{in}C_r$-nt	CAGAGGGTTAGCAGAACCCAGATAATACGACTCACTATAGGGAGATTCGTC TCCCAGAAGATGAAGATGTACCGTATAGGTACTAGGAAC

C_r-t	GCTCGTTCCTAGTACCTATACGGTACATCTTCATCTTCTGGGAGACGAATC TCCCTATAGTGAGTCG
G_rR_{out}-nt	/5TEX615/GAAGATGAAGGTGTACCGTATAGGTACTAGTAATACGACTCA CTATAGGGAGATTCGTCTCCCATGCACGCCAAACCGTGGCGACGTAAT
R_{out}-t	TCCAGCTCTATTACGTCGCCACGGTTTGGCGTGCATGGGAGACGAATCTCC CTATAGTGAGTCG
$G_{out}I_{out}$-nt	TCCTTCCATGCACGCCAAACCGTGGCGACGTAATACGACTCACTATATCCA GCTCTATTACGT
I_{out}-t	ACGTAATAGAGCTGGATATAGTGAGTCG
$G_{out}S$-nt	/5-6FAM/TCCTTCCATGCACGCCAAACCGTGGCGACGTAATACGACTCAC TATAGACATACAGATTAACCAGACAGTGAC
S-t	GTCACTGTCTGGTTAATCTGTATGTCTATAGTGAGTCG
dA_{in}	GTCGCGTGTATTATCTGGGTTCTGCTAACCCTCTG/3IABkRQSp/
dA_r	CCGACAAATATTACTAGTACCTATACGGTACACCT/3IABkRQSp/
dA_{out}	TCCAGCTCTATTACGTCGCCACGGTTTGGCGTGCA/3IABkFQ/
dB_r	GCTCGTTCCTAGTACCTATACGGTACACCTTCATCTTC
dB_{out}	GAGTAGGTCGTCGCCACGGTTTGGCGTGCATGGAAGGA
dR_{in}	CAGAGGGTTAGCAGAACCCAGATAATACACGCGAC

Parameter fitting of the genelet model

Parameter fitting of the genelet IFFL model was performed in MATLAB using a combination of the genetic algorithm function `ga` and the constrained nonlinear optimization function `fmincon`.

In the first fitting round, all model parameters were fitted to the time-series data of the output genelet $G_{out}S$ in response to input pulse durations of $10, 20, 30, 40, 60, 240\,\text{min}$ (Fig. 3E) using the genetic algorithm function `ga`. At this stage, all kinetic parameters were constrained to be identical across nodes; for example, the G_{in}, G_r, and G_{out} domains shared a common value of k_{GA}. Lower and upper bounds for each parameter were set to one order of magnitude above and below the corresponding initial value. The fitness function for this first fitting round was defined as

$$f_{\text{TS}} = \sum_{D_{\text{in}}} w_{D_{\text{in}}} \sum_{j=1}^{3} \sum_{i=1}^{N} (G_{j,\exp}(t_i) - G_{j,\text{sim}}(t_i))^2, \tag{51}$$

where D_{in} denotes the input pulse duration, t_i denotes the i-th experimental sampling time point for a given D_{in}, and N is the number of sampled time points under that condition. The index j corresponds to the genelet species, with $j = 1, 2, 3$ representing G_{in}, G_r, and G_{out}, respectively. $G_{j,\exp}$ and $G_{j,\text{sim}}$ denote the experimentally measured and simulated active fractions of genelet j. The weights $w_{D_{\text{in}}}$ and w_j control the relative contribution of each input duration and genelet species to the overall objective function.

In the second fitting round, the parameters k_{GA} and k_{GAR} associated with the $G_{out}S$ node, as well as k_{pc}, k_{pr}, k_{dc}, and k_{dr} for all nodes, were independently fitted, while all other parameters were held fixed at the values obtained from the first fitting step. The parameters were simultaneously fitted to the time-series data shown in Fig. 3E and to experimentally measured AUC values obtained by varying $[G_rR_{out}]_{\text{tot}}$ (Experiment (i) in Fig. 3H), again using the MATLAB genetic algorithm function `ga`. The resulting parameter set was subsequently refined using the MATLAB function `fmincon`. The fitness function used in this round was defined as

$$f_1 = f_{TS} + w_{exp,1} \sum_{D_{in}} (AUC_{exp,1}(D_{in}) - AUC_{sim,1}(D_{in}))^2, \tag{52}$$

where $AUC_{exp,1}$ and $AUC_{sim,1}$ denote the experimentally measured and simulated AUC values, respectively, for Experiment (i) in Fig. 3H.

In the third and fourth fitting rounds, binding rate constants associated with different toehold lengths were fitted separately to Experiments (ii) and (iii) in Fig. 3 using the `ga` function. In the third step, the

Normalization of spectrofluorometer data

dA and dB added

T7 RNA polymerase added

Normalization of plate reader data

dA and dB added

T7 RNA polymerase added

Figure 19: Normalization examples for sperctrofluorometer dataset (top) and plate reader dataset (bottom). Each dataset has fluorescence data at three wavelength (corresponding to each row). For the spectrofluorometer dataset, the left column shows raw data, the central column shows scaled data, and the right column shows normalized data. For the plate reader data, the left column shows smoothed data before scaling, the central column shows smoothed and scaled data, and the right column shows normalized smoothed data.

Table 8: Optimization bounds and initial values (placeholders to be filled manually).

Parameter	Unit	Lower bound	Upper bound	Initial
k_{GA}	$\mathrm{M^{-1}s^{-1}}$	1×10^4	1×10^6	1×10^5
k_{GAR}	$\mathrm{M^{-1}s^{-1}}$	1×10^3	1×10^5	1×10^4
$k_{\mathrm{GAR,d}}$	$\mathrm{M^{-1}s^{-1}}$	5×10^4	5×10^6	5×10^5
k_{AR}	$\mathrm{M^{-1}s^{-1}}$	1×10^3	1×10^5	1×10^4
k_{GBC}	$\mathrm{M^{-1}s^{-1}}$	1×10^2	1×10^4	1×10^3
k_{GB}	$\mathrm{M^{-1}s^{-1}}$	1×10^4	1×10^6	1×10^5
k_{GAB}	$\mathrm{M^{-1}s^{-1}}$	1×10^3	1×10^5	1×10^4
k_{BC}	$\mathrm{M^{-1}s^{-1}}$	1×10^3	1×10^5	1×10^4
k_{IR}	$\mathrm{M^{-1}s^{-1}}$	1×10^4	1×10^6	1×10^5
k_{PR}	$\mathrm{s^{-1}}$	1×10^{-2}	1×10^0	1×10^{-1}
k_{PC}	$\mathrm{s^{-1}}$	1×10^{-2}	1×10^0	1×10^{-1}
k_{PI}	$\mathrm{s^{-1}}$	1×10^{-2}	1×10^0	1×10^{-1}
$k_{\mathrm{auto,input}}$	$\mathrm{s^{-1}}$	1×10^{-4}	1×10^{-2}	1×10^{-3}
$k_{\mathrm{auto,other}}$	$\mathrm{s^{-1}}$	1×10^{-5}	1×10^{-3}	1×10^{-4}
k_{leak}	$\mathrm{s^{-1}}$	2×10^{-3}	2×10^{-1}	2×10^{-2}
$f_{\mathrm{P,exp4}}$	-	0.9	1.1	1.0
k_{DR}	$\mathrm{s^{-1}}$	1.5×10^{-4}	1.5×10^{-2}	1.5×10^{-3}
k_{DC}	$\mathrm{s^{-1}}$	1.5×10^{-4}	1.5×10^{-2}	1.5×10^{-3}

parameters k_{ar} and k_{gar} corresponding to 6-nt and 4-nt dA_{out} toeholds were fitted, while in the fourth step, the parameters k_{bc} and k_{gbc} corresponding to 6-nt and 4-nt dB_{out} toeholds were fitted. In both steps, binding rate constants were expressed as scaling factors relative to the values for the nominal toehold length (8 nt) and were constrained to lie within the range 10^{-3} to 1. The fitness functions for the third and fourth fitting rounds were defined as

$$f_2 = f_{TS} + w_{exp,2} \sum_{D_{in}} (AUC_{exp,2}(D_{in}) - AUC_{sim,2}(D_{in}))^2 \tag{53}$$

$$f_3 = f_{TS} + w_{exp,3} \sum_{D_{in}} (AUC_{exp,3}(D_{in}) - AUC_{sim,3}(D_{in}))^2 \tag{54}$$

In the fifth fitting round, a scaling factor only for the experiment with varying $G_{in}C_{out}$ and $G_{in}C_{out}$ concentrations (Fig. 3F) (right) was fitted. This scaling factor is used only for the experiment, as the experiment was performed with a different batch of T7 RNA polymerase, which is assumed to uniformly affects all the RNA production rate constants. The fitness function for the fifth fitting round was defined as

$$f_4 = \sum_{G_{in}} (AUC_{exp,4}(G_{in}) - AUC_{sim,4}(G_{in}))^2 \tag{55}$$

Through these fitting rounds, the parameter values listed in Table 9, 10, 11, and 12 were obtained.

Table 9: Common parameters shared across all nodes (values only).

Parameter	Unit	Value
k_{GA}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	9.12×10^4
$k_{\mathrm{GAR,d}}$	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.64×10^6
k_{GB}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	1.71×10^4
k_{GAB}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	1.27×10^4
k_{IR}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	7.02×10^4
$k_{\mathrm{auto,input}}$	s^{-1}	1.11×10^{-3}
$k_{\mathrm{auto,other}}$	s^{-1}	5.42×10^{-4}
$\mathrm{k}_{\mathrm{leak}}$	s^{-1}	4.35×10^{-3}

Table 10: m-dependent parameters ($m = 5$), values only.

Parameter	Unit	$G_{in}C_{out}$	$G_{in}C_r$	$G_r R_{out}$	$G_{out}I_{out}$	$G_{out}S$
k_{PR}	s^{-1}	-	-	1.68×10^{-2}	-	-
k_{PC}	s^{-1}	3.96×10^{-2}	8.06×10^{-2}	-	-	-
k_{PI}	s^{-1}	-	-	-	2.97×10^{-2}	-
$f_{\mathrm{P,exp4}}$	-	1.10	1.10	1.10	1.10	1.10

Table 11: n-dependent parameters ($n = 3$), values only.

Parameter	Unit	G_{in}	G_r	G_{out}
k_{DR}	s^{-1}	3.52×10^{-3}	1.86×10^{-3}	9.02×10^{-4}
k_{DC}	s^{-1}	3.52×10^{-3}	1.86×10^{-3}	9.02×10^{-4}
k_{GAR}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	1.34×10^4	1.34×10^4	3.67×10^5
k_{AR}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	1.16×10^4	1.16×10^4	6.93×10^4
k_{GBC}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.12×10^3	4.12×10^3	4.12×10^3
k_{BC}	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.08×10^3	4.08×10^3	4.08×10^3

Table 12: Tuned parameters for Exp2 and Exp3.

Parameter	Unit	Value	Scale range
k_{AR} (8 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	6.93×10^4	[0.001, 1]
k_{AR} (6 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	5.48×10^4	[0.001, 1]
k_{AR} (4 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.48×10^3	[0.001, 1]
k_{GAR} (8 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	3.67×10^5	[0.001, 1]
k_{GAR} (6 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.98×10^4	[0.001, 1]
k_{GAR} (4 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	6.92×10^3	[0.001, 1]
k_{BC} (8 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.08×10^3	[0.001, 1]
k_{BC} (6 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.09×10^0	[0.001, 1]
k_{BC} (4 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.38×10^0	[0.001, 1]
k_{GBC} (8 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.12×10^3	[0.001, 1]
k_{GBC} (6 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	1.18×10^2	[0.001, 1]
k_{GBC} (4 nt)	$\mathrm{M}^{-1}\mathrm{s}^{-1}$	4.23×10^0	[0.001, 1]