Alpha and Beta Oscillations Mediate the Effect of Motivation on Neural Coding of Cognitive Flexibility

Juan M. Chau[a,b,*], Matias J. Ison[a], Paul S. Muhle-Karbe[c], Mark G. Stokes[d], Sam Hall-McMaster[e,f], Nicholas E. Myers[a,f]

[a] School of Psychology, University of Nottingham, Nottingham, UK

[b] Departamento de Ingeniería, Pontificia Universidad Católica del Perú, Lima, Peru

[c] School of Psychology & Centre for Human Brain Health, University of Birmingham, Birmingham, UK

[d] Department of Experimental Psychology & Oxford Centre for Human Brain Activity, University of Oxford, Oxford, UK

[e] Department of Psychology and Center for Brain Science, Harvard University, Massachusetts, US

[f] Joint last authors

[*] Corresponding author: juan.chaudelgado@nottingham.ac.uk

Author Contributions

Juan M. Chau: Conceptualization, Methodology, Software, Validation, Formal analysis, Writing – Original Draft. **Matias J. Ison:** Conceptualization, Writing – Review and Editing, Supervision. **Paul S. Muhle-Karbe:** Conceptualization, Investigation, Writing – Review and Editing. **Mark. G. Stokes:** Conceptualization, Investigation. **Sam Hall-McMaster:** Conceptualization, Formal analysis, Investigation, Writing – Review and Editing. **Nicholas E. Myers:** Conceptualization, Methodology, Investigation, Writing – Review and Editing, Supervision.

Abstract

Cognitive flexibility is crucial for adaptive human behaviour. Prior studies have analysed the effect of reward on cognitive flexibility; however, the neural mechanisms underlying these effects remain largely unknown. This study explores how reward influences neural oscillations and how these changes impact behavioural performance. Using time-frequency decomposition, we examined electroencephalographic data from participants engaged in rule-guided task-switching with varying reward prospects. Higher anticipated rewards lead to greater desynchronisation of alpha (8-12Hz) and beta (20-30Hz) oscillations, which in turn correlated with improved task performance. Both alpha power and event-related potential (ERP) coding of reward independently predicted reward-based performance improvements, suggesting distinct mechanisms supporting proactive control. These findings underscore the unique contributions of neural oscillations in mediating motivational effects on cognitive flexibility.

Keywords

Alpha oscillations; proactive control; time-frequency analysis; reward processing; electroencephalography (EEG)

Introduction

Understanding the neural mechanisms underlying cognitive flexibility and motivation is crucial for advancing our understanding of how these processes support adaptive behaviour in complex environments. For instance, in everyday life, cognitive flexibility allows individuals to switch between different tasks efficiently, such as a parent juggling work responsibilities while helping their child with homework. Motivation plays a key role in this process, as a motivated individual is more likely to stay focused and adapt to changing demands (Braem & Egner, 2018). Similarly, in sports, an athlete's ability to adjust their strategy based on the opponent's moves and stay motivated, especially throughout high-stakes events, can significantly impact their performance.

Cognitive control encompasses both reactive and proactive control mechanisms (Braver et al., 2009; Braver, 2012). Reactive control involves spontaneous adjustment of behaviour in response to unexpected changes in task demands, often relying on immediate cues to guide actions. In contrast, proactive control entails the anticipatory maintenance of task-relevant information in situations where fast and accurate responses are incentivized. This type of control has been linked to midfrontal neural oscillations, particularly in the theta band (4-8 Hz; Cooper et al., 2016; Kaiser & Schütz-Bosbach, 2019). These oscillations are thought to play a role in preparatory adjustments that optimize performance in response to expected task demands. Proactive control is essential for cognitive flexibility, allowing individuals to adapt their behaviour based on anticipation of changing task requirements and reward contingencies.

Hall-McMaster et al. (2019) investigated which aspects of sequential task processing are affected by reward to optimise cognitive flexibility. They found that high reward prospects increased neural representations for task rule information, which was associated with performance improvements. However, they raised an open-ended question about the exact mechanism by which a stronger separation of task representations translates into performance improvements. This question suggests that while reward enhances the clarity and distinctiveness of neural coding, the neural mechanisms through which motivation influences overall cognitive and behavioural performance remain to be fully understood.

One possibility comes from sharpening task control through oscillations in the alpha band (8-12 Hz). Alpha oscillations have been implicated in various cognitive functions, including attention and memory (Klimesch, 2012; Palva & Palva, 2007; Rihs et al., 2009). For instance, desynchronisation of alpha oscillations may contribute to the disinhibition of task-relevant areas to facilitate anticipated stimulus processing demands (Gould et al., 2011; Haegens et al., 2011; Worden et al., 2000). Prior studies have shown that alpha power can be modulated by task demands and reward, influencing behavioural outcomes such as response times (RTs; Pessoa & Engelmann, 2010; Van Dijk et al., 2008). For instance, a decrease in alpha power has been associated with enhanced cognitive control and faster RTs in high-reward conditions, suggesting a link between motivation and neural efficiency (Sawaki et al., 2015; van Driel et al., 2015). Additionally, alpha oscillations have been found to play a role in the suppression of irrelevant (Foxe & Snyder, 2011; Jensen & Mazaheri, 2010; Klimesch, 1999) or less-rewarding (Heuer et al., 2017) information, thereby facilitating task performance. While oscillations have been used to study various aspects of cognitive control, they have not been extensively explored in the context of information coding and cognitive flexibility. Our prediction is that the effect of reward coding on cognitive flexibility is mediated by alpha oscillations.

In this study, we directly tested this possibility by examining the neural oscillatory responses through electroencephalography (EEG) to reward cues and their impact on task performance. We

found a robust desynchronisation in the alpha band to reward cues that co-occurred with broadband reward coding and independently predicted performance. Contrary to our initial hypothesis, this indicates potentially distinct mechanisms for proactive control, with one acting on task rule reconfiguration and the other directly acting on invigoration of the response. Interestingly, we also found an unexpected response in the beta band that was not correlated with broadband reward coding, but contributed towards performance.

Methods

Data source

The data for this study were from a previously published experiment investigating the impact of reward on neural coding of task rules. The original dataset was previously described in Hall-McMaster et al. (2019) and is publicly available at https://osf.io/kuzye/.

Participants

Thirty participants aged between 18 and 35 years (mean age: 23 years; 19 females) took part in the study. All participants had normal or corrected-to-normal vision and reported no history of neurological or psychiatric conditions. Participants were compensated at a rate of £8 per hour or received course credit, with the potential to earn up to an additional £10 based on their performance. Ethical approval was granted by the Central University Research Ethics Committee at the University of Oxford, and all participants provided informed consent prior to participation.

Experimental setup and stimuli

The original data collection involved presenting stimuli on a 22-inch screen with a spatial resolution of 1280 × 1024 and a refresh rate of 60 Hz. Stimulus presentation was controlled using Psychophysics Toolbox-3 (Kleiner et al., 2007). Reward cues and feedback were displayed in size 30 Arial font. Task cues and target stimuli had visual angles of approximately 2.52° (100 × 100 pixels) and 1.26° (50 × 50 pixels), respectively, based on an estimated viewing distance of 60 cm. Responses were recorded using the F and J keys on a standard QWERTY keyboard.

Experimental design

In this task (Fig. 1), participants aimed to accumulate as many points as possible by categorizing bidimensional target stimuli based on either their colour (yellow vs. blue) or shape (square vs. circle). On each trial one feature dimension (colour or shape) was task- relevant while the other served as an irrelevant distractor. The relevant feature dimension was indicated by a visual task cue presented before the target onset. Additionally, each trial offered either a high or low reward magnitude for correct responses, signalled at the beginning of each trial by a single pound sign (£; low reward, 5–10 points) or three pound signs (£££; high reward, 50–100 points).

Figure 1. Experimental design. On each trial, the reward cue was presented, followed by an empty-screen delay. A task cue was presented, indicating the relevant feature of the upcoming stimulus to respond to. After a second empty-screen delay, a coloured shape appeared until the participant responded, for a maximum time of 1.4 seconds. Feedback based on both accuracy and speed were given before the inter-trial empty-screen delay.

On each trial, the reward cue (£ or £££) was displayed for 800 ms, followed by a 400 ms delay. Next, the task cue (one of four abstract shapes) appeared for 200 ms, with the mapping of two cues to each task counterbalanced between participants. After a 400 ms delay, the target (a yellow square, blue square, yellow circle, or blue circle) was presented and remained on screen until a response was made or for a maximum of 1400 ms. If the cued task rule was colour, the correct response mapping was *F* for yellow and *J* for blue. If the rule was shape, *F* corresponded to square and *J* to circle. The response phase was followed by 200 ms of feedback. Incorrect responses or omissions resulted in feedback showing 0 points, while correct responses displayed X points, where X varied within the high or low reward ranges based on response time (RT).

RT criteria for different points were initialized so that responses faster than 400, 600, 800, 1000, 1200, and 1400 ms earned 100/10, 90/9, 80/8, 70/7, 60/6, and 50/5 points on high/low reward trials, respectively. For correct trials, the current trial RT was added to an array for its reward condition. Once each array contained more than six values, individualized points criteria were recalculated following Shen and Chun (2011), rewarding responses faster than 95%, 80%, 65%, 50%, and 35% of previous condition RTs with the most to least points. The trial concluded with a randomly selected ITI duration, drawn from a uniform distribution of 1000, 1100, 1200, 1300, or 1400 ms.

Participants were trained to achieve a minimum of 70% accuracy before completing 10 experimental blocks of 65 trials each. Excluding the first trial in each block, equal numbers of reward cues, task cues, stimuli, and ITI durations were presented. The presentation was pseudorandomized to ensure trials were balanced based on task, target congruency, and task sequence for each reward condition. Target congruency referred to whether task-relevant and task-irrelevant features were mapped to the same (congruent) or different (incongruent) response hands. Task sequence referred to whether the task rule was different from the previous trial (switch trial) or the same (repeat trial).

EEG data acquisition and preprocessing

EEG data were recorded using 61 Ag/AgCl sintered electrodes (EasyCap), a NeuroScan SynAmps RT amplifier, and Curry 7 acquisition software (RRID:SCR_009546). The EEG data were preprocessed in EEGLAB (version 14.1.1b; Delorme and Makeig, 2004). EEG analyses were conducted in MATLAB (version 2022b) using the FieldTrip toolbox (revision 3f959be1b; Oostenveld, 2011) along with custom scripts.

EEG data were down-sampled from 1000 Hz to 250 Hz and filtered using a 0.01 Hz high-pass filter and a 40 Hz low-pass filter. For each participant, channels with excessive noise were identified through visual inspection and replaced via interpolation, using a weighted average of the surrounding electrodes. The data were then rereferenced by subtracting the mean activation across all electrodes from each individual electrode at each time point. Data were segmented into epochs ranging from -1000 to 5000 ms relative to the onset of the reward cue. Epochs containing artifacts, such as muscle activity, were rejected based on visual inspection. The data also underwent independent component analysis to remove stereotyped artifacts such as eye blinks. A Laplacian filter was applied to reduce volume conductivity using the spline method with a Legendre polynomial degree of 14. Power spectral density (PSD) was calculated using an 800 ms Hamming window with a 20 ms step, allowing for a frequency range between 1.9531 Hz and 39.0625 Hz, and a frequency resolution of 0.9766 Hz. This resulted in the dataset used for subsequent analyses. Prior to each analysis, data were baseline corrected using a time window

of 600 to 300 ms before the onset of the reward cue, or 250 to 50 ms before the onset of the task or target cues.

Data analysis

We explored how reward modulated oscillatory power, and the effect this had on response times. For this, we observed whether there was a significant effect of reward cue on power across the frequency spectrum. We next tested whether power differences could explain behavioural differences between high and low reward trials by performing a median split analysis. We divided participants into two groups based on the difference between response times in low- and high-reward trials and then examined the reward effect on oscillatory power in both groups. We also performed a correlation to explore potential contributions of different frequency bands over time towards response times.

We used broadband representational similarity analysis (RSA; Kriegeskorte et al., 2008) to replicate the decoding performed by Hall-McMaster et al. (2019). We also used RSA in the time-frequency domain to explore whether multivariate patterns of oscillatory power coded for the different task variables. This method allowed us to explore whether the task variables were encoded within independent frequency bands, and if this modulation occurred at different time windows. By examining the temporal dynamics of frequency-specific neural coding, we aimed to identify distinct periods during which task-relevant information was most prominently represented.

Both of these analyses were performed considering only the trials in which participants responded correctly, across four different regions of interest (ROI): all 61 channels, frontal (AF3, AFz, AF4, F3, F1, Fz, F2, F4), central (C3, C1, Cz, C2, C4), and posterior channels (O1, Oz, O2, PO3, POz, PO4) to explore regional specificity in representing information.

In all EEG analyses, we used one-dimensional (for broadband analyses) or two-dimensional (for time-frequency-based analyses) cluster-based permutation t-tests (10,000 permutations, significance threshold $\alpha=0.05$).

Representational Similarity Analysis

Representational similarity analysis (RSA) is a powerful tool for examining how different cognitive processes are encoded in the brain over time (Kriegeskorte et al., 2008). RSA leverages pattern information that would typically be averaged out in univariate analyses, enhancing its sensitivity to distributed neural activity (Kriegeskorte et al., 2006). This method allows researchers to explore the dynamic nature of neural representations and their modulation by external factors such as reward levels (Hall-McMaster et al., 2019; Luyckx et al., 2019). While this method is commonly used for event-related potential (ERP) decoding (Hall-McMaster et al., 2019; Wei et al., 2023), it also allows for additional dimensions such as frequency bands (Sommer et al., 2022), or channels (Riddeaux, 2024) to be explored simultaneously. Time-frequency RSA has the potential to be applied in various domains, including visual perception, memory, and decision-making, revealing how neural representations change with task demands and contextual factors (Furl et al., 2017; Kikumoto & Mayr, 2020).

We performed this process twice for each participant, once for the broadband decoding and once for the time-frequency decoding. The first step was to calculate the average pattern per condition, obtaining a matrix of channels x time points x frequency points x conditions. Then, the Mahalanobis distance (MD) between each condition was calculated for each time-frequency

point combination using the difference between the power in those conditions, as well as the channel covariance matrix through Equation 1.

$$MD_{AB} = \sqrt{(Power_A - Power_B)^T \times Cov^{-1} \times (Power_A - Power_B)} \qquad (1)$$

We then calculated representational dissimilarity matrices (RDM) of multivariate condition distances for each time-frequency point and for each participant. A total of five 16 x 16 RDMs (two reward levels, two tasks, two colours, and two shapes) were built to capture neural oscillatory patterns related to different task variables (reward, task type, task-relevant and -irrelevant features, and motor coding). These RDMs had zeroes in positions where conditions matched on the variable of interest (e.g., low reward blue square and low reward yellow circle), and ones in the remaining positions. As these RDMs are symmetric, the upper triangular portion of each was transformed into a distance vector (DV) and concatenated before being entered into a linear multiple regression where the time-frequency data (TFD) was the dependent variable, as shown in Equation 2.

$$TFD = \beta_0 + \beta_1 \times rewardDV + \beta_2 \times taskDV + \beta_3 \times task.relevantDV \qquad (2)$$
$$+ \beta_4 \times task.irrelevantDV + \beta_5 \times motor.codingDV + \varepsilon$$

This regression was performed three times considering baseline windows before the onset of the reward, task, and target cues.

Code accessibility

The analysis code, as well the preprocessed data can be accessed at ([link to github to be provided upon acceptance]).

Results

Reward magnitude is decodable in the time-frequency domain along the trial

We used RSA to test for coding of task variables in the time-frequency data (Fig. 2). We first examined neural patterns across all channels or within frontal, central, or posterior regions of interest. Reward decoding was observed in all channels (window tested = 0-3500 ms from reward cue onset), where a cluster in the theta and alpha bands appeared immediately after the reward cue and lasted until shortly before the task cue onset (cluster window = 93-1007 ms, 5.5-15 Hz, corrected p<0.0001). A second, slightly lower-frequency, cluster occurred after the target onset (cluster window = 2253-3007 ms, 2-13 Hz, p<0.0001). In the frontal ROI, a cluster in the alpha band could be observed after the reward cue and lasted until after the onset of the task cue (cluster window = 133-1407 ms, 8.5-14 Hz, p<0.0001). A second cluster in the theta and alpha bands also occurred after the target onset (2253-2967 ms, 2-13 Hz, p=0.0009). There were three clusters in the central ROI: the first one appeared in the high alpha and low beta bands shortly before the task cue and lasted until right before the target cue onset (cluster window = 853-1747 ms, 11.5-15 Hz, p=0.0069). The second cluster also occurred in the alpha and low beta bands after the target cue onset (cluster window = 2373-2907 ms, 9.5-14 Hz). The third cluster was observed between the delta (<4 Hz) and theta bands, also after the target cue onset (cluster window = 2453-3027 ms, 2.5-5 Hz, p=0.0244). Finally, one cluster was found in the posterior ROI in the alpha band after the target cue onset (cluster window = 2513-3027 ms, 8.5-11 Hz, p=0.0423).

The target's task-relevant feature (i.e., blue or yellow on colour trials, and circle or square on shape trials) was only briefly represented in all channels (window tested = 0-2700 ms from the target cue onset), in the low frequencies (cluster window = 153-627 ms, 2-8 Hz, p=0.0001). The task type and the target's task-irrelevant feature (e.g., blue or yellow on shape trials) were not represented in the time-frequency domain (corrected p>0.05). Finally, the (left- or right-hand) response was represented in all channels (window tested = 0-2700 ms from the target cue onset), with clusters in the delta, theta, and lower alpha bands (cluster window = 113-927 ms, 2-10 Hz, p<0.0001), and in the beta band (cluster windows = 193-1067 ms, 15.5-23.5 Hz, p=0.003; 1053-1847 ms, 17.5-24.5 Hz, p=0.0042). In the central ROI, an alpha cluster occurred immediately after the target cue (cluster window = 113-687 ms, 4.5-9 Hz, p=0.0081). A delta-frequency cluster (cluster window = 233-847 ms, 2-3 Hz, p=0.0273), and a large beta cluster (293-2387 ms, 15.5-26.5 Hz, p<0.0001) were also observed briefly after the target cue.

Figure 2. Average decoding of different task-related features in the time-frequency domain. Each row corresponds to a different ROI: all, frontal, central, or posterior channels; and each column corresponds to a different element: reward level, task type, task-relevant and -irrelevant features, and motor coding. Highlighted areas contain significant clusters at the α=0.05 level.

Reward prospect desynchronises alpha-beta oscillations

The multivariate analysis indicated that the pattern of alpha-band oscillations differed somehow between reward levels, but does not reveal what the difference was. To better understand how oscillations differed between reward levels, we next used univariate comparisons of the time-frequency response between reward conditions (Fig. 3). Given that many induced effects might dilute when averaging over all channels together in a univariate analysis, we limited the analysis in this section to each individual ROI to capture localized oscillatory changes.

Relative to the pre-trial baseline, both alpha and beta bands desynchronised throughout most of the trial, particularly in the central and posterior ROIs. When comparing average power between high- and low-reward trials, a significant cluster was observed in the frontal ROI (window tested = 0-3500ms from reward cue onset) in the alpha and beta bands shortly before the target cue (cluster window = 1553-2787 ms, 8.5-18 Hz, p=0.01). Two larger alpha and beta band clusters appeared in the central ROI, after the reward cue onset, and lasted until after the target cue (cluster windows = 293-1362 ms, 16.5-27.5 Hz, p=0.038; 413-2907 ms, 7.5-26.5 Hz, p<0.0001). A strong desynchronisation in the alpha and lower beta bands was observed in the posterior ROI, starting during the reward phase, and ending after the target cue onset (cluster window = 353-2242 ms, 5.5-16 Hz, p=0.003). Finally, a beta synchronisation cluster appeared in the same ROI by the end of the trial (cluster window = 2693-3887 ms, 12.5-19 Hz, p=0.044). Therefore, oscillatory responses to reward prospect manifested in widespread desynchronisation starting at posterior sites in the alpha band spreading to more anterior sites and higher frequencies around the time of the task cue presentation and subsequent task execution.

Figure 3. Average power spectral density for different reward conditions. Each row corresponds to a different trial grouping: low-reward, high-reward, and difference between high- and low- reward trials; and each column corresponds to a different ROI: frontal, central, or posterior channels. Highlighted areas contain significant clusters at the α=0.05 level.

Reward effects on behaviour predict reward sensitivity of alpha-beta modulation

We then subdivided our sample based on a median split of the RT differences between high- and low-reward trials. Participants with larger RT differences unsurprisingly had significantly lower RTs when reward was higher (t(14)=7.0788, p<0.0001) but this difference was only at a trend level in the other half (t(14)=2.0249, p=0.0624).

Moreover, participants with a larger RT benefit on high-reward trials presented significant reward-related desynchronisation in alpha and beta power in the frontal (window tested = 0-3500 from reward cue onset, cluster windows = 313-2367 ms, 20-26.5 Hz, p=0.0027; 873-2827 ms, 7.5-14 Hz, p=0.0212), central (cluster windows = 253-2327 ms, 4.5-22 Hz, p=0.0025; 453-1647 ms, 19-27.5 Hz, p=0.0345), and posterior (cluster window = 313-2227 ms, 5.5-14 Hz, p=0.0053) ROIs (Fig. 4A). By contrast, participants with lower RT differences between reward conditions showed no significant oscillatory modulation (Fig. 4B).

We also performed individual t-tests on the alpha (window tested = 500-2500 ms from the reward cue onset, 8-12 Hz) and beta (window tested = 500-2500 ms from the reward cue onset, 20-30 Hz) power bands to confirm significant differences across reward conditions for each half of the split. For the high-RT-difference group, we found a stronger desynchronisation difference in the frontal ROI for both alpha (t(14)=3.4508, p=0.0039) and beta (t(14)=4.8668, p=0.002) power.

Similar results were observed in the central ROI for alpha (t(14)=2.9199, p=0.0112) and beta (t(14)=2.5818, p=0.0217) power. However, in the posterior ROI, the desynchronisation was only stronger in alpha (t(14)=3.7473, p=0.0022) and not in beta power (t(14)=-0.3535, p=0.729). Conversely, for the low-RT-difference group, there were no desynchronisation differences in the frontal ROI for either alpha (t(14)=0.3942, p=0.6994) or beta (t(14)=-0.7271, p=0.4791) power. Similarly, no desynchronisation was found in the central ROI for alpha (t(14)=1.1707, p=0.2613) or beta (t(14)=1.2329, p=0.2379) power. Finally, no desynchronisation was observed in the posterior ROI for alpha (t(14)=1.7740, p=0.0978) or beta (t(14)=0.1106, p=0.9135) power.

Figure 4. Average power spectral density for participants split by their RT differences in low- and high-reward trials. The first row corresponds to the average difference between high- and low- reward trials, and the second row shows the average alpha/beta power for low (blue) and high (red) reward trials; and each column corresponds to a different ROI: frontal, central, or posterior channels. (A) Participants who had a higher RT difference between reward conditions. (B) Participants who had a lower RT difference between reward conditions. Highlighted areas contain significant clusters at the α=0.05 level. Significance level for pairwise comparisons * = 0.05, ** = 0.01, *** = 0.001.

Individual differences in alpha and beta power predict response times differences between reward levels

While the above analysis showed a strikingly different pattern of results between groups, we did not test whether the groups themselves differed significantly. To further establish the role of oscillatory power during the reward phase and then compare the relative contribution of different oscillations to performance, we next used signed-rank Spearman correlations to confirm that higher alpha power differences translated into a higher RT difference between reward levels across participants. Average alpha power differences (averaged over 500-1000 ms from the reward cue onset and between 8-12 Hz) correlated with RT differences over all channels (ρ=0.3651, p=0.048), as well as the posterior (ρ=0.3628, p=0.0495) ROIs, and there was a trend in the frontal (ρ=0.3571, p=0.0534) ROI. No significant clusters were found in the central (ρ=0.2988, p=0.1089) ROI.

We then used a cluster-based permutation signed-rank correlation test to find time-frequency windows that predicted the RT difference across reward levels (Fig. 5). This revealed two significant clusters in all channels along the trial (window tested = 0-3500 ms from the reward cue onset): one in the alpha band (cluster window = 193-2367 ms, 6.5-14 Hz, p=0.0088), and one in the beta band (cluster window = 353-2067 ms, 22-29.5 Hz, p=0.0116). The beta cluster could also be found in the frontal ROI (cluster window = 353-2647 ms, 22-26 Hz, p=0.0015), while the alpha cluster was observed in the posterior ROI (cluster window = 373-1507 ms, 3.5-11 Hz, p=0.0083).

Figure 5. Correlation between desynchronisation differences and response time differences for low and high reward trials. Each plot corresponds to a different ROI: all, frontal, central, and posterior channels, respectively.

Neural desynchronisation makes a distinct contribution beyond decoding

Finally, we investigated whether the reward-related information in the broadband ERP signal and the oscillatory components observed in the alpha and beta band made independent contributions to the behavioural response. We replicated the ERP decoding approach from Hall-McMaster et al. (2019; Fig. 6A), which found significant reward level decoding throughout the trial (cluster window = 67-2973 ms, p=0.0002). We then calculated partial correlations between the average alpha power differences (averaged over 0-1000 ms from the reward cue onset, between 8-12 Hz), the average decoding (0-1000 ms from the reward cue onset), and the difference in median RTs (RT_{diff}) between reward levels (Fig. 6B).

When averaging alpha power across all channels, signed-rank Spearman partial correlations revealed that stronger ERP-based reward decoding predicted a higher RT_{diff} (ρ=0.4924, p=0.0067), and stronger alpha desynchronisation showed a predicting trend towards higher RT_{diff} (ρ=0.3669, p=0.0503), but there was no correlation between ERP decoding and alpha desynchronisation (ρ=-

0.0277, p=0.8865). Therefore, alpha desynchronisation and reward decoding appear to be independent predictors of performance.

We next tested whether beta desynchronisation also independently predicted performance. When averaging alpha or beta power (0-1000 ms from the reward cue onset, 20-30 Hz) across all channels, signed-rank Spearman partial correlations also revealed that stronger ERP decoding predicted a higher RT_{diff} (ρ=0.4841, p=0.009), and that the alpha and beta desynchronisation were correlated (ρ=0.4169, p=0.0273). However, neither alpha (ρ=0.2609, p=0.18) nor beta desynchronisation (ρ=0.1634, p=0.406) predicted RT_{diff}, possibly because they competed for the same variance since they were themselves correlated. When we restricted alpha and beta power to channels from the frontal ROI, ERP decoding still predicted higher RT_{diff} (ρ=0.5592, p=0.002), but now RT_{diff} was separately predicted by stronger beta desynchronisation (ρ=0.4943, p=0.0075), with no significant correlations between alpha desynchronisation and any of the other measures (p>0.05). Stronger ERP decoding also led to higher RT_{diff} in the central (ρ=0.5021, p=0.0065) and posterior (ρ=0.4708, p=0.0115) ROIs. Interestingly, after taking ERP decoding into account, alpha or beta desynchronization measured in the central or posterior ROIs no longer correlated with RT_{diff} (central alpha: ρ=0.2332, p=0.2324; central beta: ρ=0.2069, p=0.2907; posterior alpha: ρ=0.1479, p=0.4525; posterior beta: ρ=-0.0575 ,p=0.7713), Overall, while decoding seems to be largely independent of both alpha and beta desynchronisation and accounting separately for performance improvements, oscillations in the two bands tended to be highly correlated and therefore accounting for similar variance in RT_{diff}.

Figure 6. Contributions from different band powers and the ERP decoding to RT. (A) ERP decoding replicated from Hall-McMaster et al. (2019). (B) Partial correlations between alpha power, beta power, ERP decoding, and RT_{diff} across reward levels.

Discussion

This study aimed to investigate how reward modulates neural oscillations, and their effects on behavioural performance. We used time-frequency RSA to explore changes in the neural coding of task-related variables, finding significant representations of reward magnitude and motor coding in the spatial pattern of low-frequency oscillatory power. We next looked at desynchronisation changes in different frequency bands as a function of reward, finding that anticipation of larger rewards led to greater alpha and beta desynchronisation. Moreover, across participants the difference in alpha and beta desynchronisation between high and low reward was correlated with differences in RT across reward levels, corroborating the behavioural relevance of reward-related oscillatory changes. Finally, we observed that differences in ERP decoding and oscillatory desynchronisation between reward magnitude conditions were both predictive of reward-induced performance benefits, suggesting independent mechanisms.

We observed that the representation of reward magnitude, features, and responses were distinct in the time-frequency domain. Reward decoding was prominent across all channels and specific regions of interest (ROIs), indicating that reward cues are robustly encoded in the brain's oscillatory activity. Etzel et al. (2016) had previously evidenced that reward cues enhanced neural activity in frontoparietal regions using fMRI recordings. This study replicates these results using EEG recordings, while also providing evidence of both alpha and beta oscillations being involved in this process. The presence of reward-related oscillations in the alpha and beta bands suggests that these frequencies play a crucial role in encoding motivational signals. An interesting difference with the results found in Hall-McMaster et al. (2019) is that the task type could not be decoded in the time-frequency domain. Two possible explanations for this could be that the neural patterns associated with this specific task feature are either only phase-locked, or the main components of the elicited ERPs are contained in lower frequencies that fell outside our analysed frequency range (e.g., below 1 Hz).

Our analysis revealed significant desynchronisation in the alpha and beta bands across different ROIs in high-reward trials. The alpha modulation is consistent with the idea of an increase of allocated attentional resources (Klimesch, 2012; Palva & Palva, 2007) and the subsequent enhancement of task-relevant processing (Foxe & Snyder, 2011; Heuer et al., 2017; Jensen & Mazaheri, 2010) as a function of reward prospect. While the changes in the beta band were unexpected, we believe they could also be related to reward expectation and task cost anticipation (Gheza et al., 2018), task rule retrieval from long-term memory (Hanslmayr et al., 2012), changes in spatial attention (Sauseng et al., 2005; Siegel et al., 2008), or to anticipated visuomotor planning (Kilavik et al., 2013).

We found that participants with higher RT differences between reward conditions exhibited significant desynchronisation changes in alpha and beta power, whereas those with lower RT differences did not show such modulation. This suggests that individual differences in alpha power modulation may underlie variations in cognitive flexibility and performance. Our results are also consistent with Sawaki et al. (2015), who provided evidence of alpha desynchronisation being associated with faster RTs in high-reward conditions. Here, we additionally found that beta-band desynchronisation may also enhance behaviour. These individual differences in reward processing may be related to the participants' intrinsic motivation within the task, as those who are more intrinsically motivated might engage more robustly with the reward cues, leading to greater neural modulation and improved performance (Lee & Reeve, 2017).

The correlational analysis revealed that higher alpha power differences were associated with greater RT differences across reward levels. This relationship was particularly strong in the posterior ROI, between the reward and target cues, and may reflect a shift in spatial attention through an increase in cortical sensitivity towards the upcoming target cue (Klimesch, 2012; Rihs et al., 2009). Beta power differences in the frontal ROI, on the other hand, may indicate enhanced readiness and efficiency in executing the task, driven by the motivational influence of anticipated rewards (Zaepffel et al., 2013). Finally, we found that the ERP decoding through RSA and alpha/beta desynchronisation differences provided individual contributions to the RT differences across reward levels. We believe that the ERP contribution could be a representation of motivation as a function of reward level, as had already been highlighted by Hall-McMaster et al. (2019), while the oscillatory changes may represent a distinct attentional component, showcasing the relevance of exploring multidimensional EEG recording analysis methods to expand on the interaction between ERP and oscillatory components. Interestingly, the partial correlation analysis did not reveal a significant contribution of alpha desynchronisation to RT differences in the posterior region. This could be due to the chosen time window size being larger than the duration of the desynchronisation.

In conclusion, our study highlights the importance of alpha and beta oscillations in the neural coding of task rules and their modulation by reward. Our results provide evidence for reward directly influencing alpha/beta desynchronisation, particularly during the reward cue phase of the task, which then translates into a faster RT. Finally, we found that ERP decoding and alpha/beta modulation contribute independently to behaviour, possibly suggesting that the modulation in the alpha and beta bands might not necessarily be related to a representation of reward, but to an increased engagement with proactive control.

Declaration of Generative AI and AI-assisted technologies

During the preparation of this work the authors used Microsoft Copilot as a peer reviewer and to check for consistency/typographical errors. After using this tool/service, the authors reviewed and edited the content as needed and take full responsibility for the content of the publication.

References

Braem, S., & Egner, T. (2018). Getting a grip on cognitive flexibility. *Current directions in psychological science*, *27*(6), 470-476. https://doi.org/10.1177/0963721418787475

Braver, T. S., Paxton, J. L., Locke, H. S., & Barch, D. M. (2009). Flexible neural mechanisms of cognitive control within human prefrontal cortex. *Proceedings of the National Academy of Sciences*, *106*(18), 7351-7356. https://doi.org/10.1073/pnas.0808187106

Braver, T. S. (2012). The variable nature of cognitive control: a dual mechanisms framework. *Trends in cognitive sciences*, *16*(2), 106-113. https://doi.org/10.1016/j.tics.2011.12.010

Cooper, P. S., Darriba, Á., Karayanidis, F., & Barceló, F. (2016). Contextually sensitive power changes across multiple frequency bands underpin cognitive control. *NeuroImage*, *132*, 499-511. https://doi.org/10.1016/j.neuroimage.2016.03.010

Delorme, A., & Makeig, S. (2004). EEGLAB: an open source toolbox for analysis of single-trial EEG dynamics including independent component analysis. *Journal of neuroscience methods*, *134*(1), 9-21. https://doi.org/10.1016/j.jneumeth.2003.10.009

Etzel, J. A., Cole, M. W., Zacks, J. M., Kay, K. N., & Braver, T. S. (2016). Reward motivation enhances task coding in frontoparietal cortex. *Cerebral cortex*, *26*(4), 1647-1659. https://doi.org/10.1093/cercor/bhu327

Foxe, J. J., & Snyder, A. C. (2011). The role of alpha-band brain oscillations as a sensory suppression mechanism during selective attention. *Frontiers in psychology*, *2*, 154. https://doi.org/10.3389/fpsyg.2011.00154

Furl, N., Lohse, M., & Pizzorni-Ferrarese, F. (2017). Low-frequency oscillations employ a general coding of the spatio-temporal similarity of dynamic faces. *Neuroimage*, *157*, 486-499. https://doi.org/10.1016/j.neuroimage.2017.06.023

Gheza, D., De Raedt, R., Baeken, C., & Pourtois, G. (2018). Integration of reward with cost anticipation during performance monitoring revealed by ERPs and EEG spectral perturbations. *NeuroImage*, *173*, 153-164. https://doi.org/10.1016/j.neuroimage.2018.02.049

Gould, I. C., Rushworth, M. F., & Nobre, A. C. (2011). Indexing the graded allocation of visuospatial attention using anticipatory alpha oscillations. *Journal of neurophysiology*, *105*(3), 1318-1326. https://doi.org/10.1152/jn.00653.2010

Haegens, S., Nácher, V., Luna, R., Romo, R., & Jensen, O. (2011). α-Oscillations in the monkey sensorimotor network influence discrimination performance by rhythmical inhibition of neuronal spiking. *Proceedings of the National Academy of Sciences*, *108*(48), 19377-19382. https://doi.org/10.1073/pnas.1117190108

Hall-McMaster, S., Muhle-Karbe, P. S., Myers, N. E., & Stokes, M. G. (2019). Reward boosts neural coding of task rules to optimize cognitive flexibility. *Journal of Neuroscience*, *39*(43), 8549-8561. https://doi.org/10.1523/JNEUROSCI.0631-19.2019

Hanslmayr, S., Staudigl, T., & Fellner, M. C. (2012). Oscillatory power decreases and long-term memory: the information via desynchronization hypothesis. *Frontiers in human neuroscience*, *6*, 74. https://doi.org/10.3389/fnhum.2012.00074

Heuer, A., Wolf, C., Schütz, A. C., & Schubö, A. (2017). The necessity to choose causes reward-related anticipatory biasing: Parieto-occipital alpha-band oscillations reveal suppression of low-value targets. *Scientific reports*, *7*(1), 14318. https://doi.org/10.1038/s41598-017-14742-w

Jensen, O., & Mazaheri, A. (2010). Shaping functional architecture by oscillatory alpha activity: gating by inhibition. *Frontiers in human neuroscience*, *4*, 186. https://doi.org/10.3389/fnhum.2010.00186

Kaiser, J., & Schütz-Bosbach, S. (2019). Proactive control without midfrontal control signals? The role of midfrontal oscillations in preparatory conflict adjustments. *Biological Psychology*, *148*, 107747. https://doi.org/10.1016/j.biopsycho.2019.107747

Kikumoto, A., & Mayr, U. (2020). Conjunctive representations that integrate stimuli, responses, and rules are critical for action selection. *Proceedings of the National Academy of Sciences*, *117*(19), 10603-10608. https://doi.org/10.1073/pnas.1922166117

Kilavik, B. E., Zaepffel, M., Brovelli, A., MacKay, W. A., & Riehle, A. (2013). The ups and downs of beta oscillations in sensorimotor cortex. *Experimental neurology*, *245*, 15-26. https://doi.org/10.1016/j.expneurol.2012.09.014

Kleiner, M., Brainard, D., & Pelli, D. (2007). What's new in Psychtoolbox-3? *Perception 36 ECVP Abstract Supplement*.

Klimesch, W. (1999). EEG alpha and theta oscillations reflect cognitive and memory performance: a review and analysis. *Brain research reviews*, *29*(2-3), 169-195. https://doi.org/10.1016/S0165-0173(98)00056-3

Klimesch, W. (2012). Alpha-band oscillations, attention, and controlled access to stored information. *Trends in cognitive sciences*, *16*(12), 606-617. http://dx.doi.org/10.1016/j.tics.2012.10.007

Kriegeskorte, N., Goebel, R., & Bandettini, P. (2006). Information-based functional brain mapping. *Proceedings of the National Academy of Sciences*, *103*(10), 3863-3868. https://doi.org/10.1073/pnas.0600244103

Kriegeskorte, N., Mur, M., & Bandettini, P. A. (2008). Representational similarity analysis-connecting the branches of systems neuroscience. *Frontiers in systems neuroscience*, *2*, 249. https://doi.org/10.3389/neuro.06.004.2008

Lee, W., & Reeve, J. (2017). Identifying the neural substrates of intrinsic motivation during task performance. *Cognitive, Affective, & Behavioral Neuroscience*, *17*, 939-953. https://doi.org/2010.3758/s13415-017-0524-x

Luyckx, F., Nili, H., Spitzer, B., & Summerfield, C. (2019). Neural structure mapping in human probabilistic reward learning. *elife*, *8*, e42816. https://doi.org/10.7554/eLife.42816

Oostenveld, R., Fries, P., Maris, E., & Schoffelen, J. M. (2011). FieldTrip: open source software for advanced analysis of MEG, EEG, and invasive electrophysiological data. *Computational intelligence and neuroscience*, *2011*(1), 156869. https://doi.org/10.1155/2011/156869

Palva, S., & Palva, J. M. (2007). New vistas for α-frequency band oscillations. *Trends in neurosciences*, *30*(4), 150-158. http://dx.doi.org/10.1016/j.tins.2007.02.001

Pessoa, L., & Engelmann, J. B. (2010). Embedding reward signals into perception and cognition. *Frontiers in neuroscience*, *4*, 17. https://doi.org/10.3389/fnins.2010.00017

Rideaux, R. (2024). Task-related modulation of event-related potentials does not reflect changes to sensory representations. *Imaging Neuroscience*, *2*, 1-13. https://doi.org/10.1162/imag_a_00266

Rihs, T. A., Michel, C. M., & Thut, G. (2009). A bias for posterior α-band power suppression versus enhancement during shifting versus maintenance of spatial attention. *Neuroimage*, *44*(1), 190-199. https://doi.org/10.1016/j.neuroimage.2008.08.022

Sauseng, P., Klimesch, W., Stadler, W., Schabus, M., Doppelmayr, M., Hanslmayr, S., Gruber, W. R., & Birbaumer, N. (2005). A shift of visual spatial attention is selectively associated with human EEG alpha activity. *European journal of neuroscience*, *22*(11), 2917-2926. https://doi.org/10.1111/j.1460-9568.2005.04482.x

Sawaki, R., Luck, S. J., & Raymond, J. E. (2015). How attention changes in response to incentives. *Journal of Cognitive Neuroscience*, *27*(11), 2229-2239. https://doi.org/10.1162/jocn_a_00847

Shen, Y. J., & Chun, M. M. (2011). Increases in rewards promote flexible behavior. *Attention, Perception, & Psychophysics*, *73*, 938-952. https://doi.org/10.3758/s13414-010-0065-7

Siegel, M., Donner, T. H., Oostenveld, R., Fries, P., & Engel, A. K. (2008). Neuronal synchronization along the dorsal visual pathway reflects the focus of spatial attention. *Neuron*, *60*(4), 709-719. https://doi.org/10.1016/j.neuron.2008.09.010

Sommer, V. R., Mount, L., Weigelt, S., Werkle-Bergner, M., & Sander, M. C. (2022). Spectral pattern similarity analysis: Tutorial and application in developmental cognitive neuroscience. *Developmental cognitive neuroscience*, *54*, 101071. https://doi.org/10.1016/j.dcn.2022.101071

Van Dijk, H., Schoffelen, J. M., Oostenveld, R., & Jensen, O. (2008). Prestimulus oscillatory activity in the alpha band predicts visual discrimination ability. *Journal of Neuroscience*, *28*(8), 1816-1823. https://doi.org/10.1523/JNEUROSCI.1853-07.2008

van Driel, J., Swart, J. C., Egner, T., Ridderinkhof, K. R., & Cohen, M. X. (2015). (No) time for control: Frontal theta dynamics reveal the cost of temporally guided conflict anticipation. *Cognitive, Affective, & Behavioral Neuroscience*, *15*, 787-807. https://doi.org/10.3758/s13415-015-0367-2

Wei, W., Huang, Z., Feng, C., & Qu, Q. (2023). Predicting phonological information in language comprehension: evidence from ERP representational similarity analysis and Chinese idioms. *Cerebral Cortex*, *33*(15), 9367-9375. https://doi.org/10.1093/cercor/bhad209

Worden, M. S., Foxe, J. J., Wang, N., & Simpson, G. V. (2000). Anticipatory biasing of visuospatial attention indexed by retinotopically specific alpha-band electroencephalography increases over occipital cortex. *The Journal of neuroscience: the official journal of the Society for Neuroscience*, *20*(6), RC63-RC63. https://doi.org/10.1523/JNEUROSCI.20-06-j0002.2000

Zaepffel, M., Trachel, R., Kilavik, B. E., & Brochier, T. (2013). Modulations of EEG beta power during planning and execution of grasping movements. *PloS one*, *8*(3), e60060. https://doi.org/10.1371/journal.pone.0060060