Focal Infrared Neural Stimulation Propagates Dynamical Transformations in Auditory Cortex

Brandon S Coventry[a,b,c], Cuong P Luu[d], Edward L Bartlett[a,b,c,e*]

[a]Weldon School of Biomedical Engineering, Purdue University, West Lafayette, IN 47907 USA
[b]Center for Implantable Devices, Purdue University, West Lafayette, IN 47907 USA
[c]Institute for Integrative Neuroscience, Purdue University, West Lafayette, IN 47907 USA
[d]School of Medicine and Public Health, University of Wisconsin-Madison, Madison, WI 53907 USA
[e]Department of Biological Sciences, Purdue University, West Lafayette, IN 47907 USA
[*]Corresponding Author

Abstract

Significance: Infrared neural stimulation (INS) has emerged as a potent neuromodulation technology, offering safe and focal stimulation with superior spatial recruitment profiles compared to conventional electrical methods. However, the neural dynamics induced by INS stimulation remain poorly understood. Elucidating these dynamics will help develop new INS stimulation paradigms and advance its clinical application.

Aim: In this study, we assessed the local network dynamics of INS entrainment in the auditory thalamocortical circuit using the chronically implanted rat model; our approach focused on measuring INS energy-based local field potential (LFP) recruitment induced by focal thalamocortical stimulation. We further characterized linear and nonlinear oscillatory LFP activity in response to single-pulse and periodic INS and performed spectral decomposition to uncover specific LFP band entrainment to INS. Finally, we examined spike-field transformations across the thalamocortical synapse using spike-LFP coherence coupling.

Results: We found that INS significantly increases LFP amplitude as a log-linear function of INS energy per pulse, primarily entraining to LFP β and γ bands with synchrony extending to 200 Hz in some cases. A subset of neurons demonstrated nonlinear, chaotic oscillations linked to information transfer across cortical circuits. Finally, we utilized spike-field coherences to correlate spike coupling to LFP frequency band activity and suggest an energy-dependent model of network activation resulting from INS stimulation.

Conclusions: We show that INS reliably drives robust network activity and can potently modulate cortical field potentials across a wide range of frequencies in a stimulus parameter-dependent manner. Based on these results, we propose design principles for developing full coverage, all-optical thalamocortical auditory neuroprostheses.

Keywords: Infrared Neural Stimulation, Thalamocortical Circuits, Deep Brain Stimulation, Cochlear Implant, Cortex, Chaos, Thalamus.

***Edward Bartlett, E-mail: ebartle@purdue.edu

1   Introduction

Infrared neural stimulation (INS) is a potent optical stimulation modality, utilizing coherent infrared light[1,2] to drive excitatory[3–5] and inhibitory[6] responses in nerves[7–10], neurons[3,11,12], and other excitable cells[13]. Compared to conventional electrical stimulation, INS demonstrates an advantageous spatial recruitment profile with limited spread of off-target activation[3,14,15]. Furthermore, INS safety[16,17] and ablation thresholds[18,19] have been well characterized in preclinical animal models and preliminary human studies. Advancements in implantable fiber optics satisfying the technical demands of therapeutic laser stimulation[20] have made INS an attractive stimulation paradigm for clinical neural modulation in cochlear implants[2,21], deep brain stimulation[3,17], and peripheral nerve stimulation[7,22–24]. However, while INS in the human cerebral cortex has shown focal and reliable responses[17], limited mechanistic understanding of neural entrainment to INS activation has restricted further translation of INS neural modulation into

therapeutic use. Our previous work has shown that thalamocortical INS stimulation evokes short-latency spiking in auditory cortex neurons[3]. Other studies using patch clamp have shown robust inward depolarizing currents in response to infrared stimuli[4,25,26], with some evidence of synaptic modulation at the level of the single neuron[25]. Studies aimed at elucidating the primary driver of neural activation have pointed to thermal gradients[27–29], modulation of cellular lipid bilayers[13,30,31], induction of intracellular calcium cycling[32,33], and direct modulation of voltage gated channels[34] as potential primary drivers of INS neural recruitment. Regardless of the mechanism of excitation, how INS activates brain networks that generates or resets cortical rhythms remains largely unknown. The vast majority of studies of cortical recruitment with INS utilize intracortical INS rather than the natural thalamic inputs to the cortex[11,17,35–39]. While these studies have been foundational in the understanding of INS recruitment of large-scale cortical circuits, studies which utilize thalamic and subthalamic inputs traditionally employed for clinical neuromodulation are necessary to advance knowledge of INS network entrainment and to put INS studies in alignment with current clinical neuromodulation therapies. Such knowledge will facilitate the optimization of INS parameters and design as well as further identification of therapeutic neural targets for clinical use, given that cortical rhythms are critical for the coordination of cortical activities[40–43]. Validation and characterization of cross-network INS entrainment can also position INS as a powerful tool for network neuroscience studies[3,44].

Thalamocortical transformations are critical to the function of higher order neural circuits, performing complex coding to facilitate feedforward fine-tuned encoding of sensory and perceptual input[45–48] with robust intracortical and corticofugal feedback projections allowing for both local and widespread regulation and plasticity[49–53]. Cortex wide processing is often assessed through measurement of local field potentials (LFPs), which function as a readout of grouped electric field activity[54] and closely related transmembrane currents[55–57]. Analysis of band-limited oscillatory LFP activity in θ (4-8Hz), α (8-13Hz), β (13-30Hz), and γ (30-200Hz) can be utilized to assess thalamocortical encoding mechanisms, information transmission, and gain modulation[58] as well as serving as discriminative biomarkers for disease state[59]. Modulation of thalamocortical network function has also been implicated as an important biomarker in therapeutic deep brain stimulation[60–64], exemplified by effective DBS stimulation showing rapid reduction in β band activity and transient increases in high γ band activity in Parkinson's disease[65–67]. Therefore, to realize the clinical and basic science potential of INS, a fuller understanding of the INS parameter-dependent induced network transformations is necessary.

In this study, we assess thalamocortical transformation and encoding of INS stimulation through chronic local field potential recordings in the rat. We quantify LFP INS dose-response characteristics while showing entrainment of INS primarily within β and γ LFP frequency bands. We also utilized LFP and single unit correlations to quantify dynamic transformations in the auditory thalamocortical circuit. To assess nonlinear dynamics of INS stimulation, we utilize tests for chaos dynamics to show that the auditory cortex contains neurons which exhibit chaotic neural dynamics that are directly modulated by INS stimulation of the thalamus. We further quantify single-unit spike contribution to LFP oscillatory activity through spike-field coherence measures, showing spike entrainment primarily through β and γ bands. Finally, owing to the observed neural encoding dynamics in this study, we provide guidance for use of INS as a thalamic auditory neuroprosthesis.

2　Materials and Methods

All experimental and surgical procedures and protocols were approved by the Institutional Animal Care and Use Committee (PACUC) of Purdue University (West Lafayette, IN, #120400631) and in accordance with the guidelines of the American Association for Laboratory Animal Science (AALAS) and the National Institutes of Health guidelines for animal research.

2.1 Surgical Procedures

Detailed INS optrode and electrode implant procedures can be found in the following protocol[68]. Briefly, adult Sprague Dawley rats weighing between 300-400g (Envigo, Indianapolis IN) were initially anesthetized with 5% isoflurane in O_2 (1.2 mL/min flow rate) followed by a bolus intramuscular injection of a ketamine/dexmedetomidine cocktail ($70\frac{mg}{kg}$ ketamine, $0.2\frac{mg}{kg}$ dexmedetomidine) to achieve a surgical plane of anesthesia. Rats were given an intramuscular injection of Buprenorphine ($1\frac{mg}{kg}$) for analgesia at least 30 minutes prior to first incision. After induction, rats were transferred to a stereotaxic frame secured by hollow ear bars. Animal heart rate and pulse oximetry were monitored throughout the duration of the surgery and recovery, with anesthetic surgical plane assessed via lack of toe-pinch reflex every 15 minutes. An initial incision was made over midline and the periosteum removed via blunt dissection to reveal cranial sutures. Three stainless steel bone screws were placed in the skull to provide stability for implanted devices and headcap with a fourth titanium bone screw secured to the skull to serve as recording electrode ground and reference. A craniectomy was made above auditory thalamus (-6 anterior/posterior, -3.5 medial/lateral, -6 dorsal/ventral) and a fiber optic optrode (Thor Labs, Newton, NJ, USA, $200\mu m$ fiber diameter, 0.22 NA) was slowly advanced and placed in the medial geniculate body. The optrode was sealed into place using UV-curable dental acrylic (Pentron, Wallingford, CT, USA). Next the right temporalis muscle was gently reflected off the skull and a 2x2 mm craniectomy was made over auditory cortex. Dura mater was gently resected using a 25G bent tip needle. A 2 mm × 2 mm 16 channel microwire array (TDT, Alachua, FL, USA, electrode spacing given in Fig. 1A) was slowly inserted perpendicular into auditory cortex. Broadband 80dB-SPL gaussian-noise stimuli were applied to the contralateral ear during electrode insertion to putatively confirm putative placement of recording arrays into primary afferent layer III/IV as evidenced by recordings of short latency, high amplitude multiunit activity entrained to auditory stimuli. One animal received 3 mm linear recording array (NeuroNexus A1-16, $200\mu m$ between contacts) in layer III/IV of auditory cortex. Devices were sealed into placed by the application of Qwik-Sil (World-Precision Instruments) to seal the craniectomy followed by application of UV-curable dental acrylic. A low profile headcap was completed to ensure device stability. After the completion of the surgery, animals were returned to their home cage and allowed to recover for at least 72 hours. Supplemental Buprenorphine analgesia was administered every 6-12 hours for a minimum of 72 hours. A total of 5 rats had functional longitudinal optrode and electrode implants and were included in the study.

2.2 Infrared Stimulation

Optical stimulation was provided by INSight, our custom designed, open source optical neuromodulation platform[3,69] using a 1907 nm semiconductor laser module(Akela Trio, Jamesburg, NJ, USA) fiber coupled to the implanted optrode(Thor Labs FG200LCC). Laser pulse train stimuli were controlled via analog outputs of a RX-7 stimulator base-station (Tucker-Davis

Technologies, Alachua FL) with laser energies between 0-4 mJ constrained below ablation
thresholds[19] with interpulse stimulation intervals between $0.2 - 100$ms. Optical stimulation was
provided by INSight, our custom designed, open source optical neuromodulation platform[3,69] using
a 1907 nm semiconductor laser module(Akela Trio, Jamesburg, NJ, USA) fiber coupled to the
implanted optrode(Thor Labs FG200LCC). Laser pulse train stimuli were controlled via analog
outputs of a RX-7 stimulator base-station (Tucker-Davis Technologies, Alachua FL) with laser
energies between 0-4 mJ constrained below ablation thresholds[19] with interpulse stimulation
intervals (ISI) between $0.2 - 100$ms.

2.3 Electrophysiological recordings

LFP and multiunit activity was recorded across all channels of the implanted recording array (Fig
1B). All recordings were performed in a $9' \times 9'$ electrically and acoustically isolated chamber
(Industrial Acoustics Corporation, Naperville, IL, USA) with laser electronics placed outside of
the chamber to prevent field interactions from large magnitude current pulses[70,71]. Rats were given
intramuscular injections of Dexmedetomidine $\left(0.2\frac{mg}{kg}\right)$ sedative[72–74] to reduce movement artifact
disruptions in neural recordings. Each recording trial was composed of a 200 ms prestimulus
interval to facilitate spontaneous rate calculations followed by application INS with total trial
lengths equal to 1s. INS laser energies were randomized to limit stimulus adaptation effects with
30-60 trials per INS energy. Signals from implanted recording arrays were amplified via a Medusa
preamplification headstage (Tucker-Davis Technologies) and discretized with a sampling rate of
24.414kHz (TDT standard sampling rate) and recorded into a RZ-2 bioprocessor (Tucker-Davis
Technologies). Real-time visualization of recorded signals was made using OpenEx software, with
Spike channel bandpass filter cutoffs set to $0.3 - 5$kHz and LFP channel bandpass filter cutoffs
set to $3 - 300$Hz.

2.4 Data Processing and Analyses

All data analysis was performed on a Windows-based computer with a Xeon 16 core processing
and an Nvidia Titan X GPU for parallel and multithreaded processing. LFPs were down sampled
to a sampling rate of 1526 Hz for analysis. Multiunit signals were exported and processed using
custom-written programs in the Matlab programming environment (Mathworks, Natick MA).
Multiunit activity was sorted into single units using wavelet-based superparamagnetic clustering
methods in Wave-Clus[75]. Spikes were then derandomized and sorted into spike-time rasters and
exported to Python for further analyses.
165
166 Time-domain INS dose response curves were quantified by first high-pass filtering raw LFPs to
167 remove slow-baseline drifts (10 Hz filter cutoff, Chebyshev Type II high-pass filter). Evoked LFP
168 onset amplitudes were quantified as the root-mean-squared (RMS) magnitude between stimulus
169 onset through the first negative (N1)-second positive (P2) peaks. Dose-response characteristics
170 were then quantified through Bayesian multilinear regressions (see 2.8 Statistical Inference).
171
For LFP frequency band analyses, raw mean LFPs were decomposed into θ (4-8Hz), α (8-13Hz),
β(13-30Hz), low γ (30-80Hz), and high γ (80-200Hz) using the continuous fast wavelet
transform[76]. CWTs were utilized over short-time Fourier transforms as CWTs have been found to
provide better frequency resolution in non-stationary field potential recordings[77]. For frequency

band analyses, the 10Hz high pass filter was not applied, with recorded signals only filtered by
hardware high pass filters (cutoff = 3Hz). The total power in a frequency band was calculated as

$$P_f = 2 * \int S_f df$$

179 where S_f is the band-power spectral density from wavelet decomposition and the factor of 2
180 included to account for frequency folding inherent to time-frequency decomposition. Numerical
181 integration was performed using Simpsons rule[78]. Stimulus-induced changes in frequency bands
182 from baseline was quantified as:

$$dB_{\Delta\theta,\alpha,\beta,\gamma} = 10log_{10}\left(\frac{P_f}{\mu_b}\right)$$

184 Where μ_b is the mean power in the 200ms prestimulus window respectively.
185
186 *2.5 Temporal Modulation Transfer Functions*
187
To assess the sensitivity of INS-evoked LFPs to stimulus ISI, temporal modulation transfer
functions (tMTF) were calculated. Fast-Fourier transforms (FFT) from raw LFPs were calculated
using Bluestein's method[79] in Python. FFTs were calculated for baseline LFPs 200ms prior to
stimulation onset and for stimulation windows consisting of the stimulation time + 100ms for
longer lasting LFP responses. Spectral power at the stimulus ISI frequency was extracted from
baseline and stimulation condtions with analysis completed for ISI frequencies < 763 Hz to ensure
the Nyquist sampling criterion was met. Change in LFP power from baseline at the ISI frequency
was calculated as:

$$tMTF = 10 \log_{10}\left(\frac{P_s}{P_B}\right)$$

197 where P_s, P_B are the LFP power at the ISI frequency for stimulation and baseline windows
198 respectively. ISI modulation was considered significant if the tMTF had a value of ≥ 3 dB
199 corresponding to a doubling in LFP-ISI power from baseline.
200
201 *2.6 Estimation of Chaotic Cortical Dynamics*
202
To estimate the criticality and chaoticity of LFP cortical dynamics, a modified 0-1 test was used[80–
82]. The 0-1 test assesses the degree of chaotic dynamics in recorded time series of deterministic
dynamical systems by mapping dynamics to a 2D space of the form:
$$p(n + 1) = p(n) + \varphi(n)cos\,(c * n)$$
$$q(n + 1) = q(n) + \varphi(n)sin\,(c * n)$$
where φ(n) is the discretized LFP timeseries and c is a random value between $\frac{\pi}{5}, 4\frac{\pi}{5}$. The range of
c helps prevent overestimation due to mapping system resonance[81]. The dynamics of the system
$p(n), q(n)$ are such that regular, non-chaotic dynamics are bounded, and chaotic dynamics are
unbounded and show movement similar to 2D Brownian motion process, and thus exhibit diffusive
growth proportional to $\sqrt{n}$. [81]. Examples of $p(n), q(n)$ systems for non-chaotic and chaotic
dynamics are shown in Fig S1. From the new $p(n), q(n)$ system, the time-averaged mean squared
displacement is calculated as:

$$M_{disp}(n) = \lim_{N\to\infty} \frac{1}{N} \sum_{i=1}^{N} \left(\left(p(i+n) - p(i)\right)^2 + \left(q(i+n) - q(i)\right)^2\right) + \sigma\rho_n$$

216   where ρ_n is a uniformly distributed random variable between $(-\frac{1}{2}, \frac{1}{2})$ with σ the noise perturbation
217   amplitude, set to 0.5 with N corresponding to the total number of samples contained in the time
218   series. It can be shown that $\lim_{N \to \infty}$ exists[81]. In practice, M_{disp} is calculated for $n \leq N_0$ where $N_0 \ll$
219   N. A value of $N_0 = \frac{n}{10}$ was chosen as it shows good performance on LFP timeseries[82,83]. The
220   asymptotic growth rate of M_{disp} is then calculated as:

221
$$K = \frac{\log M_{disp}(n)}{\log n}$$

K thus describes a measure of "boundedness" of the system, scaled between (0,1), with 0
corresponding to bounded periodic dynamics and 1 corresponding to unbounded, chaotic
dynamics. K values on the continuum between (0,1) thus represent degrees of unbounded growth.
As periodic and aperiodic dynamics are sensitive to values of c, K is computed for 100 iterations
of the 0-1 test with c randomly drawn from a uniform distribution with support $(\frac{\pi}{5}, 4\frac{\pi}{5})$. The
median asymptotic growth rate coefficient is then calculated as:

228
$$K_c = median\left(\frac{cov(M, n)}{\sqrt{\sigma^2(M)\sigma^2(n)}}\right)$$

229   where $M = (M_{disp}(n)_{c1}, M_{disp}(n)_{c2}, \dots, M_{disp}(n)_{c100})$ and σ^2 is the variance operator. Code for
230   0-1 testing was adapted and modified from the Chaos decision tree toolbox[82].
231
Information content contained within LFPs was calculated using estimation of Shannon mutual
information (MI). MI quantifies the reduction in uncertainty in neural responses (R) given
knowledge of a particular stimulus (S_x) and thus quantifies thalamocortical encoding and
separability of differing INS stimuli. Stimulus-Response $p(r|s_x)$ and total response $p(r)$
probability density functions were estimated from total LFP responses using kernel density
estimation with a total of 21 bins. Optimal bin counts were calculated using the Doane estimate[84],
which is robust for potentially non-normal distributions. MI was calculated using the methods of
Borst and Theunissen[85] as:

240
$$I(R; S_x) = \sum_i p(r_i|s_x) \log_2\left(\frac{p(r_i|s_x)}{p(r_i)}\right)$$

241   Bias in estimates of $I(R; S_x)$ due to imperfect knowledge of probability density functions was
242   corrected using the methods of quadratic extrapolation[72,86,87] as follows:

243
$$I_{estimate} = I_{true} + \frac{a}{N} + \frac{b}{N^2}$$

244   where N is the number of trials used in the MI estimate and a, b are free parameters corresponding
245   to stimulus-response dependence on sample size and is learned by least-squares regression from
246   calculations of MI with sample sizes of $N, 0.50N$, and $0.25N$. All information measures are
247   reported after bias correction.
248
249   *2.7 Spike-Field Coherence Measures*

250   Spike-field coherence (SFC) measures were calculated to assess the band frequency in which
251   spikes and LFPs are consistently entrained as a function of applied energy. Electrodes showing
252   both LFP activity and graded single-unit firing rates in response to INS were included in this
253   analysis. SFCs were calculated as:

254
$$SFC = \frac{|\langle S_{ny,j} \rangle|}{\sqrt{\langle \overline{S_{nn,j}} \rangle} \sqrt{\langle \overline{S_{yy,j}} \rangle}}$$

255 where $|\langle S_{ny,j} \rangle|$ is the magnitude of the trial-averaged cross power spectral density between per-
256 trial j spike train n and LFP y, $\langle \overline{S_{nn,j}} \rangle$ the trial-averaged auto power spectral density of spike train
257 n across trial j, and $\langle \overline{S_{yy,j}} \rangle$ the trial-averaged auto power spectral density of the LFP y across trial
258 j. SFCs were calculated using the Electrophysiology Analysis Toolbox[88] synched in Python to
259 SPyke across all applied INS energies.
260
261 *2.8 Statistical Inference*
262
Statistical inference was performed using Bayesian inference methods[89–92]. Bayesian methods
allow for robust quantification of parameter effects and model uncertainty driven purely by
observed data with robust model validation controls. Hierarchical Bayesian models are
particularly suited for analysis of repeated measures designs and provides robust control of within
and between subject variance[89] such as this study. Significance of effect was assessed using
observations of posterior distribution 95% highest density intervals and credible regions, in line
with Bayesian convention[90–92]. Bayesian inference requires explicit declaration of prior
distributions that quantify current state of knowledge. Prior distributions for each model are
described below and are weakly informative and have minimal effect on posterior distributions
owing to relative scarcity of data surrounding auditory cortex cortical oscillations in response to
INS. Bayesian inference reporting follows the Bayesian analysis reporting guidelines outlined in
[93] with posterior predictive checks of model fits to data and prior sensitivity checks reported in the
supplementary material. Statistical significance is summarized in posterior maximum a priori
(MAP) estimates of model parameters and posterior highest density intervals (HDIs) and credible
regions in Bayesian inference convention.
278
279 Changes in LFP RMS magnitude and frequency band power as a function of applied energy were
280 assessed via Bayesian Hierarchical Linear Regressions (BHLR). The hierarchical structure of
281 BHLR allows for accommodation of within and between subject variance necessary for repeated
282 measures designs. BHLR take the form of:
283
284
$$LFP_{RMS} = \beta_0 + \beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}(E * ISI) + \epsilon$$
285
$$max\left(dB_{\Delta\theta,\alpha,\beta,\gamma}\right) = \beta_0 + \beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}(E * ISI) + \epsilon$$
286
Where E corresponds to energy per pulse, ISI corresponding to interpulse stimulus interval, and
$(E * ISI)$ corresponds to an energy per pulse and interpulse stimulus interval interactions. The β_0
and ϵ represent the regression intercept and model error respectively. Model comparison through
leave-one out (LOO) criterion[94] suggested that natural log transformation of response and
independent variables provided regression models that best fit observed data (model comparisons
show in supplementary information) in both regression modles. The $\beta_{x,i}$ terms correspond to
regression slope coefficients for each factor for each electrode/animal group i. Full model structure
is shown in Fig S2. Priors were set as broad, uninformative normal priors. Prior sensitivity analyses
were performed to assess the quality of statistical model fit to data and are given in supplementary
information. Regression parameters were considered significant if their 95% HDI and credible

intervals, summarizing the range in which there is a 95% probability that the true estimate of the
regression coefficient lies in the interval given evidence from observed data, does not contain 0 in
line with Bayesian convention[90,93]. Results are presented as the maximum *a priori* estimate (95%
credible interval) of each regression parameter.

LFP frequency band correlations were quantified as Pearson's R correlation coefficient in the
Scipy environment. Significance of correlation was assessed as a two-sided p-value, which if given
the measured value R and a surrogate measure $\overline{R}$, representing the correlation coefficient between
shuffled input timeseries, is the probability of $\left|(\overline{R})\right| \geq |(R)|$. Significance level for correlation
analysis was set to $\alpha = 0.05$.

Spike rate, N1-P2 LFP RMS amplitude correlations were assessed using Bayesian linear
regressions of the form:

$$LFP_{N1-P2\ RMS} = a + ln(\beta_1 * spike\ rate) + ln(\beta_2 * ISI)$$

where a is the regression intercept coefficient, spike rate corresponds to average spike rate within
the stimulus interval plus a 50 ms offset interval, ln corresponds to a natural log transform, and
β_1, β_2 are the slope coefficients for spike rate and ISI predictors respectively. Priors were set as
broad, uninformative normal priors set on regression parameters. Regression parameters were
considered significant if their 95% HDI and credible intervals, summarizing the range in which
there is a 95% probability that the true estimate of the regression coefficient lies in the interval
given evidence from observed data, does not contain 0. Results are presented as maximum *a priori*
estimate of the regression parameters (95% credible interval).

Increases in spike-field coherence as a function of applied INS energy was assessed through
Bayesian linear regressions of the form:

$$SFC = \alpha + \beta * E$$

325 where α is the intercept coefficient and β is the slope coefficient corresponding to applied natural
326 log INS energy per pulse (E). Observations of SFCs showed that some bands displayed jump
327 discontinuities in regression parameters (Fig. S6), necessitating piecewise linear regression models
328 to capture off vs on states. Piecewise linear regressions were implemented as Bayesian basis spline
329 regression models[95] of the form:

$$SFC = \alpha + \beta_i * w_i * E$$

333 where α is the intercept term and β_i is a spline defined as:

$$\beta_i = \begin{cases} non-zero & if\ t_i < t \\ 0 & otherwise \end{cases}$$

336 where t is the point of concatenation of the piecewise linear regions known as a knot. The w term
337 is a learned parameter with the regression slope of each piecewise region described by

$$\beta = \beta_i * w_i$$

Knot positions were determined by calculating the derivative of the mean SFC as a function of
INS energy per pulse and estimating the energy point of a step discontinuity. Knots were confirmed
after Bayesian estimation of regression parameters by plotting the domain of each spline to confirm
that each spline term only impacts the defined domain above and below the knot. If domain
influence significantly overlapped, knots were redefined and models recomputed. Regression
parameters were considered significant if their 95% HDI and credible intervals, summarizing the
range in which there is a 95% probability that the true estimate of the regression coefficient lies in
the interval given evidence from observed data, does not contain 0. Results are presented as
maximum *a priori* estimate (95% credible interval) of the regression parameters.

2.9 Code, Data, and Materials Availability

Data from this study has been deposited into the following open science framework repository:
10.17605/OSF.IO/JRN65. All source code used in this study is hosted at the following GitHub
repository: https://github.com/bscoventry/Focal-Infrared-Neural-Stimulation-Propagates-
Dynamical-Transformations-in-A1 . A free-standing version of Spyke for LFP analyses can be
found in the following GitHub repository: https://github.com/bscoventry/SPyke. Due to online
data repository storage limits, raw spike and LFP traces are available upon request.

3 Results

3.1 Variation of INS Stimulus Parameters Drives Graded LFP Recruitment

To first quantify thalamic recruitment as a function of INS laser parameters, INS dose-response
characteristics were modeled using Bayesian hierarchical linear regression (BHLR). BHLR
modeled linear changes in LFP RMS voltage between N1-P2 peaks response as a function of INS
laser energy-per-pulse, laser ISI, and laser energy-ISI interactions. Regression parameters were
summarized by their maximum *a priori* (MAP) estimate (i.e. most probable value) with
independent variables considered significant contributors to response if the highest-density
interval (HDI) of the parameter distribution corresponding to the 95% most probable parameter
values did not overlap 0, following Bayesian inference convention. The 95% HDI credible
intervals (CI) are reported to assess uncertainty in parameter estimates. The hierarchical structure
of the linear regression model allows for control of both within and between subject variances due
to slight differences in electrode placements between animals and active recording channels. All
statistical models, sensitivity analyses, and posterior predictive checks are given in the
supplementary material. Example subthreshold and suprathreshold LFPs are shown in Fig. 2A.
BHLR model responses show that modulation of cortical activity is primarily driven by laser
energy per pulse $(\beta_1 = 0.087, CI: 0.059, 0.12)$ and laser ISI$(\beta_2 = 0.065, CI: 0.018, 0.11)$. There
was no significant interaction between laser energy and ISI parameters$(\beta_3 =$
$-0.0038, CI: -0.0061, 0.0038)$. Model error was significantly greater than 0, but low in
magnitude$(\epsilon = 0.51, CI: 0.47, 0.57)$. The relatively high spread of the energy-per-pulse slope
parameter CI suggests a heterogeneity in feedforward thalamocortical activation with increases in
laser energy. While increases in LFP magnitude as a function of energy are in line with our

previous studies showing that auditory thalamocortical single-unit responses were driven primarily
by INS laser energy-per-pulse[3], the dependence of ISI was not seen in single-unit data.

3.2 Frequency Band Decomposition

We next quantified the role of thalamic recruitment in modulation of α, β, θ, low γ, and high γ
bands. Time-frequency decomposition of LFPs into constituent frequency bands was performed
using continuous wavelet transforms (CWT). A representative example of the LFP spectrogram is
shown in Fig. 3A in response to 5 pulses of 3.1 mJ per pulse INS (red line). Pre-stimulus activity
was low in all measured frequency bands. INS stimulation elicited a short latency LFP frequency
response that showed increased power for frequencies up to about 30 Hz that lasted for hundreds
of milliseconds after stimulus offset and approximately 300 ms afterwards. Statistics for the
evoked LFP frequency responses are summarized in Table 1. Total band power during onset
periods (stimulus window + 100ms) and offset (after onset to end of trial) were calculated. We
found significant increases in all frequency bands during stimulation (Table I, Energy slope) as a
function of increased energy per pulse. However, band increases were dominated by β-
band$(\beta_{energy} = 0.17, CI: 0.089, 0.25)$, low γ-band $(\beta_{energy} = 0.34, CI: 0.21, 0.47$, and high γ-
band $(\beta_{energy} = 0.49, CI: 0.32, 0.67)$ with data and regression estimates shown in Fig 3B. There
was an observed marginal increase θ and α LFP band modulation as a function of decreased ISI
$(\beta_{ISI\theta} = -0.016, CI: -0.031, -0.006, \beta_{ISI\alpha} = -0.075, CI: -0.1, -0.054)$. This is indicative
of neural integration of multiple pulses into singular impulse events, potentially driving lower
frequency onset band responses at lower thresholds. We next examined band activity in the offset
period defined as a post stimulation period of 100 ms after stimulus offset to the end of the trial,
which ends at $t = 1$ second. Unlike during stimulation, we found significant decreases in α, β, θ,
and low γ band power from baseline as a function of applied energy (Table I). The high γ band,
however, did not show any significant INS energy-induced decrease in power. The offset decrease
was also most prominent in β and low γ bands (Fig 3C). This data is consistent with a post-
stimulation synaptic inhibition which was also observed in postsynaptic firing in our previous
studies[3]. We next assessed the linear covariance between onset and offset β − low γ, β − high γ,
and low γ − high γ band powers using Pearson correlation coefficient analysis from responses
binned into $500\mu J$ bins. Individual frequency bands represent multiscale cortical processing
incorporating feedforward excitatory spiking activity, local inhibitory interneuron signaling, and
feedback projection activity[96–99]. Pairwise correlations showed increases in positively correlated
activity with increased energy per pulse, with β − low γ showing the strongest positive
correlations (Fig 3D). However, the presence of outliers with strong negative correlations suggests
that there is heterogeneity in INS driven LFP responses. LFP band correlations in the offset region
did not show any pairwise changes in correlated activity (Fig 3E) suggesting covarying band
activity is only driven in the INS stimulation window.
413
To evaluate the impact of ISI on LFP entrainment during infrared neural stimulation (INS),
temporal modulation transfer functions (tMTFs) were computed. These were defined as the
deviation from baseline in ISI frequency power, serving as a metric for the LFP's synchronization
to INS pulses. Results are presented as tMTFs across ISI frequencies and INS energy per pulse bin
(Figure 4), with the proportion of LFPs exhibiting significant changes ($\geq$3 dB magnitude from
baseline) summarized in Table II. Our findings indicate that LFPs tend to entrain at lower
frequencies (longer ISIs) under moderate stimulation conditions (~2 mJ per pulse). The

preferential response to low frequency ISIs at lower energy levels may be explained by shorter ISI
being integrated by neurons as singular, longer width pulses. However, increases in INS energy
begin to entrain higher frequency ISIs, potentially due to rapid thermal energy gradients which are
known to facilitate rapid, low latency responses[29]. However, these trends are not universally
represented across all energy bins, with 2-2.5 mJ per pulse bins showing significant responses for
20,40,100 and 200Hz ISIs respectively. Despite this variability, the overall trend of increases in
ISI power bands (Table II) suggests that LFP phases generally entrain to INS pulse frequency up
to 40Hz and with weaker but significant entrainment even to 100 and 200 Hz stimulation rates.
This finding is in alignment with studies showing cortical neuron entrainment to click trains
peaking at 50-75Hz repetition rates and weaker entrainment at higher frequencies[100,101]. While
more responses showed increases in ISI-band power, some responses demonstrate significant
decreases in ISI-band power, indicative of inhibitory entrainment to INS stimulation. This mix of
excitatory and inhibitory responses is suggestive of the extensive network modulatory capability
of INS. Variability in maximal entrainment frequencies may be further described by exact
receptive field placement of recording arrays in A1 which show differential tMTF responses to
click stimulation[102] or the use of dexmedetomidine sedatives which may alter temporal
processing[103,104].

3.3 Nonlinear Analysis Reveal Distinct Information Transformation from INS

Previous studies in thalamocortical connectivity have shown that thalamocortical encoding and
function is supported by varying states of high and low information transmission capacity which
exhibit chaotic or near chaotic dynamics[83], a state which is called criticality. Criticality may be a
feature inherent to normally functioning neural circuits allowing for rapid adaptation to new
homeostatic set points from salient stimuli [105,106] or as amplification mechanism of synaptic
events[107]. To assess the changes in network criticality as a function of INS, the 0-1 test for chaos
was used to assess the degree of criticality in a response as a function of the mutual information
of stimulus to response. The 0-1 test produces a chaos statistic K describing a measure of
"boundedness" of the system, scaled between (0,1), with 0 corresponding to bounded periodic
dynamics and 1 corresponding to unbounded, chaotic dynamics. Description and applications of
the 0-1 test on canonical nonlinear and chaotic systems can be found in the supplementary methods
section (Supp. Fig 1). As the 0-1 test for chaos struggles to delineate true deterministic chaos from
stochastic responses, a secondary permutation entropy test for stochasticity[108] was performed on
responses, with only strongly non-stochastic responses included in analysis. After testing for
stochasticity, 0.92% of responses exhibited dynamics suitable for criticality measurements. Initial
inspection of degree of criticality vs mutual information suggested an inflection point where
responses diverged from highly chaotic responses to mixed high and low chaotic responses (Figure
5). Responses were then clustered using K-means clustering into 2 groups, with total number of
classes chosen by the Silhouette method[109]. Chaos vs mutual information clustering suggests a
fundamental regime change as evidenced by a bifurcation at informative stimulation > 0.4 bits
that produces responses which tend toward more deterministic firing as evidenced by lower K-
statistic values (Fig 5), suggesting that sub and near-threshold basal firing can exhibit chaotic
dynamics. The nature of chaotic dynamics facilitate a high sensitivity to perturbations of the
network, which has been demonstrated in computational studies of cortical neurons[110]. Thus, the
observed auditory neurons showing chaotic responses may allow for rapid adaptation to temporally
complex stimulation[111] which may not be necessary when highly informative stimulation activates
well-defined thalamocortical networks. This transition to purely deterministic dynamics is not

complete, however, as there exists a subset of responses which maintain highly chaotic firing
patterns in tandem with high mutual information. This state represents responses which are
separable by applied INS energy which still exhibit drastically varying response profiles, and thus
suggests field-potential responses which are continually at the edge of criticality. This potentially
is a result of groups of neurons which naturally exhibit chaotic dynamics as part of normal cellular
processing by facilitating the encoding of rapidly changing sensory[112] or synaptic[107,113] inputs.

3.4 LFP Amplitudes are Correlated with Evoked Spike Rates

We next investigated the correlation between driven single unit responses (stimulation spike
rate$\geq$ 1.75 basal firing rate) and LFP N1-P2 RMS amplitudes. Bayesian linear regressions (Fig 6
A,B, Bayesian P-value Fig. S5) suggest that LFP N1-P2 RMS amplitudes increase with increased
natural log-transformed spike rate $(\beta_{spikerate} = 1.8, CI: 1.7,2)$ and decreased RMS amplitudes
with increased natural log-transformed ISI $(\beta_{ISI} = -0.047, CI: -0.059, -0.037)$, suggesting
sublinear LFP summation for short-interval pulses. Comparing responses from fixed ISIs (Fig 6
C-E) suggested that short ISI pulse trains integrate to produce higher amplitude N1-P2 LFP and
spike rate responses while longer ISI trains produced lower LFP and spike rate responses
indicated of discrete pulse events driving moderate responses. Similar spike-LFP synergies have
been observed in sensory regions across cortex in response to sensory stimulation[114–116] and is
suggestive that INS can elicit sensory relevant responses in cortex.

3.5 Dual Regime Synaptic Transformations Are Driven by INS

Firing of thalamocortical neurons, whether driven by sensory, motor, cognitive, or INS
stimulation, induces a rapid reorganization of local cortical activity due to spiking and synaptic
activities[45,117,118]. We utilized spike-field coherence (SFC), a measure of system causal input-
output power transfer, as a function of applied INS energy to assess frequency-band specific
network modulation. Dependence of spike-LFP coherence on INS laser parameters was then
assessed using Bayesian multilinear regressions, with all results presented in table III. SFC
regressions are shown in Fig 7A. Regressions revealed a slow increase in high γ SFC
$(\beta_{high\,\gamma} = 0.015, CI: 0.015, 0.016)$ in response to log increase in INS energy. Increases in γ-band
SFC are linked to faster afferent spiking activities[98,119] as well as parvalbumin(PV)-expressing
interneuron activities[120], suggesting that increased INS energy drives increased LFP to spiking
activity with putative interneuron recurrent inhibition, similar to what has been seen in electrically
mediated neural recruitment[121]. This is also consistent with our previous results showing log-linear
increases in spiking activity with increased INS energy[3]. Studies utilizing electrical stimulation of
auditory thalamocortical circuits display similar interlayer side-band inhibition[122] which can
putatively be attributed to interneuron inhibition. Observation of low γ regressions suggested the
presence of a nonlinear discontinuity in spike-field coupling (supplementary figure S6),
necessitating a piecewise linear regression model. Low γ SFC dynamics were captured using a
basis-spline regression model performing piecewise linear estimates around the nonlinear jump
discontinuity, called a knot. The low γ knot was determined by estimating the step discontinuity
in the derivative of the mean SFC as a function of ln(energy), with knot placement confirmed by
observation of the spline domain to determine relative influence of each spline in the total
regression model. Piecewise regression coefficients are shown in Table III. Low γ knot was

determined to occur at 0.15 mJ per pulse, below which spike-field coupling showed no significant
increase as a function of applied energy per pulse ($\beta_{low\,\gamma} = 0.048$, CI: 0,0.07). However, above
the knot value, low γ spike-LFP coupling significantly increases as a function of INS energy
($\beta_{low\,\gamma} = 0.156$, CI: 0.11,0.262). The presence of a discontinuity suggests an early local activation
followed by a rapid increase in the number of cortical afferents recruited. SFC regressions in the
β band also suggested the presence of a step discontinuity (supplementary figure S4). The knot
point in β SFCs was determined to be at 0.125 mJ per pulse. Piecewise basis spline regressions
showed no significant increase in β band SFC $\left(\beta_\beta = 0.034, \text{CI: } 0,0.05\right)$ as a function of INS
energy below the knot and a significant increase in β band SFC $\left(\beta_\beta = 0.143, \text{CI: } 0.0979, 0.24\right)$ as
a function of INS energy above the knot. Synchronous β coherence is associated with multi-
synapse thalamocortical feedback activity[123] and a broad range of interneuron subtypes[97]. Finally,
linear increases in α-SFCs were observed ($\beta_\alpha = 0.024$, CI: 0.023,0.024), even at low stimulus
energies α-SFCs have been associated with stimulus adaptation[124] also from thalamocortical
feedback circuits and cortical inhibitory processing[96]. It should be noted that a small, but
significant increase in θ-SFC was also observed($\beta_\theta = 0.0037$, CI: 0.0034,0.004). However,
given the small regression MAP estimate, this increase is likely due to low frequency LFP drift
coupled with co-activation by INS.
527
This data thus suggests two separate thalamocortical encoding paradigms: a first state in which
low to moderate INS stimulation drives weak local activity in cortex amplified by cortical feedback
expressed as low level α activity with log-linear increases as a function of stimulus energy.
Increased INS stimulation energy then causes a shift to a second state characterized by onset of β
and γ activity, with increases in INS energy leading to log-linear increases in these bands. Given
the observed data and extensive knowledge of auditory thalamocortical architectures, we propose
a model of thalamocortical INS recruitment, schematized in Fig 7B. INS at near threshold energy
levels recruits local excitatory projections[125] driving local activation subthreshold to observation
but facilitated and amplified by α band cortico-cortical feedback[126]. Increases in INS energy per
pulse will eventually cross a threshold in which substantial spiking activity is recruited[3], evidenced
by increased γ band activity and supported through α and β band cortico-cortical feedback
projections with PV interneuron activity concentrated in layer III/IV. We suggest that the second
regime is characterized by more widespread activation of interneurons, including PV and
somatostatin expressing subtypes[127]. It is also likely that increased stimulation energies will further
drive cortical-thalamic and cortical-fugal feedback projections from layer V/VI, but these
projections likely only weakly drive observed cortical LFP activity in lower frequency α and β
bands.

4   Discussion

While INS is increasingly used in the study of neural circuit function and evaluated for clinical
neuromodulation therapies, the stimulus-driven dynamics for thalamocortical INS has, until this
point, not been a primary focus of study. Surface or intracortical stimulation has typically been
used to drive cortical activity, rather than the natural thalamocortical pathway[11,12,17,128]. One prior
thalamocortical INS study other than our lab examined slower thalamocortical connectivity using
fMRI in anesthetized macaques[44]. In this study, we evaluated thalamocortical encoding of INS
stimulation using measures of local field potentials as a readout for cortical network modulation
resulting from thalamic stimulation in a chronic rat preparation.

4.1 LFP Magnitude is Driven by INS Stimulation Energy and ISI and is Coupled Primarily to β and γ LFP Frequency Bands

We tested the relationships between stimulus-intensity and frequency band-specific LFP magnitudes, which is a crucial characteristic for basic or translational use of INS. We showed that cortical network dynamics are driven by applied INS energy (Fig. 2) and have significant entrainment to stimulus pulse frequencies even up to 200 Hz (Fig. 4). Notably, our results indicate that cortical temporal encoding of INS stimulation frequencies followed patterns similar to those observed in auditory click train processing. Specifically, the temporal modulation transfer functions (tMTFs) of LFP responses to INS resemble those elicited by auditory click train stimulation[100,129]. This data suggests that INS can drive standard temporal coding in cortical neurons with a mechanism of activation sufficiently fast enough to recapitulate thalamocortical temporal responses.

Decomposition of the LFP into frequency bands also showed that INS activity is primarily coupled to β and γ band activity. Specifically, INS energy per pulse couples strongly to β and high-γ frequency bands with weaker coupling to α and low-γ bands. Furthermore, α and β bands are significantly increased with decreased ISI, suggesting that INS pulses close in time can integrate to create stronger activation while pulses with longer ISIs create distinct activation events that are adapting to multiple pulses. Similar high-γ coupling may also arise from thalamic rebound firing to stimulus offset[130–133]. Delineation of thalamic tonic vs rebound firing could not be assessed in the present study but should be investigated in future patch clamp studies. INS coupling to β and γ bands has interesting clinical potential, with modulation of these bands used as physiological readouts for closed-loop deep brain stimulation efficacy in Parkinson's disease[66,134,135] and obsessive-compulsive disorder[136,137]. Whether or not similar entrainment is consistent between similar thalamocortical and subcortical-cortical circuits related to these diseases requires further study.

4.2 Neurons Showing Chaotic Dynamics Exhibit Distinct Firing State Changes from INS Stimulation

Linear methods of assessing neural encoding of artificial and sensory stimulation are powerful; but fundamentally limited to studies of neural activity with strong linear entrainment to a stimulus. While linear methods are often sufficient for the understanding of neural coding, nonlinear approaches can provide a deeper understanding of spontaneous and evoked neural behavior and activity. In this study, we used the 0-1 test for chaos to assess criticality in the auditory thalamocortical circuit. As chaotic dynamics in other thalamocortical circuits were found to correlate with information transfer capabilities[83] coupled with INS' ability to produce information-rich responses in auditory cortex[3], we mapped statistics indicative of chaotic dynamics to thalamocortical information transfer from INS stimulation and found evidence of chaotic activity in the auditory cortex that is most prominent in subthreshold stimulation in a subset of A1 neurons (Fig. 5). While we cannot properly deduce the primary function of chaotic firing in this study, chaos in other cortical circuits has been linked with facilitation of information transmission[138] and entrainment to temporally complex firing[112], features of which may be critically important in A1 function. We further show a bifurcation in chaotic firing states from complete chaotic firing regimes to mixed chaotic and non-chaotic responses that were correlated with information transfer.

This suggests that some neurons display chaotic firing during subthreshold or low-level
stimulation that converge to more stereotyped, linear responses when stimuli drive informative
thalamocortical responses. These responses may act as adaptive feature detectors to facilitate
dynamic range adaptation present in subsets of A1 neurons[46,139,140]. However, other responses
observed exhibit chaotic dynamics across all stimulus information sets. This subclass of neurons
display constant chaotic dynamics may be a fundamental feature of A1 neural circuits to facilitate
rapid circuit gain changes and pattern detection[112] capabilities. It is likely, however, that the
number of neurons expressing chaotic dynamics that we observed is undersampled, as passing the
permutation entropy test for stochasticity was a stringent requirement for inclusion in chaos
analysis. This precludes responses which may have mixed deterministic chaos and stochastic
responses, in which random dynamical systems theory[141] may be used to better understand chaotic
dynamics in the presence of stochastic dynamics. Furthermore, the study of stochastic dynamics
and chaos is still in its infancy[142] with others suggesting that the chaos seen in neural circuits
represents an entirely new form of dynamical process[143]. We also believe that similar INS studies
can be used to better understand neural dynamical processes as INS produces no electrical artifact
into evoked responses and is easily used in both *in vivo* and *in vitro* preparations.

4.3 Thalamocortical Transformations Underlie The Encoding of INS Stimulation

SFC regression analysis revealed two distinct thalamocortical regimes of dynamic thalamocortical
transformations in response to INS. The first regime is characterized by focal excitation of
primarily excitatory afferent responses as evidenced by increases γ SFC indicative of
thalamocortical synapses onto dendrites driving spiking activity as well as PV interneuron
activity[98,119,120]. The first regime also has evidence of slight stimulus driven cortico-cortico
feedback, as evidenced by slight increases in α SFC[124]. The second regime is characterized by full
entrainment of the thalamocortical circuit with continued cortico-cortical feedback excitatory
activation and PV interneuron activation as evidenced by γ SFC along with recruitment. Auditory
β and high γ coupling also reflects stimulus evoked synaptic drive localized to microcircuit
activation[98] potentially from neurons with similar receptive fields[144]. Other evidence in visual
cortex also suggests that β and high γ coupling involves single and multisynaptic coupling[123]. It
should be noted that α and β power bands can also reflect cortico-thalamo-cortical feedback loops
as a part of normal function of thalamocortical processing[145,146]. Our current study was not
designed to assess corticothalamic feedback, which should be investigated for full understanding
of INS stimulation of thalamocortical circuits. Our data provides a model of network
thalamocortical activation (Fig 7B) which can help facilitate understanding of the therapeutic
potential of INS. INS intensity, pulse characteristics, and pulse timing as variables generates a vast
parameter space for control of thalamocortical dynamics, including frequency-band specific
modulation that may be relevant for restoring function or managing pathological conditions. This
is particularly salient for the clinical use of INS in which a myriad of network recruitment profiles
may be desired[147,148]. We also note that the thalamocortical order of recruitment presented by our
model is in alignment with naturalistic thalamocortical recruitment in somatosensory[149,150] and
auditory cortices[127,151,152], in response to naturalistic stimuli, as well as in human thalamocortical
circuits in response to propofol-induced brain state modulation[153], further suggesting INS drives
naturalistic neural firing. It is also likely that thalamocortical and activation will also recruit
thalamic reticular network neurons[154] coupled to α and β oscillations[145,155]. This is not yet included
in our model as thalamic reticular network neuronal responses to thalamic INS were not measured.

4.4 Towards a Full Coverage Auditory Thalamic Neuroprosthesis

While the cochlear implant (CI) remains one of the most clinically successful neuromodulation
tools, there remains a dearth of options for patients who cannot benefit from CI use. One example
is that of patients diagnosed with Neurofibromatosis Type 2, characterized by tumor growth on
the auditory nerve[156]. While this patient group may receive auditory brainstem implants, the tumor
resection surgery is known to damage the cochlear nucleus implantation site[157], limiting the
efficacy of therapeutic stimuli[158]. While inferior colliculus auditory midbrain implants have also
been tested[159,160], the inferior colliculus is a difficult implantation target due to the need to replicate
the convergence of disparate inputs from all lower auditory nuclei[161-163]. The MGB, however, is
characterized by a small number of parallel sets of excitatory and inhibitory inputs from inferior
colliculus to MGB[50,155,164,165], with little long term potentiation or depression after development[166],
potentially allowing for the generation of robust stimulation waveforms to generate reliable
auditory percepts. Furthermore, the MGB is adjacent to areas commonly targeted by deep brain
stimulation[167], so it is more straightforward to access surgically. The present INS encoding data
combined with INS' advantageous spatial specificity, information transfer properties[3,10,14,22,168]
and favorable safety profile[16-19,22] suggests that an INS-based thalamic implant may serve as a
potent auditory restoration tool. An example of such a device is shown in Figure 8 for human
cortex[167]. Much progress has been made in fabricating optical devices for chronic
stimulation[20,169,170], with the potential for multicolumnar stimulation[35] facilitating the creation of
stimulation devices similar to clinical gold standard stimulation arrays. One potential
implementation (Fig.8 top) would be a coronal plane implantation, which would allow for
recruitment of primary (ventral MGB) and non-primary (dorsal and medial MGB). A potentially
more advantageous approach would be a sagittal-plane implant (Fig 8 Bottom), allowing for more
optrode coverage in the ventral division of MGB and the potential to provide finer resolution of
input auditory waveforms. Some coverage of nonlemniscal dorsal MGB can also be leveraged to
modulate circuit state and large-scale gain control and modulation of auditory
responses[155,165,171,172], providing a pathway for precise control of lemniscal and nonlemniscal
auditory function. However, the amount of MGB coverage for restoration to cochlear-implant level
of hearing is not known, requiring fine-tuned behavioral and information processing studies in
preclinical animal models. Furthermore, INS neural recruitment, like conventional electrical
stimulation, is heavily dependent on the geometry of the stimulated area. As INS activation profiles
are dependent on the width of the optical stimulation area and the penetration depth of the chosen
wavelength[15,173], the total volume of tissue recruited in small animal models is likely to be larger
than what is observed in human. Therefore, larger animal studies combined with computational
modeling of optic field propagation in human MGB is necessary to help establish best electrode
design for implanted auditory stimulation optrodes.

Disclosures

BSC is an unpaid scientific consultant for BECATech Inc for work unrelated to the present study.
BSC also holds provisional patents in neural spectral decomposition methods. The other authors
declare no conflicts of interest for the data presented in this study.

Code, Data, and Materials

The data and statistical posterior distributions presented in this article are publicly available in an
Open Science Framework repository at 10.17605/OSF.IO/JRN65. All source code for data

analysis and statistics is archived in a GitHub/Zenodo repository at https://github.com/bscoventry/Thalamic-Infrared-Neural-Stimulation-Propagates-Linear-And-Chaotic-Coding-Transformations-in-A1. Build instructions and bill of materials for the INSight optical neuromodulation platform can be found in the following Zenodo repository: 10.5281/zenodo.11086673

Acknowledgments

This study was supported by grants from the National Institutes of Health (NIDCD R01DC011580, PI: E.L.B.) and the Purdue Institute for Integrative Neuroscience collaborative training grant (PI: B.S.C.). BSC is now with the Wisconsin Institute for Translational Neuroengineering, the Department of Neurological Surgery, and the Department of Biomedical Engineering, University of Wisconsin-Madison USA.

References

1. J. Wells et al., "Application of infrared light for in vivo neural stimulation.," Journal of biomedical optics **10**(6), 064003 (2005) [doi:10.1117/1.2121772].
2. C.-P. Richter et al., "Neural stimulation with optical radiation.," Laser & photonics reviews **5**(1), 68–80 (2011) [doi:10.1002/lpor.200900044].
3. B. S. Coventry et al., "Characterization and closed-loop control of infrared thalamocortical stimulation produces spatially constrained single-unit responses," PNAS Nexus **3**(2), pgae082 (2024) [doi:10.1093/pnasnexus/pgae082].
4. W. G. A. Brown et al., "Whole cell patch clamp for investigating the mechanisms of infrared neural stimulation.," Journal of visualized experiments : JoVE(77), e50444 (2013) [doi:10.3791/50444].
5. J. M. Cayce et al., "Infrared neural stimulation of thalamocortical brain slices," IEEE Journal on Selected Topics in Quantum Electronics **16**(3), 565–572 (2010) [doi:10.1109/JSTQE.2009.2032424].
6. A. R. Duke et al., "Transient and selective suppression of neural activity with infrared light," Sci Rep **3**(1), 2600 (2013) [doi:10.1038/srep02600].
7. B. S. Coventry et al., "Short-wave Infrared Neural Stimulation Drives Graded Sciatic Nerve Activation Across A Continuum of Wavelengths," in 2020 42nd Annual International Conference of the IEEE Engineering in Medicine & Biology Society (EMBC), IEEE (2020) [doi:10.1109/EMBC44109.2020.9176177].
8. J. Wells et al., "Biophysical mechanisms of transient optical stimulation of peripheral nerve.," Biophysical journal **93**(7), 2567–2580, Elsevier (2007) [doi:10.1529/biophysj.107.104786].
9. I. U. Teudt et al., "Optical stimulation of the facial nerve: a new monitoring technique?," The Laryngoscope **117**(9), 1641–1647 (2007) [doi:10.1097/MLG.0b013e318074ec00].
10. A. D. Izzo et al., "Selectivity of neural stimulation in the auditory system: a comparison of optic and electric stimuli.," Journal of biomedical optics **12**(2), 021008 (2007) [doi:10.1117/1.2714296].
11. J. M. Cayce et al., "Infrared neural stimulation of primary visual cortex in non-human primates," NeuroImage **84**(2), 181–190 (2014) [doi:10.1016/j.neuroimage.2013.08.040].

12. J. M. Cayce et al., "Pulsed infrared light alters neural activity in rat somatosensory cortex in
vivo," NeuroImage **57**(1), 155–166, Elsevier Inc. (2011)
[doi:10.1016/j.neuroimage.2011.03.084].
13. M. G. Shapiro et al., "Infrared light excites cells by changing their electrical capacitance,"
Nature Communications **3**(1) (2012) [doi:10.1038/ncomms1742].
14. A. I. Matic, J. T. Walsh, and C.-P. Richter, "Spatial extent of cochlear infrared neural
stimulation determined by tone-on-light masking," Journal of Biomedical Optics **16**(11),
118002 (2011) [doi:10.1117/1.3655590].
15. J. Wells et al., "Pulsed laser versus electrical energy for peripheral nerve stimulation,"
Journal of Neuroscience Methods **163**(2), 326–337 (2007)
[doi:10.1016/j.jneumeth.2007.03.016].
16. A. I. Matic et al., "Longterm infrared neural stimulation in the chronic implanted cat," in
Proc. SPIE 8565 **8565**, pp. 85655T-85655T – 7 (2013) [doi:10.1117/12.2013851].
17. L. Pan et al., "Infrared Neural Stimulation in Human Cerebral Cortex," Brain Stimulation
16(2), 418–430 (2023) [doi:10.1016/j.brs.2023.01.1678].
18. J. D. Wells et al., "Optically mediated nerve stimulation: Identification of injury thresholds,"
Lasers in Surgery and Medicine **39**(6), 513–526 (2007) [doi:10.1002/lsm.20522].
19. M. M. Chernov, G. Chen, and A. W. Roe, "Histological Assessment of Thermal Damage in
the Brain Following Infrared Neural Stimulation," Brain Stimulation **7**(3), 476–482 (2014)
[doi:10.1016/j.brs.2014.01.006].
20. M. Meneghetti et al., "Soft monolithic infrared neural interface for simultaneous
neurostimulation and electrophysiology," Light Sci Appl **12**(1), 127 (2023)
[doi:10.1038/s41377-023-01164-9].
21. S. M. Rajguru et al., "Optical cochlear implants: Evaluation of surgical approach and laser
parameters in cats," Hearing Research **269**(1–2), 102–111, Elsevier B.V. (2010)
[doi:10.1016/j.heares.2010.06.021].
22. J. M. Cayce et al., "Infrared neural stimulation of human spinal nerve roots in vivo,"
Neurophotonics **2**(1), 015007 (2015) [doi:10.1117/1.NPh.2.1.015007].
23. O. Yetis et al., "Vagus nerve bundle stimulation using 1505-nm laser irradiation in an in-
vivo rat model," Journal of Biophotonics **15**(1), e202100197 (2022)
[doi:10.1002/jbio.202100197].
24. J. Rozman and S. Ribarič, "A setup for selective infrared stimulation of an isolated porcine
vagus nerve," Sensors and Actuators A: Physical **292**, 97–104 (2019)
[doi:10.1016/j.sna.2019.04.010].
25. B. Entwisle et al., "In vitro neuronal depolarization and increased synaptic activity induced
by infrared neural stimulation," Biomed. Opt. Express **7**(9), 3211 (2016)
[doi:10.1364/BOE.7.003211].
26. S. M. Rajguru et al., "Infrared photostimulation of the crista ampullaris.," The Journal of
physiology **589**(Pt 6), 1283–1294 (2011) [doi:10.1113/jphysiol.2010.198333].
27. R. D. Rabbitt et al., "Heat pulse excitability of vestibular hair cells and afferent neurons.,"
Journal of neurophysiology **116**(2), 825–843 (2016) [doi:10.1152/jn.00110.2016].
28. A. D. Izzo et al., "Laser stimulation of auditory neurons: effect of shorter pulse duration and
penetration depth.," Biophysical journal **94**(8), 3159–3166, Elsevier (2008)
[doi:10.1529/biophysj.107.117150].
29. Q. Liu et al., "Exciting cell membranes with a blustering heat shock," Biophysical Journal
106(8), 1570–1577, Biophysical Society (2014) [doi:10.1016/j.bpj.2014.03.008].

30. H. T. Beier et al., "Plasma membrane nanoporation as a possible mechanism behind infrared
excitation of cells," Journal of neural engineering **11**(6), 066006–066006, IOP Publishing
(2014) [doi:10.1088/1741-2560/11/6/066006].

31. M. Plaksin et al., "Thermal Transients Excite Neurons through Universal Intramembrane
Mechanoelectrical Effects," Phys. Rev. X **8**(1), 011043 (2018)
[doi:10.1103/PhysRevX.8.011043].

32. G. P. Tolstykh et al., "Ryanodine and IP 3 receptor-mediated calcium signaling play a
pivotal role in neurological infrared laser modulation," Neurophotonics **4**(2), 025001 (2017)
[doi:10.1117/1.NPh.4.2.025001].

33. V. Lumbreras et al., "Pulsed infrared radiation excites cultured neonatal spiral and vestibular
ganglion neurons by modulating mitochondrial calcium cycling.," Journal of
neurophysiology **112**(6), 1246–1255 (2014) [doi:10.1152/jn.00253.2014].

34. X. Liu et al., "Nonthermal and reversible control of neuronal signaling and behavior by
midinfrared stimulation," Proceedings of the National Academy of Sciences **118**(10),
e2015685118 (2021) [doi:10.1073/pnas.2015685118].

35. F. Tian et al., "A novel interface for cortical columnar neuromodulation with multipoint
infrared neural stimulation," Nat Commun **15**(1), 6528 (2024) [doi:10.1038/s41467-024-
50375-0].

36. P. Fu et al., "Two-photon imaging of excitatory and inhibitory neural response to infrared
neural stimulation," Neurophoton. **11**(02) (2024) [doi:10.1117/1.NPh.11.2.025003].

37. S. Shi et al., "Infrared neural stimulation with 7T fMRI: A rapid in vivo method for mapping
cortical connections of primate amygdala," NeuroImage **231**, 117818 (2021)
[doi:10.1016/j.neuroimage.2021.117818].

38. A. G. Xu et al., "Focal infrared neural stimulation with high-field functional MRI: A rapid
way to map mesoscale brain connectomes," Science Advances **5**(4), eaau7046 (2019)
[doi:10.1126/sciadv.aau7046].

39. Q. Xia and T. Nyberg, "Inhibition of cortical neural networks using infrared laser," Journal
of Biophotonics **12**(7), e201800403 (2019) [doi:10.1002/jbio.201800403].

40. M. X. Cohen, "Fluctuations in Oscillation Frequency Control Spike Timing and Coordinate
Neural Networks," Journal of Neuroscience **34**(27), 8988–8998 (2014)
[doi:10.1523/JNEUROSCI.0261-14.2014].

41. J. Igarashi et al., "A θ–γ Oscillation Code for Neuronal Coordination during Motor
Behavior," J. Neurosci. **33**(47), 18515–18530 (2013) [doi:10.1523/JNEUROSCI.2126-
13.2013].

42. A. Reimer et al., "Fast Propagating Waves within the Rodent Auditory Cortex," Cerebral
Cortex **21**(1), 166–177 (2011) [doi:10.1093/cercor/bhq073].

43. W. Singer, "Cortical dynamics revisited," Trends in Cognitive Sciences **17**(12), 616–626
(2013) [doi:10.1016/j.tics.2013.09.006].

44. S. Yao et al., "Functional topography of pulvinar–visual cortex networks in macaques
revealed by INS–fMRI," J of Comparative Neurology **531**(6), 681–700 (2023)
[doi:10.1002/cne.25456].

45. E. L. Bartlett and X. Wang, "Neural Representations of Temporally Modulated Signals in the
Auditory Thalamus of Awake Primates," Journal of Neurophysiology **97**(2), 1005–1017
(2007) [doi:10.1152/jn.00593.2006].

46. E. L. Bartlett and X. Wang, "Long-Lasting Modulation by Stimulus Context in Primate
Auditory Cortex," Journal of Neurophysiology **94**(1), 83–104 (2005)
[doi:10.1152/jn.01124.2004].
47. Y. Li et al., "Linear transformation of thalamocortical input by intracortical excitation," Nat
Neurosci **16**(9), 1324–1330 (2013) [doi:10.1038/nn.3494].
48. O. Creutzfeldt, F.-C. Hellweg, and Chr. Schreiner, "Thalamocortical transformation of
responses to complex auditory stimuli," Exp Brain Res **39**(1) (1980)
[doi:10.1007/BF00237072].
49. E. Ahissar et al., "Thalamocortical loops as temporal demodulators across senses," Commun
Biol **6**(1), 562 (2023) [doi:10.1038/s42003-023-04881-4].
50. P. H. Smith, E. L. Bartlett, and A. Kowalkowski, "Cortical and Collicular Inputs to Cells in
the Rat Paralaminar Thalamic Nuclei Adjacent to the Medial Geniculate Body," Journal of
Neurophysiology **98**(2), 681–695 (2007) [doi:10.1152/jn.00235.2007].
51. L. K. Issa, N. V. C. Sekaran, and D. A. Llano, "Highly branched and complementary
distributions of layer 5 and layer 6 auditory corticofugal axons in mouse," Cerebral Cortex
33(16), 9566–9582 (2023) [doi:10.1093/cercor/bhad227].
52. R. S. Williamson and D. B. Polley, "Parallel pathways for sound processing and functional
connectivity among layer 5 and 6 auditory corticofugal neurons," eLife **8** (2019)
[doi:10.7554/eLife.42974].
53. A. M. Lesicko et al., "Corticofugal regulation of predictive coding," eLife **11**, e73289 (2022)
[doi:10.7554/eLife.73289].
54. O. Herreras, "Local Field Potentials: Myths and Misunderstandings," Front. Neural Circuits
10 (2016) [doi:10.3389/fncir.2016.00101].
55. J. D. Frost, "EEG-intracellular potential relationships in isolated cerebral cortex,"
Electroencephalography and Clinical Neurophysiology **24**(5), 434–443 (1968)
[doi:10.1016/0013-4694(68)90103-X].
56. B. Pesaran, "Neural correlations, decisions, and actions," Current Opinion in Neurobiology
20(2), 166–171 (2010) [doi:10.1016/j.conb.2010.03.003].
57. G. Buzsáki, C. A. Anastassiou, and C. Koch, "The origin of extracellular fields and currents
— EEG, ECoG, LFP and spikes," Nat Rev Neurosci **13**(6), 407–420 (2012)
[doi:10.1038/nrn3241].
58. K. J. Friston et al., "LFP and oscillations—what do they tell us?," Current Opinion in
Neurobiology **31**, 1–6 (2015) [doi:10.1016/j.conb.2014.05.004].
59. E. M. Radcliffe et al., "Oscillatory beta dynamics inform biomarker-driven treatment
optimization for Parkinson's disease," Journal of Neurophysiology **129**(6), 1492–1504
(2023) [doi:10.1152/jn.00055.2023].
60. S. H. Kim et al., "Thalamo-cortical network underlying deep brain stimulation of
centromedian thalamic nuclei in intractable epilepsy: a multimodal imaging analysis," NDT
Volume 13, 2607–2619 (2017) [doi:10.2147/NDT.S148617].
61. H. Akram et al., "Connectivity derived thalamic segmentation in deep brain stimulation for
tremor," NeuroImage: Clinical **18**, 130–142 (2018) [doi:10.1016/j.nicl.2018.01.008].
62. M. J. Redinbaugh et al., "Thalamic deep brain stimulation paradigm to reduce consciousness:
Cortico-striatal dynamics implicated in mechanisms of consciousness," PLoS Comput Biol
18(7), M. A. K. Peters, Ed., e1010294 (2022) [doi:10.1371/journal.pcbi.1010294].

63. A. Farokhniaee and M. M. Lowery, "Cortical network effects of subthalamic deep brain
stimulation in a thalamo-cortical microcircuit model," J. Neural Eng. **18**(5), 056006 (2021)
[doi:10.1088/1741-2552/abee50].
64. S. Park et al., "Centromedian thalamic deep brain stimulation for idiopathic generalized
epilepsy: Connectivity and target optimization," Epilepsia, epi.18122 (2024)
[doi:10.1111/epi.18122].
65. C. Wiest et al., "Local field potential activity dynamics in response to deep brain stimulation
of the subthalamic nucleus in Parkinson's disease," Neurobiology of Disease **143**, 105019
(2020) [doi:10.1016/j.nbd.2020.105019].
66. C. Smyth et al., "Adaptive Deep Brain Stimulation for sleep stage targeting in Parkinson's
disease," Brain Stimulation **16**(5), 1292–1296 (2023) [doi:10.1016/j.brs.2023.08.006].
67. E. Výtvarová et al., "Revealing connectivity patterns of deep brain stimulation efficacy in
Parkinson's disease," Sci Rep **14**(1), 31652 (2024) [doi:10.1038/s41598-024-80630-9].
68. B. S. Coventry and E. L. Bartlett, "Protocol for artificial intelligence-guided neural control
using deep reinforcement learning and infrared neural stimulation," STAR Protocols **6**(1),
103496 (2025) [doi:10.1016/j.xpro.2024.103496].
69. B. S. Coventry, "INSight Optical Neuromodulation Platform," [object Object] (2024)
[doi:10.5281/ZENODO.11086673].
70. I. U. Teudt et al., "Acoustic events and 'optophonic' cochlear responses induced by pulsed
near-infrared LASER," IEEE Transactions on Biomedical Engineering **58**(6), 1648–1655
(2011) [doi:10.1109/TBME.2011.2108297].
71. A. C. Thompson et al., "Infrared neural stimulation fails to evoke neural activity in the deaf
guinea pig cochlea," Hearing Research **324**, 46–53 (2015)
[doi:10.1016/j.heares.2015.03.005].
72. R. S. Verner, M. I. Banks, and E. L. Bartlett, "Global State Changes Induce Non-reciprocal
Reduction of Mutual Information in the Thalamocortical Network," BioRxiv (2017)
[doi:https://doi.org/10.1101/213272].
73. M. Ter-Mikaelian, D. H. Sanes, and M. N. Semple, "Transformation of Temporal Properties
between Auditory Midbrain and Cortex in the Awake Mongolian Gerbil," Journal of
Neuroscience **27**(23), 6091–6102 (2007) [doi:10.1523/JNEUROSCI.4848-06.2007].
74. A. Parthasarathy and E. Bartlett, "Two-channel recording of auditory-evoked potentials to
detect age-related deficits in temporal processing," Hearing Research **289**(1–2), 52–62
(2012) [doi:10.1016/j.heares.2012.04.014].
75. R. Q. Quiroga, Z. Nadasdy, and Y. Ben-Shaul, "Unsupervised spike detection and sorting
with wavelets and superparamagnetic clustering.," Neural computation **16**(8), 1661–1687
(2004) [doi:10.1162/089976604774201631].
76. L. P. A. Arts and Egon. L. Van Den Broek, "The fast continuous wavelet transformation
(fCWT) for real-time, high-quality, noise-resistant time–frequency analysis," Nat Comput
Sci **2**(1), 47–58 (2022) [doi:10.1038/s43588-021-00183-z].
77. Y. Zhan et al., "Detecting time-dependent coherence between non-stationary
electrophysiological signals—A combined statistical and time–frequency approach," Journal
of Neuroscience Methods **156**(1–2), 322–332 (2006) [doi:10.1016/j.jneumeth.2006.02.013].
78. E. Süli and D. F. Mayers, *An Introduction to Numerical Analysis*, 1st ed., Cambridge
University Press (2003) [doi:10.1017/CBO9780511801181].
79. L. Bluestein, "A linear filtering approach to the computation of discrete Fourier transform,"
IEEE Trans. Audio Electroacoust. **18**(4), 451–455 (1970) [doi:10.1109/TAU.1970.1162132].

80. R. Gopal, A. Venkatesan, and M. Lakshmanan, "Applicability of 0-1 Test for Strange
Nonchaotic Attractors," [object Object] (2013) [doi:10.48550/ARXIV.1303.0169].
81. G. A. Gottwald and I. Melbourne, "The 0-1 Test for Chaos: A Review," in Chaos Detection
and Predictability **915**, C. Skokos, G. A. Gottwald, and J. Laskar, Eds., pp. 221–247,
Springer Berlin Heidelberg, Berlin, Heidelberg (2016) [doi:10.1007/978-3-662-48410-4_7].
82. D. Toker, F. T. Sommer, and M. D'Esposito, "A simple method for detecting chaos in
nature," Commun Biol **3**(1), 11 (2020) [doi:10.1038/s42003-019-0715-9].
83. D. Toker et al., "Criticality supports cross-frequency cortical-thalamic information transfer
during conscious states," eLife **13**, e86547 (2024) [doi:10.7554/eLife.86547].
84. D. P. Doane, "Aesthetic Frequency Classifications," The American Statistician **30**(4), 181–
183 (1976) [doi:10.1080/00031305.1976.10479172].
85. A. Borst and F. E. Theunissen, "Information theory and neural coding.," Nature neuroscience
2(11), 947–957 (1999) [doi:10.1038/14731].
86. S. P. Strong et al., "Entropy and Information in Neural Spike Trains," Phys. Rev. Lett. **80**(1),
197–200 (1998) [doi:10.1103/PhysRevLett.80.197].
87. B. M. Krause et al., "Spiking in auditory cortex following thalamic stimulation is dominated
by cortical network activity," Frontiers in Systems Neuroscience **8** (2014)
[doi:10.3389/fnsys.2014.00170].
88. M. Denker, A. Yegenoglu, and S. Grün, "Collaborative HPC-enabled workflows on the HBP
Collaboratory using the Elephant framework," G-Node (2018)
[doi:10.12751/INCF.NI2018.0019].
89. A. Gelman and J. Hill, *Data Analysis Using Regression and Multilevel/Hierarchical Models*,
1st ed., Cambridge University Press, Cambridge, United Kingdom (2006).
90. J. K. Kruschke, *Doing Bayesian Data Analysis: A tutorial with R, JAGS, and stan*, 2nd ed.,
Academic Press (2014).
91. A. Gelman et al., *Bayesian Data Analysis*, 3rd ed., Chapman and Hall/CRC, Boca Raton
(2021).
92. B. S. Coventry and E. L. Bartlett, "Practical Bayesian Inference in Neuroscience: Or How I
Learned to Stop Worrying and Embrace the Distribution," eNeuro **11**(7), ENEURO.0484-
23.2024 (2024) [doi:10.1523/ENEURO.0484-23.2024].
93. J. K. Kruschke, "Bayesian Analysis Reporting Guidelines," Nat Hum Behav **5**(10), 1282–
1291 (2021) [doi:10.1038/s41562-021-01177-7].
94. A. Gelman, J. Hwang, and A. Vehtari, "Understanding predictive information criteria for
Bayesian models," Stat Comput **24**(6), 997–1016 (2014) [doi:10.1007/s11222-013-9416-2].
95. R. McElreath, *Statistical Rethinking: A Bayesian Course with Examples in R and Stan*, 2nd
ed., CRC Press, Boca Raton, Fl (2020).
96. E. A. Buffalo et al., "Laminar differences in gamma and alpha coherence in the ventral
stream," Proc. Natl. Acad. Sci. U.S.A. **108**(27), 11262–11267 (2011)
[doi:10.1073/pnas.1011284108].
97. G. Chen et al., "Distinct Inhibitory Circuits Orchestrate Cortical beta and gamma Band
Oscillations," Neuron **96**(6), 1403-1418.e6 (2017) [doi:10.1016/j.neuron.2017.11.033].
98. P. Vianney-Rodrigues, O. D. Iancu, and J. P. Welsh, "Gamma oscillations in the auditory
cortex of awake rats: Gamma oscillation and auditory cortex," European Journal of
Neuroscience **33**(1), 119–129 (2011) [doi:10.1111/j.1460-9568.2010.07487.x].

99. L. Fontolan et al., "The contribution of frequency-specific activity to hierarchical
information processing in the human auditory cortex," Nat Commun **5**(1), 4694 (2014)
[doi:10.1038/ncomms5694].
100.   G. Conti et al., "Auditory steady-state responses to click trains from the rat temporal
cortex," Clinical Neurophysiology **110**(1), 62–70 (1999) [doi:10.1016/S0168-
5597(98)00045-8].
101.   L. A. Anderson, G. B. Christianson, and J. F. Linden, "Stimulus-Specific Adaptation
Occurs in the Auditory Thalamus," J. Neurosci. **29**(22), 7359–7363 (2009)
[doi:10.1523/JNEUROSCI.0793-09.2009].
102.   L. Ma et al., "The Neuronal Responses to Repetitive Acoustic Pulses in Different Fields
of the Auditory Cortex of Awake Rats," PLoS ONE **8**(5), B. Sokolowski, Ed., e64288 (2013)
[doi:10.1371/journal.pone.0064288].
103.   R. L. Rennaker et al., "Anesthesia suppresses nonsynchronous responses to repetitive
broadband stimuli," Neuroscience **145**(1), 357–369 (2007)
[doi:10.1016/j.neuroscience.2006.11.043].
104.   R. Cai, B. D. Richardson, and D. M. Caspary, "Responses to Predictable versus Random
Temporally Complex Stimuli from Single Units in Auditory Thalamus: Impact of Aging and
Anesthesia," Journal of Neuroscience **36**(41), 10696–10706 (2016).
105.   Z. Ma et al., "Cortical Circuit Dynamics Are Homeostatically Tuned to Criticality In
Vivo," Neuron **104**(4), 655-664.e4 (2019) [doi:10.1016/j.neuron.2019.08.031].
106.   J. Touboul and A. Destexhe, "Power-law statistics and universal scaling in the absence of
criticality," Phys. Rev. E **95**(1), 012413 (2017) [doi:10.1103/PhysRevE.95.012413].
107.   J. Kadmon and H. Sompolinsky, "Transition to Chaos in Random Neuronal Networks,"
Phys. Rev. X **5**(4), 041030 (2015) [doi:10.1103/PhysRevX.5.041030].
108.   C. Bandt and B. Pompe, "Permutation Entropy: A Natural Complexity Measure for Time
Series," Phys. Rev. Lett. **88**(17), 174102 (2002) [doi:10.1103/PhysRevLett.88.174102].
109.   P. J. Rousseeuw, "Silhouettes: A graphical aid to the interpretation and validation of
cluster analysis," Journal of Computational and Applied Mathematics **20**, 53–65 (1987)
[doi:10.1016/0377-0427(87)90125-7].
110.   Y. Terada and T. Toyoizumi, "Chaotic neural dynamics facilitate probabilistic
computations through sampling," Proc. Natl. Acad. Sci. U.S.A. **121**(18), e2312992121
(2024) [doi:10.1073/pnas.2312992121].
111.   N. Mosheiff et al., "An efficient coding theory for a dynamic trajectory predicts non-
uniform allocation of entorhinal grid cells to modules," PLoS Comput Biol **13**(6), G. T.
Einevoll, Ed., e1005597 (2017) [doi:10.1371/journal.pcbi.1005597].
112.   W. J. Freeman, "Role of chaotic dynamics in neural plasticity," in Progress in Brain
Research **102**, pp. 319–333, Elsevier (1994) [doi:10.1016/S0079-6123(08)60549-X].
113.   M. Nolte et al., "Cortical reliability amid noise and chaos," Nat Commun **10**(1), 3792
(2019) [doi:10.1038/s41467-019-11633-8].
114.   A. V. Medvedev and J. S. Kanwal, "Local Field Potentials and Spiking Activity in the
Primary Auditory Cortex in Response to Social Calls," Journal of Neurophysiology **92**(1),
52–65 (2004) [doi:10.1152/jn.01253.2003].
115.   A. Belitski et al., "Sensory information in local field potentials and spikes from visual
and auditory cortices: time scales and frequency bands," J Comput Neurosci **29**(3), 533–545
(2010) [doi:10.1007/s10827-010-0230-y].

116.   R. Mukamel et al., "Invariance of firing rate and field potential dynamics to stimulus
modulation rate in human auditory cortex," Human Brain Mapping **32**(8), 1181–1193 (2011)
[doi:10.1002/hbm.21100].
117.   X. Gao and M. Wehr, "A Coding Transformation for Temporally Structured Sounds
within Auditory Cortical Neurons," Neuron **86**(1), 292–303 (2015)
[doi:10.1016/j.neuron.2015.03.004].
118. X. Wang, J. A. Hirsch, and F. T. Sommer, "Recoding of Sensory Information across the
Retinothalamic Synapse," J. Neurosci. **30**(41), 13567–13577 (2010)
[doi:10.1523/JNEUROSCI.0910-10.2010].
119. G. Buzsáki and E. W. Schomburg, "What does gamma coherence tell us about inter-
regional neural communication?," Nat Neurosci **18**(4), 484–489 (2015)
[doi:10.1038/nn.3952].
120. V. Volman, M. M. Behrens, and T. J. Sejnowski, "Downregulation of Parvalbumin at
Cortical GABA Synapses Reduces Network Gamma Oscillatory Activity," J. Neurosci.
31(49), 18137–18148 (2011) [doi:10.1523/JNEUROSCI.3041-11.2011].
121. J. R. Eles, K. C. Stieger, and T. D. Y. Kozai, "The temporal pattern of intracortical
microstimulation pulses elicits distinct temporal and spatial recruitment of cortical neuropil
and neurons," J. Neural Eng. **18**(1), 015001 (2021) [doi:10.1088/1741-2552/abc29c].
122. T. I. Shiramatsu et al., "Microelectrode mapping of tonotopic, laminar, and field-specific
organization of thalamo-cortical pathway in rat," Neuroscience **332**, 38–52 (2016)
[doi:10.1016/j.neuroscience.2016.06.024].
123. M. B. Khamechian et al., "Coupled oscillations orchestrate selective information
transmission in visual cortex," PNAS Nexus, pgae288 (2024)
[doi:10.1093/pnasnexus/pgae288].
124. M. Parto Dezfouli et al., "Stimulus-Specific Adaptation Decreases the Coupling of Spikes
to LFP Phase," Front. Neural Circuits **13**, 44 (2019) [doi:10.3389/fncir.2019.00044].
125. P. H. Smith et al., "Thalamocortical projections to rat auditory cortex from the ventral
and dorsal divisions of the medial geniculate nucleus," J of Comparative Neurology **520**(1),
34–51 (2012) [doi:10.1002/cne.22682].
126. S. Haegens et al., "Laminar Profile and Physiology of the α Rhythm in Primary Visual,
Auditory, and Somatosensory Regions of Neocortex," J. Neurosci. **35**(42), 14341–14352
(2015) [doi:10.1523/JNEUROSCI.0600-15.2015].
127. W. G. Sannita, "Stimulus-specific oscillatory responses of the brain: a time/frequency-
related coding process," Clinical Neurophysiology **111**(4), 565–583 (2000)
[doi:10.1016/S1388-2457(99)00271-0].
128. Z. Balogh-Lantos et al., "High density laminar recordings reveal cell type and layer
specific responses to infrared neural stimulation in the rat neocortex," Sci Rep **14**(1), 31523
(2024) [doi:10.1038/s41598-024-82980-w].
129. S. E. Anderson et al., "Response to broadband repetitive stimuli in auditory cortex of the
unanesthetized rat," Hearing Research **213**(1–2), 107–117 (2006)
[doi:10.1016/j.heares.2005.12.011].
130. A. Shosaku and I. Sumitomo, "Auditory neurons in the rat thalamic reticular nucleus,"
Exp Brain Res **49**(3) (1983) [doi:10.1007/BF00238784].
131. M. M. Nejad, S. Rotter, and R. Schmidt, "Basal ganglia and cortical control of thalamic
rebound spikes," Eur J of Neuroscience **54**(1), 4295–4313 (2021) [doi:10.1111/ejn.15258].

132. D. Ulrich and J. R. Huguenard, "GABA$_A$ -Receptor-Mediated Rebound Burst Firing and Burst Shunting in Thalamus," Journal of Neurophysiology **78**(3), 1748–1751 (1997) [doi:10.1152/jn.1997.78.3.1748].

133. D. A. McCormick, M. J. McGinley, and D. B. Salkoff, "Brain state dependent activity in the cortex and thalamus," Current Opinion in Neurobiology **31**, 133–140 (2015) [doi:10.1016/j.conb.2014.10.003].

134. S. Little et al., "Adaptive deep brain stimulation for Parkinson's disease demonstrates reduced speech side effects compared to conventional stimulation in the acute setting," J Neurol Neurosurg Psychiatry **87**(12), 1388–1389 (2016) [doi:10.1136/jnnp-2016-313518].

135. S. Little et al., "Adaptive deep brain stimulation in advanced Parkinson disease," Ann Neurol. **74**(3), 449–457 (2013) [doi:10.1002/ana.23951].

136. Y.-H. Nho et al., "Responsive deep brain stimulation guided by ventral striatal electrophysiology of obsession durably ameliorates compulsion," Neuron **112**(1), 73-83.e4 (2024) [doi:10.1016/j.neuron.2023.09.034].

137. A. S. Widge, "Closed-Loop Deep Brain Stimulation for Psychiatric Disorders," Harv Rev Psychiatry **31**(3), 162–171 (2023) [doi:10.1097/HRP.0000000000000367].

138. D. Toker et al., "Consciousness is supported by near-critical slow cortical electrodynamics," Proc. Natl. Acad. Sci. U.S.A. **119**(7), e2024455119 (2022) [doi:10.1073/pnas.2024455119].

139. P. V. Watkins and D. L. Barbour, "Level-Tuned Neurons in Primary Auditory Cortex Adapt Differently to Loud versus Soft Sounds," Cerebral Cortex **21**(1), 178–190 (2011) [doi:10.1093/cercor/bhq079].

140. N. Ulanovsky et al., "Multiple Time Scales of Adaptation in Auditory Cortex Neurons," J. Neurosci. **24**(46), 10440–10453 (2004) [doi:10.1523/JNEUROSCI.1905-04.2004].

141. L. Arnold, *Random dynamical systems*, 1st ed., Springer-Verlag, New York, NY (1995).

142. M. Frey and E. Simiu, "Deterministic and stochastic chaos," Comp Stoch Mech (195AD).

143. W. J. Freeman, "A proposed name for aperiodic brain activity: stochastic chaos," Neural Networks **13**, 11–13 (2000).

144. M. Brosch, E. Budinger, and H. Scheich, "Stimulus-Related Gamma Oscillations in Primate Auditory Cortex," Journal of Neurophysiology **87**(6), 2715–2725 (2002) [doi:10.1152/jn.2002.87.6.2715].

145. S. Vijayan and N. J. Kopell, "Thalamic model of awake alpha oscillations and implications for stimulus processing," Proc. Natl. Acad. Sci. U.S.A. **109**(45), 18553–18558 (2012) [doi:10.1073/pnas.1215385109].

146. G. Michalareas et al., "Alpha-Beta and Gamma Rhythms Subserve Feedback and Feedforward Influences among Human Visual Cortical Areas," Neuron **89**(2), 384–397 (2016) [doi:10.1016/j.neuron.2015.12.018].

147. A. Boutet et al., "Predicting optimal deep brain stimulation parameters for Parkinson's disease using functional MRI and machine learning," Nat Commun **12**(1), 3043 (2021) [doi:10.1038/s41467-021-23311-9].

148. T. Morishita et al., "Neuroanatomical considerations for optimizing thalamic deep brain stimulation in Tourette syndrome," Journal of Neurosurgery **136**(1), 231–241 (2022) [doi:10.3171/2021.2.JNS204026].

149. H. A. Swadlow and A. G. Gusev, "The Influence of Single VB Thalamocortical Impulses on Barrel Columns of Rabbit Somatosensory Cortex," Journal of Neurophysiology **83**(5), 2802–2813 (2000) [doi:10.1152/jn.2000.83.5.2802].

150. D. P. Aksenov et al., "Blood oxygenation level dependent signal and neuronal adaptation
to optogenetic and sensory stimulation in somatosensory cortex in awake animals," Eur J of
Neuroscience **44**(9), J. Foxe, Ed., 2722–2729 (2016) [doi:10.1111/ejn.13384].
151. S. Kaur, R. Lazar, and R. Metherate, "Intracortical Pathways Determine Breadth of
Subthreshold Frequency Receptive Fields in Primary Auditory Cortex," Journal of
Neurophysiology **91**(6), 2551–2567 (2004) [doi:10.1152/jn.01121.2003].
152. B. Liu et al., "Defining cortical frequency tuning with recurrent excitatory circuitry," Nat
Neurosci **10**(12), 1594–1600 (2007) [doi:10.1038/nn2012].
153. M. Malekmohammadi et al., "Propofol-induced loss of consciousness is associated with a
decrease in thalamocortical connectivity in humans," Brain **142**(8), 2288–2302 (2019)
[doi:10.1093/brain/awz169].
154. L. M. J. Fernandez et al., "Cortical afferents onto the nucleus Reticularis thalami promote
plasticity of low-threshold excitability through GluN2C-NMDARs," Sci Rep **7**(1), 12271
(2017) [doi:10.1038/s41598-017-12552-8].
155. E. L. Bartlett, "The organization and physiology of the auditory thalamus and its role in
processing acoustic features important for speech perception," Brain and Language **126**(1),
29–48 (2013) [doi:10.1016/j.bandl.2013.03.003].
156. S. Coy et al., "An update on the CNS manifestations of neurofibromatosis type 2," Acta
Neuropathol **139**(4), 643–665 (2020) [doi:10.1007/s00401-019-02029-5].
157. D. E. Brackmann et al., "Auditory brainstem implant: I. Issues in surgical implantation.,"
Otolaryngology–head and neck surgery : official journal of American Academy of
Otolaryngology-Head and Neck Surgery **108**(6), 624–633 (1993).
158. A. Garcia et al., "Auditory Brainstem Implant Outcomes in Tumor and Nontumor
Patients: A Systematic Review," Otolaryngol.--head neck surg. **170**(6), 1648–1658 (2024)
[doi:10.1002/ohn.662].
159. H. H. Lim and T. Lenarz, "Auditory midbrain implant: Research and development
towards a second clinical trial," Hearing Research **322**, 212–223, Elsevier B.V (2015)
[doi:10.1016/j.heares.2015.01.006].
160. H. H. Lim et al., "Electrical stimulation of the midbrain for hearing restoration: insight
into the functional organization of the human central auditory system.," The Journal of
neuroscience : the official journal of the Society for Neuroscience **27**(49), 13541–13551
(2007) [doi:10.1523/JNEUROSCI.3123-07.2007].
161. J. C. Adams, "Ascending projections to the inferior colliculus.," The Journal of
comparative neurology **183**(3), 519–538 (1979) [doi:10.1002/cne.901830305].
162. O. Barnstedt et al., "Functional Microarchitecture of the Mouse Dorsal Inferior Colliculus
Revealed through In Vivo Two-Photon Calcium Imaging," Journal of Neuroscience **35**(31),
10927–10939 (2015) [doi:10.1523/JNEUROSCI.0103-15.2015].
163. C. F. Rabang et al., "A computational model of inferior colliculus responses to amplitude
modulated sounds in young and aged rats.," Frontiers in neural circuits **6**(November), 77
(2012) [doi:10.3389/fncir.2012.00077].
164. E. L. Bartlett, "The Medical Geniculate Body," in Translational Perspectives in Auditory
Neuroscience: Normal Aspects of Hearing, 1st ed., Plural Publishing (2012).
165. D. Peruzzi et al., "A monosynaptic GABAergic input from the inferior colliculus to the
medial geniculate body in rat.," The Journal of neuroscience : the official journal of the
Society for Neuroscience **17**(10), 3766–3777 (1997).

166.   Y. Venkataraman and E. L. Bartlett, "Postnatal development of synaptic properties of the
GABAergic projection from the inferior colliculus to the auditory thalamus.," Journal of
neurophysiology **109**, 2866–2882 (2013) [doi:10.1152/jn.00021.2013].
167.   J. A. Winer, "The human medial geniculate body," Hearing Research **15**(3), 225–247
(1984) [doi:10.1016/0378-5955(84)90031-5].
168.   J. Wells et al., "Application of infrared light for in vivo neural stimulation.," Journal of
biomedical optics **10**(6), 064003 (2005) [doi:10.1117/1.2121772].
169.   M. Kiss, P. Földesy, and Z. Fekete, "Optimization of a Michigan-type silicon microprobe
for infrared neural stimulation," Sensors and Actuators B: Chemical **224**, 676–682 (2016)
[doi:10.1016/j.snb.2015.10.084].
170.   Á. C. Horváth et al., "A multimodal microtool for spatially controlled infrared neural
stimulation in the deep brain tissue," Sensors and Actuators B: Chemical **263**, 77–86 (2018)
[doi:10.1016/j.snb.2018.02.034].
171.   E. L. Bartlett and P. H. Smith, "Anatomic, Intrinsic, and Synaptic Properties of Dorsal
and Ventral Division Neurons in Rat Medial Geniculate Body," Journal of Neurophysiology
81(5), 1999–2016 (1999).
172.   C. C. Lee, "Exploring functions for the non-lemniscal auditory thalamus," Front. Neural
Circuits **9** (2015) [doi:10.3389/fncir.2015.00069].
173.   S. L. Jacques, "Optical Properties of Biological Tissues: A Review," Physics in Medicine
and Biology **58**(11), R37-61 (2013) [doi:10.1088/0031-9155/58/11/R37].
174.   G. A. Gottwald and I. Melbourne, "Testing for chaos in deterministic systems with
noise," Physica D: Nonlinear Phenomena **212**(1–2), 100–110 (2005)
[doi:10.1016/j.physd.2005.09.011].
175.   G. A. Gottwald and I. Melbourne, "On the validity of the 0–1 test for chaos,"
Nonlinearity **22**(6), 1367–1382 (2009) [doi:10.1088/0951-7715/22/6/006].
176.   I. Falconer et al., "Application of the 0-1 Test for Chaos to Experimental Data," SIAM J.
Appl. Dyn. Syst. **6**(2), 395–402 (2007) [doi:10.1137/060672571].
177.   J. Belaire-Franch, "The finite sample behavior of the 0–1 test for chaos," Physica A:
Statistical Mechanics and its Applications **555**, 124733 (2020)
[doi:10.1016/j.physa.2020.124733].
178.   J. Salvatier, T. V. Wiecki, and C. Fonnesbeck, "Probabilistic programming in Python
using PyMC3," PeerJ Computer Science **2**, e55 (2016) [doi:10.7717/peerj-cs.55].
179.   A. Gelman, "Prior distributions for variance parameters in hierarchical models (comment
on article by Browne and Draper)," Bayesian Analysis **1**(3) (2006) [doi:10.1214/06-
BA117A].
180.   J. K. Kruschke and W. Vanpaemel, "Bayesian Estimation in Hierarchical Models," in
The Oxford Handbook of Computational and Mathematical Psychology, pp. 279–299,
Oxford University Press (2015).
181.   S. A. Vasquez-Lopez et al., "Thalamic input to auditory cortex is locally heterogeneous
but globally tonotopic," eLife **6**, e25141 (2017) [doi:10.7554/eLife.25141].
182.   E. L. Bartlett and X. Wang, "Correlation of neural response properties with auditory
thalamus subdivisions in the awake marmoset," J Neurophysiol **105**(6), 2647–2667 (2011)
[doi:jn.00238.2010 [pii]\r10.1152/jn.00238.2010].
183.   X. Wang et al., "Neural coding of temporal information in auditory thalamus and cortex,"
Neuroscience **154**(1), 294–303 (2008) [doi:10.1016/j.neuroscience.2008.03.065].

184. E. L. Bartlett, E. X. Han, and A. Parthasarathy, "Neurometric amplitude modulation detection in the inferior colliculus of Young and Aged rats," Hearing Research, 109028 (2024) [doi:10.1016/j.heares.2024.109028].

185. B. S. Coventry et al., "Hierarchical winner-take-all particle swarm optimization social network for neural model fitting," Journal of Computational Neuroscience **42**(1), 72–85 (2017) [doi:10.1007/s10827-016-0628-2].

186. B. Herrmann, A. Parthasarathy, and E. L. Bartlett, "Ageing affects dual encoding of periodicity and envelope shape in rat inferior colliculus neurons," Eur J Neurosci **45**(2), J. Foxe, Ed., 299–311 (2017) [doi:10.1111/ejn.13463].

187. A. Vehtari, A. Gelman, and J. Gabry, "Practical Bayesian model evaluation using leave-one-out cross-validation and WAIC," Stat Comput **27**(5), 1413–1432 (2017) [doi:10.1007/s11222-016-9696-4].

Brandon S Coventry received his BS in electrical engineering from Saint Louis University, his MS in electrical and computer engineering from Purdue University and a PhD in biomedical engineering from Purdue University. He is currently a postdoctoral research associate at the Wisconsin Institute for Translational Neuroengineering and the Department of Neurological Surgery, and a lecturer in the Department of Biomedical Engineering, University of Wisconsin-Madison. His current research interests include translation of clinical neuromodulation tools, deep brain stimulation, infrared neural stimulation, and thalamocortical circuit function.

Cuong P Luu received his BS in bioengineering from UC Berkeley. He is currently a medical student at the University of Wisconsin, School of Medicine and Public Health. His current research interests span deep brain stimulation, neuromodulation tools, and brain computer interfaces in addition to the translation of discoveries in these fields into functional neurosurgery.

Edward L Bartlett received his BS in physics from Haverford University and PhD in neuroscience from the University of Wisconsin-Madison. He is currently a Professor of Biological Sciences and the Weldon School of Biomedical Engineering and Associate Dean for Undergraduate Affairs, College of Science, Purdue University and is an affiliate of the Purdue Institute for Integrative Neuroscience. His current research interests include dynamic interactions between auditory thalamus and cortex, alterations in hearing function from noise exposure and aging, and infrared and closed-loop control of auditory circuits.

1222

1223

Fig. 1 Schematic representation of stimulation and recording preparation. A. Rats were implanted

with planar microwire arrays into layer III/IV of auditory cortex. Spacing of recording electrodes

is schematized in this figure. Infrared optrodes were implanted into the medial geniculate body of

auditory thalamus. Activation of thalamocortical loops was controlled by laser energy per pulse

and interpulse stimulation intervals. B. Local field potential (LFP) recordings were made

concurrently across all channels. Propagation of cortical waves was analyzed across all channels.

Figure was crafted using tools from BioRender (www.biorender.com).

1231

Fig. 2 LFP amplitude is driven by increases in INS laser energy-per-pulse and interpulse stimulus

intervals. A.) Example LFPs demonstrate increased LFP amplitudes with increased INS laser

energy. B.) Bayesian hierarchical linear regression quantifies modulation of LFP N1-P2 RMS

voltages. Posterior predictive checks reveal log-log transformed models produced models that best

fit observed data. Significance was assessed following Bayesian convention with maximum a

priori (MAP) reported. Regression slope parameters were considered significant if posterior

distribution 95% highest density interval (HDI) did not contain zero. Credible interval (CI) bounds

are given on either side of the HDI boundary. The 0-significance boundary is demarcated by a

dotted orange line. Linear regression posterior parameter distributions show that increases in INS

laser pulse energy and ISI drive significantly larger N1-P2 amplitudes. There was no evidence of

laser energy-ISI interaction. Model errors were significantly above 0 but remained small.

1243

Fig. 3 Thalamic INS stimulation predominantly drives activation of β and γ LFP bands with

increases in applied energy. A. Example time-frequency band decomposition calculated using the

fast continuous wavelet transform. Analysis was performed by comparing dB changes in evoked

LFP band power responses from baseline band power during stimulus onset (time of stimulus on

to 100 ms after conclusion of INS stimulus train) and stimulus offset (end of stimulus onset

window to end of trial). B. INS activation primarily drives increases in β, low γ, and high γ power

bands during onset windows. Responses were graded, showing further power increases with

increases in INS energy per pulse. Regression lines are shown as the maximum *a priori* (MAP,

solid orange line) with 95% credible intervals (dashed orange line) describing uncertainty in the

estimation of the MAP regression. C. Offset responses suggest mild decreases in β and low γ

powers from baseline as a function of applied energy, suggesting a mild post-stimulus inhibition

after INS. This was not found in the high γ band (MAP slope HDI overlaps 0, Table I). Regression

results from all LFP bands for onset and offset windows are summarized in Table I. D. β, low γ,

and high γ correlations show increases in between band correlations from baseline and

subthreshold activation with correlations generally increasing with increased INS energy per pulse.

E. Pairwise offset β and low γ, and high γ correlated band power did not significantly change as a

function of applied INS.

1261

Fig. 4: Analysis of INS interpulse stimulation interval tMTFs. Power contained in LFP responses

at ISI frequencies was calculated through Fourier analysis with tMTFs calculated as the change of

ISI frequency power in stimulation response window from baseline. tMTFs were calculated for

binned INS energy per pulse values of A. 0-0.5 mJ, B. 0.5-1mJ, C. 1-1.5 mJ, D. 1.5-2 mJ, E. 2-2.5

mJ, F. 2.5-3 mJ, G 3-3.5 mJ, and H. > 3.5 mJ. Significantly modulated responses are given in Table

II.

1268

Fig. 5: Observation of chaotic dynamics in LFP responses is correlated to stimulation to LFP information transfer. 0-1 Chaos tests were used to assess the criticality of recorded LFPs and plotted vs mutual information of stimulus to response. Silhouette methods were used to determine the optimal number of K-means clusters (K=2). Results show a bifurcation point at stimulus-response mutual information > 0.4 bits suggest a fundamental firing state changes for neurons displaying critical, chaotic dynamics at baseline to mixed chaos responses. Mixed chaos responses are suggestive of temporally precise adaptation to changing sensory stimulation.

Fig 6: Spike rates vs LFP N1-P2 magnitude correlations. A.) Regression parameter distributions suggest a significant intercept term greater than zero with LFP N1-P2 RMS amplitudes showing increases with log spike firing rates and decreases with log ISI. B.) Scatter plot of spike rate and N1-P2 LFP RMS amplitudes across all ISI values. C-E.) Regressions for spike rate, N1-P2 amplitude correlations for 1ms ISI (C), 5 ms ISI (D), and 50 ms ISI (E). Regressions are reported as MAP parameter estimates with shaded regions representing the 95% credible interval.

Fig. 7: Spike-field coherence (SFC) regressions create a model of network entrainment from INS stimulation. A. α, β, and γ SFC regressions as a function of INS energy per pulse. All regression fits represent the mean estimate of regression parameters, with MAP parameter values and 95% HDIs given in table III and IV. SFCs in α and high-γ bands show linear behavior as a function of natural log increases in INS energy per pulse. SFCs in the β and low-γ band show log-linear behavior in higher energies which deviates at lower energies, suggestive of a nonlinear jump discontinuity. To account for this discontinuity, piecewise linear spline regressions with 1 joint knot were performed. β SFCs showed no significant increase below INS energies of 0.125 mJ with

linear increases after 0.125 mJ. Similarly, low γ activity showed no significant increases in

coherence below INS energies of 0.15 mJ per pulse with log-linear increases in response to

increases in INS energy above 0.15 mJ. Vertical grey lines denote the point of knot discontinuity.

B. Graphical model of INS network recruitment of the auditory thalamocortical circuit. INS

recruitment of the auditory thalamocortical circuit is characterized by two distinct regimes: a low

energy regime characterized by thalamic recruitment of Layer III/IV excitatory projections and

PV-interneurons and a high energy regime characterized by further excitatory recruitment with

recruitment of Layer V/VI feedback projections and interneurons of all types.

1300

1301 **Fig. 8:** A proposed full coverage INS-based thalamic neuroprostheses. A. Coronal implantation

1302 plane provides minimal coverage of ventral MGB with larger coverage of nonlemniscal auditory

1303 regions. B. Sagittal implantation routes would provide large INS coverage of lemniscal auditory

1304 pathways with adequate coverage of nonlemniscal regions which can either remain unused or serve

1305 as a route to account for auditory modulation and control.

1306

1307

1308

1309

1310

1311

1312

1313

1314

1315 **Table I:** Summary results for Bayesian hierarchical linear regressions from models of frequency
1316 band decomposition. All results are given as parameter maximum *a priori* estimates (95% credible
1317 interval).

	Intercept β_0	**Energy** β_{energy}	ISI β_{ISI}	Interaction β_{E+ISI}	Error $\in$
Onset α	0.17 (0.13,0.22)	0.056 (0.043,0.067)	-0.075 (-0.1,-0.054)	-0.021 (-0.026,-0.016)	0.45 (0.41,0.51)
Onset β	0.58 (0.37,0.79)	0.17 (0.089,0.25)	-0.018 (-0.079,0.015)	-0.017 (-0.025,-0.0066)	0.89 (0.8,1.0)
Onset θ	0.037 (0.023,0.052)	0.0093 (0.0034,0.015)	-0.016 (-0.031,-0.006)	-0.005 (-0.0087,-0.0027)	0.24 (0.21,0.26)
Onset γ_{low}	1.1 (0.71,1.4)	0.34 (0.21,0.47)	0.019 (-0.064,0.09)	-0.0021 (-0.018,0.015)	1.5 (1.3,1.6)
Onset γ_{high}	2 (1.5, 2.5)	0.49 (0.32,0.67)	-0.041 (-0.2,0.077)	-0.037 (-0.09,0.0099)	1.5 (1.4,1.7)
Offset α	-0.17 (-0.24,-0.096)	-0.074 (-0.098,-0.05)	-0.011 (-0.034,0.011)	-0.0066 (-0.015,0.0029)	0.84 (0.76,0.93)

Offset β	-0.23 (-0.51,0.036)	-0.14 (-0.25,-0.033)	-0.03 (-0.0092,0.034)	-0.0074 (-0.02,0.01)	1.4 (1.2,1.5)
Offset θ	-0.049 (-0.082,-0.015)	-0.024 (-0.038,-0.011)	-0.0062 (-0.018,0.0058)	-0.0059 (-0.011,-0.00084)	0.54 (0.49,0.6)
Offset γ_{low}	-0.078 (-0.46,0.3)	-0.24 (-0.39,-0.096)	-0.037 (-0.1,0.033)	0.0034 (-0.024,0.046)	2.1 (1.9,2.3)
Offset γ_{high}	0.66 (0.35,0.97)	-0.1 (-0.22,0.0041)	-0.059 (-0.14,0.02)	0.0027 (-0.018,0.028)	2.1 (1.8,2.3)

1318

1319

1320

1321

1322

1323

1324

1325

1326

1327   **Table II:** Percentage of tMTF band power responses above and below 3dB significance threshold.

	10 Hz	20 Hz	40 Hz	100 Hz	200 Hz
	Increased Power				
0-0.5 mJ/P	39.36	29.45	40.63	17.08	19.036
0.5-1 mJ/P	48.61	22.99	23.96	13.97	25.00
1-1.5 mJ/P	40.63	34.38	27.08	31.77	29.17
1.5-2 mJ/P	57.5	54.69	93.75	27.91	41.25
2-2.5 mJ/P	66.67	25.	N/A	21.88	31.25
2.5-3 mJ/P	18.75	55.56	71.88	54.17	51.04
3-3.5 mJ/P	81.25	71.88	96.88	62.5	35.42
>3.5 mJ/P	53.125	67.19	81.25	56.25	56.77
	Decreased Power				
0-0.5 mJ/P	9.31	14.06	3.13	22.08	21.85
0.5-1 mJ/P	9.72	8.71	7.29	25.37	17.63
1-1.5 mJ/P	3.13	5.97	11.46	15.64	17.19
1.5-2 mJ/P	7.5	4.69	0	14.84	9.58
2-2.5 mJ/P	6.25	31.25	N/A	37.5	17.19
2.5-3 mJ/P	0	10.42	6.25	2.08	4.17
3-3.5 mJ/P	0	2.34	0	0	13.54
>3.5 mJ/P	12.5	3.13	0	1.04	10.42

1328

1329

1330

1331 **Table III:** Spike-field coherence regression model parameters for α and high γ bands

	Intercept (β_0)	Energy (β_{energy})
θ	0.185 (0.1843, 0.1847)	0.0037 (0.0034, 0.004)
α	0.17 (0.1738,0.1744)	0.024 (0.023,0.024)
γ_{high}	0.2656 (0.2652, 0.2662)	0.015(0.015,0.016)

1332

1333

1334

1335

1336

1337

1338

1339

1340

1341

1342

1343

 Table IV: Spike-field coherence regression model parameters for β and low γ bands

	Intercept (β_0)	Energy Slope Low (β_{energy})	Energy Slope High (β_{energy})
β	0.034 (0.0247,0.0249)	0.034 (0,0.05)	0.143 (0.0979, 0.24)
γ_{low}	0.2656 (0.2652, 0.2662)	0.048 (0,0.07)	0.156 (0.11,0.262)

1345

1346

1347

1348

1349

1350

1351

1352

1353

1354

1355

1356

1357

1358

1359

1360 **Figures:**

1361

1362 **Figure 1**

1363

1364

1365

1366

1367

1368

1369

1370

1371

Figure 2

1372

1373

1374

Figure 3

1375

1376

1377

1378

1379

1380

1381

1382

1383

1384

1385

1386

1387

1388   **Figure 4**

Figure 5

Figure 6

Figure 7

Towards an Optical Thalamic Neuroprosthesis
Coronal Plane Implantation

Sagittal Plane Implantation

1409

Figure 8

1411

1412

1413

1414

1415

1416 **Supplemental Material**

1417 **Supporting Information for:**

1418 **Thalamic Infrared Neural Stimulation Propagates Dynamical**
1419 **Coding Transformations in Auditory Cortex**
1420

Brandon S Coventry[a,b,c], Cuong P Luu[d], Edward L Bartlett[a,b,c,e*]
[a]Weldon School of Biomedical Engineering, Purdue University, West Lafayette, IN 47907 USA
[b]Center for Implantable Devices, Purdue University, West Lafayette, IN 47907 USA
[c]Institute for Integrative Neuroscience, Purdue University, West Lafayette, IN 47907 USA
[d]School of Medicine and Public Health, University of Wisconsin-Madison, Madison, WI 53907 USA
[e]Department of Biological Sciences, Purdue University, West Lafayette, IN 47907 USA
[*]Corresponding Author

1428

Supplemental Material Outline

1. Visualization of 0-1 Chaos Testing

2. Bayesian Model Descriptions and Sensitivity Analyses

2.1. Software requirements

2.2. Goals of Bayesian Inference

2.3. Bayesian Prior Selections

2.4. Posterior Decision Rules

2.5. Final Statistical Models

1437

1. Visualization of 0-1 Chaos Testing

The 0-1 test for chaos is a method by which the degree of chaos in deterministic dynamical systems

can be determined without the need for phase space reconstruction which is difficult if not

impossible for systems without explicit mathematical models. As such, the 0-1 test can act as a

surrogate for Lyapunov exponent methods[83]. The 0-1 chaos test operates through mapping

dynamical time series to a 2D system:

The 0-1 test for chaos is a method by which the degree of chaos in deterministic dynamical systems

can be determined without the need for phase space reconstruction which is difficult if not

impossible for systems without explicit mathematical models. As such, the 0-1 test can act as a

surrogate for Lyapunov exponent methods[83]. The 0-1 chaos test operates through mapping

dynamical time series to a 2D system:

$$p(n+1) = p(n) + \varphi(n)\cos(c*n)$$

$$q(n+1) = q(n) + \varphi(n)\sin(c*n)$$

and then computing the mean path displacement as

$$M_{disp}(n) = \lim_{N\to\infty} \frac{1}{N} \sum_{i=1}^{N} \left(\left(p(i+n) - p(i)\right)^2 + \left(q(i+n) - q(i)\right)^2 \right) + \sigma\rho_n$$

The measure of degree of chaotic dynamics is then summarized in the K-statistic

$$K = \frac{\log M_{disp}(n)}{\log n}$$

The result is that non-chaotic dynamics display periodic, bounded dynamics in $p(n), q(n)$,

bounded growth $M_{disp}(n)$ and a resulting K statistic approaching 0. Alternatively, chaotic systems

display diffusive, Brownian-like motion in $p(n), q(n)$, unbounded linear growth in $M_{disp}(n)$ and

a K-statistic approaching 1. To visualize test dynamics, the logistic map was used:

$$x[n+1] = \mu x[n](1 - x[n])$$

Where μ is known as the growth rate. Plots of the logistic map as a function of μ are shown in

FigS1(top). Values of $\mu \leq \sim 3.5$ show nonchaotic dynamics while values greater than this critical

threshold show chaotic, period-doubling behavior. Plotting $p(n), q(n)$ at $\mu = 2.8$ displays

sinusoidal, bounded behavior (FigS1, bottom left) with a resulting K-statistic of 0.1789, indicative

of non-chaotic dynamics. Plotting $p(n), q(n)$ at $\mu = 3.8$ displays Brownian motion-like behavior

(FigS1, bottom right) with a resulting K-statistic of 0.9982, indicative of chaotic dynamics. Full

mathematical descriptions and validations of the 0-1 test for chaos can be found in the following

studies[81,174–177].

1468

2. Bayesian Model Descriptions and Sensitivity Analyses

This study follows the guidelines outlined in the best practices in reporting Bayesian analysis[93],

and is composed of:

• Descriptions of necessary software for replication

• Depositing of posterior traces into freely available repositories

• A description of the goals of analysis

• Detailed model descriptions

• Detailed description of prior distributions and reasoning behind choice of priors

• Sensitivity Analysis for statistical models

• Posterior and Markov-chain Monte Carlo diagnostics

2.1 Software requirements

The Bayesian inference performed in this study was computed on intel processors with no

additional GPU threading. Replication of Bayesian models is CPU bound which can be performed

on most current generation CPU platforms. All models where implemented in the PyMC

environment[178] running in Python 3. All model source code is available on our Github repositories

for this article (data and code availability) which can reproduce posterior traces used in this study.

Posterior traces can also be made available upon request.

1486

2.2 Goals of Bayesian Analysis and Inference.

Bayesian inference is particularly well suited for inference of repeated measures study designs

which contain within and between subjects variance through flexible hierarchical inference

structures[89,179,180] allowing for quantification of heterogenous LFP responses from collective

activity of groups of biophysically differing cell types[181]. Bayesian inference is particularly well

suited for inference of repeated measures study designs which contain within and between subjects

variance through flexible hierarchical inference structures[89,179,180] allowing for quantification of

heterogenous LFP responses from collective activity of groups of biophysically differing cell

types[181]. As such, Bayesian hierarchical linear regressions were used to quantify dose-response

characteristics of INS-LFP entrainment modeling increases in wave N1-P2 peak RMS as a function

of INS energy per pulse, INS interpulse stimulation intervals (ISI), and energy-ISI interactions.

Models also contained error term parameters to quantify distributions of fitting errors. Changes in

LFP $\theta, \alpha, \beta,$ and γ band powers were also quantified using Bayesian hierarchical linear regression

models with INS energy per pulse, INS interpulse stimulation intervals (ISI), and energy-ISI

interaction predictors. Hierarchical models perform 'partial pooling' of response data which

accounts for individual differences in parameter estimation. This is done by allowing distributions

around model that quantify firing rate dependencies from laser parameters while accounting for

within-subject differences. Prior selection is discussed in section 2.3. Partial pooling was

performed by adding an implicit class definition $e_{i,j}$ in PyMC (see code) which encodes the

response arising from the i^{th} electrode in the j^{th} subject. Within and between subject variances

were quantified through hyper prior distributions placed on prior parameters[179]. Within and

between subject variances were quantified through hyper prior distributions placed on prior

parameters[179].

1510

2.3 Prior selection

While LFPs elicited via INS, particularly in the auditory thalamocortical circuit, have largely been

underexplored, previous knowledge to form highly informative prior distributions are not

available. However, our extensive experience in INS single unit responses[3], biophysical properties

of auditory thalamus[45,155,166,182,183] and cortex[46,72,183], and recordings from and modeling of the

central auditory pathway as a whole[163,184–186] allow for the quantification of nominal

thalamocortical firing properties into the prior distribution. [45,155,166,182,183] and cortex[46,72,183], and

recordings from and modeling of the central auditory pathway as a whole[163,184–186] allow for the

quantification of nominal thalamocortical firing properties into the prior distribution. As such, we

have chosen to utilize moderately informative normally distributed prior distributions, allowing

for the observed data to drive posterior inference. An alternative for noninformative prior

distributions is the unform prior, which weighs all parameter outcomes as equally likely within the

uniform interval. Normally distributed priors were chosen over uniformly distributed priors as all

probabilities outside of the uniform interval are cast to 0 and are not included in the posterior

distribution. Normal distributions put small, but not 0 probability on extreme events, which, if

given enough evidence in the data, are represented in the posterior distribution. Initial observations

of data showed that log transformation of predictor and response variables provided data

distributions that were sufficiently normal, further facilitating the use of normally distributed

priors. Prior sensitivity analyses also confirmed normally distributed priors did not have undue

influence on posterior estimates.

1531

2.4 Posterior Decision Rules

Inference was conducted on posterior distributions utilizing 95% highest density interval

estimation as measured through the maximum *a posteriori* (MAP) estimation standard to Bayesian

practice[90,92]. Inference was conducted on posterior distributions utilizing 95% highest density

interval estimation as measured through the maximum *a posteriori* (MAP) estimation standard to

Bayesian practice[90,92]. Credible intervals, analogous to confidence intervals in frequentist

inference, were measured as the highest density interval (HDI) containing 95% of the posterior

distribution probability. A regression parameter was considered significant if the 95% HDI did not

contain a value of 0, with zero indicative of a predictor having a null effect. MAP estimates,

representing the mode of the posterior distribution and thus the most probable value of the

regression parameter. This set of inference allows for the quantification of the uncertainty of

parameter estimates, with narrow HDIs describing a more certain estimate of the regression

parameter given the observed data.

1545

2.5 Final Statistical Models

Posterior predictive checking was performed by sampling the posterior distribution (20,000 draws)

to create surrogate data distribution. Kernel density estimates of these posterior predictive

distributions were compared to kernel density estimates of the observed data. Goodness of fit

between the two distributions was assessed using Bayesian p-values quantifying the probability

that posterior predictive-based draws are more extreme than observed data[91]. Posterior sensitivity

to model prior and hyper prior distributions was assessed using leave-one-out cross (LOO)

validation[94]. Models of standard regression with a normally distributed likelihood function and

models of robust regression with Student-T distributed likelihood functions were compared with

varying hyper prior variances. Robust regressions tend to perform better inference with less

sensitivity to outlier data. Goodness of fit between the two distributions was assessed using

Bayesian p-values quantifying the probability that posterior predictive-based draws are more

extreme than observed data[91]. Posterior sensitivity to model prior and hyper prior distributions was

assessed using leave-one-out cross (LOO) validation[94]. Models of standard regression with a

normally distributed likelihood function and models of robust regression with Student-T

distributed likelihood functions were compared with varying hyper prior variances. Robust

regressions tend to perform better inference with less sensitivity to outlier data. Prior distributions

for scale parameters of error and Student T tail mass v were set to half-Cauchy distributions as

Expected log pointwise predictive densities (ELPD)[187] were calculated for each model.[187] were

calculated for each model. Higher values of ELPD are a result of higher out of sample predictive

fit indicative of a better model. Weight values generated by LOO cross validation were also

analyzed and predict the probability of each model given observed data. Finally, we observed the

standard error of the ELPD estimate (SE), and the difference between the model with highest

ELPD and every other model (dSE) with dSE of the top model set to 0.00 by definition. All LOO

calculations were performed post hoc with the python package arviz, a plugin for PyMC. All

models and hyperpriors are given in supplemental table I. Schematic descriptions of Bayesian

hierarchical models is given in Figure S2. Posterior predictive Bayesian p-values for models are

given in Figure S3,S4 respectively.

1574

1575

1576

1577

1578

1579   Supplemental Table 1: Final models used in statistical analyses. *ST*-Student T distributed, *N*-

1580   normally distributed.

Model Name	Likelihood	Final Hyperpriors
LFP N1-P2 dose response curves	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,1)
θ-band LFP Onset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,10)
θ-band LFP Offset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,1)
α-band LFP Onset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,5)
α-band LFP Offset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,5)
β-band LFP Onset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,1)
β-band LFP Offset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,10)
Low **γ**-band LFP Onset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,1)
Low **γ**-band LFP Offset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,5)
High **γ**-band LFP Onset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,5)
High **γ**-band LFP Offset	$ST(\beta_{1,i}E + \beta_{2,i}ISI + \beta_{3,i}E * ISI + \varepsilon)$	N(0,1)
Spike-field correlation regressions	$ST(\beta_{1}FiringRate + \beta_{2,}ISI + \varepsilon)$	N(mean(firing rate), 1)
SFC Spline Regression	$ST(\beta_{i} * w_{i})$	N(0,0.5)

1581

1582

1583

Supplemental Figure Legends.

Figure S1: Visualization of the 0-1 Chaos test using the Logistic Map. The logistic map contains regions of regular,
non-periodic and chaotic dynamics(top). Visualization of the logistic map cast into the 2D mapping p(n), q(n) shows
that regular regimes show bounded dynamics with no growth in average mean-squared displacement with a K
statistic close to 0 (0.1789)(bottom, left). Alternatively, chaotic regions of the logistic map cast into the p(n),q(n)
space show dynamics with Brownian-like motion, and a linear growth in average mean-squared displacement,
indicative of chaotic dynamics exhibiting diffusive growth of $\sqrt{n}$. This is quantified with a K-statistic close to 1
(0.9982)(bottom, right).
1592

1593 **Figure S2:** Schematic of Bayesian hierarchical linear regressions.
1594
1595 **Figure S3:** Bayesian p-value plot for N2-P1 LFP Bayesian hierarchical linear regression. Bayesian p-values suggest
1596 good model fit to data if posterior sampled distributions are near or centered about 0.5.
1597
1598 **Figure S4:** Bayesian p-values for LFP frequency band onset and offset statistical models.
1599
1600 **Figure S5:** Bayesian p-values for spike rate-LFP N1-P2 RMS amplitude regressions.
1601
1602 **Figure S6:** Hierarchical regression models for β and low γ spike-field coherences show evidence of nonlinearity as
1603 seen by low energy regression estimates which drop below measured coherences.
1604
1605
1606

Figure S1

Hierarchical Multilinear Regression Model

Figure S2

Figure S3

Figure S4

Figure S5

Figure S6