Hitting the right pitch: Cortical tracking of speech fundamental frequency in auditory and somatomotor regions

Yorguin-Jose Mantilla-Ramos[1,2,6], Ana-Sofía Hincapié-Casas[1], Annalisa Pascarella[3], Tarek Lajnef[1], Richard M. Leahy[4], Emily Coffey[5], Karim Jerbi[1,6*], and Véronique Boulenger[7*]

[1] Cognitive and Computational Neuroscience Laboratory (CoCo Lab), Psychology Department, University of Montreal, Montréal, QC H3C 3J7, Canada

[2] Neuropsychology and Behavior Group (GRUNECO), Medical School, Universidad de Antioquia, Antioquia, 050010 Colombia

[3] Institute for Applied Mathematics Mauro Picone, National Research Council, 00185 Rome, Italy

[4] Department of Electrical and Computer Engineering, University of Southern California, Los Angeles, 90089 California, USA

[5] Department of Psychology, Concordia University, Montreal, QC, H3G 1M8 Canada

[6] Mila (Quebec AI Institute), QC, H2S 3H1 Canada

[7] CNRS, Université Lyon 2, Laboratoire Dynamique du Langage, 69007 Lyon, France

[*] These authors contributed equally.

Keywords: Magnetoencephalography (MEG), fundamental frequency (F0), cortico-acoustic coupling, speech perception, auditory-motor integration

Corresponding authors: yorguin.jose.mantilla.ramos@umontreal.ca and veronique.boulenger@cnrs.fr

Abstract

Low-frequency neural oscillations contribute to the parsing of continuous speech into linguistic units. Little is known however on the coupling of brain rhythms to higher-frequencies in speech such as fundamental frequency (F0) or pitch. Using magnetoencephalography, we investigated whole-brain cortical tracking of F0 while participants listened to sentences produced at normal rate or fast rate, where pitch naturally increases, and to artificially accelerated sentences, where F0 remains unchanged. Our results revealed significant brain-to-F0 coupling across all speech rates not only in right auditory but also in right parietal, insular, and pre- and postcentral regions, likely including the ventral larynx area. Importantly, the cortico-acoustic coupling peak frequency was higher for natural fast speech to reflect the corresponding F0 increase compared to normal rate and time-compressed speech. These findings demonstrate the engagement of an auditory-somato-motor network in F0 tracking, supporting its role in facilitating phonemic processing during the perception of naturally-produced speech.

1 Introduction

By tracking speech temporal structure, neural oscillations contribute to the parsing of the acoustic stream into hierarchically-organized linguistic constituents[1–4]. Substantial evidence from electro/magnetoencephalography (E/MEG) revealed phase-coupling of delta- (~1-3 Hz) and theta-band (~4-8 Hz) auditory cortical activity to the slow modulations of speech amplitude envelope, which mainly reflect the syllable rate[5–9]. Speech envelope has also been shown to modulate low (35-45 Hz) and high gamma (> 50 Hz) amplitude as well as theta phase/low gamma amplitude coupling[6,10–14].

Besides syllabic structure, speech periodicity is another temporal cue of chief importance for speech perception and communication as it conveys segmental (voicing, manner of articulation) and suprasegmental (intonation, stress) information[15]. It results from the quasi-periodic vibration of the vocal folds during production and includes a representation of the speaker's fundamental frequency (F0), which is the prime acoustic correlate of voice pitch. Only limited evidence exists regarding cortical tracking of F0 in naturally-produced speech. Many studies on pitch encoding measured the Frequency-Following Response (FFR), a sustained oscillatory response generally recorded by averaging responses to repeated syllables or tones that mimics stimulus periodicity and reflects precise auditory temporal processing[16–19]. Although the FFR recorded in EEG at the scalp is believed to originate primarily from the brainstem[20], contributions from the thalamus and auditory cortex were also reported, with cortical activity peaking at the stimulus F0[21–28]. Brain coupling to F0 in continuous sound streams has been given less attention. The studies available so far focusing on neural encoding of the F0 in naturalistic speech showed responses in the auditory cortex at the F0 of isolated sentences or stories[29–32]. For instance, using a linear modelling approach in EEG, Van Canneyt and colleagues[33] reported that the F0 of stories could be reconstructed from brain activity likely arising from the brainstem and the primary auditory cortex.

Here, we provide a novel contribution to this line of research by assessing whether neural

oscillations, in the auditory cortex but also in other cortical regions, couple their oscillatory

activity with the F0 of natural speech produced at different rates. We note that the term

"coupling" is used here descriptively to refer to a statistical relationship between brain activity

and the stimulus F0, without assuming whether this reflects the entrainment of endogenous

oscillations or stimulus-driven phase-locked responses, a distinction that remains debated in

the field[34]. Besides spectro-temporal modifications (e.g., shortening of acoustic cues, enhanced

coarticulation)[35], naturally speaking faster induces changes in the phonetic realization of F0.

Acoustic studies in fact reported a shift in the frequency of the pitch range with increasing

speech rate, namely decreased or increased pitch depending on speakers and languages[36,37]. We

aimed to characterize how cortical F0 representation changes as a function of speech rate in

natural speech.

Following earlier work showing that low-frequency cortical activity (e.g., 2-9 Hz) adjusts its

coupling frequency to match the faster syllable rate[38,39], we asked whether a similar frequency-

shift occurs at higher frequencies to track the F0 changes accompanying speech rate increase.

We note that the mechanisms underlying coupling at these different frequency scales likely

differ: whereas theta/delta entrainment involves endogenous oscillatory dynamics, activity in

the 77-97 Hz range examined here falls within the high-gamma band, which is generally

thought to reflect local population firing rates rather than narrow-band oscillations[40,41].

Nonetheless, the question of whether brain-to-stimulus coupling at these frequencies exhibits

a comparable rate-dependent frequency shift remains relevant and largely unexplored.

Using MEG, we examined brain coupling to the F0 of sentences naturally produced at a normal

or fast rate, as well as of artificially accelerated (i.e. time-compressed) sentences. Given that

time-compression reduces signal duration while keeping its spectral and pitch content intact[42],

time-compressed speech has the same F0 as normal rate speech despite a faster syllabic rate.

By contrast, F0 inherently increases in naturally-produced accelerated speech compared to both

normal rate and time-compressed speech. Using Minimum Norm Estimation source

reconstruction methods, we compared cortico-acoustic coupling and power modulations during

sentence perception in the three speech rate conditions. In keeping with previous studies[7,38], we

analysed coupling in two frequency ranges centred on the mean F0 of our sentence material

(77-84 Hz for normal rate/time-compressed sentences and 90-97 Hz for natural fast speech). In

addition, a whole-brain analysis allowed us to investigate whether coupling to sentences' F0

only occurs in the auditory cortex or whether it involves a more distributed cortical network,

noting that previous work used region-of-interest based analyses, mostly in the primary auditory

cortex[e.g.23,32]. We are aware of only one stereotactic EEG / MEG study showing FFR in a

temporo-parieto-frontal cortical network in response to musical tones[43].

Our results reveal significant cortico-acoustic coupling in frequency ranges that are specific to

the sentences' fundamental frequency. Coupling indeed occurred in the higher frequency band

(90-97 Hz) for naturally-produced fast speech compared to normal rate speech, mirroring the

natural increase in speech F0. No change in coupling frequency (77-84 Hz) was observed for

time-compressed sentences which have similar F0 to normal rate sentences. Crucially, brain-

to-F0 coupling was found in a right-lateralized network encompassing temporal, parietal,

precentral and postcentral cortices, known to contribute to speech perception as well as to

production. Such findings suggest that by adjusting to the rate of vocal fold vibration, neural

oscillations in sensorimotor regions contribute to the encoding of pitch and of phonemic

information conveyed by the periodicity of the speech signal.

2 Results

Twenty-four French native participants listened to natural normal rate (mean = 6.76 ± 0.57 syllables/s), natural fast rate (9.15 ± 0.60 syllables/s) and time-compressed sentences (9.15 ± 0.60 syllables/s) while their MEG brain activity was recorded. The mean F0 of the natural normal rate and time-compressed sentences was 81.3 Hz (SD 3.3) as calculated from the peaks of the power spectrum of the sentences using Python. It increased to 91.9 Hz (SD 9.8) for naturally accelerated sentences. Amplitude-modulated noise stimuli, generated with the envelopes of normal rate and fast rate stimuli, and which lack pitch and verbal information, were included as control conditions. We assessed neural tracking of changes in fundamental frequency by computing cortico-acoustic coupling between the acoustic signals and source-localized MEG time-series using phase-lag index (PLI) and, as a complementary approach, coherence measures (see Methods for more details about the selected coupling metrics). Because sentences' F0 in the different speech rate conditions overlapped to some extent, we analysed speech-brain coupling in subsets of sentences for which the F0s of the normal and time-compressed conditions were most distant from the F0s of the fast condition (see Methods and Supplementary Figure S1 and Table S1). The F0 in these subsets peaked at 80 Hz for natural normal rate and time-compressed sentences, and at 93 Hz for natural fast rate sentences. We therefore conducted the coupling analysis in two frequency bands of interest centred on these values, respectively, 77-84 Hz and 90-97 Hz. For statistical analysis, PLI and coherence measures for actual stimulus encoding were compared with measures obtained on surrogate data using a shuffling procedure and correction for multiple comparisons using, respectively, cluster-based correction and FDR (see Methods).

2.1 Cortico-acoustic phase coupling shifts with speech F0

PLI analyses revealed significant phase-locking of neural oscillations to speech fundamental frequency, with a shift in coupling frequency that mirrored the changes in F0 following natural syllable rate acceleration (Figure 1). Cortico-acoustic coupling was found at 77-84 Hz for normal rate sentences mainly in bilateral Heschl's, superior temporal, supramarginal and pre-/postcentral gyri as well as in the insula (see Supplementary Table S2 for more details). For the natural fast condition, PLI increased in the higher 90-97 Hz range in a right-lateralized network mostly including the same regions, namely Heschl's, superior temporal, supramarginal and postcentral gyri (note from Figure 1A that coupling, albeit not significant, was also observed in the left hemisphere). As previously outlined, time-compressed sentences had the same F0 as normal rate sentences. This was well reflected in the brain by a significant PLI increase for this condition in the lower, normal rate pitch range only (77-84 Hz), in a similar network as the one found for normal rate speech. No significant phase-coupling was on the contrary observed for naturally accelerated sentences in this frequency range, stressing the specificity of the effect. Additional coherence analyses corroborated this pattern of results (see Figure 2). Indeed, coherence significantly increased bilaterally in the lower frequency range for normal rate and time-compressed sentences, but in the higher range for natural fast sentences. As expected, for the amplitude-modulated noise conditions, neither PLI nor coherence measures showed any significant cortico-acoustic coupling increase in any of the two frequency bands of interest (Figures 1 and 2).

Figure 1. Cortical coupling to fundamental frequency in the frequency ranges encompassing the F0s of normal rate and time-compressed sentences (77-84 Hz) and of natural fast rate sentences (90-97 Hz). (A) Phase Lag Index (PLI) maps for coupling between the acoustic signal and brain oscillatory activity during stimulus encoding (active period), as compared to surrogate (i.e. shuffled) data. The values represent the difference in Fisher z-transformed PLI between the compared data. (B) Cluster-based statistical maps (corrected, α = .001, one-tailed) are shown for the different speech and noise conditions. Noise Normal and Noise Fast correspond to white noise stimuli modulated with the amplitude envelope of normal rate and fast rate sentences, respectively.

Figure 2. Cortico-acoustic coherence in the frequency ranges corresponding to the F0s in the normal rate and time-compressed conditions (77-84 Hz) and the natural fast rate condition (90-97 Hz). (A) Coherence maps for coupling between the acoustic signal and brain oscillatory activity during stimulus encoding (active period), as compared to surrogate (i.e. shuffled) data. The values represent the difference in Fisher z-transformed coherence between the compared data. (B) Statistical maps (FDR statistics, corrected, α = .001) are shown for the different speech and noise conditions. Noise stimuli modulated with the amplitude envelope of normal rate and fast rate sentences are referred to by Noise Normal and Noise Fast, respectively.

2.2 Coupling spectra identify top regions per parcellation

To more thoroughly assess the specific change in coupling frequency with F0 variation, we computed the coupling spectra for PLI and coherence across the three speech rate conditions, averaged over all participants and for each voxel. We then calculated the mean spectra separately over regions delimited by three different brain parcellations (see Methods). We identified the top regions in each parcellation with the highest spectral PLI peak across all speech conditions. For this analysis, we focused on the right hemisphere as it is where our PLI and coherence analyses above showed significant effects for all speech conditions. As displayed in Figure 3, this highlighted the Heschl's gyrus (aparc parcellation), the first subzone of the

postcentral gyrus (aparc_sub parcellation), and Brodmann area 43 corresponding to the

subcentral area (PALS-B12 parcellation). Analyses confirmed that for both PLI and coherence,

the coupling spectra in these regions peaked at the sentences' F0, that is at ~80 Hz for normal

rate and time-compressed speech, with a shift at ~90 Hz for naturally-accelerated speech

(Figure 3 A, B, C for PLI and E, F, G for coherence). These peaks were not found when running

the same analysis in the frontal pole which served as a control region (Figure 3 D, H). Note

from Supplementary Figures S2, S3 and S4 that the three identified auditory, inferior

postcentral and subcentral regions were found among the top 8 regions showing the highest

PLI and coherence peaks at sentences' F0, irrespective of the parcellation used. Note also that

while power modulations might explain coherence peaks (Figure 3 E-M, F-N and G-O), this

cannot be the case for the PLI curves as their calculation relies on phase measures rather than

on the amplitude spectrum.

Figure 3. Coupling and power spectra for the three speech conditions in the top regions of the right hemisphere for each brain parcellation. The regions shown (one per column) correspond to the regions in each parcellation (respectively, aparc, aparc_sub and PALS-B12) with the highest peak of Phase Lag Index (PLI) coupling, which remains the same when evaluating coherence. The curves shown correspond to the average over subjects and voxels inside each region of PLI, coherence, power and flattened power, respectively. The coupling spectra were calculated between the acoustic signal and brain oscillatory activity during stimulus encoding (active period). For comparison, the same results are provided for the frontal pole as a control region. (A) to (D) show the PLI and (E) to (H) the coherence coupling spectra, respectively, for natural normal rate (in blue), time-compressed (in green), and natural fast rate speech (in orange). A detailed listing of the top 8 peak PLI regions for each of the three parcellations is provided in Supplementary Figures S2, S3 and S4. Notably, these top 8 peak regions

include motor areas, further supporting F0 coupling beyond the auditory cortex. To evaluate the possible

effects of power modulations on the coupling, (I) to (L) display the brain activity's power spectrum

during the encoding period and (M) to (P) show the same spectra but after correcting for the 1/f-like

slope (using FOOOF[44]). The specific models used for the aperiodic fits of these curves can be seen in

Supplementary Figure S5.

2.3 Power modulations mirror coupling findings

We finally examined whether brain coupling to speech F0 is also reflected in the amplitude of

the cortical responses by analyzing source power modulations in each experimental condition

and frequency band of interest. To this end, we contrasted power during the stimulus encoding

period with power measured during the pre-stimulus baseline, using cluster-based statistical

correction. Results showed a specific increase of power as a function of sentences' F0 (Figure

4). In the normal and time-compressed conditions with F0 peaking around 80 Hz, brain activity

significantly increased in the 77-84 Hz range in the right (and most of the time left for time-

compressed speech) Heschl's, superior temporal, supramarginal, insular and postcentral gyri.

For natural fast rate sentences, the power increase was found at 90-97 Hz in a similar right-

lateralized network also encompassing the precentral gyrus. No significant increase of power

was found for amplitude-modulated noise stimuli in any of the frequency ranges.

Figure 4. **Power modulations in the frequency bands matching the F0s of natural normal rate and time-compressed sentences (77-84 Hz) and of natural fast rate sentences (90-97 Hz).** (A) Power maps during the active period (i.e. stimulus encoding), as compared to the pre-stimulus baseline. The values represent the relative difference in Fisher z-transformed power between the compared data. (B) Cluster-based statistical maps (corrected, α = .001, two-tailed) are reported for the different speech and noise conditions.

3 Discussion

Our results revealed brain coupling to speech fundamental frequency, with a shift in coupling frequency and power increase that echoed the natural F0 increase with natural speech rate acceleration. Whereas phase-coupling (PLI), coherence and amplitude were enhanced at 77-84 Hz for normal rate and time-compressed speech (F0 peak at 80 Hz), coupling shifted to 90-97 Hz for naturally produced fast speech (F0 peak at 93 Hz). Crucially, this coupling was not restricted to the auditory cortex but encompassed a network distributed over sensorimotor regions. Overall, these findings therefore provide novel evidence that high-frequency cortical oscillations couple with the fundamental frequency of speech in the case of natural speech rate variations.

Coupling and power modulations to F0 were mainly found in the right or bilateral superior temporal (including the primary auditory cortex), supramarginal, pre-/postcentral gyri and

insula, in line with previous work on pitch processing and voicing perception[45-49]. FFR studies

also reported responses in the right or bilateral auditory cortex to syllables or continuous

speech[23,26-28]. The lack of coupling to amplitude-modulated noise further suggests that phase-

locking does not reflect responses to the temporal envelope of sentences but to their high-

frequency carrier information. Importantly, our thorough whole-brain analysis using three

different cortical parcellations highlighted the right Heschl's gyrus, ventral postcentral gyrus

and subcentral area (BA 43, at the inferior edge of the postcentral gyrus) as showing maximal

coupling to sentences' F0. Note the close spatial proximity of the latter two regions (14.7 mm

based on a computation of distance between their centroids) which may correspond to the same

somatosensory area. Each of these three regions furthermore showed up among the top eight

regions with strong cortico-acoustic coupling across the three parcellations, indicating the

reliability of the results. Other right-lateralized regions such as the insula and the supramarginal

and precentral gyri also consistently coupled their oscillatory activity with speech F0,

irrespective of the parcellation used. Interestingly, these regions are part of a dorsal network

underlying speech auditory-motor integration[50,51]. The somatosensory cortex has also been

advocated to contribute to speech perception by closely interacting with auditory regions[52]. In

this regard, the subcentral gyrus (BA 43) identified in our study, owning both sensory and motor

properties[53,54], is seen as the ventral larynx motor area activated for the production of

vocalizations and pitch control[55-59]. High-gamma activity in this region has been reported to

increase before and during phoneme articulation[60] and for voiced consonant production[61],

suggesting its role in the control of vocal fold movements. This area furthermore increases its

connectivity with the auditory cortex during mere voicing perception[48], and it can decode

articulatory features of heard phonemes[62-64]. Our results concur with a functional role of this

ventral somatosensory area in speech perception as it is one of the regions that best couple its

high-frequency oscillatory activity with speech F0.

A dorsal larynx motor area, located in the precentral gyrus, is also thought to be involved in

voicing and pitch production and perception[56,57,65-69]. In fact, and although this should be further

tested, the precentral region coupling to speech F0 in our study may correspond to this dorsal

motor region. This could reflect some simulation of the laryngeal gestures underlying pitch

control during speech perception[70]. We also found reliable coupling to F0 in the supramarginal

gyrus and insula. This agrees with the inferior parietal cortex acting as a sensorimotor interface

to coordinate speech perception and production[51,71,72] as well as with its role in phonological

processing[73]. The insula is also assumed to contribute to auditory-motor speech integration[74].

It is indeed engaged in speech production and the control of laryngeal muscles and of F0

modulations[75-77], but also in prosodic perception and auditory temporal processing[78-81]. In

keeping with our work, high-gamma activity in the posterior insula was shown to track the F0

of a repetitive vowel similarly as in Heschl's gyrus[82]. The insula moreover shares connections

with auditory[83] and motor regions, including the laryngeal motor cortex[84,85]. Altogether, our

findings thus putatively suggest that besides the primary auditory cortex targeted by previous

work[23,24,32,86], a dorsal sensorimotor cortical network involved in speech auditory-motor

integration syncs to the periodicity of vocal fold vibration in perceived speech.

Whether and how our findings relate to the cortical FFR to repetitive syllables[21,23,24,27,28] is not

straightforward. One difference is that the FFR is averaged over several hundreds of the same

stimulus, whereas we assessed cortico-acoustic coupling and power modulations to a set of

varying sentences. Still, the FFR is thought to indicate phase-locked neural activity to the

stimulus F0. The different measures may therefore reflect at least some common processes. As

previously mentioned, a FFR source in the right posterior auditory cortex has been described

and would be involved in pitch computation[23,24]. Among the few studies that investigated F0

coupling to sentences or continuous speech, some focused on the brainstem[87-89], while others

examined high-gamma auditory cortex activity in light of the cortical FFR[26,30,32,33,90], occasionally including regions extending slightly beyond primary auditory cortex (e.g., ref[26,30,32,33,90]); however, none systematically mapped F0 coupling across the whole brain at the source level. Crucially, by analyzing both coupling (using two measures, PLI and coherence) and power modulations at high frequencies across widespread cortical regions, we bring new support for brain coupling to F0 in natural speech that occurs well beyond the auditory cortex, in regions that are involved in auditory-somato-motor integration (in agreement with [43] for tones).

Although the increase in coherence we found might be explained, at least partly, by power increases at the same frequencies, this cannot hold for the phase-lag index which is insensitive to amplitude modulations. Cortical coupling to speech F0 may therefore capture the periodic nature of the phenomenon. Coffey and collaborators[86] likewise proposed that their auditory cortex FFR entailed oscillatory entrainment since the brain response outlasted syllable offset (see also [43]). Along with this view, oscillatory coupling to F0 in our study could reflect a predictive coding mechanism comparing speech input periodicity with internal temporal expectations. Such an interpretation, although still speculative, would support the idea that high-gamma activity mediates pitch-level prediction errors and their feedforward propagation up to higher integrative areas in order to update predictions[91-93]. Cortico-acoustic coupling to F0 in (pre)motor regions furthermore agrees with their known role in predictive coding, despite this being usually observed in lower (delta and beta) frequencies[94-96]. Further cross-frequency coupling and functional connectivity analyses between auditory and motor regions are needed to fully substantiate the predictive coding interpretation and further delineate the role of speech F0 coupling at the cortical level. As speech periodicity conveys segmental information, phase-locking to F0 might contribute to phoneme identification by encoding the articulatory feature

of voicing or by extracting vowels' formant structure. Another, not exclusive possibility is that

it could serve more general communicative purposes, to track the relevant targets in an auditory

scene[29] and decrease sensitivity to environmental noise or competing speakers[86].

Another question relates to the upper limit of F0 cortical tracking. In our study and previous

work[23,27,86], phase-locking was examined for typical male voices with F0 not exceeding 100-

110 Hz. It has been proposed that the auditory cortex is not able, or hardly tracks frequencies

beyond 100 Hz[20], for pure tones[97,98] or for syllables produced by males[21] or females[33,90]. Some

intracranial recordings still showed phase-locked responses up to 200 Hz[19,26,99,100]. In the

present study, cortical tracking of natural fast speech was significant but less widespread than

for normal rate and time-compressed speech, although the three conditions highlighted a

comparable cortical network. This may relate to the general decrease in cortical frequency

representation towards higher frequencies and/or the greater variance in F0 for rapidly-

produced sentences. Part of the F0 distribution in this condition indeed lied beyond 110 Hz (up

to ~120 Hz) even after the selection procedure (Figure S1, panels B and D), which may have

decreased the tracking capacity of cortical oscillations. Speech F0 therefore appears as an

important parameter for the emergence of cortical tracking of speech periodicity, since phase-

locking seems to decline with increasing F0. Alternatively, greater variability in natural fast

speech F0 may have reduced statistical power, explaining the globally weaker effects in this

condition. Further examining F0 tracking in different voices and under various speech rate or

noisy conditions, will help better understanding this cortical contribution.

As in previous work in this domain, several critical aspects need to cautiously be taken into

account when interpreting our speech-brain oscillatory coupling. An important interpretive

caveat concerns whether the brain-to-F0 coupling we report reflects the entrainment of

endogenous cortical oscillations to the stimulus periodicity, or rather stimulus-driven evoked

responses phase-locked to each glottal pulse cycle[34]. Our data do not allow us to conclusively

distinguish between these two accounts. However, several aspects of our results are more readily compatible with an oscillatory tracking mechanism. First, the PLI measure, which is insensitive to amplitude modulations, showed robust coupling, suggesting that the effect is not simply driven by repeated evoked power increases. Second, the frequency-specific shift in coupling that mirrors F0 changes across conditions, present for natural fast speech but absent for time-compressed speech which shares the same F0 as normal rate, points to a flexible mechanism that adjusts to stimulus periodicity rather than a fixed evoked response. Nonetheless, we acknowledge that these observations do not constitute definitive evidence for entrainment. This distinction is particularly relevant given that activity in the 77-97 Hz range falls within the high-gamma band, which is generally associated with local population firing rates rather than with narrow-band endogenous oscillations characteristic of theta/delta entrainment[40,41]. The frequency-specific coupling we observe may therefore reflect stimulus-driven synchronization of neural population activity to the periodicity of the glottal source, rather than the entrainment of intrinsic cortical rhythms. Future work using approaches such as post-stimulus analyses of sustained oscillatory activity[86] will be needed to more firmly adjudicate between these accounts. Moreover, the reliability of the widespread network reported here would benefit from further investigation to rule out possible effects of spurious activity arising from the smoothing inherent to source reconstruction. Additionally, our coupling analyses were computed within narrow frequency bands centered on the mean F0 of each subset of sentences, which captures the brain's sensitivity to the broad underlying periodicity of the stimuli but does not address whether cortical activity dynamically tracks the time-varying F0 contour within individual sentences (e.g., intonation patterns or local pitch fluctuations). Time-resolved approaches, such as temporal response functions or time-frequency coupling methods, would be needed to assess such fine-grained tracking and further characterize the cortical encoding of F0 dynamics.

Relatedly, our analysis was based on the mean F0 of each sentence, which captures the overall

periodicity of the speech signal but does not account for within-sentence pitch variations related

to prosodic contours (e.g., intonation, stress patterns). It is plausible that sentences with more

stable F0 would yield stronger coupling than those with greater pitch variability, and that the

higher F0 variance observed in the fast rate condition (SD 9.8 Hz vs. 3.3 Hz for normal rate)

may have contributed to the weaker coupling effects in this condition. Future work could

examine how within-sentence F0 variability modulates coupling strength, for instance by

including F0 variance as a covariate in the analysis, and whether time-resolved methods can

capture cortical tracking of prosodic pitch contours beyond the mean periodicity examined

here. Importantly, while F0 is the primary acoustic correlate of pitch, prosody additionally

encompasses variations in duration, intensity, and spectral quality, all of which are affected

differently by natural acceleration and time compression. Natural fast speech alters the prosodic

structure non-linearly, with changes in stress patterns and intonation that go beyond a simple

shift in mean F0, whereas time-compressed speech preserves the original F0 contour but

compresses its temporal realization. Our analyses focused on coupling to the mean F0

periodicity and were not designed to capture these broader prosodic dimensions. As noted

above, the greater F0 variability in the fast rate condition (SD 9.8 Hz vs. 3.3 Hz for normal rate)

may have contributed to the weaker coupling observed for this condition. A promising future

direction would be to model F0 continuously on a trial-by-trial basis, for instance using

regression approaches that test whether neural coupling scales with F0 rather than relying on

categorical frequency bands, and to examine how within-sentence prosodic variations modulate

cortical tracking.

In conclusion, our study suggests that high-frequency cortical activity couples with the

fundamental frequency (F0) of speech, with a shift in coupling frequency that mirrors the F0

variation accompanying natural speech rate acceleration. Using magnetoencephalography

(MEG), we identified significant brain-to-speech F0 coupling across a network extending

beyond the auditory cortex to include the right auditory, inferior parietal, insular, and pre- and

postcentral regions, involving a dynamic auditory-somato-motor network in the encoding of

speech. These findings advance our understanding of how high-frequency cortical activity

contributes to the encoding of speech fundamental frequency, and point to a complex interplay

between auditory and motor systems in speech perception. Future work using time-resolved

approaches and diverse speaker profiles will help further characterize these cortical coupling

mechanisms and their functional significance for language processing.

4 Methods

4.1 Participants and Ethics

Twenty-four (14 females) participants aged between 18 and 45 years old (mean = 23 years old)

volunteered for the study. All were monolingual French native speakers and right-handed

(mean score at the Edinburgh handedness inventory[101] = 94). None of them reported hearing or

language problems nor history of neurological or psychiatric disorders. The protocol conformed

to the Declaration of Helsinki and was approved by the local ethical committee (Comité de

Protection des Personnes Lyon Sud-Est II; ID RCB: 2012-A00857-36). Written informed

consent was obtained for all participants before the experiment, and they were compensated for

their participation.

4.2 Stimuli

A set of 288 meaningful sentences (7-9 words) with the same syntactic structure (e.g., "Le

guide organise une excursion dans le désert" / *The guide organizes a trip to the desert*) served

as stimuli. A French native male professional theatre actor recorded the stimuli in a sound-

attenuated booth using ROC*me*! software [102]. Each sentence was first displayed on screen for

the actor to silently read before producing it aloud at his normal speech rate. He then produced

the same sentence as fast as possible while remaining intelligible, with no externally imposed

target rate. Recordings were sampled at 44.1 kHz (mono, 16 bits). The mean syllable rate of the

sentences (i.e. number of produced syllables divided by sentence duration) as calculated with

Praat[103], was 6.76 syllables/s (SD 0.57) for the natural normal rate condition, while it increased

to 9.15 syllables/s (SD 0.60) in the natural fast condition. Time compression, which is a re-

synthesis process only affecting the temporal structure of the stimuli, was then applied to

normal rate sentences by digitally shortening them with a PSOLA algorithm (Pitch

Synchronous Overlap and Add[104]). Compression rates were computed for each sentence,

namely each time-compressed sentence was matched in terms of syllable rate to its natural fast

equivalent. Therefore, time-compressed sentences had a mean syllable rate of 9.15 syllables/s

(SD 0.60) as well. Mean sentence duration was 1.67 s (SD 0.16) for natural normal rate, 1.23s

(SD 0.14) for natural fast rate, and 1.24 s (SD 0.14) for time-compressed sentences,

corresponding to a total stimulus duration of approximately 610 s, 449 s, and 449 s per

condition, respectively. For the total of 864 sound files (288×3 speech rate variants), we applied

an 80 Hz high-pass filter and smoothed sentences' amplitude envelope initially and finally. The

intensity of the sound files was finally peak normalized.

Computation of the power spectrum in the 64-128 Hz range across sentences in the three speech

rate conditions using Python showed peak frequencies at 81.6 Hz (SD 3.2) and 81 Hz (SD 3.3)

for the normal rate and time-compressed conditions respectively, and at 91.9 Hz (SD 9.8) for

the fast rate condition (see Figure S5 in the supplementary material). These peak frequencies

are consistent with the computation of the median pitch values with Praat.

To assess whether brain-to-F0 coupling occurs with the high-frequency carrier information in

speech and not with the modulations of the amplitude envelope, we generated amplitude-

modulated noise stimuli as control conditions. A total of 576 control stimuli were created by

modulating Gaussian white noise (lacking linguistic content) with the amplitude envelope of

each of the 288 natural normal rate and 288 natural fast rate sentences. We also added forty-

eight filler sentences (different from the experimental stimuli but following the same syntactic

structure) in which beep-sounds were inserted at different possible time-points (i.e. 200, 600 or

800 ms from onset) in the sentences. These filler sentences were used to encourage participants

to pay attention to the auditory stimuli during the experiment (see Experimental procedure).

The stimuli were distributed across two experimental lists, each including 288 sentences (96

for each speech rate condition), 192 amplitude-modulated noise stimuli (96 modulated with the

normal rate envelope and 96 with the fast rate envelope) and 48 filler sentences, for a total of

528 stimuli per list. Each participant was presented with one list, in which each sentence

appeared in only one of the three rate conditions (i.e., no sentence was repeated within a

participant). The assignment of sentences to rate conditions was rotated across the two lists,

such that sentences appearing in both lists were assigned to different rate conditions in each.

4.3 Experimental procedure

While comfortably sitting in a sound-attenuated, magnetically-shielded recording room with a

screen in front of them, participants were presented binaurally with stimuli through air-

conducting tubes with foam insert earphones (Etymotic ER2 and ER3). Prior to the MEG

recording, their auditory detection thresholds were determined for each ear with a pure tone.

The level was then adjusted in order to present stimuli at 50 dB Sensation Level (SL) with a

central position (stereo) with respect to the participant's head.

Each trial of the experiment ran as follows: after a fixation cross displayed at the centre of the

screen for 1500 ms, an auditory stimulus (sentence or amplitude-modulated noise) was

presented, with the fixation cross remaining on the screen. Participants were instructed to

attentively listen to all stimuli while looking at the fixation cross and to press a button (response

button Neuroscan, Pantev) with their left index finger as quickly as possible whenever they

detected beep-sounds in (filler) sentences. The next trial started after an inter-trial interval (grey

screen) of 1250 ms. Participants detected 100% of the filler trials, which were excluded from

subsequent analysis. Each participant listened to the stimuli from one of the two experimental

lists. The total of 528 stimuli were pseudo-randomly divided into 8 blocks (66 stimuli each)

separated by short breaks to allow the participants to rest. Participants were familiarized with

the stimuli and task in a training phase (5 sentences different from the experimental stimuli).

To further maintain their attention throughout the experiment, they were informed that

questions on the heard sentences would be asked at the end of the experiment. More precisely,

they had to indicate, by ticking a yes/no box on a paper sheet, whether eight proposed sentences

(three of which were not experimental stimuli) were presented during the MEG experiment.

The experiment was run with Presentation software (Neurobehavioral Systems).

4.4 MEG data acquisition and analysis

We recorded neuromagnetic brain activity of the 24 participants using a 275-channel whole-

head MEG system (CTF OMEGA 275, Canada) at 1200 Hz sampling rate. Head position within

the MEG helmet was monitored with three fiducial coils (nasion, left and right pre-auricular

points) placed on the participant's head. Horizontal and vertical eye movements were also

recorded with four electrooculography (EOG) electrodes. We recorded reference head position

before each of the 8 experimental blocks and tracked head movements throughout the

experiment using continuous head position identification (HPI).

Preprocessing of the MEG data was done with custom written Matlab scripts (Mathworks Inc.,

MA, USA) and the Fieldtrip toolbox[105]. Subsequent coupling analyses were carried out in

Python using custom scripts and the MNE-Python library[106]. In the following we describe the

processing of 1) speech recordings, 2) MEG data, 3) Magnetic Resonance Imaging (MRI) data,

and the analyses of 4) source localization, power and coupling, and 5) coupling maps and

statistics.

4.4.1 Audio Recordings (reference signals)

To examine the neural tracking of speech F0, we used the speech signal as the reference.

Inspection of the F0 distributions and power spectral densities revealed some spectral (including

F0s) overlap between sentences in the different speech rate conditions (see Supplementary

Figure S1 A and C). To test our hypothesis that brain oscillatory activity adjusts to F0 increase

with speech rate acceleration, we optimized the distinction between conditions in terms of F0s

by selecting a proportion of sentences in the natural normal rate and time-compressed

conditions with the lowest mean F0s (71% and 77% of the sentences on average per participant,

respectively). Similarly, we selected sentences in the natural fast rate condition with the highest

mean F0s (~62% on average per participant). To do this, we collected sentences from the normal

rate/time-compressed and fast rate conditions starting from opposite sides of the spectrum, thus

maximizing the spectral distance between these two subsets while keeping an acceptable

number of sentences in each condition (see Supplementary Table S1). This resulted in normal

rate and time-compressed sentences with the lowest F0s (i.e. below 83 Hz) and a F0 peak at 80

Hz, and natural fast rate sentences with the highest F0s (i.e. above 87 Hz) peaking at 93 Hz (see

Supplementary Figure S1 B and D). We analyzed brain-to-speech coupling in two frequency

ranges centered on the F0 peak values (across sentences) of the two subsets of sentences (with

7Hz bandwidth), namely 77-84 Hz and 90-97 Hz. We note that this sentence selection procedure

transforms a continuous acoustic variable into a categorical one, and that excluding sentences

with overlapping F0 reduces statistical power. However, this step was necessary to ensure

sufficient spectral separation between conditions for a meaningful test of frequency-specific

coupling. Importantly, the selection retained a majority of sentences in each condition, and the

coupling spectra computed over the full frequency range (Figure 3) confirm that the observed

peaks are not artifacts of this selection. For this coupling analysis, we selected speech segments

between 200 ms and 1000 ms post-stimulus onset, as the shortest sentences in the natural fast

and time-compressed conditions were ~1 s long (this time-window for speech segments equals

the time-window of interest of the functional MEG data, see next section).

4.4.2 MEG data

The MEG continuous data were segmented into 3 s periods (from 1 s before to 2 s after stimulus

onset). A standard semi-automatic procedure available in the Fieldtrip toolbox was used to

reject data segments contaminated by eye blinks, heartbeat and muscle artefacts. To remove

the power line artefact and its harmonics notch-filtering was applied at 50, 100 and 150 Hz.

We then detected and rejected EOG, jumps and muscle artifacts and visually double-checked

the trials. Finally, an Independent Component Analysis (ICA) was used to correct for ECG

artifacts. For each trial, the time interval of interest was set between 200 ms and 1000 ms after

stimulus onset, while the baseline extended from 1000 ms to 200 ms before onset. The cleaned

and segmented data was then imported to Python to perform the coupling analysis.

4.4.3 MRI data

T1-weighted structural MRIs (MRI 1.5 T, Siemens AvantoFit) were acquired for 23 of the 24

participants after the MEG study. Alignment of each MRI to the MEG coordinate system was

performed with the localization coils marked on the MRIs and the interactive alignment

interface available in MNE. Each MRI was segmented to compute each participant's head

model using the single-shell as volume conductor model[107]. To carry out group analyses in a

common space, we first spatially normalized a template anatomical grid from the Montreal

Neurological Institute (MNI) common coordinate system. MRI grids of each participant were

then aligned to this normalized template (this common grid has 5124 vertices). We finally

computed the cortical source space modelling for each participant using the individual MRI

volume, but with the surface grid based on the MNI template. This allowed transforming the

results to the same brain template for all participants for easier comparison.

4.4.4 Source localization, power and cortico-acoustic coupling estimation

We estimated source power and cortico-acoustic coupling given source reconstructions

calculated using Minimum Norm Estimation[108-110]. Before computing the coupling, we

resampled the speech signal to 1200 Hz to match the sampling frequency of the MEG data. In

this way, we could suitably assess the neural tracking of F0 by computing the coupling between

auditory signals and cortical activity using Phase Lag Index and coherence measures. The Phase

Lag Index provides information regarding the coupling of two signals with respect to the sign

of their phase difference[112]. It has the advantage of being insensitive to the amplitude of the

signals and moreover, neglecting zero-phase coupling that commonly arise because of volume

conduction. It can be mathematically defined as:

599
$$PLI\left(r_{ef}, r_c, f\right) = |E[sign\left(Im[C_s\left(r_{ef}, r_c, f\right)]\right)]|$$

where r_{ef} is the reference signal, namely the acoustic signal here; r_c is the brain signal at each

vertex of the anatomical grid; ***f*** is the frequency bin and ***Cs*** is the Cross Spectral Density (CSD)

matrix. The operator E[x] refers to the average over trials, |x| is the absolute value, sign(x)

returns the sign of the value, and Im[x] gives the imaginary part of a complex number.

Coherence refers to the linear correlation between two signals as a function of frequency. It can

be mathematically defined as:

607
$$Coh\left(r_{ef}, r_c, f\right) = \frac{|E[Cs\left(r_{ef}, r_c, f\right)]|}{\sqrt{E\left[Cs\left(r_{ef}, r_{ef}, f\right)\right] E[Cs\left(r_c, r_c, f\right)]}}$$

608   where the notation is the same as the one used in the previous equation.

We computed PLI and coherence using the MNE-Connectivity package within the MNE-Python ecosystem[106]. Specifically, the CSD matrix was computed using the multitaper Fast Fourier Transform (FFT) from 64 to 128 Hz, with 7 DPSS tapers (bandwidth ≈ 10 Hz) applied to 0.8 s segments (961 time points), yielding a frequency resolution of approximately 1.25 Hz. Cortico-acoustic coupling was calculated for the active period (200 to 1000 ms), the baseline (-1000 to -200 ms), and for shuffled data, the last two serving as control conditions for statistical analyses for power and coupling, respectively. In the case of surrogate data, we randomly shuffled the samples of the audio signals before computing cortico-acoustic coupling (i.e. the structure of the audio signal was lost and consequently did not match its MEG counterpart for the coupling computation). We repeated this procedure 100 times and averaged coupling across iterations for each participant, and each experimental condition and frequency bin. For both active, baseline and shuffled data, the couplings (and power) were averaged across the frequency bins inside each band of interest.

4.4.5 Cortico-acoustic coupling maps, power maps and statistical analyses

The average coupling and power maps used for visualization in the Results section were obtained by first applying the Fisher transform of the values. Then we computed the difference between the active period and a set of control data (shuffled audio for coupling, and baseline for power) for each participant and condition. In the case of power, the relative difference was used. The values were then averaged across participants for each experimental condition and subsequently mapped to the brain plots. Group statistical analysis was conducted on the raw coupling and power values (without the Fisher transform) for the 23 participants with individual MRIs. For PLI and power, we applied cluster-based permutation tests with 1024 permutations [113]. For coherence, we performed an FDR corrected t-test. The tests are one-tailed for cortico-

acoustic coupling analysis and two-tailed for power analysis. All tests use a statistical

significance threshold of 0.001. We used the Desikan-Killiany atlas to identify the regions

detected as significant in the statistical analysis[114]. The top 10 regions with the highest mean t-

value based on the PLI statistical analysis for each frequency range, condition, and hemisphere

can be found in Supplementary Table S2.

To inspect more closely the changes in coupling frequency with F0 variation, we additionally

computed - for each of the three speech rate conditions - the coupling spectra during the

encoding period, both for PLI and coherence, across a wide range of frequencies (64-128 Hz)

and averaged through participants. This was done on all voxels and then averaged into the

regions of the Desikan-Killiany atlas[114] (aparc parcellation). We simultaneously explored two

other parcellations: aparc_sub[115] (corresponding to subdivisions of the regions of the aparc

parcellation) and PALS-B12[116] (which delineates Brodmann areas). Then, the top 8 regions in

the right hemisphere with the highest PLI peak independent of the speech rate conditions were

identified for each of the three parcellations. These regions are detailed in Figures S2, S3 and

S4. We further compared the top region of each parcellation with the frontal pole, selected as

the control region since it was not expected to show any F0 response (see Figure 3; see also[23]).

Additionally, to assess the potential effects of power modulations, we computed the power

spectra of the encoding brain signals at these locations in a similar manner. To better compare

the coupling spectra to the oscillatory peaks in the brain power, we removed the aperiodic

component using the FOOOF (specparam) methodology[44]. The details of the model that fits

each of the spectra involved in Figure 3 can be seen in Supplementary Figure S5.

References

1.   Ding, N. & Simon, J. Z. Cortical entrainment to continuous speech: functional roles and

interpretations. *Front. Hum. Neurosci.* **8**, (2014).

2.   Ghitza, O. Linking Speech Perception and Neurophysiology: Speech Decoding Guided by

Cascaded Oscillators Locked to the Input Rhythm. *Front. Psychol.* **2**, (2011).

3.   Giraud, A.-L. & Poeppel, D. Cortical oscillations and speech processing: emerging computational

principles and operations. *Nat. Neurosci.* **15**, 511–517 (2012).

4.   Peelle, J. E. & Davis, M. H. Neural Oscillations Carry Speech Rhythm through to Comprehension.

Front. Psychol. **3**, (2012).

5.   Ding, N., Chatterjee, M. & Simon, J. Z. Robust Cortical Entrainment to the Speech Envelope

Relies on the Spectro-temporal Fine Structure. *NeuroImage* **88**, 41–46 (2014).

6.   Gross, J. *et al.* Speech Rhythms and Multiplexed Oscillatory Sensory Coding in the Human Brain.

PLoS Biol. **11**, e1001752 (2013).

7.   Keitel, A., Gross, J. & Kayser, C. Perceptually relevant speech tracking in auditory and motor

cortex reflects distinct linguistic features. *PLOS Biol.* **16**, e2004473 (2018).

8.   Kösem, A., Basirat, A., Azizi, L. & Wassenhove, V. van. High-frequency neural activity predicts

word parsing in ambiguous speech streams. *J. Neurophysiol.* **116**, 2497–2512 (2016).

9.   Peelle, J. E., Gross, J. & Davis, M. H. Phase-locked responses to speech in human auditory cortex

are enhanced during comprehension. *Cereb. Cortex* **23**, 1378–1387 (2013).

10.   Kubanek, J., Brunner, P., Gunduz, A., Poeppel, D. & Schalk, G. The Tracking of Speech Envelope

in the Human Cortex. *PLOS ONE* **8**, e53398 (2013).

11.   Lizarazu, M., Lallier, M. & Molinaro, N. Phase–amplitude coupling between theta and gamma

oscillations adapts to speech rate. *Ann. N. Y. Acad. Sci.* **1453**, 140–152 (2019).

12.   Mesgarani, N. & Chang, E. F. Selective cortical representation of attended speaker in multi-

talker speech perception. *Nature* **485**, (2012).

13.   Nourski, K. V. *et al.* Temporal Envelope of Time-Compressed Speech Represented in the Human

Auditory Cortex. *J. Neurosci.* **29**, 15564–15574 (2009).

14.   Zion Golumbic, E. M. *et al.* Mechanisms Underlying Selective Neuronal Tracking of Attended

Speech at a 'Cocktail Party'. *Neuron* **77**, 980–991 (2013).

15.   Rosen, S. Temporal information in speech: Acoustic, auditory and linguistic aspects. *Philos.*

Trans. R. Soc. B Biol. Sci. **336**, 367–373 (1992).

16.   Russo, N., Nicol, T., Musacchia, G. & Kraus, N. Brainstem responses to speech syllables. *Clin.*

Neurophysiol. **115**, 2021–2030 (2004).

17.   Kraus, N. & Nicol, T. Brainstem origins for cortical 'what' and 'where' pathways in the auditory

system. *Trends Neurosci.* **28**, 176–181 (2005).

18.   Kraus, N., Anderson, S., White-Schwoch, T., Fay, R. & Popper, A. The Frequency-Following

Response: A Window into Human Communication. in *The frequency-following response* 1–15

(New York: Springer, 2017). doi:10.1007/978-3-319-47944-6.

19.   Coffey, E. B. J. *et al.* Evolving perspectives on the sources of the frequency-following response.

Nat. Commun. **10**, 1–10 (2019).

20.   Chandrasekaran, B. & Kraus, N. The scalp-recorded brainstem response to speech: Neural

origins and plasticity. *Psychophysiology* **47**, 236–246 (2010).

21.   Bidelman, G. M. Subcortical sources dominate the neuroelectric auditory frequency-following

response to speech. *NeuroImage* **175**, 56–69 (2018).

22.   Bidelman, G. M. & Momtaz, S. Subcortical rather than cortical sources of the frequency-

following response (FFR) relate to speech-in-noise perception in normal-hearing listeners.

Neurosci. Lett. **746**, 135664 (2021).

23.   Coffey, E. B. J., Herholz, S. C., Chepesiuk, A. M. P., Baillet, S. & Zatorre, R. J. Cortical

contributions to the auditory frequency-following response revealed by MEG. *Nat. Commun.* **7**,

11070 (2016).

24.   Coffey, E. B. J., Musacchia, G. & Zatorre, R. J. Cortical Correlates of the Auditory Frequency-

710   Following and Onset Responses: EEG and fMRI Evidence. *J. Neurosci.* **37**, 830–838 (2017).

711   25.   Gnanateja, G. N. *et al.* Frequency-Following Responses to Speech Sounds Are Highly Conserved

712   across Species and Contain Cortical Contributions. *eNeuro* **8**, ENEURO.0451-21.2021 (2021).

713   26.   Guo, N. *et al.* Speech frequency-following response in human auditory cortex is more than a

714   simple tracking. *NeuroImage* **226**, 117545 (2021).

715   27.   Hartmann, T. & Weisz, N. Auditory cortical generators of the Frequency Following Response are

716   modulated by intermodal attention. *NeuroImage* **203**, 116185 (2019).

717   28.   Ross, B., Tremblay, K. L. & Alain, C. Simultaneous EEG and MEG recordings reveal vocal pitch

718   elicited cortical gamma oscillations in young and older adults. *NeuroImage* **204**, 116253 (2020).

719   29.   Hertrich, I., Dietrich, S., Trouvain, J., Moos, A. & Ackermann, H. Magnetic brain activity phase-

720   locked to the envelope, the syllable onsets, and the fundamental frequency of a perceived

721   speech signal. *Psychophysiology* **49**, 322–334 (2012).

722   30.   Puschmann, S., Baillet, S. & Zatorre, R. J. Musicians at the Cocktail Party: Neural Substrates of

723   Musical Training During Selective Listening in Multispeaker Situations. *Cereb. Cortex* **29**,

724   3253–3265 (2019).

725   31.   Greenlaw, K. M., Puschmann, S. & Coffey, E. B. J. Decoding of Envelope vs. Fundamental

726   Frequency During Complex Auditory Stream Segregation. *Neurobiol. Lang.* **1**, 268–287 (2020).

727   32.   Kulasingham, J. P. *et al.* High gamma cortical processing of continuous speech in younger and

728   older listeners. *NeuroImage* **222**, 117291 (2020).

729   33.   Van Canneyt, J., Wouters, J. & Francart, T. Neural tracking of the fundamental frequency of the

730   voice: The effect of voice characteristics. *Eur. J. Neurosci.* **53**, 3640–3653 (2021).

731   34.   Duecker, K. *et al.* Challenges and Approaches in the Study of Neural Entrainment. *J. Neurosci.*

732   *Off. J. Soc. Neurosci.* **44**, e1234242024 (2024).

733   35.   Berry, J. J. Speaking Rate Effects on Normal Aspects of Articulation: Outcomes and Issues.

734   *Perspect. Speech Sci. Orofac. Disord.* **21**, 15–26 (2011).

36.   Caspers, J. & van Heuven, V. J. Effects of Time Pressure on the Phonetic Realization of the Dutch

Accent-Lending Pitch Rise and Fall. *Phonetica* **50**, 161–171 (1993).

37.   Fougeron, C. & Jun, S.-A. Rate effects on French intonation: prosodic organization and phonetic

realization. *J. Phon.* **26**, 45–69 (1998).

38.   Hincapié-Casas, A. S. *et al.* Neural oscillations track natural but not artificial fast speech: Novel

insights from speech-brain coupling using MEG. *bioRxiv* 2020.10.20.344895 (2021)

doi:10.1101/2020.10.20.344895.

39.   Pefkou, M., Arnal, L. H., Fontolan, L. & Giraud, A.-L. Theta- and beta-band neural activity reflect

independent syllable tracking and comprehension of time-compressed speech. *J. Neurosci.*

2882–16 (2017) doi:10.1523/JNEUROSCI.2882-16.2017.

40.   Ray, S. & Maunsell, J. H. R. Different Origins of Gamma Rhythm and High-Gamma Activity in

Macaque Visual Cortex. *PLoS Biol.* **9**, e1000610 (2011).

41.   Buzsáki, G. & Wang, X.-J. Mechanisms of Gamma Oscillations. *Annu. Rev. Neurosci.* **35**, 203–225

(2012).

42.   Janse, E. Word perception in fast speech: artificially time-compressed vs. naturally produced

fast speech. *Speech Commun.* **42**, 155–173 (2004).

43.   Lerousseau, J. P., Trébuchon, A., Morillon, B. & Schön, D. Frequency Selectivity of Persistent

Cortical Oscillatory Responses to Auditory Rhythmic Stimulation. *J. Neurosci.* **41**, 7991–8006

(2021).

44.   Donoghue, T. *et al.* Parameterizing neural power spectra into periodic and aperiodic

components. *Nat. Neurosci.* **23**, 1655–1665 (2020).

45.   Hyde, K. L., Peretz, I. & Zatorre, R. J. Evidence for the role of the right auditory cortex in fine

pitch resolution. *Neuropsychologia* **46**, 632–639 (2008).

46.   Johnsrude, I. S., Penhune, V. B. & Zatorre, R. J. Functional specificity in the right human auditory

cortex for perceiving pitch direction. *Brain* **123**, 155–163 (2000).

47.   Meyer, M., Alter, K., Friederici, A. D., Lohmann, G. & von Cramon, D. Y. FMRI reveals brain

regions mediating slow prosodic modulations in spoken sentences. *Hum. Brain Mapp.* **17**,

73–88 (2002).

48.   Tamura, S. *et al.* Multi-modal imaging of the auditory-larynx motor network for voicing

perception. *NeuroImage* **251**, 118981 (2022).

49.   Zatorre, R. J. & Belin, P. Spectral and Temporal Processing in Human Auditory Cortex. *Cereb.*

Cortex **11**, 946–953 (2001).

50.   Hickok, G. & Poeppel, D. The cortical organization of speech processing. *Nat. Rev. Neurosci.* **8**,

393–402 (2007).

51.   Rauschecker, J. P. & Scott, S. K. Maps and streams in the auditory cortex: nonhuman primates

illuminate human speech processing. *Nat. Neurosci.* **12**, 718–724 (2009).

52.   Franken, M. K., Liu, B. C. & Ostry, D. J. Towards a somatosensory theory of speech perception. *J.*

Neurophysiol. **128**, 1683–1695 (2022).

53.   Belyk, M. & Brown, S. The origins of the vocal brain in humans. *Neurosci. Biobehav. Rev.* **77**,

177–193 (2017).

54.   Cogan, G. B. *et al.* Sensory–motor transformations for speech occur bilaterally. *Nature* **507**,

94–98 (2014).

55.   Conant, D., Bouchard, K. E. & Chang, E. F. Speech Map in the Human Ventral Sensory-Motor

Cortex. *Curr. Opin. Neurobiol.* **0**, 63–67 (2014).

56.   Dichter, B. K., Breshears, J. D., Leonard, M. K. & Chang, E. F. The Control of Vocal Pitch in

Human Laryngeal Motor Cortex. *Cell* **174**, 21-31.e9 (2018).

57.   Eichert, N., Papp, D., Mars, R. B. & Watkins, K. E. Mapping Human Laryngeal Motor Cortex

during Vocalization. *Cereb. Cortex* **30**, 6254–6269 (2020).

58.   Eichert, N., Watkins, K. E., Mars, R. B. & Petrides, M. Morphological and functional variability in

central and subcentral motor cortex of the human brain. *Brain Struct. Funct.* **226**, 263–279

(2021).

59.   Grabski, K. *et al.* Functional MRI assessment of orofacial articulators: Neural correlates of lip,

jaw, larynx, and tongue movements. *Hum. Brain Mapp.* **33**, 2306–2321 (2012).

60.   Bouchard, K. E., Mesgarani, N., Johnson, K. & Chang, E. F. Functional Organization of Human

Sensorimotor Cortex for Speech Articulation. *Nature* **495**, 327–332 (2013).

61.   Toyoda, G. *et al.* Electrocorticographic correlates of overt articulation of 44 English phonemes:

Intracranial recording in children with focal epilepsy. *Clin. Neurophysiol.* **125**, 1129–1137

(2014).

62.   Archila-Meléndez, M. E. *et al.* Sensorimotor Representation of Speech Perception. Cross-

Decoding of Place of Articulation Features during Selective Attention to Syllables in 7T fMRI.

eNeuro **5**, (2018).

63.   Arsenault, J. S. & Buchsbaum, B. R. Distributed Neural Representations of Phonological Features

during Speech Perception. *J. Neurosci.* **35**, 634–642 (2015).

64.   Correia, J. M., Jansma, B. M. B. & Bonte, M. Decoding Articulatory Features from fMRI

Responses in Dorsal Speech Regions. *J. Neurosci.* **35**, 15015–15025 (2015).

65.   Brown, S., Ngan, E. & Liotti, M. A Larynx Area in the Human Motor Cortex. *Cereb. Cortex* **18**,

837–845 (2008).

66.   D'Ausilio, A., Bufalari, I., Salmas, P., Busan, P. & Fadiga, L. Vocal pitch discrimination in the

motor system. *Brain Lang.* **118**, 9–14 (2011).

67.   Liang, B., Li, Y., Zhao, W. & Du, Y. Bilateral human laryngeal motor cortex in perceptual decision

of lexical tone and voicing of consonant. *Nat. Commun.* **14**, 4710 (2023).

68.   Lu, J. *et al.* Neural control of lexical tone production in human laryngeal motor cortex. *Nat.*

Commun. **14**, 6917 (2023).

69.   Simonyan, K. The laryngeal motor cortex: its organization and connectivity. *Curr. Opin.*

Neurobiol. **28**, 15–21 (2014).

70.   Sammler, D., Grosbras, M.-H., Anwander, A., Bestelmeyer, P. E. G. & Belin, P. Dorsal and Ventral

Pathways for Prosody. *Curr. Biol.* **25**, 3079–3085 (2015).

71.   Rauschecker, J. P. An expanded role for the dorsal auditory pathway in sensorimotor control

813   and integration. *Hear. Res.* **271**, 16–25 (2011).

814   72.   Shum, M., Shiller, D. M., Baum, S. R. & Gracco, V. L. Sensorimotor integration for speech motor

815   learning involves the inferior parietal cortex. *Eur. J. Neurosci.* **34**, 1817–1822 (2011).

816   73.   Hartwigsen, G. *et al.* Phonological decisions require both the left and right supramarginal gyri.

817   *Proc. Natl. Acad. Sci. U. S. A.* **107**, 16494–16499 (2010).

818   74.   Mutschler, I. *et al.* Functional organization of the human anterior insular cortex. *Neurosci. Lett.*

819   **457**, 66–70 (2009).

820   75.   Ackermann, H. & Riecker, A. The contribution(s) of the insula to speech production: a review of

821   the clinical and functional imaging literature. *Brain Struct. Funct.* **214**, 419–433 (2010).

822   76.   Dronkers, N. F. A new brain region for coordinating speech articulation. *Nature* **384**, 159–161

823   (1996).

824   77.   Howell, P., Jiang, J., Peng, D. & Lu, C. Neural control of fundamental frequency rise and fall in

825   Mandarin tones. *Brain Lang.* **121**, 35–46 (2012).

826   78.   Bamiou, D.-E., Musiek, F. E. & Luxon, L. M. The insula (Island of Reil) and its role in auditory

827   processing: Literature review. *Brain Res. Rev.* **42**, 143–154 (2003).

828   79.   Bamiou, D.-E. *et al.* Auditory temporal processing deficits in patients with insular stroke.

829   *Neurology* **67**, 614–619 (2006).

830   80.   Oh, A., Duerden, E. G. & Pang, E. W. The role of the insula in speech and language processing.

831   *Brain Lang.* **135**, 96–103 (2014).

832   81.   Tregellas, J. R., Davalos, D. B. & Rojas, D. C. Effect of task difficulty on the functional anatomy of

833   temporal processing. *NeuroImage* **32**, 307–315 (2006).

834   82.   Zhang, Y. *et al.* The Roles of Subdivisions of Human Insula in Emotion Perception and Auditory

835   Processing. *Cereb. Cortex* **29**, 517–528 (2019).

836   83.   Ghaziri, J. *et al.* The Corticocortical Structural Connectivity of the Human Insula. *Cereb. Cortex*

837   **27**, 1216–1228 (2017).

84.   Simonyan, K., Ostuni, J., Ludlow, C. L. & Horwitz, B. Functional But Not Structural Networks of

the Human Laryngeal Motor Cortex Show Left Hemispheric Lateralization during Syllable But

Not Breathing Production. *J. Neurosci.* **29**, 14912–14923 (2009).

85.   Simonyan, K. & Horwitz, B. Laryngeal Motor Cortex and Control of Speech in Humans. *Neurosci.*

Rev. J. Bringing Neurobiol. Neurol. Psychiatry **17**, 197–208 (2011).

86.   Coffey, E. B. J., Arseneau-Bruneau, I., Zhang, X., Baillet, S. & Zatorre, R. J. Oscillatory

entrainment of the Frequency Following Response in auditory cortical and subcortical

structures. *J. Neurosci.* https://doi.org/10.1523/JNEUROSCI.2313-20.2021 (2021)

doi:10.1523/JNEUROSCI.2313-20.2021.

87.   Etard, O., Kegler, M., Braiman, C., Forte, A. E. & Reichenbach, T. Decoding of selective attention

to continuous speech from the human auditory brainstem response. *NeuroImage* **200**, 1–11

(2019).

88.   Forte, A. E., Etard, O. & Reichenbach, T. The human auditory brainstem response to running

speech reveals a subcortical mechanism for selective attention. *eLife* **6**, e27203 (2017).

89.   Maddox, R. K. & Lee, A. K. C. Auditory Brainstem Responses to Continuous Natural Speech in

Human Listeners. *eNeuro* **5**, (2018).

90.   Schüller, A., Schilling, A., Krauss, P., Rampp, S. & Reichenbach, T. Attentional Modulation of the

Cortical Contribution to the Frequency-Following Response Evoked by Continuous Speech. *J.*

Neurosci. **43**, 7429–7440 (2023).

91.   Brodski, A., Paasch, G.-F., Helbling, S. & Wibral, M. The Faces of Predictive Coding. *J. Neurosci.*

35, 8997–9006 (2015).

92.   Lewis, A. G. & Bastiaansen, M. A predictive coding framework for rapid neural dynamics during

sentence-level language comprehension. *Cortex* **68**, 155–168 (2015).

93.   van Pelt, S. *et al.* Beta- and gamma-band activity reflect predictive coding in the processing of

causal events. *Soc. Cogn. Affect. Neurosci.* **11**, 973–980 (2016).

94. Keitel, A., Ince, R. A. A., Gross, J. & Kayser, C. Auditory cortical delta-entrainment interacts with

oscillatory power in multiple fronto-parietal networks. *NeuroImage* **147**, 32–42 (2017).

95. Morillon, B. & Baillet, S. Motor origin of temporal predictions in auditory attention. *Proc. Natl.*

Acad. Sci. U. S. A. **114**, E8913–E8921 (2017).

96. Park, H., Ince, R. A. A., Schyns, P. G., Thut, G. & Gross, J. Frontal Top-Down Signals Increase

Coupling of Auditory Low-Frequency Oscillations to Continuous Speech in Human Listeners.

Curr. Biol. **25**, 1649–1653 (2015).

97. Gorina-Careta, N., Kurkela, J. L. O., Hämäläinen, J., Astikainen, P. & Escera, C. Neural generators

of the frequency-following response elicited to stimuli of low and high frequency: A

magnetoencephalographic (MEG) study. *NeuroImage* **231**, 117866 (2021).

98. Holmes, E., Purcell, D. W., Carlyon, R. P., Gockel, H. E. & Johnsrude, I. S. Attentional Modulation

of Envelope-Following Responses at Lower (93–109 Hz) but Not Higher (217–233 Hz)

Modulation Rates. *J. Assoc. Res. Otolaryngol.* **19**, 83–97 (2018).

99. Brugge, J. F. *et al.* Coding of Repetitive Transients by Auditory Cortex on Heschl's Gyrus. *J.*

Neurophysiol. **102**, 2358–2374 (2009).

100. Nourski, K. V. *et al.* Sound identification in human auditory cortex: Differential contribution of

local field potentials and high gamma power as revealed by direct intracranial recordings. *Brain*

Lang. **148**, 37–50 (2015).

101. Oldfield, R. C. The assessment and analysis of handedness: the Edinburgh inventory.

Neuropsychologia **9**, 97–113 (1971).

102. Ferragne, E., Flavier, S. & Fressard, C. Recording of Oral Corpora Made Easy (ROCme): logiciel

d'enregistrement de corpus (2012).

103. Boersma, P. & Weenink, D. *Doing Phonetics by Computer [Computer Program]*. (2012).

104. Moulines, E. & Charpentier, F. Pitch-synchronous waveform processing techniques for text-to-

speech synthesis using diphones. *Speech Commun.* **9**, 453–467 (1990).

105. Oostenveld, R., Fries, P., Maris, E. & Schoffelen, J. M. FieldTrip: Open source software for

advanced analysis of MEG, EEG, and invasive electrophysiological data. *Comput. Intell.*

Neurosci. **2011**, (2011).

106. Gramfort, A. *et al.* MEG and EEG data analysis with MNE-Python. *Front. Neurosci.* **7**, (2013).

107. Nolte, G. The magnetic lead field theorem in the quasi-static approximation and its use for

magnetoencephalography forward calculation in realistic volume conductors. *Phys. Med. Biol.*

48, 3637–52 (2003).

108. Dale, A. M. & Sereno, M. I. Improved Localization of Cortical Activity by Combining EEG and

MEG with MRI Cortical Surface Reconstruction: A Linear Approach. *J. Cogn. Neurosci.* **5**,

162–176 (1993).

109. Gramfort, A. *et al.* MNE software for processing MEG and EEG data. *NeuroImage* **86**, 446–460

(2014).

110. Hämäläinen, M. S. & Ilmoniemi, R. J. Interpreting magnetic fields of the brain: minimum norm

estimates. *Med. Biol. Eng. Comput.* **32**, 35–42 (1994).

111. Gross, J. *et al.* Dynamic imaging of coherent sources: Studying neural interactions in the human

brain. *Proc. Natl. Acad. Sci. U. S. A.* **98**, 694–9 (2001).

112. Stam, C. J., Nolte, G. & Daffertshofer, A. Phase lag index: Assessment of functional connectivity

from multi channel EEG and MEG with diminished bias from common sources. *Hum. Brain*

Mapp. **28**, 1178–1193 (2007).

113. Maris, E. & Oostenveld, R. Nonparametric statistical testing of EEG- and MEG-data. *J. Neurosci.*

Methods **164**, 177–90 (2007).

114. Desikan, R. S. *et al.* An automated labeling system for subdividing the human cerebral cortex on

MRI scans into gyral based regions of interest. *NeuroImage* **31**, 968–980 (2006).

115. Khan, S. *et al.* Maturation trajectories of cortical resting-state networks depend on the

mediating frequency band. *NeuroImage* **174**, 57–68 (2018).

116. Van Essen, D. C. A Population-Average, Landmark- and Surface-based (PALS) atlas of human

cerebral cortex. *NeuroImage* **28**, 635–662 (2005).

CRediT authorship contribution statement: Yorguin-Jose Mantilla-Ramos: Data curation, Formal analysis, Methodology, Software, Visualization, Writing – original draft. Ana-Sofía Hincapié-Casas: Data curation, Formal analysis, Methodology, Software. Annalisa Pascarella: Methodology. Tarek Lajnef: Methodology. Richard M. Leahy: Methodology. Emily Coffey: Writing – review & editing. Karim Jerbi: Conceptualization, Methodology, Software, Validation, Resources, Writing – original draft, Supervision, Project administration, Funding acquisition. Véronique Boulenger: Conceptualization, Methodology, Validation, Investigation, Resources, Writing – original draft, Supervision, Project administration, Funding acquisition.

Acknowledgements: We thank Damien Gouy for recording the stimuli, Emmanuel Ferragne for his help with Praat software, and Mélanie Canault for discussions on articulatory phonetics. AI-assisted language tools were used during the preparation of this manuscript to improve text readability. All authors reviewed and edited the output and take full responsibility for the content of the publication.

Funding: V.B. discloses support for the research of this work from the French National Research Agency ANR (ANR-11 JSH2 005 1; PI: V.B) and the Laboratory of Excellence ASLAN (ANR-10-LABX-0081) of Université de Lyon within the program Investissements d'Avenir (ANR-11-IDEX-0007). Y-J.M-R discloses support from Mitacs through the Mitacs Globalink program. A-S.H-C was supported in part by a scholarship from Comisión Nacional de Ciencia y Tecnología de Chile (CONICYT), Colfuturo (Colombia), and by the French ANR DEFIS program (ANR-09-EMER-002). K.J. discloses support for the research of this work from the Canada Research Chairs program and a Discovery Grant (RGPIN-2015-04854) awarded by the Natural Sciences and Engineering Research Council (NSERC) of Canada (the NSERC Discovery Grant also provided support to A-S.H-C).

Declaration of competing interests: The authors declare no competing interests.