Hitting the right pitch: Cortical tracking of speech fundamental frequency in auditory and somatomotor regions

Yorguin-Jose Mantilla-Ramos[1,2,6] Ana-Sofía Hincapié-Casas[1], Annalisa Pascarella[3], Tarek Lajnef[1], Richard M. Leahy[4], Emily Coffey[5] Karim Jerbi[1,6]* and Véronique Boulenger[7]*

[1] Cognitive and Computational Neuroscience Laboratory (CoCo Lab), Psychology Department, University of Montreal, Montreal, Montréal, QC H3C 3J7, Canada

[2] Neuropsychology and Behavior Group (GRUNECO), Medical School, Universidad de Antioquia, Antioquia, 050010 Colombia

[3] Institute for Applied Mathematics Mauro Picone, National Research Council, 00185 Rome, Italy

[4] Department of Electrical and Computer Engineering, University of Southern California, Los Angeles, 90089 California, USA

[5] Department of Psychology, Concordia University, Montreal, QC, H3G 1M8 Canada

[6] Mila (Quebec AI Institute), QC, H2S 3H1 Canada

[7] CNRS, Université Lyon 2, Laboratoire Dynamique du Langage, 69007 Lyon, France

* These authors contributed equally.

Corresponding authors: yorguin.jose.mantilla.ramos@umontreal.ca and veronique.boulenger@cnrs.fr

Abstract

Low-frequency neural oscillations contribute to the parsing of continuous speech into linguistic

units. Little is known however on the coupling of brain rhythms to higher-frequencies in speech

such as fundamental frequency (F0) or pitch. Using magnetoencephalography, we investigated

whole-brain cortical tracking of F0 while participants listened to sentences produced at normal

rate or fast rate, where pitch naturally increases, and to artificially accelerated sentences, where

F0 remains unchanged. Our results revealed significant brain-to-F0 coupling across all speech

rates not only in right auditory but also in right parietal, insular, and pre- and postcentral regions,

likely including the ventral larynx area. Importantly, the cortico-acoustic coupling peak

frequency was higher for natural fast speech to reflect the corresponding F0 increase compared

to normal rate and time-compressed speech. These findings demonstrate the engagement of an

auditory-somato-motor network in F0 tracking, supporting its role in facilitating phonemic

processing during the perception of naturally-produced speech.

Introduction

By tracking speech temporal structure, neural oscillations contribute to the parsing of the acoustic stream into hierarchically-organized linguistic constituents[1–4]. Substantial evidence from electro/magnetoencephalography (E/MEG) revealed phase-coupling of delta- (~1-3 Hz) and theta-band (~4-8 Hz) auditory cortical activity to the slow modulations of speech amplitude envelope, which mainly reflect the syllable rate[5–9]. Speech envelope has also been shown to modulate low (35-45 Hz) and high gamma (> 50 Hz) amplitude as well as theta phase/low gamma amplitude coupling[6,10–14].

Besides syllabic structure, speech periodicity is another temporal cue of chief importance for speech perception and communication as it conveys segmental (voicing, manner of articulation) and suprasegmental (intonation, stress) information[15]. It results from the quasi-periodic vibration of the vocal folds during production and includes a representation of the speaker's fundamental frequency (F0), which is the prime acoustic correlate of voice pitch. Only limited evidence exists regarding cortical tracking of F0 in naturally-produced speech. Many studies on pitch encoding measured the Frequency-Following Response (FFR), a sustained oscillatory response generally recorded by averaging responses to repeated syllables or tones that mimics stimulus periodicity and reflects precise auditory temporal processing[16–19]. Although the FFR recorded in EEG at the scalp is believed to originate primarily from the brainstem[20], contributions from the thalamus and auditory cortex were also reported, with cortical activity peaking at the stimulus F0[21–28]. Brain coupling to F0 in continuous sound streams has been given less attention. The studies available so far focusing on neural encoding of the F0 in naturalistic speech showed responses in the auditory cortex at the F0 of isolated sentences or stories[29–32]. For instance, using a linear modelling approach in EEG, Van Canneyt and colleagues[33] reported that the F0 of stories could be reconstructed from brain activity likely arising from the brainstem and the primary auditory cortex.

Here, we provide novel contribution to this line of research by assessing whether neural

oscillations, in the auditory cortex but also in other cortical regions, couple their oscillatory

activity with the F0 of natural speech produced at different rates. Besides spectro-temporal

modifications (e.g., shortening of acoustic cues, enhanced coarticulation)[34], naturally speaking

faster induces changes in the phonetic realization of F0. Acoustic studies in fact reported a shift

in the frequency of the pitch range with increasing speech rate, namely decreased or increased

pitch depending on speakers and languages[35,36]. We aimed to characterize how cortical F0

representation changes as a function of speech rate in natural speech. Following earlier work

that low-frequency neural oscillations (e.g., 2-9 Hz) adjust their coupling frequency to match

the faster syllable rate[37,38], we asked whether such frequency-shift also occurs for higher-

frequency oscillations to track the F0 changes accompanying speech rate increase. Using MEG,

we examined brain coupling to the F0 of sentences naturally produced at a normal or fast rate,

as well as of artificially accelerated (i.e. time-compressed) sentences. Given that time-

compression reduces signal duration while keeping its spectral and pitch content intact[39], time-

compressed speech has the same F0 as normal rate speech despite a faster syllabic rate. By

contrast, F0 inherently increases in naturally-produced accelerated speech compared to both

normal rate and time-compressed speech. Using Minimum Norm Estimation source

reconstruction methods, we compared cortico-acoustic coupling and power modulations during

sentence perception in the three speech rate conditions. In keeping with previous studies[7,37], we

analysed coupling in two frequency ranges centred on the mean F0 of our sentence material

(77-84 Hz for normal rate/time-compressed sentences and 90-97 Hz for natural fast speech). In

addition, a whole-brain analysis allowed to investigate whether coupling to sentences' F0 only

occurs in the auditory cortex or whether it involves a more distributed cortical network, noting

that previous work used region-of-interest based analyses, mostly in the primary auditory

cortex[e.g.23,32]. We are aware of only one stereotactic EEG / MEG study showing FFR in a

temporo-parieto-frontal cortical network in response to musical tones[40].

Our results reveal significant cortico-acoustic coupling in frequency ranges that are specific to

the sentences' fundamental frequency. Coupling indeed occurred in the higher frequency band

(90-97 Hz) for naturally-produced fast speech compared to normal rate speech, mirroring the

natural increase in speech F0. No change in coupling frequency (77-84 Hz) was on the contrary

observed for time-compressed sentences which have similar F0 to normal rate sentences.

Crucially, brain-to-F0 coupling was found in a right-lateralized network encompassing

temporal, parietal, precentral and postcentral cortices, known to contribute to speech perception

as well as to production. Such findings bring evidence that by adjusting to the rate of vocal fold

vibration, neural oscillations in sensorimotor regions contribute to the encoding of pitch and of

phonemic information conveyed by the periodicity of the speech signal.

Results

Twenty-four French native participants listened to natural normal rate (mean = 6.76 ± 0.57

syllables/s), natural fast rate (9.15 ± 0.60 syllables/s) and time-compressed sentences ($9.15 \pm$

0.60 syllables/s) while their MEG brain activity was recorded. The mean F0 of the natural

normal rate and time-compressed sentences was 81.3 Hz (SD 3.3) as calculated from the peaks

of the power spectrum of the sentences using Python. It increased to 91.9 Hz (SD 9.8) for

naturally accelerated sentences. Amplitude-modulated noise stimuli, generated with the

envelopes of normal rate and fast rate stimuli, and which lack pitch and verbal information,

were included as control conditions. We assessed neural tracking of changes in fundamental

frequency by computing cortico-acoustic coupling between the acoustic signals and source-

localized MEG time-series using phase-lag index (PLI) and, as a complementary approach,

coherence measures (see Methods for more details about the selected coupling metrics).

141 Because sentences' F0 in the different speech rate conditions overlapped to some extent, we

142 analysed speech-brain coupling in subsets of sentences for which the F0s of the normal and

143 time-compressed conditions were most distant from the F0s of the fast condition (see Methods

144 and Supplementary Figure S1 and Table S1). The F0 in these subsets peaked at 80 Hz for natural

145 normal rate and time-compressed sentences, and at 93 Hz for natural fast rate sentences. We

146 therefore conducted the coupling analysis in two frequency bands of interest centred on these

147 values, respectively, 77-84 Hz and 90-97 Hz. For statistical analysis, PLI and coherence

148 measures for actual stimulus encoding were compared with measures obtained on surrogate

149 data using a shuffling procedure and correction for multiple comparisons using, respectively,

150 cluster-based correction and FDR (see Methods).

151 PLI analyses revealed significant phase-locking of neural oscillations to speech fundamental

152 frequency, with a shift in coupling frequency that mirrored the changes in F0 following natural

153 syllable rate acceleration (Figure 1). Cortico-acoustic coupling was found at 77-84 Hz for

154 normal rate sentences mainly in bilateral Heschl's, superior temporal, supramarginal and pre-

155 /postcentral gyri as well as in the insula (see Supplementary Table S2 for more details). For the

156 natural fast condition, PLI increased in the higher 90-97 Hz range in a right-lateralized network

157 mostly including the same regions, namely Heschl's, superior temporal, supramarginal and

158 postcentral gyri (note from Figure 1A that coupling, albeit not significant, was also observed in

159 the left hemisphere). As previously outlined, time-compressed sentences had the same F0 as

160 normal rate sentences. This was well reflected in the brain by a significant PLI increase for this

161 condition in the lower, normal rate pitch range only (77-84 Hz), in a similar network as the one

162 found for normal rate speech. No significant phase-coupling was on the contrary observed for

163 naturally accelerated sentences in this frequency range, stressing the specificity of the effect.

164 Additional coherence analyses corroborated this pattern of results (see Figure 2). Indeed,

165 coherence significantly increased bilaterally in the lower frequency range for normal rate and

time-compressed sentences, but in the higher range for natural fast sentences. As expected, for

the amplitude-modulated noise conditions, neither PLI nor coherence measures showed any

significant cortico-acoustic coupling increase in any of the two frequency bands of interest

(Figures 1 and 2).

Figure 1. Cortical coupling to fundamental frequency in the frequency ranges encompassing the

F0s of normal rate and time-compressed sentences (77-84 Hz) and of natural fast rate sentences

(90-97 Hz). (A) Phase Lag Index (PLI) maps for coupling between the acoustic signal and brain

oscillatory activity during stimulus encoding (active period), as compared to surrogate (i.e. shuffled)

data. The values represent the difference in Fisher z-transformed PLI between the compared data. (B)

Cluster-based statistical maps (corrected, α = .001, one-tailed) are shown for the different speech and

noise conditions. Noise Normal and Noise Fast correspond to white noise stimuli modulated with the

amplitude envelope of normal rate and fast rate sentences, respectively.

Figure 2: Cortico-acoustic coherence in the frequency ranges corresponding to the F0s in the normal rate and time-compressed conditions (77-84 Hz) and the natural fast rate condition (90-97 Hz). (A) Coherence maps for coupling between the acoustic signal and brain oscillatory activity during stimulus encoding (active period), as compared to surrogate (i.e. shuffled) data. The values represent the difference in Fisher z-transformed coherence between the compared data. (B) Statistical maps (FDR statistics, corrected, $\alpha = .001$) are shown for the different speech and noise conditions. Noise stimuli modulated with the amplitude envelope of normal rate and fast rate sentences are referred to by Noise Normal and Noise Fast, respectively.

To more thoroughly assess the specific change in coupling frequency with F0 variation, we computed the coupling spectra for PLI and coherence across the three speech rate conditions, averaged over all participants and for each voxel. We then calculated the mean spectra separately over regions delimited by three different brain parcellations (see Methods). We identified the top regions in each parcellation with the highest spectral PLI peak across all speech conditions. For this analysis, we focused on the right hemisphere as it is where our PLI and coherence analyses above showed significant effects for all speech conditions. As displayed in Figure 3, this highlighted the Heschl's gyrus (aparc parcellation), the first subzone of the postcentral gyrus (aparc_sub parcellation), and Brodmann area 43 corresponding to the

subcentral area (PALS-B12 parcellation). Analyses confirmed that for both PLI and coherence, the coupling spectra in these regions peaked at the sentences' F0, that is at ~80 Hz for normal rate and time-compressed speech, with a shift at ~90 Hz for naturally-accelerated speech (Figure 3 A, B, C for PLI and E, F, G for coherence). These peaks were not found when running the same analysis in the frontal pole which served as a control region (Figure 3 D, H). Note from Supplementary Figures S2, S3 and S4 that the three identified auditory, inferior postcentral and subcentral regions were found among the top 8 regions showing the highest PLI and coherence peaks at sentences' F0, irrespective of the parcellation used. Note also that while power modulations might explain coherence peaks (Figure 3 E-M, F-N and G-O), this cannot be the case for the PLI curves as their calculation relies on phase measures rather than on the amplitude spectrum.

Figure 3. Coupling and power spectra for the three speech conditions in the top regions of the
right hemisphere for each brain parcellation. The regions shown (one per column) correspond to the
regions in each parcellation (respectively, aparc, aparc_sub and PALS-B12) with the highest peak of
Phase Lag Index (PLI) coupling, which remains the same when evaluating coherence. The curves shown
correspond to the average over subjects and voxels inside each region of PLI, coherence, power and
flattened power, respectively. The coupling spectra were calculated between the acoustic signal and
brain oscillatory activity during stimulus encoding (active period). For comparison, the same results are
provided for the frontal pole as a control region. (A) to (D) show the PLI and (E) to (H) the coherence
coupling spectra, respectively, for natural normal rate (in blue), time-compressed (in green), and natural
fast rate speech (in orange). Note that Supplementary Figures S2, S3 and S4 detail the top 8 peak PLI
regions for each of the three parcellations. To evaluate the possible effects of power modulations on the

coupling, (I) to (L) display the brain activity's power spectrum during the encoding period and (M) to

(P) show the same spectra but after correcting for the 1/f-like slope (using FOOOF[41]). The specific

models used for the aperiodic fits of these curves can be seen in Supplementary Figure S5.

We finally examined whether brain coupling to speech F0 is also reflected in the amplitude of

the cortical responses by analyzing source power modulations in each experimental condition

and frequency band of interest. To this end, we contrasted power during the stimulus encoding

period with power measured during the pre-stimulus baseline, using cluster-based statistical

correction. Results showed a specific increase of power as a function of sentences' F0 (Figure

4). In the normal and time-compressed conditions with F0 peaking around 80 Hz, brain activity

significantly increased in the 77-84 Hz range in the right (and most of the time left for time-

compressed speech) Heschl's, superior temporal, supramarginal, insular and postcentral gyri.

For natural fast rate sentences, the power increase was found at 90-97 Hz in a similar right-

lateralized network also encompassing the precentral gyrus. No significant increase of power

was found for amplitude-modulated noise stimuli in any of the frequency ranges.

Figure 4. **Power modulations in the frequency bands matching the F0s of natural normal rate and**

time-compressed sentences (77-84 Hz) and of natural fast rate sentences (90-97 Hz). (A) Power

maps during the active period (i.e. stimulus encoding), as compared to the pre-stimulus baseline. The

values represent the relative difference in Fisher z-transformed power between the compared data. (B)

cluster-based statistical maps (corrected, α = .001, two tailed) are reported for the different speech and

noise conditions.

Discussion

Our results revealed brain coupling to speech fundamental frequency, with a shift in coupling

frequency and power increase that echoed the natural F0 increase with natural speech rate

acceleration. Whereas phase-coupling (PLI), coherence and amplitude were enhanced at 77-84

Hz for normal rate and time-compressed speech (F0 peak at 80 Hz), coupling shifted to 90-97

Hz for naturally produced fast speech (F0 peak at 93 Hz). Crucially, this coupling was not

restricted to the auditory cortex but encompassed a network distributed over sensorimotor

regions. Overall, these findings therefore provide novel evidence that high-frequency cortical

oscillations couple with the fundamental frequency of speech in case of natural speech rate

variations.

Coupling and power modulations to F0 were mainly found in the right or bilateral superior

temporal (including the primary auditory cortex), supramarginal, pre-/postcentral gyri and

insula, in line with previous work on pitch processing and voicing perception[42–46]. FFR studies

also reported responses in the right or bilateral auditory cortex to syllables or continuous

speech[23,26–28]. The lack of coupling to amplitude-modulated noise further suggests that phase-

locking does not reflect responses to the temporal envelope of sentences but to their high-

frequency carrier information. Importantly, our thorough whole-brain analysis using three

different cortical parcellations highlighted the right Heschl's gyrus, ventral postcentral gyrus

and subcentral area (BA 43, at the inferior edge of the postcentral gyrus) as showing maximal

coupling to sentences' F0. Note the close spatial proximity of the latter two regions (14.7 mm

based on a computation of distance between their centroids) which may correspond to the same

somatosensory area. Each of these three regions furthermore showed up among the top eight

regions with strong cortico-acoustic coupling across the three parcellations, indicating the

reliability of the results. Other right-lateralized regions such as the insula and the supramarginal

and precentral gyri also consistently coupled their oscillatory activity with speech F0,

irrespective of the parcellation used. Interestingly, these regions are part of a dorsal network

underlying speech auditory-motor integration[47,48]. The somatosensory cortex has also been

advocated to contribute to speech perception by closely interacting with auditory regions[49]. In

this regard, the subcentral gyrus (BA 43) identified in our study, owning both sensory and motor

properties[50,51], is seen as the ventral larynx motor area activated for the production of

vocalizations and pitch control[52–56]. High-gamma activity in this region has been reported to

increase before and during phoneme articulation[57] and for voiced consonant production[58],

suggesting its role in the control of vocal fold movements. This area furthermore increases its

connectivity with the auditory cortex during mere voicing perception[45], and it can decode

articulatory features of heard phonemes[59–61]. Our results concur with a functional role of this

ventral somatosensory area in speech perception as it is one of the regions that best couple its

high-frequency oscillatory activity with speech F0.

A dorsal larynx motor area, located in the precentral gyrus, is also thought to be involved in

voicing and pitch production and perception[53,54,62–66]. In fact, and although this should be further

tested, the precentral region coupling to speech F0 in our study may correspond to this dorsal

motor region. This could reflect some simulation of the laryngeal gestures underlying pitch

control during speech perception[67]. We also found reliable coupling to F0 in the supramarginal

gyrus and insula. This agrees with the inferior parietal cortex acting as a sensorimotor interface

to coordinate speech perception and production[48,68,69] as well as with its role in phonological

processing[70]. The insula is also assumed to contribute to auditory-motor speech integration[71]. It

is indeed engaged in speech production and the control of laryngeal muscles and of F0

modulations[72–74], but also in prosodic perception and auditory temporal processing[75–78]. In

keeping with our work, high-gamma activity in the posterior insula was shown to track the F0

of a repetitive vowel similarly as in Heschl's gyrus[79]. The insula moreover shares connections

with auditory[80] and motor regions, including the laryngeal motor cortex[81,82]. Altogether, our

findings thus putatively suggest that besides the primary auditory cortex targeted by previous

work[23,24,32,83], a dorsal sensorimotor cortical network involved in speech auditory-motor

integration sync to the periodicity of vocal fold vibration in perceived speech.

Whether and how our findings relate to the cortical FFR to repetitive syllables[21,23,24,27,28] is not

straightforward. One difference is that the FFR is averaged over several hundreds of the same

stimulus, whereas we assessed cortico-acoustic coupling and power modulations to a set of

varying sentences. Still, the FFR is thought to indicate phase-locked neural activity to the

stimulus F0. The different measures may therefore reflect at least some common processes. As

previously mentioned, a FFR source in the right posterior auditory cortex has been described

and would be involved in pitch computation[23,24]. Among the few studies that investigated F0

coupling to sentences or continuous speech, some focused on the brainstem[84–86], while others

examined high-gamma auditory cortex activity in light of the cortical FFR[26,30,32,33,87]. To the

best of our knowledge, all of these FFR-F0 studies, whether conducted on repetitive syllables

or continuous speech, assessed brain responses in the auditory cortex only. Crucially, by

analyzing both coupling (using two measures, PLI and coherence) and power modulations at

high frequencies, we bring new support for brain coupling to F0 in natural speech that occurs

well beyond the auditory cortex, in regions that are involved in auditory-somato-motor

integration (in agreement with [40] for tones).

Although the increase in coherence we found might be explained, at least partly, by power

increases at the same frequencies, this cannot hold for the phase-lag index which is insensitive

to amplitude modulations. Cortical coupling to speech F0 may therefore capture the periodic

nature of the phenomenon. Coffey and collaborators[83] likewise proposed that their auditory

cortex FFR entailed oscillatory entrainment since the brain response outlasted syllable offset

(see also [40]). Along with this view, oscillatory coupling to F0 in our study could reflect a

predictive coding mechanism comparing speech input periodicity with internal temporal

expectations. Such an interpretation, although still speculative, would support the idea that

high-gamma activity mediates pitch-level prediction errors and their feedforward propagation

up to higher integrative areas in order to update predictions[88–90]. Cortico-acoustic coupling to

F0 in (pre)motor regions furthermore agrees with their known role in predictive coding, despite

this is usually observed in lower (delta and beta) frequencies[91–93]. Further cross-frequency

coupling and functional connectivity analyses between auditory and motor regions are needed

to fully substantiate the predictive coding interpretation and further delineate the role of speech

F0 coupling at the cortical level. As speech periodicity conveys segmental information, phase-

locking to F0 might contribute to phoneme identification by encoding the articulatory feature

of voicing or by extracting vowels' formant structure. Another, not exclusive possibility is that

it could serve more general communicative purposes, to track the relevant targets in an auditory

scene[29] and decrease sensitivity to environmental noise or competing speakers[83].

One last question relates to the upper limit of F0 cortical tracking. In our study and previous

work[23,27,83], phase-locking was examined for typical male voices with F0 not exceeding 100-

110 Hz. It has been proposed that the auditory cortex is not able, or hardly tracks frequencies

beyond 100 Hz[20], for pure tones[94,95] or for syllables produced by males[21] or females[33,87]. Some

intracranial recordings still showed phase-locked responses up to 200 Hz[19,26,96,97]. In the present

study, cortical tracking of natural fast speech was significant but less widespread than for

normal rate and time-compressed speech, although the three conditions highlighted a

comparable cortical network. This may relate to the general decrease in cortical frequency

representation towards higher frequencies and/or the greater variance in F0 for rapidly-

produced sentences. Part of the F0 distribution in this condition indeed lied beyond 110 Hz (up

to ~120 Hz) even after the selection procedure (Figure S1, panels B and D), which may have

decreased the tracking capacity of cortical oscillations. Speech F0 therefore appears as an

important parameter for the emergence of cortical tracking of speech periodicity, since phase-

locking seems to decline with increasing F0. Alternatively, greater variability in natural fast

speech F0 may have reduced statistical power, explaining the globally weaker effects in this

condition. Further examining F0 tracking in different voices and under various speech rate or

noisy conditions, will help better understanding this cortical contribution.

As in previous work in this domain, several critical aspects need to cautiously be taken into

account when interpreting our speech-brain oscillatory coupling. Distinguishing true neuronal

entrainment and oscillations from a succession of neural representations of events that happen

to have some periodicity is a topic of current debate[98]. Moreover, the reliability of the

widespread network reported here would benefit from further investigation to rule out possible

effects of spurious activity arising from the smoothing inherent to source reconstruction.

In conclusion, our study suggests that high-frequency cortical oscillations adaptively couple

with the fundamental frequency (F0) of speech to match variations in F0 that inherently

accompany natural speech rate acceleration. Using magnetoencephalography (MEG), we

identified significant brain-to-speech F0 coupling across a network extending beyond the

auditory cortex to include the right auditory, inferior parietal, insular, and pre- and postcentral

regions, involving a dynamic auditory-somato-motor network in the encoding of speech. These

findings advance our understanding of how high-frequency cortical oscillations contribute to

language processing and hint at a complex interplay between auditory and motor systems in

speech perception, and pave the way for future work exploring how these mechanisms function

under different auditory and communicative conditions.

Methods

Participants

Twenty-four (14 females) participants aged between 18 and 45 years old (mean = 23 years old)

volunteered for the study. All were monolingual French native speakers and right-handed (mean

score at the Edinburgh handedness inventory[99] = 94). None of them reported hearing or

language problems nor history of neurological or psychiatric disorders. The protocol conformed

to the Declaration of Helsinki and was approved by the local ethical committee (Comité de

Protection des Personnes Lyon Sud-Est II; ID RCB: 2012-A00857-36). Written informed

consent was obtained for all participants before the experiment, and they were compensated for

their participation.

Stimuli

A set of 288 meaningful sentences (7-9 words) with the same syntactic structure (e.g., "Le guide

organise une excursion dans le désert" / *The guide organizes a trip to the desert*) served as

stimuli. A French native male professional theatre actor, who was able to produce sentences at

the required fast rate while remaining intelligible, recorded the stimuli in a sound-attenuated

booth using ROC*me*! software [100]. Each sentence was recorded twice (44.1 kHz, mono, 16 bits),

first at a normal and then at a fast rate. The mean syllable rate of the sentences (i.e. number of

produced syllables divided by sentence duration) as calculated with Praat[101], was 6.76

syllables/s (SD 0.57) for the natural normal rate condition, while it increased to 9.15 syllables/s

(SD 0.60) in the natural fast condition. Time compression, which is a re-synthesis process only

affecting the temporal structure of the stimuli, was then applied to normal rate sentences by

digitally shortening them with a PSOLA algorithm (Pitch Synchronous Overlap and Add[102]).

Compression rates were computed for each sentence, namely each time-compressed sentence

was matched in terms of syllable rate to its natural fast equivalent. Therefore, time-compressed

sentences had a mean syllable rate of 9.15 syllables/s (SD 0.60) as well. For the total of 864

sound files (288×3 speech rate variants), we applied an 80 Hz high-pass filter and smoothed

sentences' amplitude envelope initially and finally. The intensity of the sound files was finally

peak normalized.

Computation of the power spectrum in the 64-128 Hz range across sentences in the three speech

rate conditions using Python showed peak frequencies at 81.6 Hz (SD 3.2) and 81 Hz (SD 3.3)

for the normal rate and time-compressed conditions respectively, and at 91.9 Hz (SD 9.8) for

the fast rate condition (see Figure S5 in the supplementary material). These peak frequencies

are consistent with the computation of the median pitch values with Praat.

To assess whether brain-to-F0 coupling occurs with the high-frequency carrier information in

speech and not with the modulations of the amplitude envelope, we generated amplitude-

modulated noise stimuli) as control conditions. A total of 576 control stimuli were created by

modulating Gaussian white noise (lacking linguistic content) with the amplitude envelope of

each of the 288 natural normal rate and 288 natural fast rate sentences. We also added forty-

eight filler sentences (different from the experimental stimuli but following the same syntactic

structure) in which beep-sounds were inserted at different possible time-points (i.e. 200, 600 or

800 ms from onset) in the sentences. These filler sentences were used to encourage participants

to pay attention to the auditory stimuli during the experiment (see Experimental procedure).

The whole set of stimuli was split into two experimental lists, each including 288 sentences (96

for each speech rate condition), 192 amplitude-modulated noise stimuli (96 modulated with the

normal rate envelope and 96 with the fast rate envelope) and 48 filler sentences, for a total of

528 stimuli per list and per participant. Each stimulus appeared in each rate condition across all

participants but only once per list.

Experimental procedure

While comfortably sitting in a sound-attenuated, magnetically-shielded recording room with a

screen in front of them, participants were presented binaurally with stimuli through air-

conducting tubes with foam insert earphones (Etymotic ER2 and ER3). Prior to the MEG

recording, their auditory detection thresholds were determined for each ear with a pure tone.

The level was then adjusted in order to present stimuli at 50 dB Sensation Level (SL) with a

central position (stereo) with respect to the participant's head.

Each trial of the experiment ran as follows: after a fixation cross displayed at the centre of the

screen for 1500 ms, an auditory stimulus (sentence or amplitude-modulated noise) was

presented, with the fixation cross remaining on the screen. Participants were instructed to

attentively listen to all stimuli while looking at the fixation cross and to press a button (response

button Neuroscan, Pantev) with their left index finger as quickly as possible whenever they

detected beep-sounds in (filler) sentences. The next trial started after an inter-trial interval (grey

screen) of 1250 ms. Participants detected 100% of the filler trials, which were excluded from

subsequent analysis. Each participant listened to the stimuli from one of the two experimental

lists. The total of 528 stimuli were pseudo-randomly divided into 8 blocks (66 stimuli each)

separated by short breaks to allow the participants to rest. Participants were familiarized with

the stimuli and task in a training phase (5 sentences different from the experimental stimuli).

To further maintain their attention throughout the experiment, they were informed that

questions on the heard sentences would be asked at the end of the experiment. More precisely,

they had to indicate, by ticking a yes/no box on a paper sheet, whether eight proposed sentences

(three of which were not experimental stimuli) were presented during the MEG experiment.

The experiment was run with Presentation software (Neurobehavioral Systems).

MEG data acquisition and analysis

We recorded neuromagnetic brain activity of the 24 participants using a 275-channel whole-

head MEG system (CTF OMEGA 275, Canada) at 1200 Hz sampling rate. Head position within

the MEG helmet was monitored with three fiducial coils (nasion, left and right pre-auricular

points) placed on the participant's head. Horizontal and vertical eye movements were also

recorded with four electrooculography (EOG) electrodes. We recorded reference head position

before each of the 8 experimental blocks and tracked head movements throughout the

experiment using continuous head position identification (HPI).

Preprocessing of the MEG data was done with custom written Matlab scripts (Mathworks Inc.,

MA, USA) and the Fieldtrip toolbox[103]. Subsequent coupling analyses were carried out in

Python using custom scripts and the MNE-Python library[104]. In the following we describe the

processing of 1) speech recordings, 2) MEG data, 3) Magnetic Resonance Imaging (MRI) data,

and the analyses of 4) source localization, power and coupling, and 5) coupling maps and

statistics.

Audio Recordings (reference signals)

To examine the neural tracking of speech F0, we used the speech signal as the reference.

Inspection of the F0 distributions and power spectral densities revealed some spectral (including

F0s) overlap between sentences in the different speech rate conditions (see Supplementary

Figure S1 A and C). To test our hypothesis that brain oscillatory activity adjusts to F0 increase

with speech rate acceleration, we optimized the distinction between conditions in terms of F0s

by selecting a proportion of sentences in the natural normal rate and time-compressed

conditions with the lowest mean F0s (71% and 77% of the sentences on average per participant,

respectively). Similarly, we selected sentences in the natural fast rate condition with the highest

mean F0s (~62% on average per participant). To do this, we collected sentences from the normal

rate/time-compressed and fast rate conditions starting from opposite sides of the spectrum, thus

maximizing the spectral distance between these two subsets while keeping an acceptable

number of sentences in each condition (see Supplementary Table 12). This resulted in normal

rate and time-compressed sentences with the lowest F0s (i.e. below 83 Hz) and a F0 peak at 80

Hz, and natural fast rate sentences with the highest F0s (i.e. above 87 Hz) peaking at 93 Hz (see

Supplementary Figure S1 B and D). We analyzed brain-to-speech coupling in two frequency

ranges centered on the F0 peak values (across sentences) of the two subsets of sentences (with

7Hz bandwidth), namely 77-84 Hz and 90-97 Hz. For this coupling analysis, we selected speech

segments between 200 ms and 1000 ms post-stimulus onset, as the shortest sentences in the

natural fast and time-compressed conditions were ~1 s long (this time-window for speech

segments equals the time-window of interest of the functional MEG data, see next section).

MEG data

The MEG continuous data were segmented into 3 s periods (from 1 s before to 2 s after stimulus

onset). A standard semi-automatic procedure available in the Fieldtrip toolbox was used to

reject data segments contaminated by eye blinks, heartbeat and muscle artefacts. To remove the

power line artefact and its harmonics notch-filtering was applied at 50, 100 and 150 Hz. We

then detected and rejected EOG, jumps and muscle artifacts and visually double-checked the

trials. Finally, an Independent Component Analysis (ICA) was used to correct for ECG artifacts.

For each trial, the time interval of interest was set between 200 ms and 1000 ms after stimulus

onset, while the baseline extended from 1000 ms to 200 ms before onset. The cleaned and

segmented data was then imported to Python to perform the coupling analysis.

MRI data

T1-weighted structural MRIs (MRI 1.5 T, Siemens AvantoFit) were acquired for 23 of the 24

participants after the MEG study. Alignment of each MRI to the MEG coordinate system was

performed with the localization coils marked on the MRIs and the interactive alignment

interface available in MNE. Each MRI was segmented to compute each participant's head

model using the single-shell as volume conductor model[105]. To carry out group analyses in a

common space, we first spatially normalized a template anatomical grid from the Montreal

Neurological Institute (MNI) common coordinate system. MRI grids of each participant were

then aligned to this normalized template (this common grid has 5124 vertices). We finally

computed the cortical source space modelling for each participant using the individual MRI

volume, but with the surface grid based on the MNI template. This allowed transforming the

results to the same brain template for all participants for easier comparison.

Source localization, power and cortico-acoustic coupling estimation

We estimated source power and cortico-acoustic coupling given source reconstructions

calculated using Minimum Norm Estimation[106–108]. Before computing the coupling, we

resampled the speech signal to 1200 Hz to match the sampling frequency of the MEG data. In

this way, we could suitably assess the neural tracking of F0 by computing the coupling between

auditory signals and cortical activity using Phase Lag Index and coherence measures. The Phase

Lag Index provides information regarding the coupling of two signals with respect to the sign

of their phase difference[110]. It has the advantage of being insensitive to the amplitude of the

signals and moreover, neglecting zero-phase coupling that commonly arise because of volume

conduction. It can be mathematically defined as:

518
$$PLI(r_{ef}, r_c, f) = |E[sign(Im[C_s(r_{ef}, r_c, f)])]|$$

where r_{ef} is the reference signal, namely the acoustic signal here; r_c is the brain signal at each

vertex of the anatomical grid; f is the frequency bin and Cs is the Cross Spectral Density (CSD)

matrix. The operator E[x] refers to the average over trials, |x| is the absolute value, sign(x)

returns the sign of the value, and Im[x] gives the imaginary part of a complex number.

Coherence refers to the linear correlation between two signals as a function of frequency. It can

be mathematically defined as:

526
$$Coh(r_{ef}, r_c, f) = \frac{|E[Cs(r_{ef}, r_c, f)]|}{\sqrt{E[Cs(r_{ef}, r_{ef}, f)]E[Cs(r_c, r_c, f)]}}$$

where the notation is the same as the one used in the previous equation.

We computed PLI and coherence using the MNE-Connectivity package within the MNE-

Python ecosystem[104]. Specifically, the CSD matrix was computed using the multitaper Fast

Fourier Transform (FFT) from 64 to 128 Hz. Cortico-acoustic coupling was calculated for the

active period (200 to 1000 ms), the baseline (-1000 to -200 ms), and for shuffled data, the last

two serving as control conditions for statistical analyses for power and coupling, respectively.

In the case of surrogate data, we randomly shuffled the samples of the audio signals before

computing cortico-acoustic coupling (i.e. the structure of the audio signal was lost and

consequently did not match its MEG counterpart for the coupling computation). We repeated

this procedure 100 times and averaged coupling across iterations for each participant, and each

experimental condition and frequency bin. For both active, baseline and shuffled data, the

couplings (and power) were averaged across the frequency bins inside each band of interest.

Cortico-acoustic coupling maps, power maps and statistical analyses

The average coupling and power maps used for visualization in the Results section were

obtained by first applying the Fisher transform of the values. Then we computed the difference

between the active period and a set of control data (shuffled audio for coupling, and baseline

for power) for each participant and condition. In the case of power, the relative difference was

used. The values were then averaged across participants for each experimental condition and

subsequently mapped to the brain plots. Group statistical analysis was conducted on the raw

coupling and power values (without the Fisher transform) for the 23 participants with individual

MRIs. For PLI and power, we applied cluster-based permutation tests with 1024 permutations

[111]. For coherence, we performed an FDR corrected t-test. The tests are one-tailed for cortico-

acoustic coupling analysis and two-tailed for power analysis. All tests use a statistical

significance threshold of 0.001. We used the Desikan-Killiany atlas to identify the regions

detected as significant in the statistical analysis[112]. The top 10 regions with the highest mean t-

value based on the PLI statistical analysis for each frequency range, condition, and hemisphere

can be found in Supplementary Table S2.

To inspect more closely the changes in coupling frequency with F0 variation, we additionally

computed - for each of the three speech rate conditions - the coupling spectra during the

encoding period, both for PLI and coherence, across a wide range of frequencies (64-128 Hz)

and averaged through participants. This was done on all voxels and then averaged into the

regions of the Desikan-Killiany atlas[112] (aparc parcellation). We simultaneously explored two

other parcellations: aparc_sub[113] (corresponding to subdivisions of the regions of the aparc

parcellation) and PALS-B12[114] (which delineates Brodmann areas). Then, the top 8 regions in

the right hemisphere with the highest PLI peak independent of the speech rate conditions were

identified for each of the three parcellations. These regions are detailed in Figures S2, S3 and

S4. We further compared the top region of each parcellation with the frontal pole, selected as

the control region since it was not expected to show any F0 response (see Figure 3; see also[23]).

Additionally, to assess the potential effects of power modulations, we computed the power

spectra of the encoding brain signals at these locations in a similar manner. To better compare

the coupling spectra to the oscillatory peaks in the brain power, we removed the aperiodic

component using the FOOOF (specparam) methodology[41]. The details of the model that fits

each of the spectra involved in Figure 3 can be seen in Supplementary Figure S4.

Data availability: The data that support the findings of this study are available from the

corresponding author upon reasonable request.

References

1.   Ding, N. & Simon, J. Z. Cortical entrainment to continuous speech: functional roles and

interpretations. *Front. Hum. Neurosci.* **8**, (2014).

2.   Ghitza, O. Linking Speech Perception and Neurophysiology: Speech Decoding Guided by

Cascaded Oscillators Locked to the Input Rhythm. *Front. Psychol.* **2**, (2011).

3.   Giraud, A.-L. & Poeppel, D. Cortical oscillations and speech processing: emerging computational

principles and operations. *Nat. Neurosci.* **15**, 511–517 (2012).

4.   Peelle, J. E. & Davis, M. H. Neural Oscillations Carry Speech Rhythm through to Comprehension.

Front. Psychol. **3**, (2012).

5.   Ding, N., Chatterjee, M. & Simon, J. Z. Robust Cortical Entrainment to the Speech Envelope

Relies on the Spectro-temporal Fine Structure. *NeuroImage* **88**, 41–46 (2014).

6.   Gross, J. *et al.* Speech Rhythms and Multiplexed Oscillatory Sensory Coding in the Human Brain.

PLoS Biol. **11**, e1001752 (2013).

7.   Keitel, A., Gross, J. & Kayser, C. Perceptually relevant speech tracking in auditory and motor

cortex reflects distinct linguistic features. *PLOS Biol.* **16**, e2004473 (2018).

8.   Kösem, A., Basirat, A., Azizi, L. & Wassenhove, V. van. High-frequency neural activity predicts

word parsing in ambiguous speech streams. *J. Neurophysiol.* **116**, 2497–2512 (2016).

9.   Peelle, J. E., Gross, J. & Davis, M. H. Phase-locked responses to speech in human auditory cortex

are enhanced during comprehension. *Cereb. Cortex* **23**, 1378–1387 (2013).

10. Kubanek, J., Brunner, P., Gunduz, A., Poeppel, D. & Schalk, G. The Tracking of Speech Envelope

in the Human Cortex. *PLOS ONE* **8**, e53398 (2013).

11. Lizarazu, M., Lallier, M. & Molinaro, N. Phase−amplitude coupling between theta and gamma

oscillations adapts to speech rate. *Ann. N. Y. Acad. Sci.* **1453**, 140–152 (2019).

12. Mesgarani, N. & Chang, E. F. Selective cortical representation of attended speaker in multi-talker

speech perception. *Nature* **485**, (2012).

13. Nourski, K. V. *et al.* Temporal Envelope of Time-Compressed Speech Represented in the Human

Auditory Cortex. *J. Neurosci.* **29**, 15564–15574 (2009).

14. Zion Golumbic, E. M. *et al.* Mechanisms Underlying Selective Neuronal Tracking of Attended

Speech at a 'Cocktail Party'. *Neuron* **77**, 980–991 (2013).

15. Rosen, S. Temporal information in speech: Acoustic, auditory and linguistic aspects. *Philos.*

Trans. R. Soc. B Biol. Sci. **336**, 367–373 (1992).

16. Russo, N., Nicol, T., Musacchia, G. & Kraus, N. Brainstem responses to speech syllables. *Clin.*

Neurophysiol. **115**, 2021–2030 (2004).

17. Kraus, N. & Nicol, T. Brainstem origins for cortical 'what' and 'where' pathways in the auditory

system. *Trends Neurosci.* **28**, 176–181 (2005).

18. Kraus, N., Anderson, S., White-Schwoch, T., Fay, R. & Popper, A. The Frequency-Following

Response: A Window into Human Communication. in *The frequency-following response* 1–15

(New York: Springer, 2017). doi:10.1007/978-3-319-47944-6.

19. Coffey, E. B. J. *et al.* Evolving perspectives on the sources of the frequency-following response.

Nat. Commun. **10**, 1–10 (2019).

20. Chandrasekaran, B. & Kraus, N. The scalp-recorded brainstem response to speech: Neural origins

and plasticity. *Psychophysiology* **47**, 236–246 (2010).

21. Bidelman, G. M. Subcortical sources dominate the neuroelectric auditory frequency-following

response to speech. *NeuroImage* **175**, 56–69 (2018).

22.   Bidelman, G. M. & Momtaz, S. Subcortical rather than cortical sources of the frequency-following

response (FFR) relate to speech-in-noise perception in normal-hearing listeners. *Neurosci. Lett.*

746, 135664 (2021).

23.   Coffey, E. B. J., Herholz, S. C., Chepesiuk, A. M. P., Baillet, S. & Zatorre, R. J. Cortical

contributions to the auditory frequency-following response revealed by MEG. *Nat. Commun.* **7**,

11070 (2016).

24.   Coffey, E. B. J., Musacchia, G. & Zatorre, R. J. Cortical Correlates of the Auditory Frequency-

Following and Onset Responses: EEG and fMRI Evidence. *J. Neurosci.* **37**, 830–838 (2017).

25.   Gnanateja, G. N. *et al.* Frequency-Following Responses to Speech Sounds Are Highly Conserved

across Species and Contain Cortical Contributions. *eNeuro* **8**, ENEURO.0451-21.2021 (2021).

26.   Guo, N. *et al.* Speech frequency-following response in human auditory cortex is more than a

simple tracking. *NeuroImage* **226**, 117545 (2021).

27.   Hartmann, T. & Weisz, N. Auditory cortical generators of the Frequency Following Response are

modulated by intermodal attention. *NeuroImage* **203**, 116185 (2019).

28.   Ross, B., Tremblay, K. L. & Alain, C. Simultaneous EEG and MEG recordings reveal vocal pitch

elicited cortical gamma oscillations in young and older adults. *NeuroImage* **204**, 116253 (2020).

29.   Hertrich, I., Dietrich, S., Trouvain, J., Moos, A. & Ackermann, H. Magnetic brain activity phase-

locked to the envelope, the syllable onsets, and the fundamental frequency of a perceived speech

signal. *Psychophysiology* **49**, 322–334 (2012).

30.   Puschmann, S., Baillet, S. & Zatorre, R. J. Musicians at the Cocktail Party: Neural Substrates of

Musical Training During Selective Listening in Multispeaker Situations. *Cereb. Cortex* **29**, 3253–

3265 (2019).

31.   Greenlaw, K. M., Puschmann, S. & Coffey, E. B. J. Decoding of Envelope vs. Fundamental

Frequency During Complex Auditory Stream Segregation. *Neurobiol. Lang.* **1**, 268–287 (2020).

32.   Kulasingham, J. P. *et al.* High gamma cortical processing of continuous speech in younger and

older listeners. *NeuroImage* **222**, 117291 (2020).

33.   Van Canneyt, J., Wouters, J. & Francart, T. Neural tracking of the fundamental frequency of the

voice: The effect of voice characteristics. *Eur. J. Neurosci.* **53**, 3640–3653 (2021).

34. Berry, J. J. Speaking Rate Effects on Normal Aspects of Articulation: Outcomes and Issues.

Perspect. Speech Sci. Orofac. Disord. **21**, 15–26 (2011).

35. Caspers, J. & van Heuven, V. J. Effects of Time Pressure on the Phonetic Realization of the Dutch

Accent-Lending Pitch Rise and Fall. *Phonetica* **50**, 161–171 (1993).

36. Fougeron, C. & Jun, S.-A. Rate effects on French intonation: prosodic organization and phonetic

realization. *J. Phon.* **26**, 45–69 (1998).

37. Hincapié-Casas, A. S. *et al.* Neural oscillations track natural but not artificial fast speech: Novel

insights from speech-brain coupling using MEG. *bioRxiv* 2020.10.20.344895 (2021)

doi:10.1101/2020.10.20.344895.

38. Pefkou, M., Arnal, L. H., Fontolan, L. & Giraud, A.-L. Theta- and beta-band neural activity reflect

independent syllable tracking and comprehension of time-compressed speech. *J. Neurosci.* 2882–

16 (2017) doi:10.1523/JNEUROSCI.2882-16.2017.

39. Janse, E. Word perception in fast speech: artificially time-compressed vs. naturally produced fast

speech. *Speech Commun.* **42**, 155–173 (2004).

40. Lerousseau, J. P., Trébuchon, A., Morillon, B. & Schön, D. Frequency Selectivity of Persistent

Cortical Oscillatory Responses to Auditory Rhythmic Stimulation. *J. Neurosci.* **41**, 7991–8006

(2021).

41. Donoghue, T. *et al.* Parameterizing neural power spectra into periodic and aperiodic components.

Nat. Neurosci. **23**, 1655–1665 (2020).

42. Hyde, K. L., Peretz, I. & Zatorre, R. J. Evidence for the role of the right auditory cortex in fine

pitch resolution. *Neuropsychologia* **46**, 632–639 (2008).

43. Johnsrude, I. S., Penhune, V. B. & Zatorre, R. J. Functional specificity in the right human auditory

cortex for perceiving pitch direction. *Brain* **123**, 155–163 (2000).

44. Meyer, M., Alter, K., Friederici, A. D., Lohmann, G. & von Cramon, D. Y. FMRI reveals brain

regions mediating slow prosodic modulations in spoken sentences. *Hum. Brain Mapp.* **17**, 73–88

(2002).

45. Tamura, S. *et al.* Multi-modal imaging of the auditory-larynx motor network for voicing

perception. *NeuroImage* **251**, 118981 (2022).

46.   Zatorre, R. J. & Belin, P. Spectral and Temporal Processing in Human Auditory Cortex. *Cereb.*

678   *Cortex* **11**, 946–953 (2001).

679   47.   Hickok, G. & Poeppel, D. The cortical organization of speech processing. *Nat. Rev. Neurosci.* **8**,

680   393–402 (2007).

681   48.   Rauschecker, J. P. & Scott, S. K. Maps and streams in the auditory cortex: nonhuman primates

682   illuminate human speech processing. *Nat. Neurosci.* **12**, 718–724 (2009).

683   49.   Franken, M. K., Liu, B. C. & Ostry, D. J. Towards a somatosensory theory of speech perception.

684   *J. Neurophysiol.* **128**, 1683–1695 (2022).

685   50.   Belyk, M. & Brown, S. The origins of the vocal brain in humans. *Neurosci. Biobehav. Rev.* **77**,

686   177–193 (2017).

687   51.   Cogan, G. B. *et al.* Sensory–motor transformations for speech occur bilaterally. *Nature* **507**, 94–

688   98 (2014).

689   52.   Conant, D., Bouchard, K. E. & Chang, E. F. Speech Map in the Human Ventral Sensory-Motor

690   Cortex. *Curr. Opin. Neurobiol.* **0**, 63–67 (2014).

691   53.   Dichter, B. K., Breshears, J. D., Leonard, M. K. & Chang, E. F. The Control of Vocal Pitch in

692   Human Laryngeal Motor Cortex. *Cell* **174**, 21-31.e9 (2018).

693   54.   Eichert, N., Papp, D., Mars, R. B. & Watkins, K. E. Mapping Human Laryngeal Motor Cortex

694   during Vocalization. *Cereb. Cortex* **30**, 6254–6269 (2020).

695   55.   Eichert, N., Watkins, K. E., Mars, R. B. & Petrides, M. Morphological and functional variability

696   in central and subcentral motor cortex of the human brain. *Brain Struct. Funct.* **226**, 263–279

697   (2021).

698   56.   Grabski, K. *et al.* Functional MRI assessment of orofacial articulators: Neural correlates of lip,

699   jaw, larynx, and tongue movements. *Hum. Brain Mapp.* **33**, 2306–2321 (2012).

700   57.   Bouchard, K. E., Mesgarani, N., Johnson, K. & Chang, E. F. Functional Organization of Human

701   Sensorimotor Cortex for Speech Articulation. *Nature* **495**, 327–332 (2013).

702   58.   Toyoda, G. *et al.* Electrocorticographic correlates of overt articulation of 44 English phonemes:

703   Intracranial recording in children with focal epilepsy. *Clin. Neurophysiol.* **125**, 1129–1137 (2014).

704   59.   Archila-Meléndez, M. E. *et al.* Sensorimotor Representation of Speech Perception. Cross-

705   Decoding of Place of Articulation Features during Selective Attention to Syllables in 7T fMRI.

706   *eNeuro* **5**, (2018).

707   60.   Arsenault, J. S. & Buchsbaum, B. R. Distributed Neural Representations of Phonological Features

708   during Speech Perception. *J. Neurosci.* **35**, 634–642 (2015).

709   61.   Correia, J. M., Jansma, B. M. B. & Bonte, M. Decoding Articulatory Features from fMRI

710   Responses in Dorsal Speech Regions. *J. Neurosci.* **35**, 15015–15025 (2015).

711   62.   Brown, S., Ngan, E. & Liotti, M. A Larynx Area in the Human Motor Cortex. *Cereb. Cortex* **18**,

712   837–845 (2008).

713   63.   D'Ausilio, A., Bufalari, I., Salmas, P., Busan, P. & Fadiga, L. Vocal pitch discrimination in the

714   motor system. *Brain Lang.* **118**, 9–14 (2011).

715   64.   Liang, B., Li, Y., Zhao, W. & Du, Y. Bilateral human laryngeal motor cortex in perceptual decision

716   of lexical tone and voicing of consonant. *Nat. Commun.* **14**, 4710 (2023).

717   65.   Lu, J. *et al.* Neural control of lexical tone production in human laryngeal motor cortex. *Nat.*

718   *Commun.* **14**, 6917 (2023).

719   66.   Simonyan, K. The laryngeal motor cortex: its organization and connectivity. *Curr. Opin.*

720   *Neurobiol.* **28**, 15–21 (2014).

721   67.   Sammler, D., Grosbras, M.-H., Anwander, A., Bestelmeyer, P. E. G. & Belin, P. Dorsal and

722   Ventral Pathways for Prosody. *Curr. Biol.* **25**, 3079–3085 (2015).

723   68.   Rauschecker, J. P. An expanded role for the dorsal auditory pathway in sensorimotor control and

724   integration. *Hear. Res.* **271**, 16–25 (2011).

725   69.   Shum, M., Shiller, D. M., Baum, S. R. & Gracco, V. L. Sensorimotor integration for speech motor

726   learning involves the inferior parietal cortex. *Eur. J. Neurosci.* **34**, 1817–1822 (2011).

727   70.   Hartwigsen, G. *et al.* Phonological decisions require both the left and right supramarginal gyri.

728   *Proc. Natl. Acad. Sci. U. S. A.* **107**, 16494–16499 (2010).

729   71.   Mutschler, I. *et al.* Functional organization of the human anterior insular cortex. *Neurosci. Lett.*

730   **457**, 66–70 (2009).

72.   Ackermann, H. & Riecker, A. The contribution(s) of the insula to speech production: a review of

the clinical and functional imaging literature. *Brain Struct. Funct.* **214**, 419–433 (2010).

73.   Dronkers, N. F. A new brain region for coordinating speech articulation. *Nature* **384**, 159–161

(1996).

74.   Howell, P., Jiang, J., Peng, D. & Lu, C. Neural control of fundamental frequency rise and fall in

Mandarin tones. *Brain Lang.* **121**, 35–46 (2012).

75.   Bamiou, D.-E., Musiek, F. E. & Luxon, L. M. The insula (Island of Reil) and its role in auditory

processing: Literature review. *Brain Res. Rev.* **42**, 143–154 (2003).

76.   Bamiou, D.-E. *et al.* Auditory temporal processing deficits in patients with insular stroke.

Neurology **67**, 614–619 (2006).

77.   Oh, A., Duerden, E. G. & Pang, E. W. The role of the insula in speech and language processing.

Brain Lang. **135**, 96–103 (2014).

78.   Tregellas, J. R., Davalos, D. B. & Rojas, D. C. Effect of task difficulty on the functional anatomy

of temporal processing. *NeuroImage* **32**, 307–315 (2006).

79.   Zhang, Y. *et al.* The Roles of Subdivisions of Human Insula in Emotion Perception and Auditory

Processing. *Cereb. Cortex* **29**, 517–528 (2019).

80.   Ghaziri, J. *et al.* The Corticocortical Structural Connectivity of the Human Insula. *Cereb. Cortex*

27, 1216–1228 (2017).

81.   Simonyan, K., Ostuni, J., Ludlow, C. L. & Horwitz, B. Functional But Not Structural Networks

of the Human Laryngeal Motor Cortex Show Left Hemispheric Lateralization during Syllable But

Not Breathing Production. *J. Neurosci.* **29**, 14912–14923 (2009).

82.   Simonyan, K. & Horwitz, B. Laryngeal Motor Cortex and Control of Speech in Humans. *Neurosci.*

Rev. J. Bringing Neurobiol. Neurol. Psychiatry **17**, 197–208 (2011).

83.   Coffey, E. B. J., Arseneau-Bruneau, I., Zhang, X., Baillet, S. & Zatorre, R. J. Oscillatory

entrainment of the Frequency Following Response in auditory cortical and subcortical structures.

J. Neurosci. (2021) doi:10.1523/JNEUROSCI.2313-20.2021.

84.   Etard, O., Kegler, M., Braiman, C., Forte, A. E. & Reichenbach, T. Decoding of selective attention

to continuous speech from the human auditory brainstem response. *NeuroImage* **200**, 1–11 (2019).

85.   Forte, A. E., Etard, O. & Reichenbach, T. The human auditory brainstem response to running

speech reveals a subcortical mechanism for selective attention. *eLife* **6**, e27203 (2017).

86.   Maddox, R. K. & Lee, A. K. C. Auditory Brainstem Responses to Continuous Natural Speech in

Human Listeners. *eNeuro* **5**, (2018).

87.   Schüller, A., Schilling, A., Krauss, P., Rampp, S. & Reichenbach, T. Attentional Modulation of

the Cortical Contribution to the Frequency-Following Response Evoked by Continuous Speech.

J. Neurosci. **43**, 7429–7440 (2023).

88.   Brodski, A., Paasch, G.-F., Helbling, S. & Wibral, M. The Faces of Predictive Coding. *J. Neurosci.*

35, 8997–9006 (2015).

89.   Lewis, A. G. & Bastiaansen, M. A predictive coding framework for rapid neural dynamics during

sentence-level language comprehension. *Cortex* **68**, 155–168 (2015).

90.   van Pelt, S. *et al.* Beta- and gamma-band activity reflect predictive coding in the processing of

causal events. *Soc. Cogn. Affect. Neurosci.* **11**, 973–980 (2016).

91.   Keitel, A., Ince, R. A. A., Gross, J. & Kayser, C. Auditory cortical delta-entrainment interacts with

oscillatory power in multiple fronto-parietal networks. *NeuroImage* **147**, 32–42 (2017).

92.   Morillon, B. & Baillet, S. Motor origin of temporal predictions in auditory attention. *Proc. Natl.*

Acad. Sci. U. S. A. **114**, E8913–E8921 (2017).

93.   Park, H., Ince, R. A. A., Schyns, P. G., Thut, G. & Gross, J. Frontal Top-Down Signals Increase

Coupling of Auditory Low-Frequency Oscillations to Continuous Speech in Human Listeners.

Curr. Biol. **25**, 1649–1653 (2015).

94.   Gorina-Careta, N., Kurkela, J. L. O., Hämäläinen, J., Astikainen, P. & Escera, C. Neural generators

of the frequency-following response elicited to stimuli of low and high frequency: A

magnetoencephalographic (MEG) study. *NeuroImage* **231**, 117866 (2021).

95.   Holmes, E., Purcell, D. W., Carlyon, R. P., Gockel, H. E. & Johnsrude, I. S. Attentional

Modulation of Envelope-Following Responses at Lower (93–109 Hz) but Not Higher (217–

233 Hz) Modulation Rates. *J. Assoc. Res. Otolaryngol.* **19**, 83–97 (2018).

96.   Brugge, J. F. *et al.* Coding of Repetitive Transients by Auditory Cortex on Heschl's Gyrus. *J.*

Neurophysiol. **102**, 2358–2374 (2009).

97. Nourski, K. V. *et al.* Sound identification in human auditory cortex: Differential contribution of
local field potentials and high gamma power as revealed by direct intracranial recordings. *Brain*
Lang. **148**, 37–50 (2015).

98. Duecker, K. *et al.* Challenges and Approaches in the Study of Neural Entrainment. *J. Neurosci.*
Off. J. Soc. Neurosci. **44**, e1234242024 (2024).

99. Oldfield, R. C. The assessment and analysis of handedness: the Edinburgh inventory.
Neuropsychologia **9**, 97–113 (1971).

100. Ferragne, E., Flavier, S. & Fressard, C. Recording of Oral Corpora Made Easy (ROCme): logiciel
d'enregistrement de corpus. at (2012).

101. Boersma, P. & Weenik, D. *Doing Phonetics by Computer [Computer Program]*. (2012).

102. Moulines, E. & Charpentier, F. Pitch-synchronous waveform processing techniques for text-to-
speech synthesis using diphones. *Speech Commun.* **9**, 453–467 (1990).

103. Oostenveld, R., Fries, P., Maris, E. & Schoffelen, J. M. FieldTrip: Open source software for
advanced analysis of MEG, EEG, and invasive electrophysiological data. *Comput. Intell.*
Neurosci. **2011**, (2011).

104. Gramfort, A. *et al.* MEG and EEG data analysis with MNE-Python. *Front. Neurosci.* **7**, (2013).

105. Nolte, G. The magnetic lead field theorem in the quasi-static approximation and its use for
magnetoencephalography forward calculation in realistic volume conductors. *Phys. Med. Biol.* **48**,
3637–52 (2003).

106. Dale, A. M. & Sereno, M. I. Improved Localizadon of Cortical Activity by Combining EEG and
MEG with MRI Cortical Surface Reconstruction: A Linear Approach. *J. Cogn. Neurosci.* **5**, 162–
176 (1993).

107. Gramfort, A. *et al.* MNE software for processing MEG and EEG data. *NeuroImage* **86**, 446–460
(2014).

108. Hämäläinen, M. S. & Ilmoniemi, R. J. Interpreting magnetic fields of the brain: minimum norm
estimates. *Med. Biol. Eng. Comput.* **32**, 35–42 (1994).

109. Gross, J. *et al.* Dynamic imaging of coherent sources: Studying neural interactions in the human
brain. *Proc. Natl. Acad. Sci. U. S. A.* **98**, 694–9 (2001).

110. Stam, C. J., Nolte, G. & Daffertshofer, A. Phase lag index: Assessment of functional connectivity

from multichannel EEG and MEG with diminished bias from common sources. *Hum. Brain Mapp.*

28, 1178–1193 (2007).

111. Maris, E. & Oostenveld, R. Nonparametric statistical testing of EEG- and MEG-data. *J. Neurosci.*

Methods **164**, 177–90 (2007).

112. Desikan, R. S. *et al.* An automated labeling system for subdividing the human cerebral cortex on

MRI scans into gyral based regions of interest. *NeuroImage* **31**, 968–980 (2006).

113. Khan, S. *et al.* Maturation trajectories of cortical resting-state networks depend on the mediating

frequency band. *NeuroImage* **174**, 57–68 (2018).

114. Van Essen, D. C. A Population-Average, Landmark- and Surface-based (PALS) atlas of human

cerebral cortex. *NeuroImage* **28**, 635–662 (2005).

Acknowledgements: We thank Damien Gouy for recording the stimuli, Emmanuel Ferragne

for his help with Praat software, and Mélanie Canault for discussions on articulatory phonetics.

V.B. discloses support for the research of this work from the French National Research Agency

ANR (ANR-11 JSH2 005 1; PI: V.B) and the Laboratory of Excellence ASLAN (ANR-10-

LABX-0081) of Université de Lyon within the program Investissements d'Avenir (ANR-11-

IDEX-0007). Y-J.M-R discloses support from Mitacs through the Mitacs Globalink program.

A-S.H-C was supported in part by a scholarship from Comisión Nacional de Ciencia y

Tecnología de Chile (CONICYT, Colfuturo, Colombia) and by the French ANR DEFIS

program (ANR-09-EMER-002). K.J. discloses support for the research of this work from the

Canada Research Chairs program and a Discovery Grant (RGPIN-2015-04854) awarded by the

Natural Sciences and Engineering Research Council (NSERC) of Canada (the NSERC

Discovery Grant also provided support to A-S.H-C).

Author contributions: Yorguin-Jose Mantilla-Ramos: Data curation, Formal analysis,

Methodology, Software, Visualization, Writing – original draft. Ana-Sofía Hincapié-Casas:

Data curation, Formal analysis, Software. Annalisa Pascarella: Methodology. Tarek Lajnef:

Methodology. Richard M. Leahy: Methodology. Emily Coffey: Writing – Review and editing.

Karim Jerbi: Conceptualization, Methodology, Software, Validation, Resources, Writing –

original draft, Supervision, Project administration, Funding acquisition. Véronique Boulenger:

Conceptualization, Methodology, Validation, Investigation, Resources, Writing – original

draft, Supervision, Project administration, Funding acquisition.

Declaration of competing interests: The authors declare no competing interests.

857 **Supplementary Material**

858 Content:

859 Table S1-S2

860 Figures S1-S5

Condition	Lowest % (and number) of sentences kept across participants	Mean % (and number) of sentences kept across participants	Highest % (and number) of sentences kept across participants
Normal rate	66.67% (37)	70.95% (53.04)	79.63% (64)
Time-Compressed	71.25% (42)	77.41% (58.39)	83.13% (69)
Fast rate	55.88% (35)	62.10% (46.65)	70.27% (57)

862
Table S1: Mean percentage and percentage range of included sentences across participants by

speech rate condition, after selecting sentences to reduce F0 overlap between subsets of sentences

in the three conditions. For each MEG recording (corresponding to a participant and a condition),

sentences were selected to reduce the F0 overlap between the Fast rate condition and the other two

conditions (Normal rate and Time-Compressed). After this procedure, the number and percentage of

included sentences within that MEG recording were calculated. Subsequently, the inclusion values were

characterized by mean and range (lowest, highest) across participants within a condition. None of the

participants were excluded after this selection procedure. The minimum % of included sentences is

~56% for one participant in the fast rate condition. Nevertheless, for this condition, the overall mean

inclusion percentage is ~62% (with a maximum of ~70%). All conditions have around 3% standard

deviation of the inclusion percentage. The values in brackets represent the number of sentences

corresponding to the given percentage. For the range, these are integer numbers as they represent a

specific participant. For the mean, fractional values appear as these represent the average value of

included sentences across participants.

Condition	77-84 Hz								90-97 Hz							
	Left Hemisphere				Right Hemisphere				Left Hemisphere				Right Hemisphere			
	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count
Normal	Transverse Temporal Gyrus	5.95	0.42	17	Posterior Cingulate Cortex	5.05	0.98	41	None				None			
	Superior Temporal Gyrus	4.95	0.83	79	Transverse Temporal Gyrus	4.79	0.35	10								
	Banks of the Superior Temporal Sulcus	4.85	0.58	35	Insular Cortex	4.56	0.67	52								
	Postcentral Gyrus	4.75	0.66	72	Paracentral Lobule	4.53	0.62	30								
	Insular Cortex	4.72	0.66	62	Supramarginal Gyrus	4.49	0.63	45								
	Inferior Parietal Lobule	4.71	0.83	33	Postcentral Gyrus	4.33	0.45	73								
	Caudal Middle Frontal Gyrus	4.40	0.45	18	Superior Temporal Gyrus	4.08	0.39	93								
	Supramarginal Gyrus	4.29	0.61	82	Precentral Gyrus	4.02	0.41	114								
	Precentral Gyrus	4.28	0.51	75	Banks of the Superior Temporal Sulcus	3.86	0.22	30								
	Middle Temporal Gyrus	4.18	0.45	36	Inferior Parietal Lobule	3.79	0.17	5								
	Left Hemisphere				Right Hemisphere				Left Hemisphere				Right Hemisphere			
	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count
Fast	None				None				None				Supramarginal Cortex	4.08	0.40	64
													Transverse Temporal Cortex	3.91	0.28	6
													Postcentral Cortex	3.91	0.30	21
													Superior Temporal Cortex	3.89	0.24	13
	Left Hemisphere				Right Hemisphere				Left Hemisphere				Right Hemisphere			
	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count	Region	Mean t-value	SD	Voxel Count
Time Compressed	Transverse Temporal Gyrus	4.91	0.51	17	Transverse Temporal Gyrus	5.11	0.43	10	None				None			
	Supramarginal Gyrus	4.77	0.60	98	Posterior Cingulate Cortex	4.95	0.86	38								
	Postcentral Gyrus	4.70	0.65	101	Supramarginal Gyrus	4.95	0.87	104								
	Insular Cortex	4.62	0.66	42	Postcentral Gyrus	4.71	0.66	89								
	Posterior Cingulate Cortex	4.60	0.52	34	Insular Cortex	4.61	0.72	45								
	Superior Temporal Gyrus	4.34	0.52	72	Superior Temporal Gyrus	4.51	0.50	59								
	Precentral Gyrus	4.15	0.46	42	Paracentral Lobule	4.25	0.50	33								
	Temporal Pole	4.14	0.34	9	Banks of the Superior Temporal Sulcus	4.22	0.30	36								
	Banks of the Superior Temporal Sulcus	4.12	0.26	29	Caudal Anterior Cingulate Cortex	4.14	0.21	9								
	Lateral Orbitofrontal Cortex	4.11	0.40	40	Precentral Gyrus	4.12	0.44	106								

Table S2: Top 10 statistically significant regions from the cluster-based analysis of the PLI for each condition, frequency range and hemisphere. This represents a more tabular view of Figure 1. For each condition (Normal, Fast, Time-Compressed), frequency range (77-84 Hz and 90-97Hz) and hemisphere (left and right), the statistically significant regions with the highest mean t-value (averaged over the voxels of the region) are shown. Each region is also described by its number of voxels (voxel count) and the standard deviation of the t-values (SD).

Figure S1: Optimizing sentence selection (normal rate vs. fast rate) in order to minimize F0 overlap across speech conditions. Sentences with the lowest F0s (<83 Hz) in the normal rate/time-compressed conditions and sentences with the highest F0s (>87 Hz) in the fast rate condition were selected. In this way, the spectral distance between the two subsets of stimuli was maximized. Sentences were chosen in such a way that at least 60% of them were retained in each condition, irrespective of which participant they correspond to. This resulted in a selection of, on average, 71% of the normal rate sentences, 77% of the time-compressed sentences, and 62% of the fast rate sentences (see Table S2 in the supplementary material for the percentage of sentence selection across participants). (A) shows the original distribution of F0s which exhibits the overlap of F0 across the sets of stimuli (i.e. before the selection procedure). (B) displays the distribution of F0s after the selection procedure was applied. Note the absence of F0-overlap between the two subsets. (C) Mean spectral density of the audio spectrum per condition prior to reducing the overlap (corresponding to panel A). The highest portion of the curves for normal rate and time-compressed sentences overlaps with the lowest portion and almost the peak of the curve for fast rate sentences. (D) Same as (C) but showing the mean power spectral density after the stimulus selection procedure. Notice the right shift of the peak of audio spectra for fast rate sentences and the reduced overlap of its lowest portion with the highest portion of normal rate and time-

compressed curves. The two bands of interest that we used for the coupling analysis (77-84 Hz and 90-

97 Hz) are shaded, respectively, in gold and red in panels (C) and (D).

Figure S2: Top 8 regions of the right hemisphere of the aparc parcellation showing the highest

spectral PLI peak. The regions shown (one per column) correspond to the 8 regions of the aparc

parcellation with the highest peak PLI coupling (from left to right). The curves correspond to the average

over subjects and voxels inside each region of PLI, coherence, power and flattened power respectively.

The coupling spectra were calculated between the acoustic signal and brain oscillatory activity during

stimulus encoding (active period). (A to H) show the Phase Lag Index (PLI) and (I to P) the Coherence

coupling spectra, respectively, for natural normal rate (in blue), time-compressed (in green), and natural

fast rate speech (in orange). To evaluate the possible effects of power modulations on the coupling, (Q)

to (X) display the brain activity's power spectrum during the encoding period, and (Y) to (FF) show

their flattened curve using FOOOF.

Figure S3: Top 8 regions of the right hemisphere of the aparc_sub parcellation. The regions shown

(one in each column) correspond to the 8 regions of the aparc_sub parcellation with the highest peak

PLI coupling (from left to right). The curves correspond to the average over subjects and voxels inside

each region of PLI, coherence, power and flattened power respectively. The coupling spectra were

calculated between the acoustic signal and brain oscillatory activity during stimulus encoding (active

period). (A) to (H) show the Phase Lag Index (PLI) and (I) to (P) the Coherence coupling spectra,

respectively, for natural normal rate (in blue), time-compressed (in green), and natural fast rate speech

(in orange). To evaluate the possible effects of power modulations on the coupling, (Q) to (X) display

the brain activity's power spectrum during the encoding period, and (Y) to (FF) show their flattened

curve using FOOOF.

Figure S4: Top 8 regions of the right hemisphere of the PALS-B12 parcellation. The regions shown (one in each column) correspond to the 8 regions of the PALS-B12 parcellation with the highest peak PLI coupling (from left to right). The curves shown correspond to the average over subjects and voxels inside each region of PLI, coherence, power and flattened power respectively. The coupling spectra were calculated between the acoustic signal and brain oscillatory activity during stimulus encoding (active period). (A) to (H) show the Phase Lag Index (PLI) and (I) to (P) the Coherence coupling spectra, respectively, for natural normal rate (in blue), time-compressed (in green), and natural fast rate speech (in orange). To evaluate the possible effects of power modulations on the coupling, (Q) to (X) display the brain activity's power spectrum during the encoding period, and (Y) to (FF) show their flattened curve using FOOOF.

Figure S5: Aperiodic fits of the mean brain activity power spectra in each region. (A), (B), (C), (D) correspond to the right Heschl's gyrus (from aparc parcellation)**.** (A) Power spectra for the three speech conditions (same as Figure 3I; normal rate in blue, time-compressed in green and fast rate in orange). (B), (C) and (D) show the fitting using the FOOOF procedure (Donoghue et al., 2020) for normal rate, time-compressed and fast rate conditions, respectively. On each, the purple dashed line represents the aperiodic component, the red line the full model fit (the sum of the periodic and aperiodic components), and the third line shows the original spectra of the respective speech condition following the same color code as in (A). Similarly, the plots are repeated for the other regions. The first subzone of the right Postcentral Gyrus (from aparc_sub parcellation) corresponds to (E), (F), (G), (H). The right Brodmann Area 43 (from PALS-B12 parcellation) corresponds to (I), (J), (K), (L). The right Frontal Pole is used as a control region (from aparc parcellation); it corresponds to (M), (N), (O), (P).