Understanding the mechanism of facilitation in hoverfly TSDNs

Anindya Ghosh[1*], Sarah Nicholas[2], Karin Nordström[2], Thomas Nowotny[1], James Knight[1]

1 Sussex AI, School of Engineering and Informatics, University of Sussex, Brighton, UK

2 Flinders Health and Medical Research Institute, Flinders University, Adelaide, South Australia, Australia

* anindya128@yahoo.com

CRediT author statement

Anindya Ghosh: conceptualization, data curation, formal analysis, investigation, methodology, software, validation, visualization, writing – original draft and preparation; Sarah Nicholas: conceptualization, data curation, formal analysis, investigation, methodology, validation, writing – review and editing; Karin Nordström: conceptualization, funding acquisition, methodology, project administration, resources, supervision, visualization, writing – review and editing; Thomas Nowotny: conceptualization, funding acquisition, methodology, project administration, resources, supervision, writing – review and editing; James Knight: conceptualization, funding acquisition, methodology, project administration, resources, supervision, writing – review and editing.

Abstract

Many animals use visual motion cues to track and pursue small, fast-moving targets, such as prey or conspecifics. In target-pursuing insects, including dragonflies and hoverflies, Small Target Motion Detector (STMD) neurons are found in the optic lobes and are believed to be presynaptic to Target Selective Descending Neurons (TSDNs) that project to motor command centres. While STMDs respond robustly to target motion – even when displayed against moving backgrounds – TSDN target responses are modulated by background motion. Depending on whether the background motion is syn- or contra-directional to the target motion, the response of the TSDNs is either suppressed or facilitated (amplified). This suggests that TSDNs not only receive input from STMDs but also from neurons sensitive to background motion, but this neural circuit is not clearly understood. To explore the underlying neural mechanisms, we developed three candidate TSDN circuit models – which combine input from bio-plausible STMDs and optic flow-sensitive Lobula Plate Tangential Cells (LPTCs) in different ways – and fitted them to published electrophysiology data from hoverfly TSDNs. We then tested the best-fitting models against new electrophysiological data using different background patterns. We found that the overall best model suggests simple inhibition from LPTCs with the same preferred direction as the STMDs feeding into the TSDN. This parsimonious mechanism can explain the facilitation and suppression of TSDN responses to small targets, may inform similar studies in other animals and open new avenues for bio-inspired robotics.

Author summary

Many human sports, including tennis, football, and basketball, rely on the ability to visually detect and respond to the motion of a small, rapidly moving object. Indeed, some sports stars seem to have an uncanny ability to predict the future location of a ball. Similarly, many animals also need to detect the motion of small objects, as these may represent an approaching predator, prey, or a conspecific that needs to be avoided or pursued. Interestingly, while the detection of small visual targets is computationally a hard problem, insects, which have small brains with very modest power requirements, appear to solve this effortlessly. Thus, understanding how target detection is performed in insects can open up avenues for bio-inspired robotics. Male hoverflies naturally engage in complex pursuit behavior, and since they have specialised neurons for target tracking, hoverflies are ideal for understanding the underlying neural circuitry. Here, we combine neural recordings from hoverflies with computational modelling to show how neurons that respond selectively to target motion are combined with neurons that respond to widefield optic-flow to generate behaviourally relevant sensorimotor responses. Importantly, our model does not involve learning and hence suggests that these behaviours can be innate.

Introduction

In many species, the ability to detect small, moving targets in visual clutter is crucial for survival. For example, for a predator, these targets may represent prey, while in other animals, they may represent rivals or potential mates [1]. Thus, neural circuits underlying target-detection have been heavily studied and target-detection behaviours have been described in a range of species, including salamanders [2], zebrafish larvae [3], dragonflies [4], and hoverflies [5].

In insects, target-detection behaviours are believed to be driven by target-tuned neurons found in the visual and pre-motor regions [6]. Specifically, in hoverflies, which pursue conspecifics and other territorial intruders at high speed, there are target-tuned neurons in the optic lobes – the Small Target Motion Detectors (STMDs) [7,8] – as well as in the cervical connective – the Target Selective Descending Neurons (TSDNs) [9]. These descending neurons connect the central brain with motor command centres in the thoracic ganglia. STMDs are able to respond robustly to small, moving targets in visually cluttered environments, even when there is no relative motion between the target and the background [10]. In contrast, the responses of their presumed post-synaptic targets, the TSDNs, are modulated by background motion [11]. Indeed, while TSDNs respond strongly to targets moving across either homogeneous or cluttered stationary backgrounds, if the background pattern moves in the same direction as the target, the TSDN response is comparatively suppressed. Conversely, if the background moves in the opposite direction, the TSDN response is facilitated [11].

The outwardly surprising differences in the responses of STMDs and the TSDNS – which we assume are postsynaptic to STMDs – may be explained by hoverfly behaviour. Hoverflies perform two-stage target pursuit: (1) they start with an open-loop interception response [12], and (2) once close to the target, they transition to a 'shadowing' or following behaviour, matching their speed to that of the target to maintain a close distance [5]. Throughout flight, they perform body saccades [13], which generate widefield optic flow. This motion is detected by lobula plate tangential cells (LPTCs), which in turn project to optic flow-sensitive descending neurons that mediate the resulting optomotor response [14–16]. Thus, the robust target response provided by STMDs [7,8] can alert the central brain of the motion of a target irrespective of background motion, while the LPTCs inform the animal about self-motion. We

hypothesise that if the TSDNs combine the input from STMDs and LPTCs, they can project the information needed for flight correction. Specifically, when the target and background move in the same direction, the optomotor response itself ensures that the insect follows the target, and no extra TSDN signal is needed. In contrast, if the background moves in the opposite direction to the target, the TSDNs need to overcome the optomotor response, and therefore, the TSDN signal needs to be increased (for discussion, see [11]).

There are many models for the detection of motion (for review, see e.g. [17]), with interesting analogies between insects and vertebrates [18]. One of the classic models, the Hassenstein-Reichardt Elementary Motion Detector (EMD) model performs a non-linear comparison of signals from two points in space after delaying one of them [17,19–24]. Other more recent models, based on T4 and T5 cells in *Drosophila*, rely on the integration of fast excitatory signals with spatially offset slow inhibitory signals [24,25]. While all these models generate directional responses to widefield motion, some may also respond to smaller objects (as LPTCs do [26]). However, even if LPTCs respond to smaller objects, they are not target-tuned. Therefore, other models have been developed to explain the mechanisms underlying the ability of STMD's to detect small targets amidst clutter [7,27]. These generally either use a centre-surround mechanism [28] or cascade the centre-surround mechanism with temporal correlation filters [29,30]. Temporal correlation filters, often referred to as 1-point correlators, are based on the comparison of ON (brightness increment) and OFF (brightness decrement) signals from one point in space after delaying one of them. Thus, an elementary STMD (ESTMD) [29], which implements a 1-point correlator, detects the unique temporal signature associated with a dark target – where a leading OFF edge is immediately followed by a trailing ON edge – and thus only responds to small, dark, moving objects while being generally unaffected by background motion. A consequence of the 1-point correlator model is that, if target-like spatio-temporal signatures are found in the background, they will also elicit a response. This is indeed seen in dragonfly STMDs [30]. In addition, both STMDs and TSDNs respond poorly to signals containing only leading OFF or trailing ON edges [11,30], suggesting similar ESTMD-type input, and supporting the notion that TSDNs are post-synaptic to STMDs.

Existing models of small-object detection [28,29,31] fail to explain the observation that hoverfly TSDNs *are* affected by background motion [11]. Therefore, additional mechanisms are needed, and we hypothesised that both STMDs and LPTCs are necessary to describe the TSDN circuit mechanistically. While there are published models that incorporate ESTMD-EMD interactions, these either act to make the model ESTMD output directionally-selective [32] or to *enhance* target detection against velocity matched, syn-directional background motion [33]. As the responses of biological TSDNs are suppressed under these conditions, these models fail to explain the physiology.

To test our hypothesis, we made the outputs of the ESTMD model [29] directionally-selective [32], tiled them over the visual field, and spatially pooled their outputs to match biological STMD [34] and TSDN receptive fields [11]. We modelled optic-flow-sensitive LPTCs using EMDs (Hassenstein-Reichardt detectors) [20] and then fitted plausible TSDN circuit arrangements, combining the STMD and LPTC outputs, to previously published electrophysiological data from TSDNs [11]. Subsequently, we acquired new biological data where TSDNs responded to targets against different backgrounds and tested the candidate circuits on this new data to assess whether the models generalise. This led us to discard one of the circuits. To determine the most viable of the remaining two candidate circuits, we then tested them on other stimuli described in [11], allowing us to eliminate another circuit. Finally, we discuss how this simple circuit can mechanistically explain observations from biological TSDNs. Thus, by

Fig 1. Velocity tuning of model and biological LPTCs. (**A**) Local motion direction tuning curve obtained using a dot stimulus (see ref [45] for stimulus details). The asterisk (*) denotes the preferred direction. (**B**) Temporal frequency tuning to an 11.4° wavelength, square-wave vertical grating stimulus, with Michelson contrast of 95%. The green and purple arrows indicate motion in the preferred direction (PD) and null direction (ND), respectively. In both panels, the dashed black line denotes the spontaneous activity, and the model data represents the mean normalised response over 0.5 s stimulation. The biological LPTC data was obtained from ref [45].

combining existing neuron models of STMDs and LPTCs, we obtain a circuit configuration that can, for the first time, plausibly explain the phenomenon of facilitation and suppression observed in biological TSDNs [11].

Results

To model the responses of hoverfly TSDNs to targets moving against background motion, we took advantage of existing ESTMD [29, 35] and EMD models [17, 19]. To facilitate the continuity of the ESTMD model literature, we use the same naming conventions for the mechanisms described here as prior work [29, 35].

LPTC model captures direction and velocity tuning of biological LPTCs

LPTCs have been studied extensively in a range of dipteran flies, including the blowfly *Calliphora*, the fruitfly *Drosophila*, and the hoverfly *Eristalis*. There are 45-60 LPTCs in each hemisphere [36], including neurons that give graded responses, spiking responses, and a mix [37]. Here, we developed models based on spiking neurons, and as *Callipora* H1 and H2 are the best-studied spiking LPTCs [38–41], we used published data for these neurons for model fitting. However, considering that the velocity tuning, contrast response functions, and direction sensitivity are strikingly similar between diverse species [42–44], this choice should not affect our results substantially.

We modelled LPTCs by spatially pooling output from local elementary motion detectors (EMDs) (see Lobula Plate Tangential Cell (LPTC) modelling section) and compared our model output to biological data from blowfly H2 neurons (Fig 1). Using a

Fig 2. Response onset characteristics of model and biological LPTCs.
(**A**) The response onset to a 4 Hz stimulus, smoothed with a Gaussian filter with
$\sigma = 6$ ms. The stimulus appeared and started moving at 0 ms. The shaded region shows
the analysis window used in panel B. (**B**) The transient response (averaged over the
20−60 ms period shown in panel A) to preferred direction motion as a function of
temporal frequency. The spontaneous activity has been subtracted. The biological
LPTC data was obtained from ref [45]. All responses are normalised to their peak.

7.4° diameter dark dot stimulus on a white background (Michelson contrast of 60%),   105
Longden et al. [45] obtained the local motion direction tuning of the H2 neuron at 0°   106
elevation and 30° azimuth. We used a similar dot stimulus to obtain local motion   107
direction tuning for our model LPTC (red data, Fig 1A), with a preferred direction to   108
the right (0°) While there are other models for LPTC input [24], our EMD-based model   109
(Fig 1) also closely matches the temporal frequency tuning of the biological LPTC in   110
both the preferred (green arrow) and anti-preferred direction (purple arrow). This was   111
tested using a vertical square-wave grating with a wavelength of 11.4° and Michelson   112
contrast of 95%, presented for 0.5 s. In both biology and the model, the maximal   113
response occurs around 4 Hz. The model output shows a narrower temporal frequency   114
tuning than the biological data in the preferred direction (Fig 1B), which could be   115
changed by adding a saturating non-linearity to the model output. However, the   116
biological and model tuning curves both have their peak normalised response at the   117
same temporal frequency, which is close to the velocities relevant to our work. In   118
addition, both Figs 1A, B show that our model exhibits direction opponency, with an   119
asymmetry about the spontaneous rate in the response amplitude to motion in the   120
preferred and anti-preferred directions (see e.g. [42]).   121

Longden et al. [45] found that biological LPTCs start responding to square-wave   122
grating stimuli 20−60 ms after stimulus onset (green data, Fig 2A). In response to a   123
4 Hz stimulus, our model captures the response onset dynamics of biological LPTCs well   124
(red, Fig 2A). We quantified the mean response within a 20−60 ms time window across   125
temporal frequencies and found that our model LPTC mimicked biological data   126
(Fig 2B). Compared to the tuning curves in Fig 1B, those in Fig 2B peak at a higher   127
temporal frequency. This can be attributed to the fact that LPTCs respond faster as   128
the temporal frequency increases [46], and that the velocity response functions in Fig 2B   129

Fig 3. Comparison of spatiotemporal characteristics from model and biological STMDs. (**A**) Normalised responses to targets of different heights. The bar had a constant width of 0.8° and was moving at 50°/s. In modelling, we used bar heights between 0.35° and 9°. The biological STMD data is from ref [34](**B**) Velocity tuning of black, square targets (0.8°×0.8°). In modelling, we used velocities in the 10−600°/s range. The biological STMD data is from [10]. The black data is from [29]. Please note that the targets and bars in the pictograms are not to scale.

and Fig 2B are obtained through the mean LPTC responses over 0.5 s and 20−60 ms   130
time windows respectively. In summary, our LPTC model responses closely match those   131
of their biological counterparts (Fig 1 and Fig 2).   132

The dynamics of our STMD model match hoverfly biology   133

STMDs respond robustly to targets moving against background motion, even without   134
relative motion between the two [10]. Wiederman et al. [29] and Bagheri et al. [35]   135
proposed an elementary STMD (ESTMD) model that encapsulates this behaviour,   136
which we reproduced (see STMD modelling for algorithmic details of the STMD model).   137
In this model, each delayed OFF signal is correlated with an undelayed ON signal from   138
the same point in space. Together with spatial centre-surround inhibition, this creates a   139
selective detector for a dark target moving on a brighter background. To better match   140
hoverfly response functions, we modified the Gaussian kernel used for spatial blurring   141
(see Early visual processing in S1 Appendix) and the temporal adaptation time   142
constants (see Target matched filtering in S1 Appendix), but kept most other   143
components similar.   144

    Hoverfly STMDs vary in their directional selectivity as well as receptive field size   145
and location, with up to 20 different physiological types identified [10]. All STMDs are   146
defined by their sharp size tuning, which can be determined using a black bar with a   147
fixed width (parallel to the direction of target motion) and varying height   148
(perpendicular to the direction of target motion) moving at a constant speed. Hoverfly   149
STMDs give peak responses to targets with a height of a few degrees of the visual field   150
(green data replotted from [34], Fig 3A). Similar size tuning is found in other STMDs [8].   151
Our ESTMD model closely matches Wiederman et al.'s [29] model (compare black and   152
red data, Fig 3A), but is narrower than biology (green, Fig 3A). However, at the relevant   153

Fig 4. Candidate Model Circuits. All TSDN circuits include direct excitatory input from STMDs. *Left.* Circuit 1 involves a simple linear subtraction of the LPTC response from the STMD response. All neurons in the circuit have the same preferred direction (green arrows). *Middle.* Circuit 2 additionally includes an LPTC with the opposite preferred direction (purple arrow), multiplicatively amplifying the STMD signal. *Right.* Circuit 3 involves the addition of an STMD with the opposite preferred direction (purple arrow), multiplicatively amplifying the signal from the STMD. The circuits are reflected in the functional equations below each. α, β, κ and η are the coefficients of the relevant terms.

size ($\sim$1.4°) used in this paper, there is a close match between biology and models. ⁠154

We next look at the velocity response functions. As there is no published data from ⁠155 male STMDs, we used data from females to investigate the model's ability to ⁠156 recapitulate the velocity response function (green data replotted from [7], Fig 3B). The ⁠157 female STMD velocity sensitivity was determined using a black square of fixed size ⁠158 moving at a range of speeds in the neuron's preferred direction. Fig 3B shows the ⁠159 resulting velocity response function, which in models and experiments has its peak ⁠160 response around 30−200°/s [7, 29]. While the biological velocity tuning is broader than ⁠161 the models, Fig 3B shows that our ESTMD model matches Wiederman et al. [29]'s ⁠162 ESTMD model well, and is similar to biology at the relevant velocity ($\sim$90°/s). ⁠163

As TSDNs are directionally selective [1], they likely receive input from directionally ⁠164 selective STMDs. To capture this in our modelling, we passed the output from ⁠165 neighbouring ESTMDs through an EMD, resulting in directional selectivity (similar ⁠166 to [32]). In addition, we spatially pooled output from the directionally selective ⁠167 ESTMDs to match the receptive fields of small-field STMDs [1, 34]. Details about the ⁠168 directionally-selective STMD model are in the STMD modelling section in the Methods. ⁠169

TSDN circuit arrangements ⁠170

TSDNs are likely to be post-synaptic to STMDs [6, 47], as supported by their size, ⁠171 contrast, and velocity response functions [1], as well as their response to ON and OFF ⁠172 edges [11]. TSDNs are also highly directional with a preference for horizontal motion ⁠173 away from the visual midline [1]. Unlike LPTCs, TSDNs do not respond to motion in ⁠174 the anti-preferred direction and do not have a spontaneous firing rate. Contrary to ⁠175 dragonfly TSDNs, which constitute a heterogeneous population [48], hoverfly TSDNs are ⁠176 largely homogeneous, differing mainly in their directional selectivity [1]. An important ⁠177 difference compared to STMDs is that TSDN responses *are* affected by background ⁠178 motion, suggesting that they receive additional input from LPTCs. Syn-directional ⁠179

background motion inhibits TSDN response to target motion, where the level of inhibition is proportional to the level of LPTC excitation generated by the particular background [11, 47]. Therefore, as the strength of TSDN inhibition follows the direction, velocity, and contrast tuning of optic-flow sensitive neurons [11, 47], it seems plausible that they receive inhibitory input from LPTCs with the same preferred direction. In addition, TSDNs are facilitated by contra-directional background motion [11], suggesting that they receive input from neurons with the opposite preferred direction.

We based our modelling on published data from hoverfly TSDNs responding to small circular targets moving over a 'starfield' background [11]. This starfield pattern covers the entire visual field and was designed to simulate the type of optic flow generated by self-motion through the world, including e.g., sideslip translations and yaw rotations [14]. Because this background covers a large part of the visual field, it will strongly stimulate optic-flow sensitive neurons [14] and, because it consists of many target-sized features moving coherently (Fig 1 of [11]), it *could* also stimulate STMDs, although this has yet to be shown in biology. However, direct additive inputs from LPTCs or STMDs can be discarded categorically for the following reasons:

1. It is not plausible that LPTCs directly excite the TSDN, as this would result in TSDN responses to wide-field optic flow even in the absence of a target. This does not occur in biological TSDNs [11, 47].

2. It is not plausible that STMDs with a directional preference opposite to that of the TSDN directly excite the TSDN, as this would result in TSDN responses to both directions of motion, which does not occur in biological TSDNs [1].

Thus, we evaluate the three simple, bio-plausible circuit arrangements illustrated in Fig 4):

Circuit 1 involves a linear summation of STMD and LPTC inputs.

Circuit 2 is an extension of circuit 1, with additional excitatory input from an LPTC with the opposite preferred direction. This LPTC enhances any STMD signals, but does nothing if the STMD is inactive. Thus, in many cases, the outputs of circuits 1 and 2 are the same. However, in the event of background motion contra-directional to target motion, the STMD signal would receive an additional *boost* in circuit 2, thus resulting in a facilitated TSDN response.

Circuit 3 also amplifies the STMD input to the TSDN. However, in circuit 3, the amplification comes from an STMD with the opposite preferred direction of motion. For facilitation, circuit 3 thus relies on the background consisting of target-like objects, such as the 'starfield' background used in the published recordings of biological TSDNs [11].

In all three circuits, if a hoverfly is stationary or *hovering*, due to a lack of self-generated optic flow, the only input from the LPTC would be its spontaneous rate, and the TSDN output would be similar to the output of a TSDN receiving only STMD input.

Comparisons of candidate TSDN circuits

We fit the neuronal weight coefficients (α, β, κ and η from Fig 4) and the LPTC equation (Lobula Plate Tangential Cell (LPTC) modelling section) coefficients (g, γ and s) of our three candidate TSDN circuits to minimise the average root-mean-square error (RMSE) of model output against spike density functions obtained from published spike train data of several TSDNs responding to targets moving on a starfield background (see Data Analysis and Statistics section in Methods) [11]. In these experiments, the

Table 1. Neuronal weight and LPTC equation coefficients.

Circuit	LPTC equation			Neuronal weight			
	g	γ	s	α	β	κ	η
STMD only	-	-	-	0.4	-	-	-
Circuit 1	13	0.3	10	0.8	13.9	-	-
Circuit 2	11	0.9	10	0.3	29.9	2	-
Circuit 3	13	0.3	10	0.5	4.7	-	1

background consisted of thousands of targets moving horizontally to mimic the 226
perspective-corrected optic flow generated by the viewer sideslipping at 50 cm/s [14]. In 227
circuit 2, where two LPTCs are present, we only optimised a single set of LPTC 228
coefficients. We use an 'STMD only' circuit as a benchmark to normalise the circuit 229
errors. The 'STMD only' circuit comprises STMD output weighted by the coefficient α. 230
The coefficient values for the best fit are shown in Table 1. 231

Fig 5 shows the biological (green data replotted from [11]) and model responses of a 232
single TSDN to a target moving over either a bright background or over a starfield 233
background. When the target moves across a bright screen or against a stationary 234
pattern ('alone' and 'stationary', Fig 5), all the outputs are similar. However, when the 235
target is displayed over a starfield background moving in the same direction as the 236
target, all TSDN circuits are strongly inhibited ('syn', Fig 5). In contrast, the modelled 237
'STMD only' output remains strong, as expected from biological findings that STMDs 238
are unaffected by background motion (blue data in Fig 5; [10]). When the target is 239
displayed over a starfield background moving in the opposite direction, all TSDN 240
circuits are facilitated ('contra', Fig 5), whereas the modelled 'STMD only' output 241
remains largely unaffected. Again, this is expected from biology where STMDs are 242
unaffected by background motion (blue data in Fig 5; [10]). Note that the 'contra' 243
response from circuit 2 seems to 'overshoot' the biological TSDN response. 244

LPTCs have a spontaneous rate, i.e., they fire at a non-zero baseline rate even when 245
not stimulated [45] (dashed lines, Fig 1). When stimulated with motion in the preferred 246
direction, the response increases, whereas motion in the non-preferred direction leads to 247
an inhibition of the firing rate (see e.g. Fig 1B). The LPTC spontaneous rate means 248
that all the proposed circuits receive inhibitory LPTC input even in the 'alone' and 249
'stationary' conditions. However, for circuit 3, since in 'alone' and 'stationary' 250
conditions, only the target moves and STMDs do not have a spontaneous rate, the 251
output of the STMD with the opposite preferred direction (purple arrow, Fig 4) is zero. 252
This allows the synaptic weight of this amplifying STMD, η, to be tuned specifically 253
towards minimising the fitting error for the 'contra'-directional condition. Indeed, for 254
this example neuron (Fig 5), circuit 3 fits the biological TSDN data remarkably well. 255

To compare this across neurons, we calculated the average RMSE for each circuit per 256
condition (Fig 6) normalised against the equivalent RMSE of a TSDN circuit with only 257
an STMD input ('STMD only'). For each neuron simulation, we used the same initial 258
conditions, i.e., the same starting points for the target as were used in the 259
electrophysiology experiments, and took each neuron's receptive field into account 260
(see TSDN Receptive fields for details). We found that 'syn' resulted in the smallest 261
errors for all circuits, whereas 'contra' led to the largest errors. However, it should be 262
noted that with syn-directional motion, TSDN responses tend to be suppressed to 263
near-zero values (Fig 6; [11]). This is because the 'STMD only' circuit, which we used 264
for normalising, lacks an LPTC component and thus, inherently attempts to *average* 265
across the hyperparameter search space. This can be seen in the 'syn' panel of Fig 5 266
where the 'STMD only' response shows no suppression. 267

Across background conditions, and across neurons, circuit 1 performs better than 268

Fig 5. Example TSDN model and biological outputs to targets moving over the starfield background. The data show the spike histograms as a function of time from a single TSDN as it responds to a small target moving through its receptive field, in the neuron's preferred direction, at 900 pixels/s. The biological data (green) is replotted from [11]. The 'STMD only' circuit (blue) represents a TSDN circuit consisting only of an STMD input (no LPTC input). The different panels show the response to the black, circular target moving over a bright screen ('alone'), over a stationary starfield pattern ('stationary'), a sideslipping starfield (50 cm/s in the same direction as the target ('syn'), or in the opposite direction ('contra')). The greyscale bars under the data indicate the presence of the stimuli.

Fig 6. Errors from fitting candidate circuits to biological TSDN data for targets moving over the starfield background. For each neuron (N=35, data from [11]), we calculated the mean RMSE by comparing each circuit (described in Fig 4) with the electrophysiological data. The mean RMSE of each circuit per condition was then normalised by the equivalent RMSE of the 'STMD only' circuit. The whiskers of the black points (the mean RMSEs) indicate the variation across neurons, quantified as the standard deviation of the normalised mean RMSE of the particular bar plot. Note that the background in the pictogram has been faded out and that the target has been magnified substantially for viewing purposes.

circuit 2, and circuit 3 outperforms both circuits 1 and 2 (Fig 6). All circuits outperform the 'STMD only' circuit – the normalised errors are all below 1. Thus, across neurons, the normalised average RMSEs reflect the quality of the circuit fits exemplified for one neuron in Fig 5.

TSDN responses to targets moving across broadband backgrounds

When fitting the different circuits (Fig 6), we used published biological data where TSDNs responded to targets moving over a starfield background [11]. As the starfield background used in those experiments consists of thousands of target-like features, it *could* stimulate STMDs [27, 29] (although this remains to be shown experimentally). As this makes it difficult to separate the different circuit configurations (Fig 4), we generated new electrophysiological data (see Electrophysiology) where TSDNs responded to targets moving against two other backgrounds – 'cloud' (N=10) and 'sinusoidal' (N=6) – which do not stimulate STMDs [10].

The cloud background has a 2D power spectrum similar to that of typical natural scenes and a mean luminance of 50% [47] with a Michelson contrast of 100% (see ref [7] and Visual stimuli for more details). Consistent with earlier work [47], TSDN responses to target motion are inhibited when the target is displayed against syn-directional 'cloud' background motion (Figs 7C, F, I). Earlier work found that a similar contra-directional, naturalistic background inhibited TSDN responses to target motion [47]. However, here we find that they are strongly facilitated by contra-directional cloud background motion (Figs 7D, F, I).

The 'sinusoidal' background is a vertical sinusoidal grating with a wavelength of 7°, moving at 5 Hz, and a Michelson contrast of 25%, which should not stimulate any STMDs [10]. We found that this background also inhibited TSDN responses when

Fig 7. New electrophysiological recordings of TSDNs responding to targets moving over cloud and sinusoidal backgrounds. (**A-D**) Example raw electrophysiology data from a single TSDN responding to targets moving over a grey background ('alone'), or a 'stationary', 'syn'-directional, or 'contra'-directional cloud background. The greyscale bars under the data show the stimulus timing. (**E-G**) Spike rate responses from three different TSDN neurons for four background conditions, using the starfield (E), cloud (F), or sinusoidal grating (G) background. In all cases, the data show the spike histograms averaged across repetitions (starfield: n=9-15 repetitions; cloud: n=24 repetitions; sinusoidal: n=30 repetitions), and converted to rates as described in Methods. (**H-J**) Boxplots of TSDN responses across neurons for starfield, cloud and sinusoidal backgrounds. The whiskers of the boxplots extend across the range of the data (min to max). In all cases, we calculated the average spike frequency across the entire time the target was on the screen and normalised this to the response to a target moving over a bright (panel H), or grey (panels I and J), background. The data in panels E, H are replotted from [11]. Stars indicate statistical significance using one-way ANOVA followed by Dunnett's multiple comparisons test. Note that the pictogram targets have been magnified substantially for viewing purposes.

Fig 8. Errors from testing candidate circuits on biological TSDN data for cloud and sinusoidal backgrounds. The normalised mean RMSEs from fitting each circuit described in Fig 4 to TSDN electrophysiological data for each condition for the cloud (left) and sinusoidal (right) backgrounds. The RMSEs of each circuit per condition are normalised by the equivalent RMSE of the 'STMD only' circuit. The whiskers of the black points indicate the standard deviation of the normalised mean RMSE of the particular bar plot. Note that the targets in the pictograms have been magnified substantially for viewing purposes.

targets moved syn-directional, and facilitated TSDN responses when contra-directional (Fig 7G, J). 293 294

The new backgrounds not only allow us to test the robustness of all the fitted 295 circuits, but also let us test the viability of circuit 3 as it relies on STMD input for the 296 facilitation, and thus on backgrounds (like 'starfield') that contain target-like features. 297 Because both the cloud and sinusoidal backgrounds are devoid of target-like features, the 298 facilitation seen in the new electrophysiology (Fig 7) argues strongly against circuit 3. 299

Using the circuit coefficients listed in Table 1 (which we *fitted* on the starfield 300 dataset), we *tested* each candidate circuit on the cloud and sinusoidal datasets (Fig 7). 301 Similar to our initial testing on the starfield dataset, we used the same initial conditions, 302 i.e., same starting points of the target, as in electrophysiology, and took each neuron's 303 receptive field (see TSDN Receptive fields for details) into account in the simulations. 304 Again, the errors between the biological and modelled TSDNs were quantified by an 305 average RMSE per neuron. 306

We found that the circuit 1 errors for the cloud and sinusoidal backgrounds were 307 fairly consistent with those for the starfield background (compare Fig 6 and Fig 8). 308 However, circuits 2 and 3 produced much higher errors (Fig 8) compared to those 309 obtained on the starfield background, especially for contra-directional background 310 motion. For circuit 2, this might be due to the model output for contra-directional 311 background motion being significantly higher than the biological TSDN response (see 312 single neuron response and modelling in Fig 5), which resulted in higher errors across 313 neurons (Fig 8). For circuit 3, the large errors stemmed from the lack of target-like 314 objects in the background, and the circuit's subsequent failure to produce facilitation. 315 All three circuits had higher errors to syn-directional sinusoidal background motion 316 (Fig 8) compared with the starfield background (Fig 6). This is because some TSDNs 317 responded to targets moving across the 'syn'-directional sinusoidal background (Fig 7J), 318 resulting in model testing errors. Nevertheless, taken together (Figs 7 and 8), these 319

results suggest that circuit 3 can be discounted as a viable TSDN circuit. ₃₂₀

Circuit 1 provides best fit to results of preceding optic flow experiments ₃₂₁

Nicholas and Nordström [11] explored whether the TSDN response would also be ₃₂₂
affected by background motion that immediately preceded, but did not coincide with ₃₂₃
target motion (Fig S3 of [11]). The stimuli consisted of two parts: (1) preceding optic ₃₂₄
flow – background motion *before* the moving target appears, and (2) concurrent optic ₃₂₅
flow – background motion *while* the target is in motion. ₃₂₆

The effects of preceding optic flow on TSDN responses are thought to relate to the ₃₂₇
overlap of decaying LPTC responses and rising STMD activity and hence depend ₃₂₈
strongly on the offset and onset latencies. Therefore, to investigate how the preceding ₃₂₉
optic flow affects our model outputs, we first investigated the response latencies of our ₃₃₀
circuits. The LPTC model (see Lobula Plate Tangential Cell (LPTC) modelling section) ₃₃₁
has a decay time constant of 40 ms. The STMD model employs a temporal band-pass ₃₃₂
filter (Early visual processing section in S1 Appendix) for contrast adaptation, a ₃₃₃
temporal low-pass filter for the one-point correlator, and an HR-detector for directional ₃₃₄
selectivity (see STMD modelling section in Methods), all together introducing delays of ₃₃₅
∼16 ms. We quantified the resulting TSDN latency – which we define as the time ₃₃₆
between the onset of a stimulus and a TSDN response ≥ 1 Hz being elicited – after ₃₃₇
varying the target height (Fig 9A) or velocity (Fig 9B), for target trajectories starting ₃₃₈
within the receptive field. No published hoverfly TSDN data is available so, for ₃₃₉
biological comparison, we used data from dragonfly TSDNs, which have latencies ₃₄₀
between 20 ms and 40 ms [48]. For the relevant target height (1.4°) and velocity (90°/s), ₃₄₁
all three circuits exhibited latencies in this range (shaded areas, Fig 9). Assuming that ₃₄₂
hoverfly TSDNs have similar latencies to dragonflies, we therefore assume that our ₃₄₃
TSDN circuits all have comparable latencies to their biological counterparts. ₃₄₄

We next investigated how the preceding optic flow configurations used by Nicholas ₃₄₅
and Nordström [11] affect our models. They found that 1 s of preceding, syn-directional ₃₄₆
optic flow inhibits biological TSDN responses to targets moving over a concurrent, ₃₄₇
stationary background, whereas preceding contra-directional optic flow does not ₃₄₈
facilitate responses. An example stimulus consisting of such contra-directional preceding ₃₄₉
(rightward) optic flow with a leftward-moving target is presented in S1 Video. In our ₃₅₀
simulations, the preceding optic flow lasted 0.48 s and was either stationary, ₃₅₁
syn-directional, or contra-directional to target motion Fig 10. Importantly, as long as ₃₅₂
the optic flow is presented for at least 80 ms, it stimulates LPTCs maximally (Fig 2A). ₃₅₃
Fig 10 shows the average TSDN response throughout the 0.48 s period of target motion, ₃₅₄
averaged across neurons and conditions, and normalised against the average TSDN ₃₅₅
response to a target moving 'alone' (green data replotted from [11]). The results show ₃₅₆
that circuit 1 reproduces experimental results in all three conditions (red, Fig 10). ₃₅₇
However, circuit 2 produces significantly different results to biological TSDNs for ₃₅₈
syn-directional preceding optic flow (golden, Fig 10, one-way ANOVA, followed by a ₃₅₉
post-hoc two-sample *t*-test with Bonferroni correction, $P \leq 0.0001$), suggesting that ₃₆₀
circuit 1 is more biologically plausible. ₃₆₁

To better understand why syn-directional preceding optic flow inhibits TSDN ₃₆₂
responses, we simulated three targets that were spatially offset from each other by the ₃₆₃
distance the targets would travel in 25 ms (Fig 11). When the target starts within the ₃₆₄
TSDN receptive field (cyan target, Fig 11A, B) the modelled STMD response rises ₃₆₅
rapidly (orange, Figs 11C). When the starting position of the target is spatially offset to ₃₆₆
be outside the receptive field (green and red targets, Fig 11B), the timing of the STMD ₃₆₇
output is temporally delayed accordingly (orange, *middle* and *right*, Fig 11C). ₃₆₈

Importantly, as the timing of the preceding optic flow is the same in these three ₃₆₉
conditions, the LPTC outputs in both the preferred (LPTC$_{\text{PD}}$) and anti-preferred ₃₇₀

Fig 9. Our TSDN circuits exhibit similar latencies to biological TSDNs.
TSDN model latencies (red, circuit 1; golden, circuit 2; black, circuit 3) to changing
spatiotemporal target characteristics. (**A**) Circuit latencies for different target heights
(fixed width of 0.8°, heights 0.7−9°, moving at 50°/s). (**B**) Circuit latencies for
different velocities of square targets of fixed size 0.8°×0.8°. The velocity range is from
10−300°/s. The shaded region (20−40 ms) signifies the latency range observed in
dragonfly TSDNs [48]. Note that the pictograms are not to scale.

directions (LPTC$_\mathrm{ND}$) are also the same (green and purple, Fig 11C). Thus, when   371
preceding optic flow in the preferred direction stops, LPTC$_\mathrm{PD}$ activity decays back to   372
the spontaneous rate (green, Fig 11C), with a time course similar to the LPTC response   373
onset (*left*, Fig 2). At the same time, the inhibited LPTC$_\mathrm{ND}$ returns to the spontaneous   374
rate with a similar time course (purple, Fig 11C). Thus, when considering the model   375
output in the 0.48 s analysis window (dashed box, Fig 11A), if the target starts within   376
the receptive field (cyan target, Fig 11B), STMD activity coincides with decaying   377
LPTC$_\mathrm{PD}$ activity, and therefore the resultant TSDN output is suppressed ($\Delta t = 0$ ms,   378
Fig 11C). However, if the targets start outside the receptive field, the LPTC activity   379
has already returned to the spontaneous rate by the time the STMD activity starts,   380
leaving the TSDN output unaffected ($\Delta t = 25$ ms and $\Delta t = 50$ ms, Fig 11C).   381

We find that in the model, TSDN firing rates averaged over the 0.48 s analysis   382
window ($\bar{f}$) differ by 28.2% between the example where the target started well *outside*   383
the receptive field ($\Delta t = 50$ ms, Fig 11C, 18.1 Hz) compared with when it started *within*   384
the receptive field ($\Delta t = 0$ ms, Fig 11C, 13.0 Hz). This response reduction is similar in   385
magnitude to the difference observed in the biological TSDN firing rates between   386
preceding optic flow that was either 'stationary' or 'syn-directional' to target motion   387
(33.4%, green data, Fig 10). If the target starts at an intermediary position (green   388
target, Fig 11B) the resulting firing rate in this example was 17.3 Hz (*middle*, Fig 11C).   389

Thus, we can now hypothesise why circuit 2 suppresses the TSDN response when   390
syn-directional optic flow is concurrent with target motion (golden, Fig 5), but not when   391
there is no concurrent optic flow, only preceding optic flow (golden, Fig 10). As circuit 2   392
receives input from two LPTCs, with opposite preferred directions of motion (circuit   393
equations, Fig 4), these opposing LPTC activities cancel each other out in the preceding   394
optic flow experiments (Fig 10). In contrast, when background optic flow is concurrent   395
with target motion (see e.g. 'syn' in Fig 5), LPTC input in circuit 2 adequately   396

Fig 10. Model and biological TSDN outputs to preceding optic flow. The outputs of the fitted circuits are compared with biological TSDN responses (green, replotted from [11]). In the legend, target motion is shown in blue, and preceding optic flow with green arrows, or a dot, if stationary. The box edges denote the first and third quartiles of the data, with a line at the median. The whiskers denote the furthest data point within 1.5x the interquartile range (IQR). The unfilled circles are outliers. Significance is shown with one-way ANOVA followed by two-sample t-tests with Bonferroni correction (**** $P \leq 0.0001$).

Fig 11. The inhibition by preceding, syn-directional optic flow depends on target timing. (**A**) Raw data trace from a TSDN to a target moving in its preferred direction. For 1 s before target motion, the 'starfield' background was sideslipping at 50 cm/s, in the TSDN neuron's preferred direction. During target motion, the starfield background was stationary. The coloured bars indicate the occurrence of the preceding optic flow (green) and the presence and movement of a target (blue). The dashed box indicates the (0.48 s) analysis window, which coincides with target motion. The trace is replotted from [11]. (**B**) Three modelled targets spatially offset from each other by the distance they would travel in 25 ms, on their trajectory into the modelled TSDN's receptive field (dashed ellipse). (**C**) *Top row* Modelled spike histograms as a function of time; STMD (orange), LPTC in preferred (green, LPTC_{PD}) and anti-preferred directions (purple, LPTC_{ND}). *Bottom row* Circuit 1 output for the three different target start positions as described in panel (B). The dashed lines indicate when the preceding optic flow stops and the target appears and starts moving. The shaded areas indicate the start of the 0.48 s analysis window.

suppresses the TSDN response, providing a good fit between the model and biology. ₃₉₇

Circuit 1 provides best fit to results of dot density experiments ₃₉₈

In the experiments above, the density of the starfield background was kept at ₃₉₉
100 dots/m^3. However, Nicholas and Nordström [11] also explored whether varying the ₄₀₀
dot density from $10 - 500$ dots/m^3 affected the background modulation of the TSDN ₄₀₁
response. This is an important test as sparse widefield patterns generate weaker ₄₀₂
hoverfly LPTC responses than dense, high-contrast patterns [49], and we would ₄₀₃
therefore expect the LPTC input to be weaker at lower dot densities. Indeed, while ₄₀₄
optic-flow sensitive descending neurons respond strongly to the lowest dot density, the ₄₀₅
response is less than half of the response to the higher dot densities [11]. Our LPTC ₄₀₆
model output follows the same logarithmic behaviour as the dot density increases. Thus, ₄₀₇
the level of inhibition and facilitation should scale with dot density. However, while ₄₀₈
biological TSDN responses were not facilitated when low-density background motion ₄₀₉
was contra-directional to target motion, responses were facilitated at higher dot ₄₁₀
densities [11]. In contrast, biological TSDN responses were suppressed by ₄₁₁
syn-directional background motion at all dot densities tested. An example stimulus of ₄₁₂
the starfield background with a dot density of 500 dots/m^3 moving contra-directional to ₄₁₃
a leftward moving target is presented in S2 Video. ₄₁₄

  Fig 12 shows the normalised (to each neuron's own mean response to a target moving ₄₁₅
over a white background) model and biological TSDN responses to a target moving ₄₁₆
against stationary, syn- and contra-directional background motion, across various dot ₄₁₇
densities. Both circuits 1 and 2 reproduce the suppression observed in biology (middle ₄₁₈
row, Fig 12). Circuits 1 and 2 sometimes exhibit suppression significantly stronger than ₄₁₉
biology; these happen because while the model outputs are completely driven to zero, in ₄₂₀
biology, TSDNs may experience noise that causes occasional firing (middle row, Fig 12) ₄₂₁

  However, when it comes to facilitation (which, in biology, depends on dot ₄₂₂
density [11]), circuit 2 sometimes produces TSDN outputs that are significantly different ₄₂₃
(asterisks in Fig 12). Circuit 2 performs worse because the amplification of the STMD ₄₂₄
activity by the LPTC with the opposite preferred direction (purple arrow, *middle* ₄₂₅
circuit, Fig 4) results in model outputs that *overshoot* the biological TSDN responses ₄₂₆
(see e.g. 'contra' panel, Fig 5). Thus, for contra-directional background motion at ₄₂₇
10 dots/m^3, while circuit 2 outputs show facilitation, circuit 1 outputs match biological ₄₂₈
TSDN responses better (bottom row, Fig 12). ₄₂₉

  As modelled and biological LPTCs follow a logarithmic behaviour as dot density ₄₃₀
increases, our model suggests that, at a dot density of 10 dots/m^3 where the LPTC ₄₃₁
activity is low, there will be low/no facilitation of TSDN responses by contra-directional ₄₃₂
background motion. However, since even at a low dot density, syn-directional motion ₄₃₃
causes suppression of TSDN responses (middle row of Fig 12; [11]), this would indicate ₄₃₄
that the LPTC synaptic weight would have to be quite high relative to the STMD ₄₃₅
synaptic weight to fully suppress the STMD activity. This is confirmed in the LPTC ₄₃₆
synaptic weight (β) hyperparameter values obtained for both circuits 1 and 2 (shown in ₄₃₇
Table 1). Taken together, these last two experiments (Figs 10 and 12) again suggest ₄₃₈
that circuit 1 is the most biologically plausible. ₄₃₉

Discussion ₄₄₀

We modelled three candidate TSDN circuits (Fig 4) using plausible combinations of ₄₄₁
existing STMD [29] and LPTC [20] models to drive the suppression by syn-directional ₄₄₂
background motion and the facilitation by contra-directional background motion seen in ₄₄₃
biology (Fig 7). We fitted our circuit models to published data [11], and then used new ₄₄₄

Fig 12. Model and biological TSDN responses to targets moving over backgrounds with different dot densities. The outputs of the fitted circuits (red, circuit 1; golden, circuit 2) and biological TSDN data (green data replotted from ref [11]) to targets moving over the starfield background with variable dot density. The different motion directions are colour-coded and results are laid out as such: target (blue), stationary (grey; top row), syn- (green; middle row), and contra-directional (purple; bottom row). The default starfield background at 100 dots/m^3 is highlighted in bold. In each grid, significance is shown with one-way ANOVA followed by two-sample t-test with Bonferroni correction (*$P \leq 0.05$, **$P \leq 0.01$, ***$P \leq 0.001$, ****$P \leq 0.0001$).

electrophysiology data to rule out one of the circuits (Fig 7; Fig 8). Then, we compared the remaining circuits against published preceding optic flow (Fig 10) and dot density (Fig 12) data [11]. Through the interplay of STMD and LPTC dynamics, our best-fitting model (circuit 1) provides mechanistic explanations for suppression and facilitation of TSDN responses in the presence of syn- and contra-directional background motion (Figs 5 and 8), respectively, as well as observations related to preceding optic flow (Fig 10) and dot density (Fig 12) experiments [11].

Interestingly, the model that best fits the biological data (circuit 1, Fig 4) is the simplest one. Indeed, a similar circuit was proposed earlier [47] based on the finding that TSDN inhibition by background motion is proportional to the response amplitude of optic-flow sensitive neurons generated by that particular background. However, subsequent findings revealed asymmetries in the TSDN response [11]: facilitation from contra-directional background motion and inhibition from syn-directional motion were not balanced. These asymmetries, evident in the preceding optic flow (Fig 10) and dot density experiments (Fig 12), prompted the hypothesis that more complex mechanisms – such as those implemented in circuits 2 and 3 (Fig 4) – may be involved [11]. However, our modelling here shows that even the simple circuit can explain these findings (Figs 10 and 12).

Previous models have incorporated ESTMD and EMD output interactions [32, 33]. However, they were either aimed at making ESTMD output directionally selective using an EMD mechanism [32] – a technique we also employ in making our directionally-selective STMD (see Directional-selectivity section in Methods) – or *improving* target detection in visual clutter [33], and thus were unable to capture the TSDN responses recorded in hoverflies [11, 47]. In contrast, our modelling presented here not only explains the inhibition by syn-directional background motion but also the facilitation by contra-directional background motion seen in biology.

While there are more recent models of insect motion detection, such as the T4 model [24], we used a Hassenstein-Reichardt [20] detector to model LPTC responses. The main difference between the more recent T4 model and the EMD that *could* affect our results is the spatially offset anti-preferred direction responses in the T4 model at low background velocities. However, at the higher background velocity (90°/s) used here, responses to preferred and anti-preferred background motion follow a similar time course [24]. As such, we would not expect our findings to change dramatically with a different LPTC model, especially considering that our implementation fits biological data well with respect to temporal frequency tuning (Fig 1B), response onsets (Fig 2A), and preferred vs anti-preferred direction asymmetries (Fig 1).

While our deterministic model predicts how an *average* TSDN might respond to different target and background combinations, it cannot explain the variation between trials or between neurons seen in biology (e.g., Fig 7). In dragonflies, the equivalent neurons to TSDNs (i.e., those which specifically respond to small targets) vary vastly in receptive field size and location, direction selectivity, and response specificity [48], which could explain a large amount of inter-neuron variation. However, hoverfly TSDNs are more homogeneous with similar receptive fields and tuning characteristics [1], so heterogeneity is unlikely to explain the inter-neuron variability seen in our recordings (Fig 7). Therefore, the variability we see must come from other sources. One possible source could be the varying strengths of connections between neurons [50], which could lead to inter-neuron variability in TSDN responses. Furthermore, like dragonflies, hoverflies are poikilothermic animals with limited thermoregulation. Temperature has been shown to have a significant impact on the tuning properties of dragonfly STMD neurons [51], suggesting that any variations in temperature during recording sessions could lead to inter-trial variability. Finally, in blowflies, the response characteristics of LPTCs have been shown to depend on the activity state of the animal, i.e., LPTCs have

different response characteristics depending on whether the animal is stationary, walking or flying [52]. As this state dependence can be mimicked by the application of chlordimeform (CDM, an octopamine receptor agonist), which has also been shown to affect hoverfly LPTCs [53], it is plausible that activity- or attention-based LPTC modulation could contribute to inter-trial variability.

TSDNs are thought to contribute to target pursuit by supplying input to motor neurons [6]. Indeed, in dragonflies, TSDNs project to motor neurons responsible for wing control [48]. Additionally, other research [54] suggests that TSDNs may initiate foveating head movements, helping to stabilise the target image on the retina both before and likely during the 'shadowing' flight. Although it remains unclear whether hoverfly TSDNs directly influence head or wing movements, the simple circuit identified as the most parsimonious in our study (Fig 4) involves only minimal computational steps, suggesting it could support fast and accurate pursuit decision-making. Notably, if the hoverfly is self-generating optic flow, e.g., from body saccades, syn-directional background motion could result from a moving pursuer observing a stationary target, allowing the hoverfly to discriminate between *genuine* targets and target-like features (figure discrimination [31]), whereas contra-directional background motion may arise when the target is moving in the same direction as the pursuer. By comparing these signals, the pursuer could extract an error signal indicating the necessary corrective action. This idea is supported by research on predatory Diptera, which shows that they can use such error signals to guide efficient pursuit [55–57].

Interestingly, in response to target images reconstructed from pursuits [5], where the target is most often placed in the frontal part of the eye with binocular overlap [58], hoverfly TSDNs do not respond strongly [1]. However, these reconstructions were not completely natural as the hoverflies were pursuing artificial targets in a free-flight arena of limited size [5]. In nature, male *Eristalis* hoverflies set up territories, which they defend vigorously against other insects [59]. As they typically initially detect these intruding insects from a stationary stance, this would resemble our 'stationary' conditions. However, during pursuit, they might perform body saccades to keep the target in their visual field, and in this case, the background patterns would resemble our 'syn' and 'contra' conditions. In the future, it would be interesting to reconstruct both target images and optic flow generated during such target pursuit to determine how often the background moves 'syn'- and 'contra'-directional to the target. Indeed, it is likely that comparing the two signals is the key information needed for flight correction. Such an analysis would help evaluate the ethological impact of our findings.

Materials and methods

STMD modelling

Our STMD model implementation (Fig 13) can be partitioned into four stages: (1) 'Early visual processing', which includes the temporal and spatial filtering found in fly optics, photoreceptors and lamina monopolar cells; (2) 'Target matched filtering' which includes the processes that lead to the discrimination of the target against visual clutter; (3) 'Directional selectivity' which makes the resultant ESTMD directionally selective; (4) 'Receptive fields' to match the modelled STMD to that of a biological small-field STMD [34].

For stages (1-2), we reproduced the ESTMD model presented by Wiederman et al. [29] and Bagheri et al. [35]. We here added stages (3-4), providing directional selectivity (in a similar way to [32]) and small-field STMD receptive fields. We also tuned our ESTMD model hyperparameters to match hoverfly physiology. Details about the ESTMD model implementation are in S1 Appendix, whereas mechanisms

Fig 13. STMD model. Our STMD implementation – based on Wiederman et al. [29] with our additions to create directional selectivity (in a similar way to [32]) and mimic STMD receptive fields. Visual stimuli first undergo early visual processing in the fly photoreceptors and lamina monopolar cells (LMC). The LMC output is then separated into ON (red) and OFF (blue) channels, which are independently processed through rectifying transient cells (RTCs) found in the fly medulla. Then, the ESTMD output is a single-point correlation of a delayed OFF signal with an undelayed ON signal, as in [29, 35]. The ESTMD output is then made directionally selective and spatially pooled using a 2D Gaussian representative of a small-field STMD's receptive field [34].

Fig 14. HR-EMD mechanism leads to directional ESTMD output. (**A**) The Hassenstein Reichardt EMD mechanism detects directional motion and produces a positive or negative response, denoted by a Gaussian, corresponding to the preferred (here rightward, green) or anti-preferred (here leftward, purple) direction. (**B**) The ESTMD output, represented as a 2D matrix, is split into two spatially segregated channels (green and purple matrices) that feed into the HR-EMD mechanism described in (A). The output is then half-wave rectified. In this case, the preferred direction of target motion is rightwards (green).

introduced here are our contributions to extending the standard ESTMD model [29] to obtain a biologically plausible directionally selective small-field STMD model.

Directional-selectivity

Since TSDNs are directionally selective [1], even in the absence of widefield motion, and based on our hypothesis that STMDs primarily drive the target selectivity seen in TSDNs, input from directional model STMDs seems plausible. To implement this, the non-directionally-selective ESTMD outputs are passed through a Hassenstein-Reichardt Elementary Motion Detector (HR-EMD) [17] (similarly to [32]), resulting in a preferred and an anti-preferred direction of target motion. As illustrated in Fig 14A, in the HR-EMD mechanism, two spatially segregated inputs (x_1 and x_2), separated by distance ϕ, are correlated ($\times$) after delaying (D) one of the signals. The delay operator, D, like the one used in the Target matched filtering section in S1 Appendix, is a first-order low-pass filter with a time constant $\tau_D = 40$ ms. The correlation outputs are then subtracted, resulting in an HR-EMD output that gives positive output to one direction of motion, and negative output to the other.

The ESTMD output from 'target matched filtering' can be represented as a 2D matrix (*Top*, Fig 14B). Spatially segregating this matrix by a distance ϕ, the spatially segregated inputs to the HR-EMD can be obtained. In this case, the green and purple

Fig 15. Constructing STMD receptive fields. (**A**) *Top.* The small-field STMD receptive field [34] is modelled as a Gaussian, shown in black. The distance between the centres of two adjacent receptive fields is then 2σ, where σ is the standard deviation of the Gaussian. Due to the Gaussians overlapping, the effective STMD receptive field strength is obtained through superposing (linear summating) the Gaussians. The superposed STMD receptive field is shown in red. *Below.* The STMD receptive fields at 50% maximum (full width at half maximum; FWHM), shown as circles, are arranged in a square grid. One model STMD receptive field and associated Gaussian are highlighted in bold. (**B**) A $34°\times23°$ cropped patch of the visual field highlighting an example biological TSDN receptive field. The contours at 50% receptive field strength of the mapped TSDN receptive field (green) and a fitted 2D Gaussian (red). (**C**) The centres of the STMD receptive fields (red plusses) needed to create the biological TSDN receptive field in panel B are here overlayed on the 2D Gaussian. (**D**) The resulting modelled TSDN receptive field reconstructed from the superposed STMD receptive fields shown in panel C.

shaded regions become x_1 and x_2 respectively (as described in Fig 14A). Finally, the HR-EMD output is passed through a Rectified Linear Unit (ReLU) block so that the output is non-negative.

TSDN Receptive fields

The final STMD output is obtained by spatially pooling directionally-selective ESTMD outputs (stage 4 in Fig 13). Barnett et al. [34] found that hoverfly small-field STMD receptive fields can be roughly expressed as a 2D isotropic Gaussian with $\sigma = 3°$. Thus, to achieve a good match with hoverfly biology, each STMD pools its inputs from a 2D Gaussian with $\sigma = 3°$. The receptive fields of multiple STMDs then tile the visual field with their centres separated by 2σ [60,61], resulting in a small overlap (Fig 15A).

The receptive field mapping method for biological TSDNs described in Nicholas and Nordström [11] leads to a coarse TSDN receptive field, shown with a green outline in Fig 15B. To improve the spatial resolution of the TSDN receptive field to a degree suitable for the modelling, we fitted 2D Gaussians to the coarse biological TSDN receptive fields (red outline, Fig 15B). Since we presume that STMDs are presynaptic to TSDNs, we reconstructed the TSDN receptive field from model STMD receptive fields

to ensure the model is TSDN receptive field-size invariant. In this way, since the receptive fields of small-field STMDs are smaller than those of TSDNs, multiple STMD outputs are pooled to give a single TSDN output. To calculate the number and locations of STMDs comprising each TSDN, we correlated the tiled STMDs across the visual field with the location of the TSDN receptive field (using the 50% Gaussian). In Fig 15C, the resultant STMD centres are shown as red plusses. Thus, by superposing the outstanding model STMD receptive fields, a reconstructed model TSDN receptive field was achieved (Fig 15D).

The widefield STMD used in circuit 3 (Fig 4) was modelled in a similar way to the small-field STMD. However, the large-field STMD spans over an azimuthal range of $0 - 30°$ and an elevation from $30-69°$ (the upper bound of the visual field stimulated in electrophysiology) ipsilateral to the TSDN receptive field [10].

Lobula Plate Tangential Cell (LPTC) modelling

Optic-flow sensitive neurons in the fly optic lobe are known as Lobula Plate Tangential Cells (LPTCs). LPTCs integrate local motion signals from small-field T4 and T5 neurons [62]. In the absence of motion, spiking LPTCs fire at a spontaneous (baseline) rate and their activity increases or decreases from this baseline, depending on whether widefield motion is in the preferred direction (PD) or null direction (ND) (green data, Fig 1). However, the change in LPTC activity in response to widefield motion is asymmetric and dependent on the direction of the motion [63], i.e., the increase in LPTC activity is proportionally higher than the decrease in LPTC activity for the same amount of widefield motion in the preferred and null directions, respectively (green data, Fig 1).

We used the classic Hassenstein-Reichardt detector [20, 22, 23, 64] model for our EMDs, and passed each ON-ON and OFF-OFF combination of inputs through a 2-quadrant-detector [65], to obtain two EMD outputs – one that has a PD to the right and another to the left (green and purple respectively in Fig 16). Each EMD output is half-wave rectified and spatially pooled. Spatial pooling creates a uniform directionally selective LPTC receptive field spanning across all elevations to either side of the azimuthal midline, e.g. left side of the visual field has LPTC with preferred direction to the left. The resultant ND response is multiplied by a ratio, γ, before subtracting from the resultant PD response (Fig 16) to provide an LPTC output. This linear subtraction imbues the LPTC output with an asymmetric sensitivity to widefield motion.

γ (Fig 16A) is defined as the ratio of maximum increment to maximum decrement of the LPTC response about the spontaneous rate. The functional equation of the LPTC model involves the linear subtracted output (encompassed in curly brackets, Fig 16B) being scaled by a scaling coefficient, g, before being added to a non-zero spontaneous rate, s. The LPTC model response is clamped at zero as the spiking frequency cannot be negative. The delay operator in the 2-quadrant-detectors (blank square structural motif, Fig 16A), D, is expressed the same as in the Target matched filtering section in S1 Appendix, with a time constant, τ_D ($\tau_D = 40\,\text{ms}$).

Electrophysiology

Male *Eristalis tenax* hoverflies were immobilised at room temperature, ventral side up, using a mixture of beeswax and resin. A small region of the cuticle was removed at the anterior end of the thorax to expose the cervical connective. A fine wire hook was placed under the cervical connective for mechanical support, and a silver wire was inserted into the cavity as a reference electrode.

Extracellular recordings were made from the cervical connective using a sharp polyimide-insulated tungsten microelectrode ($2\,\text{M}\Omega$; Microprobes). Data were amplified

Fig 16. LPTC modelling (**A**) The inputs from two spatially-segregated points (x_1 and x_2) first undergo the same 'early visual processing' as the STMD model (Fig 13). Using 2-quadrant-detectors where only input combinations of the same contrast polarity are processed (ON-ON, OFF-OFF), directionally selective EMDs in the preferred direction (PD, green) and null direction (ND, purple) are obtained. In this case, the PD is to the right and the ND is to the left. The structural motifs in this circuit are the same as those in Fig 14A. (**B**) The direction sensitivity and the effect of different velocities of motion (longer and darker arrows denote higher velocity) in the PD and the ND on the modelled response. The grey arrows denote the direction of motion of the bar. In this case, the PD of motion is to the right, denoted by the *.

at 100 gain and filtered through a $10-3000\,\text{Hz}$ bandwidth filter using a DAM50 differential amplifier (World Precision Instruments), with $50\,\text{Hz}$ noise removed with a Hum Bug (Quest Scientific). Data were acquired and digitised at $40\,\text{kHz}$ using Powerlab 4/30 and LabChart 7 Pro (ADInstruments). Single units were discriminated by amplitude and half-width using Spike Histogram software (ADInstruments).

During the experiment, hoverflies were positioned perpendicular to and $6.5\,\text{cm}$ away from the middle of a linearised LCD screen (ASUS) with a mean illuminance of $200\,\text{lx}$, a refresh rate of $165\,\text{Hz}$, and a spatial resolution of 2560×1440 pixels (59.5×33.5 cm), giving a projected screen size of $155° \times 138°$. Visual stimuli were displayed using custom software written [66] in MATLAB (version R2019b; MathWorks) using the Psychophysics toolbox [67,68].

TSDNs were identified as described [9]. In short, we mapped the receptive field of each neuron by scanning a target horizontally and vertically at 20 evenly spaced elevations and azimuths [1] to calculate the local motion sensitivity and local preferred direction. We then scanned targets of varying height through the small, dorso–frontal receptive fields to confirm that each neuron was sharply size tuned with a peak response to targets subtending $3°$ to $6°$, with no response to larger bars, to looming or widefield stimuli [1,9].

Visual stimuli

To test the effects of background motion on the TSDN response, we displayed targets against one of three different backgrounds (shown in Fig 17). Unless otherwise mentioned, targets were black and round with a diameter of 15 pixels (starfield background) or 15×15 pixels black squares (cloud and sinusoidal backgrounds), moving at a velocity of 900 pixels/s for $0.48\,\text{s}$. When converted to angular values and taking the small frontal TSDN receptive fields into account [1], this corresponds to an average diameter of $3°$ and a velocity of $130°/\text{s}$ [47]. Unless otherwise stated, each target travelled in each neuron's preferred horizontal direction (i.e., left or right) and across the centre of its receptive field. The target elevation was varied slightly between repetitions to minimise habituation [11]. There was a minimum of $4\,\text{s}$ between each stimulus presentation.

The background stimuli all covered the entire visual monitor, i.e. they had a spatial extent of 2560×1440 pixels, corresponding to $155° \times 138°$ [11]:

Starfield a 2D rendering of a simulated 3D environment containing randomly located spheres. These were perspective corrected to display the optic flow that would be generated if the hoverfly was sideslipping at $50\,\text{cm/s}$, with size and greyscale indicating their relative distance from the hoverfly (see ref [14] for more details). Some of the spheres had the same spatio-temporal characteristics as the target.

Cloud a greyscale background with a 2D power spectrum similar to that of typical natural scenes and a mean luminance of ~ 128 where luminance $\in [0, 255]$ [47] with a Michelson contrast of 100% (see ref [7] for more details).

Sinusoidal a vertical sinusoidal grating with an average wavelength of $7°$, drifting at $5\,\text{Hz}$, and a Michelson contrast of 25%.

For each background, four conditions were tested. (1) 'alone': the target moved across a homogeneous white (control for starfield) or grey (controls for cloud and sinusoidal) background; (2) 'stationary': the target moved over a non-moving background; (3) 'syn'-directional: the background moved in the same direction as the target; (4) 'contra'-directional: the background moved in the opposite direction to the target. The same stimuli shown to the hoverflies were also presented to the model as a sequence of images, each presented for $1\,\text{ms}$.

Fig 17. Target-background combinations. The three background stimuli used for both electrophysiology and simulations: (**A**) Starfield, (**B**) Cloud, (**C**) Sinusoidal. The target for the background in (**A**) was 15 pixels diameter black dots moving at 900 pixels/s. The targets for the backgrounds in (**B,C**) were 15 pixels side length black squares moving at 900 pixels/s. The targets traversed the background in the preferred direction of each TSDN – in this case, to the left. Note that the targets are not to scale.

Data Analysis and Statistics

We recorded from N=10 TSDNs (cloud) and N=6 TSDNs (sinusoidal) in 16 male hoverflies. We kept data from all TSDNs that showed a robust response to a target moving over a white background. We repeated this control throughout the recording and only kept data from neurons that responded consistently. We only kept data from experiments with a minimum of 12 repetitions. The data from repetitions within a neuron were converted to rates and averaged per condition. We normalised the responses to each neuron's own mean response to a target moving over a white or grey background.

To compare the TSDN spike trains with the output of our rate-based model, we convolved them with Gaussian kernels to obtain a Spike Density Function (SDF) [69]:

$$s(t) = \sum_i \kappa(t - t_i) \tag{1}$$

$$\kappa(t) = \frac{1}{\sigma\sqrt{2\pi}} \exp\left(-\frac{t^2}{2\sigma^2}\right) \tag{2}$$

where t_i are the times of individual spike and $\sigma = 20$ ms is the standard deviation of the Gaussian kernel κ.

Data analysis of electrophysiology data was performed in MATLAB. Throughout the paper, n refers to the number of repetitions within one neuron and N to the number of neurons. The sample size, type of test, and P value are indicated in the corresponding figure legends. For the cloud and sinusoidal electrophysiological recordings (Fig 7), paired t-tests or one-way ANOVAs, followed by Dunnett's post hoc test for multiple comparisons, were used (using Prism 10.4.1 for Mac OS X (GraphPad Software)). For the preceding optic flow (Fig 10; S1 Video) and dot density results (Fig 12; S2 Video), one-way ANOVA followed by two-sample t-tests with Bonferroni correction for multiple comparisons was used.

TSDN candidate circuit cost function ₇₀₀

In the electrophysiology experiments, the target elevation was varied slightly between repetitions to minimise habituation (Section Visual stimuli, Nicholas and Nordström [11]). At each target elevation, a single time-series produced by our circuit was compared against the repetition-averaged time series of spike rates obtained from our electrophysiological recordings (see section Data Analysis and Statistics) to give a root-mean-square error (RMSE). The RMSEs from each dimension of the electrophysiology recordings were averaged, i.e., over elevations (E), conditions (C), e.g., 'alone' or 'stationary', and neurons (N). Thus, the total RMSE ($RMSE_{total}$) that a circuit yields is expressed as:

$$RMSE_{total} = \frac{1}{NCE} \sum_{n=0}^{N} \sum_{c=0}^{C} \sum_{e=0}^{E} \underbrace{\sqrt{\frac{1}{T} \sum_{t=0}^{T} (y_{t,e,c,n}^{circuit} - y_{t,e,c,n}^{ephys})^2}}_{\text{RMSE per target elevation}} \qquad (3)$$

where $y^{circuit}$ is the deterministic circuit output and y^{ephys} is the repetition-averaged TSDN spike rates – both time-series. When fitting against the starfield background, the aim was to minimise the $RMSE_{total}$ to obtain the optimal circuit and LPTC coefficients (α, β, κ, η, g, γ and s) (Figure 16, Table 1). However, when testing the performance of the circuits against the cloud and sinusoidal backgrounds, we used the $RMSE_{total}$ for each circuit normalised by the $RMSE_{total}$ of the 'STMD only' circuit (Fig 5).

Data and code availability ₇₁₆

Electrophysiology data has been deposited on Figshare `https://figshare.com/s/c1d9631df02f4ea4637b`. The code is available on GitHub `https://github.com/anindyaghosh/TSDN_facilitation`.

Acknowledgments ₇₂₀

SN and KN thank Biomedical Engineering at SAHLN and the Botanic Gardens of Adelaide for their ongoing support.

References

1. Ogawa Y, Nicholas S, Thyselius M, Nowotny T, Knight JC, Nordstrom K. Neural responses to reconstructed target pursuits. bioRxiv. 2023; p. 2023–05.

2. Roth G. Visual behavior in salamanders. vol. 14. Springer Science & Business Media; 2012.

3. Zhu SI, Goodhill GJ. From perception to behavior: The neural circuits underlying prey hunting in larval zebrafish. Frontiers in Neural Circuits. 2023;17:1087993.

4. Combes S, Salcedo M, Pandit M, Iwasaki J. Capture success and efficiency of dragonflies pursuing different types of prey. Integrative and comparative biology. 2013;53(5):787–798.

5. Thyselius M, Ogawa Y, Leibbrandt R, Wardill TJ, Gonzalez-Bellido PT, Nordström K. Hoverfly (Eristalis tenax) pursuit of artificial targets. Journal of Experimental Biology. 2023;226(4):jeb244895.

6. Gonzalez-Bellido PT, Fabian ST, Nordström K. Target detection in insects: optical, neural and behavioral optimizations. Current opinion in neurobiology. 2016;41:122–128.

7. Nordström K, O'Carroll DC. Small object detection neurons in female hoverflies. Proceedings of the Royal Society B: Biological Sciences. 2006;273(1591):1211–1216.

8. Nordström K. Neural specializations for small target detection in insects. Current opinion in neurobiology. 2012;22(2):272–278.

9. Nicholas S, Leibbrandt R, Nordström K. Visual motion sensitivity in descending neurons in the hoverfly. Journal of Comparative Physiology A. 2020;206(2):149–163.

10. Nordström K, Barnett PD, O'Carroll DC. Insect detection of small targets moving in visual clutter. PLoS Biology. 2006;4(3):e54.

11. Nicholas S, Nordström K. Facilitation of neural responses to targets moving against optic flow. Proceedings of the National Academy of Sciences. 2021;118(38):e2024966118.

12. Collett T, Land M. How hoverflies compute interception courses. Journal of comparative physiology. 1978;125:191–204.

13. Collett T, Land M. Visual control of flight behaviour in the hoverfly Syritta pipiens L. Journal of comparative physiology. 1975;99:1–66.

14. Leibbrandt R, Nicholas S, Nordström K. The impulse response of optic flow-sensitive descending neurons to roll m-sequences. Journal of Experimental Biology. 2021;224(23):jeb242833.

15. Pokusaeva VO, Satapathy R, Symonova O, Joesch M. Bilateral interactions of optic-flow sensitive neurons coordinate course control in flies. Nature Communications. 2024;15(1):8830.

16. Haikala V, Joesch M, Borst A, Mauss AS. Optogenetic control of fly optomotor responses. Journal of Neuroscience. 2013;33(34):13927–13934.

17. Borst A. Models of motion detection. Nature neuroscience. 2000;3(11):1168–1168.

18. Tanaka R, Portugues R. On analogies in vertebrate and insect visual systems. Nature Reviews Neuroscience. 2025; p. 1–20.

19. Reichardt W, Poggio T, Hausen K. Figure-ground discrimination by relative movement in the visual system of the fly: Part II: Towards the neural circuitry. Biological Cybernetics. 1983;46:1–30.

20. Hassenstein B, Reichardt W. Systemtheoretische analyse der zeit-, reihenfolgen-und vorzeichenauswertung bei der bewegungsperzeption des rüsselkäfers chlorophanus. Zeitschrift für Naturforschung B. 1956;11(9-10):513–524.

21. Borst A, Haag J. Neural networks in the cockpit of the fly. Journal of Comparative Physiology A. 2002;188:419–437.

22. Adelson EH, Bergen JR. Spatiotemporal energy models for the perception of motion. Journal of the optical society of america A. 1985;2(2):284–299.

23. Torre V, Poggio T. A synaptic mechanism possibly underlying directional selectivity to motion. Proceedings of the Royal Society of London Series B Biological Sciences. 1978;202(1148):409–416.

24. Gruntman E, Romani S, Reiser MB. Simple integration of fast excitation and offset, delayed inhibition computes directional selectivity in Drosophila. Nature neuroscience. 2018;21(2):250–257.

25. Gruntman E, Romani S, Reiser MB. The computation of directional selectivity in the Drosophila OFF motion pathway. Elife. 2019;8:e50706.

26. Nordström K, Barnett PD, de Miguel IMM, Brinkworth RS, O'Carroll DC. Sexual dimorphism in the hoverfly motion vision pathway. Current Biology. 2008;18(9):661–667.

27. Wiederman SD, O'Carroll DC. Discrimination of features in natural scenes by a dragonfly neuron. Journal of Neuroscience. 2011;31(19):7141–7144.

28. Tanaka R, Clark DA. Object-displacement-sensitive visual neurons drive freezing in Drosophila. Current Biology. 2020;30(13):2532–2550.

29. Wiederman SD, Shoemaker PA, O'Carroll DC. A model for the detection of moving targets in visual clutter inspired by insect physiology. PLoS ONE. 2008;3(7):e2784.

30. Wiederman SD, Shoemaker PA, O'Carroll DC. Correlation between OFF and ON channels underlies dark target selectivity in an insect visual system. Journal of Neuroscience. 2013;33(32):13225–13232.

31. Egelhaaf M. On the neuronal basis of figure-ground discrimination by relative motion in the visual system of the fly: II. Figure-detection cells, a new class of visual interneurones. Biological Cybernetics. 1985;52(3):195–209.

32. Wiederman SD, O'Carroll DC. Biomimetic target detection: modeling 2nd order correlation of off and on channels. In: 2013 IEEE Symposium on Computational Intelligence for Multimedia, Signal and Vision Processing (CIMSIVP). IEEE; 2013. p. 16–21.

33. Wiederman SD, Brinkworth RS, O'Carroll DC. Bio-inspired target detection in natural scenes: optimal thresholds and ego-motion. In: Biosensing. vol. 7035. SPIE; 2008. p. 203–213.

34. Barnett PD, Nordström K, O'carroll DC. Retinotopic organization of small-field-target-detecting neurons in the insect visual system. Current Biology. 2007;17(7):569–578.

35. Bagheri ZM, Wiederman SD, Cazzolato BS, Grainger S, O'Carroll DC. Performance of an insect-inspired target tracker in natural conditions. Bioinspiration & biomimetics. 2017;12(2):025006.

36. Zhao A, Nern A, Koskela S, Dreher M, Erginkaya M, Laughland CW, et al. A comprehensive neuroanatomical survey of the Drosophila Lobula Plate Tangential Neurons with predictions for their optic flow sensitivity. bioRxiv. 2023;.

37. Kretzberg J, Warzecha AK, Egelhaaf M. Neural coding with graded membrane potential changes and spikes. Journal of computational neuroscience. 2001;11:153–164.

38. Maddess T, Laughlin SB. Adaptation of the motion-sensitive neuron H1 is generated locally and governed by contrast frequency. Proceedings of the Royal society of London Series B Biological sciences. 1985;225(1239):251–275.

39. Longden KD, Muzzu T, Cook DJ, Schultz SR, Krapp HG. Nutritional state modulates the neural processing of visual motion. Current Biology. 2014;24(8):890–895.

40. Borst A, Flanagin VL, Sompolinsky H. Adaptation without parameter change: dynamic gain control in motion detection. Proceedings of the National Academy of Sciences. 2005;102(17):6172–6176.

41. Saleem AB, Longden KD, Schwyn DA, Krapp HG, Schultz SR. Bimodal optomotor response to plaids in blowflies: mechanisms of component selectivity and evidence for pattern selectivity. Journal of Neuroscience. 2012;32(5):1634–1642.

42. Barnett PD, Nordström K, O'Carroll DC. Motion adaptation and the velocity coding of natural scenes. Current Biology. 2010;20(11):994–999.

43. Borst A, Groschner LN. How flies see motion. Annual review of neuroscience. 2023;46(1):17–37.

44. Nordström K, O'Carroll DC. The motion after-effect: local and global contributions to contrast sensitivity. Proceedings of the Royal Society B: Biological Sciences. 2009;276(1662):1545–1554.

45. Longden KD, Krapp HG. Octopaminergic modulation of temporal frequency coding in an identified optic flow-processing interneuron. Frontiers in Systems Neuroscience. 2010;4:153.

46. Warzecha AK, Egelhaaf M. Response latency of a motion-sensitive neuron in the fly visual system: dependence on stimulus parameters and physiological conditions. Vision research. 2000;40(21):2973–2983.

47. Nicholas S, Supple J, Leibbrandt R, Gonzalez-Bellido PT, Nordström K. Integration of small-and wide-field visual features in target-selective descending neurons of both predatory and nonpredatory dipterans. Journal of Neuroscience. 2018;38(50):10725–10733.

48. Gonzalez-Bellido PT, Peng H, Yang J, Georgopoulos AP, Olberg RM. Eight pairs of descending visual neurons in the dragonfly give wing motor centers accurate population vector of prey direction. Proceedings of the National Academy of Sciences. 2013;110(2):696–701.

49. O'Carroll DC, Barnett PD, Nordström K. Temporal and spatial adaptation of transient responses to local features. Frontiers in Neural Circuits. 2012;6:74.

50. Renart A, Machens CK. Variability in neural activity and behavior. Current opinion in neurobiology. 2014;25:211–220.

51. Hussaini MM, Evans BJ, O'Carroll DC, Wiederman SD. Temperature modulates the tuning properties of small target motion detector neurons in the dragonfly visual system. Current Biology. 2024;34(18):4332–4337.

52. Longden KD, Krapp HG. State-dependent performance of optic-flow processing interneurons. Journal of neurophysiology. 2009;102(6):3606–3618.

53. de Haan R, Lee YJ, Nordström K. Octopaminergic modulation of contrast sensitivity. Frontiers in Integrative Neuroscience. 2012;6:55.

54. Lin HT, Siwanowicz I, Leonardo A. Wireless recordings from dragonfly target detecting neurons during prey interception flight. bioRxiv. 2024; p. 2024–11.

55. Talley J, Pusdekar S, Feltenberger A, Ketner N, Evers J, Liu M, et al. Predictive saccades and decision making in the beetle-predating saffron robber fly. Current Biology. 2023;33(14):2912–2924.

56. Wardill TJ, Fabian ST, Pettigrew AC, Stavenga DG, Nordström K, Gonzalez-Bellido PT. A novel interception strategy in a miniature robber fly with extreme visual acuity. Current Biology. 2017;27(6):854–859.

57. Fabian ST, Sumner ME, Wardill TJ, Gonzalez-Bellido PT. Avoiding obstacles while intercepting a moving target: a miniature fly's solution. Journal of Experimental Biology. 2022;225(4):jeb243568.

58. Straw AD, Warrant EJ, O'Carroll DC. A bright zone in male hoverfly (Eristalis tenax) eyes and associated faster motion detection and increased contrast sensitivity. Journal of Experimental Biology. 2006;209(21):4339–4354.

59. Wellington W, Fitzpatrick SM. Territoriality in the drone fly, Eristalis tenax (Diptera: Syrphidae). The Canadian Entomologist. 1981;113(8):695–704.

60. Earland K, Lee M, Shaw P, Law J. Overlapping structures in sensory-motor mappings. PloS one. 2014;9(1):e84240.

61. Scott EK, Raabe T, Luo L. Structure of the vertical and horizontal system neurons of the lobula plate in Drosophila. Journal of Comparative Neurology. 2002;454(4):470–481.

62. Strother JA, Wu ST, Wong AM, Nern A, Rogers EM, Le JQ, et al. The emergence of directional selectivity in the visual motion pathway of Drosophila. Neuron. 2017;94(1):168–182.

63. Single S, Haag J, Borst A. Dendritic computation of direction selectivity and gain control in visual interneurons. Journal of Neuroscience. 1997;17(16):6023–6030.

64. Barlow H, Levick WR. The mechanism of directionally selective units in rabbit's retina. The Journal of physiology. 1965;178(3):477.

65. Eichner H, Joesch M, Schnell B, Reiff DF, Borst A. Internal structure of the fly elementary motion detector. Neuron. 2011;70(6):1155–1164.

66. Jaxon-Mitchell, RJAoukar. HoverflyLab/FlyFly: Version 4.2.3; 2025. Available from: https://doi.org/10.5281/zenodo.15044256.

67. Brainard DH, Vision S. The psychophysics toolbox. Spatial vision. 1997;10(4):433–436.

68. Pelli DG. The VideoToolbox software for visual psychophysics: transforming numbers into movies. Spatial vision. 1997;10(4):437–442.

69. Szűcs A. Applications of the spike density function in analysis of neuronal firing patterns. Journal of neuroscience methods. 1998;81(1-2):159–167.

List of legends

S1 Appendix.   Implementation details of the STMD model.

S1 Video.   Example preceding optic flow video. Video at 60 fps of an example stimulus used in the preceding optic flow experiments. The preceding optic flow is contra-directional (rightward) while the concurrent optic flow is stationary. The target moves leftward. The black ellipse indicates the boundary of the particular TSDN's receptive field at 50% of the maximum response. Data from [11].

S2 Video.   Example dot density video. Video at 60 fps of an example stimulus used in the dot density experiments. The starfield background has a dot density of 500 dots/m^3 and is moving contra-directional to the target (rightward). The target moves leftward. The black ellipse indicates the boundary of the particular TSDN's receptive field at 50% of the maximum response. Data from [11].