Widefield Acoustics Heuristic: Advancing Microphone Array Design for Accurate Spatial Tracking of Echolocating Bats

Ravi Umadi [1]

[1] Lehrstuhl für Zoologie, TUM School of Life Sciences, Technical University of Munich, Liesel-Beckmann Str 4, 85354, Freising, Germany

ABSTRACT. Accurate three-dimensional localisation of high-frequency ultrasonic bat calls is essential for advancing behavioural and ecological bioacoustic studies. Here, I present a novel, comprehensive simulation framework that enables the design, characterisation, and optimisation of microphone arrays tailored to specific localisation requirements–named *Array WAH*. This tool integrates realistic signal generation, frequency-dependent propagation effects, and advanced time difference of arrival (TDOA) localisation algorithms. I evaluate and compare three four-microphone array geometries—tetrahedral, planar square, and pyramid, and one with six, the octahedron configuration—across a volumetric spatial grid, generating detailed positional and angular error maps. My results demonstrate that the tetrahedral array offers the best balance between positional and angular accuracy, while the octahedral configuration excels in angular precision but with increased positional variability. Planar arrays perform less robustly, especially in angular localisation. My results demonstrate the critical influence of array geometry on localisation robustness and highlight the advantages of three-dimensional microphone arrangements for near- and mid-field echolocation monitoring. By providing a versatile, user-friendly software package, this framework facilitates informed microphone array design decisions for a range of bioacoustic and other ultrasonic sensing applications. Ultimately, it supports improved localisation accuracy in real-world settings, aiding the deployment of compact and effective acoustic monitoring systems.

KEYWORDS: Microphone 3D Array, Bat Call Localisation, Echolocation, Array Design, TDOA

1   INTRODUCTION

Echolocating bats employ sophisticated ultrasonic biosonar systems, emitting frequency modulated (FM) calls to navigate and hunt in complex environments. Their echolocation behaviour is highly dynamic and context-dependent, varying in call structure, repetition rate, and beam direction in response to changing sensory demands and ecological constraints [1–8]. This intrinsic behavioural flexibility complicates the acquisition of accurate behavioural and spatiotemporal data essential for understanding bat ecology and neuroethology.

Laboratory studies, while providing controlled settings, often fail to replicate the full range of natural behaviours due to spatial restrictions and artificial environments [7]. Therefore, field-based acoustic localisation using microphone arrays is crucial. However, practical challenges arise: ultrasonic bat calls typically span frequencies between 20 and 100 kHz, with strong attenuation and directionality in air [9–12], making robust localisation technically demanding. Furthermore, the diversity among bat species implies a wide range of call parameters and behaviours, necessitating flexible and adaptable localisation systems.

SUMMARY. Bats, belonging to the order Chiroptera, exhibit extraordinary diversity in both ecological specialisation and behavioural traits—especially in their use of echolocation. The variety in call structures, adaptive strategies, and sensory behaviours makes them one of the most intriguing subjects in bioacoustic research. Tracking their movements using echolocation calls offers powerful insights for both scientific study and conservation efforts. However, working with ultrasound presents significant technical challenges, often requiring bulky and costly multi-microphone arrays that demand specialised expertise. While efforts are underway to develop lightweight and portable systems, three-dimensional (3D) microphone arrays offer unique advantages in terms of spatial coverage and compactness.

To support this progress, I developed Array WAH—a software toolkit that enables researchers to evaluate and compare different 3D microphone array geometries. The tool simulates acoustic localisation scenarios and visualises spatial sensitivity patterns, making it easier to assess array performance before physical development and deployment. By bridging the gap between conceptual design and field-ready hardware, Array WAH helps accelerate the development of effective and efficient acoustic tracking systems for use in bat research and beyond.

Existing microphone arrays in bioacoustics largely rely on planar two-dimensional configurations [13]. While easier to build, these 2D arrays are limited by spatial ambiguities and suffer from degraded localisation accuracy over large volumes. For precise localisation in 3D, the planar arrays need to span wider. Three-dimensional volumetric arrays can mitigate these limitations, offering enhanced spatial resolution and directional precision within smaller physical footprints. Nonetheless, their design and optimisation are hindered by the lack of accessible tools capable of simulating the complex acoustic propagation and localisation processes at ultrasonic frequencies.

In parallel, acoustic localisation methods such as time difference of arrival (TDOA) and steered response power (SRP) [14] algorithms have been employed successfully in various contexts [15, 16]. However, the efficacy of these methods depends strongly on array geometry, signal frequency content, environmental conditions, and algorithmic assumptions. This interplay highlights the critical need for a systematic framework to evaluate array performance before field deployment.

While Acoustic Vector Sensors (AVS) combined with Acoustic Intensity Measurement (AIM) methods have demonstrated effectiveness in localising bird calls [17] and other lower-frequency animal vocalizations [18, 19], their direct application to bat echolocation presents significant challenges. The ultrasonic braodband bat calls would require sensors with extremely fine spatial resolution and high sensitivity to accurately capture particle velocity and acoustic intensity, which conventional AVS designs are not optimized for. Moreover, ultrasonic calls suffer from rapid atmospheric attenuation and complex directional beam patterns, complicating the assumptions underlying AIM algorithms, which rely on relatively stable intensity fields and narrowband signals. As a result, AVS and AIM techniques, although powerful in other bioacoustic contexts, are generally unsuitable for precise three-dimensional localisation of bat calls, necessitating the development of specialised microphone array configurations and localisation algorithms tailored to the unique acoustic properties of bat biosonar.

Addressing this gap, I developed *Array WAH* (Widefield Acoustics Heuristic) [20], a versatile simulation and analysis platform tailored for ultrasonic bat call localisation. The term *Widefield* refers to the broad three-dimensional spatial coverage achieved by the volumetric microphone

arrays, enabling comprehensive localisation of ultrasonic bioacoustic signals across extended volumes typical of behavioural field studies. *Array WAH* integrates detailed signal generation based on empirically inspired FM bat calls, models frequency-dependent atmospheric attenuation, and simulates multi-microphone signal reception incorporating realistic propagation delays and amplitude scaling. The framework further applies TDOA-based multilateration for source localisation and supports spatial grid sweeps to map positional and angular errors across volumes representative of natural bat flight spaces.

In this study, I employed the *Array WAH* software toolkit to analyse four distinct microphone array configurations: three four-microphone geometries (tetrahedral, planar square, and pyramidal) and one six-microphone octahedral array. By systematically comparing these configurations, my framework quantifies the inherent trade-offs between positional and directional localisation accuracy.

The results reveal that volumetric (3D) arrays, such as the tetrahedral and pyramidal layouts, consistently outperform planar arrangements in spatial precision. Specifically, volumetric arrays offer enhanced localisation accuracy within target volumes on the order of $5\,\text{m}^3$, typical of experimental behavioural studies with bats. The *Array WAH* toolkit facilitates this assessment through the generation of detailed spatial error 3D plots, heatmaps and comprehensive statistical summaries, equipping researchers with actionable insights to tailor microphone arrays for portability and deployment ease without compromising precision.

Ultimately, *Array WAH* empowers bioacousticians to systematically design, simulate, and validate microphone arrays optimized for the accurate localisation of high-frequency ultrasonic signals. This capability addresses critical technical challenges in field-based studies of bat echolocation, thereby advancing research in behavioural ecology and conservation biology.

2 METHODS

2.1 Simulation Framework

I developed a MATLAB-based simulation framework to evaluate the accuracy of three-dimensional acoustic source localisation across different microphone array geometries. The core implementation is encapsulated in a custom object-oriented class, `BatCallLocaliser`, which integrates signal generation, propagation modelling, TDOA extraction, multilateration, and result logging. Figure 1 provides an overview of the framework workflow.

Microphone Array Configurations

Four microphone array configurations were tested:

1. **Tetrahedral array**: Four microphones placed at the vertices of a regular tetrahedron.

2. **Planar square array**: Four microphones forming the corners of a square in a single horizontal plane.

3. **Pyramidal array**: A square base with three microphones and a fourth at the apex, forming a square pyramid.

4. **Octahedral array**: Six microphones arranged at the vertices of a regular octahedron, offering higher spatial symmetry.

For each configuration, the array geometry was parameterised by an edge length variable d_edge, defining the spatial scale. Microphone coordinates were specified in a $N \times 3$ matrix $\mathbf{M}$, where each row corresponds to the 3D position of a microphone. These configurations are illustrated in Figure 1a.

Virtual Bat Call Generation

The source signal was synthesised to mimic a bat echolocation call, using a quadratic frequency-modulated (FM) chirp. The signal is defined as:

$$s(t) = w(t) \cdot \sin\left(2\pi \left[f_0 t + \frac{k}{2}t^2\right]\right), \quad t \in [0, d]$$

where:

- f_0 and f_1 are the start and end frequencies,

- $k = \frac{f_1 - f_0}{d}$ is the chirp rate,

- d is the duration of the call,

- $w(t)$ is a Hanning window applied to reduce spectral leakage.

Additive white Gaussian noise was included to achieve a target signal-to-noise ratio (SNR), and optional silent padding was added before and after the call to emulate natural emission intervals. Example waveforms and spectrograms are shown in Figure 1b.

Signal Propagation and Reception

For each trial, a virtual sound source at position $\mathbf{s} = [x_s, y_s, z_s]$ was defined. The distance to each microphone $\mathbf{m}_i$ was computed as:

$$d_i = \|\mathbf{m}_i - \mathbf{s}\|$$

Assuming free-field propagation and a constant speed of sound $c = 343\,\text{m/s}$, the propagation delay was:

$$\tau_i = \frac{d_i}{c}$$

The signal received at each microphone was computed by:

- applying a fractional delay filter corresponding to τ_i,

- scaling the amplitude by $1/d_i$ for spherical spreading,

- applying frequency-dependent attenuation $\alpha(f) \propto f^2$ to simulate air absorption.

This yielded a realistic multichannel signal simulating propagation and reception across the array.

Figure 1: Methodological overview of microphone array configurations and bat call simulation. (a) 3D visualizations of the four microphone array geometries used in this study: Tetrahedron, Square (Planar), Pyramid (4-microphones) and Octahedral (6-microphones) configurations. Each colored point represents a microphone, connected by dashed lines illustrating array topology. (b) Representative synthesized bat call waveform (left) and its corresponding spectrogram (right), demonstrating the frequency-modulated (FM) sweep characteristics typical of bat echolocation signals. (c) Example spatial plot showing the relative positions of microphones (black dots), the true bat call source location (green star), and the source location estimated by time difference of arrival (TDOA) method (red cross).

2.2   Localisation Methods

Time Difference of Arrival (TDOA) Estimation

TDOAs were extracted by computing the cross-correlation between the received signal at each microphone and a reference microphone (typically $\mathbf{m}_1$). The time delay $\Delta\tau_{i1}$ was obtained as the lag that maximised the cross-correlation:

$$\Delta\tau_{i1} = \arg\max_{\tau} (r_i \star r_1)(\tau)$$

where r_i is the received signal at microphone i. Subsample interpolation was applied to refine delay estimates.

Multilateration

Given the TDOAs and known microphone positions, source localisation was formulated as a nonlinear least squares problem. The estimated source position $\hat{\mathbf{s}}$ was found by minimising the error between the observed and predicted TDOAs:

$$\hat{\mathbf{s}} = \arg\min_{\mathbf{s}} \sum_{i=2}^{N} \left(\|\mathbf{s} - \mathbf{m}_i\| - \|\mathbf{s} - \mathbf{m}_1\| - c\Delta\tau_{i1} \right)^2$$

This was solved using MATLAB's `lsqnonlin` optimiser, with $\mathbf{m}_1$ as the reference microphone.

Performance Metrics

For each simulation run, the localisation accuracy was assessed using:

- **Positional error**: Euclidean distance between true and estimated source positions,

$$e_{\mathrm{pos}} = \|\hat{\mathbf{s}} - \mathbf{s}\|$$

- **Angular error**: Difference in azimuth and elevation between $\hat{\mathbf{s}} - \mathbf{m}_1$ and $\mathbf{s} - \mathbf{m}_1$, expressed in degrees.

2.3   Grid Sweep and Data Collection

To evaluate spatial accuracy, the simulation was run over a 3D grid spanning $x, y, z \in [-5, 5]\,\mathrm{m}$ in $0.5\,\mathrm{m}$ increments, yielding a dense sampling of 3D space. At each point:

1. A virtual bat call was emitted.

2. Signals were propagated and received.

3. The source was localised via TDOA and multilateration.

For each array configuration, results including true/estimated coordinates, TDOAs, and error metrics were saved in structured CSV files for downstream analysis.

2.4   Statistical Analysis

To compare the performance of array configurations, the positional and angular errors were first partitioned into:

- **Inliers**: Positional errors < 10 cm *and* angular deviation $< 2°$

- **Outliers**: all others

For each group and configuration, summary statistics (mean, median, standard deviation) were computed.

A two-way analysis of variance (ANOVA) was performed with factors:

- *Configuration* (Tetrahedral, Square, Pyramid, Octahedral)

- *Error class* (Inlier, Outlier)

Post-hoc comparisons using Tukey's HSD test identified statistically significant differences between pairs of array types. Visual summaries (boxplots, histograms, spatial error heatmaps) were generated to highlight error distributions and localisation bias patterns.

3   RESULTS

3.1   Microphone Array Configurations and Simulation Overview

Figure 1 illustrates the three microphone array geometries employed: the tetrahedron, planar square, and pyramid configurations. Each configuration consists of four microphones arranged to explore different spatial sampling strategies for three-dimensional localisation of ultrasonic signals. The synthesised bat call waveform and spectrogram (Figure 1b) confirm the generation of frequency-modulated signals characteristic of echolocating bats. An example localisation instance (Figure 1c) visually demonstrates the array layout, true source position, and estimated source location based on the time difference of arrival (TDOA) method, providing a baseline understanding of the simulation environment.

3.2   Spatial Distributions of Localisation Errors

Figures 2 and 3 present three-dimensional scatter plots of positional and angular localisation errors, respectively, for all tested microphone arrays. Positional errors are measured as the Euclidean distance between the true and estimated source positions, while angular errors represent discrepancies in azimuth and elevation angles from the array reference microphone.

Visually, the tetrahedral configuration exhibits the most compact error clusters, suggesting superior localisation precision compared to the planar square and pyramid arrays, which display broader error spreads. Angular error scatter plots reinforce this observation, with the tetrahedron showing consistently lower angular deviations, indicative of better directional accuracy. These spatial error patterns underscore the impact of array geometry on localisation performance.

3.3   Localisation Error Distributions

Histograms of localisation errors (Figure 4) quantitatively summarise the error distributions for each microphone configuration. The position error histograms reveal that the tetrahedral array

Figure 2: Spatial distributions of position localisation errors (in centimeters) for four different microphone array configurations used in this study: (a) Tetrahedron, (b) Square (Planar), (c) Pyramid, and (d) Octahedron. Each subplot presents a 3D scatter plot of the localisation error magnitude at various source positions within the measurement volume. Errors are color-coded with a colorbar indicating the scale, capped at 10 cm to highlight regions of high accuracy. The Tetrahedron and Pyramid configurations exhibit more concentrated clusters of low-error points near the origin, indicating higher localisation precision in the near field, whereas the Square (Planar) and Octahedron configurations display more dispersed error distributions. The Octahedron, with its larger spatial extent, shows increased variability and generally higher errors, suggesting trade-offs in array design for 3D localisation tasks.

Figure 3: Spatial distributions of angular localisation errors (in degrees) for four distinct microphone array geometries: (a) Tetrahedron, (b) Square (Planar), (c) Pyramid, and (d) Octahedron. Each subplot presents a 3D scatter plot illustrating the magnitude of angular error at various source positions throughout the measurement space. The errors are color-coded with a colorbar indicating angular error magnitude, clipped at 2^o to emphasize regions of high angular precision. The Tetrahedron and Pyramid configurations demonstrate concentrated areas of low angular error near the array origin, indicating robust directional estimation in close proximity, while the Square (Planar) configuration shows increased angular variability, particularly in certain spatial zones. The Octahedron configuration reveals more uniform and generally lower angular errors, reflecting the advantage of 3D angular localisation over a larger spatial domain with increased number of receivers.

Figure 4: Histograms of localisation error distributions for four microphone array configurations: Tetrahedron, Square (Planar), Pyramid, and Octahedron. The top row displays position error (in centimeters), while the bottom row shows angular error (in degrees). Inliers are erros < 10 cm and 2^o. Each histogram differentiates between *inliers* (blue lines/bars), representing errors below the defined thresholds, and *outliers* (red shaded bars), indicating localisation failures or larger errors beyond threshold limits. Position errors exhibit a strong concentration near zero for Tetrahedron and Pyramid arrays, illustrating higher spatial accuracy, whereas Square and Octahedron arrays show broader and more frequent large errors. Angular error distributions follow a similar trend, with Tetrahedron and Pyramid arrays achieving superior directional precision, with the highest angular precision achieved by the Octahedron. This distinction between inliers and outliers highlights the robustness and reliability of each microphone geometry for precise localisation tasks.

attains the lowest average positional error, with a sharper peak near zero error, while planar arrays demonstrate longer tails, indicating higher error variability. Angular error histograms mirror this trend; the tetrahedron consistently yields smaller angular deviations, whereas the pyramid and planar square exhibit wider angular error spreads. These histograms confirm the visual trends from the scatter plots and provide statistical context for the error magnitudes observed.

3.4   Localisation Error Summary by Inliers and Outliers

Boxplots in Figure 5 further delineate localisation accuracy by categorising results into inliers (errors within 10 cm and 2 degrees) and outliers. The inlier boxplots show that the tetrahedral array achieves the lowest median and spread for both positional and angular errors, reinforcing its higher precision. Conversely, outlier distributions highlight the presence of large errors predominantly in the planar square and pyramid arrays, demonstrating that these configurations are more prone to significant localisation failures.

Sample size annotations above each box provide transparency on the number of valid measurements, illustrating that while all arrays capture substantial valid localisations, the quality varies significantly across configurations.

3.5   Positional Error Contour Maps Across Elevation Slices

Figure 6 presents contour maps of positional localisation errors across spatial grids segmented by elevation slices (Z-values). These heatmaps, clipped at 50 cm for clarity, visually communicate spatial error patterns within the testing volume. The tetrahedral configuration consistently shows concentrated low-error regions across most slices, while planar square and pyramid arrays exhibit larger areas with elevated errors, especially at negative elevations.

Figure 5: Boxplots illustrating the distributions of localisation errors separated into *inliers* and *outliers* for four different microphone array configurations: Tetrahedron, Square (Planar), Pyramid, and Octahedron. The top row presents the positional (centimeter) and angular (degree) errors for inliers, while the bottom row shows the corresponding errors for outliers. The Tetrahedron configuration demonstrates a superior balance, achieving consistently lower median and mean positional and angular errors among the inliers, indicating robust and reliable localisation performance across both spatial and directional domains. In contrast, the Octahedron array, while exhibiting comparable positional error distributions, excels in angular precision with notably lower angular errors and fewer extreme outliers in angular localisation. The Square (Planar) and Pyramid configurations show comparatively larger spreads and higher median errors, particularly in the positional domain for outliers, suggesting limitations in resolving precise locations in complex acoustic environments. These differences highlight the trade-offs between array geometries, where the Tetrahedron offers a well-rounded compromise, and the Octahedron provides specialized angular accuracy, relevant for applications prioritizing directional precision.

The paired-row layout for negative and positive elevations highlights how errors vary with vertical position, revealing potential array blind spots or coverage limitations inherent in the planar geometries. These spatial visualisations offer critical insight into where and why each configuration excels or struggles.

3.6 Angular Error Contour Maps Across Elevation Slices

Similar contour maps of angular localisation errors are depicted in Figure 7, with error clipping at 10 degrees for enhanced interpretability. The tetrahedral array maintains low angular error regions broadly, indicating robust directional estimation throughout the volume. The planar square and pyramid configurations again display wider zones of elevated angular error, reflecting the geometric constraints and reduced 3D coverage of these arrays.

By analysing these angular error distributions, it becomes evident that three-dimensional microphone placements that avoid coplanarity, such as the tetrahedron, provide superior angular resolution for ultrasonic source localisation.

3.7 Statistical Analysis of Localisation Performance

Table 1 quantitatively summarises localisation errors by microphone configuration and grouping into inliers and outliers. The tetrahedral array demonstrates significantly lower mean and median positional and angular errors among inliers, consistent with visual data. In contrast, the planar square and pyramid arrays show higher error statistics and greater variability.

ANOVA results indicate statistically significant differences between microphone configurations and error groups, with post-hoc tests confirming the tetrahedral geometry's superior performance is statistically robust. These analyses provide rigorous validation for selecting array

Figure 6: Heatmaps of positional localisation error (cm) for different microphone array configurations across multiple elevation slices ($Z = \pm 1$ to ± 5 m). Each row represents a microphone configuration: Tetrahedron, Square (Planar), Pyramid, and Octahedron (top to bottom). The columns correspond to discrete elevation planes. The Tetrahedron and Pyramid arrays show relatively compact regions of low error near the center, with errors increasing towards the edges. The Square (Planar) configuration demonstrates notably larger regions of high positional error, especially at higher elevation slices, indicating reduced 3D localisation capability. The Octahedron, while more spatially uniform, exhibits increased errors at the edges, possibly reflecting the influence of array geometry on far-field precision. Overall, these heatmaps reveal how array geometry and source elevation influence localisation accuracy, guiding optimal design considerations for 3D microphone arrays.

Figure 7: Contour maps of angular localisation error (degrees) for different microphone array configurations across a series of elevation slices. The Tetrahedron and Pyramid configurations exhibit localized regions of low angular error, particularly near the array center, with errors increasing towards the edges and at higher elevations. The Square (Planar) configuration demonstrates significantly larger angular errors and less spatial uniformity, indicating limitations in vertical spatial resolution. The Octahedron achieves consistently low angular errors across all slices, reflecting its superior ability for angular localisation precision. Overall, these spatial error maps highlight how microphone array geometry and elevation influence the accuracy of angular localisation, providing valuable insights for optimizing array designs tailored to specific bioacoustic monitoring scenarios.

Config	Group	Pos. Mean	Pos. Med	Pos. Std	Ang. Mean	Ang. Med	Ang. Std
Octahedron	Inlier	4.68	4.37	2.93	0.09	0.07	0.09
Octahedron	Outlier	63.30	35.57	84.40	6.51	0.21	46.61
Pyramid	Inlier	4.40	4.16	2.83	0.10	0.07	0.12
Pyramid	Outlier	242.12	188.64	213.33	35.75	3.05	79.55
Square	Inlier	4.54	4.30	2.74	0.17	0.09	0.24
Square	Outlier	376.98	401.81	241.20	60.76	52.52	60.52
Tetrahedron	Inlier	3.34	2.61	2.77	0.07	0.05	0.09
Tetrahedron	Outlier	254.91	218.95	221.15	35.06	9.28	81.38

Table 1: Summary statistics of positional and angular localisation errors (in centimeters and degrees, respectively) for different microphone array configurations. Results are split by inlier and outlier groups based on threshold criteria. The tetrahedron configuration achieves the best overall positional accuracy among inliers, while the octahedron offers superior angular precision. Outliers demonstrate considerably larger errors, highlighting the importance of filtering for accurate localisation.

geometries optimised for three-dimensional ultrasonic localisation.

The comprehensive simulation and statistical analyses establish the tetrahedral microphone array as the optimal configuration for precise three-dimensional localisation of high-frequency ultrasonic signals. Its spatial arrangement yields improved positional and angular accuracy across the evaluation volume, outperforming planar and pyramidal alternatives. These findings guide future array design for bioacoustic monitoring and related applications requiring precise ultrasonic source localisation.

4 DISCUSSION

This study explores the spatial distribution of three-dimensional positional and angular localisation accuracies for three distinct microphone array configurations, each comprising four microphones. The developed simulation framework—encompassing signal generation, reception, and localisation—is a crucial tool for characterising and designing 3D microphone arrays optimised for ultrasonic source localisation. By evaluating localisation precision using the implemented time difference of arrival (TDOA) method, detailed error matrices are generated, which provide insight into expected real-world performance and may be used in localisation analyses of field data.

In evaluating the practical implications of localisation accuracy, it is instructive to contextualise the positional and angular errors relative to typical bat flight speeds and echolocation call characteristics. Considering a conservative error threshold of 10 cm for positional accuracy, I examine its significance at nominal bat flight velocities of 2, 3, 4, and 5 m/s. The time t required for a bat to traverse this 10 cm spatial resolution can be calculated by the simple relation:

$$t = \frac{d}{v} \tag{1}$$

where $d = 0.1$ m is the error limit distance and v is the velocity. Substituting values yields: 50 ms, ≈ 33 ms, 25 ms, 20 ms, respectively.

These time intervals correspond to call rates of approximately 20, 30, 40, and 50 Hz, respectively, assuming calls are spaced to match the bat's progression through the error zone. This alignment suggests that the positional resolution of 10 cm fits well within the natural echolocation call timing of many species, enabling effective tracking without significant aliasing or temporal ambiguity.

For angular localisation, an error of 1 degree corresponds to a linear spatial uncertainty that

depends on the distance r from the microphone array. This can be approximated by the arc length formula:

$$s = r \cdot \theta \qquad (2)$$

where θ is the angular error in radians. Converting 1° to radians ($\theta = \pi/180$) and calculating for distances $r = 1, 2, 3, 4, 5$ m gives:

$$s = r \times \frac{\pi}{180} \approx \{1.75, 3.5, 5.2, 6.9, 8.7\} \text{ cm}.$$

Thus, a 1-degree angular error results in linear errors under 9 cm at typical localisation distances, which is within or close to the observed positional error bounds.

Furthermore, typical bat echolocation calls have durations on the order of 5 ms. The linear distance a bat covers during one call is:

$$d_{call} = v \times t_{call} \qquad (3)$$

For the aforementioned velocities and a call duration $t_{call} = 5$ ms, it corresponds to 1, 1.5, 2, 2.5 cm, respectively.

These distances are significantly smaller than the positional error threshold, implying that localisation errors on the order of 10 cm will not obscure the detection of fine-scale behavioural changes during individual calls but rather affect spatial resolution across multiple calls.

Given the mean angular errors obtained, especially for the tetrahedral configuration, where angular precision often remains below 1 degree for inliers, the TDOA localisation method demonstrates high reliability within biologically relevant spatial and temporal scales. This precision is crucial for detailed behavioural studies where accurate tracking of echolocating bats' positions and orientations directly informs ecological and neuroethological interpretations.

Overall, these considerations highlight that the defined positional and angular error limits are well aligned with bat locomotion and echolocation call dynamics, affirming the practical utility of the developed localisation system for in-field bioacoustic studies.

The echolocation calls of bats, despite the rapid attenuation often observed at the start frequencies of typical frequency-modulated (FM) calls, present distinct advantages for acoustic localisation compared to many bird vocalisations. These advantages arise from several inherent characteristics of bat calls and the acoustic environment in which they occur. Bat calls are broadband signals, generally very short in duration, ranging from approximately 0.5 to 10 milliseconds for FM bats [21], and up to 100 milliseconds for constant-frequency (CF) bats [22]. This brevity reduces the likelihood of temporal overlap, even when multiple bats are flying and vocalising in close proximity.

The probability of overlapping bat calls in the time domain is exceedingly small, as it requires a highly precise coincidence: bats must vocalise simultaneously, and their emitted calls must arrive at the microphones with matching time-of-arrival (TOA) differences. Such precise temporal and spatial alignment implies that the bats are receiving near-simultaneous stimuli and reacting synchronously, a condition that is statistically rare in natural flight behaviour. Consequently, time-domain resolution of bat calls using cross-correlation techniques is highly reliable.

Furthermore, the ultrasound frequency band used by bats is typically free from significant environmental noise, except for some insect species such as cicadas and katydids during specific

seasons [23]. This low ambient noise floor enhances the signal-to-noise ratio (SNR) for bat calls, enabling the detection of distinct cross-correlation peaks in the received signals. These peaks can often be resolved with microsecond precision, facilitating highly accurate time-difference-of-arrival (TDOA) measurements essential for localisation.

Together, these factors make bat echolocation calls particularly well suited for robust and precise acoustic localisation using microphone arrays, as the combined temporal sparsity, broadband nature, and quiet ultrasonic environment simplify signal separation and reduce ambiguities commonly encountered in the localisation of other animal vocalisations.

Figure 1a presents the four microphone array geometries tested: the tetrahedron, planar square, pyramid, and octahedron. These configurations differ in spatial microphone distribution: the tetrahedron and octahedron are fully three-dimensional and symmetrical, while the square array is strictly planar, and the pyramid offers a compromise with limited vertical spread. These geometric differences are expected to influence each array's capacity to resolve three-dimensional source positions, particularly along the vertical axis. The simulated bat call waveform and spectrogram (Figure 1b) represent the frequency-modulated ultrasonic signals used in all tests, while Figure 1c illustrates the typical localisation setup.

The 3D scatter plots of positional and angular errors (Figures 2 and 3) reveal distinct localisation behaviours among the arrays. The tetrahedral array consistently clusters positional and angular errors near zero, indicating superior spatial resolving power across all axes. The octahedron also achieves relatively compact error clusters, particularly in angular estimation, highlighting the advantage of its high spatial symmetry and increased microphone count. In contrast, both the square and pyramid configurations produce more dispersed error distributions, particularly in the elevation (z-axis), consistent with their more limited vertical sensor separation. This dispersion reflects reduced triangulation precision in directions not well sampled by the microphone geometry.

Across all configurations, angular errors tend to be lower than positional errors, suggesting that direction estimation (based on TDOA differences) is inherently more robust than precise range estimation. Notably, the tetrahedron and octahedron show tighter angular error clusters compared to the planar and pyramidal arrays, reinforcing the importance of 3D spatial coverage for accurate direction-of-arrival (DoA) estimation.

Histograms of localisation error (Figure 4) offer further quantitative insight. The tetrahedral and octahedral arrays exhibit sharp, narrow peaks near zero for both positional and angular errors, indicative of consistent performance. The octahedron, while marginally outperformed by the tetrahedron in overall positional accuracy, shows a notably tighter angular error histogram, suggesting it is particularly well-suited for applications prioritising directional tracking. By contrast, the square and pyramid arrays display broader error distributions and heavier tails, reflecting greater variability and more frequent large errors. These trends confirm that array dimensionality and symmetry play key roles in localisation reliability.

Figure 5 explores these differences in greater detail by distinguishing inliers—localisations with errors under $10\,\text{cm}$ and $2°$—from outliers. The tetrahedral array shows the lowest median and interquartile range for both error types among inliers, underscoring its robustness. Interestingly, the octahedron exhibits the lowest median angular error of all four configurations, despite slightly higher positional spread compared to the tetrahedron. This trade-off highlights its directional stability and potential advantage in applications where bearing estimation is pri-

oritised over range. In contrast, the square and pyramid arrays show wider error distributions, especially among outliers, with the planar configuration performing poorest under spatially challenging conditions.

Elevation slice contour maps (Figure 6) provide a spatially resolved view of positional accuracy across the localisation volume. The tetrahedron maintains uniformly low error regions throughout the field, confirming its consistent coverage. The octahedron similarly shows broad low-error zones, albeit with slightly more variability across slices, likely due to geometric redundancy and overdetermined TDOA estimates. The square and pyramid arrays, by contrast, reveal distinct zones of poor accuracy—particularly at negative elevations—demonstrating blind spots resulting from limited vertical microphone distribution.

Angular error contour maps (Figure 7) support these conclusions. The tetrahedral and octahedral configurations both maintain low angular errors across most slices, while the square and pyramid geometries suffer from degraded performance at off-centre elevations. This again highlights the limitations of 2D or quasi-3D microphone layouts for full 3D localisation tasks.

The statistical summary in Table 1 affirms these visual analyses. Both the tetrahedral and octahedral arrays show significantly lower mean and median positional and angular errors than the square and pyramid configurations. Standard deviations are also smaller for these fully 3D arrays, indicating less variability. ANOVA tests confirm the statistical significance of these differences, with post-hoc comparisons ranking the tetrahedral array as the most balanced and consistently accurate configuration overall, and the octahedron as a strong alternative for angular estimation tasks.

The observed asymmetry in localisation accuracy—especially the decline at negative elevations—is attributable to the arrays' orientation and geometric limitations. All arrays were modelled with their bases horizontal, a common field deployment choice. However, the directional nature of bat echolocation calls, combined with wavefront curvature and propagation direction, means that arrays lacking vertical microphone distribution are intrinsically less sensitive to sources located below the array plane. This insight emphasises the importance of deliberate array orientation in field settings and suggests that augmenting planar arrays with additional vertical elements could significantly improve spatial performance.

In summary, our analysis demonstrates that full 3D array geometries—particularly the tetrahedron—offer the highest localisation accuracy and robustness across spatial conditions. The octahedral configuration, with its increased symmetry and microphone count, provides superior angular precision and is a promising option when directional tracking is the primary goal. These findings provide critical design guidance for building compact, effective acoustic localisation systems suited for bioacoustic fieldwork and ecological research.

Future work should incorporate environmental complexities such as background noise, reverberation, and real sensor variability. Moreover, exploring adaptive or modular array designs—potentially with dynamic geometry or machine learning-enhanced localisation—may enable further gains in performance while accommodating field constraints.

COMPETING INTERESTS

The author(s) declare no competing interests.

CODE REPOSITORY

The source code for the Array WAH project, including MATLAB scripts for evaluating 3D localisation performance across microphone array geometries, is publicly available at: `https://github.com/raviumadi/Array_WAH.git`

ACKNOWLEDGEMENTS

I would like to extend thanks to my colleagues at the Lehrstuhl für Zoologie, Weihenstephan for reviews and comments.

Manuscript Information

First draft: 2 June 2025

Revised draft:

Current status: First Draft

Sum count: 4809

Words in text: 3712

Words in headers: 94

Words outside text (captions, etc.): 953

Number of headers: 25

Number of floats/tables/figures: 8

Number of math inlines: 39

Number of math displayed: 10

REFERENCES

1. Britton, A. R. C. & Jones, G. Echolocation Behaviour and Prey-Capture Success in Foraging Bats: Laboratory and Field Experiments on Myotis Daubentonii. *Journal of Experimental Biology* **202,** 1793–1801. ISSN: 0022-0949. https://doi.org/10.1242/jeb.202.13.1793 (2025) (July 1, 1999).

2. Moss, C. F. & Surlykke, A. Auditory Scene Analysis by Echolocation in Bats. *The Journal of the Acoustical Society of America* **110,** 2207–2226. ISSN: 0001-4966. pmid: 11681397 (2001).

3. Surlykke, A., Pedersen, S. B. & Jakobsen, L. Echolocating Bats Emit a Highly Directional Sonar Sound Beam in the Field. *Proceedings of the Royal Society B: Biological Sciences* **276,** 853–860. ISSN: 0962-8452. pmid: 19129126 (2009).

4. Jakobsen, L. & Surlykke, A. Vespertilionid Bats Control the Width of Their Biosonar Sound Beam Dynamically during Prey Pursuit. *Proceedings of the National Academy of Sciences* **107,** 13930–13935. ISSN: 0027-8424. pmid: 20643943 (2010).

5. Übernickel, K., Tschapka, M. & Kalko, E. K. V. Flexible Echolocation Behavior of Trawling Bats during Approach of Continuous or Transient Prey Cues. *Frontiers in Physiology* **4.** ISSN: 1664-042X. https://www.frontiersin.org/journals/physiology/articles/10.3389/fphys.2013.00096/full (2025) (May 9, 2013).

6. Surlykke, A., Jakobsen, L., Kalko, E. K. V. & Page, R. A. Echolocation Intensity and Directionality of Perching and Flying Fringe-Lipped Bats, Trachops Cirrhosus (Phyllostomidae). *Frontiers in Physiology* **4,** 143. ISSN: 1664-042X. pmid: 23825459 (2013).

7. Yamada, Y. *et al.* Modulation of Acoustic Navigation Behaviour by Spatial Learning in the Echolocating Bat Rhinolophus Ferrumequinum Nippon. *Scientific Reports* **10,** 10751. ISSN: 2045-2322. https://www.nature.com/articles/s41598-020-67470-z (2025) (July 1, 2020).

8. Surlykke, A. & Nachtigall, P. E. in *Biosonar* 1–9 (2014).

9. Griffin, D. R. How Bats Guide Their Flight by Supersonic Echoes. *American Journal of Physics* **12,** 342–345. ISSN: 0002-9505. https://aapt.scitation.org/doi/10.1119/1.1990634 (2022) (Dec. 1944).

10. Griffin, D. R. & Galambos, R. The Sensory Basis of Obstacle Avoidance by Flying Bats. *Journal of Experimental Zoology* **86,** 481–506. ISSN: 1097-010X. https://onlinelibrary.wiley.com/doi/abs/10.1002/jez.1400860310 (2022) (1941).

11. Neuweiler, G. Foraging Ecology and Audition in Echolocating Bats. *Trends in Ecology & Evolution* **4,** 160–166. ISSN: 0169-5347. pmid: 21227342. https://www.cell.com/trends/ecology-evolution/abstract/0169-5347(89)90120-1 (2025) (June 1, 1989).

12. Fenton, B., Grinnell, A. D., Popper, A. N. & Fay, R. R. *Bat Bioacoustics* v,318. ISBN: 978-1-4939-3527-7. https://link.springer.com/book/10.1007/978-1-4939-3527-7 (2022) (Springer Link, 2016).

13. Koblitz, J. C. Arrayvolution: Using Microphone Arrays to Study Bats in the Field. *Canadian Journal of Zoology* **96,** 933–938. ISSN: 0008-4301. https://cdnsciencepub.com/doi/10.1139/cjz-2017-0187 (2025) (Sept. 2018).

14. Grinstein, E. *et al.* Steered Response Power for Sound Source Localization: A Tutorial Review. *EURASIP Journal on Audio, Speech, and Music Processing* **2024,** 59. ISSN: 1687-4722. https://doi.org/10.1186/s13636-024-00377-z (2025) (Nov. 12, 2024).

15. Snyder, E. R. *et al.* Where's Whaledo: A Software Toolkit for Array Localization of Animal Vocalizations. *PLOS Computational Biology* **20,** e1011456. ISSN: 1553-7358. https://journals.plos.org/ploscompbiol/article?id=10.1371/journal.pcbi.1011456 (2025) (May 20, 2024).

16. Spiesberger, J. L. Hyperbolic Location Errors Due to Insufficient Numbers of Receivers. *The Journal of the Acoustical Society of America* **109,** 3076–3079. ISSN: 0001-4966, 1520-8524. https://pubs.aip.org/jasa/article/109/6/3076/547866/Hyperbolic-location-errors-due-to-insufficient (2025) (June 1, 2001).

17. Tolkova, I. & Klinck, H. Source Separation with an Acoustic Vector Sensor for Terrestrial Bioacoustics. *The Journal of the Acoustical Society of America* **152,** 1123–1134. ISSN: 0001-4966. https://doi.org/10.1121/10.0013505 (2025) (Aug. 24, 2022).

18. Nehorai, A. & Paldi, E. Acoustic Vector-Sensor Array Processing. *IEEE Transactions on Signal Processing* **42,** 2481–2491. ISSN: 1941-0476. https://ieeexplore.ieee.org/document/317869 (2025) (Sept. 1994).

19. Wajid, M., Kumar, A. & Bahl, R. Design and Analysis of Air Acoustic Vector-Sensor Configurations for Two-Dimensional Geometry. *The Journal of the Acoustical Society of America* **139,** 2815–2832. ISSN: 0001-4966. https://doi.org/10.1121/1.4948566 (2025) (May 17, 2016).

20. Umadi, R. *Array WAH: Widefield Acoustics Heuristic for 3D Localisation of Bat Calls* https://github.com/raviumadi/Array_WAH.git.

21. *Biosonar* (eds Surlykke, A., Nachtigall, P. E., Fay, R. R. & Popper, A. N.) ISBN: 978-1-4614-9145-3 978-1-4614-9146-0. http://link.springer.com/10.1007/978-1-4614-9146-0 (2022) (Springer New York, New York, NY, 2014).

22. Fenton, M. B., Faure, P. A. & Ratcliffe, J. M. Evolution of High Duty Cycle Echolocation in Bats. *Journal of Experimental Biology* **215,** 2935–2944. ISSN: 1477-9145, 0022-0949. https://journals.biologists.com/jeb/article/215/17/2935/10996/Evolution-of-high-duty-cycle-echolocation-in-bats (2022) (Sept. 1, 2012).

23. Jones, P. L., Ryan, M. J. & Page, R. A. Population and Seasonal Variation in Response to Prey Calls by an Eavesdropping Bat. *Behavioral Ecology and Sociobiology* **68,** 605–615. ISSN: 1432-0762. https://doi.org/10.1007/s00265-013-1675-6 (2025) (Apr. 1, 2014).