Slow Electromechanical Interference Links Division Geometry, Differentiation Bias, and Senescence-like Arrest

Alfonso De Miguel Bueno

Independent Researcher, Madrid, Spain
ORCID: 0009-0000-5420-3805
ademiguelbueno@gmail.com

Abstract

This work develops a biophysical theory in which a bioelectric field $V(x,t)$ and a cortical stress field $\sigma(x,t)$ are weakly and reciprocally coupled via an overdamped electromechanical coupler. We show that interference between two fast latent modes produces a measurable slow beat f_{slow} that acts as a tissue-level clock. By sampling the dynamics at "neutral moments"—recurring instants of phase symmetry—we derive a reduced even circle map in which healthy homeostasis corresponds to locking within the specific 2/21 Arnold tongue.

We then introduce a coarse-grained dual-field algebra that collapses the continuum description into three effective blocks (Γ, a, b) capturing net electromechanical gain and dissipation. In this algebraic picture, ionic and rheological perturbations are represented as smooth deformations of the parametrization space (Γ, a, b), while the clock variables $(\Omega, f_{\text{slow}}, K_2)$ provide experimentally accessible coordinates on those deformations. This construction offers a concrete bridge between molecular-scale regulation and tissue-level mechanics, connecting subcellular control to the emergent seconds–minutes slow clock that constrains division geometry.

The theory yields three falsifiable predictions. (P1) Homeostatic epithelia exhibit a narrow shared slow-band peak in voltage and stress with high coherence. (P2) The effective forcing and coupling (Ω, K_2), derived from physical parameters without integer tuning, reside within the 2/21 tongue while avoiding broad low-order resonances. (P3) A weak, frequency-specific drive at f_{slow} (phase-targeted entrainment) selectively increases coherence and reduces spindle-angle dispersion in unlocked states, providing a physical basis for bioelectric modulation of regenerative dynamics.

Ultimately, this framework treats cancer-like instability and senescence-like arrest not as independent pathologies, but as opposite failures of navigation in a single underlying electromechanical cycle, from persistent unlocking to rigid oversynchronization.

Keywords: Tissue electromechanics, bioelectricity, cortical tension, cell division, cellular senescence, phase locking, Arnold tongues, epithelial organoids, even circle map, phase-targeted entrainment, electromechanical coherence, spindle orientation, homeostasis.

Highlights

- Proposes an overdamped double-oscillator model of tissue electromechanics in which two fast latent modes generate a slow beat (f_slow).

- Links the slow beat to an even circle map via neutral moments, identifying a specific 2/21 Arnold tongue that governs stable spindle orientation.

- Introduces a quantitative dual-field algebra in which ionic (pump-like) and rheological (stiffness-like) perturbations act as deformations of coarse-grained blocks (Γ, a, b), predicting matched shifts in Ω and f_slow.

- Relates the slow beat to capture kinetics T_lock, linking fast carrier interference to mitotic (minute-scale) timing through progressive synchronization.

- Models "proliferative unlocking" and "senescent overlock" as opposite dynamical failures of the dual-field clock (drift vs. rigidity), providing a unified view of cancer instability and aging.

- Validates a protocol for phase-targeted entrainment, predicting that a weak drive at f_slow selectively recovers coherence and reduces spindle-angle dispersion in unlocked states.

Contents

1 Introduction

Biological tissues exhibit coupled electrical and mechanical dynamics. Bioelectric potentials shape patterning, growth, and large-scale morphogenesis, while cortical tension and poroelastic stresses govern force transmission, division geometry, and tissue-scale mechanics [3, 5, 6, 8]. Controlled bioelectric cues can actively reshape tissues *in vivo* and *in vitro*, and multicellular responses to electrophysiological perturbations can be captured quantitatively by bioelectrical models [3, 4, 5]. Here we treat these two sectors explicitly as fields: a bioelectric field $V(\mathbf{x}, t)$ and a cortical stress field $\sigma(\mathbf{x}, t)$ that are weakly and *reciprocally* coupled.

In the fast band, the observable dynamics arise from *two weakly coupled first-order latent modes* that generate two damped carriers in the 1–3 Hz range. Their slight detuning produces a measurable slow beat $f_{\text{slow}} = |\Omega_+ - \Omega_-|/(2\pi)$ at the mesoscale set by the effective thickness ℓ (i.e., $k^* = \pi/\ell$). This two-mode coupling succinctly accounts for the apparent second-order features in the measured time series–namely, voltage-imaging traces $V(t)$ and traction/AFM-based stress reconstructions $\sigma(t)$ in epithelial monolayers.

Sampling the dynamics at the *neutral moment*–the recurring near-symmetric crossing between V and σ where the relative phase ψ passes through 0 (mod π) with positive slope yields an *even* circle map (mod π) for the slow phase. In this reduced description, the forcing Ω and the even-harmonic coupling K_2 are defined directly from data: to first order,

$$\Omega \simeq \tfrac{\pi}{2}\big(1 - r_{\text{eff}}\big), \qquad r_{\text{eff}} = \frac{\Omega_-}{\Omega_+},$$

with r_{eff} obtained from the fast-band carriers, while K_2 is estimated by neutral-moment regression.

Within this framework we propose that the slow electromechanical phase does not just exist spectrally, but coordinates two biological scales that are usually treated separately. On one side, it constrains spindle geometry and cortical anchoring during mitosis, limiting spindle-angle dispersion and chromatin torsional load at division checkpoints. On the other side, it provides a dynamical compatibility window for helical coordination. We focus on a narrow high-order lock, the 2/21 tongue, used here as a concrete target whose center is $\Omega_{2/21} = \pi \cdot 2/21$. We do not assume a direct forcing of molecular helical pitch by a tissue-scale cadence; any apparent alignment remains to be established empirically. The analysis concerns tissue-level observables (f_{slow}, Λ, and (Ω, K_2)), with cross-scale links treated operationally via the cycle-resolved neutral-reset analysis (E).

A central observable is the cross-spectral coherence $\Lambda \equiv C_{V\sigma}(f_{\text{slow}})$ between V and σ at f_{slow}. High Λ indicates that the bioelectric and mechanical sectors share a common slow cadence and remain phase-locked across neutral moments, whereas low Λ indicates slow-cadence drift between sectors. Together with the neutral-moment map parameters

(Ω, K_2), Λ provides a concrete test of whether tissue sits within a specific high-order Arnold tongue (notably 2/21) and whether departures from that window correlate with pathological states.

Physiological tissue is not expected to sit forever in a perfectly locked, stationary regime. Instead, E formalizes a *cycle-resolved* analysis in which healthy tissue repeatedly *re-enters* the 2/21 band on each slow cycle. Operationally, we identify each neutral moment, compute local slow-band coherence around it, and track the sliding estimates $(\widehat{\Omega}, \widehat{K}_2)$ over many cycles. Failure to re-enter takes two characteristic forms. First, *persistent unlocking*: the system drifts out of 2/21, Λ collapses, and spindle orientation becomes erratic. Second, *aging-like overlock*: the system remains trapped near the neutral state, Λ stays high but rigid, and adaptability is lost. In this reading, cancer-like genomic instability and aging-like loss of plasticity can be viewed as opposite dynamical arrests of the same electromechanical cycle.

The theory yields three preregisterable predictions (P1–P3) with direct experimental readouts. P1: homeostatic epithelia exhibit two fast-band carriers together with a narrow shared slow-band peak and a coherence maximum $\Lambda = C_{V\sigma}(f_{\text{slow}})$. P2: the forcing/coupling pair (Ω, K_2), obtained from the fast-band carriers (for Ω) and neutral-moment stroboscopy (for K_2), lies inside the predicted 2/21 Arnold tongue while avoiding broad low-order tongues. P3: a weak, frequency-specific electrical or mechanical drive at f_{slow} should increase Λ and reduce spindle-angle dispersion relative to an energy-matched off-resonant control.

G gives a preregistered assay for P3 and an *in silico* prevalidation in which a synthetic unlocked state is driven weakly at f_{slow}, showing selective recovery of slow-phase locking (higher Λ) and reduced angular noise in the neutral map, while off-band controls at $f_{\text{slow}}(1 \pm 0.10)$ fail to reproduce both effects together. Small persistent biases are also considered: a tonic offset breaks the π-symmetry of the neutral map, mixes parities, elevates even harmonics and $(f_0, f_0 \to 2f_0)$ bicoherence, and produces a non-monotonic power versus coherence response (H).

Within P3 we also preregister three mechanistic subtests–**P3a** (phase-locked neutral crossings), **P3b** (transition sharpness vs. slow-band power), and **P3c** (bias-induced parity mixing and rectified pumping)–which share the same weak-drive paradigm and serve as falsifiers of linear, phase-preserving alternatives (see App. H and App. G).

Beyond the slow-phase map, App. K develops a complementary functional and algebraic formulation of the dual-field clock. In that framework, the coarse-grained parameters $(\Omega, K_2, f_{\text{slow}})$ arise from three operator blocks (Γ, a, b) inherited from the overdamped electromechanical coupler, and small Na^+/K^+-like and pH/stiffness-like perturbations are represented as controlled deformations in this dual-field algebra. This provides an analytic explanation for the near-colinearity of the susceptibilities of Ω and f_{slow} and offers a compact language to interpret ionic and pharmacological interventions as trajectories in a constrained parameter space.

All analysis code, the preregistered workflow, and the cycle-resolved diagnostics are provided in App. E and App. G; the main text is self-contained.

2 Background and gaps the model addresses

Existing accounts of tissue coordination tend to split into two largely separate traditions. One focuses on molecular and statistical detail, treating voltage gradients, gene-regulatory programmes and double-helix structure as self-contained, with mechanics appearing only as boundary conditions. The other works at the scale of tissues and organs, modelling

collective mechanics, division geometry or cortical tension without an explicit dual electrical–mechanical dynamics or a concrete link back to molecular carriers. Both perspectives lack a dynamical, directly falsifiable mechanism that can coordinate cell-cycle events and division geometry without relying on manual integer tuning.

Here we introduce a dual-field framework that is designed to address this gap. We treat the bioelectric field $V(\mathbf{x}, t)$ and the cortical-stress field $\sigma(\mathbf{x}, t)$ as weakly and reciprocally coupled. In the fast band, this interaction can be reduced to two first-order latent modes with slightly detuned damped carriers $\Omega_\pm$; their interference generates an emergent slow beat

$$f_{\text{slow}} \;=\; \frac{|\Omega_+ - \Omega_-|}{2\pi},$$

which we propose as a tissue-scale clock for division timing and spindle geometry. Crucially, f_{slow} is not introduced as a free parameter but is determined by the electrical and mechanical latencies of the two coupled sectors.

To turn this slow cadence into a predictive structure, we sample the fast electrical phase at recurrent near-symmetric crossings between V and σ (the *neutral moments*). Operationally, these are the instants at which the analytic-phase difference $\psi(t) = \arg Z_V(t) - \arg Z_\sigma(t)$ crosses $0 \pmod \pi$ with positive slope. Strobing at neutral moments yields an *even* circle map, defined modulo π, for the reduced phase variable θ_n,

$$\theta_{n+1} \;=\; \theta_n + \Omega - K_2 \sin(2\theta_n) \pmod \pi,$$

whose rotation number ρ_π and Arnold-tongue structure are entirely controlled by two parameters (Ω, K_2). The effective forcing Ω is set by the ratio of the two carriers, $r_{\text{eff}} = \Omega_-/\Omega_+$, via $\Omega \simeq \frac{\pi}{2}(1 - r_{\text{eff}})$, and the even-harmonic coupling K_2 is estimated by neutral-moment regression on the observed strobe. In this setting, the high-order lock $\rho_\pi = 2/21$ used throughout the paper is not imposed as an ad hoc quantization rule; it *emerges* from the even map once the carriers have been measured.

Because the map is even $(\bmod \pi)$, the same construction naturally distinguishes between symmetric (latency-matched) and desynchronized (latency-mismatched) regimes. Neutral-moment strobing enforces even parity and reveals a specific locking pattern; full-cycle strobing (odd parity) is predicted to degrade that structure in a characteristic way. This built-in parity control provides an internal falsification test: if the proposed mechanism is correct, mode locking and curvature of the circle map should be visible under neutral-moment sampling and should change in a parity-sensitive manner when sampling is shifted away from neutral moments.

Finally, all quantities entering the reduced slow-phase map are traceable to measurable tissue properties. Membrane time constants, cortical stiffness and viscosity, diffusivities (D_V, D_σ) and weak electromechanical gains $(\gamma, \beta_R, \beta_I)$ constrain the latent carriers and their ratio r_{eff}, and thus Ω. The coupling K_2 is obtained from data by neutral-moment regression. This parameter provenance enables preregistered tests of specific locking scenarios, rather than post hoc tuning of integers or free phases.

2.1 Relation to prior bioelectric models

Classical bioelectric frameworks emphasize voltage gradients, ionic currents and patterning cues, often without an explicitly reciprocal mechanical field. In many such models, mechanics appears only as a static substrate, and no slow interference cadence is identified. In contrast, the present dual-field reduction

(i) treats V and σ as weakly but reciprocally coupled degrees of freedom,

(ii) predicts two narrow-band carriers in the fast band together with a slow interference beat f_{slow} that is, in principle, directly measurable rather than inferred,

(iii) yields an *even* circle map at neutral moments, providing a built-in parity switch (even vs. odd strobing) that acts as an internal falsification control,

(iv) computes the effective forcing Ω and the even coupling K_2 from directly measurable electrical and mechanical properties of the tissue, with no ad hoc integer quantization, and

(v) defines a functional order parameter $\Lambda = C_{V\sigma}(f_{\text{slow}})$ as the cross-spectral coherence between V and σ at the slow beat, providing a compact way to test whether different observables (slow-band voltage power, slow-band stress power, division geometry) are governed by the same underlying electromechanical locking.

In this sense, our model is intended to complement existing bioelectric accounts of growth control, morphogenesis and tissue-scale coordination, and to align with recent work showing that bioelectric control of tissue shape and collective responses to electrophysiological perturbations can be quantified and tested in a predictive manner [3, 7, 4, 5].

3 Physical identity of the fields and oscillatory reduction

3.1 Latent-mode representation and slow-beat emergence

In the fast band we represent the coupled bioelectric and mechanical dynamics by two weakly coupled first-order latent modes. In complex-amplitude form,

$$\dot{u}_1 = (-\alpha_1 + i\omega_1)\, u_1 + J\, u_2 + \xi_1(t), \qquad \dot{u}_2 = (-\alpha_2 + i\omega_2)\, u_2 + J\, u_1 + \xi_2(t), \qquad (1)$$

where $\alpha_k > 0$ are decay rates, $\omega_k > 0$ are carrier frequencies, J is a small complex coupling, and $\xi_k(t)$ collect fast noise and residual driving. The measured channels are real projections of these modes,

$$V(t) = \Re\{h_{V1}u_1 + h_{V2}u_2\}, \qquad \sigma(t) = \Re\{h_{S1}u_1 + h_{S2}u_2\}, \qquad (2)$$

with complex coefficients $h_{(\cdot)k}$ encoding the mixing between latent modes and observed fields. Apparent second-order behaviour of the fast band is captured here by the two-mode coupling itself: no extra "hidden" oscillator is introduced beyond Eqs. (1)–(4).

Writing $\bar{\alpha} = \frac{\alpha_1+\alpha_2}{2}$, $\bar{\omega} = \frac{\omega_1+\omega_2}{2}$, $\Delta\alpha = \alpha_1 - \alpha_2$ and $\Delta\omega = \omega_1 - \omega_2$, the four eigenvalues of the 4×4 real system can be written as

$$s_\pm = -\bar{\alpha} + i\,\bar{\omega} \;\pm\; \frac{1}{2}\sqrt{(\Delta\alpha - i\,\Delta\omega)^2 + 4\,|J|^2}. \qquad (3)$$

Generically this yields *two* damped carriers with observable frequencies $\Omega_\pm = \Im s_\pm$. In the symmetric case $\Delta\alpha = 0$,

$$|\Delta\omega| > 2|J| \;\Rightarrow\; \Omega_\pm = \bar{\omega} \pm \tfrac{1}{2}\sqrt{\Delta\omega^2 - 4|J|^2}, \qquad |\Delta\omega| \le 2|J| \;\Rightarrow\; \Omega_+ = \Omega_- = \bar{\omega}.$$

The emergent slow beat is then

$$f_{\text{slow}} = \frac{|\Omega_+ - \Omega_-|}{2\pi} = \frac{1}{2\pi}\left|\Im\sqrt{(\Delta\alpha - i\Delta\omega)^2 + 4\,|J|^2}\right|. \qquad (4)$$

Thus, two weakly coupled first-order modes are sufficient to account for the fast-band structure. When $|\Delta\omega| > 2|J|$ the spectrum exhibits two damped carriers $\Omega_\pm$ with a slow beat $f_{\text{slow}} = |\Omega_+ - \Omega_-|/(2\pi)$; under locking ($|\Delta\omega| \le 2|J|$), the split collapses to a single carrier and $f_{\text{slow}} \to 0$. In this sense, the "effective second order" of the observed response is generated by the two-mode coupling rather than by an ad hoc second-order term.

In what follows we refer to the regime with two distinct carriers and ongoing relative precession between the two sectors as the *antisymmetric, latency-mismatched* regime. When the carriers merge into a single frequency and the electric and mechanical sectors stop precessing against each other, we speak of the *symmetric, latency-matched* regime.

Observed phases and projection structure If the projections are cross-dominant, $|h_{V1}| \gg |h_{V2}|$ and $|h_{S2}| \gg |h_{S1}|$, each channel follows, in the antisymmetric latency-mismatched regime, the phase of the latent mode that dominates its projection. Under locking, approximately odd/even combinations $h_{V1} \approx -h_{V2}$ and $h_{S1} \approx h_{S2}$ produce phase opposition in V and phase alignment in σ for the locked solution, matching the phenomenology we seek to explain at the tissue level.

In the antisymmetric, latency-mismatched regime, dominance between the two sectors alternates over each slow cycle: during one half-beat the electrical projection is closer to the fast carrier, whereas during the other half-beat the mechanical projection leads. This periodic exchange of roles preserves the slow beat while preventing either sector from becoming permanently dominant. In the symmetric, latency-matched regime one sector effectively freezes the relative phase and the alternation collapses, a point that will be important below when we discuss proliferative versus senescent regimes.

Role of nonlinearity (P3) Nonlinearity does not create the carriers; it mixes and rectifies their interference under a weak tonic bias ε_b. This raises even harmonics, enhances the $(f_+, f_+ \to 2f_+)$ bicoherence and transmits the cadence f_{slow} into the slow map. In other words, nonlinearity is needed to *read out* the beat, not to generate it.

Falsifiable check for two damped carriers The presence of two complex poles can be tested directly. A brief, spatially uniform impulse followed by traction or stress readout should exhibit a short-lived oscillatory ring-down in the carrier band if the spectrum contains two damped modes. Fitting the impulse response with a single-carrier versus a two-carrier model discriminates whether a split consistent with Eqs. (3)–(4) is present. In the antisymmetric, latency-mismatched regime ($|\Delta\omega| > 2|J|$), Hilbert-phase drift between V and σ provides an independent estimate of f_{slow} and its collapse when $|\Delta\omega| \leq 2|J|$.

3.2 Phase-map reduction and parity structure

In the antisymmetric, latency-mismatched regime the two damped normal modes at $k^* = \pi/\ell$ alternate in dominance. We define the *neutral moment* as the recurrent instant when the instantaneous phase difference between V and σ is 0 (mod π) with positive slope,

$$\phi_V(t) - \phi_\sigma(t) = 0 \ (\text{mod} \ \pi), \qquad \frac{d}{dt}\big[\phi_V(t) - \phi_\sigma(t)\big] > 0,$$

so that the signals are locally mirror-symmetric even if amplitudes remain unbalanced. Operationally, this marks a transient balance between inward (electrical) and outward (mechanical) tendencies and resets the slow cadence.

Taking the neutral moments as a Poincaré section identifies $\theta \equiv \theta + \pi$. In this π-quotient the leading nonlinearity is even, and the reduced slow-phase map is

$$\begin{aligned}
&\theta_{n+1} = \theta_n + \Omega - K_2 \sin(2\theta_n) + \mathcal{O}(\sin 4\theta) \quad (\text{mod} \ \pi), \\
&\Omega \simeq \tfrac{\pi}{2}\big(1 - r_{\text{eff}}\big), \\
&r_{\text{eff}} = \frac{\Omega_-}{\Omega_+} \in (0, 1),
\end{aligned}$$
(5)

where r_{eff} is the carrier-frequency ratio obtained from Eqs. (1)–(4). The forcing Ω is therefore fixed by the measured carriers, and the even-harmonic coupling K_2 is estimated by neutral-moment regression on the observed strobe.

Type of nonlinearity and empirical checks   Because neutral-moment strobing identifies θ with $\theta + \pi$, the reduced map (5) must be parity-even. The leading nonlinear correction is therefore quadratic and appears as $-K_2 \sin(2\theta)$, with higher even orders $\mathcal{O}(\sin 4\theta)$. Odd harmonics (e.g. $\sin \theta$) are symmetry-forbidden in the unbiased regime and only emerge when parity is broken by a sustained bias (see Sec. H.4). In the Supplementary Material we report two compact empirical checks supporting this classification: the even/odd spectral ratio $P(2f_+)/P(3f_+)$ and the normalized bicoherence at $(f_+, f_+ \to 2f_+)$ with phase-randomization p-values.

Bias and parity mixing   A small tonic bias (electrical DC offset or mechanical prestress) does not remove slow alternation; it perturbs the reduced phase map by mixing even and odd harmonics. To leading order,

$$\theta_{n+1} = \theta_n + \Omega \ - \ K_2 \sin(2\theta_n) \ - \ \varepsilon_b K_1 \sin(\theta_n) \ + \ \mathcal{O}(\sin 3\theta, \sin 4\theta) \quad (\text{mod } \pi), \quad (6)$$

where ε_b measures the tonic offset and K_1 is the odd-parity projection at neutral moments. In the 2π lift of the section the odd term is 2π-periodic; Eq. (31) (Sec. H.4) gives the explicit form used in the rectification analysis. The odd correction skews dwell times around neutral moments and *rectifies* the phase-gated exchange, increasing slow-band power and reducing adaptability as the operating point approaches tongue boundaries. Here Ω and r_{eff} are obtained directly from the fast band, and K_2 is estimated by neutral-moment regression, with no ad hoc integer fitting.

Within the π-circle convention, a p/q phase lock is centered at $\Omega \simeq \pi\, p/q$. For 2/21,

$$\Omega_{2/21} = \pi \cdot \frac{2}{21} \approx 0.2992 \text{ rad},$$

so the 2/21 plateau we focus on is a high-order Arnold tongue of the even (mod π) circle map in the standard sense of driven phase locking [1, 2].

When the lagged/quadrature component locks to the in-phase component (symmetric, latency-matched regime; the two sectors stop precessing against each other and the two carriers merge into a single synchronized oscillation), the π identification is lost. The relevant section becomes 2π-periodic and the map reverts to odd parity,

$$\theta_{n+1} \ = \ \theta_n + \Omega_{\text{sym}} - K_1 \sin \theta_n + \cdots \quad (\text{mod } 2\pi), \quad (7)$$

with constant forcing Ω_{sym} defined by the locked fast carrier. In the biological interpretation developed below, the antisymmetric, latency-mismatched regime underlies normal proliferative cycling, whereas progressive bias and eventual symmetry lead to "overlock" and senescence-like arrest.

4 Even circle map and rotation number

After neutral-moment reduction, the slow phase dynamics of the coupled bioelectric–mechanical system are captured by the even (mod π) circle map

$$\theta_{n+1} \ = \ \theta_n \ + \ \Omega \ - \ K_2 \sin(2\theta_n) \quad (\text{mod } \pi), \quad (8)$$

where Ω is the effective forcing set by the carrier-frequency ratio $r_{\mathrm{eff}} = \Omega_-/\Omega_+$ and K_2 is the even-harmonic coupling obtained by neutral-moment regression (sec. 3). Equation (8) describes how the slow phase θ_n advances from one neutral moment to the next.

Let $\{\Theta_n\}$ be a lift of (8) to $\mathbb{R}$, so that $\Theta_{n+1} - \Theta_n = \Omega - K_2 \sin(2\Theta_n)$. The associated rotation number on the π-quotient is

$$\rho_\pi(\Omega, K_2) \;=\; \lim_{N \to \infty} \frac{\Theta_N - \Theta_0}{\pi N}, \tag{9}$$

whenever the limit exists (which it does for circle maps with lifts of bounded variation). Intuitively, ρ_π measures the average phase advance (in units of π) per neutral moment; in our biological interpretation it controls the average angular offset of spindle orientation and the effective helical pitch of the integrated dynamics.

At fixed K_2, the function $\Omega \mapsto \rho_\pi(\Omega, K_2)$ is a nondecreasing "devil's staircase" [2, 10]: it is constant on mode-locked plateaus at rationals $\rho_\pi = p/q$ and strictly increases only on a Cantor set of Ω values. Each rational p/q defines an Arnold tongue in the (Ω, K_2)-plane, within which the map is locked with average rotation $\rho_\pi = p/q$. For $K_2 \ll 1$, the width of the tongue associated with p/q scales generically like $\mathcal{O}(K_2^q)$, so higher-order locks become progressively narrower but can still be robust if K_2 is not vanishingly small. In the uncoupled limit $K_2 = 0$ one recovers the trivial relation $\rho_\pi = \Omega/\pi$.

Within this even (mod π) convention, the lock of interest in this work is $\rho_\pi = 2/21$. It corresponds to a narrow high-order tongue centred at $\Omega \simeq \pi \cdot 2/21 \approx 0.2992$ rad, and it implies that the slow phase advances by $2\pi/21$ per neutral moment. In subsequent sections we show that this $2/21$ locking regime organizes both spindle-orientation statistics and P1–P3 timing, and we outline how its presence can be tested numerically and experimentally.

5 Helical quantization without fitted integers

In the even (mod π) convention, a neutral-moment step advances the slow phase on average by $\rho_\pi \pi$ radians. For a rational lock $\rho_\pi = p/q$, p neutral cycles correspond to a net phase advance of π, and q neutral cycles produce an advance of $p\pi$. Defining a helical unit as p neutral-moment increments that yield a mechanical half-turn (π), the number of units per full 2π turn is

$$n \;=\; \frac{q}{p}.$$

The value $n \approx 10.5$ corresponds numerically to the rational $\rho_\pi = 2/21$.

In the present framework, the $2/21$ plateau is an emergent locking regime of the even map, determined by the carrier ratio and the coupling (Ω, K_2) inferred from tissue measurements. The coincidence with the B-DNA pitch is obtained without introducing fitted integers or explicit slow forcing at the molecular scale. We regard this as a cross-scale numerical correspondence; no direct dynamical coupling between the tissue beat and individual base pairs is assumed.

We ask whether physiologically plausible parameters can place the system inside the $2/21$ tongue while avoiding low-order locks.

Observation (Compatibility of physiological strips with $2/21$ locking) Let independently measured parameters induce a strip

$$\mathcal{S} = \big\{(\Omega, K_2): \; \Omega \in [\Omega_1, \Omega_2], \quad K_2 \in [K_{2,\mathrm{min}}, K_{2,\mathrm{max}}]\big\}$$

in the (Ω, K_2) plane via Eqs. (1)–(4) and (8). For ranges consistent with homeostatic epithelia, numerical continuation shows that $\mathcal{S}$ can intersect the 2/21 tongue of the even map while remaining separated from lower-order tongues with $q \leq 6$. If, for a given tissue, the empirically derived strip $\mathcal{S}$ does not intersect the 2/21 tongue, the 2/21 scenario is not supported under those conditions.

In practical terms, once (Ω_1, Ω_2) and $(K_{2,\min}, K_{2,\max})$ have been constrained from data, either $\mathcal{S}$ intersects the 2/21 tongue or it does not; no additional integer fitting is available to enforce that lock.

6 An experimental coherence observable

Let $S_V(f)$ and $S_\sigma(f)$ denote the power spectral densities of V and σ, and let $S_{V\sigma}(f)$ be their cross-spectrum. We define the electromechanical coherence at the slow cadence as

$$
\Lambda \equiv C_{V\sigma}(f_{\text{slow}}) = \frac{\left| S_{V\sigma}(f_{\text{slow}}) \right|^2}{S_V(f_{\text{slow}}) \, S_\sigma(f_{\text{slow}})}, \qquad f_{\text{slow}} = |f_+ - f_-|, \tag{10}
$$

with f_{slow} given by Eqs. (3)–(4). The quantity $\Lambda \in [0, 1]$ is a directly measurable order parameter that quantifies how strongly the electrical field V and the cortical stress σ are phase-locked at the slow beat.

Practically, V can be recorded with voltage-sensitive dyes or fast optical electrophysiology, and σ can be estimated from traction force microscopy or AFM-based stress reconstruction in epithelial monolayers. High Λ indicates robust electromechanical interference at f_{slow} (locked slow phase); low Λ indicates partial unlocking or drift. The definition of Λ does not rely on the circle-map description and can therefore be used as an independent test of the proposed locking scenario.

7 Mechanistic link to division and differentiation

Within the dual-field framework, the position of (Ω, K_2) relative to the relevant Arnold tongue (here, the 2/21 tongue of the even map) controls slow-phase locking. When (Ω, K_2) lies inside the tongue, the slow phase is locked, the cross-spectral coherence Λ at f_{slow} is high and stable, and spindle-angle dispersion is predicted to be low. When (Ω, K_2) approaches tongue boundaries or moves outside, locking becomes fragile or is lost: Λ decreases, and division-plane statistics broaden.

We interpret proliferative and differentiated states as operating at different locations in this control plane. Differentiated, homeostatic epithelia correspond to effective parameters (Ω, K_2) within a locked region, with high Λ and low spindle error. Proliferative states are expected to hover near tongue edges, where small parameter shifts can induce partial unlocking. Two distinct failure modes follow from the same slow-phase mechanism: a regime of *proliferative unlocking*, with persistent drift of (Ω, K_2) away from the tongue and low Λ, and a regime of *overlock*, in which locking remains strong but adaptability is reduced.

7.1 Testable pathology signatures

Aging (overlock / drift) *Prediction.* In tissues from aged donors or long-term cultures, neutral-moment strobing should yield higher effective K_2 and slow drift in r_{eff}, with Λ remaining high but changing only slowly over time. Under full-cycle (odd-parity) strobing, the curvature structure associated with even harmonics is expected to be only weakly disrupted. *Refutation.* No systematic differences in (Ω, K_2, Λ) relative to young controls.

Proliferative unlocking *Prediction.* In hyperproliferative monolayers with impaired checkpoint control, (Ω, K_2) should display a broad distribution of Ω values displaced from $\pi \cdot 2/21$, Λ at f_{slow} should be low, and spindle misorientation should increase. Under parity switching (even to odd), only limited additional change is expected, because the even-harmonic organization is already degraded. *Refutation.* Persistently high Λ with (Ω, K_2) remaining inside the 2/21 tongue despite unchecked proliferation.

These two signatures correspond, in parameter space, to different displacements of (Ω, K_2) away from the interior of the 2/21 tongue, together with predictable changes in Λ and division-plane statistics.

Parameter-grounded view Independent of any specific gene-expression program, aging-related changes in tissue mechanics and electrophysiology are expected to move (Ω, K_2). For example, cortical or ECM stiffening and increased viscous loss ($\kappa \uparrow, \eta \uparrow$) act through $b = \kappa + D_\sigma k^{*2}$ to lower Ω and strengthen even-harmonic feedback (larger K_2). Electrical remodeling (changes in gap-junctional coupling D_V or membrane time constant τ_m) can bias Ω in either direction. The net displacement is empirical and, in principle, quantifiable through (Ω, K_2, Λ) under neutral-moment stroboscopy.

7.2 Phase-guided modulation (phase-targeted entrainment)

If a partial phase-locking capacity is present, the same slow-phase structure suggests a simple control strategy: low-amplitude entrainment at f_{slow} aimed at moving (Ω, K_2) back towards the interior of the locking tongue. In this view, (Ω, K_2, Λ) estimated in vivo provide both a baseline and a target region in the control plane.

A practical protocol would proceed in three steps: (i) estimate (Ω, K_2, Λ) from voltage imaging and traction/stress readouts using neutral-moment stroboscopy; (ii) apply a weak electrical or mechanical drive at f_{slow}, with detuning chosen to lie well inside the inferred tongue; and (iii) test for an increase in Λ and a reduction in spindle misorientation relative to matched off-resonant controls. The weak-drive Popper test (Methods) rules out purely linear alternatives and justifies on-band, low-amplitude stimulation.

7.3 Regenerative bioelectrical stimulation and dynamical specificity

Low-frequency electrical stimulation is used empirically in regenerative settings (dental pulp, bone, peripheral nerves) with carrier frequencies in the spanning the sub-Hz to tens of Hz range. Reported protocols typically arise from screening and differ across tissues, with no shared mechanism for why a given frequency is effective in one context and not in another.

In the dual-field framework the relevant quantity is not a universal carrier frequency but the tissue-specific slow cadence f_{slow} emerging from electromechanical interference. Successful stimulation is expected when the effective drive envelope lies inside the interior of the locking tongue for the target tissue. In particular, a fixed-frequency protocol may be pro-regenerative in one preparation and ineffective in another if the corresponding (Ω, K_2) place the two tissues in different regions of the control plane.

A testable prediction follows. Outcomes of regenerative protocols should correlate more strongly with individualized matching of the slow envelope to f_{slow} (with (Ω, K_2) inside the interior of the relevant tongue) than with fixed carrier frequency alone. In crossover designs using the same hardware, moving the envelope from off-band to on-band, while holding total delivered charge and carrier constant, is predicted to improve efficacy if the locking mechanism is operative.

8 Falsifiable experimental targets

P1 Spectral coherence (slow band, even parity). Homeostatic monolayers are expected to exhibit a coincident slow-band peak in S_V and S_σ at $f_{\text{slow}} = |f_+ - f_-|$, together with elevated cross-coherence $\Lambda \equiv C_{V\sigma}(f_{\text{slow}}) > 0.6$ estimated as in Methods (band-limited Welch, neutral-moment strobing; S_V^{slow} and S_σ^{slow} as defined there). Failure to detect a slow-band peak at f_{slow}, or observing $\Lambda < 0.2$, falsifies the dual-field locking picture for that tissue and set of conditions, or indicates that the sample is in a non-homeostatic regime (unlocking or overlock).

In the latency-based refinement, homeostatic preparations that satisfy P1 are also expected to show latency parity consistent with even synchrony, with the electric and mechanical relaxation times lying on the same side of T_{slow} and of comparable magnitude (latency-parity indices $S_{\text{lag}} > 0$ and $D_{\text{lag}} \approx 1$ in the notation of the Appendices). Persistent $S_{\text{lag}} < 0$ together with low slow-band coherence would instead signal an odd-desynchronized regime, i.e. effective unlocking or overlock of the dual-field oscillator.

P2 Mode selection in (Ω, K_2) without integer fitting. Independently measured physical parameters are used to compute the two carriers and their beat (Eqs. 1–4), and the slow forcing via the even map (Eq. 8), yielding a point (Ω, K_2) in the control plane. The model predicts that (Ω, K_2) falls inside the 2/21 Arnold tongue and avoids lower-order tongues, provided that the latency-based coupling proxy C_{proxy} (F.3) is not collapsed toward zero (near-quadrature mismatch), so that even-harmonic coupling at neutral moments remains effective.

P2 (quantitative). P2 holds if (Ω, K_2) lies within the 2/21 tongue and the distance in Ω to the nearest tongue centre with $q \leq 6$ exceeds $3\,\sigma_\Omega$. In addition, a Monte Carlo under physiological priors places (Ω, K_2) inside 2/21 with probability ≥ 0.30. This assumes negligible low-order overlap for $K_2 \ll 1$; if local overlaps occur, the exclusion margin is computed with respect to the nearest overlapping boundary instead of the tongue centre. A systematic displacement of (Ω, K_2) outside 2/21, robust locking to a lower-order tongue, or a consistently collapsed $C_{\text{proxy}} \approx 0$ falsifies the proposed selection mechanism.

P3 Phase-targeted entrainment (weak, frequency specific). A weak external electrical or mechanical drive at f_{slow} is predicted to increase Λ and decrease spindle-angle dispersion (proxy for spindle-orientation noise), whereas an off-resonant control of matched energy and duty cycle but $\sim 10\%$ detuning should not produce both effects simultaneously. Operationally, preregister the contrasts

$$\Delta\Lambda \equiv \Lambda_{\text{drive}} - \Lambda_{\text{base}}, \qquad \Delta\text{Var}_{\text{map}} \equiv \text{Var}_{\text{map,drive}} - \text{Var}_{\text{map,base}},$$

with the "weakness" constraint $|\Delta f_\pm| < 3\%$. Absence of a selective on-band improvement in both $\Delta\Lambda$ and $\Delta\text{Var}_{\text{map}}$ relative to off-band controls falsifies the phase-targeted entrainment mechanism.

G provides the preregistration and the in-silico prevalidation.

P3 (refined capture-time prediction). In the latency-based, first-order formulation the capture time is further constrained by the inter-channel phase at the slow cadence. Let $\tau_{\text{e}}, \tau_{\text{m}}$ be the electric/mechanical relaxation times, and C_{proxy} the latency-based coupling proxy defined in F.3. Near a tongue boundary the slow locking time obeys the scaling

$$T_{\text{lock}} \propto \frac{1}{f_{\text{slow}}\sqrt{\delta_0\, C_{\text{proxy}}}}, \qquad \delta_0 = \frac{K_{\text{eff}}}{\Delta\omega} - 1,$$

so that on-band weak drive should shorten T_{lock} primarily by increasing C_{proxy} (improved latency parity and coincidence), whereas an equal-energy off-band drive should not. Empirically, pro-meta and metaphase dwell times are expected to regress against $(f_{\text{slow}}\sqrt{C_{\text{proxy}}})^{-1}$ with approximately unit slope on log-log axes; systematic deviations or loss of on-band superiority relative to off-band controls falsify the refined capture picture.

9 Materials and methods

9.1 Electrical and mechanical parameters

The parameters entering the coupled electromechanical model are obtained from standard optical electrophysiology, traction/stress imaging, and micromechanical assays.

The electrical diffusivity D_V and membrane time constant τ_m are estimated from voltage-sensitive dyes / fast optical electrophysiology by fitting a diffusive RC response: spatial decay of V constrains D_V, and step responses constrain τ_m (after correcting for dye kinetics). The in-plane elastic modulus κ, viscous coefficient η, and stress diffusivity D_σ are obtained from AFM indentation, traction force microscopy (TFM), and poroelastic/viscoelastic relaxation fits. In this overdamped framework, κ captures effective cortical stiffness in the carrier band, η quantifies viscous loss in the $\sim$ 1–3 Hz band, and D_σ characterizes stress redistribution.

The cross-coupling coefficients $(\beta_R, \beta_I, \gamma)$ are inferred from linear-response gains and phase lags around the mechanical carrier band: β_R and β_I describe the in-phase and quadrature components of the stress-to-voltage gain, and γ the voltage-to-displacement gain. Together with $D_V, \tau_m, \kappa, \eta, D_\sigma$, these parameters determine two latent carrier branches $\omega_\pm(k)$ of an overdamped electromechanical coupler. The mesoscale ratio

$$r_{\text{eff}} \;=\; \frac{\omega_{-,r}(k^*)}{\omega_{+,r}(k^*)} \;=\; \frac{f_-}{f_+},$$

and the slow interference cadence $\Omega_{\text{slow}} = \omega_{+,r}(k^*) - \omega_{-,r}(k^*)$ are evaluated at the morphological wavenumber $k^* = \pi/\ell$ set by cortical shell thickness ℓ.

9.2 Candidate systems and parameter acquisition

Table 1 summarizes (i) how each primitive parameter is obtained experimentally and (ii) typical orders of magnitude. These values are indicative placeholders: system-specific values (e.g. MDCK vs. HaCaT vs. neuronal monolayer) are intended to be preregistered ahead of data collection.

9.3 Spectral estimation and coherence

Paired time series $V(t)$ and $\sigma(t)$ are acquired simultaneously at sampling rate $\geq$ 100 Hz for durations $\geq$ 600 s in confluent monolayers. After detrending, Welch spectra are computed with 10 s Hanning windows, 50 % overlap, and averaged to estimate $S_V(f)$, $S_\sigma(f)$, and the cross-spectrum $S_{V\sigma}(f)$. The electromechanical coherence

$$\Lambda \;=\; C_{V\sigma}(f_{\text{slow}}) = \frac{|S_{V\sigma}(f_{\text{slow}})|^2}{S_V(f_{\text{slow}})\, S_\sigma(f_{\text{slow}})}, \qquad f_{\text{slow}} = \frac{\Omega_{\text{slow}}}{2\pi} = f_+ - f_-,$$

is then evaluated at the slow interference cadence.

For prediction P1, slow-band spectra are explicitly isolated. For each signal $X \in \{V, \sigma\}$, a narrowband analytic signal $X_{\text{slow}}(t)$ is constructed by demodulating around f_{slow} with a

Parameter	Units	Typical order	Acquisition (method / note)
D_V	m^2/s	10^{-10}–10^{-8}	Optical electrophysiology; spatial decay of V; fit diffusive RC model.
τ_m	s	0.1–2	Membrane charging from voltage steps; corrected for dye kinetics.
κ	N/m	10^{-4}–10^{-2}	Effective cortical stiffness from small-amplitude TFM/AFM fits.
η	N·s/m	10^{-4}–10^{-2}	Viscous loss from frequency sweeps in the $1--3$ Hz band.
D_σ	m^2/s	10^{-12}–10^{-10}	Stress diffusion inferred from relaxation of traction patterns.
γ	m/V	small	Voltage-to-displacement gain of u per volt (report peak gain near $f_\pm$). If only stress drive is available, report in $N\,m^{-2}V^{-1}$.
β_R, β_I	V per (stress unit)	small	Stress-to-voltage cross-gain; in-phase (β_R) and quadrature (β_I) via lock-in / phase-lag measurements.
ℓ	m	10^{-5}–10^{-3}	Effective cortical/shell thickness from confocal optical sectioning.

Table 1: Parameter provenance for computing (Ω, K_2), r_{eff}, and f_{slow} in the overdamped, two-latent-mode framework. Orders of magnitude are indicative; system-specific values are to be preregistered for each experimental system.

symmetric band-pass (typically ±0.05–0.08 Hz about f_{slow}, or a multitaper equivalent). $S_X^{\text{slow}}(f)$ denotes the power spectrum of $X_{\text{slow}}(t)$, which is used to assess whether both channels exhibit a coincident slow-band peak. Confidence intervals for Λ are obtained by temporal shuffling (typically 1000 circular time-shift permutations) and by fixed-cell baselines.

9.4 Rotation number and stroboscopic regression

To estimate the slow-phase map parameters (Ω, K_2) and the rotation ratio ρ_π, the analysis proceeds in the slow-phase frame.

First, analytic signals $Z_X(t) = X(t) + i\,\mathcal{H}[X(t)]$ are formed for V and σ, where $\mathcal{H}$ denotes the Hilbert transform. The instantaneous phase difference $\psi(t) = \arg Z_V(t) - \arg Z_\sigma(t)$ tracks the lag between electrical and mechanical sectors.

Neutral moments $\{\tau_n\}$ are defined as the recurrent instants where the two sectors align modulo π:

$$\psi(\tau_n) \equiv 0 \pmod{\pi}, \qquad \dot{\psi}(\tau_n) > 0.$$

Sampling at these neutral moments enforces the even (mod π) Poincaré section described in the main text. Let $\phi_+(t)$ be the instantaneous phase of the $+$ carrier branch (the higher-frequency carrier), and set $\theta_n = \phi_+(\tau_n)$. The slow-phase increments are $\Delta\theta_n = \theta_{n+1} - \theta_n$.

Regressing $\Delta\theta_n$ against $\sin(2\theta_n)$ yields estimates of Ω (intercept) and K_2 (slope), and the inferred rotation number ρ_π follows from the extracted Ω via $\Omega \simeq \frac{\pi}{2}(1 - r_{\text{eff}})$.

9.5 Statistical model for the coupling K_2

Let $\Delta\theta_n = \theta_{n+1} - \theta_n$, unwrapped to $\mathbb{R}$. The stroboscopic slow-phase map is modeled as

$$\Delta\theta_n = \Omega - K_2\sin(2\theta_n) + \epsilon_n, \qquad \epsilon_n \sim \text{WN}(0, \sigma^2), \tag{11}$$

where WN denotes wrapped-normal innovations (approximately Gaussian for small increments). Here K_2 is interpreted as the even-harmonic feedback strength at neutral moments (the coupling amplitude of the slow-phase map). Parameters (Ω, K_2) are estimated by constrained ordinary least squares with $K_2 \geq 0$, and Newey–West robust standard errors are reported. Block-bootstrap confidence intervals (CIs) are provided as an additional robustness check. Model adequacy is assessed by whiteness of residuals and a circular R^2 diagnostic.

9.6 Biological King plot: common-curvature test (pre-experimental)

To test whether slow-phase control and downstream readouts share a common quadratic structure across perturbations, a "biological King plot" analysis is defined as follows. Choose controlled conditions A_k (for example, cortex thickness h, osmotic compression, confluence changes) and a reference A_{ref}. For each A_k, compute $\Omega(A_k)$ via neutral-moment stroboscopy (even parity) and extract the slow-band observables

$$Y^{(j)}(A_k), \quad j \in \{\text{peak of } S_V^{\text{slow}}, \text{ peak of } S_\sigma^{\text{slow}}, \text{ log} \Lambda, K_2\}.$$

To account for morphology, apply a rescaling $m_{A_k} \propto 1/h$ and define

$$X_k \equiv m_{A_k} \left[\Omega(A_k) - \Omega(A_{\text{ref}}) \right], \qquad Y_k^{(j)} \equiv m_{A_k} \left[Y^{(j)}(A_k) - Y^{(j)}(A_{\text{ref}}) \right].$$

Under the neutral (even-parity) strobe, the rescaled observables are expected to follow

$$Y^{(j)} = A^{(j)} + B^{(j)} X + \kappa_{\text{uni}} X^2 + r^{(j)}, \tag{12}$$

with approximately the same quadratic curvature κ_{uni} across all j. This "common curvature" is interpreted as evidence that voltage slow-band power, cortical-stress slow-band power, $\log \Lambda$, and K_2 are co-driven by a single electromechanical interference mode at f_{slow}. Switching to the full-cycle strobe (odd parity) provides an internal control: it introduces an additional odd component, disrupts the shared quadratic curvature across readouts, and increases the alternation index (A).

9.7 Experimental candidates and realism

Homeostatic epithelial monolayers (e.g. MDCK, HaCaT) and dense neuronal cultures provide paired $V(t)$ and $\sigma(t)$, controllable ℓ, and standard AFM / TFM / optical readouts. These systems allow direct estimation of $(D_V, \tau_m, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma)$, construction of the slow-phase map (Ω, K_2), and measurement of Λ. Pilot datasets will be preregistered to populate Table 1 and to execute the prevalidation plan below.

Algorithm 1 Cycle-resolved workflow (overdamped, two-latent-mode framework)

1: Estimate $(D_V, \tau_m, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma)$ and compute the latent branches $\omega_\pm(k)$; evaluate at $k^* = \pi/\ell$ to obtain $\omega_\pm(k^*)$.
2: Set $f_\pm = \omega_\pm(k^*)/(2\pi)$, compute $r_{\text{eff}} = f_-/f_+$ and the slow beat $f_{\text{slow}} = |f_+ - f_-|$; equivalently, $\Omega_{\text{slow}} = \omega_+(k^*) - \omega_-(k^*)$.
3: Set $\Omega \simeq \frac{\pi}{2}(1 - r_{\text{eff}})$ and estimate the even coupling K_2 by regressing $\Delta\theta_n$ on $\sin(2\theta_n)$ at neutral moments (Eq. (11)).
4: Record $V(t), \sigma(t)$; compute $C_{V\sigma}(f)$; set $\Lambda = C_{V\sigma}(f_{\text{slow}})$.
5: If (Ω, K_2) lies within the 2/21 tongue and $\Lambda > 0.6$, predict low spindle misorientation; otherwise predict increased spindle-angle dispersion.

Prevalidation plan (addressing P2 robustness). Uncertainty from parameter estimation is propagated to (Ω, K_2) before any biological interpretation. Profile likelihoods and Monte Carlo sampling are used to propagate uncertainty in (γ, a, b, k^*), where $a = \tau_m^{-1} + D_V k^{*2}$ and $b = \kappa + D_\sigma k^{*2}$. The resulting sampling distribution of (Ω, K_2) is summarized by two preregistered conditions: *(C1)* $P\big((\Omega, K_2) \in \text{tongue}(2/21)\big) \geq 0.3$ (95% CI), and *(C2)* the safety margin to the nearest lower-order tongue $(1/2, 1/3, 2/5)$ exceeds $3\sigma_\Omega$, where σ_Ω is the robust SE for Ω from neutral-moment regression. In parallel, Λ is estimated with temporal shuffling ($N \geq 1000$ permutations) and a fixed-cell baseline; $\Lambda > 0.6$ (95% CI) is preregistered as the operational "high-locking" threshold.

9.8 Preregistered reanalysis on public datasets (Level-1 verification)

To obtain an initial test of the slow-phase mechanism without collecting new data, an *a priori* (preregistered) reanalysis will be performed on suitable public datasets.

Dataset types and inclusion criteria Candidate datasets include: (i) confluent epithelial monolayers (MDCK/HaCaT/Caco-2), (ii) dense neuronal cultures as a positive dynamical control, and (iii) organoid monolayers or early spheroids. Inclusion criteria:

- **Sampling and duration:** frame rate $\geq 80\,\text{Hz}$ (to resolve carrier peaks in the $1--3\,\text{Hz}$ band) and total duration $\geq 300\,\text{s}$.
- **Observables:** (A) paired electrical/mechanical channels (preferred): a voltage reporter (GEVI or fast dye) and traction/stress (TFM/AFM or micropillar arrays); or (B) a voltage channel plus a mechanical proxy (bright-field kymographs, optical-flow divergence, speckle-based strain) that can be collapsed to a scalar $\sigma(t)$; or (C) a mechanical channel plus a slower electrical proxy with documented SNR.
- **Stationarity:** no global drifts larger than one carrier period; field of view approximately uniform (no wound edges unless masked).

Reconstruction of observables From raw movies, $V(t)$ is taken as the field-averaged GEVI/dye signal (after photobleach correction and detrending). $\sigma(t)$ is obtained as either the spatial mean traction (TFM) / principal component of the traction field, or a calibrated mechanical proxy (e.g. optical-flow divergence). Causal (phase-distorting) filters are avoided; band-pass steps are applied symmetrically.

Analysis pipeline (fixed, preregistered)

1. **Carrier identification:** estimate $S_V(f)$ and $S_\sigma(f)$ (Welch; 10 s windows; 50% overlap). Identify two carrier peaks f_- and f_+ in $[1, 3]$ Hz with peak prominence > 3 dB above local baseline.
2. **Neutral-moment stroboscopy:** form analytic signals Z_X and the phase lag $\psi(t) = \arg Z_V - \arg Z_\sigma$. Define neutral moments $\{\tau_n : \psi(\tau_n) \equiv 0 \pmod{\pi}, \ \dot{\psi}(\tau_n) > 0\}$.
3. **Even-map regression:** sample $\theta_n = \phi_+(\tau_n)$ (phase of the $+$ carrier) and regress $\Delta\theta_n = \theta_{n+1} - \theta_n$ on $\sin(2\theta_n)$ to estimate $(\widehat{\Omega}, \widehat{K}_2)$ with Newey–West standard errors and block-bootstrap CIs (Eq. (11)).
4. **Slow-band coherence:** demodulate around $f_{\text{slow}} = f_+ - f_-$ and compute $\Lambda = C_{V\sigma}(f_{\text{slow}})$, using 1000-fold temporal shuffling for confidence intervals.
5. **Parity control:** repeat the regression using the full-cycle strobe (odd parity). Report the alternation index and loss of common quadratic curvature as in A.

Level-1 pass/fail criteria.

Evidence consistent with the dual-field locking picture in homeostatic monolayers:

- (E1) two resolved carrier peaks $f_\pm$ with $f_{\text{slow}} = f_+ - f_-$ above noise;
- (E2) $\Lambda > 0.6$ at f_{slow} (95% CI) under neutral strobing;
- (E3) $\widehat{\Omega}$ lies within ± 0.1 rad of $\Omega_{2/21} = \pi \cdot 2/21$, and switching parity (even→odd) disrupts common curvature / increases alternation index.
  Because most public datasets lack independent estimates of $(D_V, \tau_m, \kappa, \eta, \ldots)$, criterion (E3) is interpreted as a reduced form of P2: $\widehat{\Omega}$ is obtained from $r_{\text{eff}} = f_-/f_+$ rather than from full parameter provenance.
- (E4) $\widehat{K}_2 > 0$ with significant slope (two-tailed $p < 0.05$).

Contra-evidence in the same datasets:

- (C1) no resolvable f_{slow} or $\Lambda < 0.2$;
- (C2) $\widehat{\Omega}$ displaced > 0.2 rad from $\Omega_{2/21}$ with tight CI, or non-significant K_2 regression;
- (C3) parity switching fails to alter alternation / common-curvature metrics.

Candidate repositories and data modalities Suitable material is expected in (i) traction-microscopy movies (micropillar arrays, TFM), (ii) AFM-based viscoelastic sweeps on confluent epithelia, and (iii) GEVI/dye voltage recordings of confluent monolayers. When only one channel (electrical or mechanical) is available, the analysis is included in an exploratory label and not counted toward Level-1 criteria.

Negative and adversarial controls Fixed-cell preparations (no dynamics), sparse low-density cultures lacking collective mechanics, and small-molecule decoupling of the cortex (e.g. actomyosin inhibition) are expected to suppress K_2 and lower Λ. Off-strobe windows (misaligned stroboscopic sampling) serve as additional negative controls.

Reporting For each dataset a one-page report will be generated, including QC plots, $S_V(f)$ and $S_\sigma(f)$, slow-band spectra, $(\widehat{\Omega}, \widehat{K}_2, \Lambda)$ with confidence intervals, parity metrics, and pass/fail flags for (E1)–(E4). This reporting structure is preregistered to avoid hindsight tuning.

10 In-silico validation: continuum sandbox and cell-based models

Level A: continuum sandbox (overdamped PDE electromechanical coupler)
Eqs. 16–18 are integrated on a 2D periodic domain of linear size L using pseudo-spectral or finite-difference time stepping.

Parameters $(D_V, \tau_m, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma)$ are drawn from physiologically plausible priors; no ad hoc integer constraints are imposed. Observables are the spatial means $V(t) = \langle V(\mathbf{x}, t) \rangle$ and $\sigma(t) = \langle \sigma(\mathbf{x}, t) \rangle$, or equivalently the Fourier mode at $k^* = \pi/\ell$ (the mesoscale set by cortical thickness ℓ). The sandbox is required to reproduce: (i) two carrier peaks $f_\pm$ in the fast band generated by an *overdamped* dual-mode coupler, (ii) a slow interference band at $f_{\text{slow}} = |f_+ - f_-|$, (iii) neutral-moment stroboscopy (even parity) that yields a well-defined slow-phase map and estimates $(\widehat{\Omega}, \widehat{K}_2)$, and (iv) Monte Carlo sampling over priors that places (Ω, K_2) near the 2/21 Arnold tongue while avoiding lower-order tongues for a non-negligible fraction of draws. Weak external drives (electrical or mechanical) at f_{slow} are then applied to test phase-targeted entrainment (P3) by checking whether,

relative to matched off-band controls, an on-band drive produces $\Delta\Lambda > 0$ together with a drop in neutral-map angular variance $\mathrm{Var_{map}}$.

Level B: cell-based model (vertex / Cellular Potts / agent-based) A confluent epithelial sheet is simulated with explicit cells and a diffusive bioelectric layer. Each cell i carries a transmembrane potential V_i with gap-junctional coupling; the mechanical sheet is represented as an *overdamped* (first-order) vertex / Cellular Potts / agent-based layer whose active cortical tension is modulated by V. Readouts are processed through exactly the same analysis pipeline as in experiments: estimation of $S_V(f)$ and $S_\sigma(f)$, detection of the two fast-band carriers $f_\pm$ and the slow beat $f_{\mathrm{slow}} = |f_+ - f_-|$, neutral-moment stroboscopy (even parity) to obtain $(\widehat{\Omega}, \widehat{K}_2)$, and slow-band electromechanical coherence Λ at f_{slow}.

Phase-targeted entrainment tests and falsification To assess P3, a weak periodic drive is applied at f_{slow}: (i) an electrical perturbation $V \leftarrow V + A_V \sin(2\pi f_{\mathrm{slow}} t)$ (globally or within a subdomain), and/or (ii) a mechanical/traction drive $A_\sigma \sin(2\pi f_{\mathrm{slow}} t)$. Controls use off-resonant drives at $f_{\mathrm{slow}}(1 \pm 0.10)$ with amplitude and duty cycle matched to the on-band drive (equal-energy "sham"), so that any improvement in locking must be frequency-specific rather than a generic power injection. The primary endpoints are (a) $\Delta\Lambda > 0$ specifically under on-band drive, and (b) a selective reduction in $\mathrm{Var_{map}}$ (interpreted as reduced spindle-angle dispersion) under on-band drive but not under the off-band controls. Secondary endpoints include an increase in the even-harmonic coupling estimate $\widehat{K}_2$. Falsification criteria are: absence of a resolvable f_{slow} band, persistently low coherence ($\Lambda < 0.2$), non-significant even-map regression (ill-defined $\widehat{\Omega}$ or $\widehat{K}_2$), or lack of on-band specificity relative to off-resonant controls. G implements and prevalidates this logic in silico.

10.1 Reference implementation (concept and usage)

Purpose. Listing L (L) is a minimal, CPU-light reference implementation of the dual-field sandbox. It operationalizes P1 and P2 (shared slow-band cadence, placement of (Ω, K_2) in the 2/21 tongue) and reproduces the basic Case D "recovery by on-band entrainment" scenario.

G adds a dedicated script (Listing L) that implements the full preregistered P3 assay, including off-band controls and $\mathrm{Var_{map}}$.

What it does. In each run the code:

1. generates two *latent carriers* in the fast band with small noise and slow drift (either by integrating the full overdamped PDE coupler or by using a lightweight two-carrier signal generator with the same structure);
2. computes Welch spectra $S_V(f)$, $S_\sigma(f)$ and the magnitude-squared coherence $\Lambda(f)$;
3. identifies the carrier pair (f_-, f_+) and the slow interference cadence $f_{\mathrm{slow}} = |f_+ - f_-|$;
4. performs neutral-moment stroboscopy (even parity) and regresses the even slow-phase map to estimate $(\widehat{\Omega}, \widehat{K}_2)$;
5. optionally applies a weak, narrow-band drive during a defined time window (phase-targeted entrainment test) and reports $\Delta\Lambda$;
6. saves diagnostic figures (space–time $V(x,t)$, spectra with $f_\pm$ and f_{slow}, and time-resolved $\Lambda(t)$) and prints summary diagnostics.

How it is used here. For the illustrative regimes in Cases A–D, the same pipeline is run

Regime	Inputs (relative to baseline)	Expected signatures (pipeline readouts)
(A) Baseline (locked)	Physiological-scale priors; no external drive	Narrow $f_\pm$, resolved f_{slow}, $\Lambda \gtrsim 0.6$, and stable (Ω, K_2) near the 2/21 tongue.
(B) Proliferative unlocking	$\beta_R \downarrow$, $\beta_I \uparrow$, $\tau_m \downarrow$, $D_V \downarrow$ (reduced coordinated coupling)	$\Lambda \downarrow$; Ω broader and/or shifted away from $\pi \cdot 2/21$; weakened even-parity structure.
(C) Aging / overlock	$\kappa, \eta \uparrow$ (stiffer, more dissipative sheet)	High yet slowly declining Λ; $\Omega \downarrow$; increased K_2 (stronger even-harmonic feedback).
(D) Entrainment (recovery)	Weak on-band drive at f_{slow} with matched off-band / sham controls	On-band $\Delta\Lambda > 0$ and $K_2 \uparrow$; off-band $\approx$ null.

Table 2: Checklist of in-silico regimes (Cases A–D). "Inputs" are controlled perturbations to the baseline draw from physiological priors; "Expected signatures" are the corresponding readouts of the same analysis pipeline used for experimental data. Full code, including parameter dictionaries and drive protocol, is provided in L.

on a lightweight signal generator (two carriers, controlled noise, slow drift) to make the logic transparent. The parameter tweaks defining each regime are summarized in Table 2 and listed explicitly in L. Listing L in L is the pseudo-spectral reference implementation of this workflow.

How to run and modify. The implementation depends only on standard scientific Python (NumPy, SciPy, Matplotlib, and a basic linear-regression routine). Running the main script produces: (i) a figure with three panels (space–time signal, spectra with $f_\pm$ and f_{slow}, and $\Lambda(t)$); (ii) numerical estimates of f_-, f_+, f_{slow} and $\Lambda(f_{\text{slow}})$; (iii) $(\widehat{\Omega}, \widehat{K}_2)$ and, if an on-band drive was applied, $\Delta\Lambda$ comparing driven vs. undriven windows. Stable, high Λ corresponds to locking (Case A); low, bursty Λ corresponds to unlocking (Case B/B'); a gently declining $\Lambda(t)$ corresponds to overlock with drift (Case C); and an on-band increase in Λ under weak drive corresponds to partial recovery by phase-targeted entrainment (Case D).

Scope. The sandbox is designed to validate the dynamical mechanism captured by P1 and P2, and to generate preregisterable targets for P3. It is not a molecular-scale model; its role is to link measurable electromechanical parameters to slow-phase locking, coherence Λ, division geometry, and responsiveness to weak on-band entrainment.

The explicit computational prevalidation of P3, including frequency-specific rescue of Λ and suppression of Var_{map} under on-band (but not off-band) drive, is provided in G; see also Figs. G.2 and G.1.

11 Reproducible in-silico regimes: implementation and outputs

Case A – Baseline (locked) *Setup.* Carrier frequencies in the $\sim$1–2 Hz band (e.g. $f_- \approx 1.6$ Hz, $f_+ \approx 2.0$ Hz). Both $V(t)$ and $\sigma(t)$ contain these carriers with small noise and minimal detuning. No external drive is applied.

Expected outcome. Narrow peaks at f_- and f_+; a slow interference band at $f_{\text{slow}} = |f_+ - f_-|$ in the sub-Hz range; $\Lambda \gtrsim 0.6$ at f_{slow}; and stroboscopic estimates $(\widehat{\Omega}, \widehat{K}_2)$ lying near the center of the 2/21 tongue (i.e. close to $\Omega_{2/21} = \pi \cdot 2/21$ with nonzero K_2).

Diagnostics (illustrative numbers).

- Carrier estimate: $f_- \in [1.55, 1.70]$ Hz, $f_+ \in [1.95, 2.05]$ Hz; $f_{\text{slow}} \approx 0.37$–$0.40$ Hz.
- $\Lambda(f_{\text{slow}}) \geq 0.60$; median $\Lambda(t)$ typically 0.5–0.8 with only small window-induced ripples.
- Neutral-moment stroboscopy: thousands of strobes in ~ 600 s; even-map regression with circular $R^2 \gtrsim 0.4$; $\widehat{\Omega}$ within ± 0.2 rad of $\pi \cdot (2/21)$.

Figure 11.1: Case A (baseline/locked). The slow band at f_{slow} is present and $\Lambda(t)$ remains high; $(\widehat{\Omega}, \widehat{K}_2)$ fall near the 2/21 tongue. All figures for Cases A–D are generated automatically by the same analysis pipeline.

Quick internal checks.

- **Phase alignment control:** force V and σ to be trivially aligned (identical carrier mixtures, no relative precession).
  Prediction: the slow-band structure and the neutral-moment even-map fit degrade, confirming that the locking signature depends on a small but finite electromechanical lag.
- **Mild detuning robustness:** shift $f_{\pm}$ by ± 0.02 Hz.
  Prediction: f_{slow} and elevated Λ persist, indicating tolerance to small detuning.

Case B – Proliferative unlocking (moderate) We emulate proliferative unlocking by selectively degrading coordinated electromechanical coupling in the mechanical surrogate $\sigma(t)$: we weaken the in-phase component, introduce slow drift in the σ phase, add modest detuning only in σ, and increase its noise.

Implementation (summary; details in L).

- Keep $V(t)$ carriers near the baseline pair (~ 1.6 Hz, ~ 2.0 Hz).
- Reduce the in-phase carrier weights in $\sigma(t)$.
- Impose a slow phase drift and mild frequency detuning in σ only.
- Add moderate noise to σ.
- Track time-resolved coherence $\Lambda(t)$ at f_{slow} using a fixed window (e.g. 20 s) and a ± 0.05 Hz band.

Expected outcome. $S_\sigma(f)$ broadens around $f_{\pm}$ relative to $S_V(f)$; f_{slow} remains detectable; and $\Lambda(t)$ shows a lower and more bursty baseline than in Case A, typically ~ 0.4–0.6 with transient drops below 0.3. This corresponds to partial unlocking and reduced slow-phase coordination.

Figure 11.2: Case B (proliferative unlocking, moderate). Left to right: (a) toy space–time $V(x,t)$; (b) power spectra with broadened S_σ (orange); (c) $\Lambda(t)$ showing a lower, burstier baseline compared with Case A, including transient drops.

Case B' – Strong proliferative unlocking (sensitivity)   To stress-test the signature of unlocking, we push decoupling harder by further weakening in-phase alignment, adding stronger detuning, and injecting an off-band mechanical component.

Implementation (summary).

- Strongly suppress the in-phase carrier contribution in σ.
- Impose larger carrier-frequency detuning in σ.
- Add a weak off-band tone (e.g. ~ 0.9 Hz) to σ.
- Increase σ-channel noise.
- Recompute $\Lambda(t)$ around f_{slow} with a longer window (e.g. 30 s) and a narrower band (± 0.01 Hz).

Result. $S_\sigma(f)$ broadens substantially and develops an off-band shoulder around the injected ~ 0.9 Hz component.

In an experimental setting this would flag non-resonant mechanical drive or uncoordinated contractile noise. $\Lambda(t)$ shows a much lower baseline and bursty excursions, with median values often in the ~ 0.2–0.4 range.

This captures the expected trend **proliferative unlocking $\Rightarrow$ coherence loss** (P1).

Figure 11.3: Case B' (strong unlocking). Left to right: (a) $V(x,t)$ toy pattern; (b) power spectra with broadened S_σ (orange) and an off-band sub-peak near ~ 0.9 Hz; (c) time-resolved coherence $\Lambda(t)$ with a reduced baseline and bursty profile.

Case C – Aging / overlock   We emulate aging / overlock by increasing effective stiffness and viscosity: $\kappa \uparrow, \eta \uparrow$.

This shifts carriers slightly lower in frequency, strengthens even-harmonic feedback, and reduces adaptability while maintaining high coherence.

Implementation (summary).

- Shift both carrier frequencies slightly lower (e.g. $f_- \approx 1.5$ Hz, $f_+ \approx 1.85$ Hz).
- Impose a slow amplitude decay in $\sigma(t)$ and a small, quasi-static phase bias between V and σ.
- Keep noise relatively low.
- Track $\Lambda(t)$ with a sliding window and plot a smoothed trend.

Expected outcome. A lower carrier pair in the 1–2 Hz band; $\Lambda(t)$ remains high but displays a gentle downward drift over time (reduced adaptability); and the neutral-moment regression returns a modestly increased K_2, consistent with stronger even-harmonic feedback.

Figure 11.4: Case C (aging / overlock). Left to right: (a) $V(x,t)$ toy pattern; (b) power spectra showing the lowered carrier pair; (c) time-resolved coherence $\Lambda(t)$ with a slowly declining trend over the run.

Case D – Recovery by on-band entrainment Starting from an unlocking configuration (Case B), we apply a weak global drive at the slow cadence f_{slow} during a limited time window to test phase-targeted entrainment (P3). Case D demonstrates qualitatively that an on-band drive can transiently restore coordination between V and σ.

G formalizes this by adding symmetric off-band controls ($\pm 10\%$ detuning), quantifying $\Delta\Lambda$ and $\mathrm{Var}_{\mathrm{map}}$, and spelling out preregistered falsification criteria.

Implementation (summary).

- Add to $V(t)$ a small sinusoidal drive at f_{slow} during a defined time window (tens of seconds).
- Keep the drive amplitude low enough that the carrier peaks $f_\pm$ shift by no more than $\sim$ 1–3%.
- Repeat with an *off-band* control drive at frequency $f_{\mathrm{slow}} \cdot (1 + 0.10)$, with amplitude and duty cycle matched to the on-band drive.
- Define $\Delta\Lambda \equiv \overline{\Lambda}_{\mathrm{in}} - \overline{\Lambda}_{\mathrm{out}}$, where "in" refers to the drive window and "out" to the surrounding baseline.

Result. In Case D, the on-band drive produces an increase in $\Lambda(t)$ confined to the driven window, yielding $\Delta\Lambda > 0$, while an off-band control with matched amplitude and duty cycle produces $\Delta\Lambda \approx 0$. Carrier frequencies $f_\pm$ remain essentially unchanged, indicating that the drive is weak and spectrally specific rather than a gross perturbation.

G extends this test and shows that, in a proliferative-like unlocked state with high $\mathrm{Var}_{\mathrm{map}}$, a weak on-band drive at f_{slow} simultaneously increases Λ and reduces $\mathrm{Var}_{\mathrm{map}}$,

whereas off-band drives of identical amplitude fail to reproduce both effects together. This behavior is the in-silico analogue of phase-targeted entrainment (P3).

Figure 11.5: Case D (recovery by on-band entrainment). Left to right: (a) $V(x,t)$ toy pattern; (b) power spectra (carrier peaks unchanged, consistent with a weak drive); (c) time-resolved coherence $\Lambda(t)$: the on-band drive (solid) increases Λ inside the shaded window, whereas the off-band control (dashed) shows no effect despite matched amplitude and duty cycle.

Scope and extensions These in-silico regimes are designed to validate the *dynamic* mechanism summarized by P1–P3: slow-phase locking with high Λ, proliferative unlocking with reduced Λ and bursty coherence, aging-like overlock with rigid high Λ but reduced adaptability, and recovery by weak on-band entrainment with frequency-specific rescue of Λ and suppression of $\mathrm{Var}_{\mathrm{map}}$. In baseline draws from physiological-scale priors, $\Lambda(f_{\mathrm{slow}}) > 0.6$ occurs for a non-negligible fraction; on-band drives produce selective improvements that off-band drives (detuned by $\sim 10\%$) do not.

Extension to 2D/3D sheets introduces anisotropic carriers and potentially multiple slow interference modes. Neutral-moment locking remains applicable provided local homogeneity at the mesoscale $k^* = \pi/\ell$. Weak broadband noise can assist coherence (stochastic resonance) but amplitudes must remain below thresholds that shift $f_\pm$ or cause damage in vitro.

All implementation details (parameter dictionaries for Cases A–D, drive schedules, plotting commands) are consolidated in L, and the full preregistered P3 prevalidation (including off-band controls and $\mathrm{Var}_{\mathrm{map}}$) is given in G.

12 Results: analytical and numerical evidence

Before turning to width bounds and numerical scans, we summarize how the reduced even circle map arises from the overdamped electromechanical model. Starting from the continuum coupler (Eqs. 16–18), we project onto two latent carriers with complex eigenfrequencies $\Omega_\pm$ (Eqs. 1–4), whose real parts define the fast-band pair $f_\pm$ and hence the slow beat $f_{\mathrm{slow}} = |\Omega_+ - \Omega_-|/(2\pi)$. In the time domain, we then identify neutral crossings $\{\tau_n\}$ where the electrical and mechanical phases momentarily align modulo π with positive slope (Appendix E). Sampling the fast phase at these times, $\theta_n = \phi_+(\tau_n)$, yields the neutral-moment stroboscopic map

$$\theta_{n+1} = \theta_n + \Omega - K_2 \sin(2\theta_n) \pmod{\pi},$$

with forcing Ω fixed by the carrier ratio $r_{\mathrm{eff}} = f_-/f_+$ and even-harmonic coupling K_2 estimated from regression at neutral moments. The analytical structure of this even

(mod π) map, and its numerical Arnold tongue diagram in the (Ω, K_2) plane, are developed in Appendix J.

12.1 Analytical width bounds

To characterize slow-phase locking we consider the even circle map

$$\theta_{n+1} = \theta_n + \Omega - K_2 \sin(2\theta_n) \quad (\text{mod } \pi),$$

sampled at the neutral moment. For $K_2 \ll 1$, the Arnold tongue of a rational lock p/q has a width in Ω that scales as

$$\Delta\Omega_{p/q} = \mathcal{O}(K_2^q).$$

Low-order ratios (small q, such as $1/2$, $1/3$, $2/5$) therefore occupy parametrically broader regions of the (Ω, K_2) plane, whereas higher-order ratios (large q) carve out much narrower slivers. This scaling suffices to rank low versus high order and to motivate P2: within physiological variability of (Ω, K_2), it should be feasible to avoid persistent capture by $q \le 6$ tongues while still intersecting the narrow $2/21$ tongue, centred at $\Omega_{2/21} = \pi \cdot 2/21 \simeq 0.30$ rad.

Importantly, this construction means that the $2/21$ plateau is not chosen by hand. Once the two fast carriers $f_\pm$ have been measured, the effective forcing Ω is fixed (up to uncertainty) by their ratio $r_{\text{eff}} = f_-/f_+$ via $\Omega \simeq \frac{\pi}{2}(1 - r_{\text{eff}})$. Together with an independent estimate of the even coupling K_2 from neutral-moment regression, this defines a narrow physiological strip in the (Ω, K_2) plane. Because low-order tongues p/q with $q \le 6$ are parametrically wide whereas higher-order tongues are much narrower, requiring that this strip avoid the broad low-order plateaus while still permitting slow-phase capture leaves very little freedom: within the measured range of (Ω, K_2) the first accessible high-order plateau of the even map is precisely the $2/21$ tongue. In this sense the integer ratio $2/21$ is not tuned as an extra parameter; it emerges from the carrier frequencies and the tongue-width hierarchy encoded in the even map.

12.2 Sensitivity and low-order exclusion for P2

In the overdamped dual-field picture, the slow forcing follows the carrier-frequency ratio:

$$\Omega \simeq \frac{\pi}{2}\left(1 - r_{\text{eff}}\right), \qquad r_{\text{eff}} \equiv \frac{f_-}{f_+},$$

so small changes obey

$$d\Omega \simeq -\frac{\pi}{2} dr_{\text{eff}}, \qquad \frac{dr_{\text{eff}}}{r_{\text{eff}}} = d\ln f_- - d\ln f_+. \tag{13}$$

For weak electromechanical coupling the carrier split is small. Writing $f_\pm = f_c \pm \frac{1}{2}\Delta f$ with $f_c = \frac{1}{2}(f_+ + f_-)$ a local mean,

$$r_{\text{eff}} \approx 1 - \frac{\Delta f}{f_c}, \qquad \Omega \approx \frac{\pi}{2}\frac{\Delta f}{f_c}.$$

At a coarse-grained level the split scales like

$$\Delta f \propto \frac{\Gamma}{g(a,b)}, \quad \Gamma = |\gamma|\,\beta_R, \quad a = \tau_m^{-1} + D_V k^{*2}, b = \kappa + D_\sigma k^{*2}, \quad k^* = \pi/\ell,$$

where $g(a, b) > 0$ lump the electrical and mechanical dissipative blocks. The relative sensitivity of Ω can then be organized as

$$d\ln\Omega \approx d\ln\Gamma - d\ln g(a, b) - d\ln f_c, \tag{14}$$

which depends only on coupling strength and dissipation, without invoking areal inertia.

Operationally, we (i) estimate σ_Ω from neutral-moment regression using Newey-West robust errors, (ii) compute the distance in Ω to the nearest low-order centre $\{1/2, 1/3, 2/5\}$, and (iii) require simultaneously that the safety margin $\Delta\Omega_{\text{low}} \geq 3\,\sigma_\Omega$ and that Monte Carlo over physiological priors places (Ω, K_2) inside the 2/21 tongue with probability at least 0.3.

(Ω, K_2) should sit in or near the 2/21 strip at a distance from broad low-order tongues that is large compared with its own uncertainty. This implements P2 as an exclusion rule: tissues that live in the narrow 2/21 region while steering clear of wide low-order tongues are deemed phase-selected; tissues that sit in a broad low-order wedge, or never approach 2/21, are not.

Numerically, Monte Carlo sampling over physiological priors for the parameter vector

$$\mathbf{p} = (\tau_m, D_V, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma, \ell)$$

populates a compact band in the (Ω, K_2) plane that overlaps the 2/21 tongue while remaining separated from the centres of the $q \leq 6$ tongues by several σ_Ω (Appendix J). This acts as a coarse-grained phase diagram: typical parameter draws visit the 2/21 strip but do not realize persistent capture in low-order wedges, reinforcing that the 2/21 plateau is a robust outcome of physiological parameter variability rather than a fine-tuned choice.

12.3 Phase-locking geometry in the even convention

Figure 12.1: **Electromechanical locking landscape in the even (mod π) convention.** **(a)** Schematic (Ω, K_2) plane for the even circle map $\theta_{n+1} = \theta_n + \Omega - K_2 \sin 2\theta_n \pmod{\pi}$ sampled at the neutral moment. The shaded vertical band marks the strip around $\Omega_{2/21} = \pi \cdot 2/21 \simeq 0.30$ rad, interpreted here as the high-order 2/21 tongue. Farther to the right, broad low-order tongues (e.g. 1/3, 1/2) open near $\Omega \simeq \pi/2$ and occupy a larger region. **(b)** Stylized devil's staircase view of the locked ratio $\rho_\pi(\Omega)$ versus Ω in the same even convention, highlighting the narrow 2/21 plateau and broad low-order plateaus.

Figure 12.1 summarizes the slow-phase geometry. In panel (a) the tissue is placed on the (Ω, K_2) plane of the even map under neutral-moment stroboscopy. Ω is the effective

slow forcing set by the beat between the two latent carriers; K_2 is the even-harmonic feedback strength estimated from data. The vertical band around $\Omega_{2/21}$ represents the 2/21 tongue; farther to the right schematic wedges denote broad low-order tongues. P2 asks whether homeostatic epithelia systematically fall inside the narrow 2/21 strip while avoiding the wide low-order regions.

Panel (b) recasts the same structure as a staircase $\rho_\pi(\Omega)$, with ρ_π the effective winding number (locked ratio between slow-phase advance and the neutral strobe). The 2/21 plateau is narrow in Ω compared with generic low-order plateaus such as 1/3 or 1/2. In this picture, proliferative unlocking corresponds to drift away from the 2/21 plateau, and aging/overlock corresponds to remaining trapped in a broad low-order wedge with reduced adaptability.

While Fig. 12.1 is schematic, the same structure arises from direct numerical analysis of the even (mod π) phase map. The existence of a narrow 2/21 locking tongue is not imposed by construction but emerges from the reduced equations used for the electromechanical analysis. To verify this numerically, we scanned the (Ω, K_2) plane and estimated the rotation number $\rho = f_1/f_2$ from long integrations of the coupled-phase model. A zoom around the 2/21 tongue and a transverse cut at $\Omega = 2/21$ are shown in J, Figs. J.1 and J.2. These calculations confirm that the parameter range used for the electromechanical map lies in the transition region between the 2/21 plateau and the onset of near-1:1 locking, rather than deep inside a low-order tongue.

12.4 Slow-band spectra and coherence (P1)

The first empirical prediction (P1) targets a directly measurable signature of dual-field interference. In frequency space, the model predicts an electromechanical slow cadence f_{slow} that is shared by the bioelectric sector $V(\mathbf{x}, t)$ and the mechanical sector $\sigma(\mathbf{x}, t)$.

Figure 12.2: **Slow-band spectra and coherence supporting P1.** Slow-band power spectra of voltage (S_V^{slow}, blue) and cortical stress (S_σ^{slow}, orange), together with the cross-spectral coherence $C_{V\sigma}$ (red). All three display a narrow peak at the same low frequency $f_{\text{slow}} \approx 0.38$ Hz (vertical line). P1 asks for this signature in homeostatic monolayers: both V and σ exhibit slow-band power concentrated at a common cadence f_{slow}, and the coherence at that cadence, $\Lambda = C_{V\sigma}(f_{\text{slow}})$, is high.

Figure 12.2 illustrates the expected pattern: the slow-band voltage spectrum $S_V^{\text{slow}}(f)$ and the slow-band stress spectrum $S_\sigma^{\text{slow}}(f)$ both exhibit a narrow peak at f_{slow}, and the cross-spectral coherence $C_{V\sigma}(f)$ is also high at that same frequency. We summarize this by the scalar

$$\Lambda \equiv C_{V\sigma}(f_{\text{slow}}).$$

According to the model, a reproducible, narrowband, high-coherence slow peak ($\Lambda \gtrsim 0.6$) in homeostatic monolayers constitutes P1. Failure to observe a shared slow-band peak or obtaining $\Lambda \ll 0.6$ under quasi-homeostatic conditions would refute P1 for that tissue.

12.5 Common-curvature signatures (preliminary *in silico*)

Using synthetic data matched to the prevalidation regime ($f_{\text{slow}} \simeq 0.38$ Hz; $f_{\pm} \simeq 1.6,\ 2.0$ Hz), we construct "biological King plots" for three observables: the peak of S_V^{slow}, the peak of S_σ^{slow} and $\log \Lambda$, all evaluated under the neutral-moment strobe. Regressing each observable Y against a morphology-weighted slow-map shift X yields nearly identical quadratic curvature across all three, which we refer to as the common-curvature signature.

Figure 12.3: **Biological King plot (schematic).** Quadratic fits of slow-band observables Y versus a morphology-weighted slow-map shift X under neutral-moment stroboscopy (even convention) for synthetic data: peak of S_V^{slow}, peak of S_σ^{slow} and $\log \Lambda$. The three curves share nearly identical quadratic curvature, consistent with a common electromechanical interference mode at f_{slow}. Full details are given in A.

When the analysis is repeated with a full-cycle strobe (odd parity), odd contributions appear, the alternation index increases and the cross-observable quadratic collapse is lost (A). This parity control acts as an internal check that the slow band is genuinely electromechanical.

12.6 Fast-band spectra (carriers $f_{\pm}$)

The model predicts that the cortex supports two weakly coupled latent carriers in the 1–3 Hz band: an electrical branch and a mechanical branch with slightly different carrier frequencies. We denote these f_- and f_+ and interpret their small frequency offset as the source of the slow interference beat $f_{\text{slow}} = |f_+ - f_-|$.

In the coupled two-mode generator (Eqs. 1–4), these carriers correspond to the two damped eigenfrequencies $\Omega_{\pm}$, and the slow beat is $f_{\text{slow}} = |\Omega_+ - \Omega_-|/(2\pi)$ in the desynchronized regime; under locking the split collapses and $f_{\text{slow}} \to 0$. The fast-band spectra in Fig. 12.4 are therefore the direct spectral manifestation of the same dual-mode structure that sets Ω, K_2 and Λ.

13 Pre-experimental validation of mode selection

We check, prior to any wet-lab test, that the combination of oscillatory reduction, viscoelastic mechanics, weak phase-lag coupling, and neutral-moment strobing can place the system near the 2/21 lock without inserting integers by hand.

Figure 12.4: **Fast-band power spectra and carrier peaks.** Fast-band power spectra of voltage (S_V^{fast}, blue) and cortical stress (S_σ^{fast}, orange). Both channels exhibit two carrier peaks in the 1–3 Hz range: one near f_- and one near f_+ (dashed lines). The offset between these carriers is the source of the slow interference cadence $f_{\text{slow}} = |f_+ - f_-|$.

13.1 Slow forcing from the carrier ratio

At leading order, the slow forcing of the even map is controlled by the ratio of the two damped carriers produced by the latent-mode generator. Denoting by $\Omega_\pm$ the observable carrier angular frequencies of Eqs. 3–4, we use

$$\Omega \simeq \frac{\pi}{2}\left(1 - r_{\text{eff}}\right), \qquad r_{\text{eff}} \equiv \frac{\Omega_-}{\Omega_+} = \frac{f_-}{f_+}, \qquad 0 < r_{\text{eff}} \leq 1. \tag{15}$$

This expression is dimensionless, invariant to absolute projection gains, and valid when both carriers are resolvable ($|\Delta\omega| > 2|J|$). In the synchronized regime ($|\Delta\omega| \leq 2|J|$) the split collapses, $r_{\text{eff}} \to 1$, and $\Omega \to 0$, consistently with a vanishing beat.

Practically, $\Omega_\pm$ (or $f_\pm = \Omega_\pm/2\pi$) are estimated from the carrier peaks of S_V and S_σ (Level-1 pipeline). The ratio $r_{\text{eff}} = f_-/f_+$ is then plugged into Eq. (15) to obtain the slow forcing Ω, while the even feedback K_2 is obtained from neutral-moment stroboscopic regression (Eq. 11).

Compared with the full primitive parameter set, the slow forcing is thus controlled at first order by a single lumped ratio r_{eff}, with dissipation and quadrature components acting mainly through K_2 and higher-order corrections to Ω.

13.2 Example parameter set and proximity to the $2/21$ lock

Using a physiologically plausible set of parameters not tuned to any rational ratio (viscoelastic stiffnesses placing the mechanical branch in the $1--3$ Hz band, weak electromechanical coupling with a small quadrature component, and a mesoscale thickness $\ell \sim 500\,\mu\text{m}$), a forward model of the linear electromechanical spectrum gives

$$\Omega_{+,r} \approx 12.43\,\text{rad/s}\ (f_+ \approx 1.98\,\text{Hz}), \quad \Omega_{-,r} \approx 10.05\,\text{rad/s}\ (f_- \approx 1.60\,\text{Hz}),$$

so that $r_{\text{eff}} = 0.8089$ and

$$\Omega = \frac{\pi}{2}\left(1 - r_{\text{eff}}\right) \approx 0.3005\,\text{rad},$$

which lies close to the center of the $2/21$ tongue ($\Omega_{2/21} = \pi \cdot 2/21 \simeq 0.2992\,\text{rad}$). The associated slow cadence is

$$f_{\text{slow}} = \frac{\Omega_{+,r} - \Omega_{-,r}}{2\pi} \approx 0.378\,\text{Hz}.$$

A coarse $\pm 20\%$ sweep over stiffnesses and thickness ℓ (keeping coupling weak) yields $\Omega = 0.314 \pm 0.186$ rad (mean $\pm$ s.d.), with about 40% of draws within ± 0.1 rad of $\Omega_{2/21}$ and a non-negligible subset within ± 0.02 rad. Within this overdamped dual-field picture, typical cortical-scale electromechanical parameters can therefore place (Ω, K_2) in the vicinity of the 2/21 tongue without explicit integer fitting.

13.3 Implications for P1–P3

In the proposed framework, P1, P2, and P3 become concrete checks on the same reduced variables. With (Ω, K_2) obtained from carrier ratios and neutral-moment regression, and Λ from slow-band coherence:

- P1 is supported if V and σ share a narrow slow-band peak at f_{slow} with high cross-spectral coherence, $\Lambda = C_{V\sigma}(f_{\text{slow}}) \gtrsim 0.6$; absence of a shared peak or $\Lambda \ll 0.6$ would refute P1 for that tissue and condition.
- P2 is supported if (Ω, K_2) lies inside the 2/21 tongue while maintaining a safety margin to low-order tongues ($q \leq 6$) that is large compared with the uncertainty on Ω; systematic displacement outside 2/21 or persistent capture by a broad low-order tongue would not support the proposed selection mechanism.
- P3 is supported if a weak external drive at f_{slow} produces a selective increase in Λ and a selective decrease in Var_{map} relative to off-resonant controls of matched amplitude and duty cycle; absence of frequency specificity would refute phase-targeted entrainment under those conditions.

These criteria can be evaluated without further structural assumptions once $f_{\pm}$, f_{slow}, (Ω, K_2), and Λ have been measured.

14 Robustness, physiological levers, and scope

We assess how independently measurable parameters move the slow-phase control point (Ω, K_2) in the even-map Arnold diagram under the overdamped dual-field model. The key observable is

$$\Omega \simeq \frac{\pi}{2}\left(1 - r_{\text{eff}}\right), \qquad r_{\text{eff}} \equiv \frac{f_-}{f_+} \ \text{ at } \ k^* = \pi/\ell,$$

so that small shifts in the carrier pair (f_-, f_+) directly displace the slow forcing. Using the sensitivity relations in Eqs. 13–14, these shifts can be organized in terms of a coarse-grained split

$$\Delta f \propto \frac{\Gamma}{g(a,b)}, \ \Gamma = |\gamma|\beta_R, \ a = \tau_m^{-1} + D_V k^{*2}, \ b = \kappa + D_\sigma k^{*2}, \ k^* = \pi/\ell,$$

with $g(a,b) > 0$ a monotone lumping of electrical and mechanical dissipation. Intuitively, Ω is raised by stronger in-phase electromechanical coupling ($\Gamma \uparrow$) and reduced electrical dissipation ($a \downarrow$), and lowered by stronger mechanical dissipation ($b \uparrow$) or by an increased quadrature component β_I, which effectively reduces in-phase transfer.

Physiological levers Common electrical and mechanical perturbations shift (Ω, K_2) in predictable directions:

- *Electrical levers.* Changes in membrane time constant and voltage spread (τ_m, D_V) primarily act through $a = \tau_m^{-1} + D_V k^{*2}$. Shortening τ_m or increasing D_V tends to lower Ω; gap-junction blockade (lower D_V) or a longer τ_m tends to raise it. Modulators

that alter the phase of electromechanical transfer increase β_I and typically reduce Ω while weakening even-harmonic feedback.

- *Mechanical and ECM levers.* Cortex/ECM stiffening and increased viscous loss ($\kappa \uparrow, \eta \uparrow$) act through $b = \kappa + D_\sigma k^{*2}$, tending to lower Ω and, depending on geometry, to move K_2 either upward (stronger even feedback) or downward (dominant dissipation). Actomyosin inhibition or mechanical unloading reduce κ and η, generally raising Ω and in some cases increasing K_2 by reducing dissipation.
- *Morphology.* Changes in effective thickness ℓ move $k^* = \pi/\ell$ and thus both a and b. Thicker shells (larger ℓ) reduce k^* and typically raise Ω; thinner shells push k^* upward and tend to lower it.

In all cases, the net effect is a displacement of (Ω, K_2) relative to the 2/21 tongue, with corresponding changes in slow-band coherence Λ and spindle statistics. Sampling a physiological hyper-rectangle in $(\tau_m, D_V, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma, \ell)$ and mapping each draw to (Ω, K_2) provides a quantitative measure of how often typical parameter combinations visit the 2/21 strip or fall into broad low-order wedges.

Scope to other helices In principle, the same construction could be applied to other biological helices (e.g. RNA, collagen, microtubules) if suitable electrical and mechanical observables can be defined. In such cases, one would again identify a coupled carrier pair, construct the slow interference beat and the associated phase map, and ask whether a high-order locking window plays a comparable organizing role. This extension is not developed in detail here and is left as a possible direction for future work.

15 Limitations

The present framework assumes (i) weak phase-lag electromechanical coupling such that two fast-band carrier branches remain well defined with a small but resolvable split; (ii) approximate spatial uniformity at the mesoscale $k^* = \pi/\ell$ so that a single effective k^* represents the local patch; and (iii) approximate stationarity over the recording window so that the neutral-moment strobe samples a quasi-steady slow phase.

Stronger coupling or heterogeneous tissues could generate additional locking tongues, mixed parities (coexisting even- and odd-harmonic contributions), or multiple slow cadences not captured by the single-map reduction. Marked anisotropy or sharp curvature gradients may induce orientation-dependent carrier pairs and more than one beat within the same field of view, in which case the neutral-moment analysis is best applied patchwise.

The empirical estimate of K_2 inherits finite-sample bias and serial correlation from stroboscopic regression. We mitigate this with heteroskedasticity- and autocorrelation-robust errors plus block bootstrap, but very short recordings will be underpowered. Departures from quasi-stationarity (e.g. slow drifts in $a = \tau_m^{-1} + D_V k^{*2}$ or $b = \kappa + D_\sigma k^{*2}$) can blur the slow-band peak and inflate uncertainty on (Ω, K_2). Instrumental factors (dye kinetics in voltage imaging, motion coupling in stress readouts) should be characterized and, when possible, regressed out or incorporated via partial coherence.

15.1 Scope and extensions

Extension to 2D/3D tissues The one-dimensional reduction around a single mesoscale $k^* = \pi/\ell$ captures the slow interference that drives the even-map dynamics, but real epithelia are two- or three-dimensional. In 2D, anisotropic tissues admit a family of wavevectors on the ring $|\mathbf{k}| = k^*$, and directional anisotropy can split the carrier pair

differently along different orientations, potentially generating more than one slow cadence in the same field of view. Within a sufficiently local patch, one slow interference mode is typically dominant, and the neutral-moment stroboscopic analysis around f_{slow} remains meaningful for that patch. Tissue boundaries or curvature gradients enter as slow spatial drifts of k^*, which are already represented as shifts of a and b in the robustness analysis.

Molecular interface Small electrical manipulations (ion-channel modulation, gap-junction coupling) primarily move the forcing Ω via changes in τ_m and D_V, whereas mechanical levers (RhoA/ROCK activity, adhesion/anchoring complexes, stress redistribution D_σ) tend to modulate K_2 through the mechanical dissipative block $b = \kappa + D_\sigma k^{*2}$ and parity reinforcement. A more detailed mapping from specific molecular perturbations to (Ω, K_2, Λ), together with dedicated assays, is left for future work.

15.2 Limits of the weak-coupling approximation

The analytical structure used here (two fast-band carriers, a slow interference beat, and an even slow-phase map sampled at neutral moments) presumes weak phase-lag coupling, moderate quadrature components, and moderate viscous damping. As K_2 increases, Arnold tongues widen and acquire secondary resonances; for $K_2 \gtrsim 0.3$ mixed parities and quasi-periodic or weakly chaotic windows can appear, smearing the slow-band peak in $\Lambda(f)$. In homeostatic epithelia we expect K_2 in the 0.05–0.2 range, where the 2/21 prediction is robust and off-band entrainment remains largely ineffective.

Experimentally, external drive should remain weak enough not to shift the carrier peaks $f_\pm$ and should primarily test resonance specificity at the native f_{slow}, rather than induce new dynamical states. Near complete synchronization the carrier split may transiently collapse; in such intervals the neutral-moment (even-parity) sampling loses leverage, and odd-parity strobing plus multi-window estimation provide internal controls.

16 Conclusion

We proposed a falsifiable electromechanical slow-phase mechanism that links tissue-scale interference to a specific high-order lock without arbitrary integer fitting. The key observables are (i) a slow-band coherence peak Λ shared by bioelectric and cortical-stress channels, and (ii) a physically computed point (Ω, K_2) which, under neutral-moment strobing (even parity), falls inside the 2/21 tongue while avoiding broad low-order tongues. The 2/21 tongue is one of many possible lock-in regimes ("Arnold tongues") of the slow-phase map; its narrowness and high order make it both precise and fragile. A compact prevalidation plan (parameter lumping, parity-controlled diagnostics, and Monte Carlo robustness) turns this structure into experimentally testable predictions.

Physiological tissue is not expected to remain permanently in a purely antisymmetric or purely symmetric electromechanical configuration. Instead, it should alternate between these regimes along a slow cycle. Operationally, we sample the near-symmetric crossing – the neutral moment, defined by $\psi \equiv 0 \pmod{\pi}$ with positive slope – and use it as the Poincaré section for the slow phase. This yields an even $(\text{mod } \pi)$ circle map with forcing/coupling pair (Ω, K_2). In this picture, the slow cadence f_{slow} is not just a spectral line but the temporal signature of repeated alternation between antisymmetric bias and near-symmetric recombination.

We explicitly interpret pathology as the loss of this cycle. One failure mode is persistent unlocking: the system drifts out of 2/21, neutral crossings cease to recenter the slow phase, and spindle fidelity degrades (loss of robust cortical anchoring of the mitotic spindle). The

other failure mode is aging-like overlock: the system remains trapped near the neutral state, Λ stays high but plasticity collapses, and the antisymmetric exchange that normally refreshes division geometry is suppressed. In this view, "fine tuning" is replaced by an operational criterion: healthy tissue repeatedly re-enters the 2/21 window each slow cycle, whereas proliferative unlocking and aging overlock are opposite dynamical arrests of the same electromechanical process.

The link to nucleic-acid geometry is not invoked as a direct mechanical forcing of Ångström-scale pitch by a ~ 0.4 Hz tissue-scale cadence. Instead, the 2/21 lock is interpreted as a compatibility constraint between two coupled structures that must cooperate during mitosis: cortical anchoring of the spindle (set by the electromechanical interference modeled here) and torsional management of centromeric chromatin. In this interpretation, the apparent match to the canonical B-DNA helical pitch is read as an evolutionary canalization of a compatibility window, not as instantaneous macroscopic forcing of DNA.

Small tonic biases refine this picture. A sustained offset breaks the π-symmetry of the neutral map, converts the alternating exchange into a net pump on the slow envelope, and produces a non-monotonic dependence of slow-band power on bias. Moderate shifts can raise slow-envelope power even as Λ declines before the power peak; sufficiently large shifts can suppress alternation altogether. Likewise, parameter modulation (chemical or mechanical) moves (Ω, K_2) along state-dependent trajectories that are beneficial only within a finite window and overlocking or destabilizing outside it. This makes the 2/21 lock a precise yet fragile readout for distinguishing healthy cycling from dynamical arrest.

The mechanism is directly testable with existing tools. All required observables are accessible with optical electrophysiology, traction force microscopy, and standard cell-cycle imaging: simultaneous voltage and mechanical readouts in living tissue. In practical terms, the framework calls for four steps: measure f_{slow}; extract Λ at that cadence under neutral-moment strobing; locate (Ω, K_2) from independently measured electrical and mechanical parameters; and apply weak, phase-targeted entrainment at f_{slow} to ask whether spindle misorientation decreases relative to matched off-band controls.

G provides an *in silico* preregistration of this weak-drive experiment: in a proliferative-like unlocked state, a small on-band drive at f_{slow} selectively increases slow-band electromechanical coherence Λ and decreases the neutral-map angular noise Var_{map}, whereas equally weak off-band drives do not. Taken together, the framework yields a parity-resolved slow-phase map, identifies a specific high-order lock (2/21), and turns it into falsifiable experimental readouts – emerging without manual integer fitting – as a slow physical route to helical selection.

A Common-curvature diagnostics (SVD and alternation)

In the main text we define a "biological King plot" linking the slow-phase forcing Ω to slow-band observables: peak S_V^{slow}, peak S_σ^{slow}, $\log \Lambda$, and K_2. Operationally:

1. For each controlled condition A_k, estimate $\Omega(A_k)$ via neutral-moment stroboscopy (even map).
2. Compute $Y^{(j)}(A_k)$ for each observable j: peak S_V^{slow}, peak S_σ^{slow}, $\log \Lambda$ and K_2.
3. Apply morphology rescaling with $m_{A_k} \propto 1/h$ (thickness proxy) to form X_k and $Y_k^{(j)}$ as in Eq. (12).
4. Fit the neutral-strobe quadratic relation

$$Y^{(j)} = A^{(j)} + B^{(j)} X + \kappa_{\text{uni}} X^2 + r^{(j)}.$$

Under neutral-moment strobing, all observables share approximately the same quadratic

curvature κ_{uni}. This is consistent with the view that voltage slow-band power, cortical-stress slow-band power, the functional order parameter Λ (cross-spectral coherence between V and σ at f_{slow}), and K_2 are co-driven by a single electromechanical interference mode at f_{slow}. Switching to full-cycle strobing (odd parity) disrupts this shared curvature: each channel acquires an additional odd component and the cross-observable curvature coherence breaks. This parity-sensitive breakdown provides an internal control for the electromechanical origin of the slow band.

For conditions A_k and observables $Y^{(j)}$, assemble the centered, morphology-weighted matrix

$$\mathbf{M}_{kj} \equiv m_{A_k}\left(Y^{(j)}(A_k) - \widehat{A}^{(j)} - \widehat{B}^{(j)}X_k\right),$$

where $\widehat{A}^{(j)}$ and $\widehat{B}^{(j)}$ are the linear-fit coefficients in Eq. (12). Perform the singular value decomposition $\mathbf{M} = \mathbf{U}\mathbf{S}\mathbf{V}^\top$ with singular values $s_1 \geq s_2 \geq \cdots$. Rank-one dominance

$$R_1 \equiv \frac{s_1}{\sum_i s_i}$$

near 0.8 indicates that a single common quadratic mode accounts for most of the across-condition variation under the neutral strobe.

A parity-sensitive alternation index along ordered conditions $\{A_k\}_{k=1}^{K}$,

$$\mathcal{A}_j \equiv \frac{1}{K-1}\sum_{k=1}^{K-1}(-1)^k \operatorname{sgn}\left(M_{k+1,j} - M_{k,j}\right)\frac{|M_{k+1,j} - M_{k,j}|}{\sum_{\ell=1}^{K-1}|M_{\ell+1,j} - M_{\ell,j}|},$$

captures parity-dependent structure directly. A high $\mathcal{A}_j$ under full-cycle strobing reflects alternating (odd-parity) deviations, whereas a low value under even strobing is consistent with a shared quadratic curvature across observables.

Reference code and reproducibility The full analysis and simulation pipeline (pseudo-spectral dual-field sandbox; generation of $V(t)$ and $\sigma(t)$ on a periodic domain; estimation of $f_\pm$, f_{slow}, Λ, and stroboscopic regression of $(\widehat{\Omega}, \widehat{K}_2)$) is provided in the Supplementary Code Listings (§L). Listing L contains the pseudo-spectral sandbox and analysis pipeline used for the in-silico regimes (Cases A–D), together with inline notes on how we toggle parameters to produce locking, proliferative unlocking, aging overlock, and on-band entrainment.

B Numerical simulation of the overdamped continuum coupler (Eqs. 16–18)

B.1 Overdamped continuum electromechanical coupler

We consider the overdamped dual-field continuum model

$$\partial_t V = D_V \nabla^2 V - \tau_m^{-1}V + \beta_R\,\sigma + \beta_I\,\partial_t\sigma + \xi_V, \tag{16}$$

$$\eta\,\partial_t u + \kappa\,u - D_\sigma\nabla^2 u = \gamma\,V + \xi_u, \tag{17}$$

$$\sigma = \kappa\,u + \eta\,\partial_t u - D_\sigma\nabla^2 u, \tag{18}$$

where $V(\mathbf{x}, t)$ is a coarse-grained bioelectric field, $u(\mathbf{x}, t)$ a cortical displacement field, and $\sigma(\mathbf{x}, t)$ the corresponding in-plane stress. The parameters $D_V, \tau_m, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma$ are obtained from independent measurements (see Methods).

Minimal 1D ring discretization For the sandbox implementation we restrict to a one-dimensional periodic domain $x \in [0, L)$ discretized into N points with spacing $\Delta x = L/N$ and periodic boundary conditions. Spatial derivatives use the standard second-order finite-difference Laplacian. Time stepping can be explicit (e.g. RK4) or semi-implicit (IMEX) for the diffusive terms. A conservative stability guideline is

$$\Delta t \lesssim 0.1 \cdot \min\left\{\tau_m,\ \eta/\kappa,\ \tfrac{\Delta x^2}{4D_V},\ \tfrac{\Delta x^2}{4D_\sigma}\right\}.$$

Weak additive noise terms ξ_V, ξ_u seed broadband spectra.

Eliminating $\partial_t \sigma$ (state-space form) Using Eqs. (17)–(18), we can express σ directly in terms of V and noise,

$$\sigma \;=\; \kappa u + \eta\,\partial_t u - D_\sigma \nabla^2 u \;=\; \gamma V \;+\; \xi_u,$$

so that $\partial_t \sigma = \gamma\,\partial_t V + \partial_t \xi_u$. Substituting into Eq. (16) and collecting $\partial_t V$ terms yields

$$\alpha_{\mathrm{eff}}\,\partial_t V \;=\; D_V \nabla^2 V \;-\; \tau_m^{-1} V \;+\; \beta_R\left(\gamma V + \xi_u\right) \;+\; \xi_V \;+\; \beta_I\,\partial_t \xi_u, \qquad \alpha_{\mathrm{eff}} \equiv 1 - \beta_I \gamma,$$

so that

$$\partial_t V \;=\; \frac{D_V \nabla^2 V - \tau_m^{-1} V + \beta_R\,\gamma V}{\alpha_{\mathrm{eff}}} \;+\; \frac{\beta_R\,\xi_u + \xi_V + \beta_I\,\partial_t \xi_u}{\alpha_{\mathrm{eff}}}.$$

In parallel, we advance the mechanical field as

$$\partial_t u \;=\; \frac{-\kappa\,u + D_\sigma \nabla^2 u + \gamma V}{\eta} \;+\; \frac{\xi_u}{\eta}.$$

Conditioning. When $|\alpha_{\mathrm{eff}}|$ is small the explicit voltage update becomes ill-conditioned. In practice we restrict $|\beta_I \gamma| < 1$ in the prior sweep or, if needed, treat the $\alpha_{\mathrm{eff}}\,\partial_t V$ term implicitly in V.

Simulation protocol A single sandbox run proceeds as follows:
1. Draw $(D_V, \tau_m, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma)$ from preregistered physiological priors.
2. Initialize $V(x, 0)$ and $u(x, 0)$ with small random perturbations, add weak broadband noise ξ_V, ξ_u.
3. Integrate Eqs. (16)–(18) for $T \simeq 600$–1200 s.
4. Compute Welch spectra $S_V(f)$ and $S_\sigma(f)$; identify the fast-band carrier peaks $f_\pm$ and set $f_{\mathrm{slow}} = |f_+ - f_-|$.
5. Compute the electromechanical coherence $\Lambda = C_{V\sigma}(f_{\mathrm{slow}})$.
6. Perform neutral-moment stroboscopy (even parity) and regress the slow-phase map to estimate $(\widehat{\Omega}, \widehat{K}_2)$.
7. Repeat over Monte Carlo draws from the priors and map where (Ω, K_2) falls relative to the 2/21 tongue and lower-order tongues.

Outputs For each run we report $S_V(f)$, $S_\sigma(f)$, the cross-spectrum and $\Lambda(f)$, the fast carriers $f_\pm$, the slow-band peak near f_{slow}, and the neutral-map staircase with any plateau near $\rho_\pi \approx 2/21$. The (Ω, K_2) obtained from the known generator provide a ground-truth reference for the stroboscopic regression. Weak on-band drives at f_{slow} versus matched off-band controls can be added to test P3 *in silico* (gain in Λ together with a selective drop in $\mathrm{Var}_{\mathrm{map}}$; see G).

C Molecular integration of the electromechanical tissue model

Aim

We place the physical framework of the main text—a weakly coupled system between a tissue-scale bioelectric field $V(\mathbf{x}, t)$ and a cortical-tension field $\sigma(\mathbf{x}, t)$—within molecular and genetic language. Specifically, we indicate (i) which molecular pathways modulate the physical parameters, (ii) how those parameters collapse into two effective tissue control variables, Ω and K_2, and (iii) how (Ω, K_2) maps onto outcomes such as controlled proliferation, differentiation, and aging. The goal is not to replace molecular biology but to provide an organizing layer on top of it.

From physical parameters to control variables

In the main text, $V(\mathbf{x}, t)$ is an effective bioelectric potential that spreads with diffusivity D_V and relaxes with an effective membrane timescale τ_m. The cortical field $\sigma(\mathbf{x}, t)$ is characterized by an effective surface modulus κ (N/m), an effective viscosity η, and a lateral stress-redistribution coefficient D_σ. The two fields are weakly but reciprocally coupled by $(\gamma, \beta_R, \beta_I)$.

Interference between the dominant collective modes (observable carriers Ω_+, Ω_-) generates a slow cadence

$$f_{\text{slow}} \;=\; \frac{|\Omega_+ - \Omega_-|}{2\pi}.$$

Sampling at neutral moments yields an even circle map controlled by Ω (an effective forcing set by the carrier ratio $r_{\text{eff}} = \Omega_- / \Omega_+$) and K_2 (even-harmonic coupling), with slow-band cross-coherence

$$\Lambda \;\equiv\; C_{V\sigma}(f_{\text{slow}})$$

quantifying the strength of electromechanical locking. When (Ω, K_2) lies inside the 2/21 Arnold tongue, the slow phase locks; outside, the system either unlocks or becomes overlocked.

Electrical sector: primarily tuning Ω

The electrical sector is controlled by canonical bioelectric mechanisms:

- *Gap-junction coupling (connexins).* Connexin expression, assembly, and gating modulate lateral charge spread, shifting D_V and hence the carrier ratio and Ω.
- *Membrane conductances and pumps.* Ion channels, exchangers, and electrogenic pumps set the effective RC constant τ_m and resting potential statistics, shifting Ω via the same mechanism.

Genetic or small-molecule perturbations of connexins, channels, or pumps therefore primarily shift the electrical contribution to Ω.

Mechanical sector: primarily tuning K_2

The mechanical sector is governed by the actomyosin cortex and its anchorage:

- *Actomyosin contractility.* RhoA/ROCK signalling, MLCK activity, and myosin II assembly modulate κ and η. In the overdamped framework these changes primarily tune K_2 (even-harmonic feedback) and only secondarily shift the carrier pair.
- *Adhesion and anchoring.* Cadherins (adherens junctions), integrins (focal adhesions), cortex-membrane linkers, and ECM coupling modify κ, η, and D_σ, thereby tuning K_2 and, more weakly, r_{eff}.

Transducers and outcomes

Spindle orientation during mitosis is read out by cortical anchoring complexes (LGN / NuMA scaffolds) that recruit dynein/kinesin to astral microtubules and sense cortical geometry and tension. In this framework, a stable electromechanical lock (high Λ with (Ω, K_2) inside 2/21) stabilizes cortex geometry at f_{slow}, which stabilizes astral pulling, organelle and fate-determinant partitioning, and chromatin torsion management.

Mechanosensitive pathways such as Hippo/YAP-TAZ convert mechanical state into transcriptional programs. Here, YAP/TAZ can be viewed as a nuclear effector reporting the tissue's (Ω, K_2) state.

State map in (Ω, K_2)

The pair (Ω, K_2) serves as a tissue-state coordinate that can be moved experimentally with standard tools. Its location predicts:

- *Inside* 2/21. Slow-phase locking with high Λ; robust spindle orientation, low missegregation, controlled proliferation compatible with organized differentiation.
- *Near the boundary.* Partial unlocking; more permissive proliferation, broader spindle-angle dispersion, increased sensitivity to perturbations.
- *Deep overlock.* Stereotyped slow cadence with reduced adaptability; high Λ but low plasticity, aging-like phenotype.

Falsifiable perturbations (molecular → physical → outcome)

Summary

The electromechanical theory does not replace pathway-level models; it organizes them. Ion channels, pumps, and gap junctions set D_V and τ_m (upstream of Ω); RhoA/ROCK, myosin II, cadherins, integrins, and cortex-membrane linkers set κ, η, and D_σ (upstream of K_2); LGN/NuMA-dynein/kinesin complexes transmit cortical tension to the spindle; and YAP/TAZ reports mechanical state to the nucleus. These routes act upstream of (Ω, K_2), which locate the tissue relative to the 2/21 tongue and set the stability of the shared slow cadence f_{slow} and the coherence Λ. In this view, controlled proliferation, organized differentiation, and structural aging are different regimes of the same slow-phase mechanism, testable with standard genetic and small-molecule perturbations.

D Biological basis of the 2/21 lock

D.1 Why 2/21 matters biologically (compatibility window)

The slow electromechanical phase of a living epithelium, sampled at neutral-moment crossings, obeys an even circle map

$$\theta_{n+1} = \theta_n + \Omega - K_2 \sin(2\theta_n) \pmod{\pi},$$

whose rational locks correspond to effective helical pitches $n = q/p$. The canonical B-DNA pitch $n \simeq 10.5$ bases/turn corresponds to $\rho_\pi = p/q = 2/21$, and the center of that high-order tongue sits at $\Omega_{2/21} = \pi \cdot 2/21 \simeq 0.2992$ rad in the even (mod π) convention, without fitting integers by hand.

We do not claim that a $\sim$0.3–0.4 Hz tissue-scale cadence mechanically forces an Å-scale helical pitch in real time. Instead, in this framework 2/21 is interpreted as a *compatibility window* in which two coupled structures cooperate during mitosis: (i) cortical anchoring of the mitotic spindle, which transmits torque through astral microtubules to the poles, and

(ii) centromeric chromatin, which must absorb that torque without persistent merotelic attachments or torsional failure.

Locking near 2/21 is therefore proposed to minimize spindle misorientation and limit chromatin torsional excursions, thereby reducing segregation errors and aneuploidy during division.

The high-order nature of 2/21 is useful in this context: it is specific enough to avoid broad, low-order locks (e.g. 1/2, 1/3) that would trap the tissue in an over-rigid state, yet narrow enough to be re-entered cycle after cycle. In the present work we treat this as a mechanistic compatibility hypothesis at the tissue scale, to be tested by locating (Ω, K_2) and Λ experimentally.

D.2 Prevalidation and falsifiability: how the lock is tested

The theory makes three falsifiable predictions (P1–P3): P1 requires a shared slow-band cadence f_{slow} in both voltage $V(t)$ and cortical stress $\sigma(t)$, with high cross-spectral coherence $\Lambda = C_{V\sigma}(f_{\text{slow}})$.

P2 requires that the forcing/coupling pair (Ω, K_2), computed *a priori* from independently measured physical parameters, falls inside the 2/21 tongue and avoids wide low-order tongues. P3 states that weak on-band drive at f_{slow} increases Λ and reduces spindle misorientation (equivalently, Var_{map}) relative to off-band controls.

G implements this logic *in silico*. In a synthetic proliferative-like unlocked state with high Var_{map}, an on-band weak drive at f_{slow} produces a frequency-specific increase in Λ together with a suppression of Var_{map} that $\pm 10\%$ detuned controls do not reproduce.

The same pipeline shows that paired recordings $V(t), \sigma(t)$ at ~ 100 Hz for ~ 600 s are, in principle, sufficient to recover $(f_-, f_+, f_{\text{slow}})$, estimate $(\widehat{\Omega}, \widehat{K}_2)$ via neutral-moment strobing, and compute $\Lambda(f)$ with parity switching as an internal control.

In these synthetic datasets, locked regimes yield $\Lambda(f_{\text{slow}}) \gtrsim 0.6$ and $(\widehat{\Omega}, \widehat{K}_2)$ near the 2/21 band; proliferative unlocking produces phase drift and low/bursty Λ; and aging-like overlock produces rigid high Λ with reduced adaptability.

We preregister that the same analysis will be applied, once available, to confluent epithelial monolayers providing simultaneous traction-force (or cortical-stress) imaging and fast optical voltage readouts from the same field of view.

For each preparation we will report $(f_-, f_+, f_{\text{slow}})$, (Ω, K_2) with robust standard errors, Λ at f_{slow}, parity condition, ECM context, on-band drive spectra and RMS, and $\pm 10\%$ off-band controls. Failure of P1 or P2 under those conditions refutes the dual-field hypothesis for that system; failure of P3 (no selective on-band rescue relative to off-band) refutes the phase-targeted entrainment mechanism.

D.3 Level-0 computational validation on publicly available epithelial data

We next asked whether the predicted dual-field signature-two weakly damped fast modes in the ~ 1–2 Hz band whose interference produces a dominant slow beat f_{slow} in the sub-Hz band is already present in real confluent epithelia, without collecting new data.

As a Level-0 test we re-analyzed an openly released high-speed voltage-imaging movie of a dense epithelial(-like) monolayer published by Quicke *et al.* (2022). In that dataset, hundreds of cells in a confluent sheet were recorded at ~ 5 frames/s ($f_s \approx 5$ Hz, Nyquist ≈ 2.5 Hz) for ~ 500 s (~ 2500 frames). We defined a fixed rectangular region of interest (ROI) fully inside the monolayer (pixel bounds $x = [309, 617]$, $y = [151, 301]$ in a 452×926 px field of view), averaged the raw fluorescence in that ROI frame by frame, detrended and z-scored the resulting trace, and treated that normalized signal as a local

proxy $V(t)$ for membrane voltage (Fig. D.1).

Figure D.1: **ROI-averaged $V(t)$ (z-scored).** Mean fluorescence in a fixed rectangular ROI inside a confluent epithelial(-like) monolayer recorded by Quicke *et al.* (2022) at ~ 5 Hz for ~ 500 s (~ 2500 frames). After detrending and z-scoring, this trace is treated as a local voltage proxy $V(t)$.

The Welch power spectral density of $V(t)$ exhibited two narrowband carrier peaks in the ~ 1 Hz range, at $f_+ \simeq 1.2$ Hz and $f_- \simeq 1.4$ Hz (Fig. D.2). These correspond to two weakly damped fast modes below Nyquist. Their beat,

$$f_{\text{slow}} = |f_+ - f_-| \simeq 0.20 \text{ Hz},$$

defines a slow multi-second cadence of ~ 5 s per cycle.

Figure D.2: **Power spectral density of $V(t)$.** Welch PSD of $V(t)$, revealing two narrowband carrier peaks in the ~ 1 Hz band at $f_+ \simeq 1.2$ Hz and $f_- \simeq 1.4$ Hz. Their beat $f_{\text{slow}} = |f_+ - f_-| \simeq 0.20$ Hz defines a slow multi-second cadence of ~ 5 s per cycle.

To test whether this slow beat is physically expressed in the tissue rather than being a numerical subtraction, we computed the analytic-signal envelope of $V(t)$ via the Hilbert transform and treated that envelope as the instantaneous amplitude of the fast carriers (Fig. D.3). We then computed the power spectrum of the envelope. The envelope spectrum showed a sharply dominant, narrow sub-Hz peak at $f_{\text{slow}} \simeq 0.20$ Hz whose power exceeded the median background by a factor $\gtrsim 2 \times 10^3$ (Fig. D.4). Thus the slow beat f_{slow} is the principal coherent amplitude modulation of the ~ 1 Hz carriers in this living confluent monolayer.

Figure D.3: **Hilbert amplitude envelope of** $V(t)$**.** Instantaneous amplitude of $V(t)$ obtained as the modulus of the analytic signal. This envelope tracks the slow modulation of the ~ 1 Hz carriers and visibly oscillates on multi-second timescales near $f_{\text{slow}} \simeq 0.20$ Hz.

Figure D.4: **Envelope power spectrum and dominant** f_{slow}**.** Welch PSD of the amplitude envelope of $V(t)$. A narrow peak appears at $f_{\text{slow}} \simeq 0.20$ Hz (period ~ 5 s), whose power exceeds the median background by a factor $\gtrsim 2 \times 10^3$. This indicates that the slow beat f_{slow} is the dominant coherent amplitude modulation of the fast carriers in this monolayer.

This Level-0 analysis supports two core claims of the model. First, real epithelial(-like) monolayers already express at least two weakly damped fast modes in the ~ 1–2 Hz band. Second, those modes share a slow sub-Hz cadence f_{slow} that dominantly modulates their amplitude envelope.

The analysis uses only public data from Quicke *et al.* (2022) and imposes no hand-picked integer locking such as 2/21. It also provides an immediate falsification handle: the same study includes ion-channel block and EMT-like transformations. Within our framework, chemically induced loss of electromechanical coupling should strongly attenuate the slow-envelope peak at f_{slow}; if that peak remains robust under conditions that suppress coupling, that outcome would challenge the interference mechanism.

All panels in Fig. D.1–D.4 are produced automatically by the Level-0 analysis script in Listing L.

D.4 Level-1 dual-channel analysis pipeline (synthetic demonstration and applicability)

Level-1 targets the case in which a confluent epithelial monolayer is imaged with two fully synchronized channels: a fast optical voltage proxy $V(t)$ (e.g. a GEVI or a fast voltage-sensitive dye) and a co-registered mechanical / cortical-stress readout $\sigma(t)$ (e.g. traction or monolayer-stress microscopy, interferometric contractility, or high-speed strain imaging).

The preregistered requirement is that both signals are collected from the *same* field of view, at $\gtrsim$ 80–100 Hz sampling, continuously for hundreds of seconds. To our knowledge, no such dual-channel, high-rate, long-duration epithelial dataset is publicly available at the time of submission. This is why Level-1 is framed as a preregistered experimental test rather than an already executed analysis.

The Level-1 pipeline operates as follows. From two simultaneous traces, a voltage-like channel $V(t)$ and a mechanical-like channel $\sigma(t)$, we (i) estimate power spectra and identify two narrow-band carrier peaks f_+ and f_- in the $\sim$ 1 Hz range; (ii) define their beat $f_{\text{slow}} = |f_+ - f_-|$ in the sub-Hz band; (iii) compute the magnitude-squared coherence $\Lambda(f)$ and evaluate Λ at f_{slow} as an electromechanical order parameter; (iv) extract instantaneous phases $\phi_V(t)$ and $\phi_\sigma(t)$, build the phase difference $\psi(t) = \phi_V(t) - \phi_\sigma(t)$, and identify neutral alignment events where ψ crosses 0 modulo π with positive slope; and (v) sample at those events the fast electrical phase θ_n and construct the neutral stroboscopic map

$$\Delta\theta_n \equiv \theta_{n+1} - \theta_n = \Omega - K_2 \sin(2\theta_n),$$

which yields $(\widehat{\Omega}, \widehat{K}_2)$ and their uncertainties.

In the model, a healthy, adaptively locked state corresponds to: (a) a clear two-carrier structure in the $\sim$ 1 Hz band; (b) a well-defined slow beat f_{slow}; (c) strong slow-band coherence $\Lambda(f_{\text{slow}})$ between $V(t)$ and $\sigma(t)$; (d) a significant even-harmonic coupling $K_2 \neq 0$; and (e) an $\widehat{\Omega}$ that lies near $\Omega_{2/21} = \pi \cdot 2/21$. Large displacements of $\widehat{\Omega}$ from $\Omega_{2/21}$, collapse of $\Lambda(f_{\text{slow}})$, or vanishing $\widehat{K}_2$ under well-controlled conditions are direct falsification signals.

To demonstrate that this pipeline is operational, we generated a synthetic dual-channel dataset that mimics two weakly damped $\sim$ 1 Hz carriers ($f_+ \simeq 1.20$ Hz and $f_- \simeq 1.03$ Hz) whose interference produces a dominant slow beat $f_{\text{slow}} \simeq 0.17$ Hz. We assigned those carriers to two observed channels $V(t)$ and $\sigma(t)$ with a small phase lag, slow modulation, and added noise, sampled at $f_s = 100$ Hz for 120 s.

(a) Simultaneous z-scored traces $V(t)$ and $\sigma(t)$ for the synthetic dual-channel dataset.

(b) Welch power spectra of $V(t)$ and $\sigma(t)$, with carrier peaks f_+ and f_- in the ~ 1 Hz band.

(c) Electromechanical coherence $\Lambda(f)$ between $V(t)$ and $\sigma(t)$, with slow-band value $\Lambda(f_{\text{slow}})$ marked at $f_{\text{slow}} = |f_+ - f_-|$.

(d) Neutral stroboscopic map $\Delta\theta_n = \theta_{n+1} - \theta_n$ versus θ_n, with even-harmonic fit $\Delta\theta = \Omega - K_2 \sin(2\theta)$ and comparison to the predicted lock $\Omega_{2/21} = \pi(2/21)$.

Figure D.5: **Preregistered Level-1 benchmark on a controlled synthetic dual-channel dataset.** Panels (a)–(d) summarize the Level-1 outputs: paired time series; narrow-band carrier peaks f_+ and f_- in the ~ 1 Hz range and their beat $f_{\text{slow}} = |f_+ - f_-|$; slow-band electromechanical coherence $\Lambda(f_{\text{slow}})$ between the voltage-like and mechanical-like channels; and the neutral stroboscopic map fitted with $\Delta\theta = \Omega - K_2 \sin(2\theta)$ to estimate (Ω, K_2) and compare Ω with the theoretical lock $\Omega_{2/21}$. Reported values correspond to this synthetic field of view. The synthetic dataset and analysis pipeline are generated by Listing L

Running the Level-1 analysis (Fig. D.5) automatically recovers f_+ and f_-, identifies f_{slow}, reports a strong slow-band cross-coherence $\Lambda(f_{\text{slow}}) \approx 0.7$, and builds the neutral stroboscopic map. The even-harmonic fit yields $\widehat{\Omega} \approx 0.14 \pm 0.08$ rad and a significant coupling term $\widehat{K}_2 \approx 0.42 \pm 0.12$, with $\widehat{\Omega}$ lying within ~ 0.16 rad of $\Omega_{2/21} \approx 0.299$ rad.

The same code can be applied without modification to any dataset providing two synchronized high-speed channels from the same multicellular field of view.

High-speed dual-channel electromechanical datasets of this type already exist in other multicellular systems, notably human iPSC-derived cardiomyocyte syncytia with simultaneous widefield voltage mapping and interferometric contraction readouts.

What is not yet publicly available is a single confluent epithelial dataset that captures both fast transmembrane voltage $V(t)$ and cortical stress $\sigma(t)$ at $\gtrsim 80$–100 Hz for hundreds of seconds in homeostatic conditions. For that reason we treat epithelial Level-1 as a preregistered experimental target.

Because all analysis steps (power spectra, $\Lambda(f)$, neutral strobing, $(\widehat{\Omega}, \widehat{K}_2)$ extraction, and comparison to $\pi \cdot 2/21$) are fully specified and implemented (Listing L), the falsifiability of the model is operational.

D.5 Parameter dictionary (experimental interpretation)

To aid experimental interpretation we summarize the key effective parameters and how they are obtained. In particular, Ω and K_2 are not free fit parameters: they are derived from independently measurable electrical and mechanical properties of the tissue and then extracted from the slow-phase map without imposing hand-picked integers. Table 4 collects their experimental handles and biological interpretation.

Parameter	Experimental handle	Biological meaning	Phenotypic drift if altered
Ω	Ratio of carrier frequencies (f_-, f_+) (i.e. $r_{\text{eff}} = f_-/f_+$); upstream dependence on D_V, τ_m, κ, η, D_σ, γ, β_R, β_I via the carrier split	Effective slow driving of the electromechanical phase per neutral cycle. Shifts with ion-channel conductance, gap-junction coupling, cortical stiffness and ECM load	Drift of Ω away from $\pi \cdot 2/21$ destabilizes locking: persistent drift $\to$ proliferative unlocking; excessive confinement $\to$ aging-like overlock.
K_2	Even-harmonic coupling in the neutral stroboscopic map $\theta_{n+1} - \theta_n = \Omega - K_2 \sin(2\theta_n)$	Strength of shared slow cadence between V and σ at neutral crossings. Increases with cortex–membrane anchoring, actomyosin tension, and astral pulling	Low K_2 weakens electromechanical entrainment and favors proliferative unlocking. Excessively high K_2 locks the tissue into a rigid, low-plasticity, aging-like state.
Λ	Cross-coherence between $V(t)$ and $\sigma(t)$ at f_{slow}	Order parameter for coordinated slow cadence. High Λ means voltage and cortical stress share the same slow beat and remain phase-coupled at neutral moments	Collapse of Λ marks proliferative unlocking (loss of coordinated cadence). Rigid, saturated high Λ with poor adaptability marks aging-like overlock.

Table 4: **Dictionary of key effective parameters.** Columns indicate how each parameter is obtained, its biological meaning in terms of ion channels, gap junctions, actomyosin contractility, adhesion, and spindle anchoring, and the qualitative phenotype expected if the parameter drifts chronically.

D.6 Bidirectional correction loops (homeostatic control)

The dual-field framework is not purely feed-forward. Cells possess feedback loops that sense deviations from coordinated locking and tend to restore them. Mechanosensitive ion channels alter membrane potential and junctional conductance in response to cortical tension, shifting D_V and τ_m and thus Ω. Conversely, spindle anchoring complexes (LGN/NuMA scaffolds recruiting dynein/kinesin) pull on the cortex via astral microtubules, reinforcing or remodeling cortical tension and anchorage, thereby tuning K_2. We interpret healthy tissue homeostasis as a recurring traversal of the antisymmetric/symmetric loop with clean neutral crossings, high but adaptable Λ, and repeated re-entry into the 2/21 tongue.

Pathology corresponds to breakdowns of this homeostatic correction: (i) persistent unlocking (loss of re-entry, low Λ, broad Ω drift) maps to proliferative instability and checkpoint failure; (ii) aging overlock (rigid high Λ, excessively large K_2, reduced adaptability) maps to senescence-like stiffening and loss of plasticity.

D.7 Relation to canonical signalling pathways

Classical pathway models (Hippo / YAP–TAZ, Wnt, Notch) describe how transcriptional programs choose proliferation, self-renewal, or differentiation in response to local cues such as tension, crowding, or ligand gradients. In our framework these pathways act as effectors downstream of the coordinated slow cadence. YAP/TAZ nuclear localization reads cortical tension and thus reports the current (Ω, K_2) state. Spindle orientation, which is constrained by the locked slow cadence at neutral moments, selects symmetric vs. asymmetric division and therefore biases lineage decisions that downstream Notch/Wnt programs then realize.

The dual-field model does not replace canonical signalling. It specifies the tissue-scale dynamical condition quantified by $(\Omega, K_2, \Lambda, f_{\text{slow}})$, under which those pathways can operate stably without catastrophic spindle error (proliferative unlocking) or irreversible mechanical stiffening (aging-like overlock). In this sense, the model provides a falsifiable, frequency-resolved coordination layer above classical signalling rather than an alternative to it.

E Cycle-resolved neutral-phase analysis, re-entry, and sliding-window map fits

This appendix formalizes how to (i) identify neutral crossings in real time, (ii) quantify local coherence and recovery across those crossings, and (iii) track slow drift of the effective map parameters (Ω, K_2) over many cycles without assuming strict stationarity. The workflow extends the preregistered pipeline (spectra $\rightarrow f_{\pm} \rightarrow f_{\text{slow}} \rightarrow \Lambda \rightarrow (\widehat{\Omega}, \widehat{K}_2)$) by adding cycle-resolved diagnostics. It is designed to test whether a tissue repeatedly *re-enters* the predicted 2/21 lock window, or instead drifts away and fails to recover.

E.1 Neutral crossings and slow-phase sampling

Let $V(t)$ be the voltage-like channel and $\sigma(t)$ the cortical-stress (traction-like) channel, both sampled at rate f_{s}. Define their analytic signals

$$Z_V(t) = V(t) + i\,\mathcal{H}[V](t), \qquad Z_\sigma(t) = \sigma(t) + i\,\mathcal{H}[\sigma](t),$$

where $\mathcal{H}[\cdot]$ is the Hilbert transform, and phases $\phi_V(t) = \arg Z_V(t)$, $\phi_\sigma(t) = \arg Z_\sigma(t)$. The instantaneous phase difference is

$$\psi(t) \;=\; \phi_V(t) - \phi_\sigma(t).$$

We define a *neutral crossing* as a time τ_n such that

$$\psi(\tau_n) \equiv 0 \pmod{\pi}, \qquad \frac{d\psi}{dt}(\tau_n) > 0,$$

i.e. V and σ are aligned in sign (mod π) and V is rotating ahead of σ with positive slope. This matches the even-parity convention in the main text (neutral-moment strobe). We detect $\{\tau_n\}$ by finding sign changes of $\psi(t)$ through 0 modulo π with positive derivative, after low-pass smoothing of $\psi(t)$ around f_{slow}.

At each neutral crossing τ_n we also sample a fast phase θ_n, e.g. $\theta_n = \phi_V(\tau_n)$ modulo π, which is used to build the neutral stroboscopic map.

E.2 Local windows A / B / C around each neutral crossing

To characterize how coherence builds and relaxes around each neutral crossing, we define short time windows around τ_n:

$$\mathcal{A}_n = [\tau_n - W, \tau_n), \qquad \mathcal{B}_n = [\tau_n, \tau_n + W), \qquad \mathcal{C}_n = [\tau_n + W, \tau_n + 2W),$$

with W on the order of a few periods of f_{slow} (e.g. $W \simeq 2$–5 s for $f_{\text{slow}} \sim 0.2$–0.4 Hz). Intuitively, $\mathcal{A}_n$ is the approach to the neutral moment, $\mathcal{B}_n$ the neutral crossing itself, and $\mathcal{C}_n$ the relaxation after the crossing.

Within any window I (e.g. $I = \mathcal{B}_n$) we compute a short-time, band-limited magnitude-squared coherence between V and σ at f_{slow},

$$\Lambda_{\text{local}}(I) = C_{V\sigma}(f_{\text{slow}} \mid I),$$

using Welch-style segments restricted to that window. We then define a reset ratio

$$R_{\text{reset}}(n) = \frac{\Lambda_{\text{local}}(\mathcal{B}_n)}{\Lambda_{\text{local}}(\mathcal{A}_n)},$$

which measures how much the neutral crossing increases slow-band electromechanical coherence relative to immediately before the crossing. Values $R_{\text{reset}}(n) > 1$ indicate that the neutral moment acted as a re-synchronization event; $R_{\text{reset}}(n) \approx 1$ indicates no net gain; systematic $R_{\text{reset}}(n) < 1$ indicates failure to recover coherence.

Neutral resets as seconds-to-minutes integrators Let e_n be the spindle-axis misalignment just before the n-th neutral crossing. A neutral reset with local slow-band coherence Λ_n contracts this error on average as

$$e_{n+1} = (1 - \alpha_n)\, e_n + \xi_n, \qquad \alpha_n \propto \Lambda_n,$$

with ξ_n a bounded perturbation. Over N cycles one has $\mathbb{E}[|e_N|] \lesssim (1 - \bar{\alpha})^N |e_0| + O(1)$, so multi-cycle improvements can arise from repeated seconds-scale resets. Operationally, $R_{\text{reset}}(n) > 1$ is an empirical proxy for α_n.

Similarly, we track the slow-phase drift rate just before each neutral crossing. Let

$$\dot{\psi}_{\text{slow}}(t) = \frac{d}{dt} \big[\psi(t)\big]_{\text{low-pass}},$$

i.e. the derivative of $\psi(t)$ band-limited around f_{slow}. We define a pre-crossing drift magnitude

$$D_{\text{pre}}(n) = \Big\langle \big|\dot{\psi}_{\text{slow}}(t)\big| \Big\rangle_{t \in \mathcal{A}_n}.$$

Large $D_{\text{pre}}(n)$ together with $R_{\text{reset}}(n) \gg 1$ suggests that the neutral moment corrects accumulated drift. Conversely, small $D_{\text{pre}}(n)$ but $R_{\text{reset}}(n) \lesssim 1$ suggests overlock / rigidity: the system is already stuck and not actively re-synchronizing.

E.3 Sliding-window estimation of $(\widehat{\Omega}, \widehat{K}_2)$

The slow-phase map at neutral crossings is modeled as

$$\Delta\theta_n \equiv \theta_{n+1} - \theta_n = \Omega - K_2 \sin(2\theta_n) + \epsilon_n,$$

where ϵ_n captures noise and higher harmonics. In the main text we fit (Ω, K_2) to the pooled set of all neutral crossings in a recording, assuming quasi-stationarity.

Here we allow slow drift by using a sliding-window fit. Let $\{\tau_n\}$ be the ordered list of neutral crossings and let N_{win} be a fixed window length in number of crossings (e.g. $N_{\text{win}} = 50$). For each index $n \geq N_{\text{win}}$ we consider the subsequence

$$\mathcal{W}_n = \{(\theta_j, \Delta\theta_j) \mid j \in [n - N_{\text{win}} + 1,\, n]\}.$$

We then perform a regression of

$$\Delta\theta_j = \Omega_n - K_{2,n} \sin(2\theta_j)$$

over $\mathcal{W}_n$, yielding local estimates $(\widehat{\Omega}_n, \widehat{K}_{2,n})$ and their standard errors (e.g. Newey-West to handle autocorrelation). Each pair $(\widehat{\Omega}_n, \widehat{K}_{2,n})$ is assigned to the most recent neutral crossing time τ_n.

Plotting $\widehat{\Omega}_n$ versus τ_n reveals whether the tissue repeatedly re-enters the predicted lock band around

$$\Omega_{2/21} = \pi \cdot \frac{2}{21} \simeq 0.2992 \text{ rad},$$

or instead drifts away and fails to return. Likewise, plotting $\widehat{K}_{2,n}$ versus τ_n tests whether even-harmonic coupling (our proxy for electromechanical anchoring at neutral crossings) degrades or saturates over time.

A single cycle $[\tau_n, \tau_{n+1}]$ only provides one $(\theta_n, \Delta\theta_n)$ pair, which is insufficient to fit two parameters. The sliding window $\mathcal{W}_n$ provides tens of such pairs, making $(\widehat{\Omega}_n, \widehat{K}_{2,n})$ well defined statistically.

E.4 Cycle-resolved timing of the sync transition and division phases

We anchor time per cell at the last neutral crossing before spindle assembly. Let the measured carrier split define

$$f_{\text{slow}} = \frac{|\Omega_+ - \Omega_-|}{2\pi}, \qquad T_{\text{slow}} = \frac{1}{f_{\text{slow}}}.$$

Sampling at neutral moments yields the even map (main text, Eq. 5). On the 2π lift, a standard continuous approximation near a p/q tongue is the Adler-type flow

$$\dot{\phi} = \Delta\omega - K_{\text{eff}} \sin\phi + \xi(t), \qquad \Delta\omega \equiv 2\pi f_{\text{slow}}, \quad K_{\text{eff}} \propto K_2 \Delta\omega, \tag{19}$$

with weak noise $\xi(t)$ capturing finite-window estimation and cellular variability. Inside the tongue interior ($K_{\text{eff}} > \Delta\omega$) a stable fixed point $\phi^\star$ exists with linear relaxation rate

$$\lambda_{\text{lock}} = \sqrt{K_{\text{eff}}^2 - \Delta\omega^2} = \Delta\omega \sqrt{2\delta + \mathcal{O}(\delta^2)}, \qquad \delta \equiv \frac{K_{\text{eff}}}{\Delta\omega} - 1 \ (> 0 \text{ near threshold}), \tag{20}$$

so the deterministic capture time scales as

$$T_{\text{lock}} \sim \lambda_{\text{lock}}^{-1} \simeq \frac{1}{2\pi f_{\text{slow}} \sqrt{2\delta}}, \tag{21}$$

up to a mild logarithmic factor from the initial phase spread.

Operationally we estimate the slow-band electromechanical coherence in sliding windows of width W,

$$\Lambda(t) \equiv C_{V\sigma}(f_{\text{slow}}; t; W),$$

and fit its approach to a plateau by a single-pole model

$$\Lambda(t) = \Lambda_\infty - (\Lambda_\infty - \Lambda_0) e^{-t/\tau_\Lambda}, \qquad \tau_\Lambda \approx c\, T_{\text{lock}}, \quad c = \mathcal{O}(1), \tag{22}$$

with Newey-West errors to control autocorrelation and heteroscedasticity across multiple slow cycles. In practice we calibrate c once on *in silico* traces by regressing τ_Λ on T_{lock}.

In the latency-based refinement, T_{lock} itself depends on the electric and mechanical relaxation times via

$$T_{\text{lock}}(\tau_e, \tau_m) \propto \frac{1}{f_{\text{slow}} \sqrt{\delta_0\, C_{\text{proxy}}(\tau_e, \tau_m)}}, \qquad C_{\text{proxy}} \equiv \frac{1 + S_{\text{lag}}}{2}\, D_{\text{lag}},$$

so that seconds-to-minutes capture times that set $t_{\text{prom}\rightarrow\text{meta}}$ and T_{meta} are controlled jointly by the slow cadence f_{slow} and by latency parity and coincidence.

Phase timing readouts We define three falsifiable time markers:

(i) *Pro-meta capture.* The end of prophase/early prometaphase (entry into a stable symmetric regime) is declared at

$$t_{\text{prom}\rightarrow\text{meta}} = \inf \left\{ t : \begin{array}{l} \Lambda(t) \geq \Lambda_\infty(1 - \varepsilon_\Lambda), \\ N_{\text{neutral}}(t, t+\Delta) = 0, \\ \mathcal{P}_{\text{odd}}(t) > \mathcal{P}_{\text{even}}(t) \end{array} \right\}, \tag{23}$$

where $\varepsilon_\Lambda \in [0.05, 0.1]$ is a pre-registered tolerance, N_{neutral} counts neutral crossings in a guard window $\Delta \simeq (2\text{–}3)T_{\text{slow}}$, and $\mathcal{P}_{\text{odd/even}}$ are parity-fit scores from the odd vs. even stroboscopic regressions.

(ii) *Metaphase dwell.* The metaphase duration is the interval where coherence remains near plateau and odd parity dominates:

$$T_{\text{meta}} = \text{meas}\left\{ t : \Lambda(t) \geq \Lambda_\infty(1 - \varepsilon_\Lambda), \; \mathcal{P}_{\text{odd}}(t) > \mathcal{P}_{\text{even}}(t) \right\}. \tag{24}$$

In the OU approximation, T_{meta} is $\mathcal{O}(\tau_\Lambda)$ in the absence of drift; slow drift in $a = \tau_m^{-1} + D_V k^{*2}$ or $b = \kappa + D_\sigma k^{*2}$ shortens T_{meta} by reducing δ.

(iii) *Ana-telo onset.* Exit is identified by a loss of odd-parity stability or a coherence roll-off:

$$t_{\text{ana\_on}} = \inf \left\{ t > t_{\text{prom}\rightarrow\text{meta}} : \frac{d\Lambda}{dt}(t) < -\eta_\Lambda \; \text{ or } \; \mathcal{P}_{\text{odd}}(t) \leq \mathcal{P}_{\text{even}}(t) \right\}, \tag{25}$$

with pre-registered slope threshold $\eta_\Lambda > 0$ set by surrogate traces.

Practical accuracy With $f_{\text{slow}} \sim 0.1\text{–}0.3$ Hz and sampling ≥ 25 Hz, neutral-crossing timestamps are precise to a few tens of ms; coherence windows $W = 8\text{–}12$ s give typical standard errors on $\Lambda(t)$ of 0.03–0.06, yielding time uncertainty for $t_{\text{prom}\rightarrow\text{meta}}$ and $t_{\text{ana\_on}}$ on the order of several seconds. The scaling in Eq. (21) predicts seconds-to-minutes capture when $\delta \in [0.02, 0.2]$, consistent with *in silico* prevalidation.

Minimal reporting Report $f_\pm$, f_{slow} and T_{slow}; the fitted $(\widehat{\Omega}, \widehat{K_2})$ and Λ_∞; the pair $(T_{\text{lock}}, \tau_\Lambda)$ with confidence bands; and the three time markers $t_{\text{prom}\to\text{meta}}$, T_{meta}, $t_{\text{ana\_on}}$ per cell, stratified by condition.

E.5 Diagnostic figure (conceptual layout)

For clarity we propose a four-panel diagnostic figure:

- Panel 1: Raw (or bandpassed) $V(t)$ and $\sigma(t)$, showing that they are not identical but partially phase-shifted.
- Panel 2: The slow phase difference $\psi(t)$ with vertical lines at neutral crossings τ_n. Windows $\mathcal{A}_n$, $\mathcal{B}_n$, $\mathcal{C}_n$ are shaded.
- Panel 3: The local slow-band coherence trace $t \mapsto \Lambda_{\text{local}}(t)$, highlighting $\Lambda_{\text{local}}(\mathcal{A}_n)$ vs. $\Lambda_{\text{local}}(\mathcal{B}_n)$ and annotating $R_{\text{reset}}(n)$.
- Panel 4: The sliding-window trajectories $n \mapsto \widehat{\Omega}_n$ and $n \mapsto \widehat{K}_{2,n}$, plotted against τ_n, together with the reference band around $\Omega_{2/21}$.

Panels 1–4 provide (i) a direct view of how V and σ march in and out of alignment, (ii) a per-crossing measure of whether coherence is being actively rebuilt (R_{reset}), and (iii) a slow drift of $(\widehat{\Omega}, \widehat{K_2})$ that tests the central claim: healthy, adaptable tissue should repeatedly re-enter the narrow high-order 2/21 tongue instead of either drifting away without return (persistent unlocking, proliferative instability) or freezing into an overlocked, low-plasticity state (aging-like overlock).

E.6 Biophysical interpretation: bidirectional exchange versus axial recentering

In the dual-field framework, the electrical and cortical-mechanical sectors exchange electromechanical load when they are not fully synchronized. In this antisymmetric (alternating) regime, each half-cycle corresponds to a lateral handoff: one sector compresses and donates, while the other expands and accepts. This oscillatory give-and-take acts as a mesoscale exchange of load between sectors, keeping both engaged and preventing unilateral locking.

At a neutral crossing τ_n, the two sectors momentarily re-align in phase modulo π. In that instant, the system transiently behaves more like the symmetric regime: instead of continuing the left-right handoff of which sector carries the load, the load is briefly recentered along the common axis of deformation/polarization. Operationally, this event acts as an axial reset for the slow cadence.

Within our analysis, $R_{\text{reset}}(n) > 1$ is the empirical signature that such axial recentering occurred: the cross-spectral coherence between V and σ at f_{slow} increases across τ_n, indicating that both sectors are marching together rather than exchanging load in opposition. Repeated neutral crossings with $R_{\text{reset}}(n) > 1$ correspond to periodic re-entry into a synchronized, checkpoint-like state.

Conversely, if the tissue remains stuck in a single polarity (overlocked, low-plasticity) or drifts without recentering (persistent unlocking), we expect either $R_{\text{reset}}(n) \approx 1$ with negligible drift correction (rigid overlock / aging-like state) or $R_{\text{reset}}(n) < 1$ and large pre-crossing drift $D_{\text{pre}}(n)$ (runaway proliferative instability). In both cases, the bidirectional exchange that, in the antisymmetric regime, supports plastic turnover fails to converge into a stable axial reset. In our framework, this failure links dysregulated division geometry and chromatin torsional stress to pathological proliferation or aging-associated loss of plasticity.

F Capture kinetics across time scales: quantitative predictions and in-silico prevalidation

Aim. We quantify how a weak on-band drive at the slow cadence shortens the time to recover slow-phase lock, bridging sub-second carrier dynamics to minute-scale re-entrainment. The result is a falsifiable scaling law for the capture time near tongue boundaries, together with a minimal in-silico assay.

F.1 Averaged slow-phase flow and capture time

Near a p/q plateau of the even (mod π) map, the slow-phase difference φ obeys a standard averaged flow (Adler-type) with weak noise:

$$\dot{\varphi} \;=\; 2\pi f_{\text{slow}}\Big(\delta \;-\; \kappa\,\sin\varphi\Big) \;+\; \sqrt{2D}\,\xi(t), \qquad \langle \xi(t)\xi(t')\rangle = \delta(t-t'), \qquad (26)$$

where f_{slow} is the interference cadence, δ is the signed detuning from the tongue center along the Ω axis (even convention), $\kappa > 0$ is an effective locking gain proportional to the even coupling ($\kappa \propto K_2$) and to the measured coherence ($\kappa \uparrow$ with Λ), and D is a small diffusion constant capturing residual phase jitter.

In the noise-free limit ($D \to 0$) and for $|\delta| < \kappa$ there exist a stable and an unstable fixed point. Approaching the locking boundary ($|\delta| \to \kappa^{-}$), the fixed points coalesce in a saddle-node on a circle (SNIC), and the mean capture time from generic initial conditions diverges with the universal square-root law of a one-dimensional saddle-node:

$$T_{\text{lock}} \;\sim\; \frac{C}{2\pi f_{\text{slow}}}\frac{1}{\sqrt{\kappa^2 - \delta^2}} \;=\; \frac{C}{2\pi f_{\text{slow}}\sqrt{2\kappa}}\frac{1}{\sqrt{\kappa - |\delta|}} \quad \text{as } |\delta| \uparrow \kappa, \qquad (27)$$

with $C = \mathcal{O}(1)$ set by the basin average.[1]

Equation (27) yields two falsifiable consequences: (i) T_{lock} scales inversely with f_{slow} (faster cadence, faster capture), and (ii) T_{lock} grows as the inverse square root of the distance to the locking boundary along Ω.

With weak noise ($D > 0$) the SNIC singularity is rounded; standard Kramers-like arguments give

$$\mathbb{E}\,T_{\text{lock}} \;\approx\; \frac{C}{2\pi f_{\text{slow}}}\frac{1}{\sqrt{\kappa^2 - \delta^2}} \;\times\; \Phi\!\left(\frac{\kappa - |\delta|}{D^{2/3}}\right), \qquad \Phi(0^+) \in (1, \text{few}), \qquad (28)$$

i.e., the same square-root scaling with a modest renormalization near the boundary.

Dimensional link to observables We parameterize $\kappa = \alpha\,K_2\,\Lambda$ with α a dimensionless calibration set once per dataset (Methods).

The detuning is $\delta \equiv \Omega - \Omega_{p/q}$ along the even-map axis (cf. Eq. 5). Thus,

$$T_{\text{lock}} \;\propto\; \frac{1}{f_{\text{slow}}}\frac{1}{\sqrt{\alpha K_2\Lambda - |\Omega - \Omega_{p/q}|}}. \qquad (29)$$

At fixed tissue and drive, moving from the tongue interior toward its boundary increases T_{lock} from seconds to tens of seconds and, close enough to the edge, to minutes.

---

[1]For the canonical Adler equation the exact prefactor for deterministic capture from a uniform phase is $C = \pi/\sqrt{2}$; we keep C explicit to absorb implementation details (windowing, entry criterion).

F.2 Testable timing for division-scale phases

If $f_{\text{slow}} \in [0.1, 0.3]$ Hz and $\alpha K_2 \Lambda \sim 0.05\text{--}0.15$ (G), then Eq. (29) predicts:

- *Interior (comfortable on-band):* $|\Omega - \Omega_{p/q}| \approx 0.2\,\alpha K_2 \Lambda \Rightarrow T_{\text{lock}} \sim 3\text{--}10\,\text{s}.$
- *Mid-tongue:* $|\Omega - \Omega_{p/q}| \approx 0.6\,\alpha K_2 \Lambda \Rightarrow T_{\text{lock}} \sim 10\text{--}40\,\text{s}.$
- *Near boundary:* $|\Omega - \Omega_{p/q}| \approx 0.9\,\alpha K_2 \Lambda \Rightarrow T_{\text{lock}}$ climbs to $1\text{--}3\,\text{min}.$

This provides a quantitative route to the observed shift from carrier-scale seconds (fast) to checkpoint-scale minutes (slow re-centering), governed by tongue geometry rather than by ad hoc integrators.

Latency-based refinement In the first-order latency view, the effective detuning that controls the capture time is further modulated by the relative phase between the electric and mechanical relaxators at the slow cadence. Let $\omega_s = 2\pi f_{\text{slow}}$ and

$$\phi_e = -\arctan(\omega_s \tau_e), \qquad \phi_m = -\arctan(\omega_s \tau_m), \qquad \Delta\phi = \phi_m - \phi_e.$$

The in-phase projection is encoded as

$$C_{\text{even}} \equiv \max\{\cos(\Delta\phi),\, 0\},$$

so that the effective detuning becomes

$$\delta_{\text{eff}} = \left(\frac{K_{\text{eff}}}{\Delta\omega} - 1\right) C_{\text{even}}, \qquad T_{\text{lock}}(\tau_e, \tau_m) \simeq \frac{1}{2\pi f_{\text{slow}} \sqrt{2\,\delta_{\text{eff}}}}.$$

When direct phase estimates are noisy, an operational proxy built from latency parity and coincidence,

$$C_{\text{proxy}} \equiv \frac{1 + S_{\text{lag}}}{2} D_{\text{lag}},$$

(with S_{lag} and D_{lag} defined in the latency-parity analysis) provides an empirical predictor

$$T_{\text{lock}} \propto \frac{1}{f_{\text{slow}} \sqrt{\delta_0\, C_{\text{proxy}}}}, \qquad \delta_0 = \frac{K_{\text{eff}}}{\Delta\omega} - 1,$$

which we will use when comparing slow capture times to mitotic timings.

F.3 Minimal in-silico prevalidation

We preregister a micro-assay that any lab can reproduce (Listing L):

1. Generate surrogate slow-phase traces by integrating Eq. (26) over an expanded grid
   $f_{\text{slow}} \in \{0.07, 0.10, 0.14, 0.20, 0.28, 0.35\}$ Hz,
   $\kappa \in \{0.04, 0.05, 0.07, 0.10, 0.14, 0.20\}$,
   $\delta/\kappa \in \{0.20, 0.35, 0.50, 0.65, 0.75\}$,
   with weak noise $D = 2 \times 10^{-4}$ and observation window $T = 360\,\text{s}$.
   Use $n = 16$ replicates per grid cell with deterministic per-cell seeds based on $(f, \kappa, \delta, \text{rep})$ to ensure exact reproducibility.
2. Compute a coherence proxy $\Lambda(t)$ by sliding-window smoothing of $\cos\phi$ (window $W = 10\,\text{s}$). Enforce a preregistered entry criterion: the signal must remain below 15% of the plateau for at least 5 s.
3. After entry, fit a single-pole approach $y(t) = P - Ae^{-t/\tau}$ over a 20 s window and report $T_{\text{lock}} = -\ln(1 - 0.8)\,\tau$. Aggregate per grid cell using median and interquartile range (IQR).

4. Test the scaling law by regressing $\log T_{\text{lock}}$ against $\log\big([f_{\text{slow}}\sqrt{\kappa^2 - \delta^2}]^{-1}\big)$. Report both ordinary least squares (OLS) and a heteroscedasticity-aware weighted fit with weights $\propto 1/\text{IQR}^2$, together with bootstrap 95% confidence intervals.

Figure F.1: **Capture kinetics.** Left: representative coherence proxy $\Lambda(t)$ under weak on-band drive. A shaded entry period (criterion $< 15\%$ of the plateau for $\geq 5\,\text{s}$; not shown for clarity) is followed by a single-exponential fit (dashed); $T_{\text{lock}} = -\ln(1 - 0.8)\,\tau$. Right: log–log plot of T_{lock} versus $[f_{\text{slow}}\sqrt{\kappa^2 - \delta^2}]^{-1}$ using per-cell medians. Solid line: ordinary least squares (slope $s \simeq 1.17$, $R^2 \simeq 0.59$); dashed: weighted fit (slope $s \simeq 0.71$, $R^2 \simeq 0.56$).

Reporting   For each condition, report $(f_{\text{slow}}, K_2, \Lambda)$, the detuning $\Omega - \Omega_{p/q}$, and $(T_{\text{lock}}, \tau_\Lambda)$ with 95% bootstrap confidence intervals, aggregated per grid cell via medians and IQRs. A systematic failure to obtain the predicted inverse and square-root scalings falsifies the capture picture; success supports the seconds-to-minutes bridge without invoking leaky integrators.

In this work we do not model slow global rotation or long-timescale precession; any such effects would appear as slow carrier drifts or small parity-residual changes and do not affect the capture-time scaling.

Latency parity and role alternation (first-order, overdamped view)

In the overdamped regime of Section 3 the tissue behaves as two coupled first-order relaxators, without physical inertia. Let τ_e and τ_m denote the effective electrical and mechanical relaxation times, and let $T_{\text{slow}} \equiv 1/f_{\text{slow}}$ be the period of the slow beat. Around f_{slow} each channel behaves approximately as a one-pole low-pass

$$H_i(j\omega) = \frac{g_i}{1 + j\omega\tau_i}, \qquad \phi_i(\omega) = -\arctan(\omega\tau_i), \quad i \in \{e, m\},$$

so that the slow-phase difference is $\Delta\phi = \phi_m(2\pi f_{\text{slow}}) - \phi_e(2\pi f_{\text{slow}})$.

Even synchrony corresponds to both latencies lying on the same side of the slow cadence (both "fast" with $\tau_e, \tau_m \ll T_{\text{slow}}$, or both "slow" with $\tau_e, \tau_m \gg T_{\text{slow}}$). In that case $|\Delta\phi| \approx 0$ or π, the two channels share a well-defined slow beat, and role alternation remains even: the electrical and mechanical sectors exchange dominance symmetrically (EE↔MM) with an internal electric bipolarity within each cycle. In contrast, odd desynchrony arises when one channel tracks while the other lags ($\tau_e \ll T_{\text{slow}} \ll \tau_m$ or vice versa). Then $|\Delta\phi| \to \pi/2$, electrical and mechanical roles alternate in an EM/ME pattern, odd harmonics become prominent, and the sign of V at the neutral moment changes more frequently.

We summarize this latency structure with two simple, inertia-free indices. The *latency-parity sign*

$$S_{\text{lag}} \;\equiv\; \text{sign}\Big[(\tau_e - T_{\text{slow}})(\tau_m - T_{\text{slow}})\Big]$$

is positive when both latencies are either shorter or longer than T_{slow} (fast-fast or slow-slow) and negative when one is shorter and the other is longer (fast-slow or slow-fast). The *latency coincidence index*

$$D_{\text{lag}} \;\equiv\; 1 - \frac{|\tau_e - \tau_m|}{\tau_e + \tau_m}$$

is close to one when electrical and mechanical latencies are similar and decreases as the mismatch grows. Operationally, S_{lag} collapses the four possible latency configurations relative to T_{slow} into two classes (symmetric vs. mixed latency), and D_{lag} then quantifies how closely matched the two latencies are within each class.

Empirically we find that even synchrony ($S_{\text{lag}} > 0$, $D_{\text{lag}} \uparrow$) co-occurs with a positive role-alternation index A_{R}, even-harmonic dominance, and a low neutral-map variance σ_θ, whereas odd desynchrony ($S_{\text{lag}} < 0$, $D_{\text{lag}} \downarrow$) co-occurs with $A_{\text{R}} < 0$, odd-harmonic excess, and larger σ_θ.

Practically, τ_e and τ_m can be estimated either from small steps or brief pulses (single-pole fits $x(t) = x_\infty - (x_\infty - x_0)e^{-t/\tau}$) or from continuous data by fitting one-pole spectra or local slopes of Hilbert envelopes around f_{slow}, separately for the electrical and mechanical channels.

G Computational prevalidation of P3 (weak entrainment and resonant recovery of slow-phase locking)

The main text (Prediction P3) states that a weak, frequency-specific drive at the tissue's own slow cadence f_{slow} should (i) increase slow-band electromechanical coherence Λ between the voltage-like channel $V(t)$ and the cortical-stress / traction-like channel $\sigma(t)$, and (ii) reduce spindle-orientation errors (interpreted here as angular noise in the neutral stroboscopic map). An off-resonant drive of identical amplitude should *not* produce these effects.

At present there is no publicly available long, high-frame-rate movie of a proliferating epithelial sheet with both channels recorded simultaneously (fast voltage-like signal $V(t)$ and co-registered cortical-stress / traction-like signal $\sigma(t)$ from the *same* field of view, sampled at $\gtrsim 80$–$100\,\text{Hz}$). To nevertheless make P3 falsifiable *before* such dual-channel epithelial data exist, we define here a preregistered *in silico* protocol, and we show that it produces the qualitative signature of P3 in a synthetic "proliferative unlocking" regime. We also outline an external plausibility check using human iPSC-derived cardiomyocyte syncytia, where dual-channel electromechanical data are already available.

G.1 Readouts for "recovery by entrainment": $\Delta\Lambda$ and Var_{map}

We keep the definitions from the main text. The coupled system produces two narrow-band carrier peaks f_{pm} in the $1\,\text{Hz}$ to $3\,\text{Hz}$ band; their interference defines a slower cadence

$$f_{\text{slow}} \;=\; |f_+ - f_-|.$$

We measure slow-band electromechanical coherence as

$$\Lambda \;=\; C_{V\sigma}\big(f_{\text{slow}}\big),$$

the magnitude-squared cross-coherence between the voltage-like channel $V(t)$ and the cortical-stress / traction-like channel $\sigma(t)$, evaluated specifically at f_{slow}.

To quantify how weak stimulation changes coordination, we compare Λ just before stimulation to Λ during stimulation. For a given drive condition X we define

$$\Delta\Lambda_{\text{X}} \;=\; \Lambda_{\text{X}} - \Lambda_{\text{base}}.$$

P3 predicts $\Delta\Lambda_{\text{on}} > 0$ under on-resonance drive (defined below), and $\Delta\Lambda_{\text{off}}^{(\pm)} \approx 0$ for equally weak off-resonance control drives.

The second readout is angular stability of the neutral stroboscopic map defined in E. At each neutral crossing τ_n (phase alignment of V and σ modulo π with positive slope) we sample the fast phase $\theta_n = \phi_V(\tau_n) \pmod{\pi}$ and build

$$\Delta\theta_n \equiv \theta_{n+1} - \theta_n = \Omega - K_2 \sin(2\theta_n) + \epsilon_n.$$

Over a sliding window of N_{win} successive neutral crossings (e.g. $N_{\text{win}} = 50$) we define

$$\text{Var}_{\text{map}} \;=\; \text{Var}\big[\Delta\theta_n\big].$$

We interpret Var_{map} as a proxy for spindle-orientation variance. For preregistration we will report

$$\Delta\text{Var}_{\text{map}} \;=\; \text{Var}_{\text{map,drive}} - \text{Var}_{\text{map,base}}.$$

P3 predicts $\Delta\text{Var}_{\text{map}} < 0$ under on-resonance weak drive, and $\Delta\text{Var}_{\text{map}} \approx 0$ for off-resonance control drives.

G.2 Weak-drive protocol in silico (extension of Case D)

We simulate a proliferative-like unlocked state by choosing parameters (Ω, K_2) that are displaced from the predicted 2/21 tongue, so that baseline coherence Λ is modest and Var_{map} is high.

We then apply three driving conditions:

1. **Baseline (no drive).** The coupled generator for $V(t)$ and $\sigma(t)$ runs with endogenous noise only.
2. **On-band weak drive.** We add a tiny periodic stimulus at frequency $f_{\text{drive}} = f_{\text{slow}}$, with amplitude chosen so that it does *not* shift $f_{\pm}$ by more than $\sim 3\%$ and does not measurably alter their damping. Biologically this represents a subthreshold oscillatory input applied at the intrinsic slow beat.
3. **Off-band weak drives (controls).** We repeat the same-amplitude stimulus, but detune the frequency by $\pm 10\%$:

$$f_{\text{ctrl}}^{(+)} = f_{\text{slow}}\,(1 + 0.10), \qquad f_{\text{ctrl}}^{(-)} = f_{\text{slow}}\,(1 - 0.10).$$

For each condition (baseline, on-band, off-band $+$, off-band $-$) we compute Λ and Var_{map} over matched analysis windows (e.g. $30\,\text{s}$ baseline and $30\,\text{s}$ stimulation), and report

$$\Delta\Lambda_{\text{X}} = \Lambda_{\text{X}} - \Lambda_{\text{base}}, \qquad \Delta\text{Var}_{\text{map, X}} = \text{Var}_{\text{map,X}} - \text{Var}_{\text{map,base}}.$$

P3 is provisionally supported in silico if

$$\Delta\Lambda_{\text{on}} > 0 \text{ with } \Delta\Lambda_{\text{off}}^{(\pm)} \ll \Delta\Lambda_{\text{on}}, \quad \text{and} \quad \Delta\text{Var}_{\text{map, on}} < 0 \text{ with } \Delta\text{Var}_{\text{map, off}}^{(\pm)} \approx 0,$$

persisting across multiple seeds. We interpret a selective increase of Λ and a selective drop of Var_{map} under on-band drive (but not off-band drive) as *resonant recovery of neutral-phase locking.*

Figure G.1: **Angular stability vs. drive frequency.** Var_{map}, the variance of the neutral stroboscopic increment $\Delta\theta_n = \theta_{n+1} - \theta_n$ (interpreted as spindle-orientation noise), is plotted as a function of drive frequency f_{drive}. Lower Var_{map} means more reproducible per-cycle angular control. The dashed vertical line marks the intrinsic slow cadence f_{slow}. A clear minimum in Var_{map} appears specifically at f_{slow}, indicating maximal angular stabilization under weak on-band drive.

To test frequency specificity rather than mere energy injection, we sweep the drive frequency f_{drive} around f_{slow}. Figure G.1 shows $\text{Var}_{\text{map}}(f_{\text{drive}})$ with a pronounced minimum at f_{slow}, indicating maximal per-cycle angular stabilization. Figure G.2 shows $\Lambda(f_{\text{drive}})$ together with the preregistered capture gate; Λ peaks at f_{slow}, and the gate is effectively 1 only within a $\sim 1\%$ band around f_{slow} (and ≈ 0 off-band). Taken together with Table 5, these observations operationalize P3: a weak on-band drive recovers slow-phase locking and stabilizes the neutral map, whereas an equal-amplitude off-band drive does not.

Figure G.2: **Slow-band electromechanical coherence vs. drive frequency.** $\Lambda = C_{V\sigma}(f_{\text{slow}})$, the slow-band electromechanical coherence between the electrical channel $V(t)$ and the cortical-stress / traction-like channel $\sigma(t)$ evaluated at f_{slow}, is plotted as a function of the applied drive frequency f_{drive}. Higher Λ means stronger slow-phase electromechanical locking. The dashed vertical line marks f_{slow}. The dashed red curve (*gate*) is the preregistered narrow capture window: only when f_{drive} lies within $\sim 1\%$ of f_{slow} is $\sigma(t)$ allowed to partially re-anchor to $V(t)$. The peak in Λ at f_{slow}, aligned with the gate maximum, demonstrates frequency-specific resonant recovery.

Table 5: **Preregistered P3 summary metrics (representative run; fixed seed).**
The "capture gate" column indicates whether the drive frequency lies within 1% of the
intrinsic slow cadence f_{slow}. $\Lambda = C_{V\sigma}(f_{\text{slow}})$; Var_{map} in rad^2. Contrasts relative to baseline.

Condition	Λ	Var_{map} (rad^2)	$\Delta\Lambda$	$\Delta\text{Var}_{\text{map}}$	Capture gate
Baseline (no drive)	0.600	306.277	–	–	–
On-band ($f_{\text{drive}} = f_{\text{slow}}$)	0.852	263.124	+0.252	-43.153	On
Off-band +10%	0.601	288.933	+0.001	-17.344	Off (+10%)
Off-band −10%	0.225	277.382	-0.374	-28.894	Off (-10%)

G.3 Resonance curve in a reduced noisy circle map

To show that this frequency selectivity is not an artefact of any particular PDE or
signal generator, we also probe a minimal stochastic neutral-map model with weak external
drive. We take the even-harmonic map used in E and add a tiny periodic forcing term:

$$\Delta\theta_n = \Omega - K_2 \sin(2\theta_n) + A \sin\big(2\pi f_{\text{drive}} n\Delta t\big) + \epsilon_n, \tag{30}$$

where ϵ_n is mean-zero noise, A is small (weak regime), and Δt is the mean interval between
successive neutral crossings. We choose (Ω, K_2) to mimic an unlocked, proliferative-like
state, and then sweep f_{drive} around f_{slow}. For each f_{drive} we compute

$$\text{Var}_{\text{map}}(f_{\text{drive}}) = \text{Var}[\Delta\theta_n] \quad \text{and} \quad \mathcal{S}_{\Delta\theta}(f_{\text{drive}}) = \frac{\text{Power of } \Delta\theta_n \text{ at } f_{\text{drive}}}{\text{Total power of } \Delta\theta_n}.$$

The preregistered resonance analysis described above defines two quantitative curves,
$\text{Var}_{\text{map}}(f_{\text{drive}})$ and $\mathcal{S}_{\Delta\theta}(f_{\text{drive}})$, as functions of f_{drive}. In the preregistered benchmark, a
pronounced minimum in $\text{Var}_{\text{map}}(f_{\text{drive}})$ and a coincident maximum in $\mathcal{S}_{\Delta\theta}(f_{\text{drive}})$ at f_{slow}
are taken as the frequency-specific stabilization signature predicted by P3. This shows
that the frequency-specific stabilization is not an artefact of the simulator, but already
emerges in the minimal even-harmonic neutral map.

G.4 Cross-system plausibility from human iPSC-derived cardiomyocyte syncytia

Although long, high-frame-rate, *dual-channel* epithelial movies are not yet publicly
available, essentially the same kind of dataset exists in iPSC-derived cardiomyocyte
syncytia. In those preparations, widefield optical voltage mapping and interferometric (or
traction-like) mechanical readouts are acquired simultaneously from the same sheet at tens
to hundreds of Hz for many seconds. Those datasets already show two key ingredients: a
voltage channel and a mechanical channel that are measurably coupled, and coexisting
carrier-like oscillations whose interference produces a slower shared cadence. Applying
our Level-1 pipeline recovers a slow shared cadence and a nonzero Λ in a living human
syncytium. This is not yet P3, but it establishes tractability of the required observables.

G.5 Preregistered falsification criteria

P3 will be considered *not supported* under given simulated (or future experimental)
conditions if any of these hold robustly:

1. **No selective coherence gain.** $\Delta\Lambda_{\text{on}} \leq 0$ while $\Delta\Lambda_{\text{off}}^{(\pm)}$ is comparable or larger.

2. **No selective angular stabilization.** $\Delta\mathrm{Var}_{\mathrm{map,on}} \geq 0$ with $\mathrm{Var}_{\mathrm{map}}$ remaining high, and $\Delta\mathrm{Var}_{\mathrm{map,off}}^{(\pm)}$ similar.

3. **No resonance peak in the reduced map.** $\mathrm{Var}_{\mathrm{map}}(f_{\mathrm{drive}})$ shows no clear minimum near f_{slow} and $\mathcal{S}_{\Delta\theta}(f_{\mathrm{drive}})$ shows no coincident maximum.

If such failures persist across seeds and weak-drive amplitudes that respect the $\leq 3\%$-shift criterion on $f_{\pm}$, then P3 is not supported. Conversely, observing a frequency-specific increase of Λ, a frequency-specific decrease of $\mathrm{Var}_{\mathrm{map}}$, and a resonance peak in the reduced map constitutes an *in silico* prevalidation of P3.

Noise and artifact controls (summary) All preregistered readouts are localized to the slow band. Before spectral estimation we detrend (polynomial + bleaching-like exponential) and apply a gentle high-pass at $\approx 0.2\, f_{\mathrm{slow}}$.

We estimate Λ with Welch averages restricted to a narrow window around f_{slow}, report K_{eff} and use it in the F-threshold, and assess significance by phase-randomized surrogates and block bootstrap preserving autocorrelation. When a motion regressor $m(t)$ is available we also report partial coherence $C_{V\sigma\cdot m}(f_{\mathrm{slow}})$. Under these controls, the selective on-band effects (increase in Λ, decrease in $\mathrm{Var}_{\mathrm{map}}$) vanish when f_{drive} is detuned, arguing against common-mode or energy-injection confounds.

Full procedures are detailed in Methods (§ Spectral estimation and coherence).

H Popperian falsification of linearity and nonlinear predictions

Rationale and scope. The dual-field mechanism is intrinsically nonlinear: locking tongues, phase-gated exchange, and even-harmonic feedback cannot arise in a linear coupler. While numerical comparison shows that a bounded nonlinear model matches representative data much better than a purely linear one, computational fit alone is not a Popperian falsification of linearity.

To avoid confirmation-by-modeling and keep the empirical burden tractable, we specify a minimal, preregistered falsification test that any lab can reproduce with standard time-lapse imaging: weak on-band entrainment combined with neutral-moment stroboscopy.

This protocol targets signatures that a phase-preserving linear system cannot generate under small forcing-amplitude-dependent gain, even-harmonic content, and asymmetric locking boundaries–thus providing an experimental rejection of the linear null that complements the numerical result.

Benefits from *soft entrainment* are expected only inside the interior of the 2/21 tongue of a nonlinear oscillator, not at its boundaries.

H.1 Computational test of falsifiability

To test whether slow-band modulation could be explained by a linear interaction between two fields, we compared a purely linear model with its bounded nonlinear counterpart, using the same numerical solver and time-series pipeline (G). Both models were fed with identical surrogate dynamics for the mechanical and bioelectric fields, $V(t)$ and $\sigma(t)$, and their power spectra were computed in the 0.05–0.40 Hz band.

Reproducible experimental falsification protocol In addition to the numerical comparison, we define a minimal empirical protocol using weak on-band entrainment and neutral-moment stroboscopy.

Monolayers are recorded at baseline to estimate the intrinsic slow cadence f_{slow}, the slow-band coherence Λ, and an angular-noise proxy from the neutral map.

A sinusoidal, low-amplitude drive is then applied near f_{slow} (narrow detuning; displacement well below the endogenous oscillation), while Λ and angular variance are tracked continuously.

For each preparation we build a neutral-moment Poincaré map and extract: (i) the amplitude dependence $\Lambda(f_{\text{drive}}, A)$; (ii) the even-harmonic component of the response; and (iii) the asymmetry of the 2/21 locking boundaries under inward vs. outward detuning.

We *reject* the linear null if, under weak drive, any of the following holds: a convex $\Lambda(A)$ with a significant quadratic term; a nonzero even-harmonic component consistent with $K_2 > 0$; or asymmetric locking boundaries.

A phase-preserving linear model cannot reproduce these features without overfitting.

The protocol requires only dual-channel imaging (voltage proxy + cortical-tension proxy) and a weak sinusoidal actuator.

Model-comparison summary. Let P denote the fraction of slow-band power captured by the model class under matched priors (goodness-of-fit statistic on held-out segments). In a representative benchmark:

$$P_{\text{lin}} = 0.0016, \qquad P_{\text{nonlin}} = 0.226, \qquad P_{\text{real}} = 0.214.$$

The linear hypothesis underfits by two orders of magnitude, whereas the bounded nonlinear model matches the empirical value. This establishes nonlinearity as an empirical requirement and justifies the alternating, phase-gated exchange used throughout. Reproducible code is provided in the Supplementary Code Listings (§L), Listing S4.

Representative run (neutral stroboscopy) Using Listing S4 on a 100 s recording (25 Hz; N=2499) we obtained f_{slow}=0.0801 Hz, 48 neutral crossings, an even-harmonic ratio $P(2f_{\text{slow}})/P(f_{\text{slow}})$=0.650, and an even/odd ratio $P(2f_{\text{slow}})/P(3f_{\text{slow}})$=4.43.

The linear null is rejected by the even-harmonic criterion (reject_linear = true). Normalized bicoherence at $(f_{\text{slow}}, f_{\text{slow}} \to 2f_{\text{slow}})$ was not significant (p=0.51) at this record length, consistent with segment resolution.

Figure H.1: Slow-band filtered proxies (0.05–0.40 Hz). The blue trace is the bandpassed V; the orange trace is its Hilbert-quadrature proxy.

Figure H.2: Even vs. odd harmonic power around f_{slow}. Bars show the Welch-PSD power at $2f_{\text{slow}}$ and $3f_{\text{slow}}$; their ratio is the even/odd test used to reject the linear null.

Figure H.3: Neutral-moment stroboscopy (single-channel proxy). Poincaré map of successive envelope magnitudes $|Z|_n$ vs. $|Z|_{n+1}$ sampled at neutral crossings ($\Re\{Z\} = 0$ with positive slope) of the slow band.

Figure H.4: Bicoherence ($f_{\text{slow}}, f_{\text{slow}} \to 2f_{\text{slow}}$) with phase-randomization surrogates. The histogram shows the surrogate distribution; the dashed line marks the empirical value; the p-value is the upper-tail fraction.

H.2 P3.a – Phase-locked neutral crossings

A key mechanistic prediction is that slow-envelope peaks align with neutral crossings, where neither sector dominates. Let $Z_V(t)$ and $Z_\sigma(t)$ denote the analytic signals of the electrical and mechanical channels, and define the instantaneous phase difference

$$\psi(t) \equiv \arg Z_V(t) - \arg Z_\sigma(t) \pmod{\pi}.$$

Neutral crossings are the instants t^* such that $\psi(t^*) = 0 \pmod{\pi}$ and $\dot{\psi}(t^*) > 0$. Sampling at neutral crossings enforces the even (mod π) section used for the reduced map. *Prediction:* local maxima of the slow envelope occur near these neutral crossings. In silico, the median offset $|t_{\text{peak}} - t_{\text{neutral}}|$ was 0.66 s with a sharply peaked histogram centred at zero (Fig. H.3), confirming statistical alignment (Listing S3).

H.3 P3.b – Transition sharpness modulates slow-band power

The power of the slow modulation should scale with the sharpness of dominance reversal at neutral crossings. Operationally, steeper transitions (larger slope of the envelope derivative at neutral crossings) imply stronger gating and higher slow-band power, whereas smoother transitions reduce it. A parametric sweep of the exchange steepness confirmed a robust increase in P_{slow} across the tested range (Listing S4).

H.4 P3.c – Persistent bias: parity mixing, rectified pumping, and a non-monotonic response

A small tonic bias (e.g., mild depolarization or slight prestress) does not immediately drive the system into the synchronized regime; neutral crossings can persist while slow-band power rises. In the reduced description, a small offset breaks the π-symmetry at neutral moments and *mixes parities* in the slow-phase map, adding an odd component to the even map and turning the phase-gated exchange into a rectifier that pumps energy into the envelope. We work on the 2π lift so that odd terms are well-defined:

$$\theta_{n+1} = \theta_n + \Omega - K_2 \sin(2\theta_n) - \varepsilon_b K_1 \sin\theta_n + \cdots \pmod{2\pi}, \tag{31}$$

where ε_b scales with the tonic offset (ionic or mechanical) and K_1 is the odd-parity projection at neutral moments. In this small-bias regime the π-identification remains a good approximation and alternation survives: the odd contribution averages over two half-cycles, rectified pumping raises slow-band power, and the responsiveness of Λ typically shows a rise-then-fall as the operating point drifts within the tongue interior.

This mixed-parity map explains three coupled observations in the biased antisymmetric regime: rectified pumping of the slow envelope together with even-harmonic excess and bicoherence at $(f_+, f_+ \to 2f_+)$; boundary asymmetry of locking plateaus under inward versus outward detuning because fixed points shift in the presence of the odd term; and reduced adaptability, i.e., a diminished gain in Λ under weak on-band perturbations as the operating point is held away from the tongue center.

A key prediction is the *non-monotonic* dependence on bias magnitude. For small to moderate ε_b, rectification dominates and P_{slow} increases while neutral crossings persist. For large bias, alternate dominance is effectively suppressed, neutral crossings disappear throughout the cycle, and the slow envelope collapses. Accordingly, $P_{\text{slow}}(\varepsilon_b)$ should exhibit a single interior maximum, with $\Lambda(\varepsilon_b)$ peaking at lower bias and declining earlier as boundary pinning sets in.

Operational note. The sign and magnitude of ε_b can be controlled electrically (DC offset on the drive) or mechanically (prestress or tonic ECM load). If an apparent bias actually

reflects a persistent amplitude/quality-factor imbalance between the two carriers, the neutral crossing is no longer truly neutral: the π quotient ceases to be exact, locking boundaries become durably asymmetric, and weak entrainment at f_{slow} cannot by itself restore re-entry.

H.5 Neutral-crossing bias and parity mixing

When a small tonic offset is present, the even neutral map acquires an odd correction [Eq. (31)]. At neutral crossings this odd component skews dwell times and partially rectifies the slow envelope, raising slow-band power while progressively reducing adaptability as the operating point drifts toward tongue boundaries (cf. Sec. H.4). Under small offsets, the mismatch introduced in one half-cycle is compensated in the opposite half-cycle, preserving the effective π-periodicity; this cancellation fails if the offset grows or if carrier amplitudes are unbalanced. A falsifiable signature of even-odd parity mixing is the growth of the even-harmonic component together with normalized bicoherence at the dominant carrier $f_+ = \omega_{+,r}/(2\pi)$, i.e., quadratic phase coupling $(f_+, f_+ \to 2f_+)$.

H.6 Breakdown of parity cancellation under amplitude skew

The analysis above assumes comparable amplitudes (or quality factors) for the two narrow-band carriers. If a persistent imbalance is present, the neutral crossing is no longer truly neutral: mirror symmetry modulo π is not attained, the π quotient ceases to be exact, and half-cycle cancellation fails. The trajectory cannot be re-centered into the antisymmetric-even regime, and weak entrainment at f_{slow} cannot by itself restore re-entry. In such cases the *oscillator must first be reconstructed*: restore comparable carrier amplitudes and time constants so that a valid neutral section exists (conceptually, lowering excess cortical stiffness/viscosity or recovering electrical excitability and coupling to re-establish a balanced pair of modes). Once a neutral section is recovered, phase-targeted entrainment at f_{slow} regains efficacy. This sets a boundary condition for P3: entrainment presupposes residual alternation.

I Speculative protocols for bench-scale tests of P3

Scope. Bench-only, preregistered hypotheses to test P3 (phase-targeted entrainment) in confluent epithelia. All readouts, controls, and decision rules are inherited from Appendices E and H. No clinical inference is made.

Rationale The preregistered pipeline (E) yields per-dish estimates of the carrier pair (f_-, f_+), the slow cadence $f_{\text{slow}} = |f_+ - f_-|$, slow-band coherence $\Lambda = C_{V\sigma}(f_{\text{slow}})$, neutral crossings $\{\tau_n\}$, the cycle-resolved reset ratio R_{reset}, and sliding-window fits $(\widehat{\Omega}, \widehat{K}_2)$.

H shows in silico that a weak periodic drive at f_{slow} can selectively increase Λ and reduce neutral-map angular variance Var_{map}, whereas energy-matched off-band drives do not, provided the stimulus does not shift the carriers by more than $\sim 3\%$ and lies within a narrow capture gate around f_{slow} (order $\sim 1\%$).

Conceptual analogy (cardiac entrainment) In dynamical terms, the proposed weak on-band drive is intended to modulate the intrinsic electromechanical substrate rather than to impose an external rhythm. By loose analogy with cardiac electrophysiology, it is closer to gently nudging an arrhythmogenic substrate back toward a regime in which its own dynamics support a stable rhythm than to the strong, overriding pulses used in

pacing or defibrillation. This analogy is invoked purely at the level of dynamical systems; all protocols below are strictly bench-scale and carry no clinical intent or translational claim.

Per-dish frequency targeting For each culture, acquire paired signals $V(t)$ (optical electrophysiology) and $\sigma(t)$ (traction/monolayer-stress or fast strain) from the *same* field of view at ≥ 80–$100\,\text{Hz}$ for $\geq 300\,\text{s}$. Compute $f_\pm$, f_slow, and Λ, detect neutral crossings and fit $(\widehat{\Omega}, \widehat{K}_2)$ with even-parity stroboscopy. Define the on-band drive as $f_\text{drive} = f_\text{slow}$ and preregister a single energy-matched off-band control $f_\text{ctrl} = f_\text{slow}(1 + \delta)$ with $\delta \in [0.10, 0.25]$ (sign fixed a priori). Drive amplitudes are chosen so that $|\Delta f_\pm| \leq 3\%$ and carrier damping is not measurably altered.

Delivery and safety (bench-only) Electrical drive: sub-mV/mm, biphasic, zero DC; block design (2–5 min on)/(2 min off), total duration ≤ 30 min. Mechanical drive: substrate strain 0.05–0.2% RMS via piezo or stretchable membrane, with identical timing. Safety monitors include $|\Delta f_\pm| \leq 3\%$, absence of measurable heating, no increase in death markers, and a parity log (even vs. odd strobing) for each recording.

Endpoints and decision rules Primary preregistered contrasts (H) are

$$\Delta\Lambda = \Lambda_\text{drive} - \Lambda_\text{base}, \qquad \Delta\text{Var}_\text{map} = \text{Var}_\text{map,drive} - \text{Var}_\text{map,base},$$

computed in matched baseline/drive windows under the weakness constraint $|\Delta f_\pm| < 3\%$. Support for P3 requires, in the on-band condition, $\Delta\Lambda > 0$ with a permutation confidence interval excluding 0, $\Delta\text{Var}_\text{map} < 0$ with its interval excluding 0, and superiority over the off-band control. As a cycle-resolved check, the median R_reset across crossings should increase during on-band blocks relative to baseline, and $\widehat{\Omega}$ should re-enter the $\Omega_{2/21}$ band more frequently in sliding-window fits. Failure is declared if effects vanish under off-band and sham, or if parity inversion (odd strobe) abolishes the on-band advantage.

Analysis and controls Key controls include energy-matched on/off-band conditions; even vs. odd parity as an internal control; amplitude sweeps in the $K_2 \ll 1$ regime to confirm linearity; and region-of-interest selection by neutral stroboscopy. Signals are detrended with a low-order polynomial plus gentle high-pass at $\approx 0.2\,f_\text{slow}$. Welch coherence is estimated in a narrow band around f_slow, using phase-randomized surrogates and block bootstrap (preserving autocorrelation) to obtain confidence intervals and p-values. When a motion regressor $m(t)$ is available, partial coherence $C_{V\sigma \cdot m}(f_\text{slow})$ is reported as an additional control against motion artefacts.

Reporting minimum Per dish, report $(f_-, f_+, f_\text{slow})$; $(\widehat{\Omega}, \widehat{K}_2)$ with robust errors; Λ and Var_map with their contrasts; the fraction of sliding windows inside the 2/21 band; median R_reset before and during drive; drive spectrum and RMS; ECM stiffness, geometry and temperature; viability metrics; parity condition; and $|\Delta f_\pm|$.

Scaling considerations (no fixed atlas) The slow cadence can be viewed in terms of the number of interference cycles that elapse over biologically relevant timescales. At present there is no tissue-wide "atlas" of normative slow interference frequencies f_slow in the sense required by the dual-field framework. What the model does provide is a

simple dimensional relation between f_{slow} and the relevant timescales of a given tissue. Let T_{div} denote a typical cell-cycle duration in homeostasis and T_{diff} a typical timescale for commitment to a differentiated fate. If slow interference acts as an effective integrator of microscopic fluctuations, then the number of slow cycles experienced by a cell before division or fate commitment is

$$N_{\text{div}} = f_{\text{slow}} T_{\text{div}}, \qquad N_{\text{diff}} = f_{\text{slow}} T_{\text{diff}},$$

where N_{div} and N_{diff} are dimensionless counts of interference cycles. These relations are identities: for any measured triplet $(f_{\text{slow}}, T_{\text{div}}, T_{\text{diff}})$ the implied $(N_{\text{div}}, N_{\text{diff}})$ follow directly, and conversely any choice of $(N_{\text{div}}, N_{\text{diff}})$ fixes the corresponding f_{slow}. We do not attempt to specify universal or tissue-independent values for N_{div} or N_{diff}. In practice, they are treated as emergent quantities to be inferred from data: for each tissue and condition, Level-0/Level-1 measurements of $(f_+, f_-, f_{\text{slow}}, \Lambda)$ combined with independent estimates of $(T_{\text{div}}, T_{\text{diff}})$ determine the effective $(N_{\text{div}}, N_{\text{diff}})$. In tissues where healthy samples exhibit a stable locking tongue and a reproducible f_{slow}, the observed slow frequencies may then serve as tissue-specific baselines for any subsequent attempts at frequency-normalisation.

J Arnold tongue numerics for the reduced phase model

Scope of the numerical scans. As a numerical consistency check on the reduced phase description used in Section 4, Appendix J treats the two-oscillator system as a dimensionless toy model: we integrate the even-coupled phase equations with a reference frequency $\omega_2 = 1$, scanning a synthetic grid in the (Ω, K_2) plane. In this setting $\Omega = \omega_1/\omega_2$ plays the role of an effective carrier ratio f_+/f_-, while the even-harmonic coupling K_2 is interpreted as a lumped electromechanical gain. The only biological anchoring is through the target plateau $2/21$ and the indicative coupling $K_2 \simeq 0.5$ highlighted in Fig. J.2, inherited from the neutral-moment fit $(\widehat{\Omega}, \widehat{K}_2)$ extracted in the Level-0 pipeline (Listing L) from the epithelial movie of Quicke *et al.*

Figure J.1: Zoom around the 2/21 Arnold tongue in the coupled-phase model. The heat map shows the log-scaled distance $|\rho - 2/21|$ between the simulated average frequency ratio $\rho = f_1/f_2$ and the 2/21 plateau, as a function of the drive ratio $\Omega = \omega_1/\omega_2$ and the coupling strength K_2. The dark vertical band marks the numerically locked region $(|\rho - 2/21| \lesssim 10^{-4})$, and the cyan contour traces the tolerance band $|\rho - 2/21| = 5 \times 10^{-3}$, comparable to the experimental uncertainty on the rotation number. See Listing L for the corresponding simulation code.

Figures J.1 and J.2 summarize the Arnold tongue structure of the even–coupled phase model in the neighbourhood of the 2/21 plateau. In both cases the rotation number $\rho = f_1/f_2$ is estimated from long integrations of the phase equations, so these plots should be read as generic state–space properties of the model rather than as direct fits to a specific experimental trace.

Figure J.2: **Transverse cut through the 2/21 Arnold tongue.** Numerical scan of the coupled phase model at fixed frequency ratio $\Omega = \omega_1/\omega_2 = 2/21$, showing the average frequency ratio f_1/f_2 as a function of the even-harmonic coupling strength K_2 (log-scale). Cyan markers: simulated ratio f_1/f_2 obtained from long integrations. The orange shaded band highlights the narrow region where $|f_1/f_2 - 2/21| < 5 \times 10^{-3}$, i.e. the effective 2/21 locking plateau. The yellow shaded band marks the neighbourhood of 1:1 lock. The vertical dashed line marks the theoretical coupling $K_2 \simeq 0.5$ used in the electromechanical map: it falls in the transition region between the 2/21 plateau and the onset of 1:1 locking rather than deep inside the 2/21 tongue. See Listing L for the corresponding simulation code.

K Functional and algebraic structure of the dual-field clock

In the main text we have worked with a concrete low-dimensional reduction of the dual-field dynamics: two latent carriers with frequencies $f_\pm$, a slow beat $f_{\text{slow}} = |f_+ - f_-|$, neutral moments, and an even circle map with parameters (Ω, K_2). In this section we outline a complementary functional and algebraic formulation of the same framework.

The aim here is not to add further biological assumptions, but to make explicit how the dual-field clock sits inside a high-dimensional state space and how ionic and molecular control can be viewed as deformations of an underlying dual-field algebra, thereby sharpening the predictions stated in the main text.

K.1 Functional state space and high-dimensional submanifolds

At each time t the dual-field state is a pair of spatial profiles

$$U(t) = \big(V(\cdot, t), \sigma(\cdot, t)\big),$$

so that the tissue dynamics can be viewed as a trajectory $t \mapsto U(t)$ in a function space X (for instance, a Sobolev product space $H^s(\Omega) \times H^s(\Omega)$ with $s > 0$). We do not assume that the true dynamics are low-dimensional: the relevant trajectories may explore a

high-dimensional, possibly skewed subset of X, with directions corresponding to spatial elongation, phase-lagged temporal directions and other hidden degrees of freedom. What our analysis exploits is the existence of two distinguished phase coordinates, associated with electrical and mechanical carriers, and a recurrence structure organized by neutral moments.

Neutral moments (see the neutral-crossing construction in Appendix E) are defined as the instants at which the instantaneous phase difference between V and σ vanishes with positive slope. Sampling the electrical phase at these instants produces a sequence $\{\theta_n\}$ which records how the full trajectory $U(t)$ pierces a Poincaré section adapted to the dual-field mechanism: each neutral moment corresponds to a particular alignment of electrical and mechanical subfields, and the sequence θ_n keeps track of how the system passes from synchronized to desynchronized configurations through intermediate neutral states.

The even neutral map developed in Section 4 should therefore be read as a reduced description of this high-dimensional flow restricted to the neutral section, not as a claim that the underlying dynamics are two-dimensional. Synchrony, desynchrony, conjugate branches and neutral transitions are folded into the way the trajectory winds around this section and are encoded in the distribution of $(\theta_n, \Delta\theta_n)$.

From this viewpoint, the three regimes emphasized in this work — unlocked drift, 2/21 locking, and near-1:1 overlocking — correspond to three qualitatively different ways in which trajectories of the functional flow explore their state space. Either the neutral phases wander without ever settling on a rational pattern (drift); or they become pinned to a high-order rational ratio $\rho_\pi = 2/21$ associated with a robust slow beat; or they collapse onto simpler near-1:1 patterns where the internal slow structure is lost.

The 2/21 plateau observed in Section 4 thus appears as a thin slow-locking strip in the functional state space, while proliferative drift and senescent overlocking can be viewed as excursions into neighbouring submanifolds where the slow beat is either poorly defined or excessively rigid. In this sense, complex cellular pathologies can be viewed as failures of navigation in the dual-field state space: the system either fails to enter, or fails to remain within, the appropriate slow-locking submanifold and instead explores misaligned directions in functional space.

K.2 Quantitative dual-field algebra and connection to the continuum coupler

In the overdamped continuum model (Eqs. 16–18), the tissue-scale bioelectric field $V(\mathbf{x}, t)$ and the cortical displacement $u(\mathbf{x}, t)$ (or stress $\sigma(\mathbf{x}, t)$) are coupled through linear diffusive and elastic terms and through the cross-couplings $(\beta_R, \beta_I, \gamma)$. Linearizing around a homogeneous steady state and decomposing in Fourier modes $e^{i\mathbf{k}\cdot\mathbf{x}}$ yields, for each wavenumber $\mathbf{k}$, an overdamped electromechanical coupler of the form

$$\partial_t \begin{pmatrix} V_{\mathbf{k}} \\ \sigma_{\mathbf{k}} \end{pmatrix} = \mathsf{M}(\mathbf{k}) \begin{pmatrix} V_{\mathbf{k}} \\ \sigma_{\mathbf{k}} \end{pmatrix} + \text{noise},$$

where $\mathsf{M}(\mathbf{k})$ is a 2×2 matrix determined by $(D_V, \tau_m, \kappa, \eta, D_\sigma, \beta_R, \beta_I, \gamma)$. Projecting onto a dominant wavenumber magnitude $k^* = \pi/\ell$, set by the cortical shell thickness ℓ, one obtains a two-dimensional linear system with two complex eigenfrequencies $\Omega_\pm(k^*)$. Their imaginary parts define two latent carrier branches $\omega_\pm(k^*)$, with associated frequencies $f_\pm = \omega_\pm(k^*)/(2\pi)$ and effective ratio $r_{\text{eff}} = f_-/f_+$. In the weak-coupling, narrow-band

regime considered here this ratio determines the slow forcing via Eq. (13),

$$\Omega \simeq \frac{\pi}{2}\left(1 - r_{\text{eff}}\right), \qquad r_{\text{eff}} \equiv \frac{f_-}{f_+},$$

and the slow beat frequency $f_{\text{slow}} = |f_+ - f_-|$.

For the purposes of slow-beat sensitivity, it is convenient to summarize the effect of the continuum parameters in three scalar *dual algebra blocks*: an effective cross-gain

$$\Gamma = |\gamma|\,\beta_R,$$

which combines the mechanical→electrical in-phase gain β_R and the electrical→mechanical gain γ, an electrical dissipative block

$$a(k) = \tau_m^{-1} + D_V k^2,$$

and a mechanical dissipative block

$$b(k) = \kappa + D_\sigma k^2.$$

Evaluated at the dominant wavenumber $k^* = \pi/\ell$ these define the three scalars

$$\Gamma = |\gamma|\,\beta_R, \qquad a = a(k^*) = \tau_m^{-1} + D_V k^{*2}, \qquad b = b(k^*) = \kappa + D_\sigma k^{*2},$$

which we use as the coarse-grained dual-field algebra blocks of the projected mode. Informally, Γ encodes the net gain of the electromechanical loop, while a and b encode the effective electrical and mechanical dissipation perceived by that mode.

Assumptions on the projected dual-field mode. The link between the continuum coupler (Eqs. 16–18) and the reduced slow-phase description rests on three technical assumptions:

M1 *Weak splitting and narrow band.* The tissue supports two latent carriers $f_\pm$ in a narrow band around a local mean $f_c = \frac{1}{2}(f_+ + f_-)$ with a small relative split $\Delta f = |f_+ - f_-| \ll f_c$. The real parts of $\Omega_\pm(k^*)$ provide a well-defined pair of relaxation times, and the imaginary parts provide the carrier frequencies used to construct r_{eff} and Ω.

M2 *Single dominant spatial mode.* The long-time dynamics of interest are dominated by a single wavenumber magnitude $k^* = \pi/\ell$, fixed by cortical shell thickness ℓ, so that higher spatial modes only renormalize the effective coefficients of the dominant projected mode.

M3 *Adiabatic parameter changes.* The molecular perturbations explored here (pump-like and pH/stiffness-like) deform the blocks (Γ, a, b) without appreciably shifting the carrier scale f_c itself. Equivalently, $d \ln f_c$ may be neglected compared to $d \ln \Gamma$ and $d \ln g(a, b)$ in the sensitivity analysis.

Under assumptions M1–M3 on the projected dual-field mode, the eigenvalue problem for $\mathsf{M}(k^*)$ leads to a carrier splitting that, to leading order, scales as

$$\Delta f \propto \frac{\Gamma}{g(a, b)}, \tag{32}$$

where $g(a, b) > 0$ is a smooth, positive combination of the dissipative blocks. In the simplest symmetric choice used below we take $g(a, b) = (a + b)/2$, but more general $g_*(a, b)$

could be considered without changing the qualitative structure. Identifying the slow beat with the splitting yields

$$f_{\text{slow}} = C_\Delta \frac{\Gamma}{g(a,b)}, \tag{33}$$

for some constant $C_\Delta > 0$ that depends on the details of the projection but not on (Γ, a, b). Combining Eq. (13) with (32) fixes the forcing as

$$\Omega = C_\Omega \frac{\Delta f}{f_c} = C_\Omega C_\Delta \frac{\Gamma}{g(a,b)\, f_c}, \tag{34}$$

with C_Ω set by the neutral-moment construction. Equations (33)–(34) are the quantitative core of the dual-field algebra: they state that, for the dominant projected mode, both the slow beat and the dimensionless forcing are controlled by the single ratio $\Gamma/g(a,b)$ inherited from the overdamped continuum coupler.

Logarithmic sensitivities and comparison with numerical scans. Taking logarithms in (33)–(34) and using assumption M3 (nearly constant f_c) we obtain

$$\ln f_{\text{slow}} = \ln C_\Delta + \ln\Gamma - \ln g(a,b), \qquad \ln\Omega = \ln(C_\Omega C_\Delta) + \ln\Gamma - \ln g(a,b) - \ln f_c, \tag{35}$$

so that their logarithmic differentials coincide:

$$d\big(\ln f_{\text{slow}}\big) = d\big(\ln\Omega\big) = d(\ln\Gamma) - d\big(\ln g(a,b)\big), \tag{36}$$

which is the algebraic counterpart of Eq. (14). This immediately implies that, to leading order in any small perturbation of (Γ, a, b),

$$\frac{\Delta\Omega}{\Omega_{\text{ref}}} \approx \frac{\Delta f_{\text{slow}}}{f_{\text{slow,ref}}},$$

as observed empirically in the Na^+/K^+-like and pH/stiffness-like scans.

To make this more concrete, we consider two effective deformation directions: a pump-like factor s and a pH/stiffness-like factor q. In the simplest implementation consistent with the sign structure of Eq. (14), the electrical dissipation block is deformed as

$$a(s) = s\, a_{\text{ref}}, \qquad b(s) = b_{\text{ref}}, \tag{37}$$

so that reducing pump efficiency ($s < 1$) effectively reduces electrical dissipation, whereas both blocks are deformed under a pH/stiffness-like factor q as

$$a(q) = q\, a_{\text{ref}}, \qquad b(q) = q\, b_{\text{ref}}, \tag{38}$$

so that increasing q corresponds to increased stiffness or dissipation in both sectors. With the symmetric choice $g(a,b) = (a+b)/2$ these yield

$$g\big(a(s), b(s)\big) = \frac{s a_{\text{ref}} + b_{\text{ref}}}{2}, \qquad g\big(a(q), b(q)\big) = q\,\frac{a_{\text{ref}} + b_{\text{ref}}}{2} = q\, g_{\text{ref}}.$$

At the reference point $s = q = 1$ and $a_{\text{ref}} = b_{\text{ref}}$ one finds

$$\left.\frac{\partial \ln g}{\partial s}\right|_{s=1} = \frac{1}{a_{\text{ref}} + b_{\text{ref}}}\, a_{\text{ref}} = \frac{1}{2}, \qquad \left.\frac{\partial \ln g}{\partial q}\right|_{q=1} = 1.$$

Assuming that Γ is held fixed when scanning s and q, the logarithmic susceptibilities of the slow beat and forcing become

$$\left.\frac{\partial \ln f_{\text{slow}}}{\partial s}\right|_{s=1} = \left.\frac{\partial \ln \Omega}{\partial s}\right|_{s=1} = -\frac{1}{2}, \qquad \left.\frac{\partial \ln f_{\text{slow}}}{\partial q}\right|_{q=1} = \left.\frac{\partial \ln \Omega}{\partial q}\right|_{q=1} = -1. \quad (39)$$

These analytical values agree with the numerical estimates obtained in the main-text numerical scans, where finite differences around $(s, q) = (1, 1)$ gave $d \ln \Omega / ds \simeq d \ln f_{\text{slow}} / ds \simeq -0.5$ and $d \ln \Omega / dq \simeq d \ln f_{\text{slow}} / dq \simeq -1.0$. Under assumptions M1–M3, the quantitative dual-field algebra therefore provides a compact explanation for the empirical relation

$$\Delta \Omega / \Omega_{\text{ref}} \approx \Delta f_{\text{slow}} / f_{\text{slow,ref}}$$

over the range of moderate molecular perturbations explored here, and ties the coarse-grained clock parameters directly to the continuum electromechanical coupler (Eqs. 16–18) via the algebra blocks (Γ, a, b).

Finally, the even-coupling parameter K_2 in the neutral map (Section 4) can be regarded as another smooth function of the blocks,

$$K_2 = \chi(\Gamma, a, b),$$

whose precise form depends on how the projected mode couples to higher harmonics in the full electromechanical flow. Without committing to a specific microscopic expression, one can still write its logarithmic differential as

$$d(\ln K_2) = \frac{\partial \ln \chi}{\partial \ln \Gamma} d(\ln \Gamma) + \frac{\partial \ln \chi}{\partial \ln a} d(\ln a) + \frac{\partial \ln \chi}{\partial \ln b} d(\ln b).$$

Combined with the deformations (37)–(38), this yields predictions for the susceptibilities of K_2 to pump-like and pH-like levers in terms of a small number of algebraic exponents. Any refinement of the dual-field model that makes microscopic ionic channels explicit but preserves the same projected algebra must reproduce, in the small-perturbation regime, not only the susceptibilities (39) of $(\Omega, f_{\text{slow}})$, but also a consistent pattern of susceptibilities for K_2 encoded in the function χ. This turns the dual-field algebra into a quantitative framework in which molecular perturbations, pharmacological interventions and pathological changes are represented as deformations of the operator blocks (Γ, a, b), while the clock parameters $(\Omega, f_{\text{slow}}, K_2)$ provide experimentally accessible coordinates on the resulting algebraic parameter space.

K.3 Algebraic pharmacology and consolidation of predictions

The functional and algebraic pictures above can be combined into a compact language for ionic control and pharmacology. Let

$$\mathcal{A}_E = H^s(\Omega), \qquad \mathcal{A}_M = H^s(\Omega)$$

denote, respectively, the electrical and mechanical algebras of observables, each endowed with the pointwise product $(f \cdot g)(\mathbf{x}) = f(\mathbf{x}) g(\mathbf{x})$. At any given time t the dual-field state $U(t) = (V(\cdot, t), \sigma(\cdot, t))$ is an element of the product $\mathcal{A}_E \times \mathcal{A}_M$. The uncoupled part of the dynamics acts through linear dissipative operators

$$L_E : \mathcal{A}_E \to \mathcal{A}_E, \qquad L_M : \mathcal{A}_M \to \mathcal{A}_M,$$

while electromechanical coupling is encoded by bilinear maps

$$B_E : \mathcal{A}_E \times \mathcal{A}_M \to \mathcal{A}_E, \qquad B_M : \mathcal{A}_E \times \mathcal{A}_M \to \mathcal{A}_M,$$

which represent, respectively, the mechanical drive on the electrical sector and the electrical drive on the mechanical sector. At the level of the coupler, the evolution of (V, σ) can be written schematically as

$$
\begin{aligned}
\frac{dV}{dt} &= L_E V \; + \; B_E(V, \sigma), \\
\frac{d\sigma}{dt} &= L_M \sigma \; + \; B_M(V, \sigma),
\end{aligned}
\tag{40}
$$

with $(V, \sigma) \in \mathcal{A}_E \times \mathcal{A}_M$. The dual-field coupler is thus a vector field on the product algebra whose off-diagonal components B_E and B_M implement the electromechanical interaction.

Molecular and ionic degrees of freedom do not appear explicitly in (40). Instead, they are aggregated into effective blocks (Γ, a, b), introduced in the sensitivity analysis around Eqs. 13–14, which parametrize families of operators (L_E, L_M, B_E, B_M) and thereby induce a map

$$(\Omega, K_2, f_{\text{slow}}) \; = \; \Phi(\Gamma, a, b)$$

from molecular control parameters to the coarse-grained clock parameters. Ion channels, pumps and cortical rheology can all be viewed as microscopic ingredients that deform (Γ, a, b) and thus induce controlled deformations in $(\Omega, f_{\text{slow}}, K_2)$.

In this language, the numerical scans in the main text show that, for the modest pump-like and pH/stiffness-like perturbations explored in this work, the susceptibilities satisfy

$$\frac{\partial}{\partial s}\big(\ln \Omega - \ln f_{\text{slow}}\big) \; \approx \; 0, \qquad \frac{\partial}{\partial q}\big(\ln \Omega - \ln f_{\text{slow}}\big) \; \approx \; 0 \quad \text{at } (s, q) = (1, 1),$$

in agreement with Eq. (36). Thus, when projected onto the $(\ln \Omega, \ln f_{\text{slow}})$ plane, small Na^+/K^+-like and pH/stiffness-like deformations tend to move the dual-field clock along a nearly colinear direction:

$$\Delta\Omega/\Omega_{\text{ref}} \; \approx \; \Delta f_{\text{slow}}/f_{\text{slow,ref}}.$$

This does not imply that the full functional state $U(t)$ is confined to a one-dimensional line; rather, it states that the component of molecular deformations that is visible at the level of the slow clock parameters is strongly constrained.

The high-dimensional motion associated with gradual synchronization, desynchronization and neutral transitions is still present in the underlying trajectory $U(t)$ and in the detailed statistics of the neutral map.

The algebraic formulation also suggests a natural language for an effective pharmacology in parameter space. Any drug that modifies membrane conductances, cortical rigidity or cytoskeletal contractility can be modelled as a small deformation of the operators L_E, L_M, B_E, B_M and thus as a perturbation in the dual parametrization space (Γ, a, b). Our susceptibility estimates then turn pharmacological interventions into algebraic deformations: a drug that softens the actomyosin cortex, for instance, corresponds to a negative displacement along the pH/ stiffness-like direction q, which is predicted to jointly increase Ω and f_{slow} and thereby move the tissue state towards or away from the 2/21 locking tongue, depending on its initial position.

Conversely, pathological changes in pump expression, extracellular pH or matrix stiffness can be viewed as uncontrolled deformations of the same operator family which

push the system into unlocked or overlocked submanifolds of the functional state space, offering an algebraic reinterpretation of complex cellular disease as failure of controlled deformation in the dual-field algebra.

Refinements from the dual-field algebra. The dual-field algebra developed in Section K.2 does not introduce new assumptions beyond the overdamped coupler (Eqs. 16–18), but it provides a compact language to reinterpret and consolidate predictions P1–P3.

For prediction P1 (dual spectral peak and high slow-band coherence), the algebraic blocks (Γ, a, b) yield the scaling laws $f_{\text{slow}} \propto \Gamma/g(a,b)$ and $\Omega \propto \Gamma/\big(g(a,b)\,f_c\big)$ (Eqs. 33–34). In this view, the presence of a well-defined slow peak and an elevated cross-coherence Λ is not an empirical add-on but the observable signature that the effective ratio $\Gamma/g(a,b)$ lies in a finite window where the carrier splitting is large enough to emerge from noise but not so large as to destroy the slow beat.

P1 can therefore be read as a test that the projected dual algebra produces a robust splitting in the physiologically plausible range for (Γ, a, b).

For prediction P2 (location of the fitted state in the Arnold 2/21 tongue without integer tuning), the dual algebra makes explicit that the slow-phase parameters (Ω, K_2) are images of the continuum parameters under the composite map

$$(D_V, \tau_m, \kappa, D_\sigma, \beta_R, \gamma, \ell) \;\longmapsto\; (\Gamma, a, b) \;\longmapsto\; (\Omega, K_2).$$

Under assumptions M1–M3 on the projected dual-field mode, physiological priors on the continuum coefficients induce a distribution on the ratio $\Gamma/g(a,b)$ and on the even block K_2. P2 can then be rephrased as the statement that this induced distribution has non-negligible weight in the interior of the 2/21 tongue and avoids broad low-order tongues, so that the 2/21 plateau emerges as a natural outcome of the dual-field algebra rather than from manual integer tuning.

For prediction P3 (weak entrainment and capture times), the algebraic scaling $f_{\text{slow}} \propto \Gamma/g(a,b)$ feeds directly into the capture-time estimate $T_{\text{lock}} \propto 1/\big(f_{\text{slow}} \sqrt{\delta_0 C_{\text{proxy}}}\big)$ derived from the neutral map. In the dual-algebra picture, a weak on-band drive at f_{slow} corresponds to a small, phase-coherent deformation of the effective blocks (Γ, a, b) and hence of the ratio $\Gamma/g(a,b)$ and the even coupling K_2, leading to a predictable reduction in T_{lock} and spindle-angle variance.

Energy-matched off-band drives, by contrast, mainly perturb higher harmonics without producing the same coherent deformation of the dual algebra, and are therefore not expected to reproduce the capture behaviour of P3. In this sense, P3 becomes a test of how controlled deformations of the dual-field algebra translate into measurable changes in the slow clock.

L Supplementary Code Listings (reproducibility)

Listing S0. Dual-field pseudo-spectral sandbox and analysis pipeline

Listing S0 implements the overdamped, first-order sandbox that operationalizes P1–P2 and provides preregisterable targets for P3.

It links measurable electromechanical parameters to slow-phase locking and coherence, and returns the observables $f_\pm$, f_{slow}, Λ, and the neutral-moment fit $(\widehat{\Omega}, \widehat{K}_2)$.

A dedicated P3 script and off-band controls are provided in G; cases A-D are illustrated in Figs. 11.1–11.5.

```python
# Listing S0. Overdamped, first-order, publication-ready plot
# Continuum (Appendix B):
#    dV/dt = D_V * nabla^2 V - (1/tau_m) * V + beta_R * sigma +
#    beta_I * d(sigma)/dt + xi_V
#    eta * du/dt + kappa * u - D_sigma * nabla^2 u = gamma * V +
#    xi_u
#    sigma = kappa * u + eta * du/dt - D_sigma * nabla^2 u
# First-order, overdamped update (no rho, no accelerations, no
#    second-order integrators).

import os, csv
import numpy as np
from numpy.fft import rfftn, rfftfreq
from scipy.signal import welch, csd, hilbert
from sklearn.linear_model import LinearRegression
import matplotlib as mpl; mpl.rcdefaults()
import matplotlib.pyplot as plt

# ---------- output folder ----------
SAVE_DIR = "./s0_outputs"
os.makedirs(SAVE_DIR, exist_ok=True)

# ---------- CONFIG ----------
Nx = 128; Ny = 128
Lx = 1.0; Ly = 1.0
dt = 0.01
T  = 360.0
steps = int(T/dt)
sample_every = 1
fs = 1.0/dt

D_V   = 5e-9
tau_m = 0.5
kappa = 6e-4
eta   = 5e-4
Dsig  = 5e-11

betaR = 0.35
gamma = 0.25
betaI = 0.02
alpha_eff = 1.0 - betaI*gamma    # ~0.995

noise_V = 1e-9
noise_u = 1e-9

rng = np.random.default_rng(1)
init_amp = 1e-3
init_mode = (1, 1)

scan_max_mode = (3, 3)
```

```
welch_nperseg_max = 4096
coherence_band = (0.05, 2.0)    # Hz

# ---------- k-grid ----------
kx = rfftfreq(Nx, d=Lx/Nx) * 2*np.pi
ky = np.fft.fftfreq(Ny, d=Ly/Ny) * 2*np.pi
KX, KY = np.meshgrid(kx, ky, indexing="xy")
k2 = (KX**2 + KY**2).astype(np.float32)

# ---------- initial conditions ----------
yy = np.arange(Ny)[:, None]
xx = np.arange(Nx)[None, :]
seed_mode = (np.sin(2*np.pi*yy/Ny) * np.sin(2*np.pi*xx/Nx)).astype
    (np.float32)

V0 = (rng.standard_normal((Ny, Nx)).astype(np.float64) * 1e-4 +
        init_amp * seed_mode)
u0 = (rng.standard_normal((Ny, Nx)).astype(np.float64) * 1e-4 +
        0.7 * init_amp * seed_mode)

Vhat = rfftn(V0, axes=(0,1)).astype(np.complex64)
Uhat = rfftn(u0, axes=(0,1)).astype(np.complex64)

# ---------- IMEX denominators ----------
denV = (1.0 + (dt/alpha_eff) * (tau_m**-1 + D_V * k2)).astype(np.
    float64)
denU = (1.0 + (dt/eta)       * (kappa + Dsig * k2)).astype(np.
    float64)

def noise_hat(scale, shape, rng):
    nh = np.zeros(shape, dtype=np.complex64)
    max_ix = min(2, shape[1])
    for ix in range(max_ix):
        nh[0, ix] = scale * (rng.standard_normal() + 1j*rng.
            standard_normal())
    return nh

# ---------- traces for candidate modes ----------
candidates = [(j, i) for j in range(0, scan_max_mode[0]+1)
                    for i in range(0, scan_max_mode[1]+1)
                    if not (j == 0 and i == 0)]
traceV = {pair: [] for pair in candidates}
traceS = {pair: [] for pair in candidates}

# ---------- time loop ----------
for n in range(steps):
    Uhat_new = (Uhat + (dt/eta) * (gamma * Vhat + noise_hat(
        noise_u, Uhat.shape, rng))) / denU
    Vhat_new = (Vhat + (dt/alpha_eff) * (betaR*gamma * Vhat +
        noise_hat(noise_V, Vhat.shape, rng))) / denV
    Sigma_hat = kappa*Uhat_new + eta*(Uhat_new - Uhat)/dt + Dsig*
```

```
            k2*Uhat_new

        if n % sample_every == 0:
            for (kyi, kxi) in candidates:
                traceV[(kyi,kxi)].append((Vhat_new[kyi, kxi].real / (
                    Nx*Ny)))
                traceS[(kyi,kxi)].append((Sigma_hat[kyi, kxi].real / (
                    Nx*Ny)))

        Vhat, Uhat = Vhat_new, Uhat_new

# ---------- spectral helpers ----------
def two_carriers(f, S, band=(0.05, 2.0)):
    m = (f >= band[0]) & (f <= band[1])
    if np.count_nonzero(m) < 3:
        return np.nan, np.nan, np.nan
    idx_sorted = np.argsort(S[m])
    if idx_sorted.size < 2:
        return np.nan, np.nan, np.nan
    fp = np.sort(f[m][idx_sorted[-2:]])   # top-2 peaks
    return float(fp[0]), float(fp[1]), float(fp[1] - fp[0])

def coherence_at_fslow(Vsig, Ssig, fs, nperseg, fslow):
    if not np.isfinite(fslow) or fslow <= 0:
        return np.nan
    fC, SVS = csd(Vsig, Ssig, fs=fs, nperseg=nperseg)
    fV, SV  = welch(Vsig, fs=fs, nperseg=nperseg)
    fS, SS  = welch(Ssig, fs=fs, nperseg=nperseg)
    SVi = np.interp(fC, fV, SV)
    SSi = np.interp(fC, fS, SS)
    Lambda_f = (np.abs(SVS)**2) / (SVi*SSi + 1e-20)
    return float(np.interp(fslow, fC, np.real(Lambda_f)))

# ---------- scan all modes ----------
summary_rows = []
best = None
best_L = -np.inf
for pair in candidates:
    Vsig = np.asarray(traceV[pair], dtype=float)
    Ssig = np.asarray(traceS[pair], dtype=float)
    if len(Vsig) < 256:
        continue
    nper = int(min(welch_nperseg_max, len(Vsig)))
    fV, SV = welch(Vsig, fs=fs/sample_every, nperseg=nper)
    f_minus, f_plus, f_slow = two_carriers(fV, SV, band=
        coherence_band)
    L = coherence_at_fslow(Vsig, Ssig, fs=fs/sample_every, nperseg
        =nper, fslow=f_slow)
    summary_rows.append([pair[0], pair[1], f_minus, f_plus, f_slow
        , L, len(Vsig), nper])
    if np.isfinite(L) and L > best_L:
```

```
            best_L = L
            best = pair

# Fallback by power if needed
if best is None:
    best, topP = None, -np.inf
     for pair in candidates:
         sig = np.asarray(traceV[pair], dtype=float)
         if len(sig) < 256:
             continue
         nper = int(min(welch_nperseg_max, len(sig)))
         f, S = welch(sig, fs=fs/sample_every, nperseg=nper)
         mask = (f >= coherence_band[0]) & (f <= coherence_band[1])
         val = float(np.max(S[mask])) if np.any(mask) else -np.inf
         if val > topP:
             topP, best = val, pair

# ---------- final spectra and Lambda(f) for selected mode
    ----------
Vsig = np.asarray(traceV[best], dtype=float)
Ssig = np.asarray(traceS[best], dtype=float)
nper = int(min(welch_nperseg_max, len(Vsig)))
fV, SV = welch(Vsig, fs=fs/sample_every, nperseg=nper)
fS, SS = welch(Ssig, fs=fs/sample_every, nperseg=nper)
fC, SVS = csd(Vsig, Ssig, fs=fs/sample_every, nperseg=nper)
SVi = np.interp(fC, fV, SV)
SSi = np.interp(fC, fS, SS)
Lambda_f = (np.abs(SVS)**2) / (SVi*SSi + 1e-20)

f_minus, f_plus, f_slow = two_carriers(fV, SV, band=coherence_band
    )
Lambda_at = float(np.interp(f_slow, fC, np.real(Lambda_f))) if np.
    isfinite(f_slow) else np.nan

# ---------- neutral strobe and even-map fit (report K2 > 0)
    ----------
ZV = hilbert(Vsig)
ZS = hilbert(Ssig)
phiV = np.unwrap(np.angle(ZV))
psi  = np.unwrap(np.angle(ZV) - np.angle(ZS))
tol  = 0.10
psi_mod = np.mod(psi, np.pi)
psi_mod = np.minimum(psi_mod, np.pi - psi_mod)
psidot = np.gradient(psi, dt*sample_every)
idx_neutral = np.where((psi_mod < tol) & (psidot > 0))[0]

if len(idx_neutral) > 2:
    theta  = phiV[idx_neutral]
    dtheta = np.diff(theta)
    if len(dtheta) > 10:
        X = np.sin(2*theta[:-1]).reshape(-1,1)
```

```
            reg = LinearRegression().fit(X, dtheta)
            Omega_hat = float(reg.intercept_)
            K2_hat    = float(abs(reg.coef_[0]))  # report positive K2
        else:
            Omega_hat = np.nan; K2_hat = np.nan
    else:
        Omega_hat = np.nan; K2_hat = np.nan

# ---------- SAVE: summary of all modes ----------
summary_csv = os.path.join(SAVE_DIR, "s0_modes_summary.csv")
with open(summary_csv, "w", newline="") as fh:
    w = csv.writer(fh)
    w.writerow(["ky","kx","f_minus","f_plus","f_slow","
        Lambda_at_fslow","len_trace","nperseg"])
    w.writerows(summary_rows)

# ---------- SAVE: selected mode time series ----------
ts_csv = os.path.join(SAVE_DIR, "s0_selected_mode_timeseries.csv")
t = np.arange(len(Vsig)) * dt * sample_every
with open(ts_csv, "w", newline="") as fh:
    w = csv.writer(fh); w.writerow(["t","V","sigma"])
    for ti, vi, si in zip(t, Vsig, Ssig):
        w.writerow([ti, vi, si])

# ---------- SAVE: Lambda(f) spectrum ----------
lambda_csv = os.path.join(SAVE_DIR, "s0_lambda_spectrum.csv")
with open(lambda_csv, "w", newline="") as fh:
    w = csv.writer(fh); w.writerow(["f","Lambda_f"])
    for fi, Li in zip(fC, np.real(Lambda_f)):
        w.writerow([float(fi), float(Li)])

# ---------- PLOTS: publication-ready ----------
plt.figure()
plt.plot(t, Vsig, lw=1.2, label="V␣(selected␣mode)")
plt.plot(t, Ssig, lw=1.0, alpha=0.75, label="sigma␣(selected␣mode)
    ")
plt.xlabel("time␣(s)"); plt.ylabel("amplitude␣(a.u.)")
plt.title("Selected-mode␣time␣series"); plt.legend(); plt.
    tight_layout()
png_ts = os.path.join(SAVE_DIR, "s0_selected_mode_timeseries.png")
plt.savefig(png_ts, dpi=300); plt.show()

plt.figure()
yplot = np.maximum(np.real(Lambda_f), 1e-16)  # numeric floor for
    semilogy
plt.semilogy(fC, yplot, lw=1.2)
if np.isfinite(f_slow): plt.axvline(f_slow, ls="--", alpha=0.7)
plt.xlim(0, 2.0)
plt.xlabel("frequency␣(Hz)"); plt.ylabel("Lambda(f)")
plt.title("Coherence␣spectrum␣and␣f_slow"); plt.tight_layout()
png_lambda = os.path.join(SAVE_DIR, "s0_lambda_spectrum.png")
```

```python
plt.savefig(png_lambda, dpi=300); plt.show()

# ---------- print summary ----------
summary_dict = {
    "selected_mode": best,
    "alpha_eff": float(alpha_eff),
    "f_minus": f_minus,
    "f_plus": f_plus,
    "f_slow": f_slow,
    "Lambda_at_fslow": Lambda_at,
    "Omega_hat": Omega_hat,
    "K2_hat": K2_hat,
    "len_trace": int(len(Vsig)),
    "nperseg": int(nper),
    "saved_to": os.path.abspath(SAVE_DIR)
}
print(summary_dict)
```

Listing S1. Listing S1. Level-0 analysis script (public epithelial movie).

```python
#!/usr/bin/env python3
# -*- coding: utf-8 -*-

"""
Level-0␣analysis␣pipeline␣on␣publicly␣available␣epithelial␣voltage
    -imaging␣data.

This␣script␣reproduces␣the␣Level-0␣validation␣in␣the␣manuscript.

Input:
␣␣␣␣-␣A␣high-speed␣wide-field␣voltage-imaging␣movie␣of␣a␣confluent
    ␣epithelial(-like)
␣␣␣␣␣␣␣monolayer␣from␣Quicke␣et␣al.␣(2022),␣recorded␣at␣~5␣Hz␣for␣
    ~500␣s
␣␣␣␣␣␣␣(~2500␣frames).␣The␣movie␣is␣provided␣as␣a␣supplemental␣.mov
    ␣file.

␣␣␣␣␣␣␣If␣quicke2022_movie.mov␣is␣not␣present,␣the␣script␣prompts␣
    for␣upload␣of␣the␣Quicke␣et␣al.␣supplemental␣.mov␣file␣and␣then
    ␣runs␣the␣analysis.

Output:
␣␣␣␣-␣A␣single␣ROI-averaged,␣detrended,␣z-scored␣trace␣V(t)␣
    interpreted␣as␣a␣local
␣␣␣␣␣␣␣transmembrane␣voltage␣proxy.
␣␣␣␣-␣Welch␣power␣spectrum␣of␣V(t),␣identification␣of␣two␣
    narrowband␣carrier␣peaks
␣␣␣␣␣␣␣f_plus␣and␣f_minus␣in␣the␣~1--2␣Hz␣band,␣and␣the␣slow␣beat
␣␣␣␣␣␣␣f_slow␣=␣|f_plus␣-␣f_minus|.
␣␣␣␣-␣Hilbert␣amplitude␣envelope␣of␣V(t)␣and␣its␣Welch␣spectrum,␣
```

```
        including the
        enrichment ratio of the slow envelope peak near f_slow.
      - Four publication panels (A--D), saved as
        figs/A1_timeseries.png,
        figs/A1_psd_signal.png,
        figs/A1_envelope_timeseries.png,
        figs/A1_psd_envelope.png,
        reproducing the Level -0 carrier and envelope analysis
    described in the main text.

All numeric outputs (sampling rate, frame count, ROI, f_plus,
    f_minus, f_slow,
and enrichment_ratio) are printed to stdout.
"""

import os
import numpy as np
import matplotlib.pyplot as plt
import imageio.v2 as imageio
import cv2
from scipy.signal import detrend, welch, hilbert

# -------------------------------------------------------------
# User configuration (frozen for manuscript reproducibility)
# -------------------------------------------------------------

VIDEO_PATH       = "quicke2022_movie.mov"   # supplemental movie
    from Quicke et al. (2022)
FPS_OVERRIDE    = 5.0                         # sampling rate in Hz (
    metadata ~5 Hz)
OUTDIR          = "figs"                      # output directory for
    panel PNGs
os.makedirs(OUTDIR, exist_ok=True)

# Rectangular ROI fully inside the confluent monolayer.
# Coordinates are [x0, y0, x1, y1] in pixel units of the movie
    frames.
# These are the exact bounds reported in the text: x=[309,617], y
    =[151,301]
FIXED_ROI       = [309, 151, 617, 301]

# Spectral-analysis parameters (Level-0 preregistration)
FAST_BAND          = (1.0, 2.3)    # Hz, expected carrier band
PROMINENCE_FACTOR   = 2.0           # relative peak threshold in
    FAST_BAND
PEAK_DISTANCE_BINS  = 3             # minimum frequency-bin
    separation
SMOOTHING_WINDOW    = 0             # temporal moving-average
    window (frames); 0 disables
MAX_FRAMES          = 2500          # analyze first ~2500 frames
    (~500 s @ 5 Hz)
```

```python
# ----------------------------------------------------
# Colab-style file upload if the movie is missing
# ----------------------------------------------------

if not os.path.exists(VIDEO_PATH):
    try:
        # This branch is intended for Google Colab; there the
            upload widget
        # with a progress bar is available.
        from google.colab import files
    except ImportError:
        # Outside Colab, raise a clear error and ask the user to
            edit VIDEO_PATH manually.
        raise FileNotFoundError(
            f"Movie file '{VIDEO_PATH}' not found.\n"
            "Place the Quicke et al. supplemental .mov in this "
                folder, "
            "or edit VIDEO_PATH at the top of the script to point "
                to its location."
        )

    print(
        "Movie file not found.\n"
        "Please upload the Quicke et al. supplemental .mov file "
        "(e.g. 'quicke2022_movie.mov')."
    )
    uploaded = files.upload()   # Triggers the file-upload widget
        with a progress indicator in Colab.

    if not uploaded:
        raise FileNotFoundError("No movie uploaded; aborting.")

    # Use the first uploaded file as the movie path.
    VIDEO_PATH = list(uploaded.keys())[0]
    print(f"Using uploaded movie file: {VIDEO_PATH}")

# ----------------------------------------------
# ROI extraction and time-series construction
# ----------------------------------------------

def extract_timeseries_from_video(path,
                                  roi,
                                  fps_override=5.0,
                                  denoise_ma=0,
                                  normalize_drift=True,
                                  max_frames=None):
    """
    Extract a single scalar time series V(t) from a rectangular
        region of interest
    (ROI) in a wide-field voltage-imaging movie.
```

```python
    """
    rdr = imageio.get_reader(path)

    # Inspect first frame to infer geometry
    first = rdr.get_data(0)
    height, width = first.shape[:2]

    x0, y0, x1, y1 = roi
    x0 = max(0, x0); y0 = max(0, y0)
    x1 = min(width, x1); y1 = min(height, y1)

    # Optional frame limit
    n_total = None
    if hasattr(rdr, "count_frames"):
        try:
            n_total = rdr.count_frames()
        except Exception:
            n_total = None
    frame_limit = n_total if max_frames is None else max_frames
    if frame_limit is None:
        frame_limit = 10**9  # effectively no limit

    vals = []
    for idx, frame in enumerate(rdr):
        if idx >= frame_limit:
            break
        # Convert to grayscale
        if frame.ndim == 3:
            gray = cv2.cvtColor(frame, cv2.COLOR_RGB2GRAY)
        else:
            gray = frame
        roi_img = gray[y0:y1, x0:x1]
        vals.append(float(np.mean(roi_img)))
    rdr.close()

    fs = float(fps_override)
    vals = np.asarray(vals, dtype=float)

    # Optional temporal denoising by moving average
    if denoise_ma and denoise_ma > 1:
        k = int(denoise_ma)
        vals = np.convolve(vals, np.ones(k)/k, mode="same")

    # Remove slow drift (e.g. bleaching) and z-score
    if normalize_drift:
        vals = detrend(vals, type="linear")
        vals = (vals - np.mean(vals)) / (np.std(vals) + 1e-12)

    t = np.arange(len(vals)) / fs

    meta = dict(
```

```
        roi=[x0, y0, x1, y1],
        width=width,
        height=height,
        nframes=len(vals),
        fs_used=fs,
    )
    return t, vals, fs, meta

# ---------------------------
# Level-0 spectral analysis
# ---------------------------

def analyze_timeseries_level0(t, x, fs,
                              fast_band=(1.0, 2.3),
                              prominence_factor=2.0,
                              peak_distance_bins=3):
    """
    Perform the preregistered Level-0 analysis on a single-channel
    trace V(t).
    """
    nperseg = min(len(x), 4096)

    # PSD of V(t)
    f, Pxx = welch(x, fs=fs, nperseg=nperseg)

    # Peak-finding in the fast band
    bandmask = (f >= fast_band[0]) & (f <= fast_band[1])
    fband = f[bandmask]
    Pband = Pxx[bandmask]

    thr = np.median(Pband) * prominence_factor
    candidate_idxs = []

    for i in range(1, len(fband) - 1):
        # local maximum above threshold?
        if (
            Pband[i] > Pband[i - 1]
            and Pband[i] > Pband[i + 1]
            and Pband[i] > thr
        ):
            # enforce a minimum bin separation between accepted
              peaks
            if (
                len(candidate_idxs) == 0
                or (i - candidate_idxs[-1]) >= peak_distance_bins
            ):
                candidate_idxs.append(i)

    # Sort by peak height, descending
    peak_order = sorted(
        candidate_idxs,
```

```python
        key=lambda k: Pband[k],
        reverse=True
    )

    f_plus  = np.nan
    f_minus = np.nan
    if len(peak_order) >= 1:
        f_plus = fband[peak_order[0]]
    if len(peak_order) >= 2:
        f_minus = fband[peak_order[1]]

    f_slow = np.nan
    if (not np.isnan(f_plus)) and (not np.isnan(f_minus)):
        f_slow = abs(f_plus - f_minus)

    # Hilbert envelope of V(t)
    env = np.abs(hilbert(x))
    f_env, P_env = welch(env, fs=fs, nperseg=nperseg)

    # Enrichment of the slow-beat envelope peak
    enrichment_ratio = np.nan
    if not np.isnan(f_slow):
        win = 0.2   # +/- 20 %
        m = (f_env >= (1 - win) * f_slow) & (f_env <= (1 + win) *
            f_slow)
        if np.any(m):
            peak_env  = np.max(P_env[m])
            base_env  = np.median(P_env)
            enrichment_ratio = peak_env / (base_env + 1e-15)

    return {
        "t": t,
        "x": x,
        "fs": fs,
        "f": f,
        "Pxx": Pxx,
        "f_env": f_env,
        "P_env": P_env,
        "env_signal": env,
        "f_plus": f_plus,
        "f_minus": f_minus,
        "f_slow": f_slow,
        "enrichment_ratio": enrichment_ratio,
    }

# -------------------------------------
# Panel generation: save and display
# -------------------------------------

def save_and_show_panels(res, outdir):
    """
```

```
    Generate the four publication panels (A--D).
    """
    t     = res["t"]
    x     = res["x"]
    f     = res["f"]
    Pxx   = res["Pxx"]
    f_env = res["f_env"]
    P_env = res["P_env"]
    env   = res["env_signal"]

    f_plus  = res["f_plus"]
    f_minus = res["f_minus"]
    f_slow  = res["f_slow"]

    # Panel A: time series V(t)
    plt.figure(figsize=(6, 2))
    plt.plot(t, x, lw=0.7)
    plt.xlabel("time (s)")
    plt.ylabel("z-score (a.u.)")
    plt.title("ROI-averaged V(t)")
    plt.tight_layout()
    outA = os.path.join(outdir, "A1_timeseries.png")
    plt.savefig(outA, dpi=300)
    plt.show()

    # Panel B: PSD[V]
    plt.figure(figsize=(6, 2))
    plt.semilogy(f, Pxx, lw=0.7, label="PSD[V]")
    if not np.isnan(f_plus):
        plt.axvline(
            f_plus,
            ls="--",
            color="C1",
            label=f"f_plus ~ {f_plus:.2f} Hz"
        )
    if not np.isnan(f_minus):
        plt.axvline(
            f_minus,
            ls="--",
            color="C2",
            label=f"f_minus ~ {f_minus:.2f} Hz"
        )
    plt.xlim(0, 2.5)
    plt.xlabel("frequency (Hz)")
    plt.ylabel("power")
    plt.title("PSD of V(t)")
    plt.legend(fontsize=6)
    plt.tight_layout()
    outB = os.path.join(outdir, "A1_psd_signal.png")
    plt.savefig(outB, dpi=300)
    plt.show()
```

```python
        # Panel C: Hilbert envelope in time
        plt.figure(figsize=(6, 2))
        plt.plot(t, env, lw=0.7)
        plt.xlabel("time (s)")
        plt.ylabel("amplitude")
        plt.title("Hilbert envelope of V(t)")
        plt.tight_layout()
        outC = os.path.join(outdir, "A1_envelope_timeseries.png")
        plt.savefig(outC, dpi=300)
        plt.show()

        # Panel D: PSD[envelope] with f_slow
        plt.figure(figsize=(6, 2))
        plt.semilogy(f_env, P_env, lw=0.7, label="PSD[envelope]")
        if not np.isnan(f_slow):
            plt.axvline(
                f_slow,
                ls="--",
                color="red",
                label=f"f_slow ~ {f_slow:.2f} Hz"
            )
        plt.xlabel("frequency (Hz)")
        plt.ylabel("power")
        plt.title("Envelope PSD")
        plt.legend(fontsize=6)
        plt.tight_layout()
        outD = os.path.join(outdir, "A1_psd_envelope.png")
        plt.savefig(outD, dpi=300)
        plt.show()

        return outA, outB, outC, outD

# ----------------------
# Main execution
# ----------------------

t, x, fs, meta = extract_timeseries_from_video(
    VIDEO_PATH,
    roi=FIXED_ROI,
    fps_override=FPS_OVERRIDE,
    denoise_ma=SMOOTHING_WINDOW,
    normalize_drift=True,
    max_frames=MAX_FRAMES
)

print("fs_used (Hz):", meta["fs_used"])
print("frames analyzed:", meta["nframes"])
print("ROI [x0,y0,x1,y1]:", meta["roi"])
print("field of view (height x width):", meta["height"], "x", meta
    ["width"])
```

```
res = analyze_timeseries_level0(
    t, x, fs,
    fast_band=FAST_BAND,
    prominence_factor=PROMINENCE_FACTOR,
    peak_distance_bins=PEAK_DISTANCE_BINS
)

print("f_plus  (Hz):", res["f_plus"])
print("f_minus (Hz):", res["f_minus"])
print("f_slow  (Hz):", res["f_slow"])
print("enrichment_ratio (envelope peak / median background):",
      res["enrichment_ratio"])

panel_paths = save_and_show_panels(res, outdir=OUTDIR)
print("Saved panel PNGs:", panel_paths)
```

Listing S2. Level-1 dual-channel pipeline script (synthetic benchmark).

```
#!/usr/bin/env python3
# -*- coding: utf-8 -*-

"""
Synthetic preregistered "Level-1" benchmark figure.

This script:
1. Generates paired "voltage-like" (V) and "mechanical-like" (M)
   time series
   with two narrowband ~1 Hz carrier modes.
2. Computes their spectra, slow beat frequency f_slow, and
   electromechanical
   coherence at f_slow.
3. Builds the neutral stroboscopic map:
       Delta_theta_n = theta_{n+1} - theta_n  vs  theta_n
   Fits the even-harmonic map:
       Delta_theta = Omega - K2 * sin(2*theta)
   and compares Omega_hat to the predicted lock
       Omega_2over21 = pi*2/21.
4. Renders four separate panels and saves them under ./figs as:
       Level1_traces.png
       Level1_psd.png
       Level1_coherence.png
       Level1_neutral_map.png

All numbers are deterministic because we fix np.random.seed().
"""

import os
import numpy as np
np.random.seed(12345)   # make the synthetic dataset deterministic
```

```python
import matplotlib.pyplot as plt
from scipy.signal import welch, detrend, hilbert, csd
from numpy.linalg import lstsq

# -------------------------
# 1. Synthetic dual-channel generator
# -------------------------

def generate_synthetic_dual_channel():
    """
    Generate paired synthetic signals V(t) ("voltage-like") and M(
        t)
    ("mechanical-like") with two ~1 Hz carriers, plus noise and a
        shared
    slow beat.
    Returns time array t, detrended/z-scored V and M, and sampling
        rate fs.
    """
    fs = 100.0           # Hz sampling rate (preregistered spec:
        >=80-100 Hz)
    T  = 120.0           # total duration [s]
    t  = np.arange(0.0, T, 1.0/fs)

    # Two carrier frequencies in the ~1 Hz band
    f_plus_true  = 1.20  # Hz
    f_minus_true = 1.03  # Hz

    # A relative phase lag between channels
    phase_lag    = 0.40  # radians

    # "Voltage-like" raw signal
    V_clean = (
        np.sin(2*np.pi*f_plus_true  * t)
        + 0.8*np.sin(2*np.pi*f_minus_true * t)
    )
    V_noisy = V_clean + 0.05*np.random.standard_normal(len(t))

    # "Mechanical-like" raw signal with a shallow slow modulation
    M_clean = (
        0.9*np.sin(2*np.pi*f_plus_true  * t + phase_lag)
        + 0.7*np.sin(2*np.pi*f_minus_true * t + phase_lag)
    )
    slow_mod = 0.1*np.sin(2*np.pi*0.17*t + 1.0)  # ~0.17 Hz shared
        slow envelope
    M_noisy  = M_clean + slow_mod + 0.05*np.random.standard_normal
        (len(t))

    # Detrend + z-score each channel
    Vd = detrend(V_noisy, type="linear")
    Vd = (Vd - np.mean(Vd)) / (np.std(Vd) + 1e-12)
```

```python
    Md = detrend(M_noisy, type="linear")
    Md = (Md - np.mean(Md)) / (np.std(Md) + 1e-12)

    return t, Vd, Md, fs

# -----------------------
# 2. Spectral analysis helpers
# -----------------------

def welch_psd(x, fs, nperseg=None):
    """
    Compute Welch power spectral density (PSD).
    Returns frequency array f and PSD Pxx.
    """
    if nperseg is None:
        nperseg = min(len(x), 4096)
    f, Pxx = welch(x, fs=fs, nperseg=nperseg)
    return f, Pxx

def find_two_carriers(f, Pxx, fast_band,
                      prominence_factor=2.0,
                      min_distance_bins=3):
    """
    Identify up to two strong carrier peaks in a specified '
       fast_band'
    (e.g. 0.5-2 Hz). We do a simple local-maximum scan with a
       relative
    threshold, keep the top two peaks by amplitude, and define the
       slow beat
    f_slow = |f_plus - f_minus|.
    """
    mask = (f >= fast_band[0]) & (f <= fast_band[1])
    fband = f[mask]
    Pband = Pxx[mask]

    if len(fband) < 3:
        return np.nan, np.nan, np.nan

    thr = np.median(Pband) * prominence_factor
    peak_ids = []
    for i in range(1, len(fband)-1):
        if (Pband[i] > Pband[i-1] and
            Pband[i] > Pband[i+1] and
            Pband[i] > thr):
            if len(peak_ids) == 0 or (i - peak_ids[-1]) >=
                min_distance_bins:
                peak_ids.append(i)

    if len(peak_ids) == 0:
        return np.nan, np.nan, np.nan
```

```python
    # sort by peak height, descending
    peak_ids_sorted = sorted(peak_ids, key=lambda k: Pband[k],
        reverse=True)

    f_plus  = fband[peak_ids_sorted[0]] if len(peak_ids_sorted) >=
        1 else np.nan
    f_minus = fband[peak_ids_sorted[1]] if len(peak_ids_sorted) >=
        2 else np.nan

    f_slow = np.nan
    if (not np.isnan(f_plus)) and (not np.isnan(f_minus)):
        f_slow = abs(f_plus - f_minus)

    return f_plus, f_minus, f_slow

def coherence_spectrum(V, M, fs, nperseg=None):
    """
    Magnitude-squared coherence Lambda(f) between V and M:
        Lambda(f) = |S_VM|^2 / (S_V * S_M)
    Returns frequency array f and coherence array coh(f).
    """
    if nperseg is None:
        nperseg = min(len(V), 4096)

    f, Sv  = welch(V, fs=fs, nperseg=nperseg)
    _, Sm  = welch(M, fs=fs, nperseg=nperseg)
    _, Svm = csd(V, M, fs=fs, nperseg=nperseg)

    coh = (np.abs(Svm)**2) / (Sv * Sm + 1e-15)
    return f, coh

def get_coherence_at_frequency(f, coh, f_target, rel_window=0.15):
    """
    Extract the coherence magnitude near a target frequency
    f_target,
    i.e. within +/- (rel_window * f_target).
    """
    if np.isnan(f_target) or f_target <= 0 or f_target > np.max(f)
        :
        return np.nan

    lo = (1.0 - rel_window)*f_target
    hi = (1.0 + rel_window)*f_target

    mask = (f >= lo) & (f <= hi)
    if not np.any(mask):
        return np.nan

    return float(np.max(coh[mask]))
```

```python
# ------------------------
# 3. Phase, neutral strobing, even-harmonic fit
# ------------------------

def unwrap_phase(sig):
    """
    Hilbert-transform-based instantaneous phase, unwrapped.
    """
    analytic = hilbert(sig)
    return np.unwrap(np.angle(analytic))

def neutral_strobe(t, phi_V, phi_M):
    """
    "Neutral" events are times where the instantaneous phase
      difference
        psi(t) = phase(V) - phase(M)
    crosses 0 modulo pi with positive slope, i.e. V and M are
      mirror-symmetric.

    We detect those zero-crossings of psi(t) mod pi, then sample
      the phase
    of V at those instants.

    Returns:
        t_strobes      - times of neutral crossings
        theta_strobes  - phase(V) mod 2*pi at those crossings
    """
    psi        = phi_V - phi_M
    psi_unwrap = np.unwrap(psi)

    # Fold modulo pi into (-pi/2, +pi/2] to catch both +/- cross
    psi_fold = ((psi_unwrap + 0.5*np.pi) % np.pi) - 0.5*np.pi

    t_strobes     = []
    theta_strobes = []

    for i in range(len(t)-1):
        # crossing from negative to positive
        if (psi_fold[i] < 0.0) and (psi_fold[i+1] >= 0.0):
            frac = (-psi_fold[i]) / (psi_fold[i+1] - psi_fold[i] +
                1e-15)
            t_cross = t[i] + frac*(t[i+1] - t[i])

            # interpolate V-phase at crossing
            phiV_cross = phi_V[i] + frac*(phi_V[i+1] - phi_V[i])
            theta = np.mod(phiV_cross, 2.0*np.pi)

            t_strobes.append(t_cross)
            theta_strobes.append(theta)

    return np.array(t_strobes), np.array(theta_strobes)
```

```python
def fit_even_map(theta):
    """
    Build the neutral stroboscopic map:

        theta_n    = phase(V) at the nth neutral crossing
        Delta_theta_n = theta_{n+1} - theta_n

    Model:
        Delta_theta_n = Omega - K2 * sin(2 * theta_n)

    We fit [Omega, K2] by linear regression of
        Delta_theta_n  vs  [1, sin(2*theta_n)].

    Returns:
        Omega_hat, K2_hat,
        stderr_Omega, stderr_K2,
        (theta_n, dtheta, dtheta_fit)
    """
    if len(theta) < 3:
        return (np.nan, np.nan,
                np.nan, np.nan,
                (np.array([]), np.array([]), np.array([])))

    th0    = theta[:-1]
    th1    = theta[1:]
    dtheta = th1 - th0

    # wrap dtheta into (-pi, pi]
    dtheta = ((dtheta + np.pi) % (2.0*np.pi)) - np.pi

    # Regression design matrix for:
    #    dtheta = a + b * sin(2*theta)
    X = np.column_stack((np.ones_like(th0), np.sin(2.0*th0)))
    y = dtheta

    beta, _, _, _ = lstsq(X, y, rcond=None)
    a, b = beta[0], beta[1]    # a ~ Omega_hat, b ~ (-K2_hat)

    # Estimate standard errors assuming iid residuals
    if len(y) > 2:
        dof    = len(y) - 2
        sigma2 = np.sum((y - X @ beta)**2) / (dof if dof > 0 else
            1)
    else:
        sigma2 = np.sum((y - X @ beta)**2)

    XtX_inv   = np.linalg.inv(X.T @ X)
    cov_beta  = sigma2 * XtX_inv
    stderr_a  = np.sqrt(cov_beta[0,0])
    stderr_b  = np.sqrt(cov_beta[1,1])
```

```
    Omega_hat = a
    K2_hat    = -b                # minus sign by convention
    stderr_Om = stderr_a
    stderr_K2 = stderr_b

    dtheta_fit = X @ beta         # fitted Delta_theta_n

    return Omega_hat, K2_hat, stderr_Om, stderr_K2, (th0, dtheta,
        dtheta_fit)

# ------------------------
# 4. Run pipeline (synthetic Level-1 benchmark)
# ------------------------

# Generate synthetic simultaneous V(t), M(t)
t, Vsig, Msig, fs = generate_synthetic_dual_channel()

# Power spectra
fV, PV = welch_psd(Vsig, fs)
fM, PM = welch_psd(Msig, fs)

# Identify fast carrier peaks and beat frequency
FAST_BAND = (0.5, 2.0)  # Hz range where we expect the ~1 Hz
    carriers
f_plus, f_minus, f_slow = find_two_carriers(fV, PV, FAST_BAND)

# Coherence spectrum and its slow-band value
fCoh, Coh = coherence_spectrum(Vsig, Msig, fs)
Lambda_fslow = get_coherence_at_frequency(fCoh, Coh, f_slow,
    rel_window=0.15)

# Neutral stroboscopic map
phi_V = unwrap_phase(Vsig)
phi_M = unwrap_phase(Msig)
t_strobe, theta_strobe = neutral_strobe(t, phi_V, phi_M)

Omega_hat, K2_hat, se_Om, se_K2, mapdata = fit_even_map(
    theta_strobe)
th0, dtheta, dtheta_fit = mapdata

# Predicted lock 2/21:
Omega_lock_2_21 = np.pi * (2.0/21.0)
lock_dist       = np.abs(Omega_hat - Omega_lock_2_21)

# ------------------------
# 5. Panel-saving helpers (four separate PNGs)
# ------------------------

def save_level1_traces(t, V, M, out_png):
    """Panel␣A:␣time␣series␣of␣V(t)␣and␣M(t)."""
```

```python
    fig, ax = plt.subplots(figsize=(6, 2.3))
    ax.plot(t, V, lw=0.8, label="V(t)␣(voltage-like)")
    ax.plot(t, M, lw=0.8, label="M(t)␣(mechanical-like)")
    ax.set_title("Simultaneous␣electromechanical␣traces␣(synthetic
        )")
    ax.set_xlabel("time␣(s)")
    ax.set_ylabel("z-scored␣signal")
    ax.legend(fontsize=7, loc="upper␣right")
    fig.tight_layout()
    fig.savefig(out_png, dpi=300)
    plt.close(fig)

def save_level1_psd(f, Pvv, Pmm, f_plus, f_minus, out_png):
    """Panel␣B:␣power␣spectra␣of␣V␣and␣M␣with␣carrier␣peaks."""
    fig, ax = plt.subplots(figsize=(6, 2.3))
    ax.semilogy(f, Pvv, lw=0.8, label="PSD[V]")
    ax.semilogy(f, Pmm, lw=0.8, label="PSD[M]", alpha=0.8)
    if not np.isnan(f_plus):
        ax.axvline(f_plus, ls="--", color="tab:orange",
                   label=f"f_plus␣~␣{f_plus:.2f}␣Hz")
    if not np.isnan(f_minus):
        ax.axvline(f_minus, ls="--", color="tab:green",
                   label=f"f_minus␣~␣{f_minus:.2f}␣Hz")
    ax.set_title("Power␣spectra␣of␣V␣and␣M␣(synthetic␣dual-channel
        )")
    ax.set_xlabel("frequency␣(Hz)")
    ax.set_ylabel("power")
    ax.legend(fontsize=7, loc="upper␣right")
    fig.tight_layout()
    fig.savefig(out_png, dpi=300)
    plt.close(fig)

def save_level1_coherence(f_coh, coh, f_slow, Lambda_slow, out_png
    ):
    """Panel␣C:␣electromechanical␣coherence␣Lambda(f)␣with␣f_slow␣
        marker."""
    fig, ax = plt.subplots(figsize=(6, 2.3))
    ax.plot(f_coh, coh, lw=0.8)
    if not np.isnan(f_slow) and not np.isnan(Lambda_slow):
        ax.axvline(
            f_slow,
            ls="--",
            color="red",
            label=f"f_slow␣~␣{f_slow:.2f}␣Hz,␣Lambda␣~␣{
                Lambda_slow:.2f}"
        )
    ax.set_xlim(0, 50)
    ax.set_ylim(0, 1.05)
    ax.set_title("Electromechanical␣coherence␣(synthetic)")
    ax.set_xlabel("frequency␣(Hz)")
    ax.set_ylabel("Lambda(f)")
```

```python
    ax.legend(fontsize=7, loc="upper right")
    fig.tight_layout()
    fig.savefig(out_png, dpi=300)
    plt.close(fig)

def save_level1_neutral_map(theta_n, dtheta, dtheta_fit,
                            Omega_hat, K2_hat,
                            Omega_2over21, lock_dist,
                            out_png):
    """Panel D: neutral stroboscopic map and even-harmonic fit."""
    fig, ax = plt.subplots(figsize=(6, 2.3))
    ax.scatter(theta_n, dtheta, s=10, alpha=0.6,
               label="data", color="tab:blue")

    if len(theta_n) > 0:
        order = np.argsort(theta_n)
        ax.plot(theta_n[order], dtheta_fit[order],
                color="red", linewidth=1.3,
                label="fit: Delta_theta = Omega - K2*sin(2*theta)"
                )

    box_text = (
        "Omega_hat ~= %.3f rad, K2_hat ~= %.3f\n"
        "Omega_2over21 ~= %.3f rad\n"
        "|Omega_hat - Omega_2over21| ~= %.3f rad"
        % (Omega_hat, K2_hat, Omega_2over21, lock_dist)
    )
    ax.text(
        0.02, 0.98, box_text,
        transform=ax.transAxes,
        ha="left", va="top",
        fontsize=7,
        bbox=dict(boxstyle="round", fc="white", ec="0.8", alpha
            =0.9)
    )

    ax.set_title("Neutral stroboscopic map (synthetic)")
    ax.set_xlabel("theta_n (phase of V at neutral strobe)")
    ax.set_ylabel("theta_{n+1} - theta_n")
    ax.legend(fontsize=7, loc="lower left")
    fig.tight_layout()
    fig.savefig(out_png, dpi=300)
    plt.close(fig)

# ------------------------
# 6. Save panels and print summary
# ------------------------

outdir = "figs"
os.makedirs(outdir, exist_ok=True)
```

```
save_level1_traces(
    t, Vsig, Msig,
    os.path.join(outdir, "Level1_traces.png")
)
save_level1_psd(
    fV, PV, fM, f_plus, f_minus,
    os.path.join(outdir, "Level1_psd.png")
)
save_level1_coherence(
    fCoh, Coh, f_slow, Lambda_fslow,
    os.path.join(outdir, "Level1_coherence.png")
)
save_level1_neutral_map(
    th0, dtheta, dtheta_fit,
    Omega_hat, K2_hat,
    Omega_lock_2_21, lock_dist,
    os.path.join(outdir, "Level1_neutral_map.png")
)

# Console readout for reproducibility
print("fs = %.1f Hz" % fs)
print("f_plus  = %.3f Hz" % f_plus)
print("f_minus = %.3f Hz" % f_minus)
print("f_slow  = %.3f Hz" % f_slow)
print("Lambda(f_slow) = %.3f" % Lambda_fslow)
print("Omega_hat = %.3f +/- %.3f rad" % (Omega_hat, se_Om))
print("K2_hat     = %.3f +/- %.3f" % (K2_hat, se_K2))
print("Omega_2over21 = %.3f rad" % Omega_lock_2_21)
print("|Omega_hat - Omega_2over21| = %.3f rad" % lock_dist)
print("Saved Level-1 panels in", outdir)
```

Listing S3. `P3 sandbox` **computational prevalidation of P3 (weak resonant drive at f slow).**

```
# -*- coding: utf-8 -*-

"""
P3_sandbox.py - Computational preregistration test for P3.

Goal
----
Exercise a minimal, reproducible pipeline that demonstrates:
(i) weak, frequency-specific entrainment at the intrinsic slow
    cadence f_slow,
(ii) simultaneous increase in slow-band electromechanical
    coherence (Lambda)
     and decrease in neutral-map angular variance (Var_map) only
    on-band.

This script is deliberately argument-free (no argparse) so it runs
    cleanly
```

```
in␣Colab/Notebook␣contexts␣where␣a␣-f␣kernel␣flag␣is␣injected.

Outputs␣saved␣under␣./outputs_P3_sandbox:
␣␣-␣summary.txt␣␣␣␣␣␣␣␣␣␣␣␣(numeric␣readout)
␣␣-␣sweep.png␣␣␣␣␣␣␣␣␣␣␣␣␣␣(resonance␣curves␣for␣Var_map␣and␣Lambda
    )
␣␣-␣sweep.csv␣␣␣␣␣␣␣␣␣␣␣␣␣␣(tabulated␣results)
"""

import os, json
import numpy as np
import matplotlib.pyplot as plt
from scipy.signal import hilbert, welch, csd

# -------------------------
# 1) Unlocking-like baseline
# -------------------------
def generate_unlocking_state(
    fs=200, dur=40,
    f_plus_V=1.8, f_minus_V=1.0,
    f_plus_S=2.5, f_minus_S=0.7,
    noise_V=1.0, noise_S=1.5,
    rw_sigma_S=0.5,
    coupling_c=0.05,
):
    n = int(dur * fs)
    t = np.arange(n) / fs

    phi_plus_V  = 2 * np.pi * f_plus_V  * t
    phi_minus_V = 2 * np.pi * f_minus_V * t
    V = np.sin(phi_plus_V) + 0.7 * np.sin(phi_minus_V)
    V += noise_V * np.random.randn(n)

    drift = np.cumsum(rw_sigma_S * np.random.randn(n)) / fs
    S_intrinsic = (
        0.5 * np.sin(2 * np.pi * f_plus_S  * t + 0.5 + drift)
      + 0.4 * np.sin(2 * np.pi * f_minus_S * t + 1.0 + 0.3 * drift
        )
    )

    S = S_intrinsic + noise_S * np.random.randn(n)

    S = S + coupling_c * V

    V = (V - np.mean(V)) / (np.std(V) + 1e-12)
    S = (S - np.mean(S)) / (np.std(S) + 1e-12)

    f_slow = abs(f_plus_V - f_minus_V)
    return t, V, S, f_slow, fs

# -------------------------------------
```

```
# 2) Metrics at the slow-band f_slow
# -----------------------------------
def slow_band_coherence(V, S, fs, f_target):
    nper = min(4096, len(V))
    f, Pxx = welch(V, fs=fs, nperseg=nper)
    _, Pyy = welch(S, fs=fs, nperseg=nper)
    _, Cxy = csd(V, S, fs=fs, nperseg=nper)
    coh = (np.abs(Cxy) ** 2) / ((Pxx * Pyy) + 1e-12)
    idx = np.argmin(np.abs(f - f_target))
    return float(coh[idx])

def var_map_from_signals(V, S, fs):
    phi_V = np.unwrap(np.angle(hilbert(V)))
    phi_S = np.unwrap(np.angle(hilbert(S)))
    psi   = phi_V - phi_S
    dpsi_dt = np.gradient(np.unwrap(psi)) * fs

    # neutral crossings: psi near k*pi (sin psi ~ 0), with
        positive slope
    neutral_mask = (np.abs(np.sin(psi)) < 0.2) & (dpsi_dt > 0)
    idxs = np.where(neutral_mask)[0]
    if len(idxs) < 5:
        return float("nan")

    # enforce >=0.2 s spacing between samples
    keep = [idxs[0]]
    for j in idxs[1:]:
        if j - keep[-1] > fs * 0.2:
            keep.append(j)
    keep = np.array(keep, dtype=int)
    if len(keep) < 5:
        return float("nan")

    theta  = phi_V[keep]
    dtheta = np.diff(theta)
    return float(np.var(dtheta))

def measure_block(V, S, fs, f_slow):
    return slow_band_coherence(V, S, fs, f_slow), \
        var_map_from_signals(V, S, fs)

# -------------------------------------------
# 3) Weak drive + narrow resonance "gate"
# -------------------------------------------
def apply_drive(t, V, S, f_drive, f_slow, amp_drive=0.03,
    lock_width_frac=0.01):
    Vd = V + amp_drive * np.sin(2 * np.pi * f_drive * t)
    Sd = S.copy()
    df  = abs(f_drive - f_slow)
    tol = lock_width_frac * f_slow
    gate = np.exp(-(df ** 2) / (2 * tol ** 2))
```

```python
        Sd = (1 - gate * 0.5) * Sd + (gate * 0.5) * Vd

        Sd = (Sd - np.mean(Sd)) / (np.std(Sd) + 1e-12)
        Vd = (Vd - np.mean(Vd)) / (np.std(Vd) + 1e-12)
        return Vd, Sd, float(gate)

# ------------------------
# 4) P3 on/off-band protocol
# ------------------------
def run_protocol():
    t, V0, S0, f_slow, fs = generate_unlocking_state()
    Lam0, Var0 = measure_block(V0, S0, fs, f_slow)

    V_on, S_on, gate_on = apply_drive(t, V0, S0, f_slow, f_slow)
    Lam_on, Var_on = measure_block(V_on, S_on, fs, f_slow)

    V_p, S_p, gate_p = apply_drive(t, V0, S0, f_slow*1.10, f_slow)
    Lam_p, Var_p = measure_block(V_p, S_p, fs, f_slow)

    V_m, S_m, gate_m = apply_drive(t, V0, S0, f_slow*0.90, f_slow)
    Lam_m, Var_m = measure_block(V_m, S_m, fs, f_slow)

    return dict(
        f_slow=float(f_slow), fs=float(fs),
        baseline=dict(Lambda=float(Lam0), Var_map=float(Var0)),
        on=dict(Lambda=float(Lam_on), Var_map=float(Var_on), gate=
            float(gate_on)),
        off_plus=dict(Lambda=float(Lam_p), Var_map=float(Var_p),
            gate=float(gate_p)),
        off_minus=dict(Lambda=float(Lam_m), Var_map=float(Var_m),
            gate=float(gate_m)),
    )

# --------------------------------------------------
# 5) Frequency sweep for resonance diagnostics
# --------------------------------------------------
def frequency_sweep(t, V0, S0, f_slow, fs, fmin_factor=0.7,
    fmax_factor=1.3, n_pts=25):
    freqs = np.linspace(f_slow * fmin_factor, f_slow * fmax_factor
        , n_pts)
    Lam_list, Var_list, gate_list = [], [], []
    for fd in freqs:
        Vd, Sd, gate = apply_drive(t, V0, S0, fd, f_slow)
        Lam, Var = measure_block(Vd, Sd, fs, f_slow)
        Lam_list.append(Lam); Var_list.append(Var); gate_list.
            append(gate)
    return freqs, np.array(Lam_list), np.array(Var_list), np.array
        (gate_list)

def plot_and_save(freqs, Lam_arr, Var_arr, gate_arr, f_slow,
    out_png):
```

```python
    fig, ax = plt.subplots(2, 1, figsize=(6, 6), sharex=True)
    ax[0].plot(freqs, Var_arr, "o-", lw=1)
    ax[0].axvline(f_slow, ls="--", color="k", label="f_slow")
    ax[0].set_ylabel("Var_map (lower = more stable)")
    ax[0].legend()
    ax[0].set_title("Frequency sweep: angular stability")

    ax[1].plot(freqs, Lam_arr, "o-", lw=1)
    ax[1].axvline(f_slow, ls="--", color="k", label="f_slow")
    ax[1].set_xlabel("drive frequency (Hz)")
    ax[1].set_ylabel("Lambda (higher = more coherence)")
    ax[1].legend()
    ax[1].set_title("Frequency sweep: slow-band coherence")

    ax_gate = ax[1].twinx()
    ax_gate.plot(freqs, gate_arr, "r--", alpha=0.35)
    ax_gate.set_ylabel("gate (0-1)")

    fig.tight_layout()
    fig.savefig(out_png, dpi=200)
    plt.close(fig)

# -------------------
# 6) Script entrypoint
# -------------------
if __name__ == "__main__":
    np.random.seed(0)
    outdir = "outputs_P3_sandbox"
    os.makedirs(outdir, exist_ok=True)

    # Main protocol
    t, V0, S0, f_slow, fs = generate_unlocking_state()
    res = run_protocol()

    # Save summary
    with open(os.path.join(outdir, "summary.txt"), "w") as f:
        f.write(json.dumps(res, indent=2))

    # Sweep & figure
    freqs, Lam_arr, Var_arr, gate_arr = frequency_sweep(t, V0, S0,
        f_slow, fs)
    np.savetxt(os.path.join(outdir, "sweep.csv"),
               np.c_[freqs, Lam_arr, Var_arr, gate_arr],
               delimiter=",", header="freq,Lambda,Var_map,gate",
                   comments="")
    plot_and_save(freqs, Lam_arr, Var_arr, gate_arr, f_slow,
                  os.path.join(outdir, "sweep.png"))

    # Console readout
    print("f_slow ~ %.3f Hz" % f_slow)
    for k in ["baseline","on","off_plus","off_minus"]:
```

```
            print(k, res[k])
```

Listing S4. `Popper falsifiability`: video/CSV pipeline for neutral stroboscopy, even/odd harmonics, and bicoherence (Figs. H1–H4).

```
#!/usr/bin/env python3
# -*- coding: utf-8 -*-
"""
Listing␣S4.␣Popper_falsifiability:␣video/CSV␣pipeline␣for␣H1-H4␣
   diagnostics
(neutral␣stroboscopy,␣even/odd␣harmonics,␣and␣bicoherence).

Usage␣(CLI␣examples):
␣␣python␣s4_popper_falsifiability.py␣--video␣input.mov␣--fs␣25␣--
   roi␣100:80:320:240
␣␣python␣s4_popper_falsifiability.py␣--csv␣input.csv␣--fs␣25
␣␣#␣Optional:
␣␣#␣␣␣--downsample␣1␣--outdir␣figs␣--fmin␣0.05␣--fmax␣0.40␣--
   surrogates␣200␣--bico-nseg␣32
␣␣#␣␣␣--colab-picker␣␣␣#␣forces␣a␣picker␣in␣Colab␣(now␣it␣also␣
   opens␣automatically)
"""

import os, json, argparse, warnings
import numpy as np
import matplotlib.pyplot as plt
from scipy.signal import butter, filtfilt, hilbert, welch

SEED = 1234
np.random.seed(SEED)

# -----------------------
# Small utils
# -----------------------
def ensure_dir(path):
    os.makedirs(path, exist_ok=True)

def parse_roi(s):
    try:
        x0, y0, x1, y1 = [int(v) for v in s.split(":")]
        return (x0, y0, x1, y1)
    except Exception:
        raise ValueError("ROI␣must␣be␣'x0:y0:x1:y1'")

def in_colab():
    try:
        import google.colab  # type: ignore
        return True
    except Exception:
        return False
```

```python
# -----------------------
# DSP helpers
# -----------------------
def bandpass(x, fs, fmin, fmax, order=3):
    b, a = butter(order, [fmin/(fs/2), fmax/(fs/2)], btype='band')
    return filtfilt(b, a, x)

def norm_std(x):
    x = np.asarray(x, float)
    return (x - np.mean(x)) / (np.std(x) + 1e-12)

def psd_peak_freq(x, fs, fmin=0.5, fmax=4.0):
    nper = min(4096, len(x))
    f, Pxx = welch(x, fs=fs, nperseg=nper)
    band = (f >= fmin) & (f <= fmax)
    if not np.any(band):
        return float("nan"), f, Pxx
    k = np.argmax(Pxx[band])
    f0 = float(f[band][k])
    return f0, f, Pxx

def integrate_band(f, P, f_center, bw):
    m = (f >= max(0.0, f_center - bw)) & (f <= f_center + bw)
    if not np.any(m):
        return 0.0
    return float(np.trapz(P[m], f[m]))

# -----------------------
# IO: CSV / Video / Colab picker
# -----------------------
def load_csv(path):
    import csv
    vals = []
    with open(path, "r", newline="") as fh:
        reader = csv.reader(fh)
        for row in reader:
            if not row:
                continue
            try:
                vals.append(float(row[0]))
            except Exception:
                continue
    return np.asarray(vals, float)

def load_video_series(path, roi=None, downsample=1):
    fs = None
    frames = []
    try:
        import cv2
        cap = cv2.VideoCapture(path)
```

```python
        if not cap.isOpened():
            raise RuntimeError("OpenCV could not open video.")
        fs = cap.get(cv2.CAP_PROP_FPS)
        while True:
            ok, frame = cap.read()
            if not ok:
                break
            if roi is not None:
                x0,y0,x1,y1 = roi
                frame = frame[y0:y1, x0:x1]
            gray = frame if frame.ndim == 2 else cv2.cvtColor(
                frame, cv2.COLOR_BGR2GRAY)
            frames.append(gray.mean())
        cap.release()
    except Exception:
        try:
            import imageio.v2 as imageio
            reader = imageio.get_reader(path)
            meta = reader.get_meta_data()
            fs = meta.get("fps", fs)
            for frame in reader:
                if roi is not None:
                    x0,y0,x1,y1 = roi
                    frame = frame[y0:y1, x0:x1]
                gray = frame if frame.ndim == 2 else np.mean(frame
                    , axis=2)
                frames.append(gray.mean())
            reader.close()
        except Exception as e:
            raise RuntimeError("Could not read video. Need OpenCV 
                or imageio. Error: {}".format(e))
    frames = np.asarray(frames, float)
    if downsample > 1:
        frames = frames[::downsample]
        if fs is not None:
            fs = fs / downsample
    return frames, fs

def try_colab_upload(ask=True):
    if not ask:
        return None, None
    try:
        from google.colab import files  # type: ignore
        print("[info] Opening a file picker (Colab). Upload a 
            video (.mov/.mp4/...) or a CSV.")
        up = files.upload()
        if not up:
            print("[warn] Selection cancelled.")
            return None, None
        name = list(up.keys())[0]
        low = name.lower()
```

```
            if low.endswith((".mov",".mp4",".m4v",".avi",".mkv",".mpg"
                ,".mpeg")):
                return ("video", name)
            if low.endswith(".csv"):
                return ("csv", name)
            print("[warn] Unsupported file type; using demo instead.")
            return None, None
        except Exception:
            return None, None

    # -----------------------
    # H1-H4 feature helpers
    # -----------------------
    def neutral_pairs(V_slow, fs, zero_tol=0.35, slope_tol=0.0,
        min_sep_s=2.0):
        z = hilbert(V_slow)
        quad = np.imag(z)
        dquad = np.gradient(quad) * fs
        thr = zero_tol * (np.std(quad) + 1e-12)
        cand = (np.abs(quad) < thr) & (dquad > slope_tol)
        idx = np.flatnonzero(cand)
        if idx.size == 0:
            return [], []
        keep = []
        last = -10**9
        min_sep = int(min_sep_s * fs)
        for i in idx:
            if i - last >= min_sep:
                keep.append(i); last = i
        keep = np.asarray(keep, int)
        pairs = [(int(keep[i]), int(keep[i+1])) for i in range(len(
            keep)-1)]
        amp = np.abs(z)
        A = [(float(amp[i]), float(amp[j])) for (i,j) in pairs]
        return pairs, A

    def bicoherence_proxy(x, fs, f0, nseg=16):
        N = len(x)
        m = N // nseg
        if m < 64:
            return float("nan")
        x = x[:m*nseg]
        def fbin(fr):
            return int(round(fr * m / fs))
        k0 = fbin(f0)
        k2 = fbin(2*f0)
        num = 0+0j; den1 = 0.0; den2 = 0.0
        win = np.hanning(m)
        for s in range(nseg):
            seg = x[s*m:(s+1)*m]
            Z = np.fft.rfft(seg * win)
```

```
            if k2 < len(Z) and k0 < len(Z):
                num += Z[k0] * Z[k0] * np.conj(Z[k2])
                den1 += np.abs(Z[k0]**2)
                den2 += np.abs(Z[k2])
        if den1 <= 0 or den2 <= 0:
            return float("nan")
        return float(np.abs(num) / np.sqrt(den1 * den2 + 1e-18))

def bico_surrogates(x, fs, f0, nseg=16, nsurr=200):
    # Build surrogates preserving global magnitude spectrum of a
        block length L=m*nseg
    N = len(x)
    m = N // nseg
    L = m * nseg
    if m < 64 or L < 128:
        return np.array([])
    x_use = x[:L]
    Z = np.fft.rfft(x_use)
    mag = np.abs(Z)
    rng = np.random.default_rng(SEED)
    vals = []
    for _ in range(nsurr):
        phase = rng.uniform(0, 2*np.pi, size=Z.shape)
        phase[0] = 0.0
        if (L % 2) == 0:
            phase[-1] = 0.0
        Zs = mag * np.exp(1j * phase)
        xs = np.fft.irfft(Zs, n=L).real
        vals.append(bicoherence_proxy(xs, fs, f0, nseg=nseg))
    return np.asarray(vals, float)

# -----------------------
# Main
# -----------------------
def main():
    ap = argparse.ArgumentParser()
    ap.add_argument("--video", type=str, default=None)
    ap.add_argument("--csv",   type=str, default=None)
    ap.add_argument("--fs",    type=float, default=None, help="
        sampling rate (needed for CSV or videos without FPS)")
    ap.add_argument("--roi",   type=str, default=None, help="x0:y0
        :x1:y1 for video")
    ap.add_argument("--downsample", type=int, default=1)
    ap.add_argument("--outdir", type=str, default="figs")
    ap.add_argument("--fmin",  type=float, default=0.05)
    ap.add_argument("--fmax",  type=float, default=0.40)
    ap.add_argument("--surrogates", type=int, default=200)
    ap.add_argument("--bico-nseg", type=int, default=32)
    ap.add_argument("--colab-picker", action="store_true", help="
        force a picker in Colab")
    args, _ = ap.parse_known_args()
```

```python
ensure_dir(args.outdir)

# Decide input source
mode = "demo"
source = None
fs_used = None

if args.video:
    source = args.video
    roi = parse_roi(args.roi) if args.roi else None
    V_raw, fs_video = load_video_series(args.video, roi=roi,
        downsample=args.downsample)
    fs_used = fs_video if fs_video is not None else args.fs
    if fs_used is None:
        raise SystemExit("For video without fps metadata,
            please provide --fs.")
    mode = "video"

elif args.csv:
    source = args.csv
    V_raw = load_csv(args.csv)
    fs_used = args.fs
    if fs_used is None:
        raise SystemExit("CSV requires --fs to be provided.")
    mode = "csv"

else:
    # Auto-open picker if running in Colab or if flag was set
    use_picker = args.colab_picker or in_colab()
    picked = try_colab_upload(use_picker)
    if picked and picked[0] == "video":
        args.video = picked[1]
        source = args.video
        roi = parse_roi(args.roi) if args.roi else None
        V_raw, fs_video = load_video_series(args.video, roi=
            roi, downsample=args.downsample)
        fs_used = fs_video if fs_video is not None else args.
            fs
        if fs_used is None:
            raise SystemExit("For video without fps metadata,
                please provide --fs.")
        mode = "video"
    elif picked and picked[0] == "csv":
        args.csv = picked[1]
        source = args.csv
        V_raw = load_csv(args.csv)
        fs_used = args.fs
        if fs_used is None:
            raise SystemExit("CSV requires --fs to be provided
                .")
```

```
            mode = "csv"
        else:
            print("[warn]␣No␣video/CSV␣provided;␣falling␣back␣to␣
                synthetic␣demo.")
            fs_used = 25.0
            T = 100.0
            t = np.arange(int(T*fs_used))/fs_used
            V_raw = (np.sin(2*np.pi*1.4*t + 0.6)
                     + 0.35*np.sin(2*np.pi*2.6*t + 1.7)
                     + 0.15*np.sin(2*np.pi*0.18*t + 0.3)
                     + 0.20*np.random.randn(len(t)))
            mode = "demo"
            source = "synthetic"

    # Normalize
    V_raw = norm_std(np.asarray(V_raw, float))

    # Slow band (H1 + neutral stroboscopy)
    V_slow = bandpass(V_raw, fs_used, args.fmin, args.fmax, order
        =3)
    t = np.arange(len(V_slow))/fs_used
    z = hilbert(V_slow)
    quad = np.imag(z)

    # H1
    plt.figure(figsize=(12,4))
    plt.plot(t, V_slow, label="V␣bandpassed")
    plt.plot(t, quad, label="quadrature␣proxy")
    plt.xlabel("Time␣(s)")
    plt.ylabel("a.u.")
    plt.title("Slow-band␣(0.05-0.40␣Hz)")
    plt.legend()
    h1_path = os.path.join(args.outdir, "input_slowband.png")
    plt.tight_layout(); plt.savefig(h1_path, dpi=160); plt.close()

    # H2
    pairs, A = neutral_pairs(V_slow, fs_used, zero_tol=0.35,
        slope_tol=0.0, min_sep_s=2.0)
    A = np.asarray(A, float)
    plt.figure(figsize=(6,6))
    if len(A) > 0:
        plt.scatter(A[:,0], A[:,1], s=30)
    plt.xlabel("|Z|_n"); plt.ylabel("|Z|_{n+1}")
    plt.title("Neutral-moment␣stroboscopy␣(proxy)")
    h2_path = os.path.join(args.outdir, "input_poincare_neutral.
        png")
    plt.tight_layout(); plt.savefig(h2_path, dpi=160); plt.close()

    # H3
    f0, f_psd, P_psd = psd_peak_freq(V_raw, fs_used, fmin=0.5,
        fmax=4.0)
```

```python
nper = min(4096, len(V_raw))
f_psd, Pxx = welch(V_raw, fs=fs_used, nperseg=nper)
bw = 0.10 * max(f0, 1e-3)
def band_power(fr): return integrate_band(f_psd, Pxx, fr, bw)
P2, P3 = band_power(2.0*f0), band_power(3.0*f0)
ratio = (P2 / (P3 + 1e-18))
plt.figure(figsize=(9,6))
plt.bar(["P(2 f0)", "P(3 f0)"], [P2, P3])
plt.ylabel("Power"); plt.title("Even vs odd harmonics around
   f0")
h3_path = os.path.join(args.outdir, "input_harmonics_2f0_3f0.
   png")
plt.tight_layout(); plt.savefig(h3_path, dpi=160); plt.close()

# H4
b2 = bicoherence_proxy(V_raw, fs_used, f0, nseg=args.bico_nseg
   )
sur = bico_surrogates(V_raw, fs_used, f0, nseg=args.bico_nseg,
    nsurr=args.surrogates)
pval = float((np.sum(sur >= b2) + 1) / (len(sur) + 1)) if (sur
   .size > 0 and np.isfinite(b2)) else float("nan")
plt.figure(figsize=(10,6))
if sur.size > 0:
    plt.hist(sur, bins=24, density=True, alpha=0.8, label="
       surrogates")
if np.isfinite(b2):
    plt.axvline(b2, ls="--", label="data")
plt.xlabel("bicoherence proxy"); plt.ylabel("pdf")
plt.title("Bicoherence (f0,f0 -> 2 f0) with surrogates")
plt.legend()
h4_path = os.path.join(args.outdir, "
   input_bicoherence_surrogates.png")
plt.tight_layout(); plt.savefig(h4_path, dpi=160); plt.close()

# Summary JSON
summary = {
    "seed": SEED,
    "mode": mode,
    "source": source,
    "fs": float(fs_used),
    "slow_band": [args.fmin, args.fmax],
    "n_samples": int(len(V_raw)),
    "n_neutral_pairs": int(len(A)),
    "neutral_params": {"zero_tol_std": 0.35, "slope_tol": 0.0,
        "min_sep_s": 2.0},
    "f0_peak_hz": float(f0),
    "P2_over_P3": float(ratio),
    "bicoherence_proxy": float(b2) if np.isfinite(b2) else
       None,
    "p_value": float(pval) if np.isfinite(pval) else None,
    "figures": {"H1": h1_path, "H2": h2_path, "H3": h3_path, "
```

```
                    H4": h4_path}
    }
    with open(os.path.join(args.outdir, "summary.json"), "w") as
        fjs:
        json.dump(summary, fjs, indent=2)

    print(
        "[done]␣Wrote␣figures␣to␣'{}'.".format(args.outdir)
        + "␣Neutral␣pairs:␣{}␣|␣f0={:.3f}␣Hz␣|␣P(2f0)/P(3f0)={:.3f
            }␣|␣".format(len(A), f0, ratio)
        + "bico_proxy={:.3f}␣(p={:.2f})".format(
            b2 if np.isfinite(b2) else float("nan"),
            pval if np.isfinite(pval) else float("nan"))
    )

if __name__ == "__main__":
    with warnings.catch_warnings():
        warnings.simplefilter("ignore")
        main()
```

Listing S5. `Capture_kinetics`: **Adler-flow simulation for slow-phase capture, coherence build-up, and scaling-law prevalidation (Fig. F.1).**

The Python script below reproduces Fig. F.1. It simulates an Adler-like flow for the slow phase, computes a coherence proxy $\Lambda(t)$ with sliding-window smoothing, enforces a preregistered entry criterion (signal $< 15\%$ of the plateau for $\geq 5\,\mathrm{s}$), fits a single-pole approach to estimate the time constant τ, and reports $T_{\mathrm{lock}} = -\ln(1 - 0.8)\,\tau$. The grid is expanded across $(f_{\mathrm{slow}}, \kappa, \delta)$ with n replicates per cell; medians (and IQRs) are used per cell, and deterministic per-cell seeds based on $(f, \kappa, \delta, \mathrm{rep})$ ensure exact reproducibility. In our *in silico* validation, the lock time scaled with the predicted abscissa as $T_{\mathrm{lock}} \propto \left[f_{\mathrm{slow}}\sqrt{\kappa^2 - \delta^2}\right]^s$. Across the expanded grid, ordinary least squares on the log–log data yielded $s = 1.17$ with $R^2 = 0.59$, while a weighted fit that accounts for heteroscedasticity using weights $\propto 1/\mathrm{IQR}^2$ gave $s = 0.71$ with $R^2 = 0.56$. Nonparametric bootstrap 95% confidence intervals were $[1.05, 1.32]$ for OLS and $[0.25, 1.06]$ for the weighted fit (see Supplementary File `capture_scaling_slope.txt`).

```
# Minimal in-silico prevalidation for capture kinetics
# Expanded grid + replicates + weighted regression + bootstrap CIs
# Saves PNG/CSV/TXT to a folder and also displays figures.

import os, csv, math, numpy as np
import matplotlib as mpl; mpl.rcdefaults()
import matplotlib.pyplot as plt
from numpy.linalg import lstsq
import hashlib

# ------- deterministic seeding (reproducible per grid cell) ----
MASTER_SEED = 12345
def deterministic_seed(f, k, r, rep, master=MASTER_SEED):
    msg = f"{f:.9f}|{k:.9f}|{r:.9f}|{rep}|{master}".encode()
```

```python
        h = hashlib.blake2b(msg, digest_size=8).digest()
        return int(np.frombuffer(h, dtype=np.uint64)[0] & np.uint64(0
            xFFFFFFFF))

# ------- SDE (Adler-like phase model) --------
def simulate_adler(fslow, kappa, delta, D=2e-4, dt=1/200, T=360,
    seed=None):
    """
    Simulate an Adler-like SDE for a phase variable:
        dphi = 2*pi*fslow*(delta - kappa*sin(phi))*dt + sqrt(2*D)*
    dW
    Returns the phase trajectory and the time step used.
    """
    rng = np.random.default_rng(seed)
    n = int(T/dt)
    phi = 2*np.pi*rng.random()
    phi_traj = np.empty(n, dtype=np.float64)
    drift = 2*np.pi*fslow
    sdt = math.sqrt(dt); rt2D = math.sqrt(2*D)
    for i in range(n):
        dphi = drift*(delta - kappa*np.sin(phi))*dt + rt2D*sdt*rng
            .normal()
        phi = (phi + dphi + np.pi)%(2*np.pi) - np.pi
        phi_traj[i] = phi
    return phi_traj, dt

# ---------- coherence proxy Lambda(t) ----------
def lambda_trace(phi, fs, W=10.0):
    """
    Proxy for coherence rise: smooth cos(phi) with a W-second
    uniform
    window to emulate a single-pole approach to a plateau.
    """
    import scipy.ndimage as nd
    x = np.cos(phi)
    L = max(1, int(W*fs))
    return nd.uniform_filter1d(x, size=L, mode="nearest")

# ---------- T_lock via exponential fit ----------
def tlock_from_exp(trace, fs, frac=0.8, entry_frac=0.15,
    entry_min_sec=5.0, fit_window_sec=20.0):
    """
    Enforce entry criterion (trace must remain below entry_frac*
    plateau for >= entry_min_sec),
    then fit a single-pole approach y(t) = P - A*exp(-t/tau) using
    :
        ln(P - y) = ln(A) - t/tau
    Return T_lock = -ln(1-frac)*tau, or np.nan if conditions are
    not met.
    """
    P = np.nanmedian(trace[-int(20*fs):])  # robust plateau proxy
```

```python
        if not np.isfinite(P) or P == 0:
            return np.nan
        target_entry = entry_frac * P
        below = trace < target_entry
        run, t0_idx = 0, None
        for i, ok in enumerate(below):
            run = run + 1 if ok else 0
            if run >= int(entry_min_sec*fs):
                t0_idx = i
                break
        if t0_idx is None:
            return np.nan
        Tw = max(int(fit_window_sec*fs), 1)
        t = np.arange(t0_idx, min(len(trace), t0_idx+Tw)) / fs
        y = trace[t0_idx: min(len(trace), t0_idx+Tw)]
        Z = P - y
        mask = np.isfinite(Z) & (Z > 0)
        if mask.sum() < 30:
            return np.nan
        X = np.vstack([np.ones(mask.sum()), t[mask]]).T
        b, *_ = lstsq(X, np.log(Z[mask]), rcond=None)   # ln(Z) = b0 +
            b1 t
        b1 = b[1]
        tau = -1.0/b1 if b1 < 0 else np.nan
        if not np.isfinite(tau) or tau <= 0:
            return np.nan
        return float(-np.log(1.0 - frac) * tau)

# ---------- log-log fits ----------
def loglog_fit_ols(xs, ys):
    """Ordinary least-squares slope, intercept, R^2 for y ~ x^s (
        log-log)."""
    lx, ly = np.log(xs), np.log(ys)
    A = np.vstack([np.ones_like(lx), lx]).T
    beta, *_ = lstsq(A, ly, rcond=None)
    intercept, slope = float(beta[0]), float(beta[1])
    yhat = A @ beta
    ss_res = float(np.sum((ly - yhat)**2))
    ss_tot = float(np.sum((ly - ly.mean())**2))
    r2 = 1.0 - ss_res/ss_tot if ss_tot > 0 else np.nan
    return slope, intercept, r2

def loglog_fit_wls(xs, ys, w):
    """Weighted least-squares on log-log with nonnegative weights
        w."""
    lx, ly = np.log(xs), np.log(ys)
    w = np.asarray(w, float)
    W = np.diag(w)
    A = np.vstack([np.ones_like(lx), lx]).T
    Aw = W @ A
    yw = W @ ly
```

```python
        beta, *_ = lstsq(Aw, yw, rcond=None)
        intercept, slope = float(beta[0]), float(beta[1])
        yhat = A @ beta
        ly_bar = np.sum(w*ly)/np.sum(w)
        ss_res = float(np.sum(w*(ly - yhat)**2))
        ss_tot = float(np.sum(w*(ly - ly_bar)**2))
        r2 = 1.0 - ss_res/ss_tot if ss_tot > 0 else np.nan
        return slope, intercept, r2

def bootstrap_ci(xs, ys, fit_fn, w=None, n_boot=1000, seed=2025):
    """Nonparametric␣bootstrap␣95%␣CI␣for␣slope␣with␣fit_fn␣=␣OLS␣
        or␣WLS."""
    rng = np.random.default_rng(seed)
    n = len(xs)
    idx = np.arange(n)
    boots = []
    for _ in range(n_boot):
        sel = rng.choice(idx, size=n, replace=True)
        try:
            if w is None:
                s, _, _ = fit_fn(xs[sel], ys[sel])
            else:
                s, _, _ = fit_fn(xs[sel], ys[sel], w[sel])
            if np.isfinite(s):
                boots.append(s)
        except Exception:
            pass
    if len(boots) == 0:
        return np.nan, (np.nan, np.nan), np.array([])
    boots = np.array(boots, float)
    lo, hi = np.percentile(boots, [2.5, 97.5])
    return float(np.median(boots)), (float(lo), float(hi)), boots

# ---------- parameter grid ----------
SAVE_DIR = "./capture_kinetics_outputs"
os.makedirs(SAVE_DIR, exist_ok=True)

fslows = np.round(np.geomspace(0.07, 0.35, 6), 5).tolist()
kappas = np.round(np.geomspace(0.04, 0.2, 6), 5).tolist()
ratios = [0.20, 0.35, 0.50, 0.65, 0.75]    # avoid extreme edge
    near 1.0
REPLICATES = 16
NOISE_D    = 2e-4
T_OBS      = 360.0

records = []  # (f, k, r, delta, T_med, T_iqr, abscissa)

# ---------- run grid with deterministic seeds ----------
for f in fslows:
    for k in kappas:
        for r in ratios:
```

```
                delta = r*k
                tlocks = []
                for rep in range(REPLICATES):

                    seed = deterministic_seed(f, k, r, rep)  #
                        deterministic per-cell seed
                    phi, dt = simulate_adler(f, k, delta, D=NOISE_D,
                        dt=1/200, T=T_OBS, seed=seed)
                    fs = int(1/dt)
                    lam = lambda_trace(phi, fs=fs, W=10.0)
                    tlocks.append(
                        tlock_from_exp(lam, fs=fs, frac=0.8,
                            entry_frac=0.15, entry_min_sec=5.0,
                            fit_window_sec=20.0)
                    )
                tlocks = np.array(tlocks, float)
                T_med = float(np.nanmedian(tlocks))
                T_iqr = float(np.nanpercentile(tlocks, 75) - np.
                    nanpercentile(tlocks, 25))
                x = 1.0/(f*np.sqrt(max(k*k - (r*k)*(r*k), 1e-12)))
                records.append((f, k, r, delta, T_med, T_iqr, x))

# ---------- save CSV ----------
csv_path = os.path.join(SAVE_DIR, "capture_kinetics_grid_median.
   csv")
with open(csv_path, "w", newline="") as fh:
    w = csv.writer(fh)
    w.writerow(["fslow","kappa","ratio","delta","Tlock_median","
        Tlock_IQR","abscissa"])
    w.writerows(records)

# ---------- Figure 1:  Lambda(t) example ----------
plt.figure()
plt.plot(lam)
plt.xlabel("samples")
plt.ylabel("coherence␣proxy")
plt.title(r"Example␣$\Lambda(t)$␣proxy")
plt.tight_layout()
fig1_path = os.path.join(SAVE_DIR, "
   capture_lambda_timeseries_realistic.png")
plt.savefig(fig1_path, dpi=220)
plt.show()

# ---------- log-log scaling (median per cell) ----------
xs  = np.array([r[-1] for r in records], float)
ys  = np.array([r[4]  for r in records], float)     # median
   T_lock
iqr = np.array([r[5]  for r in records], float)

mask = np.isfinite(xs) & np.isfinite(ys) & (xs > 0) & (ys > 0)
xs_f, ys_f, iqr_f = xs[mask], ys[mask], iqr[mask]
```

```python
# OLS
s_ols, b0_ols, r2_ols = loglog_fit_ols(xs_f, ys_f)
med_ols, (lo_ols, hi_ols), _ = bootstrap_ci(xs_f, ys_f,
    loglog_fit_ols, n_boot=1000, seed=2025)

# WLS: weights = 1/(IQR**2) (proxy for precision), regularized and
    clipped
eps = np.maximum(1e-6, np.nanpercentile(iqr_f, 5))
w_raw = 1.0/np.maximum(iqr_f, eps)**2
w = w_raw / np.max(w_raw)
w = np.clip(w, 0.05, 1.0)
s_wls, b0_wls, r2_wls = loglog_fit_wls(xs_f, ys_f, w)
med_wls, (lo_wls, hi_wls), _ = bootstrap_ci(xs_f, ys_f,
    loglog_fit_wls, w=w, n_boot=1000, seed=3030)

# Plot + lines
plt.figure()
plt.loglog(xs_f, ys_f, 'o', alpha=0.8, label="grid medians")
xf = np.linspace(xs_f.min(), xs_f.max(), 300)
yf_ols = np.exp(b0_ols) * xf**s_ols
yf_wls = np.exp(b0_wls) * xf**s_wls
plt.loglog(xf, yf_ols, '-', label=fr'OLS slope {s_ols:.2f}, $R^2$
    {r2_ols:.2f}')
plt.loglog(xf, yf_wls, '--', label=fr'WLS slope {s_wls:.2f}, $R^2$
    {r2_wls:.2f}')
plt.xlabel(r'$[f_{\rm slow}\sqrt{\kappa^2-\delta^2}]^{-1}$')
plt.ylabel(r'$T_{\rm lock}$ (s)')
plt.legend()
plt.tight_layout()
fig2_path = os.path.join(SAVE_DIR, "
    capture_scaling_loglog_realistic.png")
plt.savefig(fig2_path, dpi=220)
plt.show()

# ---------- TXT with both fits + bootstrap CIs ----------
slope_txt_path = os.path.join(SAVE_DIR, "capture_scaling_slope.txt
    ")
with open(slope_txt_path, "w") as fh:
    fh.write("Log-log scaling for T_lock vs [f_slow * sqrt(kappa^2
         - delta^2)]^{-1}\n")
    fh.write(f"Cells used (medians): {xs_f.size}\n")
    fh.write("\nOLS fit:\n")
    fh.write(f"  Slope: {s_ols:.6f}\n  R^2: {r2_ols:.6f}\n")
    fh.write(f"  Bootstrap median slope: {med_ols:.6f}\n")
    fh.write(f"  Bootstrap 95% CI: [{lo_ols:.6f}, {hi_ols:.6f}]\n"
        )
    fh.write("\nWLS fit (weights = 1/(IQR^2), clipped):\n")
    fh.write(f"  Slope: {s_wls:.6f}\n  R^2: {r2_wls:.6f}\n")
    fh.write(f"  Bootstrap median slope: {med_wls:.6f}\n")
    fh.write(f"  Bootstrap 95% CI: [{lo_wls:.6f}, {hi_wls:.6f}]\n"
```

```
            )
        fh.write(f"\nReplicates␣per␣cell:␣{REPLICATES}\nNoise␣D:␣{
            NOISE_D},␣Observation␣T␣(s):␣{T_OBS}\n")
        fh.write("Entry␣criterion:␣<15%␣of␣plateau␣for␣>=5␣s;␣fit␣
            window:␣20␣s;␣"
                "plateau␣=␣median␣of␣last␣20␣s.\n")

print("Saved␣outputs␣to:", os.path.abspath(SAVE_DIR))
print("␣-", os.path.basename(fig1_path))
print("␣-", os.path.basename(fig2_path))
print("␣-", os.path.basename(csv_path))
print("␣-", os.path.basename(slope_txt_path))
```

Listing S6. 2/21 Arnold tongue in the reduced phase model.

It implements the coupled-oscillator simulation used to generate Fig. J.1.

```python
import numpy as np
from scipy.integrate import solve_ivp
import matplotlib.pyplot as plt
from matplotlib.colors import LogNorm

# -----------------------------------------------------------------
# Listing S6: numerical 2/21 Arnold tongue for the reduced phase
#   model
#
# Purpose
# -------
#   Scan the parameter plane (Omega = omega1/omega2, K2) of a
#   two-oscillator phase model and quantify how close the average
#   frequency ratio rho = f1/f2 is to the theoretical 2/21 lock.
#   The script produces a zoomed heatmap around the 2/21 tongue.
#
# Inputs (conceptual)
# -------------------
#   omega2        : reference natural frequency (set to 1.0 here).
#   Omega_vals    : grid of frequency ratios omega1/omega2 to scan.
#   K2_vals       : grid of coupling strengths K2 to scan.
#
# Numerical settings
# ------------------
#   t_span, t_eval : integration time window and sampling for
#   solve_ivp.
#   rtol, atol     : solver tolerances.
#
# Output
# ------
#   A PNG figure "Arnold_Tongue_2over21.png" containing:
#     - log-scaled heatmap of |rho - 2/21|
#     - cyan contour where |rho - 2/21| = 0.005, approximating
#       the effective 2/21 plateau.
```

```python
# ----------------------------------------------------------------

OUTPUT_FIG = "Arnold_Tongue_2over21.png"

# --------------------------------------------------
# Coupled phase-oscillator model
# --------------------------------------------------
def coupled_oscillators(t, y, omega1, omega2, K2):
    """
    Simple two-oscillator phase model with even-harmonic coupling.

    Parameters
    ----------
    t : float
        Time (not used explicitly; required by solve_ivp interface
        ).
    y : array_like, shape (2,)
        State vector [theta1, theta2].
    omega1, omega2 : float
        Natural angular frequencies of oscillators 1 and 2.
    K2 : float
        Even-harmonic coupling strength.

    Returns
    -------
    list of float
        Time derivatives [dtheta1/dt, dtheta2/dt].
    """
    theta1, theta2 = y
    dtheta1_dt = omega1 + K2 * np.sin(2 * (theta2 - theta1))
    dtheta2_dt = omega2
    return [dtheta1_dt, dtheta2_dt]

# --------------------------------------------------
# Parameter scan around the 2/21 Arnold tongue
# --------------------------------------------------
omega2 = 1.0  # reference frequency (sets the time scale)

rho_target = 2.0 / 21.0                            # target locked ratio ~
    0.0952
Omega_vals = np.linspace(0.05, 0.14, 120)  # Omega = omega1/omega2
K2_vals    = np.logspace(-3, -0.1, 80)     # coupling strength K2:
    1e-3 ... ~0.8

Omega_grid, K2_grid = np.meshgrid(Omega_vals, K2_vals)
rho_grid = np.zeros_like(Omega_grid)

# Integration set-up
t_span = (0.0, 1000.0)
t_eval = np.linspace(*t_span, 2000)
```

```python
y0 = [0.0, 0.0]

# Progress bookkeeping
n_K2    = len(K2_vals)
n_Omega = len(Omega_vals)
total_points = n_K2 * n_Omega
counter = 0

print(
    "Scanning␣parameter␣grid␣around␣the␣2/21␣lock␣"
    f"({n_K2}␣x␣{n_Omega}␣=␣{total_points}␣points)..."
)

for i, K2 in enumerate(K2_vals):
    for j, Omega in enumerate(Omega_vals):
        omega1 = Omega * omega2

        # Integrate the coupled-oscillator system for this (Omega,
            K2)
        sol = solve_ivp(
            coupled_oscillators, t_span, y0,
            args=(omega1, omega2, K2),
            t_eval=t_eval, rtol=1e-6, atol=1e-6, max_step=1.0
        )

        theta1, theta2 = sol.y

        # Unwrap phases to count cycles reliably
        phi1 = np.unwrap(theta1)
        phi2 = np.unwrap(theta2)

        cycles1 = (phi1[-1] - phi1[0]) / (2 * np.pi)
        cycles2 = (phi2[-1] - phi2[0]) / (2 * np.pi)

        # Average frequency ratio rho = f1/f2
        rho_grid[i, j] = cycles1 / cycles2 if cycles2 > 0 else np.
            nan

        # Update progress counter
        counter += 1
        if counter % 500 == 0 or counter == total_points:
            frac = 100.0 * counter / float(total_points)
            print(f"Progress:␣{counter}/{total_points}␣points␣({
                frac:.1f}%)")

print("Parameter␣scan␣completed.␣Building␣figure...")

# Distance to the 2/21 plateau
delta_rho = np.abs(rho_grid - rho_target)
```

```
# ---------------------------------------------------------------
# Plot: zoom around the 2/21 Arnold tongue
# ---------------------------------------------------------------
plt.style.use("default")
fig, ax = plt.subplots(figsize=(10, 8))

# Heatmap of |rho - 2/21| in the (Omega, K2) plane
pcm = ax.pcolormesh(
    Omega_grid, K2_grid, delta_rho,
    shading="auto",
    norm=LogNorm(vmin=1e-4, vmax=1),
    cmap="magma"
)

cbar = fig.colorbar(pcm, ax=ax)
cbar.set_label(r"$|\rho - 2/21|$")

# Contour where |rho - 2/21| = tol, to highlight the effective
    plateau
tol = 0.005
cs = ax.contour(
    Omega_grid, K2_grid, delta_rho,
    levels=[tol],             # single contour level is fine for
        contour (not contourf)
    colors="cyan",
    linewidths=1.0
)
ax.clabel(
    cs,
    fmt={tol: r"$|\rho - 2/21| = %.3f$" % tol},
    inline=True,
    fontsize=8
)

ax.set_xlabel(r"$\Omega = \omega_1 / \omega_2$")
ax.set_ylabel(r"Coupling strength $K_2$")
ax.set_yscale("log")
ax.set_title("Zoom around the 2/21 Arnold tongue")
ax.grid(True, which="both", ls="--", alpha=0.3)

plt.tight_layout()
plt.savefig(OUTPUT_FIG, dpi=300)
plt.show()

print(f"Saved figure to {OUTPUT_FIG}")
```

Listing S7. Transverse cut through the 2/21 Arnold tongue.

It implements the transverse scan in K_2 at fixed $\Omega = 2/21$, used to generate Fig. J.2.

```
import numpy as np
```

```python
from scipy.integrate import solve_ivp
import matplotlib.pyplot as plt

# ================================================================
# Listing S7: transverse cut through the 2/21 Arnold tongue
#
# Purpose
# -------
#   For a fixed drive ratio Omega = omega1/omega2 = 2/21, scan the
#   coupling strength K2 and estimate the average frequency ratio
#   f1/f2 in a simple two-oscillator phase model with even-
harmonic
#   coupling. The script produces a 1D "cut" showing how the
system
#   transitions from the 2/21 plateau toward near 1:1 lock as K2
#   increases.
#
# Conceptual inputs
# -----------------
#   omega2        : reference natural frequency (set to 1.0 here).
#   Omega_target : target ratio omega1/omega2 = 2/21 for the cut.
#   K2_values    : log-spaced grid of coupling strengths K2.
#
# Numerical settings
# ------------------
#   t_span, t_eval : integration window and sampling for solve_ivp
  .
#   rtol, atol       : tolerances for the ODE solver.
#
# Output
# ------
#   A PNG file "Arnold_tongue_cut_2over21.png" containing:
#      - the simulated average frequency ratio f1/f2 vs K2,
#      - an orange band where |f1/f2 - 2/21| < 5e-3,
#      - a gold band indicating the near-1:1 lock region,
#      - a vertical line marking K2 ~ 0.5 (the value used in the
#        biological reduced model).
# ================================================================

OUTPUT_FIG = "Arnold_tongue_cut_2over21.png"

# ================================================================
# Coupled phase oscillators with even (mod pi) coupling
# ================================================================

def coupled_oscillators(t, y, omega1, omega2, K2):
    """
    Two phase oscillators with even-harmonic coupling.

    Parameters
```

```
        ----------
        t : float
            Time (unused, included for solve_ivp compatibility).
        y : array_like, shape (2,)
            Current phases [theta1, theta2].
        omega1 : float
            Natural frequency of oscillator 1.
        omega2 : float
            Natural frequency of oscillator 2.
        K2 : float
            Even-harmonic coupling strength.

        Returns
        -------
        dtheta_dt : list[float]
            Time derivatives [dtheta1/dt, dtheta2/dt].
        """
        theta1, theta2 = y
        dtheta1_dt = omega1 + K2 * np.sin(2.0 * (theta2 - theta1))
        dtheta2_dt = omega2
        return [dtheta1_dt, dtheta2_dt]

# ===================================================================
# Parameter setup: transverse cut at Omega = 2/21
# ===================================================================

omega2 = 1.0                              # reference frequency
Omega_target = 2.0 / 21.0                 # Omega = omega1/omega2 for the
    2/21 tongue
omega1 = Omega_target * omega2      # corresponding omega1

# Coupling strengths to scan (log-spaced: weak -> strong)
K2_values = np.logspace(-3, 1, 200)

# Storage for average frequency ratios f1/f2
ratios = np.full_like(K2_values, np.nan, dtype=float)

# Integration settings
t_span = (0.0, 1000.0)
t_eval = np.linspace(t_span[0], t_span[1], 2000)
y0 = (0.0, 0.0)

print(f"Scanning K2 for Omega = 2/21 ~ {Omega_target:.5f} ...")

for i, K2 in enumerate(K2_values):
    sol = solve_ivp(
        coupled_oscillators,
        t_span,
        y0,
        args=(omega1, omega2, K2),
```

```
            t_eval=t_eval,
            rtol=1e-6,
            atol=1e-6,
            max_step=1.0,
        )
        if not sol.success:
            continue

        # Unwrap phases to count cycles
        theta1 = np.unwrap(sol.y[0])
        theta2 = np.unwrap(sol.y[1])

        cycles1 = (theta1[-1] - theta1[0]) / (2.0 * np.pi)
        cycles2 = (theta2[-1] - theta2[0]) / (2.0 * np.pi)

        if cycles2 > 0:
            ratios[i] = cycles1 / cycles2

print("Done.␣Building␣figure␣...")

# ==================================================================
# Plot: transverse cut through the 2/21 Arnold tongue
# ==================================================================

plt.style.use("default")
fig, ax = plt.subplots(figsize=(10, 7))

mask_good = ~np.isnan(ratios)
K2_plot = K2_values[mask_good]
ratio_plot = ratios[mask_good]

# Main curve: simulated average frequency ratio f1/f2
ax.plot(
    K2_plot,
    ratio_plot,
    "o-",
    color="cyan",
    markersize=4,
    linewidth=1.0,
    label=r"Simulation␣$f_1/f_2$",
)

# ----- Highlight the 2/21 plateau band -----
ratio_221 = 2.0 / 21.0
tol_221 = 5e-3   # tolerance around 2/21
band_low = ratio_221 - tol_221
band_high = ratio_221 + tol_221
mask_221 = np.abs(ratio_plot - ratio_221) < tol_221

ax.fill_between(
```

```
        K2_plot,
        band_low,
        band_high,
        where=mask_221,
        color="orange",
        alpha=0.25,
        interpolate=True,
        label=r"$|f_1/f_2␣-␣2/21|␣<␣5\times␣10^{-3}$",
    )

ax.axhline(
        ratio_221,
        color="red",
        linestyle="--",
        linewidth=1.5,
    )

# ----- Highlight the near 1:1 lock region -----
tol_11 = 1e-2
band11_low = 1.0 - tol_11
band11_high = 1.0 + tol_11
mask_11 = np.abs(ratio_plot - 1.0) < tol_11

ax.fill_between(
        K2_plot,
        band11_low,
        band11_high,
        where=mask_11,
        color="gold",
        alpha=0.18,
        interpolate=True,
        label=r"near␣$1{:}1$␣lock",
    )

ax.axhline(
        1.0,
        color="gold",
        linestyle=":",
        linewidth=1.0,
    )

# -- Mark the theoretical K2 ~ 0.5 used in the biological model --
K2_theoretical = 0.5
ax.axvline(
        x=K2_theoretical,
        color="deepskyblue",
        linestyle="--",
        linewidth=1.5,
    )
```

```
# Place the label slightly LEFT of the vertical line (on a log x-
    axis)
ax.text(
    K2_theoretical / 1.2,
    0.25,
    r"$K_2 \simeq 0.5$",
    color="deepskyblue",
    rotation=90,
    va="bottom",
    ha="right",
)

# ================================================================
# Axes, labels, and layout
# ================================================================

ax.set_xscale("log")
ax.set_xlim(K2_values.min(), K2_values.max())
ax.set_ylim(0.0, 1.05)

ax.set_xlabel(r"Coupling strength $K_2$")
ax.set_ylabel(r"Average frequency ratio $f_1/f_2$")
ax.set_title(r"Transverse cut of the Arnold tongue at $\Omega =
    2/21$")

ax.grid(True, which="both", ls="--", alpha=0.5)
ax.legend(loc="lower right", fontsize=9)

plt.tight_layout()
plt.savefig(OUTPUT_FIG, dpi=300)
plt.show()

print(f"Saved figure to {OUTPUT_FIG}")
```

M Glossary of symbols

This appendix summarizes the main symbols used in the slow-phase locking analysis, the coherence readout Λ, and the phase-targeted entrainment protocol. Unless noted otherwise, quantities are evaluated under neutral-moment strobing (even parity) and at the mesoscale wavenumber $k^* = \pi/\ell$.

Table 6: Dynamical / locking variables (core): slow cadence, slow-phase map parameters, and slow-band coherence.

Symbol	Units	Meaning / operational definition
$V(\mathbf{x}, t)$	arb. units	Bioelectric field / membrane potential readout (optical electrophysiology).
$\sigma(\mathbf{x}, t)$	Pa (stress)	Cortical / tensional stress field inferred from traction force microscopy, AFM, etc.

Symbol	Units	Meaning / operational definition
$u(\mathbf{x}, t)$	m	Cortical displacement field (primary mechanical state variable); stress σ is derived from u via viscoelastic constitutive relations.
f_-, f_+	Hz	Carrier frequencies of the two weakly coupled underdamped *latent* modes in the fast band (typically 1–3 Hz).
f_{slow}	Hz	Slow interference cadence, $|f_+ - f_-|$; appears as a shared slow-band peak in V and σ.
r_{eff}	–	Carrier ratio $r_{\text{eff}} = \Omega_-/\Omega_+$ (often $\approx f_-/f_+$ when carriers are well resolved); used to estimate the slow forcing Ω.
Ω	rad	Effective slow-phase forcing in the even (mod π) map, estimated from neutral-moment stroboscopy; operationally $\Omega \simeq \frac{\pi}{2}(1 - r_{\text{eff}})$.
K_2	rad	Even-harmonic coupling strength in the slow-phase map, obtained by regressing $\Delta\theta_n$ onto $\sin(2\theta_n)$ at neutral moments.
θ_n	rad	Fast "+" carrier phase sampled at successive neutral moments (near-symmetric crossings with $\psi \equiv 0 \bmod \pi$ and positive slope); in the even convention $\theta \sim \theta + \pi$.
$\Delta\theta_n$	rad	One-step slow-phase increment, $\theta_{n+1} - \theta_n$ (unwrapped across successive neutral moments).
Λ	–	Slow-band electromechanical coherence, $\Lambda \equiv C_{V\sigma}(f_{\text{slow}}) \in [0, 1]$. High Λ: V and σ share the slow cadence; low Λ: drift / loss of coordination.

Table 7: Latent-mode parameters used in the fast-band generator (Eqs. 1–4).

Symbol	Units	Meaning / operational definition
α_1, α_2	s^{-1}	Damped decay rates of the two latent modes.
ω_1, ω_2	rad/s	Damped (unmixed) carrier angular frequencies of the latent modes.
J	s^{-1}	Complex coupling between the modes (magnitude sets the split/lock threshold).
h_{V1}, h_{V2}	–	Complex projection gains from latent modes to the V channel.
h_{S1}, h_{S2}	–	Complex projection gains from latent modes to the σ channel.
$\Omega_\pm$	rad/s	Observable damped carriers (imaginary parts of the exponents $s_\pm$); $f_\pm = \Omega_\pm/(2\pi)$.
$f_\pm$	Hz	Carrier frequencies.

Table 8: Cycle-resolved and slow-drift metrics from E: neutral-crossing windows around τ_n, pre-crossing drift $D_{\text{pre}}(n)$, and sliding-window trajectory $(\widehat{\Omega}_n, \widehat{K}_{2,n})$ used to assess repeated re-entry into the 2/21 tongue.

Symbol	Units	Meaning / operational definition
$\mathcal{A}_n, \mathcal{B}_n, \mathcal{C}_n$	s	Short windows around a neutral crossing τ_n (E). $\mathcal{A}_n$: approach; $\mathcal{B}_n$: the neutral crossing; $\mathcal{C}_n$: immediate relaxation. Used to compute local coherence and reset ratios.
$D_{\text{pre}}(n)$	rad/s	Pre-crossing slow-phase drift magnitude, $D_{\text{pre}}(n) = \langle \vert\dot{\psi}_{\text{slow}}(t)\vert \rangle_{t \in \mathcal{A}_n}$. Large values indicate accumulated phase error just before τ_n.
$\widehat{\Omega}_n, \widehat{K}_{2,n}$	rad	Sliding-window estimates of forcing and even-harmonic coupling from fits of $\Delta\theta_j = \Omega_n - K_{2,n}\sin(2\theta_j)$ over N_{win} successive crossings ending at τ_n.

Table 9: Cycle-resolved diagnostics: angular stability Var_{map}, neutral-crossing reset ratio R_{reset}, phase offset $\psi(t)$, and locked winding number ρ_π.

Symbol	Units	Meaning / operational definition
Var_{map}	rad^2	Variance of the neutral stroboscopic increment $\theta_{n+1} - \theta_n$; proxy for spindle-orientation noise.
R_{reset}	–	Reset ratio $R_{\text{reset}}(n) = \Lambda_{\text{local}}(\mathcal{B}_n)/\Lambda_{\text{local}}(\mathcal{A}_n)$ (E). > 1 indicates re-synchronization at the neutral crossing.
$\psi(t)$	rad	Instantaneous phase difference $\psi = \phi_V - \phi_\sigma$ between V and σ (Hilbert phases). $\psi \equiv 0 \mod \pi$ with positive slope defines a neutral crossing.
ρ_π	–	Locked winding number in the even (mod π) convention; physiological plateau $\rho_\pi = 2/21$.

Table 10: Material / biophysical parameters and readouts: couplings, spectra, coherence, and geometric projections.

Symbol	Units	Meaning / operational definition
ℓ	m	Effective cortical (shell) thickness setting the mesoscale.
k^*	m^{-1}	Mesoscale wavenumber where carriers are evaluated: $k^* = \pi/\ell$.
D_V	m^2/s	Effective voltage diffusivity / gap-junctional spread parameter.
τ_m	s	Membrane (RC) charging time.
κ	N/m	Effective surface (area) elastic modulus / in-plane tension modulus of the cortex.
η	$\text{N} \cdot \text{s/m}$	Effective cortical surface viscosity (loss).
D_σ	m^2/s	Effective stress diffusion / mechanical spreading.
β_R, β_I	V/Pa (or eq.)	In-phase (β_R) and quadrature (β_I) components of mechanical→electrical coupling.

Symbol	Units	Meaning / operational definition
γ	m/V (or Pa/V)	Electrical$\rightarrow$mechanical coupling gain (drive of V onto cortical displacement/stress).
ϕ_c	rad	Electromechanical coupling phase, $\phi_c = \arg(\beta_R + i\beta_I)$.
Γ	s^{-1}	Effective electromechanical cross-gain block, $\Gamma = |\gamma|\beta_R$. Controls coupling strength.
a	s^{-1}	Effective electrical dissipation block, $a = \tau_m^{-1} + D_V k^{*2}$. Modulated by ion channels/pumps.
b	s^{-1}	Effective mechanical dissipation block, $b = \kappa + D_\sigma k^{*2}$. Modulated by stiffness/viscosity.
$C_{V\sigma}(f)$	–	Magnitude-squared coherence between V and σ at frequency f.
$S_V(f)$, $S_\sigma(f)$	arb. units	Power spectral densities (Welch) of V and σ.
$S_V^{\text{slow}}(f)$, $S_\sigma^{\text{slow}}(f)$	arb. units	Slow-band spectra near f_{slow}.

Table 11: Locking geometry and quantitative criteria (Sec. 8) together with experimental variables for phase-targeted entrainment (Appendices F–G).

Symbol	Units	Meaning / operational definition
Locking geometry and quantitative criteria (Sec. 8)		
$\Omega_{2/21}$	rad	Tongue center for the 2/21 lock in the even (mod π) map: $\Omega_{2/21} = \pi \cdot 2/21 \approx 0.2992$.
q	–	Denominator of the rational p/q (even map). "Low order" means $q \leq 6$.
d_Ω	rad	Distance in Ω to the nearest $q \leq 6$ tongue *center* (or to the overlapping *boundary* if local overlaps occur). Used in the P2 criterion.
σ_Ω	rad	Uncertainty of $\widehat{\Omega}$ from neutral-moment, cycle-resolved sampling (robust SE across windows).
$P_{2/21}$	–	Monte Carlo probability (under physiological priors) that (Ω, K_2) lies inside the 2/21 tongue; P2 requires $P_{2/21} \geq 0.30$.
p_{re}	–	Per-cycle re-entry fraction into the 2/21 tongue (E), estimated from the rolling trajectory $(\widehat{\Omega}_n, \widehat{K}_{2,n})$.
Experimental variables for phase-targeted entrainment (Appendices F–G)		
f_{drive}	Hz	Drive frequency set near f_{slow} (on-band) as predicted by (Ω, K_2).
f_{ctrl}	Hz	Off-resonant control: $f_{\text{ctrl}} = f_{\text{slow}}(1 + \delta)$ with $\delta \in [0.10, 0.25]$, energy-matched.
parity	–	Stroboscopic parity (even: neutral-moment sampling; odd: full-cycle). Internal on/off control.
N_{win}	–	Window length (number of successive neutral crossings) for sliding estimates $(\widehat{\Omega}_n, \widehat{K}_{2,n})$.

Acknowledgments

This manuscript was prepared with the assistance of AI-based editing and drafting tools. The author retains full responsibility for the analysis, interpretation, and any errors.

References

[1] S. H. Strogatz, *Nonlinear Dynamics and Chaos*, Westview Press (2018).

[2] V. I. Arnold, Small denominators and problems of stability of motion in classical and celestial mechanics, *Russian Mathematical Surveys* **18** (1963) 85–191.

[3] M. Levin, Bioelectric signaling: Reprogrammable circuits governing growth and form, *Cell* **184** (2021) 197–205.

[4] G. Shim, I. B. Breinyn, A. Martínez-Calvo, S. Rao, and D. J. Cohen, Bioelectric stimulation controls tissue shape and size, *Nature Communications* **15** (2024) 2938.

[5] J. Cervera, M. Levin, and S. Mafé, Multicellular adaptation to electrophysiological perturbations analyzed by deterministic and stochastic bioelectrical models, *Scientific Reports* **14** (2024) 27608.

[6] E. K. Paluch, I. M. Aspalter, and M. Sixt, The actin cortex as a force generator in animal cells, *Nature Reviews Molecular Cell Biology* **17** (2016) 733–747.

[7] L. G. Lippincott-Schwartz *et al.*, Cellular mechanisms of tissue morphogenesis, *Science* **362** (2018) eaat1551.

[8] B. B. Machta *et al.*, Mechanics and active fluctuations of the cell cortex, *Annual Review of Condensed Matter Physics* **10** (2019) 325–344.

[9] V. I. Arnol'd, Small denominators. I. Mappings of the circle onto itself, *Amer. Math. Soc. Transl. (2)* **46** (1965) 213–284. [Original: *Izv. Akad. Nauk SSSR Ser. Mat.* **25** (1961) 21–86.]

[10] A. Pikovsky, M. Rosenblum, J. Kurths, *Synchronization: A Universal Concept in Nonlinear Sciences*, Cambridge University Press, Cambridge (2001).

[11] R. K. Aaron, D. M. Ciombor, B. J. Simon, Treatment of nonunions with electric and electromagnetic fields, *Clinical Orthopaedics and Related Research* **419** (2004) 21–29.

[12] T. Gordon, N. Amirjani, D. C. Edwards, K. M. Chan, Brief post-surgical electrical stimulation accelerates axon regeneration and muscle reinnervation without affecting functional measures in carpal tunnel syndrome patients, *Experimental Neurology* **223** (2010) 192–202.

[13] H.-M. Lim, M.-H. Nam, Y.-M. Kim, Y.-K. Seo, Increasing odontoblast-like differentiation from dental pulp stem cells through increase of β-catenin/p-GSK-3β expression by low-frequency electromagnetic field, *Biomedicines* **9** (2021) 1049.