Theta-frequency resonance as the scale of input-output mapping in the medial entorhinal cortex

Nupur Katyare & Sujit Sikdar
Molecular Biophysics Unit, Indian Institute of Science, Bangalore, India, 560012.

Grid cell spatial period is thought to be dictated by a mapping between the speed-direction modulated excitatory inputs, and consequent modulation of the firing rate, yet, the exact underlying mechanisms are not known. Here, through experiments on the medial entorhinal cortex stellate cells, subjected to *in-vivo* like stochastic synaptic activity through the dynamic clamp, we show that such mapping can emerge from a theta-frequency resonance in the signal gain, which is HCN sensitive, robust to noise, and is potent enough to modulate the synaptic responses in the theta frequency. This modulation also extends to the corresponding theta-gamma modulation of the firing rate, the slope of whose excitation mediated increase is steeper in the presence of HCN channels. We also show that in the cells devoid of HCN channels, inhibition can emulate their role. Considering the dorso-ventral gradients of HCN and inhibition, which are present aligned to the grid spacing gradient in the medial entorhinal cortex, these findings should be noteworthy.

The computational capabilities of Stellate cells of the Medial Entorhinal Cortex (MEC) are evident from their grid-like and border-like spatial representations[1–3], their necessity for spatial learning[4], their ability to facilitate contextual representations in the downstream circuits[5], steeper slopes of phase precession[6], and their possible contributions to the theta and the gamma rhythms[7]. Although other excitatory cell types have now been reported to exhibit grid-like firing patterns[1,8], the strong correlation between the gradients of intrinsic properties and integration time window of stellate cells along the dorso-ventral (DV) axis of the Medial Entorhinal Cortex (MEC)[9–12], and a

similar gradient observed in the spacing of the grid fields[13,14], is still in need of many mechanistic

and theoretical explanations.

Theories explaining grid cell spatial periodicity generally assume a mapping between the speed-

direction modulated inputs, and the consequent modulation of the membrane voltage response;

accounting for the path integration[12,15–20]. The intrinsic mechanisms in stellate cells conjectured to

affect this mapping are mainly the intrinsic theta oscillations[19,21,22], other HCN mediated

mechanisms[9,23,24] and the membrane resistance and its effects on the time constants[9,12]. Intrinsic theta

oscillations have been confirmed in *in-vivo* intracellular recordings of the grid cells[2,3], and have been

reported to be potent enough to influence the spike timings but not to generate the firing fields on

their own, which were rather found to be generated by the slow synaptic ramps[2,3]. The involvement

of HCN channels is evident from the experiments on the HCN1 knockout mice[25], which reported

expanded grid fields and reduced slope of the theta frequency modulation by speed.

All these observations lead to the following questions: How the ramps and theta oscillations in the

membrane potential can emerge from the noisy stream of synaptic inputs? Through which

mechanisms can HCN channels influence the mapping between the excitation and the firing rate

which is thought to influence the grid spatial periodicity? And what alternate mechanisms operate in

the cells devoid of HCN channels?

A way to address these questions is to consider that although the intrinsic theta oscillations can be

weakened by the *in-vivo* noise[26], the underlying HCN dependent resonance mechanisms can still

manifest in shaping the cellular responses[27–29].

To look for such functional resonance mechanisms, we computed signal gain in stellate cells under

dynamic clamp mimicked *in-vivo* states, and observed that it indeed displays a strong HCN

dependent theta-frequency resonance, which is also robust to the underlying noise. Interestingly, we

observed that this resonance in signal gain also reflects in a strong theta modulation of the synaptic

noise, and is also accompanied by a faster gamma frequency bursting; which together lead to a

steeper theta frequency firing rate modulation by excitation.

While studying this response modulation, we also observed the membrane potential signatures of

theta oscillatory activity and the slow synaptic ramps to emerge from an interplay between the HCN

channels and the excitatory input kinetics.

We could confirm these results in a computational model of stellate cell subjected to the same input

regime, which provided additional insights regarding the role of inhibition as an alternate resonance

mechanism in the cellular circuits devoid of HCN channels.

The fact that the dorso-ventral gradients of HCN and inhibition are present in the medial entorhinal

cortex[9,11,30], aligned to the grid spacing gradient[13,14], further underlines the importance of these

results.

Our findings thus indicate that the acuteness and scaling of responses in these cells is critically

maintained by the mechanisms of resonance contributed by HCN channels and inhibition.

RESULTS

Theta frequency peak in the signal gain

We estimated signal gain of stellate cells when the cells were firing in theta frequency under the

mimicked *in-vivo* states. The stellate cells were identified from their electrophysiological responses

(**Supplementary Figure 1**) in the whole cell current clamp mode, following which the *in-vivo* states

were mimicked through the dynamic clamp[31] (**Supplementary Figure 2**). The successful mimicry[31]

was tallied from large voltage fluctuations following a large depolarization (**Fig. 1a**), and ~ 70 %

drop in the input resistance (**Fig. 1b**).

We considered two types of responses, leading to two different signal gain waveforms. $Gain_V$ (**Fig.**

1c), computed from the collective voltage trace, which mainly reflected the subthreshold frequency

selectivity; and $Gain_R$, (**Fig.1 e**), computed from a smoothly varying instantaneous firing rate

(**Supplementary Figure 3)**, which reflected whether the observed subthreshold frequency selectivity

can actually modulate the firing pattern of these cells.

The two estimates thus allowed us to assess the frequency dependent gain of subthreshold responses

(Gain$_V$) and firing rate (Gain$_R$). Considering the contribution of HCN channels in maintaining the

theta frequency resonance in stellate cells, we also re-estimated the signal gain after blocking HCN

channels. To quantify the observed changes, we compared the frequency at which the peak was

observed (f$_{peak}$), the actual gain at peak (G$_{max}$), and the relative gain in theta frequency (4-14 Hz)

(theta-index); across the control and the test cases.

In Gain$_V$, we observed a prominent peak in the theta frequency (f$_{peak}$ = 5.35 ± 0.38 Hz, mean ±

s.e.m., n=12), which shifted significantly to the lower frequencies (2.56 ± 0.19 Hz, n=12) after

blocking HCN channels with ZD7288 (ZD, 25 μM) (**Fig. 1c,d**); although the firing rates in the

control and under ZD were comparable (**Supplementary Figure 3**). A similar HCN sensitive theta

frequency selectivity was also observed in the membrane voltage power spectrum, suggesting a

reflection of the theta resonance (**Supplementary Figure 4**).

The actual gain (G$_{max}$) was slightly higher in test (114.36 ± 12.87 mV/nA, n=12) than the control

conditions (90.94 ± 6.13 mV/nA, n=12) (**Fig.1 g**), which can be expected considering the effects of

higher input resistance after blocking HCN channels. Interestingly, however, the relative theta-

frequency gain (theta-index), was significantly higher in control conditions (15.82 ± 0.18, n=12) than

the test (13.19 ± 0.12, n=12) (**Fig.1 g**).

Interestingly, Gain$_R$ too displayed a prominent peak in theta frequency (f$_{peak}$ = 4.2 ± 0.15 Hz, n=12),

which shifted significantly to lower frequencies after blocking HCN channels (2.56 ± 0.05 Hz, n=12)

(**Fig. 1e,f**); but unlike Gain$_V$, the increase in G$_{max}$ for Gain$_R$ was non-significant (**Fig. 1h**).

Interestingly, the theta-index was still significantly higher for control (13.24 ± 0.26, n=12) than the

test conditions (11.33 ± 0.25, n=12) (**Fig. 1h**).

These findings are in accordance with the previous studies which reported the influence of the

subthreshold resonance mechanisms on the active properties[27], and suggest the frequency dependent

gain as a suitable index for mapping the relationship between the sensory modalities mediated

excitation and the resulting firing rate response.

Effect of input statistics on the signal gain

Next, considering that the input statistics can have a role in determining the actual signal gain[29,32],

we systematically perturbed the synaptic parameters of the *in-vivo* regime and studied changes in the

frequency dependent gain.

To assess the effects of the excitatory drive on the signal gain, we first increased the strength of

excitation by increasing the mean and the standard deviation (SD) of the excitatory conductance one

at a time. We observed that although the firing rate increased linearly with the excitatory strength,

the f_{peak}, or the theta-index of $Gain_V$ or $Gain_R$ in control (**Fig. 2a,b**) or with ZD (**Supplementary**

Figure 5) did not show any significant change.

The G_{max}, however, showed a complex relationship with the excitatory strength, which can be

explained by considering the voltage dependent influence of the HCN current (**Supplementary**

Figure 6).

Next, in order to assess the effects of the synaptic kinetics, we repeated the gain measurements while

gradually slowing down the kinetics of the excitatory as well as inhibitory conductances, by

increasing the decay time constants of the synaptic conductances in steps of 5, 10, 50 and 100 ms.

Again, the $gain_V$ f_{peak} was apparently unaffected by the input kinetics (**Fig. 2c**). However, the theta-

index of $Gain_V$ was observed to increase significantly with the input kinetics (**Fig. 2d**), possibly,

owing to an increased summation of excitatory inputs in the theta frequency.

Next, analyzing the suprathreshold responses, we observed that the mean firing rate, while still

being in theta frequency, decreased significantly as the time constants increased beyond 10 ms

(**Supplementary Figure 7**), indicating significantly slower rate modulation. Surprisingly however, in

spite of this decrease in the mean firing rate, the f_{peak} of $Gain_R$, showed an interesting overall

increase (**Fig. 2c**). One of the underlying factors causing this can be the higher frequency bursts,

which, apart from increasing the gamma frequency power, when modulated in theta frequency, can

give rise to an overall increase in power in theta frequency. To test this, we analyzed the percentage

of spikes occurring as bursts (frequency > 50 Hz) for each group, and indeed observed that the bursts

increased significantly as the synaptic time constants increased from 5 to 50 ms (**Fig. 2e**). The $Gain_R$

G_{max}, however, increased up to a certain range (50 ms), and decreased thereafter (**Supplementary**

Figure 7).

These observations are in agreement with the previous findings[29], whereby the peak frequency of the

lower frequency resonance was observed to increase and the resonance strength was observed to

decrease with slower input time constants, as a result of modulation of bursts. Our results thus

confirm the role of bursts as a mechanism of active gain modulation.

Theta modulation of synaptic inputs by HCN

Next, to probe further whether the amplified signal gain in theta frequency manifests in the

modulation of synaptic inputs, we extracted the underlying theta oscillatory signal (**Fig. 3a**) from the

collective voltage response by 4-15 Hz band pass filtering, and analyzed it further.

Prominent subthreshold modulation in the theta range was indeed observed in this filtered signal, and

on aligning the spike timings to it, the preference of spikes for the theta peaks was clear (**Fig. 3b**).

For the default synaptic time constants, which were moderately slow, the peak in the power spectrum

of this signal was obtained near 5 Hz on average (5.07 ± 0.12 Hz, n=12) (**Fig. 3c**). This peak

frequency after blocking HCN channels was significantly reduced (3.3 ± 0.08 Hz, n=12) (**Fig. 3c,d**),

indicating a salient theta frequency modulation of synaptic inputs by HCN channels. This peak

frequency also showed a DV gradient for the sample size tested, which, interestingly, was flattened

in the presence of ZD (**Supplementary Figure 8**).

Next, in order to determine the extent to which this theta oscillatory activity influences the spike

timings, we analyzed the distribution of spike phases over the underlying theta (4-15) / delta (1.5-4

Hz) signal. We observed that most of the spikes fired at the near-peak ascending phase in control as

well as with ZD (**Fig. 3e**), and the distributions of spike phases in both cases were almost identical.

Summarizing, for the given input parameters, HCN channels significantly contribute to the theta

frequency modulation of the synaptic inputs. When the HCN induced resonance mechanisms are

absent, the underlying subthreshold signal oscillates at a slower pace, but the spikes are still

preferentially fired on the peaks of this subthreshold oscillatory signal.

Theta modulation is sensitive to excitatory input kinetics

The results so far indicated that under *in-vivo* conditions, the synaptic inputs can be paced in a

preferred frequency range by the neuron's intrinsic resonance mechanisms, and even in the absence

of such mechanisms, albeit in lower frequencies, a rhythmicity in the input structure can be present.

These findings tally with the previous reports of persistent delta frequency rhythmicity in HCN1

knockout mice[33].

Next, to assess the sensitivity of this theta modulation to the input statistics, we analyzed the

underlying theta oscillatory signal while systematically varying the input parameters. For the control

conditions, no significant change in the frequency of theta signal was observed on varying the SD

and mean of the excitatory input as before, and also on varying synaptic kinetics within a certain

range. But as the input time constants increased beyond this range, the frequency of modulation

dropped significantly beyond the theta band (**Fig. 4a**).

Interestingly, however, with the slower input kinetics, the voltage response started exhibiting slow

ramp-like motifs, which became more and more prominent on increasing the synaptic time constants

(**Fig. 4b**). The increase in time constants was thus accompanied by a decrease in theta rhythm and

emergence of slow ramps. It should be considered here that the synaptic kinetics so far were varied

similarly for the excitatory and inhibitory inputs, thus making their individual contribution

ambiguous. So next we made the excitation or inhibition selectively slower, while keeping the other

at the default (10 ms; which is relatively faster), and observed that the time constants of excitation

play a crucial role in determining the underlying rhythmic nature. When the inhibition was made

faster, the visible ramps could still form; but that was not the case when the excitation was made

faster against a slow inhibition (**Fig. 4c**); indicating that the emergence of ramps (**Fig. 4d**) requires a

predominantly slow excitation. Also, interestingly, the underlying theta signal, became visibly faster

as the excitation was switched to the fast mode (**Fig. 4e**), underlining the role of excitatory kinetics

in controlling the pace of the fluctuating synaptic activity.

Modulation of the excitation driven firing rate response

Next, in order to determine the extent to which the subthreshold theta modulation can alter the firing

rate modulation, we did a detailed analysis of the temporal and spectral characteristics of the firing

rate response. As stated previously, the firing rate increased with an increase in both, the mean and

SD of the excitatory conductance, and the initial firing rates for the control and the ZD experiments

were comparable (**Supplementary Figure 9**).

We observed however, that the percentage of spikes fired as bursts increased significantly with

increase in the mean excitatory conductance in the control case, but not with ZD (**Fig. 5a**). Also,

with increase in the SD of excitation, although the bursts increased significantly in both control as

well as with ZD, the average number of bursts were significantly higher in the control case, for the

entire middle range of the SD tested (**Fig. 5a**).

Also, to understand the relationship of these gamma frequency bursts with the underlying theta

signal, we analyzed the distribution of the spikes over the theta/delta phases as before, and observed

that, in all the cases, the neuronal firing was aligned to the peaks in the subthreshold signals, in

control as well as with ZD (**Supplementary Figure 9**).

These findings clearly indicate that in the presence of HCN, there are more number of bursts in

response to increasing excitatory drive, which are being modulated in the theta frequency, as

opposed to lesser number of bursts with ZD, which are modulated in the slower delta frequencies.

This confirms an overall stronger theta-gamma coupling in the presence of HCN channels. To study

its implications, we analyzed the theta frequency modulation of the firing rate response, and

observed that the theta-index of the power spectrum of the rate response increased significantly with

the mean excitation in the control case, but not with ZD (**Fig. 5b**). Further analysis confirmed that

the slope of this theta frequency modulation was significantly higher in the control case (**Fig. 5c**),

which parallels the findings of the HCN1 knockout experiment[25].

Inhibition as an alternate resonance mechanism

In order to verify the mechanistic understandings gathered so far, we next constructed a

computational model of MEC Stellate cell, and subjected it to similar *in-vivo* input regime.

The electrophysiological signatures of stellate cells and the hallmarks of successfully operating *in-*

vivo activity [31] could be tallied in the model (**Supplementary Figure 10**) enabling us to proceed

with the signal gain measurements.

The $Gain_V$ and $Gain_R$ estimated from this model displayed similar theta frequency selectivity as

observed experimentally (**Fig. 6a**), thus confirming the sufficiency of proposed mechanisms. Next,

for a better substantiation of the role of HCN channels, we decreased the HCN conductance in the

model in two steps (1 (maximum), 0.5 and 0), and observed a likewise lower frequency shift of f_{peak},

and a decrease in theta-index for both $Gain_V$ and $Gain_R$ (**Fig. 6a,c,d, Supplementary Figure 11**).

The experimentally observed theta-modulation by HCN channels could also be verified in the

computational model (**Supplementary Figure 10**).

Next, to understand the factors regulating the remaining frequency selectivity in the absence of HCN

channels, we decreased the strength of inhibition in two steps (1 (maximum), 0.5 and 0), and

observed a further leftward shift in the frequency preference (**Fig. 6b,c,d**). Considering that a

gradient of grid cell periodicity remains in the absence of HCN channels[25], and a dorsoventral

gradient of inhibition is present in MEC[30], these observations should be noteworthy.

Hitherto, the analysis was carried out at the default synaptic time constants. It was possible that after

removing HCN channels and inhibition, excitation can further affect the signal gain. To confirm this,

we repeated the analysis using substantially slow excitation and observed that the remaining small

frequency selectivity is noticeably affected by the slower excitation for $Gain_V$ as well as for $Gain_R$

(**Supplementary Figure 11**). The gamma frequency gain for $gain_R$ was also visibly increased

following the change in excitatory kinetics (**Supplementary Figure 11**), corroborating the

experimental findings of such increase with slower input time constants (**Supplementary Figure 7**).

Finally, to directly verify the effects of input selectivity analyzed so far, we tested the model with

chirp stimuli (**Fig. 6e**), with increase in stimulus frequency from 0 to 25 Hz in 25 sec.

The roles of HCN channels were evident from the decreased firing on lower stimulus frequencies in

the presence of HCN (**Fig. 6f,g left**), which increased after removal of the HCN channels (**Fig.6f,g**

middle). Next, removing inhibition from the cell, further accentuated the firing response at lower

frequencies (**Fig. 6f,g right**), thus suggesting the role of inhibition in contributing to weak resonance

mechanisms in the stellate cells in the absence of HCN channels.

The results so far suggest that the HCN-based resonance mechanisms in stellate cells, besides

modulating the voltage responses in theta frequency, also bias the preference of these voltage

responses for the theta-frequencies in the stimulus. Collectively, HCN and inhibition thus reduce

action potential firing both on and in the lower frequencies.

Discussion

Theta frequency resonance persists under *in-vivo* states

We observed that the HCN mediated resonance mechanisms are operational during the mimicked *in-vivo* states, despite a drastic drop in the input resistance and high noise levels, and can amplify the signal gain in the theta range.

Another major role attributed to HCN channels is their effect on the membrane resistance, which dictates the membrane time constant, and which in turn, controls the neuronal integrative properties[9]. However, under *in-vivo* states, where the membrane resistance drops by ~ 70-80%[31,34,35], these reciprocal effects of HCN conductance have been questioned[36]. Our findings reveal that under *in-vivo* states, although HCN conductance leads to an overall reduction in the gain, HCN current can modulate the gain in a frequency dependent manner, by selectively increasing the gain over theta frequencies.

Resonance as a dynamic gain control mechanism

Next, as we systematically perturbed the synaptic noise statistics, we observed that although the gain amplitude was sensitive to the input strength, its frequency selectivity was unaffected by such input scaling.

However, on making the synaptic kinetics slower, we observed a small but significant rightward shift in the otherwise unperturbed theta frequency peak, and an increase in the average gamma frequency gain. Both these findings corroborate the earlier reports of stronger higher frequency resonance when these frequencies in the input are weaker[29].

This differential responsiveness of gain to the mean, SD and kinetics of stimulus can be a dynamic gain control mechanism, wherein the neuronal sensitivity to the input statistics is enhanced, enabling a state-dependent adaptation of their responses. Thus, rather than being dampened by noise, we observed the resonance to instead emerge through the latent noise statistics.

Resonance manifests in the theta modulation of inputs

We observed a potent modulation of synaptic inputs in the theta frequency in the presence of HCN channels. Also, the spikes were phase locked to the peak of this signal, suggesting the possible influences on the firing rate modulation, which were later confirmed. In the presence of ZD, the frequency of this signal dropped to the delta range, but the spikes were observed to still occur selectively near the peak of the underlying delta signal.

Further, we observed that the frequency of this theta signal in control case was unaffected by the excitatory strength, but was sensitive to the excitatory input kinetics, which, when faster could contribute to the theta modulation, but when slower, mostly resulted in ramp-like motifs. Thus, our results bring to the fore the key targets: excitatory kinetics and synaptic integration, which when affected, can directly influence the synaptic ramp formation and theta oscillatory activity.

Summarizing, an oscillatory activity is present in the stellate cell voltage responses and is potent enough to modulate the spike timings, notwithstanding the heavy noise. The frequency of this modulation can vary from the dorsal to the ventral MEC, aligned to the HCN conductance, and can have a role in influencing grid-like responses of stellate cells as speculated earlier for the intrinsic oscillations.

Stronger theta-gamma coupling steepens the slope of the firing rate modulation

A detailed analysis of the firing rate response revealed its susceptibility to the underlying subthreshold theta signal. The slope of theta frequency modulation of firing rate with the mean excitation was significantly higher in the control case, where the underlying subthreshold activity is theta-paced, than with ZD, where it oscillates in the delta frequency. Also, it became evident from the analysis of bursts, that there exists also a corresponding theta modulation of the gamma frequency bursts, which makes the overall theta-gamma coupling stronger in the presence of HCN channels. These findings parallel the similar higher slope of theta frequency modulation by running

speed in control mice compared to the HCN1 knockout mice[25], and tally the mechanistic

implications of our findings.

Possible effects on the grid spacing

We observed the theta-peak of the signal gain to be a direct reflection of the strength of HCN

conductance, and found it to be robust to an array of input statistics. This resonance also reflected in

the theta modulation of inputs and in steeper theta-gamma firing rate modulation with excitation,

thus influencing the mapping between the excitatory inputs and the firing rate response.

Thus, there is room for speculating that the dorso-ventral gradient of grid spacing is actually a

manifestation of the dorso-ventral distribution of HCN influenced differential resonance frequencies

of the signal gain, which can reflect in the correspondingly faster theta-gamma modulation of the

firing rate with the velocity mediated excitatory drive.

The reminiscent delta frequency selectivity in signal gain after blocking HCN channels parallels the

HCN1 independent peri-threshold activity[33] and the reminiscent gradient of grid periodicity observed

in the HCN1 knockout mice[25]. This indicates a strong possibility of existence of alternate, HCN

independent/co-dependent resonance mechanisms which can also be functional in the grid cell types

devoid of HCN channels. Given that resonance is known to emerge through the interaction of two

counteracting mechanisms[37], we suspected a role of inhibition. Interestingly, we indeed observed a

leftward shift of signal gain peak with decrease in the inhibitory conductance, indicating that the

reported dorso-ventral inhibitory gradient[30] can contribute to the similar gradient of frequency

selectivity along the MEC DV axis, and can underlie the reminiscent gradient of grid periodicity

observed in the HCN1 knockout mice. These proposed roles of inhibition are in accordance with

those already known in the case of cortical circuits[38].

The combined effects of the excitatory-inhibitory dynamics discussed above, can dictate different

symmetry breaking operations along the dorso-ventral MEC axis, which can be further fine-tuned by

HCN channels, thus setting the grid scale.

Other implications

The robustness of stellate cell resonance to noise level can be an error-correction mechanism,

necessary for maintaining the accuracy of the spatial coding[39]. A possibility thus also remains that

the strong HCN dependent resonance mechanisms in stellate cells, which are also reflected in the

firing rate modulation, can influence the network level input statistics[40], thus influencing input

statistics based resonance in other cell types (in MEC as well as stellate cell's downstream targets in

the hippocampus). Stellate cells in that case can indirectly serve their long believed role of

pacemakers.

Competing interests

The authors declare that they have no conflict of competing interest.

1. Tang, Q. *et al.* Pyramidal and stellate cell specificity of grid and border representations in layer 2 of medial entorhinal cortex. *Neuron* **84,** 1191–1197 (2014).

2. Schmidt-Hieber, C. & Häusser, M. Cellular mechanisms of spatial navigation in the medial entorhinal cortex. *Nat. Neurosci.* **16,** 325–331 (2013).

3. Domnisoru, C., Kinkhabwala, A. A. & Tank, D. W. Membrane potential dynamics of grid cells. *Nature* **495,** 199–204 (2013).

4. Tennant, S. A. *et al.* Stellate Cells in the Medial Entorhinal Cortex Are Required for Spatial Learning. *Cell Rep.* **22,** 1313–1324 (2018).

5. Sun, C. *et al.* Distinct speed dependence of entorhinal island and ocean cells, including respective grid cells. *Proc. Natl. Acad. Sci.* 201511668 (2015). doi:10.1073/pnas.1511668112

6. Reifenstein, E. T. *et al.* Cell-Type Specific Phase Precession in Layer II of the Medial Entorhinal Cortex. *J. Neurosci.* **36,** 2283–2288 (2016).

7. Quilichini, P., Sirota, A. & Buzsáki, G. Intrinsic circuit organization and theta-gamma oscillation dynamics in the entorhinal cortex of the rat. *J. Neurosci.* **30,** 11128–42 (2010).

8. Boccara, C. N. *et al.* Grid cells in pre- and parasubiculum. *Nat. Neurosci.* **13,** 987–994 (2010).

9. Garden, D. L. F., Dodson, P. D., O'Donnell, C., White, M. D. & Nolan, M. F. Tuning of Synaptic Integration in the Medial Entorhinal Cortex to the Organization of Grid Cell Firing Fields. *Neuron* **60,** 875–889 (2008).

10. Giocomo, L. M., Zilli, E. a, Fransén, E. & Hasselmo, M. E. Temporal frequency of subthreshold oscillations scales with entorhinal grid cell field spacing. *Science* **315,** 1719–1722 (2007).

11. Giocomo, L. M. & Hasselmo, M. E. Time constants of h current in layer ii stellate cells differ along the dorsal to ventral axis of medial entorhinal cortex. *J. Neurosci.* **28,** 9414–25 (2008).

12. Navratilova, Z., Giocomo, L. M., Fellous, J. M., Hasselmo, M. E. & McNaughton, B. L. Phase precession and variable spatial scaling in a periodic attractor map model of medial entorhinal grid cells with realistic after-spike dynamics. *Hippocampus* **22,** 772–789 (2012).

13. Brun, V. H. *et al.* Progressive increase in grid scale from dorsal to ventral medial entorhinal cortex. *Hippocampus* **18,** 1200–1212 (2008).

14. Hafting, T., Fyhn, M., Molden, S., Moser, M.-B. & Moser, E. I. Microstructure of a spatial map in the entorhinal cortex. *Nature* **436,** 801–806 (2005).

15. McNaughton, B. L., Battaglia, F. P., Jensen, O., Moser, E. I. & Moser, M.-B. Path integration and the neural basis of the 'cognitive map'. *Nat. Rev. Neurosci.* **7,** 663–678 (2006).

16. Schmidt-Hieber, C. & Hausser, M. How to build a grid cell. *Philos. Trans. R. Soc. B Biol. Sci.* **369,** 20120520–20120520 (2013).

17. Rowland, D. C., Roudi, Y., Moser, M.-B. & Moser, E. I. Ten Years of Grid Cells. *Annu. Rev.*

Neurosci. **39,** 19–40 (2016).

18. Burgess, N. Grid cells and theta as oscillatory interference: theory and predictions. *Hippocampus* **18,** 1157–74 (2008).

19. Burgess, N., Barry, C. & Keefe, J. O. An oscillatory interference model of grid cell firing. *Hippocampus* **17,** 801–812 (2007).

20. Hasselmo, M. E., Giocomo, L. M. & Zilli, E. A. Grid cell firing may arise from interference of theta frequency membrane potential oscillations in single neurons. *Hippocampus* **17,** 1252–1271 (2007).

21. Jeewajee, A., Barry, C., O'Keefe, J. & Burgess, N. Grid cells and theta as oscillatory interference: Electrophysiological data from freely moving rats. *Hippocampus* **18,** 1175–1185 (2008).

22. Barry, C., Bush, D., O'Keefe, J. & Burgess, N. Models of grid cells and theta oscillations. *Nature* **488,** E1–E1 (2012).

23. Ferrante, M., Shay, C. F., Tsuno, Y., Chapman, G. W. & Hasselmo, M. E. Post-Inhibitory Rebound Spikes in Rat Medial Entorhinal Layer II / III Principal Cells : In-Vivo , In-Vitro Evidence for a Model of Grid Cells Generation PIRS in mEC LII Stellate and LII / III Pyramidal cell populations stimulus features mEC dorsal-ventra. 94263

24. Narayanan, R. & Johnston, D. The ascent of channels with memory. *Neuron* **60,** 735–8 (2008).

25. Giocomo, L. M. *et al.* Grid cells use HCN1 channels for spatial scaling. *Cell* **147,** 1159–1170 (2011).

26. Fernandez, F. R. & White, J. A. Artificial Synaptic Conductances Reduce Subthreshold Oscillations and Periodic Firing in Stellate Cells of the Entorhinal Cortex. *J. Neurosci.* **28,** 3790–3803 (2008).

27. Richardson, M. J. E., Brunel, N. & Hakim, V. From subthreshold to firing-rate resonance. *J.*

Neurophysiol. **89,** 2538–54 (2003).

28. Brunel, N., Hakim, V. & Richardson, M. J. E. Firing-rate resonance in a generalized integrate-and-fire neuron with subthreshold resonance. *Phys. Rev. E* **67,** 51916 (2003).

29. Higgs, M. H. & Spain, W. J. Conditional Bursting Enhances Resonant Firing in Neocortical Layer 2-3 Pyramidal Neurons. *J. Neurosci.* **29,** 1285–1299 (2009).

30. Beed, P. *et al.* Inhibitory gradient along the dorsoventral axis in the medial entorhinal cortex. *Neuron* **79,** 1197–1207 (2013).

31. Destexhe, A., Rudolph, M., Sejnowski, T. J. & Jolla, L. FLUCTUATING SYNAPTIC CONDUCTANCES RECREATE IN VIVO -LIKE ACTIVITY IN NEOCORTICAL NEURONS. *Neuroscience* **107,** 13–24 (2001).

32. Brunel, N., Chance, F. S., Fourcaud, N. & Abbott, L. F. Effects of synaptic noise and filtering on the frequency response of spiking neurons. *Phys. Rev. Lett.* **86,** 2186–2189 (2001).

33. Nolan, M. F., Dudman, J. T., Dodson, P. D. & Santoro, B. HCN1 Channels Control Resting and Active Integrative Properties of Stellate Cells from Layer II of the Entorhinal Cortex. *J. Neurosci.* **27,** 12440–12451 (2007).

34. Chance, F. S., Abbott, L. F. & Reyes, A. D. Gain modulation from background synaptic input. *Neuron* **35,** 773–82 (2002).

35. Destexhe, A., Rudolph, M. & Paré, D. The high-conductance state of neocortical neurons in vivo. *Nat. Rev. Neurosci.* **4,** 739–751 (2003).

36. Mishra, P. & Narayanan, R. High-conductance states and A-type K+ channels are potential regulators of the conductance-current balance triggered by HCN channels. *J. Neurophysiol.* **113,** 23–43 (2014).

37. Hutcheon, B. & Yarom, Y. Resonance, oscillation and the intrinsic frequency preferences of neurons. *Trends Neurosci.* **23,** 216–22 (2000).

38. Stark, E. *et al.* Inhibition-Induced theta resonance in cortical circuits. *Neuron* **80,** 1263–1276

(2013).

39.   Sreenivasan, S. & Fiete, I. Grid cells generate an analog error-correcting code for singularly

precise neural computation. *Nat. Neurosci.* **14,** 1330–1337 (2011).

40.   Sinha, M. & Narayanan, R. HCN channels enhance spike phase coherence and regulate the

phase of spikes and LFPs in the theta-frequency range. *Proc. Natl. Acad. Sci.* 201419017

(2015). doi:10.1073/pnas.1419017112

Figure 1 Mimicked in-vivo states and estimation of the signal gain in stellate cells.

a. Voltage response of a stellate cell during mimicked in-vivo states (Left). Note spontaneous theta frequency firing and a detectable rhythmicity in voltage fluctuations. Membrane voltage histogram from the voltage trace in a, SD ~ 5 mV. (Right). b. Top: ~ 10 mV Steady state Voltage deflection from -500 pA current step before switching to the in-vivo regime, Bottom: Similar ~ 10 mV Steady state Voltage deflection from -1500 pA current step in the in-vivo regime. c. $Gain_V$ in the control case (Left) and after blocking HCN channels with ZD7288 (Right). The plots represent average for 12 cells, error bars are s.e.m. d. Summary of the changes in the $Gain_V$ f_{peak} for 12 cells in the presence of ZD7288. e,f. same as c,d for $Gain_R$. g. Summary of the changes in the G_{max} (left) and theta-index (right) in the presence of ZD7288 for $Gain_V$. h. Same as g for $Gain_R$.

d,f,g,h: *** $p < 0.001$, ** $p < 0.01$, * $p < 0.05$, n.s. non-significant, Student's paired t-test.

Figure 2 Effects of stimulus statistics on the signal gain

a. Variations in the f_{peak} of $gain_V$ and $gain_R$ as a function of strength of excitation (normalized mean (n = 6) or SD (n = 9) of the excitatory conductance). b. Same as a for the theta-index of $gain_V$ and $gain_R$.

c. Variations in the f_{peak} of $gain_V$ and $gain_R$ as a function of input kinetics (n = 7). d. Same as c for the theta-index. e. Percentage of spikes occurring in bursts as a function of the input kinetics.

c,d: * $p < 0.05$, n.s. non-significant, Kruskal-Wallis test; e: *** $p < 0.001$, ** $p < 0.01$, n.s.: non significant, Student's paired t-test.

X

Figure 3 Theta frequency modulation of the synaptic inputs by HCN channels.

a. 4-15 Hz band-pass filtered signal (red) overlaid on the actual voltage trace (black). b. The theta signal in a (red), and the corresponding spike timings (grey circles). c. Average power spectrum of the theta response (Left) and same after blocking HCN channels with ZD7288 (Right). The plots represent average for 12 cells, error bars are s.e.m. d. Summary of the changes in the peak frequency of the theta power spectrum in c, for 12 cells in the presence of ZD7288. e. Spike phase histograms for the pooled spike phases of 12 cells corresponding to their theta signals (see methods for the phase assignment). d: *** $p < 0.001$, Student's paired t-test, e: n.s.: difference in the distributions non-significant, Kruskal-Wallis test.

Figure 4 Theta modulation is sensitive to the excitatory input kinetics.

a. Changes in the peak frequency of the theta power spectrum, as a function of the excitatory strength (normalized SD, mean of the excitatory conductance) and excitatory-inhibitory time constants. b. Voltage traces for the matched excitatory-inhibitory time constants varied from 50 ms, 100 ms, 200 ms, 500 ms, to 1000 ms top to bottom. c. Left: Voltage trace for the excitatory time constant = 100 ms, and inhibitory time constant = 10 ms; Right: Vice-a-versa. d. 3 Hz low-pass filtered ramp signals for the traces in c. e: 4-15 Hz band-pass filtered theta signals for the traces in c.

a: $*$ p < 0.05, Wilcoxon signed rank test, others: non-significant, Wilcoxon signed rank test & Kruskal-Wallis test.

Figure 5 HCN controls the slope of theta specific firing rate modulation with excitation

a. Percentage of spikes fired in bursts as a function of the mean and SD of the excitatory conductance (normalized) in control and with ZD (pooled data for n = 6 and 9 respectively).

b. Theta-specific modulation of the firing rate response (theta-index of the rate response power spectrum), in control and with ZD. The overall increase was significant in the control case, but not with ZD. c. One-way analysis of covariance of the data in b shows a significant difference in slopes of excitation driven theta specific firing rate modulation between control and the test case.

a : *** $p < 0.001$, ** $p < 0.01$, * $p < 0.05$, Kruskal-Wallis test for the pooled data, Student's paired t-test for the individual experiments. b: * $p < 0.05$, n.s: non-significant, Kruskal-Wallis test, c. * $p < 0.05$, Analysis of covariance, F-test.

Figure 6 Inhibition controls the frequency selectivity in signal gain in the absence of HCN channels. a. Normalized Gain$_V$ (Left) and Gain$_R$ (Right) as a function of normalized HCN conductance. b. Normalized Gain$_V$ (Left) and Gain$_R$ (Right) as a function of normalized inhibitory conductance in 0 HCN condition. The plots in a,b represent average of 10 trials of 30 sec. each. c,d. Summary of the changes in f$_{peak}$ for the traces in a and b. e. Chirp stimulus spanning 25 Hz in 25 sec. f. Voltage responses to stimulus in e injected under the in-vivo regime, for control (Left), no HCN (Middle), and no HCN-no Inhibition (Right) cases. Scale Bar: 5 sec., 20. mV in all panels. g. Histogram of spike times for total spikes fired in 10 trials as a function of stimulus frequency, for data in f.
c: ** $p < 0.01$, * $p < 0.05$, Kruskal-Wallis test.

Online Methods

Brain slice preparation

The guidelines of 'Animal Ethics and Welfare Committee' of the Indian Institute of Science,

Bangalore, India were followed in all the experiments. 5-8 week old male SD rats (weighing ~130 -

250 g) were used in the study.

Rats were anesthetized by intra-peritoneal injection of a combination of Ketamine and Xylazine

(dose calculated according to the animal weight). After onset of deep anaesthesia, as determined by

cessation of toe-pinch reflex, rats were transcardially perfused with ice-cold cutting solution (see

Solution composition) continuously bubbled with carbogen (a mixture of 95% O_2 and 5% CO_2 gas),

and then decapitated.

During dissection, the skull was carefully separated through its midline and the brain was scooped

out using a blunt spatula from the side of the cerebellum and was immediately transferred to sACSF

(see Solution composition) pre-chilled to 0-4 ºC and continuously bubbled with carbogen. This part

of the dissection was usually completed within a minute.

Parasagittal hippocampal slices (350 μm) were then obtained according to the guidelines provided by

previous reports[41], while submerged in oxygenated ice-cold cutting solution, using Leica VT1000S

vibratome. Brain slices were then transferred to the incubation solution (see Solution composition) in

an incubation chamber, maintained at 34 ºC using a water-bath. Slices were placed according to the

hemisphere maintaining the order in which they were obtained. The incubation solution was pre-

bubbled with carbogen which was continued throughout the incubation period.

After 15 minutes of incubation, the incubation chamber was transferred to room temperature (~ 24

ºC), continuing the carbogen bubbling. Electrophysiology recordings were started after 1-hour

recovery period from the end of this incubation.

Solution composition:

The following solutions were used for the electrophysiology experiments.

(all salts from Sigma Aldrich).

Sucrose based Artificial Cerebrospinal Fluid (sACSF):

The solution used for acute slicing procedure contained (in mM): Sucrose (230), KCl (2.5),

$MgCl_2.6H_2O$ (7), $CaCl_2.2H_2O$ (0.5), $NaHCO_3$ (25), NaH_2PO_4 (1.25), Glucose (10), Sodium Pyruvate

(3). pH 7.4, osmolarity $\sim 290 - 330$ milliosmoles.

Incubation Solution:

The slices were incubated in an incubation solution containing (in mM): NaCl (125), KCl (3),

$MgCl_2.6H_2O$ (1.5), $CaCl_2.2H_2O$ (2), $NaHCO_3$ (25), NaH_2PO_4 (1.25), Glucose (10), Sodium Pyruvate

(1). pH 7.4, osmolarity $\sim 290 - 310$ milliosmoles.

Artificial CerebroSpinal Fluid (nACSF):

For electrophysiology recordings, the slices were transferred to the nACSF containing (in mM):

NaCl (125), KCl (3), $MgCl_2.6H_2O$ (1), $CaCl_2.2H_2O$ (2), $NaHCO_3$ (25), NaH_2PO_4 (1.25), and Glucose

(10); pH 7.4; osmolarity $\sim 290 - 310$ milliosmoles.

Internal Solution:

The patch pipettes were back filled with an internal solution consisting of (in mM):

Potassium gluconate (120), KCl (20), HEPES (10), Disodium phosphocreatine (10), MgATP (5),

Na_2GTP (0.5), EGTA (0.2). pH 7.4; Osmolarity: $\sim 290 - 310$ milliosmoles.

Pharmacological agents:

During experiments, these were perfused with nACSF when required.

Synaptic blockers:

CNQX 10 μM, (+)bicuculline 10 μM, picrotoxin 10 μM, D,L-AP5 50 μM, CGP55845 5 μM

(Abcam). HCN blocker: ZD7288 25 μM (Tocris Bioscience).

Data acquisition and analyses:

Experiments were performed in nACSF at 34 ºC; temperature maintained with the help of a bath

chamber heater connected to an automatic temperature controller (Harvard Apparatus, USA). The

patch pipettes (1.5 mm O.D., 0.86 mm I.D.) were prepared using P-97 puller (Sutter Instruments,

USA) and fire polished to achieve a final access resistance of 3.5 - 5 MΩ. These were then back

filled for stellate cell recordings, with the internal solution.

Medial Entorhinal cortex layer II stellate cells were identified using infrared Dodt gradient contrast

video microscopy (Olympus BX51WI). These putative stellate cells were then patched in whole-cell

current-clamp configuration to record intrinsic electrophysiological properties and their modulation.

Somatic whole cell recordings in fast current-clamp mode were performed using DAGAN-BVC

700A amplifier, (Dagan Corporation, USA), Digidata 1440A Digitizer (Molecular Devices, USA),

and WinWCP software package (Strathclyde Electrophysiology Software, UK). The signals were

filtered at 5 kHz and stored on disk at > 20 kHz sampling frequency. Series resistance (< 25 MΩ)

was fully compensated in the current clamp mode. Series resistance was monitored and compensated

online using the bridge-balance circuit of the amplifier.

The following parameters i.e., resting membrane potential (RMP), input resistance (R_{in}) and series

resistance (R_s) were regularly monitored during the electrophysiological recordings. Recordings in

which the series resistance did not change > 5 MΩ throughout the duration of the experiment were

included for analysis. The stellate cells had their break-in RMP of ~ -62 - -65 mV. Unless otherwise

stated, experiments were performed at the initial resting membrane potential of the cell. Cells

showing RMP depolarized than -60 mV during the recordings were discarded from the analyses.

The system for the dynamic clamp experiments consisted of the Real-time Experiment Interface

(RTXI) (version 2.0-rc3, http://www.rtxi.org/) installed on a personal computer, Dagan BVC 700A

amplifier and PCI-6221 multi-function data acquisition (DAQ) board (National Instruments, USA),

with a BNC-2090A coaxial cable interface.

Dynamic clamp signals were filtered at 5 kHz and sampled at 10 kHz.

Mimicking in-vivo states

After recording the basic neuronal parameters in current clamp, the recording mode was switched to

the dynamic clamp.

The fluctuating synaptic conductance (Gfluct) module in the dynamic clamp (adapted from Destexhe

et. al., 2001[31] and Gfluct.mod file (ModelDB Accession: 8115)), was used to generate in-vivo like

background synaptic activity.

The Default Gfluct parameters

The mean excitatory conductance: $g\_e0 = 0.03$ µS, The mean inhibitory conductance: $g\_i0 = 0.06$

µS, Standard deviation of the excitatory conductance: std_e = 0.01 µS, Standard deviation of the

inhibitory conductance: std_i = 0.02 µS, Time constant for the excitatory conductances: Tau_e = 10

ms, Time constant for the inhibitory conductances: Tau_i = 10 ms,

Excitatory reversal potential: e_rev = 0 mV, Inhibitory reversal potential: i_rev = -75 mV.

The voltage responses and the applied current were recorded for 8-10 trials of ~10 sec. each.

This duration was increased when the slower synaptic conductances were used, to account for the

slower firing rate and to sample approximately the same number of spikes.

The changes in basic electrophysiological properties were monitored periodically. The changes in

series resistance were monitored and adjusted for in between the trials.

Experiments to test the role of input statistics

In a set of experiments designed to test the effects of varying mean and SD of excitation,

the SD of the excitatory conductance was varied from 0.002 µS to 0.02 µS in steps of ~0.005 µS,

while holding the mean unchanged at the default value. Then, the mean of the excitatory

conductance was varied from 0.02 µS to 0.04 µS in steps of 0.005 µS, while holding the SD

unchanged at the default value.

To test the role of synaptic kinetics, the time constants of excitatory and inhibitory synapses were

changed from 3-5 ms, 10 ms, 50 ms, 100 ms and 200 ms; keeping rest of the parameters default.

These values are selected considering the time constants of the synapses observed in-vivo, and those

used previously for the stellate cells [26,31].

In a small subset of experiments, extreme values of synaptic time constants such as ~ 0 or 500 –

1000 ms were used to confirm the mechanistic interpretations.

Experiments to test the role of I_h

To test the role of HCN current (I_h), ZD7288 was used as HCN channel blocker.

After recording all the control traces, 25 µM of ZD7288 was bath perfused. The test recordings were

started ~ 10 min. after starting this perfusion, and after ensuring a complete HCN block via the

electrophysiological signatures.

Data Analyses

Acquired electrophysiological data were analyzed using Igor Pro 6 (Wave Matrix, USA), Matlab

(The MathWorks, Inc.), Python programming language (Python Software Foundation), and Clampfit

(Molecular Devices, USA).

The input resistance was measured at the steady state of voltage deflection.

Estimation of signal gain

The neuronal voltage response was analysed in two different ways to estimate the signal gain.

In the first case, the collective voltage trace was analysed in the time and frequency domain.

For the further analysis, however, a vector of smoothly varying instantaneous firing rate as a function

of time was constructed from the actual voltage response (**Supplementary Figure 3**).

To calculate the signal gain, a ratio of the Fourier transform of the response and the Fourier

transform of the stimulus (applied current) was calculated (Analysis done in Matlab). The gain

function thus obtained was filtered using a Gaussian window and smoothened using a moving

average. The window width was adjusted so as to achieve a noise free trace, without compromising

on the signal information. On average, a window of 20 X-axis data points was used, corresponding to

~ 1.5 Hz.

Analysis of underlying theta oscillations and slow synaptic ramps

To compare the changes selective to the theta frequency range, the output voltage traces were band-

pass filtered using a 4-15 Hz FIR filter. Similarly, to analyze the slowly varying ramps, the output

voltage traces were low-pass filtered using a 3 Hz FIR filter.

Estimation of spike phases

For estimating the distribution of spike phases, the theta and ramp signals were used to determine

their peak times (corresponding to the positive peak), trough times (corresponding to the negative

peak), and zero-times (all time points where the signal crosses zero: The mean of the mean

subtracted, normalized signal).

Thus, three zero-points constituted one oscillatory cycle. Phases from 0-360 were then assigned to

each cycle. A phase vector corresponding to the original voltage trace could be thus obtained, which

allowed to compute the phase corresponding to each particular spike.

The mean, median, mode and variance of spike phases were then computed from a histogram of

pulled spike phase values.

Analysis of bursts

To study the percentage of spikes occurring as bursts, spikes occurring in 50-100 Hz bursts were

considered as a single spike, and spike time of only the first spike in the burst was considered. The

number of spikes and the firing rate was then recalculated.

Computational model

A single compartment model of MEC layer-II stellate cell was built in NEURON simulation

environment (Hines and Carnevale, 1997)[42], with parameters adjusted to match the observed

electrophysiological responses of the Stellate cells.

Fluctuating conductances

The in-vivo like fluctuating synapses were modelled according to the Gfuct.mod input regime

already discussed under "Mimicking in-vivo states".

Voltage gated Na$^+$ and K$^+$ channels

Adapted from a computational model by Destexhe et. al., 2001[31].

ModelDB Accession:8115

HCN channels

Adapted from Christoph Schmidt-Hieber and Häusser, 2013[22].

ModelDB Accession:150239

Persistent Na$^+$ channels

By Uebachs et al., 2010[43].

Assumes a non-inactivating conductance.

ModelDB Accession:125152

K$_{AHP}$ channels

Adapted from Migliore, Cook, Jaffe, Turner, & Johnston, 1995[44].

ModelDB Accession: 3263.

L-type Ca^{++} channels

Voltage gated high threshold activated calcium channel, adapted from Migliore, Cannia, Lytton,

Markram, & Hines, 2006[45].

ModelDB Accession: 64229

Calcium handling mechanism

Models the decay of the internal calcium concentration due to calcium currents and pumps.

Adapted from Destexhe, Contreras, Steriade, Sejnowski, & Huguenard, 1996[46].

ModelDB Accession: 17663

Statistical Analysis

The tests used for hypothesis testing and calculating the p-values are described with the individual

results.

Typically, student's paired t-test, Kruskal-Wallis test, Analysis of covariance (ANCOVA), and F-

statistics were used as appropriate.

The statistical analysis was carried out using Matlab, MS-Excel and the Python programming

language.

41.   Pastoll, H., White, M. & Nolan, M. Preparation of parasagittal slices for the investigation of dorsal-ventral organization of the rodent medial entorhinal cortex. *J. Vis. Exp.* **e3802,** 1–9 (2012).

42.   Hines, M. L. & Carnevale, N. T. The NEURON simulation environment. *Neural Comput.* **9,** 1179–209 (1997).

43.   Uebachs, M. *et al.* Efficacy Loss of the Anticonvulsant Carbamazepine in Mice Lacking

Sodium Channel Subunits via Paradoxical Effects on Persistent Sodium Currents. *J. Neurosci.* **30,** 8489–8501 (2010).

44.   Migliore, M., Cook, E. P., Jaffe, D. B., Turner, D. A. & Johnston, D. Computer simulations of morphologically reconstructed CA3 hippocampal neurons. *J. Neurophysiol.* **73,** 1157–1168 (1995).

45.   Migliore, M., Cannia, C., Lytton, W. W., Markram, H. & Hines, M. L. Parallel network simulations with NEURON. *J. Comput. Neurosci.* **21,** 119–129 (2006).

46.   Destexhe, A., Contreras, D., Steriade, M., Sejnowski, T. J. & Huguenard, J. R. In vivo, in vitro, and computational analysis of dendritic calcium currents in thalamic reticular neurons. *J. Neurosci.* **16,** 169–85 (1996).