Simplified neural encoding of social communication reflects lifestyle

K.M. Allen[1] & G. Marsat[1]

[1]Department of Biology, West Virginia University, Morgantown, WV 26505

Corresponding Author:

G. Marsat

Dept. Biology

West Virginia University

53 Campus Drive

Morgantown, WV 26505

Email: gary.marsat@mail.wvu.edu

Keywords: bursting, electrosensory, neural code, detection, discrimination, chirps

Acknowledgments: We thank G. Troy smith for discussions about this project, data on chirp properties and feedback on the manuscript. Funding was provided by West Virginia University and the National Science Foundation grant IOS-1557846.

Conflict of interest statement: The authors declare no competing financial interests.

ABSTRACT

As signal production changes through speciation, the sensory systems that receive these
signals must also adapt to extract the most relevant information effectively. In a species of
weakly electric fish, *Apteronotus albifrons* we examine the unique neurophysiological properties
that support the encoding of electrosensory communication signals that the animal would
encounter in social exchanges. We compare our findings to known coding properties of the
closely related species, *Apteronotus leptorhynchus*, to establish how these animals differ in their
ability to encode their distinctive communication signals. While there are many similarities
between these two species, we find notable differences leading to relatively poor coding of the
details of the chirp structure. As a result, small differences in chirp properties are poorly resolved
by the nervous system. We performed behavioral tests to relate *A. albifrons* chirp coding
strategies to its use of chirps during social encounters. Our results suggest that *A. albifrons* do
not exchange frequent chirps in non-breeding condition. These findings parallel the mediocre
chirp coding accuracy in that they both point to the sparse reliance on chirps in social
interactions. Therefore, our study suggests that neural coding strategies in the central nervous
system vary across species in a way that parallels the behavioral use of the sensory signals.

INTRODUCTION

Animals interact in complex sensory environments constraining the efficiency of information transfer. Potential limiting factors include environmental noise (Brumm and Slabbekoorn, 2005; Wiley and Richards, 1982), limitations of the transmission medium (Wiley and Richards, 1978) or social group size (Aubin and Jouventin, 2002). Optimization of the sensory system for any one type of signal may result in a trade-off between signal coding efficiency and a loss of sensitivity to a more diverse range of signal types. Therefore, efficiency in processing one type of signal must be balanced with the need also to encode other relevant signals. Thus, sensory systems might enhance or relax accuracy in encoding a signal depending of the ethological importance of the different aspects of that signal.

Mapping sensory tuning and deciphering information content available from neural codes are classic studies in neuroethology, with numerous examples of sender and receiver matching observed across many groups, including songbirds (Brumm and Slabbekoorn, 2005), anurans (Schul and Bush, 2002), and insects (Neuhofer et al., 2008). The majority of this work pertains specifically to sensory tuning and call matching at the periphery, but there is comparatively little research exploring adaptation within the brain as a result of sender-receiver matching. Even in drosophila, where coding of courtship song has been examined in high level auditory processing centers, the role of sender-receiver matching between species with divergent song patterns is still unclear (Tootoonian et al., 2012). This body of literature typically highlights the features that enhance the coding of species-specific signals but rarely identifies instances where coding efficiency is relaxed. Using a comparative approach, we aim to identify species-specific variations in sensory coding properties of central neurons and link them to the behavioral use of the signals.

Weakly electric fish are ideal for examining how signal production and signal reception coevolve and diversify. Apteronotid species share a common mode of communication, the modification of their electric organ discharge (EOD), but the detailed structure of their communication signals are highly diverse (Dunlap et al., 1998; Turner et al., 2007). Signal reception could also be influenced by many socially relevant factors such as EOD waveform shape (Petzold et al., 2016), chirp features (Benda et al., 2006), signal structure (Marsat and Maler, 2012; Marsat et al., 2009; Marsat et al., 2012) and social structure (Stamper et al., 2010). Chirps specifically can vary dramatically in specific properties such as duration, frequency or shape between even closely related species (Dunlap et al., 1998; Turner et al., 2007; Zakon et al., 2002; Zupanc and Maler, 1993). The sensory system of apteronotids could have similar coding properties across species and be generic enough to process these communication signals efficiently despite differences in their structure and use between species. Alternatively, differences in processing of these signals could reflect adaptations of the sensory system to varying signal structures and behavioral use.

In wave-type fish, individual EOD frequency is particularly influential on chirp reception. Fish in this group perceive ongoing amplitude modulations (AM beat) that are the product of two fish with different EOD frequencies interacting at close range (Bastian, 1981). Chirping is a brief shift in EOD frequency that creates a modulation of the beat frequency (Hagedorn and Heiligenberg, 1985; Zupanc and Maler, 1993). In species with sexually dimorphic EODs, low frequency beats, the result of fish with similar EOD frequencies interacting, are often typical of agnostic encounters between fish of similar sex and size. Higher

frequencies are more typical of encounters between fish of opposite sexes or with large
differences in body size. *A. leptorhynchus* produce Type 1 (big) chirps most often in high
frequency beat contexts (Hagedorn and Heiligenberg, 1985; Hupé and Lewis, 2008), while low
frequency interactions elicit the production of frequent Type 2 (small) chirps (Hupé & Lewis,
2008). Chirp coding has been previously well characterized in both *Apteronotus leptorhynchus*
and *Eigenmannia viscerens.* In both species, chirps cause significant changes in the synchrony of
electroreceptor firing, either increasing, or decreasing synchronicity depending on chirp type and
beat frequency (Stöckl et al., 2014; Walz et al., 2014). The two categories of signals described
above also produce different neural responses in the electrosensory lateral line lobe (ELL), the
primary sensory area. Small chirps on low frequency beats cause a synchronized and stereotyped
bursting response among the pyramidal cells of the ELL. Due to the encoding strategy and the
structure of the signal itself, small variation in these chirps cannot be discriminated (Allen and
Marsat, 2018; Marsat et al., 2009). Big and small chirps on high frequency beat lead to
heterogeneous and graded responses among pyramidal cells and variation in the signals are
accurately discriminated (Allen & Marsat, 2018; Marsat & Maler, 2010). Chirp production in *A.*
albifrons is similar, but the most notable difference between these species' chirps is duration; *A.*
leptorhynchus chirps are typically tens of milliseconds long, whereas *A. albifrons* chirps are
generally well over 100 milliseconds long (Dunlap et al., 1998; Turner et al., 2007; Zupanc and
Maler, 1993). Characterization of frequency tuning in the primary sensory area of *A. albifrons*
show differences from *A. leptorhynchus* that may be an adaptation for the coding of these
particularly long chirps (Martinez et al., 2016)

In this study, we examine the coding of conspecific social signals and the underlying
basic neural properties to understand if, and how, the sensory system is adapted to the specific
characteristics of the communication system of *A. albifrons*. Additionally, we examine the
behavior of chirp production to help understand how the behavioral use of the signals, rather than
just their structure, could influence the way they are processed. We compare our findings to the
well-studied behavior and physiology of the closely related *A. leptorhynchus* to identify specific
neurophysiological adaptations that reflect differences in the structure and behavioral use of
chirps in these two species.

RESULTS

Diversity in conspecific chirp responses

In multiple gymnotid species the lateral segment (LS) of the ELL serves as the primary location for encoding of communication and social signals (Marsat et al., 2009; Metzner, 1999; Metzner and Juranek, 1997), thus we targeted our recordings to pyramidal cells in that segment. To characterize the pattern of responses of *A. albifrons* pyramidal cells we played a series of chirps mimicking the natural range of reported *A. albifrons* chirps. Additionally, for comparison we used a small number of chirps with properties more typical of *A. leptorhynchus* (Dunlap et al., 1998; Zupanc and Maler, 1993). Detailed descriptions of chirp properties used are located in Table 1. In addition to playing chirps with diverse properties, we also varied the frequency of the beat, presenting chirps on both low (10 Hz) and high (100 Hz) frequency signals.

Figure 1 displays a representative selection of the diversity seen in chirp responses for both ON-type and OFF-type pyramidal cells. Qualitatively, responses appear to be highly heterogeneous with variability between inhibition, excitation, and desynchronization. Some patterns are in line with expectations from *A. leptorhynchus* coding strategies. On high frequency beats in particular (Fig 1A) we see a graded increase in firing rate in OFF-cell while ON-cell are inhibited during the chirp similar to responses of *A. leptorhynchus* pyramidal cells. On low frequency beats (Fig 1B), the responses also consisted of variable increses and decreases in firing rate and we did not observe synchronized burst firing across the population of pyramidal as is present in *A. leptorhynchus*' responses to small chirps on low frequency beats (Marsat and Maler, 2010; Marsat et al., 2009). Therefore, all chirps appear to be coded primarily through increases in firing among OFF-cells, and inhibition and desynchronization of ON-cells. Since *A. leptorhynchus* uses two different coding strategies to encode different categories of signal and support different perceptual abilities (discrimination vs. detection only) but *A. albifrons* uses the same coding patterns for all signals, we next quantify how well the neural responses could support detection and discrimination of chirps.

Detection of chirps varies with beat frequency

To quantify the ability of LS neurons to signal chirp occurrence (i.e. detection) we created ROC curves to determine the ability of an ideal observer to distinguish chirp responses from beat responses based on firing patterns (i.e. spike trains metric distances; see Methods for details). The results quantify the proportion of error that an ideal observe would make as a function of the number of neurons it monitors. An error of .5 would indicate chance level performance, while zero indicates perfect detection.

ON-Cells can efficiently detect all chirps to a high level of accuracy with about 8 neurons, comparable to *A. leptorhynchus* (Marsat and Maler, 2010) (Fig 2A). However, this level of accuracy only holds for chirps on the 10 Hz beat. ON-cell performance on 100 Hz is extremely poor, even with high numbers of spike trains included in the analysis (Fig 2B). OFF-cells are able to detect chirp occurrence on low frequency beats for all chirp types, although less efficiently than ON-cells (Fig 2C). On 100 Hz OFF-cells can detect the longest, most intense chirps, but perform poorly detecting smaller chirps (Fig 2D). Therefore, while chirps on low frequencies are reliably detected, detection sensitivity is poor in high frequency contexts.

Discrimination between chirps also varies

We assessed the amount of information carried by the response pattern about chirp
properties that could support the discrimination of chirp variants. This analysis is similar to that
used for chirp detection, but rather than comparing responses of chirps to beats, we compare
responses between chirps. Figure 3 shows discrimination ability for chirps grouped by size (See
Table 1; Small chirps: 5, 6, 7, 8; Big chirps: 1, 2, 3, 4, 9, 10) for both ON and OFF-cells on high
and low beat frequencies.

Chirps of all types are more easily discriminable when presented on 10Hz beats rather
than on 100Hz beats (Fig 3). On low frequencies, the all chirps are well discriminated by both
ON and OFF cells. Performance for chirps on high frequency beats was more varied (Fig 3B);
accurate discrimination was achieved only for chirps with big difference in properties (Fig 3B
and Fig S1) and both ON and OFF cell response allows similar discrimination accuracy. These
results are unexpected considering that *A. leptorhynchus* chirps on high frequency beats can be
discriminated well using as few as six neurons, and, conversely,exhibit poor discrimination
coding on low frequencies (Marsat and Maler, 2010) where *A. albifrons* performs best.
Furthermore, we do not observe an asymmetry in coding accuracy between ON and OFF cells as
observed in *A. leptorhynchus*.

When looking at which chirps are well discriminated, chirp duration and the steepness of
the frequency rise seem to be the most discriminable features, while total frequency increase and
number of peaks are less influential on coding (Fig S1). However, discriminating the most easily
separated chirps is still prone to error, even when recruiting up to 17 neurons. These data indicate
that while qualitative observations would suggest that chirp coding is similar between *A.*
albifrons and *A. leptorhynchus*, there are quantitative differences in the information content
extracted from chirps within the electrosensory system. To determine which aspects of the neural
responses could be responsible for these surprising coding differences, we characterized a wide
variety of response properties using an assortment of stimulation protocols.

Frequency tuning and information coding

Encoding amplitude modulations (AM) in stimuli is crucial for the recognition of social
signals. As shown above, *A. albifrons* neurons respond variably to chirps, which consist of both
high frequency AM signals and the low frequency changes in the contrast of the AM (i.e the
envelope). We asked whether the accuracy of detection and discrimination of chirps by *A.*
albifrons ELL neurons reflects species-specific tuning properties. Communication signals cause
spatially diffuse stimulation and we simulate this configuration using a large dipole (see
methods) that drives both the feedforward and feedback pathways. To separate the effects of
feedback from the tuning of the feed forward circuit we also stimulated only the receptive field
of each cell with a small local dipole. (Bastian, 1986).

In response to simple sine waves, *A. albifrons* exhibit the highest degree of coding
fidelity at low frequencies. Firing rate for each sine cycle peaks at 5Hz for all cell types and
stimulation configurations (Fig 4A). Maximum phase locking also peaks at low frequencies (Fig
4B). These values closely match previously reported values (Martinez et al., 2016). These peak
frequencies are lower than those reported for *A. leptorhynchus*, especially for ON-cells, which
exhibit broad- to high- frequency tuning in the LS (Krahe et al., 2008; Fig S2). Temporal coding
accuracy is conveniently quantified using random noise stimuli and information theory (Borst

and Theunissen, 1999). Lower-bound coherence reflects the amount of information encoded linearly whereas upper bound coherence takes in account both linear and non-linear aspects of the response (Fig 4C). All coherence curves peak at similar frequencies in the 5-20 Hz range (Wilcox Rank Sum, p=.19). However, OFF-cells are clearly low-pass, and exhibit a sharper decline in coherence to higher frequencies, while ON-cells exhibit a broader lower-bound coherence.

The movement of fish as well as the amplitude changes caused by chirps create low frequency changes in AM contrast, or envelopes (Stamper et al., 2013). During chirps, the AM will be high frequency (tens to hundreds of Hz above the beat frequency) whereas the envelope of the chirp is low frequency (e.g. 100 ms chirp will lead to a ~ 10Hz envelope). Therefore, the coding of chirps' low frequency content must be investigated using envelope stimuli. We probed envelope coding using stimuli consisting of RAMs with AM frequencies between 40Hz and 60 Hz, containing envelope frequencies of 0-20 Hz (Middleton et al., 2006). Although pyramidal cells do encode the envelope of these stimuli (Fig 4D), the coding accuracy is low compared with the envelope coding observed in *A. leptorhynchus* (Chacron, 2006; Middleton et al., 2006; Fig S2). This poor envelope coding, particularly for OFF-cells in response to global stimuli, may help to explain the poor chirp discrimination we observe.

Burst Firing and Chirp Detection

As described in Marsat et al. (2009) burst firing serves an important role in *A. leptorhynchus* for the efficient detection of extremely short chirps. As qualitatively shown above in Figure 1, no conspecific chirps reliably produced a burst response in *A. albifrons*. This implies that *A. albifrons* may lack a dedicated code for detection of very brief chirp signals. In *A. leptorynchus* the coding of small chirps is directly related to beat frequency. On low frequencies, small chirps are shorter than the period of one beat cycle. As beat frequency increases and the period becomes shorter, small chirps begin to last longer than one cycle. This change in duration relative to beat period mediates how small chirps are coded (Walz et al., 2014). In *A. albifrons* all chirps are much longer than *A. leptorhynchus* small chirps, spanning more than one beat cycle even on low frequencies, which may eliminate the need for a feature detection code specifically for extremely short chirps. Thus, the observed lack of bursting may result from the change either in signal structure (duration relative to beat cycle) or from underlying changes to physiology and bursting capability of LS neurons.

To determine if this change in signal coding is a result of signal structure or underlying physiology, we stimulated *A. albifrons* fish with *A. leptorhynchus* chirps known to elicit a burst response in *A. leptorhynchus* (Marsat et al., 2009). We determined burst threshold ISI for each neuron by plotting ISI distribution of chirp and beat responses and manually selecting a threshold that best distinguished between the two (Martinez-Conde et al., 2002) in order to maximize our measure of chirp-specific bursting. The mean burst threshold was 8.0ms ±0.7ms (s.e), comparable to the burst thresholds determined for RAM analyses and in other reports (Ávila-Åkerberg et al., 2010; Chacron and Bastian, 2008; Marsat et al., 2009).The majority of neurons increased firing rate only slightly more in response to *A. leptorhynchus* chirps than to the beat. There was, however, a small population (n=5) of ON-cells that did reliably burst more in response to *A. leptorhynchus* small chirps than to the beat (Fig 5A, C). The shortest *A. albifrons* chirps are most similar to the *A. leptorhynchus* chirps that elicit bursts, but are still long enough

to span more than one beat cycle. Even the bursty neurons did not respond to the shortest *A.*
albifrons chirps with bursts (Fig 5B, D).

The low numbers of neurons that burst in response to *A. leptorhynchus* chirps suggests that there
are physiologic differences between these two species in regards to burst coding of
communication. We examined the differences between bursty and non-bursty neurons in more
detail. The subset of bursty neurons also tend to have broader AM tuning (Fig 5C). While most
ON-cells exhibited peak coherence at frequencies between 10-20Hz, these cells had peak
frequencies as high as 40-50Hz and exhibited extremely high coherence across the range of
stimulus frequencies. The remainder of the ON cells displayed the low-pass tuning described in
Martinez et al. (2016) therefore the coherence for ON cells displayed in Fig 4C are broader than
previously described because of this small subset of broadly tuned neurons. These data show that
while a subset of ELL neurons are capable of bursting in response to short, high frequency chirp
stimuli, they make up a small percentage of the overall ELL population and bursting does not
seem to play a role in conspecific chirp coding.
260
261

Feature Detection

Burst firing may not be a significant aspect of communication coding in *A. albifrons*, but
other uses for burst coding may be conserved. During spontaneous activity, we observed a
baseline firing rate of 13.54 Hz (±1.37 s.e.) with 17.01% (±2.55 s.e.) of spikes in bursts. Thus,
the pyramidal neurons of *A. albifrons* are able to burst although these *A. albifrons* LS neurons are
less prone to bursting than those of *A. leptorhynchus* (S2). In *A. leptorhynchus* burst firing is not
used solely for chirp coding, but also for detection of prey like stimuli (Gabbiani et al., 1996;
Oswald et al., 2004). We examined bursting in response to local RAM stimulation (Fig 6A) to
determine if bursting could serve similar prey detection functions in *A. albifrons*. The ISI
histogram of the responses clearly showed that the neurons burst to these stimuli (Fig 6B). The
proportion of spikes occurring in bursts was as high as 63.07% (±5.64 s.e.) for stimuli in the
local configuration (Fig 6C). The average stimulus waveform triggering burst vs single spikes
follow the pattern observed in *A. leptorhynchus*: slower AM for burst than for single spikes (Fig
6D). However, in response to RAM stimuli, unlike *A. leptorhynchus* there was not a large
difference in coding error between bursting and tonic spiking (ANOVA, p=.10) (Fig 6E). These
data suggest that while bursts encode low frequency stimuli in the LS of *A. albifrons,* the role of
bursting in coding for specific stimulus features is not clear.

Stimulus adaptation

As seen in the examples of conspecific chirp responses (Fig 1), pyramidal cells often
demonstrated a rapid adaptation to chirp stimuli. For example, the responses to chirp 9 or 4
embedded in high frequency beats (Fig 1) are stronger in the first half of the chirp but weaker in
the second half. This adaptation maybe hinder the accurate encoding of chirp properties since
two chirps with different length could elicit identical responses if they adapt shortly after chirp
onset. Therefore, we characterize adaptation rate using standard step-up and -down stimuli. Both
ON and OFF cells' responses decreased throughout the 100ms stimulus without plateauing in

sharp contrast *with A. leptorhynchus* responses to global stimuli (S2, Krahe et al., 2008 see their
figure 8C&F) that adapt within 40-50ms and then plateau.

Chirp production and behavior

Our physiology data suggest that while *A. albifrons* are able to detect and discriminate
chirps they might not be as efficient or accurate as *A. leptorhynchus*. These observations suggest
a behavioral difference in chirp usage. To test this hypothesis, we recorded electrical behavior
from pairs of freely swimming and interacting fish. Chirping behavior did occur but differed
from that of *A. leptorhynchus* in a number of ways. Primarily, overall rates of chirping are
dramatically lower than numbers reported from similar studies in *A. leptorhynchus* (Hupé and
Lewis, 2008; Zupanc et al., 2006). Over 28 trials, we recorded a sum of 133 chirps, with a mean
of 4.75 (±0.61) chirps per 5-minute trial. The maximum number of chirps observed in one trial
was 13. Due to the small number of observed chirps, we did not separate them into multiple
categories for analysis, although chirps of varying frequency increases and duration occurred.
Like *A. leptorhynchus*, per trial chirp count is correlated with the difference in EODf of
interacting fish. Smaller differences in EODf correspond to higher numbers of chirps (Fig 7A).
Unlike *A. leptorhynchus*, however, chirping does not appear to be sexually dimorphic. Animals
used in behavior experiments were not sacrificed to determine sex, but grouped by EODf into
high (>1100Hz) and low (<1100Hz) groups which can correspond to females and males
respectively in many populations of *A. albifrons* (Zakon and Dunlap, 1999). This allowed us to
compare chirp rates among higher or lower frequency individuals, as well as by large or small
differences in EODf. We observed no differences in chirp production between high or low
frequency groups (Fig 7B). Further, chirp rate does not vary by pairing type, nor by relative
EODf with each pair under our conditions (Fig 7B). These results replicate previous findings that
chirp frequency in this species is not sexually dimorphic (Dunlap et al., 1998).

Chirp timing plays an important role in mediating *A. leptorhynchus* interactions,
particularly during interactions involving echo response (Henninger, 2015; Hupé and Lewis,
2008; Zupanc et al., 2006), a behavior where one fish quickly responds to the chirp of another
fish. To determine if chirp timing plays a similar role in *A. albifrons* interactions, we analyzed
inter-chirp intervals for all trials in which both fish chirped. The resulting distribution indicates
chirp latencies much longer than are typical of *A. leptorhynchus* echo responses (Fig 7C). Of all
recorded chirps, only six occurred within 2.5s of each other, making an echo response unlikely to
be an important factor in *A. albifrons* interactions. This lack of echoing, the long interchirp
intervals and the low rate of chirping in general, suggest that *A. albifrons* relies relatively little on
chirps to mediate social interaction (although see the discussion about courtship interactions).

DISCUSSION

We find that *A. albifrons* exhibit many notable differences in neurophysiology that correspond to communication strategies particular to this species. Compared to the closely related *A. leptorhynchus*, *A. albifrons* exhibit low frequency tuning, corresponding to the low frequency envelopes produced by their long chirps. However, despite this increased sensitivity to low frequency signals, coding of chirp identity is surprisingly poor. This may be due to the usage of chirps in this species. Infrequent chirping and the lack of complex bouts of back-and-forth chirping may reduce the need to encode details about chirp properties and chirper identity. Therefore, less complex chirp coding may represent a relaxation rather than optimization of the sensory system for communication.

Low frequency tuning could be adaptive for chirp coding

Our results confirm that pyramidal cells in the LS of *A. albifrons* are low pass in contrast with the ON-cells of the *A. leptorhynchus*'s ELL (Krahe et al., 2008). This difference parallels the much slower time course of *A. albifrons* chirps. However the impact of this AM tuning on chirp coding depends on the way AMs and envelopes are processed in this system. Indeed, whereas the envelope of chirps are low frequency, the AM is high frequency. Therefor the low frequency tuning to AM is not automatically helpful and we found that the coding of low-frequency envelopes was relatively poor, particularly in OFF cells which are -in *A. leptorhynchus*- best at coding chirp envelopes. However, if envelope response is synthesized before the pyramidal cells (e.g. the electroreceptors as could be the case in *A. leptorhynchus* (Savard et al., 2011) although see low frequency tuning to AM could benefit chirp coding since the input to the pyramidal cell would thereby contain low-frequencies (Metzen et al., 2018). Nevertheless, we show that the neural response does not accurately reflect the chirp envelope and that envelope coding of decreases in amplitude of RAM envelope stimuli is poor. Our data replicate the findings of Martinez et al. (2016) that also show poor coding of envelope stimuli, with coherence values of approximately 0.1. The long-lasting adaptation process we observed further supports this result. It is possible that without the low frequency tuning, chirp and envelope coding would be worse and thus compensate for other properties that hinder envelope coding.

The role of burst coding

Bursts also often play an important role in coding specific features of communication signals (Creutzig et al., 2009; Fujimoto et al., 2011). This is particularly true for *A. leptorhynchus* in which bursting enhances detectability of small chirps on low frequency beats (Marsat et al., 2009). *A. leptorhynchus* small chirps are unusual in that, for low frequency beats, they span less that a full cycle of the beat. Consequently the same chirp can be perceived as a sharp decrease in amplitude, an increase or a mix of the two, depending on the phase of the beat at which the chirp starts. It may be because of this aspect of chirp structure, and its shortness, that the sensory system of *A. leptorhynchus* uses bursts to enhance detectability. *A. albifrons* is not subject to the same constrains: chirp perceived AM is largely independent of beat phase since chirps span several cycles of the beat and their long duration might make them more conspicuous (Petzold et al., 2016) .We showed that burst coding in the LS is different between

A.leptorhynchus and *A. albifrons* and we suggest that it might reflect their different role in
coding of communication signals.

Chirp coding and behavior Our analysis presents a result in stark contrast with the coding
strategy observed in *A. leptorhynchus*: all chirps are coded with graded increases and decreases
in firing rate containing some information about chirp properties but, for high frequency beats,
coding accuracy is ineffective at supporting both chirp detection and discrimination. Our
behavioral data might shed some light on this apparent inefficiency at coding chirps, in particular
when the beat is high frequency. We showed that *A. albifrons* seldom uses chirp to meditate dyad
interactions. Furthermore we show that there a tendency (weak but significant) to chirp even less
when the beat frequency is higher. This is supported by previous findings showing that chirp
production is more frequent in same-sex contexts involving low frequency beats (Kolodziejski et
al., 2007) therefor reiterating the relevance of chirp coding on low-frequency beats. These
behavioral results suggest that chirp exchange is not central in mediating these interactions since
they chirp less than once a minute, especially in the context of high frequency beats. This is
unlike the complex chirp interactions observed in *A. leptorhynchus*, where chirps are
omnipresent and play a central role in various type of interactions (Hagedorn & Heiligenberg,
1985; Henninger, 2015; Hupé, 2012).

Our study did not test for the effects of neuromodulation on tuning and chirp coding.
Neuromodulation can change cell response properties as a result of behavioral state (Harris-
Warrick and Marder, 1991). Previous work in *A. leptorhynchus* shows that serotonin enhances
pyramidal cell excitability and responsiveness to small chirps on low frequency beats (Deemyad
et al., 2013). This work suggests a role for modulation of chirp coding in the context of same-sex
interactions, but there are likely similar effects related to other behavioral states. While we
worked on adult animals, we did not determine sex or breeding status, both of which have large
effects of the frequency and quality of chirps produced (Smith, 2013). It is likely that the effects
of neuromodulation due to behavioral state could affect the reception and encoding of these
chirps as well, altering sensitivity to chirps and possibly even coding accuracy in response to
behavioral need. This may particularly influence the coding of chirps on high frequency beats,
which we observed was surprisingly poor. This kind of interaction is more likely to occur in
breeding contexts, so it is possible that animals in breeding condition could be better able to
detect and discriminate these signals.

Trade-offs between specialization and generalization

Classical neuroethology dictates that the mode of signal production and mode of signal
reception must evolve in synchrony so that senders and receivers never lose the ability to
exchange information (Bradbury et al., 2011). There are many examples of specialization of
particular aspects of sensory systems to accomplish a highly specialized tasks (Endler, 1992). In
the case of communication, sensory tuning for sender-receiver matching has been shown
repeatedly. However, the converse may also be true. Over-specialization may come at the cost of
reduced sensitivity to more general environmental signals. In such a case, it may be more
beneficial to favor sensory generalization over specialization in animals that engage in social
behaviors less often than their more gregarious relatives do. Indeed, there are several examples
of peripheral sender-receiver mismatching that may be explained by gains in sensitivity to prey
or predator signals to (Mason, 1991; Römer, 2016). Maintaining specificity for conspecific

communication may be costly both metabolically (Niven and Laughlin, 2008) and in regards to
detecting environmental stimuli apart from communication signals.

In *A. albifrons* we show a general match between signal characteristics, low frequency
chirp envelopes, and CNS sensitivity to low frequency signals, but a lack of complex coding that
would allow for efficient discrimination of chirp identity in all contexts. For this species,
investing fewer resources into the coding of social signals may allow the electrosensory system
to focus more broadly. This low frequency tuning may be particularly adaptive for prey location
and navigation, both tasks that the electrosensory system must perform, and both tasks that
require coding of low frequencies. In such a case, our data argue for a match between neural
coding and behavior via a relaxation of sender-receiver matching.

METHODS

Animals

All animals were housed according to WVU IACUC standards, protocol 151200009.2. Wild-caught *Apteronotus albifrons* and *Apteronotus leptorhynchus* were obtained from commercial fish suppliers and housed in small groups (1-10 fish per tank). Tank conductivity was maintained at 200-500 µS. Sex was not confirmed, but adult animals with a wide range of EOD frequencies (600-1300Hz) were used for all experiments, indicating that we likely had multiple animals of both sexes.

Electrophysiology

Surgical techniques were identical to those previously described in (Marsat and Maler, 2010; Marsat et al., 2009). Cells of the LS of the ELL were targeted. *A. albifrons* brain anatomy is very similar to that of *A. leptorhynchus*, so major landmark blood vessels described in (Maler et al., 1991) and electrode depth served as an adequate guide to locate LS pyramidal cells (see Histology). *In vivo* recordings were made via metal filled extracellular electrodes (Frank and Becker, 1964) and amplified with an A-M Systems amplifier (Model 1700). Data were recorded (Axon Digidata 1500 and Axoscope software) at a 20kHz sampling rate. ON and OFF cells were identified using known response properties, particularly responses to sinusoidal stimulation (Saunders and Bastian, 1984).

Histology

In N=9 fish, correct electrode placement was confirmed by injection of Dextran Texas Red dye (Thermo Fisher, catalogue # D1829) at recording site using double barreled electrodes, similar to methods described in (Krahe et al., 2008). After recording, dye was pressure injected with a PicoPump (WPI, PV820). Animals were then anaesthetized and respirated with a solution of Tricaine-S (.5g/L, Western Chemicals) and perfused with 4% paraformaldehyde (Electron Microscopy Supply, # 15712) in PBS. Brains were postfixed overnight, sectioned (150 µm), and counterstained with Syto59 nuclear stain (Thermo Fisher, # S11341), which allowed for clear distinction between ELL segments. In all marked sections, correct placement within the LS was observed (S3).

Stimuli

All stimuli were created in Matlab (Mathworks, Inc.) and sampled at 20 kHz. Stimulation was provided by a direct modulation of a carrier frequency matching the fish's own rather than by mimicking a second EOD, based on methods commonly used in similar experiments (Benda et al., 2005; Krahe et al., 2008; Marsat et al., 2009). Baseline EOD was recorded via electrodes near the head and tail of the fish. Each EOD cycle triggered a sine wave generator (Rigol DG1022A) to generate one cycle of a sine wave matched to the animal's own. This signal was then multiplied using a custom-built signal multiplier (courtesy of the Fortune Laboratory, New Jersey Institute of Technology) by the AM stimulus to create the desired modulation of the electric field. Stimuli were played through a stimulus isolator (A-M Systems, Model 2200) into the experimental tank via either two 30.5cm carbon electrodes arranged parallel to the fish's longitudinal axis (global stimulation) or two silver chloridized point electrodes 1 cm apart from each other positioned near the receptive field on the fish's skin (local stimulation). The stimulus

strength was adjusted to provide ~20% contrast (the difference between the maximum and
minimum of amplitude modulation divided by the baseline EOD).

Random amplitude modulation (RAM) stimuli consisted of 30 seconds of random noise
filtered using a Butterworth filter to be either low pass (0-20Hz), high pass (40-60Hz) or
broadband (0-60Hz). Each stimulus was played for three repetitions in both global and local
stimulation configurations. Sinusoidal amplitude modulation (SAM) stimuli were 2 second long
periods of regular sinusoids of 2, 5, 15, 30, 60, and 90 Hz with 2 seconds between each
frequency, repeated at least three times. Step stimulations were 100 ms long increases and
decreases in amplitude, attenuated to the fish's own signal strength as described above, repeated
for 30 seconds.

Chirp stimuli were created by using recorded EOD samples (courtesy of Dr. Troy Smith,
Electric Fish Signal Library) to create a template *A. albifrons* EOD shape. Chirps of varying
durations, frequency increases, and frequency rise/fall time (Table 1) were each embedded in this
template EOD, at a rate of 1chirp/second. For each 1Hz of frequency increase, there was an
associated .11% amplitude decrease, based on Dunlap et al. (1998). To this chirp EOD we added
a second EOD either 10Hz or 100Hz lower to create an AM envelope. This envelope was
extracted via spline interpolation and played using a carrier EOD as described above. Each chirp
stimulus was played for at least 30 seconds, up to 60 seconds. Due to time constraints and
recording stability, chirps were only played in the global configuration.

Data Analysis

For all analyses spike trains were first binarized into a sequence of 1's (spike) and 0's (no
spike) representing spike timings using a bin width of .5ms. All analyses described here were
performed on these binary sequences in Matlab. Additional analyses were as described
(ANOVA, Student's T Test, Wilcoxon rank sum) and performed in Matlab using the statistical
analysis toolbox.

Synchronization Coefficient

The strength of phase locking to SAM stimulation was calculated as $\frac{\sqrt{(\Sigma x_i)^2 + (\Sigma y_i)^2}}{n}$,
where n is the number of spikes in the analysis, and x and y are the cosine and sine of the
stimulus at which spike i occurs(Goldberg and Brown, 1969; Marsat and Pollack, 2004). Values
range from 0 to 1, with 1 being perfect precision in responding to a given phase of the sine cycle.

Coherence

Lower bound coherence is a measure of linear coding of the stimulus and is calculated by
comparing the spike train against the stimulus (Borst and Theunissen, 1999). The stimulus (S(t))
and the binarized neural response (R(t)) were expressed as variations around their respective
means (S'(t) and R'(t)). These were converted into frequency domain representations of the
stimulus (S'(f)) and responses (R'(f) using a fast Fourier Transformation. A linear filter for each
response (H_i (f)) was constructed from R_i(f) as: $H_i(f) = R'_i(f) * \frac{S'_i(f)}{R'_i(f)} * R'_i(f)$. (H_i (f)) was

converted back to the time domain using the inverse Fourier transform and the result H_i (t) was
convolved with R_i (t) to create an estimate of the stimulus, $esti_i$ (t). Noise, n_i (t), was
computed as $S_i(t) - esti_i(t)$. Signal-to-noise ratio, SNR_i (f), was computed as the power
spectrum of $esti_i$ (t) divided by that of n_i (t). Lower bound coherence presented is the average
SNR (f) from all repetitions (Marsat and Pollack, 2004).

Upper bound coherence measures the total information potentially coded in the response,
including linear and non-linear information. This information potential is measured by
comparing multiple responses of one neuron to each other to determine response reliability
(Borst and Theunissen, 1999). Again, frequency domain representations of the responses were
created (R(f)) and correlated then divided by an autocorrelation to yield coherence as : $Coh = $
$\sqrt{\langle R_i(f) * R_j(f)\rangle\langle R_j(f) * R_i(f)\rangle / \langle R_i(f) * R_i(f)\rangle\langle R_j(f) * R_j(f)\rangle}$. Pairwise response
correlations were performed for all repetitions for each neuron and averaged for an average
upper bound coherence ($\overline{Coh}$). Information was calculated as $I(f) = -\log_2(1 - \overline{Coh})$ (Borst
and Theunissen, 1999).

Burst detection

Bursts in RAM and chirp responses were determined by creating a histogram of all
interspike intervals (ISIs) in the response. Generally, there was an obvious bimodal, non-
Poission distribution of ISIs, allowing us to visually identify a threshold between burst and tonic
firing. Spikes in groups with ISIs below the threshold were classed as occurring in bursts, while
all remaining spikes were classed as tonic. This method is similar to that described in (Ávila-
Åkerberg et al., 2010)

Chirp Analysis

Analysis of chirps for detection and discrimination is based on Marsat and Maler (2010).
Our analysis accounts for both the firing rate as well as the temporal pattern of spikes to quantify
how similar or dissimilar spiking patterns are (van Rossum, 2001). For detection analysis, a
window around the chirp (R_c(t)) of length L (50, 105, or 205ms) was extracted from the filtered
spike train and compared to a window of beat of the same size (R_b(t)). Different window sizes
led to qualitatively similar results, and those using 205ms are shown. The responses were
convolved with an α filter, $f(t) = t^{-2.45t/\tau}$, with τ being the width of the function at half
maximum (3, 10, 30, and 100ms; 30ms shown) (Machens et al., 2003). Detection becomes more
accurate as a function of additional neurons contributing to the response, so we looked at
population responses by summing the responses of *n* neurons using the function created
population responses, in this case by averaging multiple spike trains using the function:
$PR_i(t) = \sum_{i*t}^{n} \frac{R_i(t)}{n}$. The result (PR$_i$(t)) represents a population of neurons presented with the
same stimulus and mimics a neuron integrating postsynaptic potentials with similar weights.
Distance (D$_{cb}$ or D$_{bb}$) was calculated for all sets of combined responses, PR$_c$(t) and PR$_b$(t),
creating an array of response distances for each comparison using the function:. $D_{cb} = $
$\frac{1}{L\sum_{t*O}^{L}[R_c(t)-R_b(t)]^2}$. The probability distributions of the values in these arrays (P(D$_{cb}$) or P(D$_{bb}$))
were used for analysis. Receiver operator characteristic curves were calculated by varying a
threshold distance (T) to separate chirp and beat responses. For each threshold the probability of
detection (PD) was calculated as the sum of (P(D$_{cb}$ > T)), and the probability of false alarm (PF)
as the sum of (P(D$_{bb}$< T). The error level for each threshold value is E=1/2PF +1/2(1-PD). The

values shown in Figure 3 are the minimum calculated values of E as increasing numbers of spike
trains are included in the calculation.

Discrimination analyses were similar to those for detection, but rather than comparing
chirp and beat responses, the distances between two different chirps were compared. Similar to
detection analysis, windows of chirp responses (R(t)) of length L (50,105, and 205ms) were used
for analysis and the results using 205ms are shown. The responses were convolved with an α
filter and population averaged as described above. Up to 200 random combinations of spike
trains from all recorded neurons were used for all comparisons as more become computationally
prohibitive without improving results. Responses to chirps against different chirps (x vs. y) were
compared as well as multiple responses to the same chirp (x vs. x). Distance (D_{xy} or D_{xx}) was
calculated for all sets of combined responses, $PR_x(t)$ and $PR_y(t)$, creating an array of response
distances for each comparison using the function: $D_{xy} = \frac{1}{L\sum_{t*O}^{L}[R_x(t)-R_y(t)]^2}$. Similarly to the
detection analysis, threshold values between distributions were varied. For each threshold value,
the probability of discrimination between chirps (PD) is calculated, rather than detection. The
sum of $P(D_{xy} > T)$ being the probability of discrimination(PD) and the sum of $P(D_{xx} > T)$ being
the probability of false discrimination (PF). The error level for each threshold value is $E = 1/2PF$
$+ 1/2(1 - PD)$. The error in discrimination reported in the figures are the minimum values of E.

Adaptation

Adaptation to stimuli was measured by using the Matlab Curve fitting toolbox to fit an
exponential curve to a plot of instantaneous firing rate for each neuron resulting in a time
constant τ. The portion of the response to use for fitting was determined by selecting the time of
peak firing rate and the following 500 ms.

Behavior

Twenty-eight behavior trials were conducted in a small tank (27x27x14cm) containing
water with conductivity, pH, and temperature matched to the home system, and one shelter tube.
The tank was enclosed to block ambient light, lit with infrared lights and all trials were recorded
via infrared camera (Logitech HD Pro Webcam C920). 14cm carbon rod electrodes placed
diagonally from each other in each corner of the tank recorded electrical activity, which was then
amplified (A-M Systems, Model 1700) and recorded using a computer sound card.

Stranger fish from different home tanks were selected semi-randomly. Defining physical
features (size, markings) and EODf were noted to avoid repeatedly testing the same pair. One
fish was selected and allowed to acclimate to the test tank for 20 minutes before the introduction
of the second fish. Recording began immediately upon introduction of the intruder fish.
Interactions were recorded for five minutes.

To detect chirps we used a custom Matlab script to create a spectrogram of the electrical
recordings to identify individuals and mark chirp times. Chirps were visually identified as >10Hz
abrupt frequency increases.

579
580
581

BIBLIOGRAPHY

Allen, K. M. and Marsat, G. (2018). Task-specific sensory coding strategies are matched to detection and discrimination performance. *J. Exp. Biol.*

Aubin, T. and Jouventin, P. (2002). How to vocally identify kin in a crowd: the penguin model. *Adv. Study Behav.* **31**, 243–277.

Ávila-Åkerberg, O., Krahe, R. and Chacron, M. J. (2010). Neural heterogeneities and stimulus properties affect burst coding in vivo. *Neuroscience* **168**, 300–313.

Bastian, J. (1981). II. The effects of moving objects and other electrical stimuli on the activities of two categories of posterior lateral line lobe cells in Apteronotus albifrons. *J. Comput. Physiol.* **144**, 481–494.

Bastian, J. (1986). Gain control in the electrosensory system: a role for the descending projections to the electrosensory lateral line lobe. *J. Comp. Physiol. A* **158**, 505–515.

Benda, J., Longtin, A. and Maler, L. (2005). Spike-frequency adaptation separates transient communication signals from background oscillations. *J. Neurosci.* **25**, 2312–21.

Benda, J., Longtin, A. and Maler, L. (2006). A synchronization-desynchronization code for natural communication signals. *Neuron* **52**, 347–58.

Borst, A. and Theunissen, F. E. (1999). Information theory and neural coding. *Nat. Neurosci.* **2**, 947–957.

Bradbury, J. W., Vehrencamp, S. L., Bradbury, J.W., and S. L. V., Bradbury, J. W. and Vehrencamp, S. L. (2011). *Principles of Animal Communication*. 2nd ed. Sunderland, Mass.: Sunderland: Sinauer Associates.

Brumm, H. and Slabbekoorn, H. (2005). Acoustic Communication in Noise. *Adv. Study Behav.*

Chacron, M. J. (2006). Nonlinear Information Processing in a Model Sensory System. *J. Neurophysiol.* **95**, 2933–2946.

Chacron, M. J. and Bastian, J. (2008). Population coding by electrosensory neurons. *J. Neurophysiol.* **99**, 1825–1835.

Creutzig, F., Wohlgemuth, S., Stumpner, A., Benda, J., Ronacher, B. and Herz, A. V. M. (2009). Timescale-Invariant Representation of Acoustic Communication Signals by a Bursting Neuron. *J. Neurosci.* **29**, 2575.

Deemyad, T., Metzen, M. G., Pan, Y. and Chacron, M. J. (2013). Serotonin selectively enhances perception and sensory neural responses to stimuli generated by same-sex conspecifics. *Proc. Natl. Acad. Sci. U. S. A.* **110**, 19609–14.

Dunlap, K. D., Thomas, P. and Zakon, H. H. (1998). Diversity of sexual dimorphism in electrocommunication signals and its androgen regulation in a genus of electric fish, Apteronotus. *J. Comp. Physiol. A Sensory, Neural, Behav. Physiol.* **183**, 77–86.

Endler, J. A. (1992). Signals, Signal Conditions, and the Direction of Evolution. *Am. Nat.* **139**,

S125–S153.

Frank, K. and Becker, M. (1964). Microelectrodes for recording and stimulation. In *Physical techniques in biological research*, .

Fujimoto, H., Hasegawa, T. and Watanabe, D. (2011). Neural Coding of Syntactic Structure in Learned Vocalizations in the Songbird. *J. Neurosci.* **31**, 10023.

Gabbiani, F., Metzner, W., Wessel, R. and Koch, C. (1996). From stimulus encoding to feature extraction in weakly electric fish. *Nature* **384**, 564–567.

Goldberg, J. M. and Brown, P. B. (1969). Response of binaural neurons of dog superior olivary complex to dichotic tonal stimuli: some physiological mechanisms of sound localization. *J. Neurophysiol.* **32**, 613–636.

Hagedorn, M. and Heiligenberg, W. (1985). Court and spark: electric signals in the courtship and mating of gymnotoid fish. *Anim. Behav.* **33**, 254–265.

Harris-Warrick, R. M. and Marder, E. (1991). Modulation of neural networks for behavior. *Annu. Rev. Neurosci.* **14**, 39–57.

Henninger, J. (2015). Social Interactions in Natural populations of weakly electric fish (Doctoral Dissertation).

Hupé, G. J. (2012). Electrocommunication in a Species of Weakly Electric Fish Apteronotus Leptorhynchus: Signal Patterning and Behaviour (Doctoral Dissertation).

Hupé, G. J. and Lewis, J. E. (2008). Electrocommunication signals in free swimming brown ghost knifefish, Apteronotus leptorhynchus. *J. Exp. Biol.* **211**, 1657–1667.

Kolodziejski, J. a, Sanford, S. E. and Smith, G. T. (2007). Stimulus frequency differentially affects chirping in two species of weakly electric fish: implications for the evolution of signal structure and function. *J. Exp. Biol.* **210**, 2501–2509.

Krahe, R., Bastian, J. and Chacron, M. J. (2008). Temporal processing across multiple topographic maps in the electrosensory system. *J. Neurophysiol.* **100**, 852–67.

Machens, C. K., Schütze, H., Franz, A., Kolesnikova, O., Stemmler, M. B., Ronacher, B. and Herz, A. V. M. (2003). Single auditory neurons rapidly discriminate conspecific communication signals. *Nat. Neurosci.* **6**, 341–342.

Maler, L., Sas, E., Johnston, S. and Ellis, W. (1991). An atlas of the brain of the electric fish Apteronotus leptorhynchus. *J. Chem. Neuroanat.* **4**, 1–38.

Marsat, G. and Maler, L. (2010). Neural heterogeneity and efficient population codes for communication signals. *J. Neurophysiol.* **104**, 2543–55.

Marsat, G. and Maler, L. (2012). Preparing for the unpredictable: adaptive feedback enhances the response to unexpected communication signals. *J. Neurophysiol.* **107**, 1241–6.

Marsat, G. and Pollack, G. S. (2004). Differential temporal coding of rhythmically diverse acoustic signals by a single interneuron. *J. Neurophysiol.* **92**, 939–48.

Marsat, G., Proville, R. D. and Maler, L. (2009). Transient signals trigger synchronous bursts

656 in an identified population of neurons. *J. Neurophysiol.* **102**, 714–23.

Marsat, G., Longtin, A. and Maler, L. (2012). Cellular and circuit properties supporting different sensory coding strategies in electric fish and other systems. *Curr. Opin. Neurobiol.* **22**, 686–692.

Martinez, D., Metzen, M. G. and Chacron, M. J. (2016). Electrosensory processing in Apteronotus albifrons: implications for general and specific neural coding strategies across wave-type weakly electric fish species. *J. Neurophysiol.* **116**, 2909–2921.

Martinez-Conde, S., Macknik, S. L. and Hubel, D. H. (2002). The function of bursts of spikes during visual fixation in the awake primate lateral geniculate nucleus and primary visual cortex. *Proc. Natl. Acad. Sci. U. S. A.* **99**, 13920–13925.

Mason, A. C. (1991). Hearing in a primitive ensiferan: the auditory system of Cyphoderris monstrosa (Orthoptera: Haglidae). *J. Comp. Physiol. A* **168**, 351–363.

Metzen, M. G., Huang, C. G. and Chacron, M. J. (2018). Descending pathways generate perception of and neural responses to weak sensory input. *PLOS Biol.* **16**, e2005239.

Metzner, W. (1999). Neural circuitry for communication and jamming avoidance in gymnotiform electric fish. *J. Exp. Biol.* **202**, 1365–1375.

Metzner, W. and Juranek, J. (1997). A sensory brain map for each behavior? *Proc. Natl. Acad. Sci.* **94**,.

Middleton, J. W., Longtin, A., Benda, J. and Maler, L. (2006). The cellular basis for parallel neural transmission of a high-frequency stimulus and its low-frequency envelope. *Proc. Natl. Acad. Sci. U. S. A.* **103**, 14596–601.

Neuhofer, D., Wohlgemuth, S., Stumpner, A. and Ronacher, B. (2008). Evolutionarily conserved coding properties of auditory neurons across grasshopper species. *Proc. R. Soc. B Biol. Sci.* **275**, 1965–1974.

Niven, J. E. and Laughlin, S. B. (2008). Energy limitation as a selective pressure on the evolution of sensory systems. *J. Exp. Biol.* **211**, 1792 LP-1804.

Oswald, A.-M. M., Chacron, M. J., Doiron, B., Bastian, J. and Maler, L. (2004). Parallel processing of sensory input by bursts and isolated spikes. *J. Neurosci.* **24**, 4351–62.

Petzold, J. M., Marsat, G. and Smith, G. T. (2016). Co-adaptation of electric organ discharges and chirps in South American ghost knifefishes (Apteronotidae). *J. Physiol.*

Römer, H. (2016). Matched Filters in Insect Audition: Tuning Curves and Beyond BT - The Ecology of Animal Senses: Matched Filters for Economical Sensing. In (ed. von der Emde, G.) and Warrant, E.), pp. 83–109. Cham: Springer International Publishing.

Saunders, J. and Bastian, J. (1984). The physiology and morphology of two types of electrosensory neurons in the weakly electric fish Apteronotus leptorhynchus. *J. Comp. Physiol. A* **154**, 199–209.

Savard, M., Krahe, R. and Chacron, M. J. (2011). Neural heterogeneities influence envelope and temporal coding at the sensory periphery. *Neuroscience* **172**, 270–284.

Schul, J. and Bush, S. L. (2002). Non-parallel coevolution of sender and receiver in the acoustic
communication system of treefrogs. *Proc. R. Soc. London. Ser. B Biol. Sci.* **269**, 1847 LP-
1852.

Smith, G. T. (2013). Evolution and hormonal regulation of sex differences in the
electrocommunication behavior of ghost knifefishes (Apteronotidae). *J. Exp. Biol.* **216**,
2421 LP-2433.

Stamper, S. A., Carrera-G, E., Tan, E. W., Fugère, V., Krahe, R. and Fortune, E. S. (2010).
Species differences in group size and electrosensory interference in weakly electric fishes:
Implications for electrosensory processing. *Behav. Brain Res.* **207**, 368–376.

Stamper, S. A., Fortune, E. S. and Chacron, M. J. (2013). Perception and coding of envelopes
in weakly electric fishes. *J. Exp. Biol.* **216**, 2393 LP-2402.

Stöckl, A., Sinz, F., Benda, J. and Grewe, J. (2014). Encoding of social signals in all three
electrosensory pathways of Eigenmannia virescens. *J. Neurophysiol.* **112**, 2076–2091.

Tootoonian, S., Coen, P., Kawai, R. and Murthy, M. (2012). Neural Representations of
Courtship Song in the *Drosophila*; Brain. *J. Neurosci.* **32**, 787 LP-798.

Turner, C. R., Derylo, M., de Santana, C. D., Alves-Gomes, J. a and Smith, G. T. (2007).
Phylogenetic comparative analysis of electric communication signals in ghost knifefishes
(Gymnotiformes: Apteronotidae). *J. Exp. Biology* **210**, 4104–4122.

van Rossum, M. C. (2001). A novel spike distance. *Neural Comput.* **13**, 751–763.

Walz, H., Grewe, J. and Benda, J. (2014). Static frequency tuning accounts for changes in
neural synchrony evoked by transient communication signals. *J. Neurophysiol.* **112**, 752–
65.

Wiley, R. H. and Richards, D. G. (1978). Behavioral Ecology and Sociobiology Physical
Constraints on Acoustic Communication in the Atmosphere: Implications for the Evolution
of Animal Vocalizations. *Behav. Ecol. Sociobiol* **3**, 69–94.

Wiley, R. H. and Richards, D. G. (1982). Adaptations for acoustic communication in birds:
sound transmission and signal detection. *Acoust. Commun. birds* **1**, 131–181.

Zakon, H. H. and Dunlap, K. D. (1999). Sex steroids and communication signals in electric
fish: a tale of two species. *Brain. Behav. Evol.* **54**, 61–9.

Zakon, H., Oestreich, J., Tallarovic, S. and Triefenbach, F. (2002). EOD modulations of
brown ghost electric fish: JARs, chirps, rises, and dips. *J. Physiol. Paris* **96**, 451–8.

Zupanc, G. K. H. and Maler, L. (1993). Evoked chirping in the weakly electric fish
Apteronotus leptorhynchus : a quantitative biophysical analysis. *Can. J. Zool.* **71**, 2301–
2310.

Zupanc, G. K. H., Sirbulescu, R. F., Nichols, A. and Ilies, I. (2006). Electric interactions
through chirping behavior in the weakly electric fish, Apteronotus leptorhynchus. *J. Comp.*
Physiol. A **192**, 159–173.

FIGURE LEGENDS

Figure 1: ELL Pyramidal cells respond to conspecific signals. A. Representative Raster plots of
chirp responses on a low frequency (10Hz) beat. AM stimulus is shown in black; OFF-cells are
shown in cyan boxes, ON-cells in red boxes. Three different ON-cells and three different OFF-
cells are shown. The neurons displayed are consistent throughout. B. Identical chirps presented
on high frequency (100Hz) beat. For a detailed description of all chirps used, see Table 1.

743
744

Figure 2: Detection efficiency is mediated by beat frequency. A. Detection of chirps on 10Hz
beat by ON-cells as a factor of neurons included in the analysis (n=17). ON-cells can reliably
detect the occurrence of all chirps. Detection error levels for individual chirp identities are shown
in gray. Red line indicates mean detection error for all chirps. B. ON-cell performance is worse
on 100Hz beats. C, D Mean OFF-cell performance (cyan, n=16) is also more efficient on a 10Hz
beat.

753
754
755

Figure 3: Discrimination of chirps on high frequency beats is poor. A. Discrimination for small
chirps (50-100Hz, 50-100ms, Chirps 5,6,7,8, right) and big chirps (200-350Hz, 100-200ms,
Chirps 1,2,3,4,9,10, left) on 10Hz beat. Mean ON-cell chirp discrimination shown in red, OFF-
cells in cyan, and discrimination for individual chirps shown in gray. B. Discrimination of small
chirps on a 100Hz beat is little better than chance for both ON (red) and OFF-cells (cyan).
Discrimination of big chirps varies with chirp identity, but is still poor.

Figure 4: Low frequency coding by pyramidal cells A. Sinusoidal stimulation indicates low
frequency tuning. Firing rate for both ON (red, n=19) and OFF (cyan, n=15) cells in both
stimulation configurations (global: pink, pale blue; local: red, cyan) peaks at 5Hz. Error bars
indicate standard error. B. Phase locking to sinusoids is also best at low frequencies. Maximum
phase locking is seen at 15Hz, with the exception of locally stimulated OFF-cells, which peak at
5Hz. C. Mean coherence to noise stimulation is also low-pass. ON-cell coherence is shown in
red, OFF-cell in cyan. The upper bound coherence measure (RR, solid line) is the response-
response autocorrelation between multiple presentations of the stimulus, while the lower bound
(SR, dashed line) is stimulus-response correlation. Shaded areas indicate standard error; darker
shading indicates local stimulation. Mean global lower bound maximums: ON-cells: 23.1Hz
($\pm$.86 s.e.); OFF-cells: 11.6Hz ($\pm$.75 s.e.), (Wilcoxon rank-sum test p=.04). D. OFF-cell coding
of low frequency envelopes is poor. Envelope responses to low frequency contrast changes (ER,
solid line) are also low tuned . Both ON and OFF cells exhibit peak envelope tuning at 10.10Hz
($\pm$1.52 s.e.) (Wilcoxon rank-sum test, p=.21). OFF-cells are noticeably poorer at coding
envelopes.

783
784
785

Figure 5: Coding of chirps by a small population of high firing neurons. A. The mean
instantaneous firing rates of ON-cells over the time course of chirp and beat stimuli. The
difference in peak firing rate indicates a small population (n=5, red) that bursts in response to *A.*
A. leptorhynchus small chirps (Beat Responses, dashed lines: Peak FR 77.67 HZ +- 7.11; burst
fraction 0.38 ± 0.02; Chirp responses, solid lines: Peak FR 159.57 Hz +- 8.68; burst fraction
0.76± 0.02, Wilcoxon ranked sum test (p<<.001). The majority of the ON-cell population (n=13,
black) only showed a modest increase in bursting (Beat Response: peak FR 62.68 Hz +-1.27;
burst fractions: 0.35±0.017; chirp response: peak FR 66.56 Hz+-4.21, burst fraction 0.44±0.02,
Wicoxon ranked sum test (p=.002)). Shaded area represents standard error. B. Even the bursty
population bursts less in response to *A. albifrons* chirps compared to the beat (beat response:
peak FR 155.45 Hz +- 8.82, burst fractions 0.55± 0.03; chirp response: peak FR 117.75Hz +-
9.40, burst fraction 0.48± 0.03, Wilcoxon ranked sum test (p=.04)). C. The bursting population
(red) tends to exhibit broad stimulus coherence compared to the non-bursting population (black).
D. Example raster plots of chirp responses used for A and B. The non-bursty population (black
box) responds similarly to both *A. leptorhynchus* chirp and beat. The bursty population (red box)
bursts to *A. leptorhynchus* chirps, but not *A. albifrons* chirps.).

Figure 6: Coding of noise by bursts. A. Sample of noise stimulus (red) and representative spike
train (black) from an OFF-cell. B. Example of ISI distribution used to determine burst threshold
(dashed line). C. ON-cells (red) burst more than OFF-cells (blue) (ANOVA, p=.02), and local
stimulation (L) produced more bursting than global (G) (ANOVA, p=.01). Error bars show
standard error D. Mean burst triggered averages (red) and single spike triggered averages
(black) from ON (right) and OFF-cells (left) show that bursts are triggered by wider (lower-
frequency) stimulus features than single spikes. E. Bursts do not significantly reduce error in
feature coding. In both ON and OFF cells in both stimulus configurations bursts (B) tend to have
lower error rates than single spikes (S) but this trend is not significant (ANOVA, p=.10)

816
817

818
Figure 7: Chirping behavior in freely swimming pairs. A. The number of chirps produced during
interaction is correlated with difference in EODf (r^2=.1093) B. Chirping does not differ by
absolute EODf, relative EODf, or pairing. Mean chirp rate for low frequency (<1100Hz, L) and
high frequency fish (>1100, H) was similar (Student's t test, p=.86). Mean), mean chirps per trial
based on EODf of pairing (low frequency: low frequency, L:L; low: high, L:H; high: high, H:H)
(ANOVA, p=.47), and by relative frequency within the pairing (Lower frequency individual, Lr;
Higher frequency individual, Hr) (Student's t test, p=.55) were all extremely low and similar in
all groupings. Error bars indicate standard error. C. Interchirp intervals for all recorded chirps

show no echoing or frequent chirp exchanges. Inset: Enlarged section show that very few chirps
occur within 2s of each other.

Table 1

Chirp ID	Frequency Rise (Hz)	Duration (ms)	Other
1	200	100	α shape
2	200	200	α shape
3	350	100	α shape
4	350	200	α shape
5	50	50	α shape
6	100	50	α shape
7	50	50	Antiphase to 5
8	100	50	Antiphase to 6
9	350	200	Two frequency peaks
10	350	200	Ramp Shaped
11	60	10	*A. lept.* small chirp
12	122	15	*A. lept.* small chirp

Frequency and duration properties for all chirps used

SUPPLEMENTAL FIGURES:

S1: Detailed discrimination traces indicating results of testing specific chirps against each other.
For ease of analysis, chirps were grouped by duration frequency and duration as either big or
small. Duration appears to be the feature that is most discriminable, so big and small chirps were
not directly compared. Descriptions of chirp properties are located in Table 1. A. Chirp
discrimination on a 10 Hz beat. B) Chirp discrimination on a 100 Hz beat.

S2: *A. leptorhynchus* data for stimulation protocols matched to those used in the main text. This
data is comparable to what has already be extensively published in Krahe et al. (Krahe et al.,
2008), and thus not highlighted in the main text, but indicate that our methods are reproduce
previously published results and indicate differences between *A. albifrons* and *A. leptorhynchus*.
A. Coherence to 0-60Hz RAM stimulation. Mean coherence to noise stimulation by neuron type.
ON-cell coherence is shown in red, OFF-cell in cyan. The upper bound coherence measure is
shown with solid lines, lower bound in dotted lines B. Phase locking to sinusoids across 0-60Hz
is best at 20-30Hz, while firing rate is relatively constant across frequencies C. Coherence to low
frequency envelopes. Both ON and OFF cells perform well at coding low frequency stimulus
components. D. *A. leptorhynchus* adaptation to step stimulation (global stimulation shown).

853
854

855 S3: *A. albifrons* adaptation to step stimulation. Adaptation curves are not as sharp as those
856 observed in *A. leptorhynchus*. We compared adaptation time constant, τ, by fitting exponent
857 curves to the portion of the stimulus response after peak firing rate. For *A. albifrons* there was no
858 difference in τ between ON and OFF cells (ANOVA p= 0.13) or between local and global
859 stimulation (ANOVA p= 0.08).
860

863 S4: Histology showing location of recording within ELL. Red is Dextran Texas Red pressure
864 injected at recording site, Cyan is Syto 59 nuclear marker. Arrow indicates the tract separating
865 LS and CLS regions.

866