Neural processing of communication signals: The extent of sender-receiver matching varies across species of *Apteronotus*

Simplified neural encoding of social signals

K.M. Allen[1] & G. Marsat[1]

[1]Department of Biology, West Virginia University, Morgantown, WV 26505

Author contributions: K.A.-Designed and performed the research, analyzed data, wrote the paper; G. M.-Designed research, created analytic tools, wrote the paper

Corresponding Author: G. Marsat gary.marsat@mail.wvu.edu

Figures: 7

Tables: 1

Abstract: 238

Significance Statement: 119

Introduction: 683

Discussion: 2186

Acknowledgments: We thank G.T. Smith for discussions about this project, data on chirp

properties and feedback on the manuscript. We thank M.J. Chacron for comments on this

manuscript.

Conflict of interest statement: The authors report no conflict of interest.

Funding was provided by West Virginia University and the National Science Foundation grant IOS-1557846.

ABSTRACT

As signal production changes through speciation, the sensory systems that receive these signals also adapt to extract relevant information effectively. Shedding light on this process helps us understand how sensory codes are tailored to specific tasks. In a species of weakly electric fish, *Apteronotus albifrons*, we examined the unique neurophysiological properties that support the encoding of electrosensory communication signals that the animal encounters in social exchanges. We compare our findings to known coding properties of the closely related species, *Apteronotus leptorhynchus*, to establish how these animals differ in their ability to encode their distinctive communication signals. While there are many similarities between these two species, we found notable differences leading to relatively poor coding of the details of chirp structure occurring on high-frequency background beats. As a result, small differences in chirp properties are poorly resolved by the nervous system. We performed behavioral tests to relate *A. albifrons* chirp coding strategies to its use of chirps during social encounters. Our results suggest that *A. albifrons* do not exchange frequent chirps in non-breeding condition, particularly when the beat frequency is high. These findings parallel the mediocre chirp coding accuracy in that they both point to a reduced reliance on frequent and rich exchange of information through chirps during these social interactions. Therefore, our study suggests that neural coding strategies in the central nervous system vary across species in a way that parallels the behavioral use of the sensory signals.

SIGNIFICANCE:

Sender-receiver matching is a phenomenon commonly observed in the peripheral nervous

system. It enables communication production and reception to evolve together so that

conspecifics remain sensitive to important signals. In this manuscript we examine this

phenomenon in the central nervous system weakly electric fish *A. albifrons* and compare its

processing of communication signals to a closely related species (*A. leptorhynchus*). Although

some differences across the two species can help tailor the system for processing species-specific

signals, our data indicate that encoding of communication signals in *A. albifrons* is not as

efficient as in *A. leptorhynchus* for certain categories of signals. Our data support the idea that

the extent of sender-receiver matching can vary as a function of behavioral needs.

INTRODUCTION

Sender and receiver matching facilitating communication has been demonstrated across diverse groups, including songbirds (Brumm and Slabbekoorn, 2005), anurans (Schul and Bush, 2002), and insects (Neuhofer et al., 2008). Peripheral tuning and call matching are well characterized, but comparatively little research explores communication-specific adaptations within the brain. Even in Drosophila, where courtship song coding has been examined in high level auditory centers, matching between sender and receiver across species with divergent song patterns has not been resolved (Tootoonian et al., 2012). We aim to identify species-specific variations in coding properties of central neurons and link them to the divergent use of communication signals, showing that the extent of species-specific adaptations results in a variably tight sender-receiver match.

Weakly electric fish are ideal for examining diversification in signal production and reception. Apteronotids share a common mode of communication, modification of their electric organ discharge (EOD), but exhibit huge variety in signal structure. Voluntary modulations of EOD (chirps) vary dramatically in properties such as duration, frequency, and shape, even between closely related species (Turner et al., 2007; Zakon and Smith, 2002). Likewise, chirp reception is influenced by EOD waveform shape (Petzold et al., 2016), chirp features or structure (Benda et al., 2006; Marsat et al., 2012), and social environment (Stamper et al., 2010). The apteronotid electrosensory system could have coding properties generic enough to process these signals efficiently despite differences in structure and use between species; alternatively, differences in chirp processing could reflect adaptations of the electrosensory system to these differences in chirp production.

Relative EOD frequencies of interacting fish greatly influences chirp perception. These

fish perceive ongoing amplitude modulations (AM beat) that are the product of two fish with

different EOD frequencies interacting at close range (Bastian, 1981). Chirping modulates this

beat (Hagedorn and Heiligenberg, 1985; Zupanc and Maler, 1993). In *A. leptorhynchus*, low

frequency beats are typical of agnostic encounters between fish of similar sex and size, and fish

respond with frequent small chirps (<100Hz increase) (Hupé and Lewis, 2008). Higher

frequencies occur between fish of opposite sexes or with large differences in body size and more

often elicit big chirps (>100Hz), typical of courtship (Hagedorn and Heiligenberg, 1985;

Henninger et al., 2018).

Chirp coding has been well characterized in *A. leptorhynchus.* The two categories of

signals described above produce different responses in the primary sensory area, the

electrosensory lateral line lobe (ELL). Small chirps on low frequency beats cause stereotyped

bursting among ELL pyramidal cells. This encoding strategy, and the structure of the signal

itself, means variations in small chirps cannot be discriminated (Allen and Marsat, 2018; Marsat

et al., 2009). Conversely, both big and small chirps on high frequency beats produce

heterogeneous responses and chirp variations are accurately discriminated (Allen & Marsat,

2018; Marsat & Maler, 2010).

Chirp production in *A. albifrons* is similar to *A. leptorhynchus*, but differs primarily in

chirp duration. *A. leptorhynchus* chirps are typically tens of milliseconds long, whereas *A.*

albifrons chirps are generally over 100 milliseconds long (Dunlap et al., 1998; Turner et al.,

2007; Zupanc and Maler, 1993). This lengthening is thought to be a recent evolutionary change,

with shorter chirps representing the basal state of this branch (Smith et al., 2016). *A. albifrons*

show differences in frequency tuning from *A. leptorhynchus* (Martinez et al., 2016) that may be

adaptations for coding these long chirps. Additionally, *A. albifrons* chirps typically do not fall

into discreet "small" and "big" chirp categories like those of *A. leptorhynchus* (Turner et al.,

2007), and chirps of varying durations and frequency are used in all contexts (Kolodziejski et al.,

2007). Therefore, it is unknown whether varying chirps have different neural and behavioral

impacts in *A. albifrons*.

In this study, we examine coding of conspecific social signals and their behavioral use to

understand if the sensory system is adapted to the specific characteristics of the communication

system of *A. albifrons,* and if so, to what extent. We compare our findings to the behavior and

physiology of the closely related *A. leptorhynchus* to identify specific neurophysiological

adaptations that reflect differences in the structure and behavioral use of chirps in these two

species.

METHODS

Animals

All animals were housed according to WVU IACUC standards, protocol 151200009.2. Wild-caught *Apteronotus albifrons* and *Apteronotus leptorhynchus* were obtained from commercial fish suppliers and housed in small groups (1-10 fish per tank). Tank conductivity was maintained at 200-500 µS. Sex was not confirmed, but adult animals with a wide range of EOD frequencies (600-1300Hz) were used for all experiments, indicating that we likely had multiple animals of both sexes.

Electrophysiology

Surgical techniques were identical to those previously described in (Marsat et al., 2009; Marsat and Maler, 2010). Cells of the LS of the ELL were targeted. *A. albifrons* brain anatomy is very similar to that of *A. leptorhynchus*, so major landmark blood vessels described in Maler et al., (1991) and electrode depth served as an adequate guide to locate LS pyramidal cells (see Histology). *In vivo* recordings were made via metal filled extracellular electrodes (Frank and Becker, 1964) and amplified with an A-M Systems amplifier (Model 1700). Data were recorded (Axon Digidata 1500 and Axoscope software) at a 20kHz sampling rate. ON and OFF cells were identified using known response properties, particularly responses to sinusoidal stimulation and spike triggered average waveforms calculated from responses to 0-60Hz noise (Saunders and Bastian, 1984).

Histology

In N=9 fish, correct electrode placement was confirmed by injection of Dextran Texas Red dye (Thermo Fisher, catalogue # D1829) at recording site using double barreled electrodes,

similar to methods described in Krahe et al., (2008). After recording, dye was pressure injected

with a PicoPump (WPI, PV820). Animals were then anaesthetized and respirated with a solution

of Tricaine-S (.5g/L, Western Chemicals) and perfused with 4% paraformaldehyde (Electron

Microscopy Supply, # 15712) in 1X PBS. Brains were postfixed overnight, sectioned (150 µm),

and counterstained with Syto59 nuclear stain (Thermo Fisher, # S11341), which allowed for

clear distinction between ELL segments. In all marked sections, correct placement within the LS

was observed.

Stimuli

All stimuli were created in MatLab (Mathworks, Inc.) and sampled at 20 kHz.

Stimulation was provided by a direct modulation of the amplitude (AM) of a carrier artificial

EOD phase locked to the fish's own rather than by mimicking a second EOD. This method

(described below) is commonly used in similar experiments (Benda et al., 2005; Krahe et al.,

2008; Marsat et al., 2009) and allows precise control over the stimulus AM . Baseline EOD was

recorded via electrodes near the head and tail of the fish. Each EOD cycle triggered a sine wave

generator (Rigol DG1022A) to generate one cycle of a sine wave matched to the animal's own.

This signal was then multiplied using a custom-built signal multiplier (courtesy of the Fortune

Laboratory, New Jersey Institute of Technology) by the AM stimulus to create the desired

modulation of the electric field. Stimuli were played through a stimulus isolator (A-M Systems,

Model 2200) into the experimental tank via either two 30.5cm carbon electrodes arranged

parallel to the fish's longitudinal axis (global stimulation) or two silver chloridized point

electrodes 1 cm apart from each other positioned near the receptive field on the fish's skin (local

stimulation). The stimulus strength was adjusted to provide ~20% contrast (the difference

between the maximum and minimum of amplitude modulation divided by the baseline EOD).

See Fig1-3 for further comments on stimulus strength.

Random amplitude modulation (RAM) stimuli consisted of 30 seconds of random noise

filtered using either a low pass (0-20Hz), band pass (40-60Hz) or broadband (0-60Hz)

Butterworth filter. Each stimulus was played for three repetitions in both global and local

stimulation configurations. Sinusoidal amplitude modulation (SAM) stimuli were 2 second long

stimuli modulated at 2, 5, 15, 30, 60, and 90 Hz with 2 seconds rest between each frequency,

repeated at least three times. Step stimulations were 100ms long increases or decreases in

amplitude repeated for 30 seconds.

Chirp stimuli were created by using recorded EOD samples (courtesy of Dr. Troy Smith,

Electric Fish Signal Library) to create a 1000 Hz template *A. albifrons* EOD shape, thereby

accounting for the actual EOD shape and resulting AM beat shape. Chirps of varying durations,

frequency increases, and frequency rise/fall time (Table 1) were each embedded in this template

EOD by decreasing the template EOD period by the inverse of the desired frequency increase for

each EOD cycle in the duration of the chirp. For each 1Hz of frequency increase, the template

amplitude was decreased by .11%, based on Dunlap at al. (1998). Chirps were added at the rate

of 1 chirp per second. To this chirper EOD, a second EOD, either 990Hz or 900Hz, was added to

create a combined EOD signal with a beat AM frequency of 10 or 100Hz. The AM of this

stimulus was extracted by rectifying and low-pass filtering the combined EOD signal. The AM

signal was delivered during the experiments as described above. Each chirp stimulus was played

for at least 30 seconds and up to 60 seconds. Due to time constraints, chirps were only played in

the global configuration.

Data Analysis

For all analyses spike trains were first binarized into a sequence of 1's (spike) and 0's (no

spike) using a bin width of 0.5ms. All analyses described here were performed on these binary

sequences in MatLab. Statistical analyses (ANOVA, Student's t-Test, Wilcoxon rank sum) were

performed using the MatLab's statistical analysis toolbox.

Synchronization Coefficient

The strength of phase locking to SAM stimulation was calculated as

$$s = \frac{\sqrt{(\sum x_i)^2 + (\sum y_i)^2}}{n}$$

, where n is the number of spikes in the analysis, and x and y are the cosine and sine of the

stimulus' phase at which spike i occurs (Goldberg and Brown, 1969; Marsat and Pollack, 2004).

The vector strength, s, ranges from 0 to 1, with 1 being perfect precision in responding to a given

phase of the cycle.

Coherence

Lower bound (stimulus-response) coherence is a measure of linear coding of the stimulus

and is calculated by comparing the spike train against the RAM stimulus (Borst and Theunissen,

1999). Stimulus-response (S and R respectively) magnitude-squared coherence (C_{SR}) was

calculated as a function of frequency (f) according to:

$$C_{SR}(f) = \frac{|P_{SR}(f)|^2}{P_{SS}(f)P_{RR}(f)}$$

196   where P indicates the power-spectral or cross-spectral densities.

197   Upper bound (response-response) coherence measures the total information potentially

198   coded in the response, including linear and non-linear information. It is measured by comparing

199   multiple responses of one neuron to each other to determine response reliability (Borst and

200   Theunissen, 1999). Coherence between responses Ri and Rj was calculated as:

$$C_{RiRj}(f) = \sqrt{\frac{P_{RiRj}(f)P_{RjRi}(f)}{P_{RiRi}(f)P_{RjRj}(f)}}$$

and averaged across all pairwise combinations of responses.

Envelope responses were determined by computing the lower-bound coherence between

the responses and the envelope of the 40-60Hz RAM stimuli. To do so, the stimulus $S(t)$ in the

lower-bound analysis described above was replaced by the envelope $E(t)$ calculated by rectifying

and low pass filtering the 40-60Hz noise stimulus AM. Similar results were obtained when using

a Hilbert transform to calculate the envelope signal.

Burst detection

Bursts in RAM and chirp responses were identified by creating a histogram of all inter-

spike intervals (ISIs) in the response. Bursting neurons have a bimodal, non-Poisson distribution

of ISIs, allowing us to visually identify a threshold ISI at the upper boundary of intra-burst

intervals. Spikes in groups with ISIs below the threshold were classed as occurring in bursts,

while all remaining spikes were classed as tonic. This method is similar to that described in

(Ávila-Åkerberg et al., 2010)

Chirp detection and discrimination analysis

215   Analysis of chirps for detection and discrimination is based on Allen and Marsat (2018).

216 Our analysis accounts for both the firing rate as well as the temporal pattern of spikes to quantify

217 how similar or dissimilar spiking patterns are (van Rossum, 2001). For detection analysis, a

218 window around the chirp ($R_c(t)$) of length L (50, 105, or 205ms) was extracted from the filtered

219 spike train and compared to a window of beat of the same size ($R_b(t)$). Different window sizes

220 led to qualitatively similar results, and those using 205ms are shown. The responses were

221 convolved with an α filter, $f(t) = t * \exp(-\frac{2.45t}{\tau})$, with τ being the width of the function at half

222 maximum (3, 10, 30, and 100ms; 30ms shown) (Machens et al., 2003). Detection accuracy is

223 calculated for population responses by averaging multiple spike trains:

$$PR_i(t) = \frac{\sum_{i=t}^{n} R_i(t)}{n}$$

224 The result ($PR_i(t)$) represents a population of neurons presented with the same stimulus and

225 mimics a neuron integrating postsynaptic potentials with similar weights. Distance (D) was

226 calculated for all sets of combined responses, $PR_c(t)$ and $PR_b(t)$, creating an array of response

227 distances for each comparison using the function:.

$$D_{cb} = \frac{\sum_{t=0}^{L} [R_c(t) - R_b(t)]^2}{L}$$

228 The probability distributions of the values in these arrays ($P(D_{cb})$ or $P(D_{bb})$) were used for

229 analysis. Receiver operator characteristic curves were calculated by varying a threshold distance

230 (T) to separate chirp and beat responses. For each threshold the probability of detection (PD) was

231 calculated as the sum of ($P(D_{cb} > T)$), and the probability of false alarm (PF) as the sum of

232 ($P(D_{bb} < T)$). The error level for each threshold value is $E = PF/2 + (1-PD)/2$. The values shown in

233 Figure 3 are the minimum calculated values of E as increasing numbers of spike trains are

234 included in the calculation.

Discrimination analyses were similar to those for detection, but rather than comparing

chirp and beat responses, the distances between two different chirps were compared. Similar to

detection analysis, windows of chirp responses ($R(t)$) of length L (50,105, and 205ms) were used

for analysis and the results using 205ms are shown. The responses were convolved with an α

filter and population averaged as described above. Up to 200 random combinations of spike

trains from all recorded neurons were used for all comparisons as more become computationally

prohibitive without improving results. Responses to a given chirp against a different chirp (x vs.

y) were compared as well as multiple responses to the same chirp (x vs. x). Spike train metric

distances (D_{xy} or D_{xx}) the ensuing distribution and error rates were calculated as described for the

detection analysis.

Adaptation

Adaptation to stimuli was measured by using the MatLab Curve fitting toolbox to fit an

exponential curve to a plot of instantaneous firing rate for each neuron resulting in a time

constant τ. The portion of the response to use for fitting was determined by selecting the time of

peak firing rate and the following 500ms.

Behavior

Twenty-eight behavior trials were conducted in a small tank (27x27x14cm) containing

water with conductivity, pH, and temperature matched to the home system, and one shelter tube.

The tank was enclosed to block ambient light, lit with infrared lights and all trials were recorded

via infrared camera (Logitech HD Pro Webcam C920). 14cm carbon rod electrodes placed

diagonally from each other in each corner of the tank recorded electrical activity, which was then

amplified (A-M Systems, Model 1700) and recorded using a computer sound card.

Stranger fish from different home tanks were paired. Defining physical features (size,

markings) and EODf were noted to avoid repeatedly testing the same pairing. Individual fish

were used no more than three times, with at least seven days between each trial. One fish was

selected and allowed to acclimate to the test tank for 20 minutes before the introduction of the

second fish. Recording began immediately upon introduction of the intruder fish. Interactions

were recorded for five minutes.

To detect chirps, we used a custom MatLab script to create a spectrogram of the electrical

recordings to identify individuals and mark chirp times. Chirps were visually identified as >10Hz

abrupt frequency increases.

RESULTS

Diversity in conspecific chirp responses

In multiple gymnotid species the lateral segment (LS) of the ELL serves as the primary location for encoding of communication and social signals (Marsat et al., 2009; Metzner, 1999; Metzner and Juranek, 1997), thus we targeted our recordings to pyramidal cells in that segment. To characterize the pattern of responses of *A. albifrons* pyramidal cells we played a series of chirps mimicking the natural range of reported *A. albifrons* chirps (Turner et al., 2007). Additionally, for comparison we used a small number of chirps with properties more typical of *A. leptorhynchus* (Dunlap et al., 1998; Zupanc and Maler, 1993). Detailed descriptions of chirp properties used are located in Table 1. In addition to playing chirps with diverse properties, we also varied the frequency of the beat, presenting chirps on both low (10 Hz) and high (100 Hz) frequency signals.

Figure 1 displays a representative selection of the diversity seen in chirp responses for both ON-type and OFF-type pyramidal cells. Qualitatively, responses appear to be heterogeneous with variability between inhibition, excitation, and desynchronization. On high frequency beats (Fig 1A) we see a transient increase in tonic firing rate in OFF-cell while ON-cells are briefly and weakly inhibited during the chirp. On low frequency beats (Fig 1B), the responses also consisted of brief increases in firing rates, but were additionally characterized by periods of inhibition lasting the entire duration of the chirp. We did not observe synchronized burst firing across the population that is typical of *A. leptorhynchus*' responses to small chirps on low frequency beats (Marsat et al., 2009; Marsat and Maler, 2010), the strategy that limits ability to discriminate these chirps (Allen and Marsat, 2018). Therefore, all chirps appear to be coded primarily through increases in firing among OFF-cells, and inhibition and desynchronization and

cancelation of the beat (See Figure 1-1) of ON-cells. These results suggest that *A. albifrons*

pyramidal cells uses the same coding patterns for all chirp types, but possibly exhibit differences

based on beat frequency. Furthermore, a strong adaptation (see Figure 1-2) in firing rate seen

between the beginning and end of the chirp response could cause chirps of different length to be

poorly discriminated. Therefore, we next quantified how well the neural responses could support

both detection and discrimination of chirps.

Detection of chirps varies with beat frequency

We used a spike metric distance to measure the variability in firing patterns and how

reliably an ideal observer could distinguish chirp responses from beat responses. The results are

presented as an error level as a function of the number of neural inputs pooled in the analysis.

More efficient encoding would lead this measure to drop faster from 0.5 (chance level) as a

larger population of neurons is used in the detection task.

ON-Cells can efficiently detect all chirps to a high level of accuracy with about 8

neurons, comparable to *A. leptorhynchus* (Marsat and Maler, 2010) (Fig 2A). However, this level

of accuracy only holds for chirps on the 10 Hz beat. ON-cell performance on 100 Hz is

extremely poor, even with high numbers of spike trains included in the analysis (Fig 2B). OFF-

cells are also able to detect chirp occurrence on low frequency beats for all chirp types (Fig 2C)

but on 100 Hz they can only detect the longest, most intense chirps efficiently (Fig 2D).

Therefore, while chirps on low frequencies are reliably detected, detection sensitivity is poor in

high frequency contexts.

Discrimination between chirps also varies

We assessed the amount of information carried by the response pattern about chirp

properties that could support the discrimination of chirp variants. This analysis is similar to that

used for chirp detection, but rather than comparing responses of chirps to beats, we compare

responses between chirps. While *A. albifrons* chirps are not typically grouped into distinct

categories, we still use the terminology used in *A. lepthorhynchus* to describe the two ends of the

spectrum of chirp properties (small< 150 Hz increase; big>150 Hz). Figure 3 shows

discrimination ability for chirps grouped by size (See Table 1; Small chirps: 5, 6, 7, 8; Big

chirps: 1, 2, 3, 4, 9, 10) for both ON and OFF-cells on high and low beat frequencies.

Chirps of all types are more easily discriminable when presented on 10Hz beats (Fig 3A)

rather than on 100Hz beats (Fig 3B). Performance for chirps on high frequency beats was

variable: accurate discrimination was achieved only for chirps with large differences in

properties (Fig 3-1) and both ON and OFF cell responses allow qualitatively similar

discrimination accuracy. These results are unexpected, considering that the same analysis in *A.*

leptorhynchus shows that chirps on high frequency beats can be discriminated well using as few as

as six neurons, and conversely exhibit poor discrimination coding on low frequencies (Marsat

and Maler, 2010) where *A. albifrons* performs best. Furthermore, we do not observe an

asymmetry in coding accuracy between ON and OFF cells as observed in *A. leptorhynchus*.

When looking at which chirps are well discriminated, chirp duration and the steepness of

the frequency rise seem to be the most discriminable features, while total frequency increase and

number of peaks are less influential on coding (Fig 3-1). However, discriminating the most easily

separated chirps is still prone to error on high frequency beats, even when recruiting up to 17

neurons. These data indicate that while qualitative observations would suggest that chirp coding

is similar between *A. albifrons* and *A. leptorhynchus*, there are quantitative differences in the

information content about chirps within the electrosensory system. To determine which aspects

of the neural responses could be responsible for changes in chirp coding, we characterized a wide

variety of response properties using an assortment of stimulation protocols.

Frequency tuning and neural coding

Encoding amplitude modulations (AM) in stimuli is crucial for the recognition of social

signals. As shown above, *A. albifrons* neurons respond variably to chirps, which consist of both

high frequency AM signals and the low frequency changes in the contrast of the AM (i.e. the

envelope). We asked whether the accuracy of detection and discrimination of chirps by *A.*

albifrons ELL neurons reflects species-specific tuning properties. Communication signals cause

spatially diffuse stimulation and we simulate this configuration using a large dipole (see

methods) that drives both the feedforward and feedback pathways. To separate the effects of

feedback from the tuning of the feedforward circuit we also stimulated only the receptive field of

each cell with a small local dipole (Bastian, 1986; Chacron et al., 2005).

In response to simple sine waves, *A. albifrons* exhibit the highest degree of coding

fidelity at low frequencies. Firing rate for each sine cycle peaks at 5Hz for all cell types and

stimulation configurations (Fig 4A). Maximum phase locking also peaks at low frequencies (Fig

4B). These values closely match previously reported values (Martinez et al., 2016). Temporal

coding accuracy is conveniently quantified using random noise stimuli and information theory

(Borst and Theunissen, 1999). Lower-bound coherence reflects the amount of information

encoded linearly whereas upper bound coherence takes in account both linear and non-linear

aspects of the response (Fig 4C). Both ON and OFF cell coherence curves peak at similar

frequencies in the 5-20 Hz range (Wilcox Rank Sum, p=.19). However, OFF-cells are clearly

low-pass, and exhibit a sharp decline in coherence to higher frequencies, while ON-cells exhibit

a slightly broader lower-bound coherence (see Fig 5 and accompanying text for more details).

The movement of fish as well as the amplitude changes caused by chirps create low

frequency changes in AM contrast, or envelopes (Stamper et al., 2013). During chirps, the AM

will be high frequency (tens to hundreds of hertz above the beat frequency) whereas the envelope

of the chirp is low frequency (e.g. 100ms chirp will lead to a ~ 10Hz envelope). Therefore, the

coding of chirps' low frequency content must be investigated using envelope stimuli. We

characterized envelope coding using stimuli consisting of RAMs with AM frequencies between

40Hz and 60Hz, containing envelope frequencies of 0-20 Hz (Middleton et al., 2006). Although

pyramidal cells do encode the envelope of these stimuli (Fig 4D), the coding accuracy is low

compared with the envelope coding observed in *A. leptorhynchus* (Chacron, 2006; Middleton et

al., 2006; Fig 5-1). This poor envelope coding, particularly for OFF-cells in response to global

stimuli, may help to explain the poor chirp discrimination we observe. OFF-cells are particularly

relevant for chirp discrimination because chirps consist of a decrease in envelope amplitude that

are best encoded by OFF-cells (Marsat and Maler, 2010).

Burst Firing and Chirp Detection

As described in Marsat et al. (2009) burst firing serves an important role in *A.*

leptorhynchus for the efficient detection of extremely short chirps. As qualitatively shown above

in Figure 1, no conspecific chirps reliably produced a burst response in *A. albifrons*. This implies

that *A. albifrons* may not be using this dedicated code for detection of very brief chirp signals. In

A. leptorhynchus the coding of small chirps is directly related to beat frequency. On low

frequencies, small chirps are shorter than the period of one beat cycle. As beat frequency

increases and the period becomes shorter, small chirps begin to last longer than one cycle. This

change in duration relative to beat period mediates a change in how small chirps are coded (Walz

et al., 2014). In *A. albifrons* all chirps are much longer than *A. leptorhynchus* small chirps,

spanning more than one beat cycle even on low frequencies, which may eliminate the need for a

feature detection code specifically for extremely short chirps. Thus, the observed lack of bursting

may result from the change either in signal structure (duration relative to beat cycle) or from

underlying changes to physiology and bursting capability of LS neurons.

To determine if this change in signal coding is a result of signal structure or underlying

physiology, we stimulated *A. albifrons* fish with *A. leptorhynchus* chirps known to elicit a burst

response in 73% of *A. leptorhynchus* LS ON-cells (Marsat et al., 2009). We determined burst

threshold ISI for each neuron by plotting ISI distribution of chirp and beat responses and

manually selecting a threshold that best distinguished between the two (Martinez-Conde et al.,

2002) in order to maximize our measure of chirp-specific bursting. The mean burst threshold was

8.0ms ±0.7ms (s.e.), comparable to the burst thresholds determined for our RAM analyses and in

other reports (Ávila-Åkerberg et al., 2010; Chacron and Bastian, 2008; Marsat et al., 2009).The

majority of neurons increased firing rate only slightly more in response to *A. leptorhynchus*

chirps than to the beat. There was, however, a small percentage (~ 20%) of ON-cells that did

reliably burst more in response to *A. leptorhynchus* small chirps than to the beat (Fig 5A, C).

Most importantly, even the bursty neurons did not respond to the shortest *A. albifrons* chirps

with bursts (Fig 5B, D). Unlike *A. leptorhynchus* small chirps, the shortest *A. albifrons* chirps are

still long enough to span more than one beat cycle and so the response they elicit is largely

independent of the phase at which chirps start.

The low proportion of neurons that burst in response to *A. leptorhynchus* chirps suggests

that there are physiologic differences between these two species in regards to burst coding of

communication signals. We examined the differences between bursty and non-bursty neurons in

more detail by analyzing separately their response to RAM stimuli. The subset of bursty neurons

have broader AM tuning (Fig 5C) as tested by comparing the ratio of coherences summed over

the 0-30Hz vs 30-60Hz (bursty cells mean ratio± s.d.: 0.91 ± 0.12; non-bursty cells mean ratio:

2.35 ± 1.72; t-test not assuming equal variance, p= 0.0047; similar results were found using the

upper-bound coherence). While most ON-cells exhibited peak coherence at frequencies between

10-20Hz (non-bursty cells mean peak frequency ± s.d.: 19.6 ± 18), these cells had significantly

higher peak frequencies as high as 40-50Hz (mean ± s.d.: 40 ± 13.9 Hz; t-test, p=0.023) and

exhibited high coherence across the range of stimulus frequencies. The remainder of the ON

cells displayed the low-pass tuning described in Martinez et al. (2016). These data show that

while a subset of ELL neurons are capable of bursting in response to short chirp stimuli, they

make up a small percentage of the overall ELL population and bursting does not seem to play a

role in conspecific chirp coding.

Feature Detection

Burst firing may not be a significant aspect of communication coding in *A. albifrons*, but

other uses for burst coding may be conserved. During spontaneous activity, we observed a

baseline firing rate of 13.54 Hz (±1.37 s.e.) with 17.01% (±2.55 s.e.) of spikes in bursts. Thus,

the pyramidal neurons of *A. albifrons* are physiologically capable of bursting. In *A.*

leptorhynchus burst firing can reliably signal the presence of spatially localized prey-like stimuli

(Gabbiani et al., 1996; Oswald et al., 2004). We examined bursting in response to local RAM

stimulation (Fig 6A) to determine if bursting could serve similar prey detection functions in *A.*

albifrons. The ISI histogram of the responses clearly showed that the neurons burst to these

stimuli (Fig 6B). The proportion of spikes occurring in bursts was as high as 63.07% (±5.64 s.e.)

for stimuli in the local configuration (Fig 6C). The average stimulus waveform triggering burst

vs single spikes follows the pattern observed in other species: slower AM for bursts than for

single spikes (Fig 6D). However, in response to RAM stimuli, unlike *A. leptorhynchus* there was

not a large difference in coding error between bursting and tonic spiking (ANOVA, p=.10) (Fig

6E). These data suggest that while bursts encode low frequency stimuli in the LS of *A. albifrons,*

they do not appear to implement a burst-based feature detection code for either prey-like stimuli

or chirps.

Chirp production and behavior

Our physiology data suggest that *A. albifrons* are able to detect and discriminate chirps

on low frequency beats much more efficiently than on high frequency beats. This may be

adaptive for how the fish use chirps. To test this hypothesis, we recorded electrical behavior

from pairs of freely swimming and interacting fish. Chirping behavior did occur but differed

from that of *A. leptorhynchus* in a number of ways. Primarily, overall rates of chirping are

dramatically lower than numbers reported from similar studies in *A. leptorhynchus* (Hupé and

Lewis, 2008; Zupanc et al., 2006). Over 28 trials, we recorded a sum of 133 chirps, with a mean

of 4.75 (±0.61 s.e.) chirps per 5-minute trial whereas in a similar context male *A. leptorhynchus*

produced approximately of 125 chirps per 5 minute trials (Hupé and Lewis, 2008). The

maximum number of chirps observed in one trial was 13. Due to the small number of observed

chirps, we did not separate them into multiple categories for analysis, although chirps of varying

frequency increases and duration occurred. Chirping frequency is correlated with the difference

in EODf of interacting fish. Smaller differences in EODf correspond to higher numbers of chirps

(Fig 7A). However, under our conditions chirping does not appear to be sexually dimorphic.

Animals used in behavior experiments were not killed to determine sex, but we grouped them by

EODf into high (>1100Hz) and low (<1100Hz) frequency groups which can correspond to

females and males respectively in many populations of *A. albifrons* (Zakon and Dunlap, 1999).

We observed no differences in chirp production between high or low frequency groups (Fig 7B).

Further, chirp rate does not vary by pairing type, nor by relative EODf of individuals within each

pair under our conditions (Fig 7B). These results confirm previous findings that chirp frequency

in this species is not sexually dimorphic (Dunlap et al., 1998).

Chirp timing plays an important role in mediating *A. leptorhynchus* interactions as they

frequently exchange chirps in an echo response pattern (Henninger et al., 2018; Hupé and Lewis,

2008; Zupanc et al., 2006), a behavior where one fish responds to the chirp of another fish by

chirping back within <1s . To determine if chirp timing plays a similar role in *A. albifrons*

interactions, we analyzed inter-chirp intervals for all trials in which both fish chirped. The

resulting distribution of all chirp latencies (repeated chirps by one individual as well as

exchanges between both fish) indicates inter-chirp latencies much longer than are typical of *A.*

leptorhynchus echo responses (Fig 7C). Of all recorded chirps, only six occurred within 2.5s of

each other, making an echo response unlikely to be an important feature of *A. albifrons*

interactions. Furthermore, we fit an exponential function to the inter-chirp interval distribution

shown in Fig 7C with an R^2=0.91 suggesting a Poisson distribution of chirps relative to one

another, reinforcing the idea that chirp timing is not dependent on the timing of prior chirps. This

lack of echoing, the long inter-chirp intervals, and the low rate of chirping in general, suggest

that *A. albifrons* do not rely on the detailed decoding of individual chirp characteristics as is the

case in *A. leptorhynchus*.

DISCUSSION

We found that neurons in *A. albifrons'* primary sensory area are able to detect chirp

occurrence and do encode chirp identities on low frequency beats. However, they do not encode

the identity of chirps very accurately when presented on high frequency beats. Rather than

producing discrete burst responses for small chirps and tonic responses for big chirps, all chirps

in this species are encoded via graded and heterogeneous increase or decreases in firing rate. We

found several adaptations in the basic response properties that may explain the neural responses

to conspecific chirps. These adaptations, frequency tuning in particular, may facilitate encoding

long chirps in *A. albifrons* as well as enhancing chirp coding in the behavioral context in which

chirps are used most often. Therefore, we also asked whether chirping behavior could explain

differences in chirp coding efficiency for high and low frequencies beats. We found that the

pattern of chirp use during common social interactions is very different from that of closely

related species: *A. albifrons* produces very few chirps and do not respond to each other with echo

chirps. Infrequent chirping is particularly pronounced in the context of high-frequency beats

suggesting that certain types of interactions are not mediated by chirps. We suggest that the

observed differences in chirp coding accuracy on high frequency beats may reflect a relaxation in

demands for exchanging information via chirps in this context.

Low frequency tuning could be adaptive for chirp coding

Our results confirm that pyramidal cells in the LS of *A. albifrons* are low pass. This

finding parallels the low frequency envelopes produced by long *A. albifrons* chirps. However,

the impact of this AM tuning on chirp coding depends on the way AMs and envelopes are

processed in this system. Whereas the envelope of chirps is low frequency, the AM is high

frequency. Therefore, low frequency tuning to AM is not automatically helpful. We found that

the coding of low-frequency envelopes was relatively poor, particularly in OFF cells, which -in

A. leptorhynchus- are best at coding chirp envelopes. However, if envelope response is

synthesized before the pyramidal cells (e.g. at the electroreceptors as could be the case in *A.*

leptorhynchus (Savard et al., 2011)) low frequency tuning to AM could benefit chirp coding

since the input to the pyramidal cell would thereby contain low-frequencies (Metzen et al.,

2018). Nevertheless, we show that the neural response does not accurately reflect the chirp

envelope and that envelope coding of decreases in amplitude of RAM envelope stimuli is poor.

Our data replicate the findings of Martinez et al. (2016) that also show poor coding of envelope

stimuli, with coherence values of approximately 0.1. It is possible that without the low frequency

tuning, chirp and envelope coding would be worse and thus it compensates for other properties

that hinder envelope coding (e.g. amount of rectification performed by the receptors; (Savard et

al., 2011)).

The role of burst coding

Bursts also often play an important role in coding specific features of communication

signals (Creutzig et al., 2009; Fujimoto et al., 2011) as it is the case for *A. leptorhynchus* where

bursting enhances detectability of small chirps on low frequency beats (Marsat et al., 2009). *A.*

leptorhynchus small chirps are unusual in that, for low frequency beats, they span less than a full

cycle of the beat. Consequently, the same chirp can be perceived as a sharp decrease in

amplitude, a sharp increase, or a mix of the two, depending on the phase of the beat at which the

chirp starts (Benda et al., 2005). It may be because of this aspect of chirp structure and its

shortness, that the sensory system of *A. leptorhynchus* uses bursts to enhance detectability rather

that optimizing the coding of these chirps' properties. *A. albifrons* is not subject to the same

constraints. The perceived AM of a chirp is largely independent of beat phase since chirps span

several cycles of the beat and their long duration might make them more conspicuous (Petzold et

al., 2016). Using noise stimuli, we showed that burst coding in the LS is different in *A. albifrons*.

Since burst are not used to encode chirps and because LS primarily focuses on processing

communication signals, it is possible that these neurons do not need to use burst as a feature

detection signaling mechanism as in other species (Gabbiani et al., 1996; Oswald et al., 2004).

Chirp coding and behavior

Our chirp response analysis shows that all chirps are coded with graded increases and

decreases in firing rate containing some information about chirp properties but, for high

frequency beats, coding accuracy is inefficient at supporting both chirp detection and

discrimination. Our behavioral data might shed some light on this apparent inefficiency at coding

chirps across all social contexts. We show that, in our conditions, *A. albifrons* chirp relatively

infrequently to meditate dyad interactions. Furthermore, we show that there is a tendency to

chirp less when the beat frequency is higher. This is supported by previous findings showing that

chirp production is more frequent in interactions involving low frequency beats (Kolodziejski et

al., 2007) reiterating the relevance of chirp coding on low-frequency beats rather than high

frequency interactions.

Comparison to *A. leptorhynchus* and other electric fish

Our physiology and behavioral findings are markedly different than those observed in the

closely related *A. leptorhynchus*. Primarily, our data show *A. albifrons* exhibit poor chirp coding

on high beat frequencies, and efficient coding on low beat frequencies. This is directly in

contrast with *A. leptorhynchus* that encode chirps on high frequency stimuli well and exhibit

poorer coding of chirp identity on low frequency beats (Allen and Marsat, 2018; Marsat and

Maler, 2010). Furthermore, we find that *A. albifrons* do not rely on the same coding strategy as

used in *A. leptorhynchus* since feature detection through bursts is not involved in chirp coding.

Our data clearly demonstrate that despite being so closely related (Smith et al., 2016) the sensory

coding properties of the neurons encoding communication signals have diverged between *A.*

leptorhynchus and *A. albifrons*. Chirps have been suggested to be short in the ancestors basal to

the two species (Smith et al., 2016) and longer chirps a development of the *A. albifrons* branch.

Therefore, it is possible that the differences in frequency tuning we observed in *A. albifrons* may

be adaptive for coding these long chirps.

Our behavioral results suggest that *A. albifrons* also use chirp exchanges very differently

than *A. leptorhynchus*. Unlike the complex chirp interactions observed in *A. leptorhynchus*,

where chirps are omnipresent and play a central role in various type of interactions (Hagedorn

and Heiligenberg, 1985; Henninger et al., 2018; Hupé, 2012) *A. albifrons* chirp infrequently and

generally only in low frequency difference interactions (Kolodziejski et al., 2007). While *A.*

leptorhynchus have dedicated uses for different chirp types, small chirps between males

primarily mediating same-sex interactions, and big and small chirp exchanges used often

between males and females during courtship (Henninger et al., 2018), *A. albifrons* use all types

of chirps interchangeably for low beat frequency interactions and may not possess distinct chirp

categories (Dunlap et al., 1998; Kolodziejski et al., 2007; Turner et al., 2007). Chirps with

specific properties are used in specific contexts in *A. leptorhynchus* but the link between chirp

properties and their role in *A. albifrons* is less clear (Dunlap and Larkins-Ford, 2003). Therefore

we suggest that the latter are specifically adapted to better encode chirps on low frequency beats

where chirps are most likely to be produced.

Chirping behavior has been investigated across many species of wave-type gymnotiforms

other than *A. leptorhynchus* and *A. albifrons* (Hagedorn and Heiligenberg, 1985; Petzold et al.,

2018, 2016; Turner et al., 2007). Details of chirp encoding, however, have only been investigated

in one other species, *Eigenmannia viscerens* (Metzner and Heiligenberg, 1991; Metzner and

Viete, 1996; Stöckl et al., 2014). In this species, similarly to *A. leptorhynchus*, different chirp

types are used to mediate agonistic and courtship encounters (Hagedorn and Heiligenberg, 1985),

but in contrast to apteronotids, the characteristic feature of this species' chirps is that they

include interruptions of the EOD rather than just frequency increases. In this species, unlike the

apteronotids, chirp coding appears to be unaffected by beat frequency, at least at the level of

electroreceptors (Stöckl et al., 2014). However, the coding strategy observed in the ELL

pyramidal cells is that the duration of the chirp is the primary feature encoded. This feature is

coded via brief excitation, then inhibition of both ON and OFF-cells (dependent on sign of the

DC component of the chirp) that signals the duration of the EOD interruption (Metzner and

Heiligenberg, 1991). This strategy is similar to the coding observed in *A. albifrons* in low

frequency interactions, suggesting that perhaps *A. leptorhynchus* represent the outlier group, and

burst detection of chirps is a specialization for their unique small chirps.

Conditions affecting chirp coding

Our study did not test for the effects of neuromodulation on neural tuning and chirp

coding. Neuromodulation can change cell response properties for different behavioral states

(Harris-Warrick and Marder, 1991). Previous work in *A. leptorhynchus* shows that serotonin

enhances pyramidal cell excitability and responsiveness to small chirps on low frequency beats

(Deemyad et al., 2013). While we worked on adult animals, we did not determine sex or

breeding status, both of which have large effects of the frequency and quality of chirps produced

(Smith, 2013). It is likely that the effects of neuromodulation due to behavioral state could affect

the reception and encoding of these chirps as well, altering sensitivity to chirps and possibly even

coding accuracy in response to behavioral need. This may particularly influence the coding of

chirps on high frequency beats, which we observed was surprisingly poor. This kind of

interaction is more likely to occur in breeding contexts, so it is possible that animals in breeding

condition could be better able to detect and discriminate these signals than the results we show

here. We also did not investigate other environmental factors that could influence the sensory

specializations of both species, such as microhabitats, prey capture, and general sociality, all of

which could drive some of the adaptations seen.

Our analysis technique is widely used to quantify the encoding performance of sensory

neurons (Itatani and Klump, 2014; Mouterde et al., 2017; Neuhofer and Ronacher, 2012), and is

biologically realistic (Larson et al., 2009). Nevertheless, other analysis technics could be devised

to improve the discrimination accuracy estimate. Weighting the contribution of the different

neurons, or weighting them differently across time could be envisioned (Larson et al., 2010).

Keeping the different neurons as separate dimensions in the analysis (Houghton and Sen, 2008)

or combining ON and OFF-cell responses (Aumentado-Armstrong et al., 2015) could improve

discrimination. Performing dual recordings and then taking in account neural correlation in the

response variability could also affect the coding performance (Hofmann and Chacron, 2017).

Finally, various more complex decoding methods (e.g. multilayered neural net or PCA-type

dimensionality reduction) could be used for analysis. Nevertheless, we do not expect the neural

mechanism to differ widely across apteronotid species so our analysis provides a meaningful

comparison. The strength of our measure is that it is conservative: it gives a clear account of the

information available in ELL pyramidal cells with few assumptions about what the downstream

networks use for decoding.

Trade-offs between specialization and generalization

Classical neuroethology dictates that the mode of signal production and mode of signal

reception must evolve in synchrony so that senders and receivers never lose the ability to

exchange information (Bradbury and Vehrencamp, 2011). There are many examples of

specialization of particular aspects of sensory systems to accomplish a highly specialized tasks

(Endler, 1992). In the case of communication, sensory tuning for sender-receiver matching has

been shown repeatedly. However, the converse may also be true. Over-specialization may come

at the cost of reduced sensitivity to more general environmental signals. In such a case, it may be

more beneficial to favor sensory generalization over specialization in animals that engage in

social behaviors less often than their more gregarious relatives do. Indeed, there are several

examples of peripheral sender-receiver mismatching that may be explained by gains in

sensitivity to prey or predator signals to (Mason, 1991; Römer, 2016). While we see in *A.*

leptorhynchus dedicated codes for communication signals with distinct meaning and in distinct

contexts (Allen and Marsat, 2018; Marsat and Maler, 2010), maintaining that level of specificity

for conspecific communication may be costly both metabolically (Niven and Laughlin, 2008)

and in regards to detecting environmental stimuli apart from communication signals.

In *A. albifrons* we show a general match between signal characteristics, low frequency

chirp envelopes, and CNS sensitivity to low frequency signals, but a lack of detailed coding that

would allow for efficient discrimination of chirp identity in all contexts. Additional changes that

would lead to a more accurate chirp coding could come at the expense of the ability to encode

other stimuli. Therefore, for this species, limiting the resources dedicated to the coding of social

signals in certain contexts (e.g. aggressive encounters with a fish with a high difference in EOD

frequency) may allow the system to preserve or enhance sensitivity to other stimuli.

BIBLIOGRAPHY

Allen KM, Marsat G (2018) Task-specific sensory coding strategies matched to detection and discrimination behaviors in Apteronotus leptorhynchus. J Exp Biol In Press.

Aumentado-Armstrong T, Metzen MG, Sproule MKJ, Chacron MJ (2015) Electrosensory Midbrain Neurons Display Feature Invariant Responses to Natural Communication Stimuli. PLoS Comput Biol 11:1–28.

Ávila-Åkerberg O, Krahe R, Chacron MJ (2010) Neural heterogeneities and stimulus properties affect burst coding in vivo. Neuroscience 168:300–313.

Bastian J (1986) Gain control in the electrosensory system: a role for the descending projections to the electrosensory lateral line lobe. J Comp Physiol A 158:505–515.

Bastian J (1981) II. The effects of moving objects and other electrical stimuli on the activities of two categories of posterior lateral line lobe cells in Apteronotus albifrons. J Comput Physiol 144:481–494.

Bastian J, Chacron MJ, Maler L (2004) Plastic and nonplastic pyramidal cells perform unique roles in a network capable of adaptive redundancy reduction. Neuron 41:767–779.

Benda J, Longtin A, Maler L (2006) A synchronization-desynchronization code for natural communication signals. Neuron 52:347–358.

Benda J, Longtin A, Maler L (2005) Spike-frequency adaptation separates transient communication signals from background oscillations. J Neurosci 25:2312–21.

Borst A, Theunissen FE (1999) Information theory and neural coding. Nat Neurosci 2:947–957.

Bradbury JW, Vehrencamp SL (2011) Principles of animal communication, 2nd ed. Sunderland,

655  Mass., Mass.: Sinauer Associates.

656 Brumm H, Slabbekoorn H (2005) Acoustic Communication in Noise. Adv Study Behav.

657 Chacron MJ (2006) Nonlinear Information Processing in a Model Sensory System. J

658  Neurophysiol 95:2933–2946.

659 Chacron MJ, Bastian J (2008) Population coding by electrosensory neurons. J Neurophysiol

660  99:1825–1835.

661 Chacron MJ, Maler L, Bastian J (2005) Feedback and feedforward control of frequency tuning to

662  naturalistic stimuli. J Neurosci 25:5521–5532.

663 Creutzig F, Wohlgemuth S, Stumpner A, Benda J, Ronacher B, Herz AVM (2009) Timescale-

664  Invariant Representation of Acoustic Communication Signals by a Bursting Neuron. J

665  Neurosci 29:2575.

666 Deemyad T, Metzen MG, Pan Y, Chacron MJ (2013) Serotonin selectively enhances perception

667  and sensory neural responses to stimuli generated by same-sex conspecifics. Proc Natl Acad

668  Sci U S A 110:19609–14.

669 Dunlap KD, Larkins-Ford J (2003) Diversity in the structure of electrocommunication signals

670  within a genus of electric fish, Apteronotus. J Comp Physiol A 189:153–161.

671 Dunlap KD, Thomas P, Zakon HH (1998) Diversity of sexual dimorphism in

672  electrocommunication signals and its androgen regulation in a genus of electric fish,

673  Apteronotus. J Comp Physiol A Sensory, Neural, Behav Physiol 183:77–86.

674 Endler JA (1992) Signals, Signal Conditions, and the Direction of Evolution. Am Nat 139:S125–

675  S153.

Frank K, Becker MC (1964) Microelectrodes for recording and stimulation In: Physical

Techniques in Biological Research (Nastuk WL ed), pp23–84. New York: Academic Press.

Fujimoto H, Hasegawa T, Watanabe D (2011) Neural Coding of Syntactic Structure in Learned

Vocalizations in the Songbird. J Neurosci 31:10023.

Gabbiani F, Metzner W, Wessel R, Koch C (1996) From stimulus encoding to feature extraction

in weakly electric fish. Nature 384:564–567.

Goldberg JM, Brown PB (1969) Response of binaural neurons of dog superior olivary complex

to dichotic tonal stimuli: some physiological mechanisms of sound localization. J

Neurophysiol 32:613–636.

Hagedorn M, Heiligenberg W (1985) Court and spark: electric signals in the courtship and

mating of gymnotoid fish. Anim Behav 33:254–265.

Harris-Warrick RM, Marder E (1991) Modulation of neural networks for behavior. Annu Rev

Neurosci 14:39–57.

Henninger J, Krahe R, Kirschbaum F, Grewe J, Benda J (2018) Statistics of natural

communication signals observed in the wild identify important yet neglected stimulus

regimes in weakly electric fish. J Neurosci 318–350.

Hofmann V, Chacron MJ (2017) Differential receptive field organizations give rise to nearly

identical neural correlations across three parallel sensory maps in weakly electric fish. PLoS

Comput Biol 13:e1005716.

Houghton C, Sen K (2008) A New Multineuron Spike Train Metric. Neural Comput 20:1495–

1511.

Hupé GJ (2012) Electrocommunication in a Species of Weakly Electric Fish Apteronotus

Leptorhynchus: Signal Patterning and Behaviour. Université d'Ottawa/University of

Ottawa.

Hupé GJ, Lewis JE (2008) Electrocommunication signals in free swimming brown ghost

knifefish, Apteronotus leptorhynchus. J Exp Biol 211:1657–1667.

Itatani N, Klump GM (2014) Neural correlates of auditory streaming in an objective behavioral

task. Proc Natl Acad Sci 111:10738 LP-10743.

Kolodziejski J a, Sanford SE, Smith GT (2007) Stimulus frequency differentially affects chirping

in two species of weakly electric fish: implications for the evolution of signal structure and

function. J Exp Biol 210:2501–2509.

Krahe R, Bastian J, Chacron MJ (2008) Temporal processing across multiple topographic maps

in the electrosensory system. J Neurophysiol 100:852–67.

Larson E, Billimoria CP, Sen K (2009) A biologically plausible computational model for

auditory object recognition. J Neurophysiol 101:323–331.

Larson E, Perrone BP, Sen K, Billimoria CP (2010) A Robust and Biologically Plausible Spike

Pattern Recognition Network. J Neurosci 30:15566 LP-15572.

Machens CK et al. (2003) Single auditory neurons rapidly discriminate conspecific

communication signals. Nat Neurosci 6:341–342.

Maler L, Sas E, Johnston S, Ellis W (1991) An atlas of the brain of the electric fish Apteronotus

leptorhynchus. J Chem Neuroanat 4:1–38.

Marsat G, Maler L (2010) Neural heterogeneity and efficient population codes for

communication signals. J Neurophysiol 104:2543–55.

Marsat G, Pollack GS (2004) Differential temporal coding of rhythmically diverse acoustic
signals by a single interneuron. J Neurophysiol 92:939–48.

Marsat G, Proville RD, Maler L (2009) Transient signals trigger synchronous bursts in an
identified population of neurons. J Neurophysiol 102:714–723.

Martinez-Conde S, Macknik SL, Hubel DH (2002) The function of bursts of spikes during visual
fixation in the awake primate lateral geniculate nucleus and primary visual cortex. Proc Natl
Acad Sci U S A 99:13920–13925.

Martinez D, Metzen MG, Chacron MJ (2016) Electrosensory processing in Apteronotus
albifrons: implications for general and specific neural coding strategies across wave-type
weakly electric fish species. J Neurophysiol 116:2909–2921.

Mason AC (1991) Hearing in a primitive ensiferan: the auditory system of Cyphoderris
monstrosa (Orthoptera: Haglidae). J Comp Physiol A 168:351–363.

Metzen MG, Huang CG, Chacron MJ (2018) Descending pathways generate perception of and
neural responses to weak sensory input. PLOS Biol 16:e2005239.

Metzner W (1999) Neural circuitry for communication and jamming avoidance in gymnotiform
electric fish. J Exp Biol 202:1365–1375.

Metzner W, Heiligenberg W (1991) The coding of signals in the electric communication of the
gymnotiform fish Eigenmannia: From electroreceptors to neurons in the torus semicircularis
of the midbrain. J Comp Physiol A 169:135–150.

Metzner W, Juranek J (1997) A sensory brain map for☐each☐behavior? Proc Natl Acad Sci 94.

Metzner W, Viete S (1996) The Neuronal Basis of Communication and Orientation in the

Weakly Electric Fish, EigenmanniaI. Communication Behavior or: Seeking a Conspecific?s

Response. Naturwissenschaften 83:6–14.

Middleton JW, Longtin A, Benda J, Maler L (2006) The cellular basis for parallel neural

transmission of a high-frequency stimulus and its low-frequency envelope. Proc Natl Acad

Sci U S A 103:14596–601.

Mouterde SC, Elie JE, Mathevon N, Theunissen FE (2017) Single Neurons in the Avian

Auditory Cortex Encode Individual Identity and Propagation Distance in Naturally

Degraded Communication Calls. J Neurosci 37:3491 LP-3510.

Neuhofer D, Ronacher B (2012) Influence of Different Envelope Maskers on Signal Recognition

and Neuronal Representation in the Auditory System of a Grasshopper. PLoS One

7:e34384.

Neuhofer D, Wohlgemuth S, Stumpner A, Ronacher B (2008) Evolutionarily conserved coding

properties of auditory neurons across grasshopper species. Proc R Soc B Biol Sci 275:1965–

1974.

Niven JE, Laughlin SB (2008) Energy limitation as a selective pressure on the evolution of

sensory systems. J Exp Biol 211:1792 LP-1804.

Oswald A-MM, Chacron MJ, Doiron B, Bastian J, Maler L (2004) Parallel processing of sensory

input by bursts and isolated spikes. J Neurosci 24:4351–4362.

Petzold JM, Alves-Gomes JA, Smith GT (2018) Chirping and asymmetric jamming avoidance

responses in the electric fish Distocyclus conirostris J Exp Biol

221:jeb178913.

Petzold JM, Marsat G, Smith GT (2016) Co-adaptation of electric organ discharges and chirps in South American ghost knifefishes (Apteronotidae). J Physiol.

Römer H (2016) Matched Filters in Insect Audition: Tuning Curves and Beyond BT - The Ecology of Animal Senses: Matched Filters for Economical Sensing In: (von der Emde G, Warrant E eds), pp83–109. Cham: Springer International Publishing.

Saunders J, Bastian J (1984) The physiology and morphology of two types of electrosensory neurons in the weakly electric fish Apteronotus leptorhynchus. J Comp Physiol A 154:199–209.

Savard M, Krahe R, Chacron MJ (2011) Neural heterogeneities influence envelope and temporal coding at the sensory periphery. Neuroscience 172:270–284.

Schul J, Bush SL (2002) Non-parallel coevolution of sender and receiver in the acoustic communication system of treefrogs. Proc R Soc London Ser B Biol Sci 269:1847 LP-1852.

Smith AR, Proffitt MR, Ho WW, Mullaney CB, Maldonado-Ocampo JA, Lovejoy NR, Alves-Gomes JA, Smith GT (2016) Evolution of electric communication signals in the South American ghost knifefishes (Gymnotiformes: Apteronotidae): A phylogenetic comparative study using a sequence-based phylogeny. J Physiol 110:302–313.

Smith GT (2013) Evolution and hormonal regulation of sex differences in the electrocommunication behavior of ghost knifefishes (Apteronotidae). J Exp Biol 216:2421 LP-2433.

Stamper SA, Carrera-G E, Tan EW, Fugère V, Krahe R, Fortune ES (2010) Species differences

in group size and electrosensory interference in weakly electric fishes: Implications for

electrosensory processing. Behav Brain Res 207:368–376.

Stamper SA, Fortune ES, Chacron MJ (2013) Perception and coding of envelopes in weakly

electric fishes. J Exp Biol 216:2393 LP-2402.

Stöckl A, Sinz F, Benda J, Grewe J (2014) Encoding of social signals in all three electrosensory

pathways of Eigenmannia virescens. J Neurophysiol 112:2076–2091.

Tootoonian S, Coen P, Kawai R, Murthy M (2012) Neural Representations of Courtship Song in

the Drosophila Brain. J Neurosci 32:787 LP-798.

Turner CR, Derylo M, de Santana CD, Alves-Gomes J a, Smith GT (2007) Phylogenetic

comparative analysis of electric communication signals in ghost knifefishes

(Gymnotiformes: Apteronotidae). J Exp bBology 210:4104–4122.

van Rossum MC (2001) A novel spike distance. Neural Comput 13:751–763.

Walz H, Grewe J, Benda J (2014) Static frequency tuning properties account for changes in

neural synchrony evoked by transient communication signals. J Neurophysiol 112:752–765.

Zakon HH, Dunlap KD (1999) Sex steroids and communication signals in electric fish: a tale of

two species. Brain Behav Evol 54:61–9.

Zakon HH, Smith GT (2002) Weakly electric fish: behavior, neurobiology, and

neuroendocrinology. Horm brain Behav 3:349–375.

Zupanc GKH, Maler L (1993) Evoked chirping in the weakly electric fish Apteronotus

leptorhynchus□: a quantitative biophysical analysis. Can J Zool 71:2301–2310.

Zupanc GKH, Sirbulescu RF, Nichols A, Ilies I (2006) Electric interactions through chirping

behavior in the weakly electric fish, Apteronotus leptorhynchus. J Comp Physiol A

192:159–173.

FIGURE LEGENDS

Figure 1: ELL Pyramidal cell responses to conspecific signals. A. Raster plots of chirp

responses on a high frequency (100Hz) beat. AM stimulus is shown in black; 3 representative

OFF-cells are shown in cyan boxes while 3 ON-cells responses are displayed in red boxes. The

same 6 neurons are used for all panels. **B.** Responses to chirps on a low frequency (10Hz) beat.

For a detailed description of all chirps used, see Table 1. The shaded area highlights the duration

of the chirp. See Figure 1-1 and 1-2 for comments and analysis of specific response properties

(adaptation time and biphasic responses to low frequencies).

Figure 2: Detection efficiency depends on beat frequency. A. Detection of chirps on 10Hz

beat by ON-cells as a factor of neurons included in the analysis (n=17). ON-cells can reliably

detect the occurrence of all chirps. Detection error levels for individual chirp identities are shown

in gray. Red line indicates mean detection error for all chirps. **B.** ON-cell performance is worse

on 100Hz beats. **C, D** Mean OFF-cell performance (cyan, n=16) is also more efficient on a 10Hz

beat.

Figure 3: Discrimination of chirps on high frequency beats is poor. A. Discrimination for small chirps (Chirps 5,6,7,8, right) and big chirps (Chirps 1,2,3,4,9,10, left) on 10Hz beat. Mean ON-cell chirp discrimination shown in red, OFF-cells in cyan, and discrimination for individual chirp pairs shown in gray. **B.** Discrimination of small chirps on a 100Hz beat is relatively inefficient for both ON (red) and OFF-cells (cyan). Discrimination of big chirps varies with chirp identity, but is still poor. For chirp-by-chirp discrimination comparisons see Figure 3-1.

Figure 4: Temporal coding properties of pyramidal cells A. Mean firing in response to SAM stimuli. Mean firing rate (±s.e.) for both ON (red, n=19) and OFF (cyan, n=15) cells in both stimulation configurations (global: pink, pale blue; local: red, cyan) peaks at 5Hz. **B.** Phase locking to AM sinusoids is also best at low frequencies. Maximum phase locking is seen at 15Hz, with the exception of locally stimulated OFF-cells, which peak at 5Hz. **C.** Mean coherence to noise stimulation is also low-pass. ON-cell coherence is shown in red, OFF-cell in cyan. The upper bound coherence measure (solid line) is based on the response-response correlations between multiple presentations of the stimulus, while the lower bound (dashed line) is based on stimulus-response correlations. Shaded areas indicate standard error; darker shading indicates local stimulation. Mean global lower bound maximums: ON-cells: 23.1Hz (±.86 s.e.); OFF-cells: 11.6Hz (±.75 s.e.), (Wilcoxon rank-sum test p=.04). **D.** Coding of low frequency envelopes is poor. Mean (± s.e.) lower bound coherence between responses and the low-frequency (0-20Hz) envelope of a bandpass RAM stimulus (40-60Hz) are displayed for both local and global stimulus configurations. Both ON and OFF cells exhibit peak envelope tuning at 10.10Hz (±1.52 s.e.) (Wilcoxon rank-sum test, p=.21). OFF-cells are noticeably poorer at coding envelopes.

Figure 5: Coding of chirps by a small population of higher-pass neurons. A. The mean

instantaneous firing rates of ON-cells over the time course of chirp and beat stimuli. The

difference in peak firing rate characterize a small population (n=5, red) that bursts in response to

A. leptorhynchus small chirps (Beat responses, dashed lines: Peak FR 77.67 HZ ± 7.11; Chirp

responses, solid lines: Peak FR 159.57 Hz ± 8.68; Wilcoxon ranked sum test (p<0.001). The

majority of the ON-cell population (n=16, black) only showed a modest increase in firing (Beat

Response: peak FR 62.68 Hz ±1.27; chirp response: peak FR 66.56 Hz±4.21, Wicoxon ranked

sum test p=.002). Shaded area represents standard error. **B.** Even the bursty population fires less

in response to *A. albifrons* smallest chirps compared to the beat (beat response: peak FR 155.45

Hz ± 8.82; chirp response: peak FR 117.75Hz ± 9.40, Wilcoxon ranked sum test (p=.04)). **C.**

Mean (±s.e.) **upper-bound and lower-bound coherences for** the bursting (red) and non-

bursting (black) populations. . **D.** Example raster plots of chirp responses used for A and B. The

non-bursty population (black box) responds similarly to both *A. leptorhynchus* chirp and beat.

The bursty population (red box) bursts to *A. leptorhynchus* chirps, but not *A. albifrons* chirps.).

For comparable data obtained from *A. leptorhynchus* see Figure 5-1.

Figure 6: Coding of AM by bursts. A. Sample of noise stimulus (0-60Hz, gray) and

representative spike train (black) from an OFF-cell during local stimulation. **B.** Example of ISI

distribution used to determine burst threshold (dashed line). **C.** ON-cells (red) burst more than

OFF-cells (blue) (ANOVA, p=.02), and local stimulation produced more bursting than global

(ANOVA, p=.01). Error bars show standard error **D.** Mean burst triggered averages (red/blue)

and single spike triggered averages (black) from ON and OFF-cells show that bursts are

triggered by wider (lower-frequency) stimulus features than single spikes. **E.** Feature detection

performance for burst and isolated spikes. In both ON and OFF cells bursts (blue/red -filled bars)

tend to have lower error rates (percentage of events signaling false positives or false negatives)

in detecting optimal stimulus features than single spikes (gray-filled bars) but this trend is not

significant (ANOVA, p=.10).

Figure 7: Chirping behavior in freely swimming pairs (n=28). **A.** The number of chirps produced during interaction is correlated with difference in EODf (r^2=.1093) **B.** Chirping does not differ by absolute EODf, EODf pair type or relative EODf. Mean chirp rate for low frequency (<1100Hz) and high frequency fish (>1100) was similar (Student's t-test, p=.86). Mean chirps per trial based on EODf of pairing (Low: Low, Low: High, High: High) (ANOVA, p=.47), and by relative frequency of individuals within the pairing (Student's t test, p=.55) were all

extremely low and similar in all groupings. Error bars indicate standard deviation. **C.** Inter-chirp

intervals for all recorded chirps binned by time fall according to a Poisson distribution and show

no echoing chirp exchanges. Inset: Enlarged section show that very few chirps occur within 2s of

each other.

Table 1

Table 1: Frequency and duration properties for all chirps used. "Other" indicates differences in

chirp shape not due to peak frequency or duration, such as shape of frequency rise and fall, and

phase of the beat on which the chirp occurred.

Chirp ID	Frequency Rise (Hz)	Duration (ms)	Other
1	200	100	α shape
2	200	200	α shape
3	350	100	α shape
4	350	200	α shape
5	50	50	α shape
6	100	50	α shape
7	50	50	Antiphase to 5
8	100	50	Antiphase to 6
9	350	200	Two frequency peaks
10	350	200	Ramp Shaped
11	60	10	*A. lept.* small chirp
12	122	15	*A. lept.* small chirp

Extended Data

Figure 1-1: Cancellation observed in an LS ON cell. In some recordings a biphasic response to

stimuli is observed. While this could indicate an overly strong stimulus, it could also indicate

cancellation via feedback from the midbrain (Bastian et al., 2004). Cancellation is less prominent

in the LS of *A. leptorhynchus*, but still occurs. The biphasic responses to global SAM stimuli but

not to local stimulation indicate that our observed responses likely represent an increased

cancellation response in the LS as a result of low frequency tuning.

Figure 1-2: *A. albifrons* adaptation to step stimulation. A. Both ON and OFF cells' responses

decreased throughout the 100ms stimulus without plateauing in sharp contrast with B. *A.*

leptorhynchus responses to global stimuli (S2, Krahe et al., 2008 see their figure 8C&F) that

adapt within 40-50ms and then plateau.

943   Figure 3-1: Detailed discrimination traces indicating results of testing specific chirps against

944   each other. For ease of analysis, chirps were grouped by duration frequency and duration as

945   either big or small. Duration appears to be the feature that is most discriminable, so big and small

946   chirps were not directly compared. Descriptions of chirp properties are located in Table 1. A.

947   Chirp discrimination on a 10 Hz beat. B) Chirp discrimination on a 100 Hz beat.

Figure 5-1: *A. leptorhynchus* data for stimulation protocols matched to those used in the main text. This data is comparable to what has already be extensively published in Krahe et al. (Krahe et al., 2008), and thus not highlighted in the main text, but indicate that our methods reproduce previously published results and indicate differences between *A. albifrons* and *A. leptorhynchus*. A. Coherence to 0-60Hz RAM stimulation. Mean coherence to noise stimulation by neuron type. ON-cell coherence is shown in red, OFF-cell in cyan. The upper bound coherence measure is shown with solid lines, lower bound in dotted lines B. Phase locking to sinusoids across 0-60Hz is best at 20-30Hz, while firing rate is relatively constant across frequencies C. Coherence to low frequency envelopes. Both ON and OFF cells perform well at coding low frequency stimulus components.