Original Manuscript

Title: Electrical Fields Induced Inside the Rat Brain with Skin, Skull, and Dural Placements of the
Current Injection Electrode

Ahmet S. Asan, MS
Department of Biomedical Engineering
New Jersey Institute of Technology
University Heights
Newark, NJ 07102 USA

Sinan Gok, PhD
Department of Biomedical Engineering
New Jersey Institute of Technology
University Heights
Newark, NJ 07102 USA

Mesut Sahin, PhD
Professor of Biomedical Engineering
Associate Editor, IEEE Tran. on Biomedical Circuits and Systems
Department of Biomedical Engineering
New Jersey Institute of Technology
University Heights
Newark, NJ 07102 USA
Web: http://web.njit.edu/~sahin
Email: sahin@njit.edu

Corresponding author: Mesut Sahin, PhD

Author contributions: Ahmet S. Asan contributed to experimental design, collected the data, and
performed signal analysis. Sinan Gok was involved in data collection and drafting the manuscript. Mesut
Sahin conceived and designed the experiments, interpreted the data, and reviewed the manuscript.

Abstract

Transcranial electrical stimulation (tES) is rapidly becoming an indispensable clinical tool with its

different forms. Animal data are crucially needed for better understanding of the underlying

mechanisms of tES. For reproducibility of results in animal experiments, the electric fields inside the

brain parenchyma induced by the injected currents need to be predicted accurately. In this study, we

measured the electrical fields in the rat brain perpendicular to the brain surface when the stimulation

electrode was placed over the skin, skull, or dura mater through a craniotomy hole. The E-field

attenuation through the skin was a few times larger than that of the skull. The E-field declined much

faster in the gray matter underneath the pial surface than it did in the white matter, and thus the large

E-fields were contained mostly in the gray matter. The transition at the gray/white matter border

caused a significant peak in the E-field, as well as any other local inhomogeneties. The vertical E-field

near the cortex is about one third of what is estimated by analytical solutions for volume conductors

that assume a semi-infinite homogenous medium for the brain and a conductivity value of 0.2 S/m. A

global scaling factor of 1/3 can be useful to account for deviations from the analytical equations in rat

experiments and for more realistic estimations of the E-field peak underneath the electrode. Finally,

insertion of the current return electrode into the shoulder, submandibular, and hind leg muscles had

virtually no effects on the measured E-field amplitudes in the cortex underneath the epidural

electrodes.

Keywords: transcranial electrical stimulation, electrical field distribution, volume conductor

I. INTRODUCTION

Transcranial electrical stimulation (tES) has emerged as an effective non-invasive technique for modulation of the brain activity in recent years, while the earliest studies date back more than a century (1). In general, the safety of the tES and its derivations has now been agreed upon so long as the current is kept below 2mA, although recent reports seem to suggest 4mA as the limit (2). These tES derivations include transcranial direct current stimulation (tDCS), transcranial alternating current stimulation (tACS), and transcranial random noise stimulation (tRNS) (3). Despite widespread interest in clinical applications, the exact mechanisms of action for tES are still being investigated.

Aforementioned tES techniques inject weak electrical currents through the brain and presumably cause only subthreshold modulation of the neuronal membrane potentials (4). Early animal studies demonstrated that neuronal firing rates could be modulated by applying direct currents (DC) to the brain (5,6) and the modulatory effects of transcranial DC electric fields were confirmed in human studies (7,8). While the excitatory and inhibitory effects of tDCS are attributed to the direction of the applied current on a larger scale (anodal vs. cathodal) (6,7,9), a more detailed analysis revealed that the primary factor is the position and orientation of the individual neuronal structures relative to the electric field. *In vitro* measurements on rat hippocampal slices showed that the amplitude and delay of the population spikes evoked by orthodromic stimulation were affected linearly by the applied uniform electric fields (10). Furthermore, even small electric fields induced polarization of CA1 pyramidal cells of the hippocampus when applied parallel to the somato-dendritic axis, but failed to do so when applied perpendicularly. Studies on the rat motor cortex slices indicated that somatic polarization was also correlated with the neuronal morphology, and the layer V pyramidal cells were the most sensitive to subthreshold electric fields (11). In general it seems that a realistic estimation of the electric field distribution inside the brain parenchyma is needed as a starting point for accurate interpretations of the neurological impact of the intervention.

The electric field can be controlled by adjusting the stimulation/charge intensity and steered to

a certain extent by careful positioning of the extracranial electrodes. Nevertheless, the electrical

properties of different tissues that the current passes through play a significant role in distribution of

the electric field. Direct *in vivo* measurement of the electric field in human subjects is not an option from

a clinical standpoint, thus most investigators resort to computational models in order to approximate

the electric field distribution in the human brain under varying stimulation intensities and electrode

arrangements. Miranda *et al.* used a spherical head model and estimated that almost 50% of the

injected current is shunted through the scalp (12). Datta *et al*. used a more advanced head model where

gyri/sulci specificity was defined and predicted that the electric field was concentrated at distinct sites,

like the walls of the gyri (13). In summary, tES induced current flow is a complex phenomenon that is

influenced by several factors including: 1) skull and scalp thicknesses and their compositions, 2) CSF

thickness and conductivity, 3) gyri/sulci morphology, 4) electrode size and geometry, and 5) positioning

of the stimulating and return electrodes (13,14).

In addition to human computational models, tES effects have been studied in animals where the

main interests are understanding the underlying cellular and molecular mechanisms, optimizing

stimulation protocols, and establishing safety limits. To this end, animal models provide ample

opportunities to rapidly develop new tDCS methodologies and measure the outcomes while

manipulating the stimulation parameters within a wide range (see (15) for a review). For accurate

interpretation of the results from these animal studies, realistic estimates of the induced electric field

distribution are needed. Direct measurement of the electric fields in brain tissue goes back to as early as

1950s with experiments carried on anesthetized monkeys (16), nevertheless, these studies progressed

very slowly since then. Chan *et al.* conducted a series of experiments using isolated turtle cerebella, and

studied the relationship between the applied fields and the spontaneous neuronal activity (17,18). More

recent studies on monkeys (19) and rats (20) also reported electric field measurements, although

restricted either to the cortical surface or a single horizontal plane, respectively.

The tDCS technique can benefit from *in vivo* animal data, which are clearly lacking in the

literature, for better understanding of the mechanisms. While the computational models provide a basic

understanding of how electrical currents are distributed through the animal brain (21) as much as the

human brain, they can lead to unrealistic conclusions if they primarily depend on conductivity

measurements gathered from *ex vivo* tissue samples (22). Furthermore, anatomical differences in the

brain size and the skin, skull, and CSF thicknesses make it difficult to extrapolate the results of an electric

field model developed for one species to another. In this study, we used a rat model to measure the

intracerebral voltages at varying depths and horizontal distances from the stimulating electrode. Vertical

electric fields were reported for three stimulation conditions in which the anodic electrode was placed

over the shaved skin, the skull, and the dura mater. The rat brain was selected in this study due to its

common usage as an animal model. We anticipate that the results of this study will provide a reference

point for more realistic estimations of the electric field distribution in other studies using the rat model

and help to improve the reproducibility of the reported tES effects. Some of the results, such as the

shunting effect of the skin and the CSF, agree with modeling predictions, while some others such as the

much smaller attenuation by the rat skull, the E-field peaks at the white/gray matter border, and

insensitivity of the field to the reference electrode location are among the practical findings of this

study.

II. METHODS

Animal Surgery

Nine Sprague Dawley (SD) rats (250-350g, male) were used in this study for direct measurements of the

electric field distribution in the brain parenchyma. All procedures were approved and performed in

accordance with the guidelines of the Institutional Animal Care and Use Committee (IACUC), Rutgers

University, Newark, NJ. Anesthesia was induced with 5% isoflurane gas in an induction chamber,

maintained by 1-3% isoflurane in 95% oxygen after moving the animals to a stereotaxic frame, and

monitored using the toe pinch reflex. Blood oxygen level was monitored via a pulse oximeter from the

hind paw. Body temperature was measured with a rectal temperature probe and regulated with a

heating pad underneath the animal over the course of surgery. The hair over the head was shaved with

an electric shaver and treated with a depilatory cream to remove the fine hair. The skin was cleansed

with antiseptic solution.

Current Injection over the Skin:

Either 4mm diameter pellet electrodes (EP4, Ag/AgCl, World Precision Inst., FL) or 1.5mm diameter

helical wire electrodes were used to inject the electric currents. The pellet electrode was positioned

such that medial edge was juxtaposed to the sagittal suture and the caudal edge to the coronal suture.

For helical electrodes, a Ag/AgCl wire with 125μm uncoated thickness (A-M Systems, #786000) was

wrapped around a 1.25mm diameter rod 4 times to form a helix with a large surface area and thus a

lower impedance. The impedance was confirmed to be below 10kΩ @1kHz in PBS. The helical electrode

was filled with conductive gel in the center to ensure good contact with the skin and distribute the

current more uniformly at the base of the electrode. The helical electrode was placed with its center

positioned 2mm lateral (left or right) from the sagittal suture and 2mm either rostral or caudal to the

coronal suture. Another Ag/AgCl wire was inserted to the ipsilateral shoulder muscles as the return

(cathodic) electrode for the injected current. Ten monophasic anodic pulses were delivered as a train at

100μA amplitude, 100ms pulse width, and a repetition rate of 4Hz. The amplitude was switched to

200μA at times to increase the signal-to-noise ratio where the recorded amplitudes were too small. In

this protocol, substituting pulsed stimulation for DC allowed us to overcome the poor DC response of

the metal recording electrodes.

A sharp cut was made into the skin with a surgical blade at the edge of the stimulation electrode

to expose the skull caudally while leaving the skin underneath the electrode intact (Fig. 1B). Two 1mm

diameter craniotomy holes were drilled 2mm and 4mm away from the caudal edge of the stimulation

electrode using a micro drill (OmniDrill 35, World Precision Inst., FL). A tungsten electrode (0.5 MΩ,

TM33B05H, World Precision Inst.) was inserted into the craniotomy hole to record the induced voltages

as a function of depth with respect to another Ag/AgCl reference electrode attached on the skull near

the recording electrode using dental acrylic. The dura was punctured with the sharp tip of the tungsten

electrode and the first recording was made at the level of the cortical surface (depth=0). Using a 10μ-

resolution micromanipulator, the tungsten electrode was advanced into the brain parenchyma in 0.2mm

steps until reaching 4mm depth and thereafter in 0.5mm steps up to a depth of 6mm. The procedure

was repeated in both craniotomy holes, at 2mm and 4mm horizontal distances from the stimulation

electrode. The rising and falling edges of the recorded signals were marked using an automated

algorithm in MATLAB (Mathworks) to quantify the induced voltage amplitudes. In some animals, this

procedure was repeated on the contralateral side of the brain to obtain an additional set of

measurements.

Fig. 1: Drawings show the three different placements of the stimulation electrode on the rat's

head: A) top view. The vertical cross sections of the skin and skull in B, C, and D show the placements of

the helical wire stimulation electrode: B) over-the-skin, C) over-the-skull, and D) over-the-dura, and the

craniotomy holes for E-field measurements. Tungsten recording electrodes were inserted through the

craniotomy holes at 0mm (for over-the-dura stimulation only), 2mm and 4mm horizontal distances from

the stimulation electrode

Current Injection over the Skull:

The skin over the top of the skull was completely removed in this step, mostly in the same animals used

above. After removing the periosteum, bone wax was applied to the muscles around the edges and the

skull sutures on top to stop bleeding. The stimulation electrode (pellet or helical wire) was placed onto

the skull (Fig. 1C) at the same coordinates used with over-the-skin electrodes. The voltage recordings

were made following the same procedure above with slight repositioning of the tungsten electrode in

the same craniotomy holes in order to avoid damaged tissue from the previous penetration.

Current Injection over the Dura:

A 2mm craniotomy hole was made at the coordinates of the stimulation electrode to inject the current

directly through the dura (Fig. 1D). A helical wire electrode (1.5mm diam.) was placed about 0.5mm

above the dura matter and anchored to the edge of the skull hole with small amounts of cyanoacrylate

glue and the hole was filled with normal saline. The distances between the caudal edge of the helical

electrode and recording holes were kept at 2mm and 4mm as before. With the use of helical electrodes,

an additional set of voltage recordings were made by inserting the tungsten electrode through the

center of the stimulation electrode (horizontal distance=0mm).

Finally, in order to investigate the effect of the current return electrode position, the Ag/AgCl

wire inserted to the ipsilateral shoulder muscles was moved to the contralateral shoulder, the hind leg,

and the submandibular muscles via needle insertions. The voltage measurements were repeated near

the cortex and at various depths with the recording electrode in the center of the helical electrode for

these four different positioning of the current return electrode for comparison.

Data Collection and Analysis:

The signal were collected in a large Faraday cage and first amplified by a gain of 100 (Model 1700, A-M

Systems, WA) with filters setting of 10 Hz–10 kHz, and then sampled at 25kHz through a National

Instruments data acquisition board (PCI 6071) controlled by custom-designed MATLAB codes. Stimulus-

triggered averaging (STA) was used (N=10) to suppress the background neural activity and other sources

of random noise. The averaged signal was further band-pass filtered in MATLAB (10-1000Hz) before

analyzing. Voltage transitions within 2ms window around the rising edge of the square pulses were

taken as the induced voltage at the corresponding depth. The first derivative of the voltage data with

respect to depth was computed as the electric field (E-field). All field measurements were made

exclusively in the vertical direction (VE-field) in this study. Horizontal E-field measurements would

require derivation of the voltage measurements made through different brain penetrations and lead to

large calculation errors due to even slight changes in the absolute value of the voltages measured, which

could easily occur from repositioning of the recording reference electrode between penetrations.

Comparison with Theoretical Models

The resistance of a monopolar disk electrode at the surface of a semi-infinite, homogeneous, and

isotropic medium was first derived by Newman (23) as a function of the electrode radius (*a*), and the

conductivity of the medium (σ). The potential at the surface is found as $Vo = I/(4\sigma a)$, where *I* is the

electrode current. Wiley and Webster then solved the Laplace's equation for the voltage distribution

inside the semi-infinite volume conductor for a similar disk electrode (24). By substituting zero for the

horizontal axis *r* in their equation, we find the voltage at the electrode center, which starts from *Vo* at

z=0 and declines with increasing values of the vertical axis (*z*) according to the equation

$(2Vo/\pi)\sin^{-1}(a/\sqrt{z^2 + a^2})$. The VE-field, however, decreases as a function of $\varphi = -(2Vo/\pi)(a/z^2 +$

$a^2)$, which can be found easily by differentiating the voltage equation with respect to *z,* and the peak

value of the VE-field at the surface (*z*=0, r=0) is $\varphi = -2Vo/(\pi a)$ or $\varphi = I/(2\pi\sigma a^2)$. We fit the VE-field

equation to our data collected with the epidural placement of the electrode at its center while leaving

Vo as a free parameter (Fig. 2, 0mm). The *Vo* value that fits the experimental data best for r=0 was also

used to plot the VE-field equation at r=2mm and r=4mm from the center of the stimulation electrode in

Fig. 2 (2mm and 4mm). The VE-field is shown as a 2D heat plot in Fig. 3 for comparison with the

experimental data and will be discussed at the end.

Fig. 2: Voltage (top row) and E-field (bottom row) measurements made with epidural (as in Fig.

1D) placement of the Ag/AgCl helical wire stimulation electrode with 1.5 diam. Top Row Left to Right:

Voltage measurements made with respect to a reference on the skull and via penetrations at the center

(0mm), 2mm from the center, and 4mm from the center of the helical electrode. Seven sets of

measurements were collected in five animals. Bottom Row: The mean of the vertical E-fields calculated

by differentiating the voltage measurements shown in the top row for each penetration separately. The

shady areas indicate ± standard error. The black solid line is the VE-field predicted by the analytical

equation derived by Wiley & Webster (24) that provided the best fit, i.e. highest coefficient of

determination (R2), when V(0,0) is set to 58.33mV. For 2mm and 4mm penetrations, the analytical

equation was evaluated (solid black lines) using the same V(0,0) value for consistency.

Fig. 3: Vertical E-field distribution as a heat plot on a logarithmic scale; obtained by interpolating

the measurements (left panel) presented in Fig. 2, and predicted by the analytical equations of Wiley &

Webster (right panel). Depth=0 corresponds to the surface of the cortex.

III. RESULTS

VE-Fields with Epidural Injection of Current

The peak-to-peak voltage induced by the current pulse was measured as a function of depth down to

6mm from the dura surface (Fig. 2, top row) at 0mm (center of the helix), 2mm, and 4mm away

horizontally from the stimulation electrode (see Fig. 1). Vertical electrical fields (VE-fields) were

computed by differentiating the raw voltage measurements without any filtering or curve fitting, and

averaged across the animals (Fig. 2, bottom row). Note that the vertical offset in the voltage plots of the

top row do not carry any significance since they can vary between animals depending on where the

recording reference electrode is placed along the current pathways between the stimulation and the

returning electrodes. The voltage curves decline faster under the stimulation electrode with maximum

values underneath the dura (depth=0mm), as expected. The VE-field was also maximum under the

stimulation electrode (distance=0mm, depth=0mm) near the cortex, declined exponentially, and lost

more than 75% of its strength by 2mm below the stimulation electrode and further decreased down to

negligible levels by 6mm. The analytical equation by Wiley and Webster (see methods) was evaluated

and fit to the VE-field by using *Vo* as the free parameter. The analytical formula provided a good-fit

(R^2=0.92) including the initial plateau near the cortical surface for *Vo*=58.33mV. As the recording

electrode was moved horizontally to 2mm and 4mm away from the stimulation site, the VE-field decline

near the surface became sharper and an elevation appeared at deeper levels, the latter of which was

predicted by the analytical equation. The sharp decline was not predicted by the analytical equation

since the semi-infinite model assumes a non-conductive medium above the surface and a zero vertical

current at the boundary. The band of large VE-fields extending horizontally underneath the surface can

also be appreciated from the heat plot of Fig. 3A. Interestingly, for all penetrations (0, 2, 4mm) there

seems to be a peak in the E-field near or a little above the 2mm mark, which may indicate a sharp

change in tissue conductivity, e.g. from gray matter to white matter. The analytical equations fail to

predict the VE-field amplitudes, in general, at 2mm and 4mm from the stimulation electrode with the

same *Vo* used at 0mm. Thus, the VE-fields expand more in the horizontal direction than predicted.

Comparison of VE-Fields with Current Injections over the Skin, Skull, and Dura

Figure 4 compares the VE-fields with three different placements of the helical electrode; over the skin,

skull, and dura. The epidural stimulation produces the largest electric field intensities in the brain

parenchyma while epidermal placement produces the lowest intensity, as expected, both at 2mm and

4mm horizontal locations from the electrode. Note that for over-the-skin and skull placements of the

stimulation electrode the E-fields were not measurements in the center of the electrode in order not to

disturb the intactness of the skin or skull with a penetration hole. The skin attenuated the VE-field to a

much larger degree than the skull, as seen with both penetrations at 2mm and 4mm horizontal locations

from the edge of the stimulation electrode. The over-the-skin placement did not produce an

exponentially decreasing VE-field profile by depth as the other two placements of the stimulation

electrode, and the VE-fields measured at the cortical surface (depth=0) were about an order of

magnitude smaller. The skin thickness was measured at the end of the experiment and found to be

around 0.5mm under the stimulation electrode.

Fig. 4: Comparison of VE-fields for three different placements of the helical wire electrode over

the skin, skull, and dura mater. Measurements are repeated at 2mm (left column) and 4mm (right

column) horizontal distances from the helical electrode. The averages of (n) measurement sets are

plotted (solid lines) and the standard errors are shown as shadings.

The VE-fields were also compared with larger Ag/AgCl pellet electrodes (diam.=4mm) placed

either over the skin or skull (Fig. 5). At a horizontal distance of 2mm from the edge of the pellet

electrode, the presence of skin attenuated the electric fields by 3-4 times, similar to the smaller helical

electrodes, but the VE-field declined faster by depth with the pellet electrode compared to the smaller

helical electrodes. This was probably because the pellet electrode had a larger diameter and the 2mm

from the edge was actually further away from the electrode center compared to the helical electrodes.

A sharper decline in the field with increasing horizontal distances was also observed with the helical

electrode (Fig. 2). The VE-field bump around 1.5-2mm depth was observed consistently in these plots as

well. For both skin and skull placements of the stimulation electrode, the measurements at 4mm were

about a few times smaller than those at 2mm.

Fig. 5: Comparison of VE-fields for two different placements of the large pellet electrode; over

the skin and skull. Details are same as in Fig. 4.

Location of the Current Return Electrode

Lastly, we investigated how the location of the stimulation reference electrode affects the electric field

strength in one rat. In the previous experiments, a Ag/AgCl wire inserted into the ipsilateral shoulder

was used as the cathode for current injection. For this experiment, three alternative sites were tested

for the cathodic electrode; contralateral shoulder, the submandibular muscles, and the ipsilateral hind

limb. The epidural stimulation experiments with the helical wire electrodes were repeated against these

reference electrode placements and the VE-fields between the depths of 0.6-2.0mm were measured in

five different craniotomy holes as the stimulus was applied through the same hole. The maximum

deviation from the ipsi-shoulder measurements was less than 1% with any of the new reference points.

None of the VE-field measurement sets (N=5) against the novel reference points were significantly

different from that of the set against the ipsi-shoulder electrode (paired t-test, $p>0.5$).

IV. DISCUSSION

E-field Attenuation by Skin and Skull

The skin thickness changes around the head and rodents are no exception to this rule. Because of the

compression we applied to hold the electrode down firmly on the skin, the skin thickness decreased

under the stimulation electrode during the course of the experiment and found to be ~0.5mm at the

end. Hence, we can only make general remarks about the skin effects on the E-field measurements in

the face of these sources of variability. About a four-fold decrease occurred in the VE-field when the

electrode was placed over the skin as opposed to the skull surface. The average skull thickness was

measured to be ~0.5mm (N=5). In agreement with this data, Vöröslakos et al. reported that

transcutaneous stimulation generated several-fold weaker electric fields compared to subcutaneous

stimulation in rats (20). There was only a marginal loss of electric field intensities when the stimulation

electrode was moved from the dural surface to the skull surface in our data.

With over-the-skin electrodes and 100μA current injection, the vertical electric field drops down

to ~1mV/mm at 2mm and 4mm from the stimulation electrode (Fig. 4). Terzulo and Bullock reported

that the firing frequency of neurons can be modulated by voltage gradients as low as 1mV/mm (9),

which is also the lower bound indicated by rodent studies (20,25). The large variability in the skin

thickness and the high conductivity of skin can make the results with epidermal montage highly

unpredictable. Therefore, placing the electrode over the skull would be a reasonable compromise to

mitigate the effects of current shunting by the skin and to improve the focality of stimulation, while

avoiding large E-field peaks as they occur with epidural stimulation.

We did not measure the VE-field at the electrode center with over-the-skull electrodes. The

epidural stimulations in Fig. 2 show the VE-field under the electrode decreases by about a factor of two

from the electrode center to 2mm off the center. If we can extrapolate from over-the-skull stimulations

in Fig. 4 at 2mm off the center, the VE-field in the electrode center should be about 20mV/mm at the

cortical level.

Non-Homogeneity of the Brain

That the skull resistivity was much higher than that of the skin and brain tissue was first demonstrated

by early intracerebral voltage measurement studies in human cadavers (26) and anesthetized monkeys

(16). Hayes predicted that the high conductivity of the skin and scalp would make the electrical fields

more or less uniform inside the brain. Our data with over-the-skin stimulation does not have the

exponentially decaying profile by depth as in over the skull and dura stimulations, and thus agrees with

Hayes' prediction in general. A particular aspect to note is the VE-field peak that occurred consistently at

around 1.5-2mm depths in most plots where the gray matter transitions into the white matter and a

significant change in local conductivity is expected. The lower conductivity of the white matter seems to

cause an elevation in the VE-field at the border of the two regions. The fact that the VE-field decline in

the gray matter is faster at 2mm and 4mm horizontal locations than at the electrode center (0mm, Fig.

2) must, however, be due to the higher conductivity of the cerebrospinal fluid near the surface, rather

than the gray/white matter conductivity differences.

Electrode Size

The electrode size is the primary factor that can help focalize the induced E-field and the affected

volume of tissue (27). Smaller size electrodes require less total current than larger electrodes to induce

the same current density at a fixed target point in the brain (28). However the current density at the

electrode surface is higher than that of the larger electrodes (29). We did not specifically compare the

two different electrode sizes we had due to insufficient statistical power in the data.

Monopolar vs. Bipolar Montages

Repositioning the return electrode from the shoulder to other muscles around the body introduced

changes smaller than 1% in the VE-field. This is explained by the fact that the voltage profile near the

anodic electrode is more or less the same with the monopolar montage so long as the large surface

return electrode is placed far enough in the body. The field steering effect begins to occur when the

return electrode is brought near the stimulation electrode, hence approximating a bipolar montage. The

sensitivity to the location of the return electrode may increase with epidermal placement of the anodic

electrode, especially at locations further away from it.

The fact that the E-field declines sharply by distance with monopolar montages is advantageous

for the spatial selectivity if the targeted neural structures are near the brain surface, but makes it

difficult to achieve significant E-fields at deeper brain regions without causing extreme electric fields

near the surface. Attempts to focus the electric field at subcortical brain regions using multiple

electrodes will have to cope with this challenge. Horizontal E-field can be maximized using bipolar

montages by placing both the cathode and the anode around the head on the sides, if the targeted

neural structures are inside the cortical sulci where the somato-dendritic axis of the neurons is oriented

horizontally. A recent paper (20) proposed both spatial focusing and time-multiplexing of the stimulus

currents via multiple dipoles in order to maximize the horizontal E-field at a focal point inside the brain

by taking advantage of the slow time constant of the cellular membranes at subthreshold potentials.

While the tES methods enjoy the benefits of being non-invasive, the challenge of focalization may

persist as the main disadvantage of the technique in the long run.

Stimulation Waveform

In our protocol, substituting DC with pulsed stimulation allowed us to overcome the poor DC response

of the tungsten recording electrodes. The brain tissue can be treated primarily as a resistive medium

and hence the recorded amplitudes to be independent of frequency, up to 10kHz and even higher

ranges (12,30) owing to the "quasi-static approximation". Thus, our amplifier's high cutoff (f_c) was set

to 10kHz, which has corresponding rise time of 15.9μs ($t_r = 1/2\pi f_c$) for a first-order filter. We took the

amplitude measurements 1ms after the pulse transition, allowing several rise times for the signals to

stabilize while still being much shorter than the time constant imposed by the lower cutoff frequency of

the amplifier ($t_r = 15.9ms$, 10Hz) .

A sinusoidal waveform at a constant frequency (e.g. 1kHz) could also be used for the stimulus

current in this study instead of rectangular pulses. A stimulus waveform with a single frequency would

overcome the bandwidth limitations of the metal recording electrodes and the amplifier, which

attenuates the harmonics of a rectangular waveform to different degrees and distorts the recorded

waveforms. The advantage of the rectangular waveform, however, is that any disturbance to the

electrode tip during penetration manifests itself not only as a change in the measured amplitudes but

also as a distortion in the waveform, and thus alerts the experimenter about the quality of the signals.

With sinusoidal waveforms, only the signal amplitude would change, which would escape the attention

of the experimenter and lead to significant miscalculations of the E-field.

Comparison with Theoretical Models

Despite the fact that Wiley & Webster equation (24) assumes a homogeneous medium, and does not

account for the impedance of the electrode-electrolyte interface and the current redistribution across

the electrode surface due to amplitude and frequency dependency of the interface (31), it provides a

reference point for comparison. Comparison of the experimental data with the theoretical model in 2D

(Fig. 3) reveals some fundamental similarities but also significant differences. Both plots show that the

largest VE-fields occur under the electrode, but the experimental VE-field diminishes within the gray

matter for the most part, subsiding to negligible levels in the white matter. In the experimental data the

VE-field spreads more in the horizontal direction near the surface most likely due to the high

conductivity of the CSF, and perhaps the gray matter also. The theoretical plot assumes a non-

conductive medium above the brain and does not account for the presence of the skull. There are

clearly regions of varying conductivities in the experimental data that cause inhomogeneities in the

electric field. Lastly, the VE-peaks at the electrode edges that are suggested by the earlier analytical

models (24) were not observed in the experimental data. This may be because of the distance (~0.5mm)

allowed between the electrode surface and the brain cortex in our setup, or it may be explained partially

by the presence of the electrode-electrolyte interface as predicted by more advanced models (31).

Practical Considerations

The surface area of the electrode that is in contact with tissue primarily determines the E-field strength

in the vicinity of the electrode. Therefore, epidural placement of the stimulation electrode may lead to

large variations in the E-fields in the cortex depending on the exact position of the electrode. If the

electrode contact area with the cortex is well defined, the simple analytical equations (24) can become

very useful for predicting the potential and the VE-field underneath the electrode. The equation for the

VE-field at the surface (z=0, r=0) is $\varphi = -2Vo/(\pi a)$. For *Vo* value that gives the best fit with this equation

to our data was found to be 58.33mV. Assuming a homogenous medium, an overall conductivity value

of 0.57 S/m can be found by substituting this value of *Vo* into the Newman equation ($Vo = I/(4\sigma a)$),

which is about three times higher than the commonly used conductivity for the brain, most likely due to

the high conductivities of the CSF. For a known electrode diameter and current, one can use this

'modified' conductivity value to estimate the VE-field peak underneath the epidural electrodes. Having

an accurate prediction for the vertical E-field near the surface, where most of the cortical neurons are

found in an animal with a lissencephalic brain like the rat, can prove to be useful when direct

measurements of the field is not possible.

The current distribution across the disk electrodes is predicted to suffer from edge-effects by

earlier models (24). Inclusion of the electrode-electrolyte interface into the model produces a more

uniform current profile across the surface, although the effect is amplitude and frequency dependent

(31). The choice of the electrode material thus is crucial to minimize the electrode-electrolyte

impedance and improve reproducibility. In order to prevent the edge effects from influencing the E-

field distribution inside the brain, the stimulation electrode can be kept at a distance from the

superficial layers of the cortex. The skull can serve as a spacer in this case. The disk electrode can be

attached onto the skull at reproducible stereotaxic coordinates and the top of the electrode can be

covered with some nonconductive material to prevent current spreading through the skin. The skull

thickness at the point of electrode placement can be standardized to a degree by controlling the

weight/age of the animal. Alternatively, one can also make a craniotomy hole and fill it with conductive

gel or isotonic saline and position the stimulation electrode at a known distance above the cortex as we

did in this study. Because normal saline has a conductivity (1.67 S/m) that is about eight times higher

than that of the brain (0.2 S/m), the stimulation electrode may electrically be assumed to be on the

cortex/saline interface for practical purposes. The highly conductive saline may however be replaced

with encapsulation tissue by time in chronic implants. For most reproducible results, the E-field should

be measured directly inside the tissue in each animal separately if this can be done without disturbing

the intactness of the neurons or the E-field itself.

V. CONCLUSIONS

This study provides experimental data as a reference point for more realistic estimates of the electric

fields induced in the rat brain during tES studies. The skin attenuates the electric field much more

strongly than the skull and causes the current spread more uniformly inside the skull. For focal

stimulation, it may be best to place the stimulation electrode on the skull to avoid the skin effect. The

electrical field perpendicular to the cortex decreases exponentially near the surface and loses most of its

strength within 2mm into the brain underneath the electrode and within 1mm of depth off of the

electrode edge. A 100µA current injected through a 1.5mm over-the-skull electrode is predicted to

generate ~20mV/mm at the cortical surface. For epidural placements of the stimulation electrode

through a craniotomy hole, a modified value of 0.57 S/m for the brain conductivity can be assumed to

estimate the voltage at the cortical surface using the volume conductor equations. Significant E-field

peaks occur in the brain parenchyma, most likely due to local conductivity changes, especially at the

gray/white matter border. These large fluctuations in the E-field measurements by depth show that the

homogeneous volume conductor assumption is too simplistic for a model to estimate the local effects of

the injected currents.

ACKNOWLEDGMENTS

Supported by NIH/NINDS Grant No: R21 NS101386.

REFERENCES

1.   Priori A. Brain polarization in humans: A reappraisal of an old tool for prolonged non-invasive

modulation of brain excitability [Internet]. Vol. 114, Clinical Neurophysiology. Elsevier; 2003

[cited 2018 May 14]. p. 589–95. Available from:

https://www.sciencedirect.com/science/article/pii/S1388245702004376?via%3Dihub

2.   Chhatbar PY, Chen R, Deardorff R, Dellenbach B, Kautz SA, George MS, et al. Safety and

tolerability of transcranial direct current stimulation to stroke patients – A phase I current

escalation study. Brain Stimul [Internet]. 2017 May 1 [cited 2018 Aug 14];10(3):553–9. Available

from: https://www.sciencedirect.com/science/article/pii/S1935861X17306149?via%3Dihub

3.   Bikson M, Grossman P, Thomas C, Zannou AL, Jiang J, Adnan T, et al. Safety of Transcranial Direct

Current Stimulation: Evidence Based Update 2016 [Internet]. Vol. 9, Brain Stimulation. Elsevier;

2016 [cited 2018 Feb 17]. p. 641–61. Available from: https://www-sciencedirect-

com.libdb.njit.edu:8443/science/article/pii/S1935861X16301401

4.   Woods AJ, Antal A, Bikson M, Boggio PS, Brunoni AR, Celnik P, et al. A technical guide to tDCS,

and related non-invasive brain stimulation tools. Clin Neurophysiol [Internet]. 2016 Feb [cited

2018 Feb 12];127(2):1031–48. Available from: http://www.ncbi.nlm.nih.gov/pubmed/26652115

5.   Creutzfeldt OD, Fromm GH, Kapp H. Influence of transcortical d-c currents on cortical neuronal

activity. Exp Neurol [Internet]. 1962 Jun 1 [cited 2018 May 24];5(6):436–52. Available from:

https://www.sciencedirect.com/science/article/pii/0014488662900560

6.   Bindman LJ, Lippold OCJ, Redfearn JWT. The action of brief polarizing currents on the cerebral

cortex of the rat (1) during current flow and (2) in the production of long-lasting after-effects. J

Physiol [Internet]. 1964 Aug 1 [cited 2018 Jan 29];172(3):369–82. Available from:

http://www.ncbi.nlm.nih.gov/pubmed/14199369

7.   Nitsche MA, Paulus W. Excitability changes induced in the human motor cortex by weak

transcranial direct current stimulation. J Physiol. 2000 Sep;527 Pt 3:633–9.

8.   Lang N, Siebner HR, Ward NS, Lee L, Nitsche MA, Paulus W, et al. How does transcranial DC

stimulation of the primary motor cortex alter regional neuronal activity in the human brain? Eur J

Neurosci [Internet]. 2005 Jul 21 [cited 2018 Feb 12];22(2):495–504. Available from:

http://www.ncbi.nlm.nih.gov/pubmed/16045502

9.   Terzuolo CA, Bullock TH. Measurement of imposed voltage gradient adequate to modulate

neuronal firing. Proc Natl Acad Sci U S A [Internet]. 1956 Sep 1 [cited 2018 May 14];42(9):687–94.

Available from: http://www.ncbi.nlm.nih.gov/pubmed/16589932

10.   Bikson M, Inoue M, Akiyama H, Deans JK, Fox JE, Miyakawa H, et al. Effects of uniform

extracellular DC electric fields on excitability in rat hippocampal slices in vitro. J Physiol [Internet].

2004 May 1 [cited 2018 Feb 14];557(1):175–90. Available from:

http://doi.wiley.com/10.1113/jphysiol.2003.055772

11.   Radman T, Ramos RL, Brumberg JC, Bikson M. Role of cortical cell type and morphology in

subthreshold and suprathreshold uniform electric field stimulation in vitro. Brain Stimul

[Internet]. 2009 Oct 1 [cited 2018 Feb 12];2(4):215–228.e3. Available from: https://www-

sciencedirect-com.libdb.njit.edu:8443/science/article/pii/S1935861X09000424

12.   Miranda PC, Lomarev M, Hallett M. Modeling the current distribution during transcranial direct

current stimulation. Clin Neurophysiol [Internet]. 2006 Jul [cited 2018 Feb 17];117(7):1623–9.

Available from: https://ac-els-cdn-com.libdb.njit.edu:8443/S1388245706001726/1-s2.0-

S1388245706001726-main.pdf?_tid=spdf-bcaa1334-c0a1-4d41-ace8-

3264c5f7dbcf&acdnat=1518917934_be472fc3bac6d2140f8f7e1c73e4eb56

13.   Datta A, Bansal V, Diaz J, Patel J, Reato D, Bikson M. Gyri-precise head model of transcranial

direct current stimulation: Improved spatial focality using a ring electrode versus conventional

rectangular pad. Brain Stimul [Internet]. 2009 Oct [cited 2018 May 29];2(4):201–207.e1. Available

from: http://www.ncbi.nlm.nih.gov/pubmed/20648973

14.   Opitz A, Paulus W, Will S, Antunes A, Thielscher A. Determinants of the electric field during

transcranial direct current stimulation. Neuroimage. 2015 Apr;109:140–50.

15.   Jackson MP, Rahman A, Lafon B, Kronberg G, Ling D, Parra LC, et al. Animal models of transcranial

direct current stimulation: Methods and mechanisms. Clin Neurophysiol [Internet]. 2016 Nov

[cited 2018 Feb 12];127(11):3425–54. Available from:

http://www.ncbi.nlm.nih.gov/pubmed/27693941

16.   Hayes KJ. The current path in electric convulsion shock. Arch Neurol Psychiatry [Internet]. 1950

Jan 1 [cited 2018 Feb 20];63(1):102–9. Available from:

http://archneurpsyc.jamanetwork.com/article.aspx?doi=10.1001/archneurpsyc.1950.023101901

08008

17.   Chan CY, Nicholson C. Modulation by applied electric fields of Purkinje and stellate cell activity in

the isolated turtle cerebellum. J Physiol [Internet]. 1986 Feb [cited 2018 Jun 8];371:89–114.

Available from: http://www.ncbi.nlm.nih.gov/pubmed/3701658

18.   Chan CY, Hounsgaard J, Nicholson C. Effects of electric fields on transmembrane potential and

excitability of turtle cerebellar Purkinje cells in vitro. J Physiol [Internet]. 1988 Aug [cited 2018

Jun 8];402:751–71. Available from: http://www.ncbi.nlm.nih.gov/pubmed/3236254

19.   Opitz A, Falchier A, Yan C-G, Yeagle EM, Linn GS, Megevand P, et al. Spatiotemporal structure of

intracranial electric fields induced by transcranial electric stimulation in humans and nonhuman

primates. Sci Rep [Internet]. 2016 Nov 18 [cited 2018 Jan 29];6(1):31236. Available from:

http://www.nature.com/articles/srep31236

20.   Vöröslakos M, Takeuchi Y, Brinyiczki K, Zombori T, Oliva A, Fernández-Ruiz A, et al. Direct effects

of transcranial electric stimulation on brain circuits in rats and humans. Nat Commun [Internet].

2018 Dec 2 [cited 2018 Apr 14];9(1):483. Available from:

http://www.nature.com/articles/s41467-018-02928-3

21.   Gasca F, Marshall L, Binder S, Schlaefer A, Hofmann UG, Schweikard A. Finite element simulation

of transcranial current stimulation in realistic rat head model. In: 2011 5th International

IEEE/EMBS Conference on Neural Engineering [Internet]. IEEE; 2011 [cited 2018 Jun 25]. p. 36–9.

Available from: http://ieeexplore.ieee.org/document/5910483/

22.   Huang Y, Liu AA, Lafon B, Friedman D, Dayan M, Wang X, et al. Measurements and models of

electric fields in the in vivo human brain during transcranial electric stimulation. Elife [Internet].

2017 Feb 7 [cited 2018 May 8];6:e18834. Available from: https://elifesciences.org/articles/18834

23.   Newman J. Resistance for Flow of Current to a Disk. J Electrochem Soc [Internet]. 1966 May 1

[cited 2018 Aug 14];113(5):501. Available from: http://jes.ecsdl.org/cgi/doi/10.1149/1.2424003

24.   Wiley JD, Webster JG. Analysis and control of the current distribution under circular dispersive

electrodes. IEEE Trans Biomed Eng [Internet]. 1982 May [cited 2018 Jun 21];29(5):381–5.

Available from: http://ieeexplore.ieee.org/document/4121424/

25.   Ozen S, Sirota A, Belluscio MA, Anastassiou CA, Stark E, Koch C, et al. Transcranial electric

stimulation entrains cortical neuronal populations in rats. J Neurosci [Internet]. 2010 Aug 25

[cited 2018 Jan 29];30(34):11476–85. Available from:

http://www.ncbi.nlm.nih.gov/pubmed/20739569

26.   Smitt JW, Wegener CF. ON ELECTRIC CONVULSIVE THERAPY: with particular regard to a parietal

application of electrodes, controlled by intracerebral voltage measurements1. Acta Psychiatr

Scand [Internet]. 1944 Dec 31 [cited 2018 Jun 1];19(3–4):529–49. Available from:

http://doi.wiley.com/10.1111/j.1600-0447.1944.tb04586.x

27.   Nitsche MA, Doemkes S, Karakose T, Antal A, Liebetanz D, Lang N, et al. Shaping the Effects of

Transcranial Direct Current Stimulation of the Human Motor Cortex. J Neurophysiol [Internet].

2007 Apr [cited 2018 Jun 25];97(4):3109–17. Available from:

http://www.physiology.org/doi/10.1152/jn.01312.2006

28.   Faria P, Hallett M, Miranda PC. A finite element analysis of the effect of electrode area and inter-

electrode distance on the spatial distribution of the current density in tDCS. J Neural Eng

[Internet]. 2011 Dec 1 [cited 2018 Jun 25];8(6):066017. Available from:

http://stacks.iop.org/1741-

2552/8/i=6/a=066017?key=crossref.83f3d9681922067b4b8b72fa29d78dd5

29.   Miranda PC, Faria P, Hallett M. What does the ratio of injected current to electrode area tell us

about current density in the brain during tDCS? Clin Neurophysiol [Internet]. 2009 Jun 1 [cited

2018 May 14];120(6):1183–7. Available from:

https://www.sciencedirect.com/science/article/pii/S1388245709003046?via%3Dihub

30.   Ruffini G, Wendling F, Merlet I, Molaee-Ardekani B, Mekonnen A, Salvador R, et al. Transcranial

current brain stimulation (tCS): models and technologies. IEEE Trans Neural Syst Rehabil Eng

[Internet]. 2013 May [cited 2018 May 8];21(3):333–45. Available from:

http://ieeexplore.ieee.org/document/6290404/

31.   Cantrell DR, Inayat S, Taflove A, Ruoff RS, Troy JB. Incorporation of the electrode–electrolyte

interface into finite-element models of metal microelectrodes. J Neural Eng [Internet]. 2008 Mar

1 [cited 2018 Aug 14];5(1):54–67. Available from: http://stacks.iop.org/1741-

2552/5/i=1/a=006?key=crossref.c9d5638f9a5fad901b3b72c69ac1b84a

Pellet comparison : 2mm

4mm

Skin

Skull

n = 6

n = 6

n = 6

n = 6

VE-field (mV/mm)

Depth (mm)

Depth (mm)