A Mechanism of Real-Time Noise Modulation in Neurons

[1]Sharmila Venugopal*, [1]Soju Seki, [5]David H Terman, [3]Antonios Pantazis, [3]Riccardo Olcese, [4]Martina Wiedau-Pazos, [1,2]Scott H Chandler

[1]Department of Integrative Biology and Physiology
[2]The Brain Research Institute
[3]Departments of Anesthesiology & Perioperative Medicine and [4]Neurology
David Geffen School of Medicine, University of California Los Angeles

[5]Department of Mathematics
The Ohio State University

*Editorial and manuscript correspondence to SV
Department of Integrative Biology and Physiology
University of California Los Angeles
621, Charles E Young Drive South, LSSA 4214
Los Angeles, CA 90095
Phone: (310) 206-0332
Email: vsharmila@g.ucla.edu

pages: 25 (including online methods section)
figures: 9
words in abstract: 159
words (Introduction, Results and Discussion): 3345
references: 36

Supplementary information included as one separate file: 4 figures, 1 table and Supplementary information including 2 pieces of model code, 3 pieces of dynamic-clamp C^{++} code, and, supplementary text detailing relevant theoretical analyses.

Author contributions: SV designed the study and conducted mathematical modeling and simulations with inputs from SHC; DHT and SV performed mathematical analyses; SS conducted *in vitro* patch-clamp electrophysiology and SV and SHC provided supervision; SS and AP performed the dynamic-clamp experiments with inputs from SV and RO provided supervision; AP implemented the Markov model and SV tested it; MWP generated the mice for the study; SV made the figures and wrote the manuscript; All the authors contributed to the final version.

Additional Information

Competing Interests
The authors declare no competing interests.

Uncertainties pose an ongoing challenge for information processing in the nervous system. It is not entirely clear how neurons maintain dynamic stability of information, encoded in the temporal features of spike trains, notwithstanding stochastic influences. Here we examined the contribution of subclasses of membrane sodium currents in real-time noise modulation in sensory neurons. Fast sodium (Na$^+$) currents are essential for spike generation, and a persistent Na$^+$ current can entrain preferred input frequencies via membrane resonance. Using mathematical modeling, theory and experiments, we show that a resurgent Na$^+$ current can stabilize the temporal features of burst discharge and confer noise tolerance. These novel insights reckon the role of biophysical properties of Na$^+$ currents beyond mere spike generation. Instead, these mechanisms might be how neurons perform *real-time* signal processing to maintain order and entropy in neural discharge. Our model analysis further predicts a negative feedback loop in the molecular machinery of an underlying Nav1.6-type Na$^+$ channel gating considered in this study.

Real-time signal detection in uncertain settings is a fundamental problem for information and communication systems. Our nervous system performs the daunting task of extracting meaningful information from natural environments and guides precise behaviors in *real-time*. Sensory neurons for instance use efficient coding schemes such as bursting that aid information processing [1]. Mathematical models of bursting have helped explain the basic structure of an underlying dynamical system as one in which, a slow process dynamically modulates a faster spike-generating process, leading to stereotypical alternating phases of spiking and quiescence [2, 3]. The so-called *recovery period* of the slow process governs the intervals between bursts which is often susceptible to random perturbations. Uncertainty in spike/burst intervals can alter the timing precision and information in a neural code[4]. Consequently, a mechanism that can control the refractoriness of spike and burst intervals notwithstanding stochastic fluctuations, may maintain order in neural spike trains and aid information processing. Here we examined a candidate mechanism involving neuronal voltage-gated Na$^+$ currents for a role in stabilization of burst discharge (durations and intervals), that can be important for real-time noise modulation.

Voltage-gated Na$^+$ currents are compulsory for spike generation in neurons. The molecular and structural diversity of Na$^+$ channels and the resultant functional heterogeneity and complexity, suggest their role beyond mere spike generation [5]. For instance, in addition to the fast/transient Na$^+$ current (I_{NaT})

mediating action potentials, a subthreshold activated persistent Na^+ current (I_{NaP}) participates in the

generation of subthreshold membrane oscillations (STO) (e.g., see[6]). These oscillations can lead to

membrane resonance by which, a neuron produces the largest response to oscillatory inputs of some

preferred frequency [7, 8]. Neurons utilize this mechanism to amplify *weak* synaptic inputs at resonant

frequencies [9]. The slow inactivation and recovery of I_{NaP} further provides for the slow process required

for burst generation [10] and therefore contributes to efficient information processing in multiple ways.

However, during ongoing activity, random fluctuations can alter the precision and order of bursts, that can

distort/diminish the information in neural code. Here, we provide evidence that a frequently observed Na^+

resurgent current (I_{NaR}) known to arise from an unusual open-channel unblocking of sodium channels [11],

might be a mechanism by which neurons arbitrate uncertainty and maintain order in spike trains. Some

Na^+ channels such as the Nav1.6-type mediate all the three currents, namely, I_{NaT}, I_{NaP}, and I_{NaR} and

here we show that these biophysical properties can confer *real-time* signal processing capacity to neurons.

Results

A workflow including the approaches that we used to examine the contribution of biophysical

properties of a neuron in shaping its signal processing capacity, is shown in **Fig. 1**. First, using

mathematical modeling we assembled the known biophysical properties of Nav1.6-type Na^+ currents

using a conductance-based Hodgkin-Huxley formalism[12]; we incorporated the model conductances into a

realistic neuron model and were able to reproduce experimentally observed stereotypical bursting (**Fig.**

1a). To test the effects of the model Na^+ currents in real neurons and to validate our predictions, we used

real-time closed-loop dynamic-clamp experiments in intrinsically bursting proprioceptive sensory neurons

in the brainstem (**Fig. 1b**). Furthermore, model stability analyses, and uncertainty measurements were

combined to explain the observed behaviors (**Fig. 1c**). Specifically, **Figs. 2** and **3** provide a description of

the model I_{Na}, and its novel I_{NaR} component; **Figs. 4**, **5** and **6** show how I_{NaR} can exclusively modulate

burst refractoriness by a putative negative feedback loop in the Na$^+$ channel gating; **Figs. 7** and **8** provide

evidence for I_{NaR}'s ability for real-time noise modulation. **Figure 9** sums up the workings of I_{NaR} and

I_{NaP} and their co-contribution to signal processing in neurons.

We began by formulating a conductance-based model for the Nav1.6-type Na$^+$ currents. **Figure**

2a illustrates the total I_{Na} as a sum of the three components in our model: transient, I_{NaT}, resurgent, I_{NaR},

and, persistent, I_{NaP} currents. The classic I_{NaT} has fast inactivation, on the order of 1 ms. The novel I_{NaR}

shows decay kinetics on the order of 10 ms, and the I_{NaP} shows slow inactivation and recovery, on the

order of 1000 ms. We established the above formulation for I_{Na} with distinct conductances for the three

components to permit examination of their exclusive contributions to neural dynamics, since these

components are experimentally inseparable[13-15]. Given these macroscopic currents may arise from a single

channel, we also implemented a state-based Markovian I_{Na} model [16] that does not dissociate the three

components and ensured qualitative and quantitative similarities in the total I_{Na} during spiking in both

models (see **Supplementary Fig. 1**). We further confirmed that our model I_{Na} satisfies the key

contingencies of Na$^+$ channels carrying I_{NaR} (see **Supplementary Fig. 2**).

We incorporated the model I_{Na} into a conductance-based single-compartment neuron model (see

schematic and membrane voltage trace in black in **Fig. 2b**). Together with a minimal set of Na$^+$, K$^+$ and a

leak conductance, the model neuron faithfully reproduced the expected rhythmic burst discharge observed

in proprioceptive brainstem Mesencephalic V (Mes V) sensory neurons; The I_{Na} generated during action

potentials is shown in expanded time in the figure (red trace). **Figure. 2c** shows a real-time closed-loop

dynamic-clamp experiment in an intrinsically bursting Mes V neuron. The control burst was generated by

simply driving the neuron with a step depolarization, following which, we blocked action potential

generation by bath application of tetrodotoxin (1 μM TTX) (see black horizontal bar in **Fig. 2c**).

Subsequently, we introduced the model I_{Na} in real-time during TTX application and by adjusting the

conductances of the three I_{Na} components suitably, we were able to regenerate action potential bursts (see

Methods on choice of conductance values); The dynamic-clamp I_{Na} generated during action potentials is

shown in expanded time in the figure for comparison with the model simulation in **Fig. 2b** (red trace).

A novel formalism for resurgent Na$^+$ current

The total I_{Na} in our model has a novel resurgent component, I_{NaR}; the transient and persistent

components are similar to our previous formalism [7]. **Figure 3a (left panel)** illustrates the proposed

mechanism of Na$^+$ resurgence [16], wherein a putative blocking particle occludes an open channel following

a brief depolarization such as during an action potential; subsequently during repolarization, a voltage-

dependent unblock results in a resurgent Na$^+$ current. Our I_{NaR} formulation recapitulates this unusual

behavior of Na$^+$ channels using nonlinear ordinary differential equations for a blocking variable (b_r) and

a competing inactivation (h_r) (see **Methods**). The resultant macroscopic I_{NaR} is gated by the unblocking

process represented by $(1 - b_r)$, wherein '1' represents all open channels and b_r reflects the proportion

of channels in blocked state at any instant: the steady-state voltage dependency of unblock, $(1 - br_\infty(V))$,

and the competing inactivation ($hr_\infty(V)$), in the model are shown in **Fig. 3a (middle panel)**, along with

the equation for I_{NaR}; the purple shaded region highlights the voltage-dependency of I_{NaR} activation

during open-channel unblock. In **Fig. 3a (right panel)**, we show simulated I_{NaR} (in red), peaking during

the recovery phase of spikes (in black). In **Fig. 3b (I.)**, we reproduced experimentally observed I_{Na} and

highlight the resurgent component in both model (*left*) and experiment (*right*), (inset shows experimental

protocol; also see legend and **Methods**). A comparative current-voltage relationship for the model and

experiments is shown in **Fig. 3b (II.)**; also see **Supplementary Fig. 3** for detailed kinetics of model I_{NaR}.

Resurgent Na$^+$ and its control of spike and burst intervals

Given that I_{NaR} is activated during the recovery phase of an action potential, physiologically, any

resulting rebound depolarization may control the spike refractory period, and increase spike frequency

and burst duration [17, 18]. We tested this by selectively increasing the maximal resurgent conductance g_{NaR}

in our model neuron simulation and in dynamic-clamp experiments as shown in **Figs. 4a** and **b**. We

quantified the inter-burst intervals (IBIs), burst duration (BD) and inter-spike intervals (ISIs) as shown in

Fig.4c-e. As expected, we noted that increasing g_{NaR}, reduced ISIs and increased BDs. Additionally, we

noted that, g_{NaR} increase resulted in longer IBIs (see red double arrows in **Figs. 4a**, **b** and **Fig. 4c**). This

was in contrast with the effects of the persistent Na$^+$ conductance, g_{NaP}, that *decreased* IBIs and had

negligible effects on ISIs as shown in **Fig. 5**; both currents increased the BDs (also see **Supplementary**

Fig. 4 for g_{NaR} and g_{NaP} subtraction experiments showing consistent reverse effects).

The effects of persistent I_{NaP} in reducing IBIs can be explained by its sub-threshold activation[7],

wherein increasing g_{NaP}, can *promote* burst initiation and therefore reduce IBIs. Additionally, a high g_{NaP}

together with its slow inactivation helps maintain depolarization that can prolong BDs. Its effect on ISI is

negligible, because, once activated, its slow inactivation accumulates between spikes and does not

contribute to rebound depolarization during ISIs. Clearly, one effect that is not immediately obvious is an

increase in IBI due to increases in g_{NaR}. The intervals between bursts signify the recovery time of the

slow process underlying bursting activity. Our highly reproducible effect of g_{NaR} on IBIs in sensory Mes

V neurons using dynamic-clamp experiments and its qualitative and quantitative similarities with the

model prediction clarifies that this slow recovery process is indeed the slow inactivation/recovery variable

for I_{NaP} as in the model. As such, we examined the g_{NaR} mechanism of IBI control by further analyses of

the simulated membrane potential (grey traces) and the slow I_{NaP} inactivation/recovery variable (overlaid

magenta traces) of the model neuron under three conditions shown in **Figs. 6a-c**: 1) with control values

of g_{NaR} and g_{NaP} (**Fig. 6a**), 2) an increase in g_{NaP} compared to control (**Fig. 6b**), and, 3) an increase in

g_{NaR} compared to control (**Fig. 6c**). The peak and trough of the slow inactivation/recovery correspond to

burst *onset* and *offset* respectively. Comparing these traces in the three panels, we note that an increase in

g_{NaR} effectively *facilitated* the slow inactivation during a burst (see curvy arrow in **Fig. 6c** and legend).

This observation was further supported by estimations of theoretical thresholds for *burst onset* and *offset*

for increasing values of g_{NaR} (**Fig. 6d**) and, similar thresholds for increasing values of g_{NaP} are provided

for comparison in **Fig. 6e** (see legend and **Supplementary Information** for details). Note that changes in

g_{NaR} did not alter the burst onset thresholds, consistent with a lack of resurgent current before spike onset

(see brown arrow indicating burst onset threshold in **Fig. 6d**); Whereas, increasing g_{NaR}, consistently

lowered the burst offset threshold for the slow inactivation/recovery (see highlighted dashed box with

arrows pointing to the burst offset thresholds decreasing with increasing g_{NaR} values in **Fig.6d**). The net

effect is longer recovery time between bursts and therefore prolonged IBIs. Additionally, in **Fig. 6d**, an

increase in g_{NaR} extended the range of slow inactivation/recovery for which stable bursting regime exists

(marked by the green circles). This *gain in stability* is indicative of a *negative feedback loop* in the Na$^+$

channel gating mechanism. As shown in **Fig. 6f** (see boxed inset), during a burst, presence of channel

unblocking mechanism and the resulting resurgent Na$^+$ can facilitate slow channel inactivation, however,

increasing inactivation, eventually shuts off the unblocking events as more channels inactivate (see

arrows), and this terminates the burst. The schematic on the left summarizes a negative feedback loop

between the unblocking and slow inactivation processes of Na$^+$ channels.

Burst refractoriness and noise tolerance offered by Na$^+$ currents

During quiescence/recovery periods between bursts, the membrane voltage can be perturbed by

ambient noise and stochastic inputs, that can induce abrupt spikes and therefore disrupt IBIs. We reasoned

that the gain in stability of burst discharge due to g_{NaR} might be a mechanism for noise tolerance. To test

this, we introduced a broadband white Gaussian noise to disrupt the rhythmic burst discharge in the model

neuron when no g_{NaR} was present as shown in **Figs. 7a, b**. Subsequent addition of g_{NaR} indeed

significantly restored burst regularity (**Fig. 7c**). Model analyses in the (h_p, V) phase plane provides insight

into the mechanism of I_{NaR} mediated noise tolerance. Briefly, we project a portion of a (h_p, V) trajectory

corresponding to the termination of one burst until the beginning of the next (see expanded insets in **Figs.**

7a, b, c) to the (h_p, V) diagrams shown in **Figs 7d, e, f** respectively (see **Supplementary Information**

for details). In **Fig. 7d**, beginning at the magenta circle, the (h_p, V) trajectory (magenta trace) moves to

the right as h_p recovers during an IBI, until a burst onset threshold is crossed; point where the blue circles

meet the red and black curves (see **Supplementary Information** for details), and eventually bursting

begins; see upward arrow marking a jump-up in V at the onset of burst. During a burst, while V jumps up-

and-down during spikes, h_p moves to the left as slow inactivation accumulates during bursting (left

arrow). Finally, when h_p reduces sufficiently, (h_p, V) gets closer to the burst offset threshold (points at

which the green and blue circles meet), and the burst terminates (down arrow). *What is key in this figure*

is that the IBI is well-defined as the time period in which the (h_p, V) trajectory moves along the red curve

of steady states during the recovery process and moves past the burst onset threshold until a burst begins.

However, when stochastic influences are present, the recovery period near-threshold is subject to random

perturbations in V and can cause abrupt jump-up/spikes during the recovery period (see expanded inset in

Fig. 7b). Projecting (h_p, V) during this period on to **Fig 7e**, we note that the near-threshold noise

amplitudes can occasionally push the (h_p, V) trajectory (magenta) above a green region of attraction and

this results in such abrupt spikes. Now, when g_{NaR} is added, the apparent restoration of burst regularity

(see **Fig. 7c**) can be attributed to an expansion in this green shaded region as shown in **Fig. 7f** (see arrow

pointing to a noise-tolerant region). In this situation, near-threshold random perturbations have less of an

effect during the recovery process to induce abrupt spikes. *This way, I_{NaR} filters random perturbations at*

burst offset and in turn contributes to burst refractoriness. We suggest that such a mechanism can offer

dynamic stability to neural discharge by damping the effects of random perturbations that can alter the

precision of bursts and therefore aid information processing.

Resurgent Na$^+$ and burst entropy

The spike/burst intervals, their timing precision and order are important for information coding [19-23]. Given our prediction that I_{NaR} can offer noise tolerance and stabilize burst discharge, we examined whether it can reduce uncertainty in spike/burst intervals and restore order in burst discharge. We tested this using model simulations and also verified the predictions using real-time dynamic-clamp experiments as shown in **Fig. 8a - d**. In both simulations and *in vitro* dynamic-clamp experiments, we disrupted the inter-event intervals (IEIs) by adding a broadband white noise input in addition to a constant step depolarization as shown by spike raster plots in **Figs. 8e** and **f**. Adding the g_{NaR} conductance successfully restored the order of bursts. We used Shannon's entropy as a measure of uncertainty in IEIs and show that increases in entropy up on noise addition could be reduced to control levels by addition of I_{NaR} as in **Fig. 8g** (see **Methods**). We also quantified the Coefficient of Variation (CV) and note that adding noise which primarily reduced burst intervals, indeed decreased the CV, due to reduced standard deviation (s.d.) of the IEI distribution. Subsequent addition of I_{NaR}, which significantly lengthened the IBIs, resulted in increases in CV values due to an increase in IEI s.d. Taken together, we suggest that I_{NaR} can serve an important role in information processing through its contribution to maintaining order and precision of spike/burst intervals in *real-time*.

Discussion

Using a unique combination of mathematical modeling, simulations, theory and real-time closed-loop experiments, we demonstrate a novel consequence of complex Na$^+$ currents in burst control, noise modulation and information processing in sensory neurons. While the subclasses of Na$^+$ currents presented here are experimentally inseparable, our unique and simplified modeling approach combined with *in silico* *knock-in* of each Na$^+$ current component in closed-loop dynamic-clamp experiments, allowed examination

of their individual contributions in shaping the neural discharge. Additionally, theoretical analyses

revealed a putative negative feedback loop in the Nav1.6-type Na$^+$ channel gating mechanism. These

results portend the apparent consequences on burst control and signal processing capacity of neurons when

these currents are present.

Stabilization of burst discharge and negative feedback loop in Na$^+$ channel gating

In contrast with I_{NaP}, which drives near threshold behavior and burst generation, I_{NaR} facilitated

slow channel inactivation as bursts terminate (also note [10]). Increased channel inactivation due to I_{NaR} in

turn prolonged recovery from inactivation required to initiate subsequent burst of activity. Such an

interaction between open-channel unblock process underlying I_{NaR}, and, the slow inactivation underlying

I_{NaP}, offer a closed-loop *push-pull* modulation of IBIs, suggesting a negative feedback control of sodium

channel activity by resurgent and persistent mechanisms during ongoing bursts. Specifically, presence of

I_{NaR} facilitates slow Na$^+$ inactivation as shown by our theoretical analyses of model behavior; such

enhanced slow channel inactivation eventually shuts off channel opening and unblocking. This resulted

in stabilization of the burst structure and regulation of IBIs. Theoretically, this represents an enlarged

separatrix (or boundary) for transitioning from a sub-threshold non-spiking behavior to bursting behavior

(see enlarged green shaded region in **Fig. 7f**), and the neuron becomes refractory to burst generation. Such

burst refractoriness was also the basis for noise tolerance.

Is this apparent effect of I_{NaR} physiologically plausible? Biophysical studies indicate that recovery

from fast inactivation is facilitated in sodium channels that can pass resurgent current [16]; as shown here,

this appears to be true for slow inactivation as well. Consistently, in the SCN8a knockout Med mouse,

which lack the Nav 1.6 sodium channel subunit, recordings from mutant cells showed an absence of

maintained firing during current injections, limited recovery of sodium channels from inactivation, and

failure to accumulate in inactivated states. This is attributed to a significant deficit in I_{NaR} [10, 17, 24].

Furthermore, maintained or repeated depolarization can allow a fraction of sodium channels in many

neurons to enter inactivation states from which recovery is much slower than for normal fast inactivation

(reviewed in [25]). Here, our simulations and model analyses predict that the presence, and increase in I_{NaR}

conductance, provides for a such a physiological mechanism to maintain sustained depolarization and

promote fast and slow channel inactivation.

Sodium currents and signal processing in neurons

Neuronal voltage-gated Na$^+$ currents are essential for action potential generation and propagation,

a mechanism explained by the classic Hodgkin-Huxley model[12]. However, to enable fight-or-flight

responses, an overt spike generation mechanism must be combined with *real-time* filters to extract

biologically relevant inputs from an uncertain input space. Here we show that, the complex biophysical

properties of Na$^+$ channels, can serve a role in *real-time* signal processing. A sub-threshold activated

persistent Na$^+$ current is known to contribute to membrane resonance, a mechanism of band-pass filtering

of preferred input frequencies[8]. We call this type of input gating, which is widely known to be important

for brain rhythms[8, 22], a *tune-in* mechanism. Stochastic influences such as ambient noise and synaptic

activity, can heighten the efficacy of a tune-in mechanism by amplifying weak inputs and can indeed

promote signal detection[26, 27]. Furthermore, the persistent Na$^+$ current is important for burst generation

and therefore also contributes to efficient coding[28, 29]. Then again, a resurgent Na$^+$ current, that turns on

during the repolarizing phase of an action potential, can facilitate further spike generation by providing

an after-depolarization[17]. Here we show that this mechanism can stabilize burst duration and intervals and

maintain order of burst discharge in the presence of stochastic inputs. During ongoing sensory processing,

we think that this can provide for a real-time *tune-out* mechanism, which stabilizes the bursts encoded due

to a detected input signal. This indeed needs to be validated in the presence of natural stimuli. However,

our model predictions, analyses and experimental validation based on a broadband noise and step input

strongly supports such a putative role. As summarized in **Fig. 9**, sensory neurons can utilize these

biophysical properties as a *real-time tune-in-tune-out* mechanism for gating preferred inputs and

dynamically attenuate random membrane fluctuations which can decrease uncertainty in neural code[30].

Figure Legends

Figure 1. A workflow showing the study components and approaches. a) Development of a
mathematical models for Nav1.6-type Na$^+$ current components. This is incorporated into a minimal
conductance-based model for a bursting neuron to investigate putative roles for these currents in neural
dynamics. **b)** Model predictions are iteratively validated using real-time closed-loop dynamic-clamp
experiments in brainstem proprioceptive sensory neurons. **c)** The observed effects on neural discharge are
explained using theoretical stability and uncertainty analyses.

Figure 2. Ionic conductance-based model for Nav1.6 type Na$^+$ currents with three components. a) A
simulated trace showing I_{Na}; the tree map shows each of the three components: transient I_{NaT}, resurgent
I_{NaR}, and, persistent I_{NaP}; These are also highlighted by the color-matched dashed boxes in the top panel.
The τ_{decay} shows the order of magnitude of the decay kinetics of the three components. **b)** *Left:* A
schematic showing a conductance-based minimal model for a bursting neuron with the I_{Na} incorporated;
also shown are potassium (I_K) and leak (I_{leak}) conductances in the model. *Right:* Model simulation
demonstrates rhythmic burst discharge and inset highlights the I_{Na} current in the model during action
potentials, in red. **c)** *Left:* Schematic shows the dynamic-clamp experimental approach in neurons in the
brainstem proprioceptive sensory nucleus (red) in a live brain slice preparation; V_m, indicates the
membrane potential. *Right*: Membrane potential recorded from a rhythmically bursting sensory neuron;
action potentials were blocked using 1 μM TTX, and dynamic-clamp model I_{Na} was applied to regenerate
spikes; double slanted lines indicate break in time; Inset highlights the dynamic-clamp I_{Na} in red, during
action potentials.

Figure 3. A novel mathematical model for the unusual resurgent component of the Nav1.6-type Na$^+$
current. a) *Left:* Schematic of voltage-dependent of state transitions for a Na$^+$ channel with a known
mechanism of unusual open-channel block/unblock (green circle); classic inactivation gate is shown in
blue (blue ball and chain). *Middle:* The steady-state voltage-dependencies of open-channel unblocking
$(1 - br_\infty(V))$ and a competing inactivation process $hr_\infty(V)$ for the novel resurgent component are shown
(also see Methods and Results); The purple shaded region highlights the voltage range over which I_{NaR}
can be observed during open-channel unblocking. The equation for I_{NaR} is shown with the blocking (b_r),
and, inactivation (h_r) gating variables (also see Methods). *Right:* The simulated I_{NaR} (in magenta) with

peaks occurring during the repolarization phase of action potentials (in black) is shown. **b) I.** A comparison between simulated I_{Na} and experimentally generated I_{Na} from voltage-clamp recording is shown; Boxed inset shows the experimental protocol typically used to test for voltage-dependent activation of I_{NaR}. **II.** Graphs show the nonlinear current-voltage relationship of peak resurgent current in the model (magenta) and average peak resurgent currents measured from voltage-clamp experiments (black); error bars show standard deviation (n=5 neurons from 5 animals).

Figure 4. Physiological consequences of I_{NaR} on neural discharge. a) Simulated membrane voltage for increasing values of g_{NaR}, and its effect on burst discharge. Value of 1x g_{NaR} adjusted to match experimental data in **(b)**. **b)** Dynamic-clamp addition of I_{NaR} in an intrinsically bursting sensory neuron and its response to increases in g_{NaR}; Values of g_{NaR} used are 2 and 4 nS/pF for 1X and 2X respectively. The red double arrows highlight increases in inter-burst interval (IBI) in both **(a)** and **(b)**. **c)** Burst features are highlighted in the left inset: burst duration (BD), and inter-spike intervals (ISI); box plots show IBI **(c)**, BD **(d)**, and ISI **(e)** for experimental traces presented in **(b)** in black, and maroon circles show simulated results. Error bars show minimum and maximum of the distribution for a 10 sec recording period.

Figure 5. Physiological consequences of I_{NaP} on neural discharge. a) Simulated membrane voltage for increasing values of, g_{NaP}, and its effect on burst discharge; Value of 1x g_{NaP} was chosen to match experimental data in **(b)**. **b)** Dynamic-clamp addition of I_{NaP} in an intrinsically bursting sensory neuron and its response to increases in g_{NaP}; Values of g_{NaP} used are 0.36 and 0.54 nS/pF for 1X and 1.5X respectively. The red double arrows highlight reduction in inter-burst interval (IBI) in both **(a)** and **(b)**. **c)** Burst features are highlighted in the left inset: burst duration (BD), and inter-spike intervals (ISI); IBI **(c)**, BD **(d)**, and, ISI **(e)** are shown for experimental traces presented in **(b)** in black; Maroon circles show simulated results. Error bars show minimum and maximum of the distribution for a 10 sec recording period.

Figure 6. Mechanism of action of I_{NaR} and I_{NaP} – Model analyses. a-c) The slow inactivation/recovery variable is overlaid (magenta) on membrane voltage traces (grey) under control **(a)**, increased g_{NaP} **(b)**, and increased g_{NaR} **(c)** conditions; The dark blue dashed lines in **(a-c)** indicate the maximum and minimum values of the persistent inactivation variable under control conditions; The light green arrow in **(b)**, highlights a reduced peak recovery required for burst onset; The light blue curvy arrows in **(b, c)** indicate reduced slow inactivation for burst termination. **d, e)** Bifurcation diagrams showing the steady-states and bursting regimes in the membrane voltage (V) and slow inactivation/recovery (h_p) phase plane. The red lines represent resting/quiescence states consistent with low values of h_p recovery. The meeting point of stable equilibria (red) and unstable equilibria (black solid lines) represents the theoretical threshold for burst onset (see **Supplementary Information**). The blue open circles are the unstable periodics that form region of attraction on either side of the stable equilibria for sub-threshold membrane voltage oscillations; The meeting point of the curve of unstable periodics with the stable periodics (green filled circles) represents the theoretical threshold for burst offset/termination (see **Supplementary Information**). The dashed boxes in **(d)** and **(e)** highlight shifts in burst offset thresholds due to increases

in g_{NaR} **(d)** and g_{NaP} **(e)**; brown dashed arrows in **(e)** highlight shifts in burst onset thresholds due to g_{NaP}
increases; 1X g_{NaR} = 3.3 nS/pF and 1X g_{NaP} = 0.5 nS/pF.

Figure 7. Resurgent Na$^+$ current stabilizes burst discharge and confers noise tolerance. a - c)
Simulated membrane voltage shows neural activity patterns without any g_{NaR} **(a)**, with added white noise
input **(b)**, and with subsequent addition of g_{NaR} **(c)**. Expanded regions in **(a-c)** show membrane voltage
sub-threshold oscillations (STO) during an inter-burst interval. Also overlaid is the evolution of the slow
sodium inactivation/recovery variable; Arrow indicates recovery during IBI, and magenta circle marks an
arbitrary time point used to track these trajectories in **(d - f)**. **d - f)** Bifurcation diagrams with projected
trajectories of (h_p, V), shown in magenta to highlight the effect of addition of noise near sub-threshold
voltages **(e)** and then the enlarged region of noise tolerance (highlighted green shaded region) due to
addition of g_{NaR} in **(f)**. The magenta circle marks the beginning time points of each trajectory.

Figure 8. Resurgent Na$^+$ current reduces entropy in neural discharge. a - b) Schematic showing
introduction of random noise input along with a depolarizing step current to disrupt rhythmic bursting in
the model neuron and during dynamic-clamp experiments **(b)**; In **(a)**, I_{stim} is the sum of the constant step
input and random white noise, and in **(b)**, I_{dyn} is the sum of step, random noise and I_{NaR}. **c – d)** Raster
plots showing patterns of inter-event intervals (IEIs) for the different conditions shown in the model **(e)**,
and during real-time dynamic-clamp **(f)**. **e – f)** Time series of Log_{10}(IEI) for the different conditions shown
in the model **(e)**, and during real-time dynamic-clamp **(f)**. **g – h)** Shannon entropy (H) and coefficient of
variability (CV) measured for IEIs under the different conditions presented in **(c)** and **(d)**. Plotted circles
for the model represent an average across 10 trials, while individual trials are presented for the data points
from two cells. In both **(g)** and **(h)**, C: control, N: after addition of random noise, 1X and 2X are
supplements in g_{NaR} values.

Figure 9. A consolidated role for Na$^+$ currents in information processing. a) A sinusoidal ZAP current
input of increasing frequencies from 1 – 250 Hz over 10 sec. **b)** Sub-threshold voltage response showing
resonant behavior that is enhanced by increasing g_{NaP} (blue traces). **c)** Upper trace: membrane resonance
in the presence of ambient noise that can increase the likelihood of near-threshold behavior (arrows
indicate noise-induced heightened response); Lower trace: presence of noise increases uncertainty in
neural discharge **d)** Noise tolerance due to g_{NaR} returns order of bursts.

Supplementary Information
4 Supplementary figures and legends
1 Table
1 piece of Supplementary information providing the *Model analyses using dynamical systems methods*
2 pieces of Supplementary information providing the *Model code as MATLAB scripts*
3 pieces of Supplementary information providing the *Dynamic-clamp C^{++} code*

Acknowledgements
Grant support include NIH/NINDS NS095157 (SV); NIH/NINDS NS07134 and UCLA Faculty Research
Grant (SHC); NSF DMS1410935 (DHT); NIH/NHLBI 1R01HL134346 (RO); The David Vickter, The

Toeffler Family & Simon-Strauss Foundations (MWP). We are grateful to Dr. Bruce Bean, Dr.
Christopher Del Negro and Dr. Alan Garfinkel for helpful comments on an earlier version of the
manuscript.

Online Methods

Neuron model for bursting activity

The conductance-based Mes V neuron model that we use to investigate the physiological role for

I_{NaR} and I_{NaP} components of I_{Na} in burst discharge, incorporates a minimal set of key ionic conductances

essential for producing rhythmic bursting and for maintaining cellular excitability in these neurons [7].

These include: 1) a potassium leak current, I_{leak}, 2) sodium current, I_{Na} as described above, and, 3) a 4-

AP sensitive delayed-rectifier type potassium current (I_K) [7, 31]. The model equations follow a

conductance-based Hodgkin-Huxley formalism [12] and are as follows.

$$V' = \left(-I_{Na} - I_K - I_{leak} + I_{app}\right)/C$$

$$h_t' = \frac{ht_\infty(V) - h_t}{\tau_t}$$

$$h_p' = \frac{hp_\infty(V) - h_p}{\tau_p(V)}$$

$$b_r' = \alpha_b(1 - b_r)br_\infty(V) - k_b\beta_{br}(V)b_r$$

$$h_r' = \alpha_{hr}(V)hr_\infty(V) - 0.8\beta_{hr}(V)h_r$$

$$n' = \frac{n_\infty(V) - n}{\tau_n}$$

In what follows, we provide the formulation for each of the ionic currents and describe in detail, the novel

I_{NaR} model.

A. Voltage-gated sodium currents

In vitro action potential clamp studies in normal mouse Mes V neurons, and voltage-clamp studies in

Nav1.6 subunit SCN8a knockout mice have demonstrated existence of three functional forms of the total

sodium current, I_{Na}, including the transient (I_{NaT}), persistent (I_{NaP}) and resurgent (I_{NaR}) components [10,

13]. Each of these currents are critical for Mes V electrogenesis including burst discharge, however, their

exclusive role is yet unclear. Lack of suitable experimental model or manipulation to isolate each of these

TTX-sensitive components, led us to pursue an alternative approach involving computational model

development of the physiological I_{Na}. To further allow model-based experimental manipulation of

individual components of the I_{Na}, we designed a conductance-based model as follows. To satisfy a single

channel mediating all the three components, the equation for the total sodium current can be written as:

415
$$I_{Na} = I_{NaT} + I_{NaR} + I_{NaP}$$

416 where,

417
$$I_{NaT} = \boldsymbol{g_{NaT}}(m_{t\infty}(V)h_t)(V - E_{Na})$$

418
$$I_{NaR} = \boldsymbol{g_{NaR}}((1 - b_r)^3 h_r^5)(V - E_{Na})$$

419
$$I_{NaP} = \boldsymbol{g_{NaP}}(m_{p\infty}(V)h_P)(V - E_{Na})$$

The maximal persistent conductance, g_{NaP} was set 5-10% of the transient g_{NaT}[32] and the resurgent

was set to 15-30% of g_{NaT}, based on the relative percentage of maximum I_{NaR} and I_{NaT} as revealed by

voltage-clamp experiments (e.g., **Fig. 3**); E_{Na} is the Na$^+$ reversal potential.

Based on experimental data, the gating function/variable, $m_{t\infty}(V)$, and h_t, for I_{NaT}, and, $m_{p\infty}(V)$,

and, h_P, for I_{NaP} are modeled as described in [7]. The rate equations for the inactivation gating variables h_t,

and, h_P, model the fast and slow inactivation of the transient and persistent components respectively. The

activation gates are steady-state voltage-dependent functions, consistent with fast voltage-dependent

activation of I_{Na}.

Steady-state voltage-dependent activation and inactivation functions of *transient* sodium current

respectively include:

$$430 \qquad mt_\infty(V) = \frac{1}{1+e^{(-(V+35)/4.3)}}; \qquad ht_\infty(V) = \frac{1}{1+e^{((V+55)/7.1)}}$$

431   Steady-state activation, inactivation and steady-state voltage-dependent time constant of inactivation for

432   *persistent* sodium current respectively include:

$$433 \qquad mp_\infty(V) = \frac{1}{1+e^{(-(V+50)/6.4)}}; \qquad hp_\infty(V) = \frac{1}{1+e^{((V+52)/14)}}; \quad \tau_p(V) = 100 + \frac{10000}{1+e^{((V+60)/10)}}$$

The novel I_{NaR} formulation encapsulates the block/unblock mechanism using a block/unblock

variable (b_r), and, a second hypothetical variable for a competing inactivation, which we call, h_r. We call

this a *hybrid* model, to highlight the fact that the model implicitly incorporates the history or state-

dependent eccentric sodium resurgence, following a transient channel opening, and combines this into a

traditional Hodgkin-Huxley type conductance-based formulation. In the b_r' and h_r' rate equations for b_r,

and, h_r, the block/unblock variable, b_r increases or grows according to the term, $\alpha_b(1 - b_r)br_\infty(V)$, and

decays as per the term, $k_b\beta_{br}(V)b_r$, described as follows:

$\boldsymbol{\alpha_b(1 - b_r)br_\infty(V)}$: In this growth term, we incorporate state-dependent increase in b_r, as follows; we

assume that the rate of increase in b_r is proportional to the probability of channels currently being in the

open state, with a rate constant, α_b which we call 'rate of unblocking'; such probability is a function of

the membrane voltage given by, $br_\infty(V)$, defined as below:

$$445 \qquad br_\infty(V) = \frac{1}{1 + e^{((V+40)/12)}}$$

The term $(1 - br_\infty(V))$, models the steady-state voltage-dependency guiding the unblocking

process. The channels being in open state is represented by the term, $(1 - b_r)$. Note that if $(1 - b_r)$ is

close to 1, this means that larger proportion of channels are in an open state, and therefore b_r grows faster,

promoting blocking. We modeled $br_\infty(V)$ as a decreasing sigmoid function, such that, at negative

membrane potentials, channels have a high probability to enter future depolarized states and therefore,

$(1 - b_r) \sim 0$, in turn, b_r does not grow fast.

$\boldsymbol{k_b \beta_{br}(V) b_r}$: In this decay term, we assume that the rate of decay of b_r, is proportional to the probability

of channels being in the blocked state, with a constant of proportionality k_b, and, this probability is given

by a voltage-dependent function, $\beta_{br}(V)$, defined as below:

455
$$\beta_{br}(V) = \frac{2}{1 + e^{\left(-(V-40)/8\right)}}$$

Note that, $\beta_{br}(V)$ gives a high probability at depolarized potentials, indicating a blocked state and enables

decrease in b_r in subsequent time steps.

Taken together, b_r, represents a mechanistic implementation of a block/unblock process by a blocking

particle (see schematic of channel gating in **Fig. 3a**). Additionally, a hypothetical competing inactivation

variable, h_r, sculpts the voltage-dependent rise and decay times and peak amplitude of sodium resurgence

at -40 mV following a brief depolarization (i.e., transient activation), as observed in voltage-clamp

experiments (see **Fig. 3b**). The functions, $\alpha_{hr}(V), \beta_{hr}(V)$ and $hr_\infty(V)$ are defined as voltage-dependent

rate equations that guide the voltage-dependent kinetics and activation/inactivation of the I_{NaR} component

as given below.

The steady-state voltage-dependency of the competing inactivation necessary to generate a *resurgent* Na$^+$

current is defined as follows:

467
$$hr_\infty(V) = \frac{1}{1+e^{\left((V+40)/20\right)}}$$

468   The voltage-dependent rate functions of such inactivation is defined by two functions as follows:

469
$$\alpha_{hr}(V) = \frac{1}{1+e^{\left(-(V+45)/11\right)}}; \qquad \beta_{hr}(V) = \frac{0.5}{1+e^{\left(-(V+40)/15\right)}}$$

The steepness of the voltage-dependent sigmoid functions for activation and inactivation were tuned

to obtain the experimentally observed I_{NaR} activation (see **Fig. 3**; also see [10, 13, 16]). To obtain the kinetics

(rise and decay times) of I_{NaR} comparable to those observed during voltage-clamp experiments (see

Supplementary Fig. 3), the model required three units for the blocking variable $((1 - b_r)^3)$ and five units

for the inactivation variable $(h_r{}^5)$ (see I_{NaR} equation). Together, the modeled I_{Na} reproduced the key

contingencies of the Nav1.6 sodium currents (see **Supplementary Fig. 2**) [11, 15, 16].

Sensitivity analyses was conducted for the key parameters of I_{NaR} gating including α_b, and, k_b. Note

that these two parameters control the rate of blocking. As expected, increasing α_b, that controls rate of

increase in b_r, decreased the peak amplitude of I_{NaR}, similar to an experimental increase in block efficacy

by a β-peptide (e.g., [14]). On the other hand, k_b also moderates b_r, and increasing k_b, enhances b_r decay

rate, that significantly enhanced I_{NaR}, and, therefore burst duration (not shown). Large increases in k_b

significantly enhanced I_{NaR} , and indeed transformed bursting to high frequency tonic spiking. However,

the effects of I_{NaR} on bursting described in the results section were robust for a wide range of values of

these parameters (>100% increase from default values), and, for our simulations, the range of values, $\alpha_b =$

$0.08\ to\ 0.1$, $k_b = 0.8\ to\ 1.2$, were used to reproduce Mes V neuron discharge properties. To reproduce

experimentally observed spike width, we additionally tuned the inactivation time constant, $\tau_t = 1.5 \pm$

0.5, for I_{NaT}.

B. *Potassium and leak currents*

The 4-AP sensitive delayed-rectifier type potassium current, I_K, and the leak current, I_{leak} were

modeled similar to [7] as below; also see [31].

490
$$I_K = g_K n(V - E_K)$$

491
$$I_{leak} = g_{leak}(V - E_{leak})$$

492   where, the steady-state voltage-dependent activation function for the gating variable, n is given as:

$$n_\infty(V) = \frac{1}{1 + e^{\left(-(V-43)/3.9\right)}}$$

E_K and E_{leak} are K$^+$ and leak reversal potentials respectively. Model parameter values used are provided

in **Table. 1**.

Brain slice preparation

All animal experiments were performed in accordance to the institutional guidelines and regulations

using protocols approved by Animal Research Committee at UCLA. Experiments were performed in P8-

P14 wild-type mice of either sex. Mice were anesthetized by inhalation of isoflurane and then

decapitated. The brainstem was extracted and immersed in ice-cold cutting solution. The brain-cutting

solution used during slice preparation was composed of the following (in mM): 194 Sucrose, 30 NaCl, 4.5

KCl, 1.2 NaH_2PO_4, 26 $NaHCO_3$, 10 glucose, 1 $MgCl_2$. The extracted brain block was mounted on a

vibrating slicer (DSK Microslicer, Ted Pella) supported by an agar block. Coronal brainstem sections

consisting of rostro-caudal extent of Mes V nucleus, spanning midbrain and pons were obtained for

subsequent electrophysiological recording.

Voltage-clamp electrophysiology

To obtain direct experimental data to drive I_{NaR} model development, we performed voltage-clamp

experiments on Mes V neurons and recorded Na$^+$ currents by blocking voltage-gated K$^+$ and Ca^{2+} currents

similar to [10]. The pipette internal solution contained the following composition (in mM): 130 CsF, 9 NaCl,

10 HEPES, 10 EGTA, 1 $MgCl_2$, 3 K_2-ATP, and 1 Na-GTP. The external recording solution contained the

following composition (in mM): 131 NaCl, 10 HEPES, 3 KCl, 10 glucose, 2 $CaCl_2$, 2 $MgCl_2$, 10

tetraethylammonium (TEA)-Cl, 10 CsCl, 1 4-aminopyridine (4-AP), and 0.3 $CdCl_2$. The voltage-clamp

protocol consisted of a holding potential of -90 mV followed by a brief voltage pulse (3 ms) of +30 mV,

to remove voltage-dependent block, followed by voltage steps between -70 mV to -10 mV, in steps of 10

mV for ~ 100 ms to activate I_{NaR}, and then returned to -90 mV. A 0.5 μM TTX abolished the Na$^+$ current

and the residual leak current was subtracted to isolate evident sodium currents. Recordings with series

$R_{series} > 0.1 R_m$ were discarded.

Dynamic-clamp electrophysiology

Real-time dynamic-clamp electrophysiology and *in vitro* current-clamp recording were used for

testing the physiological effects of Na$^+$ currents on burst discharge as well as noise-mediated entropy

changes corrected by I_{NaR} [33]. We selected neurons responding with a bursting pattern in response to supra-

threshold step current injection in the Mes V nucleus in brainstem slice preparation for our study; >50%

of neurons showing other patterns (e.g., tonic or single spiking cells) were discarded. Dynamic-clamp was

successfully performed in bursting cells (n = 10). For dynamic-clamp recording, slices were placed in

normal ACSF at room temperature (22–25°C). The ACSF recording solution during patch-clamp

recording consisted of the following (in mM): 124 NaCl, 4.5 KCl, 1.2 NaH$_2$PO$_4$, 26 NaHCO$_3$, 10 glucose,

2 CaCl$_2$, 1 MgCl$_2$. Cutting and recording solutions were bubbled with carbogen (95% O$_2$, 5% CO$_2$) and

maintained at pH between 7.25 – 7.3. The pipette internal solution used in current clamp experiments was

composed of the following (in mM): 135 K-gluconate, 5 KCl, 0.5 CaCl$_2$, 5 HEPES (base), 5 EGTA, 2 Mg-

ATP, and 0.3 Na-ATP with a pH between 7.28 – 7.3, and osmolarity between 290 ± 5 mOsm. Patch

pipettes (3 – 5 MΩ) were pulled using a Brown/Flaming P-97 micro pipette puller (Sutter Instruments).

Slices were perfused with oxygenated recording solution (~2ml/min) at room temperature while secured

in a glass bottom recording chamber mounted on an inverted microscope with differential interface

contrast optics (Zeiss Axiovert 10). Current clamp (and dynamic-clamp) data were acquired and analyzed

using custom-made software (G-Patch, Analysis) with sampling frequency: 10 kHz; cut-off filter

frequency: 2 kHz.

The Linux-based Real-Time eXperimental Interface (RTXI v1.3) was used to implement dynamic-

clamp , running on a modified Linux kernel extended with the Real-Time Applications Interface, which

allows high-frequency, periodic, real-time calculations [34]. The RTXI computer interfaced with the

electrophysiological amplifier (Axon Instruments Axopatch 200A, in current-clamp mode) and the data

acquisition PC, via a National Instruments PCIe-6251 board. Computation frequency was 20 kHz.

The model I_{NaR} current used for real-time dynamic clamping into Mes V neuron *in vitro* was

developed as discussed above. The ionic conductance g_{NaR} was set to suitable values to introduce model

I_{NaR} current into a Mes V neuron during whole-cell current-clamp recording. For experiments involving

noise modulation, two approaches were used to model random noise generated in RTXI: 1) using a

Wiener-like process with normally distributed random values, 2) normally-distributed random numbers

were generated from uniformly-distributed numbers using the central limit theorem:

548
$$N(t) = \left(\sum_{i=1}^{12} U_i\right) - 6$$

549   where, $N(t)$ is a normally-distributed random number with mean, $\mu = 0$, and standard deviation, $\sigma = 1$,

550   each U_i is a uniformly-distributed random number between 0 - 1 generated using the C++ rand() function.

551   A current, I_{noise} was then generated as follows:

552
$$I_{noise}(t) = I_{noise}(t-1) + N(t) \cdot \sqrt{\Delta_t} \cdot A$$

where, $N(t)$ is a uniformly-distributed random number between 0 - 1 generated in C++ at each sampling

time t and Δ_t is the time distance between consecutive computations. In both the above cases, A is a

scaling factor representing maximal peak-to-peak noise amplitude, modified to adjust noise amplitudes

suitably to produce discernable burst irregularities. Values of A were set during experimentation and

ranged from 3 - 5 across various cells for the data presented. $I_{noise}(t)$ was injected as pA current.

Model simulation and Data analyses

Model simulation and all the analyses were performed using MATLAB (Mathworks™) (see model

code provided as **Supplementary Information**). Model bifurcation analyses were performed using

XPPAUT/AUTO [35]; A variable step Runge-Kutta method 'ode45' was used for current-clamp simulations

and 'ode23s' was used for voltage-clamp simulations.

Inter-event intervals (IEI) between spikes in dynamic-clamp recordings were detected using Clampfit

9.0 software and were classified *post hoc* as ISIs and IBIs based on a bi-modal distribution of IEIs.

Typically, IEI values < 40 ms were considered as ISIs within bursts and IEI values $\geq$ 40 ms were

considered as IBIs. Any occasional isolated spikes were eliminated from analyses for burst duration

calculations.

To calculate Shannon's entropy[36] in the inter-event intervals (IEIs), we generated histograms of and

calculated the probabilities for each bin of the underlying IEI distributions for each 10 sec spike trains.

The probability of k^{th} IEI bin from a distribution of n equal size bins was calculated from the bin counts,

$N(k)$ as:

572
$$p(k) = \frac{N(k)}{\sum_{k=1}^{n} N(k)}$$

573   The entropy, H was calculated using the following formula:

574
$$H = -\sum_{k=1}^{n} p_k \log_2 p_k$$

575   where, n is the total number of IEI bins, each with probability, p_k.

576   The coefficient of variation (CV) in IEIs was calculated as follows:

577
$$CV = \frac{s}{\bar{x}}$$

578   where, s is the IEI sample standard deviation, and, $\bar{x}$ is the sample mean.

References

1.   Krahe, R. & Gabbiani, F. Burst firing in sensory systems. *Nat Rev Neurosci* **5**, 13-23 (2004).

2.   Ermentrout, B.G. & Terman, D.H. Bursting Oscillations. in *Mathematical Foundations of Neuroscience* 103-127 (Springer-Verlag New York, 2010).

3.   Del Negro, C.A., Hsiao, C.F., Chandler, S.H. & Garfinkel, A. Evidence for a novel bursting mechanism in rodent trigeminal neurons. *Biophys J* **75**, 174-182 (1998).

4.   Bialek, W., Rieke, F., de Ruyter van Steveninck, R.R. & Warland, D. Reading a neural code. *Science* **252**, 1854-1857 (1991).

5.   Catterall, W.A. From ionic currents to molecular mechanisms: the structure and function of voltage-gated sodium channels. *Neuron* **26**, 13-25 (2000).

6.   Alonso, A. & Llinás, R.R. Subthreshold Na+-dependent theta-like rhythmicity in stellate cells of entorhinal cortex layer II. *Nature* **342**, 175-177 (1989).

7.   Wu, N.*, et al.* Persistent sodium currents in mesencephalic v neurons participate in burst generation and control of membrane excitability. *J Neurophysiol* **93**, 2710-2722 (2005).

8.   Hutcheon, B. & Yarom, Y. Resonance, oscillation and the intrinsic frequency preferences of neurons. *Trends Neurosci* **23**, 216-222 (2000).

9.   Schwindt, P.C. & Crill, W.E. Amplification of synaptic current by persistent sodium conductance in apical dendrite of neocortical neurons. *J Neurophysiol* **74**, 2220-2224 (1995).

10.   Enomoto, A., Han, J.M., Hsiao, C.F., Wu, N. & Chandler, S.H. Participation of sodium currents in burst generation and control of membrane excitability in mesencephalic trigeminal neurons. *J Neurosci* **26**, 3412-3422 (2006).

11.   Raman, I.M. & Bean, B.P. Resurgent sodium current and action potential formation in dissociated cerebellar Purkinje neurons. *J Neurosci* **17**, 4517-4526 (1997).

12.   Hodgkin, A.L. & Huxley, A.F. A quantitative description of membrane current and its application to conduction and excitation in nerve. *J Physiol* **117**, 500-544 (1952).

13.   Enomoto, A., Han, J.M., Hsiao, C.F. & Chandler, S.H. Sodium currents in mesencephalic trigeminal neurons from Nav1.6 null mice. *J Neurophysiol* **98**, 710-719 (2007).

14.   Grieco, T.M., Malhotra, J.D., Chen, C., Isom, L.L. & Raman, I.M. Open-channel block by the cytoplasmic tail of sodium channel beta4 as a mechanism for resurgent sodium current. *Neuron* **45**, 233-244 (2005).

15.   Smith, M.R., Smith, R.D., Plummer, N.W., Meisler, M.H. & Goldin, A.L. Functional analysis of the mouse Scn8a sodium channel. *J Neurosci* **18**, 6093-6102 (1998).

16.   Raman, I.M. & Bean, B.P. Inactivation and recovery of sodium currents in cerebellar Purkinje neurons: evidence for two mechanisms. *Biophys J* **80**, 729-737 (2001).

17.   Khaliq, Z.M., Gouwens, N.W. & Raman, I.M. The contribution of resurgent sodium current to high-frequency firing in Purkinje neurons: an experimental and modeling study. *J Neurosci* **23**, 4899-4912 (2003).

18.   Kim, J.H., Kushmerick, C. & von Gersdorff, H. Presynaptic resurgent Na+ currents sculpt the action potential waveform and increase firing reliability at a CNS nerve terminal. *J Neurosci* **30**, 15479-15490 (2010).

19.   Birmingham, J.T., Szuts, Z.B., Abbott, L.F. & Marder, E. Encoding of muscle movement on two time scales by a sensory neuron that switches between spiking and bursting modes. *J Neurophysiol* **82**, 2786-2797 (1999).

20.   Zheng, Y. & Escabí, M.A. Proportional spike-timing precision and firing reliability underlie efficient temporal processing of periodicity and envelope shape cues. *J Neurophysiol* **110**, 587-606 (2013).

21.   Reich, D.S., Mechler, F., Purpura, K.P. & Victor, J.D. Interspike intervals, receptive fields, and information encoding in primary visual cortex. *J Neurosci* **20**, 1964-1974 (2000).

22.   Tiesinga, P., Fellous, J.M. & Sejnowski, T.J. Regulation of spike timing in visual cortical circuits. *Nat Rev Neurosci* **9**, 97-107 (2008).

23.   Mainen, Z.F. & Sejnowski, T.J. Reliability of spike timing in neocortical neurons. *Science* **268**, 1503-1506 (1995).

24.   Raman, I.M., Sprunger, L.K., Meisler, M.H. & Bean, B.P. Altered subthreshold sodium currents and disrupted firing patterns in Purkinje neurons of Scn8a mutant mice. *Neuron* **19**, 881-891 (1997).

25.   Vilin, Y.Y. & Ruben, P.C. Slow inactivation in voltage-gated sodium channels: molecular substrates and
contributions to channelopathies. *Cell Biochem Biophys* **35**, 171-190 (2001).
26.   Béhuret, S., Deleuze, C. & Bal, T. Corticothalamic Synaptic Noise as a Mechanism for Selective Attention
in Thalamic Neurons. *Front Neural Circuits* **9**, 80 (2015).
27.   Faisal, A.A., Selen, L.P. & Wolpert, D.M. Noise in the nervous system. *Nat Rev Neurosci* **9**, 292-303
(2008).
28.   Izhikevich, E.M., Desai, N.S., Walcott, E.C. & Hoppensteadt, F.C. Bursts as a unit of neural information:
selective communication via resonance. *Trends Neurosci* **26**, 161-167 (2003).
29.   Lisman, J.E. Bursts as a unit of neural information: making unreliable synapses reliable. *Trends Neurosci*
20, 38-43 (1997).
30.   Koch, C. & Segev, I. The role of single neurons in information processing. *Nat Neurosci* **3 Suppl**, 1171-
1177 (2000).
31.   Del Negro, C.A. & Chandler, S.H. Physiological and theoretical analysis of K+ currents controlling
discharge in neonatal rat mesencephalic trigeminal neurons. *J Neurophysiol* **77**, 537-553 (1997).
32.   Taddese, A. & Bean, B.P. Subthreshold sodium current from rapidly inactivating sodium channels drives
spontaneous firing of tuberomammillary neurons. *Neuron* **33**, 587-600 (2002).
33.   Prinz, A.A., Abbott, L.F. & Marder, E. The dynamic clamp comes of age. *Trends Neurosci* **27**, 218-224
(2004).
34.   Lin, R.J., Bettencourt, J., Wha Ite, J., Christini, D.J. & Butera, R.J. Real-time experiment interface for
biological control applications. *Conf Proc IEEE Eng Med Biol Soc* **2010**, 4160-4163 (2010).
35.   Ermentrout, B. XPPAUT5.0 – the differential equations tool. (2001).
36.   Shannon, C.E. & Weaver, W. *The Mathematical Theory of Communication* (University of Illinois Press,
Urbana, 1949).

Fig. 1. Study workflow

a) Mathematical Modeling and Simulations

Ionic conductance model

gating variable

Membrane Voltage

Neuron model

b) Experimental Validation using Real-time Closed-loop Dynamic-clamp

Neuron

c) Insights from Model Stability and Uncertainty Analyses

Membrane Voltage

Bursting

Silence

gating variable

Fig. 2. Components of I_{Na}

a) A model for Nav1.6 type sodium currents

I_{Na}

100 pA

50 ms

I_{NaT}

100 pA

50 ms

τ_{decay}: O(1ms)

I_{NaR}

100 pA

τ_{decay}: O(10ms)

I_{NaP}

25 pA

τ_{decay}: O(1000ms)

$$I_{Na} = I_{NaT} + I_{NaR} + I_{NaP}$$

b)

I_K I_{leak}

Model neuron

I_{Na}

MODEL SIMULATION

40 mV

-55 mV

200 ms

I_{Na} 200 pA/pF

c)

I_{Na} V_m

I_{Na} V_m

Neuron

CLOSED-LOOP DYNAMIC-CLAMP

add model I_{Na}

TTX

control

-55 mV

40 mV

200 ms

I_{Na} 250 pA/pF

Fig. 3. A novel mathematical model for I$_{NaR}$

a)

I_{NaR} mechanism

Closed   Open   Open-block

+30 mV

-90 mV   -40 mV

Unblock/Inactivation

● Inactivation gate
● Open channel block

I_{NaR} model formalism

hr$_\infty$(V)

1-br$_\infty$(V)

I_{NaR}

Voltage (mV)

I_{NaR} during spiking activity

I_{NaR}

spikes

0.5 pA
20 mV

50 ms

$$I_{NaR} = g_{NaR} \times (1 - b_r)^3 \times h_r^5 \times (V - E_{Na})$$

b)

I_{NaR} experimental validation

I.

Simulated I_{Na}

0 pA

resurgent

≈ 100 pA

30 ms

I_{Na} from voltage-clamp recording

0 pA

resurgent

≈
100 pA

30 ms

+30 mV

-10 mV

-70 mV

-90 mV   -90 mV

II.

Peak resurgent current (pA)

Voltage (mV)

Model
Data

Fig. 4. I~NaR~ effects on burst discharge

a) MODEL PREDICTION
(membrane voltage simulations)

$g_{NaR} = 0$ $g_{NaR} = 1x$ $g_{NaR} = 2x$

20 mV
0.5 s

b) EXPERIMENTAL VALIDATION
(membrane voltage during closed-loop dynamic-clamp recording)

$g_{NaR} = 0$ $g_{NaR} = 1x$ $g_{NaR} = 2x$

20 mV
0.5 s

c) IBI

BD   ISI

- Simulation
- Dynamic-clamp

IBI (ms)
1500
1000
500
0

0   1x   2x
g_{NaR}

d) BD (ms)
1500
1000
500

0   1x   2x
g_{NaR}

e) ISI (ms)
30
20
10

0   1x   2x
g_{NaR}

Fig. 5. I$_{NaP}$ effects on burst discharge

a) MODEL PREDICTION
(membrane voltage simulations)

$g_{NaP} = 0$ $g_{NaP} = 1x$ $g_{NaP} = 1.5x$

20 mV
0.5 s

b) EXPERIMENTAL VALIDATION
(membrane voltage during closed-loop dynamic-clamp recording)

$g_{NaP} = 0$ $g_{NaP} = 1x$ $g_{NaP} = 1.5x$

20 mV
0.5 s

c) IBI

BD   ISI

● Simulation
● Dynamic-clamp

d)

e)

Fig. 6. I$_{NaR}$ facilitates slow Na$^+$ inactivation

a) Control

slow inactivation

b) ↑ g_{NaP}

slow inactivation

c) ↑ g_{NaR}

slow inactivation

20 mV

500 ms

f) unblock — slow inactivation

Unblocking

Slow inactivation

d) Neural activity thresholds controlled by g_{NaR}

BURSTING

3X 2X 1X 0 Offset Threshold

Onset Threshold

SILENCE

Membrane Voltage, V (mV)

Slow inactivation, h_p

e) Neural activity thresholds controlled by g_{NaP}

BURSTING

2.5X 2X 1.5X 1X Offset Threshold

2.5X 2X 1.5X 1X Onset Threshold

SILENCE

Membrane Voltage, V (mV)

Slow inactivation, h_p

Fig. 7. Burst refractoriness and noise tolerance conferred by I_{NaR}

a) No g_{NaR}

b) Add noise

c) Add g_{NaR}

20 mV

500 ms

slow inactivation

recovery

STO

STO

STO

d) No g_{NaR}

inactivation

burst offset

burst onset

recovery

e) Add noise

abrupt spikes during recovery

f) Add g_{NaR}

region of noise tolerance

abrupt burst onset

Membrane Voltage, V (mV)

Slow inactivation, h_p

Fig. 8. I_{NaR} maintains order of bursts

a)

b)

c) MODEL PREDICTION (simulations)

control

+ noise

+ 1x g_{NaR}

+ 2x g_{NaR}

2 s

d) EXPERIMENTAL VALIDATION (closed-loop dynamic-clamp)

control

+ noise

+ 1x g_{NaR}

+ 2x g_{NaR}

2 s

e) MODEL

control   + noise   + 1x g_{NaR} + 2x g_{NaR}

Log_{10}IEI (ms)

f) EXPERIMENTS

Log_{10}IEI (ms)

2 s

g) Entropy, H

C N 1x 2x

h) CV

C N 1x 2x

Model
Cell 1
Cell 2

Fig. 9. A Tune-In-Tune-Out mechanism

a)

Sinusoidal ZAP input

10 pA

1 s

b)

Membrane resonance

2 mV

TUNE-IN

$\uparrow g_{NaP}$

2 mV

c)

$+ Noise$

2 mV

increased uncertainty

30 mV

d) TUNE-OUT

$\uparrow g_{NaR}$

30 mV

1 s