Midfrontal theta phase coordinates behaviorally relevant brain computations during cognitive control

Joan Duprez[1, 2], Rasa Gulbinaite[3,] Michael X Cohen[1]

1 Radboud University and Radboud University Medical Center; Donders Institute for Neuroscience

2 Univ Rennes, CHU Rennes, Comportement et noyaux gris centraux-EA 4712, F-35000 Rennes, France

3 Lyon Neuroscience Research Center (CRNL), Brain Dynamics and Cognition Team, INSERM U1028, CNRS UMR5292, Université Claude Bernard Lyon 1, UdL, Lyon, France

Corresponding author and lead contact: duprez.joan@gmail.com

Funding: MXC is funded by an ERC-StG 638589

JD is funded by the Rennes Clinical Neuroscience Institute (INCR : www.incr.fr)

Summary

Neural oscillations are thought to provide a cyclic time frame for orchestrating brain

computations. Following this assumption, midfrontal theta oscillations have recently been

proposed to temporally organize brain computations during conflict processing. Using a

multivariate analysis approach, we show that brain-behavior relationships during conflict

tasks are modulated according to the phase of ongoing endogenous midfrontal theta

oscillations recorded by scalp EEG. We found reproducible results in two independent

datasets, using two different conflict tasks: brain-behavior relationships (correlation between

reaction time and theta power) were theta phase-dependent in a subject-specific manner, and

these "behaviorally optimal" theta phases were also associated with fronto-parietal cross-

frequency dynamics emerging as theta phase-locked beta power bursts. These effects were

present regardless of the strength of conflict. Thus, these results provide empirical evidence

that midfrontal theta oscillations are involved in cyclically orchestrating brain computations

likely related to response execution during the tasks rather than purely related to conflict

processing. More generally, this study supports the hypothesis that phase-based computation

is an important mechanism giving rise to cognitive processing.

Keywords: Neuronal oscillations; Midfrontal cortex; Theta; Phase-resolved correlations;

Conflict processing;

Introduction

In recent years, cognitive neuroscientists have increasingly relied on the analysis of neural oscillations measured by M/EEG, as they appear to be a well-suited brain phenomenon to bridge behavioral observations with the neurophysiological mechanisms of brain computation (Buzsáki and Draguhn, 2004; Wang, 2010; Cohen, 2014a). An important assumption about the role of neural oscillations that fuels current research is that they provide a temporal reference for brain computations, with narrow time windows grouping neuronal activities (e.g. neuronal spiking or sensitivity to inputs; Fries, 2005) that allow effective brain computations for cognitive functions. Evidence in favor of that claim comes notably from the phenomenon of phase-amplitude cross-frequency coupling, and from direct observation of the coordination of neuronal firing according to the timing of oscillations (Canolty and Knight, 2010; Mizuseki et al., 2009). In other words, if neural oscillations are important for neural computations that subserves cognition, the phase of those oscillations should shape the timing of computations (Maris et al., 2016; Bonnefond et al., 2017; Jensen et al., 2014).

The study of cognitive control, and more specifically, of response conflict processing, has benefited from the analytic and theoretical framework provided by neural oscillations. Conflict processing refers to the ability to select a relevant response among competing alternatives that can be automatically activated. It encompasses action selection and inhibition mechanisms and is usually studied using response conflict tasks such as the Simon task (van den Wildenberg et al., 2010). When facing response conflict, an increase in theta (~6 Hz) narrowband power is invariably observed around midfrontal electrodes (McDermott et al., 2017; Jiang et al., 2018; Pastötter et al., 2013; Cohen and Cavanagh, 2011; Nigbur et al., 2011). Importantly, this increase in power is demonstrated to reflect non-phase locked activity, suggesting that response conflict modulates the activity of ongoing endogenous theta oscillations in the prefrontal cortex (Cohen and Donner, 2013). Midfrontal theta (also sometimes called frontal midline theta) is a robust marker of conflict detection and resolution, as conflict-related theta effects have high statistical power, show strong correlations with task performance (reaction time), and relate to diseases such as Parkinson's and OCD (Cohen and Cavanagh, 2011; Cohen and van Gaal 2014; Cavanagh et al., 2011; Min et al., 2011). Midfrontal theta phase is also demonstrated to be relevant for conflict processing, as documented by the numerous reports of conflict-modulated changes in phase synchronization between midfrontal and prefrontal and parietal regions, which suggest the existence of a

fronto-parietal network of conflict processing (Vissers et al., 2018; van Driel et al., 2015;
Anguera et al., 2013; Cohen and van Gaal 2013; Cohen and Ridderinkhof, 2013; Hanslmayr
et al., 2008).

On the other hand, detailed predictions about the potential computational roles of
midfrontal theta have remained elusive to the macroscopic scale of non-invasive human EEG,
which has limited the ability to link narrowband phases to specific aspects of behavior or
neural computations. One key prediction for midfrontal theta phase in conflict processing is
that it provides a rhythmic structure for alternately monitoring behavior and signaling the
need for control (Cohen, 2014a). In others words, this prediction implies that monitoring and
signaling processes during cognitive control are more efficient at certain theta phases.

Here we provide novel evidence for a phase-specific relationship between task
performance (reaction time) and midfrontal theta, using guided multivariate spatial filtering
techniques to maximize the signal-to-noise ratio of single-trial data. We found that theta
power-reaction time correlations are maximal at specific theta phase regions that were
characteristic to each individual, and that predicted the timing of beta-band (~20 Hz) bursts in
a fronto-parietal network, as revealed by multivariate phase-amplitude coupling analyses.
Contrary to our hypothesis, these theta phase-dependent effects were not specific to
conditions that maximized response conflict, but rather reflected the temporal organization of
a more general mechanism likely related to response execution occurring during the conflict
tasks we used. All of the key findings were replicated in an independent dataset (Gulbinaite et
al., 2014). The two datasets were acquired using different conflict tasks (Eriksen flanker task
and Simon task; total N = 62) in two different research centers, supporting the interpretation
that these findings reflect general neural signatures of cognitive control over behavior.

Methods

We separately applied the same analysis methods to two existing datasets from studies using
response conflict tasks. Here we briefly describe the key features of these two tasks; further
details can be found in Cohen (2015) and Gulbinaite et al. (2014).

Participants

30 students from the University of Amsterdam volunteered in *study 1* (Cohen, 2015). Two
datasets were excluded because of excessive EEG artifacts. 34 students from the University
of Groningen participated in *study 2* (Gulbinaite et al., 2014). In both studies, participants had
normal or corrected-to-normal vision. The experiments were conducted in accordance with
the declaration of Helsinki and with approval of local ethics committees. Written informed
consent was obtained from all participants prior to the experiments.

Task design

Figure 1: Experiment designs. *A: Eriksen flanker task used in study 1. Stimuli could induce*
no conflict (all the letters were identical), partial conflict (letters on the left or right side
differed from the target central letter), or full conflict (all surrounding letters were different
from the target letter). B: Simon task used in study 2. Trials could either be congruent (color
and location of the stimulus indicate the same response) or incongruent (color and location
indicate different responses, hence, response conflict occurred).

Study 1 used a modified version of the Eriksen flanker task (Appelbaum et al., 2011) in which
participants had to respond to a central letter while ignoring surrounding letters that acted as
distractors. The strength of response conflict was manipulated in three different types of trials
(Figure 1A): (i) without conflict (the target and surrounding letters were identical), (ii) partial
conflict (only one side of the target had a different set of letters), and full conflict (all
surrounding letters differed from the central letter). Each participant underwent
approximately 1500 trials. Stimulus display lasted for 200 ms and participants had 1200 ms
to respond using the left or right thumb. The two stimulus letters were mapped on two
responses buttons. The next trial occurred after a 1200 ms inter-trial interval.

Study 2 used a Simon task with color circles as stimuli. Participants had to press a left or right

button according to the color of the stimulus while ignoring its position. On congruent trials

(i.e. without conflict), color and location of the stimulus indicated the same response. On

incongruent trials (i.e. conflict trials), color and location indicated opposite responses. Stimuli

were displayed until response or after a 1500 ms delay. After response, a fixation cross was

displayed for 1000 ms before the start of the next trial. The task comprised 70 practice trials

and 1024 experimental trials with the same number of possible congruency sequences: cC

(congruent following congruent), cI (incongruent following congruent), iC (congruent

following incongruent), iI (incongruent following incongruent).

EEG acquisition and preprocessing

In *study 1*, EEG data were recorded at 512 Hz from 64 electrodes placed according to the

international 10-20 system. Data were referenced offline to linked-earlobes, high-pass filtered

at 0.5 Hz, and then epoched from -1 s to 1.5 s locked on stimulus onset. Additional electrodes

were used on both earlobes and also to acquire EMG data from both thumbs' *flexor pollicis*

brevis. EMG data were used to identify small activation of the thumb muscle prior to the

response. When trials contained such activation on the side of the wrong response prior to a

correct one, they were labeled "mixed correct" (sometimes referred to as partial errors; van

den Wildenberg et al., 2010). The identification of mixed correct trials was based on changes

over time in EMG variance. The complete description of the identification algorithm can be

found in Cohen and van Gaal (2014). Given that mixed correct trials are assumed to have the

maximal amount of response conflict, their identification was done to label the trials in which

control was most strongly implemented.

All trials were visually inspected and those containing EMG or other clear artifacts were

excluded.

In *study 2*, EEG data were acquired from 62 channels at 500 Hz. The electrodes were placed

according to a modified version of the 10-10 system (electrodes FT7, PO7, O1, FT8, PO8,

and O2 were placed 10% below standard and electrodes F1, F2, CP1, CP2, FT7, and FT8

were not measured). Data were referenced off-line to the mastoids, high-pass filtered at 0.5

Hz, and then epoched from -1.5 s to 2 s locked on stimulus onset. Two artifact rejection steps

were carried out. The first consisted in the manual rejection of trials containing clear muscle

or blink artifacts and the second was an independent component analysis resulting in the

subtraction of components containing eye-blinks or noise. After artifact rejection, a surface

Laplacian spatial filter was applied to the data to attenuate spatial smearing as a result of

volume conduction (this was done in Gulbinaite et al., 2014, to facilitate connectivity

analyses).

For both studies, the epoch length was ~2 theta cycles longer than the selected window of

interest (from 300 to 1200 ms) and visual inspection of time-frequency plots did not suggest

any contamination of the selected time window by the edge artifacts.

In both datasets, the ERP was subtracted from the data (separately per channel and per

condition) prior to any other analysis to avoid stimulus-related phase resetting. This step

removes the "phase-locked" component of the signal and ensures that the results do not

reflect a stimulus-evoked transient (Cohen and Donner, 2013). This is an important

methodological step that allows us to interpret our findings in terms of the phase of ongoing

theta oscillations, as opposed to additive stimulus-related reset of theta oscillations. One

should, however, note that there is no fully accepted method to separate the phase-locked

from the non-phase-locked activity. Nonetheless, ERP subtraction is a common way of

removing the phase-locked component, and has been investigated previously with regards to

midfrontal theta activity (Cohen and Donner, 2013).

Spatial filtering of the data

All signal analyses were performed in Matlab (The Mathworks, USA, version 2016a) using

custom written code. Because of our a priori hypotheses regarding theta-band activity, we

isolated midfrontal theta using optimal spatial filters that maximized power in the theta band.

It is important to note that this approach to spatial filtering is based on statistical criteria

(channel covariance matrices) and is not designed for inference about potential cortical

generators. We limit our interpretations to topographical distributions to facilitate embedding

in the literature. Construction of the spatial filter involves finding a set of channel weights

that maximally distinguishes theta-band from broadband multichannel activity as measured

through covariance matrices (Nikulin et al., 2011; de Cheveigne and Arzounian, 2015). This

can be expressed via the Rayleigh quotient, in which the goal is to find a set of channel

weights in vector $\mathbf{w}$ that maximizes λ.

$$\lambda = \frac{\mathbf{w^T S w}}{\mathbf{w^T R w}} \qquad\qquad (1)$$

S is the covariance matrix derived from the data narrowband filtered in theta band (around

subject-specific theta peak frequency, see below) and **R** is the covariance matrix derived from

the broadband signal. The solution to equation 1 comes from a generalized eigenvalue

decomposition (GED) on the two covariance matrices, defined by the equation **SW**=**RWΛ**.

This method has been recommended to maximize power at low frequencies (Cohen, 2017a;

Nikulin et al., 2011) and has several advantages: it increases signal-to-noise ratio,

incorporates inter-individual topographical differences, and avoids the bias related to

electrode selection. The column of **W** with the highest associated generalized eigenvalue is

the spatial filter that maximizes the difference between **S** and **R**. This spatial filter was then

applied to the data as $\mathbf{y}=\mathbf{w}^T\mathbf{X}$ where **X** is the channels-by-time data matrix, and **w** is the

column of **W** chosen using a method specified in the next paragraphs. Analyses are then

applied to the data (component time series) in the row vector **y**.

The peak frequency of the temporal filter (for the **S** covariance matrix) was defined subject-

wise by searching for the frequency of peak power in the theta band in conflict conditions at

electrode FCz (conflict-related increase in theta activity has been consistently described at

this location; Cohen, 2014a). To this end, we performed a time-frequency decomposition of

the data by complex Morlet wavelet convolution, implemented by multiplying the Fourier

transform of the EEG data by the Fourier transform of a set of complex Morlet wavelets

$e^{i2\pi ft}e^{-t^2/(2s^2)}$, and taking the inverse fast-Fourier transform of the result. In the Morlet wavelets

$e^{i2\pi ft}e^{-t^2/(2s^2)}$, t is time, f is frequency (ranging from 1 to 50 Hz in 60 logarithmically spaced

steps), and s is the width of each frequency band, which is defined by $n/(2\pi f)$ (with n

logarithmically increasing from 4 to 12). Frequency specific power at each time point (t) was

defined as the the squared magnitude of the resulting analytic signal (Z) as real$[Z(t)^2]$ +

imaginary$[Z(t)^2]$. Power was baseline-corrected using a decibel (dB) transform: dB power =

10*log10(power/baseline), with baseline power defined as the average power across all

conditions from -500 to -200 before stimulus onset. The peak frequency was then defined

within a time-frequency window of 0 to 800 ms and 3 to 10 Hz. We chose a range of 3 to 10

Hz to account for the subjects' variability in theta peak. This peak frequency was then used as

a center frequency for a Gaussian narrow-band filter (FWHM = 3 Hz) to the broadband data.

The resulting theta-filtered channel data was used to compute the **S** covariance matrix,

defined in a 1000 ms (thus including several theta cycles) time window around the time of

theta peak power. The same time window was used to compute the **R** covariance matrix using

broadband channel data. The two covariance matrices then were used in GED to construct
spatial filters. Selection of the best spatial filter in the resulting eigenvector matrix **W** was a
two-step process. First, the 15 spatial filters with the highest eigenvalues were applied to the
temporally unfiltered data resulting in a set of 15 components. Only those without eye-blink
activity were retained. Components with eye-blink activity were identified as those with
higher averaged activity at electrodes near the eyes (FP1, FPz, FP2) than around midfrontal
electrodes (FC1, C1, CP1, FCz, Cz, CPz, FC2, C2, CP2, for study 1; FC1, C1, FCz, Cz, FC2,
C2, for study 2). Then, the topography of the spatial filters' activation pattern were inspected
by plotting the topographical map (using the topoplot function of the EEGlab toolbox;
Delorme and Makeig, 2004) of the activation pattern of the filter (**Sw**; Haufe et al., 2014).
Activation patterns should be centered on the FCz electrode according to the conflict-related
modulation of theta power reported in the literature (Cohen, 2014a). Thus, the component
with an activation pattern consistent with midfrontal theta activity was chosen and was then
analyzed using time-frequency decomposition methods (Cohen, 2017a). In 74.2% of cases,
the selected component was the one associated with the largest eigenvalue. In other cases, the
second or third largest component that had a midfrontal topography (monopolar with a spatial
maximum around FCz) was selected instead. When several spatial filters with midfrontal
topography were encountered (4 subjects), the one with the largest eigenvalue was always
selected.
In this study, Morlet wavelet convolution was only used as a first step to identify the theta
peak frequency for each subject and to inspect the overall time-frequency power maps of the
theta component.
269
270
271
Within subject brain-behavior relationships
Brain-behavior relationships across trials were investigated by correlating power in the theta
band with reaction time (RT) for each participant. After filtering the previously selected
component around the subject-specific peak theta power frequency found at electrode FCz
during conflict, the Hilbert transform was applied to compute the analytic signal from which
power was derived (according to the same squared magnitude method as reported above). A
condition-specific Spearman correlation coefficient was calculated between theta power at
each time point and RT resulting in a time series of correlation coefficient for each condition
and each participant. Significance was evaluated using a nonparametric permutation test of

the null hypothesis that the probability distribution of the participant-specific power-RT

correlations is symmetric around 0. At each of the 1000 iterations, the time course of

correlation coefficients was multiplied by -1 for a random subset of participants and then

averaged over participants in order to generate a matrix of 1000 subject-averaged time

courses under the null hypothesis. Then we subtracted the iteration averaged time course

from the real subject averaged time course of correlation coefficients and divided the result

by the standard deviation of the iteration averaged time course. The resulting z-valued time

course was then thresholded at $p<0.05$. Multiple comparisons were addressed by the means of

cluster-based correction so that any cluster equal or larger than 99.5% of the distribution of

null hypothesis maximal cluster sizes was considered significant. This analysis served two

purposes: (i) replicate correlation patterns usually observed between theta power and RT

during conflict and (ii) define a time window of interest (in which correlations were

significantly different from 0) for phase-resolved analyses.

Within subject phase-resolved brain-behavior relationships

In order to investigate if the theta power-RT correlations depended on theta phase, we

computed theta power-RT correlation coefficient according to the different possible phase

values in 20 discrete phase bins. To this end, the phase angle time series of the previously

Hilbert-transformed theta-defined component of each trial was divided in 20 linearly spaced

phase bins with values ranging from $-\pi$ to π. For each theta phase bin, the corresponding

power was extracted and averaged for that trial. For instance, the different power values

extracted when phase equals $\pi/2$ across the phase angles time series were averaged in order to

get the mean power at the $\pi/2$ phase for that trial (Figure 2 B and C). This operation was

repeated for all trials and separately for each condition. Phase-specific mean power was then

correlated with RT, resulting in 20 power-RT coefficients for each condition and subject

(Figure 2 D). These phase-specific correlation coefficients were then averaged across subjects

for each condition (Figure 2 E).

Within subject phase-resolved power-RT correlation analyses

In order to test whether power-RT correlations significantly varied according to phase, we

fitted the correlation values to sine waves for each subject and condition. These analyses

were done using R (version 3.4.2; R core team, 2017) and the {minpack.lme} package for

nonlinear least square fitting (Elzhov et al., 2016). Data were fitted by applying the nlsLM

function to the model: $\rho \sim A*\sin(2*\pi*F*\text{phasebin}+\theta)$, where ρ is the correlation coefficient,

and A, F and θ, are the amplitude, frequency, and phase parameters to estimate, respectively.

Parameter estimates were then used in a harmonic addition of a sine and a cosine (which is

equivalent to a single sine wave allowing for a phase shift) to enter in a linear model

following: $\rho \sim (A\sin(2\pi F*\text{phasebin} + \theta) + A\cos(2\pi F*\text{phasebin} + \theta))$. This was done in order to

estimate the overall significance and the goodness of fit of the estimated sine parameters.

The amplitude parameter and the model R^2 were compared at the group-level between all

conditions using wilcoxon paired tests with a Bonferroni corrected threshold of $p < 0.05/10 =$

0.005 because of the 10 possible conflict condition comparisons. We also statistically tested

the null hypothesis that the population distribution of preferred phases is uniform on the

circle using Rayleigh's Z.

Cross-frequency coupling

We next sought to investigate whether higher-frequency dynamics were locked to midfrontal

theta phase in a manner relevant to the phase of peak power-RT correlations. Assessing the

modulation of higher-frequency power by lower-frequency phases is usually performed by

means of a phase-amplitude coupling index. However, here we chose a different approach

that would take into account the results of theta phase-resolved power-RT correlations. We

used GED (Cohen, 2017a) to define a component that maximizes activity around the phase of

maximum brain-behavior correlation. For each subject, the **R** matrix was defined as the data

filtered between each subject theta frequency $+ 2$ Hz and 80 Hz. This frequency range was

selected to eliminate both theta activity and higher-frequency activity unlikely to reflect brain

dynamics. For the **S** matrix, the same filtering was applied but we extracted the data around

the empirically determined phase of maximum theta power-RT correlation. We identified

each occurrence of the preferred theta phase in each trial (between 300 and 1200 ms), then

extracted the data from ⅛ of a theta cycle before that phase to ⅛ of a cycle after that phase

(the exact number of ms depended on subject-specific theta frequency); the covariance

matrices from these time windows were averaged to create the **S** covariance matrix. The

spatial filter with the largest generalized eigenvalue was selected to define the component. In

this case, rather than isolating narrowband theta dynamics, GED served the purpose of

enhancing the signal's characteristics in higher frequencies occurring around the phase of

maximum theta power-RT correlation.

Next, we applied time-frequency decomposition on the selected component to compute

power for each frequency (from 10 to 50 Hz) resolved according to the phase of the GED-

identified theta component which was divided into 51 bins (we used more bins than for

phase-resolved power-RT correlation to have a better phase resolution for the phase-

frequency power maps). We used the same Morlet wavelet convolution methods as described

above. Each phase-frequency map was phase-shifted so that phase = 0 corresponds to each

subject's phase of maximum theta power-RT correlation. Then, decibel-transformed power

(computed using the same methods and baseline as described above) was z-scored for each

frequency in order to quantify phase-specific modulation of power. Finally, clusters of

significant phase-specific changes in power were defined using permutation testing. For each

iteration, all the data after a randomly-defined relative theta phase (between the 10th and the

40th bins) were shifted and a difference map between the phase-shifted map and the original

unshifted map was calculated. This operation was carried out 10,000 times, generating a

distribution of difference maps under the null hypothesis. The average real data map was z-

scored using the mean and the standard deviation of the difference maps. The resulting map

was then thresholded at $p<0.001$. Multiple comparisons were addressed by the means of

cluster-based correction so that any cluster equal or larger than 99.9% of the distribution of

null hypothesis cluster sizes was considered significant. Power data from the biggest

significant cluster was then extracted and compared at the group level between conflict

conditions using a one-way ANOVA.

A GED component time series

B Filter at theta peak frequency and Hilbert transform

Time window for analysis

C θ mean power as a function of phase   Reaction Time

D

Averaged across subjects

E Phase resolved power-RT correlation

Figure 2: Overview of the method used to compute phase-resolved power-RT correlations. Each trial (A) was filtered using the theta frequency of maximum power previously found at FCz, and the Hilbert transform of that filtered signal was taken to extract phase and power. Power at each corresponding theta phase bin was extracted (B) and the average power for each phase bin was computed for all trials (C). Then, Spearman's ρ between power and RT were calculated at each phase bin for all subjects (D) and were then averaged across subjects (E).

Results

Behavioral results

The classical slowing of RTs as a function of conflict was observed in both studies (study 1: $F_{(1, 26)} = 6.17$, $p = 0.016$; study 2: $F_{(1,32)} = 20.81$, $p < 0.001$). Conflict trials were also significantly less accurate in study 1 (study 1: $F_{(1, 26)} = 60.6$, $p<0.0001$), and showed a similar trend in study 2 ($F_{(1,32)} = 3.54$, $p = 0.069$). For a more detailed description of behavioral results, please refer to Cohen (2015) and Gulbinaite et al. (2014).

GED results, component topography, and time-frequency power

Figure 3: A: Topographical map showing the activation pattern of the spatial filter designed by GED in study 1. B: Time-frequency plot of power (decibel-transformed) of the component defined by GED in study 1. C1 and C2: theta power time courses (vertical dashed lines

indicate the time window selected to compute the peak of power) and peak of power
according to the strength of conflict. D to F2: same plots for study 2.
Given our a priori focus on the theta band, we applied GED to find a spatial filter that best
isolates theta band activity from the broadband activity in the signal. Data reduction using
GED was implemented using the theta-filtered channel covariance matrix data as the **S** matrix
(mean theta frequency used for filtering: study 1: 4.6 ± 1.6 Hz, study 2: 5.4 ± 0.7 Hz) and the
broadband data channel covariance matrix as the **R** matrix. Figure 3 A and D show the
topography of the activation pattern of the selected spatial filters averaged across participants.
For both studies, a clear higher activation can be seen around midfrontal electrodes,
consistent with the topography of what is usually reported in the literature as midfrontal theta.
Time-frequency decomposition of the selected component in study 1 shows a clear increase
in power compared to baseline in the theta band (Figure 3B). This power increase was
stronger with increasing conflict strength and was the highest for errors (Figure 3C1). Figure
3C1 and C2 shows the same pattern focusing on the power time course of the peak theta
frequency and the peak of power for that frequency respectively. In study 2, the same results
were observed with a clear theta power increase that was stronger in the situations of
strongest conflict (cI trials) compared to all other trials (cC, iI, and iC trials; Figure 3E, F1
and F2). As in study 1, errors showed the strongest increase in theta power. As a whole, these
results show that applying GED for spatial filtering successfully produced a signal that
exhibits all effects that are typically reported in conflict resolution studies. Given that the data
in study 2 were Laplacian-transformed (which was not the case in study 1), we Laplacian-
transformed the data from study 1 and recomputed the GED spatial filters as well as the time-
frequency power maps to ensure that the main results did not depend on Laplacian
transformation. Applying the Laplacian transform did not change the results both at the
subject- or at the group-level with similar topographies and nearly identical time-frequency
power maps (see supplemental figure S1).

Theta power-RT correlations

Following previous reports (Cohen and van Gaal, 2014), we first investigated brain-behavior
relationships by means of cross-trial correlations between power and RT (ignoring theta
phase). This analysis also served the purpose to define a time-window of significant theta
power-RT correlation to investigate the potential modulation according to theta phase. For
each subject and each condition, Spearman's rho was computed across trials between power

at the peak theta frequency and RT at each time point, resulting in one time course of power-

RT rho values per subject and condition (see Figure 4, for group average result). In both

studies, an increase in theta power-RT correlation began around 200-300 ms, peaked around

500-600 ms and was immediately followed by a decrease in all conditions, except error trials.

The pattern of power-RT correlation for errors was clearly distinct, beginning with a sharp

decrease around 200-300 ms, followed by an increase peaking around 600-700 ms and finally

a return to zero. Using cluster-based permutation tests, we tested the null hypothesis that the

population distribution of the power-RT correlations is symmetric around zero. Rejection of

the null hypothesis at $p < 0.05$ was observed from roughly 300 ms to 1200 ms in Study 1

(Figure 4A), and from 200 ms to 1200 ms in Study 2 (Figure 4C). Based on this result, for

subsequent phase-resolved analyses we selected the following time windows: 300 to 1200 ms

for study 1 and 200 to 1200 ms for study 2.

Study 1

A

Study 2

C

B1

D1

B2

D2

Figure 4: *Time course of Spearman's ρ between theta power and RT averaged across subjects for each condition in study 1 (A) and 2 (C). Horizontal bars above the x-axis denote windows of statistical significance at the group-level. B1 and B2: phase-resolved Spearman's rho between theta power and RT. These plots show the average (B1) and detrended (B2) theta power-RT correlation coefficient according to theta phase. D1 and D2: same plots for study 2.*

In both studies, and consistent with previous reports (Cohen and Cavanagh, 2011; Cohen and van Gaal, 2014), the highest peak of correlation was observed for the trials with the strongest conflict (mixed correct and cI trials respectively). However, statistical testing confirmed this was the case only in study 1. We extracted the peak of maximum correlation from the time windows defined above and applied pairwise Wilcoxon paired test to compare between

conflict conditions. We found that partial errors were indeed the situation in which RT-power

correlations were maximal (mixed correct vs. no conflict: $p = 1.26*10^{-6}$; partial error vs.

partial conflict: $p = 7.2*10^{-5}$; full conflict vs. no conflict: $p = 0.0014$; all other conflict

conditions comparisons were non-significant at $p>0.005$ using Bonferroni correction).

However, in study 2, the peak of maximum correlation did not differ between conflict

conditions (all $p>0.005$).

Phase-resolved theta power RT correlation

We further investigated the influence of theta phase on brain-behavior relationships. We

reasoned that if theta phase defines certain time-windows of behaviorally-relevant brain

computations, fluctuations of theta power-RT correlations would vary as a function of theta

phase. To test this, we averaged power in 20 discrete theta phase bins (in previously defined

significant theta power-RT correlation time windows), and correlated this phase-resolved

average theta power with RTs. This was done separately for each subject and condition.

Given that the size of the selected time windows was 900 ms for study 1 and 1000 ms for

study 2, and given that the average theta frequency was 4.6 ± 1.6 Hz in study 1 and 5.4 ± 0.7

Hz in study 2, all phase-resolved theta power-RT correlations were obtained based on at least

4 theta cycles.

At the group-level, correlations were higher for some theta phases than for the others in all

conditions and in both studies. This can be seen in Figure 4B1 and D1, but is more evident in

the detrended coefficients in Figure 4B2 and D2. Closer inspection, however, revealed

subject-level phase preferences across conditions and subjects (see sine fit plots in Figure

5A). We therefore computed nonlinear least square estimations for each subject and for each

condition, specifying a sine function with sine parameters to be estimated from the data. The

estimated parameters were then entered in a linear model to inspect overall significance and

the goodness of fit of the models.

481   ○   Sine fit

All sine fit graphs are depicted in supplementary figure S2 and S3, and an example fit can be

seen in figure 5A. For each condition and in both studies, sine waves were significant

predictors for the observed phase-resolved power-RT correlations, across subjects and

conditions in both studies. Since the amplitude parameter is the best predictor of the size of

the phase-resolved effect, we only report these results here (see supplementary table S1 to see

the proportion of subjects with significant parameters r). In study 1, 100, 96, 96, 100 and

100% of the nls fits showed significant amplitude parameters for the no conflict, partial

conflict, full conflict, mixed correct, and error conditions respectively. In study 2, 100, 97,

100, 97, 97 % of the nls fits showed significant amplitude parameters for the cC, iC, iI, cI and

error conditions respectively. Overall, for both studies, 95.8% of the linear models using nls-

defined parameters significantly fitted the data. This indicates that in both studies, and in all

conditions, theta power-RT correlations were stronger for some phases than for others.

Figure 5: A: example of the sine fit for 18 subjects in the no-conflict condition in study 1. All
sine fit plots can be seen in supplementary figure S2 and S3. B1 and C1: average amplitude
parameter according to conditions for study 1 and 2, respectively. In both studies, errors had
a significantly higher amplitude parameter than all other conditions (p<0.001). B2 and C2:
average R-squared according to condition for study 1 and 2 respectively. Color coding of
conditions is the same as in Figure 4 (weaker to stronger conflict and errors from left to
right). Error bars represent the standard error of the mean.

503   ○ Group-level amplitude and R-squared comparison

We tested whether the theta phase influence on brain-behavior relationships depended on the
strength of conflict, assessed as the amplitude of the fitted sine wave, as this indicates the
magnitude of theta phase on theta power-RT correlations. We performed pairwise Wilcoxon
tests on the condition-specific amplitude parameters, using a significance threshold of $p <$
0.005 (Bonferroni correction for 10 comparisons). As can be seen in figure 5B1 and C1, the
amplitude parameter was not statistically different across correct conditions, and was
different for error trials. Indeed, amplitude for errors was significantly higher than for other
conditions in both studies (all error-other condition pairwise wilcoxon paired test were
significant at $p<0.0001$ in both studies; all other pairwise comparisons were non-significant).
We subsequently tested whether the strength of conflict impacted the fit of the models to the
data (R^2). In both studies, R^2 did not significantly differ between conditions (all pairwise
wilcoxon paired test were non-significant) (Figure 5B2 and C2), suggesting that the goodness
of fit of the models were similar across the different levels of conflict in both studies.

○   Phase consistency

Given the fluctuations of theta power-RT correlations according to theta phase, we also
investigated whether the phase preference (the phase of maximal theta power-RT correlation
defined by the empirical data) was consistent across subjects in each condition. To that end,
we computed phase clustering of the phase of maximal theta power-RT correlation for each
condition (see supplemental figure S4). Preferred phase was not clustered and was relatively
homogeneously distributed, except for errors in study 2 which showed significant clustering
(p =0.002) around phase = 0. In all other cases, clustering measures were non-significant,
confirming that the phase of maximum theta power-RT correlation was subject- and
condition-specific.

○   Power and RT as a function of phase

To further contextualize the theta-phase-modulated brain-behavior correlations, and to
evaluate whether the fluctuating correlations were due to information fluctuations in the
individual variables, we examined whether theta power or RT independently were modulated
by theta phase. We used the same theta phase discretization as for the correlation analyses,
but now focusing on theta power and RT separately rather than on their correlation.

Supplementary figure S5B1-D1, and S5B2-C2 show the detrended average theta power and

standard deviation, respectively, according to phase for study 1 and 2. Theta power and its

standard deviation in both studies displayed a clear modulation according to phase, thus

indicating that power was stronger at certain theta phases and lower at others. Such

asymmetries in power over phase bins also point to a non-sinusoidal waveform shape (Cole

and Voytek, 2017). Conversely, average RT and its standard deviation in both studies

(supplementary figure S5F1-H1 and S5F2-H2) showed no clear evidence of phase-dependent

fluctuations.

Control analyses

Although all the results argue in favor of the hypothesis that theta phase influences brain-

behavior relationships, we wanted to test whether the effect we found was specific to the

theta band and whether the effect was reproducible within each dataset individually (cross-

validation). We chose to test phase-resolved brain-behavior correlations in the beta band,

since beta suppression is also typically observed around RT in conflict tasks (see Figure 3B

and E) and since beta activity has been shown to relate to RT and errors (Doyle et al., 2005;

Torrecillos et al., 2015).

557   ○ Theta band specificity - test of beta phase-resolved power-RT correlations

We extracted power from the Hilbert transform of the beta bandpass-filtered (between 15 and

20 Hz) theta-defined component and computed power-RT Spearman correlations at each time

point. We selected the beta band because it is another frequency range that is observable in

midfrontal topographical regions during conflict tasks (Figure 3). As can be seen in

supplementary figure S6A and S6C, the patterns of power-RT correlations are clearly

different from the theta results in both studies. For all conditions in study 1, only negative

correlations can be observed occurring between around 500 and 1000 ms and with an effect

roughly half the size of what was observed in theta. Study 2 shows the same pattern of

negative correlation occurring this time mostly between 500 and 900 ms with a significant

increase beginning at 1000 ms.

In order to test theta-specificity of phase-resolved results, we computed beta power-RT

correlation for the 20 beta phase bins during the significant theta power-RT correlation time

window. Supplementary figure S6B1-B2 and S6D1-D2 show the average and detrended

version of the phase-resolved beta power-RT correlations for study 1 and 2. Even though

visual inspection did not suggest an effect of phase, given a high interindividual variability in

theta phase preference when investigating theta phase-resolved power-RT correlation, we

nonetheless inspected beta phase-resolved results at the subject level and performed the same

sine wave modeling as for the theta results. As expected, no clear oscillation of correlation

according to the beta phase was observed: sine wave model accounted for the data with 50,

39, 28, 25 and 25% of significant nls fits for the no conflict, partial conflict, full conflict,

mixed correct, and error conditions respectively in study 1. For study 2, the same results were

observed with 41, 29, 26, 35, and 47% of significant *nls* sine fits amplitude parameter for the

cC, iC, iI, cI and error conditions respectively (see supplementary table 1 for details of all

parameters). This control analysis provides further support for theta-band specificity in phase

dependent power-RT correlations.

○   Split-half reliability

In order to evaluate if the phase dependent theta power-RT correlation effect was consistent

across trials within subject, we re-analyzed all the data separately for two halves of the data

collapsed across conditions. This operation was repeated 100 times by randomly selecting

two groups of trials. In both studies, results matched the pattern of theta power-RT

correlation observed when analyzing all the data. We next examined whether the preferred

phase that maximized power-RT correlations was consistent between the two halves of the

data. We therefore computed the subject-averaged difference in preferred phases between the

two halves, for each iteration; this generated a distribution of 100 phase difference values, on

which we computed phase clustering. If the preferred phases are consistent, the different

distribution should cluster around 0 radians across subjects. We observed significant

clustering of the phase differences around 0 for both studies (study 1: $p<0.001$, study 2:

$p<0.001$; supplemental figure S7A and S7B). We further inspected the overall correlation

between the two halves of the data for those 100 iterations and observed significant positive

correlations in 100% of the cases in both studies (mean $\rho = 0.48$, mean $p < 0.0001$ for study 1

and mean $\rho = 0.44$, mean $p < 0.0001$ for study 2. Taken together, these results show that the

phase effect we found was consistent across the experiment.

Cross-frequency coupling

The previous sets of analyses demonstrated that theta phase is relevant for brain-behavior
relationships. We next investigated whether this same theta phase is relevant for higher-
frequency EEG activity. We focused on phase-amplitude CFC (Canolty & Knight, 2010)
under the assumption that if theta phase is relevant for brain computations that serve
behavior, then specific patterns of CFC could appear around the phases of maximal power-
RT correlations.

We applied the GED framework to identify a component that maximizes EEG activity around
the phase of maximum theta power-RT correlation at higher-frequencies. Figure 6A1 and A2
show the topography of the activation pattern of the spatial filter for study 1. Figure 6A2 is
the laplacian-transformed spatial filter topography that we computed in order to better
compare with the topography of study 2 (Figure 6D) in which the data were scalp-Laplacian-
transformed. In both studies, but even more so in study 2, the topographies highlighted
centro-parietal and parietal electrodes. In study 1 higher activation was observed around
midfrontal electrodes.

We inspected power at each theta phase bin (51 bins) and for each frequency. Figure 6B1 and
E1 show theta phase-frequency power maps for study 1 and 2 respectively. In both cases
cluster-corrected permutation testing revealed significant increases in power between 0 and -
$\pi/2$ and in the upper alpha-beta frequency range (biggest cluster in the map) (power peaks
were at phase $-\pi/5$ and at 19 Hz for study 1 and at phase $-\pi/6$ at 17 Hz for study 2). Note that
these phase angles are relative to subject-specific peak power-RT correlations, not absolute
theta phase angles. Power was extracted in the biggest significant cluster and was compared
between conditions (Figure 6B2 and E2). In both studies, power did not differ between
conflict conditions (study 1: $F(4, 135) = 0.44$, $p = 0.8$; study 2: $F(4, 165) = 0.62$, $p = 0.65$),
suggesting that phase-specific increase in power reflected a general mechanism that was
related to response execution but not specific to conflict processing.

Figure 6: *A1-A2: topography of the spatial filter defined by GED (A2 is the scalp Laplacian-transformed topography) in study 1. D: spatial filter topography for study 2. In both studies, activation around centro-parietal and parietal electrodes can be observed. More midfrontal activation is seen in study 1. B1 and E1: theta phase-frequency power map for study 1 and 2, respectively. Contour lines show significant clusters (with sizes exceeding the mean cluster size plus 2 standard deviations after cluster correction of permutation testing). B2 and E2: power extracted from the common cluster of study 1 and 2, respectively. C1 and F1: theta phase-frequency power map computed by averaging the maps calculated using a cross-validation approach from study 1 and 2, respectively. C2 and F2: power extracted from the common cluster from study 1 and 2, respectively. Color coding of conditions is the same as in previous figures and goes from weaker to stronger conflict and errors from left to right. Error bars represent the standard error of the mean.*

To ensure that these results were robust, and that they were not biased by overfitting, we re-analyzed the data using a cross-validation approach. We used 90% of the data to compute the cross-frequency-coupling spatial filter using the same criteria as previously described, and applied it to the remaining 10% of the data. This operation was carried out 10 times, and the

resulting phase-frequency maps were averaged over iterations for each subject. The same

permutation testing as in the original CFC analyses was then applied. The spatial filter

topographies looked the same as the ones in our first set of analyses, and thus are not depicted

in figure 6. Although some differences with the first analyses can be seen, the previously

described common cluster was also present here with a significant increase in power between

0 and $-\pi/2$ in the upper alpha-beta band (Figure 6C1 and F1). In both studies the frequency

and theta phase of the peak of power from that cluster was very similar to the first analysis

with a peak at 22.8 Hz $-\pi/5$ for study 1 and at 24.8 Hz and $-4\pi/7$ for study 2. Similar to the

first analysis, power extracted from those clusters did not show any significant change

according to the strength of conflict (Figure 6C2 and F2; study 1: $F_{(4, 135)} = 0.48$, $p = 0.7$;

study 2: $F_{(4, 165)} = 0.87$, $p = 0.5$). As a whole, both the cross-validation approach and the

replication in the 2 independent datasets strongly suggest that there was a specific increase in

power in the beta band around $-\pi/5$ relative to the phase of maximum power-RT correlation

that was not specific to the strength of conflict but rather generally involved in response

execution.

Discussion

In their formulation of the theta-gamma neural code, Lisman and Jensen (2013)

emphasized that theta oscillations may "provide a way of ordering multipart messages."

Although their conclusions specifically related to the role of hippocampal theta phase in

spatial location and memory, this formulation also echoes with the proposal that neural

oscillations have a general role in providing time references for brain computation (Fries,

2005; Voytek and Knight, 2015). With this study we investigated a key hypothesis of one

potential role of midfrontal theta oscillations, namely, whether they define specific time

windows during which brain computations that are relevant for response conflict processing

occur (Cohen, 2014a). We computed phase-resolved brain-behavior correlation based on a

multivariate analysis method that maximizes signal-to-noise ratio of relevant features of the

EEG signal. Results from two independent studies confirmed the robustness of the findings.

Implications for the role of midfrontal theta in brain computations

Although theta phase has already been shown to be important for perceptual and

motor activities (Drewes and van Rullen, 2011; Tomassini et al., 2017; Han and van Rullen,

2017), to our knowledge this study provides the first empirical evidence of a temporal

organization relying on an internal reference frame defined by the phase of ongoing theta

activity around midfrontal electrodes during cognitive control (Panzeri et al., 2010). It has

been proposed that different computations for conflict processing would be implemented by a

neural microcircuit in the midfrontal cortex in a layer-specific manner (Cohen, 2014a).

Although it would be hazardous to speculate on the contribution of the layer-specific activity

in the scalp EEG signal and their theta phase-relative organization, if midfrontal theta

oscillations organize conflict processing, it is plausible that different theta phase regions

could provide temporal constraints for computations occurring in different cortical layers. In

that manner, specific computations during conflict processing may take place at specific theta

phases. For instance, the relevant phase described in this study could be specific to a largely

motor-related mechanism that underlies response execution, while time windows of opposite

phases could preferentially support conflict integration, or communication with long range

task-relevant cortical areas responsible for selective inhibition or modulation of attention. A

more physiologically detailed understanding of the role of midfrontal theta oscillations in

conflict processing will require additional work with invasive recordings (including local

field potential and single units). However, the results of this study provide strong evidence

for the oscillatory nature of the signals involved in conflict processing and, most importantly,

gives insights on the existence of a temporal organization during conflict processing by

midfrontal theta oscillations in humans.

Our findings also have implications for ongoing discussions about the nature of midfrontal

theta. In particular, whether the EEG signature of response conflict monitoring truly reflects a

"neural oscillation" or simply a non-oscillatory transient remains debated (Yeung et al., 2007,

Trujillo & Allen, 2007, Cohen & Donner 2013). Our phase-dependent brain-behavior

findings provide new evidence for the interpretation of a neural oscillation. A phase-specific

finding that is present after removing the phase-locked part of the signal reflects amplitude

modulations of ongoing narrowband activity, and thus is inconsistent with an interpretation of

the conflict-modulated theta burst as an additive transient (which was removed from the data

prior to our analyses).

Midfrontal theta phase influences the strength of brain-behavior relationships

Midfrontal theta has been consistently shown to be relevant for behavior during conflict
processing, as RT strongly correlates with power (McDermott et al., 2017; Jiang et al., 2015a;
Jiang et al., 2015b; Jiang et al., 2018). This correlation is especially strong for high-conflict
trials and immediately preceding the response (Cohen and Cavanagh, 2011; Cohen and van
Gaal 2014). The present study provides yet another replication of these results (in Study 1)
and, in line with our hypothesis, further shows that the strength of these correlations depends
on the phase of the ongoing midfrontal theta oscillation. The effect was specific to the theta
band and reliable across the experiments in two different conflict tasks (Eriksen flanker task
and Simon task). Furthermore, specific investigation of phase-resolved power revealed that
theta power was non-uniformly distributed around the theta cycle, which is indicative of a
non-sinusoidal waveform shape (Cole and Voytek, 2017). This suggests that the influence of
theta phase on brain-behavior relationships may have resulted from the waveform shape of
the midfrontal theta oscillation. The phase effect on RT-power correlation was independent
on the strength of conflict, which points to a general response execution mechanism
occurring during conflict processing rather than a purely conflict-related mechanism as we
hypothesized. We nonetheless observed some condition differences, with a greater phase
effect for errors compared to all other conditions. This error-specific modulation is consistent
with a general observation that errors have qualitatively distinct patterns of theta-RT
correlations compared to correct responses, with negative correlations followed by positive
correlations while only positive correlations occur in correct responses (Cohen and van Gaal
2014). EEG signatures of errors also differ from those of conflict in correct responses
because of their additional recruitment of delta power (Yordanova et al., 2004; Cohen and
van Gaal, 2014) and phase-locked component (Trujillo and Allen, 2007; Munneke et al.,
2015).
An intriguing point is that the phase of maximal power-RT correlation was not only subject-
specific, but also condition-specific. This pattern, although robust in the results, is hard to
interpret. Indeed, we don't have any evidence that the different conflict conditions might re-
align the phase of maximum correlation because stimuli in both studies were randomly
displayed. Moreover, this was especially true for mixed correct trials, which were not even an
experimental condition *per se* but a way to isolate the situations of high conflict based on the
participants' behavior (muscular activation of incorrect and correct responses). Further work
will be needed to clarify this point.

Midfrontal theta "clocks" large-scale cross-frequency coupling

A phase-dependency of a brain-behavior correlation suggests that certain computations are
more likely to occur at certain theta phases. An ideal analysis to evaluate this hypothesis is to
test for phase-specific activation of cell assemblies. In lieu of such an approach, however, we
turned to phase-amplitude coupling, with the hypothesis that the behaviorally-optimal theta
phase should also predict activity represented in higher frequencies. We applied a recently
developed multivariate phase-amplitude coupling method that allowed us to differentiate
between topographies of the phase-providing and the power-responding networks (Cohen
2017a). This analysis revealed that cross-frequency interactions were most pronounced in a
fronto-parietal topography in the Simon task, and a fronto-lateral topography in the Eriksen
flanker task. These topographical differences may be attributed to differences in the source of
response conflict in these two tasks: although both tasks generate conflict as incongruency in
response hands, *spatial* incongruity elicits conflict in the Simon task, whereas stimulus
identity incongruency elicits conflict in the Eriksen flanker task. Such task differences have
been shown to elicit slight differences in temporal and spatial dynamics of the brain activity
(Frühholz et al., 2011; Nigbur et al., 2011).

Importantly, the pattern of theta-phase-locked time-frequency power looked remarkably
similar despite the topographical idiosyncrasies, suggesting that the conflict-related theta
rhythm provides a fundamental organizational principle that is used in similar ways by
potentially distinct task-specific networks. In particular, the relevant theta phase was
associated with power bursts in the beta band. This pattern was consistent across both
datasets and was robust to two distinct statistical evaluation methods (permutation testing and
cross-validation). Beta oscillatory activity has consistently been associated with motor
control (Kilavik et al., 2013; Neuper et al., 2006), notably because of the exaggerated beta
activity in Parkinson's disease (Oswal et al., 2013). Motor-related beta is centered around the
motor cortex and emerges as short-lived burst that are suggested to underlie response
execution (Feingold et al., 2015). This suggests that the theta-phase-locked beta power bursts
we found around motor areas relate to response execution. Moreover, we did not detect
condition-specific modulations of multivariate phase-amplitude coupling. This also argues for
a signature of a general response-related mechanism. On the other hand, condition differences
might be too subtle or small-scale to be reliably detected with extracranial EEG. It is also
possible that theta phase is regulating rhythmic fluctuations in attention through rhythmic

enhancement of visual processing (Fiebelkorn et al., 2018), which might be important for task

performance but equally prevalent across conditions.

Guided source separation for guided network discovery

The kinds of findings reported here may be subtle (low signal-to-noise at the level of EEG),

temporally transient, and spectrally narrowband. However, they are linearly distributed over

many electrodes, which means that targeted multivariate analysis methods can help reveal

patterns in the data that may be too mixed to uncover when analyzing only individual

electrodes. We used a blend of hypothesis-driven (e.g., defining a component that maximizes

theta activity) and data-driven (to define a component that maximizes specific theta phase

activity) approaches in applying generalized eigendecomposition as spatial filters. This

increased the signal-to-noise ratio and highlighted features of behaviorally-relevant brain

activity that otherwise might have remained too subtle to be observed. We believe that these

kinds of methods may be useful for elucidating subtle brain-behavior relationships in other

contexts as well.

Author contributions:

JD: Conceptualization, Methodology, Formal analysis, Data curation, Writing - original

draft, review & editing

RG: Conceptualization, Resources, Data curation, Writing - review & editing

MXC: Conceptualization, Resources, Methodology, Data curation, Writing - review &

editing, Supervision

Declaration of Interests

The authors declare no competing interests.

References

Anguera, J.A., Boccanfuso, J., Rintoul, J.L., Al-Hashimi, O., Faraji, F., Janowich, J., Kong,
E., Larraburo, Y., Rolle, C., Johnston, E., et al. (2013). Video game training enhances
cognitive control in older adults. Nature *501*, 97–101.

Appelbaum, L.G., Smith, D.V., Boehler, C.N., Chen, W.D., and Woldorff, M.G. (2011).
Rapid modulation of sensory processing induced by stimulus conflict. J. Cogn. Neurosci. *23*,
2620–2628.

Bonnefond, M., Kastner, S., and Jensen, O. (2017). Communication between Brain Areas
Based on Nested Oscillations. ENeuro.

Buzsáki, G., and Draguhn, A. (2004). Neuronal oscillations in cortical networks. Science *304*,
1926–1929.

Canolty, R.T., and Knight, R.T. (2010). The functional role of cross-frequency coupling.
Trends Cogn. Sci. *14*, 506–515.

Cavanagh, J.F., Wiecki, T.V., Cohen, M.X., Figueroa, C.M., Samanta, J., Sherman, S.J., and
Frank, M.J. (2011). Subthalamic nucleus stimulation reverses mediofrontal influence over
decision threshold. Nat. Neurosci. *14*, 1462–1467.

de Cheveigné, A., and Arzounian, D. (2015). Scanning for oscillations. J. Neural Eng. *12*.

Cohen, M.X. (2014a). A neural microcircuit for cognitive conflict detection and signaling.
Trends Neurosci. *37*, 480–490.

Cohen, M.X. (2014b). Analyzing neural time series data: theory and practice (MIT press).

Cohen, M.X. (2015). Comparison of different spatial transformations applied to EEG data: A
case study of error processing. Int. J. Psychophysiol. *97*, 245–257.

Cohen, M.X. (2017a). Multivariate cross-frequency coupling via generalized
eigendecomposition. ELife *6*.

Cohen, M.X. (2017b). Comparison of linear spatial filters for identifying oscillatory activity
in multichannel data. J. Neurosci. Methods *278*, 1–12.

Cohen, M.X., and Cavanagh, J.F. (2011). Single-trial regression elucidates the role of
prefrontal theta oscillations in response conflict. Front. Psychol. *2*, 30.

Cohen, M.X., and Donner, T.H. (2013). Midfrontal conflict-related theta-band power reflects
neural oscillations that predict behavior. J. Neurophysiol. *110*, 2752–2763.

Cohen, M.X., and van Gaal, S. (2013). Dynamic interactions between large-scale brain
networks predict behavioral adaptation after perceptual errors. Cereb. Cortex N. Y. N 1991
23, 1061–1072.

Cohen, M.X., and van Gaal, S. (2014). Subthreshold muscle twitches dissociate oscillatory
neural signatures of conflicts from errors. NeuroImage *86*, 503–513.

Cohen, M.X., and Ridderinkhof, K.R. (2013). EEG source reconstruction reveals frontal-
parietal dynamics of spatial conflict processing. PloS One *8*, e57293.

Cole, S.R., and Voytek, B. (2017). Brain Oscillations and the Importance of Waveform
Shape. Trends Cogn. Sci. *21*, 137–149.

Delorme, A., and Makeig, S. (2004). EEGLAB: an open source toolbox for analysis of
single-trial EEG dynamics including independent component analysis. J. Neurosci. Methods
134, 9–21.

Doyle, L.M., Yarrow, K., and Brow, P. (2005). Lateralization of event-related beta
desynchronization in the EEG during pre-cued reaction time tasks. Clin. Neurophysiol. *116*,
1879-1888.

Drewes, J., and VanRullen, R. (2011). This is the rhythm of your eyes: the phase of ongoing
electroencephalogram oscillations modulates saccadic reaction time. J. Neurosci. Off. J. Soc.
Neurosci. *31*, 4698–4708.

van Driel, J., Swart, J.C., Egner, T., Ridderinkhof, K.R., and Cohen, M.X. (2015). (No) time
for control: frontal theta dynamics reveal the cost of temporally guided conflict anticipation.
Cogn. Affect. Behav. Neurosci. *15*, 787–807.

Elzhov, T. V., Mullen, K. M., Spiess, A. N., and Bolker, B. (2016). R Interface to the
Levenberg-Marquardt Nonlinear Least-Squares Algorithm Found in MINPACK, Plus
Support for Bounds.

Feingold, J., Gibson, D.J., DePasquale, B., and Graybiel, A.M. (2015). Bursts of beta
oscillation differentiate postperformance activity in the striatum and motor cortex of monkeys
performing movement tasks. PNAS *112*, 13687–13692.

Fiebelkorn, I. C., Pinsk, M. A., and Kastner, S. (2018). A dynamic interplay within the
frontoparietal network underlies rhythmic spatial attention. Neuron. *99*, 842-853.
909
910 Fries, P. (2005). A mechanism for cognitive dynamics: neuronal communication through
911 neuronal coherence. Trends Cogn. Sci. *9*, 474–480.
912
913 Frühholz, S., Godde, B., Finke, M., and Herrmann, M. (2011). Spatio-temporal brain
914 dynamics in a combined stimulus-stimulus and stimulus-response conflict task. NeuroImage
915 *54*, 622–634.
916
917 Gulbinaite, R., van Rijn, H., and Cohen, M.X. (2014). Fronto-parietal network oscillations
918 reveal relationship between working memory capacity and cognitive control. Front. Hum.
919 Neurosci. *8*, 761.
920
921 Han, B., and VanRullen, R. (2017). The rhythms of predictive coding? Pre-stimulus phase
922 modulates the influence of shape perception on luminance judgments. Sci. Rep. *7*, 43573.
923
924 Hanslmayr, S., Pastötter, B., Bäuml, K.-H., Gruber, S., Wimber, M., and Klimesch, W.
925 (2008). The electrophysiological dynamics of interference during the Stroop task. J. Cogn.
926 Neurosci. *20*, 215–225.
927
928 Haufe, S., Meinecke, F., Görgen, K., Dähne, S., Haynes, J.-D., Blankertz, B., and Bießmann,
929 F. (2014). On the interpretation of weight vectors of linear models in multivariate
930 neuroimaging. NeuroImage *87*, 96–110.
931
932 Jensen, O., Gips, B., Bergmann, T.O., and Bonnefond, M. (2014). Temporal coding
933 organized by coupled alpha and gamma oscillations prioritize visual processing. Trends
934 Neurosci. *37*, 357–369.
935
936 Jiang, J., Zhang, Q., and van Gaal, S. (2015a). Conflict awareness dissociates theta-band
937 neural dynamics of the medial frontal and lateral frontal cortex during trial-by-trial cognitive
938 control. NeuroImage *116*, 102–111.
939
940 Jiang, J., Zhang, Q., and Gaal, S.V. (2015b). EEG neural oscillatory dynamics reveal
941 semantic and response conflict at difference levels of conflict awareness. Sci. Rep. *5*, 12008.
942
943 Jiang, J., Bailey, K., and Xiao, X. (2018). Midfrontal Theta and Posterior Parietal Alpha
944 Band Oscillations Support Conflict Resolution in a Masked Affective Priming Task. Front.
945 Hum. Neurosci. *12*.
946
947 Kilavik, B.E., Zaepffel, M., Brovelli, A., MacKay, W.A., and Riehle, A. (2013). The ups and
948 downs of β oscillations in sensorimotor cortex. Exp. Neurol. *245*, 15–26.
949
Lisman, J.E., and Jensen, O. (2013). The θ-γ neural code. Neuron *77*, 1002–1016.

Maris, E., Fries, P., and van Ede, F. (2016). Diverse Phase Relations among Neuronal
Rhythms and Their Potential Function. Trends Neurosci. *39*, 86–99.

McDermott, T.J., Wiesman, A.I., Proskovec, A.L., Heinrichs-Graham, E., and Wilson, T.W.
(2017). Spatiotemporal oscillatory dynamics of visual selective attention during a flanker
task. NeuroImage *156*, 277–285.

Min, B.-K., Kim, S.J., Park, J.Y., and Park, H.-J. (2011). Prestimulus top-down reflection of
obsessive-compulsive disorder in EEG frontal theta and occipital alpha oscillations. Neurosci.
Lett. *496*, 181–185.

Mizuseki, K., Sirota, A., Pastalkova, E., and Buzsáki, G. (2009). Theta oscillations provide
temporal windows for local circuit computation in the entorhinal-hippocampal loop. Neuron
64, 267–280.

Munneke, G.-J., Nap, T.S., Schippers, E.E., and Cohen, M.X. (2015). A statistical
comparison of EEG time- and time-frequency domain representations of error processing.
Brain Res. *1618*, 222–230.

Neuper, C., Wörtz, M., and Pfurtscheller, G. (2006). ERD/ERS patterns reflecting
sensorimotor activation and deactivation. Prog. Brain Res. *159*, 211–222.

Nigbur, R., Ivanova, G., and Stürmer, B. (2011). Theta power as a marker for cognitive
interference. Clin. Neurophysiol. Off. J. Int. Fed. Clin. Neurophysiol. *122*, 2185–2194.

Nikulin, V.V., Nolte, G., and Curio, G. (2011). A novel method for reliable and fast
extraction of neuronal EEG/MEG oscillations on the basis of spatio-spectral decomposition.
NeuroImage *55*, 1528–1535.

Oswal, A., Brown, P., and Litvak, V. (2013). Synchronized neural oscillations and the
pathophysiology of Parkinson's disease. Curr. Opin. Neurol. *26*, 662–670.

Panzeri, S., Brunel, N., Logothetis, N.K., and Kayser, C. (2010). Sensory neural codes using
multiplexed temporal scales. Trends Neurosci. *33*, 111–120.

Pastötter, B., Dreisbach, G., and Bäuml, K.-H.T. (2013). Dynamic adjustments of cognitive
control: oscillatory correlates of the conflict adaptation effect. J. Cogn. Neurosci. *25*, 2167–
2178.

R Development Core Team, (2017). R: A language and environment for statistical
computing. R Foundation for Statistical Computing, Vienna, Austria. ISBN 3-900051-07-0,
URL http://www.R-project.org.

Tomassini, A., Ambrogioni, L., Medendorp, W.P., and Maris, E. (2017). Theta oscillations
locked to intended actions rhythmically modulate perception. ELife *6*.
997
998 Torrecillos, F., Alayrangues, J., Kilavik, B.E., and Malfait, N. (2015). Distinct Modulations
999 in Sensorimotor Postmovement and Foreperiod β-Band Activities Related to Error Salience
1000 Processing and Sensorimotor Adaptation. J. Neurosci. *35*. 12753-12765.
1001
1002 Trujillo, L. T., and Allen, J. J. (2007). Theta EEG dynamics of the error-related negativity.
1003 Clin Neurophysiol. *118*(3), 645-68.
1004
1005 Vissers, M.E., Ridderinkhof, K.R., Cohen, M.X., and Slagter, H.A. (2018). Oscillatory
1006 Mechanisms of Response Conflict Elicited by Color and Motion Direction: An Individual
1007 Differences Approach. J. Cogn. Neurosci. *30*, 468–481.
1008
1009 Voytek, B., and Knight, R.T. (2015). Dynamic network communication as a unifying neural
1010 basis for cognition, development, aging, and disease. Biol. Psychiatry *77*, 1089–1097.
1011
1012 Wang, X.-J. (2010). Neurophysiological and computational principles of cortical rhythms in
1013 cognition. Physiol. Rev. *90*, 1195–1268.
1014
1015 van den Wildenberg, W.P.M., Wylie, S.A., Forstmann, B.U., Burle, B., Hasbroucq, T., and
1016 Ridderinkhof, K.R. (2010). To head or to heed? Beyond the surface of selective action
1017 inhibition: a review. Front. Hum. Neurosci. *4*, 222.
1018
1019 Yeung, N., Bogacz, R., Holroyd, C.B., Nieuwenhuis, S., and Cohen, J.D. (2007). Theta phase
1020 resetting and the error-related negativity.Psychophysiology. *44*, 39-49.
1021
1022 Yordanova, J., Falkenstein, M., Hohnsbein, J., and Kolev, V. (2004). Parallel systems of error
1023 processing in the brain. Neuroimage *22*, 590–602.

1038

1039

1040

1041   **Supplemental information**

1042

1043

Figure S1:   A1: Topographical map showing the activation pattern of the spatial filter
designed by GED and the corresponding time-frequency power map for one subject in study
1 without the Laplacian spatial filter. A2: same plots with the Laplacian spatial filter. B1:
Topographical map showing the activation pattern of the spatial filter designed by GED and
the corresponding time-frequency power map averaged over all subjects in study 1 without
the Laplacian spatial filter. B2: same plots with the Laplacian spatial filter.

1050

1051

1052

1053

1054

1055

1056

1057

1058

1059

1060

1061

1062
1063   **Figure S2: Sine fit plots of all subjects and in all conditions in study 1.** The plots show
1064   theta power-RT correlation as a function of theta phase. Color coding of conditions is the
1065   same as in previous figures and goes from weaker to stronger conflict and errors from upper
1066   left to bottom right.

Figure S3: Sine fit plots of all subjects and in all conditions in study 2. The plots show theta power-RT correlation as a function of theta phase. Color coding of conditions is the same as in previous figures and goes from weaker to stronger conflict and errors from upper left to bottom right.

1072

1073 **Table S1: Overview of the sine fit results for the theta and beta analyses for study 1 and**
1074 **2.** Numbers show the percentage of significant parameters/model at $p < 0.05$ for each
1075 condition.

1076

	Study 1						Study 2			
	amplitude	frequency	phase	linear model			amplitude	frequency	phase	linear model
theta						**theta**				
No conflict	100	96.4	93	96.4		cC	100	100	100	94.1
Partial conflict	96.4	100	96.4	93		iC	97	100	94.1	97
Full conflict	96.4	96.4	96.4	96.4		iI	100	100	100	97
Mixed correct	100	100	100	93		cI	97	97	94.1	97
Error	100	100	100	100		Error	97	100	100	94.1
beta						**beta**				
No conflict	50	75	67.8	28.6		cC	41.2	82.3	73.5	20.6
Partial conflict	39.3	64.3	57.1	17.8		iC	29.4	61.8	55.9	17.6
Full conflict	28.6	64.3	60.7	17.8		iI	26.5	67.6	64.7	17.6
Mixed correct	25	75	50	14.2		cI	35.3	82.3	70.6	20.6
Error	25	78.6	60.7	7.1		Error	47	82.3	79.4	26.5

1105

1106

1107

1108 **Figure S4:** Clustering of phase of maximal power-RT correlation for each experimental
1109 condition for study 1 (A) and study 2 (B). Phase could only take 20 values since it was
1110 discretized in 20 bins. The thick black line represents the average complex vector, its angle
1111 represents the average phase angle, while its length indicates the size of clustering.

1112

1113

1114

1115

1116

1117

1118

1119

1120

1121

1122

1123

1124

1125

1126

1127
1128 **Figure S5: Theta phase resolved power and reaction time.** Numbers 1 and 2 are for study
1129 1 and 2 respectively. A and B show the phase resolved power and detrended power; C and D
1130 show the phase resolved standard deviation and the detrended standard deviation of power; E
1131 and F show the phase resolved RT and detrended RT; G and H show the phase resolved
1132 standard deviation and detrended standard deviation of RT.

1133
Figure S6: Time course of Spearman's rho between beta power and RT averaged across
subjects for each condition in study 1 (A) and 2 (C). Lower horizontal bars show time of
rejection of symmetry around 0 at the group-level tested using permutation testing. B1 and
B2: phase-resolved Spearman's rho between beta power and RT. These plots show the
average (B1) and detrended (B2) beta power-RT correlation coefficient according to beta
phase. D1 and D2: same plots for study 2.
1140

1141

Figure S7: Clustering of phase of maximum correlation differences between two halves of data randomly selected over 100 iterations. Each grey bar represents the angle of the mean vector of phase preference differences between the two halves of the data over subjects for one iteration of random selection of data halves. Polar histograms in blue show the repartition of the phase differences mean vector angle. The black thick line represents the mean vector of all the 100 iterations of mean vector angles.