Phase-specific manipulation of neural oscillatory activity by transcranial

alternating current stimulation

Marina Fiene[a], Bettina C. Schwab[a], Jonas Misselhorn[a], Christoph S. Herrmann[b,c], Till R.

Schneider[a], Andreas K. Engel[a]

[a] Department of Neurophysiology and Pathophysiology, University Medical Center Hamburg-

Eppendorf, Hamburg, 20246 Germany; [b] Experimental Psychology Lab, Department of

Psychology, Cluster of Excellence "Hearing4all", European Medical School, Carl von

Ossietzky University Oldenburg, Oldenburg, 26129 Germany; [c] Research Center Neurosensory

Science, Carl von Ossietzky University Oldenburg, Oldenburg, 26129 Germany

Corresponding author

Marina Fiene

Department of Neurophysiology and Pathophysiology, University Medical Center Hamburg-

Eppendorf

Martinistraße 52, 20246 Hamburg, Germany

Phone: +49 (0)40 7410-54680

Email: m.fiene@uke.de

Keywords

Transcranial alternating current stimulation, Electroencephalogram, Entrainment, Alpha

oscillations, Visual flicker

Abstract

Background: Oscillatory phase has been proposed as a key parameter defining the

spatiotemporal structure of neural activity. To enhance our understanding of brain rhythms and

improve clinical outcomes in pathological conditions, phase-specific modulation of oscillations

by transcranial alternating current stimulation (tACS) emerged as a promising approach.

However, the effectiveness of tACS in humans is still critically debated.

Objective: Here, we investigated the phase-specificity of tACS effects on visually evoked

steady state responses (SSRs) in 24 healthy human participants of either sex.

Methods: To this end, we used an intermittent electrical stimulation protocol and assessed the

influence of tACS on SSR amplitude in the interval immediately following tACS.

Results: We observed that the phase shift between flicker and tACS modulates evoked SSR

amplitudes. The tACS effect size was dependent on the strength of flicker-evoked oscillatory

activity, with larger effects in participants showing weaker locking of neural responses to

flicker phase. Neural sources of phase-specific effects were localized in the parieto-occipital

cortex within flicker-entrained regions. Importantly, the optimal phase shift between flicker and

tACS associated with strongest SSRs was correlated with cortical SSR onset delays over the

visual cortex.

Conclusions: Overall, our data provide electrophysiological evidence for phase-specific

modulations of oscillatory activity by tACS in humans. As the optimal timing of tACS

application was dependent on neural conduction times as measured by SSR onset delays, data

suggest that the interaction between tACS effect and SSR was cortical in nature. These findings

corroborate the physiological efficacy of tACS and highlight its potential for controlled

modulations of brain signals.

Introduction

Oscillations are a prominent feature of activity in neural networks proposed to be of particular importance for neural processing and, by extension, for normal and pathological brain function [1–4]. Modulation of such cortical activity by means of non-invasive brain stimulation represents a promising approach to advance knowledge on the functional role of the temporal patterning of neural activity and to improve clinical outcomes in disorders related to aberrant neural synchrony. Specifically, transcranial alternating current stimulation (tACS) is widely applied with the aim to entrain neural activity, implying a periodic modulation of membrane potentials and a phase alignment of intrinsic oscillations to the tACS phase. This assumption is supported by in vitro slice preparations and recordings in primates showing phase-specific modulations of neuronal spiking patterns by externally applied electric fields [5–8]. However, evidence from invasive recordings in animals may not directly be transferable to tACS effects in the human brain. Despite its broad use in basic and clinical science, the neural mechanism of tACS in humans is still under investigation and its overall efficacy has recently been challenged. Measurements of the electric field strength in human cadaver brains and epilepsy patients with implanted electrodes showed that most of the scalp-applied current is attenuated by skin and skull thereby questioning significant neural entrainment [9–11]. These findings, paralleled by inconsistent behavioral tACS effects [12–14], encouraged a reconsideration of study requirements to investigate the physiological mechanisms of tACS.

The theoretically ideal approach to directly measure tACS-induced effects on neural activity is complicated by strong, hard-to-predict electrical artifacts in concurrent recordings of neural activity [15,16]. To provide evidence for online phase-specific neuronal effects despite these methodological constraints, most studies assessed tACS effects on indirect measures assumed to be mediated by brain rhythms. For instance, tACS applied in the alpha and beta range was shown to lead to cyclic modulations of auditory, somatosensory or visual stimulus perception [17–20]. Further insight has been provided in the motor domain, by showing tACS-phase-

dependent changes in cortical excitability [21–23] or peripheral tremor [24–26]. Yet, tACS-effects on the motor cortex were shown to be dominated by cutaneous co-stimulation of peripheral nerves in the skin leading to rhythmic activation of the somatosensory system rather than by transcranial modulation of cortical tissue [27]. Related evidence might thus not necessarily be generalizable to transcranial entrainment effects in cortical regions apart from the motor cortex. Further, prior conclusions only hold true under the assumption that the chosen outcome measures, e.g., behavior or cortical excitability, are reliable proxies for cortical oscillatory activity.

Here, we used an innovative approach that combines rhythmic electrical with rhythmic sensory stimulation to target the phase-specificity of tACS effects directly on cortical oscillatory activity. Via electroencephalography (EEG), we measured neural tACS effects on precisely controlled brain rhythms evoked by visual flicker, i.e., visually evoked steady state responses (SSRs), as a function of six phase shifts between tACS and flicker onset. Using an intermittent electrical stimulation protocol, concurrent 10 Hz flicker and multi-electrode tACS targeting the occipital cortex were applied in two sessions under active and sham tACS. Artifact free epochs in the immediate interval following tACS were used for SSR amplitude analysis (Figure 1). We predicted that the phase shift between flicker- and tACS-induced membrane voltage fluctuations should systematically modulate the amplitude of net SSRs.

Figure 1.

Materials and Methods

Participants

24 healthy volunteers (mean age 25.1 ± 3.3 years; 16 female; 8 male; 22 right-handed) were recruited from the University Medical Center Hamburg-Eppendorf, Germany. The sample size was chosen based on the effect sizes between sham and active tACS in previous studies showing

phase-dependent stimulation effects on sensory perception or peripheral tremor [18,24,28]. All

participants reported normal or corrected-to-normal vision, no history of psychiatric or

neurological disorders and were blind towards the tACS stimulation sequence. The

experimental protocol was approved by the ethics committee of the Hamburg Medical

Association and was conducted in accordance with the Declaration of Helsinki. All participants

gave written informed consent before participation. Participants were monetarily compensated

and debriefed immediately after the experiment.

Experimental design

All subjects participated in two separate sessions in a randomized, counterbalanced order

once under sham and active tACS. Participants were seated in a dimly lit, electrically shielded

and sound-attenuated EEG chamber at a distance of approximately 40 cm to a white light

emitting diode (LED). Due to a nonlinear relation between forward voltage and luminosity of

the used LED, we assessed LED luminosity per duty cycle of the pulse-width modulation by a

luminance meter (LS-100, Konica Minolta). The resulting function was multiplied with a pure

10 Hz sine to generate a 10 Hz luminance signal. The LED had a maximal light intensity of 100

cd/m^2. Prior to the main tACS block, 3 min eyes-open resting state EEG (Pre RS) was recorded

while participants fixated the white illuminated LED. Afterwards, EEG during an 8 min SSR

block without tACS (Pre SSR) was recorded. Single flicker periods (50 in total) were presented

for 5.5 sec followed by short breaks of 3-5 sec. The timing of flicker presentation was identical

to the procedure used in the main tACS block. In the tACS block, EEG was recorded

continuously during the intermittent tACS protocol. Each trial started with tACS only and was

followed by flicker onset after 3-5 sec. The flicker continued until the end of the trial for 5.5

sec in total. tACS free intervals of 2.5 sec were used for EEG data analysis. Single tACS periods

had a duration of 6-8 sec. Between successive tACS epochs, tACS phase was continuous by

adjusting only the amplitude but not the phase of the sine wave spanning the whole testing

session. To account for the varying phase delay between neural activity induced by sensory and

electrical stimulation, the visual flicker started at six different phase angles (0°, 60°, 120°, 180°,

240° and 300°) relative to the tACS cycle. 50 trials were recorded for each of the six phase shift

conditions (300 trials in total). The sequence of trials was randomized such that every phase

shift condition was followed equally likely by all other conditions. Moreover, to avoid

confounding time-on-task effects on alpha amplitude, trials belonging to different conditions

were evenly distributed over the course of the testing session by iterate permutation. The tACS

block was divided in two blocks interrupted by a 10 min break. After the tACS block, another

SSR block without tACS (Post SSR) and resting state EEG (Post RS) were recorded.

To ensure that participants fixate the LED and thus to enhance SSR detection, participants

were instructed to detect oddball trials in which LED luminance changed after 3-4 sec.

Participants responded per button press as soon as they detected a luminance change. 16 oddball

trials were included in the tACS block and two oddball trials in the pre and post SSR blocks,

respectively. Participants showed a mean detection accuracy of 97.66 ± 9.99 % (mean ± sd)

during the tACS blocks and 97.92 ± 12.39 % during the pre and post SSR blocks.

Electrophysiological recording

EEG was recorded continuously from 64 Ag/AgCl electrodes (12 mm diameter) mounted

in an elastic cap (Easycap). The electrooculogram (EOG) was recorded from two electrodes

placed below both eyes with the EEG referenced to the nose tip. Electrodes were prepared with

abrasive conducting gel (Abralyt 2000, Easycap) keeping impedance below 20 kΩ. EEG data

were recorded using BrainAmp DC amplifiers (Brain Products GmbH) and the corresponding

software (Brain Products GmbH, Recorder 1.20). Data were recorded with an online passband

of 0.016-250 Hz and digitized with a sampling rate of 1000 Hz.

tACS and electric field simulation

Multi-electrode tACS was applied via five additional Ag/AgCl electrodes (12 mm diameter) mounted between EEG electrodes. The montage was connected to a battery-driven current source (DC-Stimulator Plus, NeuroConn). After preparation with Signa electrolyte gel (Parker Laboratories Inc.), impedance of each outer electrode to the middle electrode was kept below 20 kΩ. Moreover, impedances were kept comparable to achieve an evenly distributed electric field. A sinusoidal alternating current of 2 mA peak-to-peak was applied at 10 Hz using an intermittent stimulation protocol. It has previously been shown that flicker-evoked SSRs show strongest amplitudes in the alpha frequency range [29]. Also, most reliable evidence for aftereffects of tACS on oscillatory power has been demonstrated in the alpha band that was proposed to result from online neural phase-alignment [30,31]. Thus, we chose 10 Hz to test for the general feasibility of phase-specific effects by tACS, although our approach is not limited to this stimulation frequency. During sham and active stimulation, the current was ramped in over 15 sec to 2 mA. After 90 sec of continuous stimulation, tACS periods of 6-8 sec without ramp were applied interrupted by short breaks of 2.5 sec for EEG analysis. Total stimulation time during the active session was 40 min. For sham stimulation, the current was ramped in and out over 15 sec each. This procedure ensured that in both stimulation conditions, participants experienced initial itching sensation. All participants confirmed that stimulation was acceptable and did not induce painful skin sensations. The most common side-effect was a tingling feeling on the scalp under the electrode. During the debriefing at the end of the final session, except for two subjects all participants correctly rated the sequence of active and sham stimulation. Further, exploration of the experience of phosphenes during tACS in the beginning of each session revealed that no participant reported phosphene perception. This finding is in line with our simulation of the tACS-induced electric field which greatly diminishes with increasing distance to stimulation electrodes and is expected to be low in the retina [32].

Placement of tACS electrodes was chosen to target brain regions activated by visual

stimulation. We aimed to achieve largest magnitudes of current density in the primary visual

cortex to maximally interfere with early stages of cortical sensory processing. Quantitative field

distributions $\vec{E}$ could directly be computed by linear superposition of lead fields $\vec{L}$, weighted by

the injected currents α_i at electrodes $i = \{1,2,3,4,5\}$:

$$\vec{E}(\vec{x}) = \sum_i (\vec{L_i}(\vec{x})\, \alpha_i) \tag{1}$$

$\vec{L}$ was estimated with the boundary element method using a volume conduction model by

Oostenveld et al. [33] at 5 mm spatial resolution.

Data analysis

Data preprocessing

64-channel EEG data were preprocessed and analyzed in Matlab (The MathWorks Inc.)

using the analysis toolbox FieldTrip [34]. Circular statistics were calculated with the CircStat

toolbox [35]. EEG recordings during the pre and post SSR blocks without tACS were

segmented into epochs from -1.5 to 6.5 sec around flicker onset. For the tACS block, EEG was

segmented into epochs from 0.1 to 2.5 sec after tACS offset. The first 0.1 sec after stimulation

offset were rejected before filtering to avoid leakage of capacitive discharge effects after tACS

offset, appearing as a short-lasting voltage drift back to baseline EEG level [30,36].

Examination of voltage across 20 ms time segments confirmed no further significant voltage

offset change beyond 0.1 sec after the end of stimulation. EEG data were bandpass filtered from

1 to 20 Hz using a Hamming-windowed sinc FIR filter. Oddball trials and trials during which

participants erroneously responded via button press were excluded. To automatically screen for

high noise level electrodes, channels whose standard deviation exceeded 3 times the median

standard deviation of all channels per participant were excluded. On average, 4.0 ± 1.9 channels

were removed. Data were downsampled to 100 Hz. Afterwards, independent component

analysis (ICA) was computed using the infomax ICA algorithm [37]. Remaining eye-

movement, cardiac and noise artifacts were removed based on visual inspection of the

components' time course, spectrum and topography. For eye-blink artifact removal, Pearson

linear correlation coefficient between EOG and ICA components was calculated and

components showing correlation coefficients greater than .25 were rejected. On average, 20.1

± 3.9 components were excluded. Finally, all trials were visually inspected and trials containing

artifacts that had not been detected by previous steps were manually removed. On average,

49.19 ± 1.2 out of 50 trials remained for the pre and post SSR blocks and 296.9 ± 3.5 out of

300 trials remained for the tACS block per participant.

Source reconstruction

At the cortical source level, neural activity was estimated using exact low resolution brain

electromagnetic tomography (eLORETA). Before source projection, data were bandpass

filtered between 7-13 Hz with a 4th order butterworth filter. The cortical grid was defined using

the Automated Anatomical Labeling (AAL) atlas consisting of 38 regions after excluding

subcortical and cerebellar structures [38]. Three-dimensional time series were estimated in a

linearly spaced grid of 4077 cortical points with 7.5 mm distance in all three spatial directions

using the boundary element method volume conduction model by Oostenveld et al. [33].

eLORETA was applied per trial with 5% regularization. To reduce spatial dimensions, the three

resulting time series were projected to the direction of maximal power at each grid point.

Spectral analysis and SSR amplitude modulation indices

EEG spectral analysis was performed on sensor and source level. We expected to find

phase-specific tACS-induced modulations of SSR amplitude at electrode positions showing a

clear response to visual flicker, i.e., where phase alignment to flicker stimulation is prominent.

Therefore, we assessed the spatial distribution of phase locking of EEG to visual flicker in the

pre SSR blocks without tACS for the sham and active tACS testing session. A Hilbert transform

was computed on the flicker signal and EEG time series during flicker stimulation (1.0 to 5.5

sec after flicker onset) for each trial at each electrode and source level grid point. The first 1

sec after flicker onset was removed to ensure the SSR has fully build up. To assess phase

stability, the time-dependent differences in phase signals $(\phi_{flicker}(t) - \phi_{EEG}(t))$ were

computed and the extent of entrainment quantified by the phase locking value (PLV) over all

trials.

$$PLV = \left| \frac{1}{N_{trials}} \sum_{k=1}^{N_{trials}} \left(\frac{1}{N_{time}} \sum_{t=1}^{N_{time}} e^{i(\phi_{flicker}(t) - \phi_{EEG}(t))} \right) \right| \qquad (2)$$

For sensor level analysis, we selected those channels showing prominent phase entrainment

with mean PLV > 0.5 over all participants. Pearson correlation coefficient was computed to

quantify the relation between PLV and SSR amplitude increase from resting state to pre SSR

blocks. SSR amplitude was calculated by Fourier transform of 1 sec time windows with an

overlap of 0.5 sec for each 3 min resting state block (pre RS) and for each 4.5 sec trial of the

pre SSR blocks. To correct for global alpha amplitude fluctuations over time independent of

experimental manipulation, SSR amplitude was defined as a relative amplitude value by

subtracting the mean amplitude at neighboring frequencies (9 and 11 Hz) from the absolute

amplitude at the stimulation frequency.

For analysis of SSR amplitude modulation during the tACS block, we computed the Fourier

transform of each trial separately for the time epochs of 0.1 to 1.1 sec, 0.6 to 1.6 sec and 1.1 to

2.1 sec after tACS offset. To assess modulation of SSR amplitude dependent on the relative

phase shift between tACS and flicker onset, bar diagrams were constructed showing the

variation in SSR amplitude over phase shift conditions. SSR amplitude was normalized by the

sum of amplitude values over all six conditions. Assignment of trials to phase conditions for

the sham session was performed using the same trial numbers as under tACS stimulation,

thereby ensuring equal time-on-task effects for both sessions. If there was no phase-specific

amplitude modulation by concurrent tACS, bar graphs should be uniformly distributed. In case

of phase-specific interactions, the SSR amplitude should be higher in a condition that shows an

optimal phase shift for that participant. Assuming that the optimal phase shift between flicker

and tACS onset leading to increased SSR amplitudes might vary between participants, any

preference in phase shift condition compared to sham can be considered as evidence for phase

specific tACS effects. Amplitude modulation was quantified by three modulation measures.

First, we calculated the Kullback-Leibler divergence (D_{KL}) which is a common premetric used

in statistics to calculate the difference between two distributions. The deviation of the observed

amplitude distribution P from the uniform distribution U is defined as

$$D_{KL}(P,U) = \sum_{i=1}^{N} P(i) \, log\left[\frac{P(i)}{U(i)}\right] \tag{3}$$

where N is the number of phase bins [39]. Strict uniformly distributed amplitude values would

be reflected in $D_{KL} = 0$ whereas D_{KL} increases the further away P gets from U. While D_{KL}

measures the overall deviation of amplitude values from uniform distribution, we additionally

assessed whether the tACS-induced amplitude modulation over phase conditions follows a

cyclic pattern, as hypothesized based on the sinusoidal nature of the tACS signal. Therefore,

we calculated the phase locking value of amplitude values to phase condition. This cyclic

amplitude phase locking (APL) index is defined as

$$APL = \left|\sum_b A_b \, e^{i\theta b}\right| \tag{4}$$

where A and θ are the normalized relative amplitude and phase shift for each of the six phase

shift conditions b. To further investigate whether the tACS-induced SSR amplitude modulation

can be described by a sinusoidal pattern, we fitted one-cycle sine waves to SSR amplitude bar

diagram values [18,40]. The following equation was fit to the six normalized SSR amplitude

values per participant and stimulation condition,

$$y = b + a * \sin\,(10Hz * 2\pi * x \,+\, c) \tag{5}$$

where x corresponds to the flicker-tACS phase shifts during one cycle (x = {0, 1/6T, 2/6T,…

5/6∗T} with period T = 0.1 sec). The parameters a, b and c were estimated by the fitting

procedure where b is the intercept, a the amplitude and c the phase shift. Parameters a and b

were bound between -1 and 1 and c between 0 and 2π. Start values were drawn randomly from

within the range of restrictions for each parameter. Model fits were computed using the Matlab

fittype function allowing for 1000 iterations to find the best model. We examined the absolute

sine fit amplitude values as index for the strength of SSR amplitude modulation. The

significance of the sine fit was assessed by dependent samples t-tests comparing the proportion

of explained variance R^2 as goodness-of-fit index between sham and active tACS session.

Statistical analysis

For each of the three modulation indices, we calculated dependent samples t-tests for the

epochs of 0.1 to 1.1 sec, 0.6 to 1.6 sec and 1.1 to 2.1 sec after tACS offset between sham and

active tACS on sensor level. Effect sizes were determined by calculating Cohen's d_z for paired

t-test comparisons. To account for comparisons in multiple time windows, we applied

Bonferroni correction to the significance level and report test statistics if the corresponding

p-value fell below the corrected alpha of α_{bonf} = .0167 (= .05/3).

For further investigation of tACS effects, we analyzed the APL parameter resulting from

the epoch immediately following tACS offset in source space. APL is the more specific, phase-

dependent modulation index relative to D_{KL} and a more robust measure not requiring any

presuppositions on parameter ranges as compared to sine fit. For source localization of APL

effects, dependent samples t-tests were computed for each grid point using cluster-based

permutation tests to correct for multiple comparisons. Clusters were obtained by summing up

t-values which were adjacent in space and below an alpha level of 5 % (two-sided). A

permutation distribution was generated by randomly shuffling APL values between active and

sham condition within participants in each of 1000 iterations. The observed cluster was

considered statistically significant when the sum of t-values exceeded 95 % of the permutation

distribution. To further examine whether the strength of tACS effects quantified by APL is

dependent on the underlying strength of flicker-evoked oscillatory activity, we assessed

Pearson correlation coefficients between APL and EEG-flicker PLV for sham and active tACS

blocks. Moreover, we assessed the dependency of the increase in APL from sham to tACS on

the change in mean SSR amplitude, the standard deviation of SSR amplitudes or EEG-flicker

PLVs over all trials per participant by computing Pearson correlation coefficients.

Finally, to disentangle retinal from cortical stimulation effects, we examined the

dependency of optimal flicker-tACS phase shifts on the cortical flicker-SSR phase delays by

computing circular-circular correlations per channel using cluster-based permutation tests [35].

The flicker-SSR phase delay was computed as the mean time-dependent difference in phase

signals $(\phi_{flicker}(t) - \phi_{EEG}(t))$ based on the Hilbert transform of the EEG and flicker signal

over all trials of the tACS block. Cluster-level test statistics were calculated by taking the

maximum average of correlation coefficients across neighboring electrodes showing

significance of circular correlations (p < .05). The permutation distribution was generated by

between-subject randomization of flicker-tACS and SSR onset phase delay data over 1000

iterations.

Results

Flicker-evoked phase alignment in the parieto-occipital cortex

334   To analyze evoked flicker entrainment, we assessed the degree and spatial distribution of

335 PLVs between EEG and 10 Hz flicker stimulation. Estimated time series on source level

336 displayed a prominent peak of parieto-occipital EEG-flicker PLV (Figure 2B). Strong phase

337 locking was located in the superior and middle occipital gyrus as well as in bilateral precuneus

and cuneus. For sensor level analysis, four parieto-occipital channels showing a population mean PLV > 0.5 (corresponding to electrodes O1, O2, POz, Pz) were selected for further analysis of SSR amplitude modulation by tACS. Mean PLV for the selected channels during both pre SSR blocks over all participants was 0.56 ± 0.16 (mean $\pm$ sd). As illustrated in the lower part of Figure 2B, data show varying phase delays between flicker onset and cortical SSR across participants related to differences in neural conduction delays along the visual pathway. Further, amplitude spectra revealed an amplitude increase at the flicker stimulation frequency compared to resting state (Figure 2C). Between-subject correlation showed that the strength of EEG-flicker PLV was positively correlated with the increase in SSR amplitude from resting state to pre SSR blocks ($r = .43$, $p = .037$) (Figure 2D).

Figure 2.

Phase-dependent SSR amplitude modulation by tACS

To test the hypothesis that simultaneous tACS and flicker stimulation lead to phase-specific interactions between evoked neural activity and electric field, we assessed the degree of tACS-phase-dependence of SSR amplitude values via three modulation measures: (1) the deviation of amplitude values from a uniform distribution (D_{KL}), (2) the locking of amplitude values to phase conditions (APL) and (3) one-cycle sine fits to SSR amplitude values. Figure 3A shows normalized SSR amplitude bar diagrams over the six phase shift conditions for one exemplary participant. During sham, data are almost uniformly distributed across phase bins, showing small fluctuations in SSR amplitude with no preference for a particular phase shift condition. On the contrary, the bar diagram for active stimulation shows phase-dependent modulations of SSR amplitudes indicating an interaction between tACS-induced electric field and flicker-evoked oscillatory activity. On sensor level, analysis of the deviation of amplitude values from uniform distribution revealed a significantly greater D_{KL} under tACS compared to sham within

the first 1 sec epoch (0.1 to 1.1 sec) after tACS offset ($t(23) = 3.21$, $p = .004 < \alpha_{bonf}$, $d_z = 0.66$)

(Figure 3B). Phase locking of amplitude values to phase condition measured by APL was

significantly larger after tACS ($t(23) = 3.12$, $p = .005 < \alpha_{bonf}$, $d_z = 0.64$). In accordance, also the

one-cycle sine wave fit to SSR amplitudes showed a significantly greater amplitude of the sine

fit under tACS ($t(23) = 3.52$, $p = .002 < \alpha_{bonf}$, $d_z = 0.72$) (Figure 3B). The proportion of

explained variance R^2 by sine fit was greater for SSR amplitude modulation under tACS

compared to sham ($t(23) = 2.65$, $p = .014$, $d_z = 0.54$). In successive time windows, the

modulatory tACS effect decayed for all three modulation parameters ([0.6, 1.6] sec: D_{KL}, $t(23)$

$= 0.46$, $p = .650$, $d_z = 0.09$; APL, $t(23) = 2.29$, $p = .032$, $d_z = 0.47$; Sine fit, $t(23) = 2.23$, $p =$

$.036$, $d_z = 0.45$; [1.1, 2.1] sec: D_{KL}, $t(23) = -0.30$, $p = .769$, $d_z = -0.06$; APL, $t(23) = -0.25$, $p =$

$.806$, $d_z = -0.05$; Sine fit, $t(23) = 0.52$, $p = .610$, $d_z = 0.11$; Figure 3E). Importantly, the phase-

dependent effects of tACS on SSR amplitude were not caused by overall 10 Hz alpha amplitude

differences between conditions (Figure 3C). A repeated-measures t-test revealed no significant

difference in mean SSR amplitude ($t(23) = -1.02$, $p = .317$, $d_z = 0.21$) over all trials per

participant between tACS and sham condition during the first 1 sec interval after tACS offset

(Figure 3D). Also, the standard deviation of SSR amplitude values over all trials per participant

did not differ between sham and active stimulation condition ($t(23) = -.31$, $p = .759$, $d_z = 0.06$).

This implies a strengthening or dampening of SSR amplitudes dependent on the phase shift

between flicker and tACS stimulation.

Figure 3.

Spatial localization and dependency of tACS effects on individual physiology

The spatial specificity of tACS effects was analyzed in source space for the APL modulation

parameter. Compared to D_{KL}, APL is a more specific index assuming systematic amplitude

modulations by tACS. Moreover, its computation is more stable compared to sine fit as no

assumptions about parameter ranges are required. Cluster analysis in source space showed

significantly increased APL values during active tACS relative to sham in a cluster over the

parieto-occipital cortex (cluster test: $p = .006$) (Figure 4A). Significant differences were located

primarily in the bilateral precuneus, superior parietal gyrus and midcingulate area as well as the

cuneus and calcarine sulcus. These are part of flicker-entrained brain areas, located in tACS-

targeted cortical regions and connected higher visual areas. Interestingly, tACS effects on SSR

amplitude were not seen in the middle and superior occipital gyrus where neural phase

alignment to the visual flicker peaked, but rather in neighboring occipital and parietal regions

(insert in Figure 4B).

In accordance with this finding, we further observed a highly significant between-subject

correlation of SSR amplitude modulation quantified by APL with the underlying strength of

EEG-flicker PLV during the active tACS block on sensor level ($r = -.65, p < .001$). Participant

with weaker PLV of SSR to flicker phase showed greater APL under tACS (Figure 4B). This

relation was non-significant during the sham session ($r = -.38, p = .067$). As the difference in

PLV between sham and tACS session showed no significant correlation with the difference in

corresponding APL values ($r = -.29, p = .166$), data suggest that the strong negative relation

between underlying PLV and SSR modulation is not generally valid but specific for tACS-

induced neuromodulation. Our results thus emphasize the impact of the individual physiology,

influenced by the neuronal response strength to visual flicker, for the detection of neural tACS

effects.

Importantly, the increase in APL from sham to tACS could not be explained by a concurrent

increase in mean SSR amplitude ($r = -.22, p = .309$) or standard deviation of SSR amplitude

values ($r = -.13, p = .556$) over all trials of the tACS blocks per participant, thereby supporting

the causal influence of the experimental manipulation of tACS-flicker phase shift (Figure 4C).

Figure 4.

 Cortical level of interaction between SSRs and tACS effects

To examine the involvement of retinal co-stimulation on SSR amplitude modulation, we

analyzed the dependency of optimal flicker-tACS phase shifts associated with strongest SSRs

on individual flicker-SSR phase delays resulting from neural conduction times from the retina

to visual cortex. Assuming an interaction between flicker and electric field at the retinal level

before conduction delays of the visual system take effect, the SSR phase delay should have no

predictive value for the optimal timing of tACS application. Notably, only during the tACS

session, permutation tests revealed a significant cluster of occipital electrodes (O1, O2, O9,

O10; cluster test: $p = .009$) showing a circular correlation between SSR phase delay and optimal

flicker-tACS phase shift across participants. The mean correlation coefficient across cluster

electrodes was $r = -.54$. Corresponding permutation tests during sham showed no significant

electrode cluster.

Figure 5.

Discussion

Here, we used an innovative approach to study the phase-specificity of electrophysiological

tACS effects in humans by systematically pairing rhythmic electrical with rhythmic visual

stimulation. Specifically, we evaluated the amplitude of flicker-evoked SSRs in the interval

immediately following tACS delivered at six different phase shifts relative to flicker onset. We

demonstrate that SSR amplitudes are modulated in a tACS phase-dependent manner and that

tACS effect size is inversely related to the strength of the underlying flicker response.

Furthermore, we found that the individual phase delay between flicker onset and cortical SSR

is predictive of the optimal timing of tACS application.

Previous investigations into the tACS mechanism of action typically aimed to modulate

ongoing or task-related brain oscillations which show high variability in frequency and phase

consistency. Here, we used SSRs that allow the precise setting of the oscillatory phase in the visual cortex. While the neural mechanism underlying SSR generation is still debated, increasing evidence supports the involvement of entrained endogenous oscillations in the processing of rhythmic visual input [41–43]. Yet, irrespective of their exact physiological origin, SSRs can be treated as stimulus-driven brain rhythms with predictable time course, which enables a highly specific targeting by tACS. Notably, compared to ongoing activity, the phase of the SSR is not expected to be shifted by tACS as EEG recordings will always show dominant phase locking to the driving flicker. Rather, if voltage modulations by electrical and sensory stimulation interact in a phase-specific manner, SSRs should reflect this interaction in net amplitude modulations. Our data confirmed that SSR amplitudes measured immediately after tACS offset are dependent on the relative phase shift between flicker and tACS which provides first conclusive evidence for the phase-specificity of tACS effects in human EEG recordings. Importantly, as data show no overall amplitude increase of SSRs by tACS (Figure 3D), results imply a phase-dependent enhancement and suppression of flicker responses due to the sinusoidal nature of the tACS signal. This is in accordance with recent invasive recordings in animals, showing that tACS is capable of modulating the timing of neural spike discharges [7,8].

The phase-dependent modulatory effect on SSRs was robust under three modulation measures but already decayed after the first 1 sec time epoch. While lasting power enhancement after prolonged alpha tACS has been repeatedly shown and ascribed to synaptic plasticity mechanisms [30,31,44], evidence for outlasting effects on phase synchronization is still sparse. Yet, neural oscillatory activity entrained during rhythmic electric, magnetic or visual stimulation were shown to remain stable for a few cycles after stimulation offset [45–47]. These short-lived reverberations of oscillatory activity, phase-locked to the external force, have been termed entrainment echoes [36,46]. Notably, Vossen et al. [30] could not find evidence for entrainment echoes after short tACS epochs of 3 or 8 sec length. However, while tACS phase

effects might not be detectable via PLV in ongoing brain activity, flicker-induced brain rhythms may increase the signal-to-noise ratio and thereby enhance the detectability of short-lived tACS aftereffects. These results are compatible with the assumption of online tACS-induced entrainment of neural activity, which yet cannot be tested directly due to artifact-contaminated EEG recordings. We speculate that the observed effects generalize to tACS and SSRs in other frequency bands of the human EEG, which should be systematically tested in future studies.

Interestingly, the efficacy of tACS was inversely related to the strength of the underlying flicker response. More precisely, tACS-induced SSR amplitude modulation was stronger in participants showing weaker phase locking between flicker and evoked oscillatory activity. Furthermore, tACS effects were especially prominent in brain areas that were not maximally driven by the driving flicker. While maximal phase locking to the visual stimulus occurred in the middle and superior occipital gyrus, maximal SSR amplitude effects of tACS were seen in early visual cortex and superior parietal cortex. As tACS effects were also observed in downstream visual cortical areas, these results suggest that stimulation effects might not only act locally in regions targeted by the electric field but also affect connected areas via polysynaptic interactions [48–50]. Moreover, these findings emphasize a dependency of tACS effects on the individual physiology. It has repeatedly been demonstrated that tACS effect sizes are related to the baseline level of oscillatory activity, with effects only being measurable when power at the stimulated frequency was low [51–53]. Similarly, our data indicate that in participants and anatomical regions exhibiting strong EEG-flicker phase locking, the dominance of synchronous neural activity may have led to ceiling effects in alpha amplitude with no room for further enhancement. Also, the ratio between the strength of the external tACS stimulation relative to the strength of the neural oscillation was suggested as a critical factor for successful entrainment [53], that may explain differential tACS effect sizes for varying flicker-evoked oscillation strengths.

Important to consider in the interpretation of tACS effects is the possible involvement of

sensory co-stimulation effects, that may indirectly lead to neural entrainment. First, electric

stimulation of peripheral nerves in the skin can induce rhythmic activation of the somatosensory

cortex that was shown to at least partly explain tACS effects on motor cortex [27]. Yet, recent

studies demonstrated that tACS affects neural activity even if somatosensory input is controlled

for [7,54]. In our study, the dependency of tACS effects on the SSR phase delay over the

primary visual cortex, i.e., the target region of the electrical stimulation, point to transcranial

stimulation effects on SSR at early stages of visual cortical processing with concurrent spread

of activity to higher visual areas. However, to rule out entirely that SSRs were influenced by

somatosensory co-stimulation, a control electrode montage would be necessary that elicits

equivalent tactile sensation without stimulating the cortex. This is challenging as cutaneous

stimulation effects depend not only on current strength but also on the distribution and

sensitivity of skin receptors in the stimulated area [55]. Therefore, the development of valid

control montages is one of the key goals in future tACS research. Second, it has been noted that

tACS can cause activation of the retinae due to shunting of scalp-applied currents across the

skin. Although no participant reported phosphene sensation with the used focal ring montage,

sub-threshold activation of the retinae could in principle have an impact on visual processing,

which was previously dealt with by using control electrode montages [55]. Here, our

experimental approach allowed to directly disentangle cortical from retinal stimulation effects.

It is well known that flicker stimulation will inevitably lead to variable delays in the recordable

SSR that likely result from interindividual differences of the conduction times along the visual

pathway. Accordingly, a cortical interaction between tACS effects and SSRs should be

associated with varying optimal phase shifts between tACS and flicker across participants. This

was exemplified in a study by Ruhnau et al. [56], showing that simultaneously started tACS

and flicker did not lead to tACS-induced power increases of the fundamental SSR component

in the overall sample. In our study, we could show that the optimal flicker-tACS phase shift

associated with strongest SSRs was correlated with the individual flicker-SSR phase delay over

the primary visual cortex. This finding suggests that it is possible to predict the optimal timing

of tACS application based on subject-specific conduction delays of the visual system.

Importantly, this dependency cannot be explained by an interference between flicker and

electric field at the retinal level, which should be independent of postretinal neural conduction

times and, therefore, result in comparable optimal flicker-tACS phase shifts across participants.

Thus, our finding strongly suggests that the interaction between tACS effect and SSR was

cortical rather than retinal in nature.

In conclusion, we provide the first conclusive electrophysiological evidence for the efficacy

of tACS to modulate cortical oscillatory activity in a phase-dependent manner in humans.

Importantly, we found that the optimal phase shift between electrical and visual stimulation

varied between participants and depended on baseline conduction delays of the visual system.

This result cannot be explained by peripheral electric co-stimulation of the retina and thus

strongly supports a cortical origin of tACS effects. Furthermore, our data corroborate the notion

that tACS effect size is limited by the strength of the targeted oscillatory activity level. Taken

together, our findings show that individual functional properties and the current oscillatory

brain state need to be considered to achieve specific, custom-fit neuromodulation. In the context

of the ongoing debate on the overall capability of tACS to entrain oscillatory activity in humans,

our results make a strong case for its periodic impact on neuronal excitability that would allow

for frequency- and phase-specific modulations of brain signals.

Conflict of interest

The authors declare no competing financial interests.

Acknowledgements

This work was supported by the Deutsche Forschungsgemeinschaft (SFB 936/A3 awarded

to A.K.E. and T.R.S.; SPP 1665/EN 533/13-1 and SFB TRR 169/B1 awarded to A.K.E.; SPP

1665/SCHN 1511/1-2 awarded to T.R.S.). We thank Jonathan Daume, Alexander Maye, Jan-

Ole Radecke and Darius Zokai for helpful discussions on the data, Malte Sengelmann and

Guido Nolte for methodological support, and Karin Deazle and Darius Zokai for assistance in

data recording.

References

[1] Fries P. A mechanism for cognitive dynamics: Neuronal communication through

neuronal coherence. Trends Cogn Sci 2005;9:474–80.

https://doi.org/10.1016/j.tics.2005.08.011.

[2] Schnitzler A, Gross J. Normal and pathological oscillatory communication in the brain.

Nat Rev Neurosci 2005;6:285–96. https://doi.org/10.1038/nrn1650.

[3] Ronconi L, Melcher D. The role of oscillatory phase in determining the temporal

organization of perception: Evidence from sensory entrainment. J Neurosci

2017;37:10636–44. https://doi.org/10.1523/JNEUROSCI.1704-17.2017.

[4] Engel AK, Fries P, Singer W. Dynamic predictions: Oscillations and synchrony in top–

down processing. Nat Rev Neurosci 2001;2:704–16. https://doi.org/10.1038/35094565.

[5] Ali MM, Sellers KK, Fröhlich F. Transcranial alternating current stimulation modulates

large-scale cortical network activity by network resonance. J Neurosci 2013;33:11262–

75. https://doi.org/10.1523/JNEUROSCI.5867-12.2013.

[6] Reato D, Rahman A, Bikson M, Parra LC. Effects of weak transcranial alternating

current stimulation on brain activity—a review of known mechanisms from animal

studies. Front Hum Neurosci 2013;7:687. https://doi.org/10.3389/fnhum.2013.00687.

[7] Krause MR, Vieira PG, Csorba BA, Pilly PK, Pack CC. Transcranial alternating current

stimulation entrains single-neuron activity in the primate brain. Proc Natl Acad Sci

2019:201815958. https://doi.org/10.1073/pnas.1815958116.

[8] Johnson L, Alekseichuk I, Krieg J, Doyle A, Yu Y, Vitek J, et al. Dose-dependent effects

of transcranial alternating current stimulation on spike timing in awake nonhuman

primates. BioRxiv:696344 2019. https://doi.org/10.1101/696344.

[9] Vöröslakos M, Takeuchi Y, Brinyiczki K, Zombori T, Oliva A, Fernández-Ruiz A, et al.

Direct effects of transcranial electric stimulation on brain circuits in rats and humans.

Nat Commun 2018;9:483. https://doi.org/10.1038/s41467-018-02928-3.

[10]   Huang Y, Liu AA, Lafon B, Friedman D, Dayan M, Wang X, et al. Measurements and

582   models of electric fields in the in vivo human brain during transcranial electric

583   stimulation. Elife 2017;6:1–26. https://doi.org/10.7554/eLife.18834.

584   [11]   Underwood E. Cadaver study challenges brain stimulation methods. Science

585   2016;352:397–397. https://doi.org/10.1126/science.352.6284.397.

586   [12]   Brignani D, Ruzzoli M, Mauri P, Miniussi C. Is transcranial alternating current

587   stimulation effective in modulating brain oscillations? PLoS One 2013;8:e56589.

588   https://doi.org/10.1371/journal.pone.0056589.

589   [13]   Fekete T, Nikolaev AR, De Knijf F, Zharikova A, van Leeuwen C. Multi-electrode alpha

590   tACS during varying background tasks fails to modulate subsequent alpha power. Front

591   Neurosci 2018;12:428. https://doi.org/10.3389/fnins.2018.00428.

592   [14]   Vossen A. Modulation of neural oscillations and associated behaviour by transcranial

593   alternating current stimulation (tACS). PhD thesis. 2017.

594   [15]   Noury N, Hipp JF, Siegel M. Physiological processes non-linearly affect

595   electrophysiological recordings during transcranial electric stimulation. Neuroimage

596   2016;140:99–109. https://doi.org/10.1016/j.neuroimage.2016.03.065.

597   [16]   Noury N, Siegel M. Phase properties of transcranial electrical stimulation artifacts in

598   electrophysiological recordings. Neuroimage 2017;158:406–16.

599   https://doi.org/10.1016/j.neuroimage.2017.07.010.

600   [17]   Gundlach C, Müller MM, Nierhaus T, Villringer A, Sehm B. Phasic modulation of

601   human somatosensory perception by transcranially applied oscillating currents. Brain

602   Stimul 2016;9:712–9. https://doi.org/10.1016/j.brs.2016.04.014.

603   [18]   Neuling T, Rach S, Wagner S, Wolters CH, Herrmann CS. Good vibrations: Oscillatory

604   phase shapes perception. Neuroimage 2012;63:771–8.

605   https://doi.org/10.1016/j.neuroimage.2012.07.024.

[19]   Helfrich RF, Schneider TR, Rach S, Trautmann-Lengsfeld SA, Engel AK, Herrmann

CS. Entrainment of brain oscillations by transcranial alternating current stimulation. Curr

Biol 2014;24:333–9. https://doi.org/10.1016/j.cub.2013.12.041.

[20] Riecke L, Formisano E, Herrmann CS, Sack AT. 4-Hz transcranial alternating current

stimulation phase modulates hearing. Brain Stimul 2015;8:777–83.

https://doi.org/10.1016/j.brs.2015.04.004.

[21] Nakazono H, Ogata K, Kuroda T, Tobimatsu S. Phase and frequency-dependent effects

of transcranial alternating current stimulation on motor cortical excitability. PLoS One

2016;11:e0162521. https://doi.org/10.1371/journal.pone.0162521.

[22] Guerra A, Pogosyan A, Nowak M, Tan H, Ferreri F, Di Lazzaro V, et al. Phase

dependency of the human primary motor cortex and cholinergic inhibition cancelation

during beta tACS. Cereb Cortex 2016;26:3977–90.

https://doi.org/10.1093/cercor/bhw245.

[23] Schilberg L, Engelen T, ten Oever S, Schuhmann T, de Gelder B, de Graaf TA, et al.

Phase of beta-frequency tACS over primary motor cortex modulates corticospinal

excitability. Cortex 2018;103:142–52. https://doi.org/10.1016/j.cortex.2018.03.001.

[24] Khatoun A, Breukers J, Op de Beeck S, Nica IG, Aerts J-M, Seynaeve L, et al. Using

high-amplitude and focused transcranial alternating current stimulation to entrain

physiological tremor. Sci Rep 2018;8:8221. https://doi.org/10.1038/s41598-018-26013-

3.

[25] Mehta AR, Brittain J-S, Brown P. The selective influence of rhythmic cortical versus

cerebellar transcranial stimulation on human physiological tremor. J Neurosci

2014;34:7501–8. https://doi.org/10.1523/JNEUROSCI.0510-14.2014.

[26] Brittain J-S, Probert-Smith P, Aziz TZ, Brown P. Tremor suppression by rhythmic

transcranial current stimulation. Curr Biol 2013;23:436–40.

https://doi.org/10.1016/j.cub.2013.01.068.

[27] Asamoah B, Khatoun A, Mc Laughlin M. tACS motor system effects can be caused by

transcutaneous stimulation of peripheral nerves. Nat Commun 2019;10:266.

https://doi.org/10.1038/s41467-018-08183-w.

[28] Riecke L, Sack AT, Schroeder CE. Endogenous delta/theta sound-brain phase

entrainment accelerates the buildup of auditory streaming. Curr Biol 2015;25:3196–201.

https://doi.org/10.1016/j.cub.2015.10.045.

[29] Herrmann CS. Human EEG responses to 1-100 Hz flicker: Resonance phenomena in

visual cortex and their potential correlation to cognitive phenomena. Exp Brain Res

2001;137:346–53. https://doi.org/10.1007/s002210100682.

[30] Vossen A, Gross J, Thut G. Alpha power increase after transcranial alternating current

stimulation at alpha frequency (α-tACS) reflects plastic changes rather than entrainment.

Brain Stimul 2015;8:499–508. https://doi.org/10.1016/j.brs.2014.12.004.

[31] Zaehle T, Rach S, Herrmann CS. Transcranial alternating current stimulation enhances

individual alpha activity in human EEG. PLoS One 2010;5:e13766.

https://doi.org/10.1371/journal.pone.0013766.

[32] Laakso I, Hirata A. Computational analysis shows why transcranial alternating current

stimulation induces retinal phosphenes. J Neural Eng 2013;10:046009.

https://doi.org/10.1088/1741-2560/10/4/046009.

[33] Oostenveld R, Stegeman DF, Praamstra P, van Oosterom A. Brain symmetry and

topographic analysis of lateralized event-related potentials. Clin Neurophysiol

2003;114:1194–202. https://doi.org/10.1016/S1388-2457(03)00059-2.

[34] Oostenveld R, Fries P, Maris E, Schoffelen J-M. FieldTrip: Open source software for

advanced analysis of MEG, EEG, and invasive electrophysiological data. Comput Intell

Neurosci 2011;2011:1–9. https://doi.org/10.1155/2011/156869.

[35] Berens P. CircStat: A MATLAB toolbox for circular statistics. J Stat Softw 2009;31:1–

21.

[36] Stonkus R, Braun V, Kerlin JR, Volberg G, Hanslmayr S. Probing the causal role of

prestimulus interregional synchrony for perceptual integration via tACS. Sci Rep

2016;6:32065.

[37]　Bell AJ, Sejnowski TJ. Blind separation and blind deconvolution: An information-

theoretic approach 2002;5:3415–8. https://doi.org/10.1109/ICASSP.1995.479719.

[38]　Hahm J, Lee H, Park H, Kang E, Kim YK, Chung CK, et al. Gating of memory encoding

of time-delayed cross-frequency MEG networks revealed by graph filtration based on

persistent homology. Sci Rep 2017;7:41592. https://doi.org/10.1038/srep41592.

[39]　Tort ABL, Komorowski R, Eichenbaum H, Kopell N. Measuring phase-amplitude

coupling between neuronal oscillations of different frequencies. J Neurophysiol

2010;104:1195–210. https://doi.org/10.1152/jn.00106.2010.

[40]　Wilsch A, Neuling T, Obleser J, Herrmann CS. Transcranial alternating current

stimulation with speech envelopes modulates speech comprehension. Neuroimage

2018;172:766–74. https://doi.org/10.1016/j.neuroimage.2018.01.038.

[41]　Keitel C, Keitel A, Benwell CSY, Daube C, Thut G, Gross J. Stimulus-driven brain

rhythms within the alpha band: The attentional-modulation conundrum. J Neurosci

2019;39:3119–29. https://doi.org/10.1523/JNEUROSCI.1633-18.2019.

[42]　Notbohm A, Kurths J, Herrmann CS. Modification of brain oscillations via rhythmic

light stimulation provides evidence for entrainment but not for superposition of event-

related　　responses.　　Front　　Hum　　Neurosci　　2016;10:10.

https://doi.org/10.3389/fnhum.2016.00010.

[43]　Zoefel B, ten Oever S, Sack AT. The involvement of endogenous neural oscillations in

the processing of rhythmic input: More than a regular repetition of evoked neural

responses. Front Neurosci 2018;12:1–13. https://doi.org/10.3389/fnins.2018.00095.

[44]　Wischnewski M, Engelhardt M, Salehinejad MA, Schutter DJLG, Kuo MF, Nitsche MA.

NMDA receptor-mediated motor cortex plasticity after 20 Hz transcranial alternating

current　　stimulation.　　Cereb　　Cortex　　2019;29:2924–31.

https://doi.org/10.1093/cercor/bhy160.

[45]   Marshall L, Helgadóttir H, Mölle M, Born J. Boosting slow oscillations during sleep

potentiates memory. Nature 2006;444:610–3. https://doi.org/10.1038/nature05278.

[46]   Hanslmayr S, Matuschek J, Fellner M-C. Entrainment of prefrontal beta oscillations

induces an endogenous echo and impairs memory formation. Curr Biol 2014;24:904–9.

https://doi.org/10.1016/j.cub.2014.03.007.

[47]   Halbleib A, Gratkowski M, Schwab K, Ligges C, Witte H, Haueisen J. Topographic

analysis of engagement and disengagement of neural oscillators in photic driving. J Clin

Neurophysiol 2012;29:33–41. https://doi.org/10.1097/WNP.0b013e318246ad6e.

[48]   Ozen S, Sirota A, Belluscio MA, Anastassiou CA, Stark E, Koch C, et al. Transcranial

electric stimulation entrains cortical neuronal populations in rats. J Neurosci

2010;30:11476–85. https://doi.org/10.1523/JNEUROSCI.5252-09.2010.

[49]   Cabral-Calderin Y, Anne Weinrich C, Schmidt-Samoa C, Poland E, Dechent P, Bähr M,

et al. Transcranial alternating current stimulation affects the BOLD signal in a frequency

and task-dependent manner. Hum Brain Mapp 2016;37:94–121.

https://doi.org/10.1002/hbm.23016.

[50]   Chai Y, Sheng J, Bandettini PA, Gao J-H. Frequency-dependent tACS modulation of

BOLD signal during rhythmic visual stimulation. Hum Brain Mapp 2018;39:2111–20.

https://doi.org/10.1002/hbm.23990.

[51]   Ruhnau P, Neuling T, Fuscá M, Herrmann CS, Demarchi G, Weisz N. Eyes wide shut:

Transcranial alternating current stimulation drives alpha rhythm in a state dependent

manner. Sci Rep 2016;6:27138. https://doi.org/10.1038/srep27138.

[52]   Neuling T, Rach S, Herrmann CS. Orchestrating neuronal networks: Sustained after-

effects of transcranial alternating current stimulation depend upon brain states. Front

Hum Neurosci 2013;7:161. https://doi.org/10.3389/fnhum.2013.00161.

[53]   Alagapan S, Schmidt SL, Lefebvre J, Hadar E, Shin HW, Fröhlich F. Modulation of

cortical oscillations by low-frequency direct cortical stimulation is state-dependent.

PLOS Biol 2016;14:e1002424. https://doi.org/10.1371/journal.pbio.1002424.

[54]   Vieira PG, Krause MR, Pack CC. tACS entrains neural activity while somatosensory

input is blocked. BioRxiv 2019:691022. https://doi.org/10.1101/691022.

[55]   Herring JD, Esterer S, Marshall TR, Jensen O, Bergmann TO. Low-frequency alternating

current stimulation rhythmically suppresses gamma-band oscillations and impairs

perceptual performance. Neuroimage 2019;184:440–9.

https://doi.org/10.1016/j.neuroimage.2018.09.047.

[56]   Ruhnau P, Keitel C, Lithari C, Weisz N, Neuling T. Flicker-driven responses in visual

cortex change during matched-frequency transcranial alternating current stimulation.

Front Hum Neurosci 2016;10:184. https://doi.org/10.3389/fnhum.2016.00184.

Figures

Figure 1. Experimental setup. (A) Schematic display of the experimental timeline. The experiment was conducted on two separate days for active tACS and sham stimulation. Resting state (RS) and visual evoked steady state response (SSR) data without tACS were recorded pre and post to the tACS blocks. (B) tACS electrode montage and power of the tACS-induced stimulation field. The occipital electrode montage induced highest current densities over the primary visual cortex and current spread in surrounding areas. Maximum peak-to-peak difference in field strength is about 0.7 V/m. (C) Illustration of one trial of the intermittent tACS protocol. Each trial started with tACS only, followed by flicker onset after 3-5 sec. The flicker continued for 5.5 sec until the end of the trial. The gray-shaded tACS free intervals were used for EEG data analysis. (D) To vary the phase between neural activity induced by electrical and sensory rhythmic stimulation, visual flicker started at six different phase shifts relative to the tACS cycle. 50 trials per phase angle were presented in randomized order.

Figure 2. Phase locking values (PLVs) of steady state responses (SSRs) to flicker phase over all trials of the active and sham pre SSR blocks. (A) SSR during 5.5 sec flicker stimulation computed as the average of 50 raw EEG traces of one exemplary participant at channel POz. Dashed lines mark the onset and offset of visual flicker. The gray-shaded area depicts the time window used for EEG data analysis. (B) The upper part depicts the spatial distribution of mean PLVs over all participants with maximal phase locking over the parieto-occipital cortex. Markers correspond to channels selected on sensor level for SSR amplitude analysis. The lower part shows the interindividual variation in phase delays between flicker onset and cortical SSR exemplary for electrode O1. (C) Mean amplitude spectrum during flicker stimulation and resting state over all participants for the four selected channels on sensor level. Shaded areas indicate the standard error. (D) The strength of EEG-flicker PLV at the four parieto-occipital channels is positively correlated with the increase in SSR amplitude from resting state to flicker stimulation during pre SSR blocks across participants ($r = .43$, $p = .037$, n = 24). * $p < .05$.

Figure 3. Steady state response (SSR) amplitude modulation by tACS shown for the time window of 0.1 to 1.1 sec after stimulation offset during the tACS block on sensor level. (A) SSR amplitude bar graphs for one exemplary participant. SSR amplitude values differ in the degree of phase dependence under tACS compared to sham. Black lines show sinusoidal fits to the data. (B) Significantly increased Kullback-Leibler divergence (D_{KL}), enhanced phase locking of amplitude values to phase condition (APL) and sine fit amplitudes under tACS relative to sham. (C, D) Phase-dependent amplitude modulation is not paralleled by differences in mean absolute 10 Hz alpha amplitude or mean SSR amplitude over all trials and participants between stimulation conditions. Shaded areas and error bars indicate the standard error. (E) Decay in tACS effect size over three time windows after tACS offset. Bar graphs show the mean difference in SSR amplitude modulation between active and sham tACS condition quantified via three modulation measures. Asterisks mark the uncorrected *p*-value of dependent samples t-tests. Only statistical tests for the first 1 sec time epoch after tACS offset remain significant after Bonferroni correction for comparisons in multiple time windows (α_{bonf} = 0.0167; 0.05/3). Error bars represent the standard error. * $p < .05$; ** $p < .01$.

Figure 4. Analysis of tACS-induced amplitude phase locking (APL) of steady state responses (SSRs) during the first 1 sec epoch after tACS. (A) Significant differences in APL between active and sham tACS were localized in a cluster over the parieto-occipital cortex within flicker-entrained brain regions. (B) On sensor level, between-subject correlation shows that the tACS effect size quantified via APL is negatively related to EEG-flicker phase locking (PLV) during the tACS block ($r = -.65$, $p < .001$, n = 24). The insert illustrates that after source reconstruction, tACS effects (APL cluster boundary shown as dotted line) are mainly observed in regions where EEG-flicker PLVs did not peak during the tACS block. (C) The increase in APL values under tACS compared to sham is independent of overall changes in mean SSR amplitude or standard deviation (sd) of amplitude values over all trials per participant (sensor level data). MOG, middle occipital gyrus; SOG, superior occipital gyrus; SPG, superior parietal gyrus; *** $p < .001$.

Figure 5. Analysis of the relation between individual cortical SSR onset delays and the optimal

timing of tACS application associated with strongest SSRs. (A) Raw EEG data during the tACS

block of one representative participant at electrode O1. Data during the last 0.2 sec of tACS

stimulation show strong electrical artifacts. The gray-shaded area depicts the time window used

for data analysis. (B) In case of an interference of flicker and electric field in the retina, visual

response would be modulated before neural conduction delays along the visual pathway take

effect. Thus, the optimal flicker-tACS phase shift should be independent of individual SSR

onset delays and be comparable across participants as exemplified in the polar plot. In contrast,

a significant cluster of occipital electrodes reveals a circular correlation between flicker-tACS

phase shift and subject-specific SSR onset delays only during the tACS session. This suggests

an interaction of tACS effects and SSR at early stages of visual cortical processing with

concurrent spread of activity to higher visual areas. (C) Polar plots show flicker-SSR phase

delays for all participants grouped by optimal flicker-tACS phase shift conditions exemplary

for electrode O1. Blue circles show the mean flicker-SSR phase delay computed over all trials

per participant and arrows depict the mean phase angle over all trials per optimal flicker-tACS

801   phase shift condition. Circular plots on the right summarize the course of the mean flicker-SSR

802   phase angles over the six flicker-tACS phase shift conditions (gray color code corresponds to

803   flicker-tACS phase shifts of preceding polar plots). During tACS, data show a significant

804   circular correlation between individual SSR phase delays and optimal flicker-tACS phase shifts

805   across participants. There is no significant circular correlation during the sham session.