Action Potential Propagation and Synchronisation in Myelinated Axons

Helmut Schmidt[1*], Thomas R. Knösche[1],

1 Max Planck Institute for Human Cognitive and Brain Sciences, Leipzig, Germany

* hschmidt@cbs.mpg.de

Abstract

With the advent of advanced MRI techniques it has become possible to study axonal white matter non-invasively and in great detail. Measuring the various parameters of the long-range connections of the brain opens up the possibility to build and refine detailed models of large-scale neuronal activity. One particular challenge is to find a mathematical description of action potential propagation that is sufficiently simple, yet still biologically plausible to model signal transmission across entire axonal fibre bundles. We develop a mathematical framework in which we replace the Hodgkin-Huxley dynamics by a leaky integrate-and-fire model with passive sub-threshold dynamics and explicit, threshold-activated ion channel currents. This allows us to study in detail the influence of the various model parameters on the action potential velocity and on the entrainment of action potentials between ephaptically coupled fibres without having to recur to numerical simulations. Specifically, we recover known results regarding the influence of axon diameter, node of Ranvier length and internode length on the velocity of action potentials. Additionally, we find that the velocity depends more strongly on the thickness of the myelin sheath than was suggested by previous theoretical studies. We further explain the slowing down and synchronisation of action potentials in ephaptically coupled fibres by their dynamic interaction. In summary, this study presents a solution to incorporate detailed axonal parameters into a whole-brain modelling framework.

Author summary

With more and more data becoming available on white-matter tracts, the need arises to develop modelling frameworks that incorporate these data at the whole-brain level. This requires the development of efficient mathematical schemes to study parameter dependencies that can then be matched with data, in particular the speed of action potentials that cause delays between brain regions. Here, we develop a method that describes the formation of action potentials by threshold activated currents, often referred to as spike-diffuse-spike modelling. A particular focus of our study is the dependence of the speed of action potentials on structural parameters. We find that the diameter of axons and the thickness of the myelin sheath have a strong influence on the speed, whereas the length of myelinated segments and node of Ranvier length have only a marginal effect. In addition to examining single axons, we demonstrate that action potentials between nearby axons can synchronise and slow down their propagation speed.

Introduction

Neurons communicate via chemical and electrical signals, and an integral part of this communication is the transmission of action potentials along their axons. The velocity of action potentials is crucial for the right timing in information processing and depends on the dynamics of ion channels studding the axon, but also on its geometrical properties. For instance, the velocity increases approximately linearly with the diameter of myelinated axons [1]. Myelin sheaths around axons are an evolutionary trait in most vertebrates and some invertebrates, which developed independently in several taxa [2]. The presence of a myelin sheath increases the velocity of action potentials by enabling saltatory conduction [3]. Long-term, activity-dependent changes in the myelination status of axons are related to learning [4]. The functional role of differentiated myelination is to regulate and synchronise signal transmission across different axonal fibres to enable cognitive function, sensory integration and motor skills [5]. White-matter architecture has also been found to affect the peak frequency of the alpha rhythm [6]. Axons and their supporting cells make up the white matter, which has, for a long time, only been accessible to histological studies [7,8]. With the advent of advanced MRI techniques, some of the geometric parameters of axonal fibre bundles have become accessible to non-invasive methods. Techniques have been proposed to determine the orientation of fibre bundles in the white matter [9] as well as to estimate the distribution of axonal diameters [10], the packing density of axons in a fibre bundle [11,12], and the ratio of the diameters of the axon and the myelin sheath (g-ratio) [13].

First quantitative studies were done by Hursh [14] who established the (approximately) linear relationship between action potential velocity and axonal radius in myelinated axons, and Tasaki [3] who first described saltatory conduction in myelinated axons. Seminal work on ion channel dynamics was later done by Hodgkin and Huxley, establishing the voltage-dependence of ion channel currents [15]. The general result of voltage-dependent gating has been confirmed in vertebrates [16], yet a recent result for mammals suggests that the gating dynamics of sodium channels is faster than described by the Hodgkin-Huxley model, thereby enabling faster generation and transmission of action potentials [17]. In general, parameters determining channel dynamics differ widely across neuron types [18].

Seminal studies into signal propagation in myelinated axons using computational techniques were done by FitzHugh [19] and Goldman and Albus [20]. Goldman and Albus gave the first computational evidence for the linear increase of the conduction velocity with the radius of the axon, provided that the length of myelinated segments also increases linearly with the axonal radius. The latter relationship is supported by experimental evidence [21]. More recently, computational studies have investigated the role of the myelin sheath and the relationship between models of different complexity with experimental results [22]. One of the key findings here was that only a myelin sheath with finite capacitance and resistance reproduced experimental results for axonal conduction velocity. Other studies investigated the role of the width of the nodes of Ranvier on signal propagation [23,24], or the effect of ephaptic coupling on signal propagation [25–32].

Most computational studies employ numerical schemes, i.e. they discretise the mathematical problem in space and time and use numerical integration methods to investigate the propagation of action potentials. One problem that arises here is that the spatial discretisation must be relatively coarse to ensure numerical stability, which can be remedied to some extent by advanced numerical methods and computational effort. The other problem, however, cannot be remedied that easily: it is the lack of insight into how the model parameters influence the results, since there is a large number of parameters involved. A way to illustrate parameter dependencies in an

efficient manner is to use analytical techniques all the while simplifying the model equations and extracting essential features. Studies that use analytical methods are few and far between [33–36]; yet it is also worth noting that from a mathematical perspective, myelinated axons are similar to spine-studded dendrites, in the sense that active units are coupled by passive leaky cables. An idea that we pick up from the latter is to simplify the ionic currents crossing the membrane [37, 38], there at dendritic spines mediated by neurotransmitters, here at nodes of Ranvier mediated by voltage-gated dynamics.

The goal of this article is to use analytical methods to study the influence of parameters controlling action potential generation, and geometric and electrophysiological parameters of the myelinated axon, on the speed of action potentials. The main focus here is on parameters determining the axonal structure. This will be achieved by replacing the Hodgkin-Huxley dynamics with an integrate-and-fire scheme for action potential generation, i.e. the subthreshold dynamics of a node of Ranvier is considered to be governed by passive currents until a threshold value is reached, causing an ion current to be released. These ion channel currents are considered voltage-independent, but we investigate different forms of currents, ranging from instantaneous currents to currents that incorporate time delays. We also investigate ion currents that closely resemble sodium currents measured experimentally. Our aim is to derive closed-form solutions for the membrane potential along an axon, which yields the relationship of action potential velocity with model parameters.

The specific questions we seek to answer here are the following. First, we query how physiological parameters can be incorporated into our mathematical framework, especially parameters that control the dynamics of the ionic currents. We test if parameters from the literature yield physiologically plausible results for the shape and amplitude of action potentials, and test whether a nearest-neighbour description of saltatory conduction is appropriate, or whether the ionic currents from multiple nearby nodes of Ranvier contribute to the formation of action potentials. Secondly, we ask how geometric parameters of an axon affect the transmission speed in a single axon, and how sensitive the transmission speed is to changes in these parameters. We seek to reproduce known results from the literature, such as the dependence of the velocity on axon diameter. We also explore other dependencies, such as on the g-ratio, and other microscopic structural parameters resulting from myelination. Thirdly, we investigate how ephaptic coupling affects the transmission speed of action potentials, and what the conditions are for action potentials to synchronise. In particular, we examine how restricted extra-axonal space leads to coupling between two identical axons, and how action potentials travelling through the coupled axons interact.

Results

For the mathematical treatment of action potential propagation along myelinated axons, we consider a hybrid system of active elements coupled by passively conducting cables. The latter represent myelinated segments of the axons (internodes) and are appropriately described as leaky cable, whereas the active elements represent the nodes of Ranvier. In mathematical terms, the governing equation is an inhomogeneous cable equation, which describes the membrane potential $V(x, t)$ of a leaky cable in space and time in response to an input current:

$$C_m \frac{\partial V}{\partial t} = \frac{1}{R_c} \frac{\partial^2 V}{\partial x^2} - \frac{V}{R_m} + I_{chan}(V, t). \tag{1}$$

Here, C_m and R_m are the (radial) capacitance and resistance of a myelinated fibre, and R_c is its axial resistance. We choose these parameters in accordance with experimental

Fig 1. Action potential propagation in a myelinated axon. A: The axon is made of myelinated segments (internodes), with the nodes of Ranvier forming periodic gaps in the myelin sheath. **B**: The nodes of Ranvier constitute active sites at which threshold-triggered ion currents are released. **C**: The currents entering nearby nodes of Ranvier determine the membrane potential at each node, thus forming an action potential. **D** The velocity of an action potential is determined by the distance L between two consecutive nodes, and the time difference t_{sp} it takes to reach a given threshold value.

results and keep them fixed throughout our analysis, see the Methods section for details.

The input currents generated by the ion channel dynamics at the nodes of Ranvier is commonly described by a Hodgkin-Huxley framework. However, the Hodgkin-Huxley equations are a challenge to solve analytically, and in order to proceed with our mathematical treatment we opt for a simplified description using threshold-activated currents with standardised current profiles. We analyse different current profiles, ranging from delta-spikes to combinations of exponentials which give a good approximation of the ion currents observed experimentally. We solve the cable equation for these currents analytically which yields the dynamics of the membrane potential describing the resulting depolarisation / hyperpolarisation along the axon. The linearity of the cable equation in V allows us to describe the response to multiple input currents by the superposition of solutions for single currents. A sketch of the framework is shown in Fig. 1.

Ion channel dynamics

The classical Hodgkin-Huxley model is described by a set of nonlinear equations which need to be solved numerically. Over the years, it has seen several modifications and improvements such as the one by Frankenhaeuser and Huxley [16], or the incorporation of additional ion currents [39] given the multitude of ion channels [40,41]. Also,

attempts were made to provide better fits by modifying the exponents of the gating variables [42]. In essence, it is difficult to determine what is the 'right' Hodgkin-Huxley model for specific neuron types. For this reason, it seems prudent to go into the opposite direction and to try to simplify the description of the ion channel dynamics.

Two important contributions into this direction are the one by Fitzhugh [43, 44] and Nagumo [45], and the one by Morris and Lecar [46]. They provide a framework in which the slow and the fast variables are lumped and thus yield a two-dimensional reduction of the Hodgkin-Huxley model. The ion currents here are still voltage-dependent.

A crucial simplification towards analytically treatable models is the separation of sub-threshold dynamics and spike generation in integrate-and-fire models [47, 48]. For instance, in the leaky integrate-and-fire model and the quadratic integrate-and-fire model, the time-to-spike can be computed analytically, given initial conditions and a threshold value for the membrane potential. The ion currents are then often modelled as delta-spikes since the ion dynamics is fast in comparison to the (dendritic and somatic) membrane dynamics.

Here, we consider four forms of channel current models. All of these have in common that the ion current is initiated after the membrane potential has crossed a threshold V_{thr}, and has a predetermined profile. Below this threshold, the membrane dynamics of a node is assumed to be completely governed by capacitive and resistive currents. We denote the four scenarios by the letters A, B, C, and D. In scenario A, the ion channel current is released immediately and instantaneously, i.e.

$$I_{chan}(t) = I_0 \delta(t - t_0). \tag{2}$$

Here, I_0 denotes the overall ion current, t_0 denotes the time when the membrane potential crosses the threshold, and $\delta(\cdot)$ is the delta-distribution, or Dirac's delta. In scenario B, the ion current is also released instantaneously, but with a delay Δ:

$$I_{chan}(t) = I_0 \delta(t - t_0 - \Delta), \tag{3}$$

In scenario C, the ionic current is exponential:

$$I_{chan}(t) = I_0 e^{-(t-t_0)/\tau_{sp}} \Theta(t - t_0). \tag{4}$$

Here, τ_{sp} is the decay time, and $\Theta(\cdot)$ is the Heaviside step function. With scenario D we aim to approximate the ion currents as measured in mammals such as the rabbit [49] and in the rat [50], which can be described by a superposition of exponential currents:

$$I_{chan}(t) = I_0 \sum_{n=1}^{N} A_n \exp(-(t - t_0)/\tau_n) \Theta(t - t_0), \tag{5}$$

A sketch of all these scenarios is shown in Figure 2, alongside typical depolarisation curves of the membrane potential.

Current influx and separation

According to Kirchhoff's first law, the channel current that flows into the axon, $I_{chan}(t)$ is counter-balanced by currents flowing axially both ways along the axon, $I_{cable}(t)$, and a radial current that flows back out across the membrane of the node, I_{node}, see Fig. 3A for a graphical representation. The ratio of currents that pass along the cable and back across the nodal membrane is determined by the respective resistances:

$$I_{cable} = \frac{I_{chan}}{1 + \frac{R_\lambda}{2R_{node}}}. \tag{6}$$

Fig 2. Sketch of ion channel currents considered here, with representative profiles of membrane potential.
After the membrane potential V reaches the threshold value V_{thr}, the current I is released. **A**: The instantaneous current is described by a delta-peak at t_0, when the threshold value is reached. **B**: The simplest way to accommodate delays or refractoriness is to introduce a refractory period Δ, after which the instantaneous current is released. **C**: Exponential current with characteristic time scale τ_{sp}. **D:** A combination of exponential currents describes a realistic current profile.

Fig 3. Channel currents divide into a current entering the axon and a current flowing back across the Node of Ranvier. A: Sketch of currents entering and leaving a node of Ranvier. **B**: Plot of currents as function of node length. Since we assume constant channel density, the channel current increases linearly with the node length.

Based on experimental findings, we assume that the channel density is constant [50], which implies that the total channel current increases linearly with the node length. This is counterbalanced by the fact that the inverse of the resistance of a node, R_{node}, also increases linearly with its length. At large node lengths, the current that enters the axon saturates, see Fig. 3B. We will examine further below how the node length influences the propagation speed.

Analytical solutions

In mathematical terms, the depolarisation of the neighbouring node is a convolution of the current entering the cable with the Green's function of the homogeneous cable equation $G(t)$, which describes the propagation of depolarisation along the myelinated segment:

$$V(x,t) = R_m \int_0^t I_{cable}(t-s)G(x,s)\mathrm{d}s. \tag{7}$$

In the following we present the analytical solutions for all the current types. We also present and compare linearisations of the rising phase of the depolarisation, which allows for an explicit description of the inverse relationship of t with V, i.e. how long it takes until V reaches a specific value.

Scenario A - fast current

Since the fast current is described by a delta function, the convolution of integral retains the time dependence of the Green's function:

$$V(x,t) = \frac{\sqrt{\tau} R_\lambda I_0}{\sqrt{4\pi t}} \exp\left(-\frac{x^2 \tau}{4\lambda^2 t} - \frac{t}{\tau}\right). \tag{8}$$

Here τ and λ are the characteristic time constant and length constant of the myelinated axon, given by $\tau = C_m R_m$ and $\lambda = \sqrt{R_m/R_c}$. I_0 is the amplitude of the input current, and $R_\lambda = R_m/\lambda$.

Scenario B - delayed fast current

The membrane dynamics in scenario B is exactly the same as in scenario A, except for an additional offset Δ:

$$V(x,t) = \frac{\sqrt{\tau} R_\lambda I_0}{\sqrt{4\pi (t-\Delta)}} \exp\left(-\frac{x^2 \tau}{4\lambda^2 (t-\Delta)} - \frac{t-\Delta}{\tau}\right) \Theta(t-\Delta). \tag{9}$$

Here, $\Theta(\cdot)$ represents the Heaviside step function.

Scenario C - exponential current

Here we have to solve the convolution integral of the cable equation with an exponential function, which yields

$$V(x,t) = \mathrm{e}^{-t/\tau_c} \frac{R_\lambda I_0 \sqrt{\tau \hat{\tau}}}{2\tau} \Im\left[\exp\left(i\frac{x\sqrt{\tau}}{\lambda\sqrt{\hat{\tau}}}\right)\left(\mathrm{erf}\left(\frac{x\sqrt{\tau}}{2\lambda\sqrt{t}} + i\sqrt{\frac{t}{\hat{\tau}}}\right) - 1\right)\right], \tag{10}$$

with $\hat{\tau} = (\tau^{-1} - \tau_c^{-1})^{-1}$. See the Methods section for the evaluation of the convolution integral.

Scenario D - combination of exponentials

The linearity of the cable equation allows us to recur to the solution for scenario C to describe the response to currents described by multiple exponentials. Denoting the solution for one exponential input current with time constant τ_s by

$$\phi(x,t;\tau_s) = \mathrm{e}^{-t/\tau_s} \frac{R_\lambda I_0}{2\tau} \sqrt{\tau\hat{\tau}} \, \Im \left[\exp\left(i\frac{x\sqrt{\tau}}{\lambda\sqrt{\hat{\tau}}} \right) \left(\mathrm{erf}\left(\frac{x\sqrt{\tau}}{2\lambda\sqrt{t}} + i\sqrt{\frac{t}{\hat{\tau}}} \right) - 1 \right) \right], \quad (11)$$

we express the solution to multiple superimposed exponential currents as

$$V(t) = \sum_{s=0}^{N} A_s \phi(t, \tau_s). \tag{12}$$

We use this formulation to describe both sodium currents and potassium currents. The sodium current is expressed as follows:

$$I_{chan,Na} = I_{0,Na} C_{Na,\gamma}^{-1} \left(1 - \exp(-t/\tau_m) \right)^\gamma \exp(-t/\tau_h). \tag{13}$$

We investigate three different exponents γ (see Methods section for details), $\gamma = 1, 2, 3$, and refer to the specific currents as the m^1-model, m^2-model, or m^3-model, respectively. The parameter γ also affects the normalisation constant, which ensures that the maximum of $I_{chan,Na}$ is $I_{0,Na}$. The potassium current is modeled as

$$I_{chan,K} = I_{0,K} C_K^{-1} \left(1 - \exp(-t/\tau_n) \right)^4 \exp(-t/\tau_k), \tag{14}$$

throughout the manuscript.

Influence of distant nodes

In the previous section we have derived expressions for the velocity caused by a single input current at a specific site. However, during the propagation of an action potential, ion channel currents are released at multiple nearby nodes that affect the shape and amplitude of the action potential. Due to the linear nature of the cable equation, the effect of multiple input currents can be described by linear superposition:

$$V(t) = \sum_{n=-N}^{N} U(t - nt_{sp}, n(L + l\lambda_n/\lambda)), \tag{15}$$

where U is the r.h.s. of the respective scenario considered, i.e. $U(t, L)$ describes the depolarisation due to the current at a neighbouring node. Here we adopt the convention $V_{thr} = V(0)$. Nodes with negative n are the ones the action potential has travelled past, and nodes with positive n are the ones the action potential will travel into. The action potential is not only shaped by the currents from preceding nodes, but also by currents from subsequent nodes that travel back along the axon. Due to the periodic nature of saltatory conduction, the nearest neighbour is depolarised at $t = -t_{sp}$, the second-nearest neighbour at $t = -2t_{sp}$, and so on. The relationship between the firing threshold V_{thr} and the time-to-spike t_{sp} is therefore given by

$$V_{thr} = \sum_{n=1}^{N} U(nt_{sp}, n(L + l\lambda_n/\lambda)). \tag{16}$$

The effect of distant nodes is dampened by the fact that in addition to passing along myelinated segments, currents from distant sources also pass by unmyelinated nodes,

Fig 4. Contribution of ion currents from nearby nodes to action potential profile. A: Sodium currents contributing to AP, and **B**: same for potassium. Depolarising effect is color-coded by node index, larger indices are lumped. Total effect is indicated by black line. **C**: Action potential composed of both currents. **D**: Contribution of sodium currents to reaching threshold value.

and therefore further losing amplitude. If nodes are relatively short, the current outflux can be regarded as instantaneous across the node as compared to changes in the current, and the correction term for the electrotonic length, $l\lambda_n/\lambda$ can be used.

In Figure 4 we dissect an AP using scenario D. It is apparent that the AP propagation is a collective process with each node regenerating the AP by a small fraction.

Sensitivity to parameters

Axon diameter

There is a wide consensus that the propagation velocity in myelinated axons is proportional to the axon diameter. This is mostly due to the fact that both the internode length as well as the electrotonic length constant increase linearly with the diameter. One quantity that does not scale linearly with the axonal diameter is the node length, which determines the amount of current that flows into the axon, as well as setting a correction term for the physical and electrotonic distance between two nodes. We find that the latter introduces a slight nonlinearity at small diameters, although at larger diameters the linear relationship is well preserved, see Fig. 5A.

The present framework also enables us to study unmyelinated axons, in which case

Fig 5. Propagation velocity as function of axon diameter. A: In myelinated axons, the relationship between velocity and diameter is nearly linear, with a slightly supralinear relationship at small diameters. Here two curves are shown for different node lengths. **B**: In unmyelinated axons, the propagation speed increases approximately with the square root of the axon diameter. Here, ρ indicates the the relative ion channel density compared with a node of Ranvier. Decreasing the ion channel density results in faster action potential propagation.

the current influx must be adapted, in addition to the physical and electrotonic distance between two neighbouring nodes, which is l and l/λ_n, respectively. Since λ_n is proportional to $\sqrt{d}$, the resulting velocity is also to be expected to scale with $\sqrt{d}$, see Fig. 5B. We study different ion channel densities, beginning with the same density as in nodes in the myelinated axon, and then reducing the density to 10% and 1% of the original density. We find that this reduction increases the propagation velocity. However, if we reduce the channel density further, then the depolarisation fails to reach the threshold value, which results in no propagation.

Node and internode length

Two geometric parameters that are not readily accessible to non-invasive MR-techniques are the length of the nodes of Ranvier, and the length of internodes. Here we examine the effect of the node and internode length on the speed of action potentials. We assume that the channel density in a node is constant, which is in agreement with experimental results [50]. The channel current that enters the node is proportional to its length, yet the increase of the node length also means that more of this current flows back across the node rather than entering the internodes. Another effect of the node length is the additional drop-off of the amplitude of axonal currents. Node lengths are known to vary between 1μm and 3μm [23].

The length of internodes is known to be proportional to the fibre diameter by a ratio of approximately $100 : 1$ [21]. This proportionality can be understood in light of the fact that the cable constant λ is also proportional to the fibre diameter, and therefore increasing the internode length ensures that the ratio L/λ remains at an optimal point for signal transmission.

We restrict the analysis to the activation by sodium currents, since potassium currents are slow and only play a minor role in the initial depolarisation to threshold value. The results are shown graphically in Figure 6 for a threshold value $V_{thr} = 15$mV and axon diameter of 1μm. Changing the threshold value did have a small effect on the maximum velocity, but did not change the relative dependence on the other parameters.

Fig 6. Velocity dependence on node length and internode length. A - C: Velocities are shown for three different versions of scenario D, which differ in the shape of the rising phase of the sodium current. **D - F**: Velocity dependence corrected for finite propagation time along nodes. Here we assume that the propagation velocity in a node is the same as for the equivalent unmyelinated axon. These results are obtained for $d = 1\mu m$ and $V_{thr} = 15$mV.

In Fig. 6A-C we show the results for models m^1, m^2 and m^3 as special cases of scenario D. The velocity is maximal at internode lengths of approximately $100\mu m$, which corresponds to a internode-diameter ratio of 100:1. Without taking into account additional delays arising from the nodal dynamics, the velocity increases monotonically with the node length. To correct for this, we take into account an additional time delay l/v_n between two consecutive nodes, where v_n is the velocity in an unmyelinated axon with the same properties as the node. This yields a maximum at finite values of l, as shown in Fig. 6D-F. The absolute maximum is at nodal lengths of approximately $3\mu m$, and internodal lengths of approximately $180\mu m$. These values are slightly above the physiologically observed values, yet we also see that the sensitivity to these parameters is quite low, with 95% of the maximum velocity being reached already at node lengths of $1.5\mu m$ and internode lengths of $100\mu m$. In Fig 7 we show cross-sections of Fig. 6D, which are very similar to the numerical results obtained in [23]. The choice of ion current model affected the maximum velocity, with the m^1-model yielding a maximum velocity of about $3m/s$, and the m^3-model yielding only a velocity of about $2.4m/s$ for an axon with $1\mu m$ diameter. However, the dependence of the node length and internode length remained virtually unchanged between them.

Myelin thickness

The relative thickness of the myelin layer is given by the g-ratio, which is defined as the ratio of inner to outer radius. Hence, a smaller g-ratio indicates a relatively thicker layer

Fig 7. Velocity in m^1-model as function of L or l. This figure shows cross-sections of Fig 6. **A**: Velocity as function of internode length for various values of l. **B**: Velocity as function of node length for various values of L.

Fig 8. Relative propagation velocity as function of g-ratio. A: Relative propagation velocity across the range of physiologically plausible values of g-ratios, here for the m^1-model and the m^3-model of the sodium current. Blue curves represent scaling with $(\ln(1/g))^\alpha$ for different values of α. **B**: Inset of A, with small values of g.

of myelin around the axon. In humans, the g-ratio is typically $0.6 - 0.7$, although it is also known to correlate with the axon diameter [51]. In our mathematical framework, the g-ratio affects the electrotonic length constant λ of the internodes, which scales with $\sqrt{\ln(1/g)}$. A classical assumption is that the propagation velocity scales in the same manner. This dependency is a special case of the more general function $(\ln(1/g))^\alpha$. Our results suggest that the propagation velocity depends more strongly on the g-ratio, with a good agreement to scenario D when α is between 0.7 and 0.8, see Fig. 8.

Ephaptic coupling and entrainment

We demonstrate here that it is possible to study the effects of ephaptic coupling on action potential propagation within our framework. We choose two axonal fibres as a simple test case, but more complicated scenarios could also be considered using our analytical approach. Ephaptic coupling occurs due to the resistance and finite size of the extra-cellular space. We follow Reutskiy *et al.* [30] in considering the axonal fibres being embedded in a finite sized extra-cellular medium (the space between the axons

Fig 9. Ephaptic coupling reduces AP speed and leads to AP synchronisation. A: Depolarisation curves for a pair of action potentials with initial offset of 0.05ms converge, reducing the time difference between action potentials. **B**: Depolarisation of a synchronous pair of action potentials is slower than for a single action potential. **C**: An action potential induces initial hyperpolarisation and subsequent depolarisation in an inactive neighbouring axon.

within an axonal fibre bundle). The resulting cable equation for the n^{th} axon reads

$$C_m \frac{\partial(V_n - V_e)}{\partial t} = \frac{1}{R_{ax,n}} \frac{\partial^2 V_n}{\partial x^2} - \frac{(V_n - V_e)}{R_m} + I_n^{chan}(t), \tag{17}$$

with V_e being the difference of electric potentials between extra-cellular medium with the fibre bundle and the medium outside the fibre bundle. In the Methods section we describe how to obtain solutions to this set of equations.

We explore solutions to Eq (17) in a number of ways, which are graphically represented in Figure 9. Again, we focus on sodium currents as described by the m^3-model. First, we study how the coupling could lead to entrainment, i.e. synchronisation of action potentials. To this end, we compare the time courses of $V_1(t)$ and $V_2(t)$, where an action potential is emitted in the first axon at $t = 0$, and in the second axon at $t = \Delta t$. We then compare the t_{sp} in the neighbouring nodes, and find that for any low threshold values V_{thr} the difference between the t_{sp} is less than Δt, meaning the two action potentials are re-synchronising, see Fig 9A. Next, we asked how the coupling affects the speed of two entrained action potentials. Now we set $\Delta_t = 0$, in which case $V_1(t) = V_2(t)$. We compare $V_{1,2}(t)$ with $V_1(t)$ if there is only an action potential travelling across the first axon, and find that the voltages rise more slowly if two action potentials are present, thus increasing t_{sp} and decreasing the speed of the two action potentials, see Fig 9B. Thirdly, we considered the case when there is an action potential only in one axon, and computed the voltage in the second, passive axon. We find that the neighbouring axon undergoes a brief spell of hyperpolarisation, with a half-width shorter than that of the action potential. This hyperpolarisation explains why synchronous or near-synchronous pairs of action potentials travel at considerably smaller velocities than single action potentials. The hyperpolarisation is followed by weaker depolarisation.

Discussion

We have developed an analytic framework for the investigation of action potential propagation based on simplified ion currents. Instead of modelling the detailed dynamics of the ion channels and its resulting transmembrane currents, we have adopted a simpler notion by which a threshold value defines the critical voltage for the ion current release.

Below that threshold value the membrane dynamics is passive, and once the threshold value is reached the ion current is released in a prescribed fashion regardless of the exact time-dependence of the voltage before or after. We studied four different scenarios, of which the simplest was described by a delta-function representing immediate and instantaneous current release. The three other scenario incorporated delays in different ways, from a shift of the delta function to exponential currents and, lastly, combinations thereof. The latter seemed most appropriate considering experimental results.

The simplified description of the ion currents permitted the use of analytical methods to derive an implicit relationship between model parameters and the time the ion current would depolarise a neighbouring node up to threshold value. This involved the solution of what is in essence a convolution integral; it was the convolution of the ion current with the Green's function of the passive cable equation. From the length of the internode and the time to threshold value in the between two consecutive nodes resulted the velocity of the action potential.

Although it was not possible to derive a closed-form explicit relationship between propagation time and threshold value, we have shown that one can achieve a good approximation by linearising the rising phase of the depolarisation curve (see Methods section). We did not explore the linearisation in every detail, but we are certain that it can be used in future work to serve as a simple return-map scheme for action potential propagation, in which parameter heterogeneities along the axon could be explored. For the full nonlinear problem we only obtained an implicit relationship, which needed to be solved using root-finding procedures. However, in comparison to full numerical simulations, our scheme still confers a computational advantage by orders of magnitude.

We used our scheme to study in detail the shape of action potentials, and we found that the ion currents released at multiple nearby nodes contribute to the shape and amplitude of an action potential. This demonstrates that action potential propagation is a collective process, during which individual nodes replenish the current amplitude without being critical to the success or failure of AP propagation. Specifically, the rising phase of an action potential is mostly determined by input currents released at backward nodes, whereas the falling phase is determined more prominently by forward nodes.

Our scheme allowed us to perform a detailed analysis of the parameter dependence of the propagation velocity. We recovered previous results for the velocity dependence on the axon diameter, which were an approximately linear relationship with the diameter in myelinated axons, and a square root relationship in unmyelinated axons. Although the node and internode length are not accessible to non-invasive imaging methods, we found it pertinent since a previous study [23] looked into this using numerical simulations. Our scheme confirms their results qualitatively and quantitatively, and by performing a more detailed screening of the node length and the internode length revealed that for a wide range around a maximum value the propagation velocity is relatively insensitive to parameter variations. We also studied the effect of the g-ratio, the effect of which was stronger than previously reported, as we find that the velocity is proportional to $(\ln(-g))^{\alpha}$ with $\alpha = 0.7 - 0.8$, whereas the classical assumption was $\alpha = 0.5$ [1].

The framework developed here also allowed us to study the effect of ephaptic coupling between axons on action potential propagation. We found that the coupling leads to the convergence between sufficiently close APs, also known as entrainment. It has been hypothesised that the functional role of entrainment is to re-synchronise spikes of source neurons. We also found that ephaptic coupling leads to a decrease in the wave speed of two synchronous APs. Since the likelihood of two or more APs to synchronise in a fibre bundle increases with the firing rate, we hypothesise that a potential effect could be that delays between neuronal populations increase with their firing rate, and therefore them being able to actively modulate delays. In addition, we examined the temporal voltage profile in a passive axon coupled to an axon transmitting an AP,

which led to a brief spell of hyperpolarisation in the passive axon. This prompts the question whether this may modulate delays in tightly packed axon bundles without necessarily synchronising APs. The three phenomena we report here were all observed by Katz and Schmitt [52] in pairs of unmyelinated axons. Our results predict that the same phenomena occur in pairs (or bundles) of myelinated axons.

There are certain limitations to the framework presented here. First of all, we calibrated the ion currents with data found in the literature. This ignores detailed ion channel dynamics, and it is an outstanding problem how to best match ion currents produced by voltage-gated dynamics with the phenomenological ion currents used in this study. Secondly, we assumed that the axon is periodically myelinated, with constant g-ratio and diameter along the entire axon. The periodicity ensured that the velocity of an action potential can be readily inferred from the time lag between two consecutive nodes. In an aperiodic medium, the threshold times need to be determined for each node separately, resulting in a framework that is computationally more involved. Here, however, it might prove suitable to exploit the linearised expressions for the membrane potential to achieve a good trade-off between accuracy and computational effort. Heterogeneities in the g-ratio or the axon diameter would be harder to resolve, as the corresponding cable equation and its Green's function would contain space-dependent parameters. If individual internodes are homogeneous, then one could probably resort to methods used in [34] to deal with (partially) demyelinated internodes. Thirdly, we studied ephaptic coupling between two identical fibres as a test case. Our framework is capable of dealing with axons of different size too, as well as large numbers of axons. In larger axon bundles, however, it might be necessary to compute the ephaptic coupling from the local field potentials, as the lateral distance between axons may no longer allow for the distance-independent coupling we used here. However, it would be interesting to extent our framework to realistic axon bundle morphologies, and test if the predictions we make here, i.e. synchronisation of action potentials and concurrent increase in axonal delay, still hold. If yes, then there may also be the possibility that delays are modulated by the firing rates of neuronal populations.

Methods

The cable equation

To model action potential propagation along myelinated axons, we consider a hybrid system of active elements coupled by passively conducting cables. The latter represent segments of myelinated axons and are appropriately described by the cable equation, whereas the active elements represent the nodes of Ranvier whose dynamics are governed by parametrically reduced, phenomenological dynamics.

In general, a myelinated axon can be described by the following cable equation:

$$C_m \frac{\partial V}{\partial t} = \frac{1}{R_c} \frac{\partial^2 V}{\partial x^2} - \frac{V}{R_m} + I_{chan}(V,t), \tag{18}$$

where V is the trans-membrane potential, $I_{chan}(V,t)$ represents the ionic currents due to the opening of ion channels, and x represents the spatial coordinate longitudinal to the cable. C_m and R_m are the capacitance and resistance of myelinated segments of the cable. Multiplying both sides of (18) with R_m yields

$$\tau \frac{\partial V}{\partial t} = \lambda^2 \frac{\partial^2 V}{\partial x^2} - V + R_m I_{chan}(t), \tag{19}$$

where $\tau = C_m R_m$ and $\lambda = \sqrt{R_m/R_c}$ are the time constant and cable constant pertaining to the internodes.

Cable parameters

The capacitance of a cylindrical capacitor (such as a myelin sheath, or the insulating part of a coaxial cable) can be found by considering the following relationship,

$$C_m = \frac{2\pi\epsilon}{\ln(1/g)}, \tag{20}$$

with g being the g-ratio, i.e. the ratio between inner diameter and outer diameter, and ϵ denotes the permittivity of the medium. The radial resistance of the cylinder is given by:

$$R_m = \frac{\rho}{2\pi} \ln\frac{1}{g}. \tag{21}$$

The constant ρ describes the resistivity of the cylindrical medium.

Experimental values for the capacitance and radial resistance of a myelinated axon are reported in Goldman and Albus [20],

$$C_m = k_1 \ln^{-1}\frac{1}{g}, \quad R_m = k_2 \ln\frac{1}{g}, \tag{22}$$

with (taking values from [53] and assuming $g = 0.8$ in the frog)

$$k_1 = 3.6pF cm^{-1}, \quad k_2 = 130M\Omega cm. \tag{23}$$

The values for k_1 and k_2 correspond to the following values for permittivity and resistivity:

$$\epsilon = 5.7 \times 10^{-11} s\Omega^{-1}m^{-1}, \quad \rho = 8.16 \times 10^6 \Omega m. \tag{24}$$

Lastly, the axial resistance per unit length along the inner medium of the cylinder is given by

$$R_c = \frac{4\rho_{ax}}{\pi d^2}, \tag{25}$$

where $\rho_{ax} = 110\Omega cm$ [20] is the resistivity of the inner-axonal medium, and $\pi d^2/4$ its cross-sectional area.

With these constants at hand, we can now define the parameters of equation (19):

$$\lambda \approx 9.65 \times 10^2 d\sqrt{\ln g^{-1}}, \quad \tau = 0.47ms. \tag{26}$$

We treat the axonal diameter d and the g-ratio g as free parameters, and ρ_{ax}, k_1 and k_2 are treated as constants.

Analytical solution

The inhomogenenous cable equation can be written in compact form:

$$\tau\dot{V} = \lambda^2 V'' - V + I. \tag{27}$$

Fourier transformation in x yields an ordinary differential equation,

$$\tau\dot{\tilde{V}} = -(\lambda^2 k^2 + 1)\tilde{V} + \tilde{I}, \tag{28}$$

where $\tilde{}$ indicates the Fourier transformed quantity. The homogeneous part has the solution

$$\tilde{V} = C\exp(-(\lambda^2 k^2 + 1)t/\tau). \tag{29}$$

Fig 10. Green's function of the cable equation A: Green's function for various values of internode length L. **B**: Green's function for $L = 1$mm, showing the slow (dotted) and fast (dash-dotted) approximation.

The inhomogeneous solution in t can be found by variation of the constant, which yields the following convolution integral in t:

$$\tilde{V} = \int_0^t \frac{1}{\tau} \exp(-(\lambda^2 k^2 + 1)(t-s)/\tau)\tilde{I}(k,s)\mathrm{d}s. \tag{30}$$

This expression can be inverse Fourier transformed, which yields the following double convolution integral in x and t:

$$V(x,t) = \frac{1}{\sqrt{2\pi\tau}} \int_0^t \int_{-\infty}^{\infty} \frac{1}{\sqrt{2\lambda^2(t-s)}} \exp\left(-\frac{(x-y)^2\tau}{4\lambda^2(t-s)} - \frac{t-s}{\tau}\right) I(y,s)\mathrm{d}y\mathrm{d}s. \tag{31}$$

Since we assume the nodes of Ranvier to be discrete sites described by delta functions in x, this integral becomes ultimately a convolution integral in time only.

Thus, we can identify the Green's function of the cable equation (18) as

$$G(t) = \frac{1}{\sqrt{4\pi\lambda^2\tau t}} \exp\left(-\frac{L^2\tau}{4\lambda^2 t} - \frac{t}{\tau}\right). \tag{32}$$

This is Green's function representing the time evolution of the voltage in a cable due to an instantaneous, normalised input current at distance L at time $t = 0$. The distance L represents the length of a myelinated segment. A graphical representation of $G(t)$ is given in Fig. 10A for various values of L.

We note here that the Green's function contains *two* time scales. The first is the characteristic time scale of the cable, τ, which indicates the voltage decay across the myelin sheath. The second time constant is $L^2\tau/4\lambda^2$, which is the time it takes $\exp(-L^2\tau/4\lambda^2 t)$ to reach $1/\mathrm{e} \approx 0.37$. This time depends on all cable parameters, and if $L/\lambda < 1$ it is significantly faster than τ. Hence, if $t \ll \tau$, the cable equation can be approximated by

$$G(t) = \frac{1}{\sqrt{4\pi\lambda^2\tau t}} \exp\left(-\frac{L^2\tau}{4\lambda^2 t}\right), \tag{33}$$

or, conversely, in the limit $t \gg \tau$, it can be approximated by

$$G(t) = \frac{1}{\sqrt{4\pi\lambda^2\tau t}} \exp\left(-\frac{t}{\tau}\right). \tag{34}$$

See Fig 10B for a comparison.

Nodal properties

Like the myelinated parts of the axon, the Ranvier nodes are characterised by their electrophysiological properties through the membrane resistance and membrane capacitance, denoted by R_n and C_n, which result in a characteristic length scale λ_n and a characteristic time scale τ_n. The following values for R_n and C_n are reported in Goldman and Albus [20]:

$$C_n = 2\mu\text{Fcm}^{-2}, \quad R_n = 33\Omega\text{cm}^2, \tag{35}$$

where $R_n = g_L^{-1}$, i.e. the inverse leak conductance. However, given later, more precise measurements of membrane capacitances [54], we use here $C_n = 1\mu\text{Fcm}^{-2}$ instead. With $\tau_n = C_n R_n$ we obtain a characteristic time of $\tau_n = 33\mu$s. This value is striking, since the nodal segment constitutes a part of the neuron, and one would be inclined to use typical time constants for neurons, ranging from 10ms to 100ms. This can be explained by the higher density of voltage-gated sodium channels at the nodes of Ranvier than at the soma. As reported in [55], there are approximately 1200 channels per μm^2 at nodal segments and only about 2.6 channels per μm^2 at the soma. Thus, the ratio of ion channel densities between node and soma is nearly 500. This is most likely to affect membrane resistance, considering that the resistance is of the order $10\text{k}\Omega\text{cm}^2$ at the soma.

Current influx and separation

The channel current that flows into the axon, $I_{chan}(t)$ is counter-balanced by currents flowing axially both ways along the axon, $I_{cable}(t)$, and a radial current that flows back out across the membrane of the node, I_{node}:

$$I_{chan}(t) = I_{node}(t) + I_{cable}(t). \tag{36}$$

The ratio of currents that pass along the cable and back across the nodal membrane is determined by the respective resistances:

$$R_{node}I_{node} = \frac{R_\lambda}{2}I_{cable}, \tag{37}$$

where R_λ is the longitudinal resistance of the axon, defined by $R_\lambda = R_m/\lambda$. This relationship yields

$$I_{cable} = \frac{I_{chan}}{1 + \frac{R_\lambda}{2R_{node}}}. \tag{38}$$

Approximations and analytical solutions

It is, in general, not possible to find closed-form solutions to the Hodgkin-Huxley model due to the nonlinear dependence of the gating variables on the voltage. We therefore focus here on idealisations of the currents generated by the ion channel dynamics, which is described by a function $I_{chan}(t)$.

In mathematical terms, the depolarisation of the neighbouring node is a convolution of the current entering the cable with the solution of the homogeneous cable equation $G(t)$, which describes the propagation of depolarisation along the myelinated segment:

$$V_{cable}(t) = R_m \int_0^t I_{cable}(t-s)G(s)\mathrm{d}s. \tag{39}$$

In the following we present the mathematical treatment for the scenarios introduced in the Results section.

Scenario A - fast current

The (in mathematical terms) simplest scenario is the in which the ion current is
described by the Dirac delta function:

$$I_{chan}(t) = I_0 \delta(t - t_0). \tag{40}$$

Without loss of generality we set the time of the current, t_0, to zero. The depolarisation
along the cable, and specifically at the neighbouring node at distance L (L is the length
of a myelinated segment, or internode) is then given by the Green's function of the cable
equation itself:

$$V(t) = \frac{\sqrt{\tau} R_\lambda I_0}{\sqrt{4\pi t}} \exp\left(-\frac{L^2 \tau}{4\lambda^2 t} - \frac{t}{\tau}\right). \tag{41}$$

If only one current is injected into the cable, the time t_{sp} when the threshold value V_{thr}
is reached is given implicitly by

$$V_{thr} = \frac{\sqrt{\tau} R_\lambda I_0}{\sqrt{4\pi t_{sp}}} \exp\left(-\frac{L^2 \tau}{4\lambda^2 t_{sp}} - \frac{t_{sp}}{\tau}\right). \tag{42}$$

Equation 42 yields an implicit relation for t_{sp} and the model parameters. There is
no obvious way of solving 42 for t_{sp} explicitly. One can solve it using Newton's method,
and test various parameter dependencies by arc-length continuation. However, we
explore the possibility to derive an approximate solution for t_{sp}, and consequently for
the axonal propagation speed v, by linearisation of (42).
A suitable pivot for the linearisation is the inflection point on the rising branch, i.e.
$V''(t) = 0$ and $V'(t) > 0$. This ensures that the linearisation around this point is
accurate up to order $\mathcal{O}(t^2)$, and error terms are of order $\mathcal{O}(t^3)$ and higher. It also
provides an unambiguous pivot for the linearisation. Differentiating (41) twice yields

$$V''(t) = \left(\frac{L^4 \tau^2}{16\lambda^4 t^4} - \frac{3L^2 \tau}{4\lambda^2 t^3} + \frac{3 - 2L^2/\lambda^2}{4t^2} + \frac{1}{\tau t} + \frac{1}{\tau^2}\right) V(t). \tag{43}$$

We multiply all terms by t^4 such that the lowest order term in t is of order zero. Since τ
is much larger than the rise time of the depolarisation, we disregard terms of order
$\mathcal{O}(t^3)$ and higher. The resulting quadratic equation for the inflection point, t_i, yields
two positive roots, the smaller of which is

$$t_i = \frac{3L^2 \tau}{2\lambda^2(3 - 2L^2/\lambda^2)} \left(1 - \sqrt{1 - \tfrac{1}{9}(3 - 2L^2/\lambda^2)}\right), \tag{44}$$

In the limit of $L/\lambda \ll 1$ we can further simplify this expression to give

$$t_i = \beta \frac{L^2 \tau}{\lambda^2}, \tag{45}$$

with $\beta = 1/2 - 1/\sqrt{6}$. The linear equation for the time-to-spike and the firing threshold
is then given by

$$t_{sp} = t_i + \frac{V_{thr} - V(t_i)}{V'(t_i)}. \tag{46}$$

The quantities $V_{cable}(t_i)$ and $V'_{cable}(t_i)$ can be approximated to be

$$V(t_i) \approx \frac{R_\lambda I_0}{\sqrt{4\pi\beta}} \frac{\lambda}{L} \exp\left(-\frac{1}{4\beta}\right), \tag{47}$$

and

$$V'_{cable}(t_i) \approx \frac{\frac{2}{\sqrt{6}}\lambda^2}{4\beta^2 L^2 \tau} V_{cable}(t_i). \tag{48}$$

A comparison of the full nonlinear solution with the linear approximation is shown in
Figure 11A.

Fig 11. Depolarisation curves and their linear approximation. A:
Depolarisation curve for instantaneous input current (scenario A). **B**: Depolarisation
curve for exponential input current ($\tau_s = 100\mu s$).

Scenario B - delayed fast current

Again we consider a fast current, but one which is emitted with a delay Δ after the
membrane potential has reached the threshold value. If we denote by t_0 the time of the
threshold crossing, then the ionic current is given by

$$I_{chan}(t) = I_0\delta(t - t_0 - \Delta). \tag{49}$$

However, by simple linear transformation we may also use t_0 to denote the time of the
spike. In this case, a spike will be generated after $t_{sp} + \Delta$ in the adjacent node, where
t_{sp} is the time to the threshold crossing in the same node, given by equation (42). The
speed of a propagating action potential is then given by

$$v = \frac{L}{t_{sp} + \Delta}. \tag{50}$$

In the limit of $t_{sp} \to 0$ we obtain the result

$$v = \frac{L}{\Delta}. \tag{51}$$

The velocity is still proportional to the axonal diameter d provided that L grows
linearly with d, but there is no dependence on the g-ratio. However, this is a rather
naive estimate, since t_{sp} needs to be sufficiently small, but not zero. Therefore, we can
use equation (50) to test the influence of Δ on the velocity and incorporate the velocity
estimates from the previous section. Also, using $\Delta = 100\mu s$, which is a realistic value for
channel delays, we obtain a proportionality factor for the action potential velocity of
$\kappa = 1\text{m s}^{-1}\ \mu\text{m}^{-1}$. This is certainly a considerable underestimation of the action
potential velocity, but as we shall see later, taking into consideration the effect of
non-neighbouring nodes yields a better estimate.

Scenario C - exponential current

At this point, we make the assumption that the channel current rises infinitely fast, and
drops off exponentially. In mathematical terms, the currents generated by an action
potential at a particular node have the following form:

$$I_{chan}(t) = I_0 \exp(-(t - t_0)/\tau_c), \tag{52}$$

where I_0 denotes the amount of current generated by the channel dynamics, and t_0 denotes the time the spike is generated. Without loss of generality we set $t_0 = 0$.

The propagated depolarisation is now given by the convolution of the exponential function with the Green's function of the cable equation:

$$V(t) = e^{-t/\tau_c} R_\lambda I_0 \int_0^t \frac{1}{\sqrt{4\pi\tau s}} \exp\left(-\frac{L^2\tau}{4\lambda^2 s} + \frac{s}{\hat{\tau}}\right) ds. \tag{53}$$

Here we use $\hat{\tau}^{-1} = -\tau^{-1} + \tau_c^{-1}$. We now briefly sketch how to solve this integral. Disregarding prefactors, the integral to be solved here is of the form

$$I = \int_0^t \frac{1}{\sqrt{s}} \exp\left(-\frac{a}{s} + \frac{s}{b}\right) ds. \tag{54}$$

Using the transform $r = \sqrt{s}$ yields

$$I = 2 \int_0^{\sqrt{t}} \exp\left(-\frac{a}{r^2} + \frac{r^2}{b}\right) dr. \tag{55}$$

In addition, we define a second integral of the form

$$I_2 = 2 \int_0^{\sqrt{t}} \frac{1}{r^2} \exp\left(-\frac{a}{r^2} + \frac{r^2}{b}\right) dr. \tag{56}$$

Next, we apply the transform $w_\pm = \sqrt{a}r \pm ir/\sqrt{b}$ to these two integrals, which yields

$$I = 2 \int_\infty^{\frac{\sqrt{a}}{\sqrt{t}} \pm i\frac{\sqrt{t}}{\sqrt{b}}} \frac{r^2}{-\sqrt{a} \pm ir^2/\sqrt{b}} \exp\left(\pm 2i\sqrt{\frac{a}{b}}\right) \exp\left(-w_\pm^2\right) dw_\pm, \tag{57}$$

and

$$I_2 = 2 \int_\infty^{\frac{\sqrt{a}}{\sqrt{t}} \pm i\frac{\sqrt{t}}{\sqrt{b}}} \frac{1}{-\sqrt{a} \pm ir^2/\sqrt{b}} \exp\left(\pm 2i\sqrt{\frac{a}{b}}\right) \exp\left(-w_\pm^2\right) dw_\pm. \tag{58}$$

The two integrals can be combined as follows:

$$\pm \frac{i}{\sqrt{b}} I - \sqrt{a} I_2 = 2 \int_\infty^{\frac{\sqrt{a}}{\sqrt{t}} \pm i\frac{\sqrt{t}}{\sqrt{b}}} \exp\left(\pm 2i\sqrt{\frac{a}{b}}\right) \exp\left(-w_\pm^2\right) dw_\pm. \tag{59}$$

The integral on the right is straightforward to evaluate:

$$\pm \frac{i}{\sqrt{b}} I - \sqrt{a} I_2 = \sqrt{\pi} \exp\left(\pm 2i\sqrt{\frac{a}{b}}\right) \left[\text{erf}\left(\frac{\sqrt{a}}{\sqrt{t}} \pm i\frac{\sqrt{t}}{\sqrt{b}}\right) - 1\right]. \tag{60}$$

Eliminating I_2 then yields

$$I = \sqrt{\pi b} \, \Im\left[\exp\left(2i\sqrt{\frac{a}{b}}\right)\left(\text{erf}\left(\frac{\sqrt{a}}{\sqrt{t}} + i\frac{\sqrt{t}}{\sqrt{b}}\right) - 1\right)\right]. \tag{61}$$

Using the appropriate prefactor and the expressions for a and b, we finally obtain

$$V(t) = e^{-t/\tau_c} \frac{R_\lambda I_0 \sqrt{\hat{\tau}}}{2\sqrt{\tau}} \, \Im\left[\exp\left(i\frac{L\sqrt{\tau}}{\lambda\sqrt{\hat{\tau}}}\right)\left(\text{erf}\left(\frac{L\sqrt{\tau}}{2\lambda\sqrt{t}} + i\sqrt{\frac{t}{\hat{\tau}}}\right) - 1\right)\right]. \tag{62}$$

Here, $\Im$ represents the imaginary part of the argument. The complex argument of the error function arises due to $\tau_c < \tau$, but this equation also holds if $\tau_c > \tau$ provided that $\hat{\tau}$ is redefined as $\hat{\tau}^{-1} = \tau^{-1} - \tau_c^{-1}$.

Once more, we aim to linearise this implicit solution around the inflection point, which in this scenario is identified as $V''(t_i) = 0$. Differentiating $V(t)$ twice yields

$$V''(t) = \frac{1}{\tau_c^2}V(t) - e^{-t/\tau_c}\frac{R_\lambda I_0\sqrt{\hat{\tau}}}{2\sqrt{\tau}}\ \Im\left[P(t)\exp\left(i\frac{L\sqrt{\tau}}{\lambda\sqrt{\hat{\tau}}}\right)\exp\left(\left(\frac{L\sqrt{\tau}}{2\lambda\sqrt{t}} + i\sqrt{\frac{t}{\hat{\tau}}}\right)^2\right)\right],$$ (63)

with

$$P(t) = \frac{L^4\tau^2}{16\lambda^4 t^4} - \frac{L^2\tau}{2\lambda^2 t^3} + \frac{L^2\tau}{2\lambda^2\hat{\tau}t^2} - \frac{L^2\tau}{2\lambda^2\tau_c t^2} + \frac{1}{\hat{\tau}^2} - \frac{1}{\tau_c\hat{\tau}}.$$ (64)

Since the inflection point occurs at small t, the terms in $P(t)$ dominate the curvature of the rising phase of $V(t)$. Multiplying $P(t)$ with t^4 and carrying on terms up to quadratic order then yields the following equation for t_i:

$$\frac{L^2\tau}{4\lambda^2} - 2t_i + 2\left(\frac{1}{\hat{\tau}} - \frac{1}{\tau_c}\right)t_i^2 = 0.$$ (65)

For $\tau_c < \tau$, this then leads to

$$t_i = \frac{1}{2(\tau^{-1} - 2\tau_c^{-1})}\left(1 - \sqrt{1 - \frac{2L^2\tau}{\lambda^2}\left(\frac{1}{\tau} - \frac{2}{\tau_c}\right)}\right).$$ (66)

In the limit of $\tau_c \ll \tau$, this expression reduces to

$$t_i = \frac{\tau_c}{4}\left(\sqrt{1 + \frac{4L^2\tau}{\lambda^2\tau_c}} - 1\right).$$ (67)

Conversely, if $\tau_c > \tau$, we find

$$t_i = \frac{\tau}{2}\left(\sqrt{1 + \frac{2L^2}{\lambda^2}} - 1\right).$$ (68)

A comparison is shown in Figure 11B.

Scenario D - combination of exponentials

Scenario C involved a single exponential function to describe the time course of the channel currents. We now explore more complex time-profiles of channel currents, which can be realised by the sum over N exponential time courses with different amplitudes A_n and time constants τ_n:

$$I_{chan}(t) = I_0\sum_{n=1}^{N} A_n\exp(-(t - t_0)/\tau_n).$$ (69)

In particular, we consider current profiles of the form

$$I_{chan}(t) = I_0 C\left(1 - \exp(-t/\tau_1)\right)^N\exp(-t/\tau_2),$$ (70)

The normalising factor C ensures that the maximum value of $I_{chan}(t)$ is I_0, which can be determined experimentally. For the sodium current, we use the current density $i_{Na} = 25\text{pA}/\mu\text{m}^2$, multiplied by the surface area of the node, throughout the manuscript [50]. Eq. 70 can be recast in the form

$$I_{chan}(t) = I_0 C\sum_{n=0}^{N}\binom{N}{n}(-1)^n\exp\left(-\left(\frac{n}{\tau_1} + \frac{1}{\tau_2}\right)t\right),$$ (71)

The maximum current is reached at

$$t_{max} = \tau_1 \ln \left(N \frac{\tau_2}{\tau_1} + 1 \right), \tag{72}$$

and has the amplitude

$$I_{chan}(t_{max}) = C^{-1} = \left(\frac{N \frac{\tau_2}{\tau_1}}{N \frac{\tau_2}{\tau_1} + 1} \right)^N \left(\frac{1}{N \frac{\tau_2}{\tau_1} + 1} \right)^{\frac{\tau_1}{\tau_2}}. \tag{73}$$

To construct realistic action potentials, we include both sodium and (fast) potassium channels. The sodium gating dynamics in the Hodgkin Huxley model is governed by a term $m^3 h$, where m is the activating gating variable, and h is the inactivating gating variable. We follow [56] in assuming that the dynamics of these variables is exponential, and pose:

$$I_{chan,Na} = I_{0,Na} C_{Na,3}^{-1} \left(1 - \exp(-t/\tau_m) \right)^3 \exp(-t/\tau_h), \tag{74}$$

with

$$C_{Na,\gamma} = \left(\frac{\gamma \frac{\tau_h}{\tau_m}}{\gamma \frac{\tau_h}{\tau_m} + 1} \right)^\gamma \left(\frac{1}{\gamma \frac{\tau_h}{\tau_m} + 1} \right)^{\frac{\tau_m}{\tau_h}}, \tag{75}$$

being the normalisation constant. The parameters τ_m and τ_h represent the time scales of the activation and inactivation of the sodium ion channels. Likewise, we can define the potassium current as follows:

$$I_{chan,K} = I_{0,K} C_K^{-1} \left(1 - \exp(-t/\tau_n) \right)^4 \exp(-t/\tau_k), \tag{76}$$

with

$$C_K = \left(\frac{4 \frac{\tau_k}{\tau_n}}{4 \frac{\tau_k}{\tau_n} + 1} \right)^4 \left(\frac{1}{4 \frac{\tau_k}{\tau_n} + 1} \right)^{\frac{\tau_n}{\tau_k}}. \tag{77}$$

Here, τ_n represents the time scale of the activation of the potassium ion channels. Although there is no inactivating current for potassium in the Hodgkin-Huxley model, we define τ_k as characteristic time with which the potassium current decays. The time constants are voltage-dependent [56], but for simplicity we assume here that they remain constant throughout the formation of the action potential. The peak current $I_{0,K} = 1.875 \text{pA}/\mu\text{m}^2$ is 7.5% of $I_{0,Na}$, a ratio we derive from the sodium and potassium conductances used for myelinated axons in [57] ($\bar{g}_{Na} = 1.2 \text{S/cm}^2$ and $\bar{g}_K = 0.09 \text{S/cm}^2$).

The Hodgkin-Huxley model has been subject to continuous adaptations and modifications. Frankenhaeuser and Huxley [16] modified the term controlling the sodium dynamics to $m^2 h$ in their study, which in our framework would read

$$I_{chan,Na} = I_{0,Na} C_{Na,2}^{-1} \left(1 - \exp(-t/\tau_m) \right)^2 \exp(-t/\tau_h). \tag{78}$$

Baranauskas and Martina [17] presented data that fitted best with mh, i.e. a linear relationship with the activating gating variable. In this case, the activation current in our framework reads

$$I_{chan,Na} = I_{0,Na} C_{Na,1}^{-1} \left(1 - \exp(-t/\tau_m) \right) \exp(-t/\tau_h). \tag{79}$$

We refer to Eq 79 as the m^1-model, to Eq 78 as the m^2-model, and to Eq 74 as the m^3-model.

Throughout the manuscript we keep the time constants fixed. We set $\tau_m = 100 \mu\text{s}$, which is in accordance with data presented in [56], and $\tau_h = 200 \mu\text{s}$, which is in good

accordance with time traces presented in [50]. For the time constants of the potassium current we choose $\tau_n = 300\mu s$ and $\tau_k = 600\mu s$ to represent the slower activation.

Denoting the solution to an exponential input current with time constant τ_s by

$$\phi(t, \tau_s) = e^{-t/\tau_s} \frac{R_\lambda I_0}{2} \sqrt{\tau\hat{\tau}} \; \Im \left[\exp\left(i\frac{L\sqrt{\tau}}{\lambda\sqrt{\hat{\tau}}} \right) \left(\text{erf}\left(\frac{L\sqrt{\tau}}{2\lambda\sqrt{t}} + i\sqrt{\frac{t}{\hat{\tau}}} \right) - 1 \right) \right], \quad (80)$$

allows us to express the solution as combinations of exponential currents by

$$V(t) = \sum_{s=0}^{N} A_s\phi(t, \tau_s), \quad (81)$$

with

$$A_s = C\binom{N}{s}(-1)^s, \quad \tau_s = \left(\frac{s}{\tau_1} + \frac{1}{\tau_2} \right)^{-1}. \quad (82)$$

Once more we seek to identify the inflection point, i.e. where $V''(t) = 0$. The different time scales τ_s make it difficult to find a closed-form solution as we did for the previous scenarios. However, we find that a suitable approximation for the inflection point is

$$t_i = t_{i,cab} + t_{i,chan}, \quad (83)$$

where $t_{i,cab}$ is the inflection point of the Green's function of the cable equation in the limit of $L/\lambda \gg 1$, and $t_{i,chan}$ is the inflection point of the rising phase of the ion current. $t_{i,cab}$ can be derived from eq. 44,

$$t_{i,cab} = \frac{\sqrt{2}L\tau}{4\lambda}, \quad (84)$$

and $t_{i,chan}$ is found to be

$$t_{i,chan} = -\tau_1 \ln\left(\frac{\frac{N}{\tau_1^2} + \frac{2N}{\tau_1\tau_2} + \frac{2}{\tau_2^2}}{2\left(\frac{N}{\tau_1} + \frac{1}{\tau_2} \right)^2} \left(1 - \sqrt{1 - \frac{\frac{4}{\tau_2^2}\left(\frac{N}{\tau_1} + \frac{1}{\tau_2} \right)^2}{\left(\frac{N}{\tau_1^2} + \frac{2N}{\tau_1\tau_2} + \frac{2}{\tau_2^2} \right)^2}} \right) \right), \quad (85)$$

with N, τ_1, and τ_2 as in eq. 70.

Influence of distant nodes

Action potentials are driven by the ionic currents generated at multiple nodes along the axon. Due to the linear nature of the cable equation, the effect of multiple input currents can be described by linear superposition:

$$V(t) = \sum_{n=1}^{N} \phi(t + nt_{sp}, nL). \quad (86)$$

where ϕ is the r.h.s. of the respective scenario considered, i.e. $\phi(t, L)$ describes the depolarisation due to the current at a neighbouring node. To keep with our previous definition, time is defined by setting $t = 0$ when the neighbouring node depolarises. The relationship between the firing threshold V_{thr} and the time-to-spike t_{sp} is therefore given by

$$V_{thr} = \sum_{n=1}^{N} \phi(nt_{sp}, nL). \quad (87)$$

The effect of distant nodes is dampened by the fact that in addition to passing along myelinated segments, currents from distant sources also pass by unmyelinated nodes, and thereby further lose amplitude. If the nodes are relatively short, the current outflux can be regarded as instantaneous across the node as compared to changes in the current. The physical distance between two neighbouring nodes is then $L + l$, and the electrotonic distance is $L + (\lambda/\lambda_n)l$ in units of λ. This leads to the updated equation for the membrane potential,

$$V(t) = \sum_{n=1}^{N} \phi(t + nt_{sp}, n(L + (\lambda/\lambda_n)l)). \tag{88}$$

The velocity of the action potential is then given by $v = (L + l)/t_{sp}$.

This framework allows us to describe unmyelinated axons as well. Since the internode length is zero in this case, the node length l is now an arbitrary discretisation of the axon. The membrane potential is now described by

$$V(t) = \sum_{n=1}^{N} \phi(t + nt_{sp}, nl), \tag{89}$$

where the length constant λ in ϕ needs to be replaced by a length constant $\tilde{\lambda}$ that characterises the electrotonic length of the unmyelinated axon. We introduce a parameter ρ that describes the channel density of the unmyelinated axon relative to the channel density of a node of Ranvier. We assume that the conductivity of the axonal membrane scales linearly with the channel density, which implies that the electrotonic length constant of an unmyelinated axon is $\tilde{\lambda} = \lambda_n/\sqrt{\rho}$. Reducing the channel density therefore reduces the current that enters the axon, but currents travel further in the axon due to the increased membrane resistance. The velocity of an action potential is now defined as $v = l/t_{sp}$.

In addition to the correction terms introduced in eq (88), we also investigate delays that occur at the nodes due to finite transmission speeds. We assume that action potentials travel with velocities v determined by eq (88) along myelinated segments, and with velocities v_n inferred from eq (89) at nodes. The corrected velocity is then given by

$$v_{corr} = \frac{L + l}{\frac{L}{v} + \frac{l}{v_n}}. \tag{90}$$

It is no longer straightforward to linearise eq (88). However, we find that a reasonably good approximation can be given by linearising ϕ, i.e. by linearising the depolarisations caused by single currents separately, and then adding them up:

$$V(t) = \sum_{n=1}^{N} \left(\phi(t_{i,n}, nL) + (t + nt_{sp} - t_{i,n})\phi'(t_{i,n}, nL) \right). \tag{91}$$

Ephaptic coupling and entrainment

Here we explain how to solve Eq (17) with non-zero extra-cellular potential. The potential between intra-cellular medium and extra-cellular medium as $U_n = V_n - V_e$, which determines the channel dynamics. It follows from the electric decoupling of the fibre bundle from the external medium that the sum of longitudinal currents within the fibre bundle is zero [30]:

$$R_{ex}^{-1} \frac{\partial^2 V_e}{\partial x^2} + \sum_n R_{ax,n}^{-1} \frac{\partial^2 V_n}{\partial x^2} = 0. \tag{92}$$

R_{ex} denotes the axial resistance of the extra-cellular medium, which depends inversely on its cross-sectional area. As a result, we obtain the cable equation in terms of U_n:

$$\tau \dot{U}_n + U_n - \lambda_n^2 \frac{\partial^2 U_n}{\partial x^2} + R_m I_n^{ion}(t) + \alpha \lambda_n^2 \sum_p R_{ax,p}^{-1} \frac{\partial^2 U_p}{\partial x^2} = 0, \tag{93}$$

where α is the coupling parameter:

$$\alpha = \frac{1}{R_{ex}^{-1} + \sum_p R_{ax,p}^{-1}}. \tag{94}$$

This is a general result, but in the following we focus on two fibres.

Since these equations are linear, they can be decoupled (using orthogonalisation) into

$$\tau \frac{\partial \tilde{U}_{1,2}}{\partial t} = \tilde{\lambda}_{1,2}^2 \frac{\partial^2 \tilde{U}_{1,2}}{\partial x^2} - \tilde{U}_{1,2} + \tilde{I}_{1,2}^{ion}(t), \tag{95}$$

with $\tilde{U}_{1,2} = U_1 + c_{1,2}U_2$, $\tilde{I}_{1,2}^{ion} = I_1^{ion} + c_{1,2}I_2^{ion}$, and $\tilde{\lambda}_{1,2} = \lambda_1^2(R_{ax,1}^{-1} + 1) + c_{1,2}\lambda_2^2 R_{ax,1}^{-1}$, where

$$c_{1,2} = -\frac{\lambda_1^2(R_{ax,1}^{-1} + 1) - \lambda_2^2(R_{ax,2}^{-1} + 1)}{2\lambda_2^2 R_{ax,1}^{-1}} \tag{96}$$

$$\pm \sqrt{\left(\frac{\lambda_1^2(R_{ax,1}^{-1} + 1) - \lambda_2^2(R_{ax,2}^{-1} + 1)}{2\lambda_2^2 R_{ax,1}^{-1}}\right) + 1}. \tag{97}$$

In the case of identical axons, this expression simplifies to $c_{1,2} = \pm 1$. These equations can be solved as above, and the solutions of the coupled equations can be recovered using $U_2 = (\tilde{U}_1 - \tilde{U}_2)/(c_1 - c_2)$ and $U_1 = -(c_2\tilde{U}_1 - c_1\tilde{U}_2)/(c_1 - c_2)$.

Acknowledgments

HS was supported by the German Research Foundation (DFG Priority Program 2041 'Computational Connectomics', awarded to TRK)

References

1. W.A.H. Rushton. A theory of the effects of fibre size in medullated nerve. *Journal of Physiology*, 115:101–122, 1951.

2. A.M. Castelfranco and D.K. Hartline. Evolution of rapid nerve conduction. *Brain Research*, 1641:11–33, 2016.

3. I. Tasaki. The electro-saltatory transmission of the nerve impulse and the effect of narcosis upon the nerve fiber. *American Journal of Physiology*, 127:211–227, 1939.

4. R.D. Fields. A new mechanism of nervous system plasticity: activity-dependent myelination. *Nature Reviews Neuroscience*, 1641:756–767, 2015.

5. A.H. Seidl. Regulation of Conduction Time along Axons. *Neuroscience*, 276:126–134, 2014.

6. P.A. Valdés-Hernández, A. Ojeda-Gonzaléz, E. Martínez-Montes, A. Lage-Castellanos, T. Virués-Alba, L. Valdés-Urrutia, and P.A. Valdes-Sosa. White matter architecture rather than cortical surface area correlates with the EEG alpha rhythm. *NeuroImage*, 49:2328–2339, 2010.

7. E.R. Arbuthnott, I.A. Boyd, and K.U. Kalu. Ultrastructural dimensions of myelinated peripheral nerve fibres in the cat and their relation to conduction velocity. *Journal of Physiology*, 308:125–157, 1980.

8. D. Liewald, R. Miller, N. Logothetis, H.-J. Wagner, and A. Schüz. Distribution of axon diameters in cortical white matter: an electron-microscopic study on three human brains and a macaque. *Biological Cybernetics*, 108:541–557, 2014.

9. Y. Assaf and P.J. Basser. Composite hindered and restricted model of diffusion (CHARMED) MR imaging of the human brain. *NeuroImage*, 27:48–58, 2005.

10. Y. Assaf, T. Blumenfeld-Katzir, Y. Yovel, and P.J. Basser. AxCaliber: A Method for Measuring Axon Diameter Distribution from Diffusion MRI. *Magnetic Resonance in Medicine*, 59:1347–1354, 2008.

11. D. Nunes, T.L. Cruz, S.N. Jespersen, and N. Shemesh. Mapping axonal density and average diameter using non-monotonic time-dependent gradient-echo MRI. *Journal of Magnetic Resonance*, 277:117–130, 2017.

12. D.A. Raffelt, J.-D. Tournier, R.E. Smith, D.N. Vaughan, G. Jackson, G.R. Ridgway, and A. Connelly. Investigating white matter fibre density and morphology using fixel-based analysis. *NeuroImage*, 144:58–73, 2017.

13. S. Mohammadi, D. Carey, F. Dick, J. Diedrichsen, M.I. Sereno, M. Reisert, M.F. Callaghan, and N. Weiskopf. Whole-Brain In-vivo Measurements of the Axonal G-Ratio in a Group of 37 Healthy Volunteers. *Frontiers in Neuroscience*, 9:441, 2015.

14. J.B. Hursh. Conduction velocity and diameter of nerve fibers. *American Journal of Physiology*, 127:131–139, 1939.

15. A.L. Hodgkin and A.F. Huxley. A quantitative description of membrane current and its application to conduction and excitation in nerve. *Journal of Physiology*, 117:500–544, 1952.

16. B. Frankenhaeuser and A.F. Huxley. The action potential in the myelinated nerve fibre of Xenopus Laevis as computed on the basis of voltage clamp data. *Journal of Physiology*, 171:302–315, 1964.

17. G. Baranauskas and M. Martina. Sodium Currents Activate without a Hodgkin and Huxley- Type Delay in Central Mammalian Neurons. *The Journal of Neuroscience*, 26:671–684, 2006.

18. M. Pospischil, M. Toledo-Rodriguez, C. Monier, Z. Piwkowska, T. Bal, Y. Frégnac, H. Markram, and A. Destexhe. Minimal Hodgkin–Huxley type models for different classes of cortical and thalamic neurons. *Biological Cybernetics*, 99:427–441, 2008.

19. R. FitzHugh. Computation of impulse initiation and saltatory conduction in a myelinated nerve fibre. *Biophysical Journal*, 26:11–21, 1962.

20. L. Goldman and J.S. Albus. Computation of impulse conduction in myelinated fibers; theoretical basis of the velocity-diameter relation. *Biophysical Journal*, 8:596–607, 1968.

21. N. Snaidero and M. Simons. Myelination at a glance. *Journal of Cell Science*, 127:2999–3004, 2014.

22. A.G. Richardson, C.C. McIntyre, and W.M. Grill. Modelling the effects of electric fields on nerve fibres: influence of the myelin sheath. *Medical & Biological Engineering & Computing*, 38:438–446, 2000.

23. I.L. Arancibia-Carcamo, M.C. Ford, L. Cossell, K. Ishida, K. Tohyama, and D. Atwell. Node of Ranvier length as a potential regulator of myelinated axon conduction speed. *eLife*, 6:e23329, 2017.

24. C.F. Babbs and R. Shi. Subtle Paranodal Injury Slows Impulse Conduction in a Mathematical Model of Myelinated Axons. *PLOS One*, 8:e67767, 2013.

25. M.H. Adhikari, J.K. McIver, and E.A. Coutsias. Delay-induced destabilization of entrainment of nerve impulses on ephaptically coupled nerve fibers. *Physical Review E*, 79:011910, 2009.

26. R.G. Barr and R. Plonsey. Electrophysiological interaction through the interstitial space between adjacent unmyelinated fibers. *Biophysical Journal*, 61:1164–1175, 1992.

27. J.C. Eilbeck, S.D. Luzader, and A.C. Scott. Pulse evolution on coupled nerve fibres. *Bulletin of Mathematical Biology*, 43:389–400, 1981.

28. J.H. Goldwyn and J. Rinzel. Neuronal coupling by endogenous electric fields: cable theory and applications to coincidence detector neurons in the auditory brain stem. *Journal of Neurophysiology*, 115:2033–2051, 2016.

29. I. Maïna, C.B. Tabi, H.P. Ekobena Fouda, A Mohamadou, and T.C. Kofané. Discrete impulses in ephaptically coupled nerve fibers. *Chaos*, 25:043118, 2015.

30. S. Reutskiy, E. Rossoni, and B. Tirozzi. Conduction in bundles of demyelinated nerve fibers: computer simulation. *Biological Cybernetics*, 89:439–448, 2003.

31. S. Binczak, J.C. Eilbeck, and A.C. Scott. Ephaptic coupling of myelinated nerve fibers. *Physica D*, 148:159–174, 2001.

32. M.N. Shneider and M. Pekker. Correlation of action potentials in adjacent neurons. *Physical Biology*, 12:066009, 2015.

33. N. Iannella and S. Tanaka. Analytical solutions for nonlinear cable equations with calcium dynamics. I. Derivations. *Journal of Integrative Neuroscience*, 59:249–272, 2006.

34. R. Naud and A. Longtin. Spike-Diffuse-Spike Modelling of Axonal Propagation Links Demyelination to Compound Action Potential Dispersion. *bioarxiv*, 501379.

35. R.R. Poznanski Analytical solutions of the Frankenhaeuser-Huxley equations. I. Minimal model for backpropagation of action potentials in sparsely excitable dendrites. *Journal of Integrative Neuroscience*, 3:267 – 299, 2004.

36. J.T. Rubinstein. Analytical theory for extracellular electrical stimulation of nerve with focal electrodes. *Biophysical Journal*, 60:538–555, 1991.

37. P.C. Bressloff and S. Coombes. Solitary Waves in a Model of Dendritic Cable with Active Spines. *SIAM J. Appl. Math.*, 61:432–453, 2003.

38. G.J. Lord and S. Coombes. Traveling waves in the Baer and Rinzel model of spine studded dendritic tissue. *Physica D*, 161:1–20, 2002.

39. J. Tabak, M. Tomaiuolo, A.E. Gonzalez-Iglesias, L.S. Milescu, and R. Bertram. Fast activating voltage- and calcium-dependent potassium (BK) conductance promotes bursting in pituitary cells: a dynamic clamp study. *Journal of Neuoscience*, 31:16855–16863, 2011.

40. W.E. Crill and P.C. Schwindt. Active currents in mammalian central neurons. *Trends in Neurosciences*, 6:236–240, 1983.

41. R.R. Llinás. The Intrinsic Electrophysiological Properties of Mammalian Neurons: Insights into Central Nervous System Function. *Science*, 242:1654–1664.

42. D. Csercsik, I. Farkas, G. Szederkényi, E. Hrabovszky, Z. Liposits, and K.M. Hangos. Hodgkin–Huxley type modelling and parameter estimation of GnRH neurons. *BioSystems*, 100:198–207, 2010.

43. R. FitzHugh. Mathematical Models of Threshold Phenomena in the Nerve Membrane. *Bulletin of Mathematical Biophysics*, 17:257–278, 1955.

44. R. FitzHugh. Impulses and physiological states in theoretical models of nerve membrane. *Biophysical Journal*, 1:445–466, 1961.

45. J. Nagumo, S. Arimoto, and S. Yoshizawa. An Active Pulse Transmission Line Simulating Nerve Axon. *Proceedings of the IRE*, 50:2061–2070, 1962.

46. C. Morris and H. Lecar. Voltage oscillations in the barnacle giant muscle fiber. *Biophysical Journal*, 35:193–213, 1981.

47. A.N. Burkitt. A review of the integrate-and-fire neuron model: I. Homogeneous synaptic input. *Biol. Cybern.*, 95:1–19, 2006.

48. R. Jolivet, T.J. Lewis, and W. Gerstner. Generalized integrate-and-fire models of neuronal activity approximate spike trains of a detailed model to a high degree of accuracy. *J. Neurophysiol.*, 92:959–976, 2004.

49. S.Y. Chiu, J.M. Ritchie, R.B. Rogart, and D. Stagg. A quantitative description of membrane currents in rabbit myelinated nerve. *Journal of Physiology*, 292:149–166, 1979.

50. W. Hu, C. Tian, T. Li, M. Yang, H. Hou, and Y. Shu. Distinct contributions of Na_v 1.6 and Na_v 1.2 in action potential initiation and backpropagation. *Nature Neuroscience*, 12:996–1002, 2009.

51. E.M. Gibson, D. Purger, C.W. Mount, A.K. Goldstein, G.L. Lin, L.S. Wood, I. Inema, S.E. Miller, G. Bieri, J.B. Zuchero, B.A. Barres, P.J. Woo, H. Vogel, and M. Monje. Neuronal Activity Promotes Oligodendrogenesis and Adaptive Myelination in the Mammalian Brain. *Science*, 344:1252304, 2014.

52. B. Katz and O.H. Schmitt. Electric interaction between two adjacent nerve fibres. *J. Physiol.*, 97:471–488, 1940.

53. I. Tasaki. New Measurements of the Capacity and the Resistance of the Myelin Sheath and the Nodal Membrane of the Isolated Frog Nerve Fiber. *American Journal of Physiology*, 181:639–650, 1955.

54. L.J. Gentet, G.J. Stuart, and J.D. Clements. Direct Measurement of Specific Membrane Capacitance in Neurons. *Biophysical Journal*, 79:314–320, 2000.

55. S.A. Freeman, A. Desmazières, D. Fricker, C. Lubetzki, and N. Sol-Foulon. Mechanisms of sodium channel clustering and its influence on axonal impulse conduction. *Cell. Mol. Life Sci.*, 73:723–735, 2016.

56. J.R. Schwarz, G. Reid, and H. Bostock. Action potentials and membrane currents in the human node of Ranvier. *Pflügers Arch - Eur J Physiol*, 430:283–292, 1995.

57. S.G. Waxman and M.H. Brill. Conduction through demyelinated plaques in multiple sclerosis: computer simulations of facilitation by short internodes. *Journal of Neurology*, 41:408 – 416, 1978.