Tunable genetic devices through simultaneous control of transcription and translation

Vittorio Bartoli[1,2], Grace A. Meaker[3], Mario di Bernardo[1,2,4] and Thomas E. Gorochowski[1,5,*]

[1] BrisSynBio, University of Bristol, Life Sciences Building, Tyndall Avenue, Bristol, UK

[2] Department of Engineering Mathematics, University of Bristol, Woodland Road, Bristol, UK

[3] School of Biosciences, Cardiff University, Museum Avenue, Cardiff, UK

[4] Department of Electrical Engineering and Information Technology, University of Naples Federico II, Via Claudio 21, Napoli, Italy

[5] School of Biological Sciences, University of Bristol, Bristol, Tyndall Avenue, UK

[*] Correspondence should be addressed to T.E.G. (thomas.gorochowski@bristol.ac.uk)

Keywords: gene regulation; genetic circuits; transcription; translation; toehold switch; synthetic biology; systems biology.

Abstract

Synthetic genetic circuits allow us to modify the behavior of living cells. However, changes in environmental conditions and unforeseen interactions between a circuit and the host cell can cause deviations from a desired function, resulting in the need for time-consuming physical re-assembly to fix these issues. Here, we use a regulatory motif that controls transcription and translation to create genetic devices whose response functions can be dynamically tuned. This approach allows us, after construction, to shift the 'on' and 'off' states of a sensor by 4.5- and 28-fold, respectively, and modify genetic NOT and NOR logic gates to allow their transitions from an 'on' to 'off' state to be varied over a >6-fold range. In all cases, tuning leads to trade-offs in the fold-change and separation between the distributions of cells in 'on' and 'off' states. By using mathematical modelling, we derive design principles that help to further optimize the performance of these devices. This work lays the foundation for adaptive genetic circuits that can be tuned after their physical assembly to maintain functionality across diverse environments and design contexts.

Introduction

Gene regulatory networks, or genetic circuits as they are often known, govern when and where genes are expressed in cells and control core biochemical processes like transcription and translation [1,2]. The ability to synthesize DNA encoding engineered genetic circuits offers a means to expand the capabilities of a cell and reprogram its behavior [1,3]. Synthetic genetic circuits have been built to implement computational operations [4–12], dynamic behaviors like oscillations [13–15], and even coordinate multicellular actions across a population [16–20].

The ability to reprogram living cells is simplified by using genetically encoded devices that use common input and output signals [1,2,7,9]. This allows the output of one device to be directly connected to the input of another to create circuits implementing more complex functionalities. Signals can take many forms, but one of the most commonly used is RNA polymerase (RNAP) flux in which promoters are used to guide this signal to specific points in a circuit's DNA [7,21]. Based on such input and output signals, the response function of a genetic device captures how inputs map to outputs at steady state [1,7,21]. By ensuring the response functions of two devices are compatible, i.e. they are "matched" such that the range of the output of the first device spans the necessary range of inputs for the second device, larger circuits with desired functions can be constructed [22]. Matching of components is vital in circuits where devices exhibit switching behaviors (e.g. for Boolean logic) to ensure input signals are sufficiently separated to accurately trigger required transitions between 'on' and 'off' states as signals propagate through the circuit.

Although the use of characterized genetic devices has enabled the automated design of large genetic circuits [7,23], the response functions of these devices are often sensitive to many factors. For example, differences in host physiology due to culturing conditions [24–26] and interactions between genetic parts and the host cell [27–32], can all affect the response function of a device and subsequently its compatibility within a circuit. This makes the creation of reliable and robust genetic circuits a challenge. Even when considering carefully controlled conditions, like those in the lab, a genetic circuit often needs to be reassembled from scratch multiple times using alternative parts until a working combination is found. This is both time consuming and expensive, and often has to be repeated if the circuit is to be deployed in slightly different conditions or host strains.

In this work, we tackle this problem by developing genetic devices whose response functions can be dynamically tuned after physical assembly to correct for unwanted changes in their behavior. The ability to tune/modify the steady state input-output relationship is made possible by employing a simple regulatory motif. We show how this motif can be connected to small molecule sensors to characterize its function and then illustrate how it can be used in practice by integrating it into genetic NOT and NOR logic gates [33] to allow for the tuning of the

transition point between 'on' and 'off' states. These capabilities make these devices more broadly compatible with other components [1,7,22], but their use comes at a cost because of trade-offs in their performance. As we tune the devices, a decrease in the dynamic range is observed and the ability to differentiate 'on' and 'off' states due to variability in gene expression across a population. We use mathematical modelling to better understand these limitations and derive design principles that are then used to further optimize their design. This work is a step towards genetic circuitry whose individual components can functionally adapt, ensuring robust system-level behaviors are maintained no matter the genetic, cellular or environmental context.

Results

Controlling transcription and translation using a tunable expression system

To allow for the response of a genetic device to be modulated, we developed a tunable expression system (TES) based on a simple regulatory motif where two separate promoters control the transcription and translation rates of a gene of interest (**Figure 1a**). By using promoters as inputs, it is possible to easily connect a TES to existing genetic components/circuitry or even endogenous transcriptional signals within a cell. The TES consists of a toehold switch (THS) that enables the translation initiation rate of the gene of interest to be varied by the relative concentration of a "tuner" small RNA (sRNA) [6,34]. The main component of the THS is a 92 bp DNA sequence that encodes a structural region and a ribosome binding site (RBS) used to drive translation of a downstream protein coding region. This is expressed from a promoter that acts as the main input to the TES (**Figure 1a**). When transcribed, the structural region of the THS mRNA folds to form a hairpin loop secondary structure that makes the RBS less accessible to ribosomes and thus reduces its translation initiation rate. This structure is disrupted by a second component, a 65 nt tuner sRNA that is complementary to the first 30 nt of the THS [34]. The tuner sRNA is expressed from a second promoter, which acts as a tuner input to the device (**Figure 1a**). Complementarity between the tuner sRNA and a short unstructured region of the toehold switch enables initial binding, which then makes it thermodynamically favorable for the sRNA to unfold the secondary structure of the THS through a branch migration process. This makes the RBS more accessible to ribosomes which increases the translation initiation rate. Relative concentrations of the THS mRNA and tuner sRNA (controlled by the input and tuner promoters) enable the rate of translation initiation to be potentially varied over a 100-fold range for the toehold switch design we selected for our own [34] (**Materials and Methods**). However, THS designs exist which allow for up to a 400-fold change in translation initiation rates [6,34].

We selected as main and tuner inputs for the TES the output promoters of two sensors, P_{tet} and P_{tac}, that respond to anhydrotetracycline (aTc) and isopropyl β-D-1-thiogalactopyranoside (IPTG), respectively (**Figure 1b**). This allows us to dynamically tune transcription and translation rates of a gene to modify the overall rate of protein production. Each sensor consists of a transcription factor (TetR and LacI sensitive to aTc and IPTG, respectively) that represses its cognate promoter until an associated small molecule is present (**Figure 1b**). The small molecules bind their cognate transcription factor, altering its conformation and limiting its ability to repress the promoter, thereby turning on transcription of the downstream gene. Yellow fluorescent protein (YFP) was used as the output from the TES (**Figure 1b**) to allow us to measure the rate of protein production in single cells using flow cytometry.

Characterization of the device was performed in *Escherichia coli* cells grown in different concentrations of aTc (input) and IPTG (tuner). Steady state fluorescence measurements of single cells in exponential growth phase were taken using flow cytometry and promoter activities of both the main and tuner input were measured in relative promoter units (RPUs) to allow for direct comparisons (**Materials and Methods**; **Supplementary Figure S1**). A further advantage of characterizing our devices in RPUs is that this data can be immediately used within genetic design automation software like Cello [7], allowing our parts to be interfaced with a large library of existing sensors and logic gates[33,35].

For a fixed tuner promoter activity, we observed a sigmoidal increase in output YFP fluorescence as the input promoter activity increased from 0.002 to 6.6 RPU (**Figure 1c**). As the activity of the tuner promoter increased from 0.002 to 2.6 RPU, the entire response function shifted upwards to higher output YFP fluorescence levels. Notably, this shift was not uniform, with larger relative increases seen for lower input promoter activities; 28-fold versus 4.5-fold for inputs of 0.002 and 6.6 RPU, respectively (**Figure 1c**). Closer analysis of the flow cytometry data (**Figure 1d**), showed that these changes arose from the distributions of output YFP fluorescence for low and high inputs shifting uniformly together as the tuner promoter activity was increased. Therefore, even though a similar relative difference between outputs for low and high inputs (also referred to as the dynamic range) was observed for all tuner inputs, when the tuner input is low, the distributions are virtually identical to the autofluorescence of the cells (**Figure 1d**). This leads to even small absolute differences in the median values between low and high input states resulting in high fold-changes.

Flow cytometry data also showed a significant overlap in the output YFP fluorescence distributions for low and high input promoter activities (**Figure 1d**). Many applications require that 'on' and 'off' states in a system are well separated so that each can be accurately distinguished (e.g. for Boolean logic). To assess this separation in the TES, we calculated the fractional overlap between the output YFP fluorescence distributions for low and high input

promoter activities (**Materials and Methods**). We found a constant intersection of ~70% across all tuner promoter activity levels (**Figure 1e**), which resulted from the similar shifts we see in output across all input promoter activities (**Figure 1d**).

To better understand these effects, we derived a deterministic ordinary differential equation (ODE) model of the system (**Supplementary Text S1**). Simulations of this model for biologically realistic parameters (**Supplementary Table S1**) showed similar qualitative behavior to the experiments; increasing tuner promoter activity shifted the response curve to higher output protein production rates (**Figure 1f**). However, unlike the experiments, increases in the tuner promoter activity resulted in a small increase in the fold-change in the output between low and high inputs (**Figure 1g**, bottom). The limiting effect that the tuner sRNA can have is a possible mechanism that could account for the non-linear response observed in the experiments, whereby 'on' states do not increase as quickly as 'off' states as the tuner activity increases (**Figure 1g**, top). Because the tuner sRNA concentration is fixed for each response function, its concentration could be higher than the concentration of THS transcript when the main input is low, while also being much lower when the main input is high. This would cause the rate of protein production to be limited by the THS transcript concentration at low inputs, and by the tuner sRNA concentration at high inputs.

Another potential cause of this non-linear response could be retroactivity that occurs when the behavior of components in a biological circuit change once interconnected [36,37]. Such effects break modularity in the system and can make it difficult to predict the behavior of larger complex circuits. To explore this aspect further, we coupled our existing model to another that is able to capture retroactivity-like effects due to shifts in ribosome allocation between endogenous genes and synthetic constructs, such as the TES (**Supplementary Text S2**) [28,36,37]. Ribosomes are a key cellular resource and fluctuations in their availability due to the additional burden of a synthetic construct can cause drops in protein synthesis rates across the cell, affecting upstream components in a circuit [25,27,29,32]. Comparisons between the original models and this coupling variant, showed that retroactivity did have an effect for biologically realistic parameters, but only when the output caused a significant burden on the cell and only for the most highly expressed outputs, i.e., when both the input and tuner promoter activities were high (**Supplementary Figure S2**).

Design and assembly of a tunable genetic NOT gate

Some genetic devices rely on the expression of proteins such as transcription factors to implement basic logic functions that can be composed to carry out more complex decision-making tasks [4,7,8]. One such commonly used device is a NOT gate, which has a single input and output [33]. The function of this gate is to "invert" the input such that the output is high if the input is low and vice versa. Such a behavior can be implemented by using promoters as the

input and output, with the input promoter driving expression of a repressor protein that binds

to the DNA of the constitutive output promoter. When the input promoter is inactive, the

repressor is not synthesized and so the constitutive output promoter is active. However, once

the input promoter is activated, the repressor is expressed which binds the output promoter

and represses its activity.

Because the activity range of promoters varies, the transition point, whereby sufficient

concentrations of repressor are present to cause strong repression of the output promoter,

may make it impossible to connect other devices and ensure a signal is correctly propagated.

For example, the output promoter of a weak sensor system acting as input to a NOT gate with

a high transition point may produce insufficient repressor, causing the output promoter to be

continually active. These incompatibilities can sometimes be corrected for by modifying other

regulatory elements in the design. In the case of a repressor-based NOT gate, while the

promoters cannot be easily changed, in bacteria the translation initiation rate can be varied by

altering the ribosome binding site (RBS) for the repressor gene. Increasing the RBS strength

causes more repressor protein to be produced for the same input promoter activity, shifting

the transition point to a lower value [7,33]. While such modifications can fix issues with device

compatibility, they require reassembly of the entire genetic device.

Given that the TES allows for the rates of both transcription and translation to be

dynamically controlled, we attempted to create a proof-of-concept "tunable" NOT gate that

integrated the TES to allow its response function, and crucially the transition point, to be

altered after physical assembly. We chose an existing NOT gate design [33] that uses the PhlF

repressor to control the activity of an output P_{phlF} promoter (**Figure 2a**). Expression of PhlF

was controlled by the TES (replacing the YFP reporter protein in the original TES design;

Figure 1a). Unlike the TES, the tunable NOT gate uses promoters for both inputs and outputs

allowing it to be easily connected to other devices that use RNAP flux as an input/output signal

[7,21] (**Figure 2a**).

To enable characterization of the tunable NOT gate, the output promoter P_{phlF} was

used to drive expression of YFP. Measurements were taken using flow cytometry for cells

harboring the device in varying concentrations of aTc and IPTG, and steady state response

functions were generated (**Figures 2b** and **2c**). As expected, these displayed a negative

sigmoidal shape with transition points (*K* values from the Hill function fits to the experimental

data) that varied over a 7-fold range (**Figure 2b**). We also found that increases in the tuner

promoter activity lead to transitions at lower activity levels for the input promoter. The range

of transition points achieved by our device also covered a high proportion (35%) of the largest

collection of repressor-based NOT gates built to date (total of 20 variants; **Figure 2d**) [7].

These results demonstrate the ability of the proposed TES component to dynamically

alter a key characteristic of a NOT gate's response function (specifically the transition point)

to improve its compatibility with other genetic devices. However, it came at a cost; tuning resulted in a drop in the fold-change between low and high outputs (**Figure 2e**) and an increase in the overlap of the output YFP fluorescence distributions, which made high and low states difficult to distinguish (**Figure 2f**).

Boosting sRNA levels improves the performance of the tunable genetic devices

For the THS to function correctly, it is essential that the sRNA reaches a sufficiently high concentration relative to the THS transcript to ensure the associated RBS is in a predominantly exposed state [34]. In our design, the tuner promoter P_{tac} has less than half the maximum strength of the main input promoter P_{tet} (**Supplementary Figure S1**). Furthermore, although the tuner sRNA contains a hairpin to improve its stability, sRNAs are generally more quickly turned over than normal transcripts [38,39], yielding much lower steady state concentrations compared to the THS transcript.

To better understand the role that the THS transcript to tuner sRNA ratio had on the performance of the TES, we used our mathematical model of the system (**Supplementary Text S1**) to explore how various key parameters (e.g. transcription rates and binding affinities) affected the response function of the device. Using biologically realistic ranges of parameters (**Supplementary Table S1**), we found that for lower sRNA transcription rates the output response function could be shifted maintaining a similar fold-change between low and high output states (**Figure 3a**). At these low THS/sRNA ratios the translation rate from the THS transcript is limited by the sRNA concentration. However, as the sRNA transcription rate increased a transition point was seen (i.e. between green and blue shared curves in **Figure 3a**) whereby for low THS transcription rates the sRNAs are in excess making the output protein production rate limited by the THS transcript concentration (**Figure 3a**). In contrast, at high THS transcription rates the sRNAs become limiting again but allow for relatively much higher output protein production rates that enable a larger fold-change in the response function of the TES (**Figure 3a**). Further stochastic modelling of the system showed that increased sRNA transcription rates also reduced variability in the distribution of protein production rates across a population and lowered the fractional intersection between low and high output states (**Figure 3b**).

To experimentally verify the benefit of increasing the sRNA transcription rate, we built a complementary sRNA booster plasmid that contained a high-copy pColE1 origin of replication (50–70 copies per cell) [40] and expressed the tuner sRNA from a strong viral P_{T7} promoter (**Figure 3c**) [41]. Transcription from P_{T7} requires T7 RNA polymerase (T7RNAP). This is provided by our host strain *E. coli* BL21 Star (DE3), which has the *T7RNAP* gene under the control of an IPTG inducible P_{lacUV5} promoter within its genome (**Figure 3c**) [42]. Using IPTG, induction of the tuner P_{tac} promoter in our devices using IPTG leads to simultaneous

expression of T7 RNAP from the host genome and transcription of additional tuner sRNA from the booster plasmid (**Figure 3c**). As the tunable devices are encoded on a plasmid with a p15A origin of replication (~15 copies per cell; **Supplementary Figure S3**) [43], we would expect at least five times higher tuner sRNA concentrations are reached when the sRNA booster is present.

Cells were co-transformed with each tunable genetic device and sRNA booster plasmid, and their response functions were measured (**Figures 3D** and **3E**). As predicted by the modelling, the TES displayed improved performance with a more than doubling in the fold-change across all tuner promoter activities and a >40% drop in the intersection between low and high output YFP fluorescence distributions (**Table 1**). For the tunable NOT gate only minor differences in performance were seen with mostly small decreases in fold-change for high tuner promoter activities.

Self-cleaving ribozyme insulators impact toehold switch function

In our initial designs, a RiboJ self-cleaving ribozyme was included in the TES and NOT gate to insulate the translation of the *yfp* or *phlF* genes, respectively, from different 5' untranslated region (UTR) sequences that might be generated when using different promoters as an input (**Figures 1a, 2a**) [44]. Any variable UTR sequences would be cleaved at the RiboJ site to produce a standardized mRNA with more consistent rates of mRNA degradation and translation. Unfortunately, because RiboJ contains a number of strong secondary RNA structures [44,45], it is possible that the 23 nt hairpin at the 3'-end impacts the ability for the sRNA to interact with the THS, reducing the hybridization rate (**Figure 4a**).

To assess whether the RiboJ insulator might affect the stability of secondary structures that are crucial to the TES's function, we performed thermodynamic modelling of the binding between the toehold switch region of the mRNA and the tuner sRNA for variants of the TES design with and without RiboJ present (**Materials and Methods**). Simulations showed a 40% drop in predicted Gibbs free energy of the reactants when RiboJ was removed (−40.5 kcal/mol with versus −65 kcal/mol without RiboJ; **Figure 4b**). This suggests that binding between sRNAs and the THS may be hampered by interactions with the RiboJ insulator, lowering the effective translation initiation rate of the RBS controlled by the toehold switch and subsequently the overall performance of the devices.

To experimentally test these predictions, non-insulated variants of the TES and tunable NOT gate were constructed in which RiboJ was removed. Characterization of these devices showed major improvements in overall performance (**Figures 4c** and **4d**). The TES saw more than a doubling in the dynamic range and 10-fold increase in the fold-change between 'on' and 'off' states across low and high tuner activity levels compared to the original design (**Table 1**). In addition, the fraction of intersection of the output YFP fluorescence distributions dropped

by >50%. The tunable NOT gate saw more modest improvements with a 73% increase in the fold-change at high tuner activity levels, but an overall drop of 66% in the range of transition points (K values) that could be achieved (**Table 1**). These results highlight an important consideration often ignored. When using RNA-based devices that require proper formation of secondary structures, care must be taken in looking at how multiple devices relying on mRNA folding to function could interfere with each other, leading to cryptic failure modes.

Another counterintuitive change in the TES's response function after RiboJ removal was the large drop in output YFP fluorescence from 26 to 3 arbitrary units (a.u.) when no input or tuner was present (**Figure 4c**). Similar drops of between 4- and 11-fold were also seen for higher tuner promoter activities. Given that binding of a tuner sRNA to the THS mRNA should be less hampered when RiboJ is absent, an increase not decrease in output protein production would be expected. A possible explanation is that the stability of the THS mRNA decreased after RiboJ was removed. This is supported by recent results that have shown the RiboJ insulator both stabilizes its mRNA and also boosts the translation initiation rate of a nearby downstream RBS [46]. The precise mechanisms for this are not well understood but it is thought that the structural aspect of the RiboJ element at the 5'-end of an mRNA inhibits degradation by exonucleases, whilst the hairpin at the 3'-end of RiboJ exposes the nearby RBS by reducing the chance of unwanted secondary structure formation [44,45].

Finally, we combined the non-insulated designs with the sRNA booster plasmid to see whether further improvements could be made (**Table 1**). For the TES, we found that the dynamic range had plateaued, with only moderate increases that were mostly at low tuner promoter activities. In contrast, the fold-change between low and high outputs more than doubled across tuner promoter activities when compared to the non-insulated design, and a further drop of >18% was seen in the fractional intersection between the YFP fluorescence distributions for these output states. The tunable NOT gate showed minor decreases in performance for many of the measures (**Table 1**). However, the inclusion of the sRNA booster likely increased overall PhlF concentrations as the transition points from an 'on' to 'off' state (K value range) shifted to far below what had been seen for all other designs. This would make this specific design of value for uses where a weak input signal needs to be inverted and amplified simultaneously.

Towards complex tunable logic

To create larger genetic circuits that implement complex logic, it is vital that a sufficiently diverse set of logic gates are available for use. Because a NOT gate alone has limited capabilities, we further modified its design to create a tunable 2-input NOR gate device [7,33]. The output of a NOR gate is 'on' only when both inputs are 'off' (**Figure 5b**) and crucially this type of logic gate is functionally complete (i.e. any combinatorial logic function can be

implemented using NOR gates alone). In our new device, we added a further inducible input
promoter, P$_{BAD}$, directly before the existing P$_{tet}$ input promoter, and included the associated
sensor system (i.e. *araC* gene) to allow activity of the P$_{BAD}$ promoter to be controlled by the
concentration of L-Arabinose (**Figure 5a**). Our modifications were made to the existing NOT
gate design that included the RiboJ insulator because this produced the largest tunable range
for the 'on' to 'off' transition point.

To assess the function of the tunable NOR gate, the activities of both input promoters
P$_{BAD}$ and P$_{tet}$, and the tuner promoter P$_{tac}$ were varied by culturing cells harboring the device
in different concentrations of L-Arabinose, aTc and IPTG, respectively (**Materials and
Methods**). The two-dimensional response functions from these experiments (**Figure 5c**)
showed that NOR logic was successfully implemented and that the transition point from low
to high output for both inputs was simultaneous shifted to lower input promoter activities when
the tuner promoter was highly active (**Figure 5c**, right panel). Considering each input promoter
separately, this resulted in the transition point between 'on' and 'off' states shifting by 16- and
6-fold for P$_{BAD}$ and P$_{tet}$, respectively.

Interestingly, unlike the NOT gate, even at high tuner promoter activities, the dynamic
range was better maintained, dropping at most 35%, and the fold-change between 'on' and
'off' states remained above 4- and 8-fold for low and high tuner promoter activities, respectively
(**Supplementary Table S3**). Furthermore, the improved separation of these states leads to
smaller intersections in the output YFP distributions compared to the NOT gate. This was
especially evident when comparing NOR gate states where both input promoters were
simultaneously 'off' or 'on' with only a ~5% intersection (**Supplementary Table S3**).

The cause of this improvement is not clear but may relate to the P$_{BAD}$ promoter
insulating expression of the *phlF* gene from transcriptional read-through originating from the
tuner transcription unit that is located directly upstream in the DNA (**Supplementary Figure
S3**). Without this insulating effect, read-through would cause elevated expression of PhlF,
even when the input promoters are off, and potentially lead to a partial switch in the output
when the tuner promoter is active (as seen for the original NOT gate, **Figure 2b**). Such a
mechanism could also account for the elevated output levels for the TES when the input
promoter is off, but the tuner promoter activity is increased (**Figure 1c**).

Discussion

In this work, we have developed a new class of genetic device where an additional tuner input
is able to dynamically change key features of the device's response function. This was
achieved by employing a regulatory motif that allows for the transcription and translation rate
of a gene to be controlled by the activity of multiple input promoters. Connecting this TES to

a number of small molecule sensors, we were able to demonstrate its ability to shift the 'on'
and 'off' output states by 4.5- and 28-fold, respectively (**Figure 1**). Furthermore, we showed
how the TES could be incorporated into genetic NOT and NOR gates to enable tuning of the
crucial transition point between an 'on' and 'off' state over >6-fold range (**Figure 2**). This made
the gates more broadly compatible with other components where matching of transition points
to high and low output levels is essential for effective propagation of biological computations
[7,22]. Unfortunately, the performance of the tunable devices varied for differing tuner inputs,
leading to a trade-off between performance and the level of tuning required. Mathematical and
biophysical modelling of the TES helped to uncover: 1. the importance of ensuring sufficient
tuner sRNA is present to fully activate the THS (**Figure 3**), and 2. the presence of possible
detrimental interactions between a self-cleaving ribosome used to insulate protein expression
from genetic context and the THS that relies on the correct folding of an RNA secondary
structure to function properly (**Figure 4**). Modified designs that addressed these concerns
demonstrated improved performance for the TES in both cases, but only minor improvements
in the fold-change of the tunable NOT gate when the self-cleaving ribosome was removed
(**Table 1**). By combining these two modifications into a single system, further improvements
were observed for the TES, but not the tunable NOT gate when compared to the original
designs (**Table 1**). In contrast, the NOR gate behaved more consistently across tuner activity
levels and displayed better performance with greater separation of 'on' and 'off' states. To the
best of our knowledge the simultaneous control of transcription and translation to tune the
response function of a genetic device has not been shown before, making this work a valuable
resource for others to build on. Furthermore, unlike other attempts at tuning the response of
devices through mutation of protein components to alter catalytic rates [47], our method allows
for dynamic changes to a response function using simple to control transcriptional signals (i.e.
by the use of appropriate promoters).

A difficulty when using THSs to regulate gene expression is that high relative
concentrations of sRNA are required to achieve a strong enough activation of mRNA
translation. This stems from the regulatory mechanism relying purely on base-pairing of the
sRNA to THS, which places limits on the binding affinity that can be achieved. A possible
means of increasing the affinity between these species would be to exploit RNA chaperones
such as Hfq [48,49]. In prokaryotes, sRNAs that associate with Hfq play a variety of roles from
inhibiting and activating translation, to affecting the stability of a target mRNA [50–52]. In some
cases, these effects are significant. For example, it has been shown *in vitro* that Hfq increases
by 30- to 50-fold the binding affinity of the DsrA sRNA to the leader of the *rpoS* mRNA [53].
Designing *de novo* sRNA that binds to Hfq to increase their affinity to a target mRNA has been
demonstrated for both activation [48] and inhibition [49] of translation initiation. In both cases, Hfq
binding scaffolds from endogenous genes (e.g. *micC*) are fused with a targeting sequence.

This approach could be employed in future TES designs. In fact, previous work that used Hfq associated sRNAs to implement a metabolically cheap negative feedback control loop created a useful repressive tuning element that could be directly used in our system[49]. By combining the findings from that study with ours and incorporating recent improvements in THS design [6], it should be possible to make further strides towards high-performance tunable genetic devices.

An interesting future direction opened up by the adaptive nature of our devices is the possibility of incorporating many of them into larger circuits. This would allow many parts of a circuit to be tuned simultaneously to maximize the compatibility between components and optimize the behavior of the overall system. Unlike a typical design-build-test cycle that requires the reassembly of a genetic circuit with a new combination of parts if malfunctions are detected, this work supports a design-build-test-*tune* cycle where time consuming and costly reassembly can be avoided. Rather than reassembling a circuit after each cycle, parts can instead be dynamically tuned until they work correctly in unison. In this context, the use of sensitivity analysis during circuit design would offer valuable insight into specific components where even small deviations in behavior would adversely impact overall circuit function [54]. These would be ideal candidates to be encoded using tunable devices to allow for tweaking at these critical points. Furthermore, the use of new microfluidic culturing systems and online machine learning algorithms offers a way to rapidly discover the precise tuner inputs needed to achieve specific circuit functions under fluctuating environmental conditions [55–58].

Some practical challenges are raised by the additional tuner input in our devices. Systems composed of numerous tunable devices will require a large number of tuner inputs to be controlled simultaneously. If external signals are to be used, then a unique sensor is required for each tuner input, as well as the capability to be able to control the environment to provide the correct set of input signals over time. Although the range of small molecule [35] and light based [47,59] sensing systems available to bioengineers in *E. coli* has grown over recent years, the ability to control many environmental factors (e.g. small molecule concentrations and light intensities) simultaneously remains difficult. However, external control is not the only way to tune the behavior of these devices. The use of promoters as inputs and outputs allows them to be controlled by connecting them directly to the many transcriptional signals used natively in a cell. This offers the advantage of tapping into the cells innate capacity to sense and respond to its environment and internal protein synthesis demands. Alternatively, if an adaptive circuit is not required, sensors controlling the tuning inputs could be replaced once a working configuration is found with constitutive promoters of an identical strength. This would still reduce the reassembly required to a single step once the correct combination of tuning

inputs is found and remove the need for active control of the environment to provide necessary
stimuli for sensors.

When designing our tunable devices, we observed deviations between the
experimental and modelled responses. Further investigation suggested that this may be due
to retroactivity [36,37], specifically whereby expression of the output reporter protein places a
significant burden on the host cell (**Supplementary Text S2**). Recently, there has been
increased interest in the role of burden [60] impacting upon the function of large synthetic genetic
systems and attempts made to help mitigate its effect [61]. One approach has been to create
intracellular resource allocation schemes based on split exogenous RNAPs [62]. These limit the
maximum burden a circuit can impose by providing pools of transcriptional resources that are
orthogonal to the endogenous ones. This helps to reduce the chance of large unpredictable
physiological changes in the cell that might affect the function of synthetic circuits. Because
our tunable devices can have their sensitivity dynamically altered (i.e. transition point can
occur for weaker inputs), they offer another means of adapting to the reduced availability of
shared cellular resources. They could also be used to boost the expression of downstream
components to mitigate retroactivity effects or even be used to cap to maximum levels of
resource that can be used by a circuit (i.e. tuning the levels of several devices concurrently to
ensure protein expression does not exceed a fixed level).

For synthetic biology to have a broad and lasting impact outside of the carefully
controlled conditions of a lab, it is vital that means are developed to construct adaptive genetic
circuits able to maintain their functionality when exposed to unexpected environmental
changes or shifts in host cell physiology [63]. By combining advances in biological control
engineering [61,63–67] with the tunable genetic devices developed in this work, bioengineers have
a complementary set of tools capable of taking steps towards this goal.

Materials and Methods

Strains and media
Cloning was performed using *Escherichia coli* strain DH5-α (F⁻ *endA*1 *glnV*44 thi-1 *recA*1
*relA*1 *gyrA*96 *deoR nupG purB*20 φ80d*lacZ*ΔM15 Δ(*lacZYA–argF*)U169, *hsdR*17(r$_K^-$m$_K^+$), λ⁻)
(New England Biolabs, C2987I). Device characterization was performed using BL21 Star
(DE3) (F⁻ *ompT hsdS*$_B$ (r$_B^-$, m$_B^-$) *gal dcm rne*-131 [DE3]) (Thermo Fisher Scientific, C601003).
For cloning, cells were grown in LB Miller broth (Sigma-Aldrich, L3522). For device
characterization, cells were grown in M9 minimal media supplemented with glucose containing
M9 salts (6.78 g/L Na$_2$HPO$_4$, 3 g/L KH$_2$PO$_4$, 1 g/L NH$_4$Cl, 0.5 g/L NaCl) (Sigma-Aldrich,
M6030), 0.34 g/L thiamine hydrochloride (Sigma T4625), 0.4% D-glucose (Sigma-Aldrich,
G7528), 0.2% casamino acids (Acros, AC61204-5000), 2 mM MgSO$_4$ (Acros, 213115000),

and 0.1 mM CaCl$_2$ (Sigma-Aldrich, C8106). Antibiotic selection was performed using 50 µg/mL

kanamycin (Sigma-Aldrich, K1637) or 50 mg/mL spectinomycin (Santa Cruz Biotechnology,

sc-203279). Induction of sensor systems was performed using anhydrotetracycline (aTc)

(Sigma-Alrdich, 37919), isopropyl β-D-1-thiogalactopyranoside (IPTG) (Sigma-Aldrich, I6758)

and L-Arabinose (Ara) (Sigma-Aldrich, A3256).

Genetic device synthesis and assembly

Plasmids containing the TES and tunable NOT gate devices were constructed by gene

synthesis of the individual transcriptional units (e.g. tuner sRNA, THS-*yfp*, THS-*phlF* and *yfp*),

(GeneArt, Thermo Fisher Scientific) and insertion of these elements into a pAN1201 plasmid

backbone. pAN1201 provides all the sensor systems used for induction of the input promoters.

Assembly was performed by first PCR of the synthesized transcriptional units and the

pAN1201 plasmid (without the *lacZα* region normally used for blue/white screening) with all

primers containing a 20 bp tail homologous sequence to the previous or subsequent region in

the desired assembly. Gibson assembly (New England Biolabs, E2611S) was then used to

scarlessly assemble these fragments into a complete plasmid. The plasmid used to boost

tuner sRNA levels (pVB005) was fully synthesized (GeneArt, Thermo Fisher Scientific). The

plasmid containing the tunable NOR gate device (pVB006) was constructed by first PCR

amplification of the pAN1720 plasmid (without the *lacZα* region normally used for blue/white

screening) using primers containing an EcoRI restriction site at the 5'-end and a NotI restriction

site at the 3'-end. The tunable NOR gate DNA insert was synthesized in three parts (Integrated

DNA Technologies) which were assembled using a standard Golden Gate assembly method

(New England Biolabs, E1601S) to create a full-length linear insert. This was designed to

contain complementary EcoRI and NotI restriction sites to the amplified pAN1720 fragment.

Both linear DNA fragments were finally used in a standard restriction digest using EcoRI (New

England Biolabs, R3101) and NotI (New England Biolabs, R3189), and then a ligation reaction

(New England Biolabs, M0202S) to assemble the complete pVB006 plasmid. All plasmids

were sequence verified by Sanger sequencing (Eurofins Genomics). Annotated plasmid maps

of all devices are provided in **Supplementary Figure S3** and **Supplementary File S2**.

Genetic device characterization

Single colonies of cells transformed with the appropriate genetic constructs were inoculated

in 200 µL M9 media supplemented with glucose and necessary antibiotics for selection in a

96-well microtiter plate (Thermo Fisher Scientific, 249952) and grown for 16 hours in a shaking

incubator (Stuart, S1505) at 37 °C and 1250 rpm. Following this, cultures were diluted 9:1600

(15 µL into 185 µL, with 15 µL of this dilution loaded into 185 µL) in glucose supplemented M9

media with necessary antibiotics for selection and grown for 3 hours at the same conditions.

Next, the cultures were diluted 1:45 (10 µL into 140 µL) into supplemented M9 media with

necessary antibiotics for selection and any required inducers in a new 96-well microtiter plate

(Thermo Fisher Scientific, 249952) and grown at 37 °C and 1250 rpm for 5 hours. Finally, the

cells were diluted 1:10 (10 µL into 90 µL) in phosphate-buffered saline (PBS) (Gibco,18912-

014) containing 2 mg/mL kanamycin to halt translation and incubated at room temperature for

1 hour to allow for maturation of the YFP before performing flow cytometry.

Flow cytometry

YFP fluorescence of individual cells was measured using an Acea Biosciences NovoCyte

3000 flow cytometer equipped with a NovoSampler to allow for automated collection from 96-

well microtiter plates. Cells were excited using a 488 nm laser and measurements were taken

using a 530 nm detector. A flow rate of 40 µL/min was used to collect at least 10^5 cells for all

measured conditions. Automated gating of events using the forward (FSC-A) and side scatter

(SSC-A) channels was performed for all data using the FlowCal Python package version 1.2

[68] and the density2d function with parameters: channels = ['FSC-A', 'SSC-A'], bins = 1024,

gate_fraction = 0.5, xscale = 'logicle', yscale = 'logicle', and sigma = 10.0.

Autofluorescence correction

To measure YFP fluorescence from our constructs it was necessary to correct for the

autofluorescence of cells. An autofluorescence control strain containing the pAN1201 plasmid

[7], which does not express YFP but contains the same backbone as our genetic devices, was

measured using flow cytometry under the same culturing conditions as for characterization.

Measurements were taken from three biological replicates and an average of the medians of

the gated distributions was subtracted from the gated YFP fluorescence flow cytometry data

of the characterized devices, as in previous work [7].

Characterization of sensor systems in relative promoter units (RPU)

To allow for inputs to our devices to be controlled in standardized relative promoter units

(RPUs) [7,69], calibration curves for the two sensor systems were generated to enable a

conversion between a chemical inducer concentration and the relative promoter activity of

each sensors' output promoter (P_{tac} and P_{tet}). Cells transformed with plasmids pAN1718 and

pAN1719 for P_{tac} and P_{tet}, respectively, and the pAN1717 RPU standard [7], were cultured in

the same way as the characterization experiments. Flow cytometry was used to measure YFP

fluorescence which was further corrected for cell autofluorescence. RPU values were then

calculated by dividing the YFP output from the sensor by the YFP output from the RPU

standard and a Hill function fitted to the resultant data (**Supplementary Figure S1**).

Quantifying histogram intersections

The fraction of intersection H between two histograms (e.g. flow cytometry fluorescence distributions), x and y, was calculated using,

$$H(x,y) = \sum_{i=1}^{n} \frac{\min(x_i, y_i)}{x_i}. \tag{1}$$

Here, histograms x and y are divided into n bins that correspond to identical ranges of values for each, with x_i and y_i denoting the value of bin i for histogram x or y, respectively.

Predicting RNA binding and secondary structure

To predict the binding and secondary structure of the toehold switch and tuner sRNA (**Figure 3**), thermodynamic modelling was performed using the NUPACK web application [70]. All simulations were run using the parameters: nucleic acid = RNA, temperature = 37 °C and the concentration of toehold switch mRNA was set to 5×10^{-4} µM. The switch sequence mRNA and the switch sequence mRNA with an upstream cleaved RiboJ were simulated independently with additional parameters strand species = 1 and a maximum complex size = 1. The toehold switch mRNA with and without an upstream RiboJ sequence where also simulated in the presence of trigger sRNA set to a concentration of 7×10^{-5} µM with additional parameters: strand species = 1 and a maximum complex size = 1. Full sequences are given in **Supplementary Table S2**.

Computational analyses and data fitting

All computational analyses were performed using Python version 3.6.6. Response functions for the TES designs were generated by fitting median values of YFP fluorescence from flow cytometry data to a Hill function of the form

$$y = y_{\min} + (y_{\max} - y_{\min})\frac{x^n}{K^n + x^n}, \tag{2}$$

where y is the output YFP fluorescence (in arbitrary units), $y_{\min}$ and $y_{\max}$ are the minimum and maximum output YFP fluorescence (in arbitrary units), respectively, K is the input promoter activity (in RPU units) at which the output is halfway between its minimum and maximum, n is the Hill coefficient, and x is the input promoter activity (in RPU units). Response functions for the tunable NOT gates were generated in a similar way using a Hill function of the form

$$y = y_{\min} + (y_{\max} - y_{\min})\frac{K^n}{K^n + x^n}. \tag{3}$$

Fitting of data was performed using non-linear least squares and the curve_fit function from the SciPy.integrate Python package version 1.1.

Numerical simulation

The deterministic ODE model (**Supplementary Text S1**) was simulated using the odeint function of the SciPy.integrate Python package version 1.1 with default parameters. The delay differential equations (**Supplementary Text S2**) were simulated using the DifferentialEquations module version 6.10 using the Bogacki-Shampine 3/2 method running in Julia version 1.3. Stochastic simulations of the biochemical model (**Supplementary Text S1**) were performed using the tau-leap method in COPASI [71] version 4.24 with the following settings: number of iterations (simulations) = 4000, duration = 100 min, interval size = 1 min, number of intervals = 100 and the starting in steady state option selected. Initial steady-state conditions for the simulation are calculated automatically by COPASI using a damped Newton method.

Visualization of genetic designs

All genetic diagrams are shown using Synthetic Biology Open Language Visual (SBOL Visual) notation [72]. SBOL Visual diagrams were generated using the DNAplotlib Python package [73,74] version 1.0 which were then annotated and composed with OmniGraffle version 7.9.2.

Data availability

Systems Biology Markup Language (SBML) file implementing a model of the TES can be found in **Supplementary File S1**. Annotated sequence files in GenBank format for all plasmids are available in **Supplementary File S2**. All plasmids are available from Addgene (#127185–127189).

Acknowledgements

The authors wish to acknowledge the assistance of Dr. Andrew Herman and Dr. Lorena Sueiro Ballesteros of the University of Bristol Faculty of Biomedical Sciences Flow Cytometry Facility, and Bettina Frank of the Anderson Lab for help in preliminary plate reader assays. This work was supported by BrisSynBio, a BBSRC/EPSRC Synthetic Biology Research Centre grant BB/L01386X/1 (M.d.B., T.E.G.), EPSRC/BBSRC Centre for Doctoral Training in Synthetic Biology grant EP/L016494/1 (V.B.), the EU Horizon 2020 research project COSY-BIO grant 766840 (M.d.B), and a Royal Society University Research Fellowship grant UF160357 (T.E.G.)

Author Contributions

T.E.G. conceived of the study. V.B., T.E.G. and G.A.M. performed the experiments. V.B., M.d.B. and T.E.G. developed the mathematical models. V.B. analyzed the data. T.E.G., V.B., M.d.B. and G.A.M. wrote the manuscript.

Conflicts of Interest

599 The authors declare no competing financial interests.

References

1. Brophy, J. A. N. & Voigt, C. A. Principles of genetic circuit design. *Nat. Methods* **11**, 508 (2014).

2. Greco, F. V., Tarnowski, M. J. & Gorochowski, T. E. Living computers powered by biochemistry. *The Biochemist* **41**, 14–18 (2019).

3. Slomovic, S., Pardee, K. & Collins, J. J. Synthetic biology devices for in vitro and in vivo diagnostics. *Proc. Natl. Acad. Sci.* **112**, 14429 (2015).

4. Andrews, L. B., Nielsen, A. A. K. & Voigt, C. A. Cellular checkpoint control using programmable sequential logic. *Science* **361**, eaap8987 (2018).

5. Bashor, C. J. *et al.* Complex signal processing in synthetic gene circuits using cooperative regulatory assemblies. *Science* **364**, 593 (2019).

6. Green, A. A. *et al.* Complex cellular logic computation using ribocomputing devices. *Nature* **548**, 117 (2017).

7. Nielsen, A. A. K. *et al.* Genetic circuit design automation. *Science* **352**, aac7341 (2016).

8. Moon, T. S., Lou, C., Tamsir, A., Stanton, B. C. & Voigt, C. A. Genetic programs constructed from layered logic gates in single cells. *Nature* **491**, 249 (2012).

9. Gao, X. J., Chong, L. S., Kim, M. S. & Elowitz, M. B. Programmable protein circuits in living cells. *Science* **361**, 1252 (2018).

10. Daniel, R., Rubens, J. R., Sarpeshkar, R. & Lu, T. K. Synthetic analog computation in living cells. *Nature* **497**, 619 (2013).

11. Fernandez-Rodriguez, J., Yang, L., Gorochowski, T. E., Gordon, D. B. & Voigt, C. A. Memory and Combinatorial Logic Based on DNA Inversions: Dynamics and Evolutionary Stability. *ACS Synth. Biol.* **4**, 1361–1372 (2015).

12. Hsiao, V., Hori, Y., Rothemund, P. W. & Murray, R. M. A population-based temporal logic gate for timing and recording chemical events. *Mol. Syst. Biol.* **12**, 869 (2016).

13. Elowitz, M. B. & Leibler, S. A synthetic oscillatory network of transcriptional regulators. *Nature* **403**, 335–338 (2000).

14. Stricker, J. *et al.* A fast, robust and tunable synthetic gene oscillator. *Nature* **456**, 516 (2008).

15. Niederholtmeyer, H. *et al.* Rapid cell-free forward engineering of novel genetic ring oscillators. *eLife* **4**, e09771 (2015).

16. Kong, W., Meldgin, D. R., Collins, J. J. & Lu, T. Designing microbial consortia with defined social interactions. *Nat. Chem. Biol.* **14**, 821–829 (2018).

17. Karig, D. *et al.* Stochastic Turing patterns in a synthetic bacterial population. *Proc. Natl. Acad. Sci.* **115**, 6572–6577 (2018).

18. Cao, Y. *et al.* Programmable assembly of pressure sensors using pattern-forming
bacteria. *Nat. Biotechnol.* **35**, 1087–1093 (2017).

19. Danino, T., Mondragón-Palomino, O., Tsimring, L. & Hasty, J. A synchronized quorum
of genetic clocks. *Nature* **463**, 326–330 (2010).

20. Din, M. O. *et al.* Synchronized cycles of bacterial lysis for in vivo delivery. *Nature* **536**,
81–85 (2016).

21. Canton, B., Labno, A. & Endy, D. Refinement and standardization of synthetic biological
parts and devices. *Nat. Biotechnol.* **26**, 787 (2008).

22. P. Vaidyanathan *et al.* A Framework for Genetic Logic Synthesis. *Proc. IEEE* **103**,
2196–2207 (2015).

23. Weinberg, B. H. *et al.* Large-scale design of robust genetic circuits with multiple inputs
and outputs for mammalian cells. *Nat. Biotechnol.* **35**, 453 (2017).

24. Moser, F. *et al.* Genetic Circuit Performance under Conditions Relevant for Industrial
Bioreactors. *ACS Synth. Biol.* **1**, 555–564 (2012).

25. Gorochowski, T. E., van den Berg, E., Kerkman, R., Roubos, J. A. & Bovenberg, R. A.
L. Using Synthetic Biological Parts and Microbioreactors to Explore the Protein
Expression Characteristics of Escherichia coli. *ACS Synth. Biol.* **3**, 129–139 (2014).

26. Cardinale, S. & Arkin, A. P. Contextualizing context for synthetic biology – identifying
causes of failure of synthetic biological systems. *Biotechnol. J.* **7**, 856–866 (2012).

27. Gyorgy, A. *et al.* Isocost Lines Describe the Cellular Economy of Genetic Circuits.
Biophys. J. **109**, 639–646 (2015).

28. Gorochowski, T. E., Avcilar-Kucukgoze, I., Bovenberg, R. A. L., Roubos, J. A. &
Ignatova, Z. A Minimal Model of Ribosome Allocation Dynamics Captures Trade-offs in
Expression between Endogenous and Synthetic Genes. *ACS Synth. Biol.* **5**, 710–720
(2016).

29. Qian, Y., Huang, H.-H., Jiménez, J. I. & Del Vecchio, D. Resource Competition Shapes
the Response of Genetic Circuits. *ACS Synth. Biol.* **6**, 1263–1272 (2017).

30. Yeung, E. *et al.* Biophysical Constraints Arising from Compositional Context in Synthetic
Gene Networks. *Cell Syst.* **5**, 11-24.e12 (2017).

31. Gorochowski, T. E. *et al.* Genetic circuit characterization and debugging using RNA-seq.
Mol. Syst. Biol. **13**, 952 (2017).

32. Gorochowski, T. E. *et al.* Absolute quantification of translational regulation and burden
using combined sequencing approaches. *Mol. Syst. Biol.* **15**, e8719 (2019).

33. Stanton, B. C. *et al.* Genomic mining of prokaryotic repressors for orthogonal logic
gates. *Nat. Chem. Biol.* **10**, 99–105 (2014).

34. Green, A. A., Silver, P. A., Collins, J. J. & Yin, P. Toehold Switches: De-Novo-Designed
Regulators of Gene Expression. *Cell* **159**, 925–939 (2014).

35. Meyer, A. J., Segall-Shapiro, T. H., Glassey, E., Zhang, J. & Voigt, C. A. *Escherichia*
coli "Marionette" strains with 12 highly optimized small-molecule sensors. *Nat. Chem.*
Biol. **15**, 196–204 (2019).

36. Del Vecchio, D., Ninfa, A. J. & Sontag, E. D. Modular cell biology: retroactivity and
insulation. *Mol. Syst. Biol.* **4**, 161 (2008).

37. D. Del Vecchio & E. D. Sontag. Engineering principles in bio-molecular systems: From
retroactivity to modularity. in *2009 European Control Conference (ECC)* 658–664
(2009). doi:10.23919/ECC.2009.7074478.

38. Chen, H., Shiroguchi, K., Ge, H. & Xie, X. S. Genome-wide study of mRNA degradation
and transcript elongation in Escherichia coli. *Mol. Syst. Biol.* **11**, 781 (2015).

39. Busi, F., Arluison, V. & Régnier, P. Absolute Regulatory Small Noncoding RNA
Concentration and Decay Rates Measurements in Escherichia coli. in *Bacterial*
Regulatory RNA: Methods and Protocols (eds. Arluison, V. & Valverde, C.) 231–248
(Springer New York, 2018). doi:10.1007/978-1-4939-7634-8_14.

40. Lutz, R. & Bujard, H. Independent and Tight Regulation of Transcriptional Units in
Escherichia Coli Via the LacR/O, the TetR/O and AraC/I1-I2 Regulatory Elements.
Nucleic Acids Res. **25**, 1203–1210 (1997).

41. Dunn, J. J., Studier, F. W. & Gottesman, M. Complete nucleotide sequence of
bacteriophage T7 DNA and the locations of T7 genetic elements. *J. Mol. Biol.* **166**, 477–
535 (1983).

42. Studier, F. W. & Moffatt, B. A. Use of bacteriophage T7 RNA polymerase to direct
selective high-level expression of cloned genes. *J. Mol. Biol.* **189**, 113–130 (1986).

43. Hiszczyńska-Sawicka, E. & Kur, J. Effect of Escherichia coli IHF Mutations on Plasmid
p15A Copy Number. *Plasmid* **38**, 174–179 (1997).

44. Lou, C., Stanton, B., Chen, Y.-J., Munsky, B. & Voigt, C. A. Ribozyme-based insulator
parts buffer synthetic circuits from genetic context. *Nat. Biotechnol.* **30**, 1137 (2012).

45. Carrier, T. A. & Keasling, J. D. Engineering mRNA stability in E. coli by the addition of
synthetic hairpins using a 5′ cassette system. *Biotechnol. Bioeng.* **55**, 577–580 (1997).

46. Clifton, K. P. *et al.* The genetic insulator RiboJ increases expression of insulated genes.
J. Biol. Eng. **12**, 23 (2018).

47. Landry, B. P., Palanki, R., Dyulgyarov, N., Hartsough, L. A. & Tabor, J. J. Phosphatase
activity tunes two-component system sensor detection threshold. *Nat. Commun.* **9**, 1433
(2018).

48. Soper, T., Mandin, P., Majdalani, N., Gottesman, S. & Woodson, S. A. Positive
regulation by small RNAs and the role of Hfq. *Proc. Natl. Acad. Sci.* **107**, 9602 (2010).

49. Kelly, C. L. *et al.* Synthetic negative feedback circuits using engineered small RNAs.
Nucleic Acids Res. **46**, 9875–9889 (2018).

50. Waters, L. S. & Storz, G. Regulatory RNAs in Bacteria. *Cell* **136**, 615–628 (2009).

51. Storz, G., Opdyke, J. A. & Zhang, A. Controlling mRNA stability and translation with

small, noncoding RNAs. *Curr. Opin. Microbiol.* **7**, 140–144 (2004).

52. Gottesman, S. Micros for microbes: non-coding regulatory RNAs in bacteria. *Trends*

Genet. **21**, 399–404 (2005).

53. Soper, T. J. & Woodson, S. A. The rpoS mRNA leader recruits Hfq to facilitate

annealing with DsrA sRNA. *RNA* **14**, 1907–1917 (2008).

54. Feng, X. *et al.* Optimizing Genetic Circuits by Global Sensitivity Analysis. *Biophys. J.* **87**,

2195–2202 (2004).

55. Postiglione, L. *et al.* Regulation of Gene Expression and Signaling Pathway Activity in

Mammalian Cells by Automated Microfluidics Feedback Control. *ACS Synth. Biol.* **7**,

2558–2565 (2018).

56. Menolascina, F. *et al.* In-Vivo Real-Time Control of Protein Expression from

Endogenous and Synthetic Gene Networks. *PLOS Comput. Biol.* **10**, e1003625 (2014).

57. Bandiera, L. *et al.* On-Line Optimal Input Design Increases the Efficiency and Accuracy

of the Modelling of an Inducible Synthetic Promoter. *Processes* **6**, (2018).

58. Milias-Argeitis, A., Rullan, M., Aoki, S. K., Buchmann, P. & Khammash, M. Automated

optogenetic feedback control for precise and robust regulation of gene expression and

cell growth. *Nat. Commun.* **7**, 12546 (2016).

59. Baumschlager, A., Aoki, S. K. & Khammash, M. Dynamic Blue Light-Inducible T7 RNA

Polymerases (Opto-T7RNAPs) for Precise Spatiotemporal Gene Expression Control.

ACS Synth. Biol. **6**, 2157–2167 (2017).

60. Ceroni, F., Algar, R., Stan, G.-B. & Ellis, T. Quantifying cellular capacity identifies gene

expression designs with reduced burden. *Nat. Methods* **12**, 415–418 (2015).

61. Ceroni, F. *et al.* Burden-driven feedback control of gene expression. *Nat. Methods* **15**,

387–393 (2018).

62. Segall-Shapiro, T. H., Meyer, A. J., Ellington, A. D., Sontag, E. D. & Voigt, C. A. A

'resource allocator' for transcription based on a highly fragmented T7 RNA polymerase.

Mol. Syst. Biol. **10**, 742 (2014).

63. Segall-Shapiro, T. H., Sontag, E. D. & Voigt, C. A. Engineered promoters enable

constant gene expression at any copy number in bacteria. *Nat. Biotechnol.* **36**, 352

(2018).

64. Aoki, S. K. *et al.* A universal biomolecular integral feedback controller for robust perfect

adaptation. *Nature* **570**, 533–537 (2019).

65. D. Fiore, A. Guarino & M. di Bernardo. Analysis and Control of Genetic Toggle Switches

Subject to Periodic Multi-Input Stimulation. *IEEE Control Syst. Lett.* **3**, 278–283 (2019).

66. Mishra, D., Rivera, P. M., Lin, A., Del Vecchio, D. & Weiss, R. A load driver device for

engineering modularity in biological networks. *Nat. Biotechnol.* **32**, 1268 (2014).

67. Del Vecchio, D., Abdallah, H., Qian, Y. & Collins, J. J. A Blueprint for a Synthetic

Genetic Feedback Controller to Reprogram Cell Fate. *Cell Syst.* **4**, 109-120.e11 (2017).

68. Castillo-Hair, S. M. *et al.* FlowCal: A User-Friendly, Open Source Software Tool for

Automatically Converting Flow Cytometry Data from Arbitrary to Calibrated Units. *ACS*

Synth. Biol. **5**, 774–780 (2016).

69. Kelly, J. R. *et al.* Measuring the activity of BioBrick promoters using an in vivo reference

standard. *J. Biol. Eng.* **3**, 4 (2009).

70. Zadeh, J. N. *et al.* NUPACK: Analysis and design of nucleic acid systems. *J. Comput.*

Chem. **32**, 170–173 (2011).

71. Hoops, S. *et al.* COPASI—a COmplex PAthway SImulator. *Bioinformatics* **22**, 3067–

3074 (2006).

72. Madsen Curtis *et al.* Synthetic Biology Open Language Visual (SBOL Visual) Version

2.1. *J. Integr. Bioinforma.* (2019) doi:10.1515/jib-2018-0101.

73. Der, B. S. *et al.* DNAplotlib: Programmable Visualization of Genetic Designs and

Associated Data. *ACS Synth. Biol.* **6**, 1115–1119 (2017).

74. Bartoli, V., Dixon, D. O. R. & Gorochowski, T. E. Automated Visualization of Genetic

Designs Using DNAplotlib. in *Synthetic Biology: Methods and Protocols* (ed. Braman, J.

C.) 399–409 (Springer New York, 2018). doi:10.1007/978-1-4939-7795-6_22.

75. Chen, Y.-J. *et al.* Characterization of 582 natural and synthetic terminators and

quantification of their design constraints. *Nat. Methods* **10**, 659 (2013).

Figure 1: Design and characterization of a tunable expression system (TES). (**a**)
Schematic of the TES (top) and genetic implementation using a toehold switch (design 20) [34]
to regulate translation (TL) initiation rate of an output protein (bottom, dashed box). Yellow
fluorescent protein (YFP) is used as the output and T1 and T2 correspond to the transcriptional
terminators L3S3P11 and L3S2P21, respectively [75]. (**b**) Genetic design of the sensor modules
used to drive the main and tuner inputs to the TES. (**c**) Experimentally measured response
functions for the TES. Points denote the average of three biological replicates and error bars
show ±1 standard deviation. Each line shows a fitted Hill function for a fixed tuner input (light–
dark: 0.002, 0.03, 0.15, 0.43, 0.9, 2.6 RPU). (**d**) Flow cytometry distributions of output YFP
fluorescence when the tuner promoter activity is low (bottom; 0.002 RPU) and high (top; 2.6
RPU). Black outlined distributions correspond to a high input promoter activity (6.6 RPU) and
the filled red distributions to a low input promoter activity (0.002 RPU). Cell autofluorescence
is shown by the dashed grey line. (**e**) Fraction of intersection between YFP fluorescence
distributions for low (0.002 RPU) and high (6.6 RPU) inputs across varying tuner promoter
activities. (**f**) Response functions from a deterministic model of the TES (**Supplementary Text
S1**). Output shown as the steady state protein level. Line color corresponds to the promoter
activity of the tuner input (light–dark: 0.0001, 0.06, 0.3, 1.5, 7.6, 38, 190 RNAP/min). (**g**)
Comparison of the output for high (filled circles; 6.6 RPU) and low (unfilled circles; 0.002 RPU)
inputs across a range of tuner promoter activities (Experiment: 0.002, 0.03, 0.15, 0.43, 0.9,
2.6 RPU; Model: 0.0001, 0.3, 1.5, 7.6, 38, 190 RNAP/min).

Figure 2: Design and characterization of a tunable NOT gate. (a) Schematic of the tunable

NOT gate (top) and genetic implementation embedding the TES (bottom, dashed box). Yellow

fluorescent protein (YFP) expression is driven by the output promoter and T1 and T3

correspond to the transcriptional terminators L3S3P11 and ECK120033737, respectively [75].

(b) Experimentally measured response functions of the tunable NOT gate. Points denote the

average of three biological replicates and error bars show ±1 standard deviation. Each line

shows a fitted Hill function for a fixed tuner input (light–dark: 0.002, 0.03, 0.15, 0.43, 0.9, 2.6

RPU). **(c)** Flow cytometry distributions of the output YFP fluorescence from the tunable NOT

gate when the tuner promoter activity is low (bottom; 0.002 RPU) and high (top; 2.6 RPU).

Black outlined distributions correspond to a high input promoter activity (1.5 RPU) and the

filled blue distributions to a low input promoter activity (0.002 RPU). **(d)** Comparison of the

switching point (*K* value) for each repressor-based NOT gate from Cello [7] (black circles) to the

range achievable by the tunable NOT gate (red crosses and shaded regions). **(e)** Fraction of

intersection between output YFP fluorescence distributions for low (0.002 RPU) and high (1.5

RPU) inputs across varying tuner promoter activities. **(f)** Fold-change in the median output

YFP fluorescence between low (0.002 RPU) and high (1.5 RPU) inputs across varying tuner

promoter activities.

Figure 3: Increasing tuner sRNA transcription rate to improve device performance. (**a**)
Results of deterministic simulations of the TES model (**Supplementary Text S1**) showing
steady state protein output and THS mRNA to tuner sRNA ratio for a range of input and tuner
promoter activities. Tuner promoter activities are shown in bands between (light–dark) 0.0001,
0.0005, 0.0024, 0.012, 0.056, 0.27, 1.3, 6.4, 31, 150 and 730 RNAP/min, respectively. (**b**)
Stochastic simulation of the TES model (n = 4000) for low (1 RNAP/min; grey) and high (1.5
RNAP/min; green) input promoter activity. Top and bottom panels correspond to low (1.5
RNAP/min) and high (5 RNAP/min) tuner promoter activities, respectively. (**c**) Genetic design
of the sRNA booster. The *T7RNAP* gene is encoded in the host genome and an additional
plasmid contains a tuner sRNA expression unit. (**d**) Experimentally measured response
functions (left) and flow cytometry distributions of the YFP fluorescence output (right) for the
TES with the sRNA booster present. (**e**) Experimentally measured response functions (left)
and flow cytometry distributions of the YFP fluorescence output (right) for the tunable NOT
gate with the sRNA booster present. Points in all response functions denote the average of
three biological replicates and error bars show ±1 standard deviation. Each line shows a fitted
Hill function for a fixed tuner input (light–dark: 0.002, 0.03, 0.15, 0.43, 0.9, 2.6 RPU). All flow
cytometry distributions are shown for low (bottom; 0.002 RPU) and high (top; 2.6 RPU) tuner
promoter activity. Black outlined distributions correspond to a high input promoter activity (6.6
RPU for the TES and 1.5 RPU for the NOT gate) and filled red/blue distributions to a low input
promoter activity (0.002 RPU). Cell autofluorescence is shown by the dashed grey line.

Figure 4: Self-cleaving ribozyme insulators affect tunable device performance. (**a**) Original designs of both the TES and tunable NOT gate include a RiboJ insulating element, which can potentially interfere with binding of the tuner sRNA to the toehold switch. (**b**) RNA secondary structure predictions for THS mRNA alone and with a complimentary tuner sRNA bound. Separate structures shown when the RiboJ insulating element is present (left) and absent (right). (**c**) Experimentally measured response functions (left) and flow cytometry distributions of the output YFP fluorescence (right) for the TES with the RiboJ insulator removed. (**d**) Experimentally measured response functions (left) and flow cytometry distributions of the YFP fluorescence output (right) for the tunable NOT gate with the RiboJ insulator removed. Points in all response functions denote the average of three biological replicates and error bars show ±1 standard deviation. Each line shows a fitted Hill function for a fixed tuner input (light–dark: 0.002, 0.03, 0.15, 0.43, 0.9, 2.6 RPU). All flow cytometry distributions are shown for low (bottom; 0.002 RPU) and high (top; 2.6 RPU) tuner promoter activity. Black outlined distributions correspond to a high input promoter activity (6.6 RPU for the TES and 1.5 RPU for the NOT gate) and filled red/blue distributions to a low input promoter activity (0.002 RPU). Cell autofluorescence is shown by the dashed grey line.

Figure 5: Design and characterization of a tunable NOR gate. (**a**) Schematic of all the

sensor systems used (top, left), the tunable NOR gate (top, right), and their genetic

implementation (bottom, dashed boxes). Yellow fluorescent protein (YFP) expression is driven

by the output promoter and T1 and T3 correspond to the transcriptional terminators L3S3P11

and ECK120033737, respectively [75]. (**b**) Function of a 2-input NOR gate. (**c**) Heatmaps

showing the output of the tunable NOR gate for varying input promoter activities (Input A –

P_{BAD}: 0.008, 0.003, 0.15, 0.5, 2.5, 3.1 RPU; Input B – P_{tet}: 0.05, 0.5, 1.6, 3.1, 6.4, 7.5 RPU)

and for low (left) and high (right) tuner promoter activities. Output promoter activities shown

are average values calculated from flow cytometry data for three biological replicates. White

dashed line shows an output of 1.2 RPU and denotes the transition point from a high to low

output. (**d**) Flow cytometry distributions of the output YFP fluorescence for tuner promoter

activities of 0.002 RPU (bottom) and 2.6 RPU (top). The four distributions correspond to

combinations of the absence and presence of L-Arabinose (10 mM) and aTc (50 ng/mL).

Tables

Table 1: Performance summary of TES and tunable NOT gate.

Device	Design	Dynamic range[a,b] (a.u.)		Fold-change[a,c]		Intersection[a,d]		K range (RPU)[g]
		Low[e]	High[f]	Low[e]	High[f]	Low[e]	High[f]	
TES	Original	333 ± 53	877 ± 695	14 ± 1.7	2.4 ± 1.2	0.78 ± 0.06	0.69 ± 0.16	–
	sRNA booster[h]	538 ± 51	2064 ± 1070	227 ± 297	5.7 ± 1.8	0.46 ± 0.04	0.35 ± 0.15	–
	Non-insulated[i]	882 ± 134	2149 ± 409	445 ± 412	31 ± 16	0.26 ± 0.07	0.27 ± 0.06	–
	Combined[j]	1550 ± 209	1712 ± 584	1236 ± 613	66 ± 54	0.15 ± 0.04	0.22 ± 0.04	–
NOT gate	Original	17280 ± 1273	3512 ± 286	6.0 ± 0.1	1.5 ± 0.1	0.19 ± 0.04	0.84 ± 0.02	0.01–0.07
	sRNA booster[h]	22040 ± 1601	2170 ± 654	5.8 ± 0.3	0.9 ± 0.3	0.13 ± 0.07	0.85 ± 0.02	0.01–0.06
	Non-insulated[i]	17466 ± 1926	4061 ± 827	6.8 ± 0.3	2.6 ± 0.4	0.11 ± 0.03	0.56 ± 0.08	0.02–0.04
	Combined[j]	27751 ± 3104	2383 ± 165	6.0 ± 0.6	0.9 ± 0.1	0.08 ± 0.05	0.90 ± 0.03	0.003–0.02

a. Average values are shown ± 1 standard deviation calculated from flow cytometry data for three biological replicates.

b. Dynamic range calculated as the absolute difference in YFP fluorescence between low and high inputs (0.002 and 6.6 RPU for the TES, and 0.002 and 1.5 RPU for the NOT gate, respectively).

c. Fold-change in YFP fluorescence (corrected for cell autofluorescence) for low and high inputs (0.002 and 6.6 RPU for the TES, and 0.002 and 1.5 RPU for the NOT gate, respectively).

d. Fraction of intersection between the flow cytometry YFP fluorescence distributions for low and high inputs (0.002 and 6.6 RPU for the TES, and 0.002 and 1.5 RPU for the NOT gate, respectively) (**Materials and Methods**).

e. Performance measured for a low tuner input (0.002 RPU). This is the expected promoter activity of the P_{tac} promoter in our designs.

f. Performance measured for a high tuner input (2.61 RPU). This is the expected promoter activity of the P_{tac} promoter in our designs.

g. Range of K values from Hill functions fitted to experimental data.

h. Original designs (**Figures 1a** and **2a**) with the sRNA booster system (**Figure 3c**).

i. Design has the RiboJ insulating element removed (**Figure 4a**).

j. Design has the RiboJ insulating element removed (**Figure 4a**), and sRNA booster system present (**Figure 3c**).