Parallel Factor Analysis for multidimensional decomposition of fNIRS data

Alejandra M. Hüsser[1,a,b], Laura Caron-Desrochers[1,a,b], Julie Tremblay[a], Phetsamone Vannasing[a], Eduardo Martínez-Montes[†,c] & Anne Gallagher[†,a,b]

[a] Research Center of the Sainte-Justine University Hospital, Neurodevelopmental Optical Imaging Laboratory (LIONlab), 3175 Chemin de la Côte-Sainte-Catherine, Montreal QC, Canada, H3T 1C5
[b] Université de Montréal, Department of Psychology, Pavillon Marie-Victorin, P.O. Box 6128 Centre-ville Station, 2900 Boulevard Édouard-Montpetit, Montréal QC, Canada, QC H3T 1J4
[c] Cuban Neurosciences Center (CNEURO), 190 e/25 y 27, Cubanacan, Playa, CP 11600, Havana, Cuba

Abstract

Significance: Current techniques for data analysis in functional near-infrared spectroscopy (fNIRS), such as artifact correction, do not allow to integrate the information originating from both wavelengths, considering only temporal and spatial dimensions of the signal's structure. Parallel factor analysis (PARAFAC) has previously been validated as a multidimensional decomposition technique in other neuroimaging fields.

Aim: We aimed to introduce and validate the use of PARAFAC for the analysis of fNIRS data, which is inherently multidimensional (time, space, wavelength).

Approach: We used data acquired in 17 healthy adults during a verbal fluency task to compare the efficacy of PARAFAC for motion artifact correction to traditional 2D decomposition techniques, i.e. target principal (tPCA) and independent component analysis (ICA). Correction performance was further evaluated under controlled conditions with simulated artifacts and hemodynamic response functions.

Results: PARAFAC achieved significantly higher improvement in data quality as compared to tPCA and ICA. Correction in several simulated signals further validated its use and promoted it as a robust method independent of the artifact's characteristics.

Conclusions: This study describes the first implementation of PARAFAC in fNIRS and provides validation for its use to correct artifacts. PARAFAC is a promising data-driven alternative for multidimensional data analyses in fNIRS and this study paves the way for further applications.

Keywords: Near-infrared spectroscopy, multidimensional decomposition, parallel factor analysis (PARAFAC), canonical decomposition, artifact correction, language paradigm.

[1] Authors contributed equally to this study.
[†] Equal contribution as co-senior authors.
Anne Gallagher, E-Mail: anne.gallagher@umontreal.ca

1 Introduction

Functional near-infrared spectroscopy (fNIRS) is a non-invasive neuroimaging technique that uses

light of at least two different wavelengths in the near-infrared spectrum in order to assess brain

activity based on neurovascular coupling. The specific absorption properties of oxygenated (HbO)

and deoxygenated (HbR) hemoglobin allow individual assessments of concentration changes in

both HbO and HbR separately [1]. Although the fNIRS signal is considered to be relatively tolerant

to movement [2], quality of data may be reduced due to abrupt changes in the light intensity caused

by movement artifacts [3]. It has been shown that the dynamics of both wavelengths provide

important information for artifact detection and correction [4]. However, current techniques for

movement artifact correction (e.g. wavelet filtering, decomposition, spline interpolation, etc.)

typically assume that the behavior of both wavelengths is similar in time, thus do not take

advantage of the structured information offered by both wavelengths [5–7]. 2D analyses require that

data with more dimensions, such as fNIRS data, undergo superficial unfolding before processing,

for example, treating both wavelengths or HbO and HbR independently. Hence, some of these 2D

analysis tools are forced to impose other non-physiological constraints, such as orthogonality in

the case of principal component analysis (PCA) or statistical independence for independent

component analysis (ICA).

55   Although there are several ways to approach PCA -e.g. dimensionality reduction [8],

classification [9]-, from the signal decomposition point of view, PCA aims at extracting the so-called

principal components, i.e. those components that explain the greatest amount of variance of the

signal [10]. It has been used for artifact removal to isolate the artifact's signature, or to extract other

relevant activities in fNIRS [5,6,10,11]. In temporal PCA, the data is decomposed into a sum of

components, each one formed by the product of two vectors: one representing the temporal

principal component and the other, the corresponding topography (scores for each channel). A

basic problem with PCA is that the components defined by only two signatures (time and space)

are not uniquely determined. Therefore, orthogonality is imposed between the corresponding

temporal signatures of the different components [6,12,13]. Orthogonality among brain signals is,

however, a rather non-physiological constraint. Even with this restriction, the extracted principal

components are not completely unique, given that the arbitrary rotation of axes does not change

the explained variance of the data. This has led researchers to use different mathematical criteria

as the basis for choosing specific rotations (e.g. Varimax, Quartimax, Promax). In fNIRS, PCA

has also been applied to target time intervals (tPCA), that is only during periods where artifacts

related to articulation or other head movements occurred, instead of during the entire unsegmented

signal [3,14]. This type of targeted correction resulted in better signal quality, as compared to wavelet-

based filtering and spline interpolation, while also reducing the risk of altering the signal's global

integrity [3]. Although PCA is very common and easy to use, some authors have already discussed

its pitfalls and caveats as a method for artifact correction [7,15].

More recently, ICA has become another popular tool for data decomposition in fNIRS [16–

18]. It has the benefit of preventing rotational freedom [19]. However, uniqueness is achieved at the

cost of imposing a constraint even stronger than orthogonality, namely, statistical independence of

the temporal signatures [20,21]. Statistical independence is appropriate for identifying artifacts with

spatio-temporal signatures that are very different to those of neural activity (e.g. ocular

movements), but is less appropriate for artifacts that share spatio-temporal characteristics with

neural signals. What is more, ICA is commonly applied to the entire signal in contrast to a target

decomposition as introduced previously for tPCA [17]. It may thus be more challenging to achieve a

satisfying correction of irregular movement artifacts. In ICA, the maximal number of components

(hypothesized sources) equals the number of observations, which in neuroimaging is often rather

high. It could therefore become difficult to identify the artifact's signature, which could be split

into several components.

To overcome these limitations, a multidimensional ($\geq$ 3D) approach called parallel factor

analysis (PARAFAC) [22,23], or less frequently referred to as canonical decomposition [24], could be

considered as an alternative for the analysis of fNIRS data. PARAFAC is a decomposition

technique applicable to any dataset that can be described in more than two dimensions (e.g. time,

space, frequency, participants, conditions, signal characteristics) and allows for the extraction of

different signatures present in the data. It assumes multilinear relations between the different

dimensions and usually does not need any other mathematical constraints to find a unique

decomposition of the data. It may therefore be used in the data pre-processing steps to isolate

artifacts, as well as in the actual data analyses to extract a predominant brain activation, or other

relevant characteristics of the signal. Such multidimensional decomposition was initially

introduced in the field of psychometrics and linguistics as a tool for multi-factorial analysis [22,24,25].

Over time, its use was extended to neuroimaging signals, such as the analysis of event-related

potentials (ERPs) assessed by electroencephalography (EEG), in which time, space and

participants were considered for the signal decomposition [26,27]. Multidimensional decomposition

with PARAFAC is not limited to 3D and could potentially be applied to data with more

dimensions. In the context of ERP data, PARAFAC as a five-way analysis has successfully been

used to identify differences and common characteristics of inter-trial phase coherence across

conditions and subjects, including the dimensions of time, channels, frequency, subjects, and

conditions [26]. PARAFAC was also applied for data analysis in continuous EEG recordings, taking

into account the temporal, spatial and frequency representation of the EEG signal [13,28]. Indeed,

using a time-frequency wavelet transformation for each channel in EEG data, Miwakeichi and

colleagues [13] revealed PARAFAC as an appropriate tool for both the detection of ocular movement

artifacts and the identification of dominant brain activation patterns. In their study, some of the

artifact components identified using PARAFAC were highly similar to those extracted with principal component analysis (PCA), a well-established approach for 2D decomposition. Specifically, significant overlap was shown for eigenvalues and peaks of time/frequency components, as well as their topographical representations found with PCA and PARAFAC for activities that effectively fulfill the orthogonality requirement. PARAFAC, using the dimensions of time, space and frequency, has also been applied successfully to the EEG data of individuals with epilepsy, for the purposes of artifact detection and the identification of aberrant cerebral activation [29]. The growing popularity of PARAFAC in neuroimaging stems from the intrinsic advantage of multidimensional decomposition, as it reflects the nature of most data gathered in neuroscience. Compared to 2D methods, the application of PARAFAC does not need to impose non-physiological constraints [28]. What is more, since decomposition techniques represent data-driven approaches, PARAFAC could also contribute to enlighten new aspects of neuroimaging data compared to model-based techniques [30]. Although PARAFAC has been applied for data analysis on NIRS data in the food industry [23], it has not yet been used in fNIRS in the field of neuroscience.

The current study aimed to introduce and validate PARAFAC as a multidimensional decomposition technique to extract and correct artifacts in fNIRS data. To account for the natural complexity and variability regarding motion artifacts, we first applied the PARAFAC technique in real cognitive fNIRS data. More specifically, data were acquired from participants that performed aloud a verbal fluency task, in which the main motion artifacts are known to be task-dependent and have characteristics that might confound the estimation of the hemodynamic response function (HRF) [7]. PARAFAC's performance to correct motion artifacts was compared to two traditional bi-dimensional decomposition techniques: tPCA and ICA. In doing so, we

investigated differences in artifact correction efficacy related to the number of dimensions used in

the decomposition techniques (i.e. treating both wavelengths as independent or as a dimension).

As the true HRF was unknown and therefore did not allow to directly compare the recovered task

activation to a ground truth, we used statistical analysis of correction performance based on various

quality measures of the three different corrected signals.

Secondly, we investigated how artifact correction with PARAFAC performed in various

controlled scenarios to disentangle in which cases a multidimensional decomposition approach

that does not impose orthogonality constraints could become advantageous. For that purpose, a

real artifact was extracted from a data set of the task condition and added to a clean resting-state

signal. Different artifact parameters (e.g. amplitude, onset of overlapping artifacts) were controlled

to produce various scenarios, including variation in the level of orthogonality among the signals

combined in the simulated data. Further, the use of the resting-state signal allowed us to evaluate

how artifact correction would affect the reconstruction of a synthesized HRF (HRF_{sim}), which has

actually been named as one of the most suitable methods to validate artifact correction [5]. Artifact

correction in these scenarios was performed with PARAFAC and tPCA only, both applied

specifically during the artifacted interval (i.e. target decomposition), compared to ICA that is

typically applied to the entire signal, and thus being more comparable methods. Indices for the

similarity between the clean signal before adding artifacts and the signal after artifact correction,

the signal's quality as well as the recovery of the HRF_{sim} after correction, were used to compare

the performance of both correction approaches.

2 Methods

2.1 Sample and data acquisition

Eighteen healthy native French-speaking adults participated in this study. One participant was excluded from the analyses, as it showed continuous noise precluding the identification of individual artifacts. The final sample for the validation of using PARAFAC for artifact correction thus included 17 participants (mean age ± standard deviation = 22.8 ± 2.0 years; 9 females and 8 males). All were right-handed and presented no neurological or psychiatric disorders. Experimental procedures were approved by the local ethics committee.

fNIRS data was acquired with a multichannel Imagent Tissue Oxymeter (ISS Inc., USA) frequency-domain fNIRS device using 14 light detectors and 60 laser light emitters, each regrouping two light sources of different wavelengths ($\lambda_{1|2}$ = 690|830 nm) with an average power of 10 mW. Emitters and detectors coupled at a distance of 3 to 4.5 cm allowed for the recording of 104 channels for each wavelength. Optodes were held in place perpendicularly, using a cap that was fitted on the head of participants in accordance with the 10-20 system [31]. Optical intensity, including information regarding the average light intensity (DC), amplitude modulation (AC) and phase shift (φ), was measured with a sampling rate of 19.53 Hz (Boxy, ISS Inc., USA). The channel setup covered both hemispheres equally and included the regions of interest for the investigation of language functions, i.e. frontal, temporal and parietal lobes (Fig. 1A).

Participants sat comfortably in a soundproof room. They were instructed to relax, to avoid any intentional movements or muscular tension, and to fix their gaze on the center of a screen placed at a distance of 114 cm. Participants underwent fNIRS recording during two conditions (Fig. 1B): (1) a 12-minutes resting-state with eyes open and (2) a verbal fluency task previously validated for expressive language-related activation [32–34]. The task consisted of 11 different

familiar semantic categories (e.g. animals, colors, fruits, etc.) that appeared one at a time on the

screen. Participants were instructed to name as many words as possible belonging to the specified

category and to continue as long as the category name appeared on the screen. We used a block

design paradigm in which periods of rest (fixation cross presented on the screen) and task

(semantic category) alternated (Presentations®, Neurobehavioral Systems, 2018). The

interstimulus interval varied randomly between 25 and 29 seconds, while stimuli (one of the

semantic categories) were always presented for 30 s. An audiovisual recording of the fNIRS

session enabled visual support during offline pre-processing for the identification of movements

and the timing of word articulation. Participants completed on average 10.4 ± 0.9 blocks of the

verbal fluency task and named an average of 14 ± 2.2 words during each 30-s block. Data analysis

was conducted with the use of a homemade toolbox (LIONirs) [35] adapted in SPM12 (Statistical

Parametric Mapping) [36] in MATLAB® (The MathWorks, Inc., MA, USA).

Fig. 1 fNIRS setup: (A) Probe placement (sources in small light gray dots,
detectors in dark gray dots) as shown on an adult's head model. (B)
Experimental design including a 12-minute resting-state followed by an
expressive verbal fluency task that included 11 trials. Trials lasted 30 seconds
and interstimulus intervals varied pseudo-randomly between 25 and 29
seconds.

2.2 Validation process

Validation of PARAFAC for artifact correction was done in two realistic applications as illustrated in Fig. 2. First, artifact correction with PARAFAC was tested on the real task-based signal of the whole sample, and its performance was compared to tPCA and ICA. Indices for the signal's quality were used to compare the three techniques (see Sec. 2.6). Second, a simulation analysis was conducted to investigate the efficacy of PARAFAC to correct artifacts with controlled parameters. Similarity metrics, quality measures and reconstruction of the HRF_{sim} were used to evaluate artifact correction with PARAFAC and tPCA both applied in a target manner (see Sec. 2.6, 2.7 & 2.8).

Fig. 2 Processing streams to validate PARAFAC as a multidimensional artifact correction technique for fNIRS data. Processing of the real task data derived from 17 subjects and the simulated data based on a single-subject are indicated with dashed and dotted lines, respectively. Steps included in both are framed in a solid line. Steps in grey represent the metrics used to evaluate correction performance.

Note. $NIRS_{ini}$ = initial signal used for comparison (with artifacts for the real task data; before artifact simulation for the resting-state data). PRD = Percent root difference. RMSE = Root mean square error. R = Pearson product-moment correlation coefficient. SNR = Signal-to-noise ratio, $R\lambda$ = Pearson's correlation between wavelengths. GLM = General linear model. HRF_{sim} = simulated hemodynamic response function.

2.3 Non-simulated task-related motion artifacts

Pre-processing of the task-condition data first included the automatic exclusion of channels with

insufficient light intensity amplitude (average raw DC intensity across time < 100). The signal was

afterwards segmented into blocks of 50 s (5 s resting-state baseline, 30 s task and 15 s resting-

state), and light intensity was converted to changes in optical density (normalization of each

block). We then performed a semi-automatic artifact detection using a moving-window algorithm

to automatically mark segments where an abrupt change of the signal's variance exceeded three

times the average variance of the previous interval [37] with a window duration of 0.8 s. Events that

were 2 s or less apart were considered as one and channels that were strongly correlated with a

noisy channel (Pearson correlation of ≥ 0.8) within the aberrant segment were also marked as

artifacted. The automatic detection step was reviewed afterwards and adjusted based on an inter-

rater visual inspection of the signal's characteristics and the video recordings. Because the task

required participants to name words aloud, artifacts in the current language paradigm were mostly

due to facial movements related to the muscular contraction of articulation.

2.4 Simulated motion artifacts

A real resting-state dataset from one of the participants in which we could identify a 180-s segment

without any motion artifact was employed for the simulated artifact experiment. As for the task-

based data, channels with insufficient raw light intensity amplitude were first excluded based on

the previously mentioned criteria, yielding a total of 82 channels. The data was then converted to

changes in optical density (normalization based on the whole 180-s segment). It served as the

initial signal baseline ($NIRS_{ini}$) for similarity and quality signal assessments.

To add a motion artifact with controlled parameters, we first used PCA to decompose all

channels of a task-based fNIRS signal during a typical motion artifact (A) with a duration of 7 s.

The obtained temporal signature of the first component was then added to the NIRS$_{ini}$. The spatial

distribution of A, i.e. the weight of each channel was randomized, but the same distribution was

added to both wavelengths with only a different overall scale. Fig. *3* provides an overview of the

set of simulations and their parameters, while more details are provided in Fig. S1 of the

Supplemental Material. For the first simulation, the amplitude of the original artifact was

modulated and scaled to five different amplitudes in order to produce artifacts with various SNR

(simulations 1a-1e). For the second simulation, we aimed to produce artifacts with more complex

signatures (simulations 2a-f). The idea emerged from observations of artifact correction in the task-

related signal and also aimed at exploring the decomposition when different artifacts are not

completely orthogonal in the data. To do so, two individual artifacts (A_1, A_2) with varying time

intervals between the onset of A_1 and A_2 led to different temporal orthogonality (r) which was

evaluated for each simulation. The levels of orthogonality between the time courses of the raw

signal and the first artifact r_a (Raw x A_1) and between the time courses of the artifacted signal and

the second artifact r_b ((Raw + A_1) x A_2), were derived from the angle between both signals (i.e.

taking the time course of each signal as a vector of time points and computing the angle between

both vectors). A normalized measure of the orthogonality level is then computed such that when

the angle between the signals is 90 degrees, the measure is maximum and equal to 1, while when

the angle departs from 90 degrees (both higher or lower) the measure linearly decreases to 0. Then,

r values of 1 indicate perfect orthogonality between the two time courses, while r values lower

than 1, specifically those closer to 0 indicate that the two time courses are not orthogonal to each

other. Additionally, an HRF was synthesized (HRF$_{sim}$) in SPM by the linear combination of two

gamma functions as proposed in the literature [38]. That is, gamma functions 1 and 2 had a time-to-

peak of 5.4 s and 10.8 s respectively, a full-width-at-half maximum of 5.2 s and 7.36 s respectively,

and a scaling coefficient for the second gamma function of 0.35. The amplitude of the HRF_{sim} was

scaled by 14% for the 830 nm signal and 0.6% for the 690 nm signal, which approximately

produces an HRF with an 15μM increase in HbO concentration and a 5μM decrease in HbR

concentration [5,38–40]. The response was simulated as a convolution of the HRF with a stimulus

duration of 30 s resulting in a simulated physiological signal (HRF_{sim}) of approximately 40 s. The

HRF_{sim} was then added to the signal along with an artifact (*A*), so as to produce different overlaps

between both time courses (simulations 3a-3d).

Fig. 3 Simulated fNIRS signals: Panel A shows one example of the simulated fNIRS signal for each simulation
condition 1-3. Panel B provides the details of the varying parameters of all simulations. Five scaling factors (0.4,
0.8, 1.0, 1.5, 3.0) were used to create simulated artifacts with different amplitudes. λ1|2 = 690|830 nm, A =
artifact, HRF_{sim} = simulated hemodynamic response function.

2.5 Artifact correction

In the task-based data set, artifact correction with PARAFAC and tPCA was applied in a target

manner, i.e. to the segments identified during artifact detection as described in Sec. 2.3; while,

with ICA the analysis was applied to the entire continuous signal. In the simulated signals, target

correction was applied to a time interval of +/-2 s around the simulated artifacts. More details on

each decomposition technique will be presented in the following sections (2.5.1 & 2.5.2).

2.5.1 Two-dimensional signal decomposition for artifact correction

For both ICA and tPCA, the decomposition of the 2D data matrix X (whose elements x_{ij} are

indexed by channel i and time points j), leads to N_f components as defined in Eq. 1 and illustrated

in Fig. 4a:

281
$$x_{ij} = \sum_{f=1}^{Nf} a_{if} b_{jf} + \varepsilon_{ij}. \tag{1}$$

The matrix concatenates two separate data matrices (X_1, X_2) corresponding to the 2D

structure for both wavelengths. The maximum number of components N_f could be equal to or less

than the smaller dimension of the X matrix dimension, i.e. twice the number of channels or number

of time points. Each component is modeled as the product of two factors/vectors which represent

signatures of the space (a_f) and time (b_f) dimensions. The temporal signatures are constrained to

be orthogonal among components, and rotated in order to obtain those signatures that offer the

highest variance explanation (varimax) from all the infinite solutions of the decomposition. The

unexplained part of the data is considered irrelevant activity or noise (ε).

Artifact correction with tPCA was performed on each time interval containing artifacts as

specified by the time interval of the simulated artifacts or the identified artifact detection of the

task-based data set. From the obtained components we subtracted the first, which explains most of

the variance based on the assumption that the highest variance in the data for each segment is

assumed to be caused by the artifact.

Artifact correction with ICA, was done using BrainVision Analyzer (Brain Products

GmbH, Gilching, Germany), and followed the steps proposed by Plank [41]. First, optical density

fNIRS data were exported and ICA was applied on the entire unsegmented signal, as for the

method commonly reported in the literature [17]. Noisy intervals reflecting artifacts were identified

by semi-automatic inter-rater artifact detection (see Sec. 2.3). We visually selected the ICA

components reflecting the artifact, based first on their time course, i.e. high variation of light

intensity similar to the artifact signature. Secondly, we rejected those whose subtraction would

induce artificial artifacts elsewhere. Data was subsequently imported back into the LIONirs

toolbox [35] in order to apply segmentation (see Sec. 2.3).

Fig. 4 Schematic representation of the decomposition models applied to fNIRS data. **(A)** The data X is

arranged as a 2D data array by vertically concatenating the 2D matrices with dimensions being space (s)

and time (t) for each wavelength (w). tPCA/ICA decomposes the array into components, each being a

bilinear product of the loading vectors representing temporal ($a_{t\,f}$) and spatial signatures ($b_{s*w\,f}$). The latter

is formed by the spatial signatures for the different wavelengths, which are represented in components

without taking into account their spatial dependence, i.e. for the same temporal signature of each

component, there will be two topographies corresponding to the two wavelengths. Matrices $A = \{a_f\}$ and

$B = \{b_f\}$, contain as columns the temporal and spatial signatures for all components, respectively. **(B)** The

data X is arranged as a 3D data array with dimensions being time (t), space (s) and wavelengths (w).

PARAFAC decomposes this array into the sum of components, each being a trilinear product of loading

vectors representing temporal ($a_{t\,f}$), spatial (channel, $b_{s\,f}$) and spectral (wavelength, $c_{w\,f}$) signatures. In

practice, the decomposition consists of finding the matrices $A = \{a_f\}$, $B = \{b_f\}\,and\,C = \{c_f\}$ that

explain X with minimal residual error.

2.5.2 Multidimensional signal decomposition

The fNIRS data naturally offers the time courses of all channels for two wavelengths, i.e. two

separate data matrices. This data can be arranged in a tri-dimensional array, as illustrated in Fig.

4b. The dimensions of this 3D array are time (indexed by the time points in the analyzed segment),

space (indexed by channels) and wavelength (indexed by the two wavelengths). As explained

above, PARAFAC establishes a trilinear decomposition of each element of the fNIRS data array

(X_{tsw}) in N_f components, each being the product of three factors[5] as defined in Eq. 2:

325
$$X_{tsw} = \sum_{f=1}^{Nf} a_{tf}\, b_{sf}\, c_{wf} + \varepsilon_{tsw}. \tag{2}$$

The estimated factors, a_{tf}, b_{sf} and c_{wf} are the elements of the so-called loading matrices

A, B and C, whose column vectors $a_f = \{a_{tf}\}$, $b_f = \{b_{sf}\}$, $c_f = \{c_{wf}\}$, represent the temporal,

spatial and wavelength signatures of each component. The main advantage of this method is that

it provides a unique decomposition of the fNIRS data into components reflecting different

activities that do not need to be orthogonal or statistically independent in any of the dimensions.

As long as an activation shows a different behavior in one of the dimensions, it can be extracted

as a separate component. In this application, the spatial dependency between wavelengths is

therefore exploited in order to perform the decomposition. The uniqueness of the solution is

guaranteed when the number of components (N_f) is smaller than the sum of the ranks of the three

loading matrices. In the case of noisy data, it is very likely that the loading matrices are always

full rank. Uniqueness is thus guaranteed as long as the number of components (N_f) is smaller than

half the sum of the number of time points (N_t), number of channels (N_c), and number of

wavelengths (N_w): $Nf \le \frac{(N_t+N_c+N_w)}{2} - 1$). For instance, even in a small array of 20 time points

and eight channels at two different wavelengths, a unique decomposition could be achieved, using

up to 14 components ($\frac{20(t)+8(s)+2(w)}{2} - 1 = 14(Nf)$). Computationally, the decomposition is

achieved by the Alternating Least Squares algorithm, as it has been used in previous studies on

neuroscience data [13,28,29,42]. The only indeterminacies in the least-squares solution are trivial and

easy to handle: the order of the additive components and the relative scaling of the signatures [23].

In this work, we used the PARAFAC implementation from the N-way Toolbox [43], which

was included into the LIONirs toolbox [35] so as to visualize and apply the decomposition

exclusively during selected time intervals and channels. Components were ordered according to

their importance in explaining the data's variance (similar to tPCA). The scale of the data was kept

in the temporal signatures, while the other dimensions were normalized so as to have Frobenius

norms equal to one. Since measures from both wavelengths are sampled simultaneously at each

specific position on the scalp, movement artifacts affect their amplitudes similarly. During time

intervals containing artifacts, the time courses of the signal from the two wavelengths commonly

show a drastic and correlated increase as compared to the task-related or baseline signal [4]. By using

multidimensional PARAFAC decomposition, we can take advantage of this information for the

adequate selection of components of the artifact's signature. PARAFAC decomposition was

specified to extract between two to four components, allowing a clear separation of the artifact

signatures representing the artifacts characteristics from the rest of the signal. The appropriate

components were selected based on (1) a visual inspection of their temporal overlap with the

artifact, (2) the smallest number of possible components that would sufficiently correct the artifact,

and (3) components showing similar weights for both wavelengths. In simulations, a standardized

PARAFAC decomposition with 3 components was applied. Two components that clearly showed

evidence of an amplitude change typically related to a movement artifact, i.e. short impulses, were

discarded as reflecting the artifact in the original signal.

2.6 Signal quality

The signal's overall quality was estimated by two quality measures [4,5,44]:

(1) <u>Signal-to-noise-ratio:</u> For each data segment with an artifact we estimated the signal-

to-noise ratio (SNR), as defined by Sweeney and colleagues [44]:

$$SNR = 10log_{10}\frac{\sigma_x^2}{\sigma_e^2}, \tag{3}$$

where σ_x^2 represented the signal's variance computed in segments of data without an artifact. In

case of the real task-based data set, σ_x^2 was computed in a 5-s interval during the baseline of the

task condition. For the simulations, σ_x^2 was computed in a 5-s interval at the beginning of the

resting-state signal. σ_e^2 represented the variance of a segment where an artifact was identified or

simulated. Whenever an artifact contaminated the signal, σ_e^2 would usually be higher than σ_x^2

because it comprised both the variance of the physiological signal and the variance of the artifact.

It was therefore expected that the SNR of the signal before artifact correction would be negative.

After artifact correction, a negative SNR ($\sigma_x < \sigma_e$,) would indicate that the artifact had not been

entirely removed, a positive SNR ($\sigma_x > \sigma_e$,) would imply overcorrection meaning that artifact

correction removed the artifact as well as parts of the relevant physiological activity, and an SNR

of about 0 ($\sigma_x = \sigma_e$) would suggest that the artifact had been eliminated to the extent that the

variance of the corrected signal would not differ from the baseline segment without an artifact. In

case of the task-based data set, the SNR of the uncorrected signal served as a baseline, thus the

more the SNR of the corrected signal differed from the baseline value and approached 0, the better

the artifact had been corrected. Since the ground truth of the signal's variance was unknown and

besides the artifact also the hemodynamic response may contribute to the signal's variance, no

further interpretation of a negative or positive SNR would have been appropriate. For the

simulations, the SNR of the initial signal before artifact simulation ($NIRS_{ini}$ and $NIRS_{ini} + HRF_{sim}$)

served as a reference and the more the SNR of the corrected signal would approach this value, the

better the performance of artifact correction was assumed to be.

(2) Pearson's correlation coefficient ($R\lambda$) between the time courses of both wavelengths

from the same site were used as a subsequent quality measure to evaluate artifact correction

performance [4]. This was based on the assumption that a high correlation coefficient indicates the

presence of artifactual signals measure simultaneously by both wavelengths, since in a clean signal

these temporal courses appear much less correlated. Similar to how it was previously done for the

SNR, we computed $R\lambda$ for all segments with identified or simulated artifacts before (i.e.

uncorrected artifact reference) and after artifact correction (i.e. corrected signal). For the task-

based data, $R\lambda$ was additionally calculated for artifact-free baseline intervals (i.e. artifact-free

reference) and in case of the simulations for the intervals of the initial signal ($NIRS_{ini}$ and $NIRS_{ini}$

$+ HRF_{sim}$) before artifact simulation (i.e. artifact-free reference).

2.7 Similarity indices

For the analysis of simulated data, three additional metrics were used to evaluate performance of

artifact correction: (1) the percent root difference (PRD), (2) the root mean square error (RMSE)

and (3) the Pearson product-moment correlation (R). These allowed us to estimate the degree of

correspondence between the initial signal without simulated artifacts ($NIRS_{ini}$ and $NIRS_{ini}$ +

HRF_{sim}) and the signal after correction of the simulated artifacts [40,45,46]. PRD, RMSE and R were

defined as follows:

(1) The percent root difference (PRD)

$$PRD = 100\% * \sqrt{\sum_{i=1}^{N}(x(t_i) - y(t_i))^2 \left(\sum_{i=1}^{N} x^2(t_i)\right)^{-1}}, \qquad\qquad 1)$$

(2) <u>Root mean square error (RMSE)</u>

408
$$RMSE = \sqrt{\frac{1}{N}\sum_{i=1}^{N}(x(t_i) - y(t_i))^2},\qquad(2)$$

409   (3) <u>Pearson product-moment correlation (R)</u>

410
$$R = \frac{1}{N-1}\sum_{i=1}^{N}\left(\frac{(x(t_i)-\bar{x})}{s_x}\right)\left(\frac{(y(t_i)-\bar{y})}{s_y}\right),\qquad(3)$$

411
$$\text{where } s_x = \sqrt{\frac{1}{N}\sum_{i=1}^{N}(x(t_i)-\bar{x})^2}, s_y = \sqrt{\frac{1}{N}\sum_{i=1}^{N}(y(t_i)-\bar{y})^2}.$$

For all three indices, $x(t_i)$ and $y(t_i)$ represented the i-th point of the time courses of the

corrected signal and of the initial artifact-free signal (NIRS$_{ini}$ and NIRS$_{ini}$ + HRF$_{sim}$), respectively.

N corresponded to the duration of the time courses and $\bar{x}$ and $\bar{y}$ to their respective mean values

along time. An ideal artifact correction would have been achieved when the artifact was completely

removed, and the corrected signal maximally resembled the initial signal. As PDR and RMSE

inform on the difference of the two signals, the smaller they were, the more accurate the

performance of artifact correction was. On the contrary, the R index represents the similarity of

both signals, hence a higher value suggested better artifact correction.

2.8 HRF recovery

In order to investigate how artifact correction would affect the interpretation of the hemodynamic

response, in the last simulations (3a-d) we aimed to recover a previously synthesized HRF.

Therefore, a Butterworth low-pass filter (filter order = 4, cut-off frequency = 0.2 Hz) was applied

to the signal to remove oscillations caused by heartbeat and respiration. The optical intensity

changes of the two wavelengths were then transformed into relative concentration changes of HbO

and HbR, done so by using an age-adapted differential pathlength factor (DPF) and the modified

Beer-Lambert Law [47,48]. A general linear model (GLM) with the HRF$_{sim}$ as a predictor was then

applied. The GLM assumes that a linear relation exists between different inputs [49], and has already

been applied in several fNIRS studies to specify the HRF [6,50,51]. The cerebral activation of the

signal (y) is defined as:

431
$$y = \text{ß}_0 + \text{ß}_{HbO/HbR}x + \varepsilon, \tag{4}$$

Where y referred to the analyzed signal, ß_0 was a constant, $\text{ß}_{HbO/HbR}$ represented the

predictive value of the simulated hemodynamic response represented by x (HRF$_{sim}$) for both

concentration changes of HbO and HbR, respectively, and ε represented the error or the

unexplained part of the signal. GLM was applied to a 60-s interval that was set to 15 s before

and 45 s after the onset of the HRF$_{sim}$. The GLM allowed us to estimate how much of the signal's

variance (R^2) could be predicted by the HRF$_{sim}$. This estimation was conducted for the initial signal

without artifacts (NIRS$_{ini}$ + HRF$_{sim}$), the uncorrected signal with a simulated artifact, and for the

corrected signal.

2.9 Statistical analysis

Quality and similarity measures were computed for each channel separately and then averaged

across channels for statistical analysis. Prior to statistical analysis, correlation coefficients (R and

Rλ) were standardized using Fisher's transformation to obtain values following a normal

distribution. For the real task-based data, we conducted statistical analysis to compare the signal

quality metrics among the motion artifact correction techniques. A repeated measures ANOVA

including PARAFAC, tPCA, ICA and the uncorrected reference signal as the within factor, was

performed independently for the mean of each metric across all channels (i.e. SNR, Rλ). In case

of the Rλ, the reference of the baseline (non-artifacted signal) was included as another condition.

Follow-up paired contrasts were conducted with a critical alpha of 0.05. For the simulations, we

applied a repeated measures ANOVAs to compare the mean outcome of the quality and similarity

metrics between the different simulations, i.e. 1a-e for the amplitude scaling, 2a-2f for the complex

artifacts and 3a-d for the HRF$_{sim}$, and within correction condition, i.e. PARAFAC, tPCA, and the

uncorrected signal. Tukey correction for multiple comparisons was applied for post-hoc analysis.

3   Results

3.1 Correction of non-simulated task-related motion artifacts

First, decomposition with PARAFAC was applied for the correction of real task-based motion

artifacts. The signal's quality (SNR, Rλ) after correction with PARAFAC was evaluated and

compared to the signal before correction (Uncorrected), the signal after correction with two 2D

decomposition techniques (i.e. tPCA and ICA), and a reference signal of a segment without

artifacts (Rλ only).

Fig. **5** provides an example of target artifact correction with PARAFAC illustrating the 3D

decomposition for a motion artifact detected in the real task-based signal. The time course of the

three components obtained with PARAFAC allowed to differentiate between the two components

with distinct artifact signatures, and the one component representing the clean signal. Spatial

distribution of each component is shown as a loading matrix and helps to identify in which

channels (localization) the artifact's signatures were most important. The two components that

appear to represent the artifact showed similar scores for both wavelengths, as represented in the

wavelength signatures. Subsequently, removal of PARAFAC first and second components resulted

in a less noisy time interval and satisfyingly corrected signal.

Fig. 5 Example of target 3D PARAFAC decompositions to correct motion artifacts in a task-based fNIRS data set. Panel A Shows the initial uncorrected data segment. In panel B the temporal, spatial (channel) and wavelength ($\lambda1|2 = 690|830$ nm) signatures of the components identified with PARAFAC decomposition are presented, respectively. Panel C shows the corrected signal, illustrating the efficacy of movement artifact correction with PARAFAC after subtraction of two components (1 & 2). Y-axis is presented in arbitrary units.

Automatic and manual artifact detection agreed on a majority of the signal with an average concordance of 92.8%, so only minor manual adjustments had been applied. A total of 585 different artifactual events, on average 66 events per subject with a mean, minimal and maximal duration of 5, 0.7 and 21.2 s, respectively, were considered for correction. Comparison of the SNR included measures of every channel of both wavelengths. Repeated-measures ANOVA with Greenhouse-Geisser correction for the SNR of all conditions (Uncorrected, PARAFAC, tPCA and ICA) revealed a significant main effect, $F_{(2.3, 44966.3)} = 7550.7$, $p < 0.001$, $\eta = 0.28$. The uncorrected signal had the largest ratio of noise (-0.69), followed by the signal after ICA correction (-0.50), tPCA correction (-0.33), and PARAFAC correction (-0.31) (see Table 1). Pairwise contrasts [52] revealed that PARAFAC correction resulted in a significantly higher SNR compared to the uncorrected signal ($\eta = 0.45$), and the signal after correction with ICA ($\eta = 0.13$), both having a large effect size. Comparison of PARAFAC and tPCA, though statistically significant, revealed only a small effect size ($\eta = 0.002$). Repeated-measures ANOVA with Greenhouse-Geisser correction for the Rλ revealed a significant difference between the five conditions: $F_{(3.2, 30999.0)} = 2686.46$, $p < 0.01$, $\eta = 0.22$. Mean Rλ coefficients showed the highest association between

wavelengths for the uncorrected signal (0.74), followed by the signal after ICA correction (0.67),

tPCA correction (0.53), PARAFAC correction (0.51) and the artifact-free reference signal (0.47)

(see Table 1). Contrasts of Rλ coefficients between PARAFAC and ICA ($p = 0.14$, large effect) as

well as the uncorrected signal ($p = 0.35$, large effect) suggested that wavelengths were greatly less

correlated after PARAFAC correction. Correction with PARAFAC resulted in slightly higher Rλ

coefficients compared to segments without artifacts (artifact-free reference, $p = 0.01$, small effect),

and slightly lower Rλ coefficients compared to correction with tPCA ($p = 0.01$, small effect).

Table 1 Mean quality metrics for the evaluation of artifact correction in the task-based data set

[Mean ± SD]	Artifact-free reference	PARAFAC	tPCA	ICA	Uncorrected artifact reference
Signal-to-noise ratio (dB)	N/A	-0.31 ± 0.58	-0.33 ± 0.57	-0.50 ± 0.64	-0.69 ± 0.65
Pearson's correlation between wavelengths (Rλ)	0.47 ± 0.33	0.51 ± 0.38	0.53 ± 0.38	0.67 ± 0.38	0.74 ± 0.29

Note. Results are displayed for the three decomposition techniques, parallel factor analysis (PARAFAC), target
principal component analysis (tPCA) and independent component analysis (ICA), as well as for two reference signals,
an artifact-free segment retrieved from the baseline before task onset, and the uncorrected signal consisting of all
artifact segments before correction was applied.

3.2 Correction of simulated motion artifacts

As a second step, we evaluated the performance of PARAFAC to correct simulated artifacts with

varying parameters, see Fig. 3 for the composition of the different scenarios. Three similarity

indices (PRD, RMSE, R) for the agreement of the initial (NIRS$_{ini}$) and the corrected signal

(NIRS$_{PARAFAC/tPCA}$), two quality measures (SNR, Rλ) and the reconstruction of the synthesized

HRF were used to quantitatively compare performance of PARAFAC to tPCA. The sample for

each index (PRD, RMSE, R, SNR) consisted of 164 measures, corresponding to channels of both

wavelengths. Since Rλ is a correlation coefficient between both wavelengths, the sample consisted

of 82 values. For each simulation condition (1a-e, 2a-f, 3a-d), indices were computed for three

correction conditions (=within-subject factor), i.e. the signal corrected with PARAFAC or tPCA

and the uncorrected signal.

Repeated measures ANOVA with Greenhouse-Geisser correction revealed statistically

significant interactions for the type of correction and 1) the amplitude size (1a-e), PRD: F (8, 1630)

= 67.14, $p < 0.001$, $\eta^2_{partial} = 0.248$; RMSE: F (8, 1630) = 132.35, $p < 0.001$, $\eta^2_{partial} = 0.394$; R: F

(8, 1630) = 94.01, $p < 0.001$, $\eta^2_{partial} = 0.316$; SNR: F (8, 1630) = 214.90, $p < 0.001$, $\eta^2_{partial} =$

0.513; Rλ: F (8, 810) = 115.96, $p < 0.001$, $\eta^2_{partial} = 0.534$; 2) the onset delay of the second artifact

(2a-f), PRD: F (10, 1956) = 4.98, $p < 0.001$, $\eta^2_{partial} = 0.025$; RMSE: F (10, 1956) = 8.93, $p <$

0.001, $\eta^2_{partial} = 0.044$; R: F (10, 1956) = 7.82, $p < 0.001$, $\eta^2_{partial} = 0.038$; SNR: F (10, 1956) =

7.18, $p < 0.001$, $\eta^2_{partial} = 0.035$; Rλ: F (10, 972) = 2.36, $p = 0.01$, $\eta^2_{partial} = 0.024$; and 3) the onset

of the artifact relative to the HRF$_{sim}$ (3a-d), PRD: F (6, 1304) = 26.67, $p < 0.001$, $\eta^2_{partial} = 0.109$;

RMSE: F (6, 1304) = 52.74, $p < 0.001$, $\eta^2_{partial} = 0.195$; R: F (6, 1304) = 63.23, $p < 0.001$, $\eta^2_{partial}$

= 0.225; SNR: F (6, 1304) = 61.31, $p < 0.001$, $\eta^2_{partial} = 0.220$; Rλ: F (6, 648) = 22.06, $p = 0.009$,

$\eta^2_{partial} = 0.170$. Results of post-hoc comparisons with Tukey correction are illustrated in Fig. 6.

using the example of PRD. The results of the other indices are mostly in line with those. Detailed

results for the RMSE, R, SNR and Rλ can be found in the Supplemental Material in Fig. S2,Fig.

S3, Fig. **S4**, andFig. **S5**, respectively.

Fig. 6 Evaluation of correction in simulated motion artifacts based on signal similarity. Simulations are identified on the x-axis. A: 1a-e) artifacts with different amplitude sizes; B: 2a-f): complex artifacts with two superimposed artifacts and an onset delay between the 1^{st} (A_1) and 2^{nd} artifact (A_2); and C: 3a-d) the onset of the artifact relative to the beginning of a simulated HRF. Performance of artifact correction is illustrated by the use of the similarity index percent root difference (PRD), where a lower value represents higher resemblance between the corrected and the initial clean fNIRS signal, hence a better correction of the artifact. Results are displayed separately for the correction with PARAFAC (light grey bars) and tPCA (grey bars). The PRD of the uncorrected signal is not displayed in this figure but differed significantly from both correction techniques in all conditions, except where specified (n.s.) otherwise inside the bar. Significance level are based on post-hoc tests with Tukey correction. *** $p \leq 0.001$, n.s. $p > 0.05$. Uncorrected = $NIRS_{ini}$ + artifact (A_1) without correction, PARAFAC = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with PARAFAC, tPCA = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with tPCA.

Simulations 1a-e included artifacts with extra small, small, medium, large and extra-large

amplitudes. Similarity indices (PRD, RMSE, R) revealed that both PARAFAC and tPCA resulted

in a significant higher resemblance of the corrected signal and the initial signal compared to the

uncorrected condition for all amplitude sizes except for the artifact with an extra small amplitude

where tPCA did not lead to a significant improvement compared to the uncorrected signal.

Similarly, both correction methods led to a significantly higher signal quality, i.e. lower SNR and

$R\lambda$, compared to the uncorrected signal with the same exception for tPCA in the extra small

amplitude, where no difference was observed to the uncorrected signal. When artifacts had a small,

medium or extra-large amplitude, correction methods obtained comparable results over all indices

and did not statistically differ. The most consistent differences between correction methods can be

observed for the artifact with extra small and large amplitudes. While similarity metrics and quality

measures revealed that PARAFAC achieved significantly better results than tPCA for the

correction of artifacts with an extra small amplitude, for artifacts with a large amplitude tPCA

seemed to have a slight but statistically significant advantage as compared to PARAFAC.

Simulations 2a-f led to signals with different onset delays (1s, 2s, 3s, 4s, 5s, 10s) between

two superimposed artifacts which allowed to create different complex artifacts. Over all

conditions, notwithstanding their onset delay, similarity indices indicated a significantly higher

overlap with the initial signal for the signal corrected with PARAFAC as compared to the one

corrected with tPCA and the uncorrected signal. Similarly, quality metrics revealed a significantly

higher signal quality after correction with PARAFAC compared to the correction with tPCA and

the uncorrected signal. Nevertheless, tPCA also resulted in statistically significant better results as

compared to the uncorrected signal in all conditions both with regard to the similarity metrics and

the quality measures.

In simulations 3a-d the onset of an artifact varied relative to the beginning of a simulated

HRF_{sim}: +0s, +5s, +15s, +30s. Independent of the onset of the artifact, correction with PARAFAC

resulted in a signal that showed a significantly higher overlap with the initial signal compared to

the uncorrected condition. Similarly, quality measures showed a significant improvement of the

signal's quality after correction with PARAFAC compared to the uncorrected signal. tPCA

achieved almost identical results as PARAFAC in comparison to the uncorrected signal, except

when the artifact was placed shortly after the beginning of the HRF_{sim} (+5s) for which PRD and

RMSE did not show a significant difference between the uncorrected signal and the one corrected

with tPCA. Further, for artifacts at the very beginning (+0s), shortly after (+5s) or at the very end

(+30s) of the HRF_{sim} (at the same time than the low-frequency increase or decrease that is intrinsic

to the HRF_{sim}), similarity indices revealed a significant better overlap of the corrected signal with

the initial signal after correction with PARAFAC as opposed to tPCA. In contrast, tPCA compared

to PARAFAC seemed to have a significant advantage for the correction of artifacts during the

plateau of the HRF_{sim} (+15s), which might be explained by a higher orthogonality between the

artifact and the signal at this onset. Quality measures however only partially support these findings,

namely in favor of correction with tPCA for the artifact at the beginning (+0s) and in favor of

PARAFAC for the artifact shortly after (+5s) the beginning of the HRF_{sim}. When the artifact is at

the very beginning of the HRF_{sim} (+0s), signal quality is however significantly higher after

correction with tPCA as compared to PARAFAC. There is no statistically significant difference

between signal quality for any of the correction methods when the artifact is placed at the very end

of the HRF_{sim} (+30s). Further, results of the GLM revealed that in none of the conditions the

simulated artifact led to an important reduction of the variance explained by the HRF_{sim} as

compared to the initial signal (see Table 2). In line with the results of the similarity metrics,

reconstruction of the HRF after correction with PARAFAC was qualitatively better as compared

to tPCA when the artifact occurred at the beginning (+0s), shortly after (+5s) and at the end (+30s)

of the HRF. In particular, for the artifact 5s after the onset of the HRF, reconstruction after

correction with tPCA seemed disturbed. There was no important difference between correction

methods for the reconstruction of the HRF when the artifact was during the plateau of the HRF

(+15s).

Table 2 Percentage of explained variance by the HRF_{sim} based on the R^2 of the general linear model

[Mean ± SD]	**Initial**	**Uncorrected**	**PARAFAC**	**tPCA**
3a: HRF+0s	95.16 ± 16.24	94.88 ± 16.49	95.18 ± 15.69	94.23 ± 18.33
3b: HRF+5s	95.16 ± 16.24	94.43 ± 7.84	94.54 ± 7.78	86.96 ± 12.81
3c: HRF+15s	95.16 ± 16.24	95.00 ± 16.16	95.10 ± 16.27	95.18± 16.20
3d: HRF+30s	95.16 ± 16.24	95.14 ± 16.25	94.92 ± 16.26	91.83 ± 15.89

Note. Initial = $NIRS_{ini}$ + HRF_{sim}, Uncorrected = $NIRS_{ini}$ + artifact (A_1) without correction,
PARAFAC/tPCA = $NIRS_{ini}$ + A_1 after artifact correction with PARAFAC/tPCA.

Orthogonality measure for the relation of the time courses of the raw signal and the artifact

signal (Raw x A_1: r_a) were calculated for all simulations, orthogonality for the time courses of the

raw signal with the first artifact and the second artifact (RawA_1 x A_2: r_b) was only computed for

simulations of complex artifacts (2a-f). A value of 1, represented maximum orthogonality between

both signals meaning they are in a 90 degrees angle to each other. Any value smaller than 1 or

even 0 indicated non-orthogonality meaning that they are in any other angle than 90 degrees,

maximally 0 or 180 degrees to each other. Results of r_a revealed consistently high orthogonality

for all simulations with varying amplitudes (Min = Max = 0.97) and with complex artifacts (Min

= 0.97, Max = 0.98). Orthogonality for the simulations with the HRF revealed more variations

(Min = 0.88, Max = 0.97) where the artifact 30s after the HRF_{sim} created the least orthogonal

condition (Median ± standard error: 0.88 ± 0.03), followed by the simulation with the artifact at 0s

(Median ± standard error: 0.93 ± 0.05), 5s (Median ± standard error: 0.96 ± 0.01) and 15s (Median

± standard error: 0.97 ± 0.01) of the HRF_{sim}. Results of the second orthogonality measure r_b

indicated that the onset delay of 2s led to the least orthogonal condition (Median ± standard error:

0.75 ± 0.07), followed by the delay of 3s (Median ± standard error: 0.93 ± 0.02) and 5s (Median ±

standard error: 0.98 ± 0.02). When the second artifact had a delay of 1s, 4s or 10s, there was equally

high orthogonality for all three conditions (Median ± standard error: 0.99 ± 0.02).

4   Discussion

Promising results have been reported by using parallel factor analysis (PARAFAC) for

multidimensional (n ≥ 3) data analysis in EEG data [13,28,42]. Since the fNIRS signal has inherently

three dimensions, time × space × wavelength, we aimed to extend the application of PARAFAC

to fNIRS and validate its use for artifact correction. First, we explored the usefulness of PARAFAC

to correct movement artifacts in a data set of task-related fNIRS signals acquired during an

expressive language paradigm. Performance of artifact correction was evaluated by the use of two

signal quality metrics, (1) the SNR considering the signal's variance during the simulated intervals

after correction; and (2) the temporal similarity between both wavelengths during the simulated

intervals after correction (Pearson's correlation Rλ). Quality measures after correction with

PARAFAC were compared to those obtained after the use of two commonly used decomposition

methods in fNIRS (i.e. tPCA and ICA). Secondly, several scenarios with simulated artifacts in a

clean resting-state signal were computed to assess the performance of artifact correction with

PARAFAC and its homologue 2D target decomposition technique (tPCA) in a controlled setting.

Simulated artifacts had five amplitude sizes, 6 levels of temporal overlap with a second artifact to

create complex artifactual events and were added at four different time points of a simulated HRF.

We compared the performance of both correction methods using (1) similarity indices describing

the degree of correspondence between the corrected signal after removal of simulated artifacts and

the artifact-free signal before simulation (RMSE, PRD, and R); and (2) the two quality measures,

SNR and Rλ, already used for the task-related signal.

With regard to motion artifact correction in the task-based data set, the signal after artifact

correction with PARAFAC had the smallest signal-to-noise ratio among the three methods

(PARAFAC, tPCA, ICA), suggesting that more of the variance related to the artifact had been

removed and a better signal quality was achieved. Similarly, correction with PARAFAC led to the

lowest correlation between HbO and HbR indices, as well as the correlation index that most

resembled the non-artifactual resting-state baseline reference. Even though the resting-state signal

has been reported to show slightly different hemodynamic changes as compared to a stimuli-

induced cerebral activity [17,53], we consider it a suitable reference for a time interval without

artifacts, because it was not affected by articulation. In line with previous findings, our analyses

also revealed a robust advantage in applying target corrections (tPCA and PARAFAC) instead of

whole-block (ICA) correction, resulting in a better signal quality [14,18]. ICA was indeed applied to

the entire signal as reported in the literature [17], while tPCA and PARAFAC were used in a target

manner, i.e. only decomposing the signal during specific intervals where artifacts had been

detected. As proposed by Yücel and colleagues [3], target artifact correction prevents large changes

in the overall composition of the signal, and exclusively corrects the noisy time interval of the

artifact. It allows the decomposition to clearly sort a component representing the artifact signature,

without considering the characteristics of these channels during the intervals without artifacts.

Target decomposition is thus beneficial for a precise identification of the artifact's signatures and

PARAFAC for artifact correction in fNIRS should also be applied in a target manner.

Results of the conducted simulations with controlled parameters suggest that artifact

correction with PARAFAC led to a signal that corresponded more closely to the initial signal, as

compared to the uncorrected signal. Similarly, PARAFAC yielded a significant better signal

quality as compared to the uncorrected signal. This result is a preliminary validation of the use of

PARAFAC for artifact correction in fNIRS signals and similarity measures show that the signal

comes close to the original signal, thus it does not remove large parts of the physiological or

relevant activity. While correction with tPCA in most cases also led to better results compared to

the uncorrected signal, it has to be mentioned that its performance was less consistent over

conditions. Further, in almost all scenarios correction with PARAFAC compared to tPCA led to

either better or comparable results. Especially, when the artifact was simulated along with a

simulated HRF, PARAFAC showed superior and more robust results compared to tPCA.

According to the applied orthogonality measure, those conditions where tPCA showed a poor

performance were exactly those where the artifact and the simulated HRF were less orthogonal.

This is in line with the assumption that decomposition with PARAFAC is not affected by non-

orthogonality. Only in two simulations, namely when the artifact had a large amplitude or was

during the plateau of the simulated HRF (where the orthogonality between the HRF_{sim} and the

artifact was the highest), correction with tPCA outperformed PARAFAC. Finally, results of the

GLM indicate that artifact correction with PARAFAC did not affect the recovery of the simulated

HRF, which suggests that it successfully targeted the artifact signature and did not induce changes

of the signal that would alter interpretation of the underlying hemodynamic response. Even though

this is an encouraging result, it has to be mentioned that similar results were achieved for the

HRF$_{sim}$ of the uncorrected signal, suggesting that the simulated artifact did not have a very strong

impact on the signal and the interpretation of the HRF$_{sim}$. This could be different for more complex

or larger artifacts where correction may not sufficiently work. In most cases correction with tPCA

allowed a similarly good recovery of the simulated HRF, but was strongly affected when an artifact

was placed shortly after the beginning of the HRF$_{sim}$, i.e. when the assumption of orthogonal

artifact is not perfectly met. This is in line with the findings for the similarity and quality metrics

for this scenario.

Regarding the comparison of both targeted decomposition techniques, the small effect size

of the difference between tPCA and PARAFAC in the task-based data set suggests that both target

correction techniques led to a similar reduction of the variance induced by motion artifacts and to

an equal reduction of correlation between both wavelengths. Even though correction of simulated

artifacts outlined certain advantages of PARAFAC compared to tPCA in some conditions, there

was no consistent difference between both methods when applied to large data sets of real

movement artifacts in a verbal fluency task. Since it was previously emphasized that performing

accurate simulations of real motion artifacts is challenging, validation of an artifact correction

technique in real data is a crucial step [7]. We can conclude that its performance both in real and

simulated data was generally equally good as tPCA and slightly better under certain conditions,

suggesting the validation of PARAFAC as a new tool for artifact correction in fNIRS data.

What is more, PARAFAC's core strength compared to tPCA is mainly related to its

conceptualization. The use of a decomposition approach considering the multidimensional

structure of the fNIRS signal where a unique decomposition is achieved with few constraints, i.e.

without imposing orthogonality nor independence, is appropriate and seems advantageous

compared to tPCA as well as ICA [42,54]. Even though the results of the simulations provide some

support that artifact correction with PARAFAC was not affected by non-orthogonality,

orthogonality did not sufficiently vary among simulations and mostly reached a high orthogonality

as we used resting state as background data. Nevertheless, given that in real data, the ground truth

about the signal's composition of noise is unknown and orthogonality cannot be verified, it is safe

to say that PARAFAC represents a robust approach for artifact correction in fNIRS. Two-

dimensional decomposition, such as ICA and tPCA, analyzes both wavelengths as independent

measures of the fNIRS signal, even though they are in fact highly related, since they are acquired

at the same location [4]. Since the estimation of the hemodynamic signal is based on the signal of

both wavelengths [47], reliable conclusions require the signal to be clean in both of them. It is also

worth to notice that for artifact correction, we have followed in all our simulations the assumption

that both wavelengths are affected by artifacts equally across channels (just with a different general

scale). This is in fact the worst case for PARAFAC, as it will give better results if there are larger

differences in all dimensions of the data. Therefore, we could expect an improved performance

when artifacts have even small differences between the spatial distributions for the two

wavelengths.

Decomposition with PARAFAC offers a rather easy way to make a selection of relevant

components that differentiate between signatures related to artifacts or other relevant

characteristics of the signal. Even if fNIRS is considered to be less sensitive to movements -as

compared to other neuroimaging techniques such as fMRI and signal quality should be controlled

during data acquisition as much as possible, appropriate tools for artifact correction are an essential

part of preprocessing in fNIRS, particularly for data acquired in populations where cooperation is

limited, such as children and clinical populations [7,55,56]. PARAFAC thus appears to be a suitable

and robust alternative to the currently used approaches and will be a valuable add-on for fNIRS

studies and clinical examinations by minimizing the amount of non-usable data and improving

data quality. That being said, the researcher always has to weigh the means of applying artifact

correction and should not do so without visual inspection of the decomposition signature. It is the

overall quality of a data set, i.e. the amount of clean signal, and the duration, extent and moment

of the artifact that ought to influence the researcher's choice to reject data sets, to apply artifact

correction and to proceed with analysis.

4.1 Usefulness and limitations of PARAFAC

PARAFAC is a data-driven approach based on the linear relations of the three dimensions of the

fNIRS signal [23,26,28]. PARAFAC has the advantage of allowing for the three-way arrays of data to

be uniquely decomposed into a sum of components, each of which is a trilinear combination of

factors or signatures. The only statistical requirements of PARAFAC is that of a moderate linear

independence across components, i.e. their time course, topography and wavelength

characteristics. This is a less stringent requirement than previous models that underlie space/time

decompositions (PCA or ICA). Each component provides characteristics of a particular pattern

identified within the mixed measured fNIRS signal. When there are empirical or theoretical

reasons to expect more than one relevant component (e.g. resting state functional connectivity

analysis, epileptic activity, physiological aspects, etc.), PARAFAC would also allow disentangling

several components. Moreover, when there are reasons to include other constraints such as

orthogonality, non-negativity, smoothness and sparseness of the signatures, it has been shown that

PARAFAC can also include them in the decomposition procedure [23,57,58].

Different from ICA, PARAFAC components can be ordered according to their importance

in explaining the data's variance [59]. This is why many studies using ICA apply data reduction or

clustering techniques such as PCA prior to the execution of ICA [17,60]. Moreover, when using

PARAFAC, the description of the data is based on more dimensions, and with less theoretical

constraints (orthogonality, independence) which lead to the identification of fewer relevant

components [13,28,61,62]. Compared to ICA, the selection of the relevant components is thus

simplified. Importantly, when using PARAFAC, it is not recommended to ask for more than five

components, as this increases the risk of overfitting the data with the decomposition model.

Usually, three to five components sufficiently describe the signal's relevant characteristics [29].

Similar to PCA, a typical choice made when using PARAFAC analysis, is that of ordering the

extracted components according to their contribution to explaining the variance of the data. In this

sense, it can be expected that the first PARAFAC component will always represent the highest

activity, which, in the case of target artifact correction, will correspond to the artifact activity. This

makes PARAFAC also a promising choice to explore the development of simple automatic

methodologies for the detection and correction of such artifacts and future studies should be

devoted to this aim.

Some challenges of PARAFAC have already been discussed in previous studies [13,28]. One

limitation is related to PARAFAC's assumption of linear relations of the temporal characteristics

between different channels (which also applies to (t)PCA and ICA). Despite being one of the most

common and simple models, imposing linearity may not entirely reflect complex cerebral

processes [63]. Some attempts have been made to introduce approaches that tolerate non-linear

relations [64,65]. However, to date, linear models remain the most popular and adequate approach for

analysis of macroscopic data in neuroscience. Thus, it represents a general limit of the domain,

rather than one specific to PARAFAC. Another potential limitation of our implementation of

PARAFAC might arise from the specific use of the simple alternating least-squares algorithm to

perform the decomposition. Other methods have been proposed for estimating PARAFAC models,

but some studies have shown that, given the uniqueness of the solution, they do not usually

outperform the simple least-squares technique [66].

The need for careful preprocessing of data before characterizing brain activity constitutes

another limitation. When PARAFAC was introduced for the analysis of EEG data, the authors

emphasized the importance of searching for constant factors, outliers, and degeneracy [13,27].

Detailed information on how to deal with these aspects can be found in previous literature [13]. In

the current study, the implementation of PARAFAC into the LIONirs toolbox [35], gave us a certain

flexibility regarding the channels and time segments to be included. Thus, we were able to exclude

deviant channels prior to use PARAFAC.

Finally, among the applications of PARAFAC not yet tested in fNIRS, is its use to identify

patterns of brain activity in the hemodynamic response as it has been applied in EEG data analysis

[13,29,42]. Compared to other techniques such as GLM or global averaging who treat each channel

independently and provide a narrower spatial representation of the dominant activation,

PARAFAC analysis could reveal a wider distributed activation pattern. This would strongly

correspond to the current understanding of cerebral processing, whereby mostly large-scale

networks, and not isolated regions, are considered to be involved in various cognitive processes

[55,67,68]. PARAFAC could thus appear to be suitable for reflecting cerebral processes occurring in

distributed networks, rather than for the identification of a specific core region. This is obviously

given a sufficient fNIRS covering. Moreover, the topographic signature would correspond to a

whole time course of the extracted activations and can easily be subjected to diffusion optical

tomography in order to locate the HbO and HbR concentration changes in the brain cortex [69].

Another potential application is using PARAFAC as a screening tool. For instance, Miwakeichi

and colleagues [13] applied PARAFAC to an EEG dataset in order to extract one component related

to ocular movement artifacts, and subsequently used the PARAFAC analysis fixing spatial and

spectral signatures of that component to screen a second dataset in order to identify and correct

similar artifacts. This application can also support the development of a detection method as has

already be done in other fields such as detection of epileptic seizures [29,70] and for brain-computer

interfacing [71–74]. Although this can be useful for correcting artifacts that have consistent

topographical and wavelength profiles, movement artifacts were mostly related to articulation in

our study, often showing quite different signatures. A different paradigm may enable the testing

of this application of PARAFAC in fNIRS.

Our findings also encourage the general application of PARAFAC for multidimensional

decomposition in neuroimaging, where data can often be described in more than two dimensions.

Beyond the obvious dimensions of a technique such as that of time $\times$ space $\times$ wavelength (fNIRS)

or frequency (EEG), characteristics of the task paradigm or group variables could also be

considered in the decomposition model [42]. For instance, if a "group" dimension was to be included,

groups could be compared regarding their relative weight over the main cerebral activation

component that would have been outlined from the PARAFAC model.

4.2 Limits of the current study

The use of a language paradigm allowed for the induction of artifacts that were mainly related to

articulation, which limits the generalization from our results. From video recordings, however, we

were able to acknowledge that swallowing, jaw or tongue movements, eye blinks, and frowning

also induced artifacts in our dataset. Even though the simulated artifacts were also based on one

identified during the task-condition, parameters were modified and allowed to create noise with

different characteristics. Further fNIRS studies using PARAFAC, and including different task

paradigms, resting-state, and recording in naturalistic environments when participants are moving,

could show its utility for a wider range of artifacts (e.g. baseline shifts or physiology).

The validation of PARAFAC for artifact correction was conducted by comparing results

with two other decomposition techniques. This could be considered one limit of the present study,

because we did not consider other correction approaches for comparison. The objective of this

study was not to conduct exhaustive and systematic comparisons in order to identify the best

method for artifact correction, but rather to introduce PARAFAC as an alternative and adequate

method in fNIRS analysis. Future studies could therefore expand the validation of PARAFAC and

extend comparisons of its performance to other tools that do not necessarily use decomposition,

such as spline interpolation or wavelet filtering. With relation to that, even if there were to be a

slight advantage of PARAFAC over tPCA in artifact correction results, the small difference might

not have a concrete impact on the applicability of those two methods. Qualitative differences

between tPCA and PARAFAC regarding the type of artifacts and corrected signal should be further

assessed and described in subsequent studies to better understand how their efficacy may vary

according to the artifact's characteristics.

Last but not least, PARAFAC's components related to artifacts were selected during a

visual inspection based on their temporal overlap with the artifact, i.e. sudden change of amplitude,

and those showing similar weights for both wavelengths. The smallest number of possible

components that sufficiently corrected the artifact were selected. Even though our results show

that this procedure led to satisfying correction, it is not a fully standardized procedure which may

hamper an easier, automatic correction that would reduce the need of the researcher's expertise in

detecting and adequately applying correction. This issue could be addressed using the screening

procedure mentioned in the previous section or using other templates for the artifacts of interest or

by applying the usual automatic rules based on amplitude characteristics to the temporal signatures

obtained by PARAFAC instead of the original mixed data. The goal of the current study was not

to propose a method for artifact detection but to validate the relative efficacy of these methods in

artifact correction. It would be interesting for future studies to address the development of a more

automatic procedure based on PARAFAC analysis contributing to a faster and standardized

processing pipeline.

5   Conclusions

PARAFAC has the advantage to simultaneously treat both wavelengths or HbO and HbR during

fNIRS data analyses. Our findings from real task-related signals and controlled simulations

validate previous results in EEG data and promote multidimensional decomposition with

PARAFAC as a promising new tool for the correction of movement artifacts in fNIRS. Precisely,

PARAFAC achieves comparable results as tPCA when the artifact's signature is simple and clearly

distinguishable from the signal. It outperforms tPCA mainly when artifacts have small amplitude,

show a complex temporal signature or when they co-occur during an HRF. These results can

partially be attributed to low orthogonality between signal and noise. The advantages of

PARAFAC and tPCA, as compared to ICA, are consistent and seem to be due to the target

application. Further, PARAFAC has a strong advantage compared to both 2D decomposition

techniques because it offers a unique decomposition without orthogonality or independence

constraints, hence represents a robust decomposition technique. The validation of its use paves the

way for future use in fNIRS research to extract relevant signatures represented in the fNIRS signal.

6 Supplemental Material

851
Fig. S1 Parameters of all simulations. A real motion artifact ($A_{1/2}$) and a synthesized HRF (HRF_{sim}) were added to a normalized resting-state fNIRS signal

(Raw). A shows simulations 1a-e with an artifact of varying amplitude sizes, B simulations 2a-f with a complex artifact where the onset of the second artifact

(A_2) was varied relative to the onset of the first artifact (A_1), and C simulations 3a-d with varying onset of the artifact relative to the beginning of the HRF_{sim}.

$\lambda1|2 = 690|830$ nm.

Fig. S2 Evaluation of correction in simulated motion artifacts based on signal similarity by the use of the root mean square error (RMSE). Simulations

are identified on the x-axis. A: 1a-e) artifacts with different amplitude sizes; B: 2a-f): complex artifacts with two superimposed artifacts and an onset

delay between the 1st (A_1) and 2nd artifact (A_2); and C: 3a-d) the onset of the artifact relative to the beginning of a simulated HRF. A lower RMSE

represents higher resemblance between the corrected and the initial clean fNIRS signal, hence a better correction of the artifact. Results are displayed

separately for the correction with PARAFAC (light grey bars) and tPCA (grey bars). The RMSE of the uncorrected signal is not displayed in this figure

but differed significantly from both correction techniques in all conditions, except where specified otherwise inside the bar. Significance level are based

on post-hoc tests with Tukey correction. * $p \leq 0.05$, *** $p \leq 0.001$, n.s. $p > 0.05$. Uncorrected = $NIRS_{ini}$ + artifact (A_1) without correction, PARAFAC =

$NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with PARAFAC, tPCA = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with tPCA.

865
Fig. S3 Evaluation of correction in simulated motion artifacts based on signal similarity by the use of the Pearson product-moment correlation coefficient

(R). Simulations are identified on the x-axis. A: 1a-e) artifacts with different amplitude sizes; B: 2a-f): complex artifacts with two superimposed artifacts

and an onset delay between the 1st (A_1) and 2nd artifact (A_2); and C: 3a-d) the onset of the artifact relative to the beginning of a simulated HRF. A higher R

represents higher resemblance between the corrected and the initial clean fNIRS signal, hence a better correction of the artifact. Results are displayed

separately for the correction with PARAFAC (light grey bars) and tPCA (grey bars). The R of the uncorrected signal is not displayed in this figure but

differed significantly from both correction techniques in all conditions, except where specified otherwise inside the bar. Significance level are based on

post-hoc tests with Tukey correction. *** $p \leq 0.001$, n.s. $p > 0.05$. Uncorrected = $NIRS_{ini}$ + artifact (A_1) without correction, PARAFAC = $NIRS_{ini}$ + artifact

(A_1/A_2) after artifact correction with PARAFAC, tPCA = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with tPCA.

874
Fig. S4 Evaluation of correction in simulated motion artifacts based on signal quality by the use of the signal-to-noise ratio (SNR). Simulations are identified

on the x-axis. A: 1a-e) artifacts with different amplitude sizes; B: 2a-f): complex artifacts with two superimposed artifacts and an onset delay between the

1^{st} (A_1) and 2^{nd} artifact (A_2); and C: 3a-d) the onset of the artifact relative to the beginning of a simulated HRF. An SNR closer to 0 represents a more equal

ratio between the signal's variation during the artifact period and the clean signal. Results are displayed separately for the correction with PARAFAC (light

grey bars) and tPCA (grey bars). The SNR of the uncorrected signal is not displayed in this figure but differed significantly from both correction techniques

in all conditions, except where specified otherwise inside the bar. Significance level are based on post-hoc tests with Tukey correction. * $p \leq 0.05$, *** $p \leq$

0.001, n.s. $p > 0.05$. Uncorrected = $NIRS_{ini}$ + artifact (A_1) without correction, PARAFAC = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with

PARAFAC, tPCA = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with tPCA.

883
Fig. S5 Evaluation of correction in simulated motion artifacts based on signal quality by the use of the Pearson's correlation between wavelengths ($R\lambda$).
Simulations are identified on the x-axis. A: 1a-e) artifacts with different amplitude sizes; B: 2a-f): complex artifacts with two superimposed artifacts and an
onset delay between the 1st (A_1) and 2nd artifact (A_2); and C: 3a-d) the onset of the artifact relative to the beginning of a simulated HRF. $R\lambda$ in a clean signal is
usually lower than in artifacted signals. Results are displayed separately for the correction with PARAFAC (light grey bars) and tPCA (grey bars). The $R\lambda$ of
the uncorrected signal is not displayed in this figure but differed significantly from both correction techniques in all conditions, except where specified otherwise
inside the bar. Significance level are based on post-hoc tests with Tukey correction. *** $p \leq 0.001$, n.s. $p > 0.05$. Uncorrected = $NIRS_{ini}$ + artifact (A_1) without
correction, PARAFAC = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with PARAFAC, tPCA = $NIRS_{ini}$ + artifact (A_1/A_2) after artifact correction with
tPCA.

7 Disclosures

We have nothing to disclose.

8 Acknowledgments/Funding sources

The authors warmly thank all participants of the study, as well as Catherine Bernard, Kathya Martel and Solène Fourdain for their support during data acquisition.

This work was funded by the National Science and Engineering Research Council of Canada (NSERC) (#2015-04199 and # CGSD3-518503-2018); the Canada Research Chairs (#950-232661); the Ministère des Affaires internationales et de la Francophonie du Québec; the Fonds de Recherche du Québec Santé (FRQS, #28811 and #35450); the Fonds de recherche du Québec – Nature et technologies (FRQNT, #255473); the SickKids Foundation (#NI16-058); the Quebec Bio-Imaging Network (QBIN, FRQS - Réseaux de recherche thématique, #35450); the Savoy Foundation, and Graduate and Postdoctoral Studies Faculty (ESP) of the Université de Montréal.

9 References

1. F. F. Jobsis, "Noninvasive, infrared monitoring of cerebral and myocardial oxygen sufficiency and circulatory parameters," Science **198**(4323), 1264–1267, American Association for the Advancement of Science (1977) [doi:10.1126/SCIENCE.929199].

2. S. Lloyd-Fox, A. Blasi, and C. E. Elwell, "Illuminating the developing brain: The past, present and future of functional near infrared spectroscopy," Neuroscience and Behavioural Reviews **34**, 269–284 (2010) [doi:10.1016/j.neubiorev.2009.07.008].

3. M. A. Yücel et al., "Targeted principle component analysis: A new motion artifact correction approach for near-infrared spectroscopy," Journal of Innovative Optical Health Sciences **07**(2), 1350066 (2014) [doi:10.1142/S1793545813500661].

4.   X. Cui, S. Bray, and A. L. Reiss, "Functional near infrared spectroscopy (NIRS) signal

improvement based on negative correlation between oxygenated and deoxygenated

hemoglobin dynamics," Neuroimage **49**(4), 3039–3046 (2010)

[doi:10.1016/j.neuroimage.2009.11.050].

5.   R. J. Cooper et al., "A systematic comparison of motion artifact correction techniques for

functional near-infrared spectroscopy," Frontiers in Neuroscience **6**(OCT), 1–10 (2012)

[doi:10.3389/fnins.2012.00147].

6.   S. Tak and J. C. Ye, "Statistical analysis of fNIRS data: A comprehensive review,"

Neuroimage **85**, 72–91 (2014) [doi:10.1016/j.neuroimage.2013.06.016].

7.   S. Brigadoi et al., "Motion artifacts in functional near-infrared spectroscopy: A comparison

of motion correction techniques applied to real cognitive data," Neuroimage **85**, 181–191

(2014) [doi:10.1016/j.neuroimage.2013.04.082].

8.   H. Zhang et al., "Is resting-state functional connectivity revealed by functional near-infrared

spectroscopy test-retest reliable?," Journal of Biomedical Optics **16**(6), 067008 (2011)

[doi:10.1117/1.3591020].

9.   G. James et al., "Classification," in An Introduction to Statistical Learning, pp. 127–173,

Springer, New York, NY (2013) [doi:10.1007/978-1-4614-7138-7_4].

10.   X. Zhang et al., "Signal processing of functional NIRS data acquired during overt

speaking," Neurophotonics **4**(04), 1 (2017) [doi:10.1117/1.NPh.4.4.041409].

11.   K. Peng et al., "fNIRS-EEG study of focal interictal epileptiform discharges," Epilepsy

Research **108**, 491–505 (2014) [doi:10.1016/j.eplepsyres.2013.12.011].

12.   H. Becker et al., "Multi-way space-time-wave-vector analysis for EEG source separation,"

Signal Processing **92**, 1021–1031 (2011) [doi:10.1016/j.sigpro.2011.10.014].

13.   F. Miwakeichi et al., "Decomposing EEG data into space–time–frequency components using Parallel Factor Analysis," Neuroimage **22**(3), 1035–1045 (2004) [doi:10.1016/j.neuroimage.2004.03.039].

14.   H. F. Behrendt et al., "Motion correction for infant functional near-infrared spectroscopy with an application to live interaction data," Neurophotonics **5**(01), 1 (2018) [doi:10.1117/1.NPh.5.1.015004].

15.   S. Jahani et al., "Motion artifact detection and correction in functional near-infrared spectroscopy: A new hybrid method based on spline interpolation method and Savitzky-Golay filtering," Neurophotonics **5**(1), 1, SPIE-Intl Soc Optical Eng (2018) [doi:10.1117/1.NPh.5.1.015003].

16.   I. Tachtsidis and F. Scholkmann, "False positives and false negatives in functional near-infrared spectroscopy: issues, challenges, and the way forward," Neurophotonics **3**(3), 031405 (2016) [doi:10.1117/1.NPh.3.3.031405].

17.   H. Zhang et al., "Functional connectivity as revealed by independent component analysis of resting-state fNIRS measurements," Neuroimage **51**, 1150–1161 (2010) [doi:10.1016/j.neuroimage.2010.02.080].

18.   M. A. Kamran, M. M. N. Mannan, and M. Y. Jeong, "Cortical Signal Analysis and Advances in Functional Near-Infrared Spectroscopy Signal: A Review," Frontiers in Human Neuroscience **10**, 261 (2016) [doi:10.3389/fnhum.2016.00261].

19.   A. Jung et al., "Fastgeo-a histogram based approach to linear geometric ICA," in Proceedings of ICA Vol. 1, pp. 349–354 (2001).

20.   P. Comon, "Independent component analysis, A new concept?," Signal Processing **36**(3), 287–314 (1994) [doi:10.1016/0165-1684(94)90029-9].

21.   C. Jutten and J. Herault, "Blind separation of sources, part I: An adaptive algorithm based

on neuromimetic architecture," Signal Processing **24**(1), 1–10 (1991) [doi:10.1016/0165-

1684(91)90079-X].

22.   R. A. Harshman, "Foundations of the PARAFAC procedure: Models and conditions for an

'explanatory' multimodal factor analysis," in UCLA Working Papers in Phonetics **16**,

University Microfilms, Ann Arbor, Michigan (1970).

23.   R. Bro, "Multi-way Analysis in the Food Industry Models, Algorithms, and Applications,"

Royal Veterinary and Agricultural University (1998).

24.   J. D. Carroll and J.-J. Chang, "Analysis of individual differences in multidimensional

scaling via an n-way generalization of 'Eckart-Young' decomposition," Psychometrika

35(3), 283–319 (1970) [doi:10.1007/BF02310791].

25.   L. R. Tucker, "Some mathematical notes on three-mode factor analysis," Psychometrika

31(3), 279–311 (1966).

26.   J. Möcks, "Decomposing event-related potentials: A new topographic components model,"

Biological Psychology **26**(1–3), 199–215 (1988) [doi:10.1016/0301-0511(88)90020-8].

27.   A. S. Field and D. Graupe, "Topographic component (Parallel Factor) analysis of

multichannel evoked potentials: Practical issues in trilinear spatiotemporal decomposition,"

Brain Topography **3**(4), 407–423 (1991) [doi:10.1007/BF01129000].

28.   E. Martínez-Montes et al., "Concurrent EEG/fMRI analysis by multiway Partial Least

Squares," Neuroimage **22**(3), 1023–1034 (2004) [doi:10.1016/j.neuroimage.2004.03.038].

29.   E. Acar et al., "Multiway analysis of epilepsy tensors," Bioinformatics **23**(13), i10–i18

(2007) [doi:10.1093/bioinformatics/btm210].

30.   V. Calhoun, "Data-driven approaches for identifying links between brain structure and function in health and disease," Dialogues Clin Neurosci **20**(2), 87–99 (2018).

31.   G. H. Klem et al., "The ten-twenty electrode system of the International Federation," Electroencephalogr Clin Neurophysiol **52**(3), 3–6 (1999).

32.   W. D. Gaillard et al., "Developmental aspects of language processing: fMRI of verbal fluency in children and adults," Human Brain Mapping **18**(3), 176–185 (2003) [doi:10.1002/hbm.10091].

33.   N. Paquette et al., "Developmental patterns of expressive language hemispheric lateralization in children, adolescents and adults using functional near-infrared spectroscopy," Neuropsychologia **68**, 117–125 (2015) [doi:10.1016/j.neuropsychologia.2015.01.007].

34.   A. Gallagher, J. Tremblay, and P. Vannasing, "Language mapping in children using resting-state functional connectivity: comparison with a task-based approach," Journal of Biomedical Optics **21**(12), 125006 (2016) [doi:10.1117/1.JBO.21.12.125006].

35.   J. Tremblay et al., "LIONirs: flexible Matlab toolbox for fNIRS data analysis," Journal of Neuroscience Methods **370**, 109487, Elsevier (2022) [doi:10.1016/j.jneumeth.2022.109487].

36.   A. Villringer and U. Dirnagl, "Coupling of brain activity and cerebral blood flow: basis of functional neuroimaging," Cerebrovasc Brain Metab Rev **7**(3), 240–276 (1995).

37.   A. Aarabi and T. J. Huppert, "Characterization of the relative contributions from systemic physiological noise to whole-brain resting-state functional near-infrared spectroscopy data using single-channel independent component analysis," Neurophotonics **3**(2), 025004 (2016) [doi:10.1117/1.NPh.3.2.025004].

38.   G. H. Glover, "Deconvolution of Impulse Response in Event-Related BOLD fMRI1,"

1006   Neuroimage **9**(4), 416–429 (1999) [doi:10.1006/nimg.1998.0419].

1007   39.   L. Gagnon et al., "Improved recovery of the hemodynamic response in diffuse optical

1008   imaging using short optode separations and state-space modeling," Neuroimage **56**(3),

1009   1362–1371, Elsevier Inc. (2011) [doi:10.1016/j.neuroimage.2011.03.001].

1010   40.   L. Gagnon et al., "Short separation channel location impacts the performance of short

1011   channel regression in NIRS," Neuroimage **59**(3), 2518–2528 (2012)

1012   [doi:10.1016/j.neuroimage.2011.08.095].

1013   41.   M. Plank, "Ocular correction ICA," Brain Products Press Release **49** (2013).

1014   42.   M. Mørup et al., "Parallel Factor Analysis as an exploratory tool for wavelet transformed

1015   event-related EEG," Neuroimage **29**(3), 938–947 (2006)

1016   [doi:10.1016/j.neuroimage.2005.08.005].

1017   43.   C. A. Andersson and R. Bro, "The N-way Toolbox for MATLAB," Chemometrics and

1018   Intelligent Laboratory Systems **52**(1), 1–4 (2000) [doi:10.1016/S0169-7439(00)00071-X].

1019   44.   K. T. Sweeney et al., "A Methodology for Validating Artifact Removal Techniques for

1020   Physiological Signals," IEEE Transactions on Information Technology in Biomedicine

1021   **16**(5), 918–926 (2012) [doi:10.1109/TITB.2012.2207400].

1022   45.   F. Scholkmann et al., "How to detect and reduce movement artifacts in near-infrared

1023   imaging using moving standard deviation and spline interpolation," Physiological

1024   Measurement **31**(5), 649–662 (2010) [doi:10.1088/0967-3334/31/5/004].

1025   46.   S. Liu et al., "Empirical mode decomposition applied to tissue artifact removal from

1026   respiratory signal," in 2008 30th Annual International Conference of the IEEE Engineering

in Medicine and Biology Society, pp. 3624–3627, IEEE (2008)
[doi:10.1109/IEMBS.2008.4649991].

47. L. Kocsis, P. Herman, and A. Eke, "The modified Beer–Lambert law revisited," Physics in
Medicine and Biology **51**(5), N91–N98 (2006) [doi:10.1088/0031-9155/51/5/N02].

48. F. Scholkmann and M. Wolf, "General equation for the differential pathlength factor of the
frontal human head depending on wavelength and age," Journal of Biomedical Optics
18(10), 105004, SPIE-Intl Soc Optical Eng (2013) [doi:10.1117/1.jbo.18.10.105004].

49. K. J. Friston et al., *Statistical Parametric Mapping: The Analysis of Functional Brain*
Images, Academic Press, London, UK (2011).

50. M. L. Schroeter et al., "Towards a standard analysis for functional near-infrared imaging,"
Neuroimage **21**(1), 283–290 (2004) [doi:10.1016/j.neuroimage.2003.09.054].

51. Y. Minagawa-Kawai et al., "Optical Brain Imaging Reveals General Auditory and
Language-Specific Processing in Early Infant Development," Cerebral Cortex **21**(2), 254–
261 (2011) [doi:10.1093/cercor/bhq082].

52. J. Cohen, *Statistical Power Analysis for the Behavioral Sciences*, Second, Lawrence
Erlbaum Associates, Inc., New York, NY (1988).

53. T. T. Liu, "Neurovascular factors in resting-state functional MRI," Neuroimage **80**, 339–
348 (2013) [doi:10.1016/J.NEUROIMAGE.2013.04.071].

54. M. Mørup, "Applications of tensor (multiway array) factorizations and decompositions in
data mining," Wiley Interdisciplinary Reviews: Data Mining and Knowledge Discovery
1(1), 24–40 (2011) [doi:10.1002/widm.1].

55. S. Tak et al., "Dynamic causal modelling for functional near-infrared spectroscopy,"
Neuroimage **111**, 338–349 (2015) [doi:10.1016/j.neuroimage.2015.02.035].

56. M. A. Yücel et al., "Best practices for fNIRS publications," Neurophotonics **8**(01), 012101,

International Society for Optics and Photonics (2021) [doi:10.1117/1.nph.8.1.012101].

57. E. Martínez-Montes, J. M. Sánchez-Bornot, and P. A. Valdés-Sosa, "Penalized PARAFAC

analysis of spontaneous EEG recordings," Stat Sin **18**(4), 1449–1464 (2008).

58. E. Martínez-Montes et al., "Identifying Complex Brain Networks Using Penalized

Regression Methods," Journal of Biological Physics **34**(3–4), 315–323 (2008)

[doi:10.1007/s10867-008-9077-0].

59. D. Poeppel et al., "Towards a New Neurobiology of Language," Journal of Neuroscience

32(41), 14125–14131 (2012) [doi:10.1523/JNEUROSCI.3244-12.2012].

60. S. Makeig, "Dynamic Brain Sources of Visual Evoked Responses," Science (1979)

295(5555), 690–694 (2002) [doi:10.1126/science.1066168].

61. N. D. Sidiropoulos and R. Bro, "On the uniqueness of multilinear decomposition of N-way

arrays," Journal of Chemometrics **14**(3), 229–239 (2000) [doi:10.1002/1099-

128X(200005/06)14:3<229::AID-CEM587>3.0.CO;2-N].

62. W. Deburchgraeve et al., "Neonatal seizure localization using PARAFAC decomposition,"

Clinical Neurophysiology **120**(10), 1787–1796 (2009) [doi:10.1016/j.clinph.2009.07.044].

63. T. J. Huppert, "Commentary on the statistical properties of noise and its implication on

general linear models in functional near-infrared spectroscopy," Neurophotonics **3**(1),

010401 (2016) [doi:10.1117/1.NPh.3.1.010401].

64. M. Hu and H. Liang, "A copula approach to assessing Granger causality," Neuroimage **100**,

125–134 (2014) [doi:10.1016/j.neuroimage.2014.06.013].

65.   W. A. Freiwald et al., "Testing non-linearity and directedness of interactions between neural

1072   groups in the macaque inferotemporal cortex," Journal of Neuroscience Methods **94**(1),

1073   105–119 (1999) [doi:10.1016/S0165-0270(99)00129-6].

1074   66.   N. M. Faber, R. Bro, and P. K. Hopke, "Recent developments in

1075   CANDECOMP/PARAFAC algorithms: A critical review," in Chemometrics and Intelligent

1076   Laboratory Systems **65**(1), pp. 119–137 (2003) [doi:10.1016/S0169-7439(02)00089-8].

1077   67.   G. Jasdzewski et al., "Differences in the hemodynamic response to event-related motor and

1078   visual paradigms as measured by near-infrared spectroscopy," Neuroimage **20**(1), 479–488,

1079   Academic Press Inc. (2003) [doi:10.1016/S1053-8119(03)00311-2].

1080   68.   T. Sato et al., "Reduction of global interference of scalp-hemodynamics in functional near-

1081   infrared spectroscopy using short distance probes," Neuroimage **141**, 120–132 (2016)

1082   [doi:10.1016/j.neuroimage.2016.06.054].

1083   69.   J. Tremblay et al., "Comparison of source localization techniques in diffuse optical

1084   tomography for fNIRS application using a realistic head model," Biomedical Optics

1085   Express **9**(7), 448–454 (2018) [doi:10.1364/BOE.9.002994].

1086   70.   M. Ontivero-Ortega, Y. Garcia-Puente, and E. Martínez-Montes, "Comparison of classifiers

1087   to detect epileptic seizures via PARAFAC decomposition," in IFMBE Proceedings **49**, pp.

1088   500–503, Springer, Cham (2015) [doi:10.1007/978-3-319-13117-7_128].

1089   71.   K. Nazarpour et al., "Parallel space-time-frequency decomposition of EEG signals for brain

1090   computer interfacing; Parallel space-time-frequency decomposition of EEG signals for

1091   brain computer interfacing" (2006).

72.   A. Cichocki et al., "Noninvasive BCIs: Multiway Signal-Processing Array

Decompositions," Computer (Long Beach Calif) **41**(10), 34–42 (2008)

[doi:10.1109/MC.2008.431].

73.   A. Eliseyev et al., "L1-Penalized N-way PLS for subset of electrodes selection in BCI

experiments," Journal of Neural Engineering **9**(4) (2012) [doi:10.1088/1741-

2560/9/4/045010].

74.   A. Eliseyev and T. Aksenova, "Recursive N-Way Partial Least Squares for Brain-Computer

Interface," PLoS ONE **8**(7), 69962 (2013) [doi:10.1371/journal.pone.0069962].

1100

Alejandra M. Hüsser is a Ph.D. candidate in neuropsychology at the Université de Montréal. She has received a B.Sc. and M.Sc. degree in psychology with a specialization in cognitive sciences and neuropsychology from the University of

1104   Zurich in 2013 and 2015, respectively. Her research interests include childhood

1105   neurodevelopment, neurodevelopmental pathologies, epilepsy, cerebral language networks,

1106   language functions, neuroimaging and imaging analysis. In 2020, Alejandra was awarded a

1107   prestigious studentship by the Savoy Foundation.

Laura Caron-Desrochers is a doctorate candidate in clinical neuropsychology at the Université de Montréal. She has received a B.Sc. degree in Psychology from the same university in 2015. Her research interests include the application

1111   of fNIRS to study early cerebral neurodevelopment and the influence of prenatal environment on

1112   the establishment of cerebral language networks.

Julie Tremblay is a biomedical engineer in the LIONlab. She graduated with a B.Sc. degree in electrical engineering from the Université de Sherbrooke in 2006. Since, she specialized in data analysis, signal processing, and software development for neuroimaging data. She has participated in several projects using a wide range of imaging techniques such as NIRS, EEG, iEEG, MEG, DTI, and fMRI. Her research interests are in the integration of algorithms and understanding brain development.

Phetsamone Vannasing joined CHU Sainte-Justine in 1993 as a research coordinator and electrophysiologist. Her task is to coordinate research protocols and teach students the technical aspects of data recording, acquisition, and analysis. She set up a state-of-the-art multimodal recording platform combining EEG, NIRS, eye-tracking, and electro-dermal systems. Her research interests include neurodevelopment in clinical and healthy populations. She received the Research Professionals Excellence awards of the Fonds de recherche du Québec-Santé and CHU Sainte-Justine.

Eduardo Martínez-Montes, Ph.D., is a Senior Researcher at the Cuban Center for Neurosciences, and the director of the Human Brain Mapping Division. He has awarded with the Medal Carlos J. Finlay, the highest order given by the Cuban government for outstanding contributions to science. He has contributed to develop neuroscientific analysis, including multidimensional space-time-frequency analysis in EEG, multimodal EEG-fMRI analysis and estimation of electrophysiological brain sources. His current research focuses on the development of statistical models and the implementation of neuroinformatics tools for the analysis of brain activity.

Anne Gallagher, Ph.D. and neuropsychologist, holds a Canada Research Chair in Child Neuropsychology and Brain Imaging. She is an Associate Professor at the Department of Psychology of the Université de Montréal and the Director of the LIONlab. She uses NIRS, EEG, and neuropsychological assessment to identify predictive brain markers of neurodevelopmental outcomes in children with various clinical conditions. She is a pioneer in the use of NIRS-EEG in clinical settings, notably developing presurgical evaluation techniques in patients with epilepsy.

1157	**Fig. S4**	Evaluation of correction in simulated motion artifacts based on signal quality by
1158		the use of the signal-to-noise ratio (SNR).
1159	**Fig. S5**	Evaluation of correction in simulated motion artifacts based on signal quality by
1160		the use of the Pearson's correlation between wavelengths (Rλ).
1161	**Table 1**	Mean quality metrics for the evaluation of artifact correction in the task-based data
1162		set.
1163	**Table 2**	Percentage of explained variance by the HRFsim based on the R2 of the general
1164		linear model.