Analytical solution of linearized equations of the Morris-Lecar neuron model at large constant stimulation

A.V. Paraskevov[1,2], T.S. Zemskova[3,4]

[1]*National Research Centre "Kurchatov Institute", 123182 Moscow, Russia*
[2]*Institute for Information Transmission Problems of the Russian Academy of Sciences, 127051 Moscow, Russia*
[3]*Ecole Polytechnique, 91128 Palaiseau, France*
[4]*Moscow Institute of Physics and Technology (National Research University), 141700 Dolgoprudny, Russia*

Abstract

The classical biophysical Morris-Lecar model of neuronal excitability predicts that upon stimulation of the neuron with a sufficiently large constant depolarizing current there exists a finite interval of the current values where periodic spike generation occurs. Above the upper boundary of this interval there is a four-stage damping of the spike amplitude: 1) minor primary damping, which reflects a typical transient to stationary state, 2) plateau of nearly undamped periodic oscillations, 3) strong damping, and 4) reaching a constant stationary asymptotic value V_{st} of the neuron potential. We have linearized the Morris-Lecar model equations at the vicinity of V_{st} and have shown that the linearized equations can be reduced to a standard equation for exponentially damped harmonic oscillations. Importantly, all coefficients of this equation can be explicitly expressed through parameters of the original Morris-Lecar model, enabling direct comparison (i.e. without any fitting) of the numerical and analytical solutions for the neuron potential dynamics at later stages of the spike amplitude damping. This allows to explore quantitatively the applicability boundary of linear stability analysis that implies exponential damping.

Keywords: neuron, Morris-Lecar model, constant current stimulation, periodic spiking, damped oscillations

1. Introduction

The Morris-Lecar model [1, 2] is a classical biophysical model of spike generation by the neuron, which takes into account the dynamics of voltage-dependent ion channels and realistically describes the spike waveform. The model predicts that upon stimulation of the neuron with a sufficiently large constant depolarizing current I_{stim}, there exists a finite interval of I_{stim} values where periodic spike generation occurs [2–5]. Numerical simulations have shown that in the Morris-Lecar model the cessation of periodic generation of spikes above the upper boundary of this interval (i.e. at $I_{stim} > I_{max}$ in Fig. 1) occurs through a damping of the spike amplitude, arising with a delay inversely proportional to the value of I_{stim} [6]. In particular, the damped dynamics can be divided into four successive stages: 1) minor primary damping, which reflects a typical transient to stationary dynamic state, 2) plateau of undamped periodic oscillations, which determines the aforementioned delay, 3) strong damping, and 4) reaching a constant stationary asymptotic value V_{st} of the neuron potential. As the last two stages resemble the well-known exponentially-damped harmonic oscillations, we tackled to find an analytical description for these.

In this paper, we have linearized the Morris-Lecar model equations at the vicinity of the asymptote V_{st}. The resulting equations have been then reduced to an inhomogeneous Volterra integral equation of the 2nd kind. In turn, the latter has been transformed into an ordinary differential equation of the second order with a time-dependent coefficient at the first-order derivative. As this time dependence was just an exponential decay with the small pre-exponential factor, we considered its asymptotic value and analytically solved the final equation. In order to verify the analytical solution found, we have compared it with the numerical solution obtained using the standard MATLAB tools for systems of ordinary differential equations (see Supplementary Material).

As the result, we have accurately shown that the linearized system of equations of the Morris-Lecar model can be reduced to a standard equation of exponentially damped harmonic oscillations for the neuron potential. Since all coefficients of this equation are explicitly expressed through parameters of the original Morris-Lecar model, one can directly (i.e. without any fitting) compare the numerical and analytical solutions for dynamics of the neuron potential at last two stages of the spike amplitude damping (Fig. 2). The results allow a quantitative study of the applicability boundary of linear stability analysis that implies exponential damping.

2. Standard Morris-Lecar model

As phase plane analysis of the Morris-Lecar (ML) model is extensively described in the most of textbooks on mathematical neuroscience (e.g., [7–11]), we omit it and provide only basic facts on the model, and its formal description.

Qualitatively, the classical two-dimensional ML model [1, 2] (cf. [12]) couples the dynamics of the transmembrane potential V of the neuron with the dynamics of the transmembrane conductance w of potassium ions. Spikes represent characteristic oscillations of V (see the grey inset in Fig. 1, in the range from I_{min} to I_{max}). In the ML model the rate of change of V depends on the current value of w in such a way that the dynamics w provides a negative feedback with respect to the dynamics of V. In turn, the rate of change of w is proportional to the difference between the current value of w and some "asymptotic" value w_∞, which nonlinearly depends on V. As a result, w tends to reach w_∞, which is changed itself in time due to dynamics of V. If one neglects the relaxation of w to w_∞, i.e. assumes that it occurs instantly, then the generation of spikes in the ML model does not occur. The upper value of the stimulating current, I_{max}, above which the continuous periodic generation of spikes stops, corresponds to the onset of a fast (compared to the rate of change of V) relaxation of w to w_∞.

Quantitatively, standard equations of the Morris-Lecar model for dynamics of the neuronal potential V and for relaxation dynamics of the normalized conductance w of potassium ions are given by

$$\begin{cases} C_m dV/dt = -I_{ion}(V, w) + I_{stim}, \\ dw/dt = (w_\infty(V) - w)/\tau(V), \end{cases} \tag{1}$$

where the total sum of ion currents

$$I_{ion}(V, w) = g_{Ca} \cdot m_\infty(V) \cdot (V - V_{Ca}) + g_K \cdot w \cdot (V - V_K) + g_L \cdot (V - V_L), \tag{2}$$

I_{stim} is an external stimulating current, and the constituent functions

$$m_\infty(V) = \frac{1}{2} \left[1 + \tanh((V - V_1)/V_2) \right], \tag{3}$$

$$w_\infty(V) = \frac{1}{2} \left[1 + \tanh((V - V_3)/V_4) \right], \tag{4}$$

$$\tau(V) = \tau_{\max} / \cosh((V - V_3)/(2V_4)). \tag{5}$$

Figure 1. Dependence of spike generation frequency on constant stimulating current I_{stim} and, on the gray inset, typical examples of dynamics of the neuron potential in the corresponding ranges of I_{stim} values for the Morris-Lecar model with the 1st excitability type [2]. Spikes are characteristic oscillations of the neuron potential (see the gray inset in the range from I_{min} to I_{max}).

For numerical simulations we have used the following values of the ML model parameters corresponding the 1st neuronal excitability type [2]: $C_m = 20 \; \mu\text{F}/\text{cm}^2$, $g_{Ca} = 4 \; \text{mS}/\text{cm}^2$, $g_K = 8 \; \text{mS}/\text{cm}^2$, $g_L = 2 \; \text{mS}/\text{cm}^2$, $V_{Ca} = 120$ mV, $V_K = -84$ mV, $V_L = -60$ mV, $V_1 = -1.2$ mV, $V_2 = 18$ mV, $V_3 = 12$ mV, $V_4 = 17.4$ mV, $\tau_{\max} = 14.925$ ms.

3. Linearization of the Morris-Lecar equations at large constant stimulation

In what follows, we consider the case $I_{stim} > I_{\max}$ and seek a solution for the potential in the form $V(t) = V_{st} + U(t)$, where V_{st} is the stationary potential value determined from equation $I_{ion}(V_{st}, w_\infty(V_{st})) = I_{stim}$ and $U(t \to +\infty) = 0$. In addition, we assume that for any moment of time t the condition $|U(t)| \ll |V_{st}|$ holds. Given this, we expand $w_\infty(V)$ and $m_\infty(V)$ into a Taylor series up to the linear term with respect to U:

$$w_\infty(V_{st} + U) \approx w_\infty(V_{st}) + \frac{dw_\infty(V_{st})}{dV}U = a + b \cdot U,$$

$$m_\infty(V_{st} + U) \approx m_\infty(V_{st}) + \frac{dm_\infty(V_{st})}{dV}U = p + q \cdot U,$$

where $a = w_\infty(V_{st})$, $b = dw_\infty(V_{st})/dV$, $p = m_\infty(V_{st})$, $q = dm_\infty(V_{st})/dV$.

Next, we exactly solve the linearized ML equation on w, assuming that $\tau(V) = const = \tau(V_{st}) \equiv \tau$,

$$\begin{cases} \tau dw/dt = a + bU(t) - w, \\ w(t = t_0) = w_0. \end{cases} \tag{6}$$

Its general solution has form

$$w(t) = a + W_0(t) + b\exp(-\frac{t}{\tau})\int_{t_0}^{t} \exp(\frac{t'}{\tau})\frac{U(t')}{\tau}dt', \tag{7}$$

where $W_0(t) = (w_0 - a) \exp(-(t - t_0)/\tau)$.

We find value $w(t_0) = w_0$ in a local extremum point of the potential $V(t = t_0) = V_0 = V_{st} + U_0$, which is determined by condition $\frac{dV}{dt}(t = t_0) = 0$. One gets

$$w_0 = \frac{I_{stim} - g_{Ca} \cdot m_\infty(V_0) \cdot (V_0 - V_{Ca}) - g_L \cdot (V_0 - V_L)}{g_K \cdot (V_0 - V_K)}. \tag{8}$$

Further, writing explicitly the equation on U and neglecting nonlinear terms, we obtain a linear integro-differential equation for the potential U

$$\frac{dU}{dt} = -G(t) - A(t)U - B \exp(-\frac{t}{\tau}) \int_{t_0}^t \exp(\frac{t'}{\tau}) \frac{U(t')}{\tau} dt', \tag{9}$$

where coefficients $A(t)$, B, and $G(t)$ are as follows:

$$A(t) = [g_{Ca}(p + q(V_{st} - V_{Ca})) + g_K(a + W_0(t)) + g_L]/C_m \equiv A + A_0(t),$$
$$A = [g_{Ca}(p + q(V_{st} - V_{Ca})) + g_K a + g_L]/C_m,$$
$$A_0(t) = g_K W_0(t)/C_m \equiv A_K \exp(-(t - t_0)/\tau), \quad A_K = g_K(w_0 - a)/C_m,$$
$$B = g_K b (V_{st} - V_K)/C_m,$$
$$G(t) = A_0(t)(V_{st} - V_K) = B((w_0 - a)/b) \exp(-(t - t_0)/\tau).$$

Integrating by parts, we obtain

$$\frac{dU}{dt} = G_1(t) - A_1(t)U(t) + B \exp(-\frac{t}{\tau}) \int_{t_0}^t \exp(\frac{t'}{\tau}) \frac{dU}{dt'} dt', \tag{10}$$

where $G_1(t) = -G(t) + BU(t_0) \exp(-(t - t_0)/\tau)$ and $A_1(t) = A(t) + B$.

Further, given that $U(t) = U(t_0) + \int_{t_0}^t (dU/dt')dt'$, one can reduce the previous equation on U to an integral equation for the function $f(t) = dU/dt$,

$$f(t) = G_2(t) + \int_{t_0}^t K(t, t') f(t') dt', \tag{11}$$

where $G_2(t) = G_1(t) - A_1(t)U(t_0) = G_3 + G_4 \exp(-(t - t_0)/\tau)$, $G_3 = -(A + B)U(t_0)$, $G_4 = U(t_0)(-A_K + B) - B(w_0 - a)/b$, and

$$K(t, t') = -A_1(t) + B \exp(-\frac{(t - t')}{\tau}) = -(A + B) - A_K \exp(-\frac{(t - t_0)}{\tau}) + B \exp(-\frac{(t - t')}{\tau}). \tag{12}$$

The resulting equation (11) for $f(t)$ is an inhomogeneous Volterra integral equation of the 2nd kind. Twice differentiating both sides of Eq. (11) with respect to t, we obtain that the integral equation (11) is equivalent to an ordinary differential equation of the 2nd order

$$\frac{d^2 f}{dt^2} + (y + A_K \exp(-(t - t_0)/\tau)) \frac{df}{dt} + \left(-\frac{A_K}{\tau} \exp(-(t - t_0)/\tau) + z \right) f(t) = 0, \tag{13}$$

where constants $y = A + 1/\tau$ and $z = (A + B)/\tau$ have been introduced.

Returning to potential U and allocating the full derivative, we have

$$\frac{d^2 U}{dt^2} + (y + A_K \exp(-(t - t_0)/\tau)) \frac{dU}{dt} + zU = const. \tag{14}$$

Assuming that potential $U(t)$ and all its derivatives tend to zero at $t \to +\infty$, one gets $const = 0$. Finally, we obtain

$$\frac{d^2 U}{dt^2} + (y + A_K \exp(-(t - t_0)/\tau)) \frac{dU}{dt} + zU = 0, \tag{15}$$

Figure 2. Left graph: The gray curve is a numerical solution for the dynamics of neuron potential V in the Morris-Lecar model with the 1st excitability type at $I_{stim} = 116.3 \ \mu A/cm^2 > I_{max} = 116 \ \mu A/cm^2$, the red curve is an analytical solution of the linearized system of equations of the Morris-Lecar model with initial conditions taken at the point of a local maximum of the potential ($t_0 = 693.3$ ms, $V(t_0) = 16.35$ mV). Right graph: The corresponding numerical (gray) and analytical (red) solutions for w.

with initial conditions

$$U(t = t_0) = U_0 \equiv V_0 - V_{st}, \quad \frac{dU}{dt}(t = t_0) = 0. \tag{16}$$

4. Analytical solution of the linearized equations

Assuming that $w_0 \approx a$ and neglecting the time-dependent parameter, we arrive at

$$\frac{d^2U}{dt^2} + y\frac{dU}{dt} + zU(t) = 0. \tag{17}$$

Given the initial conditions (16), its solution has form

$$U(t) = U_0 \exp(-\frac{1}{2}(t - t_0)y) \left[\cos(\frac{1}{2}(t - t_0)f) + \frac{y}{f}\sin(\frac{1}{2}(t - t_0)f)\right], \tag{18}$$

with the oscillation frequency $f = \sqrt{4z - y^2}$. This solution corresponds well with the numerical one (Fig. 2, left graph).

One can also obtain an explicit solution $w(t)$ by substituting $U(t)$ into Eq. (7),

$$w(t) = a + (w_0 - a + w_1) \exp(-\frac{(t - t_0)}{\tau}) + w_1 \exp(-\frac{1}{2}y(t - t_0)) \left[-\cos(\frac{1}{2}f(t - t_0)) + H \sin(\frac{1}{2}f(t - t_0))\right], \tag{19}$$

where notations $w_1 = bU_0 A/B$ and $H = 2z/(fA) - y/f$ are used.

Using auxiliary trigonometric transformations, one can write functions $U(t)$ and $w(t)$ in a more compact form. Denoting

$$\cos(\eta) = \frac{1}{\sqrt{1 + (y/f)^2}} = \frac{f}{2\sqrt{z}}, \quad \sin(\eta) = \frac{y/f}{\sqrt{1 + (y/f)^2}} = \frac{y}{2\sqrt{z}}, \tag{20}$$

we get

$$U(t) = 2U_0\frac{\sqrt{z}}{f} \exp(-\frac{1}{2}(t - t_0)y) \cos(\frac{1}{2}(t - t_0)f - \eta), \tag{21}$$

where $\eta = \arctan(y/f)$ is the inverse function of $\tan(\eta) = y/f$. This expression for $U(t)$ is completely equivalent to the previous solution (18).

In turn, introducing notations

$$s = \frac{1}{f}(\frac{2}{\tau} - y), \quad \cos(\chi) = \frac{1}{\sqrt{1+s^2}}, \quad \sin(\chi) = \frac{s}{\sqrt{1+s^2}}, \tag{22}$$

we obtain a compact solution for $w(t)$,

$$w(t) = a + W_c \exp(-(t-t_0)/\tau) + W_a \exp(-\frac{1}{2}y(t-t_0))\sin(\frac{1}{2}(t-t_0)f + \chi - \eta), \tag{23}$$

where $\chi = \arctan(s)$, quantity $W_a \equiv ((2bU_0)/(f\tau))\sqrt{1+A/B}$ determines the amplitude of the damped oscillations of $w(t)$ (see Fig. 2, right graph), and $W_c \equiv (w_0 - a) - W_a \sin(\chi - \eta)$.

Acknowledgments

This work was partially funded by the Russian Foundation for Basic Research according to the research project # 17-29-07093.

References

[1] C. Morris, H. Lecar, Voltage oscillations in the barnacle giant muscle fiber, Biophys. J. **35**, 193-213 (1981).
https://doi.org/10.1016/S0006-3495(81)84782-0

[2] J. Rinzel, B. Ermentrout, Analysis of neural excitability and oscillations, In: C. Koch, I. Segev (Eds.), Methods in neuronal modeling: From synapses to networks (2nd Ed., MIT Press, 1998), pp. 251-291.
https://www.researchgate.net/publication/237128320

[3] T. Tateno, A. Harsch, H. Robinson, Threshold firing frequency-current relationships of neurons in rat somatosensory cortex: type 1 and type 2 dynamics, J. Neurophysiol. **92**, 2283-2294 (2004).
https://doi.org/10.1152/jn.00109.2004

[4] K. Tsumoto et al., Bifurcations in Morris-Lecar neuron model, Neurocomputing **69**, 293-316 (2006).
https://doi.org/10.1016/j.neucom.2005.03.006

[5] L.H. Nguyen, K.S. Hong, S. Park, Bifurcation control of the Morris-Lecar neuron model via a dynamic state-feedback control, Biol. Cybern. **106**, 587-594 (2012).
https://doi.org/10.1007/s00422-012-0508-4

[6] T. Zemskova, A. Paraskevov. On damping mechanism of periodic spiking in Morris-Lecar model at large values of constant stimulating current. Bernstein Conference 2018.
https://doi.org/10.6084/m9.figshare.11301776

[7] C. Koch, Biophysics of Computation: Information Processing in Single Neurons (Oxford University Press, 1999).
https://global.oup.com/academic/product/biophysics-of-computation-9780195181999

[8] E.M. Izhikevich, Dynamical Systems in Neuroscience: The Geometry of Excitability and Bursting (1st Ed., MIT Press, 2007).
https://mitpress.mit.edu/books/dynamical-systems-neuroscience

[9] D. Sterratt, B. Graham, A. Gillies, D. Willshaw, Principles of Computational Modelling in Neuroscience (Cambridge University Press, 2011).
https://doi.org/10.1017/CBO9780511975899

[10] G.B. Ermentrout, D.H. Terman, Mathematical Foundations of Neuroscience (Springer-Verlag New York, 2010).
https://doi.org/10.1007/978-0-387-87708-2

[11] W. Gerstner, W.M. Kistler, R. Naud, L. Paninski, Neuronal Dynamics: From Single Neurons to Networks and Models of Cognition (Cambridge University Press, 2014).
https://doi.org/10.1017/CBO9781107447615

[12] J.M. Gonzalez-Miranda, Pacemaker dynamics in the full Morris-Lecar model, Commun. Nonlinear Sci. Numer. Simulat. **19**, 3229-3241 (2014).
https://doi.org/10.1016/j.cnsns.2014.02.020