Title: **Learning to synchronize: Midfrontal theta dynamics during rule switching**

Abbreviated title: **Midfrontal theta during rule switching**

Authors: Pieter Verbeke[1], Kate Ergo[1], Esther De Loof[1], Tom Verguts[1]

Affiliations: [1]Department of Experimental Psychology; Ghent University; B9000

Corresponding author email: pjverbek.verbeke@ugent.be

Number of pages: 32

Number of figures: 8

Number of tables: 1

Number of words:

Abstract: 221

Introduction: 638

*Discussion:*1499

Conflict of interests: The authors declare no competing financial interests.

Acknowledgements: PV and KE were supported by grant 1102519N and grant 1153418N from Research Foundation Flanders, respectively. EDL and TV were supported by grant BOF17/GOA/004 from the Ghent University Research Council. We thank Clay Holroyd for useful comments on this paper.

Abstract

In recent years, several hierarchical extensions of well-known learning algorithms have been proposed. For example, when stimulus-action mappings vary across time or context, the brain may learn two or more stimulus-action mappings in separate modules, and additionally (at a hierarchically higher level) learn to appropriately switch between those modules. However, how the brain mechanistically coordinates neural communication to implement such hierarchical learning, remains unknown. Therefore, the current study tests a recent computational model that proposed how midfrontal theta oscillations implement such hierarchical learning via the principle of binding by synchrony (Sync model). More specifically, the Sync model employs bursts at theta frequency to flexibly bind appropriate task modules by synchrony. 64-channel EEG signal was recorded while 27 human subjects (Female: 21, Male: 6) performed a probabilistic reversal learning task. In line with the Sync model, post-feedback theta power showed a linear relationship with negative prediction errors, but not with positive prediction errors. This relationship was especially pronounced for subjects with better behavioral fit (measured via AIC) of the Sync model. Also consistent with Sync model simulations, theta phase-coupling between midfrontal electrodes and temporo-parietal electrodes was stronger after negative feedback. Our data suggest that the brain uses theta power and synchronization for flexibly switching between task rule modules, as is useful for example when multiple stimulus-action mappings must be retained and used.

Significance Statement

Everyday life requires flexibility in switching between several rules. A key question in understanding this ability is how the brain mechanistically coordinates such switches. The current study tests a recent computational framework (Sync model) that proposed how midfrontal theta oscillations coordinate activity in hierarchically lower task-related areas. In line with predictions of this Sync model, midfrontal theta power was stronger when rule switches were most likely (strong negative prediction error), especially in subjects who obtained a better model fit. Additionally, also theta phase connectivity between midfrontal and task-related areas was increased after negative feedback. Thus, the data

provided support for the hypothesis that the brain uses theta power and synchronization for flexibly switching between rules.

Switching between rules is key to function in a complex and rapidly changing environment.

For instance, when at the pub with friends, our behavior is likely guided by different social rules than

at work. However, when the boss suddenly walks into the pub, this requires to flexibly switch between

these two sets of social rules. Importantly, an empirically valid model that explains how the human

brain mechanistically deals with such switches, remains lacking.

In experimental settings, this cognitive flexibility in rule switching is typically tested in a

reversal learning setup (Izquierdo, Brigman, Radke, Rudebeck, & Holmes, 2017). Here, agents must

learn task rules, each consisting of a collection of stimulus-action mappings. During the task, these rules

are regularly reversed. One popular framework to explain performance during reversal learning tasks is

the Rescorla-Wagner model (RW; Rescorla & Wagner, 1972; Widrow & Hoff, 1960). Here, on every

trial, obtained reward is used to update the value of active stimulus-action mappings. By learning fast,

the agent can flexibly deal with changes in task rules. However, when feedback is probabilistic (e.g.,

Cools, Clark, Owen, & Robbins, 2002), this approach experiences difficulties. Specifically, a high

learning rate will lead agents to "chase the noise" introduced by probabilistic feedback. In contrast, a

low learning rate increases robustness against noise, but decreases flexibility on rule switches. Thus,

some researchers have proposed that learning rate should be adaptive (e.g., Bai, Katahira, & Ohira,

2014; Behrens, Woolrich, Walton, & Rushworth, 2007; Silvetti, Vassena, Abrahamse, & Verguts,

2018). In this adaptive learning rate (ALR) proposal, agents track rule switches by comparing an

estimate of reward probability to received reward. Consistently high prediction errors indicate that the

underlying rule has changed, and learning rate should be increased. More fundamentally however,

irrespective of learning rate flexibility, both RW and ALR frameworks assume that, on every rule

reversal, old information is overwritten. Especially for more complex problems, this is inefficient, as is

demonstrated by the problem of catastrophic forgetting in artificial neural networks (French, 1999).

To overcome catastrophic forgetting, separate task rules may be stored (Saez, Rigotti, Ostojic,

Fusi, & Salzman, 2015; Wilson, Takahashi, Schoenbaum, & Niv, 2014). This poses a new problem of

keeping track which task rule is currently relevant. Recent fMRI research focusing on this hierarchical

approach toward reversal learning has pointed to midfrontal cortex as the responsible neural structure

for keeping track of the current task rule (Wilson et al., 2014). However, how midfrontal cortex

mechanistically coordinates neural communication in switching between task rules, remains an open

question.

This question was recently addressed by a novel computational framework of hierarchical

learning (Verbeke & Verguts, 2019). This Sync model retains separate mappings for every task rule,

and keeps track of rule reversals by calculating prediction error (e.g., Holroyd & McClure, 2015), thus

avoiding catastrophic forgetting. In order to guide neural communication between areas holding the

appropriate mappings, the model relies on binding by synchrony (BBS; Fries, 2005, 2015; Gray &

Singer, 1989; Womelsdorf et al., 2007) in theta frequency (4-8 Hz). Specifically, midfrontal theta

oscillations synchronize neuronal activity along task-relevant pathways. Thus, task-relevant neurons

can communicate and learn, while stability is achieved in currently irrelevant pathways.

The current study empirically tests this Sync model (Fig 1A). For this purpose, the model is

fitted on data of subjects performing a probabilistic reversal learning paradigm, and empirically

compared to alternative models (Bai et al., 2014; Rescorla & Wagner, 1972). Then, Sync model

simulations provided several predictions for EEG measured during the task, specifically in theta

frequency (model-driven EEG predictions). First, a linear relationship between midfrontal theta power

and negative prediction errors was predicted, especially in subjects with good behavioral Sync model

fit. Second, a peak of midfrontal theta power was predicted for data locked to rule switches. Third,

phase-coupling between midfrontal and posterior electrodes was predicted to be stronger after negative

feedback.

Materials and Methods

Materials

The experiment was run on a Dell Optiplex 9010 mini-tower running PsychoPy software

(Peirce et al., 2019). Electrophysiological data were recorded using a BioSemi ActiveTwo system

(BioSemi, Amsterdam, Netherlands) with 64 Ag/AgCl electrodes arranged in the standard international

10–20 electrode mapping (Jasper, 1958), with a posterior CMS-DRL electrode pair. Two reference

electrodes were positioned at the left and right mastoids. Eye movements were registered with a pair of

electrodes above and below the left eye and two additional electrodes at the outer canthi of both eyes.

EEG signals were recorded at a sampling rate of 1024 Hz.

57   Models were fitted using the differential evolution method of the SciPy (version 1.4.1)

58   package in Python (version 3.7.6). Other behavioral analyses were done using R software (R Core

59   Team, 2017). The electrophysiological data were preprocessed in MATLAB R2016b (The MathWorks

60   Inc., 2016) using an EEGLAB preprocessing pipeline (Delorme & Makeig, 2004). Also for simulations

61   of the Sync model MATLAB R2016b was used.

62   **Code and Data Accessibility**

63   All code used to provide the results described in the current paper is provided at

64   https://github.com/CogComNeuroSci/PieterV_public/tree/master/Reversal_learning.   At   publication,

65   also the data will be made freely accessible at https://osf.io/wt36f/.

66   **Experimental Task**

67   Both the model (27 simulations) and human subjects ($N = 27$) performed a probabilistic

reversal learning task (see Fig 1B). Agents had to learn task rules consisting of two stimulus-action

mappings which were regularly reversed during the task. Every trial started with a centrally presented

white fixation cross for 2000 milliseconds. Then the stimulus was presented for a period of 100

milliseconds. This stimulus was a centrally presented circular grating with a raised-cosine mask and a

size of 7 visual degrees. The grating was either vertically or horizontally oriented. After stimulus

presentation, the screen turned blank until response. Responses were given by pressing the 'f'- (left) or

'j' (right) key on an azerty keyboard. In task rule 1, the horizontal stimulus mapped to a left response

and the vertical stimulus to the right response; this was reversed for task rule 2. During the task (480

trials), 15 rule switches were introduced. These rule switches occurred at random (uniform distribution

from 15 to 45 trials after the previous task switch). After response, probabilistic feedback was presented

in the center of the screen. This feedback consisted of '+10 points' for rewarded trials, '+0 points' for

unrewarded trials or 'Respond faster!' when response times (RT) were slower than 1000 milliseconds.

Subjects had an 80% probability of receiving reward feedback after correct responses and 20% after

incorrect responses. After feedback, the fixation cross appeared again for another 2000 milliseconds.

Crucially, the experiment was divided into two experimental blocks (240 trials each). In one block, the

reporting block, the post-feedback fixation cross was presented in green. During this period, subjects

were instructed to press the space bar if they thought the task rule had switched. The purpose of this

approach was to obtain an indication of when the subject reached his or her own 'Switch threshold', as

happens in the Sync model. This was only done during one block, so critical changes due to this

difference in task structure could be checked. The order of the two blocks was counterbalanced across

subjects. In between blocks, as well as three times within a block, subjects were allowed a short break.

This break could only occur if there was no rule switch within 10 trials from the break.

Human Testing Procedure

34 subjects participated in this study, 7 subjects were removed because of either technical

problems with the EEG recording (4) or an inability to give a correct response on more than 2/3 of the

trials (3), resulting in $N = 27$ ($N_{male} = 6$, $N_{female} = 21$). Subjects were told they would receive €25 for their

participation, with a possibility to earn up to €3 extra reward depending on their performance.

Before starting the task, the subject had to go through two short practice sessions with gratings

that were tilted 45º to the left or to the right relative to a vertical line. In the first practice session, the

subject performed 30 trials with only one task rule. Here, the goal was to let the subject get acquainted

with the general paradigm and learn a task rule through probabilistic feedback. Subjects were only

allowed to continue to the second practice session if they performed above chance level (50%) and

could report the correct task rule to the experimenter. If not, they performed this practice session again.

In the second practice session, subjects performed 60 trials of the task with 3 rule switches and with the

post-feedback green fixation cross (as in the reporting block). In this session, subjects pressed the space

bar to indicate a task switch and received feedback for each press. The press was considered correct if

subjects responded within 10 trials from the actual rule switch. They were allowed to continue to the

next task if they were able to perform above chance level and had at least 1 correct indication of a rule

switch. After successfully performing both practice sessions, subjects performed 480 trials of the actual

task.

Behavioral Analyses

To check for differences between the reporting block (green fixation cross) and the non-reporting block (see Experimental Task and Fig 1B), paired t-tests were performed for both accuracy and RT, depending on experimental block. In order to deal with the skewed distribution of RT, the natural log of RT was used for all analyses. Additionally, trials with too late responses (RT > 1000 milliseconds; 2.11% of all data) were excluded for both behavioral and EEG analyses.

Model Analyses

More extensive analyses of behavioral data were done with a model-based approach. Current work aims to test the Sync model (Verbeke & Verguts, 2019), but two baseline models were fitted as well. In the following section, we first provide a detailed overview of the Sync model, followed by a description of all three models that were fitted on behavioral data. Then, we describe how model fit was evaluated.

The Sync model

An overview of model architecture is provided in Fig 1A. The Sync model consists of two units, the Mapping and Switch unit. The Mapping unit contains a classic network with 2 layers (visual input and motor output). Here, weights are adapted with the RW algorithm (Widrow & Hoff, 1960). In the Sync model, 4 nodes (2 for each response option) at the motor output layer, are divided in 2 rule modules, one for each task rule. Hence, as in (Wilson et al., 2014), the Mapping unit holds separate stimulus-action mappings for each task rule. In addition, a Switch unit forms a hierarchically higher network modeled after primate prefrontal cortex. This Switch unit keeps track of switches in task rule. Specifically, the Switch unit consists of the lateral frontal cortex (LFC), posterior medial frontal cortex (pMFC) and anterior midfrontal cortex (aMFC). Here, the LFC holds pointers (e.g., Botvinick et al., 2001; Cohen, Dunbar, & McClelland, 1990) that indicate which rule should be synchronized in the Mapping unit. Since BBS implements gating, allowing efficient communication between synchronized nodes and blocking communication between non-synchronized nodes (Fries, 2005, 2015), the agents' behavior will be guided by the synchronized rule. This synchronization process is then executed by the binding by random bursts principle (Springer & Paulsson, 2006; Verguts, 2017; Zhou, Chen, & Aihara,

2005). In the Sync model, a theta-frequency-paced signal produced in the pMFC is responsible for

sending these bursts (see Verbeke & Verguts, 2019; Verguts, 2017 for details). The aMFC contains a

neural network (for simplicity not shown in Fig 1A) that is adapted from previous work (Silvetti,

Seurinck, & Verguts, 2011). Here, again RW learning is employed but on a hierarchically higher level.

More specifically, the aMFC learns an expected reward (*V*) for the currently used rule module (see

Equation (6)). This expected reward is compared to an external reward signal (*Rew*; Reward in Fig 1A)

in order to compute prediction errors. The negative prediction error signal is propagated to both the

Accumulator neuron (within the aMFC neural network) and to pMFC. A single negative prediction

error increases (via bursting) the power of the theta signal in pMFC (bursting connection in Fig 1A; see

Verbeke & Verguts, 2019 for details). Instead, the Accumulator neuron evaluates the prediction error

signal on a slower time scale (see also Holroyd & McClure, 2015), and thus requires multiple prediction

errors before activation in the Accumulator neuron reaches its Switch threshold (see Equation (5)).

When this happens, aMFC signals the need for a switch to the LFC. Correspondingly, the LFC will

change the signal to the Mapping unit, and synchronize another rule module. In sum, bursts received

by the Mapping unit are the result of a cooperation between LFC and pMFC. The pMFC determines

the intensity of theta bursts, while the LFC determines which task rule in the Mapping unit is susceptible

to the bursts. For further details see (Verbeke & Verguts, 2019).

All nodes in the visual input and motor output layer of the Mapping unit as well as the pMFC

are oscillatory nodes. In line with previous work (Verguts, 2017), oscillatory nodes consist of neuronal

triplets. The neural triplet contains one excitatory-inhibitory pair of phase code neurons (E, I) and a rate

code neuron. Here, excitatory neurons are updated by

$$\Delta E_i(t) = CI_i(t) - D \times J(r > r_{min}) \times E_i(t) + B_i(t) \qquad (1)$$

158   where $\Delta E(t) = E(t + \Delta t) – E(t)$; and inhibitory neurons are updated by

$$\Delta I_i(t) = -CE_i(t) - D \times J(r > r_{min}) \times I_i(t) \qquad (2)$$

Here, phase code neurons will oscillate at a frequency of $C/2\pi$. In the pMFC, which executes top-down

control by sending bursts, activity oscillates at theta (6 Hz) frequency, in line with suggestions of

previous empirical work (Cavanagh & Frank, 2014; Womelsdorf, Johnston, Vinck, & Everling, 2010).

Different from our previous modelling work, theta frequency was used in the Mapping unit (see

Discussion) as well. Because bursts (B(t)) lead to a significant increase of power, a radius parameter

(r_{min}) is implemented in order to attract power (r) back to baseline after a burst. Since continuously high

pMFC power is computationally suboptimal and empirically implausible (Holroyd, 2016), power in the

pMFC was attracted towards a smaller radius, $r_{min} = .50$, than in the Mapping unit, $r_{min} = 1$. How fast

oscillations decay to baseline is determined by a damping parameter (D) which was set to $D = .30$ in

the Mapping unit. Since the pMFC not only receives bursts but also sends them, a slower decay $D = .01$

was implemented here to allow a sufficient activity window ($\sim$ 500 ms/3 theta cycles) for bursts to be

sent. In order to reduce model complexity, no oscillations were used in the LFC and aMFC. For a full

description of model dynamics see Verbeke & Verguts, (2019).

Thus, in the Sync model, on every trial multiple time steps were simulated in which oscillations

occurred. Here, motor nodes accumulate activation over time. The motor node with the maximal

accumulated activation over time, was considered as the model response. Values of stimulus action

pairs (Q) in each rule module (R) are updated by

$$Q(s,a)_{j+1} = Q(s,a)_j + \alpha * (Rew - Q(s,a)_j) \tag{3}$$

180   in which α is the Mapping learning rate and *Rew* is the reward received by the agent.

181   As described above, the Sync model has an additional Switch unit which adds a hierarchical

182   learning algorithm on top of the RW (fixed learning rate) algorithm in the Mapping unit. This Switch

183   unit evaluates whether there was a rule switch. More specifically, it learns a value (V) for every rule

184   module (R) by

$$V(R)_{j+1} = V(R)_j + \alpha_{high} * (Rew - V(R)_j) \qquad (4)$$

187   in which α_{high} is the hierarchically higher Switch learning rate. The difference between the expected

188   value $V(R)$ in Equation (6) and the obtained *Rew* (i.e., the prediction error) is accumulated in the

189   Accumulator neuron (A) via

$$A_{j+1} = \gamma * A_j + (1 - \gamma) * f(Rew - V(R)_j) \qquad (5)$$

Since switches are only required when negative feedback occurs, the Accumulator neuron was selective

for negative prediction errors. Specifically, $f(Rew - V(R)) = -(Rew - V(R))$ when the prediction

error is negative and $f(Rew - V(R)) = 0$ when the prediction error is positive. Here, γ is the

Cumulation parameter which determines how strongly the Accumulation neuron is affected by a single

prediction error. While a low Cumulation parameter causes the agent to strongly weigh single prediction

error and therefore regularly switch between rule modules, a high Cumulation parameter implements a

more conservative approach. When the Accumulator neuron reaches a Switch threshold of .5, the model

will switch to another rule module (R) in the Mapping unit.

Behavioral data fitting

For behavioral data fitting only, the full Sync model was simplified by introducing a hard gating

process between task rules instead of BBS and a softmax response selection mechanism described by

$$p(a = i) = \frac{e^{Q(s,i)/\tau}}{\sum_{a=1}^{2} e^{Q(s,a)/\tau}} \qquad (6)$$

in which $Q(s,a)$ is the value of a given stimulus-action pair (s, a) and τ is the temperature parameter

which determines how strongly the agent explores different actions (i). This allowed to skip the loop of

1500 timesteps every trial, which was needed to simulate oscillations (see Equations (1) and (2)). We

refer to this model as the behavioral Sync (bSync) model.

On top of the bSync model, two other models were fitted as well. The RW and ALR model

are both restricted to only the Mapping unit (with one rule module). Both models use a response

selection mechanism as described by Equation (6) and learn stimulus-action pairs by Equation (3).

Importantly, the RW model (Rescorla & Wagner, 1972) had a constant learning rate while the ALR

model (Bai et al., 2014), was implemented with an adaptable learning rate. Here, the Mapping learning

rate is updated on every trial by

$$\alpha_{j+1} = \eta * \left| Rew - Q(s,a)_j \right| + (1 - \eta) * \alpha_j \tag{7}$$

217   in which η determines how strongly the learning rate is influenced by the current difference between

218   *Rew* and *Q* (lower-level prediction error).

219   ***Model evaluation***

220   For each subject, the goodness of fit of these three models on the behavioral data was

221   compared by using three measures. The log-likelihood (*LL*)

$$LL = \sum_{j=1}^{J} a_j * \ln \left(p(a_j = 1) \right) + (1 - a_j) * \ln \left(p(a_j = 0) \right) \tag{8}$$

224   in which *p(a)* is the probability of the given action (see Equation (6)) and *J* represents the number of

225   trials. The Akaike information criterion (AIC) uses this *LL* but includes a penalty for the number of

226   parameters (*k; k* = 2 for RW, *k* = 3 for ALR and *k* = 4 for bSync) that were used in the model:

$$AIC = 2 * k - 2 * LL \tag{9}$$

229   From this AIC, AIC weights (*wAIC*) can be derived which allows to make a relative comparison

230   between the model fit of the three different models. These wAIC values are computed as

$$wAIC = \frac{e^{-\frac{1}{2}\Delta AIC_m}}{\sum_{m=1}^{M} e^{-\frac{1}{2}\Delta AIC_m}} \qquad (10)$$

233   in which M is the number of models that are compared ($M = 3$) and

$$\Delta AIC_m = AIC_m - \min(AIC) \qquad (11)$$

Here, min(AIC) is the lowest AIC value out of the three models for that subject. Thus, Equation (10)

results in a wAIC value for each model. The sum of all three wAIC values is 1 and models with higher

wAIC values provide a better fit to the data.

Simulations

In order to provide hypotheses for EEG data, 27 simulations of the full Sync model were

performed. For all simulations, the same parameter values were used. These parameter values were

sampled from the distribution of best fitting parameter values of the bSync model so that overall

accuracy of model simulations ($M = 78.00\%$, $SD = 1.30$) closely resembled accuracy of subjects ($M =$

76.80%, $SD = 4.91$). This resulted in a Mapping learning rate (α) of .8, a Switch learning rate (α_{high}) of

.1 and a Cumulation parameter (γ) of .3. The full Sync model did not use a Temperature (τ) parameter;

instead, the synchronization procedure introduces noise, which also introduces some randomness in

behavior. The Switch threshold was always fixed to .5. Trials were simulated as a fixed period of 500

ms in which the visual layer received stimulation. After this period, the response node with the highest

maximum activation was registered as the response of the model. Thereafter, 1500 ms of inter-trial

interval was simulated in order to provide a post-feedback period that could be analyzed in the same

way as the empirical data. All other aspects of the task, such as the frequency and timing of rule

switches, were the same for the model as for the human subjects.

Power Analyses

Time-frequency decomposition was performed on the excitatory neuron (see Equation (1))

within the neuronal triplet of the model's pMFC node in the model. Complex Morlet wavelets were

used for frequencies between 2 and 48 Hz defined in 25 logarithmically spaced steps. For each

frequency, between 3 and 8 cycles were used, also defined in 25 logarithmically spaced steps. Power

was extracted as the squared absolute value of the time-frequency decomposed signal. In order to locate

activity that was specific to feedback processing, the difference between power in trials with negative

feedback and trials with positive feedback was computed. For simplicity, we selected the 2.5% most

positive values as a cluster of interest. This cluster contained one group of data points in theta frequency

and approximately 250-500 ms after feedback (see Verbeke & Verguts, 2019 for timing details). On

every trial, the mean power in this cluster was computed and entered in the consecutive analyses. Since

a negative prediction error in the model increases activity of the pMFC, we performed a linear

regression of cluster power with prediction error as the independent variable. To test our first

hypothesis, that this relationship was specific to negative prediction error, a second regression model

was used that also included the interaction between prediction error and reward. The second hypothesis

states that because negative prediction errors are strongest at the moment of a rule switch, a peak of

post-feedback theta power should be found when data is locked to rule switches. To investigate this, we

extracted power from the model cluster in trials within a 31-trial window around the rule switch (-15 to

+15). The time course (one data point for each of the 31 trials) that resulted after averaging over all (15)

rule switches and all (27) simulations was then used as a regressor in a linear regression with data from

the empirical clusters.

Phase Analyses

275   Our third hypothesis stated that phase-coupling between pMFC and model nodes in the

Mapping unit was stronger after negative feedback. Specifically, theta power in the model pMFC

increases after negative prediction errors. When there is sufficient power in the pMFC, it will increase

synchronization in the Mapping unit (posterior/lateral task-related regions, e.g., pre-motor or visual

areas). For this purpose, the pMFC uses binding by random bursts (Verguts, 2017). Here, the pMFC

will send bursts to the Mapping unit at specific phases. Thereby it will shift the phase of neurons in the

Mapping unit (see Verbeke & Verguts, 2019 for details). This leads to phase shifts in these lower pre-

motor or visual task-related areas, and a short period of phase-alignment between these task-related

areas in the Mapping unit and pMFC. Phase was extracted in all model nodes by taking the angle of the

Hilbert transform of the raw signal. For simplicity the model was implemented without inter-areal

delays. Furthermore, in contrast to analyses on the empirical EEG data (see Equation (12)), control for

volume conduction was not needed, so the regular phase locking value (PLV; Lachaux, Rodriguez,

Martinerie, & Varela, 1999) was computed between the model pMFC and the nodes in the motor layer

of the Mapping unit. This PLV was then averaged over all 4 motor nodes and the time period included

in the power cluster (~250-500 ms post feedback).

EEG Analyses

Preprocessing

The data were re-referenced offline to the average of the mastoid electrodes. Breaks or other

offline periods were manually removed. Particularly noisy electrodes were interpolated between

neighboring electrodes on all timesteps. For three subjects, one electrode was interpolated; for another

three subjects we had to interpolate two electrodes; because of a bridge, one subject needed interpolation

for five posterior electrodes. Additionally, activity was band-pass filtered between 1 and 48 Hz in order

to remove slow drifts and line noise of 50 Hz. Eyeblinks and other motor-related noise components

were removed through EEGLAB independent component analysis (ICA). After ICA-removal, the data

was epoched, once locked to feedback onset, and once to stimulus onset. The epochs based on stimulus

onset were used to extract baseline activation, which was -1500 to -500 ms relative to stimulus onset.

This baseline activity was subtracted from all epochs. After epoching, on average 7.5% of epochs were

removed by applying an amplitude threshold of -500 to 500 mV and an improbability test with 6

standard deviations for single electrodes and 2 standard deviations for all electrodes, as described in

Makoto's preprocessing pipeline (Makoto, 2018). Before time-frequency analyses, data was also

downsampled to 512 Hz.

Time-frequency Decomposition

Time-frequency decomposition was based on code from (Cohen, 2014). Similar to model

analyses, complex Morlet wavelets were used for frequencies between 2 and 48 Hz defined in 25

logarithmically spaced steps. For each frequency, between 3 and 8 cycles were used, also defined in 25

logarithmically spaced steps.

Power Computation

312   A baseline correction was applied by dividing the power estimates for each subject, electrode

313 and frequency by the average baseline activity (-1500 ms to -500 ms from stimulus onset) across all

314 480 trials. Finally, the baseline-corrected data underwent a decibel conversion. Before final analyses,

315 also trials with late responses were removed from the data.

Power Cluster Analyses

Similar to model analyses, we were interested in activity selective for feedback. Hence, a

contrast between Z-scored power in trials with negative feedback and trials with positive feedback was

computed. On these values, a non-parametric clustering procedure was applied (Maris & Oostenveld,

2007). The distribution of statistics was computed. On each side of the distribution (two-sided test), the

1% most extreme values were entered into the clustering analysis. From these, we clustered adjacent

neighbors in the channel, frequency and time domains. To calculate our cluster-level statistic, we

multiplied the number of items (i.e., (channel, frequency, time) points) in the cluster with the largest

statistic of that cluster (see also Maris & Oostenveld, 2007). A significance threshold of 5% was

imposed on the subsequent non-parametric permutation test with 1000 iterations. Clusters that survived

this permutation test were taken into the consecutive analyses. As an exploratory analysis, we aimed to

link individual differences in behavioral model fit to EEG data; for that purpose, we extracted the mean

cluster statistic for each subject, and ran a Spearman rank correlation of these statistics with wAIC of

the bSync model obtained in the behavioral model fitting procedure.

Midfrontal Theta Power and Prediction Error

The Sync model uniquely yields specific EEG predictions, to which we now turn. To test the

first model-driven EEG hypothesis of a relation between theta power and prediction errors, we first

extracted a measure of prediction error for every subject on every trial by simulating the bSync model.

Importantly, this prediction error was extracted from the learning process on the hierarchically higher

level in the Switch unit (Equation (4)), not the lower-level learning process in the Mapping unit

(Equation (3)). This measure of prediction error was then used in a trial-by-trial linear mixed effects

model as a predictor for the Z-scored power of every cluster (averaged across all (time, electrode,

frequency points) in the cluster), that survived the feedback-locked analysis described above. Here, a

random intercept for every subject was included and a fixed slope (i.e., the prediction error). Because

the Sync model predicted different relationships for positive prediction errors and negative prediction

errors, also the interaction between prediction errors and reward was tested. Additionally, in order to

explore whether the individual differences in wAIC influenced the interaction between prediction errors

and reward, also a three-way interaction between prediction error, reward and wAIC was tested. For

these purposes, three regression models were fitted: One in which only prediction error was included

as regressor, one in which both prediction error and the interaction between prediction error and reward

were included as regressors, and finally a third model in which the main effect, the two-way interaction,

and an extra three-way interaction between prediction error, reward and wAIC were included as

regressors. These regression models were then compared via ANOVA.

Rule Switch Locking

A second model-driven EEG hypothesis considers theta power locked to the moment of a rule

switch. For this analysis, EEG data of 31 trials around the rule switch (-15 to +15 trials, including the

rule switch trial itself) were extracted. On these trials, the mean power within each cluster selective for

feedback was computed. This data was then again averaged over all trials at a specific distance (-15 to

+15) from switch, giving us a time course of mean cluster-power from -15 trials before rule switch to

15 trials after rule switch for every subject. On each time point, a 99.84% confidence interval (CI) was

computed based on a Bonferroni correction for multiple comparisons (100-(5/31)). This confidence

interval was compared to a baseline power. Baseline power was computed based on the mean power in

this cluster, averaged over all trials that were more than 15 trials removed from the rule switch.

As the rule switch trial, we considered in separate analyses both the actual rule switch and the

subjective indication of a rule switch. Hence, power close to a rule switch was compared with the mean

power of trials that were far from the rule switch. When the confidence interval did not include the

baseline value, power on this trial was considered as significantly deviating from baseline. Additionally,

we aimed to investigate the similarity between the data pattern predicted by the model and the empirical

data. For this purpose, data from the bSync model simulations (see above for details) was used as a

linear regressor for the empirical data. Also for this hypothesis, an extra analysis was performed to

investigate whether wAIC had an influence on the observed effect. Here, we extracted subject data on

trials of which cluster power significantly deviated from baseline and used this data as a dependent

variable in a linear regression with wAIC.

Midfrontal-Posterior Phase-Coupling Analyses

For the third model-driven EEG hypothesis, we considered all midline electrodes (10) as seed

and other electrodes (54) as receiver in the phase connectivity analyses. Because we were interested in

phase-locking related to rule modules conveying the correct response, all data was lateralized with

respect to the correct response. All data ipsi-lateral to the correct response was brought to the left

electrodes; all contra-lateral data was brought to the right electrodes. The iPLV (Bruña, Maestú, &

Pereda, 2018) was computed between all midline electrodes and all lateral electrodes for every time

point in the feedback-locked data. This iPLV measure was computed by the following equation

$$iPLV = |\ \frac{1}{n} \sum_{t=1}^{n} Im(e^{-i(\Delta\varphi_t)})\ | \tag{12}$$

which computes the average phase angle (φ) difference over trials (t). By only looking at the imaginary

(Im) part of this phase angle difference, phase differences of zero are eliminated. Hence, volume

conduction effects are excluded, because such volume conduction effects are represented in zero-phase

differences (Bruña et al., 2018; Nolte et al., 2004). Again, a non-parametric cluster algorithm was

performed on the contrast between iPLV for trials with negative versus positive feedback (note that the

fact that our effect of interest compares negative versus positive feedback, also safeguards against

possible volume conduction effects). For this analysis, only data of one midline electrode was used.

More specifically, we checked on which of the 10 midline electrodes the mean contrast in the theta

frequency (4-8 Hz) reached a maximum. This was in the FCz electrode, hence only iPLV between FCz

and all lateral electrodes were entered in the clustering algorithm. As for power, an exploratory analysis

was performed in which we extracted the mean cluster statistic for each subject, and ran a Spearman

rank correlation of these statistics with wAIC of the bSync model obtained in the model fitting

procedure.

<div align="center">

Results

</div>

Behavioral Data

Overall, participants had a mean accuracy of 76.80% ($SD = 4.92\%$) and a mean RT of 544ms

($SD = 71.31$ ms). A paired t-test confirmed that there were no significant differences between the

experiment block in which subjects had to indicate when a task switch happened or when they did not

have to indicate this (see Materials and Methods for details), neither in accuracy ($t(26) = .029, p = .977$),

nor in RT ($t(26) = -1.290, p = .208$).

Model Analyses

The distribution of all fitted parameter values for each model is given in Fig 2A. Goodness of

fit measures are summarized in Table 1. Here, log-likelihood was highest (best) for the bSync model,

lowest for the ALR model, with the RW model in between. When a penalty for model complexity was

applied (AIC, wAIC), the RW and bSync models performed approximately equal. Importantly, wAIC

results indicated significant differences across individuals. As illustrated in Fig 2B, subjects could be

roughly divided into three groups based on the wAIC. In one group (8 subjects), the wAIC were

significantly smaller (worse) for the bSync model ($M = .12, SD = .026$) than for the RW model ($M =$

$.78, SD = .027$). A second group (7 subjects) showed wAIC values that were approximately equally

strong for the bSync ($M = .44, SD = .036$) as for the RW model ($M = .50, SD = .032$). In a third group

(12 subjects), the bSync model showed wAIC that were significantly higher for the bSync model ($M =$

$.64, SD =. 027$) than for the RW model ($M = .32, SD = .026$).

Three parameters of the bSync model showed a significant correlation with wAIC (Fig 2C).

These parameters were the Switch learning rate ($rho = -.761, p < .001$), the Cumulation parameter (rho

$= -.708, p < .001$), and the Temperature parameter ($rho = -.497, p = .008$). There was no significant

correlation with the Mapping learning rate ($rho = -.145, p = .468$). Additionally, a correlation test

between accuracy and wAIC revealed that the bSync model fitted significantly better for subjects with

a lower accuracy ($rho = -.510, p = .007$). Also correlations between wAIC values and parameters of the

other two models were tested but none of these correlations reached significance.

We next estimated a learning curve for each model and each wAIC group (Fig 2D). This

learning curve represents the estimated likelihood of the correct response averaged over all rule switches

and all subjects within a group. Differences in learning curve between the three groups are very subtle:

We conclude that an average measure like switch-locked learning curve does not suffice to empirically

distinguish between the three models.

As described in Equation (5), the bSync model only uses negative prediction errors to evaluate

rule switches. Nevertheless, it might be argued that also positive prediction errors determine rule

switching. To test this, an alternative version of the bSync model (bSync-linear) was currently also

fitted. Here, $f\big(Rew - V(R)\big) = -(Rew - V(R))$ for all trials. Hence, switch evidence increased for

negative prediction errors and decreased for positive prediction errors. Here, we observed a clear

advantage in terms of AIC for the original bSync model ($M = 420.70, SD = 2.22$) compared to the

alternative bSync-linear model ($M = 481.12, SD = 75.28$). Hence, only the original bSync model was

used for the consecutive analyses.

In sum, we found that, for the bSync model, participants' behavior is best explained by the

model version that is biased towards negative prediction errors to evaluate rule switches. When

comparing this bSync model with the RW and ALR models, three groups of participants could be

distinguished. Moreover, the individual measures of model fit correlated significantly with accuracy

and several parameters of the bSync model.

EEG and Model Data

Power Cluster Analyses

Cluster analysis on post-feedback power revealed three significant clusters that were selective

for feedback processing (Fig 3). All three clusters appeared between 0 and 750 ms from feedback onset.

As was predicted by the Sync model (Fig 3A), one of these clusters was in the theta frequency range ($\sim$

4-8 Hz) and located on midfrontal electrodes (Fig 3B, D). This theta cluster showed more power for

negative than for positive feedback. Additionally, we found two clusters located on the posterior

channels. One of these clusters was in the delta frequency (< 4 Hz; Fig 3B, E), the other cluster was

located in the alpha-frequency range (~ 8-15 Hz; Fig 3B, C). Both the delta and alpha cluster showed

less power for negative feedback than for positive feedback. No correlation between the power contrast

of a cluster and subjects' wAIC for the bSync reached significance.

Midfrontal Theta Power and Prediction Error

We next consider the first of three model-driven EEG hypotheses. We first perform statistical

analysis on the Sync-model simulated data (Fig 4A). Theta power in the Sync model data was best

predicted by the regression model that included an interaction between reward and prediction error ($F(1$,

$11980) = 22133, p < .001$). Hence, there was a significant main effect of prediction error ($F(1, 11980)$

$= 742962, p < .001, \beta = -4.99$) and a significant interaction of prediction error and reward ($F(1, 11980)$

$= 22133, p < .001, \beta = 4.48$). Thus, as predicted, the model cluster showed a negative linear relationship

with negative prediction error, and no linear relationship with positive prediction error (Fig 4A).

In order to test this prediction in the empirical theta cluster (cluster reported in the previous

section), prediction errors were estimated by simulating the bSync model (see Fig 5A). Importantly,

these prediction error estimates were extracted from learning in the Switch unit (see Equation (4)) and

not from the learning of stimulus-action pairs in the Mapping unit (Equation (3). For theta power, the

regression model including the interaction between prediction error and reward fitted significantly

better than the regression model with only prediction error as regressor ($\chi^2(1, N = 27) = 110, p < .001$).

Additionally, the regression model including the three-way interaction between prediction error, reward

and wAIC fitted significantly better than the regression model with only the two-way interaction ($\chi^2(2,$

$N = 27) = 20.74, p < .001$). Here, all effects reached significance. Hence, there was a main effect of

prediction error ($\chi^2(1, N = 27) = 1299, p < .001, \beta = -.79$) and an interaction of prediction error with

reward ($\chi^2(1, N = 27) = 110, p < .001, \beta = .65$). Additionally, there was a significant interaction between

prediction error, reward and wAIC ($\chi^2(2, N = 27) = 20.90, p < .001$). As can be observed in Fig 4B

these results indicated a significant negative linear relationship between power and negative prediction

error, which was stronger for subjects with a high wAIC (i.e., better behavioral fit of the Sync model);

and an absence of linear relationship between power and positive prediction error which did not differ

significantly for wAIC (Fig 4B). Interestingly, the three-way interaction was significant in the

unrewarded (negative prediction error) trials (β = -.89, p < .001) but did not reach significance in the

rewarded (positive prediction error) trials (β = .44, p = .077).

For exploratory purposes, we investigated the same regression models in the delta and alpha

clusters. In the delta cluster, the difference in regression model fit between the regression models

without and with the prediction error-reward interaction term did not reach significance ($\chi^2(1, N = 27)$

$= 3.49, p = .062$). However, the regression model that also included the three-way interaction between

prediction error, reward and wAIC fitted significantly better than the regression model with no

interaction terms ($\chi^2(3, N = 27) = 9.27, p = .026$). Here, the main effect of prediction error was

significant ($\chi^2(1, N = 27) = 580, p < .001, \beta = .45$). The interaction between prediction error and reward

did not reach significance ($\chi^2(1, N = 27) = 3.49, p = .062, \beta = -.07$). Also the three-way interaction term

did not reach significance ($\chi^2(2, N = 27) = 5.83, p = .054$). However, if the interaction was considered

separately for rewarded trials ($\beta = .61, p = .018$) and unrewarded trials ($\beta = -.50, p = .033$), both reached

significance. As can be observed in Fig 4C, this meant that there was a positive linear relationship

between power and prediction error for both positive and negative prediction error (Fig 4C). For

subjects with low wAIC, the slope in unrewarded trials was similar to the slope in rewarded trials, while

for subjects with high wAIC, an inverse effect of the theta cluster was observed in which there was a

flat slope in unrewarded trials but a steeper slope in rewarded trials.

In the alpha cluster, the regression model with the two-way interaction term showed a

significantly better fit than the regression model without interaction ($\chi^2(1, N = 27) = 224, p < .001$).

When the three-way interaction was added, it did not lead to a significantly better regression model (χ^2

$(2, N = 27) = .35, p = .841$). Here, a significant main effect of prediction error ($\chi^2(1, N = 27) = 142, p$

$< .001, \beta = .85$) and a significant interaction between prediction error and reward ($\chi^2(1, N = 27) = 226,$

$p < .001$, $\beta = -1.38$) were observed. The three-way interaction between prediction error, reward and

wAIC was not significant ($\chi^2(2, N = 27) = .360$, $p = .833$). As is shown in Fig 4D, power in the alpha

cluster exhibited a positive linear relationship for negative prediction error, but a negative linear

relationship with positive prediction error. These effects did not differ with respect to wAIC.

To explore the topology of these interaction effects described above, we conducted another

cluster analysis. Here, we multiplied prediction error (scaled separately for positive and negative

prediction errors) with reward (-1 for unrewarded trials and 1 for rewarded trials) as a regressor for

power. This resulted in a contrast value for the interaction between prediction error and reward for each

electrode, timepoint and frequency. These contrast values were then entered into the clustering

algorithm. As expected, we observed a significant cluster in the alpha frequency (Fig 5B) which was

strongest on posterior electrodes (Fig 5C). We also observed significant effects in the theta and delta

frequency ranges (Fig 5D). Although the interaction pattern for theta (Fig 4B) and delta (Fig 4C) are

mirrored (and thus qualitatively different), they are represented by a similar contrast value, because in

both theta and delta empirical patterns, the slope for positive prediction errors is larger than the slope

for negative prediction errors. Because they are also topographically (partially) overlapping, they were

clustered together by the algorithm, resulting in one cluster that was a mixture of the theta and delta

effects on both time-frequency and topographical level.

In sum, in line with model predictions, we found a linear relationship between post-feedback

theta power and negative prediction errors but not with positive prediction errors (interaction between

reward and prediction error). Moreover, we found that this interaction effect was stronger for

participants that fitted better with the bSync model. On top of model predictions, two other clusters

could be distinguished in post-feedback power. Here, a delta cluster showed an almost exactly mirrored

pattern relative to the theta cluster. An alpha cluster showed an inversed U-shaped pattern with respect

to prediction errors.

Rule Switch Locking

For the second model-driven EEG hypothesis, power from the theta, alpha, and delta clusters

was extracted in trials within a 31-trial window from the rule switch (-15 to +15). In all clusters, one

trial significantly deviated from baseline power. In the theta cluster (Fig 6A), only the rule switch (0;

i.e., all trials exactly at rule switch) was significant above baseline (CI99.84 [-2.059, .256], *baseline* =

-2.340). Linear regression of the data time course (across 31 trials) on the Sync model time course

showed a significant effect ($F(1, 835) = 20.51, p < .001, R^2_{adj} = .023, \beta = .31$). In the delta cluster (Fig

6B), only the rule switch (0) was significantly below baseline (CI99.84 [-2.450, -1.265], *baseline* = -

1.201). Linear regression of the data time course on the Sync model time course revealed a significant

correlation ($F(1, 835) = 7.36, p = .007, R^2_{adj} = .008, \beta = -.18$). For the alpha cluster (Fig 6C), again one

trial was significantly below baseline (CI99.84 [-6.275, -3.603], *baseline* = -3.584). Notably, this was

the point right after the rule switch (+1; i.e., all trials right after the rule switch). Moreover, when data

was locked to the moment where subjects indicated the rule switch (Fig 6D), alpha power reaches a

minimum at this exact moment (CI99.84 [-7.675, -3.686], *baseline* = -3.584). Also in the alpha cluster,

the linear regression of the power on the Sync model pattern reached significance with a negative slope

($F(1, 835) = 32.72, p < .001, R^2_{adj} = .037, \beta = -.65$).

Power at the peak trials (trials at point 0 for theta and delta, trials at point +1 for alpha) was

extracted and added to a linear regression with wAIC as predictor. This revealed no significant effects

for the theta ($F(1, 25) = .004, p = .948, R^2_{adj} = -.040, \beta = -.10$) or delta cluster ($F(1, 25) = .680, p = .417,$

$R^2_{adj} = -.012, \beta = .66$). However, the effect of wAIC did reach significance in the alpha cluster ($F(1, 25)$

$= 7.22, p = .013, R^2_{adj} = .193, \beta = 4.17$). Fig 7 sheds light on how activity in the alpha cluster differed

depending on wAIC. For illustrative purposes, subjects were divided in three groups of low, middle and

high wAIC. For each group, the data pattern of alpha activity was plotted, once locked to the real rule

switch (Fig 7A) and once locked to the indication of a rule switch (Fig 7B). Here, it is observed that the

alpha pattern is mainly driven by subjects with a low wAIC (i.e., bad fit) for the bSync model.

In sum, simulated theta power significantly predicted empirical theta power. Here, theta

power peaked at the moment of a rule switch. Just like in the first model-driven EEG hypothesis, power

from the empirical delta cluster showed the mirrored pattern compared to theta. Remarkably, alpha

cluster showed a dip in power, not with respect to the actual rule switch but with respect to the

subjectively indicated rule switch.

Midfrontal-Posterior Phase-Coupling Analyses

We next turn to our third model-driven EEG analysis concerning an increase of phase-

coupling between midfrontal and posterior electrodes after negative feedback. As previously described,

in the Sync model, this coupling is induced by bursts that are sent from pMFC to posterior areas in the

Mapping unit. Since pMFC power is stronger after negative feedback, also the number of bursts and

the amount of phase-coupling is increased. To investigate this, we looked at phase-coupling between a

midfrontal electrode (FCz) and all lateral electrodes.

Here, non-parametric cluster analyses on the phase-locking data (Fig 8) revealed six

significant clusters that were selective for feedback (for details see Materials and Methods). These

clusters were located in the theta (4; Fig 8A, B, C) or delta (2; Fig 8A, B, D) frequency band. In the

theta frequency band, two clusters were located at temporal electrodes; two other clusters were located

on more lateral/anterior frontal electrodes. In the delta frequency band, both clusters were located on

posterior electrodes. In line with the results of Sync model simulations (Fig 8E), the theta clusters

showed an increase in phase-locking after negative feedback. This was the case for both the ipsilateral

and contralateral electrodes. The delta clusters show the inverse pattern of the theta cluster. Here, phase-

locking was stronger after positive feedback than after negative feedback in both the ipsi- and

contralateral cluster. As in the power analyses, we also explored whether the phase-locking contrast in

each cluster correlated with the subjects' wAIC for the bSync model. None of these correlations reached

significance.

In sum, as predicted by the Sync model, we found stronger phase-coupling in the theta

frequency between midfrontal and more posterior electrodes after negative feedback than after positive

feedback. Additionally, we found an increase in phase-coupling between midfrontal and lateral frontal

electrodes, also in the theta frequency range. Similar to our power analyses, we found an inverse effect

in the delta frequency compared to the theta frequency.

Discussion

The current study aimed to gain insight in the neural mechanisms that allow humans to

flexibly adapt to rule changes in the environment. Twenty-seven healthy human subjects were tested

on a probabilistic reversal learning task while measuring EEG. Behaviorally, three models of increasing

hierarchical complexity were compared. A first, RW model, updated the value of stimulus-action

mappings on a trial-by-trial basis with a fixed learning rate. In a second, ALR model, this approach was

extended with an adaptable learning rate, allowing the ALR model to flexibly adapt to rule switches

(fast learning) but to also be robust to noise evoked by probabilistic feedback (slow learning). The third,

Sync model implemented modularity to retain task-specific mappings. It employs hierarchical learning

to determine when to switch between rule modules. No evidence was found for the ALR model, while

for some subjects the RW model fit best, and for others the Sync model.

Simulations of the Sync model allowed formulation and testing of three model-driven EEG

hypotheses. The first hypothesis concerns midfrontal theta and prediction errors. In the Sync model,

prediction errors are used to evaluate how much control is needed. The level of control is represented

by theta power in the pMFC. Since only negative prediction errors inform about rule switches, the Sync

model increased control after negative prediction errors but not after positive prediction errors. Thus,

although most previous work (Cavanagh, Cohen, & Allen, 2009; Cavanagh, Frank, Klein, & Allen,

2010; Ergo, De Loof, Janssens, & Verguts, 2019) described a U-shape relationship between prediction

error and theta power, we currently hypothesized and observed a selectivity for negative prediction

errors (see also Janssen et al., 2016). A linear relationship between prediction error and power in the

theta cluster was observed for unrewarded trials (negative prediction error) but not for rewarded trials

(positive prediction error). This effect was stronger for subjects with a better Sync model fit. Based on

our theoretically driven hypothesis, we did not extract prediction errors from stimulus-action learning

but from learning in the Switch unit. Future research should investigate how midfrontal theta is

influenced by different types of prediction errors.

Since prediction errors are strongest at the rule switch, a second model-driven hypothesis

stated that theta power peaks at rule switches. Again, this hypothesis was empirically supported.

Moreover, simulated power significantly predicted power in the empirical theta cluster. Consistent with earlier work (Cunillera et al., 2012; Sauseng et al., 2006), theta power increased and alpha power decreased at rule switches. How this theta increase relates to the alpha decrease, and to the individual differences that we observed, deserves future research.

Current work provides a mechanistic explanation how increases in theta power after prediction errors implement new task rules by synchronizing modules. This resulted in a third model-driven hypothesis. Here, the Sync model uniquely predicted that phase connectivity would increase after negative feedback. We found six significant clusters. Four of them were in theta frequency range and showed the predicted pattern. Two of these clusters were located on posterior-temporal electrodes, roughly in line with our prediction of motor and visual areas. The remaining four clusters were consistent with previous work (Cavanagh et al., 2010) showing a feedback-locked, prediction-error induced increase of theta phase-coupling between midfrontal and lateral frontal sites, and a delta coupling decrease between midfrontal and posterior cortical sites.

Several hypotheses remain to be tested. First, as mentioned in the Methods, previous modeling work (Verbeke & Verguts, 2019) used gamma frequency in the Mapping unit instead of theta frequency. This frequency was currently changed because empirical work demonstrated within-frequency (theta-theta) coupling (Cavanagh et al., 2009; Clouter, Shapiro, & Hanslmayr, 2017) during cognitive tasks, in addition to cross-frequency coupling. We thus also studied within-frequency coupling empirically. Nevertheless, future work, using MEG or more invasive measurements, should also study the role of cross-frequency (theta-gamma) coupling. Second, the limited spatial resolution of EEG did not allow testing whether task rules are implemented by synchronizing task-relevant modules.

Several model extensions can be made. For instance, while for the current reversal learning task it was sufficient to use prediction error to determine when to make a binary switch, a more sophisticated approach might apply in everyday life, where contextual cues allow navigating a vast map of tasks and rules. One way to address this issue is by adding second-level contextual features which allow the LFC to (learn to) infer which of multiple task modules should be synchronized. Additionally, scalability of the Sync model is currently limited by how modularity was implemented in the Mapping

unit. Here, none of the rule-1 mappings are shared with rule 2. Such a strict division of task mappings

is optimal when mappings are orthogonal. However, when some mappings can be generalized between

tasks, the current approach does not allow knowledge transfer across contexts. As addressed earlier

(Collins & Frank, 2013; Gershman, Blei, & Niv, 2010), a more sustainable way is to construct modules

of mappings that are shared between tasks. Instead of learning each new task from scratch, this approach

allows transferring partial knowledge between tasks. Future work should explore whether these more

complex hierarchical learning algorithms can be integrated in the Sync model.

Recent work emphasized that reinforcement learning can operate not only over observed

states, but also over belief states that an agent may infer (Gershman & Uchida, 2019; Wilson et al.,

2014). In the Sync model, there were no (contextual) cues. Therefore, the Sync model could rely

exclusively on prediction errors to estimate the belief state (task rule) of the environment. When

contextual features are added, a future version of the Sync model may estimate belief states in a more

efficient manner. Note also that the Sync model uses two types of prediction error: One to adjust lower-

level mappings, and another to determine the (higher-level) task rule state. Instead, non-hierarchical

models (e.g., RW, ALR) use prediction errors only to adjust lower-level mappings.

Building on suggestions of previous work (Piray, Dezfouli, Heskes, Frank, & Daw, 2019), the

current study illustrated how individual differences in model fit can be leveraged to address cognitive

questions. Three groups were distinguished: one group aligned with the RW model, a second group

aligned with the Sync model and in a third group, the RW and Sync model could not be empirically

distinguished. Although the differences between groups were non-significant when averaging over

several trials (e.g., learning curve), more fine-grained measures (e.g., wAIC, trial-by-trial power)

revealed important individual differences. Interestingly, subjects with lower accuracy fitted better with

the Sync model. This is consistent with previous work (Verbeke & Verguts, 2019) which illustrated

that modularity as employed by the Sync model is only beneficial if the learning problem is sufficiently

complex. Furthermore, despite previous work showing a good behavioral fit of the ALR model (Bai et

al., 2014), the fit of the ALR model in the current study was consistently low. In contrast to previous

studies, the current task applied more frequent task rule switches without long stable trial blocks,

favoring constant high learning rates. Thus, future work should investigate whether subjects employ

the RW, ALR, or Sync framework depending on the structure and complexity of the task.

The Sync model implements modularity via neural oscillations between task-relevant areas.

This concords with a role of neural oscillations for a wide variety of cognitive functions, including

visual attention (Gray & Singer, 1989; Jensen, Bonnefond, & VanRullen, 2012), working memory

(Hsieh, Ekstrom, & Ranganath, 2011; Lisman & Idiart, 1995), cognitive control (Cavanagh & Frank,

2014) and declarative learning (Ergo, De Loof, & Verguts, 2020). According to the BBS hypothesis

(Fries, 2015), these cognitive functions require binding of several stimuli or features. Current work

described how oscillations, and more specifically synchronization, might be relevant in hierarchical

rule learning.

On anatomical-functional level, we built on suggestions from previous work that pMFC

cooperates with LFC to exert hierarchical control over lower-level motor processes (Alexander &

Brown, 2015; Koechlin, Ody, & Kouneiher, 2003). In the Sync model, LFC signals which rule modules

should be synchronized. Consistently, previous theories describe LFC as containing task demands

(Botvinick et al., 2001), and empirical work found strong communication between LFC and pMFC in

cognitive tasks (Cavanagh et al., 2010; Kondo, Osaka, & Osaka, 2004; Mac Donald, Cohen, Stenger,

& Carter, 2000). Also in line with previous data (Boorman, Behrens, Woolrich, & Rushworth, 2009;

Holroyd & McClure, 2015; Wilson et al., 2014), the model aMFC keeps track of the relevant task rule.

Additionally, consistent with fMRI work (Aben, Calderon, Van den Bussche, & Verguts, 2020), current

study found increased coupling between midfrontal cortex and task-related areas when more control

was needed (negative feedback). While this fMRI work showed anatomically detailed networks of

connectivity, current study described how this connectivity may work at algorithmic level.

To summarize, we have demonstrated how the brain might employ synchronization to bind

task-relevant areas for efficient rule switching. To achieve this, we used EEG, computational modelling,

individual differences, and behavioral analysis. We believe that this approach might reveal how more

complicated tasks can be implemented via synchronization as well.

References

Aben, B., Calderon, C. B., Van den Bussche, E., & Verguts, T. (2020). Cognitive effort modulates

connectivity between dorsal anterior cingulate cortex and task-relevant cortical areas. *The*

Journal of Neuroscience, *40*(19), JN-RM-2948-19. https://doi.org/10.1523/jneurosci.2948-

19.2020

Alexander, W. H., & Brown, J. W. (2015). Hierarchical error representation: A computational model

of anterior cingulate and dorsolateral prefrontal cortex. *Neural Computation*, *27*(11), 2354–

2410. https://doi.org/10.1162/NECO

Bai, Y., Katahira, K., & Ohira, H. (2014). Dual learning processes underlying human decision-making

in reversal learning tasks: Functional significance and evidence from the model fit to human

behavior. *Frontiers in Psychology*, *5*(AUG), 1–8. https://doi.org/10.3389/fpsyg.2014.00871

Behrens, T. E. J., Woolrich, M. W., Walton, M. E., & Rushworth, M. F. S. (2007). Learning the value

of information in an uncertain world. *Nature Neuroscience*, *10*(9), 1214–1221.

https://doi.org/10.1038/nn1954

Boorman, E. D., Behrens, T. E. J., Woolrich, M. W., & Rushworth, M. F. S. (2009). How green is the

grass on the other side? Frontopolar cortex and the evidence in favor of alternative courses of

action. *Neuron*, *62*(5), 733–743. https://doi.org/10.1016/j.neuron.2009.05.014

Botvinick, M. M., Braver, T. S., Barch, D. M., Carter, C. S., & Cohen, J. D. (2001). Conflict

monitoring and cognitive control. *Psychological Review*, *108*(3), 624–652.

https://doi.org/10.1037/0033-295X.108.3.624

Bruña, R., Maestú, F., & Pereda, E. (2018). Phase locking value revisited: Teaching new tricks to an

old dog. *Journal of Neural Engineering*, *15*(5). https://doi.org/10.1088/1741-2552/aacfe4

Cavanagh, J. F., Cohen, M. X., & Allen, J. J. B. B. (2009). Prelude to and resolution of an error : EEG

phase synchrony reveals cognitive control dynamics during action monitoring. *Journal of*

Neuroscience, *29*(1), 98–105. https://doi.org/10.1523/JNEUROSCI.4137-08.2009

Cavanagh, J. F., & Frank, M. J. (2014). Frontal theta as a mechanism for cognitive control. *Trends in*

Cognitive Sciences, *18*(8), 414–421. https://doi.org/10.1016/j.tics.2014.04.012

Cavanagh, J. F., Frank, M. J., Klein, T. J., & Allen, J. J. B. B. (2010). Frontal theta links prediction

errors to behavioral adaptation in reinforcement learning. *NeuroImage*, *49*(4), 3198–3209.

https://doi.org/10.1016/j.neuroimage.2009.11.080

Clouter, A., Shapiro, K. L., & Hanslmayr, S. (2017). Theta phase synchronization is the glue that

binds human associative memory. *Current Biology*, *27*(20), 1–6.

https://doi.org/10.1016/j.cub.2017.09.001

Cohen, J. D., Dunbar, K., & McClelland, J. L. (1990). On the control of automatic processes: a

parallel distributed processing account of the Stroop effect. *Psychological Review*, *97*(3), 332–

361. https://doi.org/10.1037/0033-295X.97.3.332

Cohen, M. X. (2014). *Analyzing neural time series data: Theory and practice*. Cambridge,

Massachusetts: The MIT Press.

Collins, A. G. E., & Frank, M. J. (2013). Cognitive control over learning: Creating, clustering, and

generalizing task-set structure. *Psychological Review*, *120*(1), 190–229.

https://doi.org/10.1037/a0030852

Cools, R., Clark, L., Owen, A. M., & Robbins, T. W. (2002). Defining the neural mechanisms of

probabilistic reversal learning using event-related functional magnetic resonance imaging. *The*

Journal of Neuroscience : The Official Journal of the Society for Neuroscience, *22*(11), 4563–

4567. https://doi.org/20026435

Cunillera, T., Fuentemilla, L., Periañez, J., Marco-Pallarès, J., Krämer, U. M., Càmara, E., … Antoni,

R. F. (2012). Brain oscillatory activity associated with task switching and feedback processing.

Cognitive, Affective and Behavioral Neuroscience, *12*(1), 16–33.

https://doi.org/10.3758/s13415-011-0075-5

Delorme, A., & Makeig, S. (2004). EEGLAB: An open source toolbox for analysis of single-trial

EEG dynamics including independent component analysis. *Journal of Neuroscience Methods*,

134(1), 9–21. https://doi.org/10.1016/j.jneumeth.2003.10.009

Ergo, K., De Loof, E., Janssens, C., & Verguts, T. (2019). Oscillatory signatures of reward prediction

errors in declarative learning. *NeuroImage*, *186*(September 2018), 137–145.

https://doi.org/10.1016/j.neuroimage.2018.10.083

Ergo, K., De Loof, E., & Verguts, T. (2020). Reward prediction error and declarative memory. *Trends*

in Cognitive Sciences, *24*(5), 388–397. https://doi.org/10.1016/j.tics.2020.02.009

French, R. M. (1999). Catastrophic forgetting in connectionist networks. *Trends in Cognitive*

Sciences, *6613*(April), 128–135.

Fries, P. (2005). A mechanism for cognitive dynamics: neuronal communication through neuronal

coherence. *Trends in Cognitive Sciences*, *9*(10), 474–480.

https://doi.org/10.1016/j.tics.2005.08.011

Fries, P. (2015). Rhythms for cognition: Communication through coherence. *Neuron*, *88*(1), 220–235.

https://doi.org/10.1016/j.neuron.2015.09.034

Gershman, S. J., Blei, D. M., & Niv, Y. (2010). Context, learning, and extinction. *Psychological*

Review, *117*(1), 197–209. https://doi.org/10.1037/a0017808

Gershman, S. J., & Uchida, N. (2019). Believing in dopamine. *Nature Reviews Neuroscience*, *20*(11),

703–714. https://doi.org/10.1038/s41583-019-0220-7

Gray, C. M., & Singer, W. (1989). Stimulus-specific neuronal oscillations in orientation columns of

cat visual cortex. *Proceedings of the National Academy of Sciences of the United States of*

America, *86*(5), 1698–1702. https://doi.org/10.1073/pnas.86.5.1698

Holroyd, C. B. (2016). The waste disposal problem of effortful control. In T. S. Braver (Ed.),

Motivation and cognitive control (pp. 235–260). Hove, UK: Psychology Press.

Holroyd, C. B., & McClure, S. M. (2015). Hierarchical control over effortful behavior by rodent

medial frontal cortex: A computational model. *Psychological Review*, *122*(1), 54–83.

https://doi.org/10.1037/a0038339

Hsieh, L. T., Ekstrom, A. D., & Ranganath, C. (2011). Neural oscillations associated with item and

temporal order maintenance in working memory. *Journal of Neuroscience*, *31*(30), 10803–

10810. https://doi.org/10.1523/JNEUROSCI.0828-11.2011

Izquierdo, A., Brigman, J. L., Radke, A. K., Rudebeck, P. H., & Holmes, A. (2017). The neural basis

of reversal learning: An updated perspective. *Neuroscience*, *345*, 12–26.

https://doi.org/10.1016/j.neuroscience.2016.03.021

Janssen, D. J. C., Poljac, E., & Bekkering, H. (2016). Binary sensitivity of theta activity for gain and

loss when monitoring parametric prediction errors. *Social Cognitive and Affective Neuroscience*,

11(8), 1280–1289. https://doi.org/10.1093/scan/nsw033

Jasper, H. (1958). The ten twenty electrode system of the international federation.

Electroencephalogr. Clin. Neurophysiol., (10), 371–375.

Jensen, O., Bonnefond, M., & VanRullen, R. (2012). An oscillatory mechanism for prioritizing salient

unattended stimuli. *Trends in Cognitive Sciences*, *16*(4), 200–205.

https://doi.org/10.1016/j.tics.2012.03.002

Koechlin, E., Ody, C., & Kouneiher, F. (2003). The architecture of cognitive control in the human

prefrontal cortex. *Science (New York, NY)*, *302*(5648), 1181–1185.

https://doi.org/10.1126/science.1088545

Kondo, H., Osaka, N., & Osaka, M. (2004). Cooperation of the anterior cingulate cortex and

dorsolateral prefrontal cortex for attention shifting. *NeuroImage*, *23*(2), 670–679.

https://doi.org/10.1016/j.neuroimage.2004.06.014

Lachaux, J. P., Rodriguez, E., Martinerie, J., & Varela, F. J. (1999). Measuring phase synchrony in

brain signals. *Human Brain Mapping*, *8*(4), 194–208. https://doi.org/10.1002/(SICI)1097-

0193(1999)8:4<194::AID-HBM4>3.0.CO;2-C

Lisman, J. E., & Idiart, M. A. P. (1995). Storage of 7 ± 2 short-term memories in oscillatory

subcycles. *Science*, *267*(5203), 1512–1515. https://doi.org/10.1126/science.7878473

Mac Donald, A. W., Cohen, J. D., Stenger, A. V., & Carter, C. S. (2000). Dissociating the role of the

dorsolateral prefrontal and anterior cingulate cortex in cognitive control. *Science*, *288*(June),

1835–1838. https://doi.org/10.1126/science.288.5472.1835

Makoto, M. (2018). Makoto's preprocessing pipeline. Retrieved from

https://sccn.ucsd.edu/wiki/Makoto%27s_preprocessing_pipeline

Maris, E., & Oostenveld, R. (2007). Nonparametric statistical testing of EEG- and MEG-data. *Journal*

of Neuroscience Methods, *164*(1), 177–190. https://doi.org/10.1016/j.jneumeth.2007.03.024

Nolte, G., Bai, O., Wheaton, L., Mari, Z., Vorbach, S., & Hallett, M. (2004). Identifying true brain

interaction from EEG data using the imaginary part of coherency. *Clinical Neurophysiology*,

115(10), 2292–2307. https://doi.org/10.1016/j.clinph.2004.04.029

Peirce, J., Gray, J. R., Simpson, S., MacAskill, M., Höchenberger, R., Sogo, H., … Lindeløv, J. K.

(2019). PsychoPy2: Experiments in behavior made easy. *Behavior Research Methods*, *51*(1),

195–203. https://doi.org/10.3758/s13428-018-01193-y

Piray, P., Dezfouli, A., Heskes, T., Frank, M., & Daw, N. (2019). Hierarchical Bayesian inference for

concurrent model fitting and comparison for group studies. *PLoS Computational Biology*, *15*(6),

34. https://doi.org/https://doi.org/10.1371/journal.pcbi.1007043

R Core Team. (2017). R: A language and environment for statistical computing. Vienna, Austria.

Rescorla, R. A., & Wagner, A. R. (1972). A theory of Pavlovian conditioning: Variations in the

effectiveness of reinforcement and nonreinforcement. *Classical Conditioning II Current*

Research and Theory, *21*(6), 64–99. https://doi.org/10.1101/gr.110528.110

Saez, A., Rigotti, M., Ostojic, S., Fusi, S., & Salzman, C. D. (2015). Abstract context representations

in primate amygdala and prefrontal Cortex. *Neuron*, *87*(4), 869–881.

https://doi.org/10.1016/j.neuron.2015.07.024

Sauseng, P., Klimesch, W., Freunberger, R., Pecherstorfer, T., Hanslmayr, S., & Doppelmayr, M.

(2006). Relevance of EEG alpha and theta oscillations during task switching. *Experimental*

Brain Research, *170*(3), 295–301. https://doi.org/10.1007/s00221-005-0211-y

Silvetti, M., Seurinck, R., & Verguts, T. (2011). Value and prediction error in medial frontal cortex:

Integrating the single-unit and systems levels of analysis. *Frontiers in Human Neuroscience*,

5(August), 75. https://doi.org/10.3389/fnhum.2011.00075

Silvetti, M., Vassena, E., Abrahamse, E., & Verguts, T. (2018). Dorsal anterior cingulate-brainstem

ensemble as a reinforcement meta-learner. *PLoS Computational Biology*, *14*(8), 1–32.

https://doi.org/10.1371/journal.pcbi.1006370

Springer, M., & Paulsson, J. (2006). Harmonies from noise. *Nature*, *439*(January), 27–29.

https://doi.org/doi:10.1038/439027a

The MathWorks Inc. (2016). MATLAB R2016B. Natick, Massachussetts, United States.

Verbeke, P., & Verguts, T. (2019). Learning to synchronize: How biological agents can couple neural

task modules for dealing with the stability-plasticity dilemma. *PLoS Computational Biology*,

15(8). https://doi.org/10.1371/journal.pcbi.1006604

Verguts, T. (2017). Binding by random bursts: A computational model of cognitive control. *Journal*

of Cognitive Neuroscience, *29*(6), 1103–1118. https://doi.org/10.1162/jocn

Widrow, B., & Hoff, M. M. E. (1960). Adaptive switching circuits. *IRE WESCON Convention*

Record, *4*(1), 96–104.

Wilson, R. C., Takahashi, Y. K., Schoenbaum, G., & Niv, Y. (2014). Orbitofrontal cortex as a

cognitive map of task space. *Neuron*, *81*(2), 267–279.

https://doi.org/10.1016/j.neuron.2013.11.005

Womelsdorf, T., Johnston, K., Vinck, M., & Everling, S. (2010). Theta-activity in anterior cingulate

cortex predicts task rules and their adjustments following errors. *Proceedings of the National*

Academy of Sciences, *107*(11), 5248–5253. https://doi.org/10.1073/pnas.0906194107

Womelsdorf, T., Schoffelen, J., Oostenveld, R., Singer, W., Desimone, R., Engel, A. K., & Fries, P.

(2007). Modulation of neuronal interactions through neuronal synchronization. *Science*,

316(1609), 1609–1612. https://doi.org/10.1126/science.1139178

Zhou, T., Chen, L., & Aihara, K. (2005). Molecular communication through stochastic

synchronization induced by extracellular fluctuations. *Physical Review Letters*,

178103(October), 2–5. https://doi.org/10.1103/PhysRevLett.95.178103

Figure and table legends

Fig 1. Methods. *A: The Sync model*. The left diagram represents a schematic overview of the Sync model. In the lower right corner, a detailed illustration shows how bursts originating in the pMFC synchronize task-relevant areas in the Mapping unit (see Verbeke & Verguts, 2019 for detailed explanation). *B: The task*. The time course of one trial in the experimental paradigm is shown. Elements highlighted by a blue rectangle, such as the presented stimulus and feedback, are manipulated on a trial-by-trial basis. Elements highlighted by the red rectangle are manipulated blockwise. Here, the fixation cross after feedback was green in one experimental block (half of all

Fig 2. Model comparison. *A: Parameter distributions*. Distributions of fitted parameter values are shown for each model. *B: wAIC groups*. This figure illustrates how wAIC values can be roughly divided in three groups (colors). *C: Correlation plots*. Correlations are shown between wAIC of the bSync model and all parameters of the bSync model. In the lower middle plot, also the correlation between wAIC and task accuracy is shown. *D: Learning curve fit*. Black dots represent the mean accuracy data over all subjects. The error bars show the 95%

confidence intervals. The colored lines illustrate the mean Likelihood of the correct response for each wAIC group

in B. The shades represent the 95% confidence interval.

Fig 3. Power results. *A-B: Time-Frequency plots of contrast (Negative – Positive feedback)*. Significant clusters

are indicated by the black contour line. *A:* Contrast of power in the model pMFC. *B:* Contrast for Z-scored power

in the human data, averaged over all 64 electrodes. *C-E: topographical plots of clusters found in the human data*.

Crosses indicate channels where the contrast reached significance.

Fig 4. Result of linear regression between power and prediction error (PE) in all clusters. Lines illustrate the

trial-by-trial relation between the estimated prediction errors and the mean power extracted from the clusters in

Fig 3. The shades represent 95% confidence intervals. The Model cluster (A) aimed to predict empirical data from

the theta cluster (B). For exploratory purposes, also the relation between estimated prediction errors and power in

the delta (C) and alpha (D) cluster are shown.

Fig 5. Interaction between prediction error and reward in power. *A: Distribution of prediction error*

estimates. Note that these prediction error estimates are not used for learning stimulus-action pairs, but for module

learning in the Switch unit (Equation (4)). *B: Time-frequency results*. Colors represent the contrast value of the

interaction effect. Black contours indicate significant clusters. *C: Topography of the alpha interaction cluster. D:*

Topography of the theta-delta interaction cluster. Crosses indicate channels where the contrast reached

significance.

Fig 6. Power locked to rule switch. Black lines show the mean power. Error bars show the 99.84% confidence

interval (Bonferroni correction). The horizontal grey dashed line represents baseline power and the vertical grey

dotted line indicates the moment of the rule switch. The red line visualizes the result of linear regression between

the Sync model and human data. *A-C* show data locked to the moment of the actual rule switch. *D* shows data of

the alpha cluster locked to the moment when subjects indicated they noticed the task switch.

Fig 7. Power locked to rule switch for different wAIC. Data patterns are shown for different wAIC values

(colored lines). The horizontal grey dashed line shows the baseline power over all subjects and the vertical grey

dotted line indicates the moment of the rule switch (A) or indication of rule switch (B).

Fig 8. Phase-locking with respect to FCz. *A-B: Time-Frequency plots of contrast (Negative – Positive feedback).*

Significant clusters are indicated by the black or white contour line. The black line represents posterior clusters

in C and D (black crosses) while the white line represents the frontal clusters in C (white crosses). All plots show

phase-locking with respect to the FCz electrode. A: Contrast of iPLV averaged over all ipsi-lateral electrodes. B:

Contrast of iPLV averaged over all contra-lateral electrodes. *C-D: Topographical plots of clusters*. Data was

averaged over all time points and frequencies that were included in the respective contours of A and B. Channels

where the contrast reached significance are marked by crosses or dots. The left channels (crosses) present ipsi-

lateral electrodes and the right channels (dots) present contra-lateral electrodes. Again, the white color was used

to distinguish the frontal clusters from the temporal clusters. *E:* Predicted phase-coupling in the model for the

250-500 ms post-feedback period.

Model	Mean LL	SD LL	Mean AIC	SD AIC	Mean wAIC	SD wAIC
RW	-208.08	.07	420.16	.13	.51	.20
ALR	-209.31	.05	424.63	.10	.05	.02
bSync	-206.35	1.11	420.70	2.22	.44	.22

Table 1. Goodness of fit measures. Results of log-likelihood (LL), AIC and wAIC computations over subjects

are shown for each of three models. For LL and wAIC, high values indicate a better fit, while for AIC a low value

indicates a good fit.