Title: **Learning to synchronize: midfrontal theta dynamics during reversal learning**

Abbreviated title: **Midfrontal theta during reversal learning**

Authors: Pieter Verbeke[1], Kate Ergo[1], Esther De Loof[1], Tom Verguts[1]

Affiliations: [1]Department of experimental psychology; Ghent University; B9000

Corresponding author email: pjverbek.verbeke@ugent.be

Number of pages: 35

Number of figures: 7

Number of tables: 1

<u>*Number of words:*</u>

Abstract: 197

*Introduction:*648

*Discussion:*1480

Conflict of interests: The authors declare no competing financial interests.

Acknowledgements: PV and KE were supported by respectively grant 1102519N and grant 1153418N from Research Foundation Flanders. EDL and TV were supported by grant BOF17/GOA/004 from the Ghent University Research Council.

Abstract

In recent years, several hierarchical extensions of well-known learning algorithms have been proposed. For example, when stimulus-action mappings vary across time or context, the brain may learn two or more stimulus-action mappings in separate modules, and additionally (at a hierarchically higher level) learn to appropriately switch between those modules. However, how the brain mechanistically coordinates neural communication to implement such hierarchical learning, remains unknown. Therefore, the current study tests a recent computational model that proposed how midfrontal theta oscillations implement hierarchical learning via the principle of binding by synchrony (Sync model). 64-channel EEG signal was recorded while 27 subjects performed a probabilistic reversal learning task. In line with the Sync model, post-feedback theta power showed a linear relationship with negative prediction errors, but not with positive prediction errors. This relationship was especially pronounced for subjects with better behavioral fit (measured via AIC) of the Sync model. Also consistent with Sync model simulations, theta phase-coupling between midfrontal electrodes and temporo-parietal electrodes was stronger after negative feedback. Our data suggest that the brain uses theta power and synchronization for flexibly switching between task rule modules, as is useful for example when multiple stimulus-action mappings must be retained and used.

Significance Statement

Everyday life requires flexibility in switching between several tasks. A key question in understanding this ability is how the brain mechanistically coordinates such switches. The current study tests a recent computational framework (Sync model) that proposed how midfrontal theta oscillations coordinate activity in hierarchically lower task-related areas. In line with predictions of this Sync model, midfrontal theta power was stronger when rule switches were most likely (strong negative prediction error), especially in subjects who obtained a better model fit. Additionally, also theta phase connectivity between midfrontal and task-related areas was increased after negative feedback. Thus, the data provided support for the hypothesis that the brain uses theta power and synchronization for flexibly switching between tasks.

Switching between tasks is key to function in a complex and rapidly changing environment.

For instance, when at the pub with friends, behavior is likely guided by different social rules than at

work. However, when the boss suddenly walks into the pub, this might require to flexibly switch

between these two sets of social rules. Importantly, an empirically valid model that explains how the

human brain mechanistically deals with such switches, remains lacking.

In experimental settings, this cognitive flexibility is typically tested in a reversal learning setup

(Izquierdo, Brigman, Radke, Rudebeck, & Holmes, 2017). Here, agents must learn task rules consisting

of collections of stimulus-action mappings. During the task, these rules are regularly reversed. One

popular framework to explain performance during reversal learning tasks is the Rescorla-Wagner model

(RW; Rescorla & Wagner, 1972; Widrow & Hoff, 1960). Here, on every trial, obtained reward is used

to update the value of active stimulus-action mappings. By learning fast, the agent can flexibly deal

with changes in task rules. However, when feedback is probabilistic (e.g., Cools, Clark, Owen, &

Robbins, 2002), this approach experiences difficulties. Specifically, a high learning rate will lead agents

to "chase the noise" introduced by probabilistic feedback. In contrast, a low learning rate increases

robustness against noise, but decreases flexibility on rule switches. Thus, some have proposed that

learning rate should be adaptive (e.g., Bai, Katahira, & Ohira, 2014; Behrens, Woolrich, Walton, &

Rushworth, 2007; Silvetti, Vassena, Abrahamse, & Verguts, 2018). In this adaptive learning rate (ALR)

proposal, agents track rule switches by comparing an estimate of reward probability to the received

reward. Consistently high prediction errors indicate that the underlying rule has changed, and learning

rate should be increased. More fundamentally however, irrespective of learning rate flexibility, both the

RW and ALR framework assume that, on every rule reversal, old information is overwritten. Especially

for more complex problems, this is inefficient; as is demonstrated by the problem of catastrophic

forgetting in artificial neural networks (French, 1999)).

To overcome catastrophic forgetting, separate mapping collections for every task rule may be

stored (Saez, Rigotti, Ostojic, Fusi, & Salzman, 2015; Wilson, Takahashi, Schoenbaum, & Niv, 2014).

However, this poses the agent with a new problem of keeping track which task rule is currently relevant.

Recent fMRI research focusing on this hierarchical approach toward reversal learning has pointed to

midfrontal cortex as responsible neural structure for keeping track of the current task rule (Wilson et

al., 2014). However, how midfrontal cortex mechanistically coordinates neural communication in

switching between task rules, remains an open question.

This question was recently addressed by a novel computational framework of hierarchical

learning (Verbeke & Verguts, 2019). As proposed in (Wilson et al., 2014), this model retains separate

mappings for every task rule. It keeps track of rule reversals by calculating prediction error. In order to

guide neural communication between areas holding the appropriate mappings, the model relies on

binding by synchrony (BBS; Fries, 2005, 2015; Gray & Singer, 1989; Womelsdorf et al., 2007) in theta

frequency (4-8 Hz). Specifically, midfrontal theta oscillations synchronize neuronal activity along task-

relevant pathways. Thus, task-relevant neurons can communicate and learn, while stability is achieved

in currently irrelevant pathways.

The current study empirically tests this model, further on referred to as Sync model (Fig 1B).

For this purpose, the Sync model is fitted on data of subjects performing a probabilistic reversal learning

paradigm, and empirically compared to alternative models (Bai et al., 2014; Rescorla & Wagner, 1972).

Then, Sync model simulations provided several predictions for EEG measured while subjects

performed this task, specifically in theta frequency (model-driven EEG predictions). First, a linear

relationship between midfrontal theta power and negative prediction errors was predicted, especially in

subjects with good behavioral Sync model fit. Second, a peak of midfrontal theta power was predicted

for data locked to rule switches. Third, phase coupling between midfrontal and posterior electrodes was

predicted to be stronger after negative feedback.

48   **Materials and Methods**

Materials

The experiment was run on a Dell Optiplex 9010 mini-tower running PsychoPy software

(Peirce et al., 2019). Electrophysiological data were recorded using a BioSemi ActiveTwo system

(BioSemi, Amsterdam, Netherlands) with 64 Ag/AgCl electrodes arranged in the standard international

10–20 electrode mapping (Jasper, 1958), with a posterior CMS-DRL electrode pair. Two reference

electrodes were positioned at the left and right mastoids. Eye movements were registered with a pair of

electrodes above and below the left eye and two additional electrodes at the outer canthi of both eyes.

EEG signals were recorded at a sampling rate of 1024 Hz.

Models were fitted using the differential evolution method of the SciPy (version 1.4.1)

package in Python (version 3.7.6). Other behavioral analyses were done using R software (R Core

Team, 2017). The electrophysiological data were preprocessed in MATLAB R2016b (The MathWorks

Inc., 2016) using an EEGLAB preprocessing pipeline (Delorme & Makeig, 2004). Also for simulations

of the Sync model MATLAB R2106b was used.

Code and Data Accessibility

All code used to provide the results described in the current paper is provided at

https://github.com/CogComNeuroSci/PieterV_public/tree/master/Reversal_learning. At publication,

also the data will be made freely accessible at https://osf.io/wt36f/.

Fig 1. Methods. *A: The task.* The time course of one trial in the experimental paradigm is shown. Elements

highlighted by a blue rectangle, such as the presented stimulus and feedback, are manipulated on a trial-by-trial

basis. Elements highlighted by the red rectangle are manipulated blockwise. Here, the fixation cross after feedback

was green in one experimental block (half of all trials). In this reporting block, subjects had to press space during

this period if they thought the rule had switched. *B: The Sync model.* The left diagram represents a schematic

overview of the Sync model. In the lower right corner, a detailed illustration shows how bursts originating in the

pMFC synchronize task-relevant areas in the Mapping unit (see (Verbeke & Verguts, 2019) for detailed

explanation).

Experimental Task

Both the model (27 simulations) and human subjects ($N = 27$) performed a probabilistic

reversal learning task (see Fig 1A). Agents had to learn task rules consisting of two stimulus-action

mappings which were regularly reversed during the task. Every trial started with a centrally presented

white fixation cross for 2 seconds. Then the stimulus was presented for a period of 100 milliseconds.

This stimulus was a centrally presented circular grating with a raised-cosine mask and a size of 7 visual

degrees. The grating was either vertically or horizontally oriented. After stimulus presentation, the

screen turned blank until response. Responses were given by pressing the 'f'- (left) or 'j'-key (right) on

an azerty keyboard. In task rule 1, the horizontal stimulus mapped to a left response and the vertical

stimulus to the right response; this was reversed for task rule 2. During the task (480 trials), 15 rule

switches were introduced. These rule switches occurred at random (uniform distribution from 15 to 45

trials after the previous task switch). After response, feedback was presented in the center of the screen.

This feedback consisted of '+10 points' for rewarded trials, '+0 points' for unrewarded trials or

'Respond faster!' when response times (RT) were more than 1 second. After feedback, the fixation

cross appeared again for another 2 seconds. Crucially, the experiment was divided into two

experimental blocks (240 trials each). In one block, the reporting block, the post-feedback fixation cross

was presented in green. During this period, subjects were instructed to press the space bar if they thought

the task rule had switched. The purpose of this approach was to obtain an indication of when the subject

reached his or her own 'Switch threshold', as happens in the Sync model. This was only done during

one block, so critical changes due to this difference in task structure could be checked. The order of the

two blocks was counterbalanced across subjects. In between blocks, as well as three times within a

block, subjects were allowed a small break. This break could only occur if there was no rule switch

within 10 trials from the break.

Human Testing Procedure

34 subjects participated in this study, 7 subjects were removed because of either technical

problems with the EEG recording (4) or an inability to give a correct response on more than 2/3 of the

trials (3), resulting in $N = 27$. Subjects were told they would receive €25 for their participation, with a

possibility to earn up to €3 extra reward depending on their performance.

Before starting the task, the subject had to go through two short practice sessions with gratings

that were tilted 45° to the left or to the right relative to a vertical line. In the first practice session, the

subject performed 30 trials with only one task rule. Here, the goal was to let the subject get acquainted

with the general paradigm and learn a task rule through probabilistic feedback. Subjects were only

allowed to continue to the second practice session if they performed above chance level (50%) and

could report the correct task rule to the experimenter. If not, they performed this practice session again.

In the second practice session, subjects performed 60 trials of the task with 3 rule switches and with the

post-feedback green fixation cross (as in the reporting block). In this session, subjects pressed the space

bar to indicate a task switch and received feedback for each press. The press was considered correct if

subjects responded within 10 trials from the actual rule switch. They were allowed to continue to the

next task if they were able to perform above chance level and had at least 1 correct indication of a rule

switch. After successfully performing both practice sessions, subjects performed 480 trials of the actual

task.

Behavioral Analyses

To check for differences between the reporting block (green fixation cross) and the non-

reporting block (see Experimental Task and Fig 1A), paired t-tests were performed for both accuracy

and RT, depending on experimental block. In order to deal with the skewed distribution of RT, the

natural log of RT was used for all analyses. Additionally, trials with too late responses were excluded

for both behavioral and EEG analyses.

Model Analyses

Model formulation

More extensive analyses of behavioral data were done with a model-based approach. Current

work aims to test the Sync model (Verbeke & Verguts, 2019), but two baseline models were fitted as

well. In the following section, we first provide a conceptual overview, followed by a more detailed

description of all three models. Then, we describe how model fit was evaluated.

An overview of model architecture is provided in Fig 1B. The RW and ALR model are

restricted to only the Mapping unit (with one rule module). The RW model (Rescorla & Wagner, 1972)

had a constant learning rate while the ALR model (Bai et al., 2014), was implemented with an adaptable

learning rate. The Sync model consists of two units, the Mapping and Switch unit. The Mapping unit

contains a classic network with 2 layers (visual input and motor output). Here, weights are adapted with

the RW algorithm (Widrow & Hoff, 1960). In the Sync model, 4 nodes (2 for each response option) at

the motor output layer, are divided in 2 rule modules, one for each task rule. Hence, as in (Wilson et

al., 2014), the Mapping unit holds separate stimulus-action mappings for each task rule. In addition, a

Switch unit forms a hierarchically higher network modeled after primate prefrontal cortex. This Switch

unit keeps track of switches in task rule. Specifically, the Switch unit consists of the lateral frontal

cortex (LFC), posterior medial frontal cortex (pMFC) and anterior midfrontal cortex (aMFC). Here, the

LFC holds pointers (Botvinick et al., 2001) that indicate which rule should be synchronized in the

Mapping unit. Since BBS implements gating, allowing efficient communication between synchronized

nodes and inefficient communication between non-synchronized nodes (Fries, 2005, 2015), the agents'

behavior will be guided by the synchronized rule. This synchronization process is then executed by the

binding by random bursts principle (Springer & Paulsson, 2006; Verguts, 2017; Zhou, Chen, & Aihara,

2005). In the Sync model, a theta-frequency-paced signal produced in the pMFC is responsible for

sending these bursts (see (Verbeke & Verguts, 2019; Verguts, 2017) for details). The aMFC contains a

neural network (for simplicity not shown in Fig 1B) that is adapted from previous work (Silvetti,

Seurinck, & Verguts, 2011). Here, again RW learning is employed but on a hierarchically higher level.

More specifically, the aMFC learns an expected reward (V) for the currently used rule module (see

equation (4)). Which rule module is currently used, is extracted from activation in the LFC. The

expected reward is then compared to an external reward signal (Rew; Reward in Fig 1B) in order to

compute prediction errors. The negative prediction error signal is propagated to both the Accumulator

neuron (within the aMFC neural network) and to pMFC. A single negative prediction error increases

(via bursting) the power of the theta signal in pMFC (bursting connection in Fig 1B; see (Verbeke &

Verguts, 2019) for details). Instead, the Accumulator neuron evaluates the prediction error signal on a

slower time scale, and thus requires multiple prediction errors before activation in the Accumulator

neuron reaches its Switch threshold (see equation (5)). When this happens, it signals the need for a

switch to the LFC. Correspondingly, the LFC will change the signal to the Mapping unit, and

synchronize another rule module. In sum, bursts received by the Mapping unit are the result of a

cooperation between LFC and pMFC. Here, the pMFC determines the intensity of theta bursts while

the LFC determines which task rule in the Mapping unit is susceptible to the bursts. For further details

see (Verbeke & Verguts, 2019).

All nodes in the visual input and motor output layer of the Mapping unit as well as the pMFC

are oscillatory nodes. In line with previous work (Verguts, 2017), oscillatory nodes contain neuronal

triplets. In the pMFC, which executes top-down control by sending bursts, activity oscillates at a theta

(6 Hz) frequency, in line with suggestions of previous empirical work (Cavanagh & Frank, 2014;

Womelsdorf, Johnston, Vinck, & Everling, 2010). Different from our previous modelling work, a theta

frequency was used in the Mapping unit (see Discussion) as well. Since bursts lead to a significant

increase of power, a radius parameter (r_{min}) is implemented in order to attract power back to baseline

after a burst. Since continuously high pMFC power is computationally suboptimal and empirically

implausible (Holroyd, 2016), power in the pMFC was attracted towards a smaller radius, $r_{min} = .50$. How

fast oscillations decay to baseline is determined by a damping parameter (D) which was set to $D = .30$

in the Mapping unit. Since the pMFC not only receives burst but also sends them, a slower decay $D =$

.01 was implemented here to allow a sufficient activity window (~ 500 ms/3 theta cycles) for bursts to

be sent. In order to reduce model complexity, no oscillations were used in the LFC and aMFC. For a

full description of model dynamics see (Verbeke & Verguts, 2019).

We turn now to the more detailed descriptions. On every trial, the RW and ALR models

respond with a probability based on the following softmax rule:

$$p(a) = \frac{e^{Q(s,a)/\tau}}{\sum e^{Q(s,a_i)/\tau}} \tag{1}$$

181 in which $Q(s,a)$ is the value of a given stimulus-action pair (s, a). τ is the temperature parameter which

182 determines how strongly the subject explores different actions. On every trial, $Q(s,a)$ is updated based

183 on the rule:

$$Q(s,a)_{j+1} = Q(s,a)_j + \alpha * (Rew - Q(s,a)_j) \tag{2}$$

186 in which α is the Mapping learning rate and *Rew* is the reward received by the agent.

187 In the ALR model (Bai et al., 2014), the learning rate changes in an adaptive manner. Here,

188 the Mapping learning rate is updated on every trial by

$$\alpha_{j+1} = \eta * |Rew - Q(s,a)_j| + (1 - \eta) * \alpha_j \tag{3}$$

in which η determines how strongly the learning rate is influenced by the current difference between

Rew and Q (lower-level prediction error).

The third model is the Sync model. In order to implement BBS, on every trial multiple time

steps were simulated in which oscillations occurred. Here, motor nodes accumulate activation over

time. The motor node with the maximal accumulated activation over time, was considered as the model

response. Values of stimulus action pairs (Q) in each rule module (R) are updated similar to equation

(2). As described above, this model has an additional Switch unit which adds a hierarchical learning

algorithm on top of the RW (fixed learning rate) model in the Mapping unit. This Switch unit evaluates

whether there was a rule switch. More specifically, it learns a value for every rule module by

$$V(R)_{j+1} = V(R)_j + \alpha_{high} * (Rew - V(R)_j) \tag{4}$$

202   in which α_{high} is the higher order Switch learning rate. The absolute difference between the expected

203   value $V(R)$ in equation (4) and the obtained Rew (i.e., the unsigned prediction error) is accumulated in

204   the Accumulator neuron (A) via

$$A_{j+1} = \begin{cases} \gamma * A_j + (1 - \gamma) * |Rew - V(R)_j| & if\ (Rew - V(R)_j) < 0 \\ \gamma * A_j & otherwise \end{cases} \tag{5}$$

Here, γ is the Cumulation parameter which determines how strongly the Accumulation neuron is

affected by a single prediction error. While a low Cumulation parameter causes the agent to strongly

weigh single prediction error and therefore regularly switch between rule modules, a high Cumulation

parameter implements a more conservative approach. Since switches are only required when negative

feedback occurs, the Accumulator neuron is selective for negative prediction errors. When several

negative prediction errors occur in succession, this Accumulator neuron will reach a Switch threshold

which is set to .5, and the model will switch to another rule module (R) in the Mapping unit.

For behavioral data fitting only, the full Sync model was simplified by introducing a hard gating

process between task rules instead of BBS and a response selection mechanism similar to (1). This

allowed to skip the loop of 1500 timesteps every trial, which was needed to simulate oscillations. We

refer to this model as the behavioral Sync (bSync) model.

Model evaluation

For each subject, the goodness of fit of these three models was compared by using three

measures. The log-likelihood (LL)

$$LL = \sum_{j=1}^{J} a_j * ln\ (p(a_j = 1)) + (1 - a_j) * ln\ (p(a_j = 0)) \tag{6}$$

223　　in which $p(a)$ is the probability of the given action (see equation (1)) and J represents the number of

224　　trials. The AIC uses this LL but includes a penalty for the number of parameters (k) that were used in

225　　the model:

$$AIC = 2 * k - 2 * LL \tag{7}$$

228　　From this AIC, AIC weights (*wAIC*) can be derived which allows to make a relative comparison

229　　between the model fit of the three different models. These wAIC values are computed as

$$wAIC = \frac{e^{-\frac{1}{2}\Delta AIC_m}}{\sum_{m=1}^{M} e^{-\frac{1}{2}\Delta AIC_m}} \tag{8}$$

232　　in which M is the number of models that are compared (3) and

$$\Delta AIC_m = AIC_m - \min(AIC) \tag{9}$$

Here, min(AIC*)* is the lowest AIC value out of the three models for that subject. Thus, Equation (8)

results in a wAIC value for each model. The sum of all three wAIC values is 1, and if all three models

fit the data equally well, wAIC equals .33 for all three models.

Simulations

In order to provide hypotheses for EEG data, 27 simulations of the full Sync model were

performed. For all simulations, the same parameter values were used. These parameter values were

sampled from the estimated parameter distributions of the bSync model so that overall accuracy of

model simulations ($M = 78.00\%$, $SD = 1.30$) closely resembled accuracy of subjects ($M = 76.80\%$, SD

$= 4.91$). This resulted in a Mapping learning rate (α) of .8, a Switch learning rate (α_{high}) of .1 and a

Cumulation parameter (γ) of .3. The full Sync model did not use a Temperature (τ) parameter but the

synchronization procedure introduces noise which also introduces some randomness in behavior. The

Switch threshold was always fixed to .5. Since the current model does not provide RTs, a period of 500

ms was used as trial period in which the visual layer received stimulation. Thereafter, 1500 ms of inter-

trial interval was simulated in order to provide a post-feedback period that could be analyzed in the

same way as the empirical data. All other aspects of the task, such as the frequency and timing of rule

switches, were the same for the model as for the human subjects.

Power Analyses

Time-frequency decomposition was performed on the excitatory neuron within the neuronal

triplet of the model's pMFC node in the model. Complex Morlet wavelets were used for frequencies

between 2 and 48 Hz defined in 25 logarithmically spaced steps. For each frequency, between 3 and 8

cycles were used, also defined in 25 logarithmically spaced steps. Power was extracted as the squared

absolute value of the time-frequency decomposed signal. In order to locate activity that was specific to

feedback processing, the difference between power in trials with negative feedback and trials with

positive feedback was computed. For simplicity, we selected the 2.5% most positive values as cluster

of interest. This cluster contained one group of data points in theta frequency and approximately 250-

500 ms after feedback. On every trial, the mean power in this cluster was computed and entered in the

consecutive analyses. Since a negative prediction error in the model increases activity of the pMFC, we

performed a linear regression of cluster power with prediction error as the independent variable. To test

our first hypothesis, that this relationship was specific to negative prediction error, a second regression

model was used that also included the interaction between prediction error and reward. The second

hypothesis states that because negative prediction errors are strongest at the moment of a rule switch, a

peak of post-feedback theta power should be found when we lock data to rule switches. To investigate

this, we extracted power from the model cluster in trials within a 31-trial window around the rule switch

(-15 to +15). The time course (one data point for each of the 31 trials) that resulted after averaging over

all (15) rule switches and all (27) simulations, was then used as a regressor in a linear regression with

data from the empirical clusters.

Phase Analyses

Our third hypothesis stated that phase coupling between pMFC and model nodes in the

Mapping unit was stronger after negative feedback. Specifically, theta power in the model pMFC

increases after negative prediction error. When there is sufficient power in the pMFC, it will increase

synchronization in the Mapping unit (posterior/lateral task-related regions, e.g., pre-motor or visual

areas). For this purpose, the pMFC uses binding by random bursts (Verguts, 2017). Here, the pMFC

will at specific phases, send bursts to the Mapping unit. Thereby it will shift the phase of neurons in the

Mapping unit (see Verbeke & Verguts, 2019 for details). This leads to phase shifts in these lower pre-

motor or visual task-related areas, and a short period of phase-alignment between these task-related

areas in the Mapping unit and pMFC. Phase was extracted in all model nodes by taking the angle of the

Hilbert transform of the raw signal. For simplicity the model was implemented without inter-areal

delays. Furthermore, in contrast to analyses on the empirical EEG data (see equation (10)), control for

volume conduction was not needed, so the regular phase locking value (PLV; Lachaux, Rodriguez,

Martinerie, & Varela, 1999) was computed between the model pMFC and the nodes in the motor layer

of the Mapping unit. This PLV was then averaged over all 4 motor nodes and the time period included

in the power cluster (~250-500 ms post feedback).

EEG Analyses

Preprocessing

The data were re-referenced offline to the average of the mastoid electrodes. Breaks or other

offline periods were manually removed. Particularly noisy electrodes were interpolated between

neighboring electrodes on all timesteps. For three subjects one electrode was interpolated, for another

three subjects we had to interpolate two electrodes; because of a bridge, one subject needed interpolation

for five posterior electrodes. Additionally, activity was band-pass filtered between 1 and 48 Hz in order

to remove slow drifts and line noise of 50 Hz. Eyeblinks and other motor-related noise components

were removed through EEGLAB independent component analysis (ICA). After ICA-removal, the data

was epoched, once locked to feedback onset and once to stimulus onset. The epochs based on stimulus

onset were used to extract baseline activation, which was -1500 to -500 ms relative to stimulus onset.

This baseline activity was subtracted from all epochs. After epoching, on average 7.5% of epochs were

removed by applying an amplitude threshold of -500 to 500 mV and an improbability test with 6

standard deviations for single electrodes and 2 standard deviations for all electrodes, as described in

Makoto's preprocessing pipeline (Makoto, 2018). Before time-frequency analyses, data was also

downsampled to 512 Hz.

Time-frequency Decomposition

304　Time-frequency decomposition was based on code from (Cohen, 2014). Similar to model

305　analyses, complex Morlet wavelets were used for frequencies between 2 and 48 Hz defined in 25

306　logarithmically spaced steps. For each frequency, between 3 and 8 cycles were used, also defined in 25

307　logarithmically spaced steps.

Power Computation

309　A baseline correction was applied to the power estimates for each subject, electrode and

310　frequency separately, based on the average baseline activity (-1500 ms to -500 ms from stimulus onset)

311　across all 480 trials. Finally, the baseline-corrected data underwent a decibel conversion. Before final

312　analyses, also trials with late responses were removed from the data.

Power Cluster Analyses

Similar to model analyses, we were interested in activity selective for feedback. Hence, a

contrast between Z-scored power in trials with negative feedback and trials with positive feedback was

computed. On these values, a non-parametric clustering procedure was applied (Maris & Oostenveld,

2007). The distribution of statistics was computed. On each side of the distribution (two-sided test), the

1% most extreme values were entered into the clustering analysis. From these, we clustered adjacent

neighbors in the channel, frequency and time domains. To calculate our cluster-level statistic, we

multiplied the number of items (i.e., (channel, frequency, time) points) in the cluster with the largest

statistic of that cluster. A significance threshold of 5% was imposed on the subsequent non-parametric

permutation test with 1000 iterations. Clusters that survived this permutation test were taken into the

consecutive analyses. As an exploratory analysis, we also extracted mean cluster statistics for each

subject, and ran a Spearman rank correlation of these statistics with wAIC of the bSync model obtained

in the behavioral model fitting procedure.

Midfrontal Theta Power and Prediction Error

The Sync model uniquely yields specific EEG predictions, to which we now turn. To test the

first model-driven EEG hypothesis of a relation between theta power and prediction errors, we first

extracted a measure of prediction error for every subject on every trial by simulating the bSync model.

This measure of prediction error was then used in a linear mixed effects models as a predictor for the

mean Z-scored power of every cluster that was selective for feedback. Here, a random intercept for

every subject was included and a fixed slope. Because the Sync model predicted different relationships

for positive prediction errors and negative prediction errors, also the interaction between prediction

errors and reward was tested. Additionally, in order to explore whether the wAIC influenced the

interaction between prediction errors and reward, also a three-way interaction between prediction error,

reward and wAIC was tested. More specifically, three regression models were fitted: One in which only

prediction error was included as regressor, one in which both prediction error and the interaction

between prediction error and reward were included, and finally a third model in which the main effect,

the two-way interaction, and an extra three-way interaction between prediction error, reward and wAIC

was included. These regression models were then compared via ANOVA.

Rule Switch Locking

A second model-driven EEG hypothesis considers theta power locked to the moment of a rule

switch. For this analysis, EEG data of 31 trials around the rule switch (-15 to +15 trials, including the

rule switch trial itself) were extracted. On these trials, the mean power for every cluster selective for

feedback was computed. This data was then again averaged over all switches, giving us a trial-to-trial

time course of mean cluster-power from -15 trials before rule switch to 15 trials after rule switch for

every subject. On each time point, a 99.84% confidence interval (CI) was computed based on a

Bonferroni correction for multiple comparisons (100-(5/31)). This confidence interval was compared

to a baseline power. Baseline power was computed based on the mean power in this cluster, averaged

over all trials that were more than 15 trials removed from the rule switch.

As the rule switch trial, we considered both the actual rule switch and the subjective indication

of a rule switch. Hence, power close to a rule switch was compared with the mean power of trials that

were far from the rule switch. When the confidence interval did not include the baseline value, power

on this trial was considered as significantly deviating from baseline. Additionally, we aimed to

investigate the similarity between the data pattern predicted by the model and the empirical data. For

this purpose, data from the model simulations (see above for details) was used as a linear regressor for

the empirical data. Also for this hypothesis, an extra analysis was performed to investigate whether

wAIC had an influence on the observed effect. Here, we extracted subject data on trials of which cluster

power significantly deviated from baseline and used this data as a dependent variable in a linear

regression with wAIC.

Midfrontal-posterior Phase-coupling Analyses

For the third model-driven EEG hypothesis, we considered all midline electrodes (10) as seed

and other electrodes (54) as receiver in the phase connectivity analyses. Because we were interested in

phase-locking related to rule modules conveying the correct response, all data was lateralized with

respect to the correct response. All data ipsi-lateral to the correct response was brought to the left

electrodes; all contra-lateral data was brought to the right electrodes. The iPLV (Bruña, Maestú, &

Pereda, 2018) was computed between all midline electrodes and all lateral electrodes for every time

point in the feedback-locked data. This iPLV measure was computed by the following equation

$$iPLV = |\ \frac{1}{n} \sum_{t=1}^{n} Im(e^{-i(\Delta \varphi_t)})\ | \tag{10}$$

which computes the average phase angle (φ) difference over trials (t). By only looking at the imaginary

(Im) part of this phase angle difference, phase differences of zero are eliminated. Hence volume

conduction effects are excluded, because such volume conduction effects are represented in zero-phase

differences (Bruña et al., 2018; Nolte et al., 2004). Again, a non-parametric cluster algorithm was

performed on the contrast between iPLV for trials with negative versus positive feedback. For this

analysis, only data of one midline electrode was used. More specifically, we checked on which of the

10 midline electrodes the mean contrast in the theta frequency (4-8 Hz) reached a maximum. This was

in the FCz electrode, hence only iPLV between FCz and all lateral electrodes were entered in the

clustering algorithm. As for power, an exploratory analysis was performed in which we extracted mean

cluster statistics for each subject, and ran a Spearman rank correlation of these statistics with wAIC of

the bSync model obtained in the model fitting procedure.

<div align="center">Results</div>

Behavioral Data

384   A paired t-test confirmed that there were no significant differences between the experiment

385 block in which subjects had to indicate when a task switch happened or when they did not have to

386 indicate this (see Materials and Methods for details), neither in accuracy ($t(26) = .029, p = .977$), nor in

387 RT ($t(26) = -1.290, p = .208$).

Model Analyses

The distribution of all fitted parameter values for each model is given in Fig 2A. Simulations

of the models with these parameter values allowed us to estimate a learning curve that illustrates how

accuracy increases after rule switches (Fig 2B). Goodness of fit measures are summarized in Table 1.

Here, log-likelihood was highest (best) for the bSync model, lowest for the ALR model, with the RW

model in between. When a penalty for model complexity was applied (AIC, wAIC), the RW and bSync

models performed approximately equal. Importantly, wAIC results indicated significant differences

across individuals. As illustrated in Fig 2C, subjects could be roughly divided into three groups based

on the wAIC of the bSync model. In one group (8 subjects), the wAIC were significantly smaller (better)

for the bSync model ($M = .12, SD = .026$) than for the RW model ($M = .78, SD = .027$). A second group

(7 subjects) showed wAIC values that were approximately equally strong for the bSync ($M = .44, SD = $

$.036$) as for the RW model ($M = .50, SD = .032$). In a third group (12 subjects), the bSync model showed

wAIC that were significantly higher for the bSync model ($M = .64, SD = .027$) than for the RW model

($M = .32, SD = .026$).

Model	Mean LL	SD LL	Mean AIC	SD AIC	Mean wAIC	SD wAIC
RW	-208.08	.07	420.16	.13	.51	.20
ALR	-209.31	.05	424.63	.10	.05	.02
bSync	-206.35	1.11	420.70	2.22	.44	.22

Table 1. Goodness of fit measures. Results of log-likelihood (LL), AIC and wAIC computations over subjects

are shown for each of three models. For LL and wAIC, high values indicate a better fit, while for AIC a low value

indicates a good fit.

Three parameters of the bSync model showed a significant correlation with wAIC (Fig 2D).

These parameters were the Switch learning rate ($rho = -.761, p < .001$), the Cumulation parameter (rho

$= -.708, p < .001$), and the Temperature parameter ($rho = -.497, p = .008$). There was no significant

correlation with the Mapping learning rate ($rho = -.145, p = .468$). Additionally, a correlation test

between accuracy and wAIC revealed that the bSync model fitted significantly better for subjects with

a lower accuracy ($rho = -.510, p = .007$).

Fig 2. Model comparison. *A: Parameter distributions*. Distributions of fitted parameter values are shown for

each model. *B: Learning curve fit*. Black dots represent the mean accuracy data over all subjects. The error bars

show the 95% confidence intervals. The red line illustrates the mean Likelihood of data that was simulated with

the fitted parameter values. The shade represents the 95% confidence interval. *C: wAIC groups*. This figure

illustrates how wAIC values can be roughly divided in three groups (colors). *D: Correlation plots*. Correlations

are shown between wAIC of the bSync model and all parameters of the bSync model. In the lower middle plot,

also the correlation between wAIC and task accuracy is shown.

EEG and Model Data

Power Cluster Analyses

Cluster analysis on post-feedback power revealed three significant clusters that were selective

for feedback processing (Fig 3). All three clusters appeared between 0 and 750 ms from feedback onset.

As was predicted by the Sync model (Fig 3A), one of these clusters was in the theta frequency range (~

4-8 Hz) and located on midfrontal electrodes (Fig 3B, D). This theta cluster showed more power when

feedback was negative than when it was positive. Additionally, we found two clusters located on the

posterior channels. One of these clusters was in the delta frequency (< 4 Hz; Fig 3B, E), the other cluster

was located in the alpha-frequency range (~ 8-15 Hz; Fig 3B, C). Both the delta and alpha cluster

showed less power for negative feedback than for positive feedback. No correlation between the power

contrast of a cluster and subjects' wAIC for the bSync reached significance.

Fig 3. Power results. *A-B: Time-Frequency plots of contrast (Negative – Positive feedback)*. Significant clusters

are indicated by the black contour line. *A:* Contrast of power in the model pMFC. *B:* Contrast for Z-scored power

in the human data, averaged over all 64 electrodes. *C-E: topographical plots of clusters found in the human data*.

Crosses indicate channels where the cluster statistic reached significance.

Midfrontal Theta Power and Prediction Error

We next consider the first of three model-driven EEG hypotheses. We first perform statistical

analysis on the Sync-model simulated data (Fig. 4A). Theta power in the Sync model data was best

predicted by the regression model that included an interaction between reward and prediction error ($F(1,$

$11980) = 22133, p < .001$). Hence, there was a significant main effect of prediction error ($F(1, 11980)$

$= 742962, p < .001, \beta = -4.99$) and a significant interaction of prediction error and reward ($F(1, 11980)$

$= 22133, p < .001, \beta = 4.48$). Thus, as predicted, the model cluster showed a negative linear relationship

with negative prediction error, and no linear relationship with positive prediction error (Fig 4A).

For power in the empirical theta cluster, the regression model including the interaction

between prediction error and reward fitted significantly better than the regression model with only

prediction error as regressor ($\chi^2(1, N = 27) = 110, p < .001$). Additionally, the regression model

including the three-way interaction between prediction error, reward and wAIC fitted significantly

better than the regression model with only the two-way interaction ($\chi^2(2, N = 27) = 20.74, p < .001$).

Here, all effects reached significance. Hence, there was a main effect of prediction error ($\chi^2(1, N = 27)$

$= 1299, p < .001, \beta = -.79$) and an interaction of prediction error with reward ($\chi^2(1, N = 27) = 110, p <$

$.001, \beta = .65$). Additionally, there was a significant interaction between prediction error, reward and

wAIC ($\chi^2(2, N = 27) = 20.900, p < .001$). As can be observed in Fig 4B these results indicated a

significant negative linear relationship between power and negative prediction error, which was

stronger for subjects with a high wAIC (i.e., better behavioral fit of the Sync model); and an absence of

linear relationship between power and positive prediction error which did not differ significantly for

wAIC (Fig 4B). Interestingly, the three-way interaction was significant in the unrewarded (negative

prediction error) trials ($\beta = -.89, p < .001$) but did not reach significance in the rewarded (positive

prediction error) trials ($\beta = .44, p = .077$).

For exploratory purposes, we investigated the same regression models in the delta and alpha

clusters. In the delta cluster, the difference in regression model fit between the regression models

without and with the prediction error-reward interaction term did not reach significance ($\chi^2(1, N = 27)$

$= 3.490, p = .062$). However, the regression model that also included the three-way interaction between

prediction error, reward and wAIC fitted significantly better than the regression model with no

interaction terms ($\chi^2(3, N = 27) = 9.27$, $p = .026$). Here, the main effect of prediction error was

significant ($\chi^2(1, N = 27) = 580$, $p < .001$, $\beta = .45$). The interaction between prediction error and reward

did not reach significance ($\chi^2(1, N = 27) = 3.490$, $p = .062$, $\beta = -.07$). Also the three-way interaction

term did not reach significance ($\chi^2(2, N = 27) = 5.830$, $p = .054$). However, if the interaction was

considered separately for rewarded trials ($\beta = .61$, $p = .018$) and unrewarded trials ($\beta = -.50$, $p = .033$),

both reached significance. As can be observed in Fig 4C, this meant that there was a positive linear

relationship between power and prediction error for both positive and negative prediction error (Fig

4D). For subjects with low wAIC, the slope in unrewarded trials seemed similar to the one in rewarded

trials, while for subjects with high wAIC, an inverse effect of the theta cluster was observed in which

there was a flat(ter) slope in unrewarded trials but a steeper slope in rewarded trials.

476   In the alpha cluster, the regression model with the two-way interaction term showed a

significantly better fit than the regression model without interaction ($\chi^2(1, N = 27) = 224$, $p < .001$).

When the three-way interaction was added, it did not lead to a significantly better regression model (χ^2

$(2, N = 27) = .35$, $p = .841$). Here, a significant main effect of prediction error ($\chi^2(1, N = 27) = 142$, p

$< .001$, $\beta = .85$) and a significant interaction between prediction error and reward ($\chi^2(1, N = 27) = 226$,

$p < .001$, $\beta = -1.38$) were observed. The three-way interaction between prediction error, reward and

wAIC was not significant ($\chi^2(2, N = 27) = .360$, $p = .833$). As is shown in Fig 4D, power in the alpha

cluster exhibited a positive linear relationship for negative prediction error but a negative linear

relationship with positive prediction error. These effects did not differ with respect to wAIC.

Fig 4. Result of linear regression between power and prediction error (PE) in all clusters. Lines indicate slopes and the shades represent 95% confidence intervals. The Model cluster (A) aimed to predict empirical data from the theta cluster (B).

Rule Switch Locking

For the second model-driven EEG hypothesis, power from the data clusters was extracted in trials within a 31-trial window from the rule switch (-15 to +15). In all clusters, one trial was observed that significantly deviated from baseline power. In the theta cluster (Fig 5A), only the exact trial of the rule switch (0) was significant above baseline (CI99.84 [-2.059, .256], *baseline* = -2.340). Linear regression of the data time course (across 31 trials) on the Sync model time course showed a significant effect ($F(1, 835) = 20.510$, $p < .001$, $R^2_{adj} = .023$, $\beta = .31$). In the delta cluster (Fig 5B), only the exact trial of the rule switch (0) was significantly below baseline (CI99.84 [-2.450, -1.265], *baseline* = -1.201). Linear regression of the data time course on the Sync model time course revealed a significant correlation ($F(1, 835) = 7.360$, $p = .007$, $R^2_{adj} = .008$, $\beta = -.18$). For the alpha cluster (Fig 5C), again one trial was significantly below baseline (CI99.84 [-6.275, -3.603], *baseline* = -3.584). Notably, this was the trial after the rule switch (+1). Moreover, when data was locked to the moment where subjects indicated the rule switch (Fig 5D), alpha power reaches a minimum at this exact moment (CI99.84 [-

503   7.675, -3.686], *baseline* = -3.584). Also in the alpha cluster, the linear regression of the power on the

504   Sync model pattern reached significance with a negative slope ($F(1, 835) = 32.720$, $p < .001$, $R^2_{adj} =$

505   .037, $\beta = -.65$).

Fig 5. Power locked to rule switch. Black lines show the mean power. Error bars show the 99.84% confidence

interval (Bonferroni correction). The horizontal blue dashed line represents baseline power and the vertical green

dotted line indicates the moment of the rule switch. The red line visualizes the result of linear regression between

the Sync model and human data. *A-C* show data locked to the moment of the actual rule switch. *D* shows data of

the alpha cluster locked to the moment when subjects indicated they noticed the task switch.

Power at the peak trials (0 for theta and delta, +1 for alpha) was extracted and added to a linear

regression with wAIC as predictor. This revealed no significant effects for the theta ($F(1, 25) = .004$, p

$= .948$, $R^2_{adj} = -.040$, $\beta = -.10$) or delta cluster ($F(1, 25) = .680$, $p = .417$, $R^2_{adj} = -.012$, $\beta = .66$). However,

the effect of wAIC did reach significance in the alpha cluster ($F(1, 25) = 7.220$, $p = .013$, $R^2_{adj} = .193$, β

$= 4.17$). Fig 6 sheds light on how activity in the alpha cluster differed depending on wAIC. For

illustrative purposes, subjects were divided in three groups of low, middle and high wAIC. For each

group, the data pattern of alpha activity was plotted, once locked to the real rule switch and once locked

to the indication of a rule switch (Fig 6). Here, it is observed that the alpha pattern is mainly driven by

subjects that have a low wAIC (i.e., good fit) for the bSync model.

Fig 6. Power locked to rule switch for different wAIC. Data patterns are shown for different wAIC values

(colored lines). The horizontal black dashed line shows the baseline power over all subjects and the vertical green

dotted line indicates the moment of the rule switch (A) or indication of rule switch (B).

Midfrontal-posterior Phase-coupling Analyses

We next turn to our third model-driven EEG analysis concerning an increase of phase

coupling between midfrontal and posterior electrodes after negative feedback. As previously described,

this coupling is induced by bursts that are sent from pMFC to posterior areas in the Mapping unit. Since

pMFC power is stronger after negative feedback, also the number of bursts and the amount of phase-

coupling is increased.

Here, non-parametric cluster analyses on the phase-locking data (phase-locking with

midfrontal electrodes; Fig 7) revealed six significant clusters that were selective for feedback (for details

see Materials and Methods). These clusters were located in the theta (4; Fig 7A, B, C) or delta (2; Fig

7A, B, D) frequency band. In the theta frequency band, two clusters were located at temporal electrodes;

two other clusters were located on more lateral/anterior frontal electrodes. In the delta frequency band,

both clusters were located on posterior electrodes. In line with the results of Sync model simulations

(Fig 7E), the theta clusters showed an increase in phase-locking after negative feedback. This was the

case for both the ipsilateral and contralateral electrodes. The delta clusters show the inverse pattern of

the theta cluster. Here, phase-locking was stronger after positive feedback than after negative feedback

in both the ipsi- and contralateral cluster. As in the power analyses, we also explored whether the phase-

locking contrast in each cluster correlated with the subjects' wAIC for the bSync model. None of these

correlations reached significance.

Fig 7. Phase-locking results. *A-B: Time-Frequency plots of contrast (Negative – Positive feedback)*. Significant

clusters are indicated by the black or white contour line. The black line represents posterior clusters in C and D

while the white line represent the frontal clusters in C. A: Contrast of iPLV averaged over all ipsi-lateral

electrodes. B: Contrast of iPLV averaged over all contra-lateral electrodes. *C-D: Topographical plots of clusters*.

Data was averaged over all time points and frequencies that were included in the respective contours of A and B.

Channels where cluster statistic reached significance are marked by crosses or dots. The left channels (crosses)

present ipsi-lateral electrodes and the right channels (dots) present contra-lateral electrodes. Again, the white color

was used to distinguish the frontal clusters from the temporal clusters.

555   **Discussion**

556   The current study aimed to gain insight in neural mechanisms that allow humans to flexibly

adapt to changes in the environment. For this purpose, 27 healthy human subjects were tested on a

probabilistic reversal learning task while EEG was recorded. On behavioral level, three models of

increasing hierarchical complexity were compared. A first model, the RW model, updated the value of

stimulus-action mappings on a trial-by-trial basis with a fixed learning rate. In a second model, the ALR

model, this approach was extended by employing an adaptable learning rate, allowing the ALR model

to be flexible in adapting to rule switches (fast learning rate) but to also be robust to noise evoked by

probabilistic feedback (slow learning rate). The third, Sync, model implemented modularity to retain

task-specific mappings. It employs hierarchical learning to determine when to switch between rule

modules. This approach obviates the need to relearn mappings on each rule switch. No evidence was

found for the ALR model, while for some people the RW fit best, and for others the Sync model.

Simulations of the Sync model allowed formulation and testing of three model-driven EEG

hypotheses. The first hypothesis considers the relation between midfrontal theta power and prediction

errors. In the Sync model, prediction errors are used to evaluate how much control should be exerted.

Here, the level of control is represented by theta power in pMFC. Since only negative prediction errors

inform about possible rule switches, the Sync model increased control after negative prediction errors

but not after positive prediction errors. Empirical data supported this hypothesis. A linear relationship

between prediction error and power in the theta cluster was observed for unrewarded trials (negative

prediction error) but not for rewarded trials (positive prediction error). Moreover, this effect was

stronger for subjects that fitted better with the Sync model. Since prediction errors are strongest at the

moment of a rule switch, a second model-driven hypothesis stated that theta power would peak at rule

switches. Again, this hypothesis was supported by empirical data. Moreover, simulated power

significantly predicted power in the empirical theta cluster. In a third model-driven hypothesis, the Sync

model predicted that phase connectivity would be increased after negative feedback. Here, six

significant clusters were found. Four of them were in theta frequency range and showed the pattern

predicted by the Sync model. Two of these clusters were located on posterior-temporal electrodes,

which is roughly in line with our prediction of motor and visual areas.

Several hypotheses remain to be tested. First, as was briefly mentioned in the Materials and

Methods section, previous modeling work used a gamma frequency in the Mapping unit instead of a

theta frequency. This frequency was currently changed because empirical work provides strong

evidence for within-frequency (theta-theta) coupling (Cavanagh, Cohen, & Allen, 2009; Clouter,

Shapiro, & Hanslmayr, 2017; Nigbur, Cohen, Ridderinkhof, & Stürmer, 2011) during cognitive tasks,

in addition to cross-frequency coupling. We thus also studied within-frequency coupling empirically.

Nevertheless, future work, using MEG or more invasive measurements, should also study the role of

cross-frequency (theta-gamma) coupling. Second, the limited spatial resolution of EEG did not allow

testing the prediction that different task rules are implemented by synchronizing different task-relevant

modules.

Several extensions can be made to the model as well. For instance, while for the reversal

learning task of the current study it was sufficient to use prediction error to determine when to make a

binary switch, a more sophisticated approach might apply in everyday life, where contextual cues allow

navigating a vast map of tasks and rules. One way to address this issue is by adding second level

(contextual) features which allow the LFC to (learn to) infer which of multiple task modules should be

synchronized. Additionally, scalability of the Sync model is limited by how modularity was

implemented in the Mapping unit. Here, none of the task rule 1 mappings are shared with task rule 2.

Such a strict division of task mappings is optimal when those mappings are orthogonal. However, when

some (but not all) of the mappings can be generalized between tasks, the current approach does not

allow agents to transfer knowledge across contexts. As has been addressed in previous work (Collins

& Frank, 2013; Gershman, Blei, & Niv, 2010), a more sustainable way is to construct modules of

mappings that are shared between tasks. Instead of having to learn each new task from scratch, this

approach allows agents to transfer knowledge from one task to another. Future work should explore

whether these more complex hierarchical learning algorithms can be integrated in the Sync model.

Since the current task did not contain (contextual) cues to infer the appropriate mappings, the

Sync model relied on prediction errors to estimate the hidden state (task rule) of the environment. This

is in line with previous ideas that reinforcement learning and more specifically prediction errors

signaled by dopamine are used to infer so called belief states (Gershman & Uchida, 2019; Starkweather,

Babayan, Uchida, & Gershman, 2017; Wilson et al., 2014). Instead, non-hierarchical models (such as

RW and ALR) only use prediction errors to adjust value of lower-level mappings.

Building on suggestions of previous work (Piray, Dezfouli, Heskes, Frank, & Daw, 2019),

current study illustrated how individual differences in model fit can be leveraged to address cognitive

questions. Here, three groups could be distinguished. One group of subjects aligned with the RW model,

a second group aligned with the Sync model and in a third group, no distinction could be made between

the RW and Sync model. Interestingly, subjects with lower accuracy fitted better with the Sync model. This is consistent with previous work (Verbeke & Verguts, 2019) which illustrated that modularity as employed by the Sync model is only beneficial if the learning problem is sufficiently complex. Furthermore, despite previous work showing a good behavioral fit of ALR-type models (Bai et al., 2014; Behrens et al., 2007; Silvetti, Seurinck, & Verguts, 2013), fit of the ALR model in the current study was consistently low over all subjects. Crucially, previous studies typically included long stable trial blocks in which the task rule did not change. In these periods it was beneficial to decrease learning rate. In contrast, the current task applied frequent rule switches in rapid succession, favoring tonically high learning rates. Thus, future work should investigate whether subjects flexibly employ the RW, Sync or ALR framework depending on the structure and complexity of the task.

The Sync model implements modularity via neural oscillations between task-relevant areas. This concords with a growing interest in the function of neural oscillations for a wide variety of cognitive functions, such as visual attention (e.g., Gray & Singer, 1989; Han, Lee, & Choi, 2019; Jensen, Bonnefond, & VanRullen, 2012), working memory (e.g., Hsieh, Ekstrom, & Ranganath, 2011; Hsieh & Ranganath, 2014; Lisman & Idiart, 1995), cognitive control (e.g., Cavanagh & Frank, 2014; Oehrn et al., 2014) and declarative learning (Ergo, De Loof, & Verguts, 2020). According to the BBS hypothesis (Fries, 2005, 2015), all these cognitive functions require in some way the binding of several stimuli, dimensions or features. Current work described how oscillations, and more specifically synchronization, might be relevant in hierarchical learning. Here, BBS is employed to flexibly bind mappings that are relevant for a certain task rule.

On anatomical-functional level, current work builds on suggestions from previous work that pMFC closely cooperates with LFC (Cavanagh, Frank, Klein, & Allen, 2010; Kondo, Osaka, & Osaka, 2004; Mac Donald, Cohen, Stenger, & Carter, 2000) to exert hierarchical control over lower-level motor processes (Alexander & Brown, 2015; Badre & Nee, 2018; Holroyd & McClure, 2015; Koechlin, Ody, & Kouneiher, 2003). In the Sync model, LFC signals which rule modules should be synchronized. This is in line with previous theoretical work describing LFC as containing task demands (Botvinick et al., 2001) and empirical work that found strong communication between LFC and pMFC in cognitive tasks (Cavanagh et al., 2010; Kondo et al., 2004; Mac Donald et al., 2000). Also in line with previous

empirical work (Boorman, Behrens, Woolrich, & Rushworth, 2009; Wilson et al., 2014), the model

aMFC is responsible for keeping track of the relevant task rule. Additionally, consistent with previous

fMRI work (e.g., Aben, Calderon, den Bussche, & Verguts, 2020; Hare, Schultz, Camerer, O'Doherty,

& Rangel, 2011), the current study also found increased coupling between midfrontal cortex and task-

related areas when more control was needed (negative feedback). Importantly, while this fMRI work

showed detailed networks of connectivity, current study described how this connectivity works at

algorithmic level.

To sum up, we have demonstrated how the brain might employ synchronization in order to

bind task-relevant areas for hierarchical and efficient task processing. To achieve this, we used a

combination of EEG, computational modelling, individual differences, and behavioral analysis. We

believe that such an approach might reveal how and whether more complicated tasks can be

implemented via synchronization as well, in which contexts, and in which individuals.

References

Aben, B., Calderon, C. B., Van den Bussche, E., & Verguts, T. (2020). Cognitive effort modulates

connectivity between dorsal anterior cingulate cortex and task-relevant cortical areas. *The*

Journal of Neuroscience, *40*(19), JN-RM-2948-19. https://doi.org/10.1523/jneurosci.2948-

19.2020

Alexander, W. H., & Brown, J. W. (2015). Hierarchical error representation: A computational model

of anterior cingulate and dorsolateral prefrontal cortex. *Neural Computation*, *27*(11), 2354–

2410. https://doi.org/10.1162/NECO

Badre, D., & Nee, D. E. (2018). Frontal cortex and the hierarchical control of behavior. *Trends in*

Cognitive Sciences, *22*(2), 170–188. https://doi.org/10.1016/j.tics.2017.11.005

Bai, Y., Katahira, K., & Ohira, H. (2014). Dual learning processes underlying human decision-making

in reversal learning tasks: Functional significance and evidence from the model fit to human

behavior. *Frontiers in Psychology*, *5*(AUG), 1–8. https://doi.org/10.3389/fpsyg.2014.00871

Behrens, T. E. J., Woolrich, M. W., Walton, M. E., & Rushworth, M. F. S. (2007). Learning the value

of information in an uncertain world. *Nature Neuroscience*, *10*(9), 1214–1221.

https://doi.org/10.1038/nn1954

Boorman, E. D., Behrens, T. E. J., Woolrich, M. W., & Rushworth, M. F. S. (2009). How green is the

grass on the other side? frontopolar cortex and the evidence in favor of alternative courses of

action. *Neuron*, *62*(5), 733–743. https://doi.org/10.1016/j.neuron.2009.05.014

Botvinick, M., Braver, T. S., Barch, D. M., Carter, C. S., Cohen, J. D., & Cameron, C. S. (2001).

Conflict monitoring and cognitive control. *Psychological Review*, *108*(3), 624–652.

https://doi.org/10.1037/0033-295X.108.3.624

Bruña, R., Maestú, F., & Pereda, E. (2018). Phase locking value revisited: Teaching new tricks to an

old dog. *Journal of Neural Engineering*, *15*(5). https://doi.org/10.1088/1741-2552/aacfe4

Cavanagh, J. F., Cohen, M. X., & Allen, J. J. B. B. (2009). Prelude to and resolution of an error : EEG

phase synchrony reveals cognitive control dynamics during action monitoring. *Journal of

Neuroscience*, *29*(1), 98–105. https://doi.org/10.1523/JNEUROSCI.4137-08.2009

Cavanagh, J. F., & Frank, M. J. (2014). Frontal theta as a mechanism for cognitive control. *Trends in

Cognitive Sciences*, *18*(8), 414–421. https://doi.org/10.1016/j.tics.2014.04.012

Cavanagh, J. F., Frank, M. J., Klein, T. J., & Allen, J. B. (2010). Frontal theta links prediction errors

to behavioral adaptation in reinforcement learning. *NeuroImage*, *49*(4), 3198–3209.

https://doi.org/10.1016/j.neuroimage.2009.11.080

Clouter, A., Shapiro, K. L., & Hanslmayr, S. (2017). Theta phase synchronization is the glue that

binds human associative memory. *Current Biology*, *27*(20), 1–6.

https://doi.org/10.1016/j.cub.2017.09.001

Cohen, M. X. (2014). *Analyzing neural time series data: Theory and practice*. Cambridge,

Massachusetts: The MIT Press.

Collins, A. G. E., & Frank, M. J. (2013). Cognitive control over learning: Creating, clustering, and

generalizing task-set structure. *Psychological Review*, *120*(1), 190–229.

https://doi.org/10.1037/a0030852

Cools, R., Clark, L., Owen, A. M., & Robbins, T. W. (2002). Defining the neural mechanisms of

probabilistic reversal learning using event-related functional magnetic resonance imaging. *The

Journal of Neuroscience : The Official Journal of the Society for Neuroscience, *22*(11), 4563–

4567. https://doi.org/20026435

Delorme, A., & Makeig, S. (2004). EEGLAB: An open source toolbox for analysis of single-trial

EEG dynamics including independent component analysis. *Journal of Neuroscience Methods*,

134(1), 9–21. https://doi.org/10.1016/j.jneumeth.2003.10.009

Ergo, K., De Loof, E., & Verguts, T. (2020). Reward prediction error and declarative memory. *Trends*

in Cognitive Sciences, *24*(5), 388–397. https://doi.org/10.1016/j.tics.2020.02.009

French, R. M. (1999). Catastrophic forgetting in connectionist networks. *Trends in Cognitive*

Sciences, *6613*(April), 128–135.

Fries, P. (2005). A mechanism for cognitive dynamics: neuronal communication through neuronal

coherence. *Trends in Cognitive Sciences*, *9*(10), 474–480.

https://doi.org/10.1016/j.tics.2005.08.011

Fries, P. (2015). Rhythms for cognition: Communication through coherence. *Neuron*, *88*(1), 220–235.

https://doi.org/10.1016/j.neuron.2015.09.034

Gershman, S. J., Blei, D. M., & Niv, Y. (2010). Context, learning, and extinction. *Psychological*

Review, *117*(1), 197–209. https://doi.org/10.1037/a0017808

Gershman, S. J., & Uchida, N. (2019). Believing in dopamine. *Nature Reviews Neuroscience*, *20*(11),

703–714. https://doi.org/10.1038/s41583-019-0220-7

Gray, C. M., & Singer, W. (1989). Stimulus-specific neuronal oscillations in orientation columns of

cat visual cortex. *Proceedings of the National Academy of Sciences of the United States of*

America, *86*(5), 1698–1702. https://doi.org/10.1073/pnas.86.5.1698

Han, H. B., Lee, K. E., & Choi, J. H. (2019). Functional dissociation of θ oscillations in the frontal

and visual cortices and their long-range network during sustained attention. *ENeuro*, *6*(6), 1–12.

https://doi.org/10.1523/ENEURO.0248-19.2019

Hare, T. A., Schultz, W., Camerer, C. F., O'Doherty, J. P., & Rangel, A. (2011). Transformation of

stimulus value signals into motor commands during simple choice. *Proceedings of the National*

Academy of Sciences of the United States of America, *108*(44), 18120–18125.

https://doi.org/10.1073/pnas.1109322108

Holroyd, C. B. (2016). The waste disposal problem of effortful control. In T. S. Braver (Ed.),

Motivation and cognitive control (pp. 235–260). Hove, UK: Psychology Press.

Holroyd, C. B., & McClure, S. M. (2015). Hierarchical control over effortful behavior by rodent

medial frontal cortex: A computational model. *Psychological Review*, *122*(1), 54–83.

https://doi.org/10.1037/a0038339

Hsieh, L. T., Ekstrom, A. D., & Ranganath, C. (2011). Neural oscillations associated with item and

temporal order maintenance in working memory. *Journal of Neuroscience*, *31*(30), 10803–

10810. https://doi.org/10.1523/JNEUROSCI.0828-11.2011

Hsieh, L. T., & Ranganath, C. (2014). Frontal midline theta oscillations during working memory

maintenance and episodic encoding and retrieval. *NeuroImage*, *85*, 721–729.

https://doi.org/10.1016/j.neuroimage.2013.08.003

Izquierdo, A., Brigman, J. L., Radke, A. K., Rudebeck, P. H., & Holmes, A. (2017). The neural basis

of reversal learning: An updated perspective. *Neuroscience*, *345*, 12–26.

https://doi.org/10.1016/j.neuroscience.2016.03.021

Jasper, H. (1958). The ten twenty electrode system of the international federation.

Electroencephalogr. Clin. Neurophysiol., (10), 371–375.

Jensen, O., Bonnefond, M., & VanRullen, R. (2012). An oscillatory mechanism for prioritizing salient

unattended stimuli. *Trends in Cognitive Sciences*, *16*(4), 200–205.

https://doi.org/10.1016/j.tics.2012.03.002

Koechlin, E., Ody, C., & Kouneiher, F. (2003). The architecture of cognitive control in the human

prefrontal cortex. *Science (New York, NY)*, *302*(5648), 1181–1185.

https://doi.org/10.1126/science.1088545

Kondo, H., Osaka, N., & Osaka, M. (2004). Cooperation of the anterior cingulate cortex and

dorsolateral prefrontal cortex for attention shifting. *NeuroImage*, *23*(2), 670–679.

https://doi.org/10.1016/j.neuroimage.2004.06.014

Lachaux, J. P., Rodriguez, E., Martinerie, J., & Varela, F. J. (1999). Measuring phase synchrony in

brain signals. *Human Brain Mapping*, *8*(4), 194–208. https://doi.org/10.1002/(SICI)1097-
0193(1999)8:4<194::AID-HBM4>3.0.CO;2-C

Lisman, J. E., & Idiart, M. A. P. (1995). Storage of 7 ± 2 short-term memories in oscillatory
subcycles. *Science*, *267*(5203), 1512–1515. https://doi.org/10.1126/science.7878473

Mac Donald, A. W., Cohen, J. D., Stenger, A. V., & Carter, C. S. (2000). Dissociating the role of the
dorsolateral prefrontal and anterior cingulate cortex in cognitive control. *Science*, *288*(June),
1835–1838. https://doi.org/10.1126/science.288.5472.1835

Makoto, M. (2018). Makoto's preprocessing pipeline. Retrieved from
https://sccn.ucsd.edu/wiki/Makoto%27s_preprocessing_pipeline

Maris, E., & Oostenveld, R. (2007). Nonparametric statistical testing of EEG- and MEG-data. *Journal
of Neuroscience Methods*, *164*(1), 177–190. https://doi.org/10.1016/j.jneumeth.2007.03.024

Nigbur, R., Cohen, M. X., Ridderinkhof, K. R., & Stürmer, B. (2011). Theta dynamics reveal domain-
specific control over stimulus and response conflict. *Journal of Cognitive Neuroscience*, *24*(5),
1264–1274. https://doi.org/10.1162/jocn_a_00128

Nolte, G., Bai, O., Wheaton, L., Mari, Z., Vorbach, S., & Hallett, M. (2004). Identifying true brain
interaction from EEG data using the imaginary part of coherency. *Clinical Neurophysiology*,
115(10), 2292–2307. https://doi.org/10.1016/j.clinph.2004.04.029

Oehrn, C. R., Hanslmayr, S., Fell, J., Deuker, L., Kremers, N. A., Do Lam, A. T., … Axmacher, N.
(2014). Neural communication patterns underlying conflict detection, resolution, and adaptation.
Journal of Neuroscience, *34*(31), 10438–10452. https://doi.org/10.1523/JNEUROSCI.3099-
13.2014

Peirce, J., Gray, J. R., Simpson, S., MacAskill, M., Höchenberger, R., Sogo, H., … Lindeløv, J. K.
(2019). PsychoPy2: Experiments in behavior made easy. *Behavior Research Methods*, *51*(1),
195–203. https://doi.org/10.3758/s13428-018-01193-y

Piray, P., Dezfouli, A., Heskes, T., Frank, M., & Daw, N. (2019). Hierarchical Bayesian inference for
concurrent model fitting and comparison for group studies. *PLoS Computational Biology*, *15*(6),
34. https://doi.org/https://doi.org/10.1371/journal.pcbi.1007043

R Core Team. (2017). R: A Language and Environment for Statistical Computing. Vienna, Austria.

Rescorla, R. A., & Wagner, A. R. (1972). A theory of Pavlovian conditioning: Variations in the

effectiveness of reinforcement and nonreinforcement. *Classical Conditioning II Current*

Research and Theory, *21*(6), 64–99. https://doi.org/10.1101/gr.110528.110

Saez, A., Rigotti, M., Ostojic, S., Fusi, S., & Salzman, C. D. (2015). Abstract context representations

in primate amygdala and prefrontal cortex. *Neuron*, *87*(4), 869–881.

https://doi.org/10.1016/j.neuron.2015.07.024

Silvetti, M., Seurinck, R., & Verguts, T. (2011). Value and prediction error in medial frontal cortex:

integrating the single-unit and systems levels of analysis. *Frontiers in Human Neuroscience*,

5(August), 75. https://doi.org/10.3389/fnhum.2011.00075

Silvetti, M., Seurinck, R., & Verguts, T. (2013). Value and prediction error estimation account for

volatility effects in ACC: A model-based fMRI study. *Cortex*, *49*(6), 1627–1635.

https://doi.org/10.1016/j.cortex.2012.05.008

Silvetti, M., Vassena, E., Abrahamse, E., & Verguts, T. (2018). Dorsal anterior cingulate-brainstem

ensemble as a reinforcement meta-learner. *PLoS Computational Biology*, *14*(8), 1–32.

https://doi.org/10.1371/journal.pcbi.1006370

Springer, M., & Paulsson, J. (2006). Harmonies from noise. *Nature*, *439*(January), 27–29.

https://doi.org/doi:10.1038/439027a

Starkweather, C. K., Babayan, B. M., Uchida, N., & Gershman, S. J. (2017). Dopamine reward

prediction errors reflect hidden-state inference across time. *Nature Neuroscience*, *20*(4), 581–

589. https://doi.org/10.1038/nn.4520

The MathWorks Inc. (2016). MATLAB R2016B. Natick, Massachussetts, United States.

Verbeke, P., & Verguts, T. (2019). Learning to synchronize: How biological agents can couple neural

task modules for dealing with the stability-plasticity dilemma. *PLoS Computational Biology*,

15(8). https://doi.org/10.1371/journal.pcbi.1006604

Verguts, T. (2017). Binding by random bursts: A computational model of cognitive control. *Journal*

of Cognitive Neuroscience, *29*(6), 1103–1118. https://doi.org/10.1162/jocn

Widrow, B., & Hoff, M. M. E. (1960). Adaptive switching circuits. *IRE WESCON Convention*

Record, *4*(1), 96–104.

Wilson, R. C., Takahashi, Y. K., Schoenbaum, G., & Niv, Y. (2014). Orbitofrontal cortex as a

cognitive map of task space. *Neuron*, *81*(2), 267–279.

https://doi.org/10.1016/j.neuron.2013.11.005

Womelsdorf, T., Johnston, K., Vinck, M., & Everling, S. (2010). Theta-activity in anterior cingulate

cortex predicts task rules and their adjustments following errors. *Proceedings of the National*

Academy of Sciences, *107*(11), 5248–5253. https://doi.org/10.1073/pnas.0906194107

Womelsdorf, T., Schoffelen, J., Oostenveld, R., Singer, W., Desimone, R., Engel, A. K., & Fries, P.

(2007). Modulation of neuronal interactions through neuronal synchronization. *Science*,

316(1609), 1609–1612. https://doi.org/10.1126/science.1139178

Zhou, T., Chen, L., & Aihara, K. (2005). Molecular communication through stochastic

synchronization Induced by extracellular fluctuations. *Physical Review Letters*,

178103(October), 2–5. https://doi.org/10.1103/PhysRevLett.95.178103